

Adding a Secure Access Cluster with Imported Cluster Members

Add and import a Secure Access cluster in NSM by following these procedures:

1. Installing and Configuring the Cluster on page 1
2. Adding the Cluster in NSM on page 1
3. Adding the Cluster Members in NSM on page 1
4. Configuring and Activating the DMI Agent on the Cluster on page 3
5. Importing Cluster Configuration on page 3

Installing and Configuring the Cluster

You must install and configure the Cluster to have logon credentials for an NSM administrator before you can add the cluster to NSM.

Adding the Cluster in NSM

Before you can add a Secure Access device cluster to NSM, you must first add the cluster object, and then add its members.

To add new cluster to NSM:

1. From the left pane of the NSM UI, click **Configure**.
2. Expand **Device Manager** and select **Devices**. The Devices workspace appears on the right side of the screen.
3. Click the **Device Tree** tab, click the **New** button, and select **Cluster**. The New - Cluster dialog box appears.
4. Enter the cluster name and select the required color, OS name (SA), and platform and managed OS version from the drop-down lists.
5. Click **OK**, The new cluster appears in the Device Manager.

Adding the Cluster Members in NSM

You add cluster members one at a time, in a similar manner to adding standalone devices.

Adding Cluster Members through Not Reachable Workflow

To add a cluster member through the non-reachable workflow:

1. From the left pane of the NSM UI, click **Configure**.
2. Expand **Device Manager** and select **Devices**. The Devices workspace appears on the right side of the screen.
3. Click the **Device Tree** tab, and select the cluster to which you want to add the members.

4. Click the **New** button and select **Cluster Member**. The New-Cluster Member dialog box appears.
5. Enter the cluster member name, select **Device Is Not Reachable**, and click **Next**.
6. From the Choose Device Server Connections Parameter area, select:
 - **Use Default Device Server IP Address and Port**—Connects the device to the NSM device server IP address and port.
 - **Use Device Server Through MIP**—Connects to the NSM device server through a mapped IP address and port.
7. Click **Next**, and a unique external ID gets generated automatically. This ID represents the device within the management system.
8. Enter an admin username for the device admin.
9. Set the admin user password and the first connection one-time password:
 - a. Enter a new password in the **Set Password** box.
 - b. Confirm the new password and click **OK**.

**NOTE:**

- Make a note of the unique external ID. The device administrator will need it to configure connectivity with NSM. The wizard automatically enters this value for the device. This ID number represents the device within the management system.
- Specify the administrator username and password for the SSH connection. This name and password must match the name and password already configured on the device.
- Specify the first connection one time password (OTP) that authenticates the device. Make a note of this password. The device administrator will need it to configure the connectivity with NSM.

-
10. Click **Finish** to add the cluster member to the NSM GUI. The cluster member appears in the Devices workspace.

Adding Cluster Members through Reachable Workflow

To add a cluster member:

1. From the left pane of the NSM UI, click **Configure**.
2. Expand **Device Manager** and select **Devices**. The Devices workspace appears on the right side of the screen.
3. Click the **Device Tree** tab, and select the cluster to which you want to add the members.
4. Click the **New** button and select **Cluster Member**. The New-Cluster Member dialog box appears.
5. Enter the cluster member name, select **Device Is Reachable** and click **Next**.

6. Specify the device connection settings:
 - **IP Address**—IP address of the Secure Access device.
 - **Admin User Name**—Administrator user name created for the Secure Access device.
 - **Password**—Administrator password created for the Secure Access device.
7. Click **Next**. The Secure Access device is detected and the device details are displayed.
8. Enter a new name for the Secure Access device in **Device Name** to change the host name of the device.
9. Click **Finish** to add the cluster member to the NSM GUI. The cluster member as a child of the Secure Access cluster in the Devices workspace.

Configuring and Activating the DMI Agent on the Cluster

On each cluster member device, configure and activate the DMI agent and establish an SSH session with NSM.

Importing Cluster Configuration

After adding the cluster members, you must import the cluster configurations. You do this only once and for the entire cluster because the configuration is identical for all cluster members.

To import the cluster configuration:

1. From the left pane of the NSM UI, click **Configure**.
2. Expand **Device Manager** and select **Devices**. The Devices workspace appears on the right side of the screen.
3. Click the **Device Tree** tab. Right-click the cluster to which you want to import the configurations, and select **Import Device**.

NSM starts to import the configuration and a job window reports the progress of the job. When the job finishes, the configuration status for each cluster member in the Device List tab changes from Import Needed to Managed.

After importing, the configuration appears at the cluster level in NSM. To edit the configuration, open the cluster icon, not the individual cluster members.

- Related Topics**
- Creating and Applying a Secure Access Device Template
 - Promoting a Secure Access Device Configuration to a Template
 - Adding a Secure Access Cluster Overview