

circuit-id

Syntax	<pre>circuit-id { prefix hostname; use-interface-description; use-vlan-id; }</pre>
Hierarchy Level	[edit ethernet-switching-options secure-access-port vlan (all <i>vlan-name</i>) dhcp-option82] [edit forwarding-options helpers bootp dhcp-option82] [edit forwarding-options helpers bootp interface <i>interface-name</i> dhcp-option82]
Release Information	Statement introduced in JUNOS Release 9.3 for EX-series switches.
Description	<p>Configure the circuit-id suboption (suboption 1) of DHCP option 82 (the DHCP relay agent information option) in DHCP packets destined for a DHCP server. This suboption identifies the circuit (interface and/or VLAN) on which the DHCP request arrived.</p> <p>The format of the circuit-id information for Gigabit Ethernet interfaces that use VLANs is <i>interface-name:vlan-name</i> . On a Layer 3 interface, the format is just <i>interface-name</i> .</p> <p>The remaining statements are explained separately.</p>
Default	If DHCP option 82 is enabled on the switch, the circuit ID is supplied by default in the format <i>interface-name:vlan-name</i> or, on a Layer 3 interface, just <i>interface-name</i> .
Required Privilege Level	routing—To view this statement in the configuration. routing-control—To add this statement to the configuration.
Related Topics	<ul style="list-style-type: none">■ Example: Setting Up DHCP Option 82 on an EX-series Switch with No Relay Agent Between Clients and DHCP Server■ Example: Setting Up DHCP Option 82 with an EX-series Switch as Relay Agent Between Clients and a DHCP Server■ Setting Up DHCP Option 82 on the Switch with No Relay Agent Between Clients and DHCP Server (CLI Procedure)■ Setting Up DHCP Option 82 with the Switch as a Relay Agent Between Clients and DHCP Server (CLI Procedure)■ [edit forwarding options] Configuration Statement Hierarchy■ RFC 3046, <i>DHCP Relay Agent Information Option</i>, at http://tools.ietf.org/html/rfc3046.

