



Junos[®] OS

ICMP Router Discovery Protocol Configuration Guide

Release
12.1



Published: 2012-08-10

Juniper Networks, Inc.
1194 North Mathilda Avenue
Sunnyvale, California 94089
USA
408-745-2000
www.juniper.net

This product includes the Envoy SNMP Engine, developed by Epilogue Technology, an Integrated Systems Company. Copyright © 1986-1997, Epilogue Technology Corporation. All rights reserved. This program and its documentation were developed at private expense, and no part of them is in the public domain.

This product includes memory allocation software developed by Mark Moraes, copyright © 1988, 1989, 1993, University of Toronto.

This product includes FreeBSD software developed by the University of California, Berkeley, and its contributors. All of the documentation and software included in the 4.4BSD and 4.4BSD-Lite Releases is copyrighted by the Regents of the University of California. Copyright © 1979, 1980, 1983, 1986, 1988, 1989, 1991, 1992, 1993, 1994. The Regents of the University of California. All rights reserved.

GateD software copyright © 1995, the Regents of the University. All rights reserved. Gate Daemon was originated and developed through release 3.0 by Cornell University and its collaborators. Gated is based on Kirton's EGP, UC Berkeley's routing daemon (routed), and DCN's HELLO routing protocol. Development of Gated has been supported in part by the National Science Foundation. Portions of the GateD software copyright © 1988, Regents of the University of California. All rights reserved. Portions of the GateD software copyright © 1991, D. L. S. Associates.

This product includes software developed by Maker Communications, Inc., copyright © 1996, 1997, Maker Communications, Inc.

Juniper Networks, Junos, Steel-Belted Radius, NetScreen, and ScreenOS are registered trademarks of Juniper Networks, Inc. in the United States and other countries. The Juniper Networks Logo, the Junos logo, and JunosE are trademarks of Juniper Networks, Inc. All other trademarks, service marks, registered trademarks, or registered service marks are the property of their respective owners.

Juniper Networks assumes no responsibility for any inaccuracies in this document. Juniper Networks reserves the right to change, modify, transfer, or otherwise revise this publication without notice.

Products made or sold by Juniper Networks or components thereof might be covered by one or more of the following patents that are owned by or licensed to Juniper Networks: U.S. Patent Nos. 5,473,599, 5,905,725, 5,909,440, 6,192,051, 6,333,650, 6,359,479, 6,406,312, 6,429,706, 6,459,579, 6,493,347, 6,538,518, 6,538,899, 6,552,918, 6,567,902, 6,578,186, and 6,590,785.

Junos® OS ICMP Router Discovery Protocol Configuration Guide

12.1

Copyright © 2012, Juniper Networks, Inc.
All rights reserved.

The information in this document is current as of the date on the title page.

YEAR 2000 NOTICE

Juniper Networks hardware and software products are Year 2000 compliant. Junos OS has no known time-related limitations through the year 2038. However, the NTP application is known to have some difficulty in the year 2036.

END USER LICENSE AGREEMENT

The Juniper Networks product that is the subject of this technical documentation consists of (or is intended for use with) Juniper Networks software. Use of such software is subject to the terms and conditions of the End User License Agreement ("EULA") posted at <http://www.juniper.net/support/eula.html>. By downloading, installing or using such software, you agree to the terms and conditions of that EULA.

Table of Contents

	About the Documentation	ix
	Documentation and Release Notes	ix
	Supported Platforms	ix
	Using the Examples in This Manual	ix
	Merging a Full Example	x
	Merging a Snippet	x
	Documentation Conventions	xi
	Documentation Feedback	xiii
	Requesting Technical Support	xiii
	Self-Help Online Tools and Resources	xiii
	Opening a Case with JTAC	xiv
Part 1	Overview	
Chapter 1	Introduction to ICMP Router Discovery	3
	ICMP Router Discovery Overview	3
	Operation of a Router Discovery Server	3
	Router Advertisement Messages	4
Chapter 2	ICMP Router Discovery Reference	5
	Supported ICMP and Neighbor Discovery Standards	5
Part 2	Configuration	
Chapter 3	Concept and Example	9
	Example: Configuring ICMP Router Discovery	9
	Understanding the ICMP Router Discovery Protocol	9
	Example: Configuring ICMP Router Discovery	9
Chapter 4	Configuration Statements	15
	[edit protocols router-discovery] Hierarchy Level	15
	address	16
	advertise	16
	broadcast	17
	disable	17
	ignore	17
	ineligible	18
	interface	18
	lifetime	19
	max-advertisement-interval	20
	min-advertisement-interval	21
	multicast	22

	priority	23
	router-discovery	23
	traceoptions	24
Part 3	Administration	
Chapter 5	Operational Commands	29
	monitor interface	30
	monitor start	40
	monitor stop	42
	ping	43
	show log	47
	traceroute	49
Part 4	Troubleshooting	
Chapter 6	Routing Protocol Process Memory FAQ	55
	Routing Protocol Process Memory FAQ Overview	55
	Routing Protocol Process Memory FAQs	56
	Routing Protocol Process Memory Utilization FAQs	56
	Interpreting Routing Protocol Process-Related Command Outputs FAQs	58
	Routing Protocol Process Memory Swapping FAQs	61
	Troubleshooting the Routing Protocol Process FAQs	62
Part 5	Index	
	Index	65

List of Figures

Part 2	Configuration	
Chapter 3	Concept and Example	9
	Figure 1: ICMP Router Discovery Topology	11

List of Tables

	About the Documentation	ix
	Table 1: Notice Icons	xi
	Table 2: Text and Syntax Conventions	xi
Part 3	Administration	
Chapter 5	Operational Commands	29
	Table 3: Output Control Keys for the monitor interface interface-name Command	30
	Table 4: Output Control Keys for the monitor interface traffic Command	31
	Table 5: monitor interface Output Fields	32
	Table 6: monitor start Output Fields	40
	Table 7: traceroute Output Fields	51
Part 4	Troubleshooting	
Chapter 6	Routing Protocol Process Memory FAQ	55
	Table 8: show system processes extensive Output Fields	59
	Table 9: show task memory Output Fields	60

About the Documentation

- [Documentation and Release Notes on page ix](#)
- [Supported Platforms on page ix](#)
- [Using the Examples in This Manual on page ix](#)
- [Documentation Conventions on page xi](#)
- [Documentation Feedback on page xiii](#)
- [Requesting Technical Support on page xiii](#)

Documentation and Release Notes

To obtain the most current version of all Juniper Networks® technical documentation, see the product documentation page on the Juniper Networks website at <http://www.juniper.net/techpubs/>.

If the information in the latest release notes differs from the information in the documentation, follow the product Release Notes.

Juniper Networks Books publishes books by Juniper Networks engineers and subject matter experts. These books go beyond the technical documentation to explore the nuances of network architecture, deployment, and administration. The current list can be viewed at <http://www.juniper.net/books>.

Supported Platforms

For the features described in this document, the following platforms are supported:

- [QFX Series](#)
- [PTX Series](#)
- [MX Series](#)
- [T Series](#)
- [M Series](#)

Using the Examples in This Manual

If you want to use the examples in this manual, you can use the **load merge** or the **load merge relative** command. These commands cause the software to merge the incoming

configuration into the current candidate configuration. The example does not become active until you commit the candidate configuration.

If the example configuration contains the top level of the hierarchy (or multiple hierarchies), the example is a *full example*. In this case, use the **load merge** command.

If the example configuration does not start at the top level of the hierarchy, the example is a *snippet*. In this case, use the **load merge relative** command. These procedures are described in the following sections.

Merging a Full Example

To merge a full example, follow these steps:

1. From the HTML or PDF version of the manual, copy a configuration example into a text file, save the file with a name, and copy the file to a directory on your routing platform.

For example, copy the following configuration to a file and name the file **ex-script.conf**. Copy the **ex-script.conf** file to the **/var/tmp** directory on your routing platform.

```
system {
  scripts {
    commit {
      file ex-script.xsl;
    }
  }
}
interfaces {
  fxp0 {
    disable;
    unit 0 {
      family inet {
        address 10.0.0.1/24;
      }
    }
  }
}
```

2. Merge the contents of the file into your routing platform configuration by issuing the **load merge** configuration mode command:

```
[edit]
user@host# load merge /var/tmp/ex-script.conf
load complete
```

Merging a Snippet

To merge a snippet, follow these steps:

1. From the HTML or PDF version of the manual, copy a configuration snippet into a text file, save the file with a name, and copy the file to a directory on your routing platform.

For example, copy the following snippet to a file and name the file **ex-script-snippet.conf**. Copy the **ex-script-snippet.conf** file to the **/var/tmp** directory on your routing platform.

```
commit {
  file ex-script-snippet.xml; }
```

2. Move to the hierarchy level that is relevant for this snippet by issuing the following configuration mode command:

```
[edit]
user@host# edit system scripts
[edit system scripts]
```

3. Merge the contents of the file into your routing platform configuration by issuing the **load merge relative** configuration mode command:

```
[edit system scripts]
user@host# load merge relative /var/tmp/ex-script-snippet.conf
load complete
```

For more information about the **load** command, see the [Junos OS CLI User Guide](#).

Documentation Conventions

Table 1 on page xi defines notice icons used in this guide.

Table 1: Notice Icons

Icon	Meaning	Description
	Informational note	Indicates important features or instructions.
	Caution	Indicates a situation that might result in loss of data or hardware damage.
	Warning	Alerts you to the risk of personal injury or death.
	Laser warning	Alerts you to the risk of personal injury from a laser.

Table 2 on page xi defines the text and syntax conventions used in this guide.

Table 2: Text and Syntax Conventions

Convention	Description	Examples
Bold text like this	Represents text that you type.	To enter configuration mode, type the configure command: user@host> configure
Fixed-width text like this	Represents output that appears on the terminal screen.	user@host> show chassis alarms No alarms currently active

Table 2: Text and Syntax Conventions (*continued*)

Convention	Description	Examples
<i>Italic text like this</i>	<ul style="list-style-type: none"> Introduces or emphasizes important new terms. Identifies book names. Identifies RFC and Internet draft titles. 	<ul style="list-style-type: none"> A policy <i>term</i> is a named structure that defines match conditions and actions. <i>Junos OS System Basics Configuration Guide</i> RFC 1997, <i>BGP Communities Attribute</i>
<i>Italic text like this</i>	Represents variables (options for which you substitute a value) in commands or configuration statements.	Configure the machine's domain name: [edit] root@# set system domain-name <i>domain-name</i>
Text like this	Represents names of configuration statements, commands, files, and directories; configuration hierarchy levels; or labels on routing platform components.	<ul style="list-style-type: none"> To configure a stub area, include the stub statement at the [edit protocols ospf area area-id] hierarchy level. The console port is labeled CONSOLE.
< > (angle brackets)	Enclose optional keywords or variables.	stub <default-metric metric>;
(pipe symbol)	Indicates a choice between the mutually exclusive keywords or variables on either side of the symbol. The set of choices is often enclosed in parentheses for clarity.	broadcast multicast <i>(string1 string2 string3)</i>
# (pound sign)	Indicates a comment specified on the same line as the configuration statement to which it applies.	rsvp { # Required for dynamic MPLS only
[] (square brackets)	Enclose a variable for which you can substitute one or more values.	community name members [community-ids]
Indentation and braces ({ })	Identify a level in the configuration hierarchy.	[edit] routing-options { static { route default { nexthop <i>address</i> ; retain; } } }
;(semicolon)	Identifies a leaf statement at a configuration hierarchy level.	
J-Web GUI Conventions		
Bold text like this	Represents J-Web graphical user interface (GUI) items you click or select.	<ul style="list-style-type: none"> In the Logical Interfaces box, select All Interfaces. To cancel the configuration, click Cancel.
> (bold right angle bracket)	Separates levels in a hierarchy of J-Web selections.	In the configuration editor hierarchy, select Protocols>Ospf .

Documentation Feedback

We encourage you to provide feedback, comments, and suggestions so that we can improve the documentation. You can send your comments to techpubs-comments@juniper.net, or fill out the documentation feedback form at <https://www.juniper.net/cgi-bin/docbugreport/>. If you are using e-mail, be sure to include the following information with your comments:

- Document or topic name
- URL or page number
- Software release version (if applicable)

Requesting Technical Support

Technical product support is available through the Juniper Networks Technical Assistance Center (JTAC). If you are a customer with an active J-Care or JNASC support contract, or are covered under warranty, and need post-sales technical support, you can access our tools and resources online or open a case with JTAC.

- JTAC policies—For a complete understanding of our JTAC procedures and policies, review the *JTAC User Guide* located at <http://www.juniper.net/us/en/local/pdf/resource-guides/7100059-en.pdf>.
- Product warranties—For product warranty information, visit <http://www.juniper.net/support/warranty/>.
- JTAC hours of operation—The JTAC centers have resources available 24 hours a day, 7 days a week, 365 days a year.

Self-Help Online Tools and Resources

For quick and easy problem resolution, Juniper Networks has designed an online self-service portal called the Customer Support Center (CSC) that provides you with the following features:

- Find CSC offerings: <http://www.juniper.net/customers/support/>
- Search for known bugs: <http://www2.juniper.net/kb/>
- Find product documentation: <http://www.juniper.net/techpubs/>
- Find solutions and answer questions using our Knowledge Base: <http://kb.juniper.net/>
- Download the latest versions of software and review release notes: <http://www.juniper.net/customers/csc/software/>
- Search technical bulletins for relevant hardware and software notifications: <https://www.juniper.net/alerts/>

- Join and participate in the Juniper Networks Community Forum:
<http://www.juniper.net/company/communities/>
- Open a case online in the CSC Case Management tool: <http://www.juniper.net/cm/>

To verify service entitlement by product serial number, use our Serial Number Entitlement (SNE) Tool: <https://tools.juniper.net/SerialNumberEntitlementSearch/>

Opening a Case with JTAC

You can open a case with JTAC on the Web or by telephone.

- Use the Case Management tool in the CSC at <http://www.juniper.net/cm/> .
- Call 1-888-314-JTAC (1-888-314-5822 toll-free in the USA, Canada, and Mexico).

For international or direct-dial options in countries without toll-free numbers, see <http://www.juniper.net/support/requesting-support.html> .

PART 1

Overview

- [Introduction to ICMP Router Discovery on page 3](#)
- [ICMP Router Discovery Reference on page 5](#)

CHAPTER 1

Introduction to ICMP Router Discovery

- [ICMP Router Discovery Overview on page 3](#)

ICMP Router Discovery Overview

Router discovery uses Internet Control Message Protocol (ICMP) router advertisements and router solicitation messages to allow a host to discover the addresses of operational routers on the subnet. Hosts must discover routers before they can send IP datagrams outside their subnet.

Router discovery allows a host to discover the addresses of operational routers on the subnet. The Junos OS implementation of router discovery supports server mode only.

Each router periodically multicasts a router advertisement from each of its multicast interfaces, announcing the IP address of that interface. Hosts listen for advertisements to discover the addresses of their neighboring routers. When a host starts, it can send a multicast router solicitation to ask for immediate advertisements.

The router discovery messages do not constitute a routing protocol. They enable hosts to discover the existence of neighboring routers, but do not determine which router is best to reach a particular destination.

This section discusses the following topics:

- [Operation of a Router Discovery Server on page 3](#)
- [Router Advertisement Messages on page 4](#)

Operation of a Router Discovery Server

The router discovery server distributes information about the addresses of all routers on directly connected networks and about their preferences for becoming the default router. (A host sends a packet to the default router if the host does not have a route to a destination in its routing table.) The server does this by periodically sending router advertisement packets out each interface on which router discovery is enabled. In addition to containing the router addresses, these packets also announce the existence of the server itself.

The server can either transmit broadcast or multicast router advertisement packets. Multicast packets are sent to **224.0.0.1**, which is the all-hosts multicast address. When packets are sent to the all-hosts multicast address, or when an interface is configured

for the limited-broadcast address **255.255.255.255**, all IP addresses configured on the physical interface are included in the router advertisement. When the packets are being sent to a network or subnet broadcast address, only the address associated with that network or subnet is included in the router advertisement.

When the routing protocol process first starts on the server router, the server sends router advertisement packets every few seconds. Then, the server sends these packets less frequently, commonly every 10 minutes.

The server responds to route solicitation packets it receives from a client. The response is sent unicast unless a router advertisement packet is due to be sent out momentarily.



NOTE: The Junos OS does not support the ICMP router solicitation message with the source address as 0.0.0.0.

Router Advertisement Messages

Router advertisement messages include a preference level and a lifetime field for each advertised router address.

The preference level specifies the router's preference to become the default router. When a host chooses a default router address, it chooses the address with the highest preference. You can configure the preference level by including the **priority** statement as described in [OBSOLETE - Configuring the Addresses Included in ICMP Router Advertisements](#).

The lifetime field indicates the maximum length of time that the advertised addresses are to be considered valid by hosts in the absence of further advertisements. You can configure the advertising rate by including the **max-advertisement-interval** and **min-advertisement-interval** statements, and you can configure the lifetime by including the **lifetime** statement. For configuration instructions, see [OBSOLETE - Configuring the Frequency of ICMP Router Advertisements](#) and [OBSOLETE - Modifying the Lifetime in ICMP Router Advertisements](#).

CHAPTER 2

ICMP Router Discovery Reference

- [Supported ICMP and Neighbor Discovery Standards on page 5](#)

Supported ICMP and Neighbor Discovery Standards

The Junos OS substantially supports the following RFCs, which define standards for Internet Control Message Protocol (ICMP, for IP version 4 [IPv4]) and neighbor discovery (for IP version 6 [IPv6]).

- RFC 1256, *ICMP Router Discovery Messages*
- RFC 4861, *Neighbor Discovery for IP Version 6 (IPv6)*
- RFC 4862, *IPv6 Stateless Address Autoconfiguration*
- RFC 4443, *Internet Control Message Protocol (ICMPv6) for the Internet Protocol Version 6 (IPv6) Specification*

Related Documentation

- [Supported IPv4, TCP, and UDP Standards](#)
- [Supported IPv6 Standards](#)
- [Accessing Standards Documents on the Internet](#)

PART 2

Configuration

- [Concept and Example on page 9](#)
- [Configuration Statements on page 15](#)

CHAPTER 3

Concept and Example

- [Example: Configuring ICMP Router Discovery on page 9](#)

Example: Configuring ICMP Router Discovery

- [Understanding the ICMP Router Discovery Protocol on page 9](#)
- [Example: Configuring ICMP Router Discovery on page 9](#)

Understanding the ICMP Router Discovery Protocol

The ICMP Router Discovery Protocol (IRDP) enables hosts to locate routers on the local subnet and use them as a gateway to reach other networks. Junos OS supports running IRDP in server mode, meaning that router discovery packets are generated. Junos OS does not support IRDP in client mode running as a host sending router solicitation messages. IRDP is specified in RFC 1256, *ICMP Router Discovery Messages*.

For a host to participate on an internetwork, it needs connectivity to at least one router on the local network. One way to ensure that this is the case is to manually configure each host with the address of a local router as its default router (also called a *gateway*). This method is time-consuming to set up, difficult to maintain, and inflexible.

When you enable the Dynamic Host Configuration Protocol (DHCP) on a host, you do not need to configure the default router. DHCP uses a method called router discovery to automatically discover local routers, and learn other information about them.

The information provided includes the router's address (or addresses, if it has more than one) and how long the host should retain information about the router. Router advertisement messages are sent periodically. Hosts listen for these messages. When an advertisement is received, the host processes it and adds the information about the router to its routing table. A host that has no manually configured routing information has no connectivity to routers when it first powers on. Instead of waiting for the next Router Advertisement message, the host sends a router solicitation message on its local network. This prompts any router that receives this message to immediately send an extra router advertisement message directly to that host.

Example: Configuring ICMP Router Discovery

This example shows how to configure Internet Control Message Protocol (ICMP) router advertisements to allow IPv4 hosts to discover the addresses of operational routers on

the subnet. Hosts must discover routers before they can send IP datagrams outside their subnet.

- [Requirements on page 10](#)
- [Overview on page 10](#)
- [Configuration on page 11](#)
- [Verification on page 13](#)

Requirements

This example assumes that a server or a client computer on the local network supports RFC 1256, *ICMP Router Discovery Messages*.

Overview

Before a host is able to send a message to a host outside its own subnet, it must be able to identify the address of the immediate router. This is typically done through reading a configuration file upon startup, and on some multicast networks by listening to routing protocol traffic. When a server or a client computer on the local network that supports RFC 1256 needs to locate a default gateway (router), the server or client computer uses ICMP to send a router solicitation. Hosts that support RFC 1256 send an ICMP router discovery message on the multicast address 224.0.0.2. Routers on the local network that support RFC 1256 immediately respond with a router advertisement.

The all-routers IP multicast address, 224.0.0.2, is the local IP broadcast address that IPv4 reserved. IPv4 multicast addresses in the range 224.0.0.0/24 (from 224.0.0.0 to 224.0.0.255) are reserved for the local subnet.

The ICMP Router Discovery Protocol (IRDP) uses router advertisements as well as router solicitation messages to allow hosts to learn the IP addresses of the router that is attached to the immediate network. When a host is started, it sends router solicitation messages to check for the address of the immediate router.



NOTE: Not all hosts perform router discovery using the method specified in RFC 1256. If the host has DHCP enabled, it might not use ICMP router discovery. The performance of router discovery is one of the DHCP options that is defined in RFC 1541, *Dynamic Host Configuration Protocol*. This option specifies whether the client solicits routers using the ICMP router discovery method specified in RFC 1256. A value of 1 indicates that the client performs router discovery. A value of 0 indicates that the client does not.

To configure the router to be a router discovery server, you must include at least the following statement in the configuration. All other router discovery configuration statements are optional.


```
[edit]
protocols {
  router-discovery;
}
```


To configure a router as a server for ICMP router discovery, you can include the following statements in the configuration:

```
[edit]
protocols {
  router-discovery {
    disable;
    address address {
      (advertise | ignore);
      (broadcast | multicast);
      (ineligible | priority number);
    }
    interface interface-name {
      lifetime seconds;
      max-advertisement-interval seconds;
      min-advertisement-interval seconds;
    }
    traceoptions {
      file filename <files number> <size size> <world-readable | no-world-readable>;
      flag flag <detail> <disable>;
    }
  }
}
```

Figure 1 on page 11 shows a simplified sample topology.

Figure 1: ICMP Router Discovery Topology



Configuration

CLI Quick Configuration

To quickly configure this example, copy the following commands, paste them into a text file, remove any line breaks, change any details necessary to match your network configuration, and then copy and paste the commands into the CLI at the **[edit]** hierarchy level.

```
set interfaces ge-1/2/0 unit 6 description to-R2
set interfaces ge-1/2/0 unit 6 family inet address 10.0.0.6/24
```

```
set protocols router-discovery traceoptions file icmp-log
set protocols router-discovery traceoptions flag all
set protocols router-discovery interface ge-1/2/0.6 max-advertisement-interval 60
set protocols router-discovery interface ge-1/2/0.6 min-advertisement-interval 10
set protocols router-discovery interface ge-1/2/0.6 lifetime 120
set protocols router-discovery address 10.0.0.6 multicast
set protocols router-discovery address 10.0.0.6 priority 900
```

**Step-by-Step
Procedure**

The following example requires you to navigate various levels in the configuration hierarchy. For information about navigating the CLI, see *Using the CLI Editor in Configuration Mode* in the [Junos OS CLI User Guide](#).

To configure ICMP router discovery:

1. Configure the network interfaces.

This example shows multiple loopback interface addresses to simulate attached networks.

```
[edit interfaces]
user@R1# set ge-1/2/0 unit 6 description to-R2
user@R1# set ge-1/2/0 unit 6 family inet address 10.0.0.6/24
```

2. Enable router discovery.

```
[edit protocols]
user@R1# set router-discovery
```

3. (Optional) Enable trace operations for router discovery.

```
[edit protocols router-discovery]
user@R1# set traceoptions file icmp-log
user@R1# set traceoptions flag all
```

4. (Optional) Set the IRDP maximum interval between advertisements.

```
[edit protocols router-discovery]
user@R1# set interface ge-1/2/0.6 max-advertisement-interval 60
```

5. (Optional) Set the IRDP minimum interval between advertisements.

```
[edit protocols router-discovery]
user@R1# set interface ge-1/2/0.6 min-advertisement-interval 10
```

6. (Optional) Set the IRDP period for which advertisements are valid.

```
[edit protocols router-discovery]
user@R1# set interface ge-1/2/0.6 lifetime 120
```

7. (Optional) Configure the router to include the 10.0.0.6 IP address in IRDP advertisements to the all-hosts multicast address (224.0.0.1).

If the router supports IP multicast, and if the interface supports IP multicast, **multicast** is the default. Otherwise, the addresses are included in broadcast router advertisement packets.

```
[edit protocols router-discovery]
user@R1# set address 10.0.0.6 multicast
```

8. (Optional) Set the preference of the address to become a default router.

This preference is set relative to the preferences of other router addresses on the same subnet.

```
[edit protocols router-discovery]
user@R1# set address 10.0.0.6 priority 900
```

Results From configuration mode, confirm your configuration by entering the **show interfaces** and **show protocols** commands. If the output does not display the intended configuration, repeat the configuration instructions in this example to correct it.

```
user@R1# show interfaces
ge-1/2/0 {
  unit 6 {
    description to-R2;
    family inet {
      address 10.0.0.6/24;
    }
  }
}

user@R1# show protocols
router-discovery {
  traceoptions {
    file icmp-log;
    flag all;
  }
  interface ge-1/2/0.6 {
    max-advertisement-interval 60;
    min-advertisement-interval 10;
    lifetime 120;
  }
  address 10.0.0.6 {
    multicast;
    priority 900;
  }
}
```

If you are done configuring the device, enter **commit** from configuration mode.

Verification

Confirm that the configuration is working properly.

Checking the Trace Log

Purpose Verify that the expected interfaces are sending messages.

Action From operational mode, enter the **show log icmp-log** command.

```
user@R1> show log icmp-log
Mar 21 14:42:54 trace_on: Tracing to "/var/log/icmp-log" started
Mar 21 14:42:54.409027 rdisc_ifa_change: Preference for address
10.0.0.6(ge-1/2/0.6) set to 900
Mar 21 14:43:33.983695 task_timer_uset: timer RouterDiscoveryServer_Group <Touched
Processing> set to offset 22 at 14:43:16
Mar 21 14:43:33.984263 rdisc_server_timer: group ge-1/2/0.6 timer set to 22
```

```
Mar 21 14:43:55.985225 task_timer_uset: timer RouterDiscoveryServer_Group <Touched  
Processing> set to offset 37 at 14:44:10  
Mar 21 14:43:55.985520 rdisc_server_timer: group ge-1/2/0.6 timer set to 37  
Mar 21 14:44:32.986407 task_timer_uset: timer RouterDiscoveryServer_Group <Touched  
Processing> set to offset 39 at 14:44:44  
Mar 21 14:44:32.986961 rdisc_server_timer: group ge-1/2/0.6 timer set to 39  
Mar 21 14:45:11.987331 task_timer_uset: timer RouterDiscoveryServer_Group <Touched  
Processing> set to offset 10 at 14:44:42  
Mar 21 14:45:11.987888 rdisc_server_timer: group ge-1/2/0.6 timer set to 10  
Mar 21 14:45:21.990974 task_timer_uset: timer RouterDiscoveryServer_Group <Touched  
Processing> set to offset 23 at 14:45:34  
Mar 21 14:45:21.991548 rdisc_server_timer: group ge-1/2/0.6 timer set to 23  
Mar 21 14:45:44.992150 task_timer_uset: timer RouterDiscoveryServer_Group <Touched  
Processing> set to offset 45 at 14:46:06  
Mar 21 14:45:44.992710 rdisc_server_timer: group ge-1/2/0.6 timer set to 45
```

Meaning The log output shows that the preference was set to 900 for IP address 10.0.0.6 and that messages are being sent on the ge-1/2/0.6 interface.

Related Documentation

- [Example: Configuring Secure IPv6 Neighbor Discovery](#)

CHAPTER 4

Configuration Statements

- [\[edit protocols router-discovery\] Hierarchy Level](#) on page 15

[\[edit protocols router-discovery\] Hierarchy Level](#)

The following statement hierarchy can also be included at the [\[edit logical-systems *logical-system-name*\]](#) hierarchy level.

```
protocols {
  router-discovery {
    disable;
    address address {
      (advertise | ignore);
      (broadcast | multicast);
      (ineligible | priority number);
    }
    interface interface-name {
      lifetime seconds;
      min-advertisement-interval seconds;
      max-advertisement-interval seconds;
    }
    traceoptions {
      file filename <files number> <size maximum-file-size> <world-readable |
        no-world-readable>;
      flag flag;
    }
  }
}
```

Related Documentation

- Notational Conventions Used in Junos OS Configuration Hierarchies
- [\[edit protocols\] Hierarchy Level](#)

address

Syntax	address <i>address</i> { (advertise ignore); (broadcast multicast); (priority number ineligible); }
Hierarchy Level	[edit logical-systems <i>logical-system-name</i> protocols router-discovery], [edit protocols router-discovery]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	IP addresses to include in router advertisement packets.
Options	address —IP address. To specify more than one address, specify multiple addresses or include multiple address statements. The remaining statements are explained separately.
Required Privilege Level	routing—To view this statement in the configuration. routing-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• OBSOLETE - Configuring the Addresses Included in ICMP Router Advertisements

advertise

Syntax	(advertise ignore);
Hierarchy Level	[edit logical-systems <i>logical-system-name</i> protocols router-discovery address <i>address</i>], [edit protocols router-discovery address <i>address</i>]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	Specify whether the server should advertise the IP address in its router advertisement packets: <ul style="list-style-type: none">• advertise—Advertise the IP address in its router advertisement packets.• ignore—Do not advertise the IP addresses in router advertisement packets.
Default	advertise
Required Privilege Level	routing—To view this statement in the configuration. routing-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• OBSOLETE - Configuring the Addresses Included in ICMP Router Advertisements

broadcast

Syntax	(broadcast multicast);
Hierarchy Level	[edit logical-systems <i>logical-system-name</i> protocols router-discovery address address], [edit protocols router-discovery address address]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	Specify when the server should include the IP addresses in router advertisement packets. On the same physical interfaces, some addresses might be included only in multicast packets, while others might be included only in broadcast packets. If you specify broadcast , the server includes the addresses in router advertisement packets only if the packets are broadcast.
Default	multicast if the router supports IP multicast; broadcast if the router does not support IP multicast.
Required Privilege Level	routing—To view this statement in the configuration. routing-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none"> • multicast on page 22 • OBSOLETE - Configuring the Addresses Included in ICMP Router Advertisements

disable

Syntax	disable;
Hierarchy Level	[edit logical-systems <i>logical-system-name</i> protocols router-discovery], [edit protocols router-discovery]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	Disable router discovery.
Default	The configured object is enabled (operational) unless explicitly disabled.
Required Privilege Level	routing—To view this statement in the configuration. routing-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none"> • OBSOLETE - Minimum ICMP Router Discovery Configuration

ignore

See [advertise](#)

ineligible

See [priority](#)

interface

Syntax	<pre>interface <i>interface-name</i> { min-advertisement-interval <i>seconds</i>; max-advertisement-interval <i>seconds</i>; lifetime <i>seconds</i>; }</pre>
Hierarchy Level	[edit logical-systems <i>logical-system-name</i> protocols router-discovery], [edit protocols router-discovery]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	Specify physical interfaces on which to configure timers for router advertisement messages.
Options	<p><i>interface-name</i>—Name of an interface. Specify the full interface name, including the physical and logical address components. To configure all interfaces, specify all.</p> <p>The remaining statements are explained separately.</p>
Required Privilege Level	routing—To view this statement in the configuration. OBSOLETE - Configuring the Frequency of ICMP Router Advertisements
Related Documentation	<ul style="list-style-type: none">• OBSOLETE - Modifying the Lifetime in ICMP Router Advertisements

lifetime

Syntax	<code>lifetime seconds;</code>
Hierarchy Level	[edit logical-systems <i>logical-system-name</i> protocols router-discovery interface interface-name], [edit protocols router-discovery interface interface-name]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	How long the addresses sent by the server in its router advertisement packets are valid. This time must be long enough so that another router advertisement packet is sent before the lifetime has expired. The lifetime value is placed in the advertisement lifetime field of the router advertisement packet.
Options	<p>seconds—Lifetime value. A value of 0 indicates that one or more addresses are no longer valid.</p> <p>Range: Three times the value set by the max-advertisement-interval statement through 2 hours, 30 minutes (9000 seconds)</p> <p>Default: 1800 seconds (30 minutes, which is three times the default value for the max-advertisement-interval statement)</p>
Required Privilege Level	<p>routing—To view this statement in the configuration.</p> <p>routing-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none"> • max-advertisement-interval on page 20 • OBSOLETE - Modifying the Lifetime in ICMP Router Advertisements

max-advertisement-interval

Syntax	<code>max-advertisement-interval <i>seconds</i>;</code>
Hierarchy Level	[edit logical-systems <i>logical-system-name</i> protocols router-discovery interface <i>interface-name</i>], [edit protocols router-discovery interface <i>interface-name</i>]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	Maximum time the router waits before sending periodic router advertisement packets out the interface. These packets are broadcast or multicast, depending on how the address corresponding to this physical interface is configured.
Options	<i>seconds</i> —Maximum time between router advertisement packets. Range: 4 through 1800 seconds Default: 600 seconds (10 minutes)
Required Privilege Level	routing—To view this statement in the configuration. routing-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• broadcast on page 17• lifetime on page 19• min-advertisement-interval on page 21• multicast on page 22• OBSOLETE - Configuring the Frequency of ICMP Router Advertisements

min-advertisement-interval

Syntax	<code>min-advertisement-interval <i>seconds</i>;</code>
Hierarchy Level	[edit logical-systems <i>logical-system-name</i> protocols router-discovery interface <i>interface-name</i>], [edit protocols router-discovery interface <i>interface-name</i>]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	Minimum time the router waits before sending router advertisement packets out the interface in response to route solicitation packets it receives from a client. These packets are broadcast or multicast, depending on how the address corresponding to this physical interface is configured.
Options	<p><i>seconds</i>—Minimum time between router advertisement packets.</p> <p>Range: 3 seconds through 1800 seconds</p> <p>Default: 400 seconds (0.75 times the default value for the max-advertisement-interval statement)</p>
Required Privilege Level	<p>routing—To view this statement in the configuration.</p> <p>routing-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none"> • broadcast on page 17 • max-advertisement-interval on page 20 • multicast on page 22 • OBSOLETE - Configuring the Frequency of ICMP Router Advertisements

multicast

Syntax	(multicast broadcast);
Hierarchy Level	[edit logical-systems <i>logical-system-name</i> protocols router-discovery address address], [edit protocols router-discovery address address]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	<p>Specify when the server should include the IP addresses in router advertisement packets. On the same physical interfaces, some addresses might be included only in multicast packets, while others might be included only in broadcast packets.</p> <p>If you specify multicast, the server includes the addresses in router advertisement packets only if the packets are multicast. If the router supports IP multicast, and if the interface supports IP multicast, multicast is the default. Otherwise, the addresses are included in broadcast router advertisement packets. If the router does not support IP multicast, the addresses are not included.</p>
Default	multicast if the router supports IP multicast; broadcast if the router does not support IP multicast.
Required Privilege Level	routing—To view this statement in the configuration. routing-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• broadcast on page 17• OBSOLETE - Configuring the Addresses Included in ICMP Router Advertisements

priority

Syntax	<code>priority (<i>number</i> ineligible);</code>
Hierarchy Level	[edit logical-systems <i>logical-system-name</i> protocols router-discovery address address], [edit protocols router-discovery address address]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	Preference of the address to become a default router. This preference is set relative to the preferences of other router addresses on the same subnet.
Options	<p>ineligible—Address can never become the default router.</p> <p>priority <i>number</i>—Preference of the addresses for becoming the default router. A higher value indicates that the address has a greater preference for becoming the default router.</p> <p>Range: 0 through 0x80000000</p> <p>Default: 0 (This address has the least chance of becoming the default router.)</p>
Required Privilege Level	<p>routing—To view this statement in the configuration.</p> <p>routing-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none"> • OBSOLETE - Configuring the Addresses Included in ICMP Router Advertisements

router-discovery

Syntax	<code>router-discovery { ... }</code>
Hierarchy Level	[edit logical-systems <i>logical-system-name</i> protocols], [edit protocols]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	Enable ICMP router discovery (server mode) on the router.
Default	Router discovery is disabled on the router.
Required Privilege Level	<p>routing—To view this statement in the configuration.</p> <p>routing-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none"> • OBSOLETE - Minimum ICMP Router Discovery Configuration

traceoptions

Syntax	<pre>traceoptions { file <i>filename</i> <files <i>number</i>> <size <i>size</i>> <world-readable no-world-readable>; flag <i>flag</i> <flag-modifier> <disable>; }</pre>
Hierarchy Level	[edit logical-systems <i>logical-system-name</i> protocols router-discovery], [edit protocols router-discovery]
Release Information	Statement introduced before JUNOS Release 7.4.
Description	<p>Configure ICMP protocol-level tracing options.</p> <p>To specify more than one tracing operation, include multiple flag statements.</p>
Default	The default ICMP protocol-level tracing options are inherited from the routing protocols traceoptions statement included at the [edit routing-options] hierarchy level.
Options	<p>disable—(Optional) Disable the tracing operation. One use of this option is to disable a single operation when you have defined a broad group of tracing operations, such as all.</p> <p>file <i>filename</i>—Name of the file to receive the output of the tracing operation. Enclose the name within quotation marks. All files are placed in the directory /var/log. We recommend that you place ICMP tracing output in the file icmp-log.</p> <p>files <i>number</i>—(Optional) Maximum number of trace files. When a trace file named trace-file reaches its maximum size, it is renamed trace-file.0, then trace-file.1, and so on, until the maximum number of trace files is reached. Then, the oldest trace file is overwritten.</p> <p>If you specify a maximum number of files, you also must specify a maximum file size with the size option.</p> <p>Range: 2 through 1000 files</p> <p>Default: 2 files</p> <p>flag <i>flag</i>—Tracing operation to perform. To specify more than one tracing operation, include multiple flag statements. These are the ICMP-specific tracing options:</p> <ul style="list-style-type: none">• error—Errored ICMP packets• info—ICMP information packets• packets—All packets• router-discovery—All ICMP packets• redirect—ICMP redirect packets <p>These are the global tracing options:</p>

- **all**—All tracing operations
- **general**—A combination of the **normal** and **route** trace operations
- **normal**—All normal operations

Default: If you do not specify this option, only unusual or abnormal operations are traced.

- **policy**—Policy operations and actions
- **route**—Routing table changes
- **state**—State transitions
- **task**—Interface transactions and processing
- **timer**—Timer usage

flag-modifier—(Optional) Modifier for the tracing flag. You can specify one or more of these modifiers:

- **detail**—Provide detailed trace information
- **receive**—Packets being received
- **send**—Packets being transmitted

no-world-readable—(Optional) Prevent any user from reading the log file.

size size—(Optional) Maximum size of each trace file, in kilobytes (KB), megabytes (MB), or gigabytes (GB). When a trace file named **trace-file** reaches this size, it is renamed **trace-file.0**. When the **trace-file** again reaches its maximum size, **trace-file.0** is renamed **trace-file.1** and **trace-file** is renamed **trace-file.0**. This renaming scheme continues until the maximum number of trace files is reached. Then, the oldest trace file is overwritten.

If you specify a maximum file size, you also must specify a maximum number of trace files with the **files** option.

Syntax: **xk** to specify KB, **xm** to specify MB, or **xg** to specify GB

Range: 10 KB through the maximum file size supported on your system

Default: 1 MB

world-readable—(Optional) Allow any user to read the log file.

Required Privilege Level	routing and trace—To view this statement in the configuration. routing-control and trace-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none"> • OBSOLETE - Tracing ICMP Protocol Traffic

PART 3

Administration

- [Operational Commands on page 29](#)

CHAPTER 5

Operational Commands

monitor interface

Syntax `monitor interface`
`<interface-name> | traffic <detail>`

Release Information Command introduced before Junos OS Release 7.4.
 Command introduced in Junos OS Release 9.0 for EX Series switches.
 Command introduced in Junos OS Release 11.1 for the QFX Series.

Description Display real-time statistics about interfaces, updating the statistics every second. Check for and display common interface failures, such as SONET/SDH and T3 alarms, loopbacks detected, and increases in framing errors.



NOTE: This command is not supported on the QFX3000 QFabric switch.

Options **none**—Display real-time statistics for all interfaces.

interface-name—(Optional) Display real-time statistics for the specified interface. In a TX Matrix or TX Matrix Plus router, display real-time statistics for the physical interfaces on the specified line-card chassis (LCC) only.

traffic—(Optional) Display traffic data for all active interfaces. In a TX Matrix or TX Matrix Plus router, display real-time statistics for the physical interfaces on the specified LCC only.

detail—(Optional) With traffic option only, display detailed output.

Additional Information The output of this command shows how much each field has changed since you started the command or since you cleared the counters by using the **c** key. For a description of the statistical information provided in the output of this command, see the **show interfaces extensive** command for a particular interface type in the [Junos OS Interfaces Command Reference](#). To control the output of the **monitor interface interface-name** command while it is running, use the keys listed in [Table 3 on page 30](#). The keys are not case-sensitive.

Table 3: Output Control Keys for the monitor interface interface-name Command

Key	Action
c	Clears (returns to zero) the delta counters since monitor interface was started. This does not clear the accumulative counter. To clear the accumulative counter, use the clear interfaces interval command.
f	Freezes the display, halting the display of updated statistics and delta counters.
i	Displays information about a different interface. The command prompts you for the name of a specific interface.

Table 3: Output Control Keys for the monitor interface interface-name Command (*continued*)

Key	Action
n	Displays information about the next interface. The monitor interface command displays the physical or logical interfaces in the same order as the show interfaces terse command.
q or Esc	Quits the command and returns to the command prompt.
t	Thaws the display, resuming the update of the statistics and delta counters.

To control the output of the **monitor interface traffic** command while it is running, use the keys listed in [Table 4 on page 31](#). The keys are not case-sensitive.

Table 4: Output Control Keys for the monitor interface traffic Command

Key	Action
b	Displays the statistics in units of bytes and bytes per second (bps).
c	Clears (return to 0) the delta counters in the Current Delta column. The statistics counters are not cleared.
d	Displays the Current Delta column (instead of the rate column) in bps or packets per second (pps).
p	Displays the statistics in units of packets and packets per second (pps).
q or Esc	Quits the command and returns to the command prompt.
r	Displays the rate column (instead of the Current Delta column) in bps and pps.

Required Privilege Level trace

List of Sample Output [monitor interface \(Physical\) on page 33](#)
[monitor interface \(OTN Interface\) on page 35](#)
[monitor interface \(Logical\) on page 36](#)
[monitor interface traffic on page 36](#)
[monitor interface \(QFX3500 Switch\) on page 37](#)
[monitor interface traffic on page 37](#)
[monitor interface traffic \(QFX3500 Switch\) on page 37](#)
[monitor interface traffic detail \(QFX3500 Switch\) on page 38](#)

Output Fields [Table 5 on page 32](#) describes the output fields for the **monitor interface** command. Output fields are listed in the approximate order in which they appear.

Table 5: monitor interface Output Fields

Field Name	Field Description	Level of Output
routerl	Hostname of the router.	All levels
Seconds	How long the monitor interface command has been running or how long since you last cleared the counters.	All levels
Time	Current time (UTC).	All levels
Delay x/y/z	Time difference between when the statistics were displayed and the actual clock time. <ul style="list-style-type: none"> • x—Time taken for the last polling (in milliseconds). • y—Minimum time taken across all pollings (in milliseconds). • z—Maximum time taken across all pollings (in milliseconds). 	All levels
Interface	Short description of the interface, including its name, status, and encapsulation.	All levels
Link	State of the link: Up , Down , or Test .	All levels
Current delta	Cumulative number for the counter in question since the time shown in the Seconds field, which is the time since you started the command or last cleared the counters.	All levels
Local Statistics	(Logical interfaces only) Number and rate of bytes and packets destined to the router or switch through the specified interface. When a burst of traffic is received, the value in the output packet rate field might briefly exceed the peak cell rate. It takes awhile (generally, less than 1 second) for this counter to stabilize.: <ul style="list-style-type: none"> • Input bytes—Number of bytes received on the interface. • Output bytes—Number of bytes transmitted on the interface. • Input packets—Number of packets received on the interface. • Output packets—Number of packets transmitted on the interface. 	All levels
Remote Statistics	(Logical interfaces only) Statistics for traffic transiting the router or switch. When a burst of traffic is received, the value in the output packet rate field might briefly exceed the peak cell rate. It takes awhile (generally, less than 1 second) for this counter to stabilize.: <ul style="list-style-type: none"> • Input bytes—Number of bytes received on the interface. • Output bytes—Number of bytes transmitted on the interface. • Input packets—Number of packets received on the interface. • Output packets—Number of packets transmitted on the interface. 	All levels

Table 5: monitor interface Output Fields (*continued*)

Field Name	Field Description	Level of Output
Traffic statistics	<p>Total number of bytes and packets received and transmitted on the interface. These statistics are the sum of the local and remote statistics. When a burst of traffic is received, the value in the output packet rate field might briefly exceed the peak cell rate. It takes awhile (generally, less than 1 second) for this counter to stabilize.</p> <ul style="list-style-type: none"> • Input bytes—Number of bytes received on the interface. • Output bytes—Number of bytes transmitted on the interface. • Input packets—Number of packets received on the interface. • Output packets—Number of packets transmitted on the interface. 	All levels
Description	With the traffic option, displays the interface description configured at the [edit interfaces <i>interface-name</i>] hierarchy level.	detail

Sample Output

```

monitor interface user@host> monitor interface so-0/0/0
(Physical) router1 Seconds: 19 Time: 15:46:29

Interface: so-0/0/0, Enabled, Link is Up
Encapsulation: PPP, Keepalives, Speed: 0C48
Traffic statistics: Current Delta
  Input packets: 6045 (0 pps) [11]
  Input bytes: 6290065 (0 bps) [13882]
  Output packets: 10376 (0 pps) [10]
  Output bytes: 10365540 (0 bps) [9418]
Encapsulation statistics:
  Input keepalives: 1901 [2]
  Output keepalives: 1901 [2]
  NCP state: Opened
  LCP state: Opened
Error statistics:
  Input errors: 0 [0]
  Input drops: 0 [0]
  Input framing errors: 0 [0]
  Policed discards: 0 [0]
  L3 incompletes: 0 [0]
  L2 channel errors: 0 [0]
  L2 mismatch timeouts: 0 [0]
  Carrier transitions: 1 [0]
  Output errors: 0 [0]
  Output drops: 0 [0]
  Aged packets: 0 [0]
Active alarms : None
Active defects: None
SONET error counts/seconds:
  LOS count 1 [0]
  LOF count 1 [0]
  SEF count 1 [0]
  ES-S 0 [0]
  SES-S 0 [0]
SONET statistics:
  BIP-B1 458871 [0]
  BIP-B2 460072 [0]

```

REI-L	465610	[0]
BIP-B3	458978	[0]
REI-P	458773	[0]


```

Received SONET overhead:
  F1      : 0x00  J0      : 0x00  K1      : 0x00
  K2      : 0x00  S1      : 0x00  C2      : 0x00
  C2(cmp) : 0x00  F2      : 0x00  Z3      : 0x00
  Z4      : 0x00  S1(cmp) : 0x00
Transmitted SONET overhead:
  F1      : 0x00  J0      : 0x01  K1      : 0x00
  K2      : 0x00  S1      : 0x00  C2      : 0xcf
  F2      : 0x00  Z3      : 0x00  Z4      : 0x00

```

Next='n', Quit='q' or ESC, Freeze='f', Thaw='t', Clear='c', Interface='i'

monitor interface (OTN Interface)

```
user@host> monitor interface ge-7/0/0
```

```

Interface: ge-7/0/0, Enabled, Link is Up
Encapsulation: Ethernet, Speed: 10000mbps
Traffic statistics:
  Input bytes:                0 (0 bps)
  Output bytes:               0 (0 bps)
  Input packets:              0 (0 pps)
  Output packets:             0 (0 pps)
Error statistics:
  Input errors:                0
  Input drops:                 0
  Input framing errors:        0
  Policed discards:           0
  L3 incompletes:              0
  L2 channel errors:           0
  L2 mismatch timeouts:        0
  Carrier transitions:         5
  Output errors:               0
  Output drops:                0
  Aged packets:                0
Active alarms : None
Active defects: None
Input MAC/Filter statistics:
  Unicast packets              0
  Broadcast packets            0
  Multicast packets            0
  Oversized frames             0
  Packet reject count          0
  DA rejects                   0
  SA rejects                   0
Output MAC/Filter Statistics:
  Unicast packets              0
  Broadcast packets            0
  Multicast packets            0
  Packet pad count             0
  Packet error count           0
OTN Link 0
  OTN Alarms: OTU_BDI, OTU_TTIM, ODU_BDI
  OTN Defects: OTU_BDI, OTU_TTIM, ODU_BDI, ODU_TTIM
  OTN OC - Seconds
    LOS                        2
    LOF                        9
  OTN OTU - FEC Statistics
    Corr err ratio             N/A
    Corr bytes                  0
    Uncorr words                0
  OTN OTU - Counters

```

```

BIP                                0
BBE                                0
ES                                 0
SES                                0
UAS                                422
OTN ODU - Counters
BIP                                0
BBE                                0
ES                                 0
SES                                0
UAS                                422
OTN ODU - Received Overhead      APSPCC 0-3:          0

```

```

monitor interface user@host> monitor interface so-1/0/0.0
(Logical)         host name                Seconds: 16                Time: 15:33:39
                                                Delay: 0/0/1

Interface: so-1/0/0.0, Enabled, Link is Down
Flags: Hardware-Down Point-To-Point SNMP-Traps
Encapsulation: PPP
Local statistics:
Input bytes:                0                                Current delta [0]
Output bytes:               0                                [0]
Input packets:              0                                [0]
Output packets:             0                                [0]
Remote statistics:
Input bytes:                0 (0 bps)                       [0]
Output bytes:               0 (0 bps)                       [0]
Input packets:              0 (0 pps)                       [0]
Output packets:             0 (0 pps)                       [0]
Traffic statistics:
Destination address: 192.168.8.193, Local: 192.168.8.21

Next='n', Quit='q' or ESC, Freeze='f', Thaw='t', Clear='c', Interface='i'

```

```

monitor interface user@host> monitor interface traffic
traffic          host name                Seconds: 15                Time: 12:31:09

Interface  Link  Input packets  (pps)  Output packets  (pps)
so-1/0/0   Down    0              (0)    0              (0)
so-1/1/0   Down    0              (0)    0              (0)
so-1/1/1   Down    0              (0)    0              (0)
so-1/1/2   Down    0              (0)    0              (0)
so-1/1/3   Down    0              (0)    0              (0)
t3-1/2/0   Down    0              (0)    0              (0)
t3-1/2/1   Down    0              (0)    0              (0)
t3-1/2/2   Down    0              (0)    0              (0)
t3-1/2/3   Down    0              (0)    0              (0)
so-2/0/0   Up      211035         (1)    36778          (0)
so-2/0/1   Up      192753         (1)    36782          (0)
so-2/0/2   Up      211020         (1)    36779          (0)
so-2/0/3   Up      211029         (1)    36776          (0)
so-2/1/0   Up      189378         (1)    36349          (0)
so-2/1/1   Down    0              (0)    18747          (0)
so-2/1/2   Down    0              (0)    16078          (0)
so-2/1/3   Up      0              (0)    80338          (0)
at-2/3/0   Up      0              (0)    0              (0)
at-2/3/1   Down    0              (0)    0              (0)

Bytes=b, Clear=c, Delta=d, Packets=p, Quit=q or ESC, Rate=r, Up=^U, Down=^D

```

```

monitor interface user@switch> monitor interface ge-0/0/0
(QFX3500 Switch) Interface: ge-0/0/0, Enabled, Link is Down
Encapsulation: Ethernet, Speed: Unspecified
Traffic statistics:
    Input bytes: 0 (0 bps)
    Output bytes: 0 (0 bps)
    Input packets: 0 (0 pps)
    Output packets: 0 (0 pps)
Error statistics:
    Input errors: 0
    Input drops: 0
    Input framing errors: 0
    Policed discards: 0
    L3 incompletes: 0
    L2 channel errors: 0
    L2 mismatch timeouts: 0
    Carrier transitions: 0
    Output errors: 0
    Output drops: 0
    Aged packets: 0
Active alarms : LINK
Active defects: LINK
Input MAC/Filter statistics:
    Unicast packets 0
    Broadcast packets 0 Multicast packet
Interface warnings:
    o Outstanding LINK alarm

```

```

monitor interface user@host> monitor interface traffic
traffic host name Seconds: 15 Time: 12:31:09

Interface Link Input packets (pps) Output packets (pps)
so-1/0/0 Down 0 (0) 0 (0)
so-1/1/0 Down 0 (0) 0 (0)
so-1/1/1 Down 0 (0) 0 (0)
so-1/1/2 Down 0 (0) 0 (0)
so-1/1/3 Down 0 (0) 0 (0)
t3-1/2/0 Down 0 (0) 0 (0)
t3-1/2/1 Down 0 (0) 0 (0)
t3-1/2/2 Down 0 (0) 0 (0)
t3-1/2/3 Down 0 (0) 0 (0)
so-2/0/0 Up 211035 (1) 36778 (0)
so-2/0/1 Up 192753 (1) 36782 (0)
so-2/0/2 Up 211020 (1) 36779 (0)
so-2/0/3 Up 211029 (1) 36776 (0)
so-2/1/0 Up 189378 (1) 36349 (0)
so-2/1/1 Down 0 (0) 18747 (0)
so-2/1/2 Down 0 (0) 16078 (0)
so-2/1/3 Up 0 (0) 80338 (0)
at-2/3/0 Up 0 (0) 0 (0)
at-2/3/1 Down 0 (0) 0 (0)

Bytes=b, Clear=c, Delta=d, Packets=p, Quit=q or ESC, Rate=r, Up=^U, Down=^D

```

```

monitor interface user@switch> monitor interface traffic
traffic (QFX3500 switch Seconds: 7 Time: 16:04:37

Interface Link Input packets (pps) Output packets (pps)
ge-0/0/0 Down 0 (0) 0 (0)

```

ge-0/0/1	Up	392187	(0)	392170	(0)
ge-0/0/2	Down	0	(0)	0	(0)
ge-0/0/3	Down	0	(0)	0	(0)
ge-0/0/4	Down	0	(0)	0	(0)
ge-0/0/5	Down	0	(0)	0	(0)
ge-0/0/6	Down	0	(0)	0	(0)
ge-0/0/7	Down	0	(0)	0	(0)
ge-0/0/8	Down	0	(0)	0	(0)
ge-0/0/9	Up	392184	(0)	392171	(0)
ge-0/0/10	Down	0	(0)	0	(0)
ge-0/0/11	Down	0	(0)	0	(0)
ge-0/0/12	Down	0	(0)	0	(0)
ge-0/0/13	Down	0	(0)	0	(0)
ge-0/0/14	Down	0	(0)	0	(0)
ge-0/0/15	Down	0	(0)	0	(0)
ge-0/0/16	Down	0	(0)	0	(0)
ge-0/0/17	Down	0	(0)	0	(0)
ge-0/0/18	Down	0	(0)	0	(0)
ge-0/0/19	Down	0	(0)	0	(0)
ge-0/0/20	Down	0	(0)	0	(0)
ge-0/0/21	Down	0	(0)	0	(0)
ge-0/0/22	Up	392172	(0)	392187	(0)
ge-0/0/23	Up	392185	(0)	392173	(0)
vcp-0	Down	0		0	
vcp-1	Down	0		0	
ae0	Down	0	(0)	0	(0)
bme0	Up	0		1568706	

monitor interface traffic detail
(QFX3500 Switch)

user@switch> **monitor interface traffic detail**
switch

Time: 16:03:02

Seconds: 74

Interface Description	Link	Input packets	(pps)	Output packets	(pps)
ge-0/0/0	Down	0	(0)	0	(0)
ge-0/0/1	Up	392183	(0)	392166	(0)
ge-0/0/2	Down	0	(0)	0	(0)
ge-0/0/3	Down	0	(0)	0	(0)
ge-0/0/4	Down	0	(0)	0	(0)
ge-0/0/5	Down	0	(0)	0	(0)
ge-0/0/6	Down	0	(0)	0	(0)
ge-0/0/7	Down	0	(0)	0	(0)
ge-0/0/8	Down	0	(0)	0	(0)
ge-0/0/9	Up	392181	(0)	392168	(0)
ge-0/0/10	Down	0	(0)	0	(0)
ge-0/0/11	Down	0	(0)	0	(0)
ge-0/0/12	Down	0	(0)	0	(0)
ge-0/0/13	Down	0	(0)	0	(0)
ge-0/0/14	Down	0	(0)	0	(0)
ge-0/0/15	Down	0	(0)	0	(0)
ge-0/0/16	Down	0	(0)	0	(0)
ge-0/0/17	Down	0	(0)	0	(0)
ge-0/0/18	Down	0	(0)	0	(0)
ge-0/0/19	Down	0	(0)	0	(0)
ge-0/0/20	Down	0	(0)	0	(0)
ge-0/0/21	Down	0	(0)	0	(0)
ge-0/0/22	Up	392169	(0)	392184	(1)
ge-0/0/23	Up	392182	(0)	392170	(0)
vcp-0	Down	0		0	
vcp-1	Down	0		0	

ae0	Down	0	(0)	0	(0)
bme0	Up	0		1568693	

monitor start

Syntax	<code>monitor start <i>filename</i></code>
Release Information	Command introduced before Junos OS Release 7.4. Command introduced in Junos OS Release 9.0 for EX Series switches.
Description	Start displaying the system log or trace file and additional entries being added to those files.
Options	<i>filename</i> —Specific log or trace file.
Additional Information	Log files are generated by the routing protocol process or by system logging. The log files generated by system logging are configured with the syslog statement at the [edit system] hierarchy level and the options statement at the [edit routing-options] hierarchy level. The trace files generated by the routing protocol process are configured with traceoptions statements at the [edit routing-options] , [edit interfaces] , and [edit protocols protocol] hierarchy levels.



NOTE: To monitor a log file within a logical system, issue the `monitor start logical-system-name/filename` command.

Required Privilege Level	trace
Related Documentation	<ul style="list-style-type: none"> monitor list monitor stop on page 42
List of Sample Output	monitor start on page 40
Output Fields	Table 6 on page 40 describes the output fields for the monitor start command. Output fields are listed in the approximate order in which they appear.

Table 6: monitor start Output Fields

Field Name	Field Description
<i>filename</i>	Name of the file from which entries are being displayed. This line is displayed initially and when the command switches between log files.
<i>Date and time</i>	Timestamp for the log entry.

Sample Output

```
monitor start user@host> monitor start system-log
```

```
*** system-log***
Jul 20 15:07:34 hang sshd[5845]: log: Generating 768 bit RSA key.
Jul 20 15:07:35 hang sshd[5845]: log: RSA key generation complete.
Jul 20 15:07:35 hang sshd[5845]: log: Connection from 204.69.248.180 port 912
Jul 20 15:07:37 hang sshd[5845]: log: RSA authentication for root accepted.
Jul 20 15:07:37 hang sshd[5845]: log: ROOT LOGIN as 'root' from trip.jcmax.com
Jul 20 15:07:37 hang sshd[5845]: log: Closing connection to 204.69.248.180
```

monitor stop

Syntax	<code>monitor stop <i>filename</i></code>
Release Information	Command introduced before Junos OS Release 7.4. Command introduced in Junos OS Release 9.0 for EX Series switches.
Description	Stop displaying the system log or trace file.
Options	<i>filename</i> —Specific log or trace file.
Additional Information	Log files are generated by the routing protocol process or by system logging. The log files generated by system logging are those configured with the syslog statement at the [edit system] hierarchy level and the options statement at the [edit routing-options] hierarchy level. The trace files generated by the routing protocol process are those configured with traceoptions statements at the [edit routing-options] , [edit interfaces] , and [edit protocols <i>protocol</i>] hierarchy levels.
Required Privilege Level	trace
Related Documentation	<ul style="list-style-type: none">• monitor list• monitor start on page 40
List of Sample Output	monitor stop on page 42
Output Fields	This command produces no output.

Sample Output

monitor stop user@host> monitor stop

ping

Syntax `ping host`
 <bypass-routing>
 <count *requests*>
 <detail>
 <do-not-fragment>
 <inet | inet6>
 <interface *source-interface*>
 <interval *seconds*>
 <logical-system (all | *logical-system-name*)>
 <loose-source *value*>
 <no-resolve>
 <pattern *string*>
 <rapid>
 <record-route>
 <routing-instance *routing-instance-name*>
 <size *bytes*>
 <source *source-address*>
 <strict >
 <strict-source *value*.>
 <tos *type-of-service*>
 <ttl *value*>
 <verbose>
 <wait *seconds*>

Syntax (QFX Series) `ping host`
 <bypass-routing>
 <count *requests*>
 <detail>
 <do-not-fragment>
 <inet>
 <interface *source-interface*>
 <interval *seconds*>
 <loose-source *value*>
 <mac-address *mac-address*>
 <no-resolve>
 <pattern *string*>
 <rapid>
 <record-route>
 <routing-instance *routing-instance-name*>
 <size *bytes*>
 <source *source-address*>
 <strict>
 <strict-source *value*>
 <tos *type-of-service*>
 <ttl *value*>
 <verbose>
 <wait *seconds*>

Release Information Command introduced before Junos OS Release 7.4.
 Command introduced in Junos OS Release 9.0 for EX Series switches.
 Command introduced in Junos OS Release 11.1 for the QFX Series.

Description Check host reachability and network connectivity. The **ping** command sends Internet Control Message Protocol (ICMP) ECHO_REQUEST messages to elicit ICMP ECHO_RESPONSE messages from the specified host. Type Ctrl+c to interrupt a ping command.

Options **host**—IP address or hostname of the remote system to ping.

bypass-routing—(Optional) Bypass the normal routing tables and send ping requests directly to a system on an attached network. If the system is not on a directly attached network, an error is returned. Use this option to ping a local system through an interface that has no route through it.

count requests—(Optional) Number of ping requests to send. The range of values is 1 through 2,000,000,000. The default value is an unlimited number of requests.

detail—(Optional) Include in the output the interface on which the ping reply was received.

do-not-fragment—(Optional) Set the do-not-fragment (DF) flag in the IP header of the ping packets. For IPv6 packets, this option disables fragmentation.



NOTE: In Junos OS Release 11.1 and later, when issuing the **ping** command for an IPv6 route with the **do-not-fragment** option, the maximum ping packet size is calculated by subtracting 48 bytes (40 bytes for the IPV6 header and 8 bytes for the ICMP header) from the MTU. Therefore, if the ping packet size (including the 48-byte header) is greater than the MTU, the ping operation might fail.

inet—(Optional) Ping Packet Forwarding Engine IPv4 routes.

inet6—(Optional) Ping Packet Forwarding Engine IPv6 routes.

interface source-interface—(Optional) Interface to use to send the ping requests.

interval seconds—(Optional) How often to send ping requests. The range of values, in seconds, is 1 through infinity. The default value is 1.

loose-source value—(Optional) Intermediate loose source route entry (IPv4). Open a set of values.

mac-address mac-address—(Optional) Ping the physical or hardware address of the remote system you are trying to reach.

no-resolve—(Optional) Do not attempt to determine the hostname that corresponds to the IP address.

pattern string—(Optional) Specify a hexadecimal fill pattern to include in the ping packet.

rapid—(Optional) Send ping requests rapidly. The results are reported in a single message, not in individual messages for each ping request. By default, five ping requests are

sent before the results are reported. To change the number of requests, include the count option.

record-route—(Optional) Record and report the packet's path (IPv4).

routing-instance *routing-instance-name*—(Optional) Name of the routing instance for the ping attempt.

size *bytes*—(Optional) Size of ping request packets. The range of values, in bytes, is 0 through 65,468. The default value is 56, which is effectively 64 bytes because 8 bytes of ICMP header data are added to the packet.

source *source-address*—(Optional) IP address of the outgoing interface. This address is sent in the IP source address field of the ping request. If this option is not specified, the default address is usually the loopback interface (lo.0).

strict—(Optional) Use the strict source route option (IPv4).

strict-source *value*—(Optional) Intermediate strict source route entry (IPv4). Open a set of values.

tos *type-of-service*—(Optional) Set the type-of-service (ToS) field in the IP header of the ping packets. The range of values is 0 through 255.

ttl *value*—(Optional) Time-to-live (TTL) value to include in the ping request (IPv6). The range of values is 0 through 255.

verbose—(Optional) Display detailed output.

vpls *instance-name*—(Optional) Ping the instance to which this VPLS belongs.

wait *seconds*—(Optional) Maximum wait time, in seconds, after the final packet is sent. If this option is not specified, the default delay is 10 seconds. If this option is used without the count option, a default count of 5 packets is used.

Required Privilege Level

network

Related Documentation

- Configuring the Junos OS ICMPv4 Rate Limit for ICMPv4 Routing Engine Messages

List of Sample Output

[ping hostname on page 46](#)
[ping hostname size count on page 46](#)
[ping hostname rapid on page 46](#)

Output Fields

When you enter this command, you are provided feedback on the status of your request. An exclamation point (!) indicates that an echo reply was received. A period (.) indicates that an echo reply was not received within the timeout period. An x indicates that an echo reply was received with an error code. These packets are not counted in the received packets count. They are accounted for separately.

Sample Output

```
ping hostname      user@host> ping skye
PING skye.net (192.168.169.254): 56 data bytes
64 bytes from 192.168.169.254: icmp_seq=0 ttl=253 time=1.028 ms
64 bytes from 192.168.169.254: icmp_seq=1 ttl=253 time=1.053 ms
64 bytes from 192.168.169.254: icmp_seq=2 ttl=253 time=1.025 ms
64 bytes from 192.168.169.254: icmp_seq=3 ttl=253 time=1.098 ms
64 bytes from 192.168.169.254: icmp_seq=4 ttl=253 time=1.032 ms
64 bytes from 192.168.169.254: icmp_seq=5 ttl=253 time=1.044 ms
^C [abort]

ping hostname      user@host> ping skye size 200 count 5
size count        PING skye.net (192.168.169.254): 200 data bytes
208 bytes from 192.168.169.254: icmp_seq=0 ttl=253 time=1.759 ms
208 bytes from 192.168.169.254: icmp_seq=1 ttl=253 time=2.075 ms
208 bytes from 192.168.169.254: icmp_seq=2 ttl=253 time=1.843 ms
208 bytes from 192.168.169.254: icmp_seq=3 ttl=253 time=1.803 ms
208 bytes from 192.168.169.254: icmp_seq=4 ttl=253 time=17.898 ms

--- skye.net ping statistics ---
5 packets transmitted, 5 packets received, 0% packet loss
round-trip min/avg/max = 1.759/5.075/17.898 ms

ping hostname rapid user@host> ping skye rapid
PING skye.net (192.168.169.254): 56 data bytes
!!!!
--- skye.net ping statistics ---
5 packets transmitted, 5 packets received, 0% packet loss
round-trip min/avg/max/stddev = 0.956/0.974/1.025/0.026 ms
```

show log

Syntax	<code>show log</code> <code><filename user <username>></code>
Syntax (TX Matrix Router)	<code>show log</code> <code><all-lcc lcc <i>number</i> scc></code> <code><filename user <username>></code>
Release Information	Command introduced before Junos OS Release 7.4. Command introduced in Junos OS Release 9.0 for EX Series switches. Command introduced in Junos OS Release 11.1 for the QFX Series.
Description	List log files, display log file contents, or display information about users who have logged in to the router or switch.
Options	<p>none—List all log files.</p> <p><all-lcc lcc <i>number</i> scc>—(Routing matrix only) (Optional) Display logging information about all T640 routers (or line-card chassis) or a specific T640 router (replace <i>number</i> with a value from 0 through 3) connected to a TX Matrix router. Or, display logging information about the TX Matrix router (or switch-card chassis).</p> <p><i>filename</i>—(Optional) Display the log messages in the specified log file. For the routing matrix, the filename must include the chassis information.</p> <p>user <username>—(Optional) Display logging information about users who have recently logged in to the router or switch. If you include <i>username</i>, display logging information about the specified user.</p>
Required Privilege Level	trace
List of Sample Output	show log on page 47 show log filename on page 48 show log user on page 48

Sample Output

```

user@host> show log
total 57518
-rw-r--r--  1 root  bin      211663 Oct  1 19:44 dcd
-rw-r--r--  1 root  bin      999947 Oct  1 19:41 dcd.0
-rw-r--r--  1 root  bin      999994 Oct  1 17:48 dcd.1
-rw-r--r--  1 root  bin      238815 Oct  1 19:44 rpd
-rw-r--r--  1 root  bin     1049098 Oct  1 18:00 rpd.0
-rw-r--r--  1 root  bin     1061095 Oct  1 12:13 rpd.1
-rw-r--r--  1 root  bin     1052026 Oct  1 06:08 rpd.2
-rw-r--r--  1 root  bin     1056309 Sep 30 18:21 rpd.3
-rw-r--r--  1 root  bin     1056371 Sep 30 14:36 rpd.4
-rw-r--r--  1 root  bin     1056301 Sep 30 10:50 rpd.5
-rw-r--r--  1 root  bin     1056350 Sep 30 07:04 rpd.6

```

```
-rw-r--r-- 1 root bin      1048876 Sep 30 03:21 rpd.7
-rw-rw-r-- 1 root bin      19656 Oct  1 19:37 wtmp
```

```
show log filename user@host> show log rpd
Oct  1 18:00:18 trace_on: Tracing to ?/var/log/rpd? started
Oct  1 18:00:18 EVENT <MTU> ds-5/2/0.0 index 24 <Broadcast PointToPoint Multicast
Oct  1 18:00:18
Oct  1 18:00:19 KRT rcv len 56 V9 seq 148 op add Type route/if af 2 addr
13.13.13.21 nhop type local nhop 13.13.13.21
Oct  1 18:00:19 KRT rcv len 56 V9 seq 149 op add Type route/if af 2 addr
13.13.13.22 nhop type unicast nhop 13.13.13.22
Oct  1 18:00:19 KRT rcv len 48 V9 seq 150 op add Type ifaddr index 24 devindex
43
Oct  1 18:00:19 KRT rcv len 144 V9 seq 151 op chnge Type ifdev devindex 44
Oct  1 18:00:19 KRT rcv len 144 V9 seq 152 op chnge Type ifdev devindex 45
Oct  1 18:00:19 KRT rcv len 144 V9 seq 153 op chnge Type ifdev devindex 46
Oct  1 18:00:19 KRT rcv len 1272 V9 seq 154 op chnge Type ifdev devindex 47
...
```

```
show log user user@host> show log user
darius mg2546 Thu Oct  1 19:37 still logged in
darius mg2529 Thu Oct  1 19:08 - 19:36 (00:28)
darius mg2518 Thu Oct  1 18:53 - 18:58 (00:04)
root mg1575 Wed Sep 30 18:39 - 18:41 (00:02)
root ttyt2 jun.site.per Wed Sep 30 18:39 - 18:41 (00:02)
alex ttyt1 192.168.1.2 Wed Sep 30 01:03 - 01:22 (00:19)
```

traceroute

Syntax	<pre>traceroute <i>host</i> <as-number-lookup> <bypass-routing> <clns> <gateway address> <inet inet6> <interface <i>interface-name</i>> <logical system (<i>all</i> <i>logical-system-name</i>)> <mpls (<i>ldp FEC address</i> <i>rsvp label-switched-path-name</i>)> <no-resolve> <propagate-ttl> <routing-instance <i>routing-instance-name</i>> <source <i>source-address</i>> <tos <i>value</i>> <ttl <i>value</i>> <wait <i>seconds</i>></pre>
Syntax (QFX Series)	<pre>traceroute <i>host</i> <as-number-lookup> <bypass-routing> <gateway address> <inet> <interface <i>interface-name</i>> <monitor <i>host</i>> <no-resolve> <routing-instance <i>routing-instance-name</i>> <source <i>source-address</i>> <tos <i>value</i>> <ttl <i>value</i>> <wait <i>seconds</i>></pre>
Release Information	<p>Command introduced before Junos OS Release 7.4.</p> <p>Command introduced in Junos OS Release 9.0 for EX Series switches.</p> <p>mpls option introduced in Junos OS Release 9.2.</p> <p>propagate-ttl option introduced in Junos OS Release 12.1.</p> <p>Command introduced in Junos OS Release 11.1 for the QFX Series.</p>
Description	<p>Display the route that packets take to a specified network host. Use traceroute as a debugging tool to locate points of failure in a network.</p>
Options	<p>host—IP address or name of remote host.</p> <p>as-number-lookup—(Optional) Display the autonomous system (AS) number of each intermediate hop on the path from the host to the destination.</p> <p>bypass-routing—(Optional) Bypass the normal routing tables and send requests directly to a system on an attached network. If the system is not on a directly attached network, an error is returned. Use this option to display a route to a local system through an interface that has no route through it.</p>

clns—(Optional) Trace the route belonging to Connectionless Network Service (CLNS).

gateway address—(Optional) Address of a router or switch through which the route transits.

inet | inet6—(Optional) Trace the route belonging to IPv4 or IPv6, respectively.

interface *interface-name*—(Optional) Name of the interface over which to send packets.

logical-system (all | *logical-system-name*)—(Optional) Perform this operation on all logical systems or on a particular logical system.

monitor *host*—(Optional) Display real-time monitoring information for the specified host.

monitor *host*—(Optional) Perform this operation to display real-time monitoring information.

monitor *host*—(Optional) Perform this operation to display real-time monitoring information.

mpls (ldp *FEC address* | rsvp *label-switched-path name*)—(Optional) See traceroute mpls ldp and traceroute mpls rsvp.

no-resolve—(Optional) Do not attempt to determine the hostname that corresponds to the IP address.

propagate-ttl—(Optional) On the PE router, use this option to view locally-generated Routing Engine transit traffic. This is applicable for MPLS L3VPN traffic only. Use for troubleshooting, when you want to view hop-by-hop information from the local provider router to the remote provider router, when TTL decrementing is disabled on the core network using the **no-propagate-ttl** configuration statement.



NOTE: Using **propagate-ttl** with **traceroute** on the CE router does not show hop-by-hop information.

routing-instance *routing-instance-name*—(Optional) Name of the routing instance for the traceroute attempt.

source *source-address*—(Optional) Source address of the outgoing traceroute packets.

tos *value*—(Optional) Value to include in the IP type-of-service (ToS) field. The range of values is 0 through 255.

ttl *value*—(Optional) Maximum time-to-live value to include in the traceroute request. The range of values is 0 through 128.

wait *seconds*—(Optional) Maximum time to wait for a response to the traceroute request.

Required Privilege Level network

Related Documentation

- [traceroute monitor](#)

List of Sample Output

- [traceroute on page 51](#)
- [traceroute as-number-lookup host on page 51](#)
- [traceroute no-resolve on page 51](#)
- [traceroute propagate-ttl on page 52](#)
- [traceroute \(Between CE Routers, Layer 3 VPN\) on page 52](#)
- [traceroute \(Through an MPLS LSP\) on page 52](#)

Output Fields [Table 7 on page 51](#) describes the output fields for the **traceroute** command. Output fields are listed in the approximate order in which they appear.

Table 7: traceroute Output Fields

Field Name	Field Description
traceroute to	IP address of the receiver.
hops max	Maximum number of hops allowed.
byte packets	Size of packets being sent.
<i>number-of-hops</i>	Number of hops from the source to the named router or switch.
<i>router-name</i>	Name of the router or switch for this hop.
<i>address</i>	Address of the router or switch for this hop.
Round trip time	Average round-trip time, in milliseconds (ms).

Sample Output

```

traceroute user@host> traceroute santacruz
traceroute to green.company.net (10.156.169.254), 30 hops max, 40 byte packets
 1 blue23 (10.168.1.254)  2.370 ms  2.853 ms  0.367 ms
 2 red14 (10.168.255.250) 0.778 ms  2.937 ms  0.446 ms
 3 yellow (10.156.169.254) 7.737 ms  89.905 ms  0.834 ms

```

```

traceroute as-number-lookup host user@host> traceroute as-number-lookup 10.100.1.1
traceroute to 10.100.1.1 (10.100.1.1), 30 hops max, 40 byte packets
 1 10.39.1.1 (10.39.1.1) 0.779 ms 0.728 ms 0.562 ms
 2 10.39.1.6 (10.39.1.6) [AS 32] 0.657 ms 0.611 ms 0.617 ms
 3 10.100.1.1 (10.100.1.1) [AS 10, 40, 50] 0.880 ms 0.808 ms 0.774 ms

```

```

traceroute no-resolve user@host> traceroute santacruz no-resolve
traceroute to green.company.net (10.156.169.254), 30 hops max, 40 byte packets
 1 10.168.1.254 0.458 ms 0.370 ms 0.365 ms
 2 10.168.255.250 0.474 ms 0.450 ms 0.444 ms

```

```
3 10.156.169.254 0.931 ms 0.876 ms 0.862 ms
```

```
tracroute user@host> tracroute propagate-ttl 100.200.2.2 routing-instance VPN-A
propagate-ttl tracroute to 100.200.2.2 (100.200.2.2) from 1.1.0.2, 30 hops max, 40 byte packets
```

```
1 1.2.0.2 (1.2.0.2) 2.456 ms 1.753 ms 1.672 ms
   MPLS Label=299776 CoS=0 TTL=1 S=0
   MPLS Label=299792 CoS=0 TTL=1 S=1
2 1.3.0.2 (1.3.0.2) 1.213 ms 1.225 ms 1.166 ms
   MPLS Label=299792 CoS=0 TTL=1 S=1
3 100.200.2.2 (100.200.2.2) 1.422 ms 1.521 ms 1.443 ms
```

```
tracroute (Between user@host> tracroute vpn09
CE Routers, Layer 3 tracroute to vpn09.skybank.net (10.255.14.179), 30 hops max, 40
VPN) byte packets
1 10.39.10.21 (10.39.10.21) 0.598 ms 0.500 ms 0.461 ms
2 10.39.1.13 (10.39.1.13) 0.796 ms 0.775 ms 0.806 ms
   MPLS Label=100006 CoS=0 TTL=1 S=1
3 vpn09.skybank.net (10.255.14.179) 0.783 ms 0.716 ms 0.686
```

```
tracroute user@host> tracroute mpls1
(Through an MPLS tracroute to 10.168.1.224 (10.168.1.224), 30 hops max, 40 byte packets
LSP) 1 mpls1-sr0.company.net (10.168.200.101) 0.555 ms 0.393 ms 0.367 ms
   MPLS Label=1024 CoS=0 TTL=1
2 mpls5-lo0.company.net (10.168.1.224) 0.420 ms 0.394 ms 0.401 ms
```

PART 4

Troubleshooting

- [Routing Protocol Process Memory FAQ on page 55](#)

CHAPTER 6

Routing Protocol Process Memory FAQ

- [Routing Protocol Process Memory FAQ Overview on page 55](#)
- [Routing Protocol Process Memory FAQs on page 56](#)

Routing Protocol Process Memory FAQ Overview

The Juniper Networks Junos operating system (Junos OS) is based on the FreeBSD Unix operating system. The open source software is modified and hardened to operate in the device's specialized environment. For example, some executables have been deleted while other utilities have been de-emphasized. Additionally, certain software processes have been added to enhance the routing functionality. The result of this transformation is the kernel, the heart of the Junos OS software.

The kernel is responsible for generating multiple processes that perform the actual functions of the device. Each process operates in its own protected memory space, providing isolation between the processes and resiliency in the event of a process failure. This is important in a core routing platform because a single process failure does not cause the entire device to cease functioning.

Some of the common software processes include the routing protocol process (rpd) that controls the device's protocols, the device control process (dcd) that controls the device's interfaces, the management process (mgd) that controls user access to the device, the chassis process (chassisd) that controls the device's properties itself, and the Packet Forwarding Engine process (pfed) that controls the communication between the device's Packet Forwarding Engine and the Routing Engine. Besides the above processes, there are other specialized processes that support additional functionality, such as the Simple Network Management Protocol (SNMP), Virtual Router Redundancy Protocol (VRRP), and Class of Service (CoS).

The routing protocol process is a software process within the Routing Engine software that controls the routing protocols that run on the device. Its functionality includes all protocol messages, routing table updates, and implementation of routing policies.

The routing protocol process starts all configured routing protocols and handles all routing messages. It maintains one or more routing tables, which consolidate the routing information learned from all routing protocols. From this routing information, the routing protocol process determines the active routes to network destinations and installs these routes into the Routing Engine's forwarding table. Finally, it implements the routing policy, which allows you to control the routing information that is transferred between the routing

protocols and the routing table. Using the routing policy, you can filter and limit the transfer of information as well as set properties associated with specific routes.

Related Documentation

- [Routing Protocol Process Memory FAQs on page 56](#)

Routing Protocol Process Memory FAQs

The following sections present the most frequently asked questions and answers related to the routing protocol process memory utilization, operation, interpretation of related command outputs, and troubleshooting the software process.

Routing Protocol Process Memory Utilization FAQs

This section presents frequently asked questions and answers related to the memory usage of the routing protocol process.

Why does the routing protocol process use excessive memory?

The routing protocol process uses hundreds of megabytes of RAM in the Routing Engine to store information needed for the operation of routing and related protocols, such as BGP, OSPF, ISIS, RSVP, LDP, and MPLS. Such huge consumption of memory is common for the process, as the information it stores includes routes, next hops, interfaces, routing policies, labels, and label-switched paths (LSPs). Because access to the RAM memory is much faster than access to the hard disk, most of the routing protocol process information is stored in the RAM memory instead of using the hard disk space. This ensures that the performance of the routing protocol process is maximized.

How can I check the amount of memory the routing protocol process is using?

You can check the routing protocol process memory usage by entering the **show system processes** and the **show task memory** Junos OS command-line interface (CLI) operational mode commands.

The **show system processes** command displays information about software processes that are running on the device. You can check the routing protocol process memory usage by using the **show system processes** command with the **extensive** option.

The **show task memory** command displays a report generated by the routing protocol process on the memory utilization for routing protocol tasks on the Routing Engine. Although the report generated by the routing protocol process is on its own memory usage, it does not display all the memory used by the process. The value reported by the routing protocol process does not account for the memory used for the **TEXT** and **STACK** segments, or the memory used by the process's internal memory manager. The **show task memory** command also does not include the memory which has been deactivated by the routing protocol process, although some or all of that deactivated memory has not actually been freed by the kernel.

For more information about checking the routing protocol process memory usage, see [Check Routing Protocol Process \(rpd\) Memory Usage](#) in the *Junos OS Baseline Network Operations Guide*.

For more information about the `show system processes` command and the `show task memory` command, see the [Junos OS System Basics and Services Command Reference](#).

I just deleted many routes from the routing protocol process. Why is the routing protocol process still using so much memory?

The **show system processes extensive** command displays a **RES** value measured in kilobytes. This value represents the amount of process memory resident in the physical memory. This is also known as RSS or Resident Set Size. Any amount of memory deactivated by the process might still be considered part of the **RES** value. Generally, the kernel defers the actual freeing of deactivated memory until there is a memory shortage. This can lead to large discrepancies between the values reported by the routing protocol process and the kernel, even after the routing protocol process has deactivated a large amount of memory.

Interpreting Routing Protocol Process-Related Command Outputs FAQs

This section presents frequently asked questions and answers about the routing protocol process-related Junos OS CLI command outputs that are used to display the memory usage of the routing protocol process.

How do I interpret memory numbers displayed in the show system processes extensive command output?

The **show system processes extensive** command displays exhaustive system process information about software processes that are running on the device. This command is equivalent to the UNIX **top** command. However, the UNIX **top** command shows real-time memory usage, with the memory values constantly changing, while the **show system processes extensive** command provides a snapshot of memory usage in a given moment.

To check overall CPU and memory usage, enter the **show system processes extensive** command. Refer to [Table 8 on page 59](#) for information about the **show system processes extensive** command output fields.

```
user@host> show system processes extensive
last pid: 544; load averages: 0.00, 0.00, 0.00 18:30:33
37 processes: 1 running, 36 sleeping

Mem: 25M Active, 3968K Inact, 19M Wired, 184K Cache, 8346K Buf, 202M Free
Swap: 528M Total, 64K Used, 528M Free

  PID USERNAME PRI NICE SIZE RES STATE TIME WCPU CPU COMMAND
    544 root    30  0  604K 768K RUN   0:00 0.00% 0.00% top
      3 root    28  0    0K 12K psleep 0:00 0.00% 0.00% vmdaemon
      4 root    28  0    0K 12K update 0:03 0.00% 0.00% update
    528 aviva   18  0  660K 948K pause  0:00 0.00% 0.00% tcsh
    204 root    18  0  300K 544K pause  0:00 0.00% 0.00% csh
    131 root    18  0  332K 532K pause  0:00 0.00% 0.00% cron
    186 root    18  0  196K  68K pause  0:00 0.00% 0.00% watchdog
     27 root    10  0  512M 16288K mfsidl 0:00 0.00% 0.00% mount_mfs
      1 root    10  0  620K 344K wait   0:00 0.00% 0.00% init
    304 root     3  0  884K 900K ttyin  0:00 0.00% 0.00% bash
    200 root     3  0  180K 540K ttyin  0:00 0.00% 0.00% getty
    203 root     3  0  180K 540K ttyin  0:00 0.00% 0.00% getty
    202 root     3  0  180K 540K ttyin  0:00 0.00% 0.00% getty
    201 root     3  0  180K 540K ttyin  0:00 0.00% 0.00% getty
    194 root     2  0 2248K 1640K select 0:11 0.00% 0.00% rpd
    205 root     2  0  964K  800K select 0:12 0.00% 0.00% tnp.chassisd
    189 root     2 -12 352K  740K select 0:03 0.00% 0.00% xntpd
    114 root     2  0  296K  612K select 0:00 0.00% 0.00% amd
```



```

188 root      2   0   780K   600K select  0:00  0.00%  0.00% dcd
527 root      2   0   176K   580K select  0:00  0.00%  0.00% rlogind
195 root      2   0   212K   552K select  0:00  0.00%  0.00% inetd
187 root      2   0   192K   532K select  0:00  0.00%  0.00% tnetd
 83 root      2   0   188K   520K select  0:00  0.00%  0.00% syslogd
538 root      2   0  1324K   516K select  0:00  0.00%  0.00% mgd
 99 daemon    2   0   176K   492K select  0:00  0.00%  0.00% portmap
163 root      2   0   572K   420K select  0:00  0.00%  0.00% nsrexecd
192 root      2   0   560K   400K select  0:10  0.00%  0.00% snmpd
191 root      2   0  1284K   376K select  0:00  0.00%  0.00% mgd
537 aviva     2   0   636K   364K select  0:00  0.00%  0.00% cli
193 root      2   0   312K   204K select  0:07  0.00%  0.00% mib2d
  5 root      2   0      0K    12K pfesel  0:00  0.00%  0.00% if_pfe
  2 root     -18   0      0K    12K psleep  0:00  0.00%  0.00% pagedaemon
  0 root     -18   0      0K      0K sched   0:00  0.00%  0.00% swapper

```

Table 8 on page 59 describes the output fields that represent the memory values for the **show system processes extensive** command. Output fields are listed in the approximate order in which they appear.

Table 8: show system processes extensive Output Fields

Field Name	Field Description
Mem	Information about physical and virtual memory allocation.
Active	Memory allocated and actively used by the process.
Inact	Memory allocated but not recently used, or memory deactivated by the processes. Inactive memory remains mapped in the address space of one or more processes and, therefore, counts toward the RSS value of those processes.
Wired	Memory that is not eligible to be swapped, usually used for in-kernel memory structure, memory physically locked by a process, or both.
Cache	Freed memory that is no longer associated with any process but still has valid contents that correspond to some file system blocks. Cache pages can be reclaimed as is when the corresponding file system blocks are accessed again. However, when the system is under memory pressure, the contents of Cache pages could be erased by the kernel and the pages reused to service any memory allocation requests.
Buf	Size of the virtual memory buffer used to hold data recently called from the disk.
Free	Free memory that is neither associated with any process nor contains any valid contents.
Swap	Information about swap memory. <ul style="list-style-type: none"> • Total—Total space on the swap device. • Used—Memory swapped to disk. • Free—Unused space available on the swap device.

The rest of the command output displays information about the memory usage of each process. The **SIZE** field indicates the size of the virtual address space, and the **RES** field indicates the amount of the process in physical memory, which is also known as RSS or Resident Set Size. For more information, see the **show system processes** command in the *Junos OS System Basics and Services Command Reference*.

What is the difference between Active and Inact memory that is displayed by the show system processes extensive command?

When the system is under memory pressure, the pageout process can free up memory from the **Inact** and, if necessary, **Active** pools after first preserving the contents of those pages on the swap device or backing file systems if necessary. When the pageout process runs, it scans memory to see which pages are good candidates to be unmapped and freed up. Thus, the distinction between **Active** and **Inact** memory is only used by the pageout process to determine which pool of pages to free first at the time of a memory shortage.

The pageout process first scans the **Inact** list and checks whether the pages on this list have been accessed since the time they have been listed here. The pages that have been accessed are moved from the **Inact** list to the **Active** list. On the other hand, pages that have not been accessed become prime candidates to be freed by the pageout process. If the pageout process cannot produce enough free pages from the **Inact** list, pages from the **Active** list are freed up.

Because the pageout process runs only when the system is under memory pressure, the pages on the **Inact** list remain untouched – even if they have not been accessed recently – when the amount of **Free** memory is adequate.

How do I interpret memory numbers displayed in the show task memory command output?

The **show task memory** command provides a comprehensive picture of the memory utilization for routing protocol tasks on the Routing Engine. The routing protocol process is the main task that uses Routing Engine memory.

To check routing process memory usage, enter the **show task memory** command.

```
user@host> show task memory
Memory          Size (kB)  %Available  When
Currently In Use:    29417      3%         now
Maximum Ever Used:   33882      4%         00/02/11 22:07:03
Available:          756281    100%        now
```

[Table 9 on page 60](#) describes the output fields for the **show task memory** command. Output fields are listed in the approximate order in which they appear.

Table 9: show task memory Output Fields

Field Name	Field Description
Memory Currently In Use	Memory currently in use. Dynamically allocated memory plus the DATA segment memory in kilobytes.
Memory Maximum Ever Used	Maximum memory ever used.
Memory Available	Memory currently available.

The **show task memory** command does not display all the memory used by the routing protocol process. This value does not account for the memory used for the **TEXT** and

STACK segments, or the memory used by the routing protocol process's internal memory manager. The **show task memory** command also does not include the memory which has been deactivated by the routing protocol process, although some or all of that deactivated memory has not actually been freed by the kernel.

Why is the Memory Currently In Use value less than the RES value?

The **show task memory** command displays a **Memory Currently In Use** value measured in kilobytes. This value is the dynamically allocated memory plus the **DATA** segment memory. The **show system processes extensive** command displays a **RES** value measured in kilobytes. This value represents the amount of process memory resident in the physical memory. This is also known as RSS or Resident Set Size.

The **Memory Currently In Use** value does not account for all of the memory that the routing protocol process uses. This value does not include the memory used for the **TEXT** and the **STACK** segments, and a small percentage of memory used by the routing protocol process's internal memory manager. The **show task memory** command also does not include the memory which has been deactivated by the routing protocol process, although some or all of that deactivated memory has not actually been freed by the kernel.

Any amount of memory deactivated by the routing protocol process might still be considered part of the **RES** value. Generally, the kernel defers the actual freeing of deactivated memory until there is a memory shortage. This can lead to large discrepancies between the **Memory Currently In Use** value and the **RES** value.

Routing Protocol Process Memory Swapping FAQs

This section presents frequently asked questions and answers related to the memory swapping of the routing protocol process from the Routing Engine memory to the hard disk memory.

Why does the system start swapping when I try to perform a core dump using the request system core-dumps command?

The **request system core-dumps** command displays a list of system core files created when the device has failed. This command can be useful for diagnostic purposes. Each list item includes the file permissions, number of links, owner, group, size, modification date, path, and filename. You can use the **core-filename** option and the **core-file-info**, **brief**, and **detail** options to display more information about the specified core dump files.

You can use the **request system core-dumps** command to perform a non-fatal core dump without aborting the routing protocol process. To do this, the routing protocol process is forked, generating a second copy, and then aborted. This process can double the memory consumed by the two copies of the routing protocol process, pushing the system into swap.

Why does the show system processes extensive command show that memory is swapped to disk even though there is plenty of free memory?

Memory can remain swapped out indefinitely if it is not accessed again. Therefore, the **show system processes extensive** command shows that memory is swapped to disk even though there is plenty of free memory. Such a situation is not unusual.

Troubleshooting the Routing Protocol Process FAQs

This section presents frequently asked questions and answers related to a shortage of memory and memory leakage by the routing protocol process.

What does the RPD_OS_MEMHIGH message mean?

The **RPD_OS_MEMHIGH** message is written into the system message file if the routing protocol process is running out of memory. This message alerts you that the routing protocol process is using the indicated amount and percentage of Routing Engine memory, which is considered excessive. This message is generated either because the routing protocol process is leaking memory or the use of system resources is excessive, perhaps because routing filters are not configured properly or the configured network topology is very complex.

When the memory utilization for the routing protocol process is using all available Routing Engine DRAM memory or reaches the maximum memory limit, a message of the following form is written every minute in the syslog message file:

RPD_OS_MEMHIGH: Using 188830 KB of memory, 100 percent of available

This message includes the amount (in kilobytes), the percentage, or both of the available memory in use.

This message should not appear under normal conditions, as any further memory allocations usually require a portion of existing memory to be written to swap. As a recommended solution, increase the amount of RAM in the Routing Engine. For more information, see <http://kb.juniper.net/InfoCenter/index?page=content&id=KB14186>.

What can I do when there is a memory shortage even after a swap?

We do not recommend that the system operate in this state, notwithstanding the existence of swap. The protocols that run in the routing protocol process usually have a real-time requirement that cannot reliably withstand the latency of being swapped to hard disk. If the memory shortage has not resulted from a memory leak, then either a reduction in the memory usage or an upgrade to a higher memory-capacity Routing Engine is required.

What is the task_timer?

The source of a routing protocol process memory leak can usually be identified by dumping the timers for each task. You can use the **show task *task-name*** command to display routing protocol tasks on the Routing Engine. Tasks can be baseline tasks performed regardless of the device's configuration, and other tasks that depend on the device configuration.

For more information, see the show task command in the *Junos OS System Basics and Services Command Reference*.

Related Documentation

- [Routing Protocol Process Memory FAQ Overview on page 55](#)

PART 5

Index

- [Index on page 65](#)

Index

Symbols

#, comments in configuration statements.....	xii
(), in syntax descriptions.....	xii
< >, in syntax descriptions.....	xii
[], in configuration statements.....	xii
{ }, in configuration statements.....	xii
(pipe), in syntax descriptions.....	xii

A

address statement.....	16
usage guidelines.....	9
advertise statement.....	16
usage guidelines.....	9

B

braces, in configuration statements.....	xii
brackets	
angle, in syntax descriptions.....	xii
square, in configuration statements.....	xii
broadcast mode, router discovery.....	9
broadcast statement.....	17
usage guidelines.....	9

C

comments, in configuration statements.....	xii
connections	
testing	
general connections.....	43
conventions	
text and syntax.....	xi
curly braces, in configuration statements.....	xii
customer support.....	xiii
contacting JTAC.....	xiii

D

disable statement	
router discovery.....	17
documentation	
comments on.....	xiii

E

error (tracing flag)	
router discovery.....	24

F

font conventions.....	xi
-----------------------	----

H

hosts, reachability	
general connections.....	43

I

ICMP	
supported software standards.....	5
ignore statement.....	16
usage guidelines.....	9
ineligible statement.....	23
info (tracing flag).....	24
interface statement	
router discovery.....	18
interface statistics, real-time, displaying.....	30
Internet Control Message Protocol router discovery	
See router discovery	
IRDP.....	9

K

keyboard sequences	
used with monitor interface command.....	30
used with monitor interface traffic	
command.....	31

L

lifetime statement.....	19
usage guidelines.....	9
log files	
contents, displaying.....	47
display of	
starting.....	40
stopping.....	42

M

manuals	
comments on.....	xiii
max-advertisement-interval statement.....	20
ICMP	
usage guidelines.....	9
min-advertisement-interval statement.....	21
usage guidelines.....	9
monitor interface command.....	30

monitor start command.....	40	statistics	
monitor stop command.....	42	interfaces, real-time.....	30
multicast statement		support, technical See technical support	
router discovery.....	22	syntax conventions.....	xi
usage guidelines.....	9		
N		T	
neighbor discovery		technical support	
supported software standards.....	5	contacting JTAC.....	xiii
O		trace files	
output control keys		display of	
for monitor interface command.....	30	starting.....	40
for monitor interface traffic command.....	31	stopping.....	42
P		traceoptions statement	
packets (tracing flag)		router discovery.....	24
router discovery.....	24	usage guidelines.....	9
parentheses, in syntax descriptions.....	xii	traceroute command.....	49
ping command.....	43	tracing flags	
priority statement		error	
router discovery.....	23	router discovery.....	24
R		info.....	24
real-time monitoring		packets	
interfaces.....	30	router discovery.....	24
redirect (tracing flag).....	24	redirect.....	24
RFC 1256.....	9	router-discovery.....	24
router advertisements.....	9, 20, 21	tracing operations	
router discovery		router discovery.....	9, 24
designated router, configuring.....	23		
router advertisements.....	3, 4, 9	U	
router solicitations.....	3	users	
server operation.....	3	logs, displaying.....	47
server, enabling.....	23		
tracing operations.....	9, 24		
router-discovery (tracing flag).....	24		
router-discovery statement.....	23		
routes, displaying			
to specified network host.....	49		
routing protocol process memory			
faq.....	56		
rpd			
faq.....	56		
rpd memory			
utilization.....	56		
S			
show log command.....	47		