



Junos[®] OS

High Availability Features and Configuration

Release
13.1



Published: 2013-03-12

Juniper Networks, Inc.
1194 North Mathilda Avenue
Sunnyvale, California 94089
USA
408-745-2000
www.juniper.net

This product includes the Envoy SNMP Engine, developed by Epilogue Technology, an Integrated Systems Company. Copyright © 1986-1997, Epilogue Technology Corporation. All rights reserved. This program and its documentation were developed at private expense, and no part of them is in the public domain.

This product includes memory allocation software developed by Mark Moraes, copyright © 1988, 1989, 1993, University of Toronto.

This product includes FreeBSD software developed by the University of California, Berkeley, and its contributors. All of the documentation and software included in the 4.4BSD and 4.4BSD-Lite Releases is copyrighted by the Regents of the University of California. Copyright © 1979, 1980, 1983, 1986, 1988, 1989, 1991, 1992, 1993, 1994. The Regents of the University of California. All rights reserved.

GateD software copyright © 1995, the Regents of the University. All rights reserved. Gate Daemon was originated and developed through release 3.0 by Cornell University and its collaborators. Gated is based on Kirton's EGP, UC Berkeley's routing daemon (routed), and DCN's HELLO routing protocol. Development of Gated has been supported in part by the National Science Foundation. Portions of the GateD software copyright © 1988, Regents of the University of California. All rights reserved. Portions of the GateD software copyright © 1991, D. L. S. Associates.

This product includes software developed by Maker Communications, Inc., copyright © 1996, 1997, Maker Communications, Inc.

Juniper Networks, Junos, Steel-Belted Radius, NetScreen, and ScreenOS are registered trademarks of Juniper Networks, Inc. in the United States and other countries. The Juniper Networks Logo, the Junos logo, and JunosE are trademarks of Juniper Networks, Inc. All other trademarks, service marks, registered trademarks, or registered service marks are the property of their respective owners.

Juniper Networks assumes no responsibility for any inaccuracies in this document. Juniper Networks reserves the right to change, modify, transfer, or otherwise revise this publication without notice.

Products made or sold by Juniper Networks or components thereof might be covered by one or more of the following patents that are owned by or licensed to Juniper Networks: U.S. Patent Nos. 5,473,599, 5,905,725, 5,909,440, 6,192,051, 6,333,650, 6,359,479, 6,406,312, 6,429,706, 6,459,579, 6,493,347, 6,538,518, 6,538,899, 6,552,918, 6,567,902, 6,578,186, and 6,590,785.

Junos® OS High Availability Features and Configuration

13.1

Copyright © 2013, Juniper Networks, Inc.
All rights reserved.

The information in this document is current as of the date on the title page.

YEAR 2000 NOTICE

Juniper Networks hardware and software products are Year 2000 compliant. Junos OS has no known time-related limitations through the year 2038. However, the NTP application is known to have some difficulty in the year 2036.

END USER LICENSE AGREEMENT

The Juniper Networks product that is the subject of this technical documentation consists of (or is intended for use with) Juniper Networks software. Use of such software is subject to the terms and conditions of the End User License Agreement ("EULA") posted at <http://www.juniper.net/support/eula.html>. By downloading, installing or using such software, you agree to the terms and conditions of that EULA.

Table of Contents

	About the Documentation	xv
	Documentation and Release Notes	xv
	Supported Platforms	xv
	Using the Examples in This Manual	xv
	Merging a Full Example	xvi
	Merging a Snippet	xvi
	Documentation Conventions	xvii
	Documentation Feedback	xix
	Requesting Technical Support	xix
	Self-Help Online Tools and Resources	xix
	Opening a Case with JTAC	xx
Part 1	Overview	
Chapter 1	High Availability Overview	3
	Understanding High Availability Features on Juniper Networks Routers	3
	Routing Engine Redundancy	3
	Graceful Routing Engine Switchover	3
	Nonstop Bridging	4
	Nonstop Active Routing	4
	Graceful Restart	5
	Nonstop Active Routing Versus Graceful Restart	6
	Effects of a Routing Engine Switchover	7
	VRRP	7
	Unified ISSU	7
	Interchassis Redundancy for MX Series Routers Using Virtual Chassis	7
	High Availability-Related Features in Junos OS	8
Chapter 2	Routing Engine and Switching Control Board Redundancy	11
	Understanding Routing Engine Redundancy on Juniper Networks Routers	11
	Routing Engine Redundancy Overview	11
	Conditions That Trigger a Routing Engine Failover	12
	Default Routing Engine Redundancy Behavior	13
	Routing Engine Redundancy on a TX Matrix Router	13
	Routing Engine Redundancy on a TX Matrix Plus Router	15
	Situations That Require You to Halt Routing Engines	16
	Switching Control Board Redundancy	16
	Redundant CFEBs on the M10i Router	17
	Redundant FEBs on the M120 Router	17
	Redundant SSBs on the M20 Router	19
	Redundant SFMs on the M40e and M160 Routers	20

Chapter 3	Graceful Routing Engine Switchover (GRES)	21
	Understanding Graceful Routing Engine Switchover in the Junos OS	21
	Graceful Routing Engine Switchover Concepts	21
	Effects of a Routing Engine Switchover	25
	Graceful Routing Engine Switchover System Requirements	25
	Graceful Routing Engine Switchover Platform Support	26
	Graceful Routing Engine Switchover Feature Support	26
	Graceful Routing Engine Switchover DPC Support	28
	Graceful Routing Engine Switchover and Subscriber Access	28
	Graceful Routing Engine Switchover PIC Support	28
	Requirements for Routers with a Backup Router Configuration	29
Chapter 4	Nonstop Bridging	31
	Nonstop Bridging Concepts	31
	Nonstop Bridging System Requirements	33
	Platform Support	33
	Protocol Support	34
Chapter 5	Nonstop Active Routing	35
	Nonstop Active Routing Concepts	35
	Nonstop Active Routing System Requirements	38
	Nonstop Active Routing Platform Support	38
	Nonstop Active Routing Protocol and Feature Support	39
	Nonstop Active Routing BFD Support	42
	Nonstop Active Routing BGP Support	43
	Nonstop Active Routing Layer 2 Circuit and VPLS Support	43
	Nonstop Active Routing PIM Support	44
	Nonstop Active Routing MSDP Support	46
	Nonstop Active Routing Support for RSVP-TE LSPs	47
Chapter 6	Graceful Restart	49
	Graceful Restart Concepts	49
	Graceful Restart System Requirements	50
	Aggregate and Static Routes	51
	Graceful Restart and Routing Protocols	51
	BGP	51
	ES-IS	52
	IS-IS	52
	OSPF and OSPFv3	52
	PIM Sparse Mode	53
	RIP and RIPng	53
	Graceful Restart and MPLS-Related Protocols	54
	LDP	54
	RSVP	54
	CCC and TCC	55
	Understanding Restart Signaling-Based Helper Mode Support for OSPF Graceful Restart	55
	Graceful Restart and Layer 2 and Layer 3 VPNs	56
	Graceful Restart on Logical Systems	57

Chapter 7	VRRP	59
	Understanding VRRP	59
	Junos OS Support for VRRPv3	60
	Understanding VRRPv3 Behavioral Differences	61
	Understanding VRRPv2 to VRRPv3 Transition	62
	Improving the Convergence Time for VRRP	63
Chapter 8	Unified ISSU	67
	Unified ISSU Concepts	67
	Unified ISSU Process on the TX Matrix Router	72
	Unified ISSU System Requirements	73
	Unified ISSU Junos OS Release Support	73
	Unified ISSU Platform Support	74
	Unified ISSU Protocol Support	74
	Unified ISSU Support for the Layer 2 Control Protocol Process	75
	Unified ISSU Feature Support	76
	Unified ISSU PIC Support	76
	PIC Considerations	77
	SONET/SDH PICs	77
	Fast Ethernet and Gigabit Ethernet PICs	79
	Channelized PICs	80
	Tunnel Services PICs	81
	ATM PICs	82
	Serial PICs	82
	DS3, E1, E3, and T1 PICs	83
	Enhanced IQ PICs	83
	Enhanced IQ2 Ethernet Services Engine (ESE) PIC	83
	Unified ISSU Support on MX Series 3D Universal Edge Routers	84
	Unified ISSU DPC and FPC Support on MX Series 3D Universal Edge Routers	84
	Unified ISSU MIC and MPC Support on MX Series 3D Universal Edge Routers	84
	Unified ISSU Limitation on MX Series 3D Universal Edge Routers	85
Part 2	Configuration	
Chapter 9	Routing Engine and Switching Control Board Redundancy	89
	Configuring Routing Engine Redundancy	89
	Modifying the Default Routing Engine Mastership	89
	Configuring Automatic Failover to the Backup Routing Engine	90
	Without Interruption to Packet Forwarding	90
	On Detection of a Hard Disk Error on the Master Routing Engine	90
	On Detection of a Loss of Keepalive Signal from the Master Routing Engine	90

	When a Software Process Fails	92
	Manually Switching Routing Engine Mastership	92
	Verifying Routing Engine Redundancy Status	92
	Configuring CFEB Redundancy on the M10i Router	93
	Configuring FEB Redundancy on the M120 Router	94
	Example: Configuring FEB Redundancy	95
	Configuring SFM Redundancy on M40e and M160 Routers	96
	Configuring SSB Redundancy on the M20 Router	97
	Chassis Redundancy Hierarchy	97
	Routing Engine and Switching Control Board Redundancy Configuration Statements	98
	Initial Routing Engine Configuration Example	98
Chapter 10	Graceful Routing Engine Switchover	101
	Configuring Graceful Routing Engine Switchover	101
	Enabling Graceful Routing Engine Switchover	101
	Synchronizing the Routing Engine Configuration	101
	Verifying Graceful Routing Engine Switchover Operation	102
	graceful-switchover	102
Chapter 11	Nonstop Bridging	103
	Configuring Nonstop Bridging	103
	Enabling Nonstop Bridging	103
	Synchronizing the Routing Engine Configuration	103
	Verifying Nonstop Bridging Operation	104
	nonstop-bridging	104
Chapter 12	Nonstop Active Routing	105
	Configuring Nonstop Active Routing	105
	Enabling Nonstop Active Routing	105
	Synchronizing the Routing Engine Configuration	106
	Verifying Nonstop Active Routing Operation	106
	Tracing Nonstop Active Routing Synchronization Events	107
	commit synchronize	109
	nonstop-routing	110
	traceoptions (Routing Options)	111
	Example: Configuring Nonstop Active Routing	113
Chapter 13	Graceful Restart	117
	Enabling Graceful Restart	117
	Configuring Routing Protocols Graceful Restart	118
	Enabling Graceful Restart	118
	Configuring Graceful Restart Options for BGP	119
	Configuring Graceful Restart Options for ES-IS	120
	Configuring Graceful Restart Options for IS-IS	120
	Configuring Graceful Restart Options for OSPF and OSPFv3	121
	Configuring Graceful Restart Options for RIP and RIPng	122
	Configuring Graceful Restart Options for PIM Sparse Mode	122

	Tracking Graceful Restart Events	124
	Configuring Graceful Restart for MPLS-Related Protocols	124
	Configuring Graceful Restart Globally	124
	Configuring Graceful Restart Options for RSVP, CCC, and TCC	125
	Configuring Graceful Restart Options for LDP	125
	Configuring VPN Graceful Restart	126
	Configuring Graceful Restart Globally	126
	Configuring Graceful Restart for the Routing Instance	127
	Configuring Logical System Graceful Restart	127
	Enabling Graceful Restart Globally	128
	Configuring Graceful Restart for a Routing Instance	128
	Graceful Restart Configuration Statements	129
	Example: Configuring Graceful Restart	129
	Example: Managing Helper Modes for OSPF Graceful Restart	154
Chapter 14	VRRP	157
	VRRP Configuration Hierarchy	157
	VRRP for IPv6 Configuration Hierarchy	158
	Configuring the Startup Period for VRRP Operations	159
	Configuring Basic VRRP Support	160
	Configuring VRRP Authentication (IPv4 Only)	162
	Configuring the Advertisement Interval for the VRRP Master Router	163
	Modifying the Advertisement Interval in Seconds	164
	Modifying the Advertisement Interval in Milliseconds	164
	Configuring a Backup Router to Preempt the Master Router	166
	Modifying the Preemption Hold-Time Value	166
	Configuring Asymmetric Hold Time for VRRP Routers	167
	Configuring an Interface to Accept Packets Destined for the Virtual IP Address	168
	Configuring a Logical Interface to Be Tracked	169
	Configuring a Route to Be Tracked	171
	Configuring Inheritance for a VRRP Group	172
	Configuring the Silent Period	173
	Configuring Passive ARP Learning for Backup VRRP Routers	174
	Enabling the Distributed Periodic Packet Management Process for VRRP	175
	Configuring VRRP to Improve Convergence Time	176
	Example: Configuring VRRP	177
	Example: Configuring VRRP for IPv6	179
	Example: Configuring VRRP Route Tracking	180
	Example: Configuring Multiple VRRP Owner Groups	181
	Tracing VRRP Operations	187
Chapter 15	Unified ISSU	189
	Managing and Tracing BFD Sessions During Unified ISSU Procedures	189
	no-issu-timer-negotiation	190
	traceoptions (Protocols BFD)	191

Part 3	Administration	
Chapter 16	Routing Engine and Switching Control Board Redundancy	195
	Copying a Configuration File from One Routing Engine to the Other	195
	Loading a Software Package from the Other Routing Engine	196
Chapter 17	Summary of Routing Engine and Switching Control Board Redundancy Statements	197
	cfeb	197
	description (Chassis Redundancy)	198
	failover (Chassis)	198
	failover (System Process)	199
	feb (Creating a Redundancy Group)	200
	feb (Assigning a FEB to a Redundancy Group)	200
	keepalive-time	201
	no-auto-failover	202
	on-disk-failure (Chassis Redundancy Failover)	202
	on-loss-of-keepalives	203
	redundancy	204
	redundancy-group	205
	routing-engine (Chassis Redundancy)	206
	sfm (Chassis Redundancy)	207
	ssb	208
Chapter 18	Graceful Routing Engine Switchover	209
	Resetting Local Statistics	209
Chapter 19	Nonstop Active Routing	211
	Resetting Local Statistics	211
Chapter 20	Graceful Restart	213
	Tracing Restart Signaling-Based Helper Mode Events for OSPF Graceful Restart	213
	Restart	213
	Verifying Graceful Restart Operation	214
	Graceful Restart Operational Mode Commands	214
	Verifying BGP Graceful Restart	215
	Verifying IS-IS and OSPF Graceful Restart	215
	Verifying CCC and TCC Graceful Restart	216
Chapter 21	Summary of Graceful Restart Configuration Statements	217
	disable	217
	graceful-restart (Enabling Globally)	218
	helper-disable (Multiple Protocols)	219
	maximum-helper-recovery-time	219
	maximum-helper-restart-time (RSVP)	220
	maximum-neighbor-reconnect-time	220
	maximum-neighbor-recovery-time	221
	no-strict-lsa-checking	222
	notify-duration	223
	reconnect-time	224
	recovery-time	225

	restart-duration	226
	restart-time (BGP Graceful Restart)	227
	stale-routes-time	228
	traceoptions (Protocols)	229
Chapter 22	Summary of VRRP Configuration Statements	231
	accept-data	232
	advertise-interval	233
	asymmetric-hold-time	234
	authentication-key	235
	authentication-type	236
	bandwidth-threshold	237
	delegate-processing (VRRP)	238
	fast-interval	239
	global-advertisements-threshold	240
	hold-time (VRRP)	241
	inet6-advertise-interval	242
	interface (VRRP Group)	243
	preempt (VRRP)	244
	priority (Protocols VRRP)	245
	priority-cost (VRRP)	246
	priority-hold-time	247
	route (Interfaces)	248
	skew-timer-disable	249
	startup-silent-period	249
	traceoptions (Protocols VRRP)	250
	track (VRRP)	252
	version-3	253
	virtual-address	254
	virtual-inet6-address	254
	virtual-link-local-address	255
	vrrp-group	256
	vrrp-inet6-group	257
Chapter 23	Unified ISSU	259
	Best Practices	259
	Before You Begin	259
	Verify That the Master and Backup Routing Engines Are Running the Same Software Version	260
	Back Up the Router Software	260
	Verify That Graceful Routing Engine Switchover and Nonstop Active Routing Are Configured	261
	Performing a Unified ISSU	262
	Upgrading and Rebooting Both Routing Engines Automatically	262
	Upgrading Both Routing Engines and Rebooting the New Backup Routing Engine Manually	266
	Upgrading and Rebooting Only One Routing Engine	271
	Verifying a Unified ISSU	274

Part 4	Troubleshooting	
Chapter 24	Unified ISSU	279
	Troubleshooting Unified ISSU Problems	279
Part 5	Index	
	Index	283

List of Figures

Part 1	Overview	
Chapter 3	Graceful Routing Engine Switchover (GRES)	21
	Figure 1: Preparing for a Graceful Routing Engine Switchover	23
	Figure 2: Graceful Routing Engine Switchover Process	24
Chapter 4	Nonstop Bridging	31
	Figure 3: Nonstop Bridging Switchover Preparation Process	32
	Figure 4: Nonstop Bridging During a Switchover	33
Chapter 5	Nonstop Active Routing	35
	Figure 5: Nonstop Active Routing Switchover Preparation Process	36
	Figure 6: Nonstop Active Routing During a Switchover	37
Chapter 7	VRRP	59
	Figure 7: Basic VRRP	60
Part 2	Configuration	
Chapter 13	Graceful Restart	117
	Figure 8: Layer 3 VPN Graceful Restart Topology	130

List of Tables

	About the Documentation	xv
	Table 1: Notice Icons	xvii
	Table 2: Text and Syntax Conventions	xvii
Part 1	Overview	
Chapter 3	Graceful Routing Engine Switchover (GRES)	21
	Table 3: Effects of a Routing Engine Switchover	25
	Table 4: Graceful Routing Engine Switchover Feature Support	26
Chapter 5	Nonstop Active Routing	35
	Table 5: Nonstop Active Routing Platform Support	38
	Table 6: Nonstop Active Routing Protocol and Feature Support	40
Chapter 7	VRRP	59
	Table 7: Example: VRRPv2 to VRRPv3 Transition Steps and Events	62
Chapter 8	Unified ISSU	67
	Table 8: Unified ISSU Platform Support	74
	Table 9: Unified ISSU Protocol Support	75
	Table 10: Unified ISSU PIC Support: SONET/SDH	78
	Table 11: Unified ISSU PIC Support: Fast Ethernet and Gigabit Ethernet	79
	Table 12: Unified ISSU PIC Support: Channelized	81
	Table 13: Unified ISSU PIC Support: Tunnel Services	81
	Table 14: Unified ISSU PIC Support: ATM	82
	Table 15: Unified ISSU Support: Enhanced IQ2 Ethernet Services Engine (ESE) PIC	83
	Table 16: Unified ISSU Support: MX Series 3D Universal Edge Routers	85
	Table 17: Unified ISSU Support: MX Series 3D Universal Edge Routers	85
Part 2	Configuration	
Chapter 9	Routing Engine and Switching Control Board Redundancy	89
	Table 18: Routing Engine Mastership Log	92
Chapter 14	VRRP	157
	Table 19: Interface State and Priority Cost Usage	170

About the Documentation

- [Documentation and Release Notes on page xv](#)
- [Supported Platforms on page xv](#)
- [Using the Examples in This Manual on page xv](#)
- [Documentation Conventions on page xvii](#)
- [Documentation Feedback on page xix](#)
- [Requesting Technical Support on page xix](#)

Documentation and Release Notes

To obtain the most current version of all Juniper Networks® technical documentation, see the product documentation page on the Juniper Networks website at <http://www.juniper.net/techpubs/>.

If the information in the latest release notes differs from the information in the documentation, follow the product Release Notes.

Juniper Networks Books publishes books by Juniper Networks engineers and subject matter experts. These books go beyond the technical documentation to explore the nuances of network architecture, deployment, and administration. The current list can be viewed at <http://www.juniper.net/books>.

Supported Platforms

For the features described in this document, the following platforms are supported:

- [M Series](#)
- [T Series](#)
- [MX Series](#)
- [TX Matrix Routers](#)
- [PTX Series](#)

Using the Examples in This Manual

If you want to use the examples in this manual, you can use the **load merge** or the **load merge relative** command. These commands cause the software to merge the incoming

configuration into the current candidate configuration. The example does not become active until you commit the candidate configuration.

If the example configuration contains the top level of the hierarchy (or multiple hierarchies), the example is a *full example*. In this case, use the **load merge** command.

If the example configuration does not start at the top level of the hierarchy, the example is a *snippet*. In this case, use the **load merge relative** command. These procedures are described in the following sections.

Merging a Full Example

To merge a full example, follow these steps:

1. From the HTML or PDF version of the manual, copy a configuration example into a text file, save the file with a name, and copy the file to a directory on your routing platform.

For example, copy the following configuration to a file and name the file **ex-script.conf**. Copy the **ex-script.conf** file to the **/var/tmp** directory on your routing platform.

```
system {
  scripts {
    commit {
      file ex-script.xsl;
    }
  }
}
interfaces {
  fxp0 {
    disable;
    unit 0 {
      family inet {
        address 10.0.0.1/24;
      }
    }
  }
}
```

2. Merge the contents of the file into your routing platform configuration by issuing the **load merge** configuration mode command:

```
[edit]
user@host# load merge /var/tmp/ex-script.conf
load complete
```

Merging a Snippet

To merge a snippet, follow these steps:

1. From the HTML or PDF version of the manual, copy a configuration snippet into a text file, save the file with a name, and copy the file to a directory on your routing platform.

For example, copy the following snippet to a file and name the file **ex-script-snippet.conf**. Copy the **ex-script-snippet.conf** file to the **/var/tmp** directory on your routing platform.


```
commit {
  file ex-script-snippet.xml; }
```

2. Move to the hierarchy level that is relevant for this snippet by issuing the following configuration mode command:

```
[edit]
user@host# edit system scripts
[edit system scripts]
```

3. Merge the contents of the file into your routing platform configuration by issuing the **load merge relative** configuration mode command:

```
[edit system scripts]
user@host# load merge relative /var/tmp/ex-script-snippet.conf
load complete
```

For more information about the **load** command, see the CLI User Guide.

Documentation Conventions

Table 1 on page xvii defines notice icons used in this guide.

Table 1: Notice Icons




Icon	Meaning	Description
	Informational note	Indicates important features or instructions.
	Caution	Indicates a situation that might result in loss of data or hardware damage.
	Warning	Alerts you to the risk of personal injury or death.
	Laser warning	Alerts you to the risk of personal injury from a laser.

Table 2 on page xvii defines the text and syntax conventions used in this guide.

Table 2: Text and Syntax Conventions

Convention	Description	Examples
Bold text like this	Represents text that you type.	To enter configuration mode, type the configure command: user@host> configure
Fixed-width text like this	Represents output that appears on the terminal screen.	user@host> show chassis alarms No alarms currently active

Table 2: Text and Syntax Conventions (*continued*)

Convention	Description	Examples
<i>Italic text like this</i>	<ul style="list-style-type: none"> Introduces or emphasizes important new terms. Identifies book names. Identifies RFC and Internet draft titles. 	<ul style="list-style-type: none"> A policy <i>term</i> is a named structure that defines match conditions and actions. <i>Junos OS System Basics Configuration Guide</i> RFC 1997, <i>BGP Communities Attribute</i>
<i>Italic text like this</i>	Represents variables (options for which you substitute a value) in commands or configuration statements.	Configure the machine's domain name: [edit] root@# set system domain-name <i>domain-name</i>
Text like this	Represents names of configuration statements, commands, files, and directories; configuration hierarchy levels; or labels on routing platform components.	<ul style="list-style-type: none"> To configure a stub area, include the stub statement at the [edit protocols ospf area area-id] hierarchy level. The console port is labeled CONSOLE.
< > (angle brackets)	Enclose optional keywords or variables.	stub <default-metric metric>;
(pipe symbol)	Indicates a choice between the mutually exclusive keywords or variables on either side of the symbol. The set of choices is often enclosed in parentheses for clarity.	broadcast multicast <i>(string1 string2 string3)</i>
# (pound sign)	Indicates a comment specified on the same line as the configuration statement to which it applies.	rsvp { # Required for dynamic MPLS only
[] (square brackets)	Enclose a variable for which you can substitute one or more values.	community name members [community-ids]
Indentation and braces ({ })	Identify a level in the configuration hierarchy.	[edit] routing-options { static { route default { nexthop <i>address</i> ; retain; } } }
;(semicolon)	Identifies a leaf statement at a configuration hierarchy level.	
J-Web GUI Conventions		
Bold text like this	Represents J-Web graphical user interface (GUI) items you click or select.	<ul style="list-style-type: none"> In the Logical Interfaces box, select All Interfaces. To cancel the configuration, click Cancel.
> (bold right angle bracket)	Separates levels in a hierarchy of J-Web selections.	In the configuration editor hierarchy, select Protocols>Ospf .

Documentation Feedback

We encourage you to provide feedback, comments, and suggestions so that we can improve the documentation. You can send your comments to techpubs-comments@juniper.net, or fill out the documentation feedback form at <https://www.juniper.net/cgi-bin/docbugreport/>. If you are using e-mail, be sure to include the following information with your comments:

- Document or topic name
- URL or page number
- Software release version (if applicable)

Requesting Technical Support

Technical product support is available through the Juniper Networks Technical Assistance Center (JTAC). If you are a customer with an active J-Care or JNASC support contract, or are covered under warranty, and need post-sales technical support, you can access our tools and resources online or open a case with JTAC.

- JTAC policies—For a complete understanding of our JTAC procedures and policies, review the *JTAC User Guide* located at <http://www.juniper.net/us/en/local/pdf/resource-guides/7100059-en.pdf>.
- Product warranties—For product warranty information, visit <http://www.juniper.net/support/warranty/>.
- JTAC hours of operation—The JTAC centers have resources available 24 hours a day, 7 days a week, 365 days a year.

Self-Help Online Tools and Resources

For quick and easy problem resolution, Juniper Networks has designed an online self-service portal called the Customer Support Center (CSC) that provides you with the following features:

- Find CSC offerings: <http://www.juniper.net/customers/support/>
- Search for known bugs: <http://www2.juniper.net/kb/>
- Find product documentation: <http://www.juniper.net/techpubs/>
- Find solutions and answer questions using our Knowledge Base: <http://kb.juniper.net/>
- Download the latest versions of software and review release notes: <http://www.juniper.net/customers/csc/software/>
- Search technical bulletins for relevant hardware and software notifications: <https://www.juniper.net/alerts/>

- Join and participate in the Juniper Networks Community Forum:
<http://www.juniper.net/company/communities/>
- Open a case online in the CSC Case Management tool: <http://www.juniper.net/cm/>

To verify service entitlement by product serial number, use our Serial Number Entitlement (SNE) Tool: <https://tools.juniper.net/SerialNumberEntitlementSearch/>

Opening a Case with JTAC

You can open a case with JTAC on the Web or by telephone.

- Use the Case Management tool in the CSC at <http://www.juniper.net/cm/>.
- Call 1-888-314-JTAC (1-888-314-5822 toll-free in the USA, Canada, and Mexico).

For international or direct-dial options in countries without toll-free numbers, see <http://www.juniper.net/support/requesting-support.html>.

PART 1

Overview

- [High Availability Overview on page 3](#)
- [Routing Engine and Switching Control Board Redundancy on page 11](#)
- [Graceful Routing Engine Switchover \(GRES\) on page 21](#)
- [Nonstop Bridging on page 31](#)
- [Nonstop Active Routing on page 35](#)
- [Graceful Restart on page 49](#)
- [VRRP on page 59](#)
- [Unified ISSU on page 67](#)

CHAPTER 1

High Availability Overview

- [Understanding High Availability Features on Juniper Networks Routers on page 3](#)
- [High Availability-Related Features in Junos OS on page 8](#)

Understanding High Availability Features on Juniper Networks Routers

For Juniper Networks routing platforms running the Junos operating system (Junos OS), *high availability* refers to the hardware and software components that provide redundancy and reliability for packet-based communications. This topic provides brief overviews of the following high availability features:

- [Routing Engine Redundancy on page 3](#)
- [Graceful Routing Engine Switchover on page 3](#)
- [Nonstop Bridging on page 4](#)
- [Nonstop Active Routing on page 4](#)
- [Graceful Restart on page 5](#)
- [Nonstop Active Routing Versus Graceful Restart on page 6](#)
- [Effects of a Routing Engine Switchover on page 7](#)
- [VRRP on page 7](#)
- [Unified ISSU on page 7](#)
- [Interchassis Redundancy for MX Series Routers Using Virtual Chassis on page 7](#)

Routing Engine Redundancy

Redundant Routing Engines are two Routing Engines that are installed in the same routing platform. One functions as the master, while the other stands by as a backup should the master Routing Engine fail. On routing platforms with dual Routing Engines, network convergence takes place more quickly than on routing platforms with a single Routing Engine.

Graceful Routing Engine Switchover

Graceful Routing Engine switchover (GRES) enables a routing platform with redundant Routing Engines to continue forwarding packets, even if one Routing Engine fails. Graceful Routing Engine switchover preserves interface and kernel information. Traffic is not interrupted. However, graceful Routing Engine switchover does not preserve the control

plane. Neighboring routers detect that the router has experienced a restart and react to the event in a manner prescribed by individual routing protocol specifications.



NOTE: To preserve routing during a switchover, graceful Routing Engine switchover must be combined with either graceful restart protocol extensions or nonstop active routing. For more information, see [“Understanding Graceful Routing Engine Switchover in the Junos OS” on page 21](#) and [“Nonstop Active Routing Concepts” on page 35](#).



NOTE: In T Series routers, TX Matrix routers, and TX Matrix Plus routers, the control plane is preserved in case of GRES with NSR, and 75% of line rate worth of traffic per Packet Forwarding Engine remains uninterrupted during GRES.

Nonstop Bridging

Nonstop bridging enables an MX Series 3D Universal Edge Router with redundant Routing Engines to switch from a primary Routing Engine to a backup Routing Engine without losing Layer 2 Control Protocol (L2CP) information. Nonstop bridging uses the same infrastructure as graceful Routing Engine switchover to preserve interface and kernel information. However, nonstop bridging also saves L2CP information by running the Layer 2 Control Protocol process (l2cpd) on the backup Routing Engine.



NOTE: To use nonstop bridging, you must first enable graceful Routing Engine switchover.

Nonstop bridging is supported for the following Layer 2 control protocols:

- Spanning Tree Protocol (STP)
- Rapid Spanning Tree Protocol (RSTP)
- Multiple Spanning Tree Protocol (MSTP)

For more information, see [“Nonstop Bridging Concepts” on page 31](#).

Nonstop Active Routing

Nonstop active routing (NSR) enables a routing platform with redundant Routing Engines to switch from a primary Routing Engine to a backup Routing Engine without alerting peer nodes that a change has occurred. Nonstop active routing uses the same infrastructure as graceful Routing Engine switchover to preserve interface and kernel information. However, nonstop active routing also preserves routing information and protocol sessions by running the routing protocol process (rpd) on both Routing Engines. In addition, nonstop active routing preserves TCP connections maintained in the kernel.



NOTE: To use nonstop active routing, you must also configure graceful Routing Engine switchover.

For a list of protocols and features supported by nonstop active routing, see [“Nonstop Active Routing Protocol and Feature Support” on page 39](#).

For more information about nonstop active routing, see [“Nonstop Active Routing Concepts” on page 35](#).

Graceful Restart

With routing protocols, any service interruption requires an affected router to recalculate adjacencies with neighboring routers, restore routing table entries, and update other protocol-specific information. An unprotected restart of a router can result in forwarding delays, route flapping, wait times stemming from protocol reconvergence, and even dropped packets. To alleviate this situation, graceful restart provides extensions to routing protocols. These protocol extensions define two roles for a router—*restarting* and *helper*. The extensions signal neighboring routers about a router undergoing a restart and prevent the neighbors from propagating the change in state to the network during a graceful restart wait interval. The main benefits of graceful restart are uninterrupted packet forwarding and temporary suppression of all routing protocol updates. Graceful restart enables a router to pass through intermediate convergence states that are hidden from the rest of the network.

When a router is running graceful restart and the router stops sending and replying to protocol liveness messages (hellos), the adjacencies assume a graceful restart and begin running a timer to monitor the restarting router. During this interval, helper routers do not process an adjacency change for the router that they assume is restarting, but continue active routing with the rest of the network. The helper routers assume that the router can continue stateful forwarding based on the last preserved routing state during the restart.

If the router was actually restarting and is back up before the graceful timer period expires in all of the helper routers, the helper routers provide the router with the routing table, topology table, or label table (depending on the protocol), exit the graceful period, and return to normal network routing.

If the router does not complete its negotiation with helper routers before the graceful timer period expires in all of the helper routers, the helper routers process the router's change in state and send routing updates, so that convergence occurs across the network. If a helper router detects a link failure from the router, the topology change causes the helper router to exit the graceful wait period and to send routing updates, so that network convergence occurs.

To enable a router to undergo a graceful restart, you must include the **graceful-restart** statement at either the global **[edit routing-options]** hierarchy level. When a routing session is started, a router that is configured with graceful restart must negotiate with its neighbors to support it when it undergoes a graceful restart. A neighboring router will

accept the negotiation and support helper mode without requiring graceful restart to be configured on the neighboring router.



NOTE: A Routing Engine switchover event on a helper router that is in graceful wait state causes the router to drop the wait state and to propagate the adjacency's state change to the network.

Graceful restart is supported for the following protocols and applications:

- BGP
- ES-IS
- IS-IS
- OSPF/OSPFv3
- PIM sparse mode
- RIP/RIPng
- MPLS-related protocols, including:
 - Label Distribution Protocol (LDP)
 - Resource Reservation Protocol (RSVP)
 - Circuit cross-connect (CCC)
 - Translational cross-connect (TCC)
- Layer 2 and Layer 3 virtual private networks (VPNs)

For more information, see [“Graceful Restart Concepts” on page 49](#).

Nonstop Active Routing Versus Graceful Restart

Nonstop active routing and graceful restart are two different methods of maintaining high availability. Graceful restart requires a router restart. A router undergoing a graceful restart relies on its neighbors (or helpers) to restore its routing protocol information. The restart is the mechanism by which helpers are signaled to exit the wait interval and start providing routing information to the restarting router. For more information, see [“Graceful Restart Concepts” on page 49](#).

In contrast, nonstop active routing does not involve a router restart. Both the master and standby Routing Engines are running the routing protocol process (rpd) and exchanging updates with neighbors. When one Routing Engine fails, the router simply switches to the active Routing Engine to exchange routing information with neighbors. Because of these feature differences, nonstop routing and graceful restart are mutually exclusive. Nonstop active routing cannot be enabled when the router is configured as a graceful restarting router. If you include the **graceful-restart** statement at any hierarchy level and the **nonstop-routing** statement at the **[edit routing-options]** hierarchy level and try to commit the configuration, the commit request fails. For more information, see [“Nonstop Active Routing Concepts” on page 35](#).

Effects of a Routing Engine Switchover

[“Effects of a Routing Engine Switchover” on page 21](#) describes the effects of a Routing Engine switchover when no high availability features are enabled and when graceful Routing Engine switchover, graceful restart, and nonstop active routing features are enabled.

VRRP

For Ethernet, Fast Ethernet, Gigabit Ethernet, 10-Gigabit Ethernet, and logical interfaces, you can configure the Virtual Router Redundancy Protocol (VRRP) or VRRP for IPv6. VRRP enables hosts on a LAN to make use of redundant routing platforms on that LAN without requiring more than the static configuration of a single default route on the hosts. The VRRP routing platforms share the IP address corresponding to the default route configured on the hosts. At any time, one of the VRRP routing platforms is the master (active) and the others are backups. If the master fails, one of the backup routers becomes the new master router, providing a virtual default routing platform and allowing traffic on the LAN to be routed without relying on a single routing platform. Using VRRP, a backup router can take over a failed default router within a few seconds. This is done with minimum VRRP traffic and without any interaction with the hosts.

Routers running VRRP dynamically elect master and backup routers. You can also force assignment of master and backup routers using priorities from 1 through 255, with 255 being the highest priority. In VRRP operation, the default master router sends advertisements to backup routers at regular intervals. The default interval is 1 second. If a backup router does not receive an advertisement for a set period, the backup router with the next highest priority takes over as master and begins forwarding packets.

For more information, see [“Understanding VRRP” on page 59](#).

Unified ISSU

A unified in-service software upgrade (unified ISSU) enables you to upgrade between two different Junos OS Releases with no disruption on the control plane and with minimal disruption of traffic. Unified ISSU is only supported by dual Routing Engine platforms. In addition, graceful Routing Engine switchover (GRES) and nonstop active routing (NSR) must be enabled.

With a unified ISSU, you can eliminate network downtime, reduce operating costs, and deliver higher services levels. For more information, see [“Unified ISSU Concepts” on page 67](#).

Interchassis Redundancy for MX Series Routers Using Virtual Chassis

Interchassis redundancy is a high availability feature that can span equipment located across multiple geographies to prevent network outages and protect routers against access link failures, uplink failures, and wholesale chassis failures without visibly disrupting the attached subscribers or increasing the network management burden for service providers. As more high-priority voice and video traffic is carried on the network, interchassis redundancy has become a requirement for providing stateful redundancy on broadband subscriber management equipment such as broadband services routers,

broadband network gateways, and broadband remote access servers. Interchassis redundancy support enables service providers to fulfill strict service-level agreements (SLAs) and avoid unplanned network outages to better meet the needs of their customers.

To provide a stateful interchassis redundancy solution for MX Series 3D Universal Edge Routers, you can configure a Virtual Chassis. A *Virtual Chassis* configuration interconnects two MX Series routers into a logical system that you can manage as a single network element. The member routers in a Virtual Chassis are designated as the *master router* (also known as the *protocol master*) and the *backup router* (also known as the *protocol backup*). The member routers are interconnected by means of dedicated *Virtual Chassis ports* that you configure on Trio Modular Port Concentrator/Modular Interface Card (MPC/MIC) interfaces.

An MX Series Virtual Chassis is managed by the *Virtual Chassis Control Protocol (VCCP)*, which is a dedicated control protocol based on IS-IS. VCCP runs on the Virtual Chassis port interfaces and is responsible for building the Virtual Chassis topology, electing the Virtual Chassis master router, and establishing the interchassis routing table to route traffic within the Virtual Chassis.

Starting with Junos OS Release 11.2, Virtual Chassis configurations are supported on MX240, MX480, and MX960 3D Universal Edge Routers with Trio MPC/MIC interfaces and dual Routing Engines. In addition, graceful Routing Engine switchover (GRES) and nonstop active routing (NSR) must be enabled on both member routers in the Virtual Chassis.

Related Documentation • [High Availability-Related Features in Junos OS on page 8](#)

High Availability-Related Features in Junos OS

Related redundancy and reliability features include:

- Redundant power supplies, host modules, host subsystems, and forwarding boards. For more information, see the Junos OS System Basics Configuration Guide and the *Junos OS Hardware Network Operations Guide*.
- Additional link-layer redundancy, including Automatic Protection Switching (APS) for SONET interfaces, Multiplex Section Protection (MSP) for SDH interfaces, and DLSw redundancy for Ethernet interfaces. For more information, see the Junos® OS Network Interfaces.
- Bidirectional Forwarding Detection (BFD) works with other routing protocols to detect failures rapidly. For more information, see the Junos OS Routing Protocols Configuration Guide.
- Redirection of Multiprotocol Label Switching (MPLS) label-switched path (LSP) traffic—Mechanisms such as link protection, node-link protection, and fast reroute recognize link and node failures, allowing MPLS LSPs to select a bypass LSP to circumvent failed links or devices. For more information, see the Junos OS MPLS Applications Configuration Guide.

- Related Documentation**
- [Understanding High Availability Features on Juniper Networks Routers on page 3](#)

CHAPTER 2

Routing Engine and Switching Control Board Redundancy

- [Understanding Routing Engine Redundancy on Juniper Networks Routers on page 11](#)
- [Switching Control Board Redundancy on page 16](#)

Understanding Routing Engine Redundancy on Juniper Networks Routers

This topic contains the following sections:

- [Routing Engine Redundancy Overview on page 11](#)
- [Conditions That Trigger a Routing Engine Failover on page 12](#)
- [Default Routing Engine Redundancy Behavior on page 13](#)
- [Routing Engine Redundancy on a TX Matrix Router on page 13](#)
- [Routing Engine Redundancy on a TX Matrix Plus Router on page 15](#)
- [Situations That Require You to Halt Routing Engines on page 16](#)

Routing Engine Redundancy Overview

Redundant Routing Engines are two Routing Engines that are installed in the same routing platform. One functions as the master, while the other stands by as a backup should the master Routing Engine fail. On routing platforms with dual Routing Engines, network reconvergence takes place more quickly than on routing platforms with a single Routing Engine.

When a Routing Engine is configured as master, it has full functionality. It receives and transmits routing information, builds and maintains routing tables, communicates with interfaces and Packet Forwarding Engine components, and has full control over the chassis. When a Routing Engine is configured to be the backup, it does not communicate with the Packet Forwarding Engine or chassis components.



NOTE: On devices running Junos OS Release 8.4 or later, both Routing Engines cannot be configured to be master at the same time. This configuration causes the commit check to fail.

A failover from the master Routing Engine to the backup Routing Engine occurs automatically when the master Routing Engine experiences a hardware failure or when you have configured the software to support a change in mastership based on specific conditions. You can also manually switch Routing Engine mastership by issuing one of the **request chassis routing-engine** commands. In this topic, the term *failover* refers to an automatic event, whereas *switchover* refers to either an automatic or a manual event.

When a failover or a switchover occurs, the backup Routing Engine takes control of the system as the new master Routing Engine.

- If graceful Routing Engine switchover is not configured, when the backup Routing Engine becomes master, it resets the switch plane and downloads its own version of the microkernel to the Packet Forwarding Engine components. Traffic is interrupted while the Packet Forwarding Engine is reinitialized. All kernel and forwarding processes are restarted.
- If graceful Routing Engine switchover is configured, interface and kernel information is preserved. The switchover is faster because the Packet Forwarding Engines are not restarted. The new master Routing Engine restarts the routing protocol process (rpd). All hardware and interfaces are acquired by a process that is similar to a warm restart. For more information about graceful Routing Engine switchover, see [“Understanding Graceful Routing Engine Switchover in the Junos OS” on page 21](#).
- If graceful Routing Engine switchover and nonstop active routing (NSR) are configured, traffic is not interrupted during the switchover. Interface, kernel, and routing protocol information is preserved. For more information about nonstop active routing, see [“Nonstop Active Routing Concepts” on page 35](#).
- If graceful Routing Engine switchover and graceful restart are configured, traffic is not interrupted during the switchover. Interface and kernel information is preserved. Graceful restart protocol extensions quickly collect and restore routing information from the neighboring routers. For more information about graceful restart, see [“Graceful Restart Concepts” on page 49](#).

Conditions That Trigger a Routing Engine Failover

The following events can result in an automatic change in Routing Engine mastership, depending on your configuration:

- The routing platform experiences a hardware failure. A change in Routing Engine mastership occurs if either the Routing Engine or the associated host module or subsystem is abruptly powered off. You can also configure the backup Routing Engine to take mastership if it detects a hard disk error on the master Routing Engine. To enable this feature, include the **failover on-disk-failure** statement at the **[edit chassis redundancy]** hierarchy level.
- The routing platform experiences a software failure, such as a kernel crash or a CPU lock. You must configure the backup Routing Engine to take mastership when it detects a loss of keepalive signal. To enable this failover method, include the **failover on-loss-of-keepalives** statement at the **[edit chassis redundancy]** hierarchy level.

- A specific software process fails. You can configure the backup Routing Engine to take mastership when one or more specified processes fail at least four times within 30 seconds. Include the **failover other-routing-engine** statement at the **[edit system processes process-name]** hierarchy level.

If any of these conditions is met, a message is logged and the backup Routing Engine attempts to take mastership. By default, an alarm is generated when the backup Routing Engine becomes active. After the backup Routing Engine takes mastership, it continues to function as master even after the originally configured master Routing Engine has successfully resumed operation. You must manually restore it to its previous backup status. (However, if at any time one of the Routing Engines is not present, the other Routing Engine becomes master automatically, regardless of how redundancy is configured.)

Default Routing Engine Redundancy Behavior

By default, Junos OS uses **re0** as the master Routing Engine and **re1** as the backup Routing Engine. Unless otherwise specified in the configuration, **re0** always becomes master when the acting master Routing Engine is rebooted.



NOTE: A single Routing Engine in the chassis always becomes the master Routing Engine even if it was previously the backup Routing Engine.

Perform the following steps to see how the default Routing Engine redundancy setting works:

1. Ensure that **re0** is the master Routing Engine.
2. Manually switch the state of Routing Engine mastership by issuing the **request chassis routing-engine master switch** command from the master Routing Engine. **re0** is now the backup Routing Engine and **re1** is the master Routing Engine.



NOTE: On the next reboot of the master Routing Engine, Junos OS returns the router to the default state because you have not configured the Routing Engines to maintain this state after a reboot.

3. Reboot the master Routing Engine **re1**.

The Routing Engine boots up and reads the configuration. Because you have not specified in the configuration which Routing Engine is the master, **re1** uses the default configuration as the backup. Now both **re0** and **re1** are in a backup state. Junos OS detects this conflict and, to prevent a no-master state, reverts to the default configuration to direct **re0** to become master.

Routing Engine Redundancy on a TX Matrix Router

In a routing matrix, all master Routing Engines in the TX Matrix router and connected T640 routers must run the same Junos OS release. Likewise, all backup Routing Engines in a routing matrix must run the same Junos OS release. When you run the same Junos

OS release on all master and backup Routing Engines in a routing matrix, a change in mastership to any backup Routing Engine in the routing matrix does not cause a change in mastership in any other chassis in the routing matrix.



CAUTION: (Routing matrix based on the TX Matrix or TX Matrix Plus routers only) Within the routing matrix, we recommend that all Routing Engines run the same Junos OS release. If you run different releases on the Routing Engines and a change in mastership occurs on any backup Routing Engine in the routing matrix based on TX Matrix router or TX Matrix Plus router, one or all routers might become logically disconnected from the TX Matrix router or the TX Matrix Plus router and cause data loss.

If the same Junos OS release is not running on all master and backup Routing Engines in the routing matrix, the following consequences occur when the **failover on-loss-of-keepalives** statement *is* included at the **[edit chassis redundancy]** hierarchy level:

- When the **failover on-loss-of-keepalives** statement is included at the **[edit chassis redundancy]** hierarchy level and you or a host subsystem initiates a change in mastership to the backup Routing Engine in the TX Matrix router, the master Routing Engines in the T640 routers detect a software release mismatch with the new master Routing Engine in the TX Matrix router and switch mastership to their backup Routing Engines.
- When you manually change mastership to a backup Routing Engine in a T640 router using the **request chassis routing-engine master** command, the new master Routing Engine in the T640 router detects a software release mismatch with the master Routing Engine in the TX Matrix router and relinquishes mastership to the original master Routing Engine. (Routing Engine mastership in the TX Matrix router does not switch in this case.)
- When a host subsystem initiates a change in mastership to a backup Routing Engine in a T640 router because the master Routing Engine has failed, the T640 router is logically disconnected from the TX Matrix router. To reconnect the T640 router, initiate a change in mastership to the backup Routing Engine in the TX Matrix router, or replace the failed Routing Engine in the T640 router and switch mastership to it. The replacement Routing Engine must be running the same software release as the master Routing Engine in the TX Matrix router.

If the same Junos OS release is not running on all master and backup Routing Engines in the routing matrix, the following consequences occur when the **failover on-loss-of-keepalives** statement *is not* included at the **[edit chassis redundancy]** hierarchy level:

- If you initiate a change in mastership to the backup Routing Engine in the TX Matrix router, all T640 routers are logically disconnected from the TX Matrix router. To reconnect the T640 routers, switch mastership of all master Routing Engines in the T640 routers to their backup Routing Engines.
- If you initiate a change in mastership to a backup Routing Engine in a T640 router, the T640 router is logically disconnected from the TX Matrix router. To reconnect the T640

router, switch mastership of the new master Routing Engine in the T640 router back to the original master Routing Engine.

Routing Engine Redundancy on a TX Matrix Plus Router

In a routing matrix, all master Routing Engines in the TX Matrix Plus router and the connected LCC must run the same Junos OS release. Likewise, all backup Routing Engines in a routing matrix must run the same Junos OS release. When you run the same Junos OS release on all master and backup Routing Engines in the routing matrix, a change in mastership to any backup Routing Engine in the routing matrix does not cause a change in mastership in any other chassis in the routing matrix.



CAUTION: (Routing matrix based on the TX Matrix or TX Matrix Plus routers only) Within the routing matrix, we recommend that all Routing Engines run the same Junos OS release. If you run different releases on the Routing Engines and a change in mastership occurs on any backup Routing Engine in the routing matrix based on a TX Matrix router or a TX Matrix Plus router, one or all routers might become logically disconnected from the TX Matrix router or the TX Matrix Plus router and cause data loss.

If the same Junos OS release is not running on all master and backup Routing Engines in the routing matrix, the following scenarios occur when the **failover on-loss-of-keepalives** statement is included at the **[edit chassis redundancy]** hierarchy level:

- When the **failover on-loss-of-keepalives** statement is included at the **[edit chassis redundancy]** hierarchy level and you or a host subsystem initiates a change in mastership to the backup Routing Engine in the TX Matrix Plus router, the master Routing Engines in the connected LCC detect a software release mismatch with the new master Routing Engine in the TX Matrix Plus router and switch mastership to their backup Routing Engines.
- When you manually change mastership to a backup Routing Engine in a connected LCC by using the **request chassis routing-engine master** command, the new master Routing Engine in the connected LCC detects a software release mismatch with the master Routing Engine in the TX Matrix Plus router and relinquishes mastership to the original master Routing Engine. (Routing Engine mastership in the TX Matrix Plus router does not switch in this case.)
- When a host subsystem initiates a change in mastership to a backup Routing Engine in a connected LCC because the master Routing Engine has failed, the connected LCC is logically disconnected from the TX Matrix Plus router. To reconnect the connected LCC, initiate a change in mastership to the backup Routing Engine in the TX Matrix Plus router, or replace the failed Routing Engine in the connected LCC and switch mastership to it. The replacement Routing Engine must be running the same software release as the master Routing Engine in the TX Matrix Plus router.

If the same Junos OS release is not running on all master and backup Routing Engines in the routing matrix, the following scenarios occur when the **failover on-loss-of-keepalives** statement *is not* included at the **[edit chassis redundancy]** hierarchy level:

- If you initiate a change in mastership to the backup Routing Engine in the TX Matrix Plus router, all connected LCCs are logically disconnected from the TX Matrix Plus router. To reconnect the connected LCC, switch mastership of all master Routing Engines in the connected LCC to their backup Routing Engines.
- If you initiate a change in mastership to a backup Routing Engine in a connected LCC, the connected LCC is logically disconnected from the TX Matrix Plus router. To reconnect the connected LCC, switch mastership of the new master Routing Engine in the connected LCC back to the original master Routing Engine.

Situations That Require You to Halt Routing Engines

Before you shut the power off to a routing platform that has two Routing Engines or before you remove the master Routing Engine, you must first halt the backup Routing Engine and then halt the master Routing Engine. Otherwise, you might need to reinstall Junos OS. You can use the **request system halt both-routing-engines** command on the master Routing Engine, which first shuts down the master Routing Engine and then shuts down the backup Routing Engine. To shut down only the backup Routing Engine, issue the **request system halt** command on the backup Routing Engine.

If you halt the master Routing Engine and do not power it off or remove it, the backup Routing Engine remains inactive unless you have configured it to become the master when it detects a loss of keepalive signal from the master Routing Engine.



NOTE: To restart the router, you must log in to the console port (rather than the Ethernet management port) of the Routing Engine. When you log in to the console port of the master Routing Engine, the system automatically reboots. After you log in to the console port of the backup Routing Engine, press Enter to reboot it.



NOTE: If you have upgraded the backup Routing Engine, first reboot it and then reboot the master Routing Engine.

Related Documentation

- [Understanding High Availability Features on Juniper Networks Routers on page 3](#)
- [Switching Control Board Redundancy on page 16](#)
- [Configuring Routing Engine Redundancy on page 89](#)

Switching Control Board Redundancy

This section describes the following redundant switching control boards:



NOTE: A failover from a master switching control board to a backup switching control board occurs automatically when the master experiences a hardware failure or when you have configured the software to support a change in mastership based on specific conditions. You can also manually switch mastership by issuing specific `request chassis` commands. In this chapter, the term *failover* refers to an automatic event, whereas *switchover* refers to either an automatic or a manual event.

- [Redundant CFEBs on the M10i Router on page 17](#)
- [Redundant FEBs on the M120 Router on page 17](#)
- [Redundant SSBs on the M20 Router on page 19](#)
- [Redundant SFMs on the M40e and M160 Routers on page 20](#)

Redundant CFEBs on the M10i Router

On the M10i router, the CFEB performs the following functions:

- Route lookups—Performs route lookups using the forwarding table stored in synchronous SRAM (SSRAM).
- Management of shared memory—Uniformly allocates incoming data packets throughout the router's shared memory.
- Transfer of outgoing data packets—Passes data packets to the destination Fixed Interface Card (FIC) or Physical Interface Card (PIC) when the data is ready to be transmitted.
- Transfer of exception and control packets—Passes exception packets to the microprocessor on the CFEB, which processes almost all of them. The remainder are sent to the Routing Engine for further processing. Any errors originating in the Packet Forwarding Engine and detected by the CFEB are sent to the Routing Engine using system log messages.

The M10i router has two CFEBs, one that is configured to act as the master and the other that serves as a backup in case the master fails. You can initiate a manual switchover by issuing the `request chassis cfeb master switch` command. For more information, see the Junos OS System Basics Configuration Guide.

Redundant FEBs on the M120 Router

The M120 router supports up to six Forwarding Engine Boards (FEBs). Flexible PIC Concentrator (FPCs), which host PICs, are separate from the FEBs, which handle packet forwarding. FPCs are located on the front of the chassis and provide power and management to PICs through the midplane. FEBs are located on the back of the chassis and receive signals from the midplane, which the FEBs process for packet forwarding. The midplane allows any FEB to carry traffic for any FPC.

To configure the mapping of FPCs to FEBs, use the `fpc-feb-connectivity` statement as described in the Junos OS System Basics Configuration Guide. You cannot specify a connection between an FPC and a FEB configured as a backup. If an FPC is not specified

to connect to a FEB, the FPC is assigned automatically to the FEB with the same slot number. For example, the FPC in slot 1 is assigned to the FEB in slot 1.

You can configure one FEB as a backup for one or more FEBs by configuring a FEB redundancy group. When a FEB fails, the backup FEB can quickly take over packet forwarding. A redundancy group must contain exactly one backup FEB and can optionally contain one primary FEB and multiple other FEBs. A FEB can belong to only one group. A group can provide backup on a one-to-one basis (primary-to-backup), a many-to-one basis (two or more other-FEBs-to-backup), or a combination of both (one primary-to-backup and one or more other-FEBs-to-backup).

When you configure a primary FEB in a redundancy group, the backup FEB mirrors the exact forwarding state of the primary FEB. If switchover occurs from a primary FEB, the backup FEB does not reboot. A manual switchover from the primary FEB to the backup FEB results in less than 1 second of traffic loss. Failover from the primary FEB to the backup FEB results in less than 10 seconds of traffic loss.

If a failover occurs from the other FEB and a primary FEB is specified for the group, the backup FEB reboots so that the forwarding state from the other FEB can be downloaded to the backup FEB and forwarding can continue. Automatic failover from a FEB that is not specified as a primary FEB results in higher packet loss. The duration of packet loss depends on the number of interfaces and on the size of the routing table, but it can be minutes.

If a failover from a FEB occurs when no primary FEB is specified in the redundancy group, the backup FEB does not reboot and the interfaces on the FPC connected to the previously active FEB remain online. The backup FEB must obtain the entire forwarding state from the Routing Engine after a switchover, and this update may take a few minutes. If you do not want the interfaces to remain online during the switchover for the other FEB, configure a primary FEB for the redundancy group.

Failover to a backup FEB occurs automatically if a FEB in a redundancy group fails. You can disable automatic failover for any redundancy group by including the **no-auto-failover** statement at the **[edit chassis redundancy feb redundancy-group group-name]** hierarchy level.

You can also initiate a manual switchover by issuing the **request chassis redundancy feb slot slot-number switch-to-backup** command, where **slot-number** is the number of the active FEB. For more information, see the Junos OS Operational Mode Commands.

The following conditions result in failover as long as the backup FEB in a redundancy group is available:

- The FEB is absent.
- The FEB experienced a hard error while coming online.
- A software failure on the FEB resulted in a crash.
- Ethernet connectivity from a FEB to a Routing Engine failed.
- A hard error on the FEB, such as a power failure, occurred.
- The FEB was disabled when the offline button for the FEB was pressed.

- The software watchdog timer on the FEB expired.
- Errors occurred on the links between all the active fabric planes and the FEB. This situation results in failover to the backup FEB if it has at least one valid fabric link.
- Errors occurred on the link between the FEB and all of the FPCs connected to it.

After a switchover occurs, a backup FEB is no longer available for the redundancy group. You can revert from the backup FEB to the previously active FEB by issuing the operational mode command **request chassis redundancy feb slot *slot-number* revert-from-backup**, where ***slot-number*** is the number of the previously active FEB. For more information, see the Junos OS Operational Mode Commands.

When you revert from the backup FEB, it becomes available again for a switchover. If the redundancy group does not have a primary FEB, the backup FEB reboots after you revert back to the previously active FEB. If the FEB to which you revert back is not a primary FEB, the backup FEB is rebooted so that it can align with the state of the primary FEB.

If you modify the configuration for an existing redundancy group so that a FEB connects to a different FPC, the FEB is rebooted unless the FEB was already connected to one or two Type 1 FPCs and the change only resulted in the FEB being connected either to one additional or one fewer Type 1 FPC. For more information about how to map a connection between an FPC and a FEB, see the Junos OS System Basics Configuration Guide. If you change the primary FEB in a redundancy group, the backup FEB is rebooted. The FEB is also rebooted if you change a backup FEB to a nonbackup FEB or change an active FEB to a backup FEB.

To view the status of configured FEB redundancy groups, issue the **show chassis redundancy feb** operational mode command. For more information, see the Junos OS Operational Mode Commands.

Redundant SSBs on the M20 Router

The System and Switch Board (SSB) on the M20 router performs the following major functions:

- Shared memory management on the FPCs—The Distributed Buffer Manager ASIC on the SSB uniformly allocates incoming data packets throughout shared memory on the FPCs.
- Outgoing data cell transfer to the FPCs—A second Distributed Buffer Manager ASIC on the SSB passes data cells to the FPCs for packet reassembly when the data is ready to be transmitted.
- Route lookups—The Internet Processor ASIC on the SSB performs route lookups using the forwarding table stored in SSRAM. After performing the lookup, the Internet Processor ASIC informs the midplane of the forwarding decision, and the midplane forwards the decision to the appropriate outgoing interface.
- System component monitoring—The SSB monitors other system components for failure and alarm conditions. It collects statistics from all sensors in the system and relays them to the Routing Engine, which sets the appropriate alarm. For example, if a temperature sensor exceeds the first internally defined threshold, the Routing Engine

issues a “high temp” alarm. If the sensor exceeds the second threshold, the Routing Engine initiates a system shutdown.

- Exception and control packet transfer—The Internet Processor ASIC passes exception packets to a microprocessor on the SSB, which processes almost all of them. The remaining packets are sent to the Routing Engine for further processing. Any errors that originate in the Packet Forwarding Engine and are detected by the SSB are sent to the Routing Engine using system log messages.
- FPC reset control—The SSB monitors the operation of the FPCs. If it detects errors in an FPC, the SSB attempts to reset the FPC. After three unsuccessful resets, the SSB takes the FPC offline and informs the Routing Engine. Other FPCs are unaffected, and normal system operation continues.

The M20 router holds up to two SSBs. One SSB is configured to act as the master and the other is configured to serve as a backup in case the master fails. You can initiate a manual switchover by issuing the **request chassis ssb master switch** command. For more information, see the Junos OS Operational Mode Commands.

Redundant SFMs on the M40e and M160 Routers

The M40e and M160 routers have redundant Switching and Forwarding Modules (SFMs). The SFMs contain the Internet Processor II ASIC and two Distributed Buffer Manager ASICs. SFMs ensure that all traffic leaving the FPCs is handled properly. SFMs provide route lookup, filtering, and switching.

The M40e router holds up to two SFMs, one that is configured to act as the master and the other configured to serve as a backup in case the master fails. Removing the standby SFM has no effect on router function. If the active SFM fails or is removed from the chassis, forwarding halts until the standby SFM boots and becomes active. It takes approximately 1 minute for the new SFM to become active. Synchronizing router configuration information can take additional time, depending on the complexity of the configuration.

The M160 router holds up to four SFMs. All SFMs are active at the same time. A failure or taking an SFM offline has no effect on router function. Forwarding continues uninterrupted.

You can initiate a manual switchover by issuing the **request chassis sfm master switch** command. For more information, see the Junos OS Operational Mode Commands.

Related Documentation

- [Understanding High Availability Features on Juniper Networks Routers on page 3](#)
- [Understanding Routing Engine Redundancy on Juniper Networks Routers on page 11](#)
- [Configuring CFEB Redundancy on the M10i Router on page 93](#)
- [Configuring FEB Redundancy on the M120 Router on page 94](#)
- [Configuring SFM Redundancy on M40e and M160 Routers on page 96](#)
- [Configuring SSB Redundancy on the M20 Router on page 97](#)
- `show chassis redundancy feb`

CHAPTER 3

Graceful Routing Engine Switchover (GRES)

- [Understanding Graceful Routing Engine Switchover in the Junos OS on page 21](#)
- [Graceful Routing Engine Switchover System Requirements on page 25](#)
- [Requirements for Routers with a Backup Router Configuration on page 29](#)

Understanding Graceful Routing Engine Switchover in the Junos OS

This topic contains the following sections:

- [Graceful Routing Engine Switchover Concepts on page 21](#)
- [Effects of a Routing Engine Switchover on page 25](#)

Graceful Routing Engine Switchover Concepts

Graceful Routing Engine switchover (GRES) feature in Junos OS enables a routing platform with redundant Routing Engines to continue forwarding packets, even if one Routing Engine fails. Graceful Routing Engine switchover preserves interface and kernel information. Traffic is not interrupted. However, graceful Routing Engine switchover does not preserve the control plane. Note that on T Series routers, TX Matrix routers, and TX Matrix Plus routers, the control plane is preserved in case of GRES with NSR and nearly 75% of line rate worth of traffic per Packet Forwarding Engine remains uninterrupted during GRES. Neighboring routers detect that the router has experienced a restart and react to the event in a manner prescribed by individual routing protocol specifications. To preserve routing during a switchover, graceful Routing Engine switchover must be combined with either graceful restart protocol extensions or nonstop active routing. Any updates to the master Routing Engine are replicated to the backup Routing Engine as soon as they occur. If the kernel on the master Routing Engine stops operating, the master Routing Engine experiences a hardware failure, or the administrator initiates a manual switchover, mastership switches to the backup Routing Engine.



NOTE: To quickly restore or to preserve routing protocol state information during a switchover, graceful Routing Engine switchover must be combined with either graceful restart or nonstop active routing (NSR), respectively. For more information about graceful restart, see [“Graceful Restart Concepts” on page 49](#). For more information about nonstop active routing, see [“Nonstop Active Routing Concepts” on page 35](#).

If the backup Routing Engine does not receive a keepalive from the master Routing Engine after 2 seconds (4 seconds on M20 routers), it determines that the master Routing Engine has failed and takes mastership. The Packet Forwarding Engine seamlessly disconnects from the old master Routing Engine and reconnects to the new master Routing Engine. The Packet Forwarding Engine does not reboot, and traffic is not interrupted. The new master Routing Engine and the Packet Forwarding Engine then become synchronized. If the new master Routing Engine detects that the Packet Forwarding Engine state is not up to date, it resends state update messages.



NOTE: Successive Routing Engine switchover events must be a minimum of 240 seconds (4 minutes) apart after both Routing Engines have come up.

If the router displays a warning message similar to **Standby Routing Engine is not ready for graceful switchover. Packet Forwarding Engines that are not ready for graceful switchover might be reset**. Do not attempt switchover. If you choose to proceed with switchover, only the Packet Forwarding Engines that were not ready for graceful switchover are reset. None of the FPCs should spontaneously restart. We recommend that you wait until the warning no longer appears and then proceed with the switchover.


Note that in a routing matrix with TX Matrix Plus router with 3D SIBs, for successive Routing Engine switchover, events must be a minimum of 900 seconds (15 minutes) apart after both Routing Engines have come up.



NOTE: We do not recommend performing a commit operation on the backup Routing Engine when graceful Routing Engine switchover is enabled on the router.

[Figure 1 on page 23](#) shows the system architecture of graceful Routing Engine switchover and the process a routing platform follows to prepare for a switchover.

Figure 1: Preparing for a Graceful Routing Engine Switchover




The switchover preparation process for graceful Routing Engine switchover follows these steps:

1. The master Routing Engine starts.
2. The routing platform processes (such as the chassis process [chassisd]) start.
3. The Packet Forwarding Engine starts and connects to the master Routing Engine.
4. All state information is updated in the system.
5. The backup Routing Engine starts.
6. The system determines whether graceful Routing Engine switchover has been enabled.
7. The kernel synchronization process (ksyncd) synchronizes the backup Routing Engine with the master Routing Engine.
8. After ksyncd completes the synchronization, all state information and the forwarding table are updated.

Figure 2 on page 24 shows the effects of a switchover on the routing platform.

Figure 2: Graceful Routing Engine Switchover Process



When a switchover occurs, the switchover process follows these steps:

1. When keepalives from the master Routing Engine are lost, the system switches over gracefully to the backup Routing Engine.
2. The Packet Forwarding Engine connects to the backup Routing Engine, which becomes the new master.
3. Routing platform processes that are not part of graceful Routing Engine switchover (such as the routing protocol process [rpd]) restart.
4. State information learned from the point of the switchover is updated in the system.
5. If configured, graceful restart protocol extensions collect and restore routing information from neighboring peer *helper* routers.



NOTE: On T Series and M320 routers, the Switch Interface Boards (SIBs) are taken offline and restarted one by one during a graceful Routing Engine switchover. This is done to provide the SPMB that manages the SIB enough time to populate state information for its associated SIB. However, on a fully-populated chassis where all FPCs are sending traffic at full line rate, there might be momentary packet loss during the switchover.



NOTE: When GRES is configured and the `restart chassis-control` command is executed on a TX Matrix Plus router with 3D SIBs, we cannot ascertain which Routing Engine becomes a master. This is because the `chassisd` process restarts with the execution of the `restart chassis-control` command. The `chassisd` process is responsible for maintaining and retaining mastership and when it is restarted, the new `chassisd` is processed based on the router load. As a result, any one of the Routing Engines is made the master.

Effects of a Routing Engine Switchover

Table 3 on page 25 describes the effects of a Routing Engine switchover when no high availability features are enabled and when graceful Routing Engine switchover, graceful restart, and nonstop active routing features are enabled.

Table 3: Effects of a Routing Engine Switchover

Feature	Benefits	Considerations
Dual Routing Engines only (no features enabled)	When the switchover to the new master Routing Engine is complete, routing convergence takes place and traffic is resumed.	All physical interfaces are taken offline, Packet Forwarding Engines restart, the standby Routing Engine restarts the routing protocol process (rpd), and all hardware and interfaces are discovered by the new master Routing Engine. The switchover takes several minutes and all of the router's adjacencies are aware of the physical (interface alarms) and routing (topology) change.
Graceful Routing Engine switchover enabled	During the switchover, interface and kernel information is preserved. The switchover is faster because the Packet Forwarding Engines are not restarted.	The new master Routing Engine restarts the routing protocol process (rpd). All hardware and interfaces are acquired by a process that is similar to a warm restart. All adjacencies are aware of the router's change in state.
Graceful Routing Engine switchover and nonstop active routing enabled	Traffic is not interrupted during the switchover. Interface, kernel, and routing protocol information is preserved.	Unsupported protocols must be refreshed using the normal recovery mechanisms inherent in each protocol.
Graceful Routing Engine switchover and graceful restart enabled	Traffic is not interrupted during the switchover. Interface and kernel information is preserved. Graceful restart protocol extensions quickly collect and restore routing information from the neighboring routers.	Neighbors are required to support graceful restart and a wait interval is required. The routing protocol process (rpd) restarts. For certain protocols, a significant change in the network can cause graceful restart to stop.

Related Documentation

- [Understanding High Availability Features on Juniper Networks Routers on page 3](#)
- [Graceful Routing Engine Switchover System Requirements on page 25](#)
- [Configuring Graceful Routing Engine Switchover on page 101](#)
- [Requirements for Routers with a Backup Router Configuration on page 29](#)

Graceful Routing Engine Switchover System Requirements

Graceful Routing Engine switchover is supported on all routing platforms that contain dual Routing Engines. All Routing Engines configured for graceful Routing Engine

switchover must run the same Junos OS release. Hardware and software support for graceful Routing Engine switchover is described in the following sections:

- [Graceful Routing Engine Switchover Platform Support on page 26](#)
- [Graceful Routing Engine Switchover Feature Support on page 26](#)
- [Graceful Routing Engine Switchover DPC Support on page 28](#)
- [Graceful Routing Engine Switchover and Subscriber Access on page 28](#)
- [Graceful Routing Engine Switchover PIC Support on page 28](#)

Graceful Routing Engine Switchover Platform Support

To enable graceful Routing Engine switchover, your system must meet these minimum requirements:

- M20 and M40e routers—Junos OS Release 5.7 or later
- M10i router—Junos OS Release 6.1 or later
- M320 router—Junos OS Release 6.2 or later
- T320 router, T640 router, and TX Matrix router—Junos OS Release 7.0 or later
- M120 router—Junos OS Release 8.2 or later
- MX960 router—Junos OS Release 8.3 or later
- MX480 router—Junos OS Release 8.4 or later (8.4R2 recommended)
- MX240 router—Junos OS Release 9.0 or later
- Standalone T1600 router—Junos OS Release 8.5 or later
- Standalone T4000 router—Junos OS Release 12.1R2 or later
- TX Matrix Plus router—Junos OS Release 9.6 or later
- TX Matrix Plus router with 3D SIBs—Junos Release 13.1 or later

For more information about support for graceful Routing Engine switchover, see the sections that follow.

Graceful Routing Engine Switchover Feature Support

Graceful Routing Engine switchover supports most Junos OS features in Release 5.7 and later. Particular Junos OS features require specific versions of Junos OS. See [Table 4 on page 26](#).

Table 4: Graceful Routing Engine Switchover Feature Support

Application	Junos OS Release
Aggregated Ethernet interfaces with Link Aggregation Control Protocol (LACP) and aggregated SONET interfaces	6.2
Asynchronous Transfer Mode (ATM) virtual circuits (VCs)	6.2

Table 4: Graceful Routing Engine Switchover Feature Support (*continued*)

Application	Junos OS Release
Logical systems	6.3
NOTE: In Junos OS Release 9.3 and later, the logical router feature is renamed to logical system.	
Multicast	6.4 (7.0 for TX Matrix router)
Multilink Point-to-Point Protocol (MLPPP) and Multilink Frame Relay (MLFR)	7.0
Automatic Protection Switching (APS)—The current active interface (either the designated working or the designated protect interface) remains the active interface during a Routing Engine switchover.	7.4
Point-to-multipoint Multiprotocol Label Switching MPLS LSPs (transit only)	7.4
Compressed Real-Time Transport Protocol (CRTP)	7.6
Virtual private LAN service (VPLS)	8.2
Ethernet Operation, Administration, and Management (OAM) as defined by IEEE 802.3ah	8.5
Extended DHCP relay agent	8.5
Ethernet OAM as defined by IEEE 802.1ag	9.0
Packet Gateway Control Protocol (PGCP) process (pgcpd) on Multiservices 500 PICs on T640 routers.	9.0
Subscriber access	9.4
Layer 2 Circuit and LDP-based VPLS pseudowire redundant configuration	9.6

The following constraints apply to graceful Routing Engine switchover feature support:

- When graceful Routing Engine switchover and aggregated Ethernet interfaces are configured in the same system, the aggregated Ethernet interfaces must not be configured for fast-polling LACP. When fast polling is configured, the LACP polls time out at the remote end during the Routing Engine mastership switchover. When LACP polling times out, the aggregated link and interface are disabled. The Routing Engine mastership change is fast enough that standard and slow LACP polling do not time out during the procedure. However, note that this restriction does not apply to MX Series Routers that are running Junos OS Release 9.4 or later and have distributed periodic packet management (PPM) enabled—which is the default configuration—on

them. In such cases, you can configure graceful Routing Engine switchover and have aggregated Ethernet interfaces configured for fast-polling LACP on the same device.

- VRRP changes mastership when a Routing Engine switchover occurs, even when graceful Routing Engine switchover is configured.

Graceful Routing Engine Switchover DPC Support

Graceful Routing Engine switchover supports all Dense Port Concentrators (DPCs) on the MX Series 3D Universal Edge Routers running the appropriate version of Junos OS as shown in “[Graceful Routing Engine Switchover Platform Support](#)” on page 26. For more information about DPCs, see the *MX Series DPC Guide*.

Graceful Routing Engine Switchover and Subscriber Access

Graceful Routing Engine switchover currently supports most of the features directly associated with dynamic DHCP and dynamic PPPoE subscriber access. Graceful Routing Engine switchover also supports the unified in-service software upgrade (ISSU) for the DHCP access model and the PPPoE access model used by subscriber access.

Graceful Routing Engine Switchover PIC Support

Graceful Routing Engine switchover is supported on most PICs, except for the services PICs listed in this section. The PIC must be on a supported routing platform running the appropriate version of Junos OS. For information about FPC types, FPC/PIC compatibility, and the initial Junos OS Release in which an FPC supported a particular PIC, see the PIC guide for your router platform.

The following constraints apply to graceful Routing Engine switchover support for services PICs:

- You can include the **graceful-switchover** statement at the **[edit chassis redundancy]** hierarchy level on a router with Adaptive Services, Multiservices, and Tunnel Services PICs configured on it and successfully commit the configuration. However, all services on these PICs—except the Layer 2 service packages and extension-provider and SDK applications on Multiservices PICs—are reset during a switchover.
- Graceful Routing Engine switchover is not supported on any Monitoring Services PICs or Multilink Services PICs. If you include the **graceful-switchover** statement at the **[edit chassis redundancy]** hierarchy level on a router with either of these PIC types configured on it and issue the **commit** command, the commit fails.
- Graceful Routing Engine switchover is not supported on Multiservices 400 PICs configured for monitoring services applications. If you include the **graceful-switchover** statement, the commit fails.



NOTE: When an unsupported PIC is online, you cannot enable graceful Routing Engine switchover. If graceful Routing Engine switchover is already enabled, an unsupported PIC cannot come online.

- Related Documentation**
- [Understanding High Availability Features on Juniper Networks Routers on page 3](#)
 - [Understanding Graceful Routing Engine Switchover in the Junos OS on page 21](#)
 - [Configuring Graceful Routing Engine Switchover on page 101](#)
 - [Requirements for Routers with a Backup Router Configuration on page 29](#)

Requirements for Routers with a Backup Router Configuration

If your Routing Engine configuration includes a **backup-router** statement or an **inet6-backup-router** statement, you can also use the **destination** statement to specify a subnet address or multiple subnet addresses for the backup router. Include destination subnets for the backup Routing Engine at the **[edit system (backup-router | inet6-backup-router) address]** hierarchy level. This requirement also applies to any T640 router connected to a TX Matrix router that includes a **backup-router** or **inet6-backup-router** statement.



NOTE: If you have a backup router configuration in which multiple static routes point to a gateway from the management Ethernet interface, you must configure prefixes that are more specific than the static routes or include the retain flag at the **[edit routing-options static route]** hierarchy level.

For example, if you configure the static route 172.16.0.0/12 from the management Ethernet interface for management purposes, you must specify the backup router configuration as follows:

```
backup-router 172.29.201.62 destination [172.16.0.0/13 172.16.128.0/13]
```

- Related Documentation**
- [Understanding Graceful Routing Engine Switchover in the Junos OS on page 21](#)
 - [Graceful Routing Engine Switchover System Requirements on page 25](#)

CHAPTER 4

Nonstop Bridging

- [Nonstop Bridging Concepts on page 31](#)
- [Nonstop Bridging System Requirements on page 33](#)

Nonstop Bridging Concepts


Nonstop bridging uses the same infrastructure as graceful Routing Engine switchover (GRES) to preserve interface and kernel information. However, nonstop bridging also saves Layer 2 Control Protocol (L2CP) information by running the Layer 2 Control Protocol process (l2cpd) on the backup Routing Engine.



NOTE: To use nonstop bridging, you must first enable graceful Routing Engine switchover on your routing platform. For more information about graceful Routing Engine switchover, see [“Understanding Graceful Routing Engine Switchover in the Junos OS” on page 21](#).

Figure 3 on page 32 shows the system architecture of nonstop bridging and the process a routing platform follows to prepare for a switchover.

Figure 3: Nonstop Bridging Switchover Preparation Process




The switchover preparation process for nonstop bridging follows these steps:

1. The master Routing Engine starts.
2. The routing platform processes on the master Routing Engine (such as the chassis process [chassisd] and the Layer 2 Control Protocol process [l2cpd]) start.
3. The Packet Forwarding Engine starts and connects to the master Routing Engine.
4. All state information is updated in the system.
5. The backup Routing Engine starts, including the chassis process (chassisd) and the Layer 2 Control Protocol process (l2cpd).
6. The system determines whether graceful Routing Engine switchover and nonstop bridging have been enabled.
7. The kernel synchronization process (ksyncd) synchronizes the backup Routing Engine with the master Routing Engine.
8. For supported protocols, state information is updated directly between the l2cpds on the master and backup Routing Engines.

Figure 4 on page 33 shows the effects of a switchover on the routing platform.

Figure 4: Nonstop Bridging During a Switchover



The switchover process follows these steps:

1. When keepalives from the master Routing Engine are lost, the system switches over gracefully to the backup Routing Engine.
2. The Packet Forwarding Engine connects to the backup Routing Engine, which becomes the new master. Because the Layer 2 Control Protocol process (l2cpd) and chassis process (chassisd) are already running, these processes do not need to restart.
3. State information learned from the point of the switchover is updated in the system. Forwarding and bridging are continued during the switchover, resulting in minimal packet loss.

Related Documentation

- [Understanding High Availability Features on Juniper Networks Routers on page 3](#)
- [Nonstop Bridging System Requirements on page 33](#)
- [Configuring Nonstop Bridging on page 103](#)
- [Configuring Nonstop Bridging on EX Series Switches \(CLI Procedure\)](#)

Nonstop Bridging System Requirements

This topic contains the following sections:

- [Platform Support on page 33](#)
- [Protocol Support on page 34](#)

Platform Support

Nonstop bridging is supported on MX Series 3D Universal Edge Routers. Your system must be running Junos OS Release 8.4 or later.

Nonstop bridging is supported on EX Series Ethernet Switch with redundant Routing Engines.

For a list of the EX Series switches and Layer 2 protocols that support nonstop bridging, see EX Series Switch Software Features Overview.



NOTE: All Routing Engines configured for nonstop bridging must be running the same Junos OS release.

Protocol Support

Nonstop bridging is supported for the following Layer 2 control protocols:

- Spanning Tree Protocol (STP)
- Rapid Spanning Tree Protocol (RSTP)
- Multiple Spanning Tree Protocol (MSTP)

Related Documentation

- [Nonstop Bridging Concepts on page 31](#)
- [Configuring Nonstop Bridging on page 103](#)
- [Configuring Nonstop Bridging on EX Series Switches \(CLI Procedure\)](#)

CHAPTER 5

Nonstop Active Routing

- [Nonstop Active Routing Concepts on page 35](#)
- [Nonstop Active Routing System Requirements on page 38](#)

Nonstop Active Routing Concepts


Nonstop active routing (NSR) uses the same infrastructure as graceful Routing Engine switchover (GRES) to preserve interface and kernel information. However, nonstop active routing also saves routing protocol information by running the routing protocol process (rpd) on the backup Routing Engine. By saving this additional information, nonstop active routing is self-contained and does not rely on helper routers to assist the routing platform in restoring routing protocol information. Nonstop active routing is advantageous in networks where neighbor routers do not support graceful restart protocol extensions. As a result of this enhanced functionality, nonstop active routing is a natural replacement for graceful restart.



NOTE: To use nonstop active routing, you must first enable graceful Routing Engine switchover on your routing platform. For more information about graceful Routing Engine switchover, see [“Understanding Graceful Routing Engine Switchover in the Junos OS” on page 21](#).

Figure 5 on page 36 shows the system architecture of nonstop active routing and the process a routing platform follows to prepare for a switchover.

Figure 5: Nonstop Active Routing Switchover Preparation Process




The switchover preparation process for nonstop active routing follows these steps:

1. The master Routing Engine starts.
2. The routing platform processes on the master Routing Engine (such as the chassis process [chassisd] and the routing protocol process [rpd]) start.
3. The Packet Forwarding Engine starts and connects to the master Routing Engine.
4. All state information is updated in the system.
5. The backup Routing Engine starts, including the chassis process (chassisd) and the routing protocol process (rpd).
6. The system determines whether graceful Routing Engine switchover and nonstop active routing have been enabled.
7. The kernel synchronization process (ksyncd) synchronizes the backup Routing Engine with the master Routing Engine.
8. For supported protocols, state information is updated directly between the routing protocol processes on the master and backup Routing Engines.

Figure 6 on page 37 shows the effects of a switchover on the routing platform.

Figure 6: Nonstop Active Routing During a Switchover



The switchover process follows these steps:

1. When keepalives from the master Routing Engine are lost, the system switches over gracefully to the backup Routing Engine.
2. The Packet Forwarding Engine connects to the backup Routing Engine, which becomes the new master. Because the routing protocol process (rpd) and chassis process (chassisd) are already running, these processes do not need to restart.
3. State information learned from the point of the switchover is updated in the system. Forwarding and routing are continued during the switchover, resulting in minimal packet loss.
4. Peer routers continue to interact with the routing platform as if no change had occurred. Routing adjacencies and session state relying on underlying routing information are preserved and not reset.

Related Documentation

- [Understanding High Availability Features on Juniper Networks Routers on page 3](#)
- [Nonstop Active Routing System Requirements on page 38](#)
- [Configuring Nonstop Active Routing on page 105](#)

Nonstop Active Routing System Requirements

This section contains the following topics:

- [Nonstop Active Routing Platform Support on page 38](#)
- [Nonstop Active Routing Protocol and Feature Support on page 39](#)
- [Nonstop Active Routing BFD Support on page 42](#)
- [Nonstop Active Routing BGP Support on page 43](#)
- [Nonstop Active Routing Layer 2 Circuit and VPLS Support on page 43](#)
- [Nonstop Active Routing PIM Support on page 44](#)
- [Nonstop Active Routing MSDP Support on page 46](#)
- [Nonstop Active Routing Support for RSVP-TE LSPs on page 47](#)

Nonstop Active Routing Platform Support

[Table 5 on page 38](#) lists the platforms that support nonstop active routing (NSR).

Table 5: Nonstop Active Routing Platform Support

Platform	Junos OS Release
M10i router	8.4 or later
M20 router	8.4 or later
M40e router	8.4 or later
M120 router	9.0 or later
M320 router	8.4 or later
MX Series routers	9.0 or later
PTX Series Packet Transport switches	12.1R4 or later

NOTE:

Nonstop active routing (NSR) switchover on PTX series is supported only for the following MPLS and VPN protocols and applications using chained composite next hops:

- Labeled BGP
- Layer 2 VPNs excluding Layer 2 interworking (Layer 2 stitching)
- Layer 3 VPNs
- LDP
- RSVP

Table 5: Nonstop Active Routing Platform Support (*continued*)

Platform	Junos OS Release
PTX Series Packet Transport switches	12.1R4 or later
<p>NOTE:</p> <p>Nonstop active routing (NSR) switchover on PTX series is supported only for the following MPLS and VPN protocols and applications using chained composite next hops:</p> <ul style="list-style-type: none"> • Labeled BGP • Layer 2 VPNs excluding Layer 2 interworking (Layer 2 stitching) • Layer 3 VPNs • LDP • RSVP 	
PTX Series Packet Transport switches	12.1R4 or later
<p>NOTE:</p> <p>Nonstop active routing (NSR) switchover on PTX series is supported only for the following MPLS and VPN protocols and applications using chained composite next hops:</p> <ul style="list-style-type: none"> • Labeled BGP • Layer 2 VPNs excluding Layer 2 interworking (Layer 2 stitching) • Layer 3 VPNs • LDP • RSVP 	
T320 router, T640 router, and TX Matrix router	8.4 or later
Standalone T1600 router	8.5 or later
Standalone T4000 router	12.1R2 or later
TX Plus Matrix router	10.0 or later
TX Plus Matrix router with 3D SIBs	13.1 or later



NOTE: All Routing Engines configured for nonstop active routing must be running the same Junos OS release.

Nonstop Active Routing Protocol and Feature Support

Table 6 on page 40 lists the protocols that are supported by nonstop active routing.

Table 6: Nonstop Active Routing Protocol and Feature Support

Protocol	Junos OS Release
Aggregated Ethernet interfaces with Link Aggregation Control Protocol (LACP)	9.4 or later
Bidirectional Forwarding Detection (BFD) For more information, see “Nonstop Active Routing BFD Support” on page 42.	8.5 or later
BGP For more information, see “Nonstop Active Routing BGP Support” on page 43.	8.4 or later
Labeled BGP (PTX Series Packet Transport Switches only)	12.1R4 or later
IS-IS	8.4 or later
LDP	8.4 or later
LDP-based virtual private LAN service (VPLS)	9.3 or later
LDP OAM (operation, administration, and management) features	9.6 or later
LDP (PTX Series Packet Transport Switches only) Nonstop active routing support for LDP includes: <ul style="list-style-type: none"> • LDP unicast transit LSPs • LDP egress LSPs for labeled internal BGP (IBGP) and external BGP (EBGP) • LDP over RSVP transit LSPs • LDP transit LSPs with indexed next hops • LDP transit LSPs with unequal cost load balancing 	12.3R4 or later
NOTE: Nonstop active routing is not supported for LDP Point-to-Multipoint LSPs and LDP ingress LSPs.	
Layer 2 circuits	(on LDP-based VPLS) 9.2 or later (on RSVP-TE LSP) 11.1 or later
Layer 2 VPNs	9.1 or later
Layer 2 VPNs (PTX Series Packet Transport Switches only)	12.1R4 or later
NOTE: Nonstop active routing is not supported for Layer 2 interworking (Layer 2 stitching).	
Layer 3 VPNs (see the first Note after this table for restrictions)	9.2 or later
Layer 3 VPNs (PTX Series Packet Transport Switches only)	12.1R4 or later

Table 6: Nonstop Active Routing Protocol and Feature Support (*continued*)

Protocol	Junos OS Release
Multicast Source Discovery Protocol (MSDP) For more information, see “Nonstop Active Routing MSDP Support” on page 46 .	12.1 or later
OSPF/OSPFv3 Protocol Independent Multicast (PIM) For more information, see “Nonstop Active Routing PIM Support” on page 44 .	8.4 or later (for IPv4) 9.3 or later (for IPv6) 10.4 or later
RIP and RIP next generation (RIPng)	9.0 or later
RSVP (PTX Series Packet Transport Switches only) Nonstop active routing support for RSVP includes: <ul style="list-style-type: none"> Point-to-Multipoint LSPs <ul style="list-style-type: none"> RSVP Point-to-Multipoint ingress, transit, and egress LSPs using existing non-chained next hop. RSVP Point-to-Multipoint transit LSPs using composite next hops for Point-to-Multipoint label routes. Point-to-Point LSPs <ul style="list-style-type: none"> RSVP Point-to-Point ingress, transit, and egress LSPs using non-chained next hops. RSVP Point-to-Point transit LSPs using chained composite next hops. 	12.1R4 or later
RSVP-TE LSP For more information, see “Nonstop Active Routing Support for RSVP-TE LSPs” on page 47 .	9.5 or later
VPLS	(LDP-based) 9.1 or later (RSVP-TE-based) 11.2 or later



NOTE: Layer 3 VPN support does not include dynamic GRE tunnels, multicast VPNs, or BGP flow routes.



NOTE: If you configure a protocol that is not supported by nonstop active routing, the protocol operates as usual. When a switchover occurs, the state information for the unsupported protocol is not preserved and must be refreshed using the normal recovery mechanisms inherent in the protocol.



NOTE: On routers that have logical systems configured on them, only the master logical system supports nonstop active routing.

Nonstop Active Routing BFD Support

Nonstop active routing supports the Bidirectional Forwarding Detection (BFD) protocol, which uses the topology discovered by routing protocols to monitor neighbors. The BFD protocol is a simple hello mechanism that detects failures in a network. Because BFD is streamlined to be efficient at fast liveness detection, when it is used in conjunction with routing protocols, routing recovery times are improved. With nonstop active routing enabled, BFD session states are not restarted when a Routing Engine switchover occurs.



NOTE: BFD session states are saved only for clients using aggregate or static routes or for BGP, IS-IS, OSPF/OSPFv3, or PIM.

When a BFD session is distributed to the Packet Forwarding Engine, BFD packets continue to be sent during a Routing Engine switchover. If nondistributed BFD sessions are to be kept alive during a switchover, you must ensure that the session failure detection time is greater than the Routing Engine switchover time. The following BFD sessions are not distributed to the Packet Forwarding Engine: multihop sessions, tunnel-encapsulated sessions, and sessions over integrated routing and bridging (IRB) interfaces.



NOTE: BFD is an intensive protocol that consumes system resources. Specifying a minimum interval for BFD less than 100 ms for Routing Engine-based sessions and 10 ms for distributed BFD sessions can cause undesired BFD flapping. The minimum-interval configuration statement is a BFD liveness detection parameter.

Depending on your network environment, these additional recommendations might apply:

- For large-scale network deployments with a large number of BFD sessions, specify a minimum interval of 300 ms for Routing Engine-based sessions, and 100 ms for distributed BFD sessions.
- For very large-scale network deployments with a large number of BFD sessions, contact Juniper Networks customer support for more information.
- For BFD sessions to remain up during a Routing Engine switchover event when nonstop active routing is configured, specify a minimum interval of 2500 ms for Routing Engine-based sessions. For distributed BFD sessions with nonstop active routing configured, the minimum interval recommendations are unchanged and depend only on your network deployment.

Nonstop Active Routing BGP Support

Nonstop active routing BGP support is subject to the following conditions:

- You must include the **path-selection external-router-ID** statement at the **[edit protocols bgp]** hierarchy level to ensure consistent path selection between the master and backup Routing Engines during and after the nonstop active routing switchover.
- If the BGP peer in the master Routing Engine has negotiated address-family capabilities that are not supported for nonstop active routing, then the corresponding BGP neighbor state on the backup Routing Engine shows as idle. On switchover, the BGP session is reestablished from the new master Routing Engine.

Only the following address families are supported for nonstop active routing.



NOTE: Address families are supported only on the main instance of BGP. Only unicast is supported on VRF instances.

- inet unicast
- inet labeled-unicast
- inet multicast
- inet6 labeled-unicast
- inet6 multicast
- inet6 unicast
- route-target
- l2vpn signaling
- inet6-vpn unicast
- inet-vpn unicast
- inet-mdt
- iso-vpn
- BGP route dampening does not work on the backup Routing Engine when nonstop active routing is enabled.

Nonstop Active Routing Layer 2 Circuit and VPLS Support

Nonstop active routing supports Layer 2 circuit and VPLS on both LDP-based and RSVP-TE-based networks. Nonstop active routing support enables the backup Routing Engine to track the label advertised by Layer 2 circuit and VPLS on the primary Routing Engine, and to use the same label after the Routing Engine switchover.

in Junos OS Release 9.6 and later, nonstop active routing support is extended to the Layer 2 circuit and LDP-based VPLS pseudowire redundant configurations.

Nonstop Active Routing PIM Support

Nonstop active routing supports Protocol Independent Multicast (PIM) with stateful replication on backup Routing Engines. State information replicated on the backup Routing Engine includes information about neighbor relationships, join and prune events, rendezvous point (RP) sets, synchronization between routes and next hops, multicast session states, and the forwarding state between the two Routing Engines.



NOTE: Nonstop active routing for PIM is supported for IPv4 on Junos OS Release 9.3 and later, and for IPv6 on Junos OS Release 10.4 and later. Starting with Release 11.1, Junos OS also supports nonstop active routing for PIM on devices that have both IPv4 and IPv6 configured on them.

To configure nonstop active routing for PIM, include the same statements in the configuration as for other protocols: the **nonstop-routing** statement at the **[edit routing-options]** hierarchy level and the **graceful-restart** statement at the **[edit chassis redundancy]** hierarchy level. To trace PIM nonstop active routing events, include the **flag nsr-synchronization** statement at the **[edit protocols pim traceoptions]** hierarchy level.



NOTE: The **clear pim join**, **clear pim register**, and **clear pim statistics** operational mode commands are not supported on the backup Routing Engine when nonstop active routing is enabled.

Nonstop active routing support varies for different PIM features. The features fall into the following three categories: supported features, unsupported features, and incompatible features.

Supported features:

- Auto-RP



NOTE: Nonstop active routing PIM support on IPv6 does not support auto-RP because IPv6 does not support auto-RP.

- Bootstrap router (BSR)
- Static RPs
- Embedded RP on non-RP IPv6 routers
- Local RP



NOTE: RP set information synchronization is supported for local RP and BSR (on IPv4 and IPv6), autoRP (on IPv4), and embedded RP (on IPv6).

- BFD

- Dense mode
- Sparse mode
- Source-specific multicast (SSM)
- Draft Rosen multicast VPNs (MVPNs)
- Anycast RP (anycast RP set information synchronization and anycast RP register state synchronization on IPv4 and IPv6 configurations)
- Flow maps
- Unified ISSU
- Policy features such as neighbor policy, bootstrap router export and import policies, scope policy, flow maps, and reverse path forwarding (RPF) check policies
- Upstream assert synchronization
- PIM join load balancing

Starting with Release 12.2, Junos OS extends the nonstop active routing PIM support to draft Rosen MVPNs. Nonstop active routing PIM support for draft Rosen MVPNs enables nonstop active routing-enabled devices to preserve draft Rosen MPVN-related information—such as default and data multicast distribution tree (MDT) states—across switchovers. In releases earlier than 12.2, nonstop active routing PIM configuration was incompatible with draft Rosen MPVN configuration.

The backup Routing Engine sets up the default MDT based on the configuration and the information it receives from the master Routing Engine, and keeps updating the default MDT state information.

However, for data MDTs, the backup Routing Engine relies on the master Routing Engine to provide updates when data MDTs are created, updated, or deleted. The backup Routing Engine neither monitors data MDT flow rates nor triggers a data MDT switchover based on variations in flow rates. Similarly, the backup Routing Engine does not maintain the data MDT delay timer or timeout timer. It does not send MDT join TLV packets for the data MDTs until it takes over as the master Routing Engine. After the switchover, the new master Routing Engine starts sending MDT join TLV packets for each data MDT, and also resets the data MDT timers. Note that the expiration time for the timers might vary from the original values on the previous master Routing Engine.

Starting with Release 12.3, Junos OS extends the Protocol Independent Multicast (PIM) nonstop active routing support to IGMP-only interfaces.

In Junos OS releases earlier than 12.3, the PIM joins created on IGMP-only interfaces were not replicated on the backup Routing Engine. Thus, the corresponding multicast routes were marked as pruned (meaning discarded) on the backup Routing Engine. Because of this limitation, after a switchover, the new master Routing Engine had to wait for the IGMP module to come up and start receiving reports to create PIM joins and to install multicast routes. This caused traffic loss until the multicast joins and routes were reinstated.

However, in Junos OS Release 12.3 and later, the multicast joins on the IGMP-only interfaces are mapped to PIM states, and these states are replicated on the backup Routing Engine. If the corresponding PIM states are available on the backup, the multicast routes are marked as forwarding on the backup Routing Engine. This enables uninterrupted traffic flow after a switchover. This enhancement covers IGMPv2, IGMPv3, MLDv1, and MLDv2 reports and leaves.

Unsupported features: You can configure the following PIM features on a router along with nonstop active routing, but they function as if nonstop active routing is not enabled. In other words, during Routing Engine switchover and other outages, their state information is not preserved, and traffic loss is to be expected.

- Internet Group Management Protocol (IGMP) exclude mode
- IGMP snooping

Incompatible features: Nonstop active routing does not support the following features, and you cannot configure them on a router enabled for PIM nonstop active routing. The commit operation fails if the configuration includes both nonstop active routing and one or more of these features:

- Next-generation MVPNs with PIM provider tunnels

Junos OS provides a configuration statement that disables nonstop active routing for PIM only, so that you can activate incompatible PIM features and continue to use nonstop active routing for the other protocols on the router. Before activating an incompatible PIM feature, include the **nonstop-routing disable** statement at the **[edit protocols pim]** hierarchy level. Note that in this case, nonstop active routing is disabled for all PIM features, not just incompatible features.

Nonstop Active Routing MSDP Support

Starting with Release 12.1, Junos OS extends nonstop active routing support to the Multicast Source Discovery Protocol (MSDP).

Nonstop active routing support for MSDP preserves the following MSDP-related information across the switchover:

- MSDP configuration and peer information
- MSDP peer socket information
- Source-active and related information

However, note that the following restrictions or limitations apply to nonstop active routing MSDP support:

- Because the backup Routing Engine learns the active source information by processing the source-active messages from the network, synchronizing of source active information between the master and backup Routing Engines might take up to 60 seconds. So, no planned switchover is allowed within 60 seconds of the initial replication of the sockets.

- Similarly, Junos OS does not support two planned switchovers within 240 seconds of each other.

Junos OS enables you to trace MSDP nonstop active routing events by including the **flag nsr-synchronization** statement at the **[edit protocols mdp traceoptions]** hierarchy level.

Nonstop Active Routing Support for RSVP-TE LSPs

Junos OS extends nonstop active routing support to label-switching routers (LSRs) and Layer 2 Circuits that are part of an RSVP-TE LSP. Nonstop active routing support on LSRs ensures that the master to backup Routing Engine switchover on an LSR remains transparent to the network neighbors and that the LSP information remains unaltered during and after the switchover.

You can use the **show rsvp version** command to view the nonstop active routing mode and state on an LSR. Similarly, you can use the **show mpls lsp** and **show rsvp session** commands on the standby Routing Engine to view the state recreated on the standby Routing Engine.

The Junos OS nonstop active routing feature is also supported on RSVP point-to-multipoint LSPs. Nonstop active routing support for RSVP point-to-multipoint egress and transit LSPs was added in Junos OS Release 11.4, and for ingress LSPs in Release 12.1. During the switchover, the LSP comes up on the backup Routing Engine that shares and synchronizes the state information with the master Routing Engine before and after the switchover. Nonstop active routing support for point-to-multipoint transit and egress LSPs ensures that the switchover remains transparent to the network neighbors, and preserves the LSP information across the switchover.

However, Junos OS nonstop active routing support for RSVP point-to-multipoint LSPs does not include support for dynamically created point-to-multipoint LSPs, such as VPLS and next-generation MVPNs.

The **show rsvp session detail** command enables you to check the point-to-multipoint LSP remerge state information (**P2MP LSP re-merge**; possible values are **head**, **member**, and **none**).

However, Junos OS does not support nonstop active routing for the following features:

- Generalized Multiprotocol Label Switching (GMPLS) and LSP hierarchy
- Interdomain or loose-hop expansion LSPs
- BFD liveness detection

Nonstop active routing support for RSVP-TE LSPs is subject to the following limitations and restrictions:

- Detour LSPs are not maintained across a switchover and so, detour LSPs might fail to come back online after the switchover.
- Control plane statistics corresponding to the **show rsvp statistics** and **show rsvp interface detail | extensive** commands are not maintained across Routing Engine switchovers.

- Statistics from the backup Routing Engine are not reported for **show mpls lsp statistics** and **monitor mpls label-switched-path** commands. However, if a switchover occurs, the backup Routing Engine, after taking over as the master, starts reporting statistics. Note that the **clear statistics** command issued on the old master Routing Engine does not have any effect on the new master Routing Engine, which reports statistics, including any uncleared statistics.
- State timeouts might take additional time during nonstop active routing switchover. For example, if a switchover occurs after a neighbor has missed sending two hello messages to the master, the new master Routing Engine waits for another three hello periods before timing out the neighbor.
- On the RSVP ingress router, if you configure auto-bandwidth functionality, the bandwidth adjustment timers are set in the new master after the switchover. This causes a one-time increase in the length of time required for the bandwidth adjustment after the switchover occurs.
- RSVP ingress LSPs that have BFD liveness detection enabled on them do not come up on the backup Routing Engine during the switchover. Such BFD-enabled LSPs have to be reestablished after the switchover.
- Backup LSPs —LSPs that are established between the point of local repair (PLR) and the merge point after a node or link failure—are not preserved during a Routing Engine switchover.
- When nonstop active routing is enabled, graceful restart is not supported. However, graceful restart helper mode is supported.

**Related
Documentation**

- [Nonstop Active Routing Concepts on page 35](#)
- [Configuring Nonstop Active Routing on page 105](#)

CHAPTER 6

Graceful Restart

- [Graceful Restart Concepts on page 49](#)
- [Graceful Restart System Requirements on page 50](#)
- [Aggregate and Static Routes on page 51](#)
- [Graceful Restart and Routing Protocols on page 51](#)
- [Graceful Restart and MPLS-Related Protocols on page 54](#)
- [Understanding Restart Signaling-Based Helper Mode Support for OSPF Graceful Restart on page 55](#)
- [Graceful Restart and Layer 2 and Layer 3 VPNs on page 56](#)
- [Graceful Restart on Logical Systems on page 57](#)

Graceful Restart Concepts

With routing protocols, any service interruption requires that an affected router recalculate adjacencies with neighboring routers, restore routing table entries, and update other protocol-specific information. An unprotected restart of a router can result in forwarding delays, route flapping, wait times stemming from protocol reconvergence, and even dropped packets. The main benefits of graceful restart are uninterrupted packet forwarding and temporary suppression of all routing protocol updates. Graceful restart enables a router to pass through intermediate convergence states that are hidden from the rest of the network.

Three main types of graceful restart are available on Juniper Networks routing platforms:

- Graceful restart for aggregate and static routes and for routing protocols—Provides protection for aggregate and static routes and for Border Gateway Protocol (BGP), End System-to-Intermediate System (ES-IS), Intermediate System-to-Intermediate System (IS-IS), Open Shortest Path First (OSPF), Routing Information Protocol (RIP), next-generation RIP (RIPng), and Protocol Independent Multicast (PIM) sparse mode routing protocols.
- Graceful restart for MPLS-related protocols—Provides protection for Label Distribution Protocol (LDP), Resource Reservation Protocol (RSVP), circuit cross-connect (CCC), and translational cross-connect (TCC).
- Graceful restart for virtual private networks (VPNs)—Provides protection for Layer 2 and Layer 3 VPNs.

Graceful restart works similarly for routing protocols and MPLS protocols and combines components of these protocol types to enable graceful restart in VPNs. The main benefits of graceful restart are uninterrupted packet forwarding and temporary suppression of all routing protocol updates. Graceful restart thus enables a router to pass through intermediate convergence states that are hidden from the rest of the network.

Most graceful restart implementations define two types of routers—the restarting router and the helper router. The restarting router requires rapid restoration of forwarding state information so it can resume the forwarding of network traffic. The helper router assists the restarting router in this process. Graceful restart configuration statements typically affect either the restarting router or the helper router.

**Related
Documentation**

- [Understanding High Availability Features on Juniper Networks Routers on page 3](#)
- [Graceful Restart System Requirements on page 50](#)
- [Aggregate and Static Routes on page 51](#)
- [Graceful Restart and Routing Protocols on page 51](#)
- [Graceful Restart and MPLS-Related Protocols on page 54](#)
- [Graceful Restart and Layer 2 and Layer 3 VPNs on page 56](#)
- [Graceful Restart on Logical Systems on page 57](#)
- [Example: Configuring Graceful Restart on page 129](#)
- [Configuring Graceful Restart for QFabric Systems](#)

Graceful Restart System Requirements

Graceful restart is supported on all routing platforms. To implement graceful restart for particular features, your system must meet these minimum requirements:

- Junos OS Release 5.3 or later for aggregate route, BGP, IS-IS, OSPF, RIP, RIPng, or static route graceful restart.
- Junos OS Release 5.5 or later for RSVP on egress provider edge (PE) routers.
- Junos OS Release 5.5 or later for LDP graceful restart.
- Junos OS Release 5.6 or later for the CCC, TCC, Layer 2 VPN, or Layer 3 VPN implementations of graceful restart.
- Junos OS Release 6.1 or later for RSVP graceful restart on ingress PE routers.
- Junos OS Release 6.4 or later for PIM sparse mode graceful restart.
- Junos OS Release 7.4 or later for ES-IS graceful restart (J Series Services Routers).
- Junos OS Release 8.5 or later for BFD session (helper mode only)—If a node is undergoing a graceful restart and its BFD sessions are distributed to the Packet Forwarding Engine, the peer node can help the peer with the graceful restart.
- Junos OS Release 9.2 or later for BGP to support helper mode without requiring that graceful restart be configured.

- Related Documentation**
- [Graceful Restart Concepts on page 49](#)

Aggregate and Static Routes

When you include the **graceful-restart** statement at the **[edit routing-options]** hierarchy level, any static routes or aggregated routes that have been configured are protected. Because no helper router assists in the restart, these routes are retained in the forwarding table while the router restarts (rather than being discarded or refreshed).

- Related Documentation**
- [Graceful Restart Concepts on page 49](#)
 - [Graceful Restart System Requirements on page 50](#)
 - [Enabling Graceful Restart on page 117](#)
 - [Verifying Graceful Restart Operation on page 214](#)
 - [Example: Configuring Graceful Restart on page 129](#)

Graceful Restart and Routing Protocols

This section covers the following topics:

- [BGP on page 51](#)
- [ES-IS on page 52](#)
- [IS-IS on page 52](#)
- [OSPF and OSPFv3 on page 52](#)
- [PIM Sparse Mode on page 53](#)
- [RIP and RIPng on page 53](#)

BGP

When a router enabled for BGP graceful restart restarts, it retains BGP peer routes in its forwarding table and marks them as stale. However, it continues to forward traffic to other peers (or receiving peers) during the restart. To reestablish sessions, the restarting router sets the "restart state" bit in the BGP OPEN message and sends it to all participating peers. The receiving peers reply to the restarting router with messages containing end-of-routing-table markers. When the restarting router receives all replies from the receiving peers, the restarting router performs route selection, the forwarding table is updated, and the routes previously marked as stale are discarded. At this point, all BGP sessions are reestablished and the restarting peer can receive and process BGP messages as usual.

While the restarting router does its processing, the receiving peers also temporarily retain routing information. When a receiving peer detects a TCP transport reset, it retains the routes received and marks the routes as stale. After the session is reestablished with the restarting router, the stale routes are replaced with updated route information.

ES-IS

When graceful restart for ES-IS is enabled, the routes to end systems or intermediate systems are not removed from the forwarding table. The adjacencies are reestablished after restart is complete.



NOTE: ES-IS is supported only on the J Series Services Router.

IS-IS

Normally, IS-IS routers move neighbor adjacencies to the down state when changes occur. However, a router enabled for IS-IS graceful restart sends out Hello messages with the Restart Request (RR) bit set in a restart type length value (TLV) message. This indicates to neighboring routers that a graceful restart is in progress and to leave the IS-IS adjacency intact. The neighboring routers must interpret and implement restart signaling themselves. Besides maintaining the adjacency, the neighbors send complete sequence number PDUs (CSNPs) to the restarting router and flood their entire database.

The restarting router never floods any of its own link-state PDUs (LSPs), including pseudonode LSPs, to IS-IS neighbors while undergoing graceful restart. This enables neighbors to reestablish their adjacencies without transitioning to the down state and enables the restarting router to reinitiate a smooth database synchronization.

OSPF and OSPFv3

When a router enabled for OSPF graceful restart restarts, it retains routes learned before the restart in its forwarding table. The router does not allow new OSPF link-state advertisements (LSAs) to update the routing table. This router continues to forward traffic to other OSPF neighbors (or helper routers), and sends only a limited number of LSAs during the restart period. To reestablish OSPF adjacencies with neighbors, the restarting router must send a grace LSA to all neighbors. In response, the helper routers enter helper mode and send an acknowledgement back to the restarting router. If there are no topology changes, the helper routers continue to advertise LSAs as if the restarting router had remained in continuous OSPF operation.

When the restarting router receives replies from all the helper routers, the restarting router selects routes, updates the forwarding table, and discards the old routes. At this point, full OSPF adjacencies are reestablished and the restarting router receives and processes OSPF LSAs as usual. When the helper routers no longer receive grace LSAs from the restarting router or the topology of the network changes, the helper routers also resume normal operation.



NOTE: For more information about the standard helper mode implementation, see RFC 3623, *Graceful OSPF Restart*.

Starting with Release 11.3, Junos OS supports the restart signaling-based helper mode for OSPF graceful restart configurations. The helper modes, both standard and restart

signaling-based, are enabled by default. In restart signaling-based helper mode implementations, the restarting router relays the restart status to its neighbors only after the restart is complete. When the restart is complete, the restarting router sends hello messages to its helper routers with the **restart signal (RS)** bit set in the hello packet header. When a helper router receives a hello packet with the **RS** bit set in the header, the helper router returns a hello message to the restarting router. The reply hello message from the helper router contains the **ResyncState** flag and the **ResyncTimeout** timer that enable the restarting router to keep track of the helper routers that are syncing up with it. When all helpers complete the synchronization, the restarting router exits the restart mode.



NOTE:

For more information about restart signaling-based graceful restart helper mode implementation, see RFC 4811, *OSPF Out-of-Band Link State Database (LSDB) Resynchronization*, RFC 4812, *OSPF Restart Signaling*, and RFC 4813, *OSPF Link-Local Signaling*.

Restart signaling-based graceful restart helper mode is not supported for OSPFv3 configurations.

PIM Sparse Mode

PIM sparse mode uses a mechanism called a *generation identifier* to indicate the need for graceful restart. Generation identifiers are included by default in PIM hello messages. An initial generation identifier is created by each PIM neighbor to establish device capabilities. When one of the PIM neighbors restarts, it sends a new generation identifier to its neighbors. All neighbors that support graceful restart and are connected by point-to-point links assist by sending multicast updates to the restarting neighbor.

The restart phase completes when either the PIM state becomes stable or when the restart interval timer expires. If the neighbors do not support graceful restart or connect to each other using multipoint interfaces, the restarting router uses the restart interval timer to define the restart period.

RIP and RIPv6

When a router enabled for RIP graceful restart restarts, routes that have been configured are protected. Because no helper router assists in the restart, these routes are retained in the forwarding table while the router restarts (rather than being discarded or refreshed).

Related Documentation

- [Graceful Restart Concepts on page 49](#)
- [Graceful Restart System Requirements on page 50](#)
- [Configuring Routing Protocols Graceful Restart on page 118](#)
- [Verifying Graceful Restart Operation on page 214](#)
- [Example: Configuring Graceful Restart on page 129](#)

Graceful Restart and MPLS-Related Protocols

This section contains the following topics:

- [LDP on page 54](#)
- [RSVP on page 54](#)
- [CCC and TCC on page 55](#)

LDP

LDP graceful restart enables a router whose LDP control plane is undergoing a restart to continue to forward traffic while recovering its state from neighboring routers. It also enables a router on which helper mode is enabled to assist a neighboring router that is attempting to restart LDP.

During session initialization, a router advertises its ability to perform LDP graceful restart or to take advantage of a neighbor performing LDP graceful restart by sending the graceful restart TLV. This TLV contains two fields relevant to LDP graceful restart: the reconnect time and the recovery time. The values of the reconnect and recovery times indicate the graceful restart capabilities supported by the router.

The reconnect time is configured in Junos OS as 60 seconds and is not user-configurable. The reconnect time is how long the helper router waits for the restarting router to establish a connection. If the connection is not established within the reconnect interval, graceful restart for the LDP session is terminated. The maximum reconnect time is 120 seconds and is not user-configurable. The maximum reconnect time is the maximum value that a helper router accepts from its restarting neighbor.

When a router discovers that a neighboring router is restarting, it waits until the end of the recovery time before attempting to reconnect. The recovery time is the length of time a router waits for LDP to restart gracefully. The recovery time period begins when an initialization message is sent or received. This time period is also typically the length of time that a neighboring router maintains its information about the restarting router, so it can continue to forward traffic.

You can configure LDP graceful restart both in the master instance for the LDP protocol and for a specific routing instance. You can disable graceful restart at the global level for all protocols, at the protocol level for LDP only, and for a specific routing instance only.

RSVP

RSVP graceful restart enables a router undergoing a restart to inform its adjacent neighbors of its condition. The restarting router requests a grace period from the neighbor or peer, which can then cooperate with the restarting router. The restarting router can still forward MPLS traffic during the restart period; convergence in the network is not disrupted. The restart is not visible to the rest of the network, and the restarting router is not removed from the network topology. RSVP graceful restart can be enabled on both transit routers and ingress routers. It is available for both point-to-point LSPs and point-to-multipoint LSPs.

CCC and TCC

CCC and TCC graceful restart enables Layer 2 connections between customer edge (CE) routers to restart gracefully. These Layer 2 connections are configured with the **remote-interface-switch** or **lsp-switch** statements. Because these CCC and TCC connections have an implicit dependency on RSVP LSPs, graceful restart for CCC and TCC uses the RSVP graceful restart capabilities.

RSVP graceful restart must be enabled on the provider edge (PE) routers and provider (P) routers to enable graceful restart for CCC and TCC. Also, because RSVP is used as the signaling protocol for signaling label information, the neighboring router must use helper mode to assist with the RSVP restart procedures.

- Related Documentation**
- [Graceful Restart Concepts on page 49](#)
 - [Graceful Restart System Requirements on page 50](#)
 - [Configuring Graceful Restart for MPLS-Related Protocols on page 124](#)
 - [Example: Configuring Graceful Restart on page 129](#)

Understanding Restart Signaling-Based Helper Mode Support for OSPF Graceful Restart

Starting with Release 11.4, Junos OS supports restart signaling-based helper mode for OSPF graceful restart configurations.



NOTE:

- Restart signaling-based graceful restart helper mode is not supported for OSPFv3 configurations.
- Junos OS releases prior to Release 11.4 and OSPFv3 configurations support only standard helper mode as defined in RFC 3623 . For more information about the standard helper mode implementation, see RFC 3623 and the *Junos OS High Availability Configuration Guide*.

Both standard and restart signaling-based helper modes are enabled by default, irrespective of the graceful-restart configuration status on the device.

In restart signaling-based helper mode implementations, the restarting router informs the restart status to its neighbors only after the restart is complete. When the restart is complete, the restarting router sends hello messages to its helper routers with the **restart signal (RS)** bit set in the hello packet header. When a helper router receives a hello packet with the **RS** bit set in the header, the helper router returns a hello message to the restarting router. The reply hello message from the helper router contains the **ResyncState** flag and the **ResyncTimeout** timer that enable the restarting router to keep track of the helper routers that are syncing up with it. When all helpers complete the synchronization, the restarting router exits the restart mode.

For more information about restart signaling-based graceful restart helper mode implementation, see RFC 4811, *OSPF Out-of-Band Link State Database (LSDB) Resynchronization*, RFC 4812, *OSPF Restart Signaling* and RFC 4813, *OSPF Link-Local Signaling*.

- Related Documentation**
- [Example: Managing Helper Modes for OSPF Graceful Restart on page 154](#)
 - [Tracing Restart Signaling-Based Helper Mode Events for OSPF Graceful Restart on page 213](#)

Graceful Restart and Layer 2 and Layer 3 VPNs

VPN graceful restart uses three types of restart functionality:

1. BGP graceful restart functionality is used on all PE-to-PE BGP sessions. This affects sessions carrying any service signaling data for network layer reachability information (NLRI), for example, an IPv4 VPN or Layer 2 VPN NLRI.
2. OSPF, IS-IS, LDP, or RSVP graceful restart functionality is used in all core routers. Routes added by these protocols are used to resolve Layer 2 and Layer 3 VPN NLRI.
3. Protocol restart functionality is used for any Layer 3 protocol (RIP, OSPF, LDP, and so on) used between the PE and customer edge (CE) routers. This does not apply to Layer 2 VPNs because Layer 2 protocols used between the CE and PE routers do not have graceful restart capabilities.

Before VPN graceful restart can work properly, all of the components must restart gracefully. In other words, the routers must preserve their forwarding states and request neighbors to continue forwarding to the router in case of a restart. If all of the conditions are satisfied, VPN graceful restart imposes the following rules on a restarting router:

- The router must wait to receive all BGP NLRI information from other PE routers before advertising routes to the CE routers.
- The router must wait for all protocols in all routing instances to converge (or complete the restart process) before it sends CE router information to other PE routers. In other words, the router must wait for all instance information (whether derived from local configuration or advertisements received from a remote peer) to be processed before it sends this information to other PE routers.
- The router must preserve all forwarding state in the **instance.mpls.0** tables until the new labels and transit routes are allocated and announced to other PE routers (and CE routers in a carrier-of-carriers scenario).

If any condition is not met, VPN graceful restart does not succeed in providing uninterrupted forwarding between CE routers across the VPN infrastructure.

- Related Documentation**
- [Graceful Restart Concepts on page 49](#)
 - [Graceful Restart System Requirements on page 50](#)
 - [Configuring Logical System Graceful Restart on page 127](#)

- [Verifying Graceful Restart Operation on page 214](#)
- [Example: Configuring Graceful Restart on page 129](#)

Graceful Restart on Logical Systems

Graceful restart for a logical system functions much as graceful restart does in the main router. The only difference is the location of the **graceful-restart** statement:

- For a logical system, include the **graceful-restart** statement at the **[edit logical-systems *logical-system-name* routing-options]** hierarchy level.
- For a routing instance inside a logical system, include the **graceful-restart** statement at both the **[edit logical-systems *logical-system-name* routing-options]** and **[edit logical-systems *logical-system-name* routing-instances *instance-name* routing-options]** hierarchy levels.

Related Documentation

- [Graceful Restart Concepts on page 49](#)
- [Graceful Restart System Requirements on page 50](#)
- [Configuring Logical System Graceful Restart on page 127](#)
- [Verifying Graceful Restart Operation on page 214](#)
- [Example: Configuring Graceful Restart on page 129](#)

CHAPTER 7

VRRP

- [Understanding VRRP on page 59](#)
- [Junos OS Support for VRRPv3 on page 60](#)
- [Improving the Convergence Time for VRRP on page 63](#)

Understanding VRRP

For Ethernet, Fast Ethernet, Gigabit Ethernet, 10-Gigabit Ethernet, and logical interfaces, you can configure the Virtual Router Redundancy Protocol (VRRP) or VRRP for IPv6. VRRP enables hosts on a LAN to make use of redundant routing platforms on that LAN without requiring more than the static configuration of a single default route on the hosts. The VRRP routing platforms share the IP address corresponding to the default route configured on the hosts. At any time, one of the VRRP routing platforms is the master (active) and the others are backups. If the master fails, one of the backup routers becomes the new master router, providing a virtual default routing platform and enabling traffic on the LAN to be routed without relying on a single routing platform. Using VRRP, a backup router can take over a failed default router within a few seconds. This is done with minimum VRRP traffic and without any interaction with the hosts.

Routers running VRRP dynamically elect master and backup routers. You can also force assignment of master and backup routers using priorities from 1 through 255, with 255 being the highest priority. In VRRP operation, the default master router sends advertisements to backup routers at regular intervals. The default interval is 1 second. If a backup router does not receive an advertisement for a set period, the backup router with the next highest priority takes over as master and begins forwarding packets.




NOTE: To minimize network traffic, VRRP is designed in such a way that only the router that is acting as the master sends out VRRP advertisements at any given point in time. The backup routers do not send any advertisement until and unless they take over mastership.

VRRP for IPv6 provides a much faster switchover to an alternate default router than IPv6 Neighbor Discovery (ND) procedures. Typical deployments use only one backup router.

Figure 7 on page 60 illustrates a basic VRRP topology. In this example, Routers A, B, and C are running VRRP and together they make up a virtual router. The IP address of this virtual router is 10.10.0.1 (the same address as the physical interface of Router A).

Figure 7: Basic VRRP



Because the virtual router uses the IP address of the physical interface of Router A, Router A is the master VRRP router, while Routers B and C function as backup VRRP routers. Clients 1 through 3 are configured with the default gateway IP address of 10.10.0.1. As the master router, Router A forwards packets sent to its IP address. If the master virtual router fails, the router configured with the higher priority becomes the master virtual router and provides uninterrupted service for the LAN hosts. When Router A recovers, it becomes the master virtual router again.

VRRP is defined in RFC 3768, *Virtual Router Redundancy Protocol (VRRP)*. VRRP for IPv6 is defined in Internet draft draft-ietf-vrrp-ipv6-spec-08.txt, *Virtual Router Redundancy Protocol for IPv6*. See also Internet draft draft-ietf-vrrp-unified-mib-06.txt, *Definitions of Managed Objects for the VRRP over IPv4 and IPv6*.



NOTE: Even though VRRP, as defined in RFC 3768, does not support authentication, the Junos OS implementation of VRRP supports authentication as defined in RFC 2338. This support is achieved through the backward compatibility options in RFC 3768.

Related Documentation

- [Understanding High Availability Features on Juniper Networks Routers on page 3](#)
- [Configuring Basic VRRP Support on page 160](#)

Junos OS Support for VRRPv3

Prior to Junos OS Release 12.2, Junos OS supported RFC 3768, *Virtual Router Redundancy Protocol (VRRP)* and Internet draft draft-ietf-vrrp-ipv6-spec-08, *Virtual Router Redundancy Protocol for IPv6*. Starting with Junos OS Release 12.2, Junos OS supports Virtual Router Redundancy Protocol version 3 (VRRPv3). The support for VRRPv3 is implemented in compliance with RFC 5798, *Virtual Router Redundancy Protocol (VRRP) Version 3 for IPv4 and IPv6*. Junos OS Release 12.2 also supports VRRP MIB for VRRPv3.

The support for VRRP MIB for VRRPv3 is implemented in compliance with RFC 6527, *Definitions of Managed Objects for the Virtual Router Redundancy Protocol Version 3 (VRRPv3)*.

When you configure VRRP for IPv4 or IPv6 networks, you can enable VRRPv3 by configuring the **version-3** statement at the **[edit protocols vrrp]** hierarchy level.



NOTE: When enabling VRRPv3, you must ensure that VRRPv3 is enabled on all the VRRP routers in the network. This is because VRRPv3 does not interoperate with the previous versions of VRRP.

Understanding VRRPv3 Behavioral Differences

You must consider the following aspects when enabling VRRPv3 for your IPv4 or IPv6 networks:

- When VRRP for IPv6 is configured without enabling VRRPv3, the VRRP checksum is calculated according to section 5.3.8 of RFC 3768, *Virtual Router Redundancy Protocol (VRRP)*. However, when VRRPv3 is enabled, the VRRP checksum is calculated according to section 5.3.7 of draft-ietf-vrrp-ipv6-spec-08.txt, *Virtual Router Redundancy Protocol for IPv6*. Therefore, when IPv6 VRRP packets are received or transmitted, the VRRP checksum is calculated according to:
 - RFC 3768, when VRRPv3 is *not* enabled.
 - draft-ietf-vrrp-ipv6-spec-08.txt, when VRRPv3 is enabled.
- The **tcpdump** utility calculates the VRRP checksum according to draft-ietf-vrrp-ipv6-spec-08.txt. Therefore, when **tcpdump** parses IPv6 VRRP packets that are received from older Junos OS releases (prior to Junos OS Release 12.2), the **bad vrrp cksum** message is displayed:

```
23:20:32.657328 Out
...
-----original packet-----
00:00:5e:00:02:03 > 33:33:00:00:00:12, ethertype IPv6 (0x86dd), length
94: (class 0xc0, hlim 255, next-header: VRRP (112), length: 40)
fe80::224:dcff:fe47:57f > ff02::12: VRRPv3-advertisement 40: vrid=3 prio=100
intvl=100(centisec) (bad vrrp cksum b4e2!) addrs(2):
fe80::200:5eff:fe00:3,2001:4818:f000:14::1
3333 0000 0012 0000 5e00 0203 86dd 6c00
0000 0028 70ff fe80 0000 0000 0000 0224
dcff fe47 057f ff02 0000 0000 0000 0000
0000 0000 0012 3103 6402 0064 b4e2 fe80
0000 0000 0000 0200 5eff fe00 0003 2001
4818 f000 0014 0000 0000 0000 0001
```

You can ignore this message because it does not indicate VRRP failure.

- When VRRPv3 is enabled, the **authentication-type** and **authentication-key** statements (for IPv4 VRRP) cannot be configured for any VRRP groups. Therefore, if authentication is required, you need to configure alternative non-VRRP authentication mechanisms.

- When VRRPv3 is enabled, the **advertise-interval** statement (for IPv4 VRRP) and the **inet6-advertise-interval** statement (for IPv6 VRRP) cannot be used to configure advertisement intervals. Instead, use the **fast-interval** statement to configure advertisement intervals.
- VRRPv3 for IPv4 does not interoperate with the previous versions of VRRP. If VRRPv2 IPv4 advertisement packets are received by a router on which VRRPv3 is enabled, the router transitions itself to the backup state to avoid creating multiple masters in the network. Due to this behavior, you must be cautious when enabling VRRPv3 on your existing VRRPv2 networks. See [“Understanding VRRPv2 to VRRPv3 Transition” on page 62](#) for more information.



NOTE: VRRPv3 advertisement packets are ignored by the routers on which previous versions of VRRP are configured.

Understanding VRRPv2 to VRRPv3 Transition

You must enable VRRPv3 in your network only if VRRPv3 can be enabled on all the VRRP routers in your network. Even if VRRPv3 can be enabled on all the VRRP routers in your network, care must be taken to avoid traffic loss when you transition your network to VRRPv3. This is because it is practically not possible to configure VRRPv3 on all routers simultaneously. There is a small time frame in the transition period during which VRRPv2 and VRRPv3 coexist in the network. During this period, to avoid having multiple masters in the network, the VRRPv3 IPv4 routers switch to the backup state when they receive a VRRPv2 IPv4 advertisement packet. VRRPv2 IPv4 packets are always given the highest priority. Additionally, to avoid having multiple masters in your IPv6 network due to checksum differences, you need to disable VRRP for IPv6 on the backup routers.



NOTE: Configuration change from VRRPv2 to VRRPv3 (or VRRPv3 to VRRPv2) restarts the VRRP state machine on all the configured VRRP groups.

The following example illustrates the steps and events that take place during a VRRPv2 to VRRPv3 transition:

Consider a scenario where two VRRPv2 routers, R1 and R2, are configured in two groups, G1 and G2. The R1 router acts as the master for G1 and the R2 router acts as the master for G2. [Table 7 on page 62](#) lists the transition steps and events for this setup:

Table 7: Example: VRRPv2 to VRRPv3 Transition Steps and Events

1. Upgrade the R1 router with Junos OS Release 12.2 or later.
 - R2 becomes master for both G1 and G2.
 - After the upgrade of the R1 router is completed, R1 becomes the master for G1. R2 remains as the master for G2.
2. Upgrade the R2 router with Junos OS Release 12.2 or later.
 - R1 becomes master for both G1 and G2.
 - After the upgrade of R2 router is completed, R2 becomes the master for G2. R1 remains as the master for G1.

Table 7: Example: VRRPv2 to VRRPv3 Transition Steps and Events (*continued*)

For IPv4	For IPv6
3. Enable VRRPv3 on the R1 router. <ul style="list-style-type: none"> Because VRRPv2 IPv4 advertisement packets are given higher priority, R1 becomes the backup for both G1 and G2. 	3. Deactivate the G1 and G2 groups on the R2 router. <ul style="list-style-type: none"> G1 and G2 groups on the R1 router become master.
4. Enable VRRPv3 on the R2 router. <ul style="list-style-type: none"> R1 becomes the master for G1 and R2 becomes the master for G2. 	4. Enable VRRPv3 on the R1 router. <ul style="list-style-type: none"> R1 becomes master for both G1 and G2.
	5. Enable VRRPv3 on the R2 router.
	6. Activate G1 and G2 groups on the R2 router. <ul style="list-style-type: none"> R2 becomes master for G2. R1 remains as the master for G1.

Related Documentation	<ul style="list-style-type: none"> Understanding High Availability Features on Juniper Networks Routers on page 3 Configuring Basic VRRP Support on page 160 VRRP Configuration Hierarchy on page 157 VRRP for IPv6 Configuration Hierarchy on page 158 authentication-type on page 236 authentication-key on page 235 fast-interval on page 239 inet6-advertise-interval on page 242 version-3 on page 253 virtual-link-local-address on page 255
------------------------------	--

Improving the Convergence Time for VRRP

You can enable faster convergence time for the configured Virtual Router Redundancy Protocol (VRRP), thereby reducing the traffic restoration time to less than 1 second. To improve the convergence time for the VRRP, perform the following tasks:

- **Configure the distributed periodic packet management process**—When the VRRP process is busy and does not send VRRP advertisements, the backup VRRP routers might assume that the master router is down and take over as the master router, causing unnecessary flaps. To address this problem and to reduce the load on the VRRP process, Junos OS uses the distributed periodic packet management (PPM) process to send VRRP advertisements on behalf of the VRRP process.

To configure the distributed PPM process, include the **delegate-processing** statement at the **[edit protocols vrrp]** hierarchy level.

- **Disable the skew timer**—The skew timer in VRRP is used to ensure that two backup routers do not switch to the master state at the same time in case of a failover situation. When there is only one master router and one backup router in the network deployment,

you can disable the skew timer, thereby reducing the time required to transition to the master state.

To disable the skew timer, include the **skew-timer-disable** statement at the **[edit protocols vrrp]** hierarchy level.

- **Configure the number of fast advertisements that can be missed by a backup router before it starts transitioning to the master state**—The backup router waits until a certain number of advertisement packets are lost after which it transitions to the master state. This waiting time can be fatal in scenarios such as router failure or link failure. To avoid such a situation and to enable faster convergence time, in Junos OS Release 12.2 and later, you can configure a fast advertisement interval value that specifies the number of fast advertisements that can be missed by a backup router before it starts transitioning to the master state.

To configure the fast advertisement interval, include the **global-advertisements-threshold** statement at the **[edit protocols vrrp]** hierarchy level.

- **Configure inheritance of VRRP groups**—Junos OS enables you to configure VRRP groups on the various subnets of a virtual LAN (VLAN) to inherit the state and configuration of one of the groups, which is known as the active VRRP group. When the **vrrp-inherit-from** statement is included in the configuration, only the active VRRP group, from which the other VRRP groups inherit the state, sends out frequent VRRP advertisements and processes incoming VRRP advertisements. Use inherit groups for scaled configurations. For example, if you have 1000 VRRP groups with an advertisement interval of 100 ms, then use inherit groups.

To configure inheritance for a VRRP group, include the **vrrp-inherit-from** statement at the **[edit interfaces interface-name unit logical-unit-number family inet address address vrrp-group group-id]** hierarchy level.



NOTE:

- The reduction in convergence time is not applicable when VRRP is configured over integrated routing and bridging (IRB) interfaces, aggregated Ethernet interfaces, and multichassis link aggregation group (MC-LAG) interfaces.
- Compared to other routers, the convergence time and the traffic restoration time are less for MX Series routers with MPCs.
- Reduction in convergence time is applicable for all types of configurations at the physical interface but the convergence time might not be less than 1 second for all the configurations. The convergence time depends on the number of groups that are transitioning from the backup to the master state and the interval at which these groups are transitioning.

Related Documentation

- [Configuring Inheritance for a VRRP Group on page 172](#)
- [Configuring VRRP to Improve Convergence Time on page 176](#)
- [delegate-processing on page 238](#)

- [global-advertisements-threshold](#) on page 240
- [skew-timer-disable](#) on page 249

CHAPTER 8

Unified ISSU

- [Unified ISSU Concepts on page 67](#)
- [Unified ISSU Process on the TX Matrix Router on page 72](#)
- [Unified ISSU System Requirements on page 73](#)

Unified ISSU Concepts

A unified in-service software upgrade (unified ISSU) enables you to upgrade between two different Junos OS Releases with no disruption on the control plane and with minimal disruption of traffic. Unified ISSU is only supported on dual Routing Engine platforms. In addition, the graceful Routing Engine switchover (GRES) and nonstop active routing (NSR) must be enabled.

A unified ISSU provides the following benefits:

- Eliminates network downtime during software image upgrades
- Reduces operating costs, while delivering higher service levels
- Allows fast implementation of new features



NOTE: The master Routing Engine and backup Routing Engine must be running the same software version before you can perform a unified ISSU.

You cannot take any PICs online or offline during a unified ISSU.



NOTE: You can verify the unified ISSU-compatibility of the software, hardware, and the configuration on a device by issuing the `request system software validate in-service-upgrade` command. This command runs the validation checks, and shows whether the operating system, device components, and configurations are ISSU compatible or not. For more information about the `request system software validate in-service-upgrade` command, see Junos OS Operational Mode Commands.



NOTE: Unicast RPF-related statistics are not saved across a unified ISSU, and the unicast RPF counters are reset to zero during a unified ISSU.

To perform a unified ISSU, complete the following steps:

1. Enable graceful Routing Engine switchover and nonstop active routing. Verify that the Routing Engines and protocols are synchronized.
2. Download the new software package from the Juniper Networks Support website and then copy the package to the router.
3. Issue the **request system software in-service-upgrade** command on the master Routing Engine.

A Junos OS Release package comprises three distinct systems:

- Juniper Networks Operating System, which provides system control and all the features and functions of the Juniper Networks router that executes in the Routing Engines
- Juniper Networks Packet Forwarding Engine, which supports the high-performance traffic forwarding and packet handling capabilities
- Interface control

After the **request system software in-service-upgrade** command is issued, the following process occurs.




NOTE: In the illustrations, a solid line indicates the high-speed internal link between a Routing Engine and a Packet Forwarding Engine. A dotted line indicates the chassis process (chassisd), another method of communication between a Routing Engine and a Packet Forwarding Engine. RE0m and RE1s indicate master and backup (or standby) Routing Engines, respectively.




NOTE: The following process pertains to all supported routing platforms except the TX Matrix router. For information about the unified ISSU process on the TX Matrix router, see [“Unified ISSU Process on the TX Matrix Router” on page 72](#). On M320 and T320 routers and on T640 and T1600 routers, the Packet Forwarding Engine resides on an FPC. However, on an M120 router, the Forwarding Engine Board (FEB) replaces the functions of a Packet Forwarding Engine. In the illustrations and steps, when considering an M120 router, you can regard the PFE as an FPC. As an additional step on an M120 router, after the FPCs and PICs have been upgraded, the FEBs are upgraded.


1. The master Routing Engine validates the router configuration to ensure that it can be committed using the new software version. Checks are made for disk space available for the `/var` file system on both Routing Engines, unsupported configurations, and for unsupported Physical Interface Cards (PICs). If there is not sufficient disk space available on either of the Routing Engines, the unified ISSU process fails and returns an error message saying that the Routing Engine does not have enough disk space available. However, unsupported PICs do not prevent a unified ISSU. The software issues a warning to indicate that these PICs will restart during the upgrade. Similarly, an unsupported protocol configuration does not prevent a unified ISSU. The software issues a warning that packet loss may occur for the protocol during the upgrade.




2. When the validation succeeds, the kernel state synchronization daemon (ksyncd) synchronizes the kernel on the backup Routing Engine with the master Routing Engine.
3. The backup Routing Engine is upgraded with the new software image. Before being upgraded, the backup Routing Engine gets the configuration file from the master Routing Engine and validates the configuration to ensure that it can be committed using the new software version. After being upgraded, it is resynchronized with the master Routing Engine. In the illustration, an apostrophe (') indicates the device is running the new version of software.



4. The chassis process (chassisd) on the master Routing Engine prepares other software processes for the unified ISSU. When all the processes are ready, chassisd sends an ISSU_PREPARE message to the Flexible PIC Concentrators (FPCs) installed in the router.
5. The Packet Forwarding Engine on each FPC saves its state and downloads the new software image from the backup Routing Engine. Next, each Packet Forwarding Engine sends an ISSU_READY message to the chassis process (chassisd).




6. After receiving an ISSU_READY message from a Packet Forwarding Engine, the chassis process (chassisd) sends an ISSU_REBOOT message to the FPC on which the Packet Forwarding Engine resides. The FPC reboots with the new software image. After the FPC is rebooted, the Packet Forwarding Engine restores the FPC state and a high-speed internal link is established with the backup Routing Engine running the new software. The chassis process (chassisd) is also reestablished with the master Routing Engine.
7. After all Packet Forwarding Engines have sent a READY message using the chassis process (chassisd) on the master Routing Engine, other software processes are prepared for a Routing Engine switchover. The system is ready for a switchover at this point.






NOTE: In the case of an M120 router, the FEBs are upgraded at this point. When all FEBs have been upgraded, the system is ready for a switchover.

8. The Routing Engine switchover occurs and the backup Routing Engine becomes the new master Routing Engine.



9. The new backup Routing Engine is now upgraded to the new software image. (This step is skipped if the **no-old-master-upgrade** option is specified.)



10. When the backup Routing Engine has been successfully upgraded, the unified ISSU is complete.

Related Documentation

- [Unified ISSU Process on the TX Matrix Router on page 72](#)
- [Unified ISSU System Requirements on page 73](#)
- [Best Practices on page 259](#)
- [Before You Begin on page 259](#)
- [Performing a Unified ISSU on page 262](#)

Unified ISSU Process on the TX Matrix Router

After you issue the **request system software in-service-upgrade** command on a TX Matrix router, the following process occurs.

1. The management process (mgd) on the master Routing Engine of the TX Matrix router (global master) checks whether nonstop active routing (NSR) and graceful Routing Engine switchover (GRES) are enabled in the current configuration.
2. After successful validation of nonstop active routing and graceful Routing Engine switchover configuration, the management process copies the new image to the backup Routing Engines on the TX Matrix router and the T640 routers.
3. The kernel synchronization process (ksyncd) on the backup Routing Engines synchronizes the kernel on the backup Routing Engines with that of the master Routing Engines.
4. The backup Routing Engines are upgraded with the new software and are rebooted. After rebooting, the backup Routing Engines are once again synchronized with the global master Routing Engine.
5. The unified ISSU control moves from the management process to the chassis process (chassisd). The chassis process informs the software processes about the unified ISSU and waits for responses from various software processes (such as spmb).
6. After receiving messages from the software processes indicating that the processes are ready for unified ISSU, the chassis process on the global master Routing Engine sends messages to the chassis process on the routing nodes to start the unified ISSU.
7. The chassis process on the routing nodes sends ISSU_PREPARE messages to the field replaceable units (FRUs), such as FPC and intelligent PICs.
8. On receiving an ISSU_PREPARE message, the Packet Forwarding Engines save the current state information and download the new software image from the backup Routing Engines. Next, each Packet Forwarding Engine sends ISSU_READY messages to the chassis process.
9. On receiving an ISSU_READY message from the Packet Forwarding Engines, the chassis process sends an ISSU_REBOOT message to the FRUs. While the upgrade is in progress, the FRUs keep sending ISSU_IN_PROGRESS messages to the chassis process on the routing nodes. The chassis process on each routing node, in turn, sends an ISSU_IN_PROGRESS message to the chassis process on the global master Routing Engine.
10. After the reboot, the Packet Forwarding Engines restore the saved state information and connect back to the routing nodes; the chassis process on each routing node sends an ISSU_READY message to the chassis process on the global master Routing Engine. The ISSU_READY message from the chassis process on the routing nodes indicates that the unified ISSU is complete on the FRUs.
11. The unified ISSU control moves back to the management process on the global master Routing Engine.

12. The management process initiates Routing Engine switchover on the master Routing Engines.
13. Routing Engine switchover occurs on the TX Matrix router and the T640 routers.



NOTE: Currently, the FRUs on a TX Matrix router do not support graceful Routing Engine switchover and are rebooted every time graceful Routing Engine switchover occurs.

14. After the switchover, the FRUs connect to the new master Routing Engines, and the chassis manager and PFE manager on the T640 router FRUs connect to the new master Routing Engines on the T640 routers.
15. The management process on the global master Routing Engine initiates the upgrade process on the old master Routing Engines on the T640 routers.
16. After the old master Routing Engines on the T640 routers are upgraded, the management process initiates the upgrade of the old global master Routing Engine, that is, the old master Routing Engine on the TX Matrix router.
17. After a successful unified ISSU, the TX Matrix router and the T640 routers are rebooted.

Related Documentation

- [Unified ISSU Concepts on page 67](#)
- [Unified ISSU System Requirements on page 73](#)
- [Best Practices on page 259](#)
- [Before You Begin on page 259](#)
- [Performing a Unified ISSU on page 262](#)

Unified ISSU System Requirements

This section contains the following topics:

- [Unified ISSU Junos OS Release Support on page 73](#)
- [Unified ISSU Platform Support on page 74](#)
- [Unified ISSU Protocol Support on page 74](#)
- [Unified ISSU Feature Support on page 76](#)
- [Unified ISSU PIC Support on page 76](#)
- [Unified ISSU Support on MX Series 3D Universal Edge Routers on page 84](#)

Unified ISSU Junos OS Release Support

In order to perform a unified ISSU, your router must be running a Junos OS Release that supports unified ISSU for the specific platform. See [“Unified ISSU Platform Support” on page 74](#). You can use unified ISSU to upgrade from an ISSU-capable software release to a newer software release. However, note that:

- The unified ISSU process is aborted if the Junos OS version specified for installation is a version earlier than the one currently running on the device. To downgrade from an ISSU-capable release to a previous software release (ISSU-capable or not), use the **request system add** command. Unlike an upgrade using the unified ISSU process, a downgrade using the **request system add** command can cause network disruptions and loss of data. For more information about the use of the **request system add** command, see the Installation and Upgrade Guide.
- The unified ISSU process is aborted if the specified upgrade has conflicts with the current configuration, components supported, and so forth.
- Unified ISSU does not support extension application packages developed using the Junos SDK.

Unified ISSU Platform Support

Table 8 on page 74 lists the platforms on which a unified ISSU is supported.

Table 8: Unified ISSU Platform Support

Routing Platform	Junos OS Release
M120 router	9.2 or later
M320 router	9.0 or later
M10i router with Enhanced Compact Forwarding Engine Board (CFEB-E)	9.5 or later
MX Series devices	9.3 or later
NOTE: Unified ISSU for MX Series routers does not support IEEE 802.1ag OAM and IEEE 802.3ah protocols.	11.2 or later on MX Series 3D Universal Edge Routers (with Trio Modular Port Concentrator/Modular Interface Card (MPC/MIC) interfaces).
T320 router	9.0 or later
T640 router	9.0 or later
T1600 router	9.1 or later
TX Matrix router	9.3 or later

Unified ISSU Protocol Support

Unified ISSU is dependent on nonstop active routing. Table 9 on page 75 lists the protocols that are supported during a unified ISSU.

Table 9: Unified ISSU Protocol Support

Protocol	Junos OS Release
BGP	9.0 or later
DHCP access model (subscriber access)	11.2 or later
IS-IS	9.0 or later
LDP	9.0 or later
LDP-based virtual private LAN service (VPLS)	9.3 or later
Layer 2 circuits	9.2 or later
Layer 3 VPNs using LDP	9.2 or later
Link Aggregation Control Protocol (LACP) on MX Series routers	9.4 or later
OSPF/OSPFv3	9.0 or later
PPPoE access model (subscriber access)	11.4 or later
Protocol Independent Multicast (PIM)	9.3 or later
Routing Information Protocol (RIP)	9.1 or later

Unified ISSU Support for the Layer 2 Control Protocol Process

Unified ISSU supports the Layer 2 Control Protocol process (l2cpd) on MX Series 3D Universal Edge Routers. In a Layer 2 bridge environment, spanning tree protocols share information about port roles, bridge IDs, and root path costs between bridges using special data frames called Bridge Protocol Data Units (BPDUs). The transmission of BPDUs is controlled by the l2cpd process. Transmission of hello BPDUs is important in maintaining adjacencies on the peer systems.

The transmission of periodic packets on behalf of the l2cpd process is carried out by periodic packet management (PPM), which, by default, is configured to run on the Packet Forwarding Engine. The ppm process on the Packet Forwarding Engine ensures that the BPDUs are transmitted even when the l2cpd process control plane is unavailable, and keeps the remote adjacencies alive during unified ISSU. However, if you want the distributed PPM (ppmd) process to run on the Routing Engine instead of the Packet Forwarding Engine, you can disable the ppm process on the Packet Forwarding Engine, by including the **no-delegate-processing** statement at the [edit routing-options ppm] hierarchy level.



NOTE: The `delegate-processing` statement at the `[edit routing-options ppm]` hierarchy level, which was used to enable the `ppmd` process on the Packet Forwarding Engine in Junos OS Release 9.3 and earlier, has been deprecated as the `ppmd` process is enabled on the Packet Forwarding Engine by default in Junos OS Release 9.4 and later.

Unified ISSU enhancements and nonstop active bridging support for the `l2cpd` process ensure that the new master Routing Engine is able to take control during unified ISSU without any disruptions in the control plane and minimize the disruptions in the Layer 2 data plane during unified ISSU.

Unified ISSU Feature Support

Unified ISSU supports most Junos OS features in Junos OS Release 9.0. However, the following constraints apply:

- Link Aggregation Control Protocol (LACP)—Link changes are not processed until after the unified ISSU is complete.
- Automatic Protection Switching (APS)—Network changes are not processed until after the unified ISSU is complete.
- Ethernet Operation, Administration, and Management (OAM) as defined by IEEE 802.3ah and by IEEE 802.1ag—When a Routing Engine switchover occurs, the OAM hello times out, triggering protocol convergence.
- Ethernet circuit cross-connect (CCC) encapsulation—Circuit changes are not processed until after the unified ISSU is complete.
- Logical systems—On routers that have logical systems configured on them, only the master logical system supports unified ISSU.

Unified ISSU PIC Support

The following sections list the Physical Interface Cards (PICs) that are supported during a unified ISSU.

- [PIC Considerations on page 77](#)
- [SONET/SDH PICs on page 77](#)
- [Fast Ethernet and Gigabit Ethernet PICs on page 79](#)
- [Channelized PICs on page 80](#)
- [Tunnel Services PICs on page 81](#)
- [ATM PICs on page 82](#)
- [Serial PICs on page 82](#)
- [DS3, E1, E3, and T1 PICs on page 83](#)
- [Enhanced IQ PICs on page 83](#)
- [Enhanced IQ2 Ethernet Services Engine \(ESE\) PIC on page 83](#)



NOTE: For information about FPC types, FPC/PIC compatibility, and the initial Junos OS Release in which an FPC supported a particular PIC, see the PIC guide for your router platform.

PIC Considerations

Take the following PIC restrictions into consideration before performing a unified ISSU:

- **Unsupported PICs**—If a PIC is not supported by unified ISSU, at the beginning of the upgrade the software issues a warning that the PIC will be brought offline. After the PIC is brought offline and the ISSU is complete, the PIC is brought back online with the new firmware.
- **PIC combinations**—For some PICs, newer Junos OS services can require significant Internet Processor ASIC memory, and some configuration rules might limit certain combinations of PICs on particular platforms. With a unified ISSU:
 - If a PIC combination is not supported by the software version that the router is being upgraded from, the upgrade will be aborted.
 - If a PIC combination is not supported by the software version to which the router is being upgraded, the in-service software upgrade will abort, even if the PIC combination is supported by the software version from which the router is being upgraded.
- **Interface statistics**—Interface statistics might be incorrect because:
 - During bootup of the new microkernel on the Packet Forwarding Engine (PFE), host-bound traffic is not handled and might be dropped, causing packet loss.
 - During the hardware update of the Packet Forwarding Engine and its interfaces, traffic is halted and discarded. (The duration of the hardware update depends on the number and type of interfaces and on the router configuration.)
 - During a unified ISSU, periodic statistics collection is halted. If hardware counters saturate or wrap around, the software does not display accurate interface statistics.
- **CIR oversubscription**—If oversubscription of committed rate information (CIR) is configured on logical interfaces:
 - And the sum of the CIR exceeds the physical interface's bandwidth, after a unified in-service software upgrade is performed, each logical interface might not be given its original CIR.
 - And the sum of the delay buffer rate configured on logical interfaces exceeds the physical interface's bandwidth, after a unified in-service software upgrade is performed, each logical interface might not receive its original delay-buffer-rate calculation.

SONET/SDH PICs

Table 10 on page 78 lists the SONET/SDH PICs that are supported during a unified ISSU.

Table 10: Unified ISSU PIC Support: SONET/SDH

PIC Type	Number of Ports	Model Number	Router
OC3c/STM1	4-port	PB-4OC3-SON-MM—(EOL)	M120 M320, T320, T640, T1600
		PB-4OC3-SON-SMIR—(EOL)	
		PE-4OC3-SON-MM—(EOL)	M10i
		PE-4OC3-SON-SMIR—(EOL)	
	2-port	PE-2OC3-SON-MM—(EOL)	
		PE-2OC3-SON-SMIR—(EOL)	
OC3c/STM1 with SFP	2-port	PE-2OC3-SON-SFP	M10i
OC3c/STM1, SFP (Multi-Rate)	4 OC3 ports, 4 OC12 ports	PB-4OC3-4OC12-SON-SFP	M120 M320, MX Series, T320, T640, T1600
	4 OC3 ports, 1 OC12 port	PB-4OC3-1OC12-SON-SFP	
		PB-4OC3-1OC12-SON2-SFP	M10i
		PE-4OC3-1OC12-SON-SFP	
OC12c/STM4	1-port	PE-1OC12-SON-SFP	M10i
		PE-1OC12-SON-MM—(EOL)	
		PE-1OC12-SON-SMIR—(EOL)	
		PB-1OC12-SON-MM—(EOL)	
		PB-1OC12-SON-SMIR—(EOL)	M120, M320, T320, T640, T1600, TX Matrix
	4-port	PB-4OC12-SON-MM	
		PB-4OC12-SON-SMIR	
OC12c/STM4, SFP	1-port	PB-1OC12-SON-SFP	M120, M320, T320, T640, T1600, TX Matrix
OC48c/STM16, SFP	1-port	PB-1OC48-SON-SFP	M120, M320, MX Series, T320, T640, T1600, TX Matrix
		PB-1OC48-SON-B-SFP	
	4-port	PC-4OC48-SON-SFP	
OC192/STM64	1-port	PC-1OC192-SON-VSR	MX Series routers

Table 10: Unified ISSU PIC Support: SONET/SDH (*continued*)

PIC Type	Number of Ports	Model Number	Router
OC192/STM64, XFP	1-port	PC-1OC192-SON-LR	M320, T320, T640, T1600
		PC-1OC192-SON-SR2	
		PC-1OC192-VSR	
OC192/STM64, XFP	4-port	PD-4OC192-SON-XFP	M120, T640, T1600
	1-port	PC-1OC192-SON-XFP	MX Series routers
OC768/STM256	1-port	PD-1OC768-SON-SR	T640, T1600

Fast Ethernet and Gigabit Ethernet PICs

Table 11 on page 79 lists the Fast Ethernet and Gigabit Ethernet PICs that are supported during a unified ISSU.



NOTE: Starting with Junos OS Release 9.2, new Ethernet IQ2 PIC features might cause the software to reboot the PIC when a unified ISSU is performed. For information about applicable new Ethernet IQ2 PIC features, refer to the release notes for the specific Junos OS Release.

Table 11: Unified ISSU PIC Support: Fast Ethernet and Gigabit Ethernet

PIC Type	Number of Ports	Model Number	Router
Fast Ethernet	4	PB-4FE-TX	M120, M320, T320, T640, T1600, TX Matrix
		PE-4FE-TX	M10i
	8	PB-8FE-FX	M120, M320
		PE-8FE-FX	M10i
	12	PB-12FE-TX-MDI	M120, M320, T320
		PB-12FE-TX-MDIX	
		PE-12FE-TX-MDI	M10i
		PE-12FE-TX-MDIX	
	48	PB-48FE-TX-MDI	M120, M320, T320
		PB-48FE-TX-MDIX	

Table 11: Unified ISSU PIC Support: Fast Ethernet and Gigabit Ethernet (*continued*)

PIC Type	Number of Ports	Model Number	Router
Gigabit Ethernet, SFP	1	PE-1GE-SFP	M10i
		PB-1GE-SFP	M120, M320, T320, T640, T1600, TX Matrix
	2	PB-2GE-SFP	
	4	PB-4GE-SFP	
	10	PC-10GE-SFP	
Gigabit Ethernet IQ, SFP	1	PE-1GE-SFP-QPP	M10i
		PB-1GE-SFP-QPP	M120, M320, T320, T640, T1600, TX Matrix
	2	PB-2GE-SFP-QPP	
Gigabit Ethernet IQ2, SFP	4	PB-4GE-TYPE1-SFP-IQ2	M120, M320, T320, T640, T1600, TX Matrix
	8	PB-8GE-TYPE2-SFP-IQ2	
		PC-8GE-TYPE3-SFP-IQ2	
Gigabit Ethernet IQ2, XFP	1	PC-1XGE-TYPE3-XFP-IQ2	M120, M320, T320, T640, T1600, TX Matrix
10-Gigabit Ethernet, XENPAK	1	PC-1XGE-XENPAK	M120, M320, T320, T640, T1600, TX Matrix
10-Gigabit Ethernet, DWDM	1	PC-1XGE-DWDM-CBAND	M120, M320, T320, T640, T1600, TX Matrix
10-Gigabit Ethernet	4	PD-4XGE-XFP <i>NOTE:</i> This PIC goes offline during a unified ISSU if the PIC is inserted on T-1600-FPC4-ES with revision number less than 13.	T640, T1600, TX Matrix, TX Matrix Plus
	10	PD-5-10XGE-SFPP	T640, T1600

Channelized PICs

Table 12 on page 81 lists the channelized PICs that are supported during a unified ISSU.

Table 12: Unified ISSU PIC Support: Channelized

PIC Type	Number of Ports	Model Number	Platform
Channelized E1 IQ	10	PB-10CHE1-RJ48-QPP	M120, M320, T320, T640, T1600, TX Matrix
		PB-10CHE1-RJ48-QPP-N	M120
		PE-10CHE1-RJ48-QPP	M10i
		PE-10CHE1-RJ48-QPP-N	
Channelized T1 IQ	10	PB-10CHT1-RJ48-QPP	M320, T320, T640, T1600
		PE-10CHT1-RJ48-QPP	M10i
Channelized OC IQ	1	PB-1CHOC12SMIR-QPP	M120, M320, T320, T640, T1600, TX Matrix
		PB-1CHSTM1-SMIR-QPP	
		PB-1CHOC3-SMIR-QPP	
		PE-1CHOC12SMIR-QPP	M10i
		PE-1CHOC3-SMIR-QPP	
Channelized DS3 to DS0 IQ	4	PB-4CHDS3-QPP	M120, M320, T320, T640, T1600, TX Matrix
		PE-4CHDS3-QPP	M10i
Channelized STM 1	1	PE-1CHSTM1-SMIR-QPP	M10i

Tunnel Services PICs

Table 13 on page 81 lists the Tunnel Services PICs that are supported during a unified ISSU.

Table 13: Unified ISSU PIC Support: Tunnel Services

PIC Type	Model Number	Platform
1-Gbps Tunnel	PE-TUNNEL	M10i
	PB-TUNNEL-1	M120, M320, T320, T640, T1600, TX Matrix
4-Gbps Tunnel	PB-TUNNEL	
10-Gbps Tunnel	PC-TUNNEL	

ATM PICs

Table 14 on page 82 lists the ATM PICs that are supported during a unified ISSU. This includes support on Enhanced III FPCs.

Table 14: Unified ISSU PIC Support: ATM

PIC Type	Number of Ports	Model Number	Platform
DS3	4	PB-4DS3-ATM2	M120, M320, T320, T640, T1600, TX Matrix
		PE-4DS3-ATM2	M10i
E3	4	PB-4E3-ATM2	M120, M320, T320, T640, T1600, TX Matrix
	2	PE-2E3-ATM2	M10i
OC3/STM1	2	PB-2OC3-ATM2-MM	M120, M320, T320, T640, T1600, TX Matrix
		PB-2OC3-ATM2-SMIR	
		PE-2OC3-ATM2-MM	M10i
		PE-2OC3-ATM2-SMIR	
OC12/STM4	1	PB-1OC12-ATM2-MM	M120, M320, T320, T640, T1600, TX Matrix
		PB-1OC12-ATM2-SMIR	
	2	PB-2OC12-ATM2-MM	M120, M320, T320, T640, T1600, TX Matrix
		PB-2OC12-ATM2-SMIR	
	1	PE-1OC12-ATM2-MM	M10i
		PE-1OC12-ATM2-SMIR	
OC48/STM16	1	PB-1OC48-ATM2-SFP	M120, M320, T320, T640, T1600, TX Matrix

Serial PICs

Unified ISSU supports the following 2-port EIA-530 serial PICs:

- PB-2EIA530 on M320 routers with Enhanced III FPCs, and on M120 routers
- PE-2EIA530 on M10i routers

DS3, E1, E3, and T1 PICs

Unified ISSU supports the following PICs on M120, M320, and T320 routers; T640 and T1600 routers; and the TX Matrix router:

- 4-Port DS3 PIC (PB-4DS3)
- 4-Port E1 Coaxial PIC (PB-4E1-COAX)
- 4-Port E1 RJ48 PIC (PB-4E1-RJ48)
- 4-port E3 IQ PIC (PB-4E3-QPP)
- 4-Port T1 PIC (PB-4T1-RJ48)

Unified ISSU supports the following PICs on M10i routers:

- 2-Port DS3 PIC (PE-2DS3)
- 4-Port DS3 PIC (PE-4DS3)
- 4-Port E1 PICs (PE-4E1-COAX and PE-4E1-RJ48)
- 2-Port E3 PIC (PE-2E3)
- 4-Port T1 PIC (PE-4T1-RJ48)
- 4-Port E3 IQ PIC (PE-4E3-QPP)

Enhanced IQ PICs

Unified ISSU supports the following PICs on M120, M320, and T320 routers; T640 and T1600 routers; and the TX Matrix router:

- 1-port Channelized OC12/STM4 enhanced IQ PIC (PB-1CHOC12-STM4-IQE-SFP)
- 1-port nonchannelized OC12/STM4 enhanced IQ PIC (PB-1OC12-STM4-IQE-SFP)
- 4-port Channelized DS3/E3 enhanced IQ PIC (PB-4CHDS3-E3-IQE-BNC)
- 4-port nonchannelized DS3/E3 enhanced IQ PIC (PB-4DS3-E3-IQE-BNC)
- 4-port nonchannelized SONET/SDH OC48/STM16 Enhanced IQ (IQE) PIC with SFP (PC-4OC48-STM16-IQE-SFP)

Unified ISSU supports 1-port Channelized OC48/STM16 Enhanced IQ (IQE) PIC with SFP (PB-1CHOC48-STM16-IQE-SFP) on MX Series routers.

Enhanced IQ2 Ethernet Services Engine (ESE) PIC

Unified ISSU supports the enhanced IQ2 ESE PICs listed in [Table 15 on page 83](#).

Table 15: Unified ISSU Support: Enhanced IQ2 Ethernet Services Engine (ESE) PIC

Model Number	Number of Ports	Platform
PC-8GE-TYPE3-SFP-IQ2E	8	M120, M320, T320, T640, and TX Matrix.

Table 15: Unified ISSU Support: Enhanced IQ2 Ethernet Services Engine (ESE) PIC (*continued*)

Model Number	Number of Ports	Platform
PB-8GE-TYPE2-SFP-IQ2E	8	M120, M320, T320, T640, and TX Matrix.
PB-4GE-TYPE1-SFP-IQ2E	4	M120, M320, T320, and T640.
PC-1XGE-TYPE3-XFP-IQ2E	1	M120, M320, T320, T640, and TX Matrix.
PB-1CHOC48-STM16-IQE	1	M120, M320, T320, T640, and TX Matrix.
PE-4GE-TYPE1-SFP-IQ2E	4	M10i.
PE-4GE-TYPE1-SFP-IQ2	4	M10i.

Unified ISSU Support on MX Series 3D Universal Edge Routers

The following sections list the Dense Port Concentrators (DPCs), Flexible PIC Concentrators (FPCs), Modular Port Concentrators (MPCs), and Modular Interface Cards (MICs) that are supported during a unified ISSU on MX Series 3D Universal Edge Routers.

- [Unified ISSU DPC and FPC Support on MX Series 3D Universal Edge Routers on page 84](#)
- [Unified ISSU MIC and MPC Support on MX Series 3D Universal Edge Routers on page 84](#)
- [Unified ISSU Limitation on MX Series 3D Universal Edge Routers on page 85](#)

Unified ISSU DPC and FPC Support on MX Series 3D Universal Edge Routers

Unified ISSU supports all Dense Port Concentrators (DPCs) except the Multiservices DPC on the MX Series routers. However, unified ISSU does not support either of the FPCs (FPC type 2, **MX-FPC2**, or FPC type 3, **MX-FPC3**) on the MX Series routers. For more information about DPCs and FPCs on MX Series routers, go to http://www.juniper.net/techpubs/en_US/release-independent/junos/information-products/pathway-pages/mx-series/.

Unified ISSU MIC and MPC Support on MX Series 3D Universal Edge Routers

Unified ISSU supports all the Modular Port Concentrators (MPCs) and Modular Interface Cards (MICs) listed in [Table 16 on page 85](#) and [Table 17 on page 85](#). Unified ISSU is not supported on MX80 routers nor in an MX Series Virtual Chassis.

In the MPCs on MX Series routers, interface-specific and firewall filter statistics are preserved across a unified ISSU. During the unified ISSU, counter and policer operations are disabled.

To preserve statistics across a unified ISSU on MX Series routers with MPC/MIC interfaces, the router stores the statistics data as binary large objects. The router collects the statistics before the unified ISSU is initialized, and restores the statistics after the unified ISSU completes. No statistics are collected during the unified ISSU process.

To verify that statistics are preserved across the unified ISSU, you can issue CLI operational commands such as **show interfaces statistics** after the unified ISSU completes.

Table 16: Unified ISSU Support: MX Series 3D Universal Edge Routers

MPC Type	Number of Ports	Model Number	Platform
30-Gigabit Ethernet MPC	—	MX-MPC1-3D	MX Series 3D Universal Edge Routers
30-Gigabit Ethernet Queuing MPC	—	MX-MPC1-3D-Q	MX Series 3D Universal Edge Routers
60-Gigabit Ethernet MPC	—	MX-MPC2-3D	MX Series 3D Universal Edge Routers
60-Gigabit Ethernet Queuing MPC	—	MX-MPC2-3D-Q	MX Series 3D Universal Edge Routers
60-Gigabit Ethernet Enhanced Queuing MPC	—	MX-MPC2-3D-EQ	MX Series 3D Universal Edge Routers
10-Gigabit Ethernet MPC with SFP+	16	MPC-3D-16XGE-SFPP	MX Series 3D Universal Edge Routers

Table 17: Unified ISSU Support: MX Series 3D Universal Edge Routers

MIC Type	Number of Ports	Model Number	Platform
Gigabit Ethernet MIC with SFP	20	MIC-3D-20GE-SFP	MX Series 3D Universal Edge Routers
10-Gigabit Ethernet MICs with XFP	2	MIC-3D-2XGE-XFP	MX Series 3D Universal Edge Routers
10-Gigabit Ethernet MICs with XFP	4	MIC-3D-4XGE-XFP	MX Series 3D Universal Edge Routers
Tri-Rate Copper Ethernet MIC	40	MIC-3D-40GE-TX	MX Series 3D Universal Edge Routers



NOTE: Note that unified ISSU is supported only by the MICs listed in [Table 17 on page 85](#).

Unified ISSU Limitation on MX Series 3D Universal Edge Routers

Unified in-service software upgrade (unified ISSU) is currently not supported when clock synchronization is configured for Synchronous Ethernet, Precision Time Protocol (PTP), and hybrid mode on MX80 3D Universal Edge Routers and on the MICs and MPCs on MX240, MX480, and MX960 routers.

**Related
Documentation**

- [Unified ISSU Concepts on page 67](#)
- [Unified ISSU Process on the TX Matrix Router on page 72](#)
- [Before You Begin on page 259](#)
- [Performing a Unified ISSU on page 262](#)

PART 2

Configuration

- [Routing Engine and Switching Control Board Redundancy on page 89](#)
- [Graceful Routing Engine Switchover on page 101](#)
- [Nonstop Bridging on page 103](#)
- [Nonstop Active Routing on page 105](#)
- [Graceful Restart on page 117](#)
- [VRRP on page 157](#)
- [Unified ISSU on page 189](#)

CHAPTER 9

Routing Engine and Switching Control Board Redundancy

- [Configuring Routing Engine Redundancy on page 89](#)
- [Configuring CFEB Redundancy on the M10i Router on page 93](#)
- [Configuring FEB Redundancy on the M120 Router on page 94](#)
- [Example: Configuring FEB Redundancy on page 95](#)
- [Configuring SFM Redundancy on M40e and M160 Routers on page 96](#)
- [Configuring SSB Redundancy on the M20 Router on page 97](#)
- [Chassis Redundancy Hierarchy on page 97](#)
- [Routing Engine and Switching Control Board Redundancy Configuration Statements on page 98](#)
- [Initial Routing Engine Configuration Example on page 98](#)

Configuring Routing Engine Redundancy

The following sections describe how to configure Routing Engine redundancy:



NOTE: To complete the tasks in the following sections, `re0` and `re1` configuration groups must be defined. For more information about configuration groups, see the CLI User Guide.

- [Modifying the Default Routing Engine Mastership on page 89](#)
- [Configuring Automatic Failover to the Backup Routing Engine on page 90](#)
- [Manually Switching Routing Engine Mastership on page 92](#)
- [Verifying Routing Engine Redundancy Status on page 92](#)

Modifying the Default Routing Engine Mastership

For routers with two Routing Engines, you can configure which Routing Engine is the master and which is the backup. By default, the Routing Engine in slot 0 is the master (`re0`) and the one in slot 1 is the backup (`re1`).



NOTE: In systems with two Routing Engines, both Routing Engines cannot be configured to be master at the same time. This configuration causes the commit check to fail.

To modify the default configuration, include the **routing-engine** statement at the **[edit chassis redundancy]** hierarchy level:

```
[edit chassis redundancy]
  routing-engine slot-number (master | backup | disabled);
```

slot-number can be 0 or 1. To configure the Routing Engine to be the master, specify the **master** option. To configure it to be the backup, specify the **backup** option. To disable a Routing Engine, specify the **disabled** option.



NOTE: To switch between the master and the backup Routing Engines, you must modify the configuration and then activate it by issuing the **commit synchronize** command.

Configuring Automatic Failover to the Backup Routing Engine

The following sections describe how to configure automatic failover to the backup Routing Engine when certain failures occur on the master Routing Engine.

- [Without Interruption to Packet Forwarding on page 90](#)
- [On Detection of a Hard Disk Error on the Master Routing Engine on page 90](#)
- [On Detection of a Loss of Keepalive Signal from the Master Routing Engine on page 90](#)
- [When a Software Process Fails on page 92](#)

Without Interruption to Packet Forwarding

For routers with two Routing Engines, you can configure graceful Routing Engine switchover (GRES). When graceful switchover is configured, socket reconnection occurs seamlessly without interruption to packet forwarding. For information about how to configure graceful Routing Engine switchover, see [“Configuring Graceful Routing Engine Switchover” on page 101](#).

On Detection of a Hard Disk Error on the Master Routing Engine

After you configure a backup Routing Engine, you can direct it to take mastership automatically if it detects a hard disk error from the master Routing Engine. To enable this feature, include the **on-disk-failure** statement at the **[edit chassis redundancy failover]** hierarchy level.

```
[edit chassis redundancy failover]
  on-disk-failure;
```

On Detection of a Loss of Keepalive Signal from the Master Routing Engine

After you configure a backup Routing Engine, you can direct it to take mastership automatically if it detects a loss of keepalive signal from the master Routing Engine.

To enable failover on receiving a loss of keepalive signal, include the **on-loss-of-keepalives** statement at the **[edit chassis redundancy failover]** hierarchy level:

```
[edit chassis redundancy failover]
on-loss-of-keepalives;
```

When graceful Routing Engine switchover is not configured, by default, failover occurs after 300 seconds (5 minutes). You can configure a shorter or longer time interval.



NOTE: The keepalive time period is reset to 360 seconds when the master Routing Engine has been manually rebooted or halted.

To change the keepalive time period, include the **keepalive-time** statement at the **[edit chassis redundancy]** hierarchy level:

```
[edit chassis redundancy]
keepalive-time seconds;
```

The range for **keepalive-time** is 2 through 10,000 seconds.

The following example describes the sequence of events if you configure the backup Routing Engine to detect a loss of keepalive signal in the master Routing Engine:

1. Manually configure a **keepalive-time** of 25 seconds.
2. After the Packet Forwarding Engine connection to the primary Routing Engine is lost and the keepalive timer expires, packet forwarding is interrupted.
3. After 25 seconds of keepalive loss, a message is logged, and the backup Routing Engine attempts to take mastership. An alarm is generated when the backup Routing Engine becomes active, and the display is updated with the current status of the Routing Engine.
4. After the backup Routing Engine takes mastership, it continues to function as master.



NOTE: When graceful Routing Engine switchover is configured, the keepalive signal is automatically enabled and the failover time is set to 2 seconds (4 seconds on M20 routers). You cannot manually reset the keepalive time.



NOTE: When you halt or reboot the master Routing Engine, Junos OS resets the keepalive time to 360 seconds, and the backup Routing Engine does not take over mastership until the 360-second keepalive time period expires.

A former master Routing Engine becomes a backup Routing Engine if it returns to service after a failover to the backup Routing Engine. To restore master status to the former master Routing Engine, you can use the **request chassis routing-engine master switch** operational mode command.

If at any time one of the Routing Engines is not present, the remaining Routing Engine becomes master automatically, regardless of how redundancy is configured.

When a Software Process Fails

To configure automatic switchover to the backup Routing Engine if a software process fails, include the **failover other-routing-engine** statement at the **[edit system processes process-name]** hierarchy level:

```
[edit system processes process-name]
failover other-routing-engine;
```

process-name is one of the valid process names. If this statement is configured for a process, and that process fails four times within 30 seconds, the router reboots from the other Routing Engine. Another statement available at the **[edit system processes]** hierarchy level is **failover alternate-media**. For information about the alternate media option, see the Junos OS System Basics Configuration Guide.

Manually Switching Routing Engine Mastership

To manually switch Routing Engine mastership, use one of the following commands:

- On the backup Routing Engine, request that the backup Routing Engine take mastership by issuing the **request chassis routing-engine master acquire** command.
- On the master Routing Engine, request that the backup Routing Engine take mastership by using the **request chassis routing-engine master release** command.
- On either Routing Engine, switch mastership by issuing the **request chassis routing-engine master switch** command.

Verifying Routing Engine Redundancy Status

A separate log file is provided for redundancy logging at **/var/log/mastership**. To view the log, use the **file show /var/log/mastership** command. [Table 18 on page 92](#) lists the mastership log event codes and descriptions.

Table 18: Routing Engine Mastership Log

Event Code	Description
E_NULL = 0	The event is a null event.
E_CFG_M	The Routing Engine is configured as master.
E_CFG_B	The Routing Engine is configured as backup.
E_CFG_D	The Routing Engine is configured as disabled.
E_MAXTRY	The maximum number of tries to acquire or release mastership was exceeded.
E_REQ_C	A claim mastership request was sent.
E_ACK_C	A claim mastership acknowledgement was received.
E_NAK_C	A claim mastership request was not acknowledged.

Table 18: Routing Engine Mastership Log (*continued*)

Event Code	Description
E_REQ_Y	Confirmation of mastership is requested.
E_ACK_Y	Mastership is acknowledged.
E_NAK_Y	Mastership is not acknowledged.
E_REQ_G	A release mastership request was sent by a Routing Engine.
E_ACK_G	The Routing Engine acknowledged release of mastership.
E_CMD_A	The command request chassis routing-engine master acquire was issued from the backup Routing Engine.
E_CMD_F	The command request chassis routing-engine master acquire force was issued from the backup Routing Engine.
E_CMD_R	The command request chassis routing-engine master release was issued from the master Routing Engine.
E_CMD_S	The command request chassis routing-engine master switch was issued from a Routing Engine.
E_NO_ORE	No other Routing Engine is detected.
E_TMOUT	A request timed out.
E_NO_IPC	Routing Engine connection was lost.
E_ORE_M	Other Routing Engine state was changed to master.
E_ORE_B	Other Routing Engine state was changed to backup.
E_ORE_D	Other Routing Engine state was changed to disabled.

Related Documentation

- [Understanding Routing Engine Redundancy on Juniper Networks Routers on page 11](#)
- [Switching Control Board Redundancy on page 16](#)
- [Chassis Redundancy Hierarchy on page 97](#)

Configuring CFEB Redundancy on the M10i Router

The Compact Forwarding Engine Board (CFEB) on the M10i router provides route lookup, filtering, and switching on incoming data packets, and then directs outbound packets to the appropriate interface for transmission to the network. The CFEB communicates with the Routing Engine using a dedicated 100-Mbps Fast Ethernet link that transfers routing table data from the Routing Engine to the forwarding table in the integrated ASIC. The

link is also used to transfer from the CFEB to the Routing Engine routing link-state updates and other packets destined for the router that have been received through the router interfaces.

To configure a CFEB redundancy group, include the following statements at the **[edit chassis redundancy]** hierarchy level:

```
[edit chassis redundancy]
  cfeb slot-number (always | preferred);
```

slot-number can be 0 or 1.

always defines the CFEB as the sole device.

preferred defines a preferred CFEB.

To manually switch CFEB mastership, issue the **request chassis cfeb master switch** command. To view CFEB status, issue the **show chassis cfeb** command.

**Related
Documentation**

- [Switching Control Board Redundancy on page 16](#)
- [Chassis Redundancy Hierarchy on page 97](#)

Configuring FEB Redundancy on the M120 Router

To configure a FEB redundancy group for the M120 router, include the following statements at the **[edit chassis redundancy feb]** hierarchy level:

```
[edit chassis redundancy feb]
  redundancy-group group-name {
    description description;
    feb slot-number (backup | primary);
    no-auto-failover;
  }
```

group-name is the unique name for the redundancy group. The maximum length is 39 alphanumeric characters.

slot-number is the slot number of each FEB you want to include in the redundancy group. The range is from 0 through 5. You must specify exactly one FEB as a backup FEB per redundancy group. Include the **backup** keyword when configuring the backup FEB and make sure that the FEB is not connected to an FPC.

Include the **primary** keyword to optionally specify one primary FEB per redundancy group. When the **primary** keyword is specified for a particular FEB, that FEB is configured for 1:1 redundancy. With 1:1 redundancy, the backup FEB contains the same forwarding state as the primary FEB. When no FEB in the redundancy group is configured as a primary FEB, the redundancy group is configured for *n*:1 redundancy. In this case, the backup FEB has no forwarding state. When a FEB fails, the forwarding state must be downloaded from the Routing Engine to the backup FEB before forwarding continues.

A combination of 1:1 and *n*:1 redundancy is possible when more than two FEBs are present in a group. The backup FEB contains the same forwarding state as the primary FEB, so that when the primary FEB fails, 1:1 failover is in effect. When a nonprimary FEB fails, the

backup FEB must be rebooted so that the forwarding state from the nonprimary FEB is installed on the backup FEB before it can continue forwarding.

You can optionally include the **description** statement to describe a redundancy group.

Automatic failover is enabled by default. To disable automatic failover, include the **no-auto-failover** statement. If you disable automatic failover, you can perform only a manual switchover using the operational command **request chassis redundancy feb slot *slot-number* switch-to-backup**.

To view FEB status, issue the **show chassis feb** command. For more information, see the Junos OS Operational Mode Commands.

Related Documentation

- [Switching Control Board Redundancy on page 16](#)
- [Chassis Redundancy Hierarchy on page 97](#)
- [Example: Configuring FEB Redundancy on page 95](#)

Example: Configuring FEB Redundancy

In the following configuration, two FEB redundancy groups are created:

- A FEB redundancy group named **group0** with the following properties:
 - Contains three FEBs (0 through 2).
 - Has a primary FEB (2).
 - Has a unique backup FEB (0).
 - Automatic failover is disabled.

When an active FEB in **group0** fails, automatic failover to the backup FEB does not occur. For **group0**, you can only perform a manual switchover.

- A FEB redundancy group named **group1** with the following properties:
 - Two FEBs (3 and 5). There is no primary FEB.
 - A unique backup FEB (5).
 - Automatic failover is enabled by default.

When **feb 3** in **group1** fails, an automatic failover occurs.

Because you must explicitly configure an FPC *not* to connect to the backup FEB, connectivity is set to none between **fpc 0** and **feb 0** and between **fpc 5** and **feb 5**.



NOTE: For information about the **fpc-feb-connectivity** statement, see the Junos OS System Basics Configuration Guide.

FPC to primary FEB connectivity is not explicitly configured, so by default, the software automatically assigns connectivity based on the numerical order of the FPCs.

```
[edit]
chassis {
  fpc-feb-connectivity {
    fpc 0 feb none;
    fpc 5 feb none;
  }
  redundancy feb {
    redundancy-group group0 {
      description "Interfaces to Customer X";
      feb 2 primary;
      feb 1;
      feb 0 backup;
      no-auto-failover;
    }
    redundancy-group group1 {
      feb 3;
      feb 5 backup;
    }
  }
}
```

- Related Documentation**
- [Switching Control Board Redundancy on page 16](#)
 - [Configuring FEB Redundancy on the M120 Router on page 94](#)

Configuring SFM Redundancy on M40e and M160 Routers

By default, the Switching and Forwarding Module (SFM) in slot 0 is the master and the SFM in slot 1 is the backup. To modify the default configuration, include the **sfm** statement at the **[edit chassis redundancy]** hierarchy level:

```
[edit chassis redundancy]
sfm slot-number (always | preferred);
```

On the M40e router, **slot-number** is 0 or 1. On the M160 router, **slot-number** is 0 through 3.

always defines the SFM as the sole device.

preferred defines a preferred SFM.

To manually switch mastership between SFMs, issue the **request chassis sfm master switch** command. To view SFM status, issue the **show chassis sfm** command. For more information, see the Junos OS Operational Mode Commands.

- Related Documentation**
- [Switching Control Board Redundancy on page 16](#)
 - [Chassis Redundancy Hierarchy on page 97](#)

Configuring SSB Redundancy on the M20 Router

For M20 routers with two System and Switch Boards (SSBs), you can configure which SSB is the master and which is the backup. By default, the SSB in slot 0 is the master and the SSB in slot 1 is the backup. To modify the default configuration, include the **ssb** statement at the **[edit chassis redundancy]** hierarchy level:

```
[edit chassis redundancy]
  ssb slot-number (always | preferred);
```

slot-number is 0 or 1.

always defines the SSB as the sole device.

preferred defines a preferred SSB.

To manually switch mastership between SSBs, issue the **request chassis ssb master switch** command.

To display SSB status information, issue the **show chassis ssb** command. The command output displays the number of times the mastership has changed, the SSB slot number, and the current state of the SSB: master, backup, or empty. For more information, see the Junos OS Operational Mode Commands.

Related Documentation

- [Switching Control Board Redundancy on page 16](#)
- [Chassis Redundancy Hierarchy on page 97](#)

Chassis Redundancy Hierarchy

The following redundancy statements are available at the **[edit chassis]** hierarchy level:

```
redundancy {
  cfeb slot (always | preferred);
  failover {
    on-disk-failure;
    on-loss-of-keepalives;
  }
  feb {
    redundancy-group group-name {
      description description;
      feb slot-number (backup | primary);
      no-auto-failover;
    }
  }
  graceful-switchover;
  keepalive-time seconds;
  routing-engine slot-number (master | backup | disabled);
  sfm slot-number (always | preferred);
  ssb slot-number (always | preferred);
}
```

- Related Documentation**
- [Configuring Routing Engine Redundancy on page 89](#)
 - [Configuring CFEB Redundancy on the M10i Router on page 93](#)
 - [Configuring FEB Redundancy on the M120 Router on page 94](#)
 - [Configuring SFM Redundancy on M40e and M160 Routers on page 96](#)
 - [Configuring SSB Redundancy on the M20 Router on page 97](#)

Routing Engine and Switching Control Board Redundancy Configuration Statements

- [cfeb](#)
- [description](#)
- [failover \(Chassis\)](#)
- [failover \(System Process\)](#)
- [feb \(Creating a Redundancy Group\)](#)
- [feb \(Assigning a FEB to a Redundancy Group\)](#)
- [keepalive-time](#)
- [no-auto-failover](#)
- [on-disk-failure \(Chassis Redundancy Failover\)](#)
- [on-loss-of-keepalives](#)
- [redundancy](#)
- [redundancy-group](#)
- [routing-engine](#)
- [sfm \(Chassis Redundancy\)](#)
- [ssb](#)

Initial Routing Engine Configuration Example

You can use configuration groups to ensure that the correct IP addresses are used for each Routing Engine and to maintain a single configuration file for both Routing Engines.

The following example defines configuration groups **re0** and **re1** with separate IP addresses. These well-known configuration group names take effect only on the appropriate Routing Engine.

```
groups {
  re0 {
    system {
      host-name my-re0;
    }
    interfaces {
      fxp0 {
        description "10/100 Management interface";
      }
    }
  }
}
```

```

        unit 0 {
            family inet {
                address 10.255.2.40/24;
            }
        }
    }
}
re1 {
    system {
        host-name my-re1;
    }
    interfaces {
        fxp0 {
            description "10/100 Management interface";
            unit 0 {
                family inet {
                    address 10.255.2.41/24;
                }
            }
        }
    }
}
}

```

You can assign an additional IP address to the management Ethernet interface (**fxp0** in this example) on both Routing Engines. The assigned address uses the **master-only** keyword and is identical for both Routing Engines, ensuring that the IP address for the master Routing Engine can be accessed at any time. The address is active only on the master Routing Engine's management Ethernet interface. During a Routing Engine switchover, the address moves over to the new master Routing Engine.

For example, on **re0**, the configuration is:

```

[edit groups re0 interfaces fxp0]
unit 0 {
    family inet {
        address 10.17.40.131/25 {
            master-only;
        }
        address 10.17.40.132/25;
    }
}

```

On **re1**, the configuration is:

```

[edit groups re1 interfaces fxp0]
unit 0 {
    family inet {
        address 10.17.40.131/25 {
            master-only;
        }
        address 10.17.40.133/25;
    }
}

```

For more information about the initial configuration of dual Routing Engines, see the Installation and Upgrade Guide. For more information about assigning an additional IP address to the management Ethernet interface with the **master-only** keyword on both Routing Engines, see the CLI User Guide.

**Related
Documentation**

- [Understanding Routing Engine Redundancy on Juniper Networks Routers on page 11](#)
- [Switching Control Board Redundancy on page 16](#)

CHAPTER 10

Graceful Routing Engine Switchover

- [Configuring Graceful Routing Engine Switchover on page 101](#)

Configuring Graceful Routing Engine Switchover

This section contains the following topics:

- [Enabling Graceful Routing Engine Switchover on page 101](#)
- [Synchronizing the Routing Engine Configuration on page 101](#)
- [Verifying Graceful Routing Engine Switchover Operation on page 102](#)

Enabling Graceful Routing Engine Switchover

By default, graceful Routing Engine switchover is disabled. To configure graceful Routing Engine switchover, include the **graceful-switchover** statement at the **[edit chassis redundancy]** hierarchy level.

```
[edit chassis redundancy]  
graceful-switchover;
```

When you enable graceful Routing Engine switchover, the command-line interface (CLI) indicates which Routing Engine you are using. For example:

```
{master} [edit]  
user@host#
```

To disable graceful Routing Engine switchover, delete the **graceful-switchover** statement from the **[edit chassis redundancy]** hierarchy level.

Synchronizing the Routing Engine Configuration



NOTE: A newly inserted backup Routing Engine automatically synchronizes its configuration with the master Routing Engine configuration.

When you configure graceful Routing Engine switchover, you can bring the backup Routing Engine online after the master Routing Engine is already running. There is no requirement to start the two Routing Engines simultaneously.

Verifying Graceful Routing Engine Switchover Operation

To verify whether graceful Routing Engine switchover is enabled, on the backup Routing Engine, issue the **show system switchover** command. When the output of the command indicates that the **Graceful switchover** field is set to **on**, graceful Routing Engine switchover is operational. The status of the kernel database and configuration database synchronization between Routing Engines is also provided. For example:

```
Graceful switchover: On
Configuration database: Ready
Kernel database: Ready
Peer state: Steady state
```



NOTE: You must issue the **show system switchover** command on the backup Routing Engine. This command is not supported on the master Routing Engine.

For more information about the **show system switchover** command, see the Junos OS Operational Mode Commands.

Related Documentation

- [Understanding Graceful Routing Engine Switchover in the Junos OS on page 21](#)
- [Graceful Routing Engine Switchover System Requirements on page 25](#)
- [Requirements for Routers with a Backup Router Configuration on page 29](#)
- [Resetting Local Statistics on page 209](#)
- [graceful-switchover on page 102](#)

graceful-switchover

Syntax	graceful-switchover;
Hierarchy Level	[edit chassis redundancy]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	For routing platforms with two Routing Engines, configure a master Routing Engine to switch over gracefully to a backup Routing Engine without interruption to packet forwarding.
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Documentation	• Configuring Graceful Routing Engine Switchover on page 101

CHAPTER 11

Nonstop Bridging

- [Configuring Nonstop Bridging on page 103](#)

Configuring Nonstop Bridging

This section includes the following topics:

- [Enabling Nonstop Bridging on page 103](#)
- [Synchronizing the Routing Engine Configuration on page 103](#)
- [Verifying Nonstop Bridging Operation on page 104](#)

Enabling Nonstop Bridging

Nonstop bridging requires you to configure graceful Routing Engine switchover (GRES). To enable graceful Routing Engine switchover, include the **graceful-switchover** statement at the **[edit chassis redundancy]** hierarchy level:

```
[edit chassis redundancy]  
graceful-switchover;
```

By default, nonstop bridging is disabled. To enable nonstop bridging, include the **nonstop-bridging** statement at the **[edit protocols layer2-control]** hierarchy level:

```
[edit protocols layer2-control]  
nonstop-bridging;
```

To disable nonstop active routing, remove the **nonstop-bridging** statement from the **[edit protocols layer2-control]** hierarchy level.

Synchronizing the Routing Engine Configuration

When you configure nonstop bridging, you must also include the **commit synchronize** statement at the **[edit system]** hierarchy level so that, by default, when you issue the **commit** command, the configuration changes are synchronized on both Routing Engines. If you issue the **commit synchronize** command at the **[edit]** hierarchy level on the backup Routing Engine, the Junos OS displays a warning and commits the candidate configuration.



NOTE: A newly inserted backup Routing Engine automatically synchronizes its configuration with the master Routing Engine configuration.

When you configure nonstop bridging, you can bring the backup Routing Engine online after the master Routing Engine is already running. There is no requirement to start the two Routing Engines simultaneously.

Verifying Nonstop Bridging Operation

When you enable nonstop bridging, you can issue Layer 2 Control Protocol-related operational mode commands on the backup Routing Engine. However, the output of the commands might not match the output of the same commands issued on the master Routing Engine.

Related Documentation

- [Nonstop Bridging Concepts on page 31](#)
- [Nonstop Bridging System Requirements on page 33](#)
- [nonstop-bridging on page 104](#)
- [Configuring Nonstop Bridging on EX Series Switches \(CLI Procedure\)](#)

nonstop-bridging

Syntax	nonstop-bridging;
Hierarchy Level	[edit protocols layer2-control]
Release Information	Statement introduced in Junos OS Release 8.4.
Description	For routing platforms with two Routing Engines, configure a master Routing Engine to switch over gracefully to a backup Routing Engine and preserve Layer 2 Control Protocol (L2CP) information.
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• Synchronizing the Routing Engine Configuration on page 106• Configuring Nonstop Bridging on page 103• Configuring Nonstop Bridging on EX Series Switches (CLI Procedure)

Nonstop Active Routing

- [Configuring Nonstop Active Routing on page 105](#)
- [Tracing Nonstop Active Routing Synchronization Events on page 107](#)
- [Example: Configuring Nonstop Active Routing on page 113](#)

Configuring Nonstop Active Routing

This section includes the following topics:

- [Enabling Nonstop Active Routing on page 105](#)
- [Synchronizing the Routing Engine Configuration on page 106](#)
- [Verifying Nonstop Active Routing Operation on page 106](#)

Enabling Nonstop Active Routing

Nonstop active routing (NSR) requires you to configure graceful Routing Engine switchover (GRES). To enable graceful Routing Engine switchover, include the **graceful-switchover** statement at the **[edit chassis redundancy]** hierarchy level:

```
[edit chassis redundancy]
graceful-switchover;
```

By default, nonstop active routing is disabled. To enable nonstop active routing, include the **nonstop-routing** statement at the **[edit routing-options]** hierarchy level:

```
[edit routing-options]
nonstop-routing;
```

To disable nonstop active routing, remove the **nonstop-routing** statement from the **[edit routing-options]** hierarchy level.



NOTE: When you enable nonstop active routing, you cannot enable automatic route distinguishers for multicast VPN routing instances. Automatic route distinguishers are enabled by configuring the **route-distinguisher-id** statement at the **[edit routing-instances instance-name]** hierarchy level; for more information, see the Junos OS VPNs Configuration Guide.

To enable the routing platform to switch over to the backup Routing Engine when the routing protocol process (rpd) fails rapidly three times in succession, include the

other-routing-engine statement at the **[edit system processes routing failover]** hierarchy level.

For more information about the **other-routing-engine** statement, see the Junos OS System Basics Configuration Guide.

Synchronizing the Routing Engine Configuration

When you configure nonstop active routing, you must also include the **commit synchronize** statement at the **[edit system]** hierarchy level so that configuration changes are synchronized on both Routing Engines:

```
[edit system]
commit synchronize;
```

If you try to commit the nonstop active routing configuration without including the **commit synchronize** statement, the commit fails.

If you configure the **commit synchronize** statement at the **[edit system]** hierarchy level and issue a commit in the master Routing Engine, the master configuration is automatically synchronized with the backup.

However, if the backup Routing Engine is down when you issue the commit, the Junos OS displays a warning and commits the candidate configuration in the master Routing Engine. When the backup Routing Engine comes up, its configuration will automatically be synchronized with the master.



NOTE: A newly inserted backup Routing Engine automatically synchronizes its configuration with the master Routing Engine configuration.

When you configure nonstop active routing, you can bring the backup Routing Engine online after the master Routing Engine is already running. There is no requirement to start the two Routing Engines simultaneously.

Verifying Nonstop Active Routing Operation

To see whether or not nonstop active routing is enabled, issue the **show task replication** command. For BGP nonstop active routing, you can also issue the **show bgp replication** command.

For more information about these commands, see the Junos OS Operational Mode Commands and Junos OS Operational Mode Commands, respectively.

When you enable nonstop active routing or graceful Routing Engine switchover and issue routing-related operational mode commands on the backup Routing Engine (such as **show route**, **show bgp neighbor**, **show ospf database**, and so on), the output might not match the output of the same commands issued on the master Routing Engine. For example, it is normal for the routing table on the backup Routing Engine to contain persistent phantom routes that are not present in the routing table on the master Routing Engine.

To display BFD state replication status, issue the **show bfd session** command. The **replicated** flag appears in the output for this command when a BFD session has been replicated to the backup Routing Engine. For more information, see the Junos OS Operational Mode Commands.

Related Documentation

- [Nonstop Active Routing Concepts on page 35](#)
- [Nonstop Active Routing System Requirements on page 38](#)
- [Tracing Nonstop Active Routing Synchronization Events on page 107](#)
- [Resetting Local Statistics on page 211](#)
- [Example: Configuring Nonstop Active Routing on page 113](#)
- [nonstop-routing on page 110](#)

Tracing Nonstop Active Routing Synchronization Events

To track the progress of nonstop active routing synchronization between Routing Engines, you can configure nonstop active routing trace options flags for each supported protocol and for BFD sessions and record these operations to a log file.

To configure nonstop active routing trace options for supported routing protocols, include the **nsr-synchronization** statement at the **[edit protocols protocol-name traceoptions flag]** hierarchy level and optionally specify one or more of the **detail**, **disable**, **receive**, and **send** options:

```
[edit protocols]
  bgp {
    traceoptions {
      flag nsr-synchronization <detail> <disable> <receive> <send>;
    }
  }
  isis {
    traceoptions {
      flag nsr-synchronization <detail> <disable> <receive> <send>;
    }
  }
  ldp {
    traceoptions {
      flag nsr-synchronization <detail> <disable> <receive> <send>;
    }
  }
  mpls {
    traceoptions {
      flag nsr-synchronization;
      flag nsr-synchronization-detail;
    }
  }
  msdp {
    traceoptions {
      flag nsr-synchronization <detail> <disable> <receive> <send>;
    }
  }
}
```

```

(ospf | ospf3) {
  traceoptions {
    flag nsr-synchronization <detail> <disable> <receive> <send>;
  }
}
rip {
  traceoptions {
    flag nsr-synchronization <detail> <disable> <receive> <send>;
  }
}
ripng {
  traceoptions {
    flag nsr-synchronization <detail> <disable> <receive> <send>;
  }
}
pim {
  traceoptions {
    flag nsr-synchronization <detail> <disable> <receive> <send>;
  }
}

```

To configure nonstop active routing trace options for BFD sessions, include the **nsr-synchronization** and **nsr-packet** statements at the **[edit protocols bfd traceoptions flag]** hierarchy level.

```

[edit protocols]
bfd {
  traceoptions {
    flag nsr-synchronization;
    flag nsr-packet;
  }
}

```

To trace the Layer 2 VPN signaling state replicated from routes advertised by BGP, include the **nsr-synchronization** statement at the **[edit routing-options traceoptions flag]** hierarchy level. This flag also traces the label and logical interface association that VPLS receives from the kernel replication state.

```

[edit routing-options]
traceoptions {
  flag nsr-synchronization;
}

```

Related Documentation

- [Configuring Nonstop Active Routing on page 105](#)
- [Configuring Nonstop Active Routing on EX Series Switches \(CLI Procedure\)](#)
- [Example: Configuring Nonstop Active Routing on page 113](#)
- [Example: Configuring Nonstop Active Routing on EX Series Switches](#)

commit synchronize

Syntax	commit synchronize;
Hierarchy Level	[edit system]
Release Information	Statement introduced in Junos OS Release 7.4. Statement introduced in Junos OS Release 10.4 for EX Series switches.
Description	(For devices with multiple Routing Engines only) Configure the commit command to automatically result in a commit synchronize action between dual Routing Engines within the same chassis. The Routing Engine on which you execute the commit command (the requesting Routing Engine) copies and loads its candidate configuration to the other (the responding) Routing Engine. Each Routing Engine then performs a syntax check on the candidate configuration file being committed. If no errors are found, the configuration is activated and becomes the current operational configuration on both Routing Engines.



NOTE: When you configure nonstop active routing (NSR), you must include the **commit synchronize** statement. Otherwise, the commit operation fails.

On the TX Matrix router, synchronization occurs only between the Routing Engines within the same chassis and when synchronization is complete, the new configuration is then distributed to the Routing Engines on the T640 routers. That is, the master Routing Engine on the TX Matrix router distributes the configuration to the master Routing Engine on each T640 router. Likewise, the backup Routing Engine on the TX Matrix router distributes the configuration to the backup Routing Engine on each T640 router.

On the TX Matrix Plus router, synchronization occurs only between the Routing Engines within the switch-fabric chassis and when synchronization is complete, the new configuration is then distributed to the Routing Engines on the line-card chassis (LCC). That is, the master Routing Engine on the TX Matrix Plus router distributes the configuration to the master Routing Engine on each LCC. Likewise, the backup Routing Engine on the TX Matrix Plus router distributes the configuration to the backup Routing Engine on each LCC.

In EX Series Virtual Chassis configurations:

- On EX4200 switches in Virtual Chassis, synchronization occurs between the switch in the master role and the switch in the backup role.
- On EX8200 switches in a Virtual Chassis, synchronization occurs only between the master and backup XRE200 External Routing Engines.

Options **and-quit**—(Optional) (EX Series only) Quit configuration mode if the commit synchronization succeeds.

comment—(Optional) (EX Series only) Write a message to the commit log.

and-force—(Optional) (EX Series only) Force a commit synchronization on the other Routing Engine (ignore warnings).

Required Privilege Level system—To view this statement in the configuration.
system-control—To add this statement to the configuration.

Related Documentation

- [Synchronizing the Routing Engine Configuration on page 106](#)
- Configuring Multiple Routing Engines to Synchronize Committed Configurations Automatically

nonstop-routing

Syntax nonstop-routing;

Hierarchy Level [edit logical-systems *logical-system-name* routing-options],
[edit logical-systems *logical-system-name* routing-instances *routing-instance-name* routing-options],
[edit routing-instances *routing-instance-name* routing-options],
[edit routing-options]

Release Information Statement introduced in Junos OS Release 8.4.
Statement introduced in Junos OS Release 10.4 for EX Series switches.
Statement introduced in Junos OS Release 12.3 for ACX Series routers.

Description For routing platforms with two Routing Engines, configure a master Routing Engine to switch over gracefully to a backup Routing Engine and to preserve routing protocol information.

Default disabled

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- [Configuring Nonstop Active Routing on page 105](#)
- Configuring Nonstop Active Routing on EX Series Switches (CLI Procedure)

traceoptions (Routing Options)

Syntax	<pre> traceoptions { file <i>filename</i> <files <i>number</i>> <size <i>size</i>> <world-readable no-world-readable>; flag <i>flag</i> <disable>; } </pre>
Hierarchy Level	<p>[edit logical-systems <i>logical-system-name</i> routing-instances <i>routing-instance-name</i> routing-options],</p> <p>[edit logical-systems <i>logical-system-name</i> routing-instances <i>routing-instance-name</i> routing-options multicast],</p> <p>[edit logical-systems <i>logical-system-name</i> routing-options],</p> <p>[edit logical-systems <i>logical-system-name</i> routing-options multicast],</p> <p>[edit routing-instances <i>routing-instance-name</i> routing-options],</p> <p>[edit routing-instances <i>routing-instance-name</i> routing-options multicast],</p> <p>[edit routing-options],</p> <p>[edit routing-options flow],</p> <p>[edit routing-options multicast]</p>
Release Information	<p>Statement introduced before Junos OS Release 7.4.</p> <p>nsr-synchronization flag for BGP, IS-IS, LDP, and OSPF added in Junos OS Release 8.4.</p> <p>nsr-synchronization and nsr-packet flags for BFD sessions added in Junos OS Release 8.5.</p> <p>Statement introduced in Junos OS Release 9.0 for EX Series switches.</p> <p>nsr-synchronization flag for RIP and RIPng added in Junos OS Release 9.0.</p> <p>nsr-synchronization flag for Layer 2 VPNs and VPLS added in Junos OS Release 9.1.</p> <p>nsr-synchronization flag for PIM added in Junos OS Release 9.3.</p> <p>nsr-synchronization flag for MPLS added in Junos OS Release 10.1.</p> <p>Statement introduced in Junos OS Release 11.3 for the QFX Series.</p> <p>nsr-synchronization flag for MSDP added in Junos OS Release 12.1.</p> <p>Statement introduced in Junos OS Release 12.3 for ACX Series routers.</p>
Description	<p>Define tracing operations that track all routing protocol functionality in the routing device.</p> <p>To specify more than one tracing operation, include multiple flag statements.</p>
Default	If you do not include this statement, no global tracing operations are performed.
Options	<p>Values:</p> <p>disable—(Optional) Disable the tracing operation. You can use this option to disable a single operation when you have defined a broad group of tracing operations, such as all.</p> <p>file <i>filename</i>—Name of the file to receive the output of the tracing operation. Enclose the name within quotation marks. All files are placed in the directory /var/log. We recommend that you place global routing protocol tracing output in the file routing-log.</p> <p>files <i>number</i>—(Optional) Maximum number of trace files. When a trace file named trace-file reaches its maximum size, it is renamed trace-file.0, then trace-file.1, and</p>

so on, until the maximum number of trace files is reached. Then, the oldest trace file is overwritten. Note that if you specify a maximum number of files, you also must specify a maximum file size with the **size** option.

Range: 2 through 1000 files

Default: 10 files

flag flag—Tracing operation to perform. To specify more than one tracing operation, include multiple **flag** statements. These are the global routing protocol tracing options:

- **all**—All tracing operations
- **condition-manager**—Condition-manager events
- **config-internal**—Configuration internals
- **general**—All normal operations and routing table changes (a combination of the **normal** and **route** trace operations)
- **graceful-restart**—Graceful restart operations
- **normal**—All normal operations
- **nsr-packet**—Detailed trace information for BFD nonstop active routing only
- **nsr-synchronization**—Tracing operations for nonstop active routing
- **nsr-synchronization-detail**—(MPLS only) Tracing operations for nonstop active routing in detail
- **parse**—Configuration parsing
- **policy**—Routing policy operations and actions
- **regex-parse**—Regular-expression parsing
- **route**—Routing table changes
- **state**—State transitions
- **task**—Interface transactions and processing
- **timer**—Timer usage

no-world-readable—(Optional) Prevent any user from reading the log file.

size size—(Optional) Maximum size of each trace file, in kilobytes (KB), megabytes (MB), or gigabytes (GB). When a trace file named **trace-file** reaches this size, it is renamed **trace-file.0**. When the **trace-file** again reaches its maximum size, **trace-file.0** is renamed **trace-file.1** and **trace-file** is renamed **trace-file.0**. This renaming scheme continues until the maximum number of trace files is reached. Then, the oldest trace file is overwritten. Note that if you specify a maximum file size, you also must specify a maximum number of trace files with the **files** option.

Syntax: **xk** to specify KB, **xm** to specify MB, or **xg** to specify GB

Range: 10 KB through the maximum file size supported on your system

Default: 128 KB

world-readable—(Optional) Allow any user to read the log file.

Required Privilege Level	routing and trace—To view this statement in the configuration.
	routing-control and trace-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none"> • Example: Tracing Global Routing Protocol Operations • Tracing Nonstop Active Routing Synchronization Events on page 107

Example: Configuring Nonstop Active Routing

The following example enables graceful Routing Engine switchover, nonstop active routing, and nonstop active routing trace options for BGP, IS-IS, and OSPF.

```
[edit]
system commit {
  synchronize;
}
chassis {
  redundancy {
    graceful-switchover; # This enables graceful Routing Engine switchover on
                        # the routing platform.
  }
}
interfaces {
  so-0/0/0 {
    unit 0 {
      family inet {
        address 10.0.1.1/30;
      }
      family iso;
    }
  }
  so-0/0/1 {
    unit 0 {
      family inet {
        address 10.1.1.1/30;
      }
      family iso;
    }
  }
  so-0/0/2 {
    unit 0 {
      family inet {
        address 10.2.1.1/30;
      }
      family iso;
    }
  }
  so-0/0/3 {
    unit 0 {
      family inet {
        address 10.3.1.1/30;
      }
    }
  }
}
```

```
        family iso;
    }
}
lo0 {
    unit 0 {
        family inet {
            address 192.168.2.1/32;
        }
        family iso {
            address 49.0004.1921.6800.2001.00;
        }
    }
}
}
routing-options {
    nonstop-routing; # This enables nonstop active routing on the routing platform.
    router-id 192.168.2.1;
    autonomous-system 65432;
}
protocols {
    bgp {
        traceoptions {
            flag nsr-synchronization detail; # This logs nonstop active routing
            # events for BGP.
        }
        local-address 192.168.2.1;
        group external-group {
            type external;
            export BGP_export;
            neighbor 192.168.1.1 {
                family inet {
                    unicast;
                }
                peer-as 65103;
            }
        }
        group internal-group {
            type internal;
            neighbor 192.168.10.1;
            neighbor 192.168.11.1;
            neighbor 192.168.12.1;
        }
    }
}
isis {
    traceoptions {
        flag nsr-synchronization detail; # This logs nonstop active routing events
        # for IS-IS.
    }
    interface all;
    interface fxp0.0 {
        disable;
    }
    interface lo0.0 {
        passive;
    }
}
```

```

ospf {
  traceoptions {
    flag nsr-synchronization detail; # This logs nonstop active routing events
    # for OSPF.
  }
  area 0.0.0.0 {
    interface all;
    interface fxp0.0 {
      disable;
    }
    interface lo0.0 {
      passive;
    }
  }
}
}
policy-options {
  policy-statement BGP_export {
    term direct {
      from {
        protocol direct;
      }
      then accept;
    }
    term final {
      then reject;
    }
  }
}
}

```

- Related Documentation**
- [Configuring Nonstop Active Routing on page 105](#)
 - [Tracing Nonstop Active Routing Synchronization Events on page 107](#)

Graceful Restart

- [Enabling Graceful Restart on page 117](#)
- [Configuring Routing Protocols Graceful Restart on page 118](#)
- [Configuring Graceful Restart for MPLS-Related Protocols on page 124](#)
- [Configuring VPN Graceful Restart on page 126](#)
- [Configuring Logical System Graceful Restart on page 127](#)
- [Graceful Restart Configuration Statements on page 129](#)
- [Example: Configuring Graceful Restart on page 129](#)
- [Example: Managing Helper Modes for OSPF Graceful Restart on page 154](#)

Enabling Graceful Restart

Graceful restart is disabled by default. You must configure graceful restart at the **[edit routing-options]** hierarchy level to enable the feature.

For graceful restart to function properly, graceful restart must be enabled on the **[edit routing-instance *instance-name* routing-options]** or **[edit routing-options]** hierarchy level.

For example:

```
routing-options {  
  graceful-restart;  
}
```



NOTE: If you configure graceful restart after a BGP or LDP session has been established, the BGP or LDP session restarts and the peers negotiate graceful restart capabilities.

To disable graceful restart, include the **disable** statement. To configure a time period for complete restart, include the **restart-duration** statement. You can specify a number between 120 and 900.

For a list of hierarchy levels at which you can include this statement, see the statement summary section for this statement.

When you include the **graceful-restart** statement at the **[edit routing-options]** hierarchy level, graceful restart is also enabled for aggregate and static routes.

**Related
Documentation**

- [Graceful Restart Concepts on page 49](#)
- [Graceful Restart System Requirements on page 50](#)
- [Aggregate and Static Routes on page 51](#)
- [Example: Configuring Graceful Restart on page 129](#)

Configuring Routing Protocols Graceful Restart

This topic includes the following sections:

- [Enabling Graceful Restart on page 118](#)
- [Configuring Graceful Restart Options for BGP on page 119](#)
- [Configuring Graceful Restart Options for ES-IS on page 120](#)
- [Configuring Graceful Restart Options for IS-IS on page 120](#)
- [Configuring Graceful Restart Options for OSPF and OSPFv3 on page 121](#)
- [Configuring Graceful Restart Options for RIP and RIPng on page 122](#)
- [Configuring Graceful Restart Options for PIM Sparse Mode on page 122](#)
- [Tracking Graceful Restart Events on page 124](#)

Enabling Graceful Restart

By default, graceful restart is disabled. To enable graceful restart, include the **graceful-restart** statement at the **[edit routing-instance *instance-name* routing-options]** or **[edit routing-options]** hierarchy level.

For example:

```
routing-options {  
  graceful-restart;  
}
```

To configure the duration of the graceful restart period, include the **restart-duration** at the **[edit routing-options graceful-restart]** hierarchy level.



NOTE: Helper mode (the ability to assist a neighboring router attempting a graceful restart) is enabled by default when you start the routing platform, even if graceful restart is not enabled. You can disable helper mode on a per-protocol basis.

```
[edit]  
routing-options {  
  graceful-restart {  
    disable;  
    restart-duration seconds;
```

```
}
}
```

To disable graceful restart globally, include the **disable** statement at the **[edit routing-options graceful-restart]** hierarchy level.

When graceful restart is enabled for all routing protocols at the **[edit routing-options graceful-restart]** hierarchy level, you can disable graceful restart on a per-protocol basis.



NOTE: If you configure graceful restart after a BGP or LDP session has been established, the BGP or LDP session restarts and the peers negotiate graceful restart capabilities. Also, the BGP peer routing statistics are reset to zero.

Configuring Graceful Restart Options for BGP

To configure the duration of the BGP graceful restart period, include the **restart-time** statement at the **[edit protocols bgp graceful-restart]** hierarchy level. To set the length of time the router waits to receive messages from restarting neighbors before declaring them down, include the **stale-routes-time** statement at the **[edit protocols bgp graceful-restart]** hierarchy level.

```
[edit]
protocols {
  bgp {
    graceful-restart {
      disable;
      restart-time seconds;
      stale-routes-time seconds;
    }
  }
}
routing-options {
  graceful-restart;
}
```

To disable BGP graceful restart capability for all BGP sessions, include the **disable** statement at the **[edit protocols bgp graceful-restart]** hierarchy level.



NOTE: To set BGP graceful restart properties or disable them for a group, include the desired statements at the **[edit protocols bgp group group-name graceful-restart]** hierarchy level.

To set BGP graceful restart properties or disable them for a specific neighbor in a group, include the desired statements at the **[edit protocols bgp group group-name neighbor ip-address graceful-restart]** hierarchy level.



NOTE: Configuring graceful restart for BGP resets the BGP peer routing statistics to zero. Also, existing BGP sessions restart, and the peers negotiate graceful restart capabilities.

Configuring Graceful Restart Options for ES-IS

On J Series Services Routers, to configure the duration of the ES-IS graceful restart period, include the **restart-duration** statement at the **[edit protocols esis graceful-restart]** hierarchy level.

```
[edit]
protocols {
  esis {
    graceful-restart {
      disable;
      restart-duration seconds;
    }
  }
}
routing-options {
  graceful-restart;
}
```

To disable ES-IS graceful restart capability, include the **disable** statement at the **[edit protocols esis graceful-restart]** hierarchy level.

Configuring Graceful Restart Options for IS-IS

To configure the duration of the IS-IS graceful restart period, include the **restart-duration** statement at the **[edit protocols isis graceful-restart]** hierarchy level.

```
[edit]
protocols {
  isis {
    graceful-restart {
      disable;
      helper-disable;
      restart-duration seconds;
    }
  }
}
routing-options {
  graceful-restart;
}
```

To disable IS-IS graceful restart helper capability, include the **helper-disable** statement at the **[edit protocols isis graceful-restart]** hierarchy level. To disable IS-IS graceful restart capability, include the **disable** statement at the **[edit protocols isis graceful-restart]** hierarchy level.



NOTE: If you configure Bidirectional Forwarding Detection (BFD) and graceful restart for IS-IS, graceful restart might not work as expected.



NOTE: You can also track graceful restart events with the `traceoptions` statement at the `[edit protocols isis]` hierarchy level. For more information, see [“Tracking Graceful Restart Events” on page 124](#).

Configuring Graceful Restart Options for OSPF and OSPFv3

To configure the duration of the OSPF/OSPFv3 graceful restart period, include the `restart-duration` statement at the `[edit protocols (ospf | ospf3) graceful-restart]` hierarchy level. To specify the length of time for which the router notifies helper routers that it has completed graceful restart, include the `notify-duration` at the `[edit protocols (ospf | ospf3) graceful-restart]` hierarchy level. Strict OSPF link-state advertisement (LSA) checking results in the termination of graceful restart by a helping router. To disable strict LSA checking, include the `no-strict-lsa-checking` statement at the `[edit protocols (ospf | ospf3) graceful-restart]` hierarchy level.

```
[edit]
protocols {
  ospf | ospfv3 {
    graceful-restart {
      disable;
      helper-disable
      no-strict-lsa-checking;
      notify-duration seconds;
      restart-duration seconds;
    }
  }
}
routing-options {
  graceful-restart;
}
```

To disable OSPF/OSPFv3 graceful restart, include the `disable` statement at the `[edit protocols (ospf | ospf3) graceful-restart]` hierarchy level.

Starting with Release 11.3, the Junos OS supports both the standard (based on RFC 3623, *Graceful OSPF Restart*) and the restart signaling-based (as specified in RFC 4811, RFC 4812, and RFC 4813) helper modes for OSPF version 2 graceful restart configurations. Both the standard and restart signaling-based helper modes are enabled by default. To disable the helper mode for OSPF version 2 graceful restart configurations, include the `helper-disable <both | restart-signaling | standard>` statement at the `[edit protocols ospf graceful-restart]` hierarchy level. Note that the last committed statement always takes precedence over the previous one.

```
[edit protocols ospf]
graceful-restart {
  helper-disable <both | restart-signaling | standard>
}
```

To reenabling the helper mode, delete the `helper-disable` statement from the configuration by using the `delete protocols ospf graceful-restart helper-disable <restart-signaling | standard | both>` command. In this case also, the last executed command takes precedence over the previous ones.

**NOTE:**

Restart signaling-based helper mode is not supported for OSPFv3 configurations. To disable helper mode for OSPFv3 configurations, include the **helper-disable** statement at the `[edit protocols ospfv3 graceful-restart]` hierarchy level.



TIP: You can also track graceful restart events with the `traceoptions` statement at the `[edit protocols (ospf | ospf3)]` hierarchy level. For more information, see [“Tracking Graceful Restart Events” on page 124](#).



NOTE: You cannot enable OSPFv3 graceful restart between a routing platform running Junos OS Release 7.5 and earlier and a routing platform running Junos OS Release 7.6 or later. As a workaround, make sure both routing platforms use the same Junos OS version.



NOTE: If you configure BFD and graceful restart for OSPF, graceful restart might not work as expected.

Configuring Graceful Restart Options for RIP and RIPng

To configure the duration of the RIP or RIPng graceful restart period, include the **restart-time** statement at the `[edit protocols (rip | ripng) graceful-restart]` hierarchy level.

```
[edit]
protocols {
  (rip | ripng) {
    graceful-restart {
      disable;
      restart-time seconds;
    }
  }
}
routing-options {
  graceful-restart;
}
```

To disable RIP or RIPng graceful restart capability, include the **disable** statement at the `[edit protocols (rip | ripng) graceful-restart]` hierarchy level.

Configuring Graceful Restart Options for PIM Sparse Mode

PIM sparse mode continues to forward existing multicast packet streams during a graceful restart, but does not forward new streams until after the restart is complete. After a restart, the routing platform updates the forwarding state with any updates that were received from neighbors and occurred during the restart period. For example, the routing

platform relearns the join and prune states of neighbors during the restart, but does not apply the changes to the forwarding table until after the restart.

PIM sparse mode-enabled routing platforms generate a unique 32-bit random number called a generation identifier. Generation identifiers are included by default in PIM hello messages, as specified in the IETF Internet draft *Protocol Independent Multicast - Sparse Mode (PIM-SM): Protocol Specification (Revised)*. When a routing platform receives PIM hellos containing generation identifiers on a point-to-point interface, Junos OS activates an algorithm that optimizes graceful restart.

Before PIM sparse mode graceful restart occurs, each routing platform creates a generation identifier and sends it to its multicast neighbors. If a PIM sparse mode-enabled routing platform restarts, it creates a new generation identifier and sends it to its neighbors. When a neighbor receives the new identifier, it resends multicast updates to the restarting router to allow it to exit graceful restart efficiently. The restart phase completes when either the PIM state becomes stable or when the restart interval timer expires.

If a routing platform does not support generation identifiers or if PIM is enabled on multipoint interfaces, the PIM sparse mode graceful restart algorithm does not activate, and a default restart timer is used as the restart mechanism.

To configure the duration of the PIM graceful restart period, include the **restart-duration** statement at the **[edit protocols pim graceful-restart]** hierarchy level:

```
[edit]
protocols {
  pim {
    graceful-restart {
      disable;
      restart-duration seconds;
    }
  }
}
routing-options {
  graceful-restart;
}
```

To disable PIM sparse mode graceful restart capability, include the **disable** statement at the **[edit protocols pim graceful-restart]** hierarchy level.



NOTE: Multicast forwarding can be interrupted in two ways. First, if the underlying routing protocol is unstable, multicast reverse-path-forwarding (RPF) checks can fail and cause an interruption. Second, because the forwarding table is not updated during the graceful restart period, new multicast streams are not forwarded until graceful restart is complete.

Tracking Graceful Restart Events

To track the progress of a graceful restart event, you can configure graceful restart trace options flags for IS-IS and OSPF/OSPFv3. To configure graceful restart trace options, include the **graceful-restart** statement at the **[edit protocols *protocol* traceoptions flag]** hierarchy level:

```
[edit protocols]
isis {
  traceoptions {
    flag graceful-restart;
  }
}
(ospf | ospf3) {
  traceoptions {
    flag graceful-restart;
  }
}
```

Related Documentation

- [Graceful Restart Concepts on page 49](#)
- [Graceful Restart System Requirements on page 50](#)
- [Graceful Restart and Routing Protocols on page 51](#)
- [Verifying Graceful Restart Operation on page 214](#)
- [Example: Configuring Graceful Restart on page 129](#)

Configuring Graceful Restart for MPLS-Related Protocols

This section contains the following topics:

- [Configuring Graceful Restart Globally on page 124](#)
- [Configuring Graceful Restart Options for RSVP, CCC, and TCC on page 125](#)
- [Configuring Graceful Restart Options for LDP on page 125](#)

Configuring Graceful Restart Globally

To configure graceful restart globally for all MPLS-related protocols, include the **graceful-restart** statement at the **[edit routing-options]** hierarchy level. To configure the duration of the graceful restart period, include the **restart-duration** at the **[edit routing-options graceful-restart]** hierarchy level:

```
[edit]
routing-options {
  graceful-restart {
    disable;
    restart-duration seconds;
  }
}
```

To disable graceful restart globally, include the **disable** statement at the **[edit routing-options graceful-restart]** hierarchy level.

Configuring Graceful Restart Options for RSVP, CCC, and TCC

Because CCC and TCC rely on RSVP, you must modify these three protocols as a single group.

To configure how long the router retains the state of its RSVP neighbors while they undergo a graceful restart, include the **maximum-helper-recovery-time** statement at the **[edit protocols rsvp graceful-restart]** hierarchy level. This value is applied to all neighboring routers, so it should be based on the time required by the slowest RSVP neighbor to recover.

To configure the delay between when the router discovers that a neighboring router has gone down and when it declares the neighbor down, include the **maximum-helper-restart-time** statement at the **[edit protocols rsvp graceful-restart]** hierarchy level. This value is applied to all neighboring routers, so it should be based on the time required by the slowest RSVP neighbor to restart.

```
[edit]
protocols {
  rsvp {
    graceful-restart {
      disable;
      helper-disable;
      maximum-helper-recovery-time;
      maximum-helper-restart-time;
    }
  }
}
routing-options {
  graceful-restart;
}
```

To disable RSVP, CCC, and TCC graceful restart, include the **disable** statement at the **[edit protocols rsvp graceful-restart]** hierarchy level. To disable RSVP, CCC, and TCC helper capability, include the **helper-disable** statement at the **[edit protocols rsvp graceful-restart]** hierarchy level.

Configuring Graceful Restart Options for LDP

When configuring graceful restart for LDP, you can include the following optional statements at the **[edit protocols ldp graceful-restart]** hierarchy level:

```
[edit protocols ldp graceful-restart]
disable;
helper-disable;
maximum-neighbor-reconnect-time seconds;
maximum-neighbor-recovery-time seconds;
reconnect-time seconds;
recovery-time seconds;

[edit routing-options]
graceful-restart;
```

The statements have the following effects on the graceful restart process:

- To configure the length of time required to reestablish a session after a graceful restart, include the **reconnect-time** statement; the range is 30 through 300 seconds. To limit the maximum reconnect time allowed from a restarting neighbor router, include the **maximum-neighbor-reconnect-time** statement; the range is 30 through 300 seconds.
- To configure the length of time that helper routers are required to maintain the old forwarding state during a graceful restart, include the **recovery-time** statement; the range is 120 through 1800 seconds. On the helper router, you can configure a statement that overrides the request from the restarting router and sets the maximum length of time the helper router will maintain the old forwarding state. To configure this feature, include the **maximum-neighbor-recovery-time** statement; the range is 140 through 1900 seconds.



NOTE: The value for the **recovery-time** and **maximum-neighbor-recovery-time** statements at the **[edit protocols ldp graceful-restart]** hierarchy level should be approximately 80 seconds longer than the value for the **restart-duration** statement at the **[edit routing-options graceful-restart]** hierarchy level. Otherwise, a warning message appears when you try to commit the configuration.

- To disable LDP graceful restart capability, include the **disable** statement. To disable LDP graceful restart helper capability, include the **helper-disable** statement.

Configuring VPN Graceful Restart

Graceful restart allows a router whose VPN control plane is undergoing a restart to continue to forward traffic while recovering its state from neighboring routers. Without graceful restart, a control plane restart disrupts any VPN services provided by the router. Graceful restart is supported on Layer 2 VPNs, Layer 3 VPNs, virtual-router routing instances, and VPLS.

To implement graceful restart for a Layer 2 VPN or Layer 3 VPN, perform the configuration tasks described in the following sections:

- [Configuring Graceful Restart Globally on page 126](#)
- [Configuring Graceful Restart for the Routing Instance on page 127](#)

Configuring Graceful Restart Globally

To enable graceful restart, include the **graceful-restart** statement at the **[edit routing-options]** hierarchy level. To configure a global duration for the graceful restart period, include the **restart-duration** statement at the **[edit routing-options graceful-restart]** hierarchy level.

```
[edit]
routing-options {
  graceful-restart {
    disable;
```

```

    restart-duration seconds;
  }
}

```

To disable graceful restart globally, include the **disable** statement at the **[edit routing-options graceful-restart]** hierarchy level.

Configuring Graceful Restart for the Routing Instance

For Layer 3 VPNs only, you must also configure graceful restart for all routing and MPLS-related protocols within a routing instance by including the **graceful-restart** statement at the **[edit routing-instances instance-name routing-options]** hierarchy level. Because you can configure multi-instance BGP and multi-instance LDP, graceful restart for a carrier-of-carriers scenario is supported. To configure the duration of the graceful restart period for the routing instance, include the **restart-duration** statement at the **[edit routing-instances instance-name routing-options]**.

```

[edit]
routing-instances {
  instance-name {
    routing-options {
      graceful-restart {
        disable;
        restart-duration seconds;
      }
    }
  }
}

```

You can disable graceful restart for individual protocols with the **disable** statement at the **[edit routing-instances instance-name protocols protocol-name graceful-restart]** hierarchy level.

Related Documentation

- [Graceful Restart Concepts on page 49](#)
- [Graceful Restart System Requirements on page 50](#)
- [Graceful Restart and Layer 2 and Layer 3 VPNs on page 56](#)
- [Verifying Graceful Restart Operation on page 214](#)
- [Example: Configuring Graceful Restart on page 129](#)

Configuring Logical System Graceful Restart

Graceful restart for a logical system functions much as graceful restart does in the main router. The only difference is the location of the **graceful-restart** statement.

The following topics describe what to configure to implement graceful restart in a logical system:

- [Enabling Graceful Restart Globally on page 128](#)
- [Configuring Graceful Restart for a Routing Instance on page 128](#)

Enabling Graceful Restart Globally

To enable graceful restart in a logical system, include the **graceful-restart** statement at the **[edit logical-systems *logical-system-name* routing-options]** hierarchy level. To configure a global duration of the graceful restart period, include the **restart-duration** statement at the **[edit logical-systems *logical-system-name* routing-options graceful-restart]** hierarchy level.

```
[edit]
logical-systems {
  logical-system-name {
    routing-options {
      graceful-restart {
        disable;
        restart-duration seconds;
      }
    }
  }
}
```

To disable graceful restart globally, include the **disable** statement at the **[edit logical-systems *logical-system-name* routing-options graceful-restart]** hierarchy level.

Configuring Graceful Restart for a Routing Instance

For Layer 3 VPNs only, you must also configure graceful restart globally for a routing instance inside a logical system. To configure, include the **graceful-restart** statement at the **[edit logical-systems *logical-system-name* routing-instances *instance-name* routing-options]** hierarchy level. Because you can configure multi-instance BGP and multi-instance LDP, graceful restart for a carrier-of-carriers scenario is supported. To configure the duration of the graceful restart period for the routing instance, include the **restart-duration** statement at the **[edit logical-systems *logical-system-name* routing-instances *instance-name* routing-options]**.

```
[edit]
logical-systems {
  logical-system-name {
    routing-instances {
      instance-name {
        routing-options {
          graceful-restart {
            disable;
            restart-duration seconds;
          }
        }
      }
    }
  }
}
```

To disable graceful restart for individual protocols with the **disable** statement at the **[edit logical-systems *logical-system-name* routing-instances *instance-name* protocols *protocol-name* graceful-restart]** hierarchy level.

- Related Documentation**
- [Graceful Restart Concepts on page 49](#)
 - [Graceful Restart System Requirements on page 50](#)
 - [Graceful Restart on Logical Systems on page 57](#)
 - [Verifying Graceful Restart Operation on page 214](#)
 - [Example: Configuring Graceful Restart on page 129](#)

Graceful Restart Configuration Statements

- `disable`
- `graceful-restart` (Enabling Globally)
- `helper-disable` (Multiple Protocols)
- `maximum-helper-recovery-time`
- `maximum-helper-restart-time` (RSVP)
- `maximum-neighbor-reconnect-time`
- `maximum-neighbor-recovery-time`
- `no-strict-lsa-checking`
- `notify-duration`
- `reconnect-time`
- `recovery-time`
- `restart-duration`
- `restart-time` (BGP Graceful Restart)
- `stale-routes-time`
- `traceoptions` (Protocols)

Example: Configuring Graceful Restart

To enable graceful restart, include the **graceful-restart** statement at the **[edit routing-instance *instance-name* routing-options]** or **[edit routing-options]** hierarchy level as well as in the protocol level.

For example:

```
protocols {
  bgp {
    group ext {
      graceful-restart;
    }
  }
}
routing-options {
```


```

    graceful-restart;
}

```

Figure 8 on page 130 shows a standard MPLS VPN network. Routers CE1 and CE2 are customer edge routers, PE1 and PE2 are provider edge routers, and P0 is a provider core router. Several Layer 3 VPNs are configured across this network, as well as one Layer 2 VPN. Interfaces are shown in the diagram and are not included in the configuration example that follows.

Figure 8: Layer 3 VPN Graceful Restart Topology



Router CE1 On Router CE1, configure the following protocols on the logical interfaces of **t3-3/1/0**: OSPF on unit 101, RIP on unit 102, BGP on unit 103, and IS-IS on unit 512. Also configure graceful restart, BGP, IS-IS, OSPF, and RIP on the main instance to be able to connect to the routing instances on Router PE1.

```

[edit]
interfaces {
  t3-3/1/0 {
    encapsulation frame-relay;
    unit 100 {
      dlci 100;
      family inet {
        address 10.96.100.2/30;
      }
    }
    unit 101 {
      dlci 101;
      family inet {
        address 10.96.101.2/30;
      }
    }
    unit 102 {
      dlci 102;
      family inet {
        address 10.96.102.2/30;
      }
    }
    unit 103 {
      dlci 103;
      family inet {
        address 10.96.103.2/30;
      }
    }
    unit 512 {
      dlci 512;
    }
  }
}

```

```

        family inet {
            address 10.96.252.1/30;
        }
    }
}
lo0 {
    unit 0 {
        family inet {
            address 10.245.14.172/32;
            primary;
        }
        address 10.96.110.1/32;
        address 10.96.111.1/32;
        address 10.96.112.1/32;
        address 10.96.113.1/32;
        address 10.96.116.1/32;
    }
    family iso {
        address 47.0005.80ff.f800.0000.0108.0001.0102.4501.4172.00;
    }
}
}
routing-options {
    graceful-restart;
    autonomous-system 65100;
}
protocols {
    bgp {
        group CE-PE-INET {
            type external;
            export BGP_INET_LB_DIRECT;
            neighbor 10.96.103.1 {
                local-address 10.96.103.2;
                family inet {
                    unicast;
                }
            }
            peer-as 65103;
        }
    }
}
isis {
    export ISIS_L2VPN_LB_DIRECT;
    interface t3-3/1/0.512;
}
ospf {
    export OSPF_LB_DIRECT;
    area 0.0.0.0 {
        interface t3-3/1/0.101;
    }
}
rip {
    group RIP {
        export RIP_LB_DIRECT;
        neighbor t3-3/1/0.102;
    }
}
}

```

```
}
policy-options {
  policy-statement OSPF_LB_DIRECT {
    term direct {
      from {
        protocol direct;
        route-filter 10.96.101.0/30 exact;
        route-filter 10.96.111.1/32 exact;
      }
      then accept;
    }
    term final {
      then reject;
    }
  }
  policy-statement RIP_LB_DIRECT {
    term direct {
      from {
        protocol direct;
        route-filter 10.96.102.0/30 exact;
        route-filter 10.96.112.1/32 exact;
      }
      then accept;
    }
    term final {
      then reject;
    }
  }
  policy-statement BGP_INET_LB_DIRECT {
    term direct {
      from {
        protocol direct;
        route-filter 10.96.103.0/30 exact;
        route-filter 10.96.113.1/32 exact;
      }
      then accept;
    }
    term final {
      then reject;
    }
  }
  policy-statement ISIS_L2VPN_LB_DIRECT {
    term direct {
      from {
        protocol direct;
        route-filter 10.96.116.1/32 exact;
      }
      then accept;
    }
    term final {
      then reject;
    }
  }
}
```


Router PE1 On Router PE1, configure graceful restart in the master instance, along with BGP, OSPF, MPLS, and LDP. Next, configure several protocol-specific instances of graceful restart. By including instances for BGP, OSPF, Layer 2 VPNs, RIP, and static routes, you can observe the wide range of options available when you implement graceful restart. Configure the following protocols in individual instances on the logical interfaces of **t3-0/0/0**: a static route on unit 100, OSPF on unit 101, RIP on unit 102, BGP on unit 103, and Frame Relay on unit 512 for the Layer 2 VPN instance.

```
[edit]
interfaces {
  t3-0/0/0 {
    dce;
    encapsulation frame-relay-ccc;
    unit 100 {
      dlci 100;
      family inet {
        address 10.96.100.1/30;
      }
      family mpls;
    }
    unit 101 {
      dlci 101;
      family inet {
        address 10.96.101.1/30;
      }
      family mpls;
    }
    unit 102 {
      dlci 102;
      family inet {
        address 10.96.102.1/30;
      }
      family mpls;
    }
    unit 103 {
      dlci 103;
      family inet {
        address 10.96.103.1/30;
      }
      family mpls;
    }
    unit 512 {
      encapsulation frame-relay-ccc;
      dlci 512;
    }
  }
}
t1-0/1/0 {
  unit 0 {
    family inet {
      address 10.96.0.2/30;
    }
    family mpls;
  }
}
lo0 {
  unit 0 {
```

```
        family inet {
            address 10.245.14.176/32;
        }
        family iso {
            address 47.0005.80ff.f800.0000.0108.0001.0102.4501.4176.00;
        }
    }
}
routing-options {
    graceful-restart;
    router-id 10.245.14.176;
    autonomous-system 69;
}
protocols {
    mpls {
        interface all;
    }
    bgp {
        group PEPE {
            type internal;
            neighbor 10.245.14.182 {
                local-address 10.245.14.176;
                family inet-vpn {
                    unicast;
                }
                family l2vpn {
                    unicast;
                }
            }
        }
    }
}
ospf {
    area 0.0.0.0 {
        interface t1-0/1/0.0;
        interface fxp0.0 {
            disable;
        }
        interface lo0.0 {
            passive;
        }
    }
}
ldp {
    interface all;
}
}
policy-options {
    policy-statement STATIC-import {
        from community STATIC;
        then accept;
    }
    policy-statement STATIC-export {
        then {
            community add STATIC;
            accept;
        }
    }
}
```

```

    }
  }
  policy-statement OSPF-import {
    from community OSPF;
    then accept;
  }
  policy-statement OSPF-export {
    then {
      community add OSPF;
      accept;
    }
  }
  policy-statement RIP-import {
    from community RIP;
    then accept;
  }
  policy-statement RIP-export {
    then {
      community add RIP;
      accept;
    }
  }
  policy-statement BGP-INET-import {
    from community BGP-INET;
    then accept;
  }
  policy-statement BGP-INET-export {
    then {
      community add BGP-INET;
      accept;
    }
  }
  policy-statement L2VPN-import {
    from community L2VPN;
    then accept;
  }
  policy-statement L2VPN-export {
    then {
      community add L2VPN;
      accept;
    }
  }
  community BGP-INET members target:69:103;
  community L2VPN members target:69:512;
  community OSPF members target:69:101;
  community RIP members target:69:102;
  community STATIC members target:69:100;
}
routing-instances {
  BGP-INET {
    instance-type vrf;
    interface t3-0/0/0.103;
    route-distinguisher 10.245.14.176:103;
    vrf-import BGP-INET-import;
    vrf-export BGP-INET-export;
    routing-options {

```

```

    graceful-restart;
    autonomous-system 65103;
  }
  protocols {
    bgp {
      group BGP-INET {
        type external;
        export BGP-INET-import;
        neighbor 10.96.103.2 {
          local-address 10.96.103.1;
          family inet {
            unicast;
          }
        }
        peer-as 65100;
      }
    }
  }
}
L2VPN {
  instance-type l2vpn;
  interface t3-0/0/0.512;
  route-distinguisher 10.245.14.176:512;
  vrf-import L2VPN-import;
  vrf-export L2VPN-export;
  protocols {# There is no graceful-restart statement for Layer 2 VPN instances.
    l2vpn {
      encapsulation-type frame-relay;
      site CE1-ISIS {
        site-identifier 512;
        interface t3-0/0/0.512 {
          remote-site-id 612;
        }
      }
    }
  }
}
OSPF {
  instance-type vrf;
  interface t3-0/0/0.101;
  route-distinguisher 10.245.14.176:101;
  vrf-import OSPF-import;
  vrf-export OSPF-export;
  routing-options {
    graceful-restart;
  }
  protocols {
    ospf {
      export OSPF-import;
      area 0.0.0.0 {
        interface all;
      }
    }
  }
}
RIP {

```

```

instance-type vrf;
interface t3-0/0/0.102;
route-distinguisher 10.245.14.176:102;
vrf-import RIP-import;
vrf-export RIP-export;
routing-options {
    graceful-restart;
}
protocols {
    rip {
        group RIP {
            export RIP-import;
            neighbor t3-0/0/0.102;
        }
    }
}
}
STATIC {
    instance-type vrf;
    interface t3-0/0/0.100;
    route-distinguisher 10.245.14.176:100;
    vrf-import STATIC-import;
    vrf-export STATIC-export;
    routing-options {
        graceful-restart;
        static {
            route 10.96.110.1/32 next-hop t3-0/0/0.100;
        }
    }
}
}

```

Router P0 On Router P0, configure graceful restart in the main instance, along with OSPF, MPLS, and LDP. This allows the protocols on the PE routers to reach one another.

```

[edit]
interfaces {
    t3-0/1/3 {
        unit 0 {
            family inet {
                address 10.96.0.5/30;
            }
            family mpls;
        }
    }
    t1-0/2/0 {
        unit 0 {
            family inet {
                address 10.96.0.1/30;
            }
            family mpls;
        }
    }
}
lo0 {
    unit 0 {
        family inet {

```

```

        address 10.245.14.174/32;
    }
    family iso {
        address 47.0005.80ff.f800.0000.0108.0001.0102.4501.4174.00;
    }
}
}
routing-options {
    graceful-restart;
    router-id 10.245.14.174;
    autonomous-system 69;
}
protocols {
    mpls {
        interface all;
    }
    ospf {
        area 0.0.0.0 {
            interface t1-0/2/0.0;
            interface t3-0/1/3.0;
            interface fxp0.0 {
                disable;
            }
            interface lo0.0 {
                passive;
            }
        }
    }
    ldp {
        interface all;
    }
}
}

```

Router PE2 On Router PE2, configure BGP, OSPF, MPLS, LDP, and graceful restart in the master instance. Configure the following protocols in individual instances on the logical interfaces of **t1-0/1/3**: a static route on unit 200, OSPF on unit 201, RIP on unit 202, BGP on unit 203, and Frame Relay on unit 612 for the Layer 2 VPN instance. Also configure protocol-specific graceful restart in all routing instances, except the Layer 2 VPN instance.

```

[edit]
interfaces {
    t3-0/0/0 {
        unit 0 {
            family inet {
                address 10.96.0.6/30;
            }
            family mpls;
        }
    }
    t1-0/1/3 {
        dce;
        encapsulation frame-relay-ccc;
        unit 200 {
            dlci 200;
            family inet {

```

```

        address 10.96.200.1/30;
    }
    family mpls;
}
unit 201 {
    dlci 201;
    family inet {
        address 10.96.201.1/30;
    }
    family mpls;
}
unit 202 {
    dlci 202;
    family inet {
        address 10.96.202.1/30;
    }
    family mpls;
}
unit 203 {
    dlci 203;
    family inet {
        address 10.96.203.1/30;
    }
    family mpls;
}
unit 612 {
    encapsulation frame-relay-ccc;
    dlci 612;
}
}
lo0 {
    unit 0 {
        family inet {
            address 10.245.14.182/32;
        }
        family iso {
            address 47.0005.80ff.f800.0000.0108.0001.0102.4501.4182.00;
        }
    }
}
}
routing-options {
    graceful-restart;
    router-id 10.245.14.182;
    autonomous-system 69;
}
protocols {
    mpls {
        interface all;
    }
}
bgp {
    group PEPE {
        type internal;
        neighbor 10.245.14.176 {
            local-address 10.245.14.182;
            family inet-vpn {

```

```
        unicast;
    }
    family l2vpn {
        unicast;
    }
}
}
ospf {
    area 0.0.0.0 {
        interface t3-0/0/0.0;
        interface fxp0.0 {
            disable;
        }
        interface lo0.0 {
            passive;
        }
    }
}
ldp {
    interface all;
}
policy-options {
    policy-statement STATIC-import {
        from community STATIC;
        then accept;
    }
    policy-statement STATIC-export {
        then {
            community add STATIC;
            accept;
        }
    }
    policy-statement OSPF-import {
        from community OSPF;
        then accept;
    }
    policy-statement OSPF-export {
        then {
            community add OSPF;
            accept;
        }
    }
    policy-statement RIP-import {
        from community RIP;
        then accept;
    }
    policy-statement RIP-export {
        then {
            community add RIP;
            accept;
        }
    }
    policy-statement BGP-INET-import {
        from community BGP-INET;
        then accept;
    }
}
```



```

}
policy-statement BGP-INET-export {
  then {
    community add BGP-INET;
    accept;
  }
}
policy-statement L2VPN-import {
  from community L2VPN;
  then accept;
}
policy-statement L2VPN-export {
  then {
    community add L2VPN;
    accept;
  }
}
community BGP-INET members target:69:103;
community L2VPN members target:69:512;
community OSPF members target:69:101;
community RIP members target:69:102;
community STATIC members target:69:100;
}
routing-instances {
  BGP-INET {
    instance-type vrf;
    interface t1-0/1/3.203;
    route-distinguisher 10.245.14.182:203;
    vrf-import BGP-INET-import;
    vrf-export BGP-INET-export;
    routing-options {
      graceful-restart;
      autonomous-system 65203;
    }
    protocols {
      bgp {
        group BGP-INET {
          type external;
          export BGP-INET-import;
          neighbor 10.96.203.2 {
            local-address 10.96.203.1;
            family inet {
              unicast;
            }
          }
          peer-as 65200;
        }
      }
    }
  }
}
L2VPN {
  instance-type l2vpn;
  interface t1-0/1/3.612;
  route-distinguisher 10.245.14.182:612;
  vrf-import L2VPN-import;
  vrf-export L2VPN-export;
}

```

```
protocols {# There is no graceful-restart statement for Layer 2 VPN instances.
  l2vpn {
    encapsulation-type frame-relay;
    site CE2-ISIS {
      site-identifier 612;
      interface t1-0/1/3.612 {
        remote-site-id 512;
      }
    }
  }
}
OSPF {
  instance-type vrf;
  interface t1-0/1/3.201;
  route-distinguisher 10.245.14.182:201;
  vrf-import OSPF-import;
  vrf-export OSPF-export;
  routing-options {
    graceful-restart;
  }
  protocols {
    ospf {
      export OSPF-import;
      area 0.0.0.0 {
        interface all;
      }
    }
  }
}
RIP {
  instance-type vrf;
  interface t1-0/1/3.202;
  route-distinguisher 10.245.14.182:202;
  vrf-import RIP-import;
  vrf-export RIP-export;
  routing-options {
    graceful-restart;
  }
  protocols {
    rip {
      group RIP {
        export RIP-import;
        neighbor t1-0/1/3.202;
      }
    }
  }
}
STATIC {
  instance-type vrf;
  interface t1-0/1/3.200;
  route-distinguisher 10.245.14.182:200;
  vrf-import STATIC-import;
  vrf-export STATIC-export;
  routing-options {
    graceful-restart;
  }
}
```

```

        static {
            route 10.96.210.1/32 next-hop t1-0/1/3.200;
        }
    }
}
}
}

```

Router CE2 On Router CE2, complete the Layer 2 and Layer 3 VPN configuration by mirroring the protocols already set on Routers PE2 and CE1. Specifically, configure the following on the logical interfaces of **t1-0/0/3**: OSPF on unit 201, RIP on unit 202, BGP on unit 203, and IS-IS on unit 612. Finally, configure graceful restart, BGP, IS-IS, OSPF, and RIP on the main instance to be able to connect to the routing instances on Router PE2.

```

[edit]
interfaces {
    t1-0/0/3 {
        encapsulation frame-relay;
        unit 200 {
            dlci 200;
            family inet {
                address 10.96.200.2/30;
            }
        }
        unit 201 {
            dlci 201;
            family inet {
                address 10.96.201.2/30;
            }
        }
        unit 202 {
            dlci 202;
            family inet {
                address 10.96.202.2/30;
            }
        }
        unit 203 {
            dlci 203;
            family inet {
                address 10.96.203.2/30;
            }
        }
        unit 512 {
            dlci 512;
            family inet {
                address 10.96.252.2/30;
            }
        }
    }
}
lo0 {
    unit 0 {
        family inet {
            address 10.245.14.180/32 {
                primary;
            }
        }
        address 10.96.210.1/32;
    }
}

```

```
        address 10.96.111.1/32;
        address 10.96.212.1/32;
        address 10.96.213.1/32;
        address 10.96.216.1/32;
    }
    family iso {
        address 47.0005.80ff.f800.0000.0108.0001.0102.4501.4180.00;
    }
}
}
}
routing-options {
    graceful-restart;
    autonomous-system 65200;
}
protocols {
    bgp {
        group CE-PE-INET {
            type external;
            export BGP_INET_LB_DIRECT;
            neighbor 10.96.203.1 {
                local-address 10.96.203.2;
                family inet {
                    unicast;
                }
                peer-as 65203;
            }
        }
    }
}
isis {
    export ISIS_L2VPN_LB_DIRECT;
    interface t1-0/0/3.612;
}
ospf {
    export OSPF_LB_DIRECT;
    area 0.0.0.0 {
        interface t1-0/0/3.201;
    }
}
rip {
    group RIP {
        export RIP_LB_DIRECT;
        neighbor t1-0/0/3.202;
    }
}
}
policy-options {
    policy-statement OSPF_LB_DIRECT {
        term direct {
            from {
                protocol direct;
                route-filter 10.96.201.0/30 exact;
                route-filter 10.96.211.1/32 exact;
            }
            then accept;
        }
    }
}
```

```

    term final {
        then reject;
    }
}
policy-statement RIP_LB_DIRECT {
    term direct {
        from {
            protocol direct;
            route-filter 10.96.202.0/30 exact;
            route-filter 10.96.212.1/32 exact;
        }
        then accept;
    }
    term final {
        then reject;
    }
}
policy-statement BGP_INET_LB_DIRECT {
    term direct {
        from {
            protocol direct;
            route-filter 10.96.203.0/30 exact;
            route-filter 10.96.213.1/32 exact;
        }
        then accept;
    }
    term final {
        then reject;
    }
}
policy-statement ISIS_L2VPN_LB_DIRECT {
    term direct {
        from {
            protocol direct;
            route-filter 10.96.216.1/32 exact;
        }
        then accept;
    }
    term final {
        then reject;
    }
}
}

```

Router PE1 Status Before a Restart

The following example displays neighbor relationships on Router PE1 before a restart happens:

```

user@PE1> show bgp neighbor
Peer: 10.96.103.2+3785 AS 65100 Local: 10.96.103.1+179 AS 65103
Type: External State: Established Flags: <>
Last State: OpenConfirm Last Event: RecvKeepAlive
Last Error: None
Export: [ BGP-IMPORT-import ]
Options: <Preference LocalAddress HoldTime GracefulRestart AddressFamily PeerAS
Refresh>
Address families configured: inet-unicast
Local Address: 10.96.103.1 Holdtime: 90 Preference: 170

```

```

Number of flaps: 0
Peer ID: 10.96.110.1      Local ID: 10.96.103.1      Active Holdtime: 90
Keepalive Interval: 30
Local Interface: t3-0/0/0.103
NLRI for restart configured on peer: inet-unicast
NLRI advertised by peer: inet-unicast
NLRI for this session: inet-unicast
Peer supports Refresh capability (2)
Restart time configured on the peer: 120
Stale routes from peer are kept for: 300
Restart time requested by this peer: 120
NLRI that peer supports restart for: inet-unicast
NLRI peer can save forwarding state: inet-unicast
NLRI that peer saved forwarding for: inet-unicast
NLRI that restart is negotiated for: inet-unicast
NLRI of all end-of-rib markers sent: inet-unicast
Table BGP-INET.inet.0 Bit: 30001
  RIB State: BGP restart is complete
  RIB State: VPN restart is complete
  Send state: in sync
  Active prefixes:          0
  Received prefixes:        0
  Suppressed due to damping: 0
Last traffic (seconds): Received 8    Sent 3    Checked 3
Input messages: Total 15    Updates 0    Refreshes 0    Octets 321
Output messages: Total 18    Updates 2    Refreshes 0    Octets 450
Output Queue[2]: 0

Peer: 10.245.14.182+4701 AS 69    Local: 10.245.14.176+179 AS 69
Type: Internal    State: Established    Flags: <>
Last State: OpenConfirm    Last Event: RecvKeepAlive
Last Error: None
Options: <Preference LocalAddress HoldTime GracefulRestart AddressFamily
Rib-group Refresh>
Address families configured: inet-vpn-unicast l2vpn
Local Address: 10.245.14.176 Holdtime: 90 Preference: 170
Number of flaps: 1
Peer ID: 10.245.14.182    Local ID: 10.245.14.176    Active Holdtime: 90
Keepalive Interval: 30
NLRI for restart configured on peer: inet-vpn-unicast l2vpn
NLRI advertised by peer: inet-vpn-unicast l2vpn
NLRI for this session: inet-vpn-unicast l2vpn
Peer supports Refresh capability (2)
Restart time configured on the peer: 120
Stale routes from peer are kept for: 300
Restart time requested by this peer: 120
NLRI that peer supports restart for: inet-vpn-unicast l2vpn
NLRI peer can save forwarding state: inet-vpn-unicast l2vpn
NLRI that peer saved forwarding for: inet-vpn-unicast l2vpn
NLRI that restart is negotiated for: inet-vpn-unicast l2vpn
NLRI of all end-of-rib markers sent: inet-vpn-unicast l2vpn
Table bgp.l3vpn.0 Bit: 10000
  RIB State: BGP restart is complete
  RIB State: VPN restart is complete
  Send state: in sync
  Active prefixes:          0
  Received prefixes:        0
  Suppressed due to damping: 0
Table bgp.l2vpn.0 Bit: 20000
  RIB State: BGP restart is complete
  RIB State: VPN restart is complete

```

```

    Send state: in sync
    Active prefixes:      1
    Received prefixes:    1
    Suppressed due to damping: 0
Table BGP-INET.inet.0 Bit: 30000
    RIB State: BGP restart is complete
    RIB State: VPN restart is complete
    Send state: in sync
    Active prefixes:      0
    Received prefixes:    0
    Suppressed due to damping: 0
Table OSPF.inet.0 Bit: 60000
    RIB State: BGP restart is complete
    RIB State: VPN restart is complete
    Send state: in sync
    Active prefixes:      0
    Received prefixes:    0
    Suppressed due to damping: 0
Table RIP.inet.0 Bit: 70000
    RIB State: BGP restart is complete
    RIB State: VPN restart is complete
    Send state: in sync
    Active prefixes:      0
    Received prefixes:    0
    Suppressed due to damping: 0
Table STATIC.inet.0 Bit: 80000
    RIB State: BGP restart is complete
    RIB State: VPN restart is complete
    Send state: in sync
    Active prefixes:      0
    Received prefixes:    0
    Suppressed due to damping: 0
Table L2VPN.l2vpn.0 Bit: 90000
    RIB State: BGP restart is complete
    RIB State: VPN restart is complete
    Send state: in sync
    Active prefixes:      1
    Received prefixes:    1
    Suppressed due to damping: 0
Last traffic (seconds): Received 28   Sent 28   Checked 28
Input messages: Total 2   Updates 0   Refreshes 0   Octets 86
Output messages: Total 13  Updates 10   Refreshes 0   Octets 1073
Output Queue[0]: 0
Output Queue[1]: 0
Output Queue[2]: 0
Output Queue[3]: 0
Output Queue[4]: 0
Output Queue[5]: 0
Output Queue[6]: 0
Output Queue[7]: 0
Output Queue[8]: 0

user@PE1> show route instance detail
master:
  Router ID: 10.245.14.176
  Type: forwarding      State: Active
  Restart State: Complete Path selection timeout: 300
  Tables:
    inet.0              : 17 routes (15 active, 0 holddown, 1 hidden)
    Restart Complete
    inet.3              : 2 routes (2 active, 0 holddown, 0 hidden)

```

```

Restart Complete
iso.0                : 1 routes (1 active, 0 holddown, 0 hidden)
Restart Complete
mpls.0              : 19 routes (19 active, 0 holddown, 0 hidden)
Restart Complete
bgp.l3vpn.0         : 10 routes (10 active, 0 holddown, 0 hidden)
Restart Complete
inet6.0             : 2 routes (2 active, 0 holddown, 0 hidden)
Restart Complete
bgp.l2vpn.0         : 1 routes (1 active, 0 holddown, 0 hidden)
Restart Complete
BGP-INET:
  Router ID: 10.96.103.1
  Type: vrf          State: Active
  Restart State: Complete Path selection timeout: 300
  Interfaces:
    t3-0/0/0.103
  Route-distinguisher: 10.245.14.176:103
  Vrf-import: [ BGP-INET-import ]
  Vrf-export: [ BGP-INET-export ]
  Tables:
    BGP-INET.inet.0      : 4 routes (4 active, 0 holddown, 0 hidden)
    Restart Complete
L2VPN:
  Router ID: 0.0.0.0
  Type: l2vpn         State: Active
  Restart State: Complete Path selection timeout: 300
  Interfaces:
    t3-0/0/0.512
  Route-distinguisher: 10.245.14.176:512
  Vrf-import: [ L2VPN-import ]
  Vrf-export: [ L2VPN-export ]
  Tables:
    L2VPN.l2vpn.0        : 2 routes (2 active, 0 holddown, 0 hidden)
    Restart Complete
OSPF:
  Router ID: 10.96.101.1
  Type: vrf          State: Active
  Restart State: Complete Path selection timeout: 300
  Interfaces:
    t3-0/0/0.101
  Route-distinguisher: 10.245.14.176:101
  Vrf-import: [ OSPF-import ]
  Vrf-export: [ OSPF-export ]
  Tables:
    OSPF.inet.0          : 8 routes (7 active, 0 holddown, 0 hidden)
    Restart Complete
RIP:
  Router ID: 10.96.102.1
  Type: vrf          State: Active
  Restart State: Complete Path selection timeout: 300
  Interfaces:
    t3-0/0/0.102
  Route-distinguisher: 10.245.14.176:102
  Vrf-import: [ RIP-import ]
  Vrf-export: [ RIP-export ]
  Tables:
    RIP.inet.0           : 6 routes (6 active, 0 holddown, 0 hidden)
    Restart Complete
STATIC:
  Router ID: 10.96.100.1

```



```

Type: vrf                      State: Active
Restart State: Complete Path selection timeout: 300
Interfaces:
  t3-0/0/0.100
Route-distinguisher: 10.245.14.176:100
Vrf-import: [ STATIC-import ]
Vrf-export: [ STATIC-export ]
Tables:
  STATIC.inet.0                : 4 routes (4 active, 0 holddown, 0 hidden)
  Restart Complete
__juniper_private1__:
  Router ID: 0.0.0.0
  Type: forwarding             State: Active

user@PE1> show route protocol l2vpn
inet.0: 16 destinations, 17 routes (15 active, 0 holddown, 1 hidden)
Restart Complete
inet.3: 2 destinations, 2 routes (2 active, 0 holddown, 0 hidden)
Restart Complete
BGP-INET.inet.0: 5 destinations, 6 routes (5 active, 0 holddown, 0 hidden)
Restart Complete
OSPF.inet.0: 7 destinations, 8 routes (7 active, 0 holddown, 0 hidden)
Restart Complete
RIP.inet.0: 6 destinations, 6 routes (6 active, 0 holddown, 0 hidden)
Restart Complete
STATIC.inet.0: 4 destinations, 4 routes (4 active, 0 holddown, 0 hidden)
Restart Complete
iso.0: 1 destinations, 1 routes (1 active, 0 holddown, 0 hidden)
Restart Complete
mpls.0: 20 destinations, 20 routes (20 active, 0 holddown, 0 hidden)
Restart Complete
+ = Active Route, - = Last Active, * = Both
800003                *[L2VPN/7] 00:06:00
                      > via t3-0/0/0.512, Pop      Offset: 4
t3-0/0/0.512          *[L2VPN/7] 00:06:00
                      > via t1-0/1/0.0, Push 800003, Push 100004(top) Offset: -4
bgp.l3vpn.0: 10 destinations, 10 routes (10 active, 0 holddown, 0 hidden)
Restart Complete
inet6.0: 2 destinations, 2 routes (2 active, 0 holddown, 0 hidden)
Restart Complete
L2VPN.l2vpn.0: 2 destinations, 2 routes (2 active, 0 holddown, 0 hidden)
Restart Complete
+ = Active Route, - = Last Active, * = Both
10.245.14.176:512:512:611/96
                      *[L2VPN/7] 00:06:01
                      Discard

bgp.l2vpn.0: 1 destinations, 1 routes (1 active, 0 holddown, 0 hidden)
Restart Complete

```

Router PE1 Status During a Restart

Before you can verify that graceful restart is working, you must simulate a router restart. To cause the routing process to refresh and simulate a restart, use the **restart routing** operational mode command:

```

user@PE1> restart routing
Routing protocol daemon started, pid 3558

```

The following sample output is captured during the router restart:

```

user@PE1> show bgp neighbor

```

```

Peer: 10.96.103.2      AS 65100 Local: 10.96.103.1      AS 65103
  Type: External      State: Active      Flags: <ImportEval>
  Last State: Idle      Last Event: Start
  Last Error: None
  Export: [ BGP-INET-import ]
  Options: <Preference LocalAddress HoldTime GracefulRestart AddressFamily PeerAS
Refresh>
  Address families configured: inet-unicast
  Local Address: 10.96.103.1 Holdtime: 90 Preference: 170
  Number of flaps: 0
Peer: 10.245.14.182+179 AS 69      Local: 10.245.14.176+2131 AS 69
  Type: Internal      State: Established  Flags: <ImportEval>
  Last State: OpenConfirm  Last Event: RecvKeepAlive
  Last Error: None
  Options: <Preference LocalAddress HoldTime GracefulRestart AddressFamily
Rib-group Refresh>
  Address families configured: inet-vpn-unicast l2vpn
  Local Address: 10.245.14.176 Holdtime: 90 Preference: 170
  Number of flaps: 0
  Peer ID: 10.245.14.182      Local ID: 10.245.14.176      Active Holdtime: 90
  Keepalive Interval: 30
  NLRI for restart configured on peer: inet-vpn-unicast l2vpn
  NLRI advertised by peer: inet-vpn-unicast l2vpn
  NLRI for this session: inet-vpn-unicast l2vpn
  Peer supports Refresh capability (2)
  Restart time configured on the peer: 120
  Stale routes from peer are kept for: 300
  Restart time requested by this peer: 120
  NLRI that peer supports restart for: inet-vpn-unicast l2vpn
  NLRI peer can save forwarding state: inet-vpn-unicast l2vpn
  NLRI that peer saved forwarding for: inet-vpn-unicast l2vpn
  NLRI that restart is negotiated for: inet-vpn-unicast l2vpn
  NLRI of received end-of-rib markers: inet-vpn-unicast l2vpn
Table bgp.l3vpn.0 Bit: 10000
  RIB State: BGP restart in progress
  RIB State: VPN restart in progress
  Send state: in sync
  Active prefixes:          10
  Received prefixes:        10
  Suppressed due to damping: 0
Table bgp.l2vpn.0 Bit: 20000
  RIB State: BGP restart in progress
  RIB State: VPN restart in progress
  Send state: in sync
  Active prefixes:          1
  Received prefixes:        1
  Suppressed due to damping: 0
Table BGP-INET.inet.0 Bit: 30000
  RIB State: BGP restart in progress
  RIB State: VPN restart in progress
  Send state: in sync
  Active prefixes:          2
  Received prefixes:        2
  Suppressed due to damping: 0
Table OSPF.inet.0 Bit: 60000
  RIB State: BGP restart is complete
  RIB State: VPN restart in progress
  Send state: in sync
  Active prefixes:          2
  Received prefixes:        2
  Suppressed due to damping: 0

```

```

Table RIP.inet.0 Bit: 70000
  RIB State: BGP restart is complete
  RIB State: VPN restart in progress
  Send state: in sync
  Active prefixes:          2
  Received prefixes:        2
  Suppressed due to damping: 0
Table STATIC.inet.0 Bit: 80000
  RIB State: BGP restart is complete
  RIB State: VPN restart in progress
  Send state: in sync
  Active prefixes:          1
  Received prefixes:        1
  Suppressed due to damping: 0
Table L2VPN.l2vpn.0 Bit: 90000
  RIB State: BGP restart is complete
  RIB State: VPN restart in progress
  Send state: in sync
  Active prefixes:          1
  Received prefixes:        1
  Suppressed due to damping: 0
Last traffic (seconds): Received 0    Sent 0    Checked 0
Input messages: Total 14    Updates 13    Refreshes 0    Octets 1053
Output messages: Total 3    Updates 0    Refreshes 0    Octets 105
Output Queue[0]: 0
Output Queue[1]: 0
Output Queue[2]: 0
Output Queue[3]: 0
Output Queue[4]: 0
Output Queue[5]: 0
Output Queue[6]: 0
Output Queue[7]: 0
Output Queue[8]: 0

```

```
user@PE1> show route instance detail
```

```
master:
```

```

Router ID: 10.245.14.176
Type: forwarding      State: Active
Restart State: Pending Path selection timeout: 300
Tables:
  inet.0                : 17 routes (15 active, 1 holddown, 1 hidden)
  Restart Pending: OSPF LDP
  inet.3                : 2 routes (2 active, 0 holddown, 0 hidden)
  Restart Pending: OSPF LDP
  iso.0                 : 1 routes (1 active, 0 holddown, 0 hidden)
  Restart Complete
  mpls.0                : 23 routes (23 active, 0 holddown, 0 hidden)
  Restart Pending: LDP VPN
  bgp.l3vpn.0           : 10 routes (10 active, 0 holddown, 0 hidden)
  Restart Pending: BGP VPN
  inet6.0               : 2 routes (2 active, 0 holddown, 0 hidden)
  Restart Complete
  bgp.l2vpn.0           : 1 routes (1 active, 0 holddown, 0 hidden)
  Restart Pending: BGP VPN

```

```
BGP-INET:
```

```

Router ID: 10.96.103.1
Type: vrf              State: Active
Restart State: Pending Path selection timeout: 300
Interfaces:
  t3-0/0/0.103
Route-distinguisher: 10.245.14.176:103

```

```

Vrf-import: [ BGP-INET-import ]
Vrf-export: [ BGP-INET-export ]
Tables:
  BGP-INET.inet.0      : 6 routes (5 active, 0 holddown, 0 hidden)
  Restart Pending: VPN
L2VPN:
  Router ID: 0.0.0.0
  Type: l2vpn           State: Active
  Restart State: Pending Path selection timeout: 300
  Interfaces:
    t3-0/0/0.512
  Route-distinguisher: 10.245.14.176:512
  Vrf-import: [ L2VPN-import ]
  Vrf-export: [ L2VPN-export ]
  Tables:
    L2VPN.l2vpn.0      : 2 routes (2 active, 0 holddown, 0 hidden)
    Restart Pending: VPN L2VPN
OSPF:
  Router ID: 10.96.101.1
  Type: vrf             State: Active
  Restart State: Pending Path selection timeout: 300
  Interfaces:
    t3-0/0/0.101
  Route-distinguisher: 10.245.14.176:101
  Vrf-import: [ OSPF-import ]
  Vrf-export: [ OSPF-export ]
  Tables:
    OSPF.inet.0        : 8 routes (7 active, 1 holddown, 0 hidden)
    Restart Pending: OSPF VPN
RIP:
  Router ID: 10.96.102.1
  Type: vrf             State: Active
  Restart State: Pending Path selection timeout: 300
  Interfaces:
    t3-0/0/0.102
  Route-distinguisher: 10.245.14.176:102
  Vrf-import: [ RIP-import ]
  Vrf-export: [ RIP-export ]
  Tables:
    RIP.inet.0         : 8 routes (6 active, 2 holddown, 0 hidden)
    Restart Pending: RIP VPN
STATIC:
  Router ID: 10.96.100.1
  Type: vrf             State: Active
  Restart State: Pending Path selection timeout: 300
  Interfaces:
    t3-0/0/0.100
  Route-distinguisher: 10.245.14.176:100
  Vrf-import: [ STATIC-import ]
  Vrf-export: [ STATIC-export ]
  Tables:
    STATIC.inet.0      : 4 routes (4 active, 0 holddown, 0 hidden)
    Restart Pending: VPN
__juniper_private1__:
  Router ID: 0.0.0.0
  Type: forwarding      State: Active

user@PE1> show route instance summary
Instance      Type      Primary rib      Active/holddown/hidden
master        forwarding
                               inet.0           15/0/1

```

		iso.0	1/0/0
		mpls.0	35/0/0
		l3vpn.0	0/0/0
		inet6.0	2/0/0
		l2vpn.0	0/0/0
		l2circuit.0	0/0/0
BGP-INET	vrf		
		BGP-INET.inet.0	5/0/0
		BGP-INET.iso.0	0/0/0
		BGP-INET.inet6.0	0/0/0
L2VPN	l2vpn		
		L2VPN.inet.0	0/0/0
		L2VPN.iso.0	0/0/0
		L2VPN.inet6.0	0/0/0
		L2VPN.l2vpn.0	2/0/0
OSPF	vrf		
		OSPF.inet.0	7/0/0
		OSPF.iso.0	0/0/0
		OSPF.inet6.0	0/0/0
RIP	vrf		
		RIP.inet.0	6/0/0
		RIP.iso.0	0/0/0
		RIP.inet6.0	0/0/0
STATIC	vrf		
		STATIC.inet.0	4/0/0
		STATIC.iso.0	0/0/0
		STATIC.inet6.0	0/0/0
__juniper_private1__	forwarding		
		__juniper_priva.inet.0	0/0/0
		__juniper_privat.iso.0	0/0/0
		__juniper_priv.inet6.0	0/0/0

user@PE1> show route protocol l2vpn

```
inet.0: 16 destinations, 17 routes (15 active, 1 holddown, 1 hidden)
Restart Pending: OSPF LDP

inet.3: 2 destinations, 2 routes (2 active, 0 holddown, 0 hidden)
Restart Pending: OSPF LDP

BGP-INET.inet.0: 5 destinations, 6 routes (5 active, 0 holddown, 0 hidden)
Restart Pending: VPN

OSPF.inet.0: 7 destinations, 8 routes (7 active, 1 holddown, 0 hidden)
Restart Pending: OSPF VPN

RIP.inet.0: 6 destinations, 8 routes (6 active, 2 holddown, 0 hidden)
Restart Pending: RIP VPN

STATIC.inet.0: 4 destinations, 4 routes (4 active, 0 holddown, 0 hidden)
Restart Pending: VPN

iso.0: 1 destinations, 1 routes (1 active, 0 holddown, 0 hidden)
Restart Complete

mpls.0: 24 destinations, 24 routes (24 active, 0 holddown, 0 hidden)
Restart Pending: LDP VPN
+ = Active Route, - = Last Active, * = Both

800001          *[L2VPN/7] 00:00:13
                 > via t3-0/0/0.512, Pop      Offset: 4
```

```
t3-0/0/0.512          *[L2VPN/7] 00:00:13
                      > via t1-0/1/0.0, Push 800003, Push 100004(top) Offset: -4

bgp.l3vpn.0: 10 destinations, 10 routes (10 active, 0 holddown, 0 hidden)
Restart Pending: BGP VPN

inet6.0: 2 destinations, 2 routes (2 active, 0 holddown, 0 hidden)
Restart Complete

L2VPN.l2vpn.0: 2 destinations, 2 routes (2 active, 0 holddown, 0 hidden)
Restart Pending: VPN L2VPN
+ = Active Route, - = Last Active, * = Both

10.245.14.176:512:512:611/96
                      *[L2VPN/7] 00:00:13
                      Discard
bgp.l2vpn.0: 1 destinations, 1 routes (1 active, 0 holddown, 0 hidden)
Restart Pending: BGP VPN
```

Related Documentation

- [Enabling Graceful Restart on page 117](#)
- [Configuring Routing Protocols Graceful Restart on page 118](#)
- [Configuring Graceful Restart for MPLS-Related Protocols on page 124](#)
- [Configuring VPN Graceful Restart on page 126](#)
- [Configuring Logical System Graceful Restart on page 127](#)
- [Verifying Graceful Restart Operation on page 214](#)

Example: Managing Helper Modes for OSPF Graceful Restart

- [Requirements on page 154](#)
- [Overview on page 154](#)
- [Configuration on page 155](#)
- [Verification on page 156](#)

Requirements

M Series or T Series routers running Junos OS Release 11.4 or later.

Overview

Junos OS Release 11.4 extends OSPF graceful restart support to include restart signaling-based helper mode. Both standard (RFC 3623-based) and restart signaling-based helper modes are enabled by default, irrespective of the graceful-restart configuration status on the routing device.

Junos OS, however, enables you to choose between the helper modes with the **helper-disable** <standard | restart-signaling | both> statement.

Configuration

Both standard and restart signaling-based helper modes are enabled by default, irrespective of the graceful-restart configuration status on the routing device. Junos OS allows you to disable or enable the helper modes based on your requirements.

To configure the helper mode options for graceful restart:

1. To enable graceful restart, add the **graceful-restart** statement at the **[edit routing-options]** hierarchy level.

```
[edit routing-options]
user@host# set graceful-restart
```

The helper modes, both standard and restart signaling-based, are enabled by default.

2. To disable one or both of the helper modes, add the **helper-disable <both | restart-signaling | standard>** statement at the **[edit protocols ospf graceful-restart]** hierarchy level.

- To disable both standard and restart signaling-based helper modes:

```
[edit protocols ospf graceful-restart]
user@host# set helper-disable both
```

- To disable only the restart signaling-based helper mode:

```
[edit protocols ospf graceful-restart]
user@host# set helper-disable restart-signaling
```

- To disable only the standard helper mode:

```
[edit protocols ospf graceful-restart]
user@host# set helper-disable standard
```



NOTE: You must commit the configuration before the change takes effect.

The last committed statement always takes precedence over the previous one.

3. To enable one or both of the helper modes when the helper modes are disabled, delete the **helper-disable <both | restart-signaling | standard>** statement from the **[edit protocols ospf graceful-restart]** hierarchy level.

- To enable both standard and restart signaling-based helper modes:

```
[edit protocols ospf graceful-restart]
user@host# delete helper-disable
```

- To enable the restart signaling-based helper mode:

```
[edit protocols ospf graceful-restart]
user@host# delete helper-disable restart-signaling
```

- To enable the standard helper mode:

```
[edit protocols ospf graceful-restart]
user@host# delete helper-disable standard
```



NOTE: You must commit the configuration before the change takes effect.

The last committed statement always takes precedence over the previous one.

Verification

Confirm that the configuration is working properly.

- [Verifying OSPF Graceful Restart and Helper Mode Configuration on page 156](#)

Verifying OSPF Graceful Restart and Helper Mode Configuration

Purpose Verify the OSPF graceful restart and helper mode configuration on a router.

- Action**
- Enter the **run show ospf overview** command from configuration mode.

```
user@host# run show ospf overview

~
~
~
Restart: Enabled
  Restart duration: 180 sec
  Restart grace period: 210 sec
  Graceful restart helper mode: Enabled
  Restart-signaling helper mode: Enabled
~
~
~
```

Meaning The output shows that graceful restart and both of the helper modes are enabled.

- Related Documentation**
- [Understanding Restart Signaling-Based Helper Mode Support for OSPF Graceful Restart on page 55](#)
 - [Tracing Restart Signaling-Based Helper Mode Events for OSPF Graceful Restart on page 213](#)
 - [helper-disable \(OSPF\)](#)

CHAPTER 14

VRRP

- [VRRP Configuration Hierarchy on page 157](#)
- [VRRP for IPv6 Configuration Hierarchy on page 158](#)
- [Configuring the Startup Period for VRRP Operations on page 159](#)
- [Configuring Basic VRRP Support on page 160](#)
- [Configuring VRRP Authentication \(IPv4 Only\) on page 162](#)
- [Configuring the Advertisement Interval for the VRRP Master Router on page 163](#)
- [Configuring a Backup Router to Preempt the Master Router on page 166](#)
- [Modifying the Preemption Hold-Time Value on page 166](#)
- [Configuring Asymmetric Hold Time for VRRP Routers on page 167](#)
- [Configuring an Interface to Accept Packets Destined for the Virtual IP Address on page 168](#)
- [Configuring a Logical Interface to Be Tracked on page 169](#)
- [Configuring a Route to Be Tracked on page 171](#)
- [Configuring Inheritance for a VRRP Group on page 172](#)
- [Configuring the Silent Period on page 173](#)
- [Configuring Passive ARP Learning for Backup VRRP Routers on page 174](#)
- [Enabling the Distributed Periodic Packet Management Process for VRRP on page 175](#)
- [Configuring VRRP to Improve Convergence Time on page 176](#)
- [Example: Configuring VRRP on page 177](#)
- [Example: Configuring VRRP for IPv6 on page 179](#)
- [Example: Configuring VRRP Route Tracking on page 180](#)
- [Example: Configuring Multiple VRRP Owner Groups on page 181](#)
- [Tracing VRRP Operations on page 187](#)

VRRP Configuration Hierarchy

To configure VRRP for IPv4, include the following statements:

```
vrrp-group group-id {  
  (accept-data | no-accept-data);  
  advertise-interval seconds;
```

```

authentication-key key;
authentication-type authentication;
fast-interval milliseconds;
(preempt | no-preempt) {
    hold-time seconds;
}
priority number;
track {
    interface interface-name {
        bandwidth-threshold bits-per-second priority-cost priority;
        priority-cost priority;
    }
    priority-hold-time seconds;
    route prefix/prefix-length routing-instance instance-name priority-cost priority;
}
virtual-address [ addresses ];
vrrp-inherit-from vrrp-group;
}

```

You can include these statements at the following hierarchy levels:

- [edit interfaces *interface-name* unit *logical-unit-number* family inet address *address*]
- [edit logical-systems *logical-system-name* interfaces *interface-name* unit *logical-unit-number* family inet address *address*]

If you want to enable Virtual Router Redundancy Protocol version 3 (VRRPv3), configure the **version-3** statement at the [edit protocols vrrp] hierarchy level.



NOTE: When enabling VRRPv3, you must ensure that VRRPv3 is enabled on all the VRRP routers in the network. This is because VRRPv3 does not interoperate with the previous versions of VRRP.

Related Documentation

- [Understanding VRRP on page 59](#)
- [VRRP for IPv6 Configuration Hierarchy on page 158](#)
- [Configuring Basic VRRP Support on page 160](#)
- [Example: Configuring VRRP on page 177](#)
- [Junos OS Support for VRRPv3 on page 60](#)
- [version-3 on page 253](#)

VRRP for IPv6 Configuration Hierarchy

To configure VRRP for IPv6, include the following statements:

```

vrrp-inet6-group group-id {
    (accept-data | no-accept-data);
    fast-interval milliseconds;
    inet6-advertise-interval seconds;
    (preempt | no-preempt) {

```

```

    hold-time seconds;
}
priority number;
track {
    interface interface-name {
        bandwidth-threshold bits-per-second priority-cost priority;
        priority-cost priority;
    }
    priority-hold-time seconds;
    route prefix/prefix-length routing-instance instance-name priority-cost priority;
}
virtual-inet6-address [ addresses ];
virtual-link-local-address ipv6-address;
}

```

You can include these statements at the following hierarchy levels:

- [edit interfaces *interface-name* unit *logical-unit-number* family inet6 address *address*]
- [edit logical-systems *logical-system-name* interfaces *interface-name* unit *logical-unit-number* family inet6 address *address*]

If you want to enable Virtual Router Redundancy Protocol version 3 (VRRPv3), configure the **version-3** statement at the [edit protocols vrrp] hierarchy level.



NOTE: When enabling VRRPv3, you must ensure that VRRPv3 is enabled on all the VRRP routers in the network. This is because VRRPv3 does not interoperate with the previous versions of VRRP.

Related Documentation

- [Understanding VRRP on page 59](#)
- [VRRP Configuration Hierarchy on page 157](#)
- [Example: Configuring VRRP for IPv6 on page 179](#)
- [Junos OS Support for VRRPv3 on page 60](#)
- [version-3 on page 253](#)

Configuring the Startup Period for VRRP Operations

To configure the startup period for VRRP operations, include the **startup-silent-period** statement at the [edit protocols vrrp] hierarchy level:

```

[edit protocols vrrp]
startup-silent-period seconds;

```



NOTE: During the silent startup period, the `show vrrp detail` command output shows a value of 0 for Master priority, and your own IP address for Master router. These values indicate that the Master selection is not completed yet, and these values can be ignored.

Related Documentation

- [Understanding VRRP on page 59](#)
- [VRRP Configuration Hierarchy on page 157](#)
- [Configuring Basic VRRP Support on page 160](#)
- [Configuring VRRP Authentication \(IPv4 Only\) on page 162](#)
- [Example: Configuring VRRP on page 177](#)

Configuring Basic VRRP Support

An interface can be a member of one or more VRRP groups. To configure basic VRRP support, configure VRRP groups on interfaces by including the **vrrp-group** statement:

```
vrrp-group group-id {  
    priority number;  
    virtual-address [ addresses ];  
}
```

You can include this statement at the following hierarchy levels:

- [edit interfaces *interface-name* unit *logical-unit-number* family inet address *address*]
- [edit logical-systems *logical-system-name* interfaces *interface-name* unit *logical-unit-number* family inet address *address*]

To configure basic VRRP for IPv6 support, configure VRRP group support on interfaces by including the **vrrp-inet6-group** statement:

```
vrrp-inet6-group group-id {  
    priority number;  
    virtual-inet6-address [ addresses ];  
    virtual-link-local-address ipv6-address;  
}
```

You can include this statement at the following hierarchy levels:

- [edit interfaces *interface-name* unit *logical-unit-number* family inet6 address *address*]
- [edit logical-systems *logical-system-name* interfaces *interface-name* unit *logical-unit-number* family inet6 address *address*]

Within a VRRP group, the master virtual router and the backup virtual router must be configured on two different routing platforms.

For each VRRP group, you must configure the following:

- Group identifier—Assign a value from 0 through 255.
- Address of one or more virtual routers that are members of the VRRP group—Normally, you configure only one virtual IP address per group. However, you can configure up to eight addresses. Do not include a prefix length in a virtual IP address. The following considerations apply to configuring a virtual IP address:

- The virtual router IP address must be the same for all routing platforms in the VRRP group.
- If you configure a virtual IP address to be the same as the physical interface's address, the interface becomes the master virtual router for the group. In this case, you must configure the priority to be 255, and you must configure preemption by including the **preempt** statement.
- If the virtual IP address you choose is not the same as the physical interface's address, you must ensure that the virtual IP address does not appear anywhere else in the routing platform's configuration. Verify that you do not use this address for other interfaces, for the IP address of a tunnel, or for the IP address of static ARP entries.
- You cannot configure a virtual IP address to be the same as the interface's address for an aggregated Ethernet interface. This configuration is not supported.
- For VRRP for IPv6, the EUI-64 option cannot be used. In addition, the Duplicate Address Detection (DAD) process will not run for virtual IPv6 addresses.
- You cannot configure the same virtual IP address on interfaces that belong to the same logical system and routing instance combination. However, you can configure the same virtual IP address on interfaces that belong to different logical system and routing instance combinations.
- Virtual link-local address—(VRRP for IPv6 only) You must explicitly define a virtual link-local address for each VRRP for IPv6 group. Otherwise, when you attempt to commit the configuration, the commit request fails. The virtual link-local address must be on the same subnet as the physical interface address.
- Priority for this routing platform to become the master virtual router—Configure the value used to elect the master virtual router in the VRRP group. It can be a number from 1 through 255. The default value for backup routers is 100. A larger value indicates a higher priority. The routing platform with the highest priority within the group becomes the master router.



NOTE: If there are two or more backup routers with the same priority, the router that has the highest primary address becomes the master.



NOTE: Mixed tagging (configuring two logical interfaces on the same Ethernet port, one with single-tag framing and one with dual-tag framing) is supported only for interfaces on Gigabit Ethernet IQ2 and IQ PICs. If you include the **flexible-vlan-tagging** statement at the **[edit interfaces interface-name]** hierarchy level for a VRRP-enabled interface on a PIC that does not support mixed tagging, VRRP on that interface is disabled. In the output of the **show vrrp summary** command, the interface status is listed as **Down**.



NOTE: If you enable MAC source address filtering on an interface, you must include the virtual MAC address in the list of source MAC addresses that you specify in the `source-address-filter` statement at the `[edit interfaces interface-name]` hierarchy level. (For more information, see the Junos® OS Network Interfaces.) MAC addresses ranging from 00:00:5e:00:01:00 through 00:00:5e:00:01:ff are reserved for VRRP, as defined in RFC 2378. The VRRP group number must be the decimal equivalent of the last hexadecimal byte of the virtual MAC address.

Related Documentation

- [Understanding VRRP on page 59](#)
- [Junos OS Support for VRRPv3 on page 60](#)
- [VRRP Configuration Hierarchy on page 157](#)
- [Configuring the Startup Period for VRRP Operations on page 159](#)
- [Configuring VRRP Authentication \(IPv4 Only\) on page 162](#)
- [Configuring the Advertisement Interval for the VRRP Master Router on page 163](#)
- [Example: Configuring VRRP on page 177](#)

Configuring VRRP Authentication (IPv4 Only)

VRRP (IPv4 only) protocol exchanges can be authenticated to guarantee that only trusted routing platforms participate in routing in an autonomous system (AS). By default, VRRP authentication is disabled. You can configure one of the following authentication methods. Each VRRP group must use the same method.

- Simple authentication—Uses a text password included in the transmitted packet. The receiving routing platform uses an authentication key (password) to verify the packet.
- Message Digest 5 (MD5) algorithm—Creates the authentication data field in the IP authentication header. This header is used to encapsulate the VRRP PDU. The receiving routing platform uses an authentication key (password) to verify the authenticity of the IP authentication header and VRRP PDU.

To enable authentication and specify an authentication method, include the **authentication-type** statement:

```
authentication-type authentication;
```

authentication can be **simple** or **md5**. The authentication type must be the same for all routing platforms in the VRRP group.

You can include this statement at the following hierarchy levels:

- `[edit interfaces interface-name unit logical-unit-number family inet address address vrrp-group group-id]`

- [edit logical-systems *logical-system-name* interfaces *interface-name* unit *logical-unit-number* family inet address *address* vrrp-group *group-id*]

If you include the **authentication-type** statement, you can configure a key (password) on each interface by including the **authentication-key** statement:

authentication-key *key*;

key (the password) is an ASCII string. For simple authentication, it can be from 1 through 8 characters long. For MD5 authentication, it can be from 1 through 16 characters long. If you include spaces, enclose all characters in quotation marks (" "). The key must be the same for all routing platforms in the VRRP group.

You can include this statement at the following hierarchy levels:

- [edit interfaces *interface-name* unit *logical-unit-number* family inet address *address* vrrp-group *group-id*]
- [edit logical-systems *logical-system-name* interfaces *interface-name* unit *logical-unit-number* family inet address *address* vrrp-group *group-id*]



NOTE: When VRRPv3 is enabled, the **authentication-type** and **authentication-key** statements cannot be configured for any VRRP groups. Therefore, if authentication is required, you need to configure alternative non-VRRP authentication mechanisms.

Related Documentation

- [Understanding VRRP on page 59](#)
- [Junos OS Support for VRRPv3 on page 60](#)
- [VRRP Configuration Hierarchy on page 157](#)
- [Configuring Basic VRRP Support on page 160](#)
- [Example: Configuring VRRP on page 177](#)

Configuring the Advertisement Interval for the VRRP Master Router

By default, the master router sends VRRP advertisement packets every second to all members of the VRRP group. These packets indicate that the master router is still operational. If the master router fails or becomes unreachable, the backup router with the highest priority value becomes the new master router.

You can modify the advertisement interval in seconds or in milliseconds. The interval must be the same for all routing platforms in the VRRP group.

For VRRP for IPv6, you must configure IPv6 router advertisements for the interface on which VRRP is configured to send IPv6 router advertisements for the VRRP group. To do so, include the **interface *interface-name*** statement at the [edit protocols **router-advertisement**] hierarchy level. (For information about this statement and guidelines, see the Junos OS Routing Protocols Configuration Guide.) When an interface

receives an IPv6 router solicitation message, it sends an IPv6 router advertisement to all VRRP groups configured on it. In the case of logical systems, IPv6 router advertisements are not sent to VRRP groups.



NOTE: The master VRRP for an IPv6 router must respond to a router solicitation message with the virtual IP address of the router. However, when the `interface interface-name` statement is included at the `[edit protocols router-advertisement]` hierarchy level, the backup VRRP for an IPv6 router might send a response before the VRRP master responds, so that the default route of the client is not set to the master VRRP router's virtual IP address. To avoid this situation, include the `virtual-router-only` statement at the `[edit protocols router-advertisement interface interface-name]` hierarchy level. When this statement is included, router advertisements are sent only for VRRP IPv6 groups configured on the interface (if the groups are in the master state). You must include this statement on both the master and backup VRRP for IPv6 routers.

This topic contains the following sections:

- [Modifying the Advertisement Interval in Seconds on page 164](#)
- [Modifying the Advertisement Interval in Milliseconds on page 164](#)

Modifying the Advertisement Interval in Seconds

To modify the time, in seconds, between the sending of VRRP advertisement packets, include the `advertise-interval` statement:

```
advertise-interval seconds;
```

The interval can be from 1 through 255 seconds.

You can include this statement at the following hierarchy levels:

- `[edit interfaces interface-name unit logical-unit-number family inet address address vrrp-group group-id]`
- `[edit logical-systems logical-system-name interfaces interface-name unit logical-unit-number family inet address address vrrp-group group-id]`



NOTE: When VRRPv3 is enabled, the `advertise-interval` statement cannot be used to configure advertisement intervals. Instead, use the `fast-interval` statement to configure advertisement intervals.

Modifying the Advertisement Interval in Milliseconds

To modify the time, in milliseconds, between the sending of VRRP advertisement packets, include the `fast-interval` statement:

```
fast-interval milliseconds;
```


The interval can be from 10 through 40,950 milliseconds.

You can include this statement at the following hierarchy levels:

- [edit interfaces *interface-name* unit *logical-unit-number* family (inet | inet6) address *address* (vrrp-group | vrrp-inet6-group) *group-id*]
- [edit logical-systems *logical-system-name* interfaces *interface-name* unit *logical-unit-number* family (inet | inet6) address *address* (vrrp-group | vrrp-inet6-group) *group-id*]



NOTE: In the VRRP PDU, Junos OS sets the advertisement interval to 0. When you configure VRRP with other vendors' routers, the `fast-interval` statement works correctly only when the other routers also have an advertisement interval set to 0 in the VRRP PDUs. Otherwise, Junos OS interprets other routers' settings as advertisement timer errors.

To modify the time, in milliseconds, between the sending of VRRP for IPv6 advertisement packets, include the `inet6-advertise-interval` statement:

`inet6-advertise-interval ms;`

The range of values is from 100 through 40,950 milliseconds (ms).

You can include this statement at the following hierarchy levels:

- [edit interfaces *interface-name* unit *logical-unit-number* family inet6 address *address* vrrp-inet6-group *group-id*]
- [edit logical-systems *logical-system-name* interfaces *interface-name* unit *logical-unit-number* family inet6 address *address* vrrp-inet6-group *group-id*]



NOTE: When VRRPv3 is enabled, the `inet6-advertise-interval` statement cannot be used to configure advertisement intervals. Instead, use the `fast-interval` statement to configure advertisement intervals.

Related Documentation

- [Understanding VRRP on page 59](#)
- [Junos OS Support for VRRPv3 on page 60](#)
- [VRRP Configuration Hierarchy on page 157](#)
- [Configuring Basic VRRP Support on page 160](#)
- [Configuring a Backup Router to Preempt the Master Router on page 166](#)
- [Modifying the Preemption Hold-Time Value on page 166](#)
- [Configuring Asymmetric Hold Time for VRRP Routers on page 167](#)
- [Configuring the Silent Period on page 173](#)
- [Example: Configuring VRRP on page 177](#)

Configuring a Backup Router to Preempt the Master Router

By default, a higher-priority backup router preempts a lower-priority master router. To explicitly enable the master router to be preempted, include the **preempt** statement:

```
preempt;
```

You can include this statement at the following hierarchy levels:

- [edit interfaces *interface-name* unit *logical-unit-number* family (inet | inet6) address *address* (vrrp-group | vrrp-inet6-group) *group-id*]
- [edit logical-systems *logical-system-name* interfaces *interface-name* unit *logical-unit-number* family (inet | inet6) address *address* (vrrp-group | vrrp-inet6-group) *group-id*]

To prohibit a higher-priority backup router from preempting a lower-priority master router, include the **no-preempt** statement:

```
no-preempt;
```

Related Documentation

- [Understanding VRRP on page 59](#)
- [VRRP Configuration Hierarchy on page 157](#)
- [Configuring the Advertisement Interval for the VRRP Master Router on page 163](#)
- [Modifying the Preemption Hold-Time Value on page 166](#)
- [Configuring Asymmetric Hold Time for VRRP Routers on page 167](#)
- [Example: Configuring VRRP on page 177](#)

Modifying the Preemption Hold-Time Value

The hold time is the maximum number of seconds that can elapse before a higher-priority backup router preempts the master router. You might want to configure a hold time so that all Junos OS components converge before preemption.

By default, the hold-time value is 0 seconds. A value of 0 means that preemption can occur immediately after the backup router comes online. Note that the hold time is counted from the time the backup router comes online. The hold time is only valid when the VRRP router is just coming online.

To modify the preemption hold-time value, include the **hold-time** statement:

```
hold-time seconds;
```

The hold time can be from 0 through 3600 seconds.

You can include this statement at the following hierarchy levels:

- [edit interfaces *interface-name* unit *logical-unit-number* family (inet | inet6) address *address* (vrrp-group | vrrp-inet6-group) *group-id* preempt]

- [edit logical-systems *logical-system-name* interfaces *interface-name* unit *logical-unit-number* family (inet | inet6) address *address* (vrrp-group | vrrp-inet6-group) *group-id* preempt]

**Related
Documentation**

- [VRRP Configuration Hierarchy on page 157](#)
- [Configuring the Advertisement Interval for the VRRP Master Router on page 163](#)
- [Configuring a Backup Router to Preempt the Master Router on page 166](#)
- [Configuring Asymmetric Hold Time for VRRP Routers on page 167](#)
- [Example: Configuring VRRP on page 177](#)

Configuring Asymmetric Hold Time for VRRP Routers

In Junos OS Release 9.5 and later, the **asymmetric-hold-time** statement at the [edit protocols vrrp] hierarchy level enables you to configure a VRRP master router to switch over to the backup router immediately—that is, without waiting for the priority hold time to expire—when a tracked interface or route goes down or when the bandwidth of a tracked interface decreases. Such events can cause an immediate reduction in the priority based on the configured priority cost for the event, and trigger a mastership election.

However, when the tracked route or interface comes up again, or when the bandwidth for a tracked interface increases, the backup (original master) router waits for the hold time to expire before it updates the priority and initiates the switchover if the priority is higher than the priority for the VRRP master (original backup) router.

If the **asymmetric-hold-time** statement is not configured, the VRRP master waits for the hold time to expire before it initiates a switchover when a tracked route goes down.

**Example: Configuring
Asymmetric Hold Time**

```
[edit]
user@host# set protocols vrrp asymmetric-hold-time
[edit]
user@host# show protocols vrrp
asymmetric-hold-time;
```

**Related
Documentation**

- [VRRP Configuration Hierarchy on page 157](#)
- [Configuring the Advertisement Interval for the VRRP Master Router on page 163](#)
- [Configuring a Backup Router to Preempt the Master Router on page 166](#)
- [Modifying the Preemption Hold-Time Value on page 166](#)
- [Example: Configuring VRRP on page 177](#)

Configuring an Interface to Accept Packets Destined for the Virtual IP Address

In VRRP implementations where the router acting as the master router is not the IP address owner—the IP address owner is the router that has the interface whose actual IP address is used as the virtual router's IP address (virtual IP address)—the master router accepts only the ARP packets from the packets that are sent to the virtual IP address. Junos OS enables you to override this limitation with the help of the **accept-data** configuration. When the **accept-data** statement is included in the configuration, the master router accepts all packets sent to the virtual IP address even when the master router is not the IP address owner.



NOTE: If the master router is the IP address owner or has its priority set to 255, the master router, by default, accepts all packets addressed to the virtual IP address. In such cases, the **accept-data** configuration is not required.

To configure an interface to accept all packets sent to the virtual IP address, include the **accept-data** statement:

```
accept-data;
```

You can include this statement at the following hierarchy levels:

- [edit interfaces *interface-name* unit *logical-unit-number* family (inet | inet6) address *address* (vrrp-group | vrrp-inet6-group) *group-id*]
- [edit logical-systems *logical-system-name* interfaces *interface-name* unit *logical-unit-number* family (inet | inet6) address *address* (vrrp-group | vrrp-inet6-group) *group-id*]

To prevent a master router that is the IP address owner or has its priority set to 255 from accepting packets other than the ARP packets addressed to the virtual IP address, include the **no-accept-data** statement:

```
no-accept-data;
```



NOTE:

- If you want to restrict the incoming IP packets to ICMP packets only, you must configure firewall filters to accept only ICMP packets.
- If you include the **accept-data** statement, your routing platform configuration does not comply with RFC 3768 (see section 6.4.3 of RFC 3768, *Virtual Router Redundancy Protocol (VRRP)*).

Related Documentation

- [Understanding VRRP on page 59](#)
- [VRRP Configuration Hierarchy on page 157](#)
- [Example: Configuring VRRP on page 177](#)

Configuring a Logical Interface to Be Tracked

VRRP can track whether a logical interface is up, down, or not present, and can also dynamically change the priority of the VRRP group based on the state of the tracked logical interface, triggering a new master router election. VRRP can also track the operational speed of a logical interface and dynamically update the priority of the VRRP group when the speed crosses a configured threshold.

When interface tracking is enabled, you cannot configure a priority of 255 (a priority of 255 designates the master router). For each VRRP group, you can track up to 10 logical interfaces.

To configure a logical interface to be tracked, include the following statements:

```
track {
  interface interface-name {
    bandwidth-threshold bits-per-second priority-cost priority;
    priority-cost priority;
  }
  priority-hold-time seconds;
}
```

You can include these statements at the following hierarchy levels:

- [edit interfaces *interface-name* unit *logical-unit-number* family inet address *address* *vrrp-group group-id*]
- [edit interfaces *interface-name* unit *logical-unit-number* family inet6 address *address* *vrrp-inet6-group group-id*]
- [edit logical-systems *logical-system-name* interfaces *interface-name* unit *logical-unit-number* family inet address *address* *vrrp-group group-id*]
- [edit logical-systems *logical-system-name* interfaces *interface-name* unit *logical-unit-number* family inet6 address *address* *vrrp-inet6-group group-id*]

The interface specified is the interface to be tracked for the VRRP group. The priority hold time is the minimum length of time that must elapse between dynamic priority changes. A tracking event, such as an interface state change (up or down) or a change in bandwidth, triggers one of the following responses:

- The first tracking event initiates the priority hold timer, and also initializes the pending priority based on the current priority and the priority cost. However, the current priority remains unchanged.
- A tracking event or a manual configuration change that occurs while the priority hold timer is on triggers a pending priority update. However, the current priority remains unchanged.

This ensures that Junos OS does not initiate mastership elections every time a tracked interface flaps.

When the priority hold time expires, the current priority inherits the value from the pending priority, and the pending priority ceases.



NOTE: If you have configured **asymmetric-hold-time**, VRRP does not wait for the priority hold time to expire before initiating mastership elections if a tracked interface fails (state changes from up to down), or if the available bandwidth for a tracked interface decreases. For more information about **asymmetric-hold-time**, see [“Configuring Asymmetric Hold Time for VRRP Routers” on page 167](#).

The bandwidth threshold specifies a threshold for the tracked interface. When the bandwidth of the tracked interface drops below the configured bandwidth threshold value, the VRRP group uses the bandwidth threshold priority cost. You can track up to five bandwidth threshold statements for each tracked interface.

The priority cost is the value to be subtracted from the configured VRRP priority when the tracked logical interface goes down, forcing a new master router election. The value can be from 1 through 254. The sum of the costs for all tracked logical interfaces or routes must be less than or equal to the configured priority of the VRRP group.

If you are tracking more than one interface, the router applies the sum of the priority costs for the tracked interfaces (at most, only one priority cost for each tracked interface) to the VRRP group priority. However, the interface priority cost and bandwidth threshold priority cost values for each VRRP group are not cumulative. The router uses only one priority cost to a tracked interface as indicated in [Table 19 on page 170](#):

Table 19: Interface State and Priority Cost Usage

Tracked Interface State	Priority Cost Usage
Down	<i>priority-cost priority</i>
Not down; media speed below one or more bandwidth thresholds	Priority-cost of the lowest applicable bandwidth threshold

You must configure an interface priority cost only if you have configured no bandwidth thresholds. If you have not configured an interface priority cost value, and the interface is down, the interface uses the bandwidth threshold priority cost value of the lowest bandwidth threshold.

**Related
Documentation**

- [Understanding VRRP on page 59](#)
- [VRRP Configuration Hierarchy on page 157](#)
- [Configuring a Route to Be Tracked on page 171](#)
- [Example: Configuring VRRP on page 177](#)

Configuring a Route to Be Tracked

VRRP can track whether a route is reachable (that is, the route exists in the routing table of the routing instance included in the configuration) and dynamically change the priority of the VRRP group based on the reachability of the tracked route, triggering a new master router election.

To configure a route to be tracked, include the following statements:

```
track {
  priority-hold-time seconds;
  route prefix/prefix-length routing-instance instance-name priority-cost priority;
}
```

You can include these statements at the following hierarchy levels:

- [edit interfaces *interface-name* unit *logical-unit-number* family inet address *address* *vrrp-group group-id*]
- [edit interfaces *interface-name* unit *logical-unit-number* family inet6 address *address* *vrrp-inet6-group group-id*]
- [edit logical-systems *logical-system-name* interfaces *interface-name* unit *logical-unit-number* family inet address *address* *vrrp-group group-id*]
- [edit logical-systems *logical-system-name* interfaces *interface-name* unit *logical-unit-number* family inet6 address *address* *vrrp-inet6-group group-id*]

The route prefix specified is the route to be tracked for the VRRP group. The priority hold time is the minimum length of time that must elapse between dynamic priority changes. A route tracking event, such as adding a route to or removing a route from the routing table, might trigger one or more of the following:

- The first tracking event initiates the priority hold timer, and also initializes the pending priority based on the current priority and the priority cost. However, the current priority remains unchanged.
- A tracking event or a manual configuration change that occurs while the priority hold timer is on triggers a pending priority update. However, the current priority remains unchanged.

When the priority hold time expires, the current priority inherits the value from the pending priority, and the pending priority ceases.

This ensures that Junos OS does not initiate mastership elections every time a tracked route flaps.



NOTE: If you have configured *asymmetric-hold-time*, VRRP does not wait for the priority hold time to expire before initiating mastership elections if a tracked route is removed from the routing table. For more information about *asymmetric-hold-time*, see [“Configuring Asymmetric Hold Time for VRRP Routers”](#) on page 167.

The routing instance is the routing instance in which the route is to be tracked. If the route is in the default, or global, routing instance, specify the instance name as **default**.



NOTE: Tracking a route that belongs to a routing instance from a different logical system is not supported.

The priority cost is the value to be subtracted from the configured VRRP priority when the tracked route goes down, forcing a new master router election. The value can be from 1 through 254. The sum of the costs for all tracked logical interfaces or routes must be less than or equal to the configured priority of the VRRP group.

Related Documentation

- [Understanding VRRP on page 59](#)
- [VRRP Configuration Hierarchy on page 157](#)
- [Configuring a Logical Interface to Be Tracked on page 169](#)
- [Example: Configuring VRRP Route Tracking on page 180](#)

Configuring Inheritance for a VRRP Group

Junos OS enables you to configure VRRP groups on the various subnets of a VLAN to inherit the state and configuration of one of the groups, which is known as the *active VRRP group*. When the **vrp-inherit-from** configuration statement is included in the configuration, only the active VRRP group, from which the other VRRP groups are inheriting the state, sends out frequent VRRP advertisements, and processes incoming VRRP advertisements. The groups that are inheriting the state do not process any incoming VRRP advertisement because the state is always inherited from the active VRRP group. However, the groups that are inheriting the state do send out VRRP advertisements once every 2 to 3 minutes to facilitate MAC address learning on the switches placed between the VRRP routers.

If the **vrp-inherit-from** statement is not configured, each of the VRRP master groups in the various subnets on the VLAN sends out separate VRRP advertisements and adds to the traffic on the VLAN.

To configure inheritance for a VRRP group, include the **vrp-inherit-from** statement at the **[edit interfaces *interface-name* unit *logical-unit-number* family inet address *address* *vrp-group group-id*]** hierarchy level.

```
[edit interfaces interface-name unit logical-unit-number family inet address address
  vrp-group group-id]
  vrp-inherit-from vrp-group;
```

When you configure a group to inherit a state from another group, the inheriting groups and the active group must be on the same physical interface and logical system. However, the groups do not need to necessarily be on the same routing instance (as was in Junos OS releases earlier than 9.6), VLAN, or logical interface.

When you include the **vrrp-inherit-from** statement for a VRRP group, the VRRP group inherits the following parameters from the active group:

- **advertise-interval**
- **authentication-key**
- **authentication-type**
- **fast-interval**
- **preempt | no-preempt**
- **priority**
- **track interfaces**
- **track route**

However, you can configure the **accept-data | no-accept-data** statement for the group to specify whether the interface should accept packets destined for the virtual IP address.

**Related
Documentation**

- [Understanding VRRP on page 59](#)
- [VRRP Configuration Hierarchy on page 157](#)

Configuring the Silent Period

The silent period starts when the interface state is changed from down to up. During this period, the Master Down Event is ignored. Configure the silent period interval to avoid alarms caused by the delay or interruption of the incoming VRRP advertisement packets during the interface startup phase.

To configure the silent period interval that the Master Down Event timer ignores, include the **startup-silent-period** statement at the **[edit protocols vrrp]** hierarchy level:

```
[edit protocols vrrp]
startup-silent-period seconds;
```



NOTE: During the silent startup period, the **show vrrp detail** command output shows a value of 0 for **Master priority** and your IP address for **Master router**. These values indicate that the Master selection is not completed yet, and these values can be ignored.

When you have configured **startup-silent-period**, the Master Down Event is ignored until the **startup-silent-period** expires.

For example, configure a VRRP group, *vrrp-group1*, with an advertise interval of 1 second, startup silent period of 10 seconds, and an interface *interface1* with a priority less than 255.

When *interface1* transitions from down to up:

- The *vrrp-group1* group moves to the backup state, and starts the Master Down Event timer (3 seconds; three times the value of the advertise interval, which is 1 second in this case).
- If no VRRP PDU is received during the 3-second period, the **startup-silent-period** (10 seconds in this case) is checked, and if the startup silent period has not expired, the Master Down Event timer is restarted. This is repeated until the **startup-silent-period** expires. In this example, the Master Down Event timer runs four times (12 seconds) by the time the 10-second startup silent period expires.
- If no VRRP PDU is received by the end of the fourth 3-second cycle, *vrrp-group1* takes over mastership.

**Related
Documentation**

- [Understanding VRRP on page 59](#)
- [VRRP Configuration Hierarchy on page 157](#)
- [startup-silent-period on page 249](#)

Configuring Passive ARP Learning for Backup VRRP Routers

By default, the backup VRRP router drops ARP requests for the VRRP-IP to VRRP-MAC address translation. This means that the backup router does not learn the ARP (IP-to-MAC address) mappings for the hosts sending the requests. When it detects a failure of the master router and transitions to become the new master router, the backup router must learn all the entries that were present in the ARP cache of the master router. In environments with many directly attached hosts, such as metro Ethernet environments, the number of ARP entries to learn can be high. This can cause a significant transition delay, during which the traffic transmitted to some of the hosts might be dropped.

Passive ARP learning enables the ARP cache in the backup router to hold approximately the same contents as the ARP cache in the master router, thus preventing the problem of learning ARP entries in a burst. To enable passive ARP learning, include the **passive-learning** statement at the **[edit system arp]** hierarchy level:

```
[edit system arp]
passive-learning;
```

We recommend setting passive learning on both the backup and master VRRP routers. Doing so prevents the need to manually intervene when the master router becomes the backup router. While a router is operating as the master router, the passive learning configuration has no operational impact. The configuration takes effect only when the router is operating as a backup router.

For information about configuring gratuitous ARP and the ARP aging timer, see the Junos OS System Basics Configuration Guide.

- Related Documentation**
- [Understanding VRRP on page 59](#)
 - [VRRP Configuration Hierarchy on page 157](#)

Enabling the Distributed Periodic Packet Management Process for VRRP

Typically, VRRP advertisements are sent by the VRRP process (vrrpd) on the master VRRP router at regular intervals to let other members of the group know that the VRRP master router is operational.

When the vrrpd process is busy and does not send VRRP advertisements, the backup VRRP routers might assume that the master router is down and take over as the master router, causing unnecessary flaps. This takeover might occur even though the original master router is still active and available, and might resume sending advertisements after the traffic has decreased. To address this problem and to reduce the load on the vrrpd process, Junos OS uses the periodic packet management process (ppmd) to send VRRP advertisements on behalf of the vrrpd process. However, you can further delegate the job of sending VRRP advertisements to the distributed ppm process that resides on the Packet Forwarding Engine.

The ability to delegate the sending of VRRP advertisements to the distributed ppm process ensures that the VRRP advertisements are sent even when the ppm process—which is now responsible for sending VRRP advertisements—is busy. Such delegation prevents the possibility of false alarms when the ppm process is busy. The ability to delegate the sending of VRRP advertisements to distributed ppm also adds to scalability because the load is shared across multiple ppm instances and is not concentrated on any single unit.



NOTE: CPU-intensive VRRP advertisements, such as advertisements with MD5 authentication or those sent and received over logical interfaces, such as Aggregated Ethernet interfaces, continue to be processed by the VRRP process on the Routing Engine even when distributed ppm is enabled.

To configure the distributed ppm process to send VRRP advertisements, include the **delegate-processing** statement at the **[edit protocols vrrp]** hierarchy level:

```
[edit protocols vrrp]
  delegate-processing;
```

- Related Documentation**
- [Understanding VRRP on page 59](#)
 - [VRRP Configuration Hierarchy on page 157](#)

Configuring VRRP to Improve Convergence Time

You can enable faster convergence time for the configured Virtual Router Redundancy Protocol (VRRP), thereby reducing the traffic restoration time to less than 1 second. To improve the convergence time for VRRP, perform the following tasks.

Before you begin, configure VRRP. See [“Example: Configuring VRRP” on page 177](#).

1. Configure the distributed periodic packet management (PPM) process to send VRRP advertisements when the VRRP process is busy.

```
[edit]
user@host# set protocols vrrp delegate-processing
```

2. Disable the skew timer to reduce the time required to transition to the master state.

```
[edit]
user@host# set protocols vrrp skew-timer-disable
```



NOTE: When there is only one master router and one backup router in the network deployment, you can disable the skew timer, thereby reducing the time required to transition to the master state.

3. Configure the number of fast advertisements that can be missed by a backup router before it starts transitioning to the master state.

```
[edit]
user@host# set protocols vrrp global-advertisement-threshold advertisement-value
```

4. Configure VRRP groups on the various subnets of a VLAN to inherit the state and to configure one of the groups.

```
[edit]
user@host# set interfaces interface-name unit logical-unit-number family inet address
address vrrp-group group-id
```

5. Verify the configuration in operational mode.

```
[edit]
user@host> show protocols vrrp
```



NOTE:

- The reduction in convergence time is not applicable when VRRP is configured over integrated routing and bridging (IRB) interfaces, aggregated Ethernet interfaces, and multichassis link aggregation group (MC-LAG) interfaces.
- Compared to other routers, the convergence time and the traffic restoration time are less for MX Series routers with MPCs.
- Reduction in convergence time is applicable for all types of configurations at the physical interface, but the convergence time might not be less than 1 second for all the configurations. The convergence time depends on the number of groups that are transitioning from the backup to the master state and the interval at which these groups are transitioning.

Related Documentation

- [Improving the Convergence Time for VRRP on page 63](#)
- [Configuring Inheritance for a VRRP Group on page 172](#)
- [delegate-processing on page 238](#)
- [global-advertisements-threshold on page 240](#)
- [skew-timer-disable on page 249](#)

Example: Configuring VRRP

Configure one master (Router A) and one backup (Router B) routing platform. The address configured in the **virtual-address** statements differs from the addresses configured in the **address** statements. When you configure multiple VRRP groups on an interface, you configure one to be the master virtual router for that group.

```
On Router A  [edit interfaces]
              ge-0/0/0 {
                unit 0 {
                  family inet {
                    address 192.168.1.20/24 {
                      vrrp-group 27 {
                        virtual-address 192.168.1.15;
                        priority 254;
                        authentication-type simple;
                        authentication-key booJUM;
                      }
                    }
                  }
                }
              }
```

```
On Router B  [edit interfaces]
              ge-4/2/0 {
                unit 0 {
                  family inet {
```

Configuring One Router to Be the Master Virtual Router for the Group

```

address 192.168.1.24/24 {
  vrrp-group 27 {
    virtual-address 192.168.1.15;
    priority 200;
    authentication-type simple;
    authentication-key booJUM;
  }
}

```

```

[edit interfaces]
ge-0/0/0 {
  unit 0 {
    family inet {
      address 192.168.1.20/24 {
        vrrp-group 2 {
          virtual-address 192.168.1.20;
          priority 255;
          advertise-interval 3;
          preempt;
        }
        vrrp-group 10 {
          virtual-address 192.168.1.55;
          priority 201;
          advertise-interval 3;
        }
        vrrp-group 1 {
          virtual-address 192.168.1.54;
          priority 22;
          advertise-interval 4;
        }
      }
    }
  }
}

```

Configuring VRRP and MAC Source Address Filtering

The VRRP group number is the decimal equivalent of the last byte of the virtual MAC address.

```

[edit interfaces]
ge-5/2/0 {
  gigether-options {
    source-filtering;
    source-address-filter {
      00:00:5e:00:01:0a; # Virtual MAC address
    }
  }
  unit 0 {
    family inet {
      address 192.168.1.10/24 {
        vrrp-group 10; # VRRP group number
        virtual-address 192.168.1.10;
        priority 255;
        preempt;
      }
    }
  }
}

```

```

    }
  }
}

```

- Related Documentation**
- [Understanding VRRP on page 59](#)
 - [VRRP Configuration Hierarchy on page 157](#)
 - [VRRP for IPv6 Configuration Hierarchy on page 158](#)
 - [Example: Configuring VRRP for IPv6 on page 179](#)
 - [Example: Configuring VRRP Route Tracking on page 180](#)

Example: Configuring VRRP for IPv6

Configure VRRP properties for IPv6 in one master (Router A) and one backup (Router B).

On Router A

```

[edit interfaces]
ge-1/0/0 {
  unit 0 {
    family inet6 {
      address fe80::5:0:0:6/64;
      address fec0::5:0:0:6/64 {
        vrrp-inet6-group 3; # VRRP inet6 group number
        virtual-inet6-address fec0::5:0:0:7;
        virtual-link-local-address fe80::5:0:0:7;
        priority 200;
        preempt;
      }
    }
  }
}

[edit protocols]
router-advertisement {
  interface ge-1/0/0.0 {
    prefix fec0::/64;
    max-advertisement-interval 4;
  }
}

```

On Router B

```

[edit interfaces]
ge-1/0/0 {
  unit 0 {
    family inet6 {
      address fe80::5:0:0:8/64;
      address fec0::5:0:0:8/64 {
        vrrp-inet6-group 3; # VRRP inet6 group number
        virtual-inet6-address fec0::5:0:0:7;
        virtual-link-local-address fe80::5:0:0:7;
        priority 100;
        preempt;
      }
    }
  }
}

```

```
    }  
  }  
  
  [edit protocols]  
  router-advertisement {  
    interface ge-1/0/0.0 {  
      prefix fec0::/64;  
      max-advertisement-interval 4;  
    }  
  }  
}
```

**Related
Documentation**

- [Understanding VRRP on page 59](#)
- [VRRP Configuration Hierarchy on page 157](#)
- [VRRP for IPv6 Configuration Hierarchy on page 158](#)
- [Example: Configuring VRRP on page 177](#)
- [Example: Configuring VRRP Route Tracking on page 180](#)

Example: Configuring VRRP Route Tracking

Configure Routers R1 and R2 to run VRRP. Configure static routes and a policy for exporting the static routes on Router R3. The VRRP routing instances on R2 track the routes that are advertised by R3.

On Router R1

```
[edit interfaces]  
ge-1/0/3 {  
  unit 0 {  
    vlan-id 1;  
    family inet {  
      address 200.100.50.2/24 {  
        vrrp-group 0 {  
          virtual-address 200.100.50.101;  
          priority 195;  
        }  
      }  
    }  
  }  
}
```

On Router R2

```
[edit interfaces]  
ge-1/0/1 {  
  unit 0 {  
    vlan-id 1;  
    family inet {  
      address 200.100.50.1/24 {  
        vrrp-group 0 {  
          virtual-address 200.100.50.101;  
          priority 200;  
          track {  
            route 59.0.58.153/32 routing-instance default priority-cost 5;  
            route 59.0.58.154/32 routing-instance default priority-cost 5;  
            route 59.0.58.155/32 routing-instance default priority-cost 5;
```



```

    }
  }
}
}
}

```

On Router R3

```

[edit]
policy-options {
  policy-statement static-policy {
    term term1 {
      then accept;
    }
  }
}
protocols {
  ospf {
    export static-policy;
    reference-bandwidth 4g;
    area 0.0.0.0 {
      interface all;
      interface fxp0.0 {
        disable;
      }
    }
  }
}
routing-options {
  static {
    route 59.0.0.153/32 next-hop 45.45.45.46;
    route 59.0.0.154/32 next-hop 45.45.45.46;
    route 59.0.0.155/32 next-hop 45.45.45.46;
  }
}

```

**Related
Documentation**

- [Understanding VRRP on page 59](#)
- [VRRP Configuration Hierarchy on page 157](#)
- [VRRP for IPv6 Configuration Hierarchy on page 158](#)
- [Configuring a Route to Be Tracked on page 171](#)
- [Example: Configuring VRRP on page 177](#)
- [Example: Configuring VRRP for IPv6 on page 179](#)

Example: Configuring Multiple VRRP Owner Groups

These examples show how to configure multiple virtual router redundancy protocol (VRRP) IPv4 and IPv6 owner groups.

- [Requirements on page 182](#)
- [Overview on page 182](#)

- [Configuration on page 182](#)
- [Verification on page 187](#)

Requirements

This example uses the following hardware and software components:

- A EX-Series, M-Series, MX-Series, or T-Series router.
- Junos OS release 12.3 or later

Overview

Multiple VRRP owner groups allows users to reuse interface address identifiers (IFAs) as virtual IP addresses (VIPs). You can configure multiple IPv4 owner groups, multiple IPv6 owner groups, or a mix of IPv4 and IPv6 owner groups.

Configuration

CLI Quick Configuration

To quickly configure this section of the example, copy the following commands, paste them into a text file, remove any line breaks, change any details necessary to match your network configuration, and then copy and paste the commands into the CLI at the **[edit]** hierarchy level.

Multiple IPv4 owner groups

```
edit interfaces ge-1/0/0 unit 0 family inet
set address 10.0.0.2/24 vrrp-group 2 virtual-address 10.0.0.4 accept-data
set address 20.0.0.2/24 vrrp-group 3 virtual-address 20.0.0.2 priority 255
set address 30.0.0.2/24 vrrp-group 4 virtual-address 30.0.0.2 priority 255
```

Multiple IPv6 owner groups

```
edit interfaces ge-1/0/0 unit 0 family inet6
set address 2001:4818:f000:20::1/64 vrrp-inet6-group 1 virtual-inet6-address
  2001:4818:f000:20::1
set address 2001:4818:f000:20::1/64 vrrp-inet6-group 1 virtual-link-local-address
  fe80:4818:f000:20::1
set address 2001:4818:f000:20::1/64 vrrp-inet6-group 1 priority 255
set address fe80:4818:f000:13::2/64
set address 2001:1000:f000:20::1/64 vrrp-inet6-group 2 virtual-inet6-address
  2001:1000:f000:20::1
set address 2001:1000:f000:20::1/64 vrrp-inet6-group 2 virtual-link-local-address
  fe80:1000:f000:20::1
set address 2001:1000:f000:20::1/64 vrrp-inet6-group 2 priority 255
set address 2001:2000:f000:20::1/64 vrrp-inet6-group 3 virtual-inet6-address
  2001:2000:f000:20::2
set address 2001:2000:f000:20::1/64 vrrp-inet6-group 3 virtual-link-local-address
  fe80:2000:f000:20::2
set address 2001:2000:f000:20::1/64 vrrp-inet6-group 3 priority 250
```

Multiple IPv4 and IPv6 owner groups

```
edit interfaces ge-1/0/0 unit 0
set family inet address 10.0.0.1/24 vrrp-group 5 virtual-address 10.0.0.1
set family inet address 10.0.0.1/24 vrrp-group 5 priority 255
set family inet6 address 2001:4818:f000:20::1/64 vrrp-inet6-group 1 virtual-inet6-address
  2001:4818:f000:20::1
set family inet6 address 2001:4818:f000:20::1/64 vrrp-inet6-group 1
  virtual-link-local-address fe80:4818:f000:20::1
set family inet6 address 2001:4818:f000:20::1/64 vrrp-inet6-group 1 priority 255
```

```

set family inet6 address 2001:1000:f000:20::1/64 vrrp-inet6-group 2 virtual-inet6-address
2001:1000:f000:20::1
set family inet6 address 2001:1000:f000:20::1/64 vrrp-inet6-group 2
virtual-link-local-address fe80:1000:f000:20::1
set family inet6 address 2001:1000:f000:20::1/64 vrrp-inet6-group 2 priority 255
set family inet6 address 2001:2000:f000:20::1/64 vrrp-inet6-group 3 virtual-inet6-address
2001:2000:f000:20::2
set family inet6 address 2001:2000:f000:20::1/64 vrrp-inet6-group 3
virtual-link-local-address fe80:2000:f000:20::2
set family inet6 address 2001:2000:f000:20::1/64 vrrp-inet6-group 3 priority 250

```

Configuring multiple IPv4 owner groups

Step-by-Step Procedure

To configure multiple IPv4 owner groups:

1. Create an IPv4 interface on the device

```
[edit]
user@host# edit interfaces ge-1/0/0 unit 0 family inet
```
2. Configure the first IPv4 owner group

```
[edit interfaces ge-1/0/0 unit 0 family inet]
user@host# set address 10.0.0.2/24 vrrp-group 2 virtual-address 10.0.0.4
accept-data
```
3. Configure the second IPv4 owner group

```
[edit interfaces ge-1/0/0 unit 0 family inet]
user@host# set address 20.0.0.2/24 vrrp-group 3 virtual-address 20.0.0.2 priority
255
```
4. Configure the third IPv4 owner group

```
[edit interfaces ge-1/0/0 unit 0 family inet]
user@host# set address 30.0.0.2/24 vrrp-group 4 virtual-address 30.0.0.2 priority
255
```

Configuring multiple IPv6 owner groups

Step-by-Step Procedure

To configure multiple IPv6 owner groups:

1. Create an IPv6 interface on the device

```
[edit]
user@host# edit interfaces ge-1/0/0 unit 0 family inet6
```
2. Configure the inet6 address for the first IPv6 owner group

```
[edit interfaces ge-1/0/0 unit 0 family inet6]
user@host# set address 2001:4818:f000:20::1/64 vrrp-inet6-group 1
virtual-inet6-address 2001:4818:f000:20::1
```
3.

```
[edit interfaces ge-1/0/0 unit 0 family inet6]
user@host# set address 2001:4818:f000:20::1/64 vrrp-inet6-group 1
virtual-link-local-address fe80:4818:f000:20::1
```
4.

```
[edit interfaces ge-1/0/0 unit 0 family inet6]
user@host# set address 2001:4818:f000:20::1/64 vrrp-inet6-group 1 priority 255
```

5.

```
[edit interfaces ge-1/0/0 unit 0 family inet6]
user@host# set family inet6 address 2001:1000:f000:20::1/64 vrrp-inet6-group 2
virtual-inet6-address 2001:1000:f000:20::1
```
6.

```
[edit interfaces ge-1/0/0 unit 0 family inet6]
user@host# set family inet6 address 2001:1000:f000:20::1/64 vrrp-inet6-group 2
virtual-link-local-address fe80:1000:f000:20::1
```
7.

```
[edit interfaces ge-1/0/0 unit 0 family inet6]
user@host# set family inet6 address 2001:1000:f000:20::1/64 vrrp-inet6-group 2
priority 255
```
8.

```
[edit interfaces ge-1/0/0 unit 0 family inet6]
user@host# set family inet6 address 2001:2000:f000:20::1/64 vrrp-inet6-group 3
virtual-inet6-address 2001:2000:f000:20::2
```
9.

```
[edit interfaces ge-1/0/0 unit 0 family inet6]
user@host# set family inet6 address 2001:2000:f000:20::1/64 vrrp-inet6-group 3
virtual-link-local-address fe80:2000:f000:20::2
```
10.

```
[edit interfaces ge-1/0/0 unit 0 family inet6]
user@host# set address 2001:2000:f000:20::1/64 vrrp-inet6-group 3 priority 250
```

Configuring multiple IPv4 and IPv6 owner groups

Step-by-Step Procedure

To configure multiple IPv4 and IPv6 owner groups:

1. Create an interface on the device

```
[edit]
user@host# edit interfaces ge-1/0/0 unit 0
```
2. Configure the family inet address and virtual address for the IPv4 owner group

```
[edit interfaces ge-1/0/0 unit 0]
user@host# set family inet address 10.0.0.1/24 vrrp-group 5 virtual-address 10.0.0.1
```
3. Set the priority of the IPv4 owner group to 255

```
[edit interfaces ge-1/0/0 unit 0]
set family inet address 10.0.0.1/24 vrrp-group 5 priority 255
```
4. Configure the inet6 address for the first IPv6 owner group

```
[edit interfaces ge-1/0/0 unit 0]
set family inet6 address 2001:4818:f000:20::1/64 vrrp-inet6-group 1
virtual-inet6-address 2001:4818:f000:20::1
```
5. Set the virtual link local address for the first IPv6 owner group

```
[edit interfaces ge-1/0/0 unit 0]
set family inet6 address 2001:4818:f000:20::1/64 vrrp-inet6-group 1
virtual-link-local-address fe80:4818:f000:20::1
```
6. Set the first IPv6 owner group's priority to 255

```
[edit interfaces ge-1/0/0 unit 0]
set family inet6 address 2001:4818:f000:20::1/64 vrrp-inet6-group 1 priority 255
```

7. Configure the inet6 address for the second IPv6 owner group


```
[edit interfaces ge-1/0/0 unit 0]
set family inet6 address 2001:1000:f000:20::1/64 vrrp-inet6-group 2
virtual-inet6-address 2001:1000:f000:20::1
```
8. Set the virtual link local address for the second IPv6 owner group


```
[edit interfaces ge-1/0/0 unit 0]
set family inet6 address 2001:1000:f000:20::1/64 vrrp-inet6-group 2
virtual-link-local-address fe80:1000:f000:20::1
```
9. Set the second IPv6 owner group's priority to 255


```
[edit interfaces ge-1/0/0 unit 0]
set family inet6 address 2001:1000:f000:20::1/64 vrrp-inet6-group 2 priority 255
```
10. Configure the inet6 address for the third IPv6 owner group


```
[edit interfaces ge-1/0/0 unit 0]
set family inet6 address 2001:2000:f000:20::1/64 vrrp-inet6-group 3
virtual-inet6-address 2001:2000:f000:20::2
```
11. Set the virtual link local address for the third IPv6 owner group


```
[edit interfaces ge-1/0/0 unit 0]
set family inet6 address 2001:2000:f000:20::1/64 vrrp-inet6-group 3
virtual-link-local-address fe80:2000:f000:20::2
```
12. Set the third IPv6 owner group's priority to 250


```
[edit interfaces ge-1/0/0 unit 0]
set family inet6 address 2001:2000:f000:20::1/64 vrrp-inet6-group 3 priority 250
```

Results

Multiple IPv4 owner groups

```
[edit interfaces]
ge-1/0/0
unit 0 {
  family inet {
    address 10.0.0.2/24 {
      vrrp-group 2 {
        virtual-address 10.0.0.4;
        accept-data;
      }
    }
    address 20.0.0.2/24 {
      vrrp-group 3 {
        virtual-address 20.0.0.2;
        priority 255;
      }
    }
    address 30.0.0.2/24 {
      vrrp-group 4 {
        virtual-address 30.0.0.2;
        priority 255;
      }
    }
  }
}
```

	<pre> } </pre>
Multiple IPv6 owner groups	<pre> [edit interfaces] ge-1/0/0 unit 0 { family inet6 { address 2001:4818:f000:20::1/64 { vrrp-inet6-group 1 { virtual-inet6-address 2001:4818:f000:20::1; virtual-link-local-address fe80:4818:f000:20::1; priority 255; } } address fe80:4818:f000:13::2/64; address 2001:1000:f000:20::1/64 { vrrp-inet6-group 2 { virtual-inet6-address 2001:1000:f000:20::1; virtual-link-local-address fe80:1000:f000:20::1; priority 255; } } address 2001:2000:f000:20::1/64 { vrrp-inet6-group 3 { virtual-inet6-address 2001:2000:f000:20::2; virtual-link-local-address fe80:2000:f000:20::2; priority 250; } } } } </pre>
Multiple IPv4 and IPv6 owner groups	<pre> [edit interfaces] ge-1/0/0 unit 0 { family inet { address 10.0.0.1/24 { vrrp-group 5 { virtual-address 10.0.0.1; priority 255; } } } family inet6 { address 2001:4818:f000:20::1/64 { vrrp-inet6-group 1 { virtual-inet6-address 2001:4818:f000:20::1; virtual-link-local-address fe80:4818:f000:20::1; priority 255; } } address 2001:1000:f000:20::1/64 { vrrp-inet6-group 2 { virtual-inet6-address 2001:1000:f000:20::1; virtual-link-local-address fe80:1000:f000:20::1; priority 255; } } } } </pre>

```

    }
  }
  address 2001:2000:f000:20::1/64 {
    vrrp-inet6-group 3 {
      virtual-inet6-address 2001:2000:f000:20::2;
      virtual-link-local-address fe80:2000:f000:20::2;
      priority 250;
    }
  }
}

```

Verification

To verify the configuration, run the **show interfaces ge-1/0/0** command, or use whichever name you assigned to the interface.

- Related Documentation**
- [Tracing VRRP Operations on page 187](#)
 - [Configuring Inheritance for a VRRP Group on page 172](#)

Tracing VRRP Operations

To trace VRRP operations, include the **traceoptions** statement at the **[edit protocols vrrp]** hierarchy level.

By default, VRRP logs the error, data carrier detect (DCD) configuration, and routing socket events in a file in the **/var/log** directory. By default, this file is named **/var/log/vrrpd**. The default file size is 1 megabyte (MB), and three files are created before the first one gets overwritten.

To change the configuration of the logging file, include the **traceoptions** statement at the **[edit protocols vrrp]** hierarchy level:

```

[edit protocols vrrp]
traceoptions {
  file filename <files number> <match regular-expression> <microsecond-stamp>
    <size size> <world-readable | no-world-readable>;
  flag flag;
  no-remote-trace;
}
flag flag;

```

You can specify the following VRRP tracing flags:

- **all**—Trace all VRRP operations.
- **database**—Trace all database changes.
- **general**—Trace all general events.
- **interfaces**—Trace all interface changes.
- **normal**—Trace all normal events.
- **packets**—Trace all packets sent and received.

- **state**—Trace all state transitions.
- **timer**—Trace all timer events.

**Related
Documentation**

- [Understanding VRRP on page 59](#)
- [VRRP Configuration Hierarchy on page 157](#)

Unified ISSU

- [Managing and Tracing BFD Sessions During Unified ISSU Procedures on page 189](#)

Managing and Tracing BFD Sessions During Unified ISSU Procedures

Bidirectional Forwarding Detection (BFD) sessions temporarily increase their detection and transmission timers during unified ISSU procedures. After the upgrade, these timers revert to the values in use before the unified ISSU started. The BFD process replicates the unified ISSU state and timer values to the backup Routing Engine for each session.

No additional configuration is necessary to enable unified ISSU for BFD. However, you can disable the BFD timer negotiation during the unified ISSU by including the **no-issu-timer-negotiation** statement at the **[edit protocols bfd]** hierarchy level:

```
[edit protocols bfd]
no-issu-timer-negotiation;
```

If you configure this statement, the BFD timers maintain their original values during unified ISSU.



CAUTION: The sessions might flap during unified ISSU or Routing Engine switchover, depending on the detection intervals.

For more information about BFD, see the Junos OS Routing Protocols Configuration Guide.

To configure unified ISSU trace options for BFD sessions, include the **issu** statement at the **[edit protocols bfd traceoptions flag]** hierarchy level.

```
[edit protocols]
bfd {
  traceoptions {
    flag issu;
  }
}
```

Related Documentation

- [Unified ISSU Concepts on page 67](#)
- [Unified ISSU Process on the TX Matrix Router on page 72](#)
- [Unified ISSU System Requirements on page 73](#)

- [Best Practices on page 259](#)
- [Before You Begin on page 259](#)
- [Performing a Unified ISSU on page 262](#)
- [Verifying a Unified ISSU on page 274](#)
- [Troubleshooting Unified ISSU Problems on page 279](#)

no-issu-timer-negotiation

Syntax	no-issu-timer-negotiation;
Hierarchy Level	[edit protocols bfd], [edit logical-systems <i>logical-system-name</i> protocols bfd], [edit routing-instances <i>routing-instance-name</i> protocols bfd]
Release Information	Statement introduced in Junos OS Release 9.1.
Description	Disable unified ISSU timer negotiation for Bidirectional Forwarding Detection (BFD) sessions.



.....

CAUTION: The sessions might flap during unified ISSU or Routing Engine switchover, depending on the detection intervals.

.....

Required Privilege	routing—To view this statement in the configuration.
Level	routing-control—To add this statement to the configuration.

- | | |
|------------------------------|--|
| Related Documentation | <ul style="list-style-type: none">• Managing and Tracing BFD Sessions During Unified ISSU Procedures on page 189• Junos OS Routing Protocols Configuration Guide. |
|------------------------------|--|

traceoptions (Protocols BFD)

Syntax	<pre>traceoptions { file <i>name</i> <size <i>size</i>> <files <i>number</i>> <world-readable no-world-readable>; flag <i>flag</i> <<i>flag-modifier</i>> <disable>; }</pre>
Hierarchy Level	[edit protocols bfd]
Release Information	Statement introduced before Junos OS Release 7.4. issu flag for BFD added in Junos OS Release 9.1.
Description	<p>Define tracing operations that track unified in-service software upgrade (ISSU) functionality in the router.</p> <p>To specify more than one tracing operation, include multiple flag statements.</p>
Default	If you do not include this statement, no global tracing operations are performed.
Options	<p>disable—(Optional) Disable the tracing operation. You can use this option to disable a single operation when you have defined a broad group of tracing operations, such as all.</p> <p>file <i>name</i>—Name of the file to receive the output of the tracing operation. Enclose the name within quotation marks. All files are placed in the directory /var/log. We recommend that you place global routing protocol tracing output in the file routing-log.</p> <p>files <i>number</i>—(Optional) Maximum number of trace files. When a trace file named <i>trace-file</i> reaches its maximum size, it is renamed <i>trace-file.0</i>, then <i>trace-file.1</i>, and so on, until the maximum number of trace files is reached. Then the oldest trace file is overwritten.</p> <p>Range: 2 through 1000 files Default: 2 files</p> <p>If you specify a maximum number of files, you also must specify a maximum file size with the size option.</p> <p>flag <i>flag</i>—Tracing operation to perform. There is only one unified ISSU tracing option:</p> <ul style="list-style-type: none"> issu—Trace BFD unified ISSU operations. <p>no-world-readable—Restrict users from reading the log file.</p> <p>size <i>size</i>—(Optional) Maximum size of each trace file, in kilobytes (KB), megabytes (MB), or gigabytes (GB). When a trace file named <i>trace-file</i> reaches this size, it is renamed <i>trace-file.0</i>. When the <i>trace-file</i> again reaches its maximum size, <i>trace-file.0</i> is renamed <i>trace-file.1</i> and <i>trace-file</i> is renamed <i>trace-file.0</i>. This renaming scheme continues until the maximum number of trace files is reached. Then the oldest trace file is overwritten.</p>

Syntax: *xk* to specify KB, *xm* to specify MB, or *xg* to specify GB

Range: 10 KB through the maximum file size supported on your system

Default: 128 KB

If you specify a maximum file size, you also must specify a maximum number of trace files with the **files** option.

world-readable—Allow users to read the log file.

Required Privilege Level	routing and trace—To view this statement in the configuration. routing-control and trace-control—To add this statement to the configuration.
---------------------------------	---

Related Documentation	<ul style="list-style-type: none">• Managing and Tracing BFD Sessions During Unified ISSU Procedures on page 189
------------------------------	--

PART 3

Administration

- [Routing Engine and Switching Control Board Redundancy on page 195](#)
- [Summary of Routing Engine and Switching Control Board Redundancy Statements on page 197](#)
- [Graceful Routing Engine Switchover on page 209](#)
- [Nonstop Active Routing on page 211](#)
- [Graceful Restart on page 213](#)
- [Summary of Graceful Restart Configuration Statements on page 217](#)
- [Summary of VRRP Configuration Statements on page 231](#)
- [Unified ISSU on page 259](#)

Routing Engine and Switching Control Board Redundancy

- [Copying a Configuration File from One Routing Engine to the Other on page 195](#)
- [Loading a Software Package from the Other Routing Engine on page 196](#)

Copying a Configuration File from One Routing Engine to the Other

You can use either the console port or the management Ethernet port to establish connectivity between the two Routing Engines. You can then copy or use FTP to transfer the configuration from the master to the backup, and load the file and commit it in the normal way.

To connect to the other Routing Engine using the management Ethernet port, issue the following command:

```
user@host> request routing-engine login (other-routing-engine | re0 | re1)
```

On a TX Matrix router, to make connections to the other Routing Engine using the management Ethernet port, issue the following command:

```
user@host> request routing-engine login (backup | lcc number | master |  
other-routing-engine | re0 | re1)
```

For more information about the **request routing-engine login** command, see the Junos OS Operational Mode Commands.

To copy a configuration file from one Routing Engine to the other, issue the **file copy** command:

```
user@host> file copy source destination
```

In this case, **source** is the name of the configuration file. These files are stored in the directory **/config**. The active configuration is **/config/juniper.conf**, and older configurations are in **/config/juniper.conf {1...9}**. The **destination** is a file on the other Routing Engine.

The following example copies a configuration file from Routing Engine 0 to Routing Engine 1:

```
user@host> file copy /config/juniper.conf re1:/var/tmp/copied-juniper.conf
```

The following example copies a configuration file from Routing Engine 0 to Routing Engine 1 on a TX Matrix router:

```
user@host> file copy /config/juniper.conf scc-re1:/var/tmp/copied-juniper.conf
```

To load the configuration file, enter the **load replace** command at the **[edit]** hierarchy level:

```
user@host> load replace /var/tmp/copied-juniper.conf
```



CAUTION: Make sure you change any IP addresses specified in the management Ethernet interface configuration on Routing Engine 0 to addresses appropriate for Routing Engine 1.

**Related
Documentation**

- [Understanding Routing Engine Redundancy on Juniper Networks Routers on page 11](#)
- [Switching Control Board Redundancy on page 16](#)
- [Loading a Software Package from the Other Routing Engine on page 196](#)

Loading a Software Package from the Other Routing Engine

You can load a package from the other Routing Engine onto the local Routing Engine using the existing **request system software add** *package-name* command:

```
user@host> request system software add re(0|1):/filename
```

In the **re** portion of the URL, specify the number of the other Routing Engine. In the **filename** portion of the URL, specify the path to the package. Packages are typically in the directory **/var/sw/pkg**.

**Related
Documentation**

- [Understanding Routing Engine Redundancy on Juniper Networks Routers on page 11](#)
- [Switching Control Board Redundancy on page 16](#)
- [Copying a Configuration File from One Routing Engine to the Other on page 195](#)

Summary of Routing Engine and Switching Control Board Redundancy Statements

cfeb

Syntax	<code>cfeb slot-number</code> (always preferred);
Hierarchy Level	[edit chassis redundancy]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	On M10i routers only, configure which Compact Forwarding Engine Board (CFEB) is the master and which is the backup.
Default	By default, the CFEB in slot 0 is the master and the CFEB in slot 1 is the backup.
Options	slot-number —Specify which slot is the master and which is the backup. always —Define this CFEB as the sole device. preferred —Define this CFEB as the preferred device of at least two.
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• Configuring CFEB Redundancy on the M10i Router on page 93

description (Chassis Redundancy)

Syntax	<code>description <i>description</i>;</code>
Hierarchy Level	[edit chassis redundancy feb redundancy-group <i>group-name</i>]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	Provide a description of the FEB redundancy group.
Options	<i>description</i> —Provide a description for the FEB redundancy group.
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• Configuring FEB Redundancy on the M120 Router on page 94

failover (Chassis)

Syntax	<pre>failover { on-disk-failure; on-loss-of-keepalives; }</pre>
Hierarchy Level	[edit chassis redundancy]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	Specify conditions on the master Routing Engine that cause the backup router to take mastership. The remaining statement are explained separately.
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• On Detection of a Hard Disk Error on the Master Routing Engine on page 90

failover (System Process)

Syntax	<code>failover (alternate-media other-routing-engine);</code>
Hierarchy Level	[edit system processes <i>process-name</i>]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	Configure the router to reboot if the software process fails four times within 30 seconds, and specify the software to use during the reboot.
Options	<p><i>process-name</i>—Junos OS process name. Some of the processes that support the failover statement are bootp, chassis-control, craft-control, ethernet-connectivity-fault-management, init, interface-control, neighbor-liveness, pfe, redundancy-interface-process, routing, and vrrp.</p> <p>alternate-media—Use the Junos OS image on alternate media during the reboot.</p> <p>other-routing-engine—On routers with dual Routing Engines, use the Junos OS image on the other Routing Engine during the reboot. That Routing Engine assumes mastership; in the usual configuration, the other Routing Engine is the designated backup Routing Engine.</p>
Required Privilege Level	<p>system—To view this statement in the configuration.</p> <p>system-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none">• When a Software Process Fails on page 92• processes

feb (Creating a Redundancy Group)

Syntax	<pre>feb { redundancy-group <i>group-name</i> { description <i>description</i>; feb <i>slot-number</i> (backup primary); no-auto-failover; } }</pre>
Hierarchy Level	[edit chassis redundancy]
Release Information	Statement introduced in Junos OS Release 8.2.
Description	On M120 routers only, configure a Forwarding Engine Board (FEB) redundancy group.
Options	The remaining statements are described separately.
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• Configuring FEB Redundancy on the M120 Router on page 94

feb (Assigning a FEB to a Redundancy Group)

Syntax	<pre>feb <i>slot-number</i> (backup primary);</pre>
Hierarchy Level	[edit chassis redundancy feb redundancy-group <i>group-name</i>]
Release Information	Statement introduced in Junos OS Release 8.2.
Description	On M120 routers only, configure a Forwarding Engine Board (FEB) as part of a FEB redundancy group.
Options	<p>slot-number—Slot number of the FEB. The range of values is from 0 to 5.</p> <p>backup—(Optional) For each redundancy group, you must configure exactly one backup FEB.</p> <p>primary—(Optional) For each redundancy group, you can optionally configure one primary FEB.</p>
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• Configuring FEB Redundancy on the M120 Router on page 94

keepalive-time

Syntax	<code>keepalive-time <i>seconds</i>;</code>
Hierarchy Level	[edit chassis redundancy]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	Configure the time period that must elapse before the backup router takes mastership when it detects loss of the keepalive signal.
Default	<p>The on-loss-of-keepalives statement at the [edit chassis redundancy failover] hierarchy level must be included for failover to occur.</p> <p>When the on-loss-of-keepalives statement is included and graceful Routing Engine switchover <i>is not</i> configured, failover occurs after 300 seconds (5 minutes).</p> <p>When the on-loss-of-keepalives statement is included and graceful Routing Engine switchover <i>is</i> configured, the keepalive signal is automatically enabled and the failover time is set to 2 seconds (4 seconds on M20 routers). You cannot manually reset the keepalive time.</p>
Options	seconds —Time before the backup router takes mastership when it detects loss of the keepalive signal. The range of values is 2 through 10,000.
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• On Detection of a Loss of Keepalive Signal from the Master Routing Engine on page 90• failover (Chassis) on page 198• on-loss-of-keepalives on page 203

no-auto-failover

Syntax	no-auto-failover;
Hierarchy Level	[edit chassis redundancy feb redundancy-group group-name]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	Disable automatic failover to a backup FEB when an active FEB in a redundancy group fails.
Default	Automatic failover is enabled by default.
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• Configuring FEB Redundancy on the M120 Router on page 94

on-disk-failure (Chassis Redundancy Failover)

Syntax	on-disk-failure;
Hierarchy Level	[edit chassis redundancy failover]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	Instruct the backup router to take mastership if it detects hard disk errors on the master Routing Engine.
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• On Detection of a Hard Disk Error on the Master Routing Engine on page 90

on-loss-of-keepalives

Syntax	on-loss-of-keepalives;
Hierarchy Level	[edit chassis redundancy failover]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	Instruct the backup router to take mastership if it detects a loss of keepalive signal from the master Routing Engine.
Default	<p>The on-loss-of-keepalives statement must be included at the [edit chassis redundancy failover] hierarchy level for failover to occur.</p> <p>When the on-loss-of-keepalives statement is included but graceful Routing Engine switchover <i>is not</i> configured, failover occurs after 300 seconds (5 minutes).</p> <p>When the on-loss-of-keepalives statement is included and graceful Routing Engine switchover <i>is</i> configured, the keepalive signal is automatically enabled and the failover time is set to 2 seconds (4 seconds on M20 routers) . The keepalive time is not configurable.</p>
Required Privilege Level	<p>interface—To view this statement in the configuration.</p> <p>interface-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none">• On Detection of a Loss of Keepalive Signal from the Master Routing Engine on page 90• keepalive-time on page 201

redundancy

Syntax	<pre> redundancy { cfeb slot (always preferred); failover { on-disk-failure; on-loss-of-keepalives; } feb { redundancy-group group-name { description description; feb slot-number (backup primary); no-auto-failover; } } graceful-switchover; keepalive-time seconds; routing-engine slot-number (backup disabled master); sfm slot-number (always preferred); ssb slot-number (always preferred); } </pre>
Hierarchy Level	[edit chassis]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	Configure redundancy options.
Options	The statements are explained separately.
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none"> • Chassis Redundancy Hierarchy on page 97 • Configuring Routing Engine Redundancy on page 89 • Configuring CFEB Redundancy on the M10i Router on page 93 • Configuring FEB Redundancy on the M120 Router on page 94 • Configuring SFM Redundancy on M40e and M160 Routers on page 96 • Configuring SSB Redundancy on the M20 Router on page 97

redundancy-group

Syntax	<pre>redundancy-group <i>group-name</i> { <i>description</i> <i>description</i>; feb <i>slot-number</i> (backup primary); no-auto-failover; }</pre>
Hierarchy Level	[edit chassis redundancy feb]
Release Information	Statement introduced in Junos OS Release 8.2.
Description	On M120 routers only, configure a Forwarding Engine Board (FEB) redundancy group.
Options	<p><i>group-name</i> is the unique name for the redundancy group. The maximum length is 39 alphanumeric characters.</p> <p>Other statements are explained separately.</p>
Required Privilege Level	<p>interface—To view this statement in the configuration.</p> <p>interface-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none">• Configuring FEB Redundancy on the M120 Router on page 94

routing-engine (Chassis Redundancy)

Syntax	<code>routing-engine <i>slot-number</i> (backup disabled master);</code>
Hierarchy Level	[edit chassis redundancy]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	Configure Routing Engine redundancy.
Default	By default, the Routing Engine in slot 0 is the master Routing Engine and the Routing Engine in slot 1 is the backup Routing Engine.
Options	<p><i>slot-number</i>—Specify the slot number (0 or 1).</p> <p>Set the function of the Routing Engine for the specified slot:</p> <ul style="list-style-type: none">• master—Routing Engine in the specified slot is the master.• backup—Routing Engine in the specified slot is the backup.• disabled—Routing Engine in the specified slot is disabled.
Required Privilege Level	<p>interface—To view this statement in the configuration.</p> <p>interface-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none">• Configuring Routing Engine Redundancy on page 89

sfm (Chassis Redundancy)

Syntax	<code>sfm slot-number (always preferred);</code>
Hierarchy Level	[edit chassis redundancy]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	On M40e and M160 routers, configure which Switching and Forwarding Module (SFM) is the master and which is the backup.
Default	By default, the SFM in slot 0 is the master and the SFM in slot 1 is the backup.
Options	<p>slot-number—Specify which slot is the master and which is the backup. On the M40e router, slot-number can be 0 or 1. On the M160 router, slot-number can be 0 through 3.</p> <p>always—Define this SFM as the sole device.</p> <p>preferred—Define this SFM as the preferred device of at least two.</p>
Required Privilege Level	<p>interface—To view this statement in the configuration.</p> <p>interface-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none">• Configuring SFM Redundancy on M40e and M160 Routers on page 96

ssb

Syntax	<code>ssb slot-number (always preferred);</code>
Hierarchy Level	[edit chassis redundancy]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	On M20 routers, configure which System and Switch Board (SSB) is the master and which is the backup.
Default	By default, the SSB in slot 0 is the master and the SSB in slot 1 is the backup.
Options	<p><i>slot-number</i>—Specify which slot is the master and which is the backup.</p> <p><i>always</i>—Define this SSB as the sole device.</p> <p><i>preferred</i>—Define this SSB as the preferred device of at least two.</p>
Required Privilege Level	<p>interface—To view this statement in the configuration.</p> <p>interface-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none">• Configuring SSB Redundancy on the M20 Router on page 97

Graceful Routing Engine Switchover

- [Resetting Local Statistics on page 209](#)

Resetting Local Statistics

When you enable graceful Routing Engine switchover, the master Routing Engine configuration is copied and loaded to the backup Routing Engine. User files, accounting information, and trace options information are not replicated to the backup Routing Engine.

When a graceful Routing Engine switchover occurs, local statistics such as process statistics and networking statistics are displayed as a cumulative value from the time the process first came online. Because processes on the master Routing Engine can start at different times from the processes on the backup Routing Engine, the statistics on the two Routing Engines for the same process might differ. After a graceful Routing Engine switchover, we recommend that you issue the **clear interface statistics (*interface-name* | all)** command to reset the cumulative values for local statistics. Forwarding statistics are not affected by graceful Routing Engine switchover.

For information about how to use the **clear** command to clear statistics and protocol database information, see the Junos OS Operational Mode Commands.



NOTE: The **clear firewall** command cannot be used to clear the Routing Engine filter counters on a backup Routing Engine that is enabled for graceful Routing Engine switchover.

Related Documentation

- [Understanding Graceful Routing Engine Switchover in the Junos OS on page 21](#)
- [Configuring Graceful Routing Engine Switchover on page 101](#)

CHAPTER 19

Nonstop Active Routing

- [Resetting Local Statistics on page 211](#)

Resetting Local Statistics

After a graceful Routing Engine switchover, we recommend that you issue the **clear interface statistics** (*interface-name* | all) command to reset the cumulative values for local statistics on the new master Routing Engine.

Related Documentation

- [Configuring Nonstop Active Routing on page 105](#)
- [Tracing Nonstop Active Routing Synchronization Events on page 107](#)

CHAPTER 20

Graceful Restart

- [Tracing Restart Signaling-Based Helper Mode Events for OSPF Graceful Restart on page 213](#)
- [Verifying Graceful Restart Operation on page 214](#)

Tracing Restart Signaling-Based Helper Mode Events for OSPF Graceful Restart

Junos OS provides a tracing option to log restart signaling-based helper mode events for OSPF graceful restart. To enable tracing for restart signaling-based helper mode events, include the **traceoptions flag restart-signaling** statement at the **[edit protocols ospf]** hierarchy level.

To enable tracing for restart signaling-based events:

1. Create a log file for saving the log.

```
[edit protocols ospf]  
user@host# set traceoptions file ospf-log
```

where *ospf-log* is the name of the log file.

2. Enable tracing for restart signaling-based helper mode events.

```
[edit protocols ospf]  
user@host# set traceoptions flag restart-signaling
```

3. Commit the configuration.

```
[edit protocols ospf]  
user@host# commit
```

The logs are saved to the *ospf-log* file in the */var/log* folder.

Viewing the Log File

To view the restart signaling-based events from the log file, type:

```
user@host> file show /var/log/ospf-log | match "restart signaling"
Jun 25 14:44:08.890216 OSPF Restart Signaling: Start helper mode for nbr ip
14.19.3.2 id 10.10.10.1
Jun 25 14:44:11.358636 OSPF restart signaling: Received DBD with R bit set from
nbr ip=14.19.3.2 id=10.10.10.1. Start oob-resync.
Jun 25 14:44:11.380198 OSPF restart signaling: Received DBD with LR bit on from
nbr ip=14.19.3.2 id=10.10.10.1. Save its oob-resync capability 1
Jun 25 14:44:11.467200 OSPF restart signaling: nbr fsm for nbr ip=14.19.3.2
id=10.10.10.1 moving to state Full. Reset oob-resync parameters.
```

Related Documentation

- [Understanding Restart Signaling-Based Helper Mode Support for OSPF Graceful Restart on page 55](#)
- [Example: Managing Helper Modes for OSPF Graceful Restart on page 154](#)
- [helper-disable \(OSPF\)](#)

Verifying Graceful Restart Operation

This topic contains the following sections:

- [Graceful Restart Operational Mode Commands on page 214](#)
- [Verifying BGP Graceful Restart on page 215](#)
- [Verifying IS-IS and OSPF Graceful Restart on page 215](#)
- [Verifying CCC and TCC Graceful Restart on page 216](#)

Graceful Restart Operational Mode Commands

To verify proper operation of graceful restart, use the following commands:

- **show bgp neighbor** (for BGP graceful restart)
- **show log** (for IS-IS and OSPF/OSPFv3 graceful restart)
- **show (ospf | ospfv3) overview** (for OSPF/OSPFv3 graceful restart)
- **show rsvp neighbor detail** (for RSVP graceful restart—helper router)
- **show rsvp version** (for RSVP graceful restart—restarting router)
- **show ldp session detail** (for LDP graceful restart)
- **show connections** (for CCC and TCC graceful restart)
- **show route instance detail** (for Layer 3 VPN graceful restart and for any protocols using graceful restart in a routing instance)
- **show route protocol l2vpn** (for Layer 2 VPN graceful restart)

For more information about these commands and a description of their output fields, see the Junos OS Operational Mode Commands.

Verifying BGP Graceful Restart

To view graceful restart information for BGP sessions, use the **show bgp neighbor** command:

```
user@PE1> show bgp neighbor 192.255.10.1
Peer: 192.255.10.1+179 AS 64595 Local: 192.255.5.1+1106 AS 64595
  Type: Internal    State: Established    Flags: <>
  Last State: OpenConfirm    Last Event: RecvKeepAlive
  Last Error: None
  Export: [ static ]
  Options:<Preference LocalAddress HoldTime GracefulRestart Damping PeerAS Refresh>

  Local Address: 192.255.5.1 Holdtime: 90 Preference: 170
  IPsec SA Name: hope
  Number of flaps: 0
  Peer ID: 192.255.10.1    Local ID: 192.255.5.1    Active Holdtime: 90
  Keepalive Interval: 30
  NLRI for restart configured on peer: inet-unicast
  NLRI advertised by peer: inet-unicast
  NLRI for this session: inet-unicast
  Peer supports Refresh capability (2)
  Restart time configured on the peer: 180
  Stale routes from peer are kept for: 180
  Restart time requested by this peer: 300
  NLRI that peer supports restart for: inet-unicast
  NLRI that peer saved forwarding for: inet-unicast
  NLRI that restart is negotiated for: inet-unicast
  NLRI of received end-of-rib markers: inet-unicast
  NLRI of all end-of-rib markers sent: inet-unicast
  Table inet.0 Bit: 10000
  RIB State: restart is complete
  Send state: in sync
  Active prefixes: 0
  Received prefixes: 0
  Suppressed due to damping: 0
  Last traffic (seconds): Received 19    Sent 19    Checked 19
  Input messages: Total 2    Updates 1    Refreshes 0    Octets 42
  Output messages: Total 3    Updates 0    Refreshes 0    Octets 116
  Output Queue[0]: 0
```

Verifying IS-IS and OSPF Graceful Restart

To view graceful restart information for IS-IS and OSPF, configure traceoptions (see [“Tracking Graceful Restart Events” on page 124](#)).

Here is the output of a traceoptions log from an OSPF restarting router:

```
Oct 8 05:20:12 Restart mode - sending grace lsas
Oct 8 05:20:12 Restart mode - estimated restart duration timer triggered
Oct 8 05:20:13 Restart mode - Sending more grace lsas
```

Here is the output of a traceoptions log from an OSPF helper router:

```
Oct 8 05:20:14 Helper mode for neighbor 192.255.5.1
Oct 8 05:20:14 Received multiple grace lsa from 192.255.5.1
```

Verifying CCC and TCC Graceful Restart

To view graceful restart information for CCC and TCC connections, use the **show connections** command. The following example assumes four remote interface CCC connections between CE1 and CE2:

```
user@PE1> show connections
CCC and TCC connections [Link Monitoring On]
Legend for status (St)
UN -- uninitialized
NP -- not present
WE -- wrong encapsulation
DS -- disabled
Dn -- down
-> -- only outbound conn is up
<- -- only inbound conn is up
Up -- operational
RmtDn -- remote CCC down
Restart -- restarting

Legend for connection types
if-sw: interface switching
rmt-if: remote interface switching
lsp-sw: LSP switching

Legend for circuit types
intf -- interface
tlsp -- transmit LSP
rlsp -- receive LSP
```

CCC Graceful restart : Restarting

Connection/Circuit	Type	St	Time last up	# Up trans
CE1-CE2-0	rmt-if	Restart	-----	0
fe-1/1/0.0	intf	Up		
PE1-PE2-0	tlsp	Up		
PE2-PE1-0	rlsp	Up		
CE1-CE2-1	rmt-if	Restart	-----	0
fe-1/1/0.1	intf	Up		
PE1-PE2-1	tlsp	Up		
PE2-PE1-1	rlsp	Up		
CE1-CE2-2	rmt-if	Restart	-----	0
fe-1/1/0.2	intf	Up		
PE1-PE2-2	tlsp	Up		
PE2-PE1-2	rlsp	Up		
CE1-CE2-3	rmt-if	Restart	-----	0
fe-1/1/0.3	intf	Up		
PE1-PE2-3	tlsp	Up		
PE2-PE1-3	rlsp	Up		

- Related Documentation**
- [Graceful Restart Concepts on page 49](#)
 - [Configuring Graceful Restart for QFabric Systems](#)

Summary of Graceful Restart Configuration Statements

disable

Syntax	disable;
Hierarchy Level	<p>[edit logical-systems <i>logical-system-name</i> protocols (bgp isis ldp ospf ospf3 pim rip ripng rsvp) graceful-restart],</p> <p>[edit logical-systems <i>logical-system-name</i> routing-instances <i>routing-instance-name</i> protocols (bgp ldp ospf ospf3 pim) graceful-restart],</p> <p>[edit protocols (bgp isis isis ospf ospf3 ldp pim rip ripng rsvp) graceful-restart],</p> <p>[edit protocols bgp group <i>group-name</i> graceful-restart],</p> <p>[edit protocols bgp group <i>group-name</i> neighbor <i>ip-address</i> graceful-restart],</p> <p>[edit routing-instances <i>routing-instance-name</i> protocols (bgp ldp ospf ospf3 pim) graceful-restart],</p> <p>[edit routing-instances <i>routing-instance-name</i> routing-options graceful-restart],</p> <p>[edit routing-options graceful-restart]</p>
Release Information	<p>Statement introduced before Junos OS Release 7.4.</p> <p>Statement introduced in Junos OS Release 12.1 for the QFX Series.</p> <p>Statement introduced in Junos OS Release 12.3 for ACX Series routers.</p>
Description	Disable graceful restart.
Required Privilege Level	<p>routing—To view this statement in the configuration.</p> <p>routing-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none"> • Enabling Graceful Restart on page 117 • Configuring Routing Protocols Graceful Restart on page 118 • Configuring Graceful Restart for MPLS-Related Protocols on page 124 • Configuring VPN Graceful Restart on page 126 • Configuring Logical System Graceful Restart on page 127 • Graceful Restart Configuration Statements on page 129 • Configuring Graceful Restart for QFabric Systems

graceful-restart (Enabling Globally)

Syntax	<pre>graceful-restart { disable; helper-disable; maximum-helper-recovery-time <i>seconds</i>; maximum-helper-restart-time <i>seconds</i>; notify-duration <i>seconds</i>; recovery-time <i>seconds</i>; restart-duration <i>seconds</i>; stale-routes-time <i>seconds</i>; }</pre>
Hierarchy Level	[edit logical-systems <i>logical-system-name</i> routing-options], [edit logical-systems <i>logical-system-name</i> routing-instances <i>routing-instance-name</i> routing-options], [edit routing-options], [edit routing-instances <i>routing-instance-name</i> routing-options]
Release Information	Statement introduced before Junos OS Release 7.4. Statement introduced in Junos OS Release 9.0 for EX Series switches. Statement introduced in Junos OS Release 12.1 for the QFX Series.
Description	<p>Configure graceful restart globally to enable the feature. You cannot enable graceful restart for specific protocols unless graceful restart is also enabled globally.</p> <p>For VPNs, the graceful-restart statement allows a router whose VPN control plane is undergoing a restart to continue to forward traffic while recovering its state from neighboring routers.</p> <p>For BGP, if you configure graceful restart after a BGP session has been established, the BGP session restarts and the peers negotiate graceful restart capabilities.</p>
Default	Graceful restart is disabled by default.
Options	The remaining statements are explained separately.
Required Privilege Level	routing—To view this statement in the configuration. routing-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• Enabling Graceful Restart on page 117• Configuring Routing Protocols Graceful Restart on page 118• Configuring Graceful Restart for MPLS-Related Protocols on page 124• Configuring VPN Graceful Restart on page 126• Configuring Logical System Graceful Restart on page 127• Graceful Restart Configuration Statements on page 129• Configuring Graceful Restart for QFabric Systems

helper-disable (Multiple Protocols)

Syntax	helper-disable;
Hierarchy Level	[edit logical-systems <i>logical-system-name</i> protocols (isis ldp ospf ospf3 rsvp) graceful-restart], [edit logical-systems <i>logical-system-name</i> routing-instances <i>routing-instance-name</i> protocols (ldp ospf ospf3) graceful-restart], [edit protocols (isis ldp ospf ospf3 rsvp) graceful-restart], [edit routing-instances <i>routing-instance-name</i> protocols (ldp ospf ospf3) graceful-restart]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	Disable helper mode for graceful restart. When helper mode is disabled, a router cannot help a neighboring router that is attempting to restart.
Default	Helper mode is enabled by default for these supported protocols: IS-IS, LDP, OSPF/OSPFv3, and RSVP.
Required Privilege Level	routing—To view this statement in the configuration. routing-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none"> • Configuring Routing Protocols Graceful Restart on page 118 • Configuring Graceful Restart for MPLS-Related Protocols on page 124

maximum-helper-recovery-time

Syntax	maximum-helper-recovery-time <i>seconds</i> ;
Hierarchy Level	[edit protocols rsvp graceful-restart], [edit logical-systems <i>logical-system-name</i> protocols rsvp graceful-restart]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	Specify the length of time the router retains the state of its Resource Reservation Protocol (RSVP) neighbors while they undergo a graceful restart.
Options	<p><i>seconds</i>—Length of time that the router retains the state of its Resource Reservation Protocol (RSVP) neighbors while they undergo a graceful restart.</p> <p>Range: 1 through 3600</p> <p>Default: 180</p>
Required Privilege Level	routing—To view this statement in the configuration. routing-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none"> • Configuring Graceful Restart Options for RSVP, CCC, and TCC on page 125 • maximum-helper-restart-time (RSVP) on page 220

maximum-helper-restart-time (RSVP)

Syntax	maximum-helper-restart-time <i>seconds</i> ;
Hierarchy Level	[edit protocols rsvp graceful-restart], [edit logical-systems <i>logical-system-name</i> protocols rsvp graceful-restart]
Release Information	Statement introduced in Junos OS Release 8.3.
Description	Specify the length of time the router waits after it discovers that a neighboring router has gone down before it declares the neighbor down. This value is applied to all RSVP neighbor routers and should be based on the time that the slowest RSVP neighbor requires for restart.
Options	seconds —The time the router waits after it discovers that a neighboring router has gone down before it declares the neighbor down. Range: 1 through 1800 Default: 60
Required Privilege Level	routing—To view this statement in the configuration. routing-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• Configuring Graceful Restart Options for RSVP, CCC, and TCC on page 125• maximum-helper-recovery-time on page 219

maximum-neighbor-reconnect-time

Syntax	maximum-neighbor-reconnect-time <i>seconds</i> ;
Hierarchy Level	[edit protocols ldp graceful-restart], [edit logical-systems <i>logical-system-name</i> protocols ldp graceful-restart], [edit routing-instances <i>routing-instance-name</i> protocols ldp graceful-restart]
Release Information	Statement introduced in Junos OS Release 9.1.
Description	Specify the maximum length of time allowed to reestablish connection from a restarting neighbor.
Options	seconds —Maximum time allowed for reconnection. Range: 30 through 300
Required Privilege Level	routing—To view this statement in the configuration. routing-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• Configuring Graceful Restart Options for LDP on page 125

maximum-neighbor-recovery-time

Syntax	<code>maximum-neighbor-recovery-time seconds;</code>
Hierarchy Level	[edit logical-systems <i>logical-system-name</i> protocols ldp graceful-restart], [edit logical-systems <i>logical-system-name</i> routing-instances <i>routing-instance-name</i> protocols ldp graceful-restart], [edit protocols ldp graceful-restart], [edit routing-instances <i>routing-instance-name</i> protocols ldp graceful-restart]
Release Information	Statement introduced before Junos OS Release 7.4. Statement changed from maximum-recovery-time to maximum-neighbor-recovery-time in Junos OS Release 9.1.
Description	Specify the maximum amount of time to wait before giving up an attempt to gracefully restart.
Options	seconds —Configure the maximum recovery time, in seconds. Range: 120 through 1800 seconds Default: 140 seconds
Required Privilege Level	routing—To view this statement in the configuration. routing-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• Configuring LDP Graceful Restart• Configuring Graceful Restart Options for LDP on page 125• no-strict-lsa-checking on page 222• recovery-time on page 225

no-strict-lsa-checking

Syntax	no-strict-lsa-checking;
Hierarchy Level	[edit protocols (ospf ospf3) graceful-restart]
Release Information	Statement introduced in Junos OS Release 8.5. Statement introduced in Junos OS Release 12.1 for the QFX Series.
Description	Disable strict OSPF link-state advertisement (LSA) checking to prevent the termination of graceful restart by a helping router.
Default	By default, LSA checking is enabled.
Required Privilege Level	routing—To view this statement in the configuration. routing-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• Configuring Graceful Restart Options for OSPF and OSPFv3 on page 121• Configuring Graceful Restart for QFabric Systems• maximum-neighbor-recovery-time on page 221• recovery-time on page 225

notify-duration

Syntax	<code>notify-duration <i>seconds</i>;</code>
Hierarchy Level	<p>[edit protocols (ospf ospf3) graceful-restart],</p> <p>[edit logical-systems <i>logical-system-name</i> protocols (ospf ospf3) graceful-restart],</p> <p>[edit logical-systems <i>logical-system-name</i> routing-instances <i>instance-name</i> protocols (ospf ospf3) graceful-restart],</p> <p>[edit routing-instances <i>instance-name</i> protocols (ospf ospf3) graceful-restart]</p>
Release Information	<p>Statement introduced in Junos OS Release 8.3.</p> <p>Statement introduced in Junos OS Release 12.1 for the QFX Series.</p>
Description	Specify the length of time the router notifies helper OSPF routers that it has completed graceful restart.
Options	<p><i>seconds</i>—Length of time in the router notifies helper OSPF routers that it has completed graceful restart.</p> <p>Range: 1 through 3600</p> <p>Default: 30</p>
Required Privilege Level	<p>routing—To view this statement in the configuration.</p> <p>routing-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none"> • Configuring Graceful Restart Options for OSPF and OSPFv3 on page 121 • Configuring Graceful Restart for QFabric Systems • restart-duration on page 226

reconnect-time

Syntax	<code>reconnect-time <i>seconds</i>;</code>
Hierarchy Level	[edit logical-systems <i>logical-system-name</i> protocols ldp graceful-restart], [edit protocols ldp graceful-restart], [edit routing-instances <i>routing-instance-name</i> protocols ldp graceful-restart]
Release Information	Statement introduced in Junos OS Release 9.1.
Description	Specify the length of time required to reestablish a Label Distribution Protocol (LDP) session after graceful restart.
Options	<i>seconds</i> —Time required for reconnection. Range: 30 through 300 Default: 60 seconds
Required Privilege Level	routing—To view this statement in the configuration. routing-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">Configuring LDP Graceful Restart on LDP Configuration GuideConfiguring Graceful Restart Options for LDP on page 125

recovery-time

Syntax	<code>recovery-time seconds;</code>
Hierarchy Level	[edit logical-systems <i>logical-system-name</i> protocols ldp graceful-restart], [edit logical-systems <i>logical-system-name</i> routing-instances <i>routing-instance-name</i> protocols ldp graceful-restart], [edit protocols ldp graceful-restart], [edit routing-instances <i>routing-instance-name</i> protocols ldp graceful-restart]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	Specify the length of time a router waits for Label Distribution Protocol (LDP) neighbors to assist it with a graceful restart.
Options	seconds —Time the router waits for LDP to restart gracefully. Range: 120 through 1800 Default: 160
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none"> • Configuring Graceful Restart Options for LDP on page 125 • maximum-neighbor-recovery-time on page 221 • no-strict-lsa-checking on page 222

restart-duration

Syntax	<code>restart-duration <i>seconds</i>;</code>
Hierarchy Level	<p>[edit logical-systems <i>logical-system-name</i> protocols (isis ospf ospf3 pim) graceful-restart],</p> <p>[edit logical-systems <i>logical-system-name</i> routing-instances <i>routing-instance-name</i> protocols (ospf ospf3 pim) graceful-restart],</p> <p>[edit protocols (esis isis ospf ospf3 pim) graceful-restart],</p> <p>[edit routing-instances <i>routing-instance-name</i> protocols (ospf ospf3 pim) graceful-restart],</p> <p>[edit routing-options graceful-restart]</p>
Release Information	<p>Statement introduced before Junos OS Release 7.4.</p> <p>Statement introduced in Junos OS Release 12.1 for the QFX Series.</p>
Description	<p>Configure the grace period for graceful restart globally.</p> <p>Additionally, you can individually configure the duration of the graceful restart period for the End System-to-Intermediate System (ES-IS), Intermediate System-to-Intermediate System (IS-IS), Open Shortest Path First (OSPF), and OSPFv3 protocols and for Protocol Independent Multicast (PIM) sparse mode.</p>
Options	<p><i>seconds</i>—Time for the graceful restart period.</p> <p>Range:</p> <p>The range of values varies according to whether the graceful restart period is being set globally or for a particular protocol:</p> <ul style="list-style-type: none"> • [edit routing-options graceful-restart] (global setting)—120 through 900 • ES-IS—30 through 300 • IS-IS—30 through 300 • OSPF/OSPFv3—1 through 3600 • PIM—30 through 300 <p>Default:</p> <p>The default value varies according to whether the graceful restart period is being set globally or for a particular protocol:</p> <ul style="list-style-type: none"> • [edit routing-options graceful-restart] (global setting)—300 • ES-IS—180 • IS-IS—210 • OSPF/OSPFv3—180 • PIM—60
Required Privilege Level	<p>routing—To view this statement in the configuration.</p> <p>routing-control—To add this statement to the configuration.</p>

- Related Documentation**
- [Enabling Graceful Restart on page 117](#)
 - [Configuring Routing Protocols Graceful Restart on page 118](#)
 - [Configuring Graceful Restart for MPLS-Related Protocols on page 124](#)
 - [Configuring VPN Graceful Restart on page 126](#)
 - [Configuring Graceful Restart for VPNs](#)
 - [Configuring Logical System Graceful Restart on page 127](#)
 - [Graceful Restart Configuration Statements on page 129](#)
 - [Configuring Graceful Restart for QFabric Systems](#)

restart-time (BGP Graceful Restart)

Syntax	<code>restart-time <i>seconds</i>;</code>
Hierarchy Level	<p>[edit protocols (bgp rip ripng) graceful-restart],</p> <p>[edit logical-systems <i>logical-system-name</i> protocols (bgp rip ripng) graceful-restart (Enabling Globally)],</p> <p>[edit logical-systems <i>logical-system-name</i> routing-instances <i>routing-instance-name</i> protocols bgp graceful-restart],</p> <p>[edit routing-instances <i>routing-instance-name</i> protocols bgp graceful-restart]</p>
Release Information	<p>Statement introduced in Junos OS Release 8.3.</p> <p>Statement introduced in Junos OS Release 9.0 for EX Series switches.</p> <p>Statement introduced in Junos OS Release 12.1 for the QFX Series.</p>
Description	Configure the duration of the BGP, RIP, or next-generation RIP (RIPng) graceful restart period.
Options	<p><i>seconds</i>—Length of time for the graceful restart period.</p> <p>Range: 1 through 600 seconds</p> <p>Default: Varies by protocol:</p> <ul style="list-style-type: none"> • BGP—120 seconds • RIP and RIPng—60 seconds
Required Privilege Level	<p>routing—To view this statement in the configuration.</p> <p>routing-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none"> • Configuring Graceful Restart Options for BGP on page 119 • Configuring Graceful Restart Options for RIP and RIPng on page 122 • Configuring Graceful Restart for QFabric Systems • stale-routes-time on page 228

stale-routes-time

Syntax	<code>stale-routes-time seconds</code> ;
Hierarchy Level	[edit logical-systems <i>logical-routing-name</i> protocols bgp graceful-restart], [edit logical-systems <i>logical-routing-name</i> routing-instances <i>routing-instance-name</i> protocols bgp graceful-restart], [edit protocols bgp graceful-restart], [edit routing-instances <i>routing-instance-name</i> protocols bgp graceful-restart]
Release Information	Statement introduced in Junos OS Release 8.3. Statement introduced in Junos OS Release 9.0 for EX Series switches. Statement introduced in Junos OS Release 12.1 for the QFX Series.
Description	Specify the maximum time that stale routes are kept during a restart. The stale-routes-time statement allows you to set the length of time the routing device waits to receive messages from restarting neighbors before declaring them down.
Options	seconds —Time the router waits to receive messages from restarting neighbors before declaring them down. Range: 1 through 600 seconds Default: 300 seconds
Required Privilege Level	routing—To view this statement in the configuration. routing-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• Configuring Graceful Restart Options for BGP on page 119• Configuring Graceful Restart for QFabric Systems• restart-time (BGP Graceful Restart) on page 227

traceoptions (Protocols)

Syntax	<pre>traceoptions { file <i>name</i> <size <i>size</i>> <files <i>number</i>> <world-readable no-world-readable>; flag <i>flag</i> <flag-modifier> <disable>; }</pre>
Hierarchy Level	[edit protocols isis], [edit protocols (ospf ospf3)]
Release Information	Statement introduced before Junos OS Release 7.4. graceful-restart flag for IS-IS and OSPF/OSPFv3 added in Junos OS Release 8.4.
Description	<p>Define tracing operations that graceful restart functionality in the router.</p> <p>To specify more than one tracing operation, include multiple flag statements.</p>
Default	If you do not include this statement, no global tracing operations are performed.
Options	<p>disable—(Optional) Disable the tracing operation. You can use this option to disable a single operation when you have defined a broad group of tracing operations, such as all.</p> <p>file <i>name</i>—Name of the file to receive the output of the tracing operation. Enclose the name within quotation marks. All files are placed in the directory /var/log. We recommend that you place global routing protocol tracing output in the file routing-log.</p> <p>files <i>number</i>—(Optional) Maximum number of trace files. When a trace file named trace-file reaches its maximum size, it is renamed trace-file.0, then trace-file.1, and so on, until the maximum number of trace files is reached. Then the oldest trace file is overwritten.</p> <p>Range: 2 through 1000 files Default: 2 files</p> <p>If you specify a maximum number of files, you also must specify a maximum file size with the size option.</p> <p>flag <i>flag</i>—Tracing operation to perform. To specify more than one tracing operation, include multiple flag statements. The nonstop active routing tracing option is:</p> <ul style="list-style-type: none"> graceful-restart—Tracing operations for nonstop active routing <p>no-world-readable—Restrict users from reading the log file.</p> <p>size <i>size</i>—(Optional) Maximum size of each trace file, in kilobytes (KB), megabytes (MB), or gigabytes (GB). When a trace file named trace-file reaches this size, it is renamed trace-file.0. When the trace-file again reaches its maximum size, trace-file.0 is renamed trace-file.1 and trace-file is renamed trace-file.0. This renaming scheme continues</p>

until the maximum number of trace files is reached. Then the oldest trace file is overwritten.

Syntax: *xk* to specify KB, *xm* to specify MB, or *xg* to specify GB

Range: 10 KB through the maximum file size supported on your system

Default: 128 KB

If you specify a maximum file size, you also must specify a maximum number of trace files with the **files** option.


world-readable—Allow users to read the log file.

Required Privilege Level	routing and trace—To view this statement in the configuration.
	routing-control and trace-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• Tracking Graceful Restart Events on page 124


CHAPTER 22

Summary of VRRP Configuration Statements

accept-data

Syntax	(accept-data no-accept-data);
Hierarchy Level	<p>[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> <i>vrrp-group group-id</i>],</p> <p>[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> <i>vrrp-inet6-group group-id</i>],</p> <p>[edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> <i>vrrp-group group-id</i>],</p> <p>[edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> <i>vrrp-inet6-group group-id</i>]</p>
Release Information	<p>Statement introduced before Junos OS Release 7.4.</p> <p>Statement introduced in Junos OS 11.3 for the QFX Series.</p>
Description	<p>In a Virtual Router Redundancy Protocol (VRRP) configuration, determine whether or not a router that is acting as the master router accepts all packets destined for the virtual IP address.</p> <ul style="list-style-type: none"> • accept-data—Enable the master router to accept all packets destined for the virtual IP address. • no-accept-data—Prevent the master router from accepting packets other than the ARP packets destined for the virtual IP address.
Default	<p>If the router acting as the master router is the IP address owner or has its priority set to 255, the master router, by default, responds to all packets sent to the virtual IP address. However, if the router acting as the master router does not own the IP address or has its priority set to a value less than 255, the master router responds only to ARP requests.</p>
<div>  <p>NOTE:</p> <ul style="list-style-type: none"> • If you want to restrict the incoming IP packets to ICMP packets only, you must configure firewall filters to accept only ICMP packets. • If you include the accept-data statement, your routing platform configuration does not comply with RFC 3768 (see section 6.4.3 of RFC 3768, <i>Virtual Router Redundancy Protocol (VRRP)</i>). </div>	
Required Privilege Level	<p>interface—To view this statement in the configuration.</p> <p>interface-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none"> • Configuring an Interface to Accept Packets Destined for the Virtual IP Address on page 168


advertise-interval

Syntax	<code>advertise-interval seconds;</code>
Hierarchy Level	[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> <i>vrrp-group group-id</i>], [edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> <i>vrrp-group group-id</i>]
Release Information	Statement introduced before Junos OS Release 7.4. Statement introduced in Junos OS 11.3 for the QFX Series.
Description	Configure the interval between Virtual Router Redundancy Protocol (VRRP) IPv4 advertisement packets. All routers in the VRRP group must use the same advertisement interval.
<div>  <p>NOTE: When VRRPv3 is enabled, the <code>advertise-interval</code> statement cannot be used to configure advertisement intervals. Instead, use the <code>fast-interval</code> statement to configure advertisement intervals.</p> </div>	
Options	<i>seconds</i> —Interval between advertisement packets. Range: 1 through 255 seconds Default: 1 second
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none"> • Configuring the Advertisement Interval for the VRRP Master Router on page 163 • fast-interval on page 239 • inet6-advertise-interval on page 242 • version-3 on page 253

asymmetric-hold-time

Syntax	asymmetric-hold-time;
Hierarchy Level	[edit protocols vrrp]
Release Information	Statement introduced in Junos OS Release 9.5.
Description	Enable the VRRP master router to switch over to the backup router immediately, without waiting for the priority hold time to expire, when a route goes down. However, when the route comes back online, the backup router that is acting as the master waits for the priority hold time to expire before switching the mastership back to the original master VRRP router.
Default	asymmetric-hold-time is disabled.
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• Configuring Asymmetric Hold Time for VRRP Routers on page 167

authentication-key

Syntax	<code>authentication-key key;</code>
Hierarchy Level	<p>[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> vrrp-group <i>group-id</i>],</p> <p>[edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> vrrp-group <i>group-id</i>]</p>
Release Information	<p>Statement introduced before Junos OS Release 7.4.</p> <p>Statement introduced in Junos OS 11.3 for the QFX Series.</p>
Description	<p>Configure a Virtual Router Redundancy Protocol (VRRP) IPv4 authentication key. You also must specify a VRRP authentication scheme by including the authentication-type statement.</p> <p>All routers in the VRRP group must use the same authentication scheme and password.</p>
	<div>  <p>NOTE: When VRRPv3 is enabled, the authentication-type and authentication-key statements cannot be configured for any VRRP groups.</p> </div>
Options	<p>key—Authentication password. For simple authentication, it can be 1 through 8 characters long. For Message Digest 5 (MD5) authentication, it can be 1 through 16 characters long. If you include spaces, enclose all characters in quotation marks (" ").</p>
Required Privilege Level	<p>interface—To view this statement in the configuration.</p> <p>interface-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none"> • Configuring VRRP Authentication (IPv4 Only) on page 162 • Configuring VRRP Authentication (IPv4 Only) • authentication-type on page 236 • version-3 on page 253

authentication-type

Syntax	<code>authentication-type <i>authentication</i>;</code>
Hierarchy Level	[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> <i>vrrp-group group-id</i>], [edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> <i>vrrp-group group-id</i>]
Release Information	Statement introduced before Junos OS Release 7.4. Statement introduced in Junos OS 11.3 for the QFX Series.
Description	Enable Virtual Router Redundancy Protocol (VRRP) IPv4 authentication and specify the authentication scheme for the VRRP group. If you enable authentication, you must specify a password by including the authentication-key statement. All routers in the VRRP group must use the same authentication scheme and password.



NOTE: When VRRPv3 is enabled, the **authentication-type** and **authentication-key** statements cannot be configured for any VRRP groups.

Options	<p><i>authentication</i>—Authentication scheme:</p> <ul style="list-style-type: none"> simple—Use a simple password. The password is included in the transmitted packet, so this method of authentication is relatively insecure. md5—Use the MD5 algorithm to create an encoded checksum of the packet. The encoded checksum is included in the transmitted packet. The receiving routing platform uses the authentication key to verify the packet, discarding it if the digest does not match. This algorithm provides a more secure authentication scheme. <p>Default: none (no authentication is performed).</p>
Required Privilege Level	<p>interface—To view this statement in the configuration.</p> <p>interface-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none"> • Configuring VRRP Authentication (IPv4 Only) on page 162 • Configuring VRRP Authentication (IPv4 Only) • authentication-key on page 235 • version-3 on page 253


bandwidth-threshold

Syntax	<code>bandwidth-threshold <i>bits-per-second</i> priority-cost <i>priority</i>;</code>
Hierarchy Level	<p>[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> <code>vrrp-group <i>group-id</i> track interface <i>interface-name</i></code>],</p> <p>[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> <code>vrrp-inet6-group <i>group-id</i> track interface <i>interface-name</i></code>],</p> <p>[edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> <code>vrrp-group <i>group-id</i> track interface <i>interface-name</i></code>],</p> <p>[edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> <code>vrrp-inet6-group <i>group-id</i> track interface <i>interface-name</i></code>]</p>
Release Information	<p>Statement introduced in Junos OS Release 8.1.</p> <p>Statement introduced in Junos OS 11.3 for the QFX Series.</p>
Description	Specify the bandwidth threshold for Virtual Router Redundancy Protocol (VRRP) logical interface tracking.
Options	<p><i>bits-per-second</i>—Bandwidth threshold for the tracked interface. When the bandwidth of the tracked interface drops below the specified value, the VRRP group uses the bandwidth threshold priority cost value. You can include up to five bandwidth threshold statements for each interface you track.</p> <p>Range: 1 through 10000000000000 bits per second</p> <p><i>priority-cost <i>priority</i></i>—The value subtracted from the configured VRRP priority when the tracked interface or route is down to force a new master router election. The sum of all the costs for all interfaces or routes that are tracked must be less than or equal to the configured priority of the VRRP group.</p>
Required Privilege Level	<p>interface—To view this statement in the configuration.</p> <p>interface-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none"> • Configuring a Logical Interface to Be Tracked on page 169 • Configuring a Logical Interface to Be Tracked

delegate-processing (VRRP)

Syntax	delegate-processing;
Hierarchy Level	[edit protocols vrrp]
Release Information	Statement introduced in Junos OS Release 9.6.
Description	Configure the distributed ppmmd process to send VRRP advertisements.
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration
Related Documentation	<ul style="list-style-type: none">• Enabling the Distributed Periodic Packet Management Process for VRRP on page 175

fast-interval

Syntax	<code>fast-interval milliseconds;</code>
Hierarchy Level	<p>[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> vrp-group <i>group-id</i>],</p> <p>[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> vrp-inet6-group <i>group-id</i>],</p> <p>[edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> vrp-group <i>group-id</i>],</p> <p>[edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> vrp-inet6-group <i>group-id</i>]</p>
Release Information	<p>Statement introduced before Junos OS Release 7.4.</p> <p>Statement introduced in Junos OS 11.3 for the QFX Series.</p>
Description	<p>Configure the interval, in milliseconds, between Virtual Router Redundancy Protocol (VRRP) advertisement packets.</p> <p>All routers in the VRRP group must use the same advertisement interval.</p>
Options	<p>milliseconds—Interval between advertisement packets.</p> <p>Range: 10 through 40,950 milliseconds (range extended from 100–999 to 10–40,950 in Junos OS Release 12.2).</p>
<div>  <p>NOTE: When configuring VRRP for IPv4, if you have chosen not to enable VRRPv3, you cannot set a value less than 100 for fast-interval. Commit check fails if a value less than 100 is configured.</p> </div>	
Default: 1 second	
Required Privilege Level	<p>interface—To view this statement in the configuration.</p> <p>interface-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none"> • Configuring the Advertisement Interval for the VRRP Master Router on page 163 • Configuring the Advertisement Interval for the VRRP Master • advertise-interval on page 233 • advertise-interval on page 233 • inet6-advertise-interval on page 242 • version-3 on page 253

global-advertisements-threshold

Syntax	<code>global-advertisements-threshold <i>advertisement-value</i>;</code>
Hierarchy Level	[edit protocols vrrp]
Release Information	Statement introduced in Junos OS Release 12.2.
Description	Configure the number of fast advertisements that can be missed by a backup router before the master router is declared as down.



NOTE:


- The advertisement value configured using the `global-advertisements-threshold` statement is applicable to all the Virtual Router Redundancy Protocol (VRRP) groups in the system.
- Setting the advertisement value of the `global-advertisements-threshold` configuration to 1 is not recommended for a scaled configuration with an aggressive advertisement interval. For example, if you have 1000 VRRP groups with an advertisement interval of 100 ms, then do not set the `global-advertisements-threshold` value to 1.
- Changing the advertisement value of the `global-advertisements-threshold` configuration during runtime can result in unpredictable behavior by the VRRP state machine. For example, momentary ownership change from the master router to the backup router and vice versa. Therefore, avoid changing the advertisement value of the `global-advertisements-threshold` statement during runtime.

Options	<i>advertisement-value</i> —Number of VRRP advertisements missed before the master router is declared as down. Range: 1 through 15 Default: 3
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none"> • Improving the Convergence Time for VRRP on page 63 • Configuring VRRP to Improve Convergence Time on page 176

hold-time (VRRP)

Syntax	<code>hold-time seconds;</code>
Hierarchy Level	<p>[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> vrrp-group group-id preempt],</p> <p>[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> vrrp-inet6-group group-id preempt],</p> <p>[edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> vrrp-group group-id preempt],</p> <p>[edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> vrrp-inet6-group group-id preempt]</p>
Release Information	<p>Statement introduced before Junos OS Release 7.4.</p> <p>Statement introduced in Junos OS 11.3 for the QFX Series.</p>
Description	In a Virtual Router Redundancy Protocol (VRRP) configuration, set the hold time before a higher-priority backup router preempts the master router.
Default	VRRP preemption is not timed.
Options	<p>seconds—Hold-time period.</p> <p>Range: 0 through 3600 seconds</p> <p>Default: 0 seconds (VRRP preemption is not timed.)</p>
Required Privilege Level	<p>interface—To view this statement in the configuration.</p> <p>interface-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none"> • Configuring a Backup Router to Preempt the Master Router on page 166 • Configuring VRRP Preemption and Hold Time


inet6-advertise-interval

Syntax	<code>inet6-advertise-interval <i>milliseconds</i>;</code>
Hierarchy Level	[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> vrrp-inet6-group group-id], [edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> vrrp-inet6-group group-id]
Release Information	Statement introduced in Junos OS Release 8.4R2.
Description	Configure the interval between Virtual Router Redundancy Protocol (VRRP) IPv6 advertisement packets. All routers in the VRRP group must use the same advertisement interval.
	<div>  <p>NOTE: When VRRPv3 is enabled, the <code>inet6-advertise-interval</code> statement cannot be used to configure advertisement intervals. Instead, use the <code>fast-interval</code> statement to configure advertisement intervals.</p> </div>
Options	<p><i>milliseconds</i>—Interval, in milliseconds, between advertisement packets.</p> <p>Range: 100 to 40,000 milliseconds (ms)</p> <p>Default: 1 second</p>
Required Privilege Level	<p>interface—To view this statement in the configuration.</p> <p>interface-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none"> • Configuring the Advertisement Interval for the VRRP Master Router on page 163 • advertise-interval on page 233 • fast-interval on page 239 • version-3 on page 253

interface (VRRP Group)

Syntax	<pre>interface <i>interface-name</i> { bandwidth-threshold <i>bits-per-second</i> <i>priority-cost</i> <i>priority</i>; priority-cost <i>priority</i>; }</pre>
Hierarchy Level	<p>[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> vrrp-group <i>group-id</i> track],</p> <p>[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> vrrp-inet6-group <i>group-id</i> track],</p> <p>[edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> vrrp-group <i>group-id</i> track],</p> <p>[edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> vrrp-inet6-group <i>group-id</i> track]</p>
Release Information	<p>Statement introduced before Junos OS Release 7.4.</p> <p>bandwidth-threshold statement added in Junos OS Release 8.1.</p> <p>Statement introduced in Junos OS 11.3 for the QFX Series.</p>
Description	Enable logical interface tracking for a Virtual Router Redundancy Protocol (VRRP) group.
Options	<p><i>interface-name</i>—Interface to be tracked for this VRRP group.</p> <p>Range: 1 through 10 interfaces</p> <p>The remaining statements are explained separately.</p>
Required Privilege Level	<p>interface—To view this statement in the configuration.</p> <p>interface-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none"> • Configuring a Logical Interface to Be Tracked on page 169 • Configuring a Logical Interface to Be Tracked • Junos Services Interfaces Configuration Release 12.3

preempt (VRRP)

Syntax	(preempt no-preempt) { hold-time seconds; }
Hierarchy Level	[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> <i>vrrp-group group-id</i>], [edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> <i>vrrp-inet6-group group-id</i>], [edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> <i>vrrp-group group-id</i>], [edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> <i>vrrp-inet6-group group-id</i>]
Release Information	Statement introduced before Junos OS Release 7.4. Statement introduced in Junos OS 11.3 for the QFX Series.
Description	In a Virtual Router Redundancy Protocol (VRRP) configuration, determine whether or not a backup router can preempt a master router: <ul style="list-style-type: none"> • preempt—Allow the master router to be preempted. <div style="margin-top: 10px;">  <p>NOTE: By default, a higher-priority backup router can preempt a lower-priority master router.</p> </div> <ul style="list-style-type: none"> • no-preempt—Prohibit the preemption of the master router. When no-preempt is configured, the backup router cannot preempt the master router even if the backup router has a higher priority. <p>The remaining statement is explained separately.</p>
Default	By default the preempt statement is enabled, and a higher-priority backup router preempts a lower-priority master router even if the preempt statement is not explicitly configured.
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none"> • Configuring a Backup Router to Preempt the Master Router on page 166 • Configuring VRRP Preemption and Hold Time


priority (Protocols VRRP)

Syntax	<code>priority <i>priority</i>;</code>
Hierarchy Level	<p>[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> <i>vrrp-group group-id</i>],</p> <p>[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> <i>vrrp-inet6-group group-id</i>],</p> <p>[edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> <i>vrrp-group group-id</i>],</p> <p>[edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> <i>vrrp-inet6-group group-id</i>]</p>
Release Information	<p>Statement introduced before Junos OS Release 7.4.</p> <p>Statement introduced in Junos OS 11.3 for the QFX Series.</p>
Description	Configure a Virtual Router Redundancy Protocol (VRRP) router's priority for becoming the master default router. The router with the highest priority within the group becomes the master.
Options	<p>priority—Router's priority for being elected to be the master router in the VRRP group. A larger value indicates a higher priority for being elected.</p> <p>Range: 1 through 255</p> <p>Default: 100 (for backup routers)</p>
Required Privilege Level	<p>interface—To view this statement in the configuration.</p> <p>interface-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none"> • Configuring Basic VRRP Support on page 160 • Configuring Basic VRRP Support

priority-cost (VRRP)

Syntax	<code>priority-cost priority;</code>
Hierarchy Level	<p>[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> <i>vrrp-group group-id</i> track interface <i>interface-name</i>],</p> <p>[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> <i>vrrp-inet6-group group-id</i> track interface <i>interface-name</i>],</p> <p>[edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> <i>vrrp-group group-id</i> track interface <i>interface-name</i>],</p> <p>[edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> <i>vrrp-inet6-group group-id</i> track interface <i>interface-name</i>]</p>
Release Information	<p>Statement introduced before Junos OS Release 7.4.</p> <p>Statement introduced in Junos OS 11.3 for the QFX Series.</p> <p>Statement introduced in Junos OS Release 12.2 for ACX2000 Universal Access Routers.</p>
Description	Configure a Virtual Router Redundancy Protocol (VRRP) router's priority cost for becoming the master default router. The router with the highest priority within the group becomes the master.
Options	<p>priority—The value subtracted from the configured VRRP priority when the tracked interface or route is down to force a new master router election. The sum of all the costs for all interfaces or routes that are tracked must be less than or equal to the configured priority of the VRRP group.</p> <p>Range: 1 through 254</p>
Required Privilege Level	<p>interface—To view this statement in the configuration.</p> <p>interface-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none"> • Configuring a Logical Interface to Be Tracked on page 169 • Configuring a Logical Interface to Be Tracked


priority-hold-time

Syntax	<code>priority-hold-time seconds;</code>
Hierarchy Level	<p>[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> <i>vrrp-group group-id track</i>],</p> <p>[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> <i>vrrp-inet6-group group-id track</i>],</p> <p>[edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> <i>vrrp-group group-id track</i>],</p> <p>[edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> <i>vrrp-inet6-group group-id track</i>]</p>
Release Information	<p>Statement introduced in Junos OS Release 8.1.</p> <p>Statement introduced in Junos OS 11.3 for the QFX Series.</p>
Description	<p>Configure a Virtual Router Redundancy Protocol (VRRP) router's priority hold time to define the minimum length of time that must elapse between dynamic priority changes. If the dynamic priority changes because of a tracking event, the priority hold timer begins running. If another tracking event or manual configuration change occurs while the timer is running, the new dynamic priority update is postponed until the timer expires.</p>
	<div>  <p>NOTE: When the track feature is configured, and if VRRP should pre-empt due to the tracking interface or route transition, any configured pre-empt hold time will be ignored. VRRP master will pre-empt according to the configuration of the priority-hold time.</p> </div>
Options	<p>seconds—Minimum length of time that must elapse between dynamic priority changes.</p> <p>Range: 0through 3600 seconds</p>
Required Privilege Level	<p>interface—To view this statement in the configuration.</p> <p>interface-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none"> • Configuring a Logical Interface to Be Tracked on page 169 • Configuring a Logical Interface to Be Tracked

route (Interfaces)

Syntax	<code>route <i>prefix</i> routing-instance <i>instance-name</i> priority-cost <i>priority</i>;</code>
Hierarchy Level	<p>[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> vrrp-group <i>group-id</i> track],</p> <p>[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> vrrp-inet6-group <i>group-id</i> track],</p> <p>[edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> vrrp-group <i>group-id</i> track],</p> <p>[edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> vrrp-inet6-group <i>group-id</i> track]</p>
Release Information	<p>Statement introduced in Junos OS Release 9.0.</p> <p>Statement introduced in Junos OS 11.3 for QFX Series.</p> <p>Statement introduced in Junos OS 12.1 for EX Series switches.</p>
Description	Enable route tracking for a Virtual Router Redundancy Protocol (VRRP) group.
Options	<p><i>prefix</i>—Route to be tracked for this VRRP group.</p> <p><i>priority-cost <i>priority</i></i>—The value subtracted from the configured VRRP priority when the tracked interface or route is down, forcing a new master router election. The sum of all the costs for all interfaces or routes that are tracked must be less than or equal to the configured priority of the VRRP group.</p> <p><i>routing-instance <i>instance-name</i></i>—Routing instance in which the route is to be tracked. If the route is in the default, or global, routing instance, the value for <i>instance-name</i> must be default.</p>
Required Privilege Level	<p>interface—To view this statement in the configuration.</p> <p>interface-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none"> • Configuring a Route to Be Tracked on page 171 • Configuring a Route to Be Tracked

skew-timer-disable

Syntax	skew-timer-disable;
Hierarchy Level	[edit protocols vrrp]
Release Information	Statement introduced in Junos OS Release 12.2.
Description	Disable the skew timer, thereby reducing the time required to transition from the backup state to the master state.
	<div>  <p>NOTE: The <code>skew-timer-disable</code> statement is used when there is only one master router and one backup router in the network.</p> </div>
Default	By default, the skew timer is enabled for all the VRRP groups.
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none"> • Improving the Convergence Time for VRRP on page 63 • Configuring VRRP to Improve Convergence Time on page 176

startup-silent-period

Syntax	startup-silent-period <i>seconds</i> ;
Hierarchy Level	[edit protocols vrrp]
Release Information	Statement introduced before Junos OS Release 7.4. Statement introduced in Junos OS 11.3 for the QFX Series.
Description	Instruct the system to ignore the Master Down Event when an interface transitions from the down state to the up state. This statement is used to avoid incorrect error alarms caused by the delay or interruption of incoming Virtual Router Redundancy Protocol (VRRP) advertisement packets during the interface startup phase.
Options	<p><i>seconds</i>—Number of seconds for the startup period.</p> <p>Default: 4 seconds</p> <p>Range: 1 through 2000 seconds</p>
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none"> • Configuring the Startup Period for VRRP Operations on page 159 • Configuring the Startup Period for VRRP Operations

traceoptions (Protocols VRRP)

Syntax	<pre>traceoptions { file <i>filename</i> <files <i>number</i>> <match <i>regular-expression</i>> <microsecond-stamp> <size <i>size</i>> <world-readable no-world-readable>; flag <i>flag</i>; no-remote-trace; }</pre>
Hierarchy Level	[edit protocols vrrp]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	<p>Define tracing operations for the Virtual Router Redundancy Protocol (VRRP) process.</p> <p>To specify more than one tracing operation, include multiple flag statements.</p> <p>By default, VRRP logs the error, dcd configuration, and routing socket events in a file in the directory /var/log.</p>
Default	If you do not include this statement, no VRRP-specific tracing operations are performed.
Options	<p>file <i>filename</i>—Name of the file to receive the output of the tracing operation. Enclose the name within quotation marks. All files are placed in the directory /var/log. By default, VRRP tracing output is placed in the file vrrpd.</p> <p>files <i>number</i>—(Optional) Maximum number of trace files. When a trace file named trace-file reaches its maximum size, it is renamed trace-file.0, then trace-file.1, and so on, until the maximum number of trace files is reached. When the maximum number is reached, the oldest trace file is overwritten.</p> <p>Range: 0 through 4,294,967,296 files</p> <p>Default: 3 files</p> <p>If you specify a maximum number of files, you also must specify a maximum file size with the size option.</p> <p>flag <i>flag</i>—Tracing operation to perform. To specify more than one tracing operation, include multiple flag statements. These are the VRRP-specific tracing options:</p> <ul style="list-style-type: none">• all—All VRRP tracing operations• database—Database changes• general—General events• interfaces—Interface changes• normal—Normal events• packets—Packets sent and received

- **state**—State transitions

- **timer**—Timer events

match *regular-expression*—(Optional) Refine the output to include only those lines that match the given regular expression.

microsecond-stamp—(Optional) Provide a timestamp with microsecond granularity.

no-world-readable—(Optional) Restrict users from reading the log file.

size *size*—(Optional) Maximum size of each trace file, in kilobytes, megabytes, or gigabytes. When a trace file named ***trace-file*** reaches this size, it is renamed ***trace-file.0***. When the ***trace-file*** again reaches its maximum size, ***trace-file.0*** is renamed ***trace-file.1*** and ***trace-file*** is renamed ***trace-file.0***. This renaming scheme continues until the maximum number of trace files is reached. Then the oldest trace file is overwritten.

Syntax: *xk* to specify KB, *xm* to specify MB, or *xg* to specify GB

Range: 10 KB through the maximum file size supported on your routing platform

Default: 1 MB

If you specify a maximum file size, you also must specify a maximum number of trace files with the **files** option.

world-readable—(Optional) Allow users to read the log file.

Required Privilege	interface—To view this statement in the configuration.
Level	interface-control—To add this statement to the configuration.

Related Documentation	<ul style="list-style-type: none">• Tracing VRRP Operations on page 187
------------------------------	---

track (VRRP)

Syntax	<pre>track { interface <i>interface-name</i> { bandwidth-threshold <i>bits-per-second</i> priority-cost <i>priority</i>; priority-cost <i>priority</i>; } priority-hold-time <i>seconds</i>; route <i>prefix/prefix-length</i> routing-instance <i>instance-name</i> priority-cost <i>priority</i>; }</pre>
Hierarchy Level	<p>[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> <i>vrrp-group group-id</i>],</p> <p>[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> <i>vrrp-inet6-group group-id</i>],</p> <p>[edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> <i>vrrp-group group-id</i>],</p> <p>[edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> <i>vrrp-inet6-group group-id</i>]</p>
Release Information	<p>Statement introduced before Junos OS Release 7.4.</p> <p>priority-hold-time statement added in Junos OS Release 8.1.</p> <p>route statement added in Junos OS Release 9.0.</p> <p>Statement introduced in Junos OS 11.3 for the QFX Series.</p>
Description	Enable logical interface tracking, route tracking, or both, for a Virtual Router Redundancy Protocol (VRRP) group.
Options	The remaining statements are described separately.
Required Privilege Level	<p>interface—To view this statement in the configuration.</p> <p>interface-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none"> • Configuring a Logical Interface to Be Tracked on page 169 • Configuring a Route to Be Tracked on page 171 • Configuring a Logical Interface to Be Tracked • Configuring a Route to Be Tracked

version-3

Syntax	version-3;
Hierarchy Level	[edit protocols vrrp]
Release Information	Statement introduced in Junos OS Release 12.2.
Description	Enable Virtual Router Redundancy Protocol version 3 (VRRPv3).



NOTE:

- Even though the version-3 statement can be configured only at the [edit protocols vrrp] hierarchy level, VRRPv3 is enabled on all the configured logical systems as well.
 - When enabling VRRPv3, you must ensure that VRRPv3 is enabled on all the VRRP routers in the network. This is because VRRPv3 does not interoperate with the previous versions of VRRP.
-

Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none"> • Junos OS Support for VRRPv3 on page 60 • VRRP Configuration Hierarchy on page 157 • VRRP for IPv6 Configuration Hierarchy on page 158


virtual-address

Syntax	<code>virtual-address [<i>addresses</i>];</code>
Hierarchy Level	[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> <i>vrrp-group group-id</i>], [edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i> <i>vrrp-group group-id</i>]
Release Information	Statement introduced before Junos OS Release 7.4. Statement introduced in Junos OS 11.3 for the QFX Series.
Description	Configure the addresses of the virtual routers in a Virtual Router Redundancy Protocol (VRRP) IPv4 or IPv6 group. You can configure up to eight addresses.
Options	<i>addresses</i> —Addresses of one or more virtual routers. Do not include a prefix length. If the address is the same as the interface's physical address, the interface becomes the master virtual router for the group.
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• Configuring Basic VRRP Support on page 160• Configuring Basic VRRP Support

virtual-inet6-address

Syntax	<code>virtual-inet6-address [<i>addresses</i>];</code>
Hierarchy Level	[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> <i>vrrp-inet6-group group-id</i>], [edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> <i>vrrp-inet6-group group-id</i>]
Release Information	Statement introduced before Junos OS Release 7.4.
Description	Configure the addresses of the virtual routers in a Virtual Router Redundancy Protocol (VRRP) IPv6 group. You can configure up to eight addresses.
Options	<i>addresses</i> —Addresses of one or more virtual routers. Do not include a prefix length. If the address is the same as the interface's physical address, the interface becomes the master virtual router for the group.
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• Configuring Basic VRRP Support on page 160

virtual-link-local-address

Syntax	<code>virtual-link-local-address <i>ipv6-address</i>;</code>
Hierarchy Level	[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> virtual-link-local-address <i>group-id</i>], [edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i> virtual-link-local-address <i>group-id</i>]
Release Information	Statement introduced in Junos OS Release 8.4. Statement introduced in Junos OS 11.3 for the QFX Series.
Description	Configure a virtual link-local address for a Virtual Router Redundancy Protocol (VRRP) IPv6 group. You must explicitly define a virtual link-local address for each VRRP for IPv6 group. The virtual link-local address must be in the same subnet as the physical interface address.
	<div>  <p>NOTE: You do <i>not</i> need to configure link-local addresses and virtual link-local addresses when configuring VRRP for IPv6. Junos OS automatically generates link-local addresses and virtual link-local addresses. However, if link local addresses and virtual link-local addresses are configured, Junos OS considers the configured addresses.</p> </div>
Options	<i>ipv6-address</i> —virtual link-local IPv6 address for VRRP for an IPv6 group. Range: 0 through 255
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none"> • Configuring Basic VRRP Support on page 160 • Junos OS Support for VRRPv3 on page 60

vrrp-group

Syntax	<pre> vrrp-group <i>group-id</i> { (<i>accept-data</i> <i>no-accept-data</i>); <i>advertise-interval seconds</i>; <i>authentication-key key</i>; <i>authentication-type authentication</i>; <i>fast-interval milliseconds</i>; (<i>preempt</i> <i>no-preempt</i>) { <i>hold-time seconds</i>; } <i>priority number</i>; track { <i>interface interface-name</i> { <i>bandwidth-threshold bits-per-second</i> <i>priority-cost priority</i>; <i>priority-cost priority</i>; } <i>priority-hold-time seconds</i>; <i>route prefix/prefix-length</i> <i>routing-instance instance-name</i> <i>priority-cost priority</i>; } <i>virtual-address [addresses]</i>; <i>vrrp-inherit-from vrrp-group</i>; } </pre>
Hierarchy Level	<pre> [edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i>], [edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet address <i>address</i>] </pre>
Release Information	<p>Statement introduced before Junos OS Release 7.4.</p> <p>Statement introduced in Junos OS 11.3 for the QFX Series.</p>
Description	Configure a Virtual Router Redundancy Protocol (VRRP) IPv4 group.
Options	<p><i>group-id</i>—VRRP group identifier. If you enable MAC source address filtering on the interface, you must include the virtual MAC address in the list of source MAC addresses that you specify in the source-address-filter statement. MAC addresses ranging from 00:00:5e:00:01:00 through 00:00:5e:00:01:ff are reserved for VRRP, as defined in RFC 2338. The VRRP group number must be the decimal equivalent of the last hexadecimal byte of the virtual MAC address.</p> <p>Range: 0 through 255</p> <p>The remaining statements are explained separately.</p>
Required Privilege Level	<p>interface—To view this statement in the configuration.</p> <p>interface-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none"> • Configuring Basic VRRP Support on page 160 • Example: Configuring VRRP on page 177 • Configuring Basic VRRP Support • Example: Configuring VRRP for Load Sharing

- [vrrp-inet6-group on page 257](#)

vrrp-inet6-group

Syntax	<pre> vrrp-inet6-group <i>group-id</i> { (accept-data no-accept-data); fast-interval <i>milliseconds</i>; inet6-advertise-interval <i>seconds</i>; (preempt no-preempt) { hold-time <i>seconds</i>; } priority <i>number</i>; track { interface <i>interface-name</i> { bandwidth-threshold <i>bits-per-second</i> priority-cost <i>priority</i>; priority-cost <i>priority</i>; } priority-hold-time <i>seconds</i>; route <i>prefix/prefix-length</i> routing-instance <i>instance-name</i> priority-cost <i>priority</i>; } virtual-inet6-address [<i>addresses</i>]; virtual-link-local-address <i>ipv6-address</i>; } </pre>
Hierarchy Level	<p>[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i>],</p> <p>[edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> family inet6 address <i>address</i>]</p>
Release Information	Statement introduced before Junos OS Release 7.4.
Description	Configure a Virtual Router Redundancy Protocol (VRRP) IPv6 group.
Options	<p><i>group-id</i>—VRRP group identifier. If you enable MAC source address filtering on the interface, you must include the virtual MAC address in the list of source MAC addresses that you specify in the source-address-filter statement. MAC addresses ranging from 00:00:5e:00:01:00 through 00:00:5e:00:01:ff are reserved for VRRP, as defined in RFC 2338. The VRRP group number must be the decimal equivalent of the last hexadecimal byte of the virtual MAC address.</p> <p>Range: 0 through 255</p> <p>The remaining statements are explained separately.</p>
Required Privilege Level	<p>interface—To view this statement in the configuration.</p> <p>interface-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none"> • Configuring Basic VRRP Support on page 160 • VRRP for IPv6 Configuration Hierarchy on page 158

CHAPTER 23

Unified ISSU

- [Best Practices on page 259](#)
- [Before You Begin on page 259](#)
- [Performing a Unified ISSU on page 262](#)
- [Verifying a Unified ISSU on page 274](#)

Best Practices

When you are planning to perform a unified in-service software upgrade (unified ISSU), choose a time when your network is as stable as possible. As with a normal upgrade, Telnet sessions, SNMP, and CLI access are briefly interrupted. In addition, the following restrictions apply:

- The master Routing Engine and backup Routing Engine must be running the same software version before you can perform a unified ISSU.
- During a unified ISSU, you cannot bring any PICs online or offline.
- Unicast RPF-related statistics are not saved across a unified ISSU, and the unicast RPF counters are reset to zero during a unified ISSU.

Related Documentation

- [Before You Begin on page 259](#)
- [Performing a Unified ISSU on page 262](#)
- [Verifying a Unified ISSU on page 274](#)
- [Troubleshooting Unified ISSU Problems on page 279](#)

Before You Begin

Before you begin a unified ISSU, complete the tasks in the following sections:

1. [Verify That the Master and Backup Routing Engines Are Running the Same Software Version on page 260](#)
2. [Back Up the Router Software on page 260](#)
3. [Verify That Graceful Routing Engine Switchover and Nonstop Active Routing Are Configured on page 261](#)

Verify That the Master and Backup Routing Engines Are Running the Same Software Version

To verify that both Routing Engines are running the same version of software, issue the following command:

```
{master}
user@host> show version invoke-on all-routing-engines
re0:
-----
Hostname: host
Model: m320
JUNOS Base OS boot [9.0-20071210.0]
JUNOS Base OS Software Suite [9.0-20071210.0]
JUNOS Kernel Software Suite [9.0-20071210.0]
JUNOS Crypto Software Suite [9.0-20071210.0]
JUNOS Packet Forwarding Engine Support (M/T Common) [9.0-20071210.0]
JUNOS Packet Forwarding Engine Support (M320) [9.0-20071210.0]
JUNOS Online Documentation [9.0-20071210.0]
JUNOS Routing Software Suite [9.0-20071210.0]
re1:
-----
Hostname: host
Model: m320
JUNOS Base OS boot [9.0-20071210.0]
JUNOS Base OS Software Suite [9.0-20071210.0]
JUNOS Kernel Software Suite [9.0-20071210.0]
JUNOS Crypto Software Suite [9.0-20071210.0]
JUNOS Packet Forwarding Engine Support (M/T Common) [9.0-20071210.0]
JUNOS Packet Forwarding Engine Support (M320) [9.0-20071210.0]
JUNOS Online Documentation [9.0-20071210.0]
JUNOS Routing Software Suite [9.0-20071210.0]
```

If both Routing Engines are not running the same software version, issue the **request system software add** command on the desired Routing Engine so that the software version is the same. For more information, see the Installation and Upgrade Guide.

Back Up the Router Software

As a preventive measure in case any problems occur during an upgrade, issue the **request system snapshot** command on *each* Routing Engine to back up the system software to the router's hard disk. The following is an example of issuing the command on the master Routing Engine:

```
{master}
user@host> request system snapshot
Verifying compatibility of destination media partitions...
Running newfs (220MB) on hard-disk media / partition (ad1s1a)...
Running newfs (24MB) on hard-disk media /config partition (ad1s1e)...
Copying '/dev/ad0s1a' to '/dev/ad1s1a' .. (this may take a few minutes)
Copying '/dev/ad0s1e' to '/dev/ad1s1e' .. (this may take a few minutes)
The following filesystems were archived: / /config
```




NOTE: The root file system is backed up to `/altroot`, and `/config` is backed up to `/altconfig`. After you issue the `request system snapshot` command, the router's flash and hard disks are identical. You can return to the previous version of the software only by booting the router from removable media. For more information about the `request system snapshot` command, see the Junos OS System Basics Configuration Guide.

Verify That Graceful Routing Engine Switchover and Nonstop Active Routing Are Configured

Before you begin a unified ISSU, ensure that graceful Routing Engine switchover and nonstop active routing are configured on your router.

1. To verify graceful Routing Engine switchover is configured, on the backup Routing Engine (**re1**) issue the `show system switchover` command. The output should be similar to the following example. The **Graceful switchover** field state must be **On**.

```
{backup}
user@host> show system switchover
Graceful switchover: On
Configuration database: Ready
Kernel database: Ready
Peer state: Steady State
```

2. To verify nonstop active routing is configured, on the master Routing Engine (**re0**) issue the `show task replication` command. The output should be similar to the following example.

```
{master}
user@host> show task replication
Stateful Replication: Enabled
RE mode: Master

Protocol           Synchronization Status
OSPF               Complete
IS-IS              Complete
```

If graceful Routing Engine switchover and nonstop active routing are not configured, complete the following steps:

1. On the master Routing Engine (**re0**), enable graceful Routing Engine switchover. Include the **graceful-switchover** statement at the **[edit chassis redundancy]** hierarchy level.
2. On the master Routing Engine, enable nonstop active routing. Include the **commit synchronize** statement at the **[edit system]** hierarchy level and the **nonstop-routing** statement at the **[edit routing-options]** hierarchy level.
3. On the master Router Engine, issue the **commit** command.

The system provides the following confirmation that the master and backup Routing Engines are synchronized:

```
re0:
configuration check succeeds
```

```
re1:
commit complete
re0:
commit complete
```

Related Documentation

- [Unified ISSU Concepts on page 67](#)
- [Unified ISSU Process on the TX Matrix Router on page 72](#)
- [Unified ISSU System Requirements on page 73](#)
- [Best Practices on page 259](#)
- [Performing a Unified ISSU on page 262](#)
- [Verifying a Unified ISSU on page 274](#)
- [Troubleshooting Unified ISSU Problems on page 279](#)

Performing a Unified ISSU

You can perform a unified ISSU in one of three ways:

1. [Upgrading and Rebooting Both Routing Engines Automatically on page 262](#)
2. [Upgrading Both Routing Engines and Rebooting the New Backup Routing Engine Manually on page 266](#)
3. [Upgrading and Rebooting Only One Routing Engine on page 271](#)

Upgrading and Rebooting Both Routing Engines Automatically

When you issue the **request system software in-service-upgrade** command with the **reboot** option, the system automatically upgrades both Routing Engines to the newer software and reboots both Routing Engines. This option enables you to complete the unified ISSU with a single command.

To perform a unified ISSU using the **request system software in-service-upgrade *package-name* reboot** command, complete the following steps:

1. Download the software package from the Juniper Networks Support website, <http://www.juniper.net/support/>. Choose the Canada and U.S., Worldwide, or Junos-FIPS edition. Place the package on a local server. To download the package, you must have a service contract and an access account. If you do not have an access account, complete the registration form at the Juniper Networks website: <https://www.juniper.net/registration/Register.jsp>.
2. Copy the package to the router. We recommend that you copy it to the **/var/tmp** directory, which is a large file system on the hard disk.


```
user@host>file copy ftp://username:prompt@ftp.hostname.net/filename/var/tmp/filename
```
3. To verify the current software version running on both Routing Engines, on the master Routing Engine issue the **show version invoke-on all-routing-engines** command. The following example shows that both Routing Engines are running an image of Junos OS, Release 9.0, that was built on December 11, 2007:

```
{backup}
```

```
user@host> show version invoke-on all-routing-engines
re0:
```

```
-----
Hostname: host
Model: m320
JUNOS Base OS boot [9.0-20071211.2]
JUNOS Base OS Software Suite 9.0-20071211.2]
JUNOS Kernel Software Suite [9.0-20071211.2]
JUNOS Crypto Software Suite [9.0-20071211.2]
JUNOS Packet Forwarding Engine Support (M/T Common) [9.0-20071211.2]
JUNOS Packet Forwarding Engine Support (M320) [9.0-20071211.2]
JUNOS Online Documentation [9.0-20071211.2]
JUNOS Routing Software Suite [9.0-20071211.2]
```

```
re1:
```

```
-----
Hostname: host1
Model: m320
JUNOS Base OS boot [9.0-20071211.2]
JUNOS Base OS Software Suite [9.0-20071211.2]
JUNOS Kernel Software Suite [9.0-20071211.20]
JUNOS Crypto Software Suite [9.0-20071211.2]
JUNOS Packet Forwarding Engine Support (M/T Common) [9.0-20071211.2]
JUNOS Packet Forwarding Engine Support (M320) [9.0-20071211.2]
JUNOS Online Documentation [9.0-20071211.2]
JUNOS Routing Software Suite [9.0-20071211.2]
```

4. On the master Routing Engine, issue the **request system software in-service-upgrade package-name reboot** command. The following example upgrades the current version to an image of Junos OS, Release 9.0, that was built on January 14, 2008:

```
{master}
```

```
user@host> request system software in-service-upgrade
/var/tmp/jinstall-9.0-20080114.2-domestic-signed.tgz reboot
ISSU: Validating Image
PIC 0/3 will be offlined (In-Service-Upgrade not supported)
Do you want to continue with these actions being taken ? [yes,no] (no) yes
```

```
ISSU: Preparing Backup RE
Pushing bundle to re1
Checking compatibility with configuration
Initializing...
Using jbase-9.0-20080114.2
Verified manifest signed by PackageProduction_9_0_0
Using /var/tmp/jinstall-9.0-20080114.2-domestic-signed.tgz
Verified jinstall-9.0-20080114.2-domestic.tgz signed by PackageProduction_9_0_0
Using jinstall-9.0-20080114.2-domestic.tgz
Using jbundle-9.0-20080114.2-domestic.tgz
Checking jbundle requirements on /
Using jbase-9.0-20080114.2.tgz
Verified manifest signed by PackageProduction_9_0_0
Using jkernel-9.0-20080114.2.tgz
Verified manifest signed by PackageProduction_9_0_0
Using jcrypto-9.0-20080114.2.tgz
Verified manifest signed by PackageProduction_9_0_0
Using jpfe-9.0-20080114.2.tgz
Using jdocs-9.0-20080114.2.tgz
Verified manifest signed by PackageProduction_9_0_0
Using jroute-9.0-20080114.2.tgz
```

```

Verified manifest signed by PackageProduction_9_0_0
Hardware Database regeneration succeeded
Validating against /config/juniper.conf.gz
mgd: commit complete
Validation succeeded
Installing package '/var/tmp/jinstall-9.0-20080114.2-domestic-signed.tgz' ...
Verified jinstall-9.0-20080114.2-domestic.tgz signed by PackageProduction_9_0_0
Adding jinstall...
Verified manifest signed by PackageProduction_9_0_0

WARNING: This package will load JUNOS 9.0-20080114.2 software.
WARNING: It will save JUNOS configuration files, and SSH keys
WARNING: (if configured), but erase all other files and information
WARNING: stored on this machine. It will attempt to preserve dumps
WARNING: and log files, but this can not be guaranteed. This is the
WARNING: pre-installation stage and all the software is loaded when
WARNING: you reboot the system.

Saving the config files ...
NOTICE: uncommitted changes have been saved in
/var/db/config/juniper.conf.pre-install
Installing the bootstrap installer ...

WARNING: A REBOOT IS REQUIRED TO LOAD THIS SOFTWARE CORRECTLY. Use the
WARNING: 'request system reboot' command when software installation is
WARNING: complete. To abort the installation, do not reboot your system,
WARNING: instead use the 'request system software delete jinstall'
WARNING: command as soon as this operation completes.

Saving package file in /var/sw/pkg/jinstall-9.0-20080114.2-domestic-signed.tgz
...
Saving state for rollback ...
Backup upgrade done
Rebooting Backup RE

Rebooting re1
ISSU: Backup RE Prepare Done
Waiting for Backup RE reboot
GRES operational
Initiating Chassis In-Service-Upgrade
Chassis ISSU started
ISSU: Backup RE Prepare Done
ISSU: Preparing Daemons
ISSU: Daemons Ready for ISSU
ISSU: Starting Upgrade for FRUs
ISSU: Preparing for Switchover
ISSU: Ready for Switchover
Checking In-Service-Upgrade status
  Item          Status          Reason
  FPC 0         Online (ISSU)
  FPC 1         Online (ISSU)
  FPC 2         Online (ISSU)
  FPC 6         Online (ISSU)
  FPC 7         Online (ISSU)
Resolving mastership...
Complete. The other routing engine becomes the master.
ISSU: RE switchover Done
ISSU: Upgrading Old Master RE
Installing package '/var/tmp/paKEuy' ...
Verified jinstall-9.0-20080114.2-domestic.tgz signed by PackageProduction_9_0_0
Adding jinstall...

```

Verified manifest signed by PackageProduction_9_0_0

```
WARNING: This package will load JUNOS 9.0-20080114.2 software.
WARNING: It will save JUNOS configuration files, and SSH keys
WARNING: (if configured), but erase all other files and information
WARNING: stored on this machine. It will attempt to preserve dumps
WARNING: and log files, but this can not be guaranteed. This is the
WARNING: pre-installation stage and all the software is loaded when
WARNING: you reboot the system.
```

Saving the config files ...

NOTICE: uncommitted changes have been saved in
/var/db/config/juniper.conf.pre-install

Installing the bootstrap installer ...

```
WARNING: A REBOOT IS REQUIRED TO LOAD THIS SOFTWARE CORRECTLY. Use the
WARNING: 'request system reboot' command when software installation is
WARNING: complete. To abort the installation, do not reboot your system,
WARNING: instead use the 'request system software delete jinstall'
WARNING: command as soon as this operation completes.
```

Saving package file in /var/sw/pkg/jinstall-9.0-20080114.2-domestic-signed.tgz

...

cp: /var/tmp/paKEuy is a directory (not copied).

Saving state for rollback ...

ISSU: Old Master Upgrade Done

ISSU: IDLE

Shutdown NOW!

Reboot consistency check bypassed - jinstall 9.0-20080114.2 will complete
installation upon reboot
[pid 30227]

*** FINAL System shutdown message from root@host ***

System going down IMMEDIATELY

Connection to host closed.

When the new backup (old master) Routing Engine is rebooted, you are logged out from the router.

5. After waiting a few minutes, log in to the router again. You are logged in to the new backup Routing Engine (**re0**). To verify that both Routing Engines have been upgraded, issue the following command:

```
{backup}
```

```
user@host> show version invoke-on all-routing-engines
re0:
```

```
-----
Hostname: host
Model: m320
JUNOS Base OS boot [9.0-20080114.2]
JUNOS Base OS Software Suite 9.0-20080114.2]
JUNOS Kernel Software Suite [9.0-20080114.2]
JUNOS Crypto Software Suite [9.0-20080114.2]
JUNOS Packet Forwarding Engine Support (M/T Common) [9.0-20080114.2]
JUNOS Packet Forwarding Engine Support (M320) [9.0-20080114.2]
JUNOS Online Documentation [9.0-20080114.2]
JUNOS Routing Software Suite [9.0-20080114.2]
```

```
rel:
```

```
-----
Hostname: host1
Model: m320
JUNOS Base OS boot [9.0-20080114.2]
JUNOS Base OS Software Suite [9.0-20080114.2]
JUNOS Kernel Software Suite [9.0-20080114.2]
JUNOS Crypto Software Suite [9.0-20080114.2]
JUNOS Packet Forwarding Engine Support (M/T Common) [9.0-20080114.2]
JUNOS Packet Forwarding Engine Support (M320) [9.0-20080114.2]
JUNOS Online Documentation [9.0-20080114.2]
JUNOS Routing Software Suite [9.0-20080114.2]
```

6. To make **re0** the master Routing Engine, issue the following command:

```
{backup}

user@host> request chassis routing-engine master acquire
Attempt to become the master routing engine ? [yes,no] (no) yes

Resolving mastership...
Complete. The local routing engine becomes the master.

{master}
user@host>
```

7. Issue the **request system snapshot** command on *each* Routing Engine to back up the system software to the router's hard disk.



NOTE: The root file system is backed up to `/altroot`, and `/config` is backed up to `/altconfig`. After you issue the **request system snapshot** command, the router's flash and hard disks are identical. You can return to the previous version of the software only by booting the router from removable media.

Upgrading Both Routing Engines and Rebooting the New Backup Routing Engine Manually

When you issue the **request system software in-service-upgrade** command without any options, the system upgrades and reboots the new master Routing Engine to the newer software. The new software is placed on the new backup (old master) Routing Engine; however, to complete the upgrade, you must issue the **request system reboot** command on the new backup Routing Engine.

To perform a unified ISSU using the **request system software in-service-upgrade package-name** command without any options, complete the following steps:

1. Download the software package from the Juniper Networks Support website, <http://www.juniper.net/support/>. Choose the Canada and U.S., Worldwide, or Junos-FIPS edition. Place the package on a local server. To download the package, you must have a service contract and an access account. If you do not have an access account, complete the registration form at the Juniper Networks website: <https://www.juniper.net/registration/Register.jsp>.

2. Copy the package to the router. We recommend that you copy it to the `/var/tmp` directory, which is a large file system on the hard disk.

```
user@host>file copy ftp://username:prompt@ftp.hostname.net/filename/var/tmp/filename
```

3. To verify the current software version running on both Routing Engines, on the master Routing Engine, issue the **show version invoke-on all-routing-engines** command. The following example shows that both Routing Engines are running Junos OS Release 9.0R1:

```
{master}
```

```
user@host> show version invoke-on all-routing-engines
re0:
```

```
-----
Hostname: host
Model: m320
JUNOS Base OS boot [9.0R1]
JUNOS Base OS Software Suite [9.0R1]
JUNOS Kernel Software Suite [9.0R1]
JUNOS Crypto Software Suite [9.0R1]
JUNOS Packet Forwarding Engine Support (M/T Common) [9.0R1]
JUNOS Packet Forwarding Engine Support (M320) [9.0R1]
JUNOS Online Documentation [9.0R1]
JUNOS Routing Software Suite [9.0R1]
```

```
re1:
```

```
-----
Hostname: host1
Model: m320
JUNOS Base OS boot [9.0R1]
JUNOS Base OS Software Suite [9.0R1]
JUNOS Kernel Software Suite [9.0R1]
JUNOS Crypto Software Suite [9.0R1]
JUNOS Packet Forwarding Engine Support (M/T Common) [9.0R1]
JUNOS Packet Forwarding Engine Support (M320) [9.0R1]
JUNOS Online Documentation [9.0R1]
JUNOS Routing Software Suite [9.0R1]
```

4. On the master Routing Engine, issue the **request system software in-service-upgrade package-name** command. The following example upgrades the current version to Junos OS Release 9.0R1.2:

```
user@host> request system software in-service-upgrade
/var/tmp/jinstall-9.0R1.2-domestic-signed.tgz
ISSU: Validating Image
FPC 4 will be offlined (In-Service-Upgrade not supported)
Do you want to continue with these actions being taken ? [yes,no] (no) yes

ISSU: Preparing Backup RE
```

```
Pushing bundle to re1
Checking compatibility with configuration
Initializing...
Using jbase-9.0-20080117.0
Verified manifest signed by PackageProduction_9_0_0
Using /var/tmp/jinstall-9.0R1.2-domestic-signed.tgz
Verified jinstall-9.0R1.2-domestic.tgz signed by PackageProduction_9_0_0
Using jinstall-9.0R1.2-domestic.tgz
Using jbundle-9.0R1.2-domestic.tgz
Checking jbundle requirements on /
Using jbase-9.0R1.2.tgz
Verified manifest signed by PackageProduction_9_0_0
Using jkernel-9.0R1.2.tgz
Verified manifest signed by PackageProduction_9_0_0
Using jcrypto-9.0R1.2.tgz
Verified manifest signed by PackageProduction_9_0_0
Using jpf-9.0R1.2.tgz
Using jdocs-9.0R1.2.tgz
Verified manifest signed by PackageProduction_9_0_0
Using jroute-9.0R1.2.tgz
Verified manifest signed by PackageProduction_9_0_0
Hardware Database regeneration succeeded
Validating against /config/juniper.conf.gz
mgd: commit complete
Validation succeeded
Installing package '/var/tmp/jinstall-9.0R1.2-domestic-signed.tgz' ...
Verified jinstall-9.0R1.2-domestic.tgz signed by PackageProduction_9_0_0
Adding jinstall...
Verified manifest signed by PackageProduction_9_0_0

WARNING: This package will load JUNOS 9.0R1.2 software.
WARNING: It will save JUNOS configuration files, and SSH keys
WARNING: (if configured), but erase all other files and information
WARNING: stored on this machine. It will attempt to preserve dumps
WARNING: and log files, but this can not be guaranteed. This is the
WARNING: pre-installation stage and all the software is loaded when
WARNING: you reboot the system.

Saving the config files ...
NOTICE: uncommitted changes have been saved in
/var/db/config/juniper.conf.pre-install
Installing the bootstrap installer ...

WARNING: A REBOOT IS REQUIRED TO LOAD THIS SOFTWARE CORRECTLY. Use the
WARNING: 'request system reboot' command when software installation is
WARNING: complete. To abort the installation, do not reboot your system,
WARNING: instead use the 'request system software delete jinstall'
WARNING: command as soon as this operation completes.

Saving package file in /var/sw/pkg/jinstall-9.0R1.2-domestic-signed.tgz ...
Saving state for rollback ...
Backup upgrade done
Rebooting Backup RE

Rebooting re1
ISSU: Backup RE Prepare Done
Waiting for Backup RE reboot
GRES operational
Initiating Chassis In-Service-Upgrade
Chassis ISSU started
ISSU: Backup RE Prepare Done
```



```

ISSU: Preparing Daemons
ISSU: Daemons Ready for ISSU
ISSU: Starting Upgrade for FRUs
ISSU: Preparing for Switchover
ISSU: Ready for Switchover
Checking In-Service-Upgrade status
  Item           Status           Reason
  FPC 0          Online (ISSU)
  FPC 1          Online (ISSU)
  FPC 2          Online (ISSU)
  FPC 3          Online (ISSU)
  FPC 4          Offline          Offlined by cli command
  FPC 5          Online (ISSU)
Resolving mastership...
Complete. The other routing engine becomes the master.
ISSU: RE switchover Done
ISSU: Upgrading Old Master RE
Installing package '/var/tmp/paeBi5' ...
Verified jinstall-9.0R1.2-domestic.tgz signed by PackageProduction_9_0_0
Adding jinstall...
Verified manifest signed by PackageProduction_9_0_0

WARNING: This package will load JUNOS 9.0R1.2 software.
WARNING: It will save JUNOS configuration files, and SSH keys
WARNING: (if configured), but erase all other files and information
WARNING: stored on this machine. It will attempt to preserve dumps
WARNING: and log files, but this can not be guaranteed. This is the
WARNING: pre-installation stage and all the software is loaded when
WARNING: you reboot the system.

Saving the config files ...
NOTICE: uncommitted changes have been saved in
/var/db/config/juniper.conf.pre-install
Installing the bootstrap installer ...

WARNING: A REBOOT IS REQUIRED TO LOAD THIS SOFTWARE CORRECTLY. Use the
WARNING: 'request system reboot' command when software installation is
WARNING: complete. To abort the installation, do not reboot your system,
WARNING: instead use the 'request system software delete jinstall'
WARNING: command as soon as this operation completes.

Saving package file in /var/sw/pkg/jinstall-9.0R1.2-domestic-signed.tgz ...
cp: /var/tmp/paeBi5 is a directory (not copied).
Saving state for rollback ...
ISSU: Old Master Upgrade Done
ISSU: IDLE

```

5. Issue the **show version invoke-on all-routing-engines** command to verify that the new backup (old master) Routing Engine (**re0**), is still running the previous software image, while the new master Routing Engine (**re1**) is running the new software image:

```

{backup}

user@host> show version
re0:
-----
Hostname: user
Model: m320
JUNOS Base OS boot [9.0R1]
JUNOS Base OS Software Suite [9.0R1]
JUNOS Kernel Software Suite [9.0R1]
JUNOS Crypto Software Suite [9.0R1]

```

```

JUNOS Packet Forwarding Engine Support (M/T Common) [9.0R1]
JUNOS Packet Forwarding Engine Support (M320) [9.0R1]
JUNOS Online Documentation [9.0R1]
JUNOS Routing Software Suite [9.0R1]
labpkg [7.0]
JUNOS Installation Software [9.0R1.2]

```

```
re1:
```

```

-----
Hostname: user1
Model: m320
JUNOS Base OS boot [9.0R1.2]
JUNOS Base OS Software Suite [9.0R1.2]
JUNOS Kernel Software Suite [9.0R1.2]
JUNOS Crypto Software Suite [9.0R1.2]
JUNOS Packet Forwarding Engine Support (M/T Common) [9.0R1.2]
JUNOS Packet Forwarding Engine Support (M320) [9.0R1.2]
JUNOS Online Documentation [9.0R1.2]
JUNOS Routing Software Suite [9.0R1.2]

```

6. At this point, if you choose not to install the newer software version on the new backup Routing Engine (**re1**), you can issue the **request system software delete jinstall** command on it. Otherwise, to complete the upgrade, go to the next step.
7. Reboot the new backup Routing Engine (**re0**) by issuing the **request system reboot** command:

```
{backup}
```

```

user@host> request system reboot
Reboot the system ? [yes,no] (no) yes

```

```

Shutdown NOW!
Reboot consistency check bypassed - jinstall 9.0R1.2 will complete installation
upon reboot
[pid 6170]

```

```

{backup}
user@host>
System going down IMMEDIATELY

```

```

Connection to host closed by remote host.
Connection to host closed.

```

If you are not on the console port, you are disconnected from the router session.

8. After waiting a few minutes, log in to the router again. You are logged in to the new backup Routing Engine (**re0**). To verify that both Routing Engines have been upgraded, issue the following command:

```
{backup}
```

```

user@host> show version invoke-on all-routing-engines
re0:

```

```

-----
Hostname: host
Model: m320
JUNOS Base OS boot [9.0R1.2]
JUNOS Base OS Software Suite [9.0R1.2]
JUNOS Kernel Software Suite [9.0R1.2]
JUNOS Crypto Software Suite [9.0R1.2]

```

```
JUNOS Packet Forwarding Engine Support (M/T Common) [9.0R1.2]
JUNOS Packet Forwarding Engine Support (M320) [9.0R1.2]
JUNOS Online Documentation [9.0R1.2]
JUNOS Routing Software Suite [9.0R1.2]
```

```
re1:
```

```
-----
Hostname: host1
Model: m320
JUNOS Base OS boot [9.0R1.2]
JUNOS Base OS Software Suite [9.0R1.2]
JUNOS Kernel Software Suite [9.0R1.2]
JUNOS Crypto Software Suite [9.0R1.2]
JUNOS Packet Forwarding Engine Support (M/T Common) [9.0R1.2]
JUNOS Packet Forwarding Engine Support (M320) [9.0R1.2]
JUNOS Online Documentation [9.0R1.2]
JUNOS Routing Software Suite [9.0R1.2]
```

9. To make **re0** the master Routing Engine, issue the following command:

```
{backup}
```

```
user@host> request chassis routing-engine master acquire
Attempt to become the master routing engine ? [yes,no] (no) yes
```

```
Resolving mastership...
Complete. The local routing engine becomes the master.
```

```
{master}
user@host>
```

10. Issue the **request system snapshot** command on *each* Routing Engine to back up the system software to the router's hard disk.



NOTE: The root file system is backed up to `/altroot`, and `/config` is backed up to `/altconfig`. After you issue the **request system snapshot** command, the router's flash and hard disks are identical. You can return to the previous version of the software only by booting the router from removable media.

Upgrading and Rebooting Only One Routing Engine

When you issue the **request system software in-service-upgrade** command with the **no-old-master-upgrade** option, the system upgrades and reboots only the new master Routing Engine. To upgrade the new backup (former master) Routing Engine, you must issue the **request system software add** command.

To perform a unified ISSU using the **request system software in-service-upgrade package-name no-old-master-upgrade** commands, complete the following steps:

1. Download the software package from the Juniper Networks Support website, <http://www.juniper.net/support/>. Choose the Canada and U.S., Worldwide, or Junos-FIPS edition. Place the package on a local server. To download the package, you must have a service contract and an access account. If you do not have an access account, complete the registration form at the Juniper Networks website: <https://www.juniper.net/registration/Register.jsp>.

2. Copy the package to the router. We recommend that you copy it to the **/var/tmp** directory, which is a large file system on the hard disk.

```
user@host>file copy ftp://username:prompt@ftp.hostname.net/filename/var/tmp/filename
```

3. To verify the current software version running on both Routing Engines, on the master Routing Engine issue the **show version invoke-on all-routing-engines** command. The following example shows that both Routing Engines are running an image of Junos OS Release 9.0 that was built on December 11, 2007:

```
{backup}
```

```
user@host> show version invoke-on all-routing-engines
re0:
```

```
-----
Hostname: host
Model: m320
JUNOS Base OS boot [9.0-20071211.2]
JUNOS Base OS Software Suite 9.0-20071211.2]
JUNOS Kernel Software Suite [9.0-20071211.2]
JUNOS Crypto Software Suite [9.0-20071211.2]
JUNOS Packet Forwarding Engine Support (M/T Common) [9.0-20071211.2]
JUNOS Packet Forwarding Engine Support (M320) [9.0-20071211.2]
JUNOS Online Documentation [9.0-20071211.2]
JUNOS Routing Software Suite [9.0-20071211.2]
```

```
re1:
```

```
-----
Hostname: host1
Model: m320
JUNOS Base OS boot [9.0-20071211.2]
JUNOS Base OS Software Suite [9.0-20071211.2]
JUNOS Kernel Software Suite [9.0-20071211.20]
JUNOS Crypto Software Suite [9.0-20071211.2]
JUNOS Packet Forwarding Engine Support (M/T Common) [9.0-20071211.2]
JUNOS Packet Forwarding Engine Support (M320) [9.0-20071211.2]
JUNOS Online Documentation [9.0-20071211.2]
JUNOS Routing Software Suite [9.0-20071211.2]
```

4. On the master Routing Engine, issue the **request system software in-service-upgrade package-name no-old-master-upgrade** command. The following example upgrades the current version to an image of Junos OS Release 9.0 that was built on January 16, 2008:

```
{master}
```

```
user@host> request system software in-service-upgrade
/var/tmp/jinstall-9.0-20080116.2-domestic-signed.tgz no-old-master-upgrade
ISSU: Validating Image
ISSU: Preparing Backup RE
```

```

Pushing bundle to re1
Checking compatibility with configuration
Initializing...
Using jbase-9.0-20080116.2
Verified manifest signed by PackageProduction_9_0_0
Using /var/tmp/jinstall-9.0-20080116.2-domestic-signed.tgz
Verified jinstall-9.0-20080116.2-domestic.tgz signed by PackageProduction_9_0_0
Using jinstall-9.0-20080116.2-domestic.tgz
Using jbundle-9.0-20080116.2-domestic.tgz
Checking jbundle requirements on /
Using jbase-9.0-20080116.2.tgz
Verified manifest signed by PackageProduction_9_0_0
Using jkernel-9.0-20080116.2.tgz
Verified manifest signed by PackageProduction_9_0_0
Using jcrypto-9.0-20080116.2.tgz
Verified manifest signed by PackageProduction_9_0_0
Using jpfe-9.0-20080116.2.tgz
Using jdocs-9.0-20080116.2.tgz
Verified manifest signed by PackageProduction_9_0_0
Using jroute-9.0-20080116.2.tgz
Verified manifest signed by PackageProduction_9_0_0
Hardware Database regeneration succeeded
Validating against /config/juniper.conf.gz
mgd: commit complete
Validation succeeded
Installing package '/var/tmp/jinstall-9.0-20080116.2-domestic-signed.tgz' ...
Verified jinstall-9.0-20080116.2-domestic.tgz signed by PackageProduction_9_0_0
Adding jinstall...
Verified manifest signed by PackageProduction_9_0_0

WARNING: This package will load JUNOS 9.0-20080116.2 software.
WARNING: It will save JUNOS configuration files, and SSH keys
WARNING: (if configured), but erase all other files and information
WARNING: stored on this machine. It will attempt to preserve dumps
WARNING: and log files, but this can not be guaranteed. This is the
WARNING: pre-installation stage and all the software is loaded when
WARNING: you reboot the system.

Saving the config files ...
NOTICE: uncommitted changes have been saved in
/var/db/config/juniper.conf.pre-install
Installing the bootstrap installer ...

WARNING: A REBOOT IS REQUIRED TO LOAD THIS SOFTWARE CORRECTLY. Use the
WARNING: 'request system reboot' command when software installation is
WARNING: complete. To abort the installation, do not reboot your system,
WARNING: instead use the 'request system software delete jinstall'
WARNING: command as soon as this operation completes.

Saving package file in /var/sw/pkg/jinstall-9.0-20080116.2-domestic-signed.tgz
...
Saving state for rollback ...
Backup upgrade done
Rebooting Backup RE

Rebooting re1
ISSU: Backup RE Prepare Done
Waiting for Backup RE reboot
GRES operational
Initiating Chassis In-Service-Upgrade
Chassis ISSU started

```

```

ISSU: Backup RE Prepare Done
ISSU: Preparing Daemons
ISSU: Daemons Ready for ISSU
ISSU: Starting Upgrade for FRUs
ISSU: Preparing for Switchover
ISSU: Ready for Switchover
Checking In-Service-Upgrade status
  Item           Status           Reason
  FPC 0          Online (ISSU)
  FPC 1          Online (ISSU)
  FPC 2          Online (ISSU)
  FPC 3          Online (ISSU)
  FPC 5          Online (ISSU)
Resolving mastership...
Complete. The other routing engine becomes the master.
ISSU: RE switchover Done
Skipping Old Master Upgrade
ISSU: IDLE

{backup}
user@host>

```

5. You are now logged in to the new backup (old master Routing Engine). If you want to install the new software version on the new backup Routing Engine, issue the **request system software add /var/tmp/jinstall-9.0-20080116.2-domestic-signed.tgz** command.

Related Documentation

- [Unified ISSU System Requirements on page 73](#)
- [Best Practices on page 259](#)
- [Before You Begin on page 259](#)
- [Verifying a Unified ISSU on page 274](#)
- [Troubleshooting Unified ISSU Problems on page 279](#)
- [Managing and Tracing BFD Sessions During Unified ISSU Procedures on page 189](#)

Verifying a Unified ISSU

To verify the status of FPCs and their corresponding PICs after the most recent unified ISSU, issue the **show chassis in-service-upgrade** command on the master Routing Engine:

```

user@host> show chassis in-service-upgrade
  Item           Status           Reason
  FPC 0          Online
  FPC 1          Online
  FPC 2          Online
  PIC 0          Online
  PIC 1          Online
  FPC 3          Offline          Offlined by CLI command
  FPC 4          Online
  PIC 1          Online
  FPC 5          Online
  PIC 0          Online
  FPC 6          Online

```

PIC 3 Online
FPC 7 Online

For more information about the **show chassis in-service-upgrade** command, see the Junos OS Operational Mode Commands.

**Related
Documentation**

- [Performing a Unified ISSU on page 262](#)
- [Troubleshooting Unified ISSU Problems on page 279](#)
- [Managing and Tracing BFD Sessions During Unified ISSU Procedures on page 189](#)

PART 4

Troubleshooting

- [Unified ISSU on page 279](#)

CHAPTER 24

Unified ISSU

- [Troubleshooting Unified ISSU Problems on page 279](#)

Troubleshooting Unified ISSU Problems

If the unified ISSU procedure stops progressing, complete the following steps:

1. Open a new session on the master Routing Engine and issue the **request system software abort in-service-upgrade** command.
2. Check the existing router session to verify that the upgrade has been aborted.

An “ISSU: aborted!” message is provided. Additional system messages provide you with information about where the upgrade stopped and recommendations for the next step to take.

For more information about the **request system software abort in-service-upgrade** command, see the Junos OS Operational Mode Commands.

Related Documentation

- [Unified ISSU Concepts on page 67](#)
- [Unified ISSU Process on the TX Matrix Router on page 72](#)
- [Unified ISSU System Requirements on page 73](#)
- [Best Practices on page 259](#)
- [Performing a Unified ISSU on page 262](#)
- [Verifying a Unified ISSU on page 274](#)
- [Managing and Tracing BFD Sessions During Unified ISSU Procedures on page 189](#)

PART 5

Index

- [Index on page 283](#)

Index

Symbols

#, comments in configuration statements.....	xviii
(), in syntax descriptions.....	xviii
< >, in syntax descriptions.....	xviii
[], in configuration statements.....	xviii
{ }, in configuration statements.....	xviii
(pipe), in syntax descriptions.....	xviii

A

accept-data statement.....	232
usage guidelines.....	168
advertise-interval statement.....	233
usage guidelines.....	163
advertisement intervals, VRRP.....	163
aggregate routes	
graceful restart.....	49
all (tracing flag).....	111
asymmetric-hold-time statement.....	234
configuring for VRRP routers.....	167
authentication, VRRP.....	162
authentication-key statement.....	235
usage guidelines.....	162
authentication-type statement.....	236
usage guidelines.....	162

B

backup routers, VRRP.....	59
bandwidth-threshold statement.....	237
usage guidelines.....	169
BFD, nonstop active routing.....	42
BGP	
graceful restart.....	49
nonstop active routing.....	39
unified ISSU.....	74
Bidirectional Forwarding Detection See BFD	
Border Gateway Protocol See BGP	
braces, in configuration statements.....	xviii
brackets	
angle, in syntax descriptions.....	xviii
square, in configuration statements.....	xviii

C

CCC, graceful restart.....	49
CFEB redundancy	
configuring.....	93
overview.....	17
cfeb statement.....	197
usage guidelines.....	93
circuit cross-connect See CCC	
comments, in configuration statements.....	xviii
commit synchronize statement.....	109
usage guidelines.....	106
Compact Forwarding Engine Board See CFEB	
redundancy	
config-internal (tracing flag).....	111
configuration files, copying between Routing Engines.....	195
conventions	
text and syntax.....	xvii
curly braces, in configuration statements.....	xviii
customer support.....	xix
contacting JTAC.....	xix

D

description statement.....	198
usage guidelines.....	94
disable statement.....	217
traceoption.....	111
usage guidelines	
aggregate routes.....	117
BGP.....	119
ES-IS.....	120
global.....	118, 124, 126, 128
IS-IS.....	120
OSPF.....	121
OSPFv3.....	121
PIM.....	122
RIP.....	122
RIPng.....	122
routing instances.....	127
routing instances inside a logical system.....	128
RSVP.....	125
static routes.....	117
distributed pmd process.....	175
documentation	
comments on.....	xix

E

ES-IS

graceful restart.....49

F

failover on-disk-failure statement

usage guidelines.....90

failover on-loss-of-keepalives statement

usage guidelines.....90

failover other-routing-engine statement

usage guidelines.....92

failover statement

disk or keepalive failure.....198

software process failure.....199

fast-interval statement.....239

usage guidelines.....164

FEB redundancy

configuration example.....95

configuring.....94

overview.....17

feb statement

assigning a FEB to a redundancy group.....200

creating a redundancy group.....200

usage guidelines.....94

file copy command

usage guidelines.....195

flash (tracing flag).....111

font conventions.....xvii

Forwarding Engine Board See FEB redundancy

G

general (tracing flag).....111

global-advertisements-threshold statement.....240

graceful restart

commands, operational mode.....214

concepts.....49

configuration procedure

aggregate routes.....117

MPLS protocols.....124

routing protocols.....118

static routes.....117

VPNs.....126

overview

aggregate routes.....51

MPLS protocols.....54

routing protocols.....51

static routes.....51

VPNs.....56

protocol support.....49

sample configuration.....129

system requirements.....50

trace options.....124

verifying operation of.....214

graceful Routing Engine switchover

concepts.....21

DPC support.....28

enabling.....101

feature support.....26

PIC support.....28

platform support.....26

subscriber access support.....28

system architecture.....22

system requirements.....25

verifying status of.....102

graceful-restart statement.....218

usage guidelines

aggregate routes.....117

BGP.....119

global.....118, 124, 126, 128

IS-IS.....120

LDP.....125

OSPF.....121

OSPFv3.....121

PIM.....122

RIP.....122

RIPng.....122

routing instances.....127

routing instances inside a logical

system.....128

RSVP.....125

static routes.....117

graceful-switchover statement.....102

usage guidelines.....101

H

helper-disable statement.....219

usage guidelines

IS-IS.....120

LDP.....125

OSPF.....121

OSPFv3.....121

RSVP.....125

high availability features

interchassis redundancy.....7

overview.....3

unified ISSU.....67

Virtual Chassis.....7

VRRP.....	59
VRRPv3.....	60
hold-time statement.....	241

I

in-service software upgrade See unified ISSU	
inet6-advertise-interval statement.....	242
usage guidelines.....	164
initial configuration, redundant Routing Engines.....	98
interchassis redundancy See Virtual Chassis	
interface statement	
VRRP.....	243
usage guidelines.....	169
Intermediate System-to-Intermediate System See IS-IS	
IS-IS	
IS-IS	
graceful restart.....	49
nonstop active routing.....	39
unified ISSU.....	74
ISSU See unified ISSU	

K

keepalive-time statement.....	201
usage guidelines.....	90
kernel (tracing flag).....	111

L

L2CKT, nonstop active routing.....	43
Label Distribution Protocol See LDP	
LACP	
unified ISSU.....	75
Layer 2 circuits	
nonstop active routing.....	39, 43
unified ISSU.....	74
Layer 2 circuits, nonstop active routing.....	39, 43
Layer 2 VPNs	
nonstop active routing.....	39
Layer 3 VPNs	
nonstop active routing.....	39
unified ISSU.....	74
LDP	
graceful restart.....	49
nonstop active routing.....	39
unified ISSU.....	74
LDP-based VPLS, nonstop active routing.....	43

M

manuals	
comments on.....	xix
master router, VRRP.....	59
maximum-helper-recovery-time statement.....	219
usage guidelines.....	125
maximum-helper-restart-time statement.....	220
usage guidelines.....	125
maximum-neighbor-reconnect-time	
usage guidelines.....	125
maximum-neighbor-reconnect-time statement.....	220
maximum-neighbor-recovery-time statement.....	221
usage guidelines.....	125
maximum-recovery-time statement.....	221
MPLS, graceful restart.....	49
MSDP	
nonstop active routing.....	39
MSTP, nonstop bridging.....	34
Multiple Spanning Tree Protocol See MSTP	
MX Series Virtual Chassis See Virtual Chassis	

N

next-generation RIP See RIPng	
no-accept-data statement.....	232
usage guidelines.....	168
no-auto-failover statement.....	202
usage guidelines.....	94
no-issu-timer-negotiation statement.....	190
usage guidelines.....	189
no-preempt statement.....	244
usage guidelines.....	166
no-strict-lsa-checking statement.....	222
usage guidelines	
OSPF.....	121
OSPFv3.....	121
nonstop active routing	
concepts.....	35
enabling.....	105
platform support.....	38
protocol support.....	39
sample configuration.....	113
system architecture.....	35
system requirements.....	38
trace options.....	107
verifying status of	106
nonstop bridging	
concepts.....	31
enabling.....	103

platform support.....	33
protocol support.....	34
system architecture.....	32
system requirements.....	33
verifying status of	104
nonstop-bridging statement.....	104
usage guidelines.....	103
nonstop-routing statement.....	110
usage guidelines.....	105
normal (tracing flag).....	111
notify-duration statement.....	223
usage guidelines.....	121
NSR See nonstop active routing	

O

on-disk-failure statement.....	202
on-loss-of-keepalives statement.....	203
Open Shortest Path First See OSPF	
OSPF	
graceful restart.....	49
nonstop active routing.....	39
unified ISSU.....	74
OSPFv3	
nonstop active routing.....	39
unified ISSU.....	74

P

parentheses, in syntax descriptions.....	xviii
parse (tracing flag).....	111
passive ARP learning, VRRP.....	174
periodic packet management process.....	175
PIM	
unified ISSU.....	74
PIM, graceful restart.....	49
PIM, nonstop active routing.....	44
policy (tracing flag).....	111
ppmd process.....	175
preempt statement.....	244
usage guidelines.....	166
preempting master router, VRRP.....	166
priority statement.....	245
usage guidelines.....	160
priority-cost statement.....	246
usage guidelines.....	169
priority-hold-time statement.....	247
usage guidelines.....	169, 171
Protocol Independent Multicast See PIM	

R

Rapid Spanning Tree Protocol See RSTP	
reconnect-time statement.....	224
usage guidelines.....	125
recovery-time statement.....	225
usage guidelines.....	125
redundancy feb statement	
usage guidelines.....	94
redundancy statement.....	204
usage guidelines.....	97
redundancy-group statement.....	205
usage guidelines.....	94
regex-parse (tracing flag).....	111
request chassis cfeb master switch command	
usage guidelines.....	93
request chassis redundancy feb command	
usage guidelines.....	94
request chassis routing-engine master acquire command	
usage guidelines.....	92
request chassis routing-engine master release command	
usage guidelines.....	92
request chassis routing-engine master switch command	
usage guidelines.....	92
request chassis sfm master switch command	
usage guidelines.....	96
request chassis ssb master switch command	
usage guidelines.....	97
request routing-engine login command	
usage guidelines.....	195
request system software add command	
usage guidelines.....	196
Resource Reservation Protocol See RSVP	
restart-duration statement.....	226
usage guidelines	
ES-IS.....	120
global.....	118, 124, 126, 128
IS-IS.....	120
OSPF	121
OSPFv3.....	121
PIM.....	122
routing instances.....	127
routing instances inside a logical system.....	128

-
- restart-time statement.....227
 - usage guidelines
 - BGP.....119
 - RIP.....122
 - RIPng.....122
 - RIP
 - graceful restart.....49
 - nonstop active routing.....39
 - RIPng
 - graceful restart.....49
 - nonstop active routing.....39
 - route (tracing flag)
 - routing.....111
 - route statement
 - VRRP.....248
 - usage guidelines.....171
 - Routing Engine redundancy
 - copying configuration files.....195
 - default behavior.....13
 - failover
 - conditions.....12
 - on loss of keepalive signal.....90
 - graceful Routing Engine switchover.....90
 - halting Routing Engines.....16
 - initial configuration.....98
 - log file, viewing.....92
 - mastership
 - default setup, modifying.....89
 - switching, manually.....92
 - overview.....11
 - software packages, loading196
 - TX Matrix Plus, running the same Junos OS
 - release.....15
 - TX Matrix, running the same Junos OS
 - release.....13
 - Routing Engine switchover effects
 - comparison of high availability features.....7, 25
 - Routing Information Protocol See RIP
 - Routing Information Protocol next generation See RIPng
 - routing-engine statement.....206
 - usage guidelines.....89
 - RSTP, nonstop bridging.....34
 - RSVP
 - graceful restart.....49
 - S**
 - set delegate-processing statement.....175
 - SFM redundancy
 - configuring.....96
 - overview.....20
 - sfm statement.....207
 - usage guidelines.....96
 - show bgp replication command
 - usage guidelines.....106
 - show chassis cfeb command
 - usage guidelines.....93
 - show chassis feb command
 - usage guidelines.....94
 - show chassis sfm command
 - usage guidelines.....96
 - show chassis ssb command
 - usage guidelines.....97
 - show task replication command
 - usage guidelines.....106
 - skew-timer-disable statement.....249
 - software packages
 - transferring between Routing Engines.....196
 - Spanning Tree Protocol See STP
 - SSB redundancy
 - configuring.....97
 - overview.....19
 - ssb statement.....208
 - usage guidelines.....97
 - stale-routes-time statement.....228
 - usage guidelines.....119
 - startup period, VRRP.....159
 - startup-silent-period statement.....249
 - usage guidelines.....159
 - state (tracing flag)
 - routing protocols.....111
 - static routes
 - graceful restart.....49
 - STP, nonstop bridging.....34
 - support, technical See technical support
 - Switching and Forwarding Module See SFM
 - redundancy
 - switching control board redundancy See CFEB
 - redundancy, FEB redundancy, SFM redundancy, SSB redundancy
 - synchronizing Routing Engines
 - graceful Routing Engine switchover.....101
 - nonstop active routing.....106
 - Routing Engine redundancy.....103
 - syntax conventions.....xvii
 - System and Switch Board See SSB redundancy

system requirements		
graceful restart.....	50	
graceful Routing Engine switchover.....	25	
nonstop active routing.....	38	
nonstop bridging.....	33	
unified ISSU.....	73	
T		
task (tracing flag).....	111	
TCC, graceful restart.....	49	
technical support		
contacting JTAC.....	xix	
timer (tracing flag).....	111	
traceoptions statement		
graceful restart	229	
usage guidelines.....	124	
nonstop active routing.....	111	
usage guidelines.....	107	
routing protocols.....	111	
unified ISSU.....	191	
VRRP.....	250	
usage guidelines.....	187	
tracing flags		
all.....	111	
config-internal.....	111	
flash.....	111	
general.....	111	
kernel.....	111	
normal.....	111	
parse.....	111	
policy.....	111	
regex-parse.....	111	
route		
routing.....	111	
state		
routing protocols.....	111	
task.....	111	
timer.....	111	
tracing operations		
routing protocols.....	111	
track statement.....	252	
usage guidelines.....	169, 171	
translational cross-connect See TCC		
TX Matrix Plus router		
Routing Engine redundancy.....	15	
TX Matrix router		
Routing Engine redundancy.....	13	
U		
unified in-service software upgrade See unified ISSU		
unified ISSU		
concepts.....	67	
configuration procedure		
best practices.....	259	
performing an.....	262	
preparing for.....	259	
DPC support.....	84	
MIC support.....	84	
MPC support.....	84	
PIC support		
ATM.....	82	
channelized.....	80	
DS3.....	83	
E1.....	83	
E3 IQ.....	83	
Fast Ethernet.....	79	
FPC/PIC compatibility.....	76, 84	
Gigabit Ethernet.....	79	
restrictions.....	77	
serial.....	82	
SONET/SDH.....	77	
T1.....	83	
tunnel services.....	81	
platform support.....	74	
protocol support.....	74	
system requirements.....	73	
troubleshooting.....	279	
verifying status of.....	274	
V		
version-3 statement.....	253	
Virtual Router Redundancy Protocol See VRRP See VRRPv3		
virtual-address statement.....	254	
usage guidelines.....	160	
virtual-inet6-address statement.....	254	
usage guidelines.....	160	
virtual-link-local-address statement.....	255	
usage guidelines.....	160	
VPLS		
nonstop active routing.....	39	
VPNs, graceful restart.....	49	
VRRP		
advertisement interval.....	163	
asymmetric hold time.....	167	
authentication.....	162	

basic configuration.....	160
group	
inheritance.....	172
overview.....	59
passive ARP learning.....	174
preempting master router.....	166
sample configuration.....	177
trace operations.....	187
tracking logical interface status.....	169
tracking route status.....	171
vrrp	
global-advertisements-threshold.....	240
skew-timer-disable.....	249
version-3.....	253
vrrp-group statement.....	256
usage guidelines.....	160
vrrp-inet6-group statement.....	257
usage guidelines.....	160
vrrpd process.....	175
VRRPv3	
overview.....	60

