

# Release Notes

Published  
2026-07-30

## Release Notes 26.1

---

# Table of Contents

|                                   |    |
|-----------------------------------|----|
| Introduction .....                | 2  |
| New And Changed Features.....     | 2  |
| Installation Instructions .....   | 2  |
| Upgrade Instructions .....        | 3  |
| Management Scalability .....      | 8  |
| Application Compatibility .....   | 9  |
| Supported Hardware .....          | 9  |
| Supported Devices .....           | 10 |
| Supported Junos Os Releases ..... | 24 |
| Changes In Default Behavior ..... | 24 |
| Known Behavior .....              | 26 |
| Known Issues .....                | 32 |
| Resolved Issues .....             | 32 |
| Hot Patch Releases .....          | 33 |
| Revision History.....             | 36 |

# Introduction

Junos Space is a comprehensive network management solution that simplifies and automates management of Juniper Networks switching, routing, and security devices.

Junos Space Management Applications optimize network management by extending the breadth of the Junos Space solution for various domains in service provider and enterprise environments.

These release notes accompany Junos Space Network Management Platform Release 26.1. The terms Junos Space Network Management Platform and Junos Space Platform are used interchangeably in this document.

## New and Changed Features

There are no new features or enhancements to existing features in Junos Space® Network Management Platform Release 26.1R1.

## Installation Instructions

Junos Space Network Management Platform Release 26.1R1 can be installed on a Junos Space Virtual Appliance.



**CAUTION:** During the Junos Space Network Management Platform installation process, do not modify the filename of the software image that you download from the Juniper Networks support site. If you modify the filename, the installation fails.

For installation instructions for the Junos Space Virtual Appliance, refer to the [Junos Space Virtual Appliance Deployment Overview](#) section in the [Junos Space Virtual Appliance Installation and Configuration Guide](#).

# Upgrade Instructions

This section provides information about upgrading the Junos Space Network Management Platform installations running versions earlier than Release 26.1R1.

You can download the supported Applications such as Security Director and Policy Enforcer whenever they are available on the download site Junos Space Network Management Platform

## Supported Upgrade Path

[Table 1](#) provides information on the supported upgrade path across Junos Space Network Management Platform releases.

**Table 1: Supported Upgrade Path**

| Upgrade from Junos Space Release | Junos Space Network Management Platform Release |      |
|----------------------------------|-------------------------------------------------|------|
|                                  | 24.1                                            | 26.1 |
| 23.1                             | Yes                                             | -    |
| 24.1                             | -                                               | Yes  |

You can upgrade directly to Junos Space Network Management Platform Release 26.1R1 from the following versions:

- Junos Space Network Management Platform Release 24.1R1 → Junos Space Network Management Platform Release 26.1R1
- Junos Space Network Management Platform Release 24.1R5 → Junos Space Network Management Platform Release 26.1R1

If you are currently on Junos Space Network Management Platform Release 24.1R2, 24.1R3, or 24.1R4, first upgrade to Junos Space Network Management Platform Release 24.1R5 and then upgrade to Junos Space Network Management Platform Release 26.1R1.

Before you upgrade Junos Space Platform to Release 26.1, ensure that the time on all Junos Space nodes is synchronized. For information about synchronizing time on Junos Space nodes, see [Synchronizing Time Across Junos Space Nodes](#).

**CAUTION:** During the Junos Space Network Management Platform upgrade process, do not modify the filename of the software image that you download from the Juniper Networks support site. If you modify the filename, the upgrade fails.

## Supported Upgrade Path for Junos Space Network Management Platform 24.1 Releases

The below table provides information about the supported upgrade paths for Junos Space Network Management Platform 24.1 Releases.

| Junos Space Network Management Platform Release | Supported Upgrade Path for Junos Space Platform Release 24.1 |        |        |        |        |
|-------------------------------------------------|--------------------------------------------------------------|--------|--------|--------|--------|
|                                                 | 24.1R1                                                       | 24.1R2 | 24.1R3 | 24.1R4 | 24.1R5 |
| 23.1R1                                          | Yes                                                          | -      | -      | -      | -      |
| 24.1R1                                          | -                                                            | Yes    | Yes    | Yes    | Yes    |
| 24.1R2                                          | -                                                            | -      | Yes    | -      | -      |
| 24.1R3                                          | -                                                            | -      | -      | Yes    | -      |
| 24.1R4                                          | -                                                            | -      | -      | -      | Yes    |

## Upgrade Notes

- Before the upgrade, ensure that the latest backups are available in a location other than the Junos Space server. For more information about backups, see [Backing Up the Junos Space Network Management Platform Database](#).
- To upgrade to Junos Space Network Management Platform Release 24.1, follow the procedure mentioned in [Upgrade to Junos Space Network Management Platform Release 24.1R1](#).
- To upgrade to Junos Space Network Management Platform Release 26.1R1, follow the procedure mentioned in [Upgrading Junos Space Network Management Platform](#).
- During the upgrade process, do not manually reboot the nodes if the Junos Space user interface does not come up for an extended period. Contact the Juniper Networks Support team for help in resolving this issue.
- After you upgrade Junos Space Platform to Release 26.1R1, all previously installed applications are disabled until the applications are upgraded to a version compatible with Junos Space Platform 26.1R1. You must upgrade the applications to releases that are compatible with Junos Space Platform Release 26.1R1, by using the Junos Space Platform UI.

## Instructions for Validating the Junos Space Network Management Platform OVA Image

From Junos Space Network Management Platform Release 14.1R1 onward, the Junos Space Platform open virtual appliance (OVA) image is securely signed.

### Notes:

- Validating the OVA image is optional; you can install or upgrade Junos Space Network Management Platform without validating the OVA image.
- Before you validate the OVA image, ensure that the PC on which you are performing the validation has the following utilities available: tar, openssl, and ovftool (VMWare Open Virtualization Format (OVF) Tool). You can download VMWare OVF Tool from the following location:  
<https://my.vmware.com/web/vmware/downloads/details?productId=353&downloadGroup=OVFTOOL35>

To validate the Junos Space Network Management Platform OVA image:

1. Download the Junos Space Platform OVA image and the Juniper Networks Root CA certificate chain file (JuniperRootRSACA.pem) from the Junos Space Network Management Platform - Download Software page at <https://www.juniper.net/support/downloads/space.html>.  
You need to download the Juniper Networks Root CA certificate chain file only once; you can use the same file to validate OVA images for future releases of Junos Space Network Management Platform.

2. (Optional) If you downloaded the OVA image and the Root CA certificate chain file to a PC running Windows, copy the two files to a temporary directory on a PC running Linux or Unix. You can also copy the OVA image and the Root CA certificate chain file to a temporary directory (/var/tmp or /tmp) on a Junos Space node.

Ensure that the OVA image file and the Juniper Networks Root CA certificate chain file are not modified during the validation procedure. You can do this by providing write access to these files only to the user performing the validation procedure. This is especially important if you use a generally accessible temporary directory, such as /tmp or /var/tmp, because such directories can be accessed by several users

3. Navigate to the directory containing the OVA image.
4. Unpack the OVA image by executing the following command:

`tar xf ova-filename` where *ova-filename* is the filename of the downloaded OVA image.

5. Verify that the unpacked OVA image contains a certificate chain file (junos-space-certchain.pem) and a signature file (.cert extension).
6. Validate the signature in the unpacked OVF file (extension .ovf) by executing the following command:  
`ovftool ovf-filename`, where *ovf-filename* is the filename of the unpacked OVF file.

7. Validate the signing certificate with the Juniper Networks Root CA certificate chain file by executing the following command:

`openssl verify -CAfile JuniperRootRSACA.pem -untrusted Certificate-Chain-File Signature-file`  
where **JuniperRootRSACA.pem** is the Juniper Networks Root CA certificate chain file, *Certificate-Chain-File* is the filename of the unpacked certificate chain file (extension .pem), and *Signature-file* is the filename of the unpacked signature file (extension .cert).

If the validation is successful, a message indicating that the validation is successful is displayed.

A sample of the validation procedure is as follows:

```
-bash-4.1$ ls
JuniperRootRSACA.pem space-16.1R1.3.ova
-bash-4.1$ mkdir tmp
-bash-4.1$ cd tmp
-bash-4.1$ tar xf ../space-16.1R1.3.ova
-bash-4.1$ ls junos-space-certchain.pem
space-16.1R1.3.cert      space-16.1R1.3-
disk1.vmdk.gz  space-16.1R1.3.mf  space-
16.1R1.3.ovf
-bash-4.1$ ovftool space-16.1R1.3.ovf
OVF version: 1.0
VirtualApp: false
Name:      viso-space-16.1R1.3
```

Download Size: 1.76 GB

#### Deployment Sizes:

Flat disks: 250.00 GB  
Sparse disks: 4.68 GB

#### Networks:

Name: VM Network  
Description: The VM Network network

#### Virtual Machines:

Name: viso-space-16.1R1.3  
Operating System: rhel5\_64guest

#### Virtual Hardware:

Families: vmx-04  
Number of CPUs: 4  
Cores per socket: 1  
Memory: 8.00 GB

#### Disks:

Index: 0  
Instance ID: 7  
Capacity: 250.00 GB  
Disk Types: SCSI-Isilogic

#### NICs:

```
Adapter Type: E1000
Connection: VM Network
```

```
Adapter Type: E1000
Connection: VM Network
```

```
Adapter Type: E1000
Connection: VM Network
```

```
Adapter Type: E1000
Connection: VM Network
```

```
-bash-4.1$ openssl verify -CAfile JuniperRootRSACA.pem -untrusted junos-space-
certchain.pem space-16.1R1.3.cert space-16.1R1.3.cert: OK
-bash-4.1$
```

8. (Optional) If the validation is not successful, perform the following tasks:
  - a. Determine whether the contents of the OVA image are modified. If the contents are modified, download the OVA image from the Junos Space Network Management Platform - Download Software page.
  - b. Determine whether the Juniper Networks Root CA certificate chain file is corrupted or modified. If it is corrupted or modified, download the Root CA certificate chain file from the Junos Space Network Management Platform - Download Software page.
  - c. Retry the preceding validation steps by using one or both of the new files.

## Management Scalability

We recommend the following API limit for Junos Space Network Management Platform and Security Director:

- RAM: 64GB
- CPU Cores: 8
- No of API calls per minutes: 500
- Response size: ~ 500 KB

The number of successful API calls and time taken to execute may vary based on the response payload. Extremely large payloads will slow down request completion process. The size of the response you receive from an API may differ based on the endpoint you call. Different endpoints return varying amounts of data depending on their intended functionality and purpose.

The number of API calls is limited to 250 requests per minute per source IP address. When you exceed the limit, Junos Space Network Management Platform blocks the IP address for a timespan of two minutes before unblocking the IP again.

## Application Compatibility



**WARNING :** Before you upgrade to Junos Space Network Management Platform Release 26.1R1, ensure that compatible versions of Junos Space applications are available for upgrade by referring to the Junos Space Application Compatibility [Junos Space Application Compatibility](#) knowledge base article. If you upgrade to Junos Space Platform Release 26.1R1 and the compatible version of a Junos Space application is not available, the current version of the Junos Space application is deactivated and cannot be used until Juniper Networks release a compatible version of the Junos Space application.

Junos Space Network Management Platform Release 26.1 supports Worldwide (ww) Junos OS Adapter and Security Director 26.1R1 application.

## Supported Hardware

Junos Space Network Management Platform Release 26.1R1 can be installed on the following hardware:

- VMware ESXi server 7.0 and 8.0.
- Kernel-based virtual machine (KVM) (Release 1.5.3-141.el7\_4.4 or later)

### Notes:

- Adobe Flash is no longer supported and VMware ESXi server 6.0 and 6.5 are removed.
- Starting in Junos Space Network Management Platform Release 22.3R1 onward we do not support installation on JA2500.

For detailed information about hardware requirements, see the *Hardware Documentation* section of the [Junos Space and Applications](#) page.

# Supported Devices

Junos Space Network Management Platform Release 26.1R1 supports the following additional Juniper Networks device and components running Junos OS:

Table 2 lists all the Juniper Networks product series and devices supported by Junos Space Network Management Platform.

**Table 2: Devices Supported by Junos Space Network Management Platform**

| Product Series | Model   | Junos Space Platform Release            |
|----------------|---------|-----------------------------------------|
| ACX Series     | ACX710  | Junos Space 20.1R1 hot patch v1or later |
|                | ACX1000 | Junos Space Platform 12.2 or later      |

| Product Series | Model       | Junos Space Platform Release         |
|----------------|-------------|--------------------------------------|
|                | ACX1100     | Junos Space Platform 12.3 or later   |
|                | ACX2100     | Junos Space Platform 12.3 or later   |
|                | ACX2200     | Junos Space Platform 12.3 or later   |
|                | ACX5448     | Junos Space Platform 18.4 or later   |
| EX Series      | EX2300      | Junos Space Platform 15.2R2 or later |
|                | EX2300-24MP | Junos Space Platform 18.1 or later   |
|                | EX2300-48MP | Junos Space Platform 17.2 or later   |
|                | EX3400      | Junos Space Platform 15.2R2 or later |
|                | EX4100-12T  | Junos Space Platform 22.3R1 or later |
|                | EX4100-24P  | Junos Space Platform 23.1R1 or later |
|                | EX4100-24T  | Junos Space Platform 23.1R1 or later |
|                | EX4100-48P  | Junos Space Platform 23.1R1 or later |
|                | EX4100-24MP | Junos Space Platform 23.1R1 or later |
|                | EX4100-48T  | Junos Space platform 22.3R1 or later |

|  |             |                                      |
|--|-------------|--------------------------------------|
|  | EX4100-48MP | Junos Space platform 22.3R1 or later |
|--|-------------|--------------------------------------|

| Product Series | Model        | Junos Space Platform Release         |
|----------------|--------------|--------------------------------------|
|                | EX4100-F-12P | Junos Space Platform 22.3R1 or later |
|                | EX4100-F-12T | Junos Space platform 22.3R1 or later |
|                | EX4100-F-24T | Junos Space Platform 22.3R1 or later |
|                | EX4100-F-24P | Junos Space Platform 23.1R1 or later |
|                | EX4100-F-48P | Junos Space platform 22.3R1 or later |
|                | EX4100-F-48T | Junos Space Platform 22.3R1 or later |
|                | EX4300       | Junos Space Platform 13.1 or later   |
|                | EX4300-48MP  | Junos Space Platform 18.3R1 or later |
|                | EX4400-24T   | Junos Space Platform 21.1R1 or later |
|                | EX4400-48F   | Junos Space Platform 21.1R1 or later |
|                | EX4400-48P   | Junos Space Platform 21.1R1 or later |
|                | EX4400-48T   | Junos Space Platform 21.1R1 or later |

|  |            |                                      |
|--|------------|--------------------------------------|
|  | EX4400-24X | Junos Space platform 23.1R1 or later |
|--|------------|--------------------------------------|

| Product Series     | Model       | Junos Space Platform Release         |
|--------------------|-------------|--------------------------------------|
|                    | EX4550-40G  | Junos Space Platform 12.2 or later   |
|                    | EX4600      | Junos Space Platform 13.3 or later   |
|                    | EX4650      | Junos Space Platform 18.4 or later   |
|                    | EX6200      | Junos Space Platform 13.2 or later   |
|                    | EX9200      | Junos Space Platform 13.1 or later   |
|                    | EX9204      | Junos Space Platform 13.1 or later   |
|                    | EX9208      | Junos Space Platform 13.1 or later   |
|                    | EX9214      | Junos Space Platform 13.1 or later   |
|                    | EX4400-24P  | Junos Space Platform 21.1R1 or later |
|                    | EX4400-24MP | Junos Space Platform 21.2 or later   |
|                    | EX4400-48MP | Junos Space Platform 21.2 or later   |
| EX Virtual Chassis | EX2300-VC   | Junos Space Platform 23.1R1          |
|                    | EX3300-VC   | Junos Space Platform 15.2 or later   |
|                    | EX3400-VC   | Junos Space Platform 23.1R1          |
|                    | EX4100-VC   | Junos Space Platform 22.3R1          |
|                    | EX4200-VC   | Junos Space Platform 11.4 or later   |

|  |           |                                    |
|--|-----------|------------------------------------|
|  | EX4200-VC | Junos Space Platform 11.4 or later |
|  | EX4300-VC | Junos Space Platform 13.1 or later |

| Product Series            | Model                         | Junos Space Platform Release         |
|---------------------------|-------------------------------|--------------------------------------|
|                           | EX4400-VC                     | Junos Space Platform 23.1R1          |
|                           | EX4550-VC                     | Junos Space Platform 13.1 or later   |
|                           | EX4600-VC                     | Junos Space Platform 16.1 or later   |
|                           | EX-XRE                        | Junos Space Platform 14.1R2 or later |
| Firefly                   | vSRX Virtual Firewall Firefly | Junos Space Platform 15.1 or later   |
| Junos Fusion              | Junos Fusion Edge             | Junos Space Platform 17.1 or later   |
| MCG Series                | MCG5000                       | Junos Space Platform 11.3 or later   |
| MX Series                 | MX204                         | Junos Space Platform 18.2 or later   |
|                           | MX240                         | Junos Space Platform 13.1 or later   |
|                           | MX480                         | Junos Space Platform 13.1 or later   |
|                           | MX960                         | Junos Space Platform 13.1 or later   |
|                           | MX10008                       | Junos Space Platform 18.4 or later   |
|                           | MX2008                        | Junos Space Platform 17.1 or later   |
|                           | MX2010                        | Junos Space Platform 12.3 or later   |
|                           | MX2020                        | Junos Space Platform 12.3 or later   |
| MX Series Virtual Chassis | MX-VC                         | Junos Space Platform 14.1 or later   |

|            |          |                                    |
|------------|----------|------------------------------------|
| PTX Series | PTX10008 | Junos Space Platform 17.2 or later |
|            | PTX10016 | Junos Space Platform 17.2 or later |

| Product Series | Model           | Junos Space Platform Release         |
|----------------|-----------------|--------------------------------------|
| QFX Series     | QFX3000         | Junos Space Platform 12.2 or later   |
|                | QFX3500         | Junos Space Platform 12.3 or later   |
|                | QFX3600         | Junos Space Platform 13.1 or later   |
|                | QFX5110-32Q     | Junos Space Platform 17.1 or later   |
|                | QFX5110-48S     | Junos Space Platform 17.1 or later   |
|                | QFX5120-32C     | Junos Space Platform 19.4 or later   |
|                | QFX5120         | Junos Space Platform 18.4 or later   |
|                | QFX5210         | Junos Space Platform 18.4 or later   |
|                | QFX5200         | Junos Space Platform 15.1R2 or later |
|                | QFX5200-48Y     | Junos Space Platform 18.1 or later   |
|                | QFX5210-64C     | Junos Space Platform 18.1 or later   |
|                | QFX10002-36Q    | Junos Space Platform 15.1 or later   |
|                | QFX10002-36Q-DC | Junos Space Platform 15.1 or later   |

|  |                 |                                      |
|--|-----------------|--------------------------------------|
|  | QFX10002-60C    | Junos Space Platform 18.1 or later   |
|  | QFX10002-72Q    | Junos Space Platform 15.1 or later   |
|  | QFX10002-72Q-DC | Junos Space Platform 15.1 or later   |
|  | QFX10008        | Junos Space Platform 15.1R2 or later |

| Product Series             | Model           | Junos Space Platform Release         |
|----------------------------|-----------------|--------------------------------------|
|                            | QFX10016        | Junos Space Platform 15.1R2 or later |
|                            | QFX5120-48YM-8C | Junos Space Platform 21.1R1 or later |
| QFX Series Virtual Chassis | QFX-VC          | Junos Space Platform 14.1 or later   |
| SRX Series                 | SRX240H         | Junos Space Platform 14.1R1 or later |
|                            | SRX300          | Junos Space Platform 15.1R2 or later |
|                            | SRX320          | Junos Space Platform 15.1R2 or later |
|                            | SRX320-PoE      | Junos Space Platform 15.1R2 or later |
|                            | SRX340          | Junos Space Platform 15.1R2 or later |
|                            | SRX345          | Junos Space Platform 15.1R2 or later |

|                               | SRX380                    | Junos Space 20.1R1 hot patch v1or later |
|-------------------------------|---------------------------|-----------------------------------------|
|                               | SRX550-M                  | Junos Space Platform 15.1R2 or later    |
|                               | SRX1500                   | Junos Space Platform 15.1R2 or later    |
|                               | SRX1600                   | Junos Space Platform 24.1R1 or later    |
| Product Series                | Model                     | Junos Space Platform Release            |
|                               | SRX2300                   | Junos Space Platform 24.1R1 or later    |
|                               | SRX4100                   | Junos Space Platform 16.1 or later      |
|                               | SRX4200                   | Junos Space Platform 16.1 or later      |
|                               | SRX4600                   | Junos Space Platform 17.2 or later      |
|                               | SRX5400                   | Junos Space Platform 13.2 or later      |
|                               | SRX5600                   | Junos Space Platform 18.2 or later      |
|                               | SRX5800                   | Junos Space Platform 13.3 or later      |
| Virtual SRX Series            | vSRX Virtual Firewall 3.0 | Junos Space Platform 18.2 or later      |
| Virtual route reflector (VRR) | VRR                       | Junos Space Platform 14.1R2 or later    |
| WLC Series                    | WLC device                | Junos Space Platform 14.1 or later      |

**Table 3** lists the devices supported by Junos Space Network Management Platform with compatible Junos OS Releases:

**Table 3: Devices Supported by Junos Space Platform with Compatible Junos OS Releases**

| Product Series | Model       | Supported Junos Operating System (Junos OS) Releases | Qualified Schema Version       |
|----------------|-------------|------------------------------------------------------|--------------------------------|
| ACX Series     | ACX710      | 20.2R1                                               | 20.2R1                         |
|                | ACX5448     | 18.3R1<br>18.4R1.8 or later                          | 18.4R1.8<br>18.4R1.8           |
| EX Series      | EX2300      | 18.1R3.3<br>18.4R1.8 or later<br>20.4R3-Sx           | 18.1R3.3<br>18.4R1.8<br>20.2R3 |
|                | EX2300-24T  | 21.4R3-S1                                            | 21.4R3-S1.5                    |
|                | EX3400      | 18.1R3.3<br>18.4R1.8 or later                        | 18.1R3.3<br>18.4R1.8           |
|                | EX4100-12T  | 22.3R1.12                                            | 22.3R1.12                      |
|                | EX4100-24P  | 23.1R1.2                                             | 23.1R1.2                       |
|                | EX4100-24T  | 23.1R1.2                                             | 23.1R1.2                       |
|                | EX4100-24MP | 23.1R1.2                                             | 23.1R1.2                       |
|                | EX4100-48P  | 23.1R1.2                                             | 23.1R1.2                       |
|                | EX4100-48T  | 22.3R1.12                                            | 22.3R1.12                      |
|                | EX4100-48MP | 22.3R1.12                                            | 22.3R1.12                      |
|                |             |                                                      |                                |

|  |              |           |           |
|--|--------------|-----------|-----------|
|  | EX4100-F-12P | 22.3R1.12 | 22.3R1.12 |
|  | EX4100-F-12T | 22.3R1.12 | 22.3R1.12 |

|  |              |                                  |                         |
|--|--------------|----------------------------------|-------------------------|
|  | EX4100-F-24P | 23.1R1.2                         | 23.1R1.2                |
|  | EX4100-F-24T | 22.3R1.12                        | 22.3R1.12               |
|  | EX4100-F-48P | 22.3R1.12                        | 22.3R1.12               |
|  | EX4100-F-48T | 22.3R1.12                        | 22.3R1.12               |
|  | EX4300-MP    | 21.2R3.8                         | 21.2R3.8                |
|  | EX4650       | 21.2R3.8                         | 21.2R3.8                |
|  | EX4400       | 21.3R2                           | 21.1/R1                 |
|  | EX4300       | 17.3R3-S1.5<br>18.4R1.8 or later | 17.3R3-S1.5<br>18.4R1.8 |
|  | EX4300-48MP  | 17.3R3-S1.5<br>18.4R1.8 or later | -<br>18.4R1.8           |
|  | EX4400-24P   | 21.1R1.11 or later               | 21.1R1.11               |
|  | EX4400-24MP  | 21.2R1.10 or later               | 21.2R1.10               |
|  | EX4400-48MP  | 21.2R1.10 or later               | 21.2R1.10               |
|  | EX4400-24T   | 21.1R1.11 or later               | 21.1R1.11 or later      |

|                    |               |                                  |                                   |
|--------------------|---------------|----------------------------------|-----------------------------------|
|                    | EX4400-48F    | 21.1R1.11 or later               | 21.1R1.11 or later                |
|                    | EX4400-48P    | 21.1R1.11 or later<br>21.4R3-S1  | 21.1R1.11 or later<br>21.4R3-S1.5 |
|                    | EX4400-48T    | 21.1R1.11 or later               | 21.1R1.11 or later                |
|                    | EX4400-24X    | 22.3R1.2                         | 22.3R1.2                          |
|                    | EX4600        | 17.3R3-S1.5<br>18.4R1.8 or later | 17.3R3-S1.5<br>18.4R1.8           |
|                    | EX4650        | 18.4R1.8 or later<br>20.4/R3     | 18.4R1.8<br>20.2R3-S1             |
|                    | EX4650-48Y-8C | 21.4R3-S1                        | 21.4R3-S1.5                       |
|                    | EX9200        | 17.3R3-S1.5<br>18.3R1.9 or later | 17.3R3-S1.5<br>18.3R1.9           |
|                    | EX9204        | 20.3R1.3 or later                | 20.3R1.3                          |
|                    | EX9208        | 20.3R1.3 or later                | 20.3R1.3                          |
|                    | EX9208-BASE3A | 20.4R3                           | 17.3R3-S4                         |
|                    | EX9214        | 20.3R1.3 or later                | 20.3R1.3                          |
| EX Virtual Chassis | EX4200-VC     | 12.2R1 or later                  | 15.1R7.9                          |

|                     |                 |                                        |                                     |
|---------------------|-----------------|----------------------------------------|-------------------------------------|
|                     | EX3400-VC       | 20.2R2.8 or later                      | 20.2R2.8                            |
|                     | EX4100-48T-VC   | 22.3R1.12                              | 22.3R1.12                           |
|                     | EX4100-48MP-VC  | 22.3R1.12                              | 22.3R1.12                           |
|                     | EX4100-F-48P-VC | 22.3R1.12                              | 22.3R1.12                           |
| MX Series           | MX204           | 18.4R1 or later                        | 18.4R1.8                            |
|                     | MX240           | 13.2R2.4 or later                      | 17.3R3.9<br>18.4R1.8                |
|                     | MX480           | 13.2R2.4 or later                      | 17.3R3-S2.2<br>17.3R3.9<br>19.1R1.6 |
|                     | MX10008         | 18.4R1.8 or later                      | 18.4R1.8                            |
|                     | MX960           | 21.2R1.6 or later<br>21.2R1.8 or later | 21.2R1.6<br>21.2R1.8                |
| SRX Series Firewall | SRX380          | 20.2R1                                 | 20.2R1                              |
|                     | SRX300          | 20.2R3-S2                              | 20.2R3-S2.5                         |
|                     | SRX320          | 20.2R3-S2<br>21.2R3-S2.9               | 20.2R3-S2.5<br>21.2R3.8             |
|                     | SRX340          | 21.2R3-S2.9                            | 21.2R3.8                            |
|                     | SRX345          | 21.2R3-S2.9                            | 21.2R3.8                            |

|            |                |                          |                         |
|------------|----------------|--------------------------|-------------------------|
|            | SRX550M        | 21.2R3-S2.9              | 21.2R3.8                |
|            | SRX1500        | 21.2R1 and later         | 23.4R2                  |
|            | SRX1600        | 23.3R1.8                 | 23.3R1.8                |
|            | SRX2300        | 23.4R1.6                 | 23.4R1.6                |
|            | SRX4100        | 20.4R3-S1                | 20.2R3-S2.5             |
|            | SRX4200        | 20.4R3-S1                | 20.2R3-S2.5             |
|            | SRX5600        | 20.4R3-S1<br>21.2R3-S2.9 | 20.4R3-S1<br>21.2R3.8   |
|            | SRX5800        | 20.4R3-S1<br>21.2R3-S2.9 | 20.4R3-S1<br>21.2R3.8   |
|            | SRX550-645AP-M | 20.2R3-S2.5              | 20.2R3-S2.5             |
| QFX Series | QFX5100        | 17.3R3 or later          | 17.3R3-S1.5<br>18.4R1.8 |

|  |             |                                  |                         |
|--|-------------|----------------------------------|-------------------------|
|  | QFX5110-32Q | 17.3R3 or later                  | 17.3R3-S1.5<br>19.1R1.6 |
|  | QFX5110-48S | 17.3R3-S1.5<br>19.1R1.6 or later | 17.3R3-S1.5<br>19.1R1.6 |
|  | QFX5120     | 18.4R1.8 or later                | 18.4R1.8                |

|  |                 |                             |                                     |
|--|-----------------|-----------------------------|-------------------------------------|
|  | QFX5210         | 19.1R1.6 or later           | 19.1R1.6                            |
|  | QFX5200         | 17.3R3 or later             | 17.3R3.9<br>18.4R1.8                |
|  | QFX5200-32C-32Q | 21.2R3.8                    | 21.2R3.8                            |
|  | QFX10002-36Q    | 17.3R3 or later             | 17.3R3-S1.5<br>19.1R1.6             |
|  | QFX10002-36Q-DC | 17.3R3 or later             | 17.3R3-S1.5<br>19.1R1.6             |
|  | QFX10002-60C    | 17.3R3 or later             | 17.3R3-S1.5<br>19.1R1.6             |
|  | QFX10002-72Q    | 17.3R3 or later<br>21.2R3.8 | 17.3R3-S1.5<br>19.1R1.6<br>21.2R3.8 |
|  | QFX10002-72Q-DC | 17.3R3-S1.5 or later        | 17.3R3-S1.5                         |
|  | QFX10008        | 17.3R3 or later             | 17.3R3.9<br>18.4R1.8                |
|  | QFX5120-48T-6C  | 20.2R1.10 or later          | 20.2R1.10                           |
|  | QFX5120-48YM-8C | 20.4R1.12                   | 20.4R1.12                           |

When Junos Space Platform discovers EX Series switches running Layer 2 next generation software, the device family for these devices is displayed (on the Device Management page) as junos and not as junos-ex. This behavior is currently observed on EX4300 and EX9200 switches running Layer 2 next generation software.

## Supported Junos OS Releases

Junos Space Network Management Platform Release 26.1R1 supports the following Junos OS releases:

- Junos OS Release 21.2
- Junos OS Release 22.1
- Junos OS Release 22.2
- Junos OS Release 22.3
- Junos OS Release 23.1
- Junos OS Release 24.2
- Junos OS Release 25.2R2

## Changes in Default Behavior

- From Release 17.2R1 onward, Junos Space Platform does not sort configurations while comparing templates. In releases earlier than 17.2R1, Junos Space Platform sorts configurations while comparing templates, and this causes Junos Space Platform to trigger incorrect deviation reports because of a change in the order of configuration statements caused by the sorting.
- From Release 17.2R1 onward, Junos Space Platform does not support the click action in the Top 10 Active Users in 24 Hours chart. In releases earlier than 17.2R1, you can click within the chart to view details of the selected item on the corresponding page.
- From Junos Space Platform Release 17.1R1 onward, the VLAN field in reports supports both integer and string values. In releases earlier than 17.1R1, the VLAN field in reports supports only integer values, whereas the VLAN field for logical interfaces accepts both integer and string values. This mismatch causes issues in displaying VLAN information for logical interfaces in reports.

From Release 17.1R1 onward, the VLAN option in the Add Filter Criteria section of the Create Report Definition page and the filter support for the VLAN column on the View Logical Interface page are removed.

- From Junos Space Platform Release 16.1R2 onward, the upgrade-related logs at `/var/jmp_upgrade` are added to the troubleshooting logs.
- From Release 17.1R1 onward, Junos Space Platform boot menu accepts text inputs, such as reinstall, when you install the Junos Space Platform software from USB drives. In versions earlier than Release 17.1R1, the boot menu supports only numerical values. From Release 17.1R1 onward,

when you do a reinstall, the software restarts and a local reboot occurs by default. Previously, you had to connect to the console and manually trigger a reboot.

- From Junos Space Platform Release 16.1R2 onward, validation messages are provided for tasks where CSV files are used for device selection, and all devices that are listed in the CSV file are not selected when the task is performed. Validation messages are provided when devices are selected using CSV files from the following pages and dialog boxes:

- Deploy Device Image dialog box
- Deploy Satellite Device Image dialog box
- Stage Image on Device page
- Stage Image on Satellite Device page
- Remove Image from Staged Device dialog box
- Undeploy JAM Package from Device dialog box
- Verifying checksum of image on device(s) dialog box
- Stage Scripts on Device(s) page
- Disable Scripts on Device(s) page
- Execute Script on Device(s) page
- Remove Scripts from Device(s) dialog box
- Verify Checksum of Scripts on Device(s) dialog box

From Release 17.1R1 onward, validation messages are provided for the following pages and dialog boxes, too:

- Run Operation page
- Stage Script Bundle on Devices dialog box
- Enable Script Bundle on Devices page
- Disable Script Bundle on Devices page
- Execute Script Bundle on Devices dialog box
- Starting in Junos Space Network Management Platform Release 21.3R1, unicast Junos Space cluster is the default mode for Junos Space Network Management Platform.
- Starting in Junos Space Network Management Platform Release 21.3R1, the AppLogic node restarts, when the Add Node jobs for JBoss and database nodes are successful. This is not applicable for Fault Monitoring and Performance Monitoring (FMPM) node.
- While upgrading from Junos Space Network Management Platform Release 21.1R1 (with Junos Space Network Management Platform Release 21.1R1 supported applications) or Junos Space

Network Management Platform Release 21.2R1 (with Junos Space Network Management Platform Release 21.1R1 supported applications) to Junos Space Network Management Platform Release 21.3R1, the deployment status is displayed only for the Junos Space Network Management Platform and not for the applications.

- Starting in Junos Space Network Management Platform Release 21.3R1, the scripts with existing Network Configuration protocol (NETCONF) Remote Procedure Calls (RPC) commands needs to be replaced with CLI commands with display xml option.
- Starting in Junos Space Network Management Platform Release 21.3R1, the AppLogic service restarts after the application upgrade or installation job is successful.
- Starting in Junos Space Network Management Platform Release 21.3R1, before initiating any operation like configuration change, configlet or template push to the device, make sure that the nodes are not in Deploying / Parsing Schema state.

## Known Behavior

**CAUTION:** To avoid a BEAST TLS 1.0 attack, whenever you log in to Junos Space through a browser tab or window, make sure that the tab or window was not previously used to access a non-HTTPS website. The best practice is to close your browser and relaunch it before logging into Junos Space.

:

- In Junos Space Network Management Platform Release 24.1R1, the last monitoring time does not get updated post disaster recovery reset on the standby site.
- For EX Series Switches, an explicit reboot is required, using the device CLI to complete the image deployment and upgrade process.
- Starting from Junos Space Network Management Platform Release 18.1R1 onwards, to view and edit firewall policies, users must have permissions or roles corresponding to all the attributes present under the Firewall Policies and Shared Objects predefined roles. Go to Network Management Platform>Role Based Access Control>Roles to view and assign the relevant roles.
- Tag names can be alphanumeric strings. The tag name can also contain underscores, hyphens, and spaces. However, a tag name must not:
  - Exceed 255 characters
  - Start with a space
  - Contain special characters such as commas, double quotation marks, or parentheses.
  - “Untagged” is a reserved term and, therefore, you cannot create a tag with this name.

- The right-click menu is not available on the Import Licenses (Administration > Licenses > Import License) page. You can use either the browser menu options or the keyboard shortcuts to copy and paste onto the page.  
Device-initiated connections to Junos Space can have different IP addresses from those listed in Junos Space. For example, if you use a loopback address to discover a device, you can source the SSH session of the device from its interface address (Junos OS default behavior is to select the default address) instead. This can lead to firewall conflicts.
- You might observe the following limitations on the Topology page:
- The tooltip on the node displays the status as Active/Managed even when the node is down.
- For an SRX Series cluster, topology links are displayed only for the primary member of the cluster and not for the secondary member.
- When unified in-service software upgrade (ISSU) is performed from the Manage Operations workflow, the Routing Engines are not rebooted. The Routing Engines must be manually rebooted for the image to be loaded.
- For LSYS (logical, nonroot) devices, when there are pending out-of-band changes on the root device, the Resolve out-of-band changes menu option is disabled for those child LSYS devices, even though Device Managed Status displays Device Changed. This is by design.
- RMA is not supported by devices running Junos OS, and devices that are not running with Junos OS.
- Script Manager supports only Junos OS Release 10.x and later.
- A stage device script or image supports only devices running Junos OS Release 10.x and later.
- For unified ISSU support for both device-initiated and Junos Space-initiated dual Routing Engine connections, we strongly recommend that you configure the virtual IP (VIP) on the dual Routing Engine device. Dual Routing Engine devices without VIP configuration are not fully supported on Junos Space.
- In a single node or multiple nodes, changes to the user (for example, password, roles, and disable or enable user) take effect only at the next login.
- Looking Glass functionality is not supported on logical systems.
- For devices running Junos OS Release 12.1 or later, the following parameters do not display any data in the Network Monitoring workspace because the corresponding MIB objects have been deprecated:
- `jnxJsSPUMonitoringFlowSessIPv4`
- `jnxJsSPUMonitoringFlowSessIPv6`
- `jnxJsSPUMonitoringCPSessIPv4`
- `jnxJsSPUMonitoringCPSessIPv6`
- `jnxJsNodeSessCreationPerSecIPv4`
- `jnxJsNodeSessCreationPerSecIPv6`

- jnxJsNodeCurrentTotalSessIPv4
- jnxJsNodeCurrentTotalSessIPv6
- For SNMPv3 traps, if more than one trap setting is configured in the `/opt/opennms/etc/trapd-configuration.xml` file, then the *security-name* attribute for the *snmpv3-user* element must be unique for each configuration entry. If a unique *security-name* attribute is not provided, then SNMP traps are not received by Network Monitoring.

The following is a sample snippet of the `/opt/opennms/etc/trapd-configuration.xml` file with two configuration entries:

```
<?xml version="1.0"?>
<trapd-configuration snmp-trap-port="162" new-suspect-on-trap="false">
  <snmpv3-user security-name="Space-SNMP-1" auth-passphrase="abcD123!" auth-protocol="MD5"/>
  <snmpv3-user security-name="Space-SNMP-2" auth-passphrase="abcD123!" auth-protocol="MD5"
  privacy-passphrase="zyxW321!" privacy-protocol="DES"/> </trapd-configuration>
```

- On the Network Monitoring > Node List > Node page, the *ifIndex* parameter is not displayed for IPv6 interfaces if the version of Junos OS running on the device is Release 13.1 or earlier. This is because IPv6 MIBs are supported only on Junos OS Release 13.2 and later.
- When you execute a script and click the View Results link on the Script Management Job Status page, the details of the script execution results are displayed up to a maximum of 16,777,215 characters; the rests of the results are truncated.

This might affect users who execute the *show configuration* command on devices with large configurations or if the output of a Junos OS operational command (executed on a device) is large.

- When you configure a Junos Space fabric with dedicated database nodes, the Junos Space Platform database is moved from the Junos Space nodes to the database nodes. You cannot move the database back to the Junos Space nodes.
- For a purging policy triggered by a cron job:
- If the Junos Space fabric is configured with MySQL on one or two dedicated database nodes, the database backup files and log files (mainly in the `/var/log/` directory with the filenames `*.log.*`, `messages.*`, or `SystemStatusLog.*`) are not purged from the dedicated database nodes.
- If Network Monitoring receives two traps within the same second—that is, one for a trigger alarm and another for a clear alarm—then the triggered alarm is not cleared because the clear alarm is not processed by Network Monitoring.

If you use Internet Explorer versions 8.0 or 9.0 to access the Junos Space Platform GUI, you cannot import multiple scripts or CLI Configlets at the same time.

Workaround: Use Internet Explorer Version 10.0 or later, or use a different supported browser (Mozilla Firefox or Google Chrome) to import multiple scripts or CLI Configlets at the same time.

- If you access the Junos Space Platform UI in two tabs of the same browser with two different domains selected and access the same page in both tabs, the information displayed on the page is based on the latest domain selected. To view pages that are accessible only in the Global domain, ensure that you are in the Global domain in the most recent tab in which you are accessing the UI.
- If you select the Add SNMP configuration to device check box on the Administration > Applications > Modify Network Management Platform Settings page and discover a device whose trap target is updated, clicking Resync Node from the Network Monitoring workspace does not reset the trap target for the device.
- If you clear the Add SNMP configuration to device check box on the Administration > Applications > Modify Network Management Platform Settings page, the trap target is not set for the device during device discovery and resynchronizing node operations.
- If you want to perform a global search by using partial keywords, append "\*" to the search keywords.
- To perform a partial keyword search on tags on the Tags page (Administration > Tags) or the Apply Tags dialog box (right-click a device on the Device Management page and select Tag It), append \* to the search keyword.
- Internet Explorer slows down because some scripts can take an excessive amount of time to run. The browser prompts you to decide whether to continue running the slow script. see <http://support.microsoft.com/kb/175500> for instructions on how to fix this issue.
- When you switch from Space as system of record mode to Network as system of record mode, devices with the Managed Status Device Changed or Space & Device Changed are automatically synchronized after 900 seconds. To reduce this time period, modify the Polling time period secs setting for Network Management Platform (Administration > Applications > Modify Application Settings) to a lower value such as 150 seconds.
- In Space as System of Record (SSoR) mode on Junos Space, when a new authentication key is generated, devices discovered and managed using RSA keys whose management status is Device Changed move to the Key Conflict Authentication status. To resolve the conflict on the devices and bring them back to a key-based state, upload the RSA keys manually (Devices > Upload Keys to Devices).
- The EnterpriseDefault ([uei.opennms.org/generic/trap/EnterpriseDefault](http://uei.opennms.org/generic/trap/EnterpriseDefault)) event appears on the Events page in the Network Monitoring workspace only if there is no associated event definition for a received event. To create the required event definition, compile the MIB corresponding to the object ID (OID). You can find the OID by reviewing the details of the EnterpriseDefault event. For more information about compiling SNMP MIBs, see [Compiling SNMP MIBs](#).
- When a physical hard drive is removed from a Junos Space hardware appliance or a logical hard drive is degraded, the corresponding SNMP traps (jnxSpaceHardDiskPhysicalDriveRemoved and jnxSpaceHardDiskLogicalDeviceDegraded respectively) are generated and displayed as events in the Network Monitoring workspace. Later, when the physical hard drive is reinserted, the corresponding events (jnxSpaceHardDiskPhysicalDriveAdded and jnxSpaceHardDiskLogicalDeviceRebuilding) are generated and displayed in the Network Monitoring workspace; however, the alarms previously raised for the removal of the physical hard drive are not cleared automatically. You can clear these alarms

manually, if required. The alarms for the reinsertion of the physical hard drive are automatically cleared after a few minutes because they are of the Normal type.

- If you clear the Add SNMP configuration to device check box (on the Modify Network Management Platform Settings page under Administration > Applications > Network Management Platform > Modify Application Settings) and discover devices, and subsequently select the Add SNMP configuration to device check box and resynchronize nodes (Network Monitoring > Node List > Resync Nodes), the SNMPv2 trap target is updated on the devices.
- If you discover devices with SNMP probing enabled, the correct version of the SNMP trap target is updated on the devices for the following cases:
- When you modify the virtual IP (VIP) address or the device management interface IP address
- When a separate interface for device management is configured and there is a failover of the VIP node
- When you discover devices when the Network Monitoring service is stopped and subsequently start the Network Monitoring service and resynchronize nodes (Network Monitoring > Node List > Resync Nodes)

In all other cases, the default SNMP trap target (SNMPv2) is updated on the devices. If needed, you can use the predefined SNMPv3 Configlets (CLI Configlets > CLI Configlets) to update the trap settings on the device.

- In Junos Space Platform Release 16.1R1, Network Monitoring supports only a single set of SNMPv3 trap parameters.
- In Junos Space Platform Release 16.1R1, you cannot modify the trap settings for the SNMPv3 manager on the Network Monitoring GUI. You can modify the trap settings manually in the `/opt/opennms/etc/trapd-configuration.xml` file. After modifying the trap settings manually, restart the Network Monitoring service.
- With default SNMPv3 trap settings, the discovery of devices running worldwide Junos OS (wwJunos OS devices) fails as the default SNMPv3 trap settings cannot be updated to wwJunos OS devices because wwJunos OS devices do not support privacy settings.

The setting to manage objects from all assigned domains can be enabled globally for all users by selecting the Enable users to manage objects from all allowed domains in aggregated view check box in the Domains section of the Modify Application Settings page (Administration > Applications > Network Management Platform > Modify Application Settings). Alternatively, you can enable the setting to manage objects from all assigned domains at the user level by selecting the Manage objects from all assigned domains check box on the Object Visibility tab of the Change User Settings dialog box, which appears when you click the User Settings (gear) icon on the Junos Space banner.

- The Juniper Networks Device Management Interface (DMI) schema repository (<https://xml.juniper.net/>) does not currently support IPv6. If you are running Junos Space on an IPv6 network, you can do one of the following:
- Configure Junos Space to use both IPv4 and IPv6 addresses and download the DMI schema by using the Junos Space Platform Web GUI.

- Download the DMI schema by using an IPv4 client and update or install the DMI schema by using the Junos Space Web GUI.
- If you are planning on expanding the disk space for nodes in a Junos Space fabric (cluster) comprising of virtual appliances, you must first expand the disk space on the VIP node and ensure that the VIP node has come up (the status of the JBoss and MySQL services must be “Up”) before initiating the disk expansion on the other nodes in the fabric. If you fail to do this, it might cause fabric instability, and you might be unable to access Junos Space GUI.
- In a Junos Space fabric with two or more nodes configured with both IPv4 and IPv6 addresses (dual stack), the communications between all nodes in the fabric must be enabled for both IPv4 and IPv6 addresses.
- The Network Monitoring Topology feature is not supported on Internet Explorer.
- If the network connectivity at the active disaster recovery site is down and the active site cannot connect to sufficient arbiter devices after resuming network connectivity, both sites become standby disaster recovery sites. Execute the **jmp-dr manualFailover -a** command at the VIP node of the active disaster recovery site to convert the original site to the active site and start the disaster recovery process.
- When you are discovering devices running the worldwide Junos OS (ww Junos OS devices), ensure that you wait at least 10 minutes after the Add Adapter job for the device worldwide Junos adapter has completed successfully before triggering the device discovery.
- A new pattern (requested 'commit synchronize' operation) is added to the syslog pattern in Junos Space Release 16.1R2. During the syslog registration after a device is discovered or connects back to Junos Space following a Junos Space upgrade from Release 16.1R1 to 16.1R2, the (requested 'commit synchronize' operation) pattern is added to the syslog patterns on the device. When you issue the commit synchronize command, Junos Space automatically resynchronizes only those devices that have the (requested 'commit synchronize' operation) pattern added to the syslog patterns.
- If you are using Internet Explorer to access the Junos Space Network Platform UI and need to copy the job ID value from the Job ID field of the Job Management page, you must click outside the job ID text to start the selection.
- After you upgrade Junos Space Platform from Release 16.1R1 to 17.1R1, the Last Reboot Reason field on the Administration > Fabric > View Node Detail > Reboot Detail page shows the value as Reboot from Shell/Other instead of Space reboot after Software Upgrade.
- If the device IP could not be verified, the Add Unmanaged Devices action fails.

# Known Issues

There are no known issues in Junos Space Network Management Platform Release 26.1R1.

For the most complete and latest information about known defects, use the Juniper Networks online [Junos Problem Report Search](#) application.

# Resolved Issues

This section lists the issues fixed in Junos Space Network Management Platform Release 26.1R1:

For the most complete and latest information about known defects, use the Juniper Networks online [Junos Problem Report Search](#) application.

- Static routes fail to appear in the Kernel IP routing table in Junos Space Network Management Platform releases 24.1R1 and 24.1R5. [PR1916842](#)

Workaround:

Run the following commands manually to configure a static route using the nmcli editor:

```
[root@space-<hostname> system-connections]# nmcli con edit ethernet-eth3
```

```
===| nmcli interactive connection editor |===
```

```
Editing existing '802-3-ethernet' connection: 'ethernet-eth3'
```

```
Type 'help' or '?' for available commands.
```

```
Type 'print' to show all the connection properties.
```

```
Type 'describe [<setting>.<prop>]' for detailed property description.
```

```
You may edit the following settings: connection, 802-3-ethernet (ethernet), 802-1x, dcb, sriov, ethtool, match, ipv4, ipv6,
hostname, link, tc, proxy
```

```
nmcli> set ipv4.routes <destination_network_1> <gateway_ip>
```

```
nmcli> set ipv4.routes <destination_network_2> <gateway_ip>
```

```
nmcli> save persistent
```

```
Connection 'ethernet-eth3' successfully updated.
```

```
nmcli> quit
```

Replace <destination\_network> and <gateway\_ip> with the appropriate values for your environment.

# Hot Patch Releases

This section describes the installation procedure and resolved issues in Junos Space Network Management Platform Release 26.1R1 hot patches.

During hot patch installation, the script performs the following operations:

- Blocks the device communication.
- Stops JBoss, JBoss-dc, and watchdog services.
- Backs up existing configuration files and Enterprise Application Archive (EAR) files.
- Updates the Red Hat Package Manager (RPM) files.
- Restarts the watchdog process, which restarts JBoss and JBoss-dc services.
- Unblocks device communication after restarting the watchdog process for device load balancing.

## Installation Instructions

Perform the following steps in the CLI of the JBoss-VIP node only:

1. Download the Junos Space Platform 26.1R1 Patch vX from the [download site](#).

Here, X is the hot patch version. For example, v1, v2, and so on.

2. Copy the Space-26.1R1-Hotpatch-vX.tgz file to the /home/admin location of the VIP node.
3. Verify the checksum of the hot patch for data integrity:

```
md5sum Space-26.1R1-Hotpatch-vX.tgz.
```

4. Extract the Space-26.1R1-Hotpatch-vX.tgz file:

```
tar -zxvf Space-26.1R1-hotpatch-vX.tgz
```

5. Change the directory to Space-26.1R1-Hotpatch-vX.

```
cd Space-26.1R1-Hotpatch-vX
```

6. Execute the patchme.sh script from the Space-26.1R1-Hotpatch-vX folder:

```
sh patchme.sh
```

The script detects whether the deployment is a standalone deployment or a cluster deployment and

installs the patch accordingly.

A marker file, `/etc/Space-26.1R1-Hotpatch-vX`, is created with the list of Red Hat Package Manager (RPM) details in the hot patch.

**NOTE:**

- We recommend that you install the latest available hot patch version, which is the cumulative patch
- Set the SSH option “ServerAliveInterval” to a minimum value of 300, when connecting to the Applogic VIP through SSH to apply the hotpatch.

Sample command: `ssh admin@x.x.x.x -o ServerAliveInterval=300`

## Resolved Issues

Below table lists the resolved issues in Junos Space Network Management Platform Release 26.1 hot patch.

| PR                        | Description                                                                                                    | Hot Patch Version |
|---------------------------|----------------------------------------------------------------------------------------------------------------|-------------------|
| <a href="#">PR1929610</a> | Firewall policies rules are not working as expected in configuration.                                          | v1                |
| <a href="#">PR1941958</a> | Security Director does not install firewall policy rule to local firewall.                                     | v1                |
| <a href="#">PR1955510</a> | Issue with MySQL ServerCACert when activating encryption for all application nodes beside Load balancer nodes. | v1                |
| <a href="#">PR1955711</a> | Device status remains in sync after making changes on the device CLI.                                          | v1                |
| <a href="#">PR1952121</a> | Security Director has conflicts on VPN site to site when installing DMISchema.                                 | v2                |
| <a href="#">PR1956549</a> | Incorrect primary node displayed after SRX4600 chassis cluster failover.                                       | v2                |

|           |                                                                 |    |
|-----------|-----------------------------------------------------------------|----|
| PR1960287 | Descriptions were missing from the BNG physical inventory page. | v2 |
|-----------|-----------------------------------------------------------------|----|

# Revision History

| Release                                                     | Release Date             | Updates               |
|-------------------------------------------------------------|--------------------------|-----------------------|
| Junos Space Network Management Platform 26.1R1 Hot patch v2 | 30 July 2026—Revision 3  | Added Resolved Issue  |
| Junos Space Network Management Platform 26.1R1 Hot patch v1 | 02 July 2026—Revision 2  | Added Resolved Issue  |
| Junos Space Network Management Platform 26.1R1.             | 21 April 2026—Revision 1 | Initial Release Notes |

Copyright © 2026 Juniper Networks, Inc. All rights reserved.

Juniper Networks, the Juniper Networks logo, Juniper, and Junos are registered trademarks of Juniper Networks, Inc. and its affiliates in the United States and other countries. All other trademarks might be property of their respective owners.

Juniper Networks assumes no responsibility for any inaccuracies in this document. Juniper Networks reserves the right to change, modify, transfer, or otherwise revise this publication without notice.

Juniper Networks, the Juniper Networks logo, Juniper, and Junos are registered trademarks of Juniper Networks, Inc. in the United States and other countries. All other trademarks, service marks, registered marks, or registered service marks are the property of their respective owners. Juniper Networks assumes no responsibility for any inaccuracies in this document. Juniper Networks reserves the right to change, modify, transfer, or otherwise revise this publication without notice. Copyright © 2025 Juniper Networks, Inc. All rights reserved.