

frame-period-summary

Syntax	frame-period-summary <i>count</i> ;
Hierarchy Level	[edit protocols oam ethernet link-fault-management event link-event-rate], [edit protocols oam ethernet link-fault-management interface <i>interface-name</i> event-thresholds]
Release Information	Statement introduced in JUNOS Release 9.4 for EX-series switches.
Description	<p>Configure the threshold value for sending frame period summary error events or taking the action specified in the action profile.</p> <p>An errored frame second is any 1-second period that has at least one errored frame. This event is generated if the number of errored frame seconds is equal to or greater than the specified threshold for that period.</p>
Options	<i>count</i> —Threshold count in seconds for frame period summary error events. Range: 1 through 100 seconds
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Topics	■ Configuring Ethernet OAM Link Fault Management (CLI Procedure)

