

## [edit interfaces] Configuration Statement Hierarchy

---

```
interfaces {
  ae-x {
    aggregated-ether-options {
      lacp mode {
        periodic interval;
      }
    }
  }
  ge-chassis/pic/port {
    description text;
    ether-options {
      802.3ad aex;
      auto-negotiation;
      flow-control;
      link-mode mode;
      speed (speed | auto-negotiation | no-autonegotiation);
    }
    mtu bytes;
    unit logical-unit-number {
      family ethernet-switching {
        filter input filter-name;
        filter output filter-name;
        native-vlan-id vlan-id
        port-mode mode;
        vlan {
          members [ (all | names | vlan-ids) ];
        }
      }
      vlan-id vlan-id-number;
    }
    vlan-tagging;
  }
}
```

- Related Topics**
- Configuring Gigabit Ethernet Interfaces (CLI Procedure)
  - Configuring a Layer 3 Subinterface (CLI Procedure)
  - EX-series Switches Interfaces Overview

