

## clear snmp rmon history

---

**Syntax** clear snmp rmon history <*interface-name* | all>

**Release Information** Command introduced in JUNOS Release 9.0 for EX-series switches.

**Description** Delete the samples of Ethernet statistics collected, but do not delete the RMON history configuration.

The **clear snmp rmon history** command deletes all the samples collected for the interface configured for the history group, but not the configuration of that group. If you want to delete the RMON history group configuration, you must use the **delete snmp rmon history** configuration-mode command.

**Options** *interface-name*—Delete the samples of Ethernet statistics collected for this interface.

all—Delete the samples of Ethernet statistics collected for all interfaces that have been configured for RMON monitoring.

**Required Privilege Level** clear

**Related Topics** ■ show snmp rmon history

