

Configuring Infranet Controller Standard Sign-in Pages (NSM Procedure)

A sign-in page defines the customized properties in the enduser's welcome page such as the welcome text, Help text, logo, header, footer, and error message.

To configure a standard sign-in page:

1. In the NSM navigation tree, select **Device Manager > Devices**.
2. Click the **Device Tree** tab, and then double-click the Infranet Controller device for which you want to configure the standard sign-in page.
3. Click the **Configuration** tab. In the configuration tree, select **Authentication > Signing In > Sign-in Pages > User/Administrator Sign-in Pages**.
4. Add or modify the settings of the User/Administrator Sign-in Page as specified in Table 1 on page 1.
5. Click one:
 - **OK**—Saves the changes.
 - **Cancel**—Cancels the modifications.

Table 1: Administrator Sign-in Pages Configuration Details

Option	Function	Your Action
Name	Specifies the sign-in page name.	Enter a name for the sign-in page.
Sign-in Page Type	Specifies the type of sign-in page to present to the users and administrators.	Select Standard .
Custom Text tab	Specifies the text to be used for the various screen labels.	Enter the required information. NOTE: If you use unsupported HTML tags in your custom message, the Infranet Controller may display the enduser's Infranet Controller home page incorrectly. When adding text to the Instructions box, format text and add links using the following HTML tags: <code><i></code> , <code></code> , <code>
</code> , <code></code> and <code><a href></code> .
Header Appearance tab	Specifies the logo and background color in the screen header	Browse and select the logo image and select the background color.

Table 1: Administrator Sign-in Pages Configuration Details (continued)

Option	Function	Your Action
Custom Error Messages tab	Specifies the default text that is displayed to users if they encounter certificate errors.	Enter the missing certificate and invalid certificate error message. You can include <host> , <port> , <protocol> , and <request> variables and user attribute variables, such as <UserAttr.cn> , in the custom error messages. NOTE: The variables must follow the format <variable> to distinguish them from HTML tags, which have the format <tag> .
Help tab	Provides custom Help or additional instructions for users.	Select the Show Help Button , enter the Help label to display on the button and specify an HTML file to upload to the Infranet Controller.



NOTE: For information on customized sign-in pages, see the *Custom Sign-In Pages Solution Guide*.

Related Topics ■ Configuring Infranet Controller Sign-in Policies (NSM Procedure)