

Reverting an Infranet Controller Configuration to Default Values of a Template

NSM allows you to revert the device configuration values to that of the template default values. The default value is inherited from the template based on the order of priority in which the templates are applied to the device.

To revert an Infranet Controller configuration to the default values in a template:

1. From the Devices workspace in NSM, double-click the Infranet Controller whose configuration settings you want to revert. The Infranet Controller Device dialog box appears.
2. Select the **Configuration** tab. The Device configuration tree appears.
3. From the Device configuration tree, right-click the configuration node that you want to revert and select **Revert to template/default value**.
4. Click **OK**. The Infranet Controller configuration reverts to the template default values.

- Related Topics**
- Creating and Applying an Infranet Controller Template
 - Promoting an Infranet Controller Configuration to a Template

Published: 2009-08-20