

## Configuring a Community for use in BGP Routing Policy Conditions(NSM Procedure)

A community is a group of destinations that share a common property. You can define a community for use in a BGP routing policy match condition.

To configure a community for a BGP routing policy in NSM:

1. In the navigation tree, select **Device Manager > Devices**.
2. In the **Devices** list, double-click the device to select it.
3. Click the **Configuration** tab.
4. In the configuration tree, expand **Policy Options**.
5. Select **Community**.
6. Add or modify the parameters as specified in Table 1.
7. Click one:
  - **OK**—To save the changes.
  - **Cancel**—To cancel the modifications.
  - **Apply** — To apply the protocol settings.



**NOTE:** After you make changes to a device configuration, you must push that updated device configuration to the physical security device for those changes to take effect. You can update multiple devices at one time. See the *Updating Devices* section in the *Network and Security Manager Administration Guide* for more information.

**Table 1: Community Configuration Details**

| Option       | Function  | Your Action   |
|--------------|---|---|
| Name         | Specifies the name of the community.                            | Enter the name.   |
| Comment      | Specifies the comment for the community.                        | Enter the comment.  |
| Invert Match | Enables you to invert the results for the community expression. | Select the check-box if you want to invert the results. Clear the check-box if you do not want to invert the results. |

**Table 1: Community Configuration Details** (continued)

| Option  | Function                                 | Your Action  |
|---------|--|--|
| Members | Specifies one or more community members. | <ol style="list-style-type: none"><li data-bbox="1037 384 1395 415">1. Select <b>Members</b>.</li><li data-bbox="1037 426 1419 478">2. Click the New button or select a member and click the Edit button.</li><li data-bbox="1037 489 1395 520">3. Enter the member community.</li><li data-bbox="1037 531 1370 562">4. Click <b>OK</b>, then click <b>OK</b> again.</li></ol> |

---

Published: 2009-08-23