

Chapter 32

IGMP Configuration Guidelines

To configure IGMP, you include statements at the [edit protocols igmp] hierarchy level of the configuration:

```
protocols {
  igmp {
    traceoptions {
      file name <replace> <size size> <files number> <no-stamp>
        <(world-readable | no-world-readable)>;
      flag flag <flag-modifier> <disable>;
    }
    interface interface-name {
      disable;
      query-interval seconds;
      query-last-member-interval seconds;
      query-response-interval seconds;
      robust-count number;
      version version;
    }
  }
}
```

By default, IGMP is automatically enabled on all interfaces on which you configure DVMRP or PIM.

This chapter describes the following tasks for configuring IGMP:

- Minimum IGMP Configuration on page 372
- Enable IGMP on page 372
- Modify the IGMP Host-Query Message Interval on page 372
- Modify the IGMP Query Response Interval on page 372
- Modify the Last-Member Query Interval on page 373
- Modify the Robustness Variable on page 373
- Change the IGMP Version on page 373
- Trace IGMP Protocol Traffic on page 374

Minimum IGMP Configuration

IGMP is automatically enabled on all broadcast interfaces when you configure PIM or DVMRP. All IGMP configuration statements are optional.

Enable IGMP

IGMP is automatically enabled on all broadcast interfaces when you configure PIM or DVMRP.

To enable IGMP explicitly, include the `igmp` statement at the [edit protocols] hierarchy level. Optionally, you can specify the interface or interfaces on which to enable IGMP. If you do not specify any interfaces, IGMP is enabled on all interfaces.

```
[edit protocols]
igmp {
  interface interface-name;
}
```

For information about specifying interface names, see interface naming in the *JUNOS Internet Software Configuration Guide: Interfaces and Chassis*.

Modify the IGMP Host-Query Message Interval

The IGMP querier router periodically sends general host-query messages. These messages solicit group membership information and are sent to the all-systems multicast group address, 224.0.0.1.

By default, host-query messages are sent every 125 seconds. You might want to change this interval to tune the number of IGMP messages sent on the subnet.

To modify this interval, include the `query-interval` statement at the [edit protocols igmp interface *interface-name*] hierarchy level:

```
[edit protocols igmp interface interface-name]
query-interval seconds;
```

The query interval can be range from 1 through 1024 seconds.

Modify the IGMP Query Response Interval

The query response interval is the maximum amount of time that can elapse between when the querier router sends a host-query message and when it receives a response from a host. Varying this interval allows you to tune the burstiness of IGMP messages on the subnet.

By default, the query response interval is 10 seconds. To modify this interval, include the `query-response-interval` statement at the [edit protocols igmp interface *interface-name*] hierarchy level:

```
[edit protocols igmp interface interface-name]
query-response-interval seconds;
```

The query response interval can range from 1 through 1024 seconds. It must be less than the host-query message interval.

Modify the Last-Member Query Interval

The last-member query interval is the maximum amount of time between group-specific query messages, including those sent in response to leave-group messages. You might lower this interval to reduce the amount of time it takes a route to detect the loss of the last member of a group.

The default last-member query interval is 1 second. To modify this interval, include the `query-last-member-interval` statement at the [edit protocols igmp interface *interface-name*] hierarchy level:

```
[edit protocols igmp interface interface-name]  
query-last-member-interval seconds;
```

The last-member query interval can range from 1 through 1024 seconds.

Modify the Robustness Variable

The IGMP robustness variable provides fine-tuning to allow for expected packet loss on a subnet. The value of the robustness variable is used in calculating the following IGMP message intervals:

Group member interval—Amount of time that must pass before a multicast router decides there are no more members of a group on a network. This interval is calculated as follows: (robustness variable x query interval) + (1 x query response interval).

Other querier present interval—Amount of time that must pass before a multicast router decides that there is no longer another multicast router that is the querier. This interval is calculated as follows: (robustness variable x query interval) + (0.5 x query response interval).

Last member query count—Number of group-specific queries sent before the router assumes there are no local members of a group. The default number is the value of the robustness variable.

By default, the robustness variable is set to 2. You might want to increase this value if you expect a subnet to be lossy. To change the value of the robustness variable, include the `robust-count` statement at the [edit protocols igmp interface *interface-name*] hierarchy level:

```
[edit protocols igmp interface interface-name]  
robust-count number;
```

The number can be from 2 through 10.

Change the IGMP Version

All systems on a subnet must run the same version of IGMP. By default, the router runs IGMP Version 2. To change to Version 1, include the `version` statement at the [edit protocols igmp interface *interface-name*] hierarchy level:

```
[edit protocols igmp interface interface-name]  
version 1;
```

Trace IGMP Protocol Traffic

To trace IGMP protocol traffic, you can specify options in the global traceoptions statement at the [edit routing-options] hierarchy level, and you can specify IGMP-specific options by including the traceoptions statement at the [edit protocols igmp] hierarchy level:

```
[edit protocols igmp]
traceoptions {
  file name <replace> <size size> <files number> <no-stamp>
    <(world-readable | no-world-readable)>;
  flag flag <flag-modifier> <disable>;
}
```

You can specify the following IGMP-specific flags in the IGMP traceoptions statement:

leave—Trace leave group messages (for IGMP Version 2 only).

mtrace—Trace mtrace packets.

packets—Trace all IGMP packets.

query—Trace IGMP membership query messages, including general and group-specific queries.

report—Trace membership report messages.

To trace the paths of multicast packets, use the mtrace command, as described in the *JUNOS Internet Software Command Reference*.

For general information about tracing and global tracing options, see “Trace Global Routing Protocol Operations” on page 128.

Example: Trace IGMP Protocol Traffic

Trace only unusual or abnormal operations to routing-log, and trace all IGMP packets to igmp-log:

```
[edit]
routing-options {
  traceoptions {
    file routing-log;
  }
}
protocols {
  igmp {
    traceoptions {
      file igmp-log;
      flag packets;
    }
  }
}
```