

# Chapter 9

## Upgrade to Release 6.0 or Downgrade from Release 6.0

The following section is for users who need to upgrade to JUNOS Release 6.0 from 5.x and downgrade from Release 6.0 to 5.x. After you upgrade to 6.0 using `jinstall`, use `jbundle` for subsequent upgrades or downgrades. To upgrade to Release 6.0 from a 5.x release, use the 6.0 `jinstall` package. To downgrade from Release 6.0 to 5.x, use the appropriate 5.x `jbundle` package. For technical support, contact Juniper Networks at [support@juniper.net](mailto:support@juniper.net), or at 1-888-314-JTAC (within the United States) or 408-745-9500 (from outside the United States).

This section contains the following topics:

Upgrade to Release 6.0 on page 119

Downgrade from Release 6.0 on page 123

### ***Upgrade to Release 6.0***



**Note**

Before upgrading, you should back up the currently running and active file system and configuration so that you can recover to a known, stable environment in case the upgrade is unsuccessful:

```
user@host> request system snapshot
```

The installation process removes most stored files on the router, such as configuration templates and shell scripts. The only exceptions are `log`, `juniper.conf`, and `ssh` files. To preserve the stored files, copy them to another system before upgrading or downgrading the router.

Use the `jinstall` package to upgrade from JUNOS 5.x to JUNOS 6.0. You cannot use the `jbundle` package to upgrade from JUNOS 5.x to JUNOS 6.0.

To upgrade to or downgrade from JUNOS Release 6.0, follow these steps:

1. Download the software packages you need from the Juniper Networks Support Web site, <http://www.juniper.net/support/>. Choose either Canada and U.S. Version or Worldwide Version.

To download the software packages, you must have a service contract and an access account. If you do not have an access account, complete the registration form at the Juniper Networks Web site, <https://www.juniper.net/registration/Register.jsp>.



**Note**

When installing software using the jinstall package, we recommend that you access the router by means of the console serial management port. We recommend that you upgrade and downgrade software packages out-of-band using the console because in-band connections can be lost during the downgrade or upgrade process.

If the console serial management port cannot be used, you can connect to the router through the management Ethernet port fxp0. However, important messages that might be generated during the upgrade process will not be available.

2. Log into the Juniper Networks Web site.
3. Download the jinstall package to your local host.
4. Copy the jinstall package to the router. You might want to copy it to the `/var/tmp` directory, which is on the rotating media (hard disk) and is a large file system.

```
user@host> file copy ftp://username:prompt@ftp.hostname.net/  
filename /var/tmp/filename
```

5. Add the jinstall package:

```
user@host> request system software add /var/tmp/jinstall-package-name  
NOTICE: Validating configuration against jinstall-package-name  
Checking compatibility with configuration  
Initializing...  
Using jbase-6.0-package-name  
Using /var/tmp/jinstall-6.0-package-name  
Verified MD5 checksum of  
/var/validate/tmp/jinstall/jinstall-6.0-package-name  
Using  
/var/validate/tmp/jinstall-signed/jinstall-6.0-package-name  
Using /var/validate/tmp/jinstall/jbundle-6.0-package-name  
Using /var/validate/tmp/jbundle/jbase-6.0-package-name  
Using /var/validate/tmp/jbundle/jkernel-6.0-package-name  
Using /var/validate/tmp/jbundle/jcrypto-6.0-package-name  
Using /var/validate/tmp/jbundle/jpfe-6.0-package-name  
Using /var/validate/tmp/jbundle/jdocs-6.0-package-name  
Using /var/validate/tmp/jbundle/jroute-6.0-package-name  
Validating against /config/juniper.conf  
mgd: commit complete  
Validation succeeded  
Installing package  
'/var/tmp/jinstall-6.0-package-name' ...  
Verified MD5 checksum of jinstall-6.0-package-name
```

Auto-deleting old jinstall...  
Deleting saved config files ...  
Deleting bootstrap installer ...  
Adding jinstall...

WARNING: This package will load JUNOS software *release-number*.  
WARNING: It will save JUNOS configuration files, log files, and SSH keys  
WARNING: (if configured), but erase all other files and information  
WARNING: stored on this machine. This is the pre-installation stage  
WARNING: and all the software is loaded when you reboot the system.

Saving the config files ...  
Installing the bootstrap installer ...

WARNING: A REBOOT IS REQUIRED TO LOAD THIS SOFTWARE CORRECTLY. Use the  
WARNING: 'request system reboot' command when software installation is  
WARNING: complete. To abort the installation, do not reboot your system,  
WARNING: instead use the 'request system software delete jinstall'  
WARNING: command as soon as this operation completes.

Saving package file in /var/sw/pkg/ jinstall-package-name ...  
Saving state for rollback ...



**Note**

All JUNOS software is now delivered in signed packages that contain MD5 checksums. A package is installed only if the MD5 checksum within it matches the md5 hash recorded in its corresponding.md5 file. (For example, jinstall-6.OR1-export-signed.tgz contains jinstall-6.OR1-export.tgz and jinstall-6.OR1-export.tgz.md5. The jinstall-6.OR1-export.tgz package will only be installed if it matches the md5 hash recorded in jinstall-6.OR1-export.tgz.md5.)



**Note**

The jbundle package cannot be used to upgrade from JUNOS Release 5.x to Release JUNOS 6.0.  
Use the jinstall package to completely reinstall the software. This package rebuilds the file system but retains configuration, log files, and similar information from the previous version.

6. Reboot the router to load the JUNOS software:

```
user@host> request system reboot
Reboot the system ? [yes,no] (no) yes
Shutdown NOW!
```



**Note**

To quit the installation, do not reboot your system; instead, issue the request system software delete jinstall command when software installation completes.

During the upgrade, the mirror on the flash drive is not operational. It cannot be enabled until you repartition the hard disk.

All the software is loaded when you issue the reboot command. Loading the software can take 5 to 10 minutes.

7. The router then reboots from the primary boot device on which you just installed the software. When the reboot is complete, the router displays the login prompt.



**Note**

After you add a JUNOS 6.0 jinstall package, you cannot issue the request system software rollback command to return to the previously installed software. To return to the previously installed software, use the jbundle package that corresponds with the previously installed software.

8. Log in and verify the version of software running after the router reboots. Issue the show log message or show version command.
9. Repartitioning the hard disk. Issue the request system partition hard-disk command.



**Note**

The hard disk repartitioning happens during the first reboot after you issue the request system partition hard-disk command.

```
user@host> request system partition hard-disk
```

```
WARNING: The hard disk is about to be partitioned. The contents  
WARNING: of /altroot and /altconfig will be saved and restored.  
WARNING: All other data is at risk. This is the setup stage, the  
WARNING: partition happens during the next reboot.
```

```
Setting up to partition the hard disk ...
```

```
WARNING: A REBOOT IS REQUIRED TO PARTITION THE HARD DISK. Use the  
WARNING: 'request system reboot' command when you are ready to proceed  
WARNING: with the partitioning. To abort the partition of the hard disk  
WARNING: use the 'request system partition abort' command.
```

```
user@host>
```

10. Reboot the router to repartition the hard disk.

```
user@host> request system reboot  
Reboot the system ? [yes,no] (no) yes  
Shutdown NOW!
```



**Note**

To quit the repartition, do not reboot your system; instead, issue the request system partition abort command after the request system partition hard-disk command completes.

11. After you have upgraded or downgraded the software and are satisfied that the new software is successfully running, issue the request system snapshot command to back up the new software.

The request system snapshot command causes the root file system to be backed up to /altroot, and /config to be backed up to /altconfig. The root and /config file systems are on the router's flash drive, and the /altroot and /altconfig file systems are on the router's hard disk.



**Note**

After you issue the request system snapshot command, you cannot return to the previous version of the software, because the running and backup copies of the software are identical.

To return to the previous version of JUNOS software, you must reinstall that software following these upgrade or downgrade procedures.

## ***Downgrade from Release 6.0***

To downgrade from Release 6.0 to a 5.x release, follow the procedure for upgrading, but replace the 6.0 jinstall package with jbundle labeled for the appropriate release.



**Note**

You do not need to repartition the hard disk when you downgrade from release 6.0 to 5.x.

