

vlan

Syntax	<code>vlan (vlan-id vlan-name untagged);</code>
Hierarchy Level	[edit ethernet-switching-options voip interface (all [interface-name access-ports])
Release Information	Statement introduced in JUNOS Release 9.0 for EX-series switches.
Description	For EX-series switches, specify the VLAN name or VLAN tag identifier associated with the VLAN to be sent from the authenticating server to the IP phone.
Options	<p><i>vlan-name</i>—Name of a VLAN.</p> <p><i>vlan-id</i>—The VLAN tag identifier.</p> <p>Range: 0 through 4095. Tags 0 and 4095 are reserved by JUNOS software, and you should not configure them.</p> <p><i>untagged</i>—Allow untagged VLAN traffic.</p>
Required Privilege Level	<p>routing—To view this statement in the configuration.</p> <p>routing-control—To add this statement to the configuration.</p>
Related Topics	<ul style="list-style-type: none">■ Example: Setting Up VoIP with 802.1X and LLDP-MED on an EX-series Switch■ Example: Configuring VoIP on an EX Series Switch Without Including 802.1X Authentication■ Example: Configuring VoIP on an EX Series Switch Without Including LLDP-MED Support

Published: 2009-06-29