

## aggregate-clients

---

<b>Syntax</b>	aggregate-clients ( merge   replace );
<b>Hierarchy Level</b>	[edit forwarding-options dhcp-relay dynamic-profile <i>profile-name</i> ], [edit forwarding-options dhcp-relay group <i>group-name</i> dynamic-profile <i>profile-name</i> ], [edit logical-systems <i>logical-system-name</i> forwarding-options dhcp-relay dynamic-profile <i>profile-name</i> ], [edit logical-systems <i>logical-system-name</i> forwarding-options dhcp-relay group <i>group-name</i> dynamic-profile <i>profile-name</i> ], [edit logical-systems <i>logical-system-name</i> routing-instances <i>routing-instance-name</i> forwarding-options dhcp-relay dynamic-profile <i>profile-name</i> ], [edit logical-systems <i>logical-system-name</i> routing-instances <i>routing-instance-name</i> forwarding-options dhcp-relay group <i>group-name</i> dynamic-profile <i>profile-name</i> ], [edit routing-instances <i>routing-instance-name</i> forwarding-options dhcp-relay dynamic-profile <i>profile-name</i> ], [edit routing-instances <i>routing-instance-name</i> forwarding-options dhcp-relay group <i>group-name</i> dynamic-profile <i>profile-name</i> ]
<b>Release Information</b>	Statement introduced in JUNOS Release 9.3. merge and replace options were added in JUNOS Release 9.5.
<b>Description</b>	Specify that the router merge (chain) client attributes such as firewall filters and CoS attributes or replace them when multiple client sessions exist on the same underlying VLAN.
<b>Options</b>	<b>merge</b> —Aggregate multiple client attributes for the same subscriber (logical interface)  <b>replace</b> —Replace the entire logical interface whenever a new client logs into the network using the same VLAN logical interface
<b>Required Privilege Level</b>	system—To view this statement in the configuration. system-control—To add this statement to the configuration.
<b>Related Topics</b>	■ Attaching Dynamic Profiles to DHCP Subscriber Interfaces

