

bearer-bandwidth-limit

Syntax	<code>bearer-bandwidth-limit <i>kilobits-per-second</i>;</code>
Hierarchy Level	[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> dynamic-call-admission-control], [edit logical-systems <i>logical-system-name</i> interfaces <i>interface-name</i> unit <i>logical-unit-number</i> dynamic-call-admission-control]
Release Information	Statement introduced in JUNOS Release 8.2.
Description	(J4350 and J6350 Services Routers supporting voice over IP with the TGM550 media gateway module) For Fast Ethernet and Gigabit Ethernet interfaces, ISDN BRI interfaces, and serial interfaces with PPP or Frame Relay encapsulation, configure the bearer bandwidth limit (BBL). BBL is used for dynamic call admission control (dynamic CAC) to provide enhanced control over WAN bandwidth.
Options	<i>kilobits-per-second</i> —The bearer bandwidth limit to be reported to a TGM550 media gateway module, in kilobits per second (kbps). Range: 0 through 9999 kbps Default: 1 (dynamic CAC is not enabled on the interface)
Usage Guidelines	See Configuring Dynamic Call Admission Control.
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Topics	<i>JUNOS Services Interfaces Configuration Guide, J-series Services Router Basic LAN and WAN Access Configuration Guide</i>

