

callback-wait-period

Syntax	callback-wait-period <i>time</i> ;
Hierarchy Level	[edit interfaces <i>dlr</i> unit <i>logical-unit-number</i> dialer-options], [edit logical-systems <i>logical-system-name</i> interfaces <i>dlr</i> unit <i>logical-unit-number</i> dialer-options]
Release Information	Statement introduced in JUNOS Release 7.5.
Description	<p>(J-series Services Routers) For interfaces configured for ISDN with callback, specify the amount of time the dialer waits before calling back the caller. The default wait time is 5 seconds. The wait time is necessary because, when a call is rejected, the switch waits for up to 4 seconds on point-to-multipoint connections to ensure no other device accepts the call before sending the DISCONNECT message to the originator of the call. However, the default time of 5 seconds may not be sufficient for different switches or may not be needed on point-to-point connections.</p> <p>To configure callback mode, include the callback statement at the [edit interfaces <i>dlr</i> unit <i>logical-unit-number</i> dialer-options] hierarchy level.</p> <p>If the callback statement is configured, you cannot use the caller <i>caller-id</i> statement at the [edit interfaces <i>dlr</i> unit <i>logical-unit-number</i> dialer-options] hierarchy level.</p>
Options	<i>time</i> —Time the dialer waits before calling back the caller.
Usage Guidelines	See Configuring ISDN Logical Interface Properties.
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Topics	<i>J-series Services Router Basic LAN and WAN Access Configuration Guide</i>

