

guard-band

Syntax	guard-band <i>watts</i> ;
Hierarchy Level	[edit poe]
Release Information	Statement introduced in JUNOS Release 9.0 for EX-series switches.
Description	Reserve the specified amount of power for the switch in case of a spike in PoE consumption.
Default	0 W
Options	<i>watts</i> —Amount of power to be reserved for the switch in case of a spike in PoE consumption. Range: 0 through 19 W Default: 0 W
Required Privilege Level	router—To view this statement in the configuration. router-control—To add this statement to the configuration.
Related Topics	<ul style="list-style-type: none">■ Example: Configuring PoE Interfaces on an EX-series Switch■ Example: Configuring PoE Interfaces with Different Priorities on an EX-series Switch■ Configuring PoE (CLI Procedure)■ Configuring PoE (J-Web Procedure)■ PoE and EX-series Switches Overview

