

hold-multiplier

Syntax	hold-multiplier <i>number</i> ;
Hierarchy Level	[edit protocols lldp]
Release Information	Statement introduced in JUNOS Release 9.0 for EX-series switches.
Description	Specify the multiplier used in combination with the advertisement-interval value to determine the length of time LLDP information is held before it is discarded. The default value is 4 (or 120 seconds).
Default	Disabled.
Options	<i>number</i> —A number used as a multiplier. Range: 2 through 10 Default: 4 (or 120 seconds)
Required Privilege Level	routing—To view this statement in the configuration. routing-control—To add this statement to the configuration.
Related Topics	<ul style="list-style-type: none">■ show lldp■ Configuring LLDP (CLI Procedure)■ Understanding 802.1X and LLDP and LLDP-MED on EX-series Switches

