

isdn-options

Syntax	<pre>isdn-options { bchannel-allocation (ascending descending); calling-number <i>number</i>; incoming-called-number <i>number</i> <reject>; spid1 <i>spid-string</i>; spid2 <i>spid-string</i>; static-tei-val <i>value</i>; switch-type (att5e etsi ni1 ntdms100 ntt); t310 <i>seconds</i>; tei-option (first-call power-up); }</pre>
Hierarchy Level	[edit interfaces <i>br-pim</i> /0/ <i>port</i>], [edit interfaces <i>ct1-pim</i> /0/ <i>port</i>], [edit interfaces <i>ce1-pim</i> /0/ <i>port</i>]
Release Information	Statement introduced before JUNOS Release 7.4. bchannel-allocation option added in JUNOS Release 8.3
Description	<p>For J-series Services Routers only. Specify the ISDN options for configuring ISDN interfaces for group and user sessions.</p> <p>The statements are explained separately.</p>
Usage Guidelines	See Configuring ISDN Physical Interface Properties and Allocating B-Channels for Dialout.
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Topics	<i>J-series Services Router Basic LAN and WAN Access Configuration Guide</i>

