

## t3-options

---

**Syntax**   t3-options {  
          atm-encapsulation (direct | plcp);  
          bert-algorithm *algorithm*;  
          bert-error-rate *rate*;  
          bert-period *seconds*;  
          (cbit-parity | no-cbit-parity);  
          compatibility-mode (digital-link | kentrox | larscom) <subrate *value*>;  
          fcs (16 | 32);  
          (feac-loop-respond | no-feac-loop-respond);  
          idle-cycle-flag *value*;  
          (long-buildout | no-long-buildout);  
          (loop-timing | no-loop-timing);  
          [Unresolved xref] (local | payload | remote);  
          start-end-flag *value*;  
          }

**Hierarchy Level**   [edit interfaces *interface-name*]

**Release Information**   Statement introduced before JUNOS Release 7.4.

**Description**   Configure T3-specific physical interface properties, including the properties of DS3 channels on a channelized OC12 interface. The **long-buildout** statement is not supported for DS3 channels on a channelized OC12 interface.

On T3 interfaces, the default encapsulation is PPP.

For ATM1 interfaces, you can configure a subset of E3 options statements.

The statements are explained separately.

**Usage Guidelines**   See [Unresolved xref].

**Required Privilege Level**   interface—To view this statement in the configuration.  
                                interface-control—To add this statement to the configuration.

