

## vlan

---

<b>Syntax</b>	<code>vlan (vlan-id   vlan-name   untagged);</code>
<b>Hierarchy Level</b>	[edit ethernet-switching-options voip interface (all   [interface-name   access-ports])
<b>Release Information</b>	Statement introduced in JUNOS Release 9.0 for EX-series switches.
<b>Description</b>	For EX-series switches, specify the VLAN name or VLAN tag identifier associated with the VLAN to be sent from the authenticating server to the IP phone.
<b>Options</b>	<p><i>vlan-name</i>—Name of a VLAN.</p> <p><i>vlan-id</i>—The VLAN tag identifier.</p> <p><b>Range:</b> 0 through 4095. Tags 0 and 4095 are reserved by JUNOS software, and you should not configure them.</p> <p><i>untagged</i>—Allow untagged VLAN traffic.</p>
<b>Required Privilege Level</b>	<p>routing—To view this statement in the configuration.</p> <p>routing-control—To add this statement to the configuration.</p>
<b>Related Topics</b>	<ul style="list-style-type: none"><li>■ Example: Setting Up VoIP with 802.1X and LLDP-MED on an EX-series Switch</li><li>■ Example: Configuring VoIP on an EX Series Switch Without Including 802.1X Authentication</li><li>■ Example: Configuring VoIP on an EX Series Switch Without Including LLDP-MED Support</li></ul>

---

Published: 2009-06-29