

Allocating B-Channels for Dialout

You can configure the system to allocate B-channels for dialout from lowest or highest numbered B-channel (ascending or descending order). By configuring this feature, you reduce chances of “glare” on PRI lines carrying a mix of incoming and outgoing calls.

To configure the B-channel allocation, include the `idsn-options` and `bchannel-allocation` statements at the `[edit interfaces ct1-pim/0/port | ce1-pim/0/port]` hierarchy level:

```
[edit interfaces]
(ct1-pim/0/port | ce1-pim/0/port) {
  isdn-options {
    (bchannel-allocation (ascending | descending);
  }
}
```

