

Configuring the Ingress Rate Limit

On Fast Ethernet 8-port, 12-port, and 48-port PIC interfaces only, you can apply port-based rate limiting to the ingress traffic that arrives at the PIC.

To configure an ingress rate limit on a Fast Ethernet 8-port, 12-port, or 48-port PIC interface, include the `ingress-rate-limit` statement at the `[edit interfaces interface-name fastether-options]` hierarchy level:

```
[edit interfaces interface-name fastether-options]  
ingress-rate-limit rate;
```

rate can range in value from 1 through 100 Mbps.

