

clear auto-configuration interfaces

Syntax clear auto-configuration interfaces *interface-name*

Release Information Command introduced in JUNOS Release 9.5.

Description Clear dynamically created VLAN interfaces.



NOTE: For the clear command to be successful, no interface bindings (for example, DHCP server bindings) can exist on the dynamic interface.

Options *interface-name*—Name of a physical or logical interface.

Required Privilege Level view

List of Sample Output clear auto-configuration interfaces (All Interfaces) on page 1
clear auto-configuration interfaces (Single Dynamically Created Interface) on page 1

Output Fields When you enter this command, you are provided feedback on the status of your request.

clear auto-configuration interfaces (All Interfaces) user@host> clear auto-configuration interfaces ge-1/0/0

10 interfaces removed from device ge-1/0/0

clear auto-configuration interfaces (Single Dynamically Created Interface) user@host> clear auto-configuration interfaces ge-1/0/0.1073741824

Interface ge-1/0/0.1073741824 deleted

Published: 2009-07-16