

authentication-profile-name

Syntax	authentication-profile-name <i>access-profile-name</i> ;
Hierarchy Level	[edit protocols dot1x authenticator]
Release Information	Statement introduced in JUNOS Release 9.0 for EX Series switches.
Description	Specify the name of the access profile to be used for 802.1X or MAC RADIUS authentication.
Default	No access profile is specified.
Options	<i>access-profile-name</i> —Name of the access profile. The access profile is configured at the [edit access profile] hierarchy level and contains the RADIUS server IP address and other information used for 802.1X authentication.
Required Privilege Level	routing—To view this statement in the configuration. routing-control—To add this statement to the configuration.
Related Topics	<ul style="list-style-type: none">■ Example: Connecting a RADIUS Server for 802.1X to an EX Series Switch■ Example: Configuring MAC RADIUS Authentication on an EX Series Switch■ Configuring 802.1X Interface Settings (CLI Procedure)■ Configuring 802.1X Authentication (J-Web Procedure)

Published: 2009-07-21