

vlan

Syntax	<code>vlan (vlan-id vlan-name untagged);</code>
Hierarchy Level	[edit ethernet-switching-options voip interface (all [<i>interface-name</i> access-ports])
Release Information	Statement introduced in JUNOS Release 9.0 for EX-series switches.
Description	For EX Series switches, specify the VLAN name or VLAN tag identifier associated with the VLAN to be sent from the authenticating server to the IP phone.
Options	<p><i>vlan-name</i>—Name of a VLAN.</p> <p><i>vlan-id</i>—The VLAN tag identifier.</p> <p>Range: 0 through 4095. Tags 0 and 4095 are reserved by JUNOS Software, and you should not configure them.</p> <p><i>untagged</i>—Allow untagged VLAN traffic.</p>
Required Privilege Level	<p>routing—To view this statement in the configuration.</p> <p>routing-control—To add this statement to the configuration.</p>
Related Topics	<ul style="list-style-type: none">■ Example: Setting Up VoIP with 802.1X and LLDP-MED on an EX Series Switch■ Example: Configuring VoIP on an EX Series Switch Without Including 802.1X Authentication■ Example: Configuring VoIP on an EX Series Switch Without Including LLDP-MED Support

Published: 2009-08-05