



Junos[®] OS for EX Series Ethernet Switches

OSPF Feature Guide for EX Series Switches

Release

15.1



Modified: 2015-06-12

- Download the latest versions of software and review release notes:
<http://www.juniper.net/customers/csc/software/>
- Search technical bulletins for relevant hardware and software notifications:
<http://kb.juniper.net/InfoCenter/>
- Join and participate in the Juniper Networks Community Forum:
<http://www.juniper.net/company/communities/>
- Open a case online in the CSC Case Management tool: <http://www.juniper.net/cm/>

To verify service entitlement by product serial number, use our Serial Number Entitlement (SNE) Tool: <https://tools.juniper.net/SerialNumberEntitlementSearch/>

Opening a Case with JTAC

You can open a case with JTAC on the Web or by telephone.

- Use the Case Management tool in the CSC at <http://www.juniper.net/cm/>.
- Call 1-888-314-JTAC (1-888-314-5822 toll-free in the USA, Canada, and Mexico).

For international or direct-dial options in countries without toll-free numbers, see <http://www.juniper.net/support/requesting-support.html>.

PART 1

Overview

- [Layer 3 Protocols on page 3](#)
- [OSPF Overview on page 7](#)

CHAPTER 1

Layer 3 Protocols

- [Layer 3 Protocols Supported on EX Series Switches](#) on page 3
- [Layer 3 Protocols Not Supported on EX Series Switches](#) on page 4

Layer 3 Protocols Supported on EX Series Switches

EX Series switches support the Junos OS Layer 3 features and configuration statements listed in [Table 3](#) on page 3:

Table 3: Supported Junos OS Layer 3 Protocol Statements and Features

Protocol	Notes	For More Information
BGP	Fully supported.	Junos OS Routing Protocols Configuration Guide
BFD	Fully supported.	Junos OS Routing Protocols Configuration Guide
ICMP	Fully supported.	Junos OS Routing Protocols Configuration Guide
IGMPv1, v2, and v3	Fully supported.	Junos OS Multicast Protocols Configuration Guide
IS-IS	Supported, with the exceptions noted in “ Layer 3 Protocols Not Supported on EX Series Switches ” on page 4.	Junos OS Routing Protocols Configuration Guide
MLD	Fully supported (MLD versions 1 and 2).	Junos OS Multicast Protocols Configuration Guide
MPLS	Supported, with the exceptions noted in “ Layer 3 Protocols Not Supported on EX Series Switches ” on page 4.	Junos OS MPLS Applications Configuration Guide
OSPFv1, v2 and v3	Supported, with the exceptions noted in “ Layer 3 Protocols Not Supported on EX Series Switches ” on page 4.	Junos OS Routing Protocols Configuration Guide
PIM	Fully supported.	Junos OS Multicast Protocols Configuration Guide
PPM	Supported. See <i>EX Series Switch Software Features Overview</i> for specific platform information.	Junos OS Routing Protocols Configuration Guide

- Related Documentation**
- [Using IPsec to Secure OSPFv3 Networks \(CLI Procedure\) on page 17](#)
 - [Configuring an OSPF Network \(J-Web Procedure\) on page 13](#)

PART 2

Configuration

- [Configuration Tasks on page 13](#)
- [Configuration Statements on page 19](#)

CHAPTER 4

Configuration Statements

- [\[edit protocols ospf\] Configuration Statement Hierarchy on EX Series Switches on page 20](#)
- [\[edit protocols ospf3\] Configuration Statement Hierarchy on EX Series Switches on page 24](#)
- [area on page 28](#)
- [area-range on page 30](#)
- [bandwidth-based-metrics on page 32](#)
- [bfd-liveness-detection \(Protocols OSPF\) on page 34](#)
- [dead-interval on page 38](#)
- [default-lsa on page 39](#)
- [default-metric on page 40](#)
- [disable \(OSPF\) on page 42](#)
- [domain-id on page 43](#)
- [domain-vpn-tag on page 44](#)
- [export \(Protocols OSPF\) on page 45](#)
- [external-preference \(Protocols OSPF\) on page 46](#)
- [graceful-restart \(Protocols OSPF\) on page 47](#)
- [hello-interval \(Protocols OSPF\) on page 49](#)
- [ignore-lsp-metrics on page 50](#)
- [import \(Protocols OSPF\) on page 51](#)
- [inter-area-prefix-export on page 52](#)
- [inter-area-prefix-import on page 53](#)
- [interface \(Protocols OSPF\) on page 54](#)
- [interface-type \(Protocols OSPF\) on page 57](#)
- [lsp-metric-into-summary on page 58](#)
- [metric \(Protocols OSPF Interface\) on page 59](#)
- [metric-type on page 61](#)
- [no-nssa-abr on page 62](#)


```

        no-ignore-our-externals;
        rapid-runs number;
    }
    topology {
        disable;
        rib-group group-name;
        topology-id number;
    }
    traceoptions {
        file filename <files number> <size maximum-file-size> <world-readable |
        no-world-readable>;
        flag flag <flag-modifier> <disable>;
    }
    traffic-engineering {
        advertise-unnumbered-interfaces;
        credibility-protocol-preference;
        ignore-lsp-metrics;
        multicast-rpf-routes;
        no-topology;
        shortcuts <lsp-metric-into-summary>;
    }
}
}

```

Unsupported Statements in the [edit protocols ospf] Hierarchy Level

All statements in the [edit protocols ospf] hierarchy level that are displayed in the command-line interface (CLI) on the switch are supported on the switch and operate as documented with the following exceptions:

Table 7: Unsupported [edit protocols ospf] Configuration Statements on EX Series Switches

Statement	Hierarchy
NOTE: Variables, such as <i>interface-name</i> , are not shown in the statements or hierarchies.	
backup-spf-options	[edit protocols ospf topology]
key-chain	[edit protocols ospf area interface bfd-liveness-detection authentication]
overload	[edit protocols ospf topology]
prefix-export-limit	[edit protocols ospf topology]
spf-options	[edit protocols ospf topology]
topology	[edit protocols ospf area interface]

- Related Documentation**
- *OSPF Feature Guide for Routing Devices*
 - *[edit protocols] Configuration Statement Hierarchy on EX Series Switches*


```

preference preference;
prefix-export-limit number;
realm (ipv4-multicast|ipv6-multicast) {
    ... same statements as at the [edit protocols ospf3] hierarchy level, EXCEPT FOR ...
    area area-id {
        interface interface-name {
            no-eligible-backup; # NOT valid at this level
        }
    }
    backup-spf-options { ... } # NOT valid at this level
    realm realm-identifier { ... } # NOT valid at this level
    traffic-engineering { ... } # NOT valid at this level
}
realm ipv4-unicast {
    ... same statements as at the [edit protocols ospf3] hierarchy level, PLUS ...
    area area-id {
        interface interface-name {
        }
    }
}
realm ipv6-unicast {
    ... same statements as at the [edit protocols ospf3] hierarchy level, PLUS ...
    disable;
    backup-spf-options {
        disable;
        downstream-paths-only;
        no-install;
    }
}
reference-bandwidth reference-bandwidth;
rib-group group-name;
spf-options {
    delay milliseconds;
    holddown milliseconds;
    no-ignore-our-externals;
    rapid-runs number;
}
traceoptions {
    file filename <files number> <size maximum-file-size> <world-readable |
        no-world-readable>;
    flag flag <flag-modifier> <disable>;
}
traffic-engineering {
    ignore-lsp-metrics;
    shortcuts <lsp-metric-into-summary>;
}
}
}

```

Unsupported Statements in the [edit protocols ospf3] Hierarchy Level

All statements in the [edit protocols ospf3] hierarchy level that are displayed in the command-line interface (CLI) on the switch are supported on the switch and operate as documented with the following exception:

Table 8: Unsupported [edit protocols ospf 3] Configuration Statements on EX Series Switches

Statement	Hierarchy
-----------	-----------

NOTE: Variables, such as *interface-name*, are not shown in the statements or hierarchies.

key-chain	[edit protocols ospf3 area interface bfd-liveness-detection authentication]
-----------	---

- Related Documentation**
- *OSPF Feature Guide for Routing Devices*
 - *[edit protocols] Configuration Statement Hierarchy on EX Series Switches*

override-metric *metric*—(Optional) Override the metric for the IP address range and configure a specific metric value.

restrict—(Optional) Do not advertise the configured summary. This hides all routes that are contained within the summary, effectively creating a route filter.

Range: 1 through 16,777,215

Required Privilege	routing—To view this statement in the configuration.
Level	routing-control—To add this statement to the configuration.

Related Documentation	<ul style="list-style-type: none">• <i>Example: Summarizing Ranges of Routes in OSPF Link-State Advertisements Sent into the Backbone Area</i>
------------------------------	--

Required Privilege Level	routing—To view this statement in the configuration. routing-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• <i>Example: Dynamically Adjusting OSPF Interface Metrics Based on Bandwidth</i>• metric on page 59• <i>Example: Dynamically Adjusting OSPF Interface Metrics Based on Bandwidth</i>

authentication algorithm, **authentication key-chain**, and **authentication loose-check** options introduced in Junos OS Release 9.6.

Statement introduced in Junos OS Release 12.1 for the QFX Series.

Statement introduced in Junos OS Release 14.1X53-D20 for the OCX Series.

Description Configure bidirectional failure detection timers and authentication for OSPF.

The remaining statements are explained separately.

a BFD session. Optionally, instead of using this statement, you can configure the minimum transmit interval using the **minimum-interval** statement.

Range: 1 through 255,000

version—Configure the BFD version to detect: **1** (BFD version 1) or **automatic** (autodetect the BFD version).

Default: **automatic**

Required Privilege Level	routing—To view this statement in the configuration. routing-control—To add this statement to the configuration.
---------------------------------	---

Related Documentation	<ul style="list-style-type: none">• <i>Example: Configuring BFD for OSPF</i>• <i>Example: Configuring BFD Authentication for OSPF</i>
------------------------------	--

- [stub on page 81](#)

domain-vpn-tag

Syntax	<code>domain-vpn-tag <i>number</i>;</code>
Hierarchy Level	[edit logical-systems <i>logical-system-name</i> routing-instances <i>routing-instance-name</i> protocols (ospf ospf3)], [edit routing-instances <i>routing-instance-name</i> protocols (ospf ospf3)]
Release Information	Statement introduced before Junos OS Release 7.4. Statement introduced in Junos OS Release 9.0 for EX Series switches.
Description	Set a virtual private network (VPN) tag for OSPFv2 external routes generated by the provider edge (PE) routing device.
Options	<i>number</i> —VPN tag.
Required Privilege Level	routing—To view this statement in the configuration. routing-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• <i>Configuring Routing Between PE and CE Routers in Layer 3 VPNs</i>

traceoptions (Protocols OSPF)

Syntax	<pre>traceoptions { file <i>filename</i> <files <i>number</i>> <size <i>size</i>> <world-readable no-world-readable>; flag <i>flag</i> <flag-modifier> <disable>; }</pre>
Hierarchy Level	<p>[edit logical-systems <i>logical-system-name</i> protocols (ospf ospf3)],</p> <p>[edit logical-systems <i>logical-system-name</i> protocols ospf3 realm (ipv4-unicast ipv4-multicast ipv6-multicast)],</p> <p>[edit logical-systems <i>logical-system-name</i> routing-instances <i>routing-instance-name</i> protocols (ospf ospf3)],</p> <p>[edit logical-systems <i>logical-system-name</i> routing-instances <i>routing-instance-name</i> protocols ospf3 realm (ipv4-unicast ipv4-multicast ipv6-multicast)],</p> <p>[edit protocols (ospf ospf3)],</p> <p>[edit protocols ospf3 realm (ipv4-unicast ipv4-multicast ipv6-multicast)],</p> <p>[edit routing-instances <i>routing-instance-name</i> protocols (ospf ospf3)],</p> <p>[edit routing-instances <i>routing-instance-name</i> protocols ospf3 realm (ipv4-unicast ipv4-multicast ipv6-multicast)]</p>
Release Information	<p>Statement introduced before Junos OS Release 7.4.</p> <p>Statement introduced in Junos OS Release 9.0 for EX Series switches.</p> <p>Support for the realm statement introduced in Junos OS Release 9.2.</p> <p>Support for the realm statement introduced in Junos OS Release 9.2 for EX Series switches.</p> <p>Statement introduced in Junos OS Release 11.3 for the QFX Series.</p> <p>Statement introduced in Junos OS Release 14.1X53-D20 for the OCX Series.</p>
Description	<p>Configure OSPF protocol-level tracing options.</p> <p>To specify more than one tracing operation, include multiple flag statements.</p>



NOTE: The **traceoptions** statement is not supported on QFabric systems.

Default	The default OSPF protocol-level tracing options are those inherited from the routing protocols traceoptions statement included at the [edit routing-options] hierarchy level.
Options	<p>disable—(Optional) Disable the tracing operation. You can use this option to disable a single operation when you have defined a broad group of tracing operations, such as all.</p> <p>file <i>filename</i>—Name of the file to receive the output of the tracing operation. Enclose the name within quotation marks. All files are placed in the directory /var/log. We recommend that you place OSPF tracing output in the file ospf-log.</p> <p>files <i>number</i>—(Optional) Maximum number of trace files. When a trace file named trace-file reaches its maximum size, it is renamed trace-file.0, then trace-file.1, and</p>

so on, until the maximum number of trace files is reached. Then, the oldest trace file is overwritten.

If you specify a maximum number of files, you also must specify a maximum file size with the **size** option.

Range: 2 through 1000 files

Default: 10 files

flag flag—Tracing operation to perform. To specify more than one tracing operation, include multiple **flag** statements.

OSPF Tracing Flags

- **database-description**—Database description packets, which are used in synchronizing the OSPF and OSPFv3 topological database.
- **error**—OSPF and OSPFv3 error packets.
- **event**—OSPF and OSPFv3 state transitions.
- **flooding**—Link-state flooding packets.
- **graceful-restart**—Graceful-restart events.
- **hello**—Hello packets, which are used to establish neighbor adjacencies and to determine whether neighbors are reachable.
- **ldp-synchronization**—Synchronization events between OSPF and LDP.
- **lsa-ack**—Link-state acknowledgment packets, which are used in synchronizing the OSPF topological database.
- **lsa-analysis**—Link-state analysis. Specific to the Juniper Networks implementation of OSPF, Junos OS performs LSA analysis before running the shortest-path-first (SPF) algorithm. LSA analysis helps to speed the calculations performed by the SPF algorithm.
- **lsa-request**—Link-state request packets, which are used in synchronizing the OSPF topological database.
- **lsa-update**—Link-state updates packets, which are used in synchronizing the OSPF topological database.
- **nsr-synchronization**—Nonstop routing synchronization events.
- **on-demand**—Trace demand circuit extensions.
- **packet-dump**—Content of selected packet types.
- **packets**—All OSPF packets.
- **restart-signaling**—(OSPFv2 only) Restart-signaling graceful restart events.
- **spf**—Shortest-path-first (SPF) calculations.

Global Tracing Flags

- **all**—All tracing operations.
- **general**—A combination of the **normal** and **route** trace operations.
- **normal**—All normal operations. If you do not specify this option, only unusual or abnormal operations are traced.
- **policy**—Policy operations and actions.
- **route**—Routing table changes.
- **state**—State transitions.
- **task**—Routing protocol task processing.
- **timer**—Routing protocol timer processing.

flag-modifier—(Optional) Modifier for the tracing flag. You can specify one or more of these modifiers:

- **detail**—Detailed trace information.
- **receive**—Packets being received.
- **send**—Packets being transmitted.

no-world-readable—(Optional) Prevent any user from reading the log file.

size size—(Optional) Maximum size of each trace file, in kilobytes (KB), megabytes (MB), or gigabytes (GB). When a trace file named **trace-file** reaches this size, it is renamed **trace-file.0**. When the **trace-file** again reaches its maximum size, **trace-file.0** is renamed **trace-file.1** and **trace-file** is renamed **trace-file.0**. This renaming scheme continues until the maximum number of trace files is reached. Then, the oldest trace file is overwritten.

If you specify a maximum file size, you also must specify a maximum number of trace files with the **files** option.

Syntax: **xk** to specify KB, **xm** to specify MB, or **xg** to specify GB

Range: 10 KB through the maximum file size supported on your system

Default: 128 KB

world-readable—(Optional) Allow any user to read the log file.

Required Privilege Level	routing and trace—To view this statement in the configuration. routing-control and trace-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none"> • <i>Example: Tracing OSPF Protocol Traffic</i>

traffic-engineering (OSPF)

Syntax	<pre> traffic-engineering { <advertise-unnumbered-interfaces>; <credibility-protocol-preference>; ignore-lsp-metrics; multicast-rpf-routes; no-topology; shortcuts { lsp-metric-into-summary; } } </pre>
Hierarchy Level	[edit logical-systems <i>logical-system-name</i> protocols (ospf ospf3)], [edit protocols (ospf ospf3)]
Release Information	<p>Statement introduced before Junos OS Release 7.4.</p> <p>multicast-rpf-routes option introduced in Junos OS Release 7.5.</p> <p>advertise-unnumbered-interfaces option introduced in Junos OS Release 8.5.</p> <p>Statement introduced in Junos OS Release 9.0 for EX Series switches.</p> <p>Support for OSPFv3 (ospf3) introduced in Junos OS Release 9.4.</p> <p>Support for OSPFv3 (ospf3) introduced in Junos OS Release 9.4 for EX Series switches.</p> <p>credibility-protocol-preference statement introduced in Junos OS Release 9.4.</p> <p>credibility-protocol-preference statement introduced in Junos OS Release 9.4 for EX Series switches.</p> <p>Statement introduced in Junos OS Release 11.3 for the QFX Series.</p> <p>Statement introduced in Junos OS Release 14.1X53-D20 for the OCX Series.</p>
Description	Enable the OSPF traffic engineering features.
Default	Traffic engineering support is disabled.
Options	<p>advertise-unnumbered-interfaces—(Optional) (OSPFv2 only) Include the link-local identifier in the link-local traffic-engineering link-state advertisement. This statement must be included on both ends of an unnumbered link to allow an ingress LER to update the link in its traffic engineering database and use it for CSPF calculations. The link-local identifier is then used by RSVP to signal unnumbered interfaces as defined in RFC 3477.</p> <p>credibility-protocol-preference—(Optional) (OSPFv2 only) Use the configured preference value for OSPF routes to calculate the traffic engineering database credibility value used to select IGP routes. Use this statement to override the default behavior, in which the traffic engineering database prefers IS-IS routes even if OSPF routes are configured with a lower, that is, preferred, preference value. For example, OSPF routes have a default preference value of 10, whereas IS-IS Level 1 routes have a default preference value of 15. When protocol preference is enabled, the credibility value is determined by deducting the protocol preference value from a base value of 512. Using default protocol preference values, OSPF has a credibility value of 502, whereas IS-IS has a credibility value of 497. Because the traffic engineering database prefers IGP routes with the highest credibility value, OSPF routes are now preferred.</p>

multicast-rpf-routes—(Optional) (OSPFv2 only) Install routes for multicast RPF checks into the **inet.2** routing table. The **inet.2** routing table consists of unicast routes used for multicast RPF lookup. RPF is an antispoofing mechanism used to check whether the packet is coming in on an interface that is also sending data back to the packet source.



NOTE: You must enable OSPF traffic engineering shortcuts to use the **multicast-rpf-routes** statement. You must not allow LSP advertisements into OSPF when configuring the **multicast-rpf-routes** statement.

no-topology—(Optional) (OSPFv2 only) Disable the dissemination of the link-state topology information.

The remaining statements are explained separately.



CAUTION: When the OSPF traffic engineering configuration is considerably modified, the routing table entries are deleted and the routing table is recreated. Changes to configuration that can cause this behavior include enabling or disabling:

- Traffic engineering shortcuts
- IGP shortcuts
- LDP tunneling
- Multiprotocol LSP
- Advertise summary metrics
- Multicast RPF routes

Required Privilege Level	routing—To view this statement in the configuration. routing-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none"> • <i>Example: Enabling OSPF Traffic Engineering Support</i>

transit-delay (OSPF)

Syntax	<code>transit-delay seconds;</code>
Hierarchy Level	<p>[edit logical-systems <i>logical-system-name</i> protocols ospf area <i>area-id</i> peer-interface <i>interface-name</i>],</p> <p>[edit logical-systems <i>logical-system-name</i> protocols (ospf ospf3) area <i>area-id</i> interface <i>interface-name</i>],</p> <p>[edit logical-systems <i>logical-system-name</i> protocols (ospf ospf3) area <i>area-id</i> virtual-link],</p> <p>[edit logical-systems <i>logical-system-name</i> protocols ospf3 realm (ipv4-unicast ipv4-multicast ipv6-multicast) area <i>area-id</i> interface <i>interface-name</i>],</p> <p>[edit logical-systems <i>logical-system-name</i> routing-instances <i>routing-instance-name</i> protocols ospf area <i>area-id</i> interface <i>interface-name</i>],</p> <p>[edit logical-systems <i>logical-system-name</i> routing-instances <i>routing-instance-name</i> protocols ospf area <i>area-id</i> virtual-link],</p> <p>[edit logical-systems <i>logical-system-name</i> routing-instances <i>routing-instance-name</i> protocols ospf3 realm (ipv4-unicast ipv4-multicast ipv6-multicast) area <i>area-id</i> interface <i>interface-name</i>],</p> <p>[edit protocols ospf area <i>area-id</i> peer-interface <i>interface-name</i>],</p> <p>[edit protocols (ospf ospf3) area <i>area-id</i> interface <i>interface-name</i>],</p> <p>[edit protocols (ospf ospf3) area <i>area-id</i> virtual-link],</p> <p>[edit protocols ospf3 realm (ipv4-unicast ipv4-multicast ipv6-multicast)] area <i>area-id</i> interface <i>interface-name</i>],</p> <p>[edit routing-instances <i>routing-instance-name</i> protocols ospf area <i>area-id</i> interface <i>interface-name</i>],</p> <p>[edit routing-instances <i>routing-instance-name</i> protocols ospf area <i>area-id</i> virtual-link],</p> <p>[edit routing-instances <i>routing-instance-name</i> protocols ospf3 realm (ipv4-unicast ipv4-multicast ipv6-multicast) area <i>area-id</i> interface <i>interface-name</i>]</p>
Release Information	<p>Statement introduced before Junos OS Release 7.4.</p> <p>Statement introduced in Junos OS Release 9.0 for EX Series switches.</p> <p>Support for the realm statement introduced in Junos OS Release 9.2.</p> <p>Support for the realm statement introduced in Junos OS Release 9.2 for EX Series switches.</p>
Description	<p>Set the estimated time required to transmit a link-state update on the interface. When calculating this time, make sure to account for transmission and propagation delays.</p> <p>You should never have to modify the transit delay time.</p>
Options	<p>seconds—Estimated time, in seconds.</p> <p>Range: 1 through 65,535 seconds</p> <p>Default: 1 second</p>
Required Privilege Level	<p>routing—To view this statement in the configuration.</p> <p>routing-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none"> • <i>Example: Configuring OSPF Timers</i> • <i>Configuring RSVP and OSPF for LMP Peer Interfaces</i>

type-7

Syntax	<code>type-7;</code>
Hierarchy Level	<p>[edit logical-systems <i>logical-system-name</i> protocols (ospf ospf3) area <i>area-id</i> nssa default-lsa],</p> <p>[edit logical-systems <i>logical-system-name</i> protocols ospf3 realm (ipv4-unicast ipv4-multicast ipv6-multicast) area <i>area-id</i> nssa default-lsa],</p> <p>[edit logical-systems <i>logical-system-name</i> routing-instances <i>routing-instance-name</i> protocols (ospf ospf3) area <i>area-id</i> nssa default-lsa],</p> <p>[edit logical-systems <i>logical-system-name</i> protocols ospf3 realm (ipv4-unicast ipv4-multicast ipv6-multicast) area <i>area-id</i> nssa default-lsa],</p> <p>[edit protocols (ospf ospf3) area <i>area-id</i> nssa default-lsa],</p> <p>[edit protocols ospf3 realm (ipv4-unicast ipv4-multicast ipv6-multicast) area <i>area-id</i> nssa default-lsa],</p> <p>[edit routing-instances <i>routing-instance-name</i> protocols (ospf ospf3) area <i>area-id</i> nssa default-lsa],</p> <p>[edit routing-instances <i>routing-instance-name</i> protocols ospf3 realm (ipv4-unicast ipv4-multicast ipv6-multicast) area <i>area-id</i> nssa default-lsa]</p>
Release Information	<p>Statement introduced before Junos OS Release 7.4.</p> <p>Statement introduced in Junos OS Release 9.0 for EX Series switches.</p> <p>Support for the realm statement introduced in Junos OS Release 9.2.</p> <p>Support for the realm statement introduced in Junos OS Release 9.2 for EX Series switches.</p>
Description	<p>Flood Type 7 default link-state advertisements (LSAs) if the no-summaries statement is configured.</p> <p>By default, when the no-summaries statement is configured, a Type 3 LSA is injected into not-so-stubby areas (NSSAs) for Junos OS Release 5.0 and later. To support backward compatibility with earlier Junos OS releases, include the type-7 statement. This statement enables NSSA ABRs to advertise a Type 7 default LSA into the NSSA if you have also included the no-summaries statement in the configuration.</p>
Required Privilege Level	<p>routing—To view this statement in the configuration.</p> <p>routing-control—To add this statement to the configuration.</p>
Related Documentation	<ul style="list-style-type: none"> • <i>Understanding OSPF Areas</i> • <i>Example: Configuring OSPF Not-So-Stubby Areas</i> • no-summaries on page 82

virtual-link

Syntax	<pre>virtual-link neighbor-id <i>router-id</i> transit-area <i>area-id</i> { disable; authentication key <key-id identifier>; dead-interval <i>seconds</i>; hello-interval <i>seconds</i>; ipsec-sa <i>name</i>; retransmit-interval <i>seconds</i>; transit-delay <i>seconds</i>; }</pre>
Hierarchy Level	<pre>[edit logical-systems <i>logical-system-name</i> protocols (ospf ospf3) area <i>area-id</i>], [edit logical-systems <i>logical-system-name</i> routing-instances <i>routing-instance-name</i> protocols ospf area <i>area-id</i>], [edit protocols (ospf ospf3) area <i>area-id</i>], [edit routing-instances <i>routing-instance-name</i> protocols ospf area <i>area-id</i>]</pre>
Release Information	Statement introduced before Junos OS Release 7.4. Statement introduced in Junos OS Release 9.0 for EX Series switches.
Description	For backbone areas only, create a virtual link to use in place of an actual physical link. All area border routers and other routing devices on the backbone must be contiguous. If this is not possible and there is a break in OSPF connectivity, use virtual links to create connectivity to the OSPF backbone. When configuring virtual links, you must configure links on the two routing devices that form the end points of the link, and both of these routing devices must be area border routers. You cannot configure links through stub areas.
Options	<p>neighbor-id <i>router-id</i>—IP address of the routing device at the remote end of the virtual link.</p> <p>transit-area <i>area-id</i>—Area identifier of the area through which the virtual link transits. Virtual links are not allowed to transit the backbone area.</p> <p>The remaining statements are explained separately.</p>
Required Privilege Level	routing—To view this statement in the configuration. routing-control—To add this statement to the configuration.
Related Documentation	<ul style="list-style-type: none">• <i>Understanding OSPF Areas</i>• <i>Example: Configuring OSPF Virtual Links to Connect Noncontiguous Areas</i>

PART 3

Administration

- [Routine Monitoring on page 93](#)
- [Operational Commands on page 97](#)

CHAPTER 6

Operational Commands

- `clear (ospf | ospf3) database`
- `clear (ospf | ospf3) io-statistics`
- `clear (ospf | ospf3) neighbor`
- `clear (ospf | ospf3) statistics`
- `clear (ospf | ospf3) overload`
- `show (ospf | ospf3) interface`
- `show (ospf | ospf3) io-statistics`
- `show (ospf | ospf3) log`
- `show (ospf | ospf3) neighbor`
- `show (ospf | ospf3) overview`
- `show (ospf | ospf3) route`
- `show (ospf | ospf3) statistics`
- `show ospf database`
- `show ospf3 database`

clear (ospf | ospf3) io-statistics

List of Syntax	Syntax on page 101 Syntax (EX Series Switch and QFX Series) on page 101
Syntax	clear (ospf ospf3) io-statistics <logical-system (all <i>logical-system-name</i>)>
Syntax (EX Series Switch and QFX Series)	clear (ospf ospf3) io-statistics
Release Information	Command introduced before Junos OS Release 7.4. Command introduced in Junos OS Release 9.0 for EX Series switches. Command introduced in Junos OS Release 11.3 for the QFX Series. Command introduced in Junos OS Release 14.1X53-D20 for the OCX Series.
Description	Clear Open Shortest Path First (OSPF) input and output statistics.
Options	none —Clear OSPF input and output statistics. logical-system (all <i>logical-system-name</i>) —(Optional) Perform this operation on all logical systems or on a particular logical system.
Required Privilege Level	clear
List of Sample Output	clear ospf io-statistics on page 101
Output Fields	When you enter this command, you are provided feedback on the status of your request.

Sample Output

clear ospf io-statistics

```
user@host> clear ospf io-statistics
```


List of Sample Output [clear ospf neighbor on page 103](#)

Output Fields When you enter this command, you are provided feedback on the status of your request.

Sample Output

[clear ospf neighbor](#)

```
user@host> clear ospf neighbor
```


Sample Output

show ospf io-statistics

```
user@host> show ospf io-statistics
```

```
Packets read: 7361, average per run: 1.00, max run: 1  
Receive errors:  
None
```



```
Restart: Disabled
Trace options: lsa
Trace file: /var/log/ospf size 131072 files 10
Area: 0.0.0.0
  Stub type: Not Stub
  Authentication Type: None
  Area border routers: 0, AS boundary routers: 0
  Neighbors
    Up (in full state): 1
```


Table 16: show (ospf | ospf3) statistics Output Fields (*continued*)

Field Name	Field Description
Receive errors	<p>Number and type of receive errors. Some sample receive errors include:</p> <ul style="list-style-type: none"> • mtu mismatches • no interface found • no virtual link found • nssa mismatches • stub area mismatches • subnet mismatches <p>If there are no receive errors, the output displays none.</p>

Sample Output

show ospf statistics

```

user@host> show ospf statistics
Packet type          Total          Last 5 seconds
                   Sent      Received      Sent      Received
Hello                31         14           2           2
  DbD                 9          10           0           0
  LSReq               2           2           0           0
LSUpdate             8          16           0           0
LSAck                9           9           0           0

DBDs retransmitted   :           3, last 5 seconds :           0
LSAs flooded         :          12, last 5 seconds :           0
LSAs flooded high-prio :           0, last 5 seconds :           0
LSAs retransmitted   :           0, last 5 seconds :           0
LSAs transmitted to nbr:           3, last 5 seconds :           0
LSAs requested       :           5, last 5 seconds :           0
LSAs acknowledged   :          19, last 5 seconds :           0

Flood queue depth    :           0
Total rexmit entries :           0
db summaries         :           0
lsreq entries        :           0

Receive errors:
  862 no interface found
 115923 no virtual link found

```

show ospf statistics logical-system all

```

user@host> show ospf statistics logical-system all
logical-system: C
OSPF instance is not running
-----

logical-system: B

Packet type          Total          Last 5 seconds
                   Sent      Received      Sent      Received
Hello               313740       313653           1           0

```



```
Aging timer 00:55:57
Installed 00:04:03 ago, expires in 00:55:57, sent 00:04:01 ago
Last changed 00:04:48 ago, Change count: 1, Ours
NSSA *33.1.1.1 10.255.71.242 0x80000001 293 0x28 0xeb3b 36
mask 255.255.255.255
Type 2, TOS 0x0, metric 0, fwd addr 24.1.1.1, tag 0.0.0.0
Gen timer 00:45:07
Aging timer 00:55:07
Installed 00:04:53 ago, expires in 00:55:07, sent 00:04:13 ago
Last changed 00:04:53 ago, Change count: 1, Ours
```

show ospf database summary

```
user@host> show ospf database summary
Area 0.0.0.1:
  2 Router LSAs
  2 Summary LSAs
  1 NSSA LSAs
Area 0.0.0.2:
  2 Router LSAs
  1 Network LSAs
  2 Summary LSAs
  1 NSSA LSAs
Area 0.0.0.3:
  2 Router LSAs
  1 Network LSAs
  2 Summary LSAs
  1 NSSA LSAs
Externals:
Interface fe-2/2/1.0:
Interface ge-0/3/2.0:
Interface so-0/1/2.0:
Interface so-0/1/2.0:
```


Table 18: show ospf3 database Output Fields (*continued*)

Field Name	Field Description	Level of Output
OSPF AS SCOPE link state database	Entries in the AS scope link-state database.	brief detail extensive
OSPF Link-Local link state database, interface <i>interface-name</i>	Entries in the link-local link-state database for this interface.	brief detail extensive
area	Area number. Area 0.0.0.0 is the backbone area.	All levels
Type	Type of link advertisement: Extern , InterArPfx , InterArRtr , IntraArPrx , Link , Network , NSSA , or Router .	brief detail extensive
ID	Link identifier included in the advertisement. An asterisk (*) preceding the identifier marks database entries that originated from the local routing device.	brief detail extensive
Adv Rtr	Address of the routing device that sent the advertisement.	brief detail extensive
Seq	Link sequence number of the advertisement.	brief detail extensive
Age	Time elapsed since the LSA was originated, in seconds.	brief detail extensive
Cksum	Checksum value of the LSA.	brief detail extensive
Len	Length of the advertisement, in bytes.	brief detail extensive
Router (Router Link-State Advertisements)		
bits	Flags describing the routing device that generated the LSP.	detail extensive
Options	Option bits carried in the router LSA.	detail extensive
For Each Router Link		
Type	Type of interface. The value of all other output fields describing a routing device interface depends on the interface's type: <ul style="list-style-type: none"> • PointToPoint (1)—Point-to-point connection to another routing device. • Transit (2)—Connection to a transit network. • Virtual (4)—Virtual link. 	detail extensive
Loc-if-id	Local interface ID assigned to the interface that uniquely identifies the interface with the routing device.	detail extensive
Nbr-if-id	Interface ID of the neighbor's interface for this routing device link.	detail extensive
Nbr-rtr-id	Router ID of the neighbor routing device (for type 2 interfaces, the attached link's designated router).	detail extensive
Metric	Cost of the router link.	detail extensive

