

mirror disable

Syntax	mirror disable <i>triggerType triggerValue</i>
Release Information	Command introduced before JUNOS Release 7.1.0. nas-port-id added in JUNOS Release 7.1.0.
Description	Disables a packet mirroring session that was dynamically configured for a subscriber; uses the trigger information to identify the subscriber's session. There is no no version.
Options	<ul style="list-style-type: none">■ <i>triggerType</i>—One of the following RADIUS attributes that was used as the trigger to start the packet mirroring session<ul style="list-style-type: none">■ acct-session-id—Acct-Session-Id, RADIUS attribute [44]■ calling-station-id—Calling-Station-Id, RADIUS attribute [31]■ ip-address—Framed-IP-Address, RADIUS attribute [8]; associated with the virtual router where the command is issued, RADIUS VSA [26-1]■ nas-port-id—NAS-Port-Id, RADIUS attribute [87]■ username—User-Name, RADIUS attribute [1]; associated with the virtual router where the command is issued, RADIUS VSA [26-1]■ <i>triggerValue</i>—Value of the <i>triggerType</i> (the specified RADIUS attribute) that identifies the subscriber
Mode	Privileged Exec
Related Topics	<ul style="list-style-type: none">■ Configuring CLI-Based Mirroring■ Configuring RADIUS-Based Mirroring

