

Viewing Information About Interfaces

Purpose View information about the interfaces available on the router.

Action 1. Click **Monitor > SAE > Interfaces**.

The Interfaces pane appears.

The screenshot shows the Juniper SAE Interfaces configuration pane. The left sidebar contains a navigation menu with the following items: ACP, CLI, Component, Date, Disk, Interfaces..., Iptables..., JPS, NIC, NTP, Redirect Server, Route..., SAE (highlighted), Security, and System. The main area is titled 'SAE Interfaces' and contains a form with the following fields:

Field	Description	Value
Interface Name	Name of router interface. <i>Value:</i> All or part of the interface name <i>Default:</i> No value	<input type="text"/>
Maximum Results	Number of results to be displayed. <i>Legal range:</i> 1..INF <i>Default:</i> 25	<input type="text"/>
Slot	Display SAE information for a specified slot. <i>Value:</i> Currently the chassis has only one slot. The valid value is 0. <i>Default:</i> 0	<input type="text"/>
Style	Output style. <i>Choices:</i> brief: Display only interface names <i>Default:</i> Detail	<input type="text"/>
Virtual Router	Name of virtual router. <i>Value:</i> All or part of the virtual router name <i>Default:</i> No value	<input type="text"/>

At the bottom of the form are two buttons: **OK** and **Reset**.

Copyright © 2007, Juniper Networks, Inc. All Rights Reserved. Trademark Notice. Privacy. Juniper your Net.

-
2. In the Interface Name box, enter the name of the router interface for which you want to display information. or leave the box blank to display information about all router interfaces.
3. In the Maximum Results box, enter the maximum number of results that you want to receive.
4. In the Slot box, enter the number of the slot for which you want to display interface information.
5. Select an output style from the Style list.
6. In the Virtual Router box, enter the name of the virtual router for which you want to display interfaces, or leave the box blank to display information for all virtual routers.
7. Click **OK**.

The Interfaces pane displays the interfaces available on the router.

