



Juniper Networks Junos[®] OS

System Log Messages Reference

Release

11.1



Published: 2011-02-15

Juniper Networks, Inc.
1194 North Mathilda Avenue
Sunnyvale, California 94089
USA
408-745-2000
www.juniper.net

This product includes the Envoy SNMP Engine, developed by Epilogue Technology, an Integrated Systems Company. Copyright © 1986-1997, Epilogue Technology Corporation. All rights reserved. This program and its documentation were developed at private expense, and no part of them is in the public domain.

This product includes memory allocation software developed by Mark Moraes, copyright © 1988, 1989, 1993, University of Toronto.

This product includes FreeBSD software developed by the University of California, Berkeley, and its contributors. All of the documentation and software included in the 4.4BSD and 4.4BSD-Lite Releases is copyrighted by the Regents of the University of California. Copyright © 1979, 1980, 1983, 1986, 1988, 1989, 1991, 1992, 1993, 1994. The Regents of the University of California. All rights reserved.

GateD software copyright © 1995, the Regents of the University. All rights reserved. Gate Daemon was originated and developed through release 3.0 by Cornell University and its collaborators. Gated is based on Kirton's EGP, UC Berkeley's routing daemon (routed), and DCN's HELLO routing protocol. Development of Gated has been supported in part by the National Science Foundation. Portions of the GateD software copyright © 1988, Regents of the University of California. All rights reserved. Portions of the GateD software copyright © 1991, D. L. S. Associates.

This product includes software developed by Maker Communications, Inc., copyright © 1996, 1997, Maker Communications, Inc.

Juniper Networks, Junos, Steel-Belted Radius, NetScreen, and ScreenOS are registered trademarks of Juniper Networks, Inc. in the United States and other countries. The Juniper Networks Logo, the Junos logo, and JunosE are trademarks of Juniper Networks, Inc. All other trademarks, service marks, registered trademarks, or registered service marks are the property of their respective owners.

Juniper Networks assumes no responsibility for any inaccuracies in this document. Juniper Networks reserves the right to change, modify, transfer, or otherwise revise this publication without notice.

Products made or sold by Juniper Networks or components thereof might be covered by one or more of the following patents that are owned by or licensed to Juniper Networks: U.S. Patent Nos. 5,473,599, 5,905,725, 5,909,440, 6,192,051, 6,333,650, 6,359,479, 6,406,312, 6,429,706, 6,459,579, 6,493,347, 6,538,518, 6,538,899, 6,552,918, 6,567,902, 6,578,186, and 6,590,785.

Junos® OS System Log Messages Reference

Release 11.1

Copyright © 2011, Juniper Networks, Inc.

All rights reserved. Printed in USA.

Revision History

January 2011 —R1 Junos OS 11.1

The information in this document is current as of the date listed in the revision history.

YEAR 2000 NOTICE

Juniper Networks hardware and software products are Year 2000 compliant. The Junos OS has no known time-related limitations through the year 2038. However, the NTP application is known to have some difficulty in the year 2036.

END USER LICENSE AGREEMENT

READ THIS END USER LICENSE AGREEMENT ("AGREEMENT") BEFORE DOWNLOADING, INSTALLING, OR USING THE SOFTWARE. BY DOWNLOADING, INSTALLING, OR USING THE SOFTWARE OR OTHERWISE EXPRESSING YOUR AGREEMENT TO THE TERMS CONTAINED HEREIN, YOU (AS CUSTOMER OR IF YOU ARE NOT THE CUSTOMER, AS A REPRESENTATIVE/AGENT AUTHORIZED TO BIND THE CUSTOMER) CONSENT TO BE BOUND BY THIS AGREEMENT. IF YOU DO NOT OR CANNOT AGREE TO THE TERMS CONTAINED HEREIN, THEN (A) DO NOT DOWNLOAD, INSTALL, OR USE THE SOFTWARE, AND (B) YOU MAY CONTACT JUNIPER NETWORKS REGARDING LICENSE TERMS.

1. **The Parties.** The parties to this Agreement are (i) Juniper Networks, Inc. (if the Customer's principal office is located in the Americas) or Juniper Networks (Cayman) Limited (if the Customer's principal office is located outside the Americas) (such applicable entity being referred to herein as "Juniper"), and (ii) the person or organization that originally purchased from Juniper or an authorized Juniper reseller the applicable license(s) for use of the Software ("Customer") (collectively, the "Parties").

2. **The Software.** In this Agreement, "Software" means the program modules and features of the Juniper or Juniper-supplied software, for which Customer has paid the applicable license or support fees to Juniper or an authorized Juniper reseller, or which was embedded by Juniper in equipment which Customer purchased from Juniper or an authorized Juniper reseller. "Software" also includes updates, upgrades and new releases of such software. "Embedded Software" means Software which Juniper has embedded in or loaded onto the Juniper equipment and any updates, upgrades, additions or replacements which are subsequently embedded in or loaded onto the equipment.

3. **License Grant.** Subject to payment of the applicable fees and the limitations and restrictions set forth herein, Juniper grants to Customer a non-exclusive and non-transferable license, without right to sublicense, to use the Software, in executable form only, subject to the following use restrictions:

- a. Customer shall use Embedded Software solely as embedded in, and for execution on, Juniper equipment originally purchased by Customer from Juniper or an authorized Juniper reseller.
- b. Customer shall use the Software on a single hardware chassis having a single processing unit, or as many chassis or processing units for which Customer has paid the applicable license fees; provided, however, with respect to the Steel-Belted Radius or Odyssey Access Client software only, Customer shall use such Software on a single computer containing a single physical random access memory space and containing any number of processors. Use of the Steel-Belted Radius or IMS AAA software on multiple computers or virtual machines (e.g., Solaris zones) requires multiple licenses, regardless of whether such computers or virtualizations are physically contained on a single chassis.
- c. Product purchase documents, paper or electronic user documentation, and/or the particular licenses purchased by Customer may specify limits to Customer's use of the Software. Such limits may restrict use to a maximum number of seats, registered endpoints, concurrent users, sessions, calls, connections, subscribers, clusters, nodes, realms, devices, links, ports or transactions, or require the purchase of separate licenses to use particular features, functionalities, services, applications, operations, or capabilities, or provide throughput, performance, configuration, bandwidth, interface, processing, temporal, or geographical limits. In addition, such limits may restrict the use of the Software to managing certain kinds of networks or require the Software to be used only in conjunction with other specific Software. Customer's use of the Software shall be subject to all such limitations and purchase of all applicable licenses.
- d. For any trial copy of the Software, Customer's right to use the Software expires 30 days after download, installation or use of the Software. Customer may operate the Software after the 30-day trial period only if Customer pays for a license to do so. Customer may not extend or create an additional trial period by re-installing the Software after the 30-day trial period.
- e. The Global Enterprise Edition of the Steel-Belted Radius software may be used by Customer only to manage access to Customer's enterprise network. Specifically, service provider customers are expressly prohibited from using the Global Enterprise Edition of the Steel-Belted Radius software to support any commercial network access services.

The foregoing license is not transferable or assignable by Customer. No license is granted herein to any user who did not originally purchase the applicable license(s) for the Software from Juniper or an authorized Juniper reseller.

4. **Use Prohibitions.** Notwithstanding the foregoing, the license provided herein does not permit the Customer to, and Customer agrees not to and shall not: (a) modify, unbundle, reverse engineer, or create derivative works based on the Software; (b) make unauthorized copies of the Software (except as necessary for backup purposes); (c) rent, sell, transfer, or grant any rights in and to any copy of the Software, in any form, to any third party; (d) remove any proprietary notices, labels, or marks on or in any copy of the Software or any product in which the Software is embedded; (e) distribute any copy of the Software to any third party, including as may be embedded in Juniper equipment sold in the secondhand market; (f) use any 'locked' or key-restricted feature, function, service, application, operation, or capability without first purchasing the applicable license(s) and obtaining a valid key from Juniper, even if such feature, function, service, application, operation, or capability is enabled without a key; (g) distribute any key for the Software provided by Juniper to any third party; (h) use the

Software in any manner that extends or is broader than the uses purchased by Customer from Juniper or an authorized Juniper reseller; (i) use Embedded Software on non-Juniper equipment; (j) use Embedded Software (or make it available for use) on Juniper equipment that the Customer did not originally purchase from Juniper or an authorized Juniper reseller; (k) disclose the results of testing or benchmarking of the Software to any third party without the prior written consent of Juniper; or (l) use the Software in any manner other than as expressly provided herein.

5. **Audit.** Customer shall maintain accurate records as necessary to verify compliance with this Agreement. Upon request by Juniper, Customer shall furnish such records to Juniper and certify its compliance with this Agreement.

6. **Confidentiality.** The Parties agree that aspects of the Software and associated documentation are the confidential property of Juniper. As such, Customer shall exercise all reasonable commercial efforts to maintain the Software and associated documentation in confidence, which at a minimum includes restricting access to the Software to Customer employees and contractors having a need to use the Software for Customer's internal business purposes.

7. **Ownership.** Juniper and Juniper's licensors, respectively, retain ownership of all right, title, and interest (including copyright) in and to the Software, associated documentation, and all copies of the Software. Nothing in this Agreement constitutes a transfer or conveyance of any right, title, or interest in the Software or associated documentation, or a sale of the Software, associated documentation, or copies of the Software.

8. **Warranty, Limitation of Liability, Disclaimer of Warranty.** The warranty applicable to the Software shall be as set forth in the warranty statement that accompanies the Software (the "Warranty Statement"). Nothing in this Agreement shall give rise to any obligation to support the Software. Support services may be purchased separately. Any such support shall be governed by a separate, written support services agreement. TO THE MAXIMUM EXTENT PERMITTED BY LAW, JUNIPER SHALL NOT BE LIABLE FOR ANY LOST PROFITS, LOSS OF DATA, OR COSTS OR PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES, OR FOR ANY SPECIAL, INDIRECT, OR CONSEQUENTIAL DAMAGES ARISING OUT OF THIS AGREEMENT, THE SOFTWARE, OR ANY JUNIPER OR JUNIPER-SUPPLIED SOFTWARE. IN NO EVENT SHALL JUNIPER BE LIABLE FOR DAMAGES ARISING FROM UNAUTHORIZED OR IMPROPER USE OF ANY JUNIPER OR JUNIPER-SUPPLIED SOFTWARE. EXCEPT AS EXPRESSLY PROVIDED IN THE WARRANTY STATEMENT TO THE EXTENT PERMITTED BY LAW, JUNIPER DISCLAIMS ANY AND ALL WARRANTIES IN AND TO THE SOFTWARE (WHETHER EXPRESS, IMPLIED, STATUTORY, OR OTHERWISE), INCLUDING ANY IMPLIED WARRANTY OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, OR NONINFRINGEMENT. IN NO EVENT DOES JUNIPER WARRANT THAT THE SOFTWARE, OR ANY EQUIPMENT OR NETWORK RUNNING THE SOFTWARE, WILL OPERATE WITHOUT ERROR OR INTERRUPTION, OR WILL BE FREE OF VULNERABILITY TO INTRUSION OR ATTACK. In no event shall Juniper's or its suppliers' or licensors' liability to Customer, whether in contract, tort (including negligence), breach of warranty, or otherwise, exceed the price paid by Customer for the Software that gave rise to the claim, or if the Software is embedded in another Juniper product, the price paid by Customer for such other product. Customer acknowledges and agrees that Juniper has set its prices and entered into this Agreement in reliance upon the disclaimers of warranty and the limitations of liability set forth herein, that the same reflect an allocation of risk between the Parties (including the risk that a contract remedy may fail of its essential purpose and cause consequential loss), and that the same form an essential basis of the bargain between the Parties.

9. **Termination.** Any breach of this Agreement or failure by Customer to pay any applicable fees due shall result in automatic termination of the license granted herein. Upon such termination, Customer shall destroy or return to Juniper all copies of the Software and related documentation in Customer's possession or control.

10. **Taxes.** All license fees payable under this agreement are exclusive of tax. Customer shall be responsible for paying Taxes arising from the purchase of the license, or importation or use of the Software. If applicable, valid exemption documentation for each taxing jurisdiction shall be provided to Juniper prior to invoicing, and Customer shall promptly notify Juniper if their exemption is revoked or modified. All payments made by Customer shall be net of any applicable withholding tax. Customer will provide reasonable assistance to Juniper in connection with such withholding taxes by promptly: providing Juniper with valid tax receipts and other required documentation showing Customer's payment of any withholding taxes; completing appropriate applications that would reduce the amount of withholding tax to be paid; and notifying and assisting Juniper in any audit or tax proceeding related to transactions hereunder. Customer shall comply with all applicable tax laws and regulations, and Customer will promptly pay or reimburse Juniper for all costs and damages related to any liability incurred by Juniper as a result of Customer's non-compliance or delay with its responsibilities herein. Customer's obligations under this Section shall survive termination or expiration of this Agreement.

11. **Export.** Customer agrees to comply with all applicable export laws and restrictions and regulations of any United States and any applicable foreign agency or authority, and not to export or re-export the Software or any direct product thereof in violation of any such restrictions, laws or regulations, or without all necessary approvals. Customer shall be liable for any such violations. The version of the Software supplied to Customer may contain encryption or other capabilities restricting Customer's ability to export the Software without an export license.

12. **Commercial Computer Software.** The Software is "commercial computer software" and is provided with restricted rights. Use, duplication, or disclosure by the United States government is subject to restrictions set forth in this Agreement and as provided in DFARS 227.7201 through 227.7202-4, FAR 12.212, FAR 27.405(b)(2), FAR 52.227-19, or FAR 52.227-14 (ALT III) as applicable.

13. **Interface Information.** To the extent required by applicable law, and at Customer's written request, Juniper shall provide Customer with the interface information needed to achieve interoperability between the Software and another independently created program, on payment of applicable fee, if any. Customer shall observe strict obligations of confidentiality with respect to such information and shall use such information in compliance with any applicable terms and conditions upon which Juniper makes such information available.

14. **Third Party Software.** Any licensor of Juniper whose software is embedded in the Software and any supplier of Juniper whose products or technology are embedded in (or services are accessed by) the Software shall be a third party beneficiary with respect to this Agreement, and such licensor or vendor shall have the right to enforce this Agreement in its own name as if it were Juniper. In addition, certain third party software may be provided with the Software and is subject to the accompanying license(s), if any, of its respective owner(s). To the extent portions of the Software are distributed under and subject to open source licenses obligating Juniper to make the source code for such portions publicly available (such as the GNU General Public License ("GPL") or the GNU Library General Public License ("LGPL")), Juniper will make such source code portions (including Juniper modifications, as appropriate) available upon request for a period of up to three years from the date of distribution. Such request can be made in writing to Juniper Networks, Inc., 1194 N. Mathilda Ave., Sunnyvale, CA 94089, ATTN: General Counsel. You may obtain a copy of the GPL at <http://www.gnu.org/licenses/gpl.html>, and a copy of the LGPL at <http://www.gnu.org/licenses/lgpl.html>.

15. **Miscellaneous.** This Agreement shall be governed by the laws of the State of California without reference to its conflicts of laws principles. The provisions of the U.N. Convention for the International Sale of Goods shall not apply to this Agreement. For any disputes arising under this Agreement, the Parties hereby consent to the personal and exclusive jurisdiction of, and venue in, the state and federal courts within Santa Clara County, California. This Agreement constitutes the entire and sole agreement between Juniper and the Customer with respect to the Software, and supersedes all prior and contemporaneous agreements relating to the Software, whether oral or written (including any inconsistent terms contained in a purchase order), except that the terms of a separate written agreement executed by an authorized Juniper representative and Customer shall govern to the extent such terms are inconsistent or conflict with terms contained herein. No modification to this Agreement nor any waiver of any rights hereunder shall be effective unless expressly assented to in writing by the party to be charged. If any portion of this Agreement is held invalid, the Parties agree that such invalidity shall not affect the validity of the remainder of this Agreement. This Agreement and associated documentation has been written in the English language, and the Parties agree that the English version will govern. (For Canada: Les parties aux présentes confirment leur volonté que cette convention de même que tous les documents y compris tout avis qui s'y rattache, soient rédigés en langue anglaise. (Translation: The parties confirm that this Agreement and all related documentation is and will be in the English language)).

Abbreviated Table of Contents

	About This Guide	lxv
Part 1	Overview	
Chapter 1	Configuring System Log Messages	3
Part 2	System Log Messages	
Chapter 2	ACCT System Log Messages	57
Chapter 3	ALARMD System Log Messages	61
Chapter 4	ANCPD System Log Messages	67
Chapter 5	ANTISPAM System Log Messages	69
Chapter 6	APPID System Log Messages	71
Chapter 7	APPIDD System Log Messages	73
Chapter 8	APPPXY System Log Messages	75
Chapter 9	APPTRACK System Log Messages	77
Chapter 10	ASP System Log Messages	79
Chapter 11	AUDITD System Log Messages	109
Chapter 12	AUTHD System Log Messages	113
Chapter 13	AUTOCONFD System Log Messages	115
Chapter 14	AUTOD System Log Messages	117
Chapter 15	AV System Log Messages	119
Chapter 16	BFDD System Log Messages	125
Chapter 17	BOOTPD System Log Messages	129
Chapter 18	CFMD System Log Messages	135
Chapter 19	CHASSISD System Log Messages	139
Chapter 20	CHASSISM System Log Messages	219
Chapter 21	CONTENT System Log Messages	221
Chapter 22	COSD System Log Messages	223
Chapter 23	DCBX System Log Messages	237
Chapter 24	DCD System Log Messages	239
Chapter 25	DFCD System Log Messages	245
Chapter 26	DFWD System Log Messages	249
Chapter 27	DH System Log Messages	251
Chapter 28	DHCPD System Log Messages	255

Chapter 29	DYNAMIC System Log Messages	259
Chapter 30	ESPTASK System Log Messages	265
Chapter 31	ESWD System Log Messages	267
Chapter 32	EVENTD System Log Messages	275
Chapter 33	FC System Log Messages	283
Chapter 34	FCD System Log Messages	289
Chapter 35	FCOE System Log Messages	291
Chapter 36	FIP System Log Messages	293
Chapter 37	FLOW System Log Messages	297
Chapter 38	FPCLOGIN System Log Messages	299
Chapter 39	FSAD System Log Messages	301
Chapter 40	FUD System Log Messages	311
Chapter 41	FWAUTH System Log Messages	317
Chapter 42	GPRSD System Log Messages	321
Chapter 43	HNCACHED System Log Messages	323
Chapter 44	ICCPD System Log Messages	325
Chapter 45	IDP System Log Messages	327
Chapter 46	JADE System Log Messages	333
Chapter 47	JCS System Log Messages	335
Chapter 48	JDIAMETERD System Log Messages	341
Chapter 49	JIVED System Log Messages	343
Chapter 50	JPTSPD System Log Messages	347
Chapter 51	JSRPD System Log Messages	351
Chapter 52	KMD System Log Messages	359
Chapter 53	L2ALD System Log Messages	383
Chapter 54	L2CPD System Log Messages	393
Chapter 55	L2TPD System Log Messages	403
Chapter 56	LACPD System Log Messages	433
Chapter 57	LFMD System Log Messages	435
Chapter 58	LIBESPTASK System Log Messages	437
Chapter 59	LIBJNX System Log Messages	439
Chapter 60	LIBJSNMP System Log Messages	447
Chapter 61	LIBMSRPC System Log Messages	453
Chapter 62	LICENSE System Log Messages	457
Chapter 63	LLDPD System Log Messages	461
Chapter 64	LOGIN System Log Messages	463
Chapter 65	LPDFD System Log Messages	467
Chapter 66	LRMUX System Log Messages	469

Chapter 67	MCSN System Log Messages	471
Chapter 68	MCSNOOPD System Log Messages	477
Chapter 69	MIB2D System Log Messages	479
Chapter 70	MPLS_OAM System Log Messages	485
Chapter 71	NEXTHOP System Log Messages	489
Chapter 72	NSD System Log Messages	491
Chapter 73	NSTRACED System Log Messages	493
Chapter 74	PFE System Log Messages	495
Chapter 75	PFED System Log Messages	503
Chapter 76	PGCPD System Log Messages	505
Chapter 77	PING System Log Messages	507
Chapter 78	PPMD System Log Messages	511
Chapter 79	PPPD System Log Messages	513
Chapter 80	PROFILER System Log Messages	521
Chapter 81	RDD System Log Messages	523
Chapter 82	RMOPD System Log Messages	527
Chapter 83	RPD System Log Messages	531
Chapter 84	RT System Log Messages	677
Chapter 85	RTLOG System Log Messages	689
Chapter 86	RTLOGD System Log Messages	691
Chapter 87	RTPERF System Log Messages	693
Chapter 88	SAVAL System Log Messages	695
Chapter 89	SDXD System Log Messages	697
Chapter 90	SFW System Log Messages	701
Chapter 91	SMTPD System Log Messages	703
Chapter 92	SNMP System Log Messages	705
Chapter 93	SNMPD System Log Messages	709
Chapter 94	SPD System Log Messages	721
Chapter 95	SSH System Log Messages	727
Chapter 96	SSHD System Log Messages	729
Chapter 97	TASK System Log Messages	731
Chapter 98	TFTPD System Log Messages	739
Chapter 99	UFDD System Log Messages	743
Chapter 100	UI System Log Messages	745
Chapter 101	UTMD System Log Messages	769
Chapter 102	VCCPD System Log Messages	771
Chapter 103	VRRPD System Log Messages	775
Chapter 104	VSYS System Log Messages	779

Chapter 105	WEB System Log Messages	781
Chapter 106	WEBFILTER System Log Messages	787
Part 3	Index	
	Index	793

Table of Contents

	About This Guide	lxv
	Junos OS Documentation and Release Notes	lxv
	Objectives	lxvi
	Audience	lxvi
	Supported Platforms	lxvi
	Using the Examples in This Manual	lxvii
	Merging a Full Example	lxvii
	Merging a Snippet	lxviii
	Documentation Conventions	lxviii
	Documentation Feedback	lxx
	Requesting Technical Support	lxx
	Self-Help Online Tools and Resources	lxx
	Opening a Case with JTAC	lxxi
Part 1	Overview	
Chapter 1	Configuring System Log Messages	3
	System Logging Configuration Statements	4
	Minimum and Default System Logging Configuration	4
	Minimum System Logging Configuration	5
	Default System Log Settings	5
	Configuring System Logging for a Single-Chassis System	7
	Specifying the Facility and Severity of Messages to Include in the Log	8
	Directing Messages to a Log File	10
	Logging Messages in Structured-Data Format	11
	Directing Messages to a User Terminal	12
	Directing Messages to the Console	12
	Directing Messages to a Remote Machine or the Other Routing Engine	12
	Specifying an Alternative Source Address for System Log Messages	13
	Changing the Alternative Facility Name for Remote Messages	14
	Examples: Assigning an Alternative Facility	16
	Adding a Text String to System Log Messages	16
	Adding a String	17
	Configuring the Size and Number of Log Files	17
	Including Priority Information in System Log Messages	18
	Including the Year or Millisecond in Timestamps	21
	Using Regular Expressions to Refine the Set of Logged Messages	22
	Disabling Logging of a Facility	24
	Examples: Configuring System Logging	24

Configuring System Logging for a Routing Matrix	27
Configuring Message Forwarding in the Routing Matrix	28
Messages Logged When Local and Forwarded Severity Level Are the Same	29
Messages Logged When Local Severity Level Is Lower	30
Messages Logged When Local Severity Level Is Higher	31
Configuring Optional Features for Forwarded Messages	32
Including Priority Information in Forwarded Messages	32
Adding a Text String to Forwarded Messages	33
Using Regular Expressions to Refine the Set of Forwarded Messages	33
Directing Messages to a Remote Destination from the Routing Matrix	33
Configuring System Logging Differently on Each Platform	34
Displaying and Interpreting System Log Messages	36
Displaying a Log File from a Single-Chassis System	36
Displaying a Log File from a Routing Matrix	36
Interpreting System Log Messages	37
Interpreting Messages Generated in Structured-Data Format	37
Interpreting Messages Generated in Standard Format by a Junos Process or Library	42
Interpreting Messages Generated in Standard Format by Services on a PIC	43
Format of the message-source Field	44
The message-source Field on a Single-Chassis System	44
The message-source Field on a TX Matrix Platform	44
The message-source Field on a T640 Routing Node in a Routing Matrix	46
Examples: Displaying a Log File	47
Getting Help About System Log Messages	47
Displaying and Interpreting System Log Message Descriptions	48
Examples: Displaying System Log Message Descriptions	50

Part 2

System Log Messages

Chapter 2

ACCT System Log Messages	57
ACCT_ACCOUNTING_FERROR	57
ACCT_ACCOUNTING_FOPEN_ERROR	57
ACCT_ACCOUNTING_SMALL_FILE_SIZE	57
ACCT_BAD_RECORD_FORMAT	57
ACCT_CU_RTSLIB_ERROR	58
ACCT_FORK_ERR	58
ACCT_FORK_LIMIT_EXCEEDED	58
ACCT_GETHOSTNAME_ERROR	58
ACCT_MALLOC_FAILURE	59
ACCT_UNDEFINED_COUNTER_NAME	59
ACCT_XFER_FAILED	59
ACCT_XFER_POPEN_FAIL	59

Chapter 3	ALARM System Log Messages	61
	ALARM_CONFIG_ACCESS_ERROR	61
	ALARM_CONFIG_CLOSE_ERROR	61
	ALARM_CONFIG_PARSE_ERROR	61
	ALARM_CONFIG_RECONFIG_ERROR	62
	ALARM_CONNECTION_FAILURE	62
	ALARM_DECODE_ALARM_OBJECT_ERROR	62
	ALARM_EXISTS	62
	ALARM_EXISTS_TERM_OTHER	63
	ALARM_IFDALARMS_TYPE_ERROR	63
	ALARM_IFDEV_RTSLIB_FAILURE	63
	ALARM_IPC_MSG_ERROR	63
	ALARM_IPC_MSG_WRITE_ERROR	64
	ALARM_IPC_UNEXPECTED_CONN	64
	ALARM_IPC_UNEXPECTED_MSG	64
	ALARM_MEM_ALLOC_FAILURE	64
	ALARM_MGR_CONNECT	65
	ALARM_MULTIPLE_ALARM_BIT_ERROR	65
	ALARM_PIDFILE_OPEN	65
	ALARM_PIPE_WRITE_ERROR	65
	ALARM_SOCKET_CREATE	66
	ALARM_UNEXPECTED_EXIT	66
Chapter 4	ANCPD System Log Messages	67
	ANCPD_COMMAND_OPTIONS	67
Chapter 5	ANTISPAM System Log Messages	69
	ANTISPAM_SPAM_DETECTED_MT	69
Chapter 6	APPID System Log Messages	71
	APPID_SIGNATURE_LICENSE_EXPIRED	71
Chapter 7	APPIDD System Log Messages	73
	APPIDD_APPPACK_DOWNLOAD_RESULT	73
	APPIDD_APPPACK_UNINSTALL_RESULT	73
	APPIDD_DAEMON_INIT_FAILED	73
	APPIDD_SCHEDULED_UPDATE_FAILED	74
Chapter 8	APPPXY System Log Messages	75
	APPPXY_RESOURCE_OVERUSED_MT	75
	APPPXY_SESSION_ABORT_MT	75
Chapter 9	APPTRACK System Log Messages	77
	APPTRACK_SESSION_APP_UPDATE	77
	APPTRACK_SESSION_CLOSE	77
	APPTRACK_SESSION_CREATE	78
	APPTRACK_SESSION_VOL_UPDATE	78
Chapter 10	ASP System Log Messages	79
	ASP_COS_RULE_MATCH	79
	ASP_IDS_HOST_RATE	79

ASP_IDS_HOST_RATE_APP	80
ASP_IDS_INV_CLEAR_QUERY	80
ASP_IDS_INV_CLEAR_QUERY_VER	80
ASP_IDS_INV_SHOW_QUERY	80
ASP_IDS_INV_SHOW_QUERY_VER	81
ASP_IDS_LIMIT_FLOW_RATE_BY_DEST	81
ASP_IDS_LIMIT_FLOW_RATE_BY_PAIR	81
ASP_IDS_LIMIT_FLOW_RATE_BY_SRC	82
ASP_IDS_LIMIT_OPEN_FLOWS_BY_DEST	82
ASP_IDS_LIMIT_OPEN_FLOWS_BY_PAIR	83
ASP_IDS_LIMIT_OPEN_FLOWS_BY_SRC	83
ASP_IDS_LIMIT_PKT_RATE_BY_DEST	83
ASP_IDS_LIMIT_PKT_RATE_BY_PAIR	84
ASP_IDS_LIMIT_PKT_RATE_BY_SRC	84
ASP_IDS_NO_MEM_SHOW_CMD	84
ASP_IDS_NULL_CLEAR_QUERY	85
ASP_IDS_NULL_SHOW_QUERY	85
ASP_IDS_RULE_MATCH	85
ASP_IDS_SYN_COOKIE_OFF	85
ASP_IDS_SYN_COOKIE_ON	86
ASP_IDS_TCP_SYN_ATTACK	86
ASP_L2TP_MESSAGE_INCOMPLETE	87
ASP_L2TP_NO_MEM	87
ASP_L2TP_OBJ_CAC_FAIL	87
ASP_L2TP_STATS_BULK_QUERY_FAILED	87
ASP_L2TP_STATS_VERSION_INVALID	87
ASP_L2TP_TUN_GRP_ADD_FAIL_ALLOC	88
ASP_L2TP_TUN_GRP_ADD_FAIL_EXISTS	88
ASP_L2TP_TUN_GRP_CHG_FAIL_ALLOC	88
ASP_L2TP_TUN_GRP_CHG_FAIL_INVLD	88
ASP_L2TP_TUN_GRP_DEL_FAIL_INVLD	89
ASP_NAT_OUTOF_ADDRESSES	89
ASP_NAT_OUTOF_PORTS	89
ASP_NAT_POOL_RELEASE	89
ASP_NAT_RULE_MATCH	89
ASP_PGCP_IPC_MSG_WRITE_FAILED	90
ASP_PGCP_IPC_PIPE_WRITE_FAILED	90
ASP_SFW_ALG_LEVEL_ADJUSTED	90
ASP_SFW_ALG_PROMOTION_FAILED	91
ASP_SFW_APP_MSG_TOO_LONG	91
ASP_SFW_CHANGE_INACTIVITY_TIMER	92
ASP_SFW_CREATE_ACCEPT_FLOW	92
ASP_SFW_CREATE_DISCARD_FLOW	92
ASP_SFW_CREATE_REJECT_FLOW	93
ASP_SFW_DELETE_FLOW	93
ASP_SFW_FTP_ACTIVE_ACCEPT	93
ASP_SFW_FTP_PASSIVE_ACCEPT	94
ASP_SFW_ICMP_ERROR_DROP	94
ASP_SFW_ICMP_HEADER_LEN_ERROR	94

ASP_SFW_ICMP_PACKET_ERROR_LENGTH	95
ASP_SFW_IP_FRAG_ASSEMBLY_TIMEOUT	95
ASP_SFW_IP_FRAG_OVERLAP	95
ASP_SFW_IP_OPTION_DROP_PACKET	96
ASP_SFW_IP_PACKET_CHECKSUM_ERROR	96
ASP_SFW_IP_PACKET_DST_BAD	96
ASP_SFW_IP_PACKET_FRAG_LEN_INV	97
ASP_SFW_IP_PACKET_INCORRECT_LEN	97
ASP_SFW_IP_PACKET_LAND_ATTACK	97
ASP_SFW_IP_PACKET_NOT_VERSION_4	98
ASP_SFW_IP_PACKET_PROTOCOL_ERROR	98
ASP_SFW_IP_PACKET_SRC_BAD	98
ASP_SFW_IP_PACKET_TOO_LONG	99
ASP_SFW_IP_PACKET_TOO_SHORT	99
ASP_SFW_IP_PACKET_TTL_ERROR	99
ASP_SFW_NEW_POLICY	100
ASP_SFW_NO_IP_PACKET	100
ASP_SFW_NO_POLICY	100
ASP_SFW_NO_RULE_DROP	100
ASP_SFW_PING_DUPLICATED_SEQNO	101
ASP_SFW_PING_MISMATCHED_SEQNO	101
ASP_SFW_PING_OUTOF_SEQNO_CACHE	101
ASP_SFW_POLICY_REJECT	102
ASP_SFW_RULE_ACCEPT	102
ASP_SFW_RULE_DISCARD	102
ASP_SFW_RULE_REJECT	103
ASP_SFW_SYN_DEFENSE	103
ASP_SFW_TCP_BAD_SYN_COOKIE_RESP	104
ASP_SFW_TCP_FLAGS_ERROR	104
ASP_SFW_TCP_HEADER_LEN_ERROR	104
ASP_SFW_TCP_NON_SYN_FIRST_PACKET	105
ASP_SFW_TCP_PORT_ZERO	105
ASP_SFW_TCP_RECONSTRUCT_DROP	105
ASP_SFW_TCP_SCAN	106
ASP_SFW_TCP_SEQNO_AND_FLAGS_ZERO	106
ASP_SFW_TCP_SEQNO_ZERO_FLAGS_SET	106
ASP_SFW_UDP_HEADER_LEN_ERROR	107
ASP_SFW_UDP_PORT_ZERO	107
ASP_SFW_UDP_SCAN	107
ASP_SFW_VERY_BAD_PACKET	108
ASP_SVC_SET_MAX_FLOWS_EXCEEDED	108
Chapter 11	
AUDITD System Log Messages	109
AUDITD_RADIUS_AV_ERROR	109
AUDITD_RADIUS_OPEN_FAILED	109
AUDITD_RADIUS_REQ_CREATE_FAILED	109
AUDITD_RADIUS_REQ_DROPPED	110
AUDITD_RADIUS_REQ_SEND_ERROR	110
AUDITD_RADIUS_REQ_TIMED_OUT	110

	AUDITD_RADIUS_SERVER_ADD_ERROR	111
	AUDITD_SOCKET_FAILURE	111
Chapter 12	AUTHD System Log Messages	113
	AUTHD_AUTH_CREATE_FAILED	113
	AUTHD_RADIUS_GETHOSTNAME_FAILED	113
	AUTHD_SERVER_INIT_BIND_FAIL	113
	AUTHD_SERVER_INIT_LISTEN_FAIL	114
Chapter 13	AUTOCONFD System Log Messages	115
	AUTOCONFD_AUTHENTICATE_LICENSE	115
Chapter 14	AUTOD System Log Messages	117
	AUTOD_BIND_FAILURE	117
	AUTOD_HOSTNAME_EXPANSION_FAILURE	117
	AUTOD_RECV_FAILURE	117
	AUTOD_RES_MKQUERY_FAILURE	118
	AUTOD_SEND_FAILURE	118
	AUTOD_SOCKET_CREATE_FAILURE	118
Chapter 15	AV System Log Messages	119
	AV_HUGE_FILE_DROPPED_MT	119
	AV_HUGE_FILE_NOT_SCANNED_MT	119
	AV_MANY_MSGS_DROPPED_MT	119
	AV_MANY_MSGS_NOT_SCANNED_MT	120
	AV_PATTERN_GET_FAILED	120
	AV_PATTERN_KEY_EXPIRED	120
	AV_PATTERN_KL_CHECK_FAILED	121
	AV_PATTERN_TOO_BIG	121
	AV_PATTERN_UPDATED	121
	AV_PATTERN_WRITE_FS_FAILED	121
	AV_SCANNER_DROP_FILE_MT	122
	AV_SCANNER_ERROR_SKIPPED_MT	122
	AV_SCANNER_READY	122
	AV_VIRUS_DETECTED_MT	123
Chapter 16	BFDD System Log Messages	125
	BFDD_MIRROR_ERROR	125
	BFDD_MIRROR_VERSION_MISMATCH	125
	BFDD_READ_ERROR	126
	BFDD_TRAP_MHOP_STATE_DOWN	126
	BFDD_TRAP_MHOP_STATE_UP	126
	BFDD_TRAP_SHOP_STATE_DOWN	126
	BFDD_TRAP_SHOP_STATE_UP	127
	BFDD_TRAP_STATE_DOWN	127
	BFDD_TRAP_STATE_UP	127
	BFDD_WRITE_ERROR	127
Chapter 17	BOOTPD System Log Messages	129
	BOOTPD_ARG_ERR	129
	BOOTPD_BAD_ID	129

	BOOTPD_BOOTSTRING	129
	BOOTPD_CONFIG_ERR	130
	BOOTPD_CONF_OPEN	130
	BOOTPD_DUP_PIC_SLOT	130
	BOOTPD_DUP_REV	131
	BOOTPD_DUP_SLOT	131
	BOOTPD_HWDB_ERROR	131
	BOOTPD_MODEL_CHK	131
	BOOTPD_MODEL_ERR	132
	BOOTPD_NEW_CONF	132
	BOOTPD_NO_BOOTSTRING	132
	BOOTPD_NO_CONFIG	133
	BOOTPD_PARSE_ERR	133
	BOOTPD_REPARSE	133
	BOOTPD_SELECT_ERR	133
	BOOTPD_TIMEOUT	134
Chapter 18	CFMD System Log Messages	135
	CFMD_CCM_DEFECT_CROSS_CONNECT	135
	CFMD_CCM_DEFECT_ERROR	135
	CFMD_CCM_DEFECT_MAC_STATUS	136
	CFMD_CCM_DEFECT_NONE	136
	CFMD_CCM_DEFECT_RDI	136
	CFMD_CCM_DEFECT_RMEP	136
	CFMD_CCM_DEFECT_UNKNOWN	137
	CFMD_PARSE_BAD_SWITCH	137
	CFMD_PARSE_CMD_ARG	137
	CFMD_PARSE_CMD_EXTRA	137
	CFMD_PARSE_USAGE	138
	CFMD_PPM_READ_ERROR	138
	CFMD_PPM_WRITE_ERROR	138
Chapter 19	CHASSISD System Log Messages	139
	CHASSISD_ANTICF_PIM_CHECK_FAILED	139
	CHASSISD_ANTICF_RE_CHECK_FAILED	139
	CHASSISD_ANTICF_RE_ROM_READ_FAIL	139
	CHASSISD_ANTICF_RE_SHA_READ_FAIL	140
	CHASSISD_ANTICF_ROM_READ_FAILED	140
	CHASSISD_ANTICF_SHA_READ_FAILED	140
	CHASSISD_ARGUMENT_ERROR	140
	CHASSISD_BLOWERS_SPEED	141
	CHASSISD_BLOWERS_SPEED_FULL	141
	CHASSISD_BLOWERS_SPEED_MEDIUM	141
	CHASSISD_BUS_DEVICE_OPEN_FAILURE	141
	CHASSISD_CB_CLOCK_CHECKSUM	142
	CHASSISD_CB_MASTER_BP_IGNORED	142
	CHASSISD_CB_READ	142
	CHASSISD_CB_RE_ONLINE_BP_IGNORED	142
	CHASSISD_CFEB_POWER_FAILURE	143
	CHASSISD_CLEAR_CONFIG_ERROR	143

CHASSISD_CLOCK_FAILURE	143
CHASSISD_CLOCK_NOTICE	144
CHASSISD_CLOCK_RESET_FAIL	144
CHASSISD_CMB_READBACK_ERROR	144
CHASSISD_COMMAND_ACK_ERROR	144
CHASSISD_COMMAND_ACK_SFM_ERROR	145
CHASSISD_CONCAT_MODE_ERROR	145
CHASSISD_CONFIG_ACCESS_ERROR	145
CHASSISD_CONFIG_CHANGE_IFDEV_DEL	146
CHASSISD_CONFIG_INIT_ERROR	146
CHASSISD_CONFIG_WARNING	146
CHASSISD_DEVICE_OPEN_ERROR	146
CHASSISD_EXEC_ERROR	146
CHASSISD_EXISTS	147
CHASSISD_EXISTS_TERM_OTHER	147
CHASSISD_FAN_FAILURE	147
CHASSISD_FASIC_CONFIG_COMPLETE	148
CHASSISD_FASIC_FTOKEN_ERROR	148
CHASSISD_FASIC_FTOKEN_INIT_ERROR	148
CHASSISD_FASIC_HSL_CONFIG_ERROR	148
CHASSISD_FASIC_HSL_LINK_ERROR	149
CHASSISD_FASIC_INIT_ERROR	149
CHASSISD_FASIC_INPUT_DROP	149
CHASSISD_FASIC_OUTPUT_DROP	149
CHASSISD_FASIC_PIO_READ_ERROR	150
CHASSISD_FASIC_PIO_WRITE_ERROR	150
CHASSISD_FASIC_PLL_ERROR	150
CHASSISD_FASIC_RESET_ERROR	151
CHASSISD_FASIC_SRAM_ERROR	151
CHASSISD_FASIC_VERSION_ERROR	151
CHASSISD_FCHIP_CONFIG_COMPLETE	151
CHASSISD_FCHIP_CONFIG_MD_ERROR	152
CHASSISD_FCHIP_CONFIG_RATE_ERROR	152
CHASSISD_FCHIP_CONFIG_READ_ERROR	152
CHASSISD_FCHIP_FTOKEN_ERROR	152
CHASSISD_FCHIP_FTOKEN_INIT_ERROR	153
CHASSISD_FCHIP_HSR_ERROR	153
CHASSISD_FCHIP_HSR_INIT_ERROR	153
CHASSISD_FCHIP_HSR_INIT_LINK_ERR	153
CHASSISD_FCHIP_HSR_RESET_ERROR	153
CHASSISD_FCHIP_HST_ERROR	154
CHASSISD_FCHIP_HST_INIT_ERROR	154
CHASSISD_FCHIP_HST_INIT_LINK_ERR	154
CHASSISD_FCHIP_HST_RESET_ERROR	154
CHASSISD_FCHIP_INIT_ERROR	155
CHASSISD_FCHIP_LINK_ERROR	155
CHASSISD_FCHIP_MONITOR_ERROR	155
CHASSISD_FCHIP_PIO_READ_ERROR	155
CHASSISD_FCHIP_PIO_WRITE_ERROR	156

CHASSISD_FCHIP_POLL_ERROR	156
CHASSISD_FCHIP_RATE_ERROR	156
CHASSISD_FCHIP_SIB_NOT_STARTED	156
CHASSISD_FCHIP_VERSION_ERROR	157
CHASSISD_FEB_REVERSION	157
CHASSISD_FEB_SWITCHOVER	157
CHASSISD_FHSR_READ_REG_ERROR	157
CHASSISD_FHSR_WRITE_REG_ERROR	158
CHASSISD_FHST_READ_REG_ERROR	158
CHASSISD_FHST_WRITE_REG_ERROR	158
CHASSISD_FILE_OPEN	158
CHASSISD_FILE_STAT	158
CHASSISD_FM_BAD_STATE	159
CHASSISD_FM_ERROR	159
CHASSISD_FM_ERROR_CLOS_F13_HSR	159
CHASSISD_FM_ERROR_CLOS_F13_HST	160
CHASSISD_FM_ERROR_CLOS_F2_HSR	160
CHASSISD_FM_ERROR_CLOS_F2_HST	160
CHASSISD_FM_ERROR_F13_FB_HSR_TXP	161
CHASSISD_FM_ERROR_F13_FB_RX_VC	161
CHASSISD_FM_ERROR_F13_FB_TXP	162
CHASSISD_FM_ERROR_F13_FB_TX_VC	162
CHASSISD_FM_ERROR_F13_VC_PWR	162
CHASSISD_FM_ERROR_SIB_L_FB_HSR	163
CHASSISD_FM_ERROR_SIB_L_FB_RX_VC	163
CHASSISD_FM_ERROR_SIB_L_FB_SMF	163
CHASSISD_FM_ERROR_SIB_L_FB_TXP	164
CHASSISD_FM_ERROR_SIB_L_FB_TX_VC	164
CHASSISD_FM_ERROR_SIB_L_HSR_PFE	164
CHASSISD_FM_ERROR_SIB_L_HSR_TXP	165
CHASSISD_FM_ERROR_SIB_L_MISMATCH	165
CHASSISD_FM_ERROR_SIB_L_VC_PWR	165
CHASSISD_FM_ERROR_SIB_S_FB_HSR	166
CHASSISD_FM_ERROR_SIB_S_FB_SMF	166
CHASSISD_FM_FABRIC_DOWN	166
CHASSISD_FM_MEMORY_ERROR	167
CHASSISD_FM_SIB_ERROR	167
CHASSISD_FM_SIB_FPC_TYPE_ERROR	167
CHASSISD_FPC_FABRIC_DOWN_REBOOT	167
CHASSISD_FPC_NOT_FOUND	168
CHASSISD_FPC_PIC_DETECT_TIMEOUT	168
CHASSISD_FPC_TYPE_SIB_TYPE_ERROR	168
CHASSISD_FRU_ALREADY_OFFLINE	169
CHASSISD_FRU_ALREADY_ONLINE	169
CHASSISD_FRU_EVENT	169
CHASSISD_FRU_INVALID_SLOT	169
CHASSISD_FRU_IO_ERROR	170
CHASSISD_FRU_IO_OFFSET_ERROR	170
CHASSISD_FRU_IPC_WRITE_ERROR	170

CHASSISD_FRU_OFFLINE_FAILED	170
CHASSISD_FRU_OFFLINE_NOTICE	171
CHASSISD_FRU_OFFLINE_TIMEOUT	171
CHASSISD_FRU_ONLINE_TIMEOUT	171
CHASSISD_FRU_STEP_ERROR	171
CHASSISD_FRU_UNRESPONSIVE	172
CHASSISD_FRU_UNRESPONSIVE_RETRY	172
CHASSISD_FRU_UNSUPPORTED	172
CHASSISD_FRU_VERSION_MISMATCH	172
CHASSISD_GASIC_ID_ERROR	173
CHASSISD_GBUS_NOT_READY	173
CHASSISD_GBUS_READBACK_ERROR	173
CHASSISD_GBUS_RESET_EVENT	173
CHASSISD_GBUS_SANITY_ERROR	174
CHASSISD_GENERIC_ERROR	174
CHASSISD_GENERIC_WARNING	174
CHASSISD_GETTIMEOFDAY	174
CHASSISD_GRES_UNSUPP_PIC	175
CHASSISD_HIGH_TEMP_CONDITION	175
CHASSISD_HOST_TEMP_READ	175
CHASSISD_HSR_CONFIG_READ_ERROR	175
CHASSISD_HSR_CONFIG_WRITE_ERROR	176
CHASSISD_HSR_ELEMENTS_ERROR	176
CHASSISD_HSR_FIFO_ERROR	176
CHASSISD_I2CS_READBACK_ERROR	176
CHASSISD_I2C_BAD_IDEEPROM_FORMAT	177
CHASSISD_I2C_FIC_PRESENCE_READ	177
CHASSISD_I2C_GENERIC_ERROR	177
CHASSISD_I2C_INVALID_ASSEMBLY_ID	177
CHASSISD_I2C_IOCTL_FAILURE	178
CHASSISD_I2C_IO_FAILURE	178
CHASSISD_I2C_MIDPLANE_CORRUPT	178
CHASSISD_I2C_RANGE_ERROR	178
CHASSISD_I2C_READ_ERROR	179
CHASSISD_I2C_WRITE_ERROR	179
CHASSISD_IDEEPROM_READ_ERROR	179
CHASSISD_IFDEV_CREATE_FAILURE	180
CHASSISD_IFDEV_CREATE_NOTICE	180
CHASSISD_IFDEV_DETACH_ALL_PSEUDO	180
CHASSISD_IFDEV_DETACH_FPC	180
CHASSISD_IFDEV_DETACH_PIC	181
CHASSISD_IFDEV_DETACH_PSEUDO	181
CHASSISD_IFDEV_DETACH_TLV_ERROR	181
CHASSISD_IFDEV_GETBYNAME_NOTICE	181
CHASSISD_IFDEV_GET_BY_INDEX_FAIL	182
CHASSISD_IFDEV_GET_BY_NAME_FAIL	182
CHASSISD_IFDEV_NO_MEMORY	182
CHASSISD_IFDEV_RETRY_NOTICE	182
CHASSISD_IFDEV_RTSLIB_FAILURE	183

CHASSISD_IOCTL_FAILURE	183
CHASSISD_IPC_ANNOUNCE_TIMEOUT	183
CHASSISD_IPC_CONNECTION_DROPPED	183
CHASSISD_IPC_DAEMON_WRITE_ERROR	184
CHASSISD_IPC_ERROR	184
CHASSISD_IPC_FLUSH_ERROR	184
CHASSISD_IPC_MSG_DROPPED	185
CHASSISD_IPC_MSG_ERROR	185
CHASSISD_IPC_MSG_FRU_NOT_FOUND	185
CHASSISD_IPC_MSG_QFULL_ERROR	186
CHASSISD_IPC_MSG_UNHANDLED	186
CHASSISD_IPC_UNEXPECTED_MSG	186
CHASSISD_IPC_UNEXPECTED_RECV	186
CHASSISD_IPC_WRITE_ERROR	187
CHASSISD_IPC_WRITE_ERR_NO_PIPE	187
CHASSISD_IPC_WRITE_ERR_NULL_ARGS	187
CHASSISD_ISSU_BLOB_ERROR	187
CHASSISD_ISSU_DAEMON_ERROR	188
CHASSISD_ISSU_ERROR	188
CHASSISD_ISSU_FRU_ERROR	188
CHASSISD_ISSU_FRU_IPC_ERROR	188
CHASSISD_JTREE_ERROR	188
CHASSISD_LCC_RELEASE_MASTERSHIP	189
CHASSISD_LOST_MASTERSHIP	189
CHASSISD_MAC_ADDRESS_AE_ERROR	189
CHASSISD_MAC_ADDRESS_CBP_ERROR	189
CHASSISD_MAC_ADDRESS_ERROR	190
CHASSISD_MAC_ADDRESS_FABRIC_ERR	190
CHASSISD_MAC_ADDRESS_IRB_ERROR	190
CHASSISD_MAC_ADDRESS_PIP_ERROR	190
CHASSISD_MAC_ADDRESS_SWFAB_ERR	191
CHASSISD_MAC_ADDRESS_VLAN_ERROR	191
CHASSISD_MAC_DEFAULT	191
CHASSISD_MALLOC_FAILURE	191
CHASSISD_MASTER_PCG_REMOVED	192
CHASSISD_MASTER_SCG_REMOVED	192
CHASSISD_MBUS_ERROR	192
CHASSISD_MCHASSIS_SWITCH_WARNING	192
CHASSISD_MCS_INTR_ERROR	193
CHASSISD_MGR_CONNECT	193
CHASSISD_MIC_OFFLINE_NOTICE	193
CHASSISD_MULTILINK_BUNDLES_ERROR	194
CHASSISD_NO_PCGS	194
CHASSISD_NO_SCGS	194
CHASSISD_OFFLINE_NOTICE	194
CHASSISD_OID_GEN_FAILED	195
CHASSISD_OVER_TEMP_CONDITION	195
CHASSISD_OVER_TEMP_SHUTDOWN_TIME	195
CHASSISD_PARSE_COMPLETE	196

CHASSISD_PCI_ERROR	196
CHASSISD_PEER_UNCONNECTED	196
CHASSISD_PEM_BREAKER_TRIP	196
CHASSISD_PEM_IMPROPER	197
CHASSISD_PEM_INPUT_BAD	197
CHASSISD_PEM_NOT_SUFFICIENT	197
CHASSISD_PEM_OVERLOAD	197
CHASSISD_PEM_TEMPERATURE	198
CHASSISD_PEM_VOLTAGE	198
CHASSISD_PIC_CMD_GIVEUP	198
CHASSISD_PIC_CMD_TIMEOUT	199
CHASSISD_PIC_CONFIG_CONFLICT	199
CHASSISD_PIC_CONFIG_ERROR	199
CHASSISD_PIC_HWERROR	199
CHASSISD_PIC_OFFLINE_NOTICE	200
CHASSISD_PIC_OID_GEN_FAILED	200
CHASSISD_PIC_OID_UNKNOWN	200
CHASSISD_PIC_RESET_ON_SWITCHOVER	200
CHASSISD_PIC_SPEED_INVALID	201
CHASSISD_PIC_VERSION_ERROR	201
CHASSISD_PIDFILE_OPEN	201
CHASSISD_PIPE_WRITE_ERROR	201
CHASSISD_POWER_CHECK	202
CHASSISD_POWER_EVENT	202
CHASSISD_POWER_RATINGS_EXCEEDED	202
CHASSISD_PSD_RELEASE_MASTERSHIP	203
CHASSISD_PSU_ERROR	203
CHASSISD_PSU_FAN_FAIL	203
CHASSISD_PSU_INPUT_BAD	203
CHASSISD_PSU_OVERLOAD	204
CHASSISD_PSU_TEMPERATURE	204
CHASSISD_PSU_VOLTAGE	204
CHASSISD_RANGE_CHECK	204
CHASSISD_RECONNECT_SUCCESSFUL	205
CHASSISD_RELEASE_MASTERSHIP	205
CHASSISD_RE_CONSOLE_FE_STORM	205
CHASSISD_RE_INIT_INVALID_RE_SLOT	205
CHASSISD_RE_OVER_TEMP_CONDITION	206
CHASSISD_RE_OVER_TEMP_SHUTDOWN	206
CHASSISD_RE_OVER_TEMP_WARNING	206
CHASSISD_RE_WARM_TEMP_CONDITION	207
CHASSISD_ROOT_MOUNT_ERROR	207
CHASSISD_RTS_SEQ_ERROR	207
CHASSISD_SBOARD_VERSION_MISMATCH	207
CHASSISD_SENSOR_RANGE_NOTICE	208
CHASSISD_SERIAL_ID	208
CHASSISD_SFM_MODE_ERROR	208
CHASSISD_SFM_NOT_ONLINE	209
CHASSISD_SHUTDOWN_NOTICE	209

	CHASSISD_SIB_INVALID_SLOT	209
	CHASSISD_SIGPIPE	209
	CHASSISD_SMB_ERROR	210
	CHASSISD_SMB_INVALID_PS	210
	CHASSISD_SMB_IOCTL_FAILURE	210
	CHASSISD_SMB_READ_FAILURE	210
	CHASSISD_SNMP_TRAP1	211
	CHASSISD_SNMP_TRAP10	211
	CHASSISD_SNMP_TRAP6	211
	CHASSISD_SNMP_TRAP7	211
	CHASSISD_SPI_IOCTL_FAILURE	212
	CHASSISD_SPMB_RESTART	212
	CHASSISD_SPMB_RESTART_TIMEOUT	212
	CHASSISD_SSB_FAILOVERS	212
	CHASSISD_STANDALONE_FPC_NOTICE	213
	CHASSISD_SYSCTL_ERROR	213
	CHASSISD_TEMP_HOT_NOTICE	213
	CHASSISD_TEMP_SENSOR_FAILURE	213
	CHASSISD_TERM_SIGNAL	214
	CHASSISD_TIMER_CLR_ERR	214
	CHASSISD_TIMER_ERR	214
	CHASSISD_TIMER_VAL_ERR	214
	CHASSISD_UNEXPECTED_EXIT	215
	CHASSISD_UNEXPECTED_VALUE	215
	CHASSISD_UNSUPPORTED_FPC	215
	CHASSISD_UNSUPPORTED_MODEL	215
	CHASSISD_UNSUPPORTED_PIC	216
	CHASSISD_UNSUPPORTED_PIC_MODE	216
	CHASSISD_UNSUPPORTED_SIB	216
	CHASSISD_VERSION_MISMATCH	217
	CHASSISD_VOLTAGE_READ_FAILED	217
	CHASSISD_VOLTAGE_SENSOR_INIT	217
Chapter 20	CHASSISM System Log Messages	219
	CHASSISM_SYSTEM	219
Chapter 21	CONTENT System Log Messages	221
	CONTENT_FILTERING_BLOCKED_MT	221
Chapter 22	COSD System Log Messages	223
	COSD_AGGR_CONFIG_INVALID	223
	COSD_CHASSIS_SCHED_MAP_INVALID	223
	COSD_CLASSIFIER_NO_SUPPORT_LSI	224
	COSD_CLASS_8021P_UNSUPPORTED	224
	COSD_CONF_OPEN_FAILURE	224
	COSD_DB_OPEN_FAILED	225
	COSD_EXACT_RATE_UNSUPP_INTERFACE	225
	COSD_EXACT_RATE_UNSUPP_SESSION	225
	COSD_FRAGMENTATION_MAP_CONFLICT	226
	COSD_HIGH_PRIO_QUEUES_INTERFACE	226

	COSD_HIGH_PRIO_QUEUES_SESSION	227
	COSD_IFD_OUTPUT_SHAPING_RATE_ERR	227
	COSD_IFD_SHAPER_ERR	227
	COSD_INTERFACE_NO_MEDIA	228
	COSD_L2TP_COS_NOT_CONFIGURED	228
	COSD_L2TP_COS_NOT_SUPPORTED	228
	COSD_L2TP_SHAPING_NOT_CONFIGURED	229
	COSD_LARGE_DELAY_BUFFER_INVALID	229
	COSD_MALLOC_FAILED	229
	COSD_MPLS_DSCP_CLASS_NO_SUPPORT	230
	COSD_MULTILINK_CLASS_CONFLICT	230
	COSD_NULL_INPUT_ARGUMENT	230
	COSD_OUT_OF_DEDICATED_QUEUES	231
	COSD_RATE_LIMIT_INVALID	231
	COSD_RATE_LIMIT_NOT_SUPPORTED	231
	COSD_REWRITE_RULE_LIMIT_EXCEEDED	232
	COSD_RL_IFL_NEEDS_SHAPING	232
	COSD_SCHEDULER_MAP_CONFLICT	232
	COSD_SCHED_AVG_CONST_UNSUPPORTED	233
	COSD_SCHED_MAP_GROUP_CONFLICT	233
	COSD_SHAPER_GROUP_CONFLICT	233
	COSD_STREAM_IFD_CREATE_FAILURE	233
	COSD_TIMER_ERROR	234
	COSD_TRICOLOR_ALWAYS_ON	234
	COSD_TRICOLOR_NOT_SUPPORTED	234
	COSD_TX_QUEUE_RATES_TOO_HIGH	235
	COSD_UNKNOWN_CLASSIFIER	235
	COSD_UNKNOWN_REWRITE	236
	COSD_UNKNOWN_TRANSLATION_TABLE	236
Chapter 23	DCBX System Log Messages	237
	DCBX_VERSION	237
Chapter 24	DCD System Log Messages	239
	DCD_GRE_CONFIG_INVALID	239
	DCD_MALLOC_FAILED_INIT	239
	DCD_PARSE_CFG_WARNING	239
	DCD_PARSE_EMERGENCY	240
	DCD_PARSE_ERROR_CLOCK	240
	DCD_PARSE_ERROR_HIER_SCHEDULER	240
	DCD_PARSE_ERROR_IFLSET	241
	DCD_PARSE_ERROR_MAX_HIER_LEVELS	241
	DCD_PARSE_ERROR_SCHEDULER	241
	DCD_PARSE_ERROR_SCHEDULER_LIMIT	242
	DCD_PARSE_ERROR_VLAN_TAGGING	242
	DCD_PARSE_ERR_INCOMPATIBLE_CFG	242
	DCD_PARSE_MINI_EMERGENCY	242
	DCD_PARSE_STATE_EMERGENCY	243

Chapter 25	DFCD System Log Messages	245
	DFCD_FTAP_PIC_UNSUPPORTED	245
	DFCD_GENCFG_MALLOC_FAILED	245
	DFCD_GENCFG_WRITE_FAILED	245
	DFCD_LINH_MALLOC_FAILED	246
	DFCD_LI_NEXT_HOP_ADD_FAILED	246
	DFCD_NEXT_HOP_ADD_FAILED	246
	DFCD_NEXT_HOP_DELETE_FAILED	246
	DFCD_SAMPLE_CLASS_ADD_FAILED	246
	DFCD_SAMPLE_CLASS_DELETE_FAILED	247
Chapter 26	DFWD System Log Messages	249
	DFWD_MALLOC_FAILED_INIT	249
	DFWD_PARSE_FILTER_EMERGENCY	249
	DFWD_PARSE_STATE_EMERGENCY	249
	DFWD_POLICER_LIMIT_EXCEEDED	250
Chapter 27	DH System Log Messages	251
	DH_SVC_AUTHENTICATE_LICENSE	251
	DH_SVC_BIND_FAILURE	251
	DH_SVC_RECVMSG_FAILURE	251
	DH_SVC_RTsock_FAILURE	252
	DH_SVC_SENDMSG_FAILURE	252
	DH_SVC_SENDMSG_NOINT_FAILURE	252
	DH_SVC_SETSOCKOPT_FAILURE	253
	DH_SVC_SOCKET_FAILURE	253
Chapter 28	DHCPD System Log Messages	255
	DHCPD_BIND_FAILURE	255
	DHCPD_DEGRADED_MODE	255
	DHCPD_MEMORY_ALLOCATION_FAILURE	255
	DHCPD_OVERLAY_CONFIG_FAILURE	256
	DHCPD_OVERLAY_PARSE_FAILURE	256
	DHCPD_RECVMSG_FAILURE	256
	DHCPD_RTsock_FAILURE	257
	DHCPD_SENDMSG_FAILURE	257
	DHCPD_SENDMSG_NOINT_FAILURE	257
	DHCPD_SETSOCKOPT_FAILURE	258
	DHCPD_SOCKET_FAILURE	258
Chapter 29	DYNAMIC System Log Messages	259
	DYNAMIC_VPN_AUTH_CONNECT_FAIL	259
	DYNAMIC_VPN_AUTH_FAIL	259
	DYNAMIC_VPN_AUTH_INVALID	259
	DYNAMIC_VPN_AUTH_MUL_CONN	260
	DYNAMIC_VPN_AUTH_NO_CONFIG	260
	DYNAMIC_VPN_AUTH_NO_LICENSE	260
	DYNAMIC_VPN_AUTH_OK	260
	DYNAMIC_VPN_CLIENT_CONFIG_WRITE	260
	DYNAMIC_VPN_CONN_DEL_NOTIFY	261

	DYNAMIC_VPN_CONN_DEL_REQUEST	261
	DYNAMIC_VPN_CONN_EST_NOTIFY	261
	DYNAMIC_VPN_INIT_SUCCESSFUL	261
	DYNAMIC_VPN_LICENSE_ASSIGNED	262
	DYNAMIC_VPN_LICENSE_CHECK_FAILED	262
	DYNAMIC_VPN_LICENSE_CHECK_OK	262
	DYNAMIC_VPN_LICENSE_EXHAUSTED	262
	DYNAMIC_VPN_LICENSE_FREED	262
	DYNAMIC_VPN_LICENSE_FREE_FAILED	263
	DYNAMIC_VPN_LICENSE_FREE_OK	263
	DYNAMIC_VPN_LICENSE_GET_FAILED	263
	DYNAMIC_VPN_LICENSE_GET_OK	263
	DYNAMIC_VPN_LICENSE_INSTALLED	263
	DYNAMIC_VPN_LICENSE_REQUIRED	264
	DYNAMIC_VPN_LICENSE_UNINSTALLED	264
Chapter 30	ESPTASK System Log Messages	265
	ESPTASK_PARSE_BAD_SWITCH	265
	ESPTASK_PARSE_CMD_ARG	265
	ESPTASK_PARSE_CMD_EXTRA	265
	ESPTASK_PARSE_USAGE	266
Chapter 31	ESWD System Log Messages	267
	ESWD_BPDU_BLOCK_ERROR_DISABLED	267
	ESWD_BPDU_BLOCK_ERROR_ENABLED	267
	ESWD_DAI_FAILED	267
	ESWD_DHCP_UNTRUSTED	268
	ESWD_INVALID_MAC_ADDRESS	268
	ESWD_MAC_LIMIT_ALERT	268
	ESWD_MAC_LIMIT_BLOCK	268
	ESWD_MAC_LIMIT_DROP	269
	ESWD_MAC_LIMIT_EXCEEDED	269
	ESWD_MAC_MOVE_LIMIT_BLOCK	269
	ESWD_MAC_MOVE_LIMIT_DROP	269
	ESWD_MAC_MOVE_LIMIT_EXCEEDED	270
	ESWD_MIRROR_ERROR	270
	ESWD_MIRROR_VERSION_MISMATCH	270
	ESWD_MODULE_SHUTDOWN_FAILURE	271
	ESWD_PPM_READ_ERROR	271
	ESWD_PPM_WRITE_ERROR	271
	ESWD_STP_BASE_MAC_ERROR	272
	ESWD_STP_LOOP_PROTECT_CLEARED	272
	ESWD_STP_LOOP_PROTECT_IN_EFFECT	272
	ESWD_STP_ROOT_PROTECT_CLEARED	272
	ESWD_STP_ROOT_PROTECT_IN_EFFECT	272
	ESWD_ST_CTL_BW_INFO	273
	ESWD_ST_CTL_ERROR_DISABLED	273
	ESWD_ST_CTL_ERROR_ENABLED	273
	ESWD_ST_CTL_ERROR_IN_EFFECT	273
	ESWD_ST_CTL_INFO	273

	ESWD_SYSTEM_CALL_FAILED	274
Chapter 32	EVENTD System Log Messages	275
	EVENTD_ACK_FAILED	275
	EVENTD_ALARM_CLEAR	275
	EVENTD_ALARM_FILE	275
	EVENTD_COMMAND_SUBSTITUTE_ERROR	276
	EVENTD_ESCRIPT_EXECUTION	276
	EVENTD_ESCRIPT_NOT_CONFIGURED	276
	EVENTD_EVENT_SEND_FAILED	276
	EVENTD_FORK_ERR	277
	EVENTD_PIPE_CREATION_FAILED	277
	EVENTD_POLICY_ACTION_FAILED	277
	EVENTD_POLICY_LIMIT_EXCEEDED	277
	EVENTD_POLICY_UPLOAD_FAILED	278
	EVENTD_POPEN_FAIL	278
	EVENTD_READ_ERROR	278
	EVENTD_REGEX_INVALID	278
	EVENTD_REG_VERSION_MISMATCH	278
	EVENTD_ROTATE_COMMAND_FAILED	279
	EVENTD_ROTATE_FORK_EXCEEDED	279
	EVENTD_ROTATE_FORK_FAILED	279
	EVENTD_SCRIPT_CHECKSUM_MISMATCH	279
	EVENTD_SET_PROCESS_PRIV_FAILED	280
	EVENTD_SET_TIMER_FAILED	280
	EVENTD_SYSLOG_FWD_FAILED	280
	EVENTD_TEST_ALARM	280
	EVENTD_TRANSFER_COMMAND_FAILED	281
	EVENTD_TRANSFER_FORK_EXCEEDED	281
	EVENTD_TRANSFER_FORK_FAILED	281
	EVENTD_VERSION_MISMATCH	281
	EVENTD_XML_FILENAME_INVALID	281
Chapter 33	FC System Log Messages	283
	FC_FABRIC_CREATED	283
	FC_FABRIC_DELETED	283
	FC_FABRIC_WWN_ASSIGNED	283
	FC_FABRIC_WWN_CLEARED	283
	FC_FLOGI_VN_PORT_LOGIN_FAILED	284
	FC_LOGICAL_INTERFACE_CREATED	284
	FC_LOGICAL_INTERFACE_DELETED	284
	FC_LOGICAL_INTERFACE_ISOLATED	284
	FC_PROXY_NP_PORT_LB_ADDED	285
	FC_PROXY_NP_PORT_LB_REMOVED	285
	FC_PROXY_NP_PORT_LOGIN_ABORTED	285
	FC_PROXY_NP_PORT_LOGIN_FAILED	285
	FC_PROXY_NP_PORT_LOGOUT	286
	FC_PROXY_NP_PORT_NPIV_FAILED	286
	FC_PROXY_NP_PORT_OFFLINE	286
	FC_PROXY_NP_PORT_ONLINE	286

	FC_PROXY_VN_PORT_LOGIN_ABORTED	286
	FC_PROXY_VN_PORT_LOGIN_FAILED	287
Chapter 34	FCD System Log Messages	289
	FCD_SYS_CALL_FAILED	289
Chapter 35	FCOE System Log Messages	291
	FCOE_LOGICAL_INTERFACE_CREATED	291
	FCOE_LOGICAL_INTERFACE_DELETED	291
	FCOE_LOGICAL_INTERFACE_ISOLATED	291
Chapter 36	FIP System Log Messages	293
	FIP_ENODE_CLEARED	293
	FIP_ENODE_FKA_TIMER_EXPIRED	293
	FIP_ENODE_LEARNED	293
	FIP_MAX_FCOE_FILTERS_REACHED	293
	FIP_MAX_SESSIONS_REACHED	294
	FIP_PROTOCOL_STARTED	294
	FIP_PROTOCOL_STOPPED	294
	FIP_VN_PORT_FKA_TIMER_EXPIRED	294
	FIP_VN_PORT_LOGIN_FAILED	295
	FIP_VN_PORT_SESSION_CLEARED	295
	FIP_VN_PORT_SESSION_CREATED	295
Chapter 37	FLOW System Log Messages	297
	FLOW_HIGH_WATERMARK_TRIGGERED	297
	FLOW_IP_ACTION	297
	FLOW_LOW_WATERMARK_TRIGGERED	297
Chapter 38	FPCLOGIN System Log Messages	299
	FPCLOGIN_ADDRESS_GET_FAILED	299
	FPCLOGIN_IPC_RECEIVE_FAILED	299
	FPCLOGIN_IPC_SEND_FAILED	299
	FPCLOGIN_LOGIN_FAILED	300
	FPCLOGIN_MESSAGE_INVALID	300
	FPCLOGIN_SOCKET_OPERATION_FAILED	300
Chapter 39	FSAD System Log Messages	301
	FSAD_CONFIG_ERROR	301
	FSAD_CONNTIMEDOUT	301
	FSAD_DIR_CREATE	301
	FSAD_DIR_STAT	302
	FSAD_FAILED	302
	FSAD_FILE_FAILED	302
	FSAD_FILE_REMOVE	302
	FSAD_FILE_RENAME	303
	FSAD_FILE_STAT	303
	FSAD_FILE_SYNC	303
	FSAD_FLOWC_IPC_PAYLOAD_SIZE	304
	FSAD_FLOWC_IPC_SUBTYPE	304
	FSAD_FLOWC_IPC_TYPE	304

	FSAD_FLOWC_IPC_VERSION	304
	FSAD_FLOWC_SERVICE_INACTIVE	305
	FSAD_FREE_SPACE_LOG	305
	FSAD_FREE_SPACE_TMP	305
	FSAD_FS_STAT	305
	FSAD_GEN_IPC_PAYLOAD_SIZE	306
	FSAD_GEN_IPC_SUBTYPE	306
	FSAD_GEN_IPC_TYPE	306
	FSAD_GEN_IPC_VERSION	306
	FSAD_GEN_SERVICE_INACTIVE	307
	FSAD_GEN_SERVICE_INIT_FAILED	307
	FSAD_MAXCONN	307
	FSAD_MEMORYALLOC_FAILED	307
	FSAD_NOT_ROOT	308
	FSAD_PARENT_DIRECTORY	308
	FSAD_PATH_IS_DIRECTORY	308
	FSAD_PATH_IS_NOT_DIRECTORY	308
	FSAD_PATH_IS_SPECIAL	309
	FSAD_RECVERERROR	309
	FSAD_RENAME	309
	FSAD_TERMINATED_CONNECTION	309
	FSAD_TRACEOPEN_FAILED	310
	FSAD_USAGE	310
Chapter 40	FUD System Log Messages	311
	FUD_ARGUMENT_FAILURE	311
	FUD_BAD_SERVER_ADDR_FAILURE	311
	FUD_BIND_FAILURE	311
	FUD_DAEMON_FAILURE	312
	FUD_MEMORY_ALLOCATION_FAILURE	312
	FUD_PERMISSION_FAILURE	312
	FUD_PIDLOCK_FAILURE	312
	FUD_PIDUPDATE_FAILURE	313
	FUD_RECVMSG_FAILURE	313
	FUD_RTsock_WRITE_FAILURE	313
	FUD_SENDMSG_FAILURE	314
	FUD_SENDMSG_NOINT_FAILURE	314
	FUD_SETSOCKOPT_FAILURE	314
	FUD_SOCKET_FAILURE	315
Chapter 41	FWAUTH System Log Messages	317
	FWAUTH_FTP_LONG_PASSWORD	317
	FWAUTH_FTP_LONG_USERNAME	317
	FWAUTH_FTP_USER_AUTH_ACCEPTED	317
	FWAUTH_FTP_USER_AUTH_FAIL	317
	FWAUTH_HTTP_USER_AUTH_ACCEPTED	318
	FWAUTH_HTTP_USER_AUTH_FAIL	318
	FWAUTH_TELNET_LONG_PASSWORD	318
	FWAUTH_TELNET_LONG_USERNAME	318
	FWAUTH_TELNET_USER_AUTH_ACCEPTED	318

	FWAUTH_TELNET_USER_AUTH_FAIL	319
	FWAUTH_WEBAUTH_FAIL	319
	FWAUTH_WEBAUTH_SUCCESS	319
Chapter 42	GPRSD System Log Messages	321
	GPRSD_MEMORY_ALLOC_FAILED	321
	GPRSD_RESTART_CCFG_READ_FAILED	321
Chapter 43	HNCACHED System Log Messages	323
	HNCACHED_HOST_ADDRESS_CHANGED	323
	HNCACHED_NAME_RESOLUTION_FAILURE	323
Chapter 44	ICCPD System Log Messages	325
	ICCPD_ASSERT_SOFT	325
	ICCPD_OPEN_ERROR	325
	ICCPD_READ_ERROR	326
	ICCPD_WRITE_ERROR	326
Chapter 45	IDP System Log Messages	327
	IDP_APPDDOS_APP_ATTACK_EVENT	327
	IDP_APPDDOS_APP_STATE_EVENT	327
	IDP_ATTACK_LOG_EVENT	328
	IDP_COMMIT_COMPLETED	328
	IDP_COMMIT_FAILED	328
	IDP_DAEMON_INIT_FAILED	328
	IDP_IGNORED_IPV6_ADDRESSES	329
	IDP_INTERNAL_ERROR	329
	IDP_POLICY_COMPILATION_FAILED	329
	IDP_POLICY_LOAD_FAILED	329
	IDP_POLICY_LOAD_SUCCEEDED	329
	IDP_POLICY_UNLOAD_FAILED	330
	IDP_POLICY_UNLOAD_SUCCEEDED	330
	IDP_SCHEDULEDUPDATE_START_FAILED	330
	IDP_SCHEDULED_UPDATE_STARTED	330
	IDP_SECURITY_INSTALL_RESULT	331
	IDP_SESSION_LOG_EVENT	331
	IDP_SIGNATURE_LICENSE_EXPIRED	331
Chapter 46	JADE System Log Messages	333
	JADE_ATTRIBUTES_TOO_LONG	333
	JADE_AUTH_FAILURE	333
	JADE_AUTH_SUCCESS	333
	JADE_EXEC_ERROR	333
	JADE_PAM_ERROR	334
	JADE_PAM_NO_LOCAL_USER	334
	JADE_SOCKET_ERROR	334
Chapter 47	JCS System Log Messages	335
	JCS_BBD_LOAD_FAILURE	335
	JCS_BBD_LOCAL_MISMATCH	335
	JCS_BBD_NOT_FOUND	335

	JCS_BBD_NOT_VALID	336
	JCS_BBD_PARSE_ERROR	336
	JCS_BBD_PEER_MISMATCH	336
	JCS_BBD_SYSTEM_CONFLICT	336
	JCS_EXT_LINK_STATE	336
	JCS_INVALID_BANDWIDTH_ERROR	337
	JCS_KERNEL_RSD_LINK_DOWN	337
	JCS_KERNEL_RSD_LINK_ENABLED	337
	JCS_MM_COMMUNICATION_ERROR	337
	JCS_MM_COMMUNICATION_OK	338
	JCS_PEER_BLADE_STATE	338
	JCS_READ_BANDWIDTH_ERROR	338
	JCS_READ_BBD_ERROR	338
	JCS_RSD_LINK_STATE	338
	JCS_SWITCH_BANDWIDTH_CONFIG	339
	JCS_SWITCH_COMMUNICATION_ERROR	339
	JCS_SWITCH_COMMUNICATION_OK	339
Chapter 48	JDIAMETERD System Log Messages	341
	JDIAMETERD_FUNC_HSHAKE_FAIL	341
	JDIAMETERD_FUNC_LOCACCEPT_NFOUND	341
	JDIAMETERD_FUNC_NSCK_LISTEN_FAIL	341
	JDIAMETERD_FUNC_OUT_OF_SYNC	342
	JDIAMETERD_FUNC_PICACCEPT_NFOUND	342
	JDIAMETERD_FUNC_TOO_MANY_BADEZES	342
	JDIAMETERD_FUNC_USCK_LISTEN_FAIL	342
Chapter 49	JIVED System Log Messages	343
	JIVED_ALREADY_RUNNING	343
	JIVED_EVLIB_FUNC_FAILED	343
	JIVED_INITIATE_CONN_FAILED	343
	JIVED_INIT_FAILED	344
	JIVED_NOT_ROOT	344
	JIVED_PIDFILE_LOCK_FAILED	344
	JIVED_PIDFILE_UPDATE_FAILED	344
	JIVED_SNMP_SEND_TRAP_FAILED	345
Chapter 50	JPTSPD System Log Messages	347
	JPTSPD_INIT_FAILURE	347
	JPTSPD_OUT_OF_MEMORY	347
	JPTSPD_PIC_CONNECTED	348
	JPTSPD_PIC_DISCONNECTED	348
	JPTSPD_SRC_FAST_SYNC_ABORT	348
	JPTSPD_SRC_FAST_SYNC_DONE	348
	JPTSPD_SRC_FAST_SYNC_START	348
	JPTSPD_SRC_FULL_SYNC_ABORT	349
	JPTSPD_SRC_FULL_SYNC_DONE	349
	JPTSPD_SRC_FULL_SYNC_START	349

Chapter 51	JSRPD System Log Messages	351
	JSRPD_DAEMONIZE_FAILED	351
	JSRPD_DUPLICATE	351
	JSRPD_NODE_STATE_CHANGE	351
	JSRPD_NOT_ROOT	352
	JSRPD_PID_FILE_LOCK	352
	JSRPD_PID_FILE_UPDATE	352
	JSRPD_REDUNDANCY_MODE_CHANGE	352
	JSRPD_REDUNDANCY_MODE_MISMATCH	353
	JSRPD_RG_STATE_CHANGE	353
	JSRPD_SET_CS_MON_FAILURE	353
	JSRPD_SET_INTF_MON_FAILURE	353
	JSRPD_SET_IP_MON_FAILURE	354
	JSRPD_SET_NPC_MON_FAILURE	354
	JSRPD_SET_OTHER_INTF_MON_FAIL	354
	JSRPD_SET_SPU_MON_FAILURE	354
	JSRPD_SOCKET_CREATION_FAILURE	354
	JSRPD_SOCKET_LISTEN_FAILURE	355
	JSRPD_SOCKET_RECV_HB_FAILURE	355
	JSRPD_UNSET_CS_MON_FAILURE	355
	JSRPD_UNSET_INTF_MON_FAILURE	355
	JSRPD_UNSET_IP_MON_FAILURE	356
	JSRPD_UNSET_NPC_MON_FAILURE	356
	JSRPD_UNSET_OTHER_INTF_MON_FAIL	356
	JSRPD_UNSET_SPU_MON_FAILURE	356
	JSRPD_USAGE	356
Chapter 52	KMD System Log Messages	359
	KMD_CFG_IF_ID_POOL_NOT_FOUND	359
	KMD_CFG_IF_ID_POOL_NO_ENTRY	359
	KMD_CFG_IF_ID_POOL_NO_INTERFACE	359
	KMD_CFG_IF_ID_POOL_RETURN_FAILED	360
	KMD_DPD_FAILOVER_MANUAL_TUNNEL	360
	KMD_DPD_FAILOVER_MAX_ATTEMPTS	360
	KMD_DPD_FAILOVER_NO_ACTIVE_PEER	360
	KMD_DPD_FAILOVER_NO_BACKUP_PEER	361
	KMD_DPD_FAILOVER_NO_TUNNEL_CFG	361
	KMD_DPD_IKE_SERVER_NOT_FOUND	361
	KMD_DPD_INVALID_ADDRESS	361
	KMD_DPD_INVALID_SEQUENCE_NUMBER	362
	KMD_DPD_NO_LOCAL_ADDRESS	362
	KMD_DPD_REMOTE_ADDRESS_CHANGED	362
	KMD_DPD_REMOTE_PEER_NOT_FOUND	362
	KMD_DPD_UNEXPECTED_IKE_STATUS	363
	KMD_PM_AUTH_ALGORITHM_INVALID	363
	KMD_PM_DUPLICATE_LIFE_DURATION	363
	KMD_PM_DYNAMIC_SA_INSTALL_FAILED	364
	KMD_PM_ENCRYPTION_INVALID	364
	KMD_PM_IKE_SERVER_LOOKUP_FAILED	364

KMD_PM_IKE_SERVER_NOT_FOUND	364
KMD_PM_IKE_SRV_NOT_FOUND_CREATE	365
KMD_PM_IKE_SRV_NOT_FOUND_DELETE	365
KMD_PM_ILLEGAL_REMOTE_GW_ID	365
KMD_PM_INCONSISTENT_P2_IDS	365
KMD_PM_INVALID_LIFE_TYPE	366
KMD_PM_KEY_NOT_SUPPORTED	366
KMD_PM_LIFETIME_DUPLICATE	366
KMD_PM_LIFETIME_LENGTH_UNEQUAL	366
KMD_PM_LIFETIME_NO_DURATION	367
KMD_PM_LIFETIME_TYPE_UNDEFINED	367
KMD_PM_LIFETIME_UNITS_INVALID	367
KMD_PM_NEW_GROUP_UNSUPPORTED	368
KMD_PM_NO_LIFETIME	368
KMD_PM_NO_LIFE_TYPE	368
KMD_PM_NO_PROPOSAL_FOR_PHASE1	368
KMD_PM_NO_SPD_PHASE1_FUNC_PTR	369
KMD_PM_P1_POLICY_LOOKUP_FAILURE	369
KMD_PM_P2_POLICY_LOOKUP_FAILURE	369
KMD_PM_PHASE1_GROUP_UNREADABLE	369
KMD_PM_PHASE1_GROUP_UNSPECIFIED	370
KMD_PM_PHASE1_IKE_SRV_NOT_FOUND	370
KMD_PM_PHASE1_NO_IDENTITY	370
KMD_PM_PHASE1_NO_SPD_HANDLER	370
KMD_PM_PHASE1_POLICY_LOOKUP_FAIL	371
KMD_PM_PHASE1_POLICY_NOT_FOUND	371
KMD_PM_PHASE1_POLICY_SEARCH_FAIL	371
KMD_PM_PHASE1_PROTO_INVALID	371
KMD_PM_PHASE1_PROTO_NOT_ISAKMP	372
KMD_PM_PHASE1_PROTO_TWICE	372
KMD_PM_PHASE1_TXFORM_INCOMPLETE	372
KMD_PM_PHASE1_TXFORM_INVALID	372
KMD_PM_PHASE2_IDENTITY_MISMATCH	373
KMD_PM_PHASE2_NOTIF_UNKNOWN	373
KMD_PM_PHASE2_POLICY_LOOKUP_FAIL	373
KMD_PM_PHASE2_SELECTOR_UNDEFINED	373
KMD_PM_PROPOSAL_NO_AUTH	374
KMD_PM_PROPOSAL_NO_ENCRYPTION	374
KMD_PM_PROPOSAL_NO_KEY_LENGTH	374
KMD_PM_PROPOSAL_NULL_ESP	374
KMD_PM_PROPOSAL_PROTOCOL_INVALID	375
KMD_PM_PROTO_INVALID	375
KMD_PM_PROTO_IPCOMP_UNSUPPORTED	375
KMD_PM_PROTO_ISAKMP_RESV_UNSUPP	375
KMD_PM_PROTO_NOT_NEGOTIATED	376
KMD_PM_REMOTE_PEER_INVALID	376
KMD_PM_SA_CFG_NOT_FOUND	376
KMD_PM_SA_DELETE_REJECT	376
KMD_PM_SA_INDEX_GEN_FAILED	377

	KMD_PM_SA_PEER_ABSENT	377
	KMD_PM_SA_PEER_NOT_FOUND	377
	KMD_PM_SPI_DELETE_REJECT	377
	KMD_PM_UNEQUAL_PAYLOAD_LENGTH	378
	KMD_PM_UNINITIALISE_ERROR	378
	KMD_PM_UNINITIALIZE_FAILED	378
	KMD_PM_UNKNOWN_PI_IDENTITIES	378
	KMD_PM_UNKNOWN_PHASE2_ENTITIES	379
	KMD_PM_UNKNOWN_QM_NOTIFICATION	379
	KMD_PM_UNSUPPORTED_KEY	379
	KMD_PM_UNSUPPORTED_MODE	379
	KMD_SNMP_EXTRA_RESPONSE	380
	KMD_SNMP_FATAL_ERROR	380
	KMD_SNMP_IKE_SERVER_NOT_FOUND	380
	KMD_SNMP_MALLOC_FAILED	380
	KMD_SNMP_PIC_CONNECTION_FAILED	381
	KMD_SNMP_PIC_NO_RESPONSE	381
	KMD_SNMP_PIC_SLOT_NOT_FOUND	381
	KMD_VPN_DFBIT_STATUS_MSG	381
	KMD_VPN_DOWN_ALARM_USER	382
	KMD_VPN_UP_ALARM_USER	382
Chapter 53	L2ALD System Log Messages	383
	L2ALD_BD_NAME_RESTRICTION	383
	L2ALD_DUPLICATE_RBEB_MAC	383
	L2ALD_GENCFG_OP_FAILED	383
	L2ALD_IPC_MESSAGE_ERROR	384
	L2ALD_IPC_MESSAGE_INVALID	384
	L2ALD_IPC_MESSAGE_SEND_FAILED	384
	L2ALD_IPC_PIPE_WRITE_ERROR	385
	L2ALD_MAC_LIMIT_REACHED_BD	385
	L2ALD_MAC_LIMIT_REACHED_GLOBAL	385
	L2ALD_MAC_LIMIT_REACHED_IF	386
	L2ALD_MAC_LIMIT_REACHED_IFBD	386
	L2ALD_MAC_LIMIT_REACHED_RTT	386
	L2ALD_MAC_LIMIT_RESET_BD	387
	L2ALD_MAC_LIMIT_RESET_GLOBAL	387
	L2ALD_MAC_LIMIT_RESET_IF	387
	L2ALD_MAC_LIMIT_RESET_RTT	388
	L2ALD_MAC_MOVE_NOTIFICATION	388
	L2ALD_MALLOC_FAILED	388
	L2ALD_MANAGER_CONNECT	389
	L2ALD_NAME_LENGTH_IF_DEVICE	389
	L2ALD_NAME_LENGTH_IF_FAMILY	389
	L2ALD_NAME_LENGTH_IF_LOGICAL	389
	L2ALD_PBBN_IFL_REVA	390
	L2ALD_PBBN_REINSTATE_IFBDS	390
	L2ALD_PBBN_RETRACT_IFBDS	390
	L2ALD_PIP_IFD_READ_RETRY	391

Chapter 54	L2CPD System Log Messages	393
	L2CPD_ASSERT	393
	L2CPD_ASSERT_SOFT	393
	L2CPD_EXIT	394
	L2CPD_KERNEL_VERSION	394
	L2CPD_KERNEL_VERSION_OLD	394
	L2CPD_KERNEL_VERSION_UNSUPP	395
	L2CPD_MEMORY_EXCESSIVE	395
	L2CPD_MGMT_TIMEOUT	395
	L2CPD_MIRROR_ERROR	396
	L2CPD_MIRROR_VERSION_MISMATCH	396
	L2CPD_PPM_READ_ERROR	396
	L2CPD_PPM_WRITE_ERROR	396
	L2CPD_RUNTIME_MODULE	397
	L2CPD_RUNTIME_OPERATION	397
	L2CPD_RUNTIME_TASK	397
	L2CPD_RUNTIME_TOTAL	398
	L2CPD_TASK_BEGIN	398
	L2CPD_TASK_CHILD_KILLED	398
	L2CPD_TASK_CHILD_STOPPED	398
	L2CPD_TASK_FORK	399
	L2CPD_TASK_GETWD	399
	L2CPD_TASK_MASTERSHIP	399
	L2CPD_TASK_NO_REINIT	399
	L2CPD_TASK_PID_CLOSE	400
	L2CPD_TASK_PID_LOCK	400
	L2CPD_TASK_PID_WRITE	400
	L2CPD_TASK_REINIT	400
	L2CPD_TASK_SIGNAL_IGNORE	401
	L2CPD_TERMINATE_ACTIVE	401
	L2CPD_TERMINATE_SIGNAL	401
	L2CPD_TRACE_FAILED	401
	L2CPD_XSTP_SHUTDOWN_FAILED	401
Chapter 55	L2TPD System Log Messages	403
	L2TPD_COS_PROFILE_ADD	403
	L2TPD_COS_PROFILE_DELETE	403
	L2TPD_DB_ADD_FAILED	404
	L2TPD_DB_DELETE_FAILED	404
	L2TPD_DB_INIT_FAILED	404
	L2TPD_DB_TUN_GRP_ALLOC_FAILED	404
	L2TPD_DEFAULT_PROTO_CREATE_FAIL	405
	L2TPD_EVLIB_CREATE_FAILED	405
	L2TPD_EVLIB_FD_DEREGISTER_FAILED	405
	L2TPD_EVLIB_FD_DESELECT_FAILED	405
	L2TPD_EVLIB_FD_NOT_REGISTERED	405
	L2TPD_EVLIB_FD_SELECT_FAILED	406
	L2TPD_EVLIB_TIMER_CLEAR_FAILED	406
	L2TPD_EVLIB_TIMER_SET_FAILED	406

L2TPD_FILTER_FILE_OPEN_FAILED	406
L2TPD_GLOBAL_CFG_ADD_FAILED	407
L2TPD_GLOBAL_CFG_CHANGE_FAILED	407
L2TPD_GLOBAL_CFG_DELETE_FAILED	407
L2TPD_IFD_ADD_FAILED	407
L2TPD_IFD_DELETE_FAILED	407
L2TPD_IFD_MSG_REGISTER_FAILED	408
L2TPD_IFD_ROOT_ALLOC_FAILED	408
L2TPD_IFL_ADD_FAILED	408
L2TPD_IFL_DELETE_FAILED	408
L2TPD_IFL_MSG_REGISTER_FAILED	409
L2TPD_IFL_NOT_FOUND	409
L2TPD_IFL_ROOT_ALLOC_FAILED	409
L2TPD_INSTANCE_CREATE_FAILED	409
L2TPD_INSTANCE_RESTART_FAILED	410
L2TPD_INTERFACE_ID_NOT_FOUND	410
L2TPD_MESSAGE_REGISTER_FAILED	410
L2TPD_MLPPP_BUNDLE_ALLOC_FAILED	410
L2TPD_MLPPP_BUNDLE_CREATE_FAILED	411
L2TPD_MLPPP_BUNDLE_INVALID_ID	411
L2TPD_MLPPP_COPY_CFG_FAILED	411
L2TPD_MLPPP_ID_ALLOC_FAILED	411
L2TPD_MLPPP_ID_BITMAP_ALLOC_FAIL	411
L2TPD_MLPPP_ID_NODE_ADD_FAILED	412
L2TPD_MLPPP_ID_ROOT_ALLOC_FAILED	412
L2TPD_MLPPP_LINK_CREATE_FAILED	412
L2TPD_MLPPP_LINK_MAX_EXCEEDED	412
L2TPD_MLPPP_POOL_ADDRESS_FAILED	413
L2TPD_MLPPP_SESSION_CREATE_FAIL	413
L2TPD_MLPPP_SESSION_DELETE_FAIL	413
L2TPD_MLPPP_SPEED_MISMATCH	413
L2TPD_NH_DELETE_FAILED	414
L2TPD_POLICER_ADD_FAILED	414
L2TPD_POLICER_PROFILE_DEL_FAILED	414
L2TPD_POOL_ADDRESS_FAILED	414
L2TPD_POOL_ASSIGN_ADDRESS_FAILED	415
L2TPD_PPP_ROUTE_ADD_FAILED	415
L2TPD_PPP_ROUTE_DELETE_FAILED	415
L2TPD_PROFILE_NOT_FOUND	415
L2TPD_PROFILE_NO_RADIUS_SERVERS	416
L2TPD_RADIUS_ACCT_PORT_ZERO	416
L2TPD_RADIUS_GETHOSTNAME_FAILED	416
L2TPD_RADIUS_RT_INST_ENOENT	416
L2TPD_RADIUS_RT_INST_NOT_FOUND	416
L2TPD_RADIUS_SERVER_NOT_FOUND	417
L2TPD_RADIUS_SRC_ADDR_BIND_FAIL	417
L2TPD_RADIUS_SRC_ADDR_ENOENT	417
L2TPD_RPD_ASYNC_UNREG_FAILED	417
L2TPD_RPD_ROUTE_ADD_CB_FAILED	418

L2TPD_RPD_ROUTE_ADD_FAILED	418
L2TPD_RPD_ROUTE_DELETE_CB_FAILED	418
L2TPD_RPD_ROUTE_DELETE_FAILED	418
L2TPD_RPD_ROUTE_PREFIX_TOO_LONG	419
L2TPD_RPD_SESS_CREATE_FAILED	419
L2TPD_RPD_SESS_HANDLE_ALLOC_FAIL	419
L2TPD_RPD_SOCKET_ALLOC_FAILED	419
L2TPD_RPD_TBL_LOCATE_BY_NAME	419
L2TPD_RPD_TBL_LOCATE_FAILED	420
L2TPD_RPD_VERSION_MISMATCH	420
L2TPD_RTSLIB_ASYNC_OPEN_FAILED	420
L2TPD_RTSLIB_OPEN_FAILED	420
L2TPD_SERVER_START_FAILED	421
L2TPD_SERVICE_NH_ADD_FAILED	421
L2TPD_SERVICE_NH_DELETE_FAILED	421
L2TPD_SESSION_CFG_ADD_ERROR	421
L2TPD_SESSION_CFG_ADD_FAILED	422
L2TPD_SESSION_CFG_DELETE_FAILED	422
L2TPD_SESSION_DELETE_FAILED	422
L2TPD_SESSION_IFF_NOT_FOUND	422
L2TPD_SESSION_IFL_ADD_FAILED	423
L2TPD_SESSION_IFL_ALLOC_FAILED	423
L2TPD_SESSION_IFL_CLI_TREE_ALLOC	423
L2TPD_SESSION_IFL_DELETED	423
L2TPD_SESSION_IFL_DELETE_FAILED	423
L2TPD_SESSION_IFL_GET_FAILED	424
L2TPD_SESSION_IFL_NOT_EQUAL	424
L2TPD_SESSION_IFL_NOT_FOUND	424
L2TPD_SESSION_IFL_OCCUPIED	424
L2TPD_SESSION_IFL_REMOVE_FAILED	425
L2TPD_SESSION_INVALID_PEER_IP	425
L2TPD_SESSION_ROUTE_ADD_FAILED	425
L2TPD_SESSION_RT_TBL_NOT_FOUND	425
L2TPD_SESSION_TUNNEL_ID_MISMATCH	426
L2TPD_SETSOCKOPT_FAILED	426
L2TPD_SET_ASYNC_CONTEXT	426
L2TPD_SHOW_MULTILINK	426
L2TPD_SHOW_SESSION	427
L2TPD_SHOW_TUNNEL	427
L2TPD_SOCKET_FAILED	427
L2TPD_SUBUNIT_ROUTE_ALLOC_FAILED	427
L2TPD_TRACE_FILE_OPEN_FAILED	427
L2TPD_TUNNEL_CFG_ADD_FAILED	428
L2TPD_TUNNEL_CFG_ADD_INV_ADDR	428
L2TPD_TUNNEL_CFG_DELETE_FAILED	428
L2TPD_TUNNEL_DELETE_FAILED	428
L2TPD_TUNNEL_DEST_IF_LOOKUP_FAIL	429
L2TPD_TUNNEL_GROUP_ADD_FAILED	429
L2TPD_TUNNEL_GROUP_CFG_ADD_FAIL	429

	L2TPD_TUNNEL_GROUP_CFG_DEL_FAIL	429
	L2TPD_TUNNEL_GROUP_CREATE_FAILED	430
	L2TPD_TUNNEL_GROUP_DELETE_FAILED	430
	L2TPD_TUNNEL_GROUP_IDX_MISMATCH	430
	L2TPD_TUNNEL_GROUP_RESTART_FAIL	430
	L2TPD_USER_AUTHN_NOT_FOUND	430
	L2TPD_USER_AUTHN_ORDER_UNKNOWN	431
	L2TPD_USER_AUTHN_PWD_NOT_FOUND	431
Chapter 56	LACPD System Log Messages	433
	LACPD_MEMORY_ALLOCATION_FAILED	433
Chapter 57	LFMD System Log Messages	435
	LFMD_RTsock_OPEN_FAILED	435
Chapter 58	LIBESPTASK System Log Messages	437
	LIBESPTASK_SNMP_CONN_PROG	437
	LIBESPTASK_SNMP_CONN_QUIT	437
	LIBESPTASK_SNMP_CONN_RETRY	437
	LIBESPTASK_SNMP_INVALID_SOCKET	437
	LIBESPTASK_SNMP_SOCKOPT_BLOCK	438
	LIBESPTASK_SNMP_SOCKOPT_RECVBUF	438
	LIBESPTASK_SNMP_SOCKOPT_SENDBUF	438
Chapter 59	LIBJNX System Log Messages	439
	LIBJNX_AUDIT_ERROR	439
	LIBJNX_COMPRESS_EXEC_FAILED	439
	LIBJNX_DEFAULT_IP_ADDR_NOT_SET	440
	LIBJNX_EVLIB_FAILURE	440
	LIBJNX_EXEC_EXITED	440
	LIBJNX_EXEC_FAILED	440
	LIBJNX_EXEC_PIPE	441
	LIBJNX_EXEC_SIGNED	441
	LIBJNX_EXEC_WEXIT	441
	LIBJNX_FILE_COPY_FAILED	442
	LIBJNX_FILE_SYSTEM_FAIL	442
	LIBJNX_FILE_SYSTEM_SPACE	442
	LIBJNX_INVALID_CHASSIS_ID	442
	LIBJNX_INVALID_RE_SLOT_ID	443
	LIBJNX_INVALID_XML_DATA	443
	LIBJNX_PRIV_LOWER_FAILED	443
	LIBJNX_PRIV_RAISE_FAILED	443
	LIBJNX_REPLICATE_RCP_ERROR	444
	LIBJNX_REPLICATE_RCP_EXEC_FAILED	444
	LIBJNX_SNMP_ENGINE_FILE_FAILURE	444
	LIBJNX_SNMP_ENGINE_SCAN_FAILURE	445
	LIBJNX_SOCKET_FAILURE	445
	LIBJNX_XML_DECODE_FAILED	445

Chapter 60	LIBJSNMP System Log Messages	447
	LIBJSNMP_CTX_FAILURE	447
	LIBJSNMP_IPC_ERROR	447
	LIBJSNMP_IPC_READ_ERROR	447
	LIBJSNMP_MTHD_API_UNKNOWN_TYPE	448
	LIBJSNMP_NS_LOG_CRIT	448
	LIBJSNMP_NS_LOG_EMERG	448
	LIBJSNMP_NS_LOG_ERR	449
	LIBJSNMP_OID_GEN_FAILED	449
	LIBJSNMP_READ_LEN_ERR	449
	LIBJSNMP_RTMSIZE_MISMATCH_ERR	449
	LIBJSNMP_SMS_HDR_ERR	450
	LIBJSNMP_SMS_MSG_ERR	450
	LIBJSNMP_SOCKET_OPEN_ERR	450
	LIBJSNMP_SOCKET_VER_MISMATCH	451
	LIBJSNMP_TRAP_API_FAILURE	451
	LIBJSNMP_TRAP_UTILS_ERR	451
Chapter 61	LIBMSRPC System Log Messages	453
	LIBMSRPC_CLIENT_INIT_FAILED	453
	LIBMSRPC_CLIENT_KCOM_FAILED	453
	LIBMSRPC_CLIENT_KCOM_NO_IF	453
	LIBMSRPC_CLIENT_NO_CONNECTION	454
	LIBMSRPC_CLIENT_NO_REPLY	454
	LIBMSRPC_CLIENT_PIC_DOWN	454
	LIBMSRPC_CLIENT_WRONG_OUTPUT	455
Chapter 62	LICENSE System Log Messages	457
	LICENSE_CONNECT_FAILURE	457
	LICENSE_CONN_TO_LI_CHECK_FAILURE	457
	LICENSE_CONN_TO_LI_CHECK_SUCCESS	457
	LICENSE_EXPIRED	458
	LICENSE_EXPIRED_KEY_DELETED	458
	LICENSE_GRACE_PERIOD_APPROACHING	458
	LICENSE_GRACE_PERIOD_EXCEEDED	458
	LICENSE_GRACE_PERIOD_EXPIRED	458
	LICENSE_LIST_MANAGEMENT	459
	LICENSE_NEARING_EXPIRY	459
	LICENSE_READ_ERROR	459
	LICENSE_REG_ERROR	459
	LICENSE_SIGNATURE_VERIFY_FAILED	460
	LICENSE_UNKNOWN_RESPONSE_TYPE	460
	LICENSE_VERIFICATION_FILE_ERROR	460
Chapter 63	LLDPD System Log Messages	461
	LLDPD_SYSTEM	461
Chapter 64	LOGIN System Log Messages	463
	LOGIN_ABORTED	463
	LOGIN_FAILED	463

	LOGIN_FAILED_LIMIT	463
	LOGIN_FAILED_SET_CONTEXT	463
	LOGIN_FAILED_SET_LOGIN	464
	LOGIN_HOSTNAME_UNRESOLVED	464
	LOGIN_INFORMATION	464
	LOGIN_MALFORMED_USER	464
	LOGIN_PAM_AUTHENTICATION_ERROR	465
	LOGIN_PAM_ERROR	465
	LOGIN_PAM_MAX_RETRIES	465
	LOGIN_PAM_STOP	465
	LOGIN_PAM_USER_UNKNOWN	465
	LOGIN_PASSWORD_EXPIRED	466
	LOGIN_REFUSED	466
	LOGIN_ROOT	466
	LOGIN_TIMED_OUT	466
Chapter 65	LPDFD System Log Messages	467
	LPDFD_DYN_PDB_OPEN_FAILED	467
	LPDFD_DYN_REGISTER_FAILED	467
	LPDFD_PCONN_SERVER	467
Chapter 66	LRMUX System Log Messages	469
	LRMUX_FAILED_EXEC	469
	LRMUX_LRPD_PID_LOCK	469
	LRMUX_LRPD_PID_OPEN	469
	LRMUX_LRPD_SEND_HUP	470
	LRMUX_PID_LOCK	470
Chapter 67	MCSN System Log Messages	471
	MCSN_ABORT	471
	MCSN_ACTIVE_TERMINATE	471
	MCSN_ASSERT	471
	MCSN_ASSERT_SOFT	472
	MCSN_EXIT	472
	MCSN_SCHED_CALLBACK_LONGRUNTIME	473
	MCSN_SCHED_CUMULATVE_LNGRUNTIME	473
	MCSN_SIGNAL_TERMINATE	473
	MCSN_START	473
	MCSN_SYSTEM	474
	MCSN_TASK_BEGIN	474
	MCSN_TASK_CHILDKILLED	474
	MCSN_TASK_CHILDSTOPPED	474
	MCSN_TASK_FORK	475
	MCSN_TASK_GETWD	475
	MCSN_TASK_MASTERSHIP	475
	MCSN_TASK_NOREINIT	475
	MCSN_TASK_REINIT	475
	MCSN_TASK_SIGNALIGNORE	476

Chapter 68	MCSNOOPD System Log Messages	477
	MCSNOOPD_MGMT_TIMEOUT	477
Chapter 69	MIB2D System Log Messages	479
	MIB2D_ATM_ERROR	479
	MIB2D_CONFIG_CHECK_FAILED	479
	MIB2D_FILE_OPEN_FAILURE	479
	MIB2D_IFD_IFDINDEX_FAILURE	480
	MIB2D_IFD_IFINDEX_FAILURE	480
	MIB2D_IFL_IFINDEX_FAILURE	480
	MIB2D_IF_FLAPPING_MISSING	481
	MIB2D_KVM_FAILURE	481
	MIB2D_PMON_OVERLOAD_CLEARED_TRAP	481
	MIB2D_PMON_OVERLOAD_SET_TRAP	481
	MIB2D_RTSLIB_READ_FAILURE	482
	MIB2D_RTSLIB_SEQ_MISMATCH	482
	MIB2D_SNMP_INDEX_ASSIGN	482
	MIB2D_SNMP_INDEX_DUPLICATE	483
	MIB2D_SNMP_INDEX_UPDATE_STAT	483
	MIB2D_SNMP_INDEX_WRITE	483
	MIB2D_SYSCTL_FAILURE	483
	MIB2D_TRAP_HEADER_FAILURE	484
	MIB2D_TRAP_SEND_FAILURE	484
Chapter 70	MPLS_OAM System Log Messages	485
	MPLS_OAM_FANOUT_LIMIT_REACHED	485
	MPLS_OAM_INVALID_SOURCE_ADDRESS	485
	MPLS_OAM_PATH_LIMIT_REACHED	485
	MPLS_OAM_SEND_FAILED	486
	MPLS_OAM_SOCKET_OPEN_FAILED	486
	MPLS_OAM_SOCKET_SELECT_FAILED	486
	MPLS_OAM_TRACEROUTE_INTERRUPTED	486
	MPLS_OAM_TTL_EXPIRED	487
	MPLS_OAM_UNREACHABLE	487
Chapter 71	NEXTHOP System Log Messages	489
	NEXTHOP_COMPONENTS_LIMIT_REACHED	489
Chapter 72	NSD System Log Messages	491
	NSD_MEMORY_ALLOC_FAILED	491
	NSD_RESTART_COMP_CFG_READ_FAILED	491
	NSD_SEC_NODE_COMP_SYNC_FAILED	491
Chapter 73	NSTRACED System Log Messages	493
	NSTRACED_MEMORY_ALLOC_FAILED	493
	NSTRACED_RESTART_CFG_READ_FAILED	493
Chapter 74	PFE System Log Messages	495
	PFE_ANALYZER_CFG_FAILED	495
	PFE_ANALYZER_SHIM_CFG_FAILED	495
	PFE_ANALYZER_TABLE_WRITE_FAILED	495

	PFE_ANALYZER_TASK_FAILED	495
	PFE_CBF_UNSUPPORTED	496
	PFE_COS_B2_ONE_CLASS	496
	PFE_COS_B2_UNSUPPORTED	496
	PFE_FW_DELETE_MISMATCH_ERR	496
	PFE_FW_IF_DIALER_ERR	497
	PFE_FW_IF_INPUT_ERR	497
	PFE_FW_IF_OUTPUT_ERR	497
	PFE_FW_PSF_DELETE_MISMATCH_ERR	497
	PFE_FW_SYSLOG_ETH	498
	PFE_FW_SYSLOG_IP	498
	PFE_FW_SYSLOG_IP6_GEN	498
	PFE_FW_SYSLOG_IP6_ICMP	498
	PFE_FW_SYSLOG_IP6_TCP_UDP	499
	PFE_MGCP_MEM_INIT_FAILED	499
	PFE_MGCP_REG_HDL_FAIL	499
	PFE_NH_RESOLVE_THROTTLED	499
	PFE_SCCP_ADD_PORT_FAIL	500
	PFE_SCCP_DEL_PORT_FAIL	500
	PFE_SCCP_REG_NAT_VEC_FAIL	500
	PFE_SCCP_REG_RM_FAIL	500
	PFE_SCCP_REG_VSIP_FAIL	501
	PFE_SCCP_RM_CLIENTID_FAIL	501
	PFE_SCREEN_MT_CFG_ERROR	501
	PFE_SCREEN_MT_CFG_EVENT	501
	PFE_SCREEN_MT_ZONE_BINDING_ERROR	501
	PFE_SIP_ADD_PORT_FAIL	502
	PFE_SIP_DEL_PORT_FAIL	502
	PFE_SIP_MEM_INIT_FAILED	502
	PFE_SIP_REG_HDL_FAIL	502
Chapter 75	PFED System Log Messages	503
	PFED_NOTIFICATION_STATS_FAILED	503
Chapter 76	PGCPD System Log Messages	505
	PGCPD_SHUTDOWN	505
	PGCPD_STARTUP	505
	PGCPD_SWITCH_OVER	505
Chapter 77	PING System Log Messages	507
	PING_EGRESS_JITTER_THRESH_EXCEED	507
	PING_EGRESS_STDDEV_THRESH_EXCEED	507
	PING_EGRESS_THRESHOLD_EXCEEDED	507
	PING_INGRESS_JTR_THRESH_EXCEED	508
	PING_INGRESS_STDDV_THRESH_EXCEED	508
	PING_INGRESS_THRESHOLD_EXCEEDED	508
	PING_PROBE_FAILED	508
	PING_RTT_JTR_THRESH_EXCEED	508
	PING_RTT_STDDV_THRESH_EXCEED	509
	PING_RTT_THRESHOLD_EXCEEDED	509

	PING_TEST_COMPLETED	509
	PING_TEST_FAILED	509
	PING_UNKNOWN_THRESH_TYPE_EXCEED	510
Chapter 78	PPMD System Log Messages	511
	PPMD_ASSERT_SOFT	511
	PPMD_OPEN_ERROR	511
	PPMD_READ_ERROR	512
	PPMD_WRITE_ERROR	512
Chapter 79	PPPD System Log Messages	513
	PPPD_AUTH_CREATE_FAILED	513
	PPPD_CHAP_AUTH_IN_PROGRESS	513
	PPPD_CHAP_GETHOSTNAME_FAILED	513
	PPPD_CHAP_INVALID_IDENTIFIER	514
	PPPD_CHAP_INVALID_OPCODE	514
	PPPD_CHAP_LOCAL_NAME_UNAVAILABLE	514
	PPPD_CHAP_OPERATION_UNEXPECTED	514
	PPPD_CHAP_REPLAY_ATTACK_DETECTED	515
	PPPD_EVLIB_CREATE_FAILURE	515
	PPPD_LOCAL_CREATE_FAILED	515
	PPPD_MEMORY_ALLOCATION_FAILURE	515
	PPPD_PAP_GETHOSTNAME_FAILED	516
	PPPD_PAP_INVALID_IDENTIFIER	516
	PPPD_PAP_INVALID_OPCODE	516
	PPPD_PAP_LOCAL_PASSWORD_UNAVAIL	516
	PPPD_PAP_OPERATION_UNEXPECTED	517
	PPPD_POOL_ADDRESSES_EXHAUSTED	517
	PPPD_RADIUS_ADD_SERVER_FAILED	517
	PPPD_RADIUS_ALLOC_PASSWD_FAILED	517
	PPPD_RADIUS_CREATE_FAILED	518
	PPPD_RADIUS_CREATE_REQ_FAILED	518
	PPPD_RADIUS_GETHOSTNAME_FAILED	518
	PPPD_RADIUS_MESSAGE_UNEXPECTED	518
	PPPD_RADIUS_NO_VALID_SERVERS	519
	PPPD_RADIUS_OPEN_FAILED	519
	PPPD_RADIUS_ROUTE_INST_ENOENT	519
Chapter 80	PROFILER System Log Messages	521
	PROFILER_RECONFIGURE_SIGHUP	521
Chapter 81	RDD System Log Messages	523
	RDD_EVLIB_CREATE_FAILURE	523
	RDD_IFDEV_ADD_FAILURE	523
	RDD_IFDEV_DELETE_FAILURE	523
	RDD_IFDEV_GET_FAILURE	524
	RDD_IFDEV_INCOMPATIBLE_REVERT	524
	RDD_IFDEV_INCOMPATIBLE_SWITCH	524
	RDD_IFDEV_RETRY_NOTICE	525
	RDD_NEW_INTERFACE_STATE	525

Chapter 82	RMOPD System Log Messages	527
	RMOPD_ADDRESS_MULTICAST_INVALID	527
	RMOPD_ADDRESS_SOURCE_INVALID	527
	RMOPD_ADDRESS_STRING_FAILURE	527
	RMOPD_ADDRESS_TARGET_INVALID	528
	RMOPD_ICMP_ADDR_TYPE_UNSUPPORTED	528
	RMOPD_IFINDEX_NOT_ACTIVE	528
	RMOPD_IFINDEX_NO_INFO	528
	RMOPD_IFNAME_NOT_ACTIVE	529
	RMOPD_IFNAME_NO_INFO	529
	RMOPD_ROUTING_INSTANCE_NO_INFO	529
	RMOPD_TRACEROUTE_ERROR	529
Chapter 83	RPD System Log Messages	531
	RPD_ABORT	531
	RPD_ACTIVE_TERMINATE	531
	RPD_AMT_CFG_ADDR_FMLY_INVALID	532
	RPD_AMT_CFG_ANYCAST_INVALID	532
	RPD_AMT_CFG_LOC_ADDR_INVALID	532
	RPD_AMT_CFG_PREFIX_LEN_SHORT	532
	RPD_AMT_CFG_RELAY_INVALID	533
	RPD_AMT_RELAY_DISCOVERY	533
	RPD_AMT_TUNNEL_CREATE	533
	RPD_AMT_TUNNEL_DELETE	533
	RPD_ASSERT	534
	RPD_ASSERT_SOFT	534
	RPD_BFD_READ_ERROR	534
	RPD_BFD_WRITE_ERROR	535
	RPD_BGP_CFG_ADDR_INVALID	535
	RPD_BGP_CFG_LOCAL_ASNUM_WARN	535
	RPD_BGP_NEIGHBOR_STATE_CHANGED	535
	RPD_CFG_TRACE_FILE_MISSING	536
	RPD_DYN_CFG_BUSY_SIGNAL_FAILED	536
	RPD_DYN_CFG_GET_PROFILE_FAILED	536
	RPD_DYN_CFG_GET_PROF_NAME_FAILED	536
	RPD_DYN_CFG_GET_SES_STATE_FAILED	537
	RPD_DYN_CFG_GET_SES_TYPE_FAILED	537
	RPD_DYN_CFG_GET_SNAPSHOT_FAILED	537
	RPD_DYN_CFG_PDB_CLOSE_FAILED	537
	RPD_DYN_CFG_PDB_OPEN_FAILED	538
	RPD_DYN_CFG_PROCESSING_FAILED	538
	RPD_DYN_CFG_REGISTER_FAILED	538
	RPD_DYN_CFG_REQUEST_ACK_FAILED	538
	RPD_DYN_CFG_RESPONSE_SLOW	538
	RPD_DYN_CFG_SCHEMA_OPEN_FAILED	539
	RPD_DYN_CFG_SDB_CLOSE_FAILED	539
	RPD_DYN_CFG_SDB_OPEN_FAILED	539
	RPD_DYN_CFG_SES_RECOVERY_FAILED	539
	RPD_DYN_CFG_SET_CONTEXT_FAILED	540

RPD_ESIS_ADJDOWN	540
RPD_ESIS_ADJUP	540
RPD_EXIT	540
RPD_IFD_INDEXCOLLISION	541
RPD_IFD_NAMECOLLISION	541
RPD_IFL_INDEXCOLLISION	541
RPD_IFL_NAMECOLLISION	542
RPD_IGMP_ACCOUNTING_OFF	542
RPD_IGMP_ACCOUNTING_ON	542
RPD_IGMP_ALL_SUBSCRIBERS_DELETED	542
RPD_IGMP_CFG_CREATE_ENTRY_FAILED	543
RPD_IGMP_CFG_GROUP_OUT_OF_RANGE	543
RPD_IGMP_CFG_INVALID_VALUE	543
RPD_IGMP_CFG_SOURCE_OUT_OF_RANGE	543
RPD_IGMP_DYN_CFG_ALREADY_BOUND	544
RPD_IGMP_DYN_CFG_INVALID_STMT	544
RPD_IGMP_DYN_CFG_SES_ID_ADD_FAIL	544
RPD_IGMP_DYN_CFG_SES_ID_MISMATCH	545
RPD_IGMP_JOIN	545
RPD_IGMP_LEAVE	545
RPD_IGMP_MEMBERSHIP_TIMEOUT	545
RPD_IGMP_ROUTER_VERSION_MISMATCH	546
RPD_ISIS_ADJDOWN	546
RPD_ISIS_ADJUP	546
RPD_ISIS_ADJUPNOIP	546
RPD_ISIS_LDP_SYNC	547
RPD_ISIS_LSPCKSUM	547
RPD_ISIS_NO_ROUTERID	547
RPD_ISIS_OVERLOAD	548
RPD_KRT_CCC_IFL_MODIFY	548
RPD_KRT_DELETED_RTT	548
RPD_KRT_IFA_GENERATION	549
RPD_KRT_IFDCHANGE	549
RPD_KRT_IFDEST_GET	549
RPD_KRT_IFDGET	550
RPD_KRT_IFD_CELL_RELAY_INV_MODE	550
RPD_KRT_IFD_CELL_RELAY_NO_MODE	550
RPD_KRT_IFD_GENERATION	550
RPD_KRT_IFL_CELL_RELAY_INV_MODE	551
RPD_KRT_IFL_CELL_RELAY_NO_MODE	551
RPD_KRT_IFL_GENERATION	551
RPD_KRT_KERNEL_BAD_ROUTE	552
RPD_KRT_NEXTHOP_OVERFLOW	552
RPD_KRT_NOIFD	552
RPD_KRT_VERSION	553
RPD_KRT_VERSIONNONE	553
RPD_KRT_VERSIONOLD	553
RPD_KRT_VPLS_IFL_MODIFY	554
RPD_L2VPN_LABEL_ALLOC_FAILED	554

RPD_L2VPN_REMOTE_SITE_COLLISION	554
RPD_L2VPN_SITE_COLLISION	555
RPD_LAYER2_VC_BFD_DOWN	555
RPD_LAYER2_VC_BFD_UP	555
RPD_LAYER2_VC_DOWN	555
RPD_LAYER2_VC_PING_DOWN	556
RPD_LAYER2_VC_UP	556
RPD_LDP_BFD_DOWN	556
RPD_LDP_BFD_DOWN_TRACEROUTE_FAIL	556
RPD_LDP_BFD_UP	556
RPD_LDP_GR_CFG_IGNORED	557
RPD_LDP_INTF_BLOCKED	557
RPD_LDP_INTF_UNBLOCKED	557
RPD_LDP_NBRDOWN	558
RPD_LDP_NBRUP	558
RPD_LDP_PING_DOWN	558
RPD_LDP_SESSIONDOWN	558
RPD_LDP_SESSIONUP	558
RPD_LMP_ALLOC_ACK	559
RPD_LMP_ALLOC_REQUEST_TIMEOUT	559
RPD_LMP_CONTROL_CHANNEL	559
RPD_LMP_NO_CALLBACK	559
RPD_LMP_NO_MEMORY	560
RPD_LMP_NO_PEER	560
RPD_LMP_PEER	560
RPD_LMP_PEER_IFL	560
RPD_LMP_PEER_INDEX	561
RPD_LMP_RESOURCE	561
RPD_LMP_RESOURCE_NO_LINK	561
RPD_LMP_SEND	561
RPD_LMP_SEND_ALLOCATION_MESSAGE	561
RPD_LMP_SYSFAIL	562
RPD_LMP_TE_LINK	562
RPD_LMP_TE_LINK_INDEX	562
RPD_LMP_UNEXPECTED_OPCODE	562
RPD_LOCK_FLOCKED	563
RPD_LOCK_LOCKED	563
RPD_MC_CFG_CREATE_ENTRY_FAILED	563
RPD_MC_CFG_FWD_CACHE_CONFLICT	564
RPD_MC_CFG_PREFIX_LEN_SHORT	564
RPD_MC_COSD_WRITE_ERROR	564
RPD_MC_DESIGNATED_PE_CHANGE	564
RPD_MC_DYN_CFG_ALREADY_BOUND	565
RPD_MC_DYN_CFG_SES_ID_ADD_FAIL	565
RPD_MC_DYN_CFG_SES_ID_MISMATCH	565
RPD_MC_LOCAL_DESIGNATED_PE	565
RPD_MC_OIF_REJECT	566
RPD_MC_OIF_RE_ADMIT	566
RPD_MGMT_TIMEOUT	566

RPD_MIRROR_ERROR	566
RPD_MIRROR_VERSION_MISMATCH	567
RPD_MLD_ACCOUNTING_OFF	567
RPD_MLD_ACCOUNTING_ON	567
RPD_MLD_ALL_SUBSCRIBERS_DELETED	568
RPD_MLD_CFG_CREATE_ENTRY_FAILED	568
RPD_MLD_CFG_GROUP_OUT_OF_RANGE	568
RPD_MLD_CFG_INVALID_VALUE	568
RPD_MLD_CFG_SOURCE_OUT_OF_RANGE	569
RPD_MLD_DYN_CFG_ALREADY_BOUND	569
RPD_MLD_DYN_CFG_INVALID_STMT	569
RPD_MLD_DYN_CFG_SES_ID_ADD_FAIL	569
RPD_MLD_DYN_CFG_SES_ID_MISMATCH	570
RPD_MLD_JOIN	570
RPD_MLD_LEAVE	570
RPD_MLD_MEMBERSHIP_TIMEOUT	570
RPD_MLD_ROUTER_VERSION_MISMATCH	571
RPD_MPLS_INTERFACE_ROUTE_ERROR	571
RPD_MPLS_INTF_MAX_LABELS_ERROR	571
RPD_MPLS_LSP_AUTOBW_NOTICE	571
RPD_MPLS_LSP_BANDWIDTH_CHANGE	572
RPD_MPLS_LSP_CHANGE	572
RPD_MPLS_LSP_DOWN	572
RPD_MPLS_LSP_SWITCH	572
RPD_MPLS_LSP_UP	573
RPD_MPLS_OAM_LSP_PING_REPLY_ERR	573
RPD_MPLS_OAM_PING_REPLY_TIMEOUT	573
RPD_MPLS_OAM_READ_ERROR	573
RPD_MPLS_OAM_WRITE_ERROR	574
RPD_MPLS_PATH_BANDWIDTH_CHANGE	574
RPD_MPLS_PATH_BFD_DOWN	574
RPD_MPLS_PATH_BFD_UP	574
RPD_MPLS_PATH_BW_NOT_AVAILABLE	575
RPD_MPLS_PATH_DOWN	575
RPD_MPLS_PATH_PING_DOWN	575
RPD_MPLS_PATH_UP	575
RPD_MPLS_TABLE_ROUTE_ERROR	576
RPD_MSDP_CFG_SA_LIMITS_CONFLICT	576
RPD_MSDP_CFG_SRC_INVALID	576
RPD_MSDP_PEER_DOWN	576
RPD_MSDP_PEER_UP	577
RPD_MSDP_SRC_ACTIVE_OVER_LIMIT	577
RPD_MSDP_SRC_ACTIVE_OVER_THRESH	577
RPD_MSDP_SRC_ACTIVE_UNDER_LIMIT	577
RPD_MSDP_SRC_ACTIVE_UNDER_THRESH	578
RPD_MVPN_CFG_PREFIX_LEN_SHORT	578
RPD_OSPF_CFGNBR_P2P	578
RPD_OSPF_IF_COST_CHANGE	579
RPD_OSPF_LDP_SYNC	579

RPD_OSPF_LSA_MAXIMUM_EXCEEDED	579
RPD_OSPF_LSA_WARNING_EXCEEDED	579
RPD_OSPF_NBRDOWN	580
RPD_OSPF_NBRUP	580
RPD_OSPF_OVERLOAD	580
RPD_OSPF_TOPO_IF_COST_CHANGE	580
RPD_OS_MEMHIGH	581
RPD_PARSE_BAD_LR_NAME	581
RPD_PARSE_BAD_OPTION	581
RPD_PARSE_CMD_ARG	582
RPD_PARSE_CMD_DUPLICATE	582
RPD_PARSE_CMD_EXTRA	582
RPD_PIM_NBRDOWN	582
RPD_PIM_NBRUP	583
RPD_PLCY_CFG_COMMUNITY_FAIL	583
RPD_PLCY_CFG_FWDCLASS_OVERRIDDEN	583
RPD_PLCY_CFG_IFALL_NOMATCH	583
RPD_PLCY_CFG_NH_NETMASK	583
RPD_PLCY_CFG_PARSE_GEN_FAIL	584
RPD_PLCY_CFG_PREFIX_LEN_SHORT	584
RPD_PPM_READ_ERROR	584
RPD_PPM_WRITE_ERROR	584
RPD_RA_CFG_CREATE_ENTRY_FAILED	585
RPD_RA_CFG_INVALID_VALUE	585
RPD_RA_DYN_CFG_ALREADY_BOUND	585
RPD_RA_DYN_CFG_INVALID_STMT	586
RPD_RA_DYN_CFG_SES_ID_ADD_FAIL	586
RPD_RA_DYN_CFG_SES_ID_MISMATCH	586
RPD_RDISC_CKSUM	586
RPD_RDISC_NOMULTI	587
RPD_RDISC_NORECVIF	587
RPD_RDISC_SOLICITADDR	587
RPD_RDISC_SOLICITCMP	588
RPD_RDISC_SOLICITLEN	588
RPD_RIP_AUTH_REQUEST	588
RPD_RIP_AUTH_UPDATE	589
RPD_RIP_JOIN_BROADCAST	589
RPD_RIP_JOIN_MULTICAST	589
RPD_RSVP_BACKUP_DOWN	589
RPD_RSVP_BYPASS_DOWN	590
RPD_RSVP_BYPASS_UP	590
RPD_RSVP_COS_CFG_WARN	590
RPD_RSVP_LSP_SWITCH	590
RPD_RSVP_MAXIMUM_SESSIONS	591
RPD_RSVP_NBRDOWN	591
RPD_RSVP_NBRUP	591
RPD_RT_CFG_BR_CONFLICT	591
RPD_RT_CFG_CREATE_ENTRY_FAILED	592
RPD_RT_CFG_INVALID_VALUE	592

RPD_RT_CFG_TABLE_NON_MATCHING	592
RPD_RT_DUPLICATE_RD	592
RPD_RT_DYN_CFG_INST_NOT_FOUND	593
RPD_RT_DYN_CFG_TABLE_NOT_FOUND	593
RPD_RT_ERROR	593
RPD_RT_IFUP	593
RPD_RT_INST_CFG_RESERVED_NAME	593
RPD_RT_INST_IMPORT_PLCY_WARNING	594
RPD_RT_PATH_LIMIT_BELOW	594
RPD_RT_PATH_LIMIT_REACHED	594
RPD_RT_PATH_LIMIT_WARNING	594
RPD_RT_PREFIX_LIMIT_BELOW	595
RPD_RT_PREFIX_LIMIT_REACHED	595
RPD_RT_PREFIX_LIMIT_WARNING	595
RPD_RT_SHOWMODE	596
RPD_RT_TAG_ID_ALLOC_FAILED	596
RPD_SCHED_CALLBACK_LONGRUNTIME	596
RPD_SCHED_CUMULATIVE_LONGRUNTIME	596
RPD_SCHED_MODULE_LONGRUNTIME	597
RPD_SCHED_TASK_LONGRUNTIME	597
RPD_SIGNAL_TERMINATE	597
RPD_SNMP_CONN_PROG	597
RPD_SNMP_CONN_QUIT	598
RPD_SNMP_CONN_RETRY	598
RPD_SNMP_INVALID_SOCKET	598
RPD_SNMP_SOCKOPT_BLOCK	598
RPD_SNMP_SOCKOPT_RECVBUF	598
RPD_SNMP_SOCKOPT_SENDBUF	599
RPD_START	599
RPD_SYSTEM	599
RPD_TASK_BEGIN	599
RPD_TASK_CHILDKILLED	600
RPD_TASK_CHILDSTOPPED	600
RPD_TASK_DYN_REINIT	600
RPD_TASK_FORK	600
RPD_TASK_GETWD	600
RPD_TASK_MASTERSHIP	601
RPD_TASK_NOREINIT	601
RPD_TASK_PIDCLOSED	601
RPD_TASK_PIDFLOCK	601
RPD_TASK_PIDWRITE	602
RPD_TASK_REINIT	602
RPD_TASK_SIGNALIGNORE	602
RPD_TRACE_FAILED	602
RPD_VPLS_INTF_NOT_IN_SITE	603
RPD_ABORT	603
RPD_ACTIVE_TERMINATE	603
RPD_AMT_CFG_ADDR_FMLY_INVALID	603
RPD_AMT_CFG_ANYCAST_INVALID	604

RPD_AMT_CFG_ANYCAST_MCAST	604
RPD_AMT_CFG_LOC_ADDR_INVALID	604
RPD_AMT_CFG_LOC_ADDR_MCAST	604
RPD_AMT_CFG_PREFIX_LEN_SHORT	605
RPD_AMT_CFG_RELAY_INVALID	605
RPD_AMT_RELAY_DISCOVERY	605
RPD_AMT_TUNNEL_CREATE	605
RPD_AMT_TUNNEL_DELETE	606
RPD_ASSERT	606
RPD_ASSERT_SOFT	606
RPD_BFD_READ_ERROR	607
RPD_BFD_WRITE_ERROR	607
RPD_BGP_CFG_ADDR_INVALID	607
RPD_BGP_CFG_LOCAL_ASNUM_WARN	607
RPD_BGP_NEIGHBOR_STATE_CHANGED	608
RPD_CFG_TRACE_FILE_MISSING	608
RPD_DYN_CFG_BUSY_SIGNAL_FAILED	608
RPD_DYN_CFG_GET_PROFILE_FAILED	608
RPD_DYN_CFG_GET_PROF_NAME_FAILED	609
RPD_DYN_CFG_GET_SES_STATE_FAILED	609
RPD_DYN_CFG_GET_SES_TYPE_FAILED	609
RPD_DYN_CFG_GET_SNAPSHOT_FAILED	609
RPD_DYN_CFG_PDB_CLOSE_FAILED	610
RPD_DYN_CFG_PDB_OPEN_FAILED	610
RPD_DYN_CFG_PROCESSING_FAILED	610
RPD_DYN_CFG_REGISTER_FAILED	610
RPD_DYN_CFG_REQUEST_ACK_FAILED	610
RPD_DYN_CFG_RESPONSE_SLOW	611
RPD_DYN_CFG_SCHEMA_OPEN_FAILED	611
RPD_DYN_CFG_SDB_CLOSE_FAILED	611
RPD_DYN_CFG_SDB_OPEN_FAILED	611
RPD_DYN_CFG_SES_RECOVERY_FAILED	611
RPD_DYN_CFG_SET_CONTEXT_FAILED	612
RPD_ESIS_ADJDOWN	612
RPD_ESIS_ADJUP	612
RPD_EXIT	613
RPD_IFD_INDEXCOLLISION	613
RPD_IFD_NAMECOLLISION	613
RPD_IFL_INDEXCOLLISION	614
RPD_IFL_NAMECOLLISION	614
RPD_IGMP_ACCOUNTING_OFF	614
RPD_IGMP_ACCOUNTING_ON	614
RPD_IGMP_ALL_SUBSCRIBERS_DELETED	615
RPD_IGMP_CFG_CREATE_ENTRY_FAILED	615
RPD_IGMP_CFG_GROUP_OUT_OF_RANGE	615
RPD_IGMP_CFG_INVALID_VALUE	615
RPD_IGMP_CFG_SOURCE_OUT_OF_RANGE	616
RPD_IGMP_DYN_CFG_ALREADY_BOUND	616
RPD_IGMP_DYN_CFG_INVALID_STMT	616

RPD_IGMP_DYN_CFG_SES_ID_ADD_FAIL	617
RPD_IGMP_DYN_CFG_SES_ID_MISMATCH	617
RPD_IGMP_JOIN	617
RPD_IGMP_LEAVE	617
RPD_IGMP_MEMBERSHIP_TIMEOUT	618
RPD_IGMP_ROUTER_VERSION_MISMATCH	618
RPD_ISIS_ADJDOWN	618
RPD_ISIS_ADJUP	618
RPD_ISIS_ADJUPNOIP	619
RPD_ISIS_LDP_SYNC	619
RPD_ISIS_LSPCKSUM	619
RPD_ISIS_NO_ROUTERID	620
RPD_ISIS_OVERLOAD	620
RPD_KRT_CCC_IFL_MODIFY	620
RPD_KRT_DELETED_RTT	621
RPD_KRT_IFA_GENERATION	621
RPD_KRT_IFDCHANGE	621
RPD_KRT_IFDEST_GET	622
RPD_KRT_IFDGET	622
RPD_KRT_IFD_CELL_RELAY_INV_MODE	622
RPD_KRT_IFD_CELL_RELAY_NO_MODE	622
RPD_KRT_IFD_GENERATION	623
RPD_KRT_IFL_CELL_RELAY_INV_MODE	623
RPD_KRT_IFL_CELL_RELAY_NO_MODE	623
RPD_KRT_IFL_GENERATION	623
RPD_KRT_KERNEL_BAD_ROUTE	624
RPD_KRT_NEXTHOP_OVERFLOW	624
RPD_KRT_NOIFD	625
RPD_KRT_VERSION	625
RPD_KRT_VERSIONNONE	625
RPD_KRT_VERSIONOLD	626
RPD_KRT_VPLS_IFL_MODIFY	626
RPD_L2VPN_LABEL_ALLOC_FAILED	626
RPD_L2VPN_REMOTE_SITE_COLLISION	626
RPD_L2VPN_SITE_COLLISION	627
RPD_LAYER2_VC_BFD_DOWN	627
RPD_LAYER2_VC_BFD_UP	627
RPD_LAYER2_VC_DOWN	627
RPD_LAYER2_VC_PING_DOWN	628
RPD_LAYER2_VC_UP	628
RPD_LDP_BFD_DOWN	628
RPD_LDP_BFD_DOWN_TRACEROUTE_FAIL	628
RPD_LDP_BFD_UP	629
RPD_LDP_GR_CFG_IGNORED	629
RPD_LDP_INTF_BLOCKED	629
RPD_LDP_INTF_UNBLOCKED	629
RPD_LDP_NBRDOWN	630
RPD_LDP_NBRUP	630
RPD_LDP_PING_DOWN	630

RPD_LDP_SESSIONDOWN	630
RPD_LDP_SESSIONUP	631
RPD_LMP_ALLOC_ACK	631
RPD_LMP_ALLOC_REQUEST_TIMEOUT	631
RPD_LMP_CONTROL_CHANNEL	631
RPD_LMP_NO_CALLBACK	632
RPD_LMP_NO_MEMORY	632
RPD_LMP_NO_PEER	632
RPD_LMP_PEER	632
RPD_LMP_PEER_IFL	632
RPD_LMP_PEER_INDEX	633
RPD_LMP_RESOURCE	633
RPD_LMP_RESOURCE_NO_LINK	633
RPD_LMP_SEND	633
RPD_LMP_SEND_ALLOCATION_MESSAGE	634
RPD_LMP_SYSFAIL	634
RPD_LMP_TE_LINK	634
RPD_LMP_TE_LINK_INDEX	634
RPD_LMP_UNEXPECTED_OPCODE	635
RPD_LOCK_FLOCKED	635
RPD_LOCK_LOCKED	635
RPD_MC_CFG_CREATE_ENTRY_FAILED	635
RPD_MC_CFG_FWD_CACHE_CONFLICT	636
RPD_MC_CFG_PREFIX_LEN_SHORT	636
RPD_MC_COSD_WRITE_ERROR	636
RPD_MC_DESIGNATED_PE_CHANGE	637
RPD_MC_DYN_CFG_ALREADY_BOUND	637
RPD_MC_DYN_CFG_SES_ID_ADD_FAIL	637
RPD_MC_DYN_CFG_SES_ID_MISMATCH	637
RPD_MC_LOCAL_DESIGNATED_PE	638
RPD_MC_OIF_REJECT	638
RPD_MC_OIF_RE_ADMIT	638
RPD_MGMT_TIMEOUT	638
RPD_MIRROR_ERROR	639
RPD_MIRROR_VERSION_MISMATCH	639
RPD_MLD_ACCOUNTING_OFF	639
RPD_MLD_ACCOUNTING_ON	639
RPD_MLD_ALL_SUBSCRIBERS_DELETED	640
RPD_MLD_CFG_CREATE_ENTRY_FAILED	640
RPD_MLD_CFG_GROUP_OUT_OF_RANGE	640
RPD_MLD_CFG_INVALID_VALUE	640
RPD_MLD_CFG_SOURCE_OUT_OF_RANGE	641
RPD_MLD_DYN_CFG_ALREADY_BOUND	641
RPD_MLD_DYN_CFG_INVALID_STMT	641
RPD_MLD_DYN_CFG_SES_ID_ADD_FAIL	642
RPD_MLD_DYN_CFG_SES_ID_MISMATCH	642
RPD_MLD_JOIN	642
RPD_MLD_LEAVE	642
RPD_MLD_MEMBERSHIP_TIMEOUT	643

RPD_MLD_ROUTER_VERSION_MISMATCH	643
RPD_MPLS_INTERFACE_ROUTE_ERROR	643
RPD_MPLS_INTF_MAX_LABELS_ERROR	643
RPD_MPLS_LSP_AUTOBW_NOTICE	643
RPD_MPLS_LSP_BANDWIDTH_CHANGE	644
RPD_MPLS_LSP_CHANGE	644
RPD_MPLS_LSP_DOWN	644
RPD_MPLS_LSP_SWITCH	644
RPD_MPLS_LSP_UP	645
RPD_MPLS_OAM_LSP_PING_REPLY_ERR	645
RPD_MPLS_OAM_PING_REPLY_TIMEOUT	645
RPD_MPLS_OAM_READ_ERROR	645
RPD_MPLS_OAM_WRITE_ERROR	646
RPD_MPLS_PATH_BANDWIDTH_CHANGE	646
RPD_MPLS_PATH_BFD_DOWN	646
RPD_MPLS_PATH_BFD_UP	646
RPD_MPLS_PATH_BW_NOT_AVAILABLE	647
RPD_MPLS_PATH_DOWN	647
RPD_MPLS_PATH_PING_DOWN	647
RPD_MPLS_PATH_UP	647
RPD_MPLS_TABLE_ROUTE_ERROR	648
RPD_MSDP_CFG_SA_LIMITS_CONFLICT	648
RPD_MSDP_CFG_SRC_INVALID	648
RPD_MSDP_PEER_DOWN	648
RPD_MSDP_PEER_UP	649
RPD_MSDP_SRC_ACTIVE_OVER_LIMIT	649
RPD_MSDP_SRC_ACTIVE_OVER_THRESH	649
RPD_MSDP_SRC_ACTIVE_UNDER_LIMIT	649
RPD_MSDP_SRC_ACTIVE_UNDER_THRESH	650
RPD_MVPN_CFG_PREFIX_LEN_SHORT	650
RPD_OSPF_CFGNBR_P2P	650
RPD_OSPF_IF_COST_CHANGE	651
RPD_OSPF_LDP_SYNC	651
RPD_OSPF_LSA_MAXIMUM_EXCEEDED	651
RPD_OSPF_LSA_WARNING_EXCEEDED	651
RPD_OSPF_NBRDOWN	652
RPD_OSPF_NBRUP	652
RPD_OSPF_OVERLOAD	652
RPD_OSPF_TOPO_IF_COST_CHANGE	652
RPD_OS_MEMHIGH	653
RPD_PARSE_BAD_LR_NAME	653
RPD_PARSE_BAD_OPTION	653
RPD_PARSE_CMD_ARG	654
RPD_PARSE_CMD_DUPLICATE	654
RPD_PARSE_CMD_EXTRA	654
RPD_PIM_NBRDOWN	654
RPD_PIM_NBRUP	655
RPD_PLCY_CFG_COMMUNITY_FAIL	655
RPD_PLCY_CFG_FWDCLASS_OVERRIDDEN	655

RPD_PLCY_CFG_IFALL_NOMATCH	655
RPD_PLCY_CFG_NH_NETMASK	655
RPD_PLCY_CFG_PARSE_GEN_FAIL	656
RPD_PLCY_CFG_PREFIX_LEN_SHORT	656
RPD_PPM_READ_ERROR	656
RPD_PPM_WRITE_ERROR	656
RPD_RA_CFG_CREATE_ENTRY_FAILED	657
RPD_RA_CFG_INVALID_VALUE	657
RPD_RA_DYN_CFG_ALREADY_BOUND	657
RPD_RA_DYN_CFG_INVALID_STMT	658
RPD_RA_DYN_CFG_SES_ID_ADD_FAIL	658
RPD_RA_DYN_CFG_SES_ID_MISMATCH	658
RPD_RDISC_CKSUM	658
RPD_RDISC_NOMULTI	659
RPD_RDISC_NORECVIF	659
RPD_RDISC_SOLICITADDR	659
RPD_RDISC_SOLICITCMP	660
RPD_RDISC_SOLICITLEN	660
RPD_RIP_AUTH_ACK	660
RPD_RIP_AUTH_REQUEST	661
RPD_RIP_AUTH_UPDATE	661
RPD_RIP_JOIN_BROADCAST	661
RPD_RIP_JOIN_MULTICAST	661
RPD_RSVP_BACKUP_DOWN	662
RPD_RSVP_BYPASS_DOWN	662
RPD_RSVP_BYPASS_UP	662
RPD_RSVP_COS_CFG_WARN	662
RPD_RSVP_LSP_SWITCH	663
RPD_RSVP_MAXIMUM_SESSIONS	663
RPD_RSVP_NBRDOWN	663
RPD_RSVP_NBRUP	663
RPD_RT_CFG_BR_CONFLICT	664
RPD_RT_CFG_CREATE_ENTRY_FAILED	664
RPD_RT_CFG_INVALID_VALUE	664
RPD_RT_CFG_TABLE_NON_MATCHING	664
RPD_RT_DUPLICATE_RD	665
RPD_RT_DYN_CFG_INST_NOT_FOUND	665
RPD_RT_DYN_CFG_TABLE_NOT_FOUND	665
RPD_RT_ERROR	665
RPD_RT_IFUP	666
RPD_RT_INST_CFG_RESERVED_NAME	666
RPD_RT_INST_IMPORT_PLCY_WARNING	666
RPD_RT_PATH_LIMIT_BELOW	666
RPD_RT_PATH_LIMIT_REACHED	666
RPD_RT_PATH_LIMIT_WARNING	667
RPD_RT_PREFIX_LIMIT_BELOW	667
RPD_RT_PREFIX_LIMIT_REACHED	667
RPD_RT_PREFIX_LIMIT_WARNING	668
RPD_RT_SHOWMODE	668

	RPD_RT_TAG_ID_ALLOC_FAILED	668
	RPD_SCHED_CALLBACK_LONGRUNTIME	668
	RPD_SCHED_CUMULATIVE_LONGRUNTIME	669
	RPD_SCHED_MODULE_LONGRUNTIME	669
	RPD_SCHED_TASK_LONGRUNTIME	669
	RPD_SIGNAL_TERMINATE	669
	RPD_SNMP_CONN_PROG	670
	RPD_SNMP_CONN_QUIT	670
	RPD_SNMP_CONN_RETRY	670
	RPD_SNMP_INVALID_SOCKET	670
	RPD_SNMP_SOCKOPT_BLOCK	671
	RPD_SNMP_SOCKOPT_RECVBUF	671
	RPD_SNMP_SOCKOPT_SENDBUF	671
	RPD_START	671
	RPD_SYSTEM	671
	RPD_TASK_BEGIN	672
	RPD_TASK_CHILDKILLED	672
	RPD_TASK_CHILDSTOPPED	672
	RPD_TASK_DYN_REINIT	672
	RPD_TASK_FORK	673
	RPD_TASK_GETWD	673
	RPD_TASK_MASTERSHIP	673
	RPD_TASK_NOREINIT	673
	RPD_TASK_PIDCLOSED	673
	RPD_TASK_PIDFLOCK	674
	RPD_TASK_PIDWRITE	674
	RPD_TASK_REINIT	674
	RPD_TASK_SIGNALIGNORE	674
	RPD_TRACE_FAILED	675
	RPD_VPLS_INTF_NOT_IN_SITE	675
Chapter 84	RT System Log Messages	677
	RT_FLOW_SESSION_CLOSE	677
	RT_FLOW_SESSION_CREATE	677
	RT_FLOW_SESSION_DENY	677
	RT_GTP_BAD_LICENSE	678
	RT_GTP_DEL_TUNNEL_VO	678
	RT_GTP_DEL_TUNNEL_V1	678
	RT_GTP_PKT_APN_IE	678
	RT_GTP_PKT_DESCRIPTION_CHARGING	679
	RT_GTP_PKT_DESCRIPTION_VO	679
	RT_GTP_PKT_DESCRIPTION_V1	679
	RT_GTP_PKT_ENDUSER_ADDR_IE_IPV4	679
	RT_GTP_PKT_GSNADDR_IE	680
	RT_GTP_PKT_IMSI_IE	680
	RT_GTP_PKT_MSISDN_IE	680
	RT_GTP_PKT_RESULT	680
	RT_GTP_SANITY_EXTENSION_HEADER	681
	RT_GTP_SYSTEM_ERROR	681

	RT_H323_NAT_COOKIE_NOT_FOUND	681
	RT_IPSEC_BAD_SPI	681
	RT_IPSEC_REPLAY	681
	RT_MGCP_CALL_LIMIT_EXCEED	682
	RT_MGCP_DECODE_FAIL	682
	RT_MGCP_MEM_ALLOC_FAILED	682
	RT_MGCP_REG_NAT_VEC_FAIL	682
	RT_MGCP_REG_RM_FAIL	682
	RT_MGCP_REM_NAT_VEC_FAIL	683
	RT_MGCP_RM_CLIENTID_FAIL	683
	RT_MGCP_UNREG_BY_RM	683
	RT_SCCP_CALL_LIMIT_EXCEED	683
	RT_SCCP_CALL_RATE_EXCEED	683
	RT_SCCP_DECODE_FAIL	684
	RT_SCCP_NAT_COOKIE_NOT_FOUND	684
	RT_SCCP_REM_NAT_VEC_FAIL	684
	RT_SCCP_UNREG_RM_FAIL	684
	RT_SCREEN_ICMP	685
	RT_SCREEN_IP	685
	RT_SCREEN_SESSION_LIMIT	685
	RT_SCREEN_TCP	685
	RT_SCREEN_TCP_DST_IP	685
	RT_SCREEN_TCP_SRC_IP	686
	RT_SCREEN_UDP	686
	RT_SCTP_LOG_INFO	686
	RT_SCTP_PKT_INFO	686
	RT_SIP_MEM_ALLOC_FAILED	687
Chapter 85	RTLOG System Log Messages	689
	RTLOG_JLOG_TEST	689
	RTLOG_UTP_TCP_SYN_FLOOD	689
Chapter 86	RTLOGD System Log Messages	691
	RTLOGD_LOG_BIND_ERROR	691
	RTLOGD_LOG_READ_ERROR	691
Chapter 87	RTPERF System Log Messages	693
	RTPERF_CPU_THRESHOLD_EXCEEDED	693
	RTPERF_CPU_USAGE_OK	693
Chapter 88	SAVAL System Log Messages	695
	SAVAL_RTsock_FAILURE	695
Chapter 89	SDXD System Log Messages	697
	SDXD_BEEP_FIN_FAIL	697
	SDXD_BEEP_INIT_FAIL	697
	SDXD_CHANNEL_START_FAIL	697
	SDXD_CONNECT_FAIL	698
	SDXD_DAEMONIZE_FAIL	698
	SDXD_EVLIB_FAILURE	698
	SDXD_KEEPAIVES_MISSED	699

	SDXD_KEEPLIVE_SEND_FAIL	699
	SDXD_MGMT_SOCKET_IO	699
	SDXD_OUT_OF_MEMORY	699
	SDXD_PID_FILE_UPDATE	700
	SDXD_SOCKET_FAILURE	700
Chapter 90	SFW System Log Messages	701
	SFW_LOG_FUNCTION	701
Chapter 91	SMTPD System Log Messages	703
	SMTPD_DROP_MAIL_PAYLOAD	703
	SMTPD_NO_CONFIGURED_SERVER	703
Chapter 92	SNMP System Log Messages	705
	SNMP_GET_ERROR1	705
	SNMP_GET_ERROR2	705
	SNMP_GET_ERROR3	706
	SNMP_GET_ERROR4	706
	SNMP_RTSLIB_FAILURE	706
	SNMP_TRAP_LINK_DOWN	707
	SNMP_TRAP_LINK_UP	707
	SNMP_TRAP_TRACERT_PATH_CHANGE	707
	SNMP_TRAP_TRACERT_TEST_COMPLETED	707
	SNMP_TRAP_TRACERT_TEST_FAILED	708
Chapter 93	SNMPD System Log Messages	709
	SNMPD_AUTH_FAILURE	709
	SNMPD_AUTH_PRIVILEGES_EXCEEDED	709
	SNMPD_AUTH_RESTRICTED_ADDRESS	710
	SNMPD_AUTH_WRONG_PDU_TYPE	710
	SNMPD_BIND_INFO	710
	SNMPD_CONFIG_ERROR	711
	SNMPD_CONTEXT_ERROR	711
	SNMPD_FILE_FAILURE	711
	SNMPD_GROUP_ERROR	711
	SNMPD_HEALTH_MON_THRESH_CROSS	712
	SNMPD_INIT_FAILED	712
	SNMPD_LIBJUNIPER_FAILURE	712
	SNMPD_RADIX_FAILURE	713
	SNMPD_RECEIVE_FAILURE	713
	SNMPD_RMONFILE_FAILURE	713
	SNMPD_RMON_COOKIE	714
	SNMPD_RMON_EVENTLOG	714
	SNMPD_RMON_MIBERROR	714
	SNMPD_RTSLIB_ASYNC_EVENT	714
	SNMPD_SEND_FAILURE	715
	SNMPD_SET_FAILED	715
	SNMPD_SMOID_GEN_FAILURE	715
	SNMPD_SOCKET_FAILURE	716
	SNMPD_SOCKET_FATAL_FAILURE	716

	SNMPD_SYSLIB_FAILURE	716
	SNMPD_SYSOID_FAILURE	717
	SNMPD_SYSOID_GEN_FAILURE	717
	SNMPD_THROTTLE_QUEUE_DRAINED	717
	SNMPD_TRAP_COLD_START	717
	SNMPD_TRAP_GEN_FAILURE	718
	SNMPD_TRAP_INVALID_DATA	718
	SNMPD_TRAP_QUEUED	718
	SNMPD_TRAP_QUEUE_DRAINED	719
	SNMPD_TRAP_QUEUE_MAX_ATTEMPTS	719
	SNMPD_TRAP_QUEUE_MAX_SIZE	719
	SNMPD_TRAP_THROTTLED	719
	SNMPD_TRAP_WARM_START	719
	SNMPD_USER_ERROR	720
Chapter 94	SPD System Log Messages	721
	SPD_CONFIGURATION_COMPILE	721
	SPD_CONN_FATAL_FAILURE	721
	SPD_CONN_NO_REPLY	721
	SPD_CONN_OPEN_FAILURE	722
	SPD_CONN_SEND_FAILURE	722
	SPD_CONN_UNEXPECTED_MSG	722
	SPD_DAEMONIZE_FAILED	722
	SPD_DB_IF_ADD_FAILURE	723
	SPD_DB_IF_ALLOC_FAILURE	723
	SPD_DB_SVC_SET_ADD_FAILURE	723
	SPD_DB_SVC_SET_ALLOC_FAILURE	723
	SPD_DUPLICATE	724
	SPD_EVLIB_CREATE_FAILURE	724
	SPD_EVLIB_EXIT_FAILURE	724
	SPD_GEN_NUM_FAIL	724
	SPD_NOT_ROOT	724
	SPD_OUT_OF_MEMORY	725
	SPD_PID_FILE_LOCK	725
	SPD_PID_FILE_UPDATE	725
	SPD_SERVICE_NEXT_HOP_ADD_FAILED	725
	SPD_SERVICE_NEXT_HOP_DEL_FAILED	726
	SPD_TRAP_OID_GEN_FAILED	726
	SPD_TRAP_REQUEST_FAILURE	726
	SPD_USAGE	726
Chapter 95	SSH System Log Messages	727
	SSH_FIPS_SELFTEST_EXECUTED	727
	SSH_KEYGEN_SELFTEST_DSA	727
	SSH_KEYGEN_SELFTEST_RSA	727
	SSH_RELAY_CONNECT_ERROR	727
	SSH_RELAY_SERVER_ERROR	728
	SSH_RELAY_USAGE	728

Chapter 96	SSHD System Log Messages	729
	SSHD_FIPS_SELFTEST_EXECUTED	729
	SSHD_LOGIN_FAILED_LIMIT	729
Chapter 97	TASK System Log Messages	731
	TASK_ABORT	731
	TASK_ACTIVE_TERMINATE	731
	TASK_ASSERT	731
	TASK_ASSERT_SOFT	732
	TASK_EXIT	732
	TASK_LOCK_FLOCKED	732
	TASK_LOCK_LOCKED	733
	TASK_MGMT_TIMEOUT	733
	TASK_OS_MEMHIGH	733
	TASK_SCHED_CALLBACK_LONGRUNTIME	734
	TASK_SCHED_CUMULATIVE_RUNTIME	734
	TASK_SCHED_MODULE_LONGRUNTIME	734
	TASK_SCHED_TASK_LONGRUNTIME	735
	TASK_SIGNAL_TERMINATE	735
	TASK_START	735
	TASK_SYSTEM	735
	TASK_TASK_BEGIN	736
	TASK_TASK_CHILDKILLED	736
	TASK_TASK_CHILDSTOPPED	736
	TASK_TASK_FORK	736
	TASK_TASK_GETWD	736
	TASK_TASK_NOREINIT	737
	TASK_TASK_PIDCLOSED	737
	TASK_TASK_PIDFLOCK	737
	TASK_TASK_PIDWRITE	737
	TASK_TASK_REINIT	738
	TASK_TASK_SIGNALIGNORE	738
	TASK_TRACE_FAILED	738
Chapter 98	TFTPD System Log Messages	739
	TFTPD_AF_ERR	739
	TFTPD_BIND_ERR	739
	TFTPD_CONNECT_ERR	739
	TFTPD_CONNECT_INFO	740
	TFTPD_CREATE_ERR	740
	TFTPD_FIO_ERR	740
	TFTPD_FORK_ERR	740
	TFTPD_NAK_ERR	741
	TFTPD_OPEN_ERR	741
	TFTPD_RECVCOMPLETE_INFO	741
	TFTPD_RECVFROM_ERR	741
	TFTPD_RECV_ERR	741
	TFTPD_SENDCOMPLETE_INFO	742
	TFTPD_SEND_ERR	742

	TFTPD_SOCKET_ERR	742
	TFTPD_STATFS_ERR	742
Chapter 99	UFDD System Log Messages	743
	UFDD_SYSTEM_CALL_FAILED	743
Chapter 100	UI System Log Messages	745
	UI_AUTH_EVENT	745
	UI_AUTH_INVALID_CHALLENGE	745
	UI_BOOTTIME_FAILED	745
	UI_CFG_AUDIT_NEW	746
	UI_CFG_AUDIT_OTHER	746
	UI_CFG_AUDIT_SET	746
	UI_CFG_AUDIT_SET_SECRET	746
	UI_CHILD_ARGS_EXCEEDED	747
	UI_CHILD_CHANGE_USER	747
	UI_CHILD_EXEC	747
	UI_CHILD_EXITED	748
	UI_CHILD_FOPEN	748
	UI_CHILD_OUTPUT	748
	UI_CHILD_PIPE_FAILED	748
	UI_CHILD_STOPPED	749
	UI_CHILD_WAITPID	749
	UI_CMDLINE_READ_LINE	749
	UI_CMD_AUTH_REGEX_INVALID	750
	UI_COMMIT	750
	UI_COMMIT_AT_ABORT	750
	UI_COMMIT_AT_COMPLETED	750
	UI_COMMIT_AT_FAILED	751
	UI_COMMIT_COMPRESS_FAILED	751
	UI_COMMIT_CONFIRMED_REMINDER	751
	UI_COMMIT_EMPTY_CONTAINER	751
	UI_COMMIT_NOT_CONFIRMED	752
	UI_COMMIT_PREV_CNF_SAVED	752
	UI_COMMIT_PROGRESS	752
	UI_COMMIT_ROLLBACK_FAILED	753
	UI_COMMIT_SYNC_FORCE	753
	UI_CONFIGURATION_ERROR	753
	UI_CONFIGURATION_WARNING	754
	UI_DAEMON_ACCEPT_FAILED	754
	UI_DAEMON_FORK_FAILED	754
	UI_DAEMON_SELECT_FAILED	754
	UI_DAEMON_SOCKET_FAILED	755
	UI_DBASE_ACCESS_FAILED	755
	UI_DBASE_CHECKOUT_FAILED	755
	UI_DBASE_EXTEND_FAILED	756
	UI_DBASE_LOGIN_EVENT	756
	UI_DBASE_LOGOUT_EVENT	756
	UI_DBASE_MISMATCH_EXTENT	756
	UI_DBASE_MISMATCH_MAJOR	757

	UI_DBASE_MISMATCH_MINOR	757
	UI_DBASE_MISMATCH_SEQUENCE	758
	UI_DBASE_MISMATCH_SIZE	758
	UI_DBASE_OPEN_FAILED	759
	UI_DBASE_REBUILD_FAILED	759
	UI_DBASE_REBUILD_SCHEMA_FAILED	759
	UI_DBASE_REBUILD_STARTED	760
	UI_DBASE_RECREATE	760
	UI_DBASE_REOPEN_FAILED	760
	UI_DUPLICATE_UID	760
	UI_FACTORY_OPERATION	761
	UI_INITIALSETUP_OPERATION	761
	UI_INVALID_REMOTE_PERMISSION	761
	UI_JUNOSCRIP_CMD	761
	UI_JUNOSCRIP_ERROR	762
	UI_LCC_NO_MASTER	762
	UI_LOAD_EVENT	762
	UI_LOAD_JUNOS_DEFAULT_FILE_EVENT	763
	UI_LOGIN_EVENT	763
	UI_LOGOUT_EVENT	763
	UI_LOST_CONN	763
	UI_MASTERSHIP_EVENT	763
	UI_MOTD_PROPAGATE_ERROR	764
	UI_NETCONF_CMD	764
	UI_NETCONF_ERROR	764
	UI_PARSE_JUNOSCRIP_ATTRIBUTES	764
	UI_READ_FAILED	765
	UI_READ_TIMEOUT	765
	UI_REBOOT_EVENT	765
	UI_RESCUE_OPERATION	765
	UI_RESTART_EVENT	766
	UI_SCHEMA_CHECKOUT_FAILED	766
	UI_SCHEMA_MISMATCH_MAJOR	766
	UI_SCHEMA_MISMATCH_SEQUENCE	767
	UI_SCHEMA_SEQUENCE_ERROR	767
	UI_TACPLUS_ERROR	768
	UI_VERSION_FAILED	768
	UI_WRITE_RECONNECT	768
Chapter 101	UTMD System Log Messages	769
	UTMD_MALLOC_FAILURE	769
	UTMD_SSAMLIB_FAILURE	769
Chapter 102	VCCPD System Log Messages	771
	VCCPD_KNL_VERSION	771
	VCCPD_KNL_VERSIONNONE	771
	VCCPD_KNL_VERSIONOLD	772
	VCCPD_PROTOCOL_ADJDOWN	772
	VCCPD_PROTOCOL_ADJUP	772
	VCCPD_PROTOCOL_LSPCKSUM	772

	VCCPD_PROTOCOL_OVERLOAD	773
	VCCPD_SYSTEM	773
Chapter 103	VRRPD System Log Messages	775
	VRRPD_ADVERT_TIME_MISMATCH	775
	VRRPD_AUTH_INFO_INVALID	775
	VRRPD_GET_TRAP_HEADER_FAILED	776
	VRRPD_LINK_LOCAL_ADD_MISMATCH	776
	VRRPD_MISSING_VIP	776
	VRRPD_NEW_BACKUP	777
	VRRPD_NEW_MASTER	777
	VRRPD_VIP_COUNT_MISMATCH	777
Chapter 104	VSYS System Log Messages	779
	VSYS_INIT_FAILED	779
Chapter 105	WEB System Log Messages	781
	WEB_AUTH_FAIL	781
	WEB_AUTH_SUCCESS	781
	WEB_AUTH_TIME_EXCEEDED	781
	WEB_CERT_FILE_NOT_FOUND	781
	WEB_CHILD_STATE	782
	WEB_CONFIG_OPEN_ERROR	782
	WEB_CONFIG_WRITE_ERROR	782
	WEB_COULDNT_START_HTTPD	782
	WEB_EVENTLIB_INIT	783
	WEB_KEYPAIR_FILE_NOT_FOUND	783
	WEB_MGD_BIND_ERROR	783
	WEB_MGD_CHMOD_ERROR	783
	WEB_MGD_CONNECT_ERROR	783
	WEB_MGD_FCNTL_ERROR	784
	WEB_MGD_LISTEN_ERROR	784
	WEB_MGD_RECVMSG_PEEK_ERROR	784
	WEB_MGD_SOCKET_ERROR	784
	WEB_PIDFILE_LOCK	784
	WEB_PIDFILE_UPDATE	785
	WEB_UNAME_FAILED	785
	WEB_WEBAUTH_AUTH_FAIL	785
	WEB_WEBAUTH_AUTH_OK	785
	WEB_WEBAUTH_CONNECT_FAIL	786
Chapter 106	WEBFILTER System Log Messages	787
	WEBFILTER_CACHE_NOT_ENABLED	787
	WEBFILTER_INTERNAL_ERROR	787
	WEBFILTER_REQUEST_NOT_CHECKED	787
	WEBFILTER_SERVER_CONNECTED	788
	WEBFILTER_SERVER_DISCONNECTED	788
	WEBFILTER_SERVER_ERROR	788
	WEBFILTER_URL_BLOCKED	789
	WEBFILTER_URL_PERMITTED	789

Part 3**Index**

Index	793
-------------	-----

About This Guide

This preface provides the following guidelines for using the *Junos[®] OS System Log Messages Reference*:

- Junos OS Documentation and Release Notes on page lxxv
- Objectives on page lxxvi
- Audience on page lxxvi
- Supported Platforms on page lxxvi
- Using the Examples in This Manual on page lxxvii
- Documentation Conventions on page lxxviii
- Documentation Feedback on page lxx
- Requesting Technical Support on page lxx

Junos OS Documentation and Release Notes

For a list of related Junos OS documentation, see <http://www.juniper.net/techpubs/software/junos/>.

If the information in the latest release notes differs from the information in the documentation, follow the *Junos OS Release Notes*.

To obtain the most current version of all Juniper Networks[®] technical documentation, see the product documentation page on the Juniper Networks website at <http://www.juniper.net/techpubs/>.

Juniper Networks supports a technical book program to publish books by Juniper Networks engineers and subject matter experts with book publishers around the world. These books go beyond the technical documentation to explore the nuances of network architecture, deployment, and administration using the Junos operating system (Junos OS) and Juniper Networks devices. In addition, the Juniper Networks Technical Library, published in conjunction with O'Reilly Media, explores improving network security, reliability, and availability using Junos OS configuration techniques. All the books are for sale at technical bookstores and book outlets around the world. The current list can be viewed at <http://www.juniper.net/books>.

Objectives

This reference describes system log messages generated by the Junos OS. Use the information to interpret system log messages and determine the appropriate corrective action for error conditions



NOTE: For additional information about the Junos OS—either corrections to or information that might have been omitted from this guide—see the software release notes at <http://www.juniper.net/>.

Audience

This guide is designed for network administrators who are configuring and monitoring a Juniper Networks M Series, MX Series, T Series, EX Series, or J Series router or switch.

To use this reference, you need a broad understanding of networks in general, the Internet in particular, networking principles, and network configuration. You must also be familiar with one or more of the following Internet routing protocols:

- Border Gateway Protocol (BGP)
- Distance Vector Multicast Routing Protocol (DVMRP)
- Intermediate System-to-Intermediate System (IS-IS)
- Internet Control Message Protocol (ICMP) router discovery
- Internet Group Management Protocol (IGMP)
- Multiprotocol Label Switching (MPLS)
- Open Shortest Path First (OSPF)
- Protocol-Independent Multicast (PIM)
- Resource Reservation Protocol (RSVP)
- Routing Information Protocol (RIP)
- Simple Network Management Protocol (SNMP)

Personnel operating the equipment must be trained and competent; must not conduct themselves in a careless, willfully negligent, or hostile manner; and must abide by the instructions provided by the documentation.

Supported Platforms

For the features described in this manual, the Junos OS currently supports the following platforms:

- J Series
- M Series

- MX Series
- T Series
- EX Series

Using the Examples in This Manual

If you want to use the examples in this manual, you can use the **load merge** or the **load merge relative** command. These commands cause the software to merge the incoming configuration into the current candidate configuration. If the example configuration contains the top level of the hierarchy (or multiple hierarchies), the example is a *full example*. In this case, use the **load merge** command

If the example configuration does not start at the top level of the hierarchy, the example is a *snippet*. In this case, use the **load merge relative** command. These procedures are described in the following sections.

Merging a Full Example

To merge a full example, follow these steps:

1. From the HTML or PDF version of the manual, copy a configuration example into a text file, save the file with a name, and copy the file to a directory on your routing platform.

For example, copy the following configuration to a file and name the file **ex-script.conf**. Copy the **ex-script.conf** file to the **/var/tmp** directory on your routing platform.

```
system {
  scripts {
    commit {
      file ex-script.xsl;
    }
  }
}
interfaces {
  fxp0 {
    disable;
    unit 0 {
      family inet {
        address 10.0.0.1/24;
      }
    }
  }
}
```

2. Merge the contents of the file into your routing platform configuration by issuing the **load merge** configuration mode command:

```
[edit]
user@host# load merge /var/tmp/ex-script.conf
load complete
```

Merging a Snippet

To merge a snippet, follow these steps:

1. From the HTML or PDF version of the manual, copy a configuration snippet into a text file, save the file with a name, and copy the file to a directory on your routing platform.

For example, copy the following snippet to a file and name the file **ex-script-snippet.conf**. Copy the **ex-script-snippet.conf** file to the **/var/tmp** directory on your routing platform.

```
commit {
file ex-script-snippet.xml;
}
```

2. Move to the hierarchy level that is relevant for this snippet by issuing the following configuration mode command:

```
[edit]
user@host# edit system scripts
[edit system scripts]
```

3. Merge the contents of the file into your routing platform configuration by issuing the load merge relative configuration mode command:

```
[edit system scripts]
user@host# load merge relative /var/tmp/ex-script-snippet.conf
load complete
```

For more information about the load command, see the *Junos OS CLI User Guide*

Documentation Conventions

Table 1 on page lxviii defines notice icons used in this guide.

Table 1: Notice Icons




Icon	Meaning	Description
	Informational note	Indicates important features or instructions.
	Caution	Indicates a situation that might result in loss of data or hardware damage.
	Warning	Alerts you to the risk of personal injury or death.
	Laser warning	Alerts you to the risk of personal injury from a laser.

Table 2 on page lxi defines the text and syntax conventions used in this guide.

Table 2: Text and Syntax Conventions

Convention	Description	Examples
Bold text like this	Represents text that you type.	To enter configuration mode, type the configure command: user@host> configure
Fixed-width text like this	Represents output that appears on the terminal screen.	user@host> show chassis alarms No alarms currently active
<i>Italic text like this</i>	<ul style="list-style-type: none"> Introduces important new terms. Identifies book names. Identifies RFC and Internet draft titles. 	<ul style="list-style-type: none"> A policy <i>term</i> is a named structure that defines match conditions and actions. <i>Junos OS System Basics Configuration Guide</i> RFC 1997, <i>BGP Communities Attribute</i>
<i>Italic text like this</i>	Represents variables (options for which you substitute a value) in commands or configuration statements.	Configure the machine's domain name: [edit] root@# set system domain-name <i>domain-name</i>
Text like this	Represents names of configuration statements, commands, files, and directories; interface names; configuration hierarchy levels; or labels on routing platform components.	<ul style="list-style-type: none"> To configure a stub area, include the stub statement at the [edit protocols ospf area area-id] hierarchy level. The console port is labeled CONSOLE.
< > (angle brackets)	Enclose optional keywords or variables.	stub <default-metric <i>metric</i> >;
(pipe symbol)	Indicates a choice between the mutually exclusive keywords or variables on either side of the symbol. The set of choices is often enclosed in parentheses for clarity.	broadcast multicast (<i>string1</i> <i>string2</i> <i>string3</i>)
# (pound sign)	Indicates a comment specified on the same line as the configuration statement to which it applies.	rsvp { # Required for dynamic MPLS only
[] (square brackets)	Enclose a variable for which you can substitute one or more values.	community name members [<i>community-ids</i>]
Indentation and braces ({ })	Identify a level in the configuration hierarchy.	[edit] routing-options { static { route default { nexthop <i>address</i> ; retain; } } }
;(semicolon)	Identifies a leaf statement at a configuration hierarchy level.	

J-Web GUI Conventions

Table 2: Text and Syntax Conventions (*continued*)

Convention	Description	Examples
Bold text like this	Represents J-Web graphical user interface (GUI) items you click or select.	<ul style="list-style-type: none"> In the Logical Interfaces box, select All Interfaces. To cancel the configuration, click Cancel.
> (bold right angle bracket)	Separates levels in a hierarchy of J-Web selections.	In the configuration editor hierarchy, select Protocols>Ospf .

Documentation Feedback

We encourage you to provide feedback, comments, and suggestions so that we can improve the documentation. You can send your comments to techpubs-comments@juniper.net, or fill out the documentation feedback form at <https://www.juniper.net/cgi-bin/docbugreport/>. If you are using e-mail, be sure to include the following information with your comments:

- Document or topic name
- URL or page number
- Software release version (if applicable)

Requesting Technical Support

Technical product support is available through the Juniper Networks Technical Assistance Center (JTAC). If you are a customer with an active J-Care or JNASC support contract, or are covered under warranty, and need postsales technical support, you can access our tools and resources online or open a case with JTAC.

- JTAC policies—For a complete understanding of our JTAC procedures and policies, review the JTAC User Guide located at <http://www.juniper.net/us/en/local/pdf/resource-guides/7100059-en.pdf>.
- Product warranties—For product warranty information, visit <http://www.juniper.net/support/warranty/>.
- JTAC Hours of Operation —The JTAC centers have resources available 24 hours a day, 7 days a week, 365 days a year.

Self-Help Online Tools and Resources

For quick and easy problem resolution, Juniper Networks has designed an online self-service portal called the Customer Support Center (CSC) that provides you with the following features:

- Find CSC offerings: <http://www.juniper.net/customers/support/>
- Find product documentation: <http://www.juniper.net/techpubs/>

- Find solutions and answer questions using our Knowledge Base: <http://kb.juniper.net/>
- Download the latest versions of software and review release notes:
<http://www.juniper.net/customers/csc/software/>
- Search technical bulletins for relevant hardware and software notifications:
<https://www.juniper.net/alerts/>
- Join and participate in the Juniper Networks Community Forum:
<http://www.juniper.net/company/communities/>
- Open a case online in the CSC Case Management tool: <http://www.juniper.net/cm/>

To verify service entitlement by product serial number, use our Serial Number Entitlement (SNE) Tool: <https://tools.juniper.net/SerialNumberEntitlementSearch/>

Opening a Case with JTAC

You can open a case with JTAC on the Web or by telephone.

- Use the Case Management tool in the CSC at <http://www.juniper.net/cm/> .
- Call 1-888-314-JTAC (1-888-314-5822 toll-free in the USA, Canada, and Mexico).

For international or direct-dial options in countries without toll-free numbers, visit us at <http://www.juniper.net/support/requesting-support.html>

PART 1

Overview

- [Configuring System Log Messages on page 3](#)

CHAPTER 1

Configuring System Log Messages

The Junos OS generates system log messages (also called syslog messages) to record events that occur on the routing platform, including the following:

- Routine operations, such as creation of an OSPF protocol adjacency or a user login into the configuration database
- Failure and error conditions, such as failure to access a configuration file or unexpected closure of a connection to a peer process
- Emergency or critical conditions, such as routing platform power-down due to excessive temperature

Each system log message identifies the Junos OS process that generated the message and briefly describes the operation or error that occurred. This reference provides more detailed information about each system log message and, when applicable, describes possible causes of the message and action you can take to correct error conditions.



NOTE: The configuration hierarchy in this chapter applies to Junos OS processes and libraries, not to the services on a PIC such as the Adaptive Services PIC. For information about configuring system logging for PIC services, see the *Junos Services Interfaces Configuration Guide*.

For information about interpreting messages generated by services on a PIC, see “Interpreting Messages Generated in Standard Format by Services on a PIC” on page 43.

This chapter discusses the following topics:

- System Logging Configuration Statements on page 4
- Minimum and Default System Logging Configuration on page 4
- Configuring System Logging for a Single-Chassis System on page 7
- Configuring System Logging for a Routing Matrix on page 27
- Displaying and Interpreting System Log Messages on page 36
- Getting Help About System Log Messages on page 47

System Logging Configuration Statements

To configure the routing platform to log system messages, include the **syslog** statement at the **[edit system]** hierarchy level:

```
[edit system]
syslog {
  archive {
    files number;
    size size;
    (world-readable | no-world-readable);
  }
  console {
    facility severity;
  }
  file filename {
    facility severity;
    explicit-priority;
    match "regular-expression";
    structured-data {
      brief;
    }
    archive {
      files number;
      size size;
      (world-readable | no-world-readable);
    }
  }
  host (hostname | other-routing-engine | scc-master) {
    facility severity;
    explicit-priority;
    facility-override facility;
    log-prefix string;
    match "regular-expression";
  }
  source-address source-address;
  time-format (year | millisecond | year millisecond);
  user (username | *) {
    facility severity;
    match "regular-expression";
  }
}
```

Minimum and Default System Logging Configuration

For information about the minimum and default system log settings on routing platforms that run the Junos OS, see the following sections:

- Minimum System Logging Configuration on page 5
- Default System Log Settings on page 5

Minimum System Logging Configuration

To record or view system log messages, you must include the **syslog** statement at the **[edit system]** hierarchy level. Specify at least one destination for the messages, as described in Table 3 on page 5.

Table 3: Minimum Configuration Statements for System Logging

Destination	Minimum Configuration Statements
File	<pre>[edit system syslog] file filename { facility severity ; }</pre>
Terminal session of one, several, or all users	<pre>[edit system syslog] user (username *) { facility severity ; }</pre>
Routing platform console	<pre>[edit system syslog] console { facility severity ; }</pre>
Remote machine or the other Routing Engine on the routing platform	<pre>[edit system syslog] host (hostname other-routing-engine) { facility severity ; }</pre>

Default System Log Settings

Table 4 on page 5 summarizes the default system log settings that apply to all platforms that run the Junos OS, and specifies which statement to include in the configuration to override the default value.

Table 4: Default System Logging Settings

Setting	Default	Overriding Statement	Instructions
Alternative facility for message forwarded to a remote machine	For change-log : local6 For conflict-log : local5 For dfc : local1 For firewall : local3 For interactive-commands : local7 For pfe : local4	<pre>[edit system syslog] host hostname { facility-override facility; }</pre>	“Changing the Alternative Facility Name for Remote Messages” on page 14
Format of messages logged to a file	Standard Junos format, based on UNIX format	<pre>[edit system syslog] file filename { structured-data; }</pre>	“Logging Messages in Structured-Data Format” on page 11

Table 4: Default System Logging Settings (*continued*)

Setting	Default	Overriding Statement	Instructions
Maximum number of files in the archived set	10	[edit system syslog] archive { files <i>number</i> ; } file <i>filename</i> { archive { files <i>number</i> ; } }	"Configuring the Size and Number of Log Files" on page 17
Maximum size of log file	J Series: 128 kilobytes (KB) M Series, MX Series, and T Series: 1 megabyte (MB) TX Matrix: 10 MB	[edit system syslog] archive { size <i>size</i> ; } file <i>filename</i> { archive { size <i>size</i> ; } }	"Configuring the Size and Number of Log Files" on page 17
Timestamp format	Month, date, hour, minute, second For example: Aug 21 12:36:30	[edit system syslog] time-format <i>format</i> ;	"Including the Year or Millisecond in Timestamps" on page 21
Users who can read log files	root user and users with the Junos maintenance permission	[edit system syslog] archive { world-readable; } file <i>filename</i> { archive { world-readable; } }	"Configuring the Size and Number of Log Files" on page 17

In addition, the following messages are generated by default on specific platforms. To view either type of message, you must configure at least one destination for messages as described in "Minimum System Logging Configuration" on page 5.

- On J Series platforms, a message is logged when a process running in the kernel consumes 500 or more consecutive milliseconds of CPU time.

To log the message on an M Series, MX Series, or T Series platform, include the **kernel info** statement at the appropriate hierarchy level:

```
[edit system syslog]
(console | file filename | host destination | user username) {
  kernel info;
}
```

- The master Routing Engine on each T640 routing node in a routing matrix forwards to the master Routing Engine on the TX Matrix platform all messages with a severity of **info** and higher. This is equivalent to the following configuration statement included on the TX Matrix platform:

```
[edit system syslog]
host scc-master {
  any info;
}
```

Configuring System Logging for a Single-Chassis System

The Junos system logging utility is similar to the UNIX **syslogd** utility. This section describes how to configure system logging for a single-chassis system that runs the Junos OS.

System logging configuration for the Junos-FIPS software and for Juniper Networks routing platforms in a Common Criteria environment is the same as for the Junos OS. For more information, see the *Secure Configuration Guide for Common Criteria and Junos-FIPS*.

Each system log message belongs to a facility, which groups together related messages. Each message is also preassigned a *severity level*, which indicates how seriously the triggering event affects routing platform functions. You always specify the facility and severity of the messages to include in the log. For more information, see “Specifying the Facility and Severity of Messages to Include in the Log” on page 8.

You direct messages to one or more destinations by including the appropriate statement at the **[edit system syslog]** hierarchy level:

- To a named file in a local file system, by including the **file** statement. See “Logging Messages in Structured-Data Format” on page 11.
- To the terminal session of one or more specific users (or all users) when they are logged in to the routing platform, by including the **user** statement. See “Directing Messages to a User Terminal” on page 12.
- To the routing platform console, by including the **console** statement. See “Directing Messages to the Console” on page 12.
- To a remote machine that is running the **syslogd** utility or to the other Routing Engine on the routing platform, by including the **host** statement. See “Directing Messages to a Remote Destination from the Routing Matrix” on page 33.

By default, messages are logged in a standard format, which is based on a UNIX system log format; for detailed information, see “Interpreting Messages Generated in Standard Format by a Junos Process or Library” on page 42, “Interpreting Messages Generated in Standard Format by Services on a PIC” on page 43, and “Interpreting Messages Generated in Structured-Data Format” on page 37. You can alter the content and format of logged messages in the following ways:

- In Junos 8.3 and later, you can log messages to a file in structured-data format instead of the standard Junos format. Structured-data format provides more information without adding significant length, and makes it easier for automated applications to extract information from the message. For more information, see “Logging Messages in Structured-Data Format” on page 11.
- A message’s facility and severity level are together referred to as its priority. By default, the standard Junos format for messages does not include priority information. (Structured-data format includes a priority code by default.) To include priority

information in standard-format messages directed to a file or a remote destination, include the **explicit-priority** statement. For more information, see “Including Priority Information in System Log Messages” on page 18.

- By default, the standard Junos format for messages specifies the month, date, hour, minute, and second when the message was logged. You can modify the timestamp on standard-format messages to include the year, the millisecond, or both. (Structured-data format specifies the year and millisecond by default.) For more information, see “Including the Year or Millisecond in Timestamps” on page 21.
- When directing messages to a remote machine, you can specify the IP address that is reported in messages as their source. You can also configure features that make it easier to separate Junos-specific messages or messages generated on particular routing platforms. For more information, see “Directing Messages to a Remote Destination from the Routing Matrix” on page 33.
- The predefined facilities group together related messages, but you can also use regular expressions to specify more exactly which messages from a facility are logged to a file, a user terminal, or a remote destination. For more information, see “Using Regular Expressions to Refine the Set of Logged Messages” on page 22.

For a statement summary for the statements discussed in this chapter, see the *Junos System Basics Configuration Guide*.

For detailed information about configuring system logging, see the following sections:

- Specifying the Facility and Severity of Messages to Include in the Log on page 8
- Directing Messages to a Log File on page 10
- Logging Messages in Structured-Data Format on page 11
- Directing Messages to a User Terminal on page 12
- Directing Messages to the Console on page 12
- Directing Messages to a Remote Machine or the Other Routing Engine on page 12
- Configuring the Size and Number of Log Files on page 17
- Including Priority Information in System Log Messages on page 18
- Including the Year or Millisecond in Timestamps on page 21
- Using Regular Expressions to Refine the Set of Logged Messages on page 22
- Disabling Logging of a Facility on page 24
- Examples: Configuring System Logging on page 24

Specifying the Facility and Severity of Messages to Include in the Log

Each system log message belongs to a facility, which groups together messages that either are generated by the same source (such as a software process) or concern a similar condition or activity (such as authentication attempts). Each message is also preassigned a *severity level*, which indicates how seriously the triggering event affects routing platform functions.

When you configure logging for a facility and destination, you specify a severity level for each facility. Messages from the facility that are rated at that level or higher are logged to the following destination:

```
[edit system syslog]
(console | file filename | host destination | user username) {
  facility severity ;
}
```

For more information about the destinations, see “Directing Messages to a User Terminal” on page 12, “Directing Messages to a User Terminal” on page 12, “Directing Messages to the Console” on page 12.

To log messages belonging to more than one facility to a particular destination, specify each facility and associated severity as a separate statement within the set of statements for the destination.

Table 5 on page 9 lists the facilities that you can specify in configuration statements at the `[edit system syslog]` hierarchy level.

Table 5: Junos System Logging Facilities

Facility	Type of Event or Error
any	All (messages from all facilities)
authorization	Authentication and authorization attempts
change-log	Changes to the Junos configuration
conflict-log	Specified configuration is invalid on the routing platform type
daemon	Actions performed or errors encountered by system processes
dfc	Events related to dynamic flow capture
firewall	Packet filtering actions performed by a firewall filter
ftp	Actions performed or errors encountered by the FTP process
interactive-commands	Commands issued at the Junos OS command-line interface (CLI) prompt or invoked by a client application such as a Junos XML protocol or NETCONF client
kernel	Actions performed or errors encountered by the Junos kernel
pfe	Actions performed or errors encountered by the Packet Forwarding Engine

Table 5: Junos System Logging Facilities (*continued*)

Facility	Type of Event or Error
user	Actions performed or errors encountered by user-space processes

Table 6 on page 10 lists the severity levels that you can specify in configuration statements at the `[edit system syslog]` hierarchy level. The levels from **emergency** through **info** are in order from highest severity (greatest effect on functioning) to lowest.

Unlike the other severity levels, the **none** level disables logging of a facility instead of indicating how seriously a triggering event affects routing functions. For more information, see “Disabling Logging of a Facility” on page 24.

Table 6: System Log Message Severity Levels

Severity Level	Description
any	Includes all severity levels
none	Disables logging of the associated facility to a destination
emergency	System panic or other condition that causes the routing platform to stop functioning
alert	Conditions that require immediate correction, such as a corrupted system database
critical	Critical conditions, such as hard drive errors
error	Error conditions that generally have less serious consequences than errors in the emergency, alert, and critical levels
warning	Conditions that warrant monitoring
notice	Conditions that are not errors but might warrant special handling
info	Events or nonerror conditions of interest

Directing Messages to a Log File

To direct system log messages to a file in the `/var/log` directory of the local Routing Engine, include the **file** statement at the `[edit system syslog]` hierarchy level:

```
[edit system syslog]
file filename {
  facility severity;
  explicit-priority;
  match "regular-expression";
  structured-data {
    brief;
  }
  archive {
```

```

files number ;
size size;
(world-readable | no-world-readable);
}
}

```

For the list of facilities and severity levels, see “Specifying the Facility and Severity of Messages to Include in the Log” on page 8.

To prevent log files from growing too large, the Junos OS system logging utility by default writes messages to a sequence of files of a defined size. By including the **archive** statement, you can configure the number of files, their maximum size, and who can read them, either for all log files or for a certain log file. For more information, see “Configuring the Size and Number of Log Files” on page 17.

For information about the following statements, see the indicated sections:

- **explicit-priority**—See “Including Priority Information in System Log Messages” on page 18.
- **match**—See “Using Regular Expressions to Refine the Set of Logged Messages” on page 22.
- **structured-data**—See “Logging Messages in Structured-Data Format” on page 11.

Logging Messages in Structured-Data Format

You can log messages to a file in structured-data format instead of the standard Junos format. Structured-data format provides more information without adding significant length, and makes it easier for automated applications to extract information from a message.

The structured-data format complies with Internet draft draft-ietf-syslog-protocol-23, *The syslog Protocol*, which is at <http://tools.ietf.org/html/draft-ietf-syslog-protocol-23>. The draft establishes a standard message format regardless of the source or transport protocol for logged messages.

To output messages to a file in structured-data format, include the **structured-data** statement at the **[edit system syslog file *filename*]** hierarchy level:

```

[edit system syslog file filename]
  facility severity;
  structured-data {
    brief;
  }

```

The optional **brief** statement suppresses the English-language text that appears by default at the end of a message to describe the error or event. For information about the fields in a structured-data format message, see the *Junos System Log Messages Reference*.

The structured format is used for all messages logged to the file that are generated by a Junos process or software library.



NOTE: If you include either or both of the **explicit-priority** and **time-format** statements along with the **structured-data** statement, they are ignored. These statements apply to the standard Junos system log format, not to structured-data format.

**Related
Documentation**

- Single-Chassis System Logging Configuration Overview
- Examples: Configuring System Logging

Directing Messages to a User Terminal

To direct system log messages to the terminal session of one or more specific users (or all users) when they are logged in to the local Routing Engine, include the **user** statement at the **[edit system syslog]** hierarchy level:

```
[edit system syslog]
user (username | *) {
  facility severity;
  match "regular-expression";
}
```

Specify one or more Junos OS usernames, separating multiple values with spaces, or use the asterisk (*) to indicate all users who are logged in to the local Routing Engine.

For the list of facilities and severity levels, see “Specifying the Facility and Severity of Messages to Include in the Log” on page 8. For information about the **match** statement, see “Using Regular Expressions to Refine the Set of Logged Messages” on page 22.

Directing Messages to the Console

To direct system log messages to the console of the local Routing Engine, include the **console** statement at the **[edit system syslog]** hierarchy level:

```
[edit system syslog]
console {
  facility severity;
}
```

For the list of facilities and severity levels, see “Specifying the Facility and Severity of Messages to Include in the Log” on page 8.

Directing Messages to a Remote Machine or the Other Routing Engine

To direct system log messages to a remote machine or to the other Routing Engine on the routing platform, include the **host** statement at the **[edit system syslog]** hierarchy level:

```
[edit system syslog]
host (hostname | other-routing-engine) {
  facility severity;
  explicit-priority;
  facility-override facility;
  log-prefix string;
```



```

    match "regular-expression";
}
source-address source-address;

```

To direct system log messages to a remote machine, include the **host** *hostname* statement to specify the remote machine's IP version 4 (IPv4) address, IP version 6 (IPv6) address, or fully qualified hostname. The remote machine must be running the standard **syslogd** utility. We do not recommend directing messages to another Juniper Networks routing platform. In each system log message directed to the remote machine, the hostname of the local Routing Engine appears after the timestamp to indicate that it is the source for the message.

To direct system log messages to the other Routing Engine on a routing platform with two Routing Engines installed and operational, include the **host other-routing-engine** statement. The statement is not automatically reciprocal, so you must include it in each Routing Engine's configuration if you want them to direct messages to each other. In each message directed to the other Routing Engine, the string **re0** or **re1** appears after the timestamp to indicate the source for the message.

For the list of facilities and severity levels to configure under the **host** statement, see "Specifying the Facility and Severity of Messages to Include in the Log" on page 8.

To record facility and severity level information in each message, include the **explicit-priority** statement. For more information, see "Including Priority Information in System Log Messages" on page 18.

For information about the **match** statement, see "Using Regular Expressions to Refine the Set of Logged Messages" on page 22.

When directing messages to remote machines, you can include the **source-address** statement to specify the IP address of the routing platform that is reported in the messages as their source. In each **host** statement, you can also include the **facility-override** statement to assign an alternative facility and the **log-prefix** statement to add a string to each message. For more information, see the following sections:

- Specifying an Alternative Source Address for System Log Messages on page 13
- Changing the Alternative Facility Name for Remote Messages on page 14
- Examples: Assigning an Alternative Facility on page 16
- Adding a Text String to System Log Messages on page 16
- Adding a String on page 17

Specifying an Alternative Source Address for System Log Messages

To specify the routing platform that is reported in system log messages as their source when they are directed to a remote machine, include the **source-address** statement at the **[edit system syslog]** hierarchy level:

```

[edit system syslog]
source-address source-address;

```

source-address is a valid IPv4 or IPv6 address configured on one of the routing platform interfaces. The address is reported in the messages directed to all remote machines

specified in **host *hostname*** statements at the **[edit system syslog]** hierarchy level, but not in messages directed to the other Routing Engine.

Changing the Alternative Facility Name for Remote Messages

Some facilities assigned to messages logged on the local routing platform have Junos-specific names (see Table **Junos System Logging Facilities** in “Specifying the Facility and Severity of Messages to Include in the Log” on page 8. In the recommended configuration, a remote machine designated at the **[edit system syslog host *hostname*]** hierarchy level is not a Juniper Networks routing platform, so its **syslogd** utility cannot interpret the Junos-specific names. To enable the standard **syslogd** utility to handle messages from these facilities, when messages are directed to a remote machine a standard localX facility name is used instead of the Junos-specific facility name.

Table 7 on page 14 lists the default alternative facility name used for each Junos-specific facility name. For facilities that are not listed, the default alternative name is the same as the local facility name.

Table 7: Default Facilities for Messages Directed to a Remote Destination

Junos-Specific Local Facility	Default Facility When Directed to Remote Destination
change-log	local6
conflict-log	local5
dfc	local1
firewall	local3
interactive-commands	local7
pfe	local4

The **syslogd** utility on a remote machine handles all messages that belong to a facility in the same way, regardless of the source of the message (the Juniper Networks routing platform or the remote machine itself). For example, the following statements in the configuration of the routing platform called **local-router** direct messages from the **authorization** facility to the remote machine called **monitor.mycompany.com**:

```
[edit system syslog]
host monitor.mycompany.com {
  authorization info;
}
```

The default alternative facility for the local **authorization** facility is also **authorization**. If the **syslogd** utility on **monitor** is configured to write messages belonging to the **authorization** facility to the file **/var/log/auth-attempts**, the file contains both the messages generated when users log in to local-router and the messages generated when users log in to **monitor**. Although the name of the source machine appears in each system log message, the mixing of messages from multiple machines can make it more difficult to analyze the contents of the **auth-attempts** file.

To make it easier to separate the messages from each source, you can assign an alternative facility to all messages generated on **local-router** when they are directed to **monitor**. You can then configure the **syslogd** utility on **monitor** to write messages with the alternative facility to a different file from messages generated on **monitor** itself.

To change the facility used for all messages directed to a remote machine, include the **facility-override** statement at the **[edit system syslog host *hostname*]** hierarchy level:

```
[edit system syslog host hostname]
  facility severity;
  facility-override facility;
```

In general, it makes sense to specify an alternative facility that is not already in use on the remote machine, such as one of the **localX** facilities. On the remote machine, you must also configure the **syslogd** utility to handle the messages in the desired manner.

Table 8 on page 15 lists the facilities that you can specify in the facility-override statement.

Table 8: Facilities for the facility-override Statement

Facility	Description
authorization	Authentication and authorization attempts
daemon	Actions performed or errors encountered by system processes
ftp	Actions performed or errors encountered by the FTP process
kernel	Actions performed or errors encountered by the Junos kernel
local0	Local facility number 0
local1	Local facility number 1
local2	Local facility number 2
local3	Local facility number 3
local4	Local facility number 4
local5	Local facility number 5
local6	Local facility number 6
local7	Local facility number 7
user	Actions performed or errors encountered by user-space processes

We do not recommend including the **facility-override** statement at the **[edit system syslog host *other-routing-engine*]** hierarchy level. It is not necessary to use alternative facility names when directing messages to the other Routing Engine, because its Junos system logging utility can interpret the Junos-specific names.

Examples: Assigning an Alternative Facility

Log all messages generated on the local routing platform at the error level or higher to the **local0** facility on the remote machine called **monitor.mycompany.com**:

```
[edit system syslog]
host monitor.mycompany.com {
  any error;
  facility-override local0;
}
```

Configure routing platforms located in California and routing platforms located in New York to send messages to a single remote machine called **central-logger.mycompany.com**. The messages from California are assigned alternative facility **local0** and the messages from New York are assigned to alternative facility **local2**.

- Configure California routing platforms to aggregate messages in the **local0** facility:

```
[edit system syslog]
host central-logger.mycompany.com {
  change-log info;
  facility-override local0;
}
```

- Configure New York routing platforms to aggregate messages in the **local2** facility:

```
[edit system syslog]
host central-logger.mycompany.com {
  change-log info;
  facility-override local2;
}
```

On **central-logger**, you can then configure the system logging utility to write messages from the **local0** facility to the file **california-config** and the messages from the **local2** facility to the file **new-york-config**.

Related Documentation

- Junos OS System Log Alternate Facilities for Remote Logging

Adding a Text String to System Log Messages

To add a text string to every system log message directed to a remote machine or to the other Routing Engine, include the **log-prefix** statement at the **[edit system syslog host]** hierarchy level:

```
[edit system syslog host (hostname | other-routing-engine)]
  facility severity;
  log-prefix string;
```

The string can contain any alphanumeric or special character except the equal sign (=) and the colon (:). It also cannot include the space character; do not enclose the string in quotation marks (" ") in an attempt to include spaces in it.

The Junos system logging utility automatically appends a colon and a space to the specified string. The string is inserted after the identifier for the Routing Engine that generated the message.

Adding a String

Add the string M120 to all messages to indicate that the router is an M120 router, and direct the messages to the remote machine `hardware-logger.mycompany.com`:

```
[edit system syslog]
host hardware-logger.mycompany.com {
  any info;
  log-prefix M120;
}
```

When these configuration statements are included on an M120 router called `origin1`, a message in the system log on `hardware-logger.mycompany.com` looks like the following:

```
Mar 9 17:33:23 origin1 M120: mgd[477]: UI_CMDLINE_READ_LINE: user 'root', command 'run
show version'
```

Configuring the Size and Number of Log Files

To prevent log files from growing too large, the Junos system logging utility by default writes messages to a sequence of files of a defined size. The files in the sequence are referred to as *archive* files to distinguish them from the *active* file to which messages are currently being written. The default maximum size depends on the platform type:

- 128 kilobytes (KB) for J Series Services Routers
- 1 megabyte (MB) for M Series, MX Series, and T Series routing platforms

When an active log file called *logfile* reaches the maximum size, the logging utility closes the file, compresses it, and names the compressed archive file *logfile.0.gz*. The logging utility then opens and writes to a new active file called *logfile*. When the new *logfile* reaches the configured maximum size, *logfile.0.gz* is renamed *logfile.1.gz*, and the new *logfile* is closed, compressed, and renamed *logfile.0.gz*. By default, the logging utility creates up to 10 archive files in this manner. When the maximum number of archive files is reached, each time the active file reaches the maximum size the contents of the oldest archive file are lost (overwritten by the next oldest file). The logging utility by default also limits the users who can read log files to the root user and users who have the Junos **maintenance** permission.

You can include the **archive** statement to change the maximum size of each file, how many archive files are created, and who can read log files. To configure values that apply to all log files, include the **archive** statement at the **[edit system syslog]** hierarchy level:

```
[edit system syslog]
archive {
  files number;
  size size;
  (world-readable | no-world-readable);
}
```

To configure values that apply to a particular log file, include the archive statement at the **[edit system syslog file filename]** hierarchy level:

```
[edit system syslog file filename]
facility severity;
```

```
archive {  
  files number;  
  size size;  
  (world-readable | no-world-readable);  
}
```

files *number* specifies the number of files to create before the oldest file is overwritten. The value can be from 1 through 1000.

size *size* specifies the maximum size of each file. The value can be from 64 KB (**64k**) through 1 gigabyte (**1g**); to represent megabytes, use the letter m after the integer. There is no space between the digits and the k, m, or g units letter.

world-readable enables all users to read log files. To restore the default permissions, include the **no-world-readable** statement.

Including Priority Information in System Log Messages

A message's facility and severity level are together referred to as its priority. By default, messages logged in the standard Junos format do not include information about priority. To include priority information in standard-format messages directed to a file, include the **explicit-priority** statement at the `[edit system syslog file filename]` hierarchy level:

```
[edit system syslog file filename]  
  facility severity;  
  explicit-priority;
```



NOTE: Messages logged in structured-data format include priority information by default (structured-data format is available in Junos OS Release 8.3 and later and for file destinations only). If you include the **structured-data** statement at the `[edit system syslog file filename]` hierarchy level along with the **explicit-priority** statement, the **explicit-priority** statement is ignored and messages are logged in structured-data format.

For information about the structured-data statement, see “Logging Messages in Structured-Data Format” on page 11. For information about the contents of a structured-data message, see “Displaying a Log File from a Single-Chassis System” on page 36.

To include priority information in messages directed to a remote machine or the other Routing Engine, include the **explicit-priority** statement at the `[edit system syslog host (hostname | other-routing-engine)]` hierarchy level:

```
[edit system syslog host (hostname | other-routing-engine)]  
  facility severity;  
  explicit-priority;
```

The priority recorded in a message always indicates the original, local facility name. If the **facility-override** statement is included for messages directed to a remote destination, the Junos system logging utility still uses the alternative facility for the messages themselves when directing them to the remote destination. For more information about

alternative facilities, see “Changing the Alternative Facility Name for Remote Messages” on page 14.

When the **explicit-priority** statement is included, the Junos logging utility prepends codes for the facility name and severity level to the message tag name, if the message has one:

FACILITY-severity[-TAG]

(The tag is a unique identifier assigned to some Junos system log messages; for more information, see “Interpreting Messages Generated in Structured-Data Format” on page 37, “Interpreting Messages Generated in Standard Format by Services on a PIC” on page 43, “Interpreting Messages Generated in Standard Format by a Junos Process or Library” on page 42, and “Displaying and Interpreting System Log Message Descriptions” on page 48.)

Table 9 on page 19 lists the facility codes that can appear in system log messages and maps them to facility names.



NOTE: If the second column in Table 9 on page 19 does not include the Junos facility name for a code, the facility cannot be included in a statement at the [edit system syslog] hierarchy level. The Junos OS might use the facilities in Table 9 on page 19— and others that are not listed—when reporting on internal operations

Table 9: Facility Codes Reported in Priority Information

Code	Junos Facility Name	Type of Event or Error
AUTH	authorization	Authentication and authorization attempts
AUTHPRIV		Authentication and authorization attempts that can be viewed by superusers only
CHANGE	change-log	Changes to the Junos configuration
CONFLICT	conflict-log	Specified configuration is invalid on the routing platform type
CONSOLE		Messages written to /dev/console by the kernel console output driver
CRON		Actions performed or errors encountered by the cron process
DAEMON	daemon	Actions performed or errors encountered by system processes

Table 9: Facility Codes Reported in Priority Information (*continued*)

Code	Junos Facility Name	Type of Event or Error
DFC	dfc	Actions performed or errors encountered by the dynamic flow capture process
FIREWALL	firewall	Packet filtering actions performed by a firewall filter
FTP	ftp	Actions performed or errors encountered by the FTP process
INTERACT	interactive-commands	Commands issued at the Junos OS CLI prompt or invoked by a client application such as a Junos XML protocol or NETCONF client
KERN	kernel	Actions performed or errors encountered by the Junos kernel
NTP		Actions performed or errors encountered by the Network Time Protocol (NTP) process
PFE	pfe	Actions performed or errors encountered by the Packet Forwarding Engine
SYSLOG		Actions performed or errors encountered by the Junos system logging utility
USER	user	Actions performed or errors encountered by user-space processes

Table 10 on page 20 lists the numerical severity codes that can appear in system log messages and maps them to severity levels.

Table 10: Numerical Codes for Severity Levels Reported in Priority Information

Numerical Code	Severity Level	Description
0	emergency	System panic or other condition that causes the routing platform to stop functioning
1	alert	Conditions that require immediate correction, such as a corrupted system database

Table 10: Numerical Codes for Severity Levels Reported in Priority Information (*continued*)

Numerical Code	Severity Level	Description
2	critical	Critical conditions, such as hard drive errors
3	error	Error conditions that generally have less serious consequences than errors in the emergency, alert, and critical levels
4	warning	Conditions that warrant monitoring
5	notice	Conditions that are not errors but might warrant special handling
6	info	Events or nonerror conditions of interest
7	debug	Software debugging messages (these appear only if a technical support representative has instructed you to configure this severity level)

In the following example, the **CHASSISD_PARSE_COMPLETE** message belongs to the **daemon** facility and is assigned severity **info (6)**:

```
Aug 21 12:36:30 router1 chassisd[522]:
```

```
%DAEMON-6-CHASSISD_PARSE_COMPLETE: Using new configuration
```

When the **explicit-priority** statement is not included, the priority does not appear in the message:

```
Aug 21 12:36:30 router1 chassisd[522]: CHASSISD_PARSE_COMPLETE: Using new configuration
```

For more information about message formatting, see “Displaying and Interpreting System Log Message Descriptions” on page 48.

Including the Year or Millisecond in Timestamps

By default, the timestamp recorded in a standard-format system log message specifies the month, date, hour, minute, and second when the message was logged, as in the following example:

```
Aug 21 12:36:30
```

To include the year, the millisecond, or both in the timestamp, include the **time-format** statement at the **[edit system syslog]** hierarchy level:

```
edit system syslog
time-format (year | millisecond | year millisecond);
```

The modified timestamp is used in messages directed to each destination configured by a **file**, **console**, or **user** statement at the **[edit system syslog]** hierarchy level, but not to destinations configured by a **host** statement.

The following example illustrates the format for a timestamp that includes both the millisecond (401) and the year (2006):

```
Aug 21 12:36:30.401 2006
```



NOTE: Messages logged in structured-data format (available in Junos OS Release 8.3 and later for file destinations) include the year and millisecond by default. If you include the **structured-data** statement at the **[edit system syslog file filename]** hierarchy level along with the **time-format** statement, the **time-format** statement is ignored and messages are logged in structured-data format.

For information about the **structured-data** statement, see “Logging Messages in Structured-Data Format” on page 11. For information about the information in a structured-data message, see “Displaying a Log File from a Single-Chassis System” on page 36.

Using Regular Expressions to Refine the Set of Logged Messages

The predefined facilities group together related messages, but you can also use regular expression matching to specify more exactly which messages from a facility are logged to a file, a user terminal, or a remote destination.

To specify the text string that must (or must not) appear in a message for the message to be logged to a destination, include the **match** statement and specify the regular expression which the text string must match:

```
match "regular-expression";
```

You can include this statement at the following hierarchy levels:

- **[edit system syslog file filename]** (for a file)
- **[edit system syslog user (username | *)]** (for a specific user session or for all user sessions on a terminal)
- **[edit system syslog host (hostname | other-routing-engine)]** (for a remote destination)

In specifying the regular expression, use the notation defined in POSIX Standard 1003.2 for extended (modern) UNIX regular expressions. Explaining regular expression syntax is beyond the scope of this document, but POSIX standards are available from the Institute of Electrical and Electronics Engineers (IEEE, <http://www.ieee.org>).

Table 11 on page 23 specifies which character or characters are matched by some of the regular expression operators that you can use in the match statement. In the descriptions, the term **term** refers to either a single alphanumeric character or a set of characters enclosed in square brackets, parentheses, or braces.



NOTE: The **match** statement is not case-sensitive.

Table 11: Regular Expression Operators for the match Statement

Operator	Matches
. (period)	One instance of any character except the space.
* (asterisk)	Zero or more instances of the immediately preceding term.
+ (plus sign)	One or more instances of the immediately preceding term.
? (question mark)	Zero or one instance of the immediately preceding term.
(pipe)	One of the terms that appears on either side of the pipe operator.
! (exclamation point)	Any string except the one specified by the expression, when the exclamation point appears at the start of the expression. Use of the exclamation point is Junos OS–specific.
^ (caret)	Start of a line, when the caret appears outside square brackets. One instance of any character that does not follow it within square brackets, when the caret is the first character inside square brackets.
\$ (dollar sign)	End of a line.
[] (paired square brackets)	One instance of one of the enclosed alphanumeric characters. To indicate a range of characters, use a hyphen (-) to separate the beginning and ending characters of the range. For example, [a-z0-9] matches any letter or number.
() (paired parentheses)	One instance of the evaluated value of the enclosed term. Parentheses are used to indicate the order of evaluation in the regular expression.

Using Regular Expressions

Filter messages that belong to the **interactive-commands** facility, directing those that include the string **configure** to the terminal of the root user:

```
[edit system syslog]
user root {
  interactive-commands any;
  match ".*configure.*";
}
```

Messages like the following appear on the **root** user's terminal when a user issues a **configure** command to enter configuration mode:

```
timestamp router-name mgd[PID]: UI_CMDLINE_READ_LINE: User 'user', command  
'configure private'
```

Filter messages that belong to the **daemon** facility and have a severity of **error** or higher, directing them to the file **/var/log/process-errors**. Omit messages generated by the SNMP process (**snmpd**), instead directing them to the file **/var/log/snmpd-errors**:

```
[edit system syslog]  
file process-errors {  
  daemon error;  
  match "!(.*snmpd.*)";  
}  
file snmpd-errors {  
  daemon error;  
  match ".*snmpd.*";  
}
```

Related Documentation

- [Single-Chassis System Logging Configuration Overview](#)
- [Overview of Single-Chassis System Logging Configuration](#)
- [Examples: Configuring System Logging](#)
- [Examples: Configuring System Logging](#)

Disabling Logging of a Facility

To disable the logging of messages that belong to a particular facility, include the **facility none** statement in the configuration. This statement is useful when, for example, you want to log messages that have the same severity level and belong to all but a few facilities. Instead of including a statement for each facility you want to log, you can include the **any severity** statement and then a **facility none** statement for each facility that you do not want to log. For example, the following logs all messages at the error level or higher to the console, except for messages from the **daemon** and **kernel** facilities. Messages from those facilities are logged to the file **/var/log/internals** instead:

```
[edit system syslog]  
console {  
  any error;  
  daemon none;  
  kernel none;  
}  
file internals {  
  daemon info;  
  kernel info;  
}
```

Examples: Configuring System Logging

Log messages about all commands entered by users at the CLI prompt or invoked by client applications such as Junos XML protocol or NETCONF clients, and all authentication or authorization attempts, both to the file **cli-commands** and to the terminal of any user who is logged in:

```
[edit system]
syslog {
  file cli-commands {
    interactive-commands info;
    authorization info;
  }
  user * {
    interactive-commands info;
    authorization info;
  }
}
```

Log all changes in the state of alarms to the file `/var/log/alarms`:

```
[edit system]
syslog {
  file alarms {
    kernel warning;
  }
}
```

Configure the handling of messages of various types, as described in the comments. Information is logged to two files, to the terminal of user **alex**, to a remote machine, and to the console:

```
[edit system]
syslog {
  /* write all security-related messages to file /var/log/security */
  file security {
    authorization info;
    interactive-commands info;
  }
  /* write messages about potential problems to file /var/log/messages: */
  /* messages from "authorization" facility at level "notice" and above, */
  /* messages from all other facilities at level "warning" and above */
  file messages {
    authorization notice;
    any warning;
  }
  /* write all messages at level "critical" and above to terminal of user "alex" if */
  /* that user is logged in */
  user alex {
    any critical;
  }
  /* write all messages from the "daemon" facility at level "info" and above, and */
  /* messages from all other facilities at level "warning" and above, to the */
  /* machine monitor.mycompany.com */
  host monitor.mycompany.com {
    daemon info;
    any warning;
  }
  /* write all messages at level "error" and above to the system console */
  console {
    any error;
  }
}
```

Configure the handling of messages generated when users issue Junos OS CLI commands, by specifying the **interactive-commands** facility at the following severity levels:

- **info**—Logs a message when users issue any command at the CLI operational or configuration mode prompt. The example writes the messages to the file `/var/log/user-actions`.
- **notice**—Logs a message when users issue the configuration mode commands **rollback** and **commit**. The example writes the messages to the terminal of user **philip**.
- **warning**—Logs a message when users issue a command that restarts a software process. The example writes the messages to the console.

```
[edit system]
syslog {
  file user-actions {
    interactive-commands info;
  }
  user philip {
    interactive-commands notice;
  }
  console {
    interactive-commands warning;
  }
}
```

Configuring System Logging for a Routing Matrix

This section explains how to configure system logging for the T640 Internet routing nodes and TX Matrix platform in a routing matrix. It assumes you are familiar with system logging for single-chassis systems. For more information about routing matrixes, see the *Junos System Basics Configuration Guide* and the *TX Matrix Platform Hardware Guide*.

To configure system logging for all platforms in a routing matrix, include the **syslog** statement at the **[edit system]** hierarchy level on the TX Matrix platform. The **syslog** statement applies to every platform in the routing matrix.

```
[edit system]
syslog {
  archive {
    files number;
    size size;
    (world-readable | no-world-readable);
  }
  console {
    facility severity;
  }
  file filename {
    facility severity;
    explicit-priority;
    match "regular-expression";
    structured-data {
      brief;
    }
    archive {
      files number;
      size size;
      (world-readable | no-world-readable);
    }
  }
  host (hostname | other-routing-engine | scc-master) {
    facility severity;
    explicit-priority;
    facility-override facility;
    log-prefix string;
    match "regular-expression";
  }
  source-address source-address;
  time-format (year | millisecond | year millisecond);
  user (username | *) {
    facility severity;
    match "regular-expression";
  }
}
```

When included in the configuration on the TX Matrix platform, the following configuration statements have the same effect as on a single-chassis system, except that they apply to every platform in the routing matrix:

- **archive**—Sets the size and number of log files archived on each platform in the routing matrix. See “Configuring the Size and Number of Log Files” on page 17.
- **console**—Directs the specified messages to the console of each platform in the routing matrix. See “Directing Messages to the Console” on page 12.
- **file**—Directs the specified messages to a file of the same name on each platform in the routing matrix. See “Logging Messages in Structured-Data Format” on page 11.
- **match**—Limits the set of messages logged to a destination to those that contain (or do not contain) a text string matching a regular expression. See “Using Regular Expressions to Refine the Set of Logged Messages” on page 22.

The separate **match** statement at the `[edit system syslog host scc-master]` hierarchy level applies to messages forwarded from the T640 routing nodes to the TX Matrix platform.

- **source-address**—Sets the IP address of the routing platform to report in system log messages as the message source, when the messages are directed to the remote machines specified in all **host hostname** statements at the `[edit system syslog]` hierarchy level, for each platform in the routing matrix. The address is not reported in messages directed to the other Routing Engine on each platform or forwarded to the TX Matrix platform by the T640 routing nodes. See “Specifying an Alternative Source Address for System Log Messages” on page 13.
- **structured-data**—Writes messages to a file in structured-data format. See “Logging Messages in Structured-Data Format” on page 11.
- **time-format**—Adds the millisecond, year, or both to the timestamp in each standard-format message. See “Including the Year or Millisecond in Timestamps” on page 21.
- **user**—Directs the specified messages to the terminal session of one or more specified users on each platform in the routing matrix that they are logged in to. See “Directing Messages to a User Terminal” on page 12.

The effect of the other statements differs somewhat for a routing matrix than for a single-chassis system. For more information, see the following sections:

- Configuring Message Forwarding in the Routing Matrix on page 28
- Configuring Optional Features for Forwarded Messages on page 32
- Directing Messages to a Remote Destination from the Routing Matrix on page 33
- Configuring System Logging Differently on Each Platform on page 34

Configuring Message Forwarding in the Routing Matrix

By default, the master Routing Engine on each T640 routing node forwards to the master Routing Engine on the TX Matrix platform all messages from all facilities with severity

info and higher. To change the facility, the severity level, or both, include the **host scc-master** statement at the **[edit system syslog]** hierarchy level on the TX Matrix platform:

```
[edit system syslog]
host scc-master {
  facility severity;
}
```

To disable message forwarding, set the facility to **any** and the severity level to **none**:

```
[edit system syslog]
host scc-master {
  any none;
}
```

In either case, the setting applies to all T640 routing nodes in the routing matrix.

To capture the messages forwarded by the T640 routing nodes (as well as messages generated on the TX Matrix platform itself), you must also configure system logging on the TX Matrix platform. Direct the messages to one or more destinations by including the appropriate statements at the **[edit system syslog]** hierarchy level on the TX Matrix platform:

- To a file, as described in [Directing Messages to a Log File](#).
- To the terminal session of one or more specific users (or all users), as described in [“Directing Messages to a User Terminal”](#) on page 12.
- To the console, as described in [“Directing Messages to the Console”](#) on page 12.
- To a remote machine that is running the **syslogd** utility or to the other Routing Engine. For more information, see [“Directing Messages to a Remote Destination from the Routing Matrix”](#) on page 33.

As previously noted, the configuration statements included on the TX Matrix platform also configure the same destinations on each T640 routing node.

When specifying the severity level for local messages (at the **[edit system syslog (file | host | console | user)]** hierarchy level) and forwarded messages (at the **[edit system syslog host scc-master]** hierarchy level), you can set the same severity level for both, set a lower severity level for local messages, or set a higher severity level for local messages. The following examples describe the consequence of each configuration. (For simplicity, the examples use the **any** facility in every case. You can also specify different severities for different facilities, with more complex consequences.)

- [Messages Logged When Local and Forwarded Severity Level Are the Same](#) on page 29
- [Messages Logged When Local Severity Level Is Lower](#) on page 30
- [Messages Logged When Local Severity Level Is Higher](#) on page 31

Messages Logged When Local and Forwarded Severity Level Are the Same

When the severity level is the same for local and forwarded messages, the log on the TX Matrix platform contains all messages from the logs on the T640 routing nodes. For example, you can specify severity **info** for the **/var/log/messages** file, which is the default severity level for messages forwarded by T640 routing nodes:

```
[edit system syslog]
file messages {
  any info;
}
```

Table 12 on page 30 specifies which messages are included in the logs on the T640 routing nodes and the TX Matrix platform

Table 12: Example: Local and Forwarded Severity Level Are Both info

Log Location	Source of Messages	Lowest Severity Included
T640 routing node	Local	info
TX Matrix platform	Local	info
	Forwarded from T640 routing nodes	info

Messages Logged When Local Severity Level Is Lower

When the severity level is lower for local messages than for forwarded messages, the log on the TX Matrix platform includes fewer forwarded messages than when the severities are the same. Locally generated messages are still logged at the lower severity level, so their number in each log is the same as when the severities are the same.

For example, you can specify severity **notice** for the `/var/log/messages` file and severity **critical** for forwarded messages

```
[edit system syslog]
file messages {
  any notice;
}
host scc-master {
  any critical;
}
```

Table 13 on page 31 specifies which messages are included in the logs on the T640 routing nodes and the TX Matrix platform. The T640 routing nodes forward only those messages with severity **critical** and higher, so the log on the TX Matrix platform does not include the messages with severity **error**, **warning**, or **notice** that the T640 routing nodes log locally:

Table 13: Example: Local Severity Is notice, Forwarded Severity Is critical

Log Location	Source of Messages	Lowest Severity Included
T640 routing node	Local	notice
TX Matrix platform	Local	notice
	Forwarded from T640 routing nodes	critical

Messages Logged When Local Severity Level Is Higher

When the severity level is higher for local messages than for forwarded messages, the log on the TX Matrix platform includes fewer forwarded messages than when the severities are the same, and all local logs contain fewer messages overall.

For example, you can specify severity **critical** for the `/var/log/messages` file and severity **notice** for forwarded messages:

```
[edit system syslog]
file messages {
  any critical;
}
host scc-master {
  any notice;
}
```

Table 14 on page 31 specifies which messages are included in the logs on the T640 routing nodes and the TX Matrix platform. Although the T640 routing nodes forward messages with severity **notice** and higher, the TX Matrix platform discards any of those messages with severity lower than **critical** (does not log forwarded messages with severity **error**, **warning**, or **notice**). None of the logs include messages with severity **error** or lower.

Table 14: Example: Local Severity Is critical, Forwarded Severity Is notice

Log Location	Source of Messages	Lowest Severity Included
T640 routing node	Local	critical
TX Matrix platform	Local	critical
	Forwarded from T640 routing nodes	critical

We do not recommend this type of configuration, because it wastes bandwidth for the routing nodes to forward messages that are not recorded in the log on the TX Matrix platform.

Configuring Optional Features for Forwarded Messages

To configure additional optional features when specifying how the T640 routing nodes forward messages to the TX Matrix platform, include statements at the **[edit system syslog host scc-master]** hierarchy level. To include priority information (facility and severity level) in each forwarded message, include the **explicit-priority** statement. To insert a text string in each forwarded message, include the **log-prefix** statement. To use regular expression matching to specify more exactly which messages from a facility are forwarded, include the **match** statement.

```
[edit system syslog host scc-master]
  facility severity;
  explicit-priority;
  log-prefix string;
  match "regular-expression";
}
```



NOTE: You can also include the **facility-override** statement at the **[edit system syslog host scc-master]** hierarchy level, but we do not recommend doing so. It is not necessary to use alternative facilities for messages forwarded to the TX Matrix platform, because it runs the Junos system logging utility and can interpret the Junos-specific facilities. For more information about alternative facilities, see “Changing the Alternative Facility Name for Remote Messages” on page 14.

1. Including Priority Information in Forwarded Messages on page 32
2. Adding a Text String to Forwarded Messages on page 33
3. Using Regular Expressions to Refine the Set of Forwarded Messages on page 33

Including Priority Information in Forwarded Messages

When you include the **explicit-priority** statement at the **[edit system syslog host scc-master]** hierarchy level, messages forwarded to the TX Matrix platform include priority information. For the information to appear in a log file on the TX Matrix platform, you must also include the **explicit-priority** statement at the **[edit system syslog file filename]** hierarchy level for the file on the TX Matrix platform. As a consequence, the log file with the same name on each platform in the routing matrix also includes priority information for locally generated messages.

To include priority information in messages directed to a remote machine from all platforms in the routing matrix, also include the **explicit-priority** statement at the **[edit system syslog host hostname]** hierarchy level for the remote machine. For more information, see “Directing Messages to a Remote Destination from the Routing Matrix” on page 33.

In the following example, the **/var/log/messages** file on all platforms includes priority information for messages with severity **notice** and higher from all facilities. The log on the TX Matrix platform also includes messages with those characteristics forwarded from the T640 routing nodes.

```
[edit system syslog]
host scc-master {
  any notice;
  explicit-priority;
}
file messages {
  any notice;
  explicit-priority;
}
```

Adding a Text String to Forwarded Messages

When you include the **log-prefix** statement at the `[edit system syslog host scc-master]` hierarchy level, the string that you define appears in every message forwarded to the TX Matrix platform. For more information, see “Adding a Text String to System Log Messages” on page 16.

Using Regular Expressions to Refine the Set of Forwarded Messages

When you include the **match** statement at the `[edit system syslog host scc-master]` hierarchy level, the regular expression that you specify controls which messages from the T640 routing nodes are forwarded to the TX Matrix platform. The regular expression is not applied to messages from the T640 routing nodes that are directed to destinations other than the TX Matrix platform. For more information about regular expression matching, see “Using Regular Expressions to Refine the Set of Logged Messages” on page 22.

Directing Messages to a Remote Destination from the Routing Matrix

You can configure a routing matrix to direct system logging messages to a remote machine or the other Routing Engine on each routing platform, just as on a single-chassis system. Include the host statement at the `[edit system syslog]` hierarchy level on the TX Matrix platform:

```
[edit system syslog]
host (hostname | other-routing-engine) {
  facility severity ;
  explicit-priority;
  facility-override facility;
  log-prefix string;
  match "regular-expression";
}
source-address source-address;
```

The TX Matrix platform directs messages to a remote machine or the other Routing Engine in the same way as a single-chassis system, and the optional statements (**explicit-priority**, **facility-override**, **log-prefix**, **match**, and **source-address**) also have the same effect as on a single-chassis system.

For the TX Matrix platform to include priority information when it directs messages that originated on a T640 routing node to the remote destination, you must also include the **explicit-priority** statement at the `[edit system syslog host scc-master]` hierarchy level.

The **other-routing-engine** statement does not interact with message forwarding from the T640 routing nodes to the TX Matrix platform. For example, if you include the statement

in the configuration for the Routing Engine in slot 0 (**re0**), the **re0** Routing Engine on each T640 routing node sends messages to the **re1** Routing Engine on its platform only. It does not also send messages directly to the **re1** Routing Engine on the TX Matrix platform.

Because the configuration on the TX Matrix platform applies to the T640 routing nodes, any T640 routing node that has interfaces for direct access to the Internet also directs messages to the remote machine which has the following consequences:

- If the T640 routing nodes are configured to forward messages to the TX Matrix platform (as in the default configuration), the remote machine receives two copies of some messages: one directly from the T640 routing node and the other from the TX Matrix platform. Which messages are duplicated depends on whether the severities are the same for local logging and for forwarded messages. For more information, see “Messages Logged When Local Severity Level Is Lower” on page 30, “Messages Logged When Local Severity Level Is Higher” on page 31, and “Messages Logged When Local and Forwarded Severity Level Are the Same” on page 29.
- If the **source-address** statement is configured at the [**edit system syslog**] hierarchy level, all platforms in the routing matrix report the same source routing platform in messages directed to the remote machine. This is appropriate, because the routing matrix functions as a single routing platform.
- If the **log-prefix** statement is included, the messages from all platforms in the routing matrix include the same text string. You cannot use the string to distinguish between the platforms in the routing matrix.

Configuring System Logging Differently on Each Platform

We recommend that all platforms in a routing matrix use the same configuration, which implies that you include system logging configuration statements on the TX Matrix platform only. In rare circumstances, however, you might choose to log different messages on different platforms. For example, if one platform in the routing matrix is experiencing problems with authentication, a Juniper Networks support representative might instruct you to log messages from the **authorization** facility on that platform.

To configure platforms separately, include configuration statements in the appropriate groups at the [**edit groups**] hierarchy level on the TX Matrix platform:

- To configure settings that apply to the TX Matrix platform but not the T640 routing nodes, include them in the **re0** and **re1** configuration groups.
- To configure settings that apply to particular T640 routing nodes, include them in the **lccn-re0** and **lccn-re1** configuration groups, where n is the line-card chassis (LCC) index number of the routing node.

When you use configuration groups, do not issue CLI configuration-mode commands to change the statements at the [**edit system syslog**] hierarchy level on the TX Matrix platform. If you do, the resulting statements overwrite the statements defined in configuration groups and apply to the T640 routing nodes also. (We further recommend that you do not issue CLI configuration mode commands on the T640 routing nodes at any time.)

For more information about the configuration groups for a routing matrix, see the chapter about configuration groups in the *Junos OS CLI User Guide*.

The following example shows how to configure the `/var/log/messages` files on three platforms to include different sets of messages:

- On the TX Matrix platform, local messages with severity `info` and higher from all facilities. The file does not include messages from the T640 routing nodes, because the `host scc-master` statement disables message forwarding.
- On the T640 routing node designated LCC0, messages from the `authorization` facility with severity `info` and higher.
- On the T640 routing node designated LCC1, messages with severity `notice` from all facilities.

```
[edit groups]
re0 {
  system {
    syslog {
      file messages {
        any info;
      }
    }
    host scc-master {
      any none;
    }
  }
}
re1 {
  ... same statements as for re0 ...
}
lcc0-re0 {
  system {
    syslog {
      file messages {
        authorization info;
      }
    }
  }
}
lcc0-re1 {
  ... same statements as for lcc0-re0 ...
}
lcc1-re0 {
  system {
    syslog {
      file messages {
        any notice;
      }
    }
  }
}
lcc0-re1 {
```

```
... same statements as for lcc1-re0 ...  
}
```

Displaying and Interpreting System Log Messages

This section explains how to display a log file and interpret the contents of system log messages:

For more information about the commands discussed in this section, see the *Junos System Basics and Services Command Reference*.

- Displaying a Log File from a Single-Chassis System on page 36
- Displaying a Log File from a Routing Matrix on page 36
- Interpreting System Log Messages on page 37
- Format of the message-source Field on page 44
- Examples: Displaying a Log File on page 47

Displaying a Log File from a Single-Chassis System

To display a log file stored on a single-chassis system, enter Junos OS CLI operational mode and issue either of the following commands:

```
user@host> show loglog-filename  
user@host> file show log-file-pathname
```

By default, the commands display the file stored on the local Routing Engine. To display the file stored on a particular Routing Engine, prefix the file- or pathname with the string **re0** or **re1** and a colon. The following examples both display the `/var/log/messages` file stored on the Routing Engine in slot 1:

```
user@host> show log re1:messages  
user@host> file show re1:/var/log/messages
```

For information about the fields in a log message, see “Interpreting Messages Generated in Standard Format by a Junos Process or Library” on page 42, “Interpreting Messages Generated in Standard Format by Services on a PIC” on page 43, and “Interpreting Messages Generated in Structured-Data Format” on page 37. For examples, see “Examples: Displaying a Log File” on page 47.

Displaying a Log File from a Routing Matrix

One way to display a log file stored on the local Routing Engine of any of the individual platforms in a routing matrix (T640 routing nodes or TX Matrix platform) is to log in to a Routing Engine on the platform, enter Junos OS CLI operational mode, and issue the **show log** or **file show** command described in “Displaying a Log File from a Single-Chassis System” on page 36.

To display a log file stored on a T640 routing node during a terminal session on the TX Matrix platform, issue the **show log** or **file show** command and add a prefix that specifies the T640 routing node’s LCC index number as **lccn**, followed by a colon. The index can be from 0 (zero) through 3:

```
user@host> show log lccn:log-filename
```



```
user@host> file show lccn:log-file-pathname
```

By default, the **show log** and **file show** commands display the specified log file stored on the master Routing Engine on the T640 routing node. To display the log from a particular Routing Engine, prefix the file- or pathname with the string **lccn-master**, **lccn-re0**, or **lccn-re1**, followed by a colon. The following examples all display the **/var/log/messages** file stored on the master Routing Engine (in slot 0) on routing node LCC2:

```
user@host> show log lcc2:messages
user@host> show log lcc2-master:messages
user@host> show log lcc2-re0:messages
user@host> file show lcc2:/var/log/messages
```

If the T640 routing nodes are forwarding messages to the TX Matrix platform (as in the default configuration), another way to view messages generated on a T640 routing node during a terminal session on the TX Matrix platform is simply to display a local log file. However, the messages are intermixed with messages from other T640 routing nodes and the TX Matrix platform itself. For more information about message forwarding, see “Messages Logged When Local Severity Level Is Lower” on page 30, “Messages Logged When Local Severity Level Is Higher” on page 31, and “Messages Logged When Local and Forwarded Severity Level Are the Same” on page 29.

For information about the fields in a log message, see “Interpreting Messages Generated in Structured-Data Format” on page 37, “Interpreting Messages Generated in Standard Format by Services on a PIC” on page 43, and “Interpreting Messages Generated in Standard Format by a Junos Process or Library” on page 42. For examples, see “Examples: Displaying a Log File” on page 47.

Interpreting System Log Messages

The fields in a message written to the system log depend on whether the message was generated by a Junos process or subroutine library, or by services on a PIC, and whether it is in standard format or structured-data format. For more information, see the following sections:

- Interpreting Messages Generated in Structured-Data Format on page 37
- Interpreting Messages Generated in Standard Format by a Junos Process or Library on page 42
- Interpreting Messages Generated in Standard Format by Services on a PIC on page 43

Interpreting Messages Generated in Structured-Data Format

Beginning in Junos OS Release 8.3, when the **structured-data** statement is included in the configuration for a log file, Junos processes and software libraries write messages to the file in structured-data format instead of the standard Junos format. For information about the **structured-data** statement, see “Logging Messages in Structured-Data Format” on page 11.

Structured-format makes it easier for automated applications to extract information from the message. In particular, the standardized format for reporting the value of variables (elements in the English-language message that vary depending on the circumstances that triggered the message) makes it easy for an application to extract

those values. In standard format, the variables are interspersed in the message text and not identified as variables.

The structured-data format for a message includes the following fields (which appear here on two lines only for legibility):

```
<priority code>version timestamp hostname process processID TAG [junos@2636.platform
variable-value-pairs] message-text
```

Table 15 on page 38 describes the fields. If the system logging utility cannot determine the value in a particular field, a hyphen (-) appears instead.

Table 15: Fields in Structured-Data Messages

Field	Description	Examples
<priority code>	Number that indicates the message's facility and severity. It is calculated by multiplying the facility number by 8 and then adding the numerical value of the severity. For a mapping of the numerical codes to facility and severity, see Table: Facility and Severity Codes in the priority-code Field in "Specifying the Facility and Severity of Messages to Include in the Log" on page 8.	<165> for a message from the pfe facility (facility=20) with severity notice (severity=5).
version	Version of the Internet Engineering Task Force (IETF) system logging protocol specification.	1 for the initial version
timestamp	Time when the message was generated, in one of two representations: <ul style="list-style-type: none"> YYYY-MM-DDTHH:MM:SS.MSZ is the year, month, day, hour, minute, second and millisecond in Universal Coordinated Time (UTC) YYYY-MM-DDTHH:MM:SS.MS+/-HH:MM is the year, month, day, hour, minute, second and millisecond in local time; the hour and minute that follows the plus sign (+) or minus sign (-) is the offset of the local time zone from UTC 	2007-02-15T09:17:15.719Z is 9:17 AM UTC on 15 February 2007. 2007-02-15T01:17:15.719-08:00 is the same timestamp expressed as Pacific Standard Time in the United States.
hostname	Name of the host that originally generated the message.	router1
process	Name of the Junos process that generated the message.	mgd
processID	UNIX process ID (PID) of the Junos process that generated the message.	3046
TAG	Junos system log message tag, which uniquely identifies the message.	UI_DATABASE_LOGOUT_EVENT

Table 15: Fields in Structured-Data Messages (*continued*)

Field	Description	Examples
<code>junos@2636.platform</code>	An identifier for the type of hardware platform that generated the message. The <code>junos@2636</code> prefix indicates that the platform runs the Junos OS. It is followed by a dot-separated numerical identifier for the platform type. For a list of the identifiers, see Table 17 on page 41.	<code>junos@2636.1.1.1.2.18</code> for the M120 router
<i>variable-value-pairs</i>	A variable-value pair for each element in the <i>message-text</i> string that varies depending on the circumstances that triggered the message. Each pair appears in the format <i>variable</i> = " <i>value</i> ".	<code>username="regress"</code>
<i>message-text</i>	English-language description of the event or error (omitted if the brief statement is included at the <code>[edit system syslog file <i>filename</i> structured-data]</code> hierarchy level). For the text for each message, see the chapters following System Log Messages.	User 'regress' exiting configuration mode

By default, the structured-data version of a message includes English text at the end, as in the following example (which appears on multiple lines only for legibility):

```
<165>1 2007-02-15T09:17:15.719Z router1 mgd 3046 UI_DBASE_LOGOUT_EVENT
[junos@2636.1.1.1.2.18 username="regress"] User 'regress' exiting configuration mode
```

When the brief statement is included at the `[edit system syslog file filename structured-data]` hierarchy level, the English text is omitted, as in this example:

```
<165>1 2007-02-15T09:17:15.719Z router1 mgd 3046 UI_DBASE_LOGOUT_EVENT
[junos@2636.1.1.1.2.18 username="regress"]
```

Table 16 on page 39 maps the codes that appear in the *priority-code* field to facility and severity level.



NOTE: Not all of the facilities and severities listed in Table 16 on page 39 can be included in statements at the `[edit system syslog]` hierarchy level (some are used by internal processes). For a list of the facilities and severity levels that can be included in the configuration, see “Specifying the Facility and Severity of Messages to Include in the Log” on page 8.

Table 16: Facility and Severity Codes in the priority-code Field

Facility (number)	Severity emergency	alert	critical	error	warning	notice	info	debug
kernel (0)	1	1	2	3	4	5	6	7

Table 16: Facility and Severity Codes in the priority-code Field (*continued*)

Facility (number)	Severity emergency	alert	critical	error	warning	notice	info	debug
user (1)	8	9	10	11	12	13	14	15
mail (2)	16	17	18	19	20	21	22	23
daemon (3)	24	25	26	27	28	29	30	31
authorization (4)	32	33	34	35	36	37	38	39
syslog (5)	40	41	42	43	44	45	46	47
printer (6)	48	49	50	51	52	53	54	55
news (7)	56	57	58	59	60	61	62	63
uucp (8)	64	65	66	67	68	69	70	71
clock (9)	72	73	74	75	76	77	78	79
authorization-private (10)	80	81	82	83	84	85	86	87
ftp (11)	88	89	90	91	92	93	94	95
ntp (12)	96	97	98	99	100	101	102	103
security (13)	104	105	106	107	108	109	110	111
console (14)	112	113	114	115	116	117	118	119
local0 (16)	128	129	130	131	132	133	134	135
dfc (17)	136	137	138	139	140	141	142	143
local2 (18)	144	145	146	147	148	149	150	151
firewall (19)	152	153	154	155	156	157	158	159
pfe (20)	160	161	162	163	164	165	166	167
conflict-log (21)	168	169	170	171	172	173	174	175
change-log (22)	176	177	178	179	180	181	182	183
interactive-commands (23)	184	185	186	187	188	189	190	191

Table 17 on page 41 lists the numerical identifiers for routing platforms that appear in the **platform** field. The identifier is derived from the platform's SNMP object identifier (OID) as defined in the Juniper Networks routing platform MIB. For more information about OIDs, see the *Junos Network Management Configuration Guide*.

Table 17: Platform Identifiers in the platform Field

Identifier	Platform Name
1.1.1.2.1	M40 router
1.1.1.2.2	M20 router
1.1.1.2.3	M160 router
1.1.1.2.4	M10 router
1.1.1.2.5	M5 router
1.1.1.2.6	T640 routing node
1.1.1.2.7	T320 router
1.1.1.2.8	M40e router
1.1.1.2.9	M320 router
1.1.1.2.10	M7i router
1.1.1.2.11	M10i router
1.1.1.2.13	J2300 Services Router
1.1.1.2.14	J4300 Services Router
1.1.1.2.15	J6300 Services Router
1.1.1.2.17	TX Matrix platform
1.1.1.2.18	M120 router
1.1.1.2.19	J4350 Services Router
1.1.1.2.20	J6350 Services Router
1.1.1.2.23	J2320 Services Router
1.1.1.2.24	J2350 Services Router

Interpreting Messages Generated in Standard Format by a Junos Process or Library

The syntax of a standard-format message generated by a Junos OS process or subroutine library depends on whether it includes priority information:

- When the **explicit-priority** statement is included at the [**edit system syslog file *filename***] or [**edit system syslog host (*hostname* | other-routing-engine)**] hierarchy level, a system log message has the following syntax:

```
timestamp message-source: %facility-severity-TAG: message-text
```

- When directed to the console or to users, or when the **explicit-priority** statement is not included for files or remote hosts, a system log message has the following syntax:

```
timestamp message-source: TAG: message-text
```

Table 18 on page 42 describes the message fields.

Table 18: Fields in Standard-Format Messages Generated by a Junos Process or Library

Field	Description
<i>timestamp</i>	Time at which the message was logged.
<i>message-source</i>	Identifier of the process or component that generated the message and the routing platform on which the message was logged. This field includes two or more subfields, depending on how system logging is configured. See “The message-source Field on a TX Matrix Platform” on page 44, “The message-source Field on a T640 Routing Node in a Routing Matrix” on page 46, and “The message-source Field on a Single-Chassis System” on page 44.
<i>facility</i>	Code that specifies the facility to which the system log message belongs. For a mapping of codes to facility names, see Table: Facility Codes Reported in Priority Information in “Including Priority Information in System Log Messages” on page 18.
<i>severity</i>	Numerical code that represents the severity level assigned to the system log message. For a mapping of codes to severity names, see Table: Numerical Codes for Severity Levels Reported in Priority Information in “Including Priority Information in System Log Messages” on page 18.
<i>TAG</i>	Text string that uniquely identifies the message, in all uppercase letters and using the underscore (_) to separate words. The tag name begins with a prefix that indicates the generating software process or library. The entries in this reference are ordered alphabetically by this prefix. Not all processes on a routing platform use tags, so this field does not always appear.
<i>message-text</i>	Text of the message. For the text for each message, see the chapters following System Log Messages.

Interpreting Messages Generated in Standard Format by Services on a PIC

Standard-format system log messages generated by services on a PIC, such as the Adaptive Services (AS) PIC, have the following syntax:

```
timestamp (FPC Slot fpc-slot, PIC Slot pic-slot) {service-set} [SERVICE]:
optional-string TAG: message-text
```



NOTE: System logging for services on PICs is not configured at the [edit system syslog] hierarchy level as discussed in this chapter. For configuration information, see the *Junos Services Interfaces Configuration Guide*.

The (FPC Slot *fpc-slot*, PIC Slot *pic-slot*) field appears only when the standard system logging utility that runs on the Routing Engine writes the messages to the system log. When the PIC writes the message directly, the field does not appear.

Table 19 on page 43 describes the message fields.

Table 19: Fields in Messages Generated by a PIC

Field	Description
<i>timestamp</i>	Time at which the message was logged.
<i>fpc-slot</i>	Slot number of the Flexible PIC Concentrator (FPC) that houses the PIC that generated the message.
<i>pic-slot</i>	Number of the PIC slot on the FPC in which the PIC that generated the message resides.
<i>service-set</i>	Name of the service set that generated the message.
<i>SERVICE</i>	Code representing the service that generated the message. The codes include the following: <ul style="list-style-type: none"> FWNAT—Network Address Translation (NAT) service IDS—Intrusion detection service
<i>optional-string</i>	A text string that appears if the configuration for the PIC includes the log-prefix statement at the [edit interfaces interface-name services-options syslog] hierarchy level. For more information, see the <i>Junos Services Interfaces Configuration Guide</i> .
<i>TAG</i>	Text string that uniquely identifies the message, in all uppercase letters and using the underscore (_) to separate words. The tag name begins with a prefix that indicates the generating PIC. The entries in this reference are ordered alphabetically by this prefix.
<i>message-text</i>	Text of the message. For the text of each message, see System Log Messages.

Format of the message-source Field

The *message-source* field discussed in “Interpreting Messages Generated in Standard Format by a Junos Process or Library” on page 42 has two or more subfields, depending on whether the message is logged on a single-chassis system or on a platform in a routing matrix, and whether message forwarding is configured in the routing matrix.

For more information, see the following sections:

- The message-source Field on a Single-Chassis System on page 44
- The message-source Field on a TX Matrix Platform on page 44
- The message-source Field on a T640 Routing Node in a Routing Matrix on page 46

The message-source Field on a Single-Chassis System

The format of the *message-source* field in a message on a single-chassis system depends on whether the message was generated on the local Routing Engine or the other Routing Engine (on a system with two Routing Engines installed and operational). Messages from the other Routing Engine appear only if its configuration includes the **other-routing-engine** statement at the **[edit system syslog host]** hierarchy level.

- When the local Routing Engine generated the message, there are two subfields:

hostname process[process-ID]

- When the other Routing Engine generated the message, there are three subfields:

hostname reX process[process-ID]

hostname is the hostname of the local Routing Engine.

process[process-ID] is the name and PID of the process that generated the message. If the *reX* field also appears, the process is running on the other Routing Engine. If a process does not report its PID, the *[process-ID]* part does not appear.

reX indicates that the other Routing Engine generated the message (*X* is **0** or **1**).

The message-source Field on a TX Matrix Platform

The format of the *message-source* field in a message on a TX Matrix platform depends on several factors:

- Whether the message was generated on the TX Matrix platform or a T640 routing node in the routing matrix. By default, the master Routing Engine on each T640 routing node forwards messages from all facilities with severity info and higher to the master Routing Engine on the TX Matrix platform. When you configure system logging on the TX Matrix platform, its logs include the forwarded messages. For more information, see “Messages Logged When Local Severity Level Is Lower” on page 30, “Messages Logged When Local Severity Level Is Higher” on page 31, and “Messages Logged When Local and Forwarded Severity Level Are the Same” on page 29.
- Whether the message was generated on the local Routing Engine or the other Routing Engine on the originating machine (TX Matrix platform or T640 routing node). Messages

from the other Routing Engine appear only if its configuration includes the **other-routing-engine** statement at the **[edit system syslog host]** hierarchy level.

- Whether the message was generated by a kernel or user-space process, or by the microkernel on a hardware component.

Table 20 on page 45 specifies the format of the message-source field in the various cases.

Table 20: Format of message-source Field in Messages Logged on TX Matrix Platform

Generating Machine	Generating Routing Engine	Process or Component	Format
TX Matrix platform	Local	Process	<i>hostname process[processID]</i>
		Component	<i>hostname scc-reX process[processID]</i>
	Other	Process	<i>hostname scc-reX scc-componentZ process</i>
		Component	<i>hostname scc-reX scc-componentZ process</i>
T640 routing node	Local	Process	<i>hostname lccY-masterprocess[processID]</i>
		Component	<i>hostname lccY-master scc-componentZ process</i>
	Other	Process	<i>hostname lccY-master lccY-reX process[processID]</i>
		Component	<i>hostname lccY-master lccY-reX lccY-componentZ process</i>

hostname is the hostname of the local Routing Engine on the TX Matrix platform.

lccY-master is the master Routing Engine on the T640 routing node with the indicated LCC index number (**Y** is from **0** through **3**).

lccY-reX indicates that the backup Routing Engine on the T640 routing node generated the message (**X** is **0** or **1**). The routing node has the indicated LCC index number (**Y** matches the value in the **lccY-master** field).

lccY-componentZ process identifies the hardware component and process on the T640 routing node that generated the message (**Y** matches the value in the **lccY-master** field and the range of values for **Z** depends on the component type). For example, **lcc2-fpc1 PFEMAN** refers to a process on the FPC in slot 1 on the T640 routing node with index LCC2.

process[process-ID] is the name and PID of the kernel or user-space process that generated the message. If the **scc-reX** or **lccY-reX** field also appears, the process is running on the other Routing Engine. If a process does not report its PID, the **[process-ID]** part does not appear.

scc-componentZ process identifies the hardware component and process on the TX Matrix platform that generated the message (the range of values for **Z** depends on the component type). For example, **smb1 GSIB** refers to a process on one of the processor boards in the Switch Interface Board (SIB) with index 1.

scc-reX indicates that the other Routing Engine on the TX Matrix platform generated the message (**X** is 0 or 1).

The message-source Field on a T640 Routing Node in a Routing Matrix

The format of the **message-source** field in a message on a T640 routing node in a routing matrix depends on two factors:

- Whether the message was generated on the local Routing Engine or the other Routing Engine. Messages from the other Routing Engine appear only if its configuration includes the **other-routing-engine** statement at the **[edit system syslog host]** hierarchy level.
- Whether the message was generated by a kernel or user-space process, or by the microkernel on a hardware component.

Table 21 on page 46 specifies the format of the **message-source** field in the various cases.

Table 21: Format of message-source Field in Messages Logged on TX Matrix Platform

Generating Routing Engine	Process or Component	Format
Local	Process	<i>hostname-lccY process[processID]</i>
	Component	<i>hostname-lccY lccY-componentZ process</i>
Other	Process	<i>hostname-lccY lccY-reX process[processID]</i>
	Component	<i>hostname-lccY lccY-reX lccY-componentZ process</i>

hostname-lccY is the hostname of the local Routing Engine and the T640 routing node's LCC index number.

lccY-componentZ process identifies the hardware component and process that generated the message (**Y** matches the value in the **hostname-lccY** field and the range of values for **Z** depends on the component type). For example, **lcc0-fpc0 CMLC** refers to a process on the FPC in slot 0. The T640 routing node has index **LCC0** in the routing matrix.

lccY-reX indicates that the other Routing Engine on the routing node generated the message (**Y** matches the value in the **hostname-lccY** field and **X** is 0 or 1).

process[process-ID] is the name and PID of the kernel or user-space process that generated the message. If the **lccY-reX** field also appears, the process is running on the other Routing Engine. If a process does not report its PID, the **[process-ID]** part does not appear.

Examples: Displaying a Log File

Display the contents of the **/var/log/messages** file stored on the local Routing Engine. (The **/var/log** directory is the default location for log files, so you do not need to include it in the filename. The **messages** file is a commonly configured destination for system log messages.)

```
user@host> show log messages Apr 11 10:27:25 router1 mgd[3606]:
  UI_DBASE_LOGIN_EVENT: User 'barbara' entering configuration mode
Apr 11 10:32:22 router1 mgd[3606]: UI_DBASE_LOGOUT_EVENT: User 'barbara' exiting
  configuration mode
Apr 11 11:36:15 router1 mgd[3606]: UI_COMMIT: User 'root' performed commit: no comment
Apr 11 11:46:37 router1 mib2d[2905]: SNMP_TRAP_LINK_DOWN: ifIndex 82, ifAdminStatus
  up(1), ifOperStatus down(2), ifName at-1/0/0
```

Display the contents of the file **/var/log/processes**, which has been previously configured to include messages from the **daemon** facility. When issuing the **file show** command, you must specify the full pathname of the file:

```
user@host> file show /var/log/processes Feb 22 08:58:24 router1 snmpd[359]:
  SNMPD_TRAP_WARM_START: trap_generate_warm: SNMP trap: warm start
Feb 22 20:35:07 router1 snmpd[359]: SNMPD_THROTTLE_QUEUE_DRAINED:
  trap_throttle_timer_handler: cleared all throttled traps
Feb 23 07:34:56 router1 snmpd[359]: SNMPD_TRAP_WARM_START: trap_generate_warm:
  SNMP trap: warm start
Feb 23 07:38:19 router1 snmpd[359]: SNMPD_TRAP_COLD_START: trap_generate_cold:
  SNMP trap: cold start
```

Display the contents of the file **/var/log/processes** when the **explicit-priority** statement is included at the **[edit system syslog file processes]** hierarchy level:

```
user@host> file show /var/log/processes Feb 22 08:58:24 router1 snmpd[359]:
  %DAEMON-3-SNMPD_TRAP_WARM_START: trap_generate_warm: SNMP trap: warm
  start
Feb 22 20:35:07 router1 snmpd[359]:
  %DAEMON-6-SNMPD_THROTTLE_QUEUE_DRAINED: trap_throttle_timer_handler: cleared
  all throttled traps
Feb 23 07:34:56 router1 snmpd[359]:
  %DAEMON-3-SNMPD_TRAP_WARM_START: trap_generate_warm: SNMP trap: warm
  start
Feb 23 07:38:19 router1 snmpd[359]:
  %DAEMON-2-SNMPD_TRAP_COLD_START: trap_generate_cold: SNMP trap: cold start
```

Getting Help About System Log Messages

System log message tag names begin with a prefix that indicates which Junos OS process, subroutine library, or service on a PIC generated the message. This section explains how to learn more about the messages with each prefix, both in this reference and while you are using the CLI.

For a list of the prefixes for messages described in this reference, see System Log Messages. For information about displaying and interpreting messages, see the following sections:

- Displaying and Interpreting System Log Message Descriptions on page 48
- Examples: Displaying System Log Message Descriptions on page 50

Displaying and Interpreting System Log Message Descriptions

This reference lists the messages available at the time of its publication. To display the list of messages that applies to the version of the Junos OS that is running on a routing platform, enter Junos OS CLI operational mode and issue the following command:

```
user@host> help syslog ?
```

To display the list of available descriptions for tags whose names begin with a specific character string, substitute the string (in all capital letters) for the variable **TAG-PREFIX** (there is no space between the prefix and the question mark):

```
user@host> help syslog TAG-PREFIX?
```

To display the complete descriptions for tags whose name includes a regular expression, substitute a Perl-based expression for the variable **regex**. The match is not case-sensitive. For information about Perl-based regular expressions, consult a Perl reference manual or website such as <http://perldoc.perl.org>.

```
user@host> help syslog regex
```

To display the complete description of a particular message, substitute its name for the variable **TAG** (in all capital letters):

```
user@host> help syslog TAG
```

Table 22 on page 48 describes the fields in a system log message description in this reference or in the CLI.

Table 22: Fields in System Log Message Descriptions

Field Name in Reference	Field Name in CLI	Description
—	Name	The message tag in all capital letters.

Table 22: Fields in System Log Message Descriptions (*continued*)

Field Name in Reference	Field Name in CLI	Description
System Log Message	Message	<p>Text of the message written to the system log. In the log, a specific value is substituted for each variable that appears in italics in this reference or in angle brackets (< >) in the CLI.</p> <p>In this reference, the message text appears on the second line of the System Log Message field. The first line is the message tag (the same text as in the CLI Name field). The prefix on each tag identifies the message source and the rest of the tag indicates the specific event or error.</p>
—	Help	<p>Short description of the message, which also appears in the right-hand column of CLI output for the help syslog command when the output lists multiple messages.</p>
Description	Description	More detailed explanation of the message.
Type	Type	<p>Category to which the message belongs:</p> <ul style="list-style-type: none"> • Error: The message reports an error or failure condition that might require corrective action. • Event: The message reports a condition or occurrence that does not generally require corrective action.
Severity	Severity	<p>Message severity level as described in Table: System Log Message Severity Levels in “Specifying the Facility and Severity of Messages to Include in the Log” on page 8.</p>
Cause	Cause	<p>(Optional) Possible cause for message generation. There can be more than one cause.</p>

Table 22: Fields in System Log Message Descriptions (*continued*)

Field Name in Reference	Field Name in CLI	Description
Action	Action	(Optional) Action you can perform to resolve the error or failure condition described in the message. If this field does not appear in an entry, either no action is required or the action is self-explanatory.

Examples: Displaying System Log Message Descriptions

Display the list of all currently available system log message descriptions:

```
user@host> help syslog ?

Possible completions:
<syslog-tag>   Syslog tag
. . . . .
BOOTPD_ARG_ERR  Command-line option was invalid
BOOTPD_BAD_ID   Request failed because assembly ID was unknown
BOOTPD_BOOTSTRING tnp.bootpd provided boot string
BOOTPD_CONFIG_ERR tnp.bootpd could not parse configuration file;
                  used default settings
BOOTPD_CONF_OPEN tnp.bootpd could not open configuration file
BOOTPD_DUP_REV   Extra boot string definitions for revision were
                  ignored
---(more 4%)---
```

Display the list of all currently available system log message descriptions for tags that begin with the letters **ACCT** (there is no space between **ACCT** and the question mark, and some descriptions are shortened for legibility):

```
user@host> help syslog ACCT?

Possible completions:
<syslog-tag>      System log tag or regular expression
ACCT_ACCOUNTING_ERROR Error occurred during file processing
ACCT_ACCOUNTING_FOPEN_ERROR Open operation failed on file
ACCT_ACCOUNTING_SMALL_FILE_SIZE Maximum file size is smaller than ...
ACCT_BAD_RECORD_FORMAT Record format does not match accounting profile
ACCT_CU_RTSLIB_ERROR Error occurred obtaining current class usage ...
ACCT_FORK_ERR      Could not create child process
ACCT_FORK_LIMIT_EXCEEDED Could not create child process because of limit
ACCT_GETHOSTNAME_ERROR gethostname function failed
ACCT_MALLOC_FAILURE Memory allocation failed
ACCT_UNDEFINED_COUNTER_NAME Filter profile used undefined counter name
ACCT_XFER_FAILED    Attempt to transfer file failed
ACCT_XFER_POPEN_FAIL File transfer failed
```

Display the description of the **UI_CMDLINE_READ_LINE** message:

```
user@host> help syslog UI_CMDLINE_READ_LINE

Name:      UI_CMDLINE_READ_LINE
Message:   User '<users>', command '<input>'
Help:      User entered command at CLI prompt
Description: The indicated user typed the indicated command at the CLI
```

prompt and pressed the Enter key, sending the command string
to the management process (mgd).
Type: Event: This message reports an event, not an error
Severity: info

PART 2

System Log Messages

- ACCT System Log Messages on page 57
- ALARMD System Log Messages on page 61
- ANCPD System Log Messages on page 67
- ANTISPAM System Log Messages on page 69
- APPID System Log Messages on page 71
- APPIDD System Log Messages on page 73
- APPPY System Log Messages on page 75
- APPTRACK System Log Messages on page 77
- ASP System Log Messages on page 79
- AUDITD System Log Messages on page 109
- AUTHD System Log Messages on page 113
- AUTOCONFD System Log Messages on page 115
- AUTOD System Log Messages on page 117
- AV System Log Messages on page 119
- BFDD System Log Messages on page 125
- BOOTPD System Log Messages on page 129
- CFMD System Log Messages on page 135
- CHASSISD System Log Messages on page 139
- CHASSISM System Log Messages on page 219
- CONTENT System Log Messages on page 221
- COSD System Log Messages on page 223
- DCBX System Log Messages on page 237
- DCD System Log Messages on page 239
- DFCD System Log Messages on page 245
- DFWD System Log Messages on page 249
- DH System Log Messages on page 251
- DHCPD System Log Messages on page 255
- DYNAMIC System Log Messages on page 259
- ESPTASK System Log Messages on page 265

- ESWD System Log Messages on page 267
- EVENTD System Log Messages on page 275
- FC System Log Messages on page 283
- FCD System Log Messages on page 289
- FCOE System Log Messages on page 291
- FIP System Log Messages on page 293
- FLOW System Log Messages on page 297
- FPCLOGIN System Log Messages on page 299
- FSAD System Log Messages on page 301
- FUD System Log Messages on page 311
- FWAUTH System Log Messages on page 317
- GPRSD System Log Messages on page 321
- HNCACHED System Log Messages on page 323
- ICCPD System Log Messages on page 325
- IDP System Log Messages on page 327
- JADE System Log Messages on page 333
- JCS System Log Messages on page 335
- JDIAMETERD System Log Messages on page 341
- JIVED System Log Messages on page 343
- JPTSPD System Log Messages on page 347
- JSRPD System Log Messages on page 351
- KMD System Log Messages on page 359
- L2ALD System Log Messages on page 383
- L2CPD System Log Messages on page 393
- L2TPD System Log Messages on page 403
- LACPD System Log Messages on page 433
- LFMD System Log Messages on page 435
- LIBESPTASK System Log Messages on page 437
- LIBJNX System Log Messages on page 439
- LIBJSNMP System Log Messages on page 447
- LIBMSRPC System Log Messages on page 453
- LICENSE System Log Messages on page 457
- LLDPD System Log Messages on page 461
- LOGIN System Log Messages on page 463
- LPDFD System Log Messages on page 467
- LRMUX System Log Messages on page 469
- MCSN System Log Messages on page 471

- MCSNOOPD System Log Messages on page 477
- MIB2D System Log Messages on page 479
- MPLS_OAM System Log Messages on page 485
- NEXTHOP System Log Messages on page 489
- NSD System Log Messages on page 491
- NSTRACED System Log Messages on page 493
- PFE System Log Messages on page 495
- PFED System Log Messages on page 503
- PGCPD System Log Messages on page 505
- PING System Log Messages on page 507
- PPMD System Log Messages on page 511
- PPPD System Log Messages on page 513
- PROFILER System Log Messages on page 521
- RDD System Log Messages on page 523
- RMOPD System Log Messages on page 527
- RPD System Log Messages on page 531
- RT System Log Messages on page 677
- RTLOG System Log Messages on page 689
- RTLOGD System Log Messages on page 691
- RTPERF System Log Messages on page 693
- SAVAL System Log Messages on page 695
- SDXD System Log Messages on page 697
- SFW System Log Messages on page 701
- SMTPD System Log Messages on page 703
- SNMP System Log Messages on page 705
- SNMPD System Log Messages on page 709
- SPD System Log Messages on page 721
- SSH System Log Messages on page 727
- SSHD System Log Messages on page 729
- TASK System Log Messages on page 731
- TFTPDP System Log Messages on page 739
- UFDD System Log Messages on page 743
- UI System Log Messages on page 745
- UTMD System Log Messages on page 769
- VCCPD System Log Messages on page 771
- VRRPD System Log Messages on page 775
- VSYSD System Log Messages on page 779

- WEB System Log Messages on page 781
- WEBFILTER System Log Messages on page 787

CHAPTER 2

ACCT System Log Messages

This chapter describes messages with the **ACCT** prefix. They are generated by the accounting statistics process, which collects and records interface, filter, and class usage statistics.

ACCT_ACCOUNTING_FERROR

System Log Message	Unexpected error <i>error-code</i> from file <i>filename</i>
Description	An error prevented the accounting statistics process from processing the indicated file.
Type	Error: An error occurred
Severity	warning
Facility	LOG_PFE

ACCT_ACCOUNTING_FOPEN_ERROR

System Log Message	Failed to open file <i>filename: error-code</i>
Description	The accounting statistics process could not open the indicated file.
Type	Error: An error occurred
Severity	warning
Facility	LOG_PFE

ACCT_ACCOUNTING_SMALL_FILE_SIZE

System Log Message	File <i>filename</i> size (<i>file-size</i>) is smaller than record size (<i>record-size</i>)
Description	The size limit configured for the indicated file is smaller than the record to be written to it.
Type	Error: An error occurred
Severity	warning
Facility	LOG_PFE

ACCT_BAD_RECORD_FORMAT

System Log Message	Invalid statistics record: <i>entry</i>
---------------------------	---

Description The number of columns in the indicated record does not match the number of columns in the accounting profile.

Type Error: An error occurred

Severity warning

Facility LOG_PFE

ACCT_CU_RTSLIB_ERROR

System Log Message Error getting class usage statistics for interface *interface-name.unit-id: error-message*

Description The accounting statistics process could not obtain current class usage statistics.

Type Error: An error occurred

Severity error

Facility LOG_PFE

ACCT_FORK_ERR

System Log Message Unable to fork: *error-message*

Description The accounting statistics process could not create a child process for transferring files, for the indicated reason.

Type Error: An error occurred

Severity error

Facility LOG_PFE

ACCT_FORK_LIMIT_EXCEEDED

System Log Message Unable to fork: too many child processes

Description The accounting statistics process could not create a child process for transferring files, because adding another child would have made the number of children exceed the limit.

Type Error: An error occurred

Severity error

Facility LOG_PFE

ACCT_GETHOSTNAME_ERROR

System Log Message Error *error-code* trying to get hostname

Description A call to the gethostname() function failed.

Type Error: An error occurred

Severity error

Facility LOG_PFE

ACCT_MALLOC_FAILURE

System Log Message	Memory allocation failed while reallocating filter profile interface list
Description	The accounting statistics process could not allocate memory from the heap.
Type	Error: An error occurred
Severity	error
Facility	LOG_PFE
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

ACCT_UNDEFINED_COUNTER_NAME

System Log Message	Counter <i>profile-name</i> in accounting profile <i>counter-name</i> is not defined in a firewall using this filter profile
Description	The indicated filter profile referenced the indicated counter name, which is not defined in a firewall filter that uses the filter profile.
Type	Error: An error occurred
Severity	warning
Facility	ANY
Action	Change the filter profile counter name to match the name defined in the firewall configuration.

ACCT_XFER_FAILED

System Log Message	Error transferring <i>filename</i>
Description	An attempt to transfer the indicated file failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_PFE

ACCT_XFER_POPEN_FAIL

System Log Message	Error <i>error-code</i> in invoking command <i>command</i> to transfer file <i>filename</i>
Description	A call to the popen() function failed when the accounting statistics process invoked the indicated command to transfer the indicated file.
Type	Error: An error occurred
Severity	error

Facility LOG_PFE

CHAPTER 3

ALARMD System Log Messages

This chapter describes messages with the **ALARMD** prefix. They are generated by the alarm process (alarmd).

ALARMD_CONFIG_ACCESS_ERROR

System Log Message	<i>function-name: error-message</i>
Description	The alarm process (alarmd) experienced the indicated problem while attempting to parse the configuration database.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

ALARMD_CONFIG_CLOSE_ERROR

System Log Message	Unable to close configuration database
Description	The alarm process (alarmd) could not close the configuration database.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

ALARMD_CONFIG_PARSE_ERROR

System Log Message	Unable to parse configuration; using defaults
Description	The alarm process (alarmd) could not parse the configuration and used default values while initializing.
Type	Error: An error occurred
Severity	error

Facility	LOG_DAEMON
Action	Contact your technical support representative.

ALARMD_CONFIG_RECONFIG_ERROR

System Log Message	Re-configuration failed, using previous values
Description	The alarm process (alarmd) could not parse new configuration and used previous values.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

ALARMD_CONNECTION_FAILURE

System Log Message	after <i>count</i> attempts <i>process-name</i> connect returned error: <i>error-message</i>
Description	The alarm process (alarmd) was unable to connect to the indicated process
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

ALARMD_DECODE_ALARM_OBJECT_ERROR

System Log Message	Cannot decode error test from object <i>alarm-object</i> , reason <i>alarm-reason</i> for if_name <i>interface-type</i>
Description	The alarm process (alarmd) encountered invalide alarm object.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

ALARMD_EXISTS

System Log Message	alarmd already running; exiting
Description	The alarm process (alarmd) exited because it discovered that another alarmd process is already running.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON

ALARMD_EXISTS_TERM_OTHER

System Log Message	Killing existing alarmd and exiting
Description	The alarm process (alarmd) discovered that another alarmd process is already running. It terminated the other process and exited.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON

ALARMD_IFDALARM_TYPE_ERROR

System Log Message	Unknown interface alarm type: <i>alarm-type</i>
Description	The alarm process (alarmd) could not recognize an interface type alarm due to it's unknown alarm type.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

ALARMD_IFDEV_RTSLIB_FAILURE

System Log Message	<i>function-name: library-function-name</i> failed on <i>error-message</i> socket (<i>socket-option</i>)
Description	The alarm process (alarmd) failed to access an interface device because an error occurred during the indicated call to the routing socket library.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

ALARMD_IPC_MSG_ERROR

System Log Message	<i>function-name: error code error-code</i> , type <i>message-type</i> , subtype <i>message-subtype</i> , opcode <i>message-opcode</i>
Description	The alarm process (alarmd) detected an error in an interprocess communication (IPC) message with the indicated characteristics.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

Action Contact your technical support representative.

ALARMD_IPC_MSG_WRITE_ERROR

System Log Message alarmd_send_msg: ipc_msg_write failed: *error-message*.

Description The alarm process (alarmd) is not able to write a new ipc message to the given ipc pipe.

Type Error: An error occurred

Severity warning

Facility LOG_DAEMON

ALARMD_IPC_UNEXPECTED_CONN

System Log Message Invalid connection id: *connection-who*

Description The alarm process (alarmd) received an ipc message from an unexpected connection.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

ALARMD_IPC_UNEXPECTED_MSG

System Log Message *function-name*: invalid message received: *message* (message type *message-type*, subtype *message-subtype*)

Description The alarm process (alarmd) received an unexpected message with the indicated characteristics.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

ALARMD_MEM_ALLOC_FAILURE

System Log Message *function-name*: alarmd memory allocation failed

Description The alarm process (alarmd) could not allocate memory.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

ALARMD_MGR_CONNECT

System Log Message	<i>function-name</i> evSelectFD: initial pipe create aborted (errno <i>error-code</i>)
Description	The alarm process (alarmd) could not open a pipe for interprocess communication (IPC).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

ALARMD_MULTIPLE_ALARM_BIT_ERROR

System Log Message	Multiple alarm bits: <i>Oxalarm-bit</i>
Description	The alarm process (alarmd) expected one alarm bit set for an interface alarm when it received multiple.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

ALARMD_PIDFILE_OPEN

System Log Message	Unable to open PID file ' <i>filename</i> ': errno <i>error-code</i>
Description	The alarm process (alarmd) could not open the file where it stores its process ID (PID).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	The alarm process (alarmd) might have detected that another alarmd process was running and tried to read the file so that it could use the PID recorded there when terminating the other process.

ALARMD_PIPE_WRITE_ERROR

System Log Message	Pipe write error: <i>error-message</i>
Description	The alarm process (alarmd) experienced a fatal error while writing to a pipe.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

Cause There was no reader for the pipe.

ALARMD_SOCKET_CREATE

System Log Message Unable to create socket for *process-name* connection: *errno error-code*

Description The alarm process (alarmd) could not create socket.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

ALARMD_UNEXPECTED_EXIT

System Log Message evMainLoop returned *return-value* (*errno error-code*)

Description The alarm process (alarmd) exited unexpectedly and reported the indicated error.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHAPTER 4

ANCPD System Log Messages

This chapter describes messages with the **ANCPD** prefix. They are generated by the Access Node Control Protocol process (ancpd), also known as Layer 2 control (l2c), which works with a special Internet Group Management Protocol (igmp) session to collect outgoing interface (oif) mapping events in a scalable manner.

ANCPD_COMMAND_OPTIONS

System Log Message	ancpd_cmd_opts called with option <i>index</i> arg <i>argument</i>
Description	ancpd process cmd line options not handled by junos_app_init
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

CHAPTER 5

ANTISPAM System Log Messages

This chapter describes messages with the **ANTISPAM** prefix. They are generated by the antispam process, which decides what action should be performed when the device detects a message that it deems to be spam.

ANTISPAM_SPAM_DETECTED_MT

System Log Message	AntiSpam: SPAM detected: <i>source-name (source-address) action reason: reason</i>
Description	The email is detected as a spam; the IP address of the source and its name will be logged together with the reason for it being categorized as spam
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_PFE
Cause	The email is detected as a spam
Action	Verify the spam to make sure it is not a false positive

CHAPTER 6

APPID System Log Messages

This chapter describes messages with the **APPID** prefix. They are generated by the application identification process (appid), which is a passive application protocol identification library that implements a state machine for efficient pattern matching of regex-like application content signatures.

APPID_SIGNATURE_LICENSE_EXPIRED

System Log Message	APPID signature update license(ID= <i>feature-id</i>) has expired
Description	APPID signature update license key has expired. Signature update may not work any more.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

CHAPTER 7

APPIDD System Log Messages

This chapter describes messages with the **APPIDD** prefix. They are generated by the application identification process (appid), which is a passive application protocol identification library that implements a state machine for efficient pattern matching of regex-like application content signatures.

APPIDD_APPPACK_DOWNLOAD_RESULT

System Log Message	Application package download result(<i>status</i>)
Description	Application package download result
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

APPIDD_APPPACK_UNINSTALL_RESULT

System Log Message	Application package uninstall result(<i>status</i>)
Description	Application package uninstall result
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

APPIDD_DAEMON_INIT_FAILED

System Log Message	Aborted. A failure was encountered <i>error-message</i>
Description	An attempt to start AI policy daemon failed because an error was encountered during initialization.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

APPIDD_SCHEDULED_UPDATE_FAILED

System Log Message	Failed to update application packge. error: <i>error-message</i>
Description	The scheduled application-identification application package update failed to start. Device will try it again at the next scheduled time
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHAPTER 8

APPPXY System Log Messages

This chapter describes messages with the **APPPXY** prefix. They are generated by the Application Proxy process (appxyd) which performs all of the services of a proxy, but only for specific applications. The application proxy will only process packets that related to the applications it supports.

APPPXY_RESOURCE_OVERUSED_MT

System Log Message	ApplicationProxy: Suspicious client <i>source-address:source-port</i> (-> <i>destination-address:destination-port</i>) used <i>percentage-value</i> connections, which exceeded the maximum allowed <i>maximum-value</i> connections
Description	For ApplicationProxy, the amount of traffic from the specified source address exceeded the amount permitted from one source. The maximum amount of traffic from one source is a fixed percentage of the total amount of traffic
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_PFE

APPPXY_SESSION_ABORT_MT

System Log Message	ApplicationProxy: session from <i>source-address:source-port</i> to <i>destination-address:destination-port</i> aborted due to <i>error-message</i> (code <i>error-code</i>)
Description	Report application protocol (ftp/http/pop3/smtp/imap) session is aborted
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_PFE

CHAPTER 9

APPTRACK System Log Messages

This chapter describes messages with the **APPTRACK** prefix. They are generated by the application tracking process (apptrack).

APPTRACK_SESSION_APP_UPDATE

System Log Message AppTrack app update: *source-address/source-port->destination-address/destination-port service-name application nested-application nat-source-address/nat-source-port->nat-destination-address/nat-destination-port src-nat-rule-name dst-nat-rule-name protocol-id policy-name source-zone-name destination-zone-name session-id-32 packets-from-client(bytes-from-client) packets-from-server(bytes-from-server) elapsed-time*

Description The log is sent when an application identification service identified a application in a session.

Type Event: This message reports an event, not an error

Severity info

Facility ANY

APPTRACK_SESSION_CLOSE

System Log Message AppTrack session closed *reason: source-address/source-port->destination-address/destination-port service-name application nested-application nat-source-address/nat-source-port->nat-destination-address/nat-destination-port src-nat-rule-name dst-nat-rule-name protocol-id policy-name source-zone-name destination-zone-name session-id-32 packets-from-client(bytes-from-client) packets-from-server(bytes-from-server) elapsed-time*

Description A security session being tracked by the Application tracking service was closed.

Type Event: This message reports an event, not an error

Severity info

Facility ANY

APPTRACK_SESSION_CREATE

System Log Message	AppTrack session created <i>source-address/source-port->destination-address/destination-port service-name application nested-application nat-source-address/nat-source-port->nat-destination-address/nat-destination-port src-nat-rule-name dst-nat-rule-name protocol-id policy-name source-zone-name destination-zone-name session-id-32</i>
Description	A security session was created which will be monitored by the Application tracking service.
Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

APPTRACK_SESSION_VOL_UPDATE

System Log Message	AppTrack volume update: <i>source-address/source-port->destination-address/destination-port service-name application nested-application nat-source-address/nat-source-port->nat-destination-address/nat-destination-port src-nat-rule-name dst-nat-rule-name protocol-id policy-name source-zone-name destination-zone-name session-id-32 packets-from-client(bytes-from-client) packets-from-server(bytes-from-server) elapsed-time</i>
Description	Periodic updates are sent for a session monitored by the Application tracking service. The periodicity is decided by configuration.
Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

CHAPTER 10

ASP System Log Messages

This chapter describes messages with the **ASP** prefix. They are generated by services on the Adaptive Services PIC (AS PIC), such as stateful firewall, Network Address Translation (NAT), and intrusion detection service (IDS). For information about configuring system logging for services on the AS PIC, see the *Junos Services Interfaces Configuration Guide*.

For information about the fields in messages with the ASP prefix, see “Interpreting Messages Generated in Standard Format by Services on a PIC” on page 43.

ASP_COS_RULE_MATCH

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name) application: application, source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type rule-set: rule-set-name, rule: rule-name, term: term-name*

Description A packet matched the indicated term in the indicated class-of-service (CoS) rule. If the rule belongs to a rule set, the name of the rule set is also displayed. The matching packet contained the indicated information about its protocol (numerical identifier and name), application, source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error

Severity info

Facility LOG_PFE

ASP_IDS_HOST_RATE

System Log Message *Host destination-address, event-type ... rate=rate events/sec*

Description The indicated event occurred at the indicated rate (events per second) for the indicated destination IP address. The rate exceeds the intrusion detection services (IDS) threshold configured with the 'threshold' statement at the [edit services rule <rule-name> term <term-name> then logging] hierarchy level. This message is logged every 60 seconds until the rate no longer exceeds the threshold.

Type Event: This message reports an event, not an error

Severity error

Facility LOG_PFE

ASP_IDS_HOST_RATE_APP

System Log Message Host *destination-address (application)*, *event-type* ... rate=*rate* events/sec

Description The indicated event occurred at the indicated rate (events per second) for the indicated application at the indicated destination IP address. The rate exceeds the intrusion detection services (IDS) threshold set by the 'threshold' statement at the [edit services ids rule <rule-name> term <term-name> then logging] hierarchy level. The application is specified by the 'applications' or 'application-sets' statement at the [edit services ids rule <rule-name> term <term-name> from] hierarchy level. This message is logged every 60 seconds until the rate no longer exceeds the threshold.

Type Event: This message reports an event, not an error

Severity error

Facility LOG_PFE

ASP_IDS_INV_CLEAR_QUERY

System Log Message CLEAR: Invalid query type *received-value* expecting *expected-value*

Description Intrusion detection services (IDS) received a request to clear information from IDS tables. The request included the indicated type of query, which IDS cannot interpret.

Type Error: An error occurred

Severity critical

Facility LOG_PFE

Action Contact your technical support representative.

ASP_IDS_INV_CLEAR_QUERY_VER

System Log Message CLEAR: Invalid query version *received-value* expecting *expected-value*

Description Intrusion detection services (IDS) received a request to clear information from IDS tables. The request's version number did not match the version number of requests that IDS can service.

Type Error: An error occurred

Severity critical

Facility LOG_PFE

Action Contact your technical support representative.

ASP_IDS_INV_SHOW_QUERY

System Log Message SHOW: Invalid query type *received-value* expecting *expected-value*

Description	Intrusion detection services (IDS) received a request to show information from IDS tables. The request included the indicated type of query, which IDS cannot interpret.
Type	Error: An error occurred
Severity	critical
Facility	LOG_PFE
Action	Contact your technical support representative.

ASP_IDS_INV_SHOW_QUERY_VER

System Log Message	SHOW: Invalid query version <i>received-value</i> expecting <i>expected-value</i>
Description	Intrusion detection services (IDS) received a request to show information from IDS tables. The request's version number did not match the version number of requests that IDS can service.
Type	Error: An error occurred
Severity	critical
Facility	LOG_PFE
Action	Contact your technical support representative.

ASP_IDS_LIMIT_FLOW_RATE_BY_DEST

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The stateful firewall discarded the packet with the indicated characteristics and did not create a new flow, because the flow rate at the firewall exceeded the intrusion detection services (IDS) limit configured by the 'rate' statement at the [edit services ids rule <rule-name> term <term-name> then session-limit by-destination] hierarchy level. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_PFE

ASP_IDS_LIMIT_FLOW_RATE_BY_PAIR

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The stateful firewall discarded the packet with the indicated characteristics and did not create a new flow, because the flow rate at the firewall exceeded the intrusion detection

services (IDS) limit configured by the 'rate' statement at the [edit services ids rule <rule-name> term <term-name> then session-limit by-pair] hierarchy level. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_PFE

ASP_IDS_LIMIT_FLOW_RATE_BY_SRC

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type*

Description The stateful firewall discarded the packet with the indicated characteristics and did not create a new flow, because the flow rate at the firewall exceeded the intrusion detection services (IDS) limit configured by the 'rate' statement at the [edit services ids rule <rule-name> term <term-name> then session-limit by-source] hierarchy level. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_PFE

ASP_IDS_LIMIT_OPEN_FLOWS_BY_DEST

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type*

Description The stateful firewall discarded the packet with the indicated characteristics and did not create a new flow, because the number of open flows exceeded the intrusion detection services (IDS) limit configured by the 'maximum' statement at the [edit services ids rule <rule-name> term <term-name> then session-limit by-destination] hierarchy level. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_PFE

ASP_IDS_LIMIT_OPEN_FLOWS_BY_PAIR

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The stateful firewall discarded the packet with the indicated characteristics and did not create a new flow, because the number of open flows exceeded the intrusion detection services (IDS) limit configured by the 'maximum' statement at the [edit services ids rule <rule-name> term <term-name> then session-limit by-pair] hierarchy level. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_PFE

ASP_IDS_LIMIT_OPEN_FLOWS_BY_SRC

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The stateful firewall discarded the packet with the indicated characteristics and did not create a new flow, because the number of open flows exceeded the intrusion detection services (IDS) limit configured by the 'maximum' statement at the [edit services ids rule <rule-name> term <term-name> then session-limit by-source] hierarchy level. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_PFE

ASP_IDS_LIMIT_PKT_RATE_BY_DEST

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The stateful firewall discarded the packet with the indicated characteristics, because the number of packets per second (aggregated over all monitored flows) exceeded the intrusion detection services (IDS) limit configured by the 'packets' statement at the [edit services ids rule <rule-name> term <term-name> then session-limit by-destination] hierarchy level. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_PFE

ASP_IDS_LIMIT_PKT_RATE_BY_PAIR

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type*

Description The stateful firewall discarded the packet with the indicated characteristics, because the number of packets per second (aggregated over all monitored flows) exceeded the intrusion detection services (IDS) limit configured by the 'packets' statement at the [edit services ids rule <rule-name> term <term-name> then session-limit by-pair] hierarchy level. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_PFE

ASP_IDS_LIMIT_PKT_RATE_BY_SRC

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type*

Description The stateful firewall discarded the packet with the indicated characteristics, because the number of packets per second (aggregated over all monitored flows) exceeded the intrusion detection services (IDS) limit configured by the 'packets' statement at the [edit services ids rule <rule-name> term <term-name> then session-limit by-source] hierarchy level. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_PFE

ASP_IDS_NO_MEM_SHOW_CMD

System Log Message Not enough memory for show command

Description Intrusion detection services (IDS) could not service a request to show information from IDS tables, because not enough memory was available.

Type	Error: An error occurred
Severity	critical

Facility LOG_PFE

ASP_IDS_NULL_CLEAR_QUERY

System Log Message Failure: NULL query for CLEAR command.

Description Intrusion detection services (IDS) invoked a query handler to service a request to clear information from IDS tables. The handler did not receive the request.

Type Event: This message reports an event, not an error

Severity critical

Facility LOG_PFE

Action Contact your technical support representative.

ASP_IDS_NULL_SHOW_QUERY

System Log Message Failure: NULL query for SHOW command.

Description Intrusion detection services (IDS) invoked a query handler to service a request to show information from IDS tables. The handler did not receive the request.

Type Event: This message reports an event, not an error

Severity critical

Facility LOG_PFE

Action Contact your technical support representative.

ASP_IDS_RULE_MATCH

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name) application: application, source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type rule-set: rule-set-name, rule: rule-name, term: term-name*

Description A packet matched the indicated term in the indicated intrusion detection services (IDS) rule. If the rule belongs to a rule set, the rule set name is also displayed. The matching packet contained the indicated information about its protocol (numerical identifier and name), application, source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error

Severity info

Facility LOG_PFE

ASP_IDS_SYN_COOKIE_OFF

System Log Message Host *destination-address*, SYN-COOKIE protection deactivated

Description	Intrusion detection services (IDS) deactivated SYN cookie protection for the indicated destination address. IDS deactivates this protection when it learns from the stateful firewall that the rate of certain events has returned to a level below the threshold set by the 'threshold' statement at the [edit services ids rule <rule-name> term <term-name> then syn-cookie] hierarchy level. The relevant events include the ones reported by the ASP_IDS_TCP_SYN_ATTACK, ASP_SFW_SYN_DEFENSE, and ASP_SFW_TCP_SCAN system log messages.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_PFE

ASP_IDS_SYN_COOKIE_ON

System Log Message	Host <i>destination-address</i> , SYN-COOKIE protection activated
Description	Intrusion detection services (IDS) activated SYN cookie protection for the indicated destination address, because it learned from the stateful firewall that the rate of certain events exceeded the threshold set by the 'threshold' statement at the [edit services ids rule <rule-name> term <term-name> then syn-cookie] hierarchy level. The events include the ones reported by the ASP_IDS_TCP_SYN_ATTACK, ASP_SFW_SYN_DEFENSE, and ASP_SFW_TCP_SCAN system log messages. When SYN cookie protection is activated for a flow to a destination and the TCP handshake has not completed, the stateful firewall generates a SYN/ACK packet for each SYN packet directed to the destination.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_PFE

ASP_IDS_TCP_SYN_ATTACK

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The stateful firewall received the packet with the indicated characteristics and determined that it was a duplicate Transmission Control Protocol (TCP) SYN packet (the SYN flag was set and a SYN packet was already received for the flow to the destination). The event was reported to intrusion detection services (IDS) and can cause IDS to activate SYN cookie protection. The packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_PFE

ASP_L2TP_MESSAGE_INCOMPLETE

System Log Message	IPC message lacked variable portion
Description	The Layer 2 Tunneling Protocol (L2TP) did not process an interprocess communication (IPC) message because the variable portion of the message was missing.
Type	Error: An error occurred
Severity	error
Facility	LOG_PFE

ASP_L2TP_NO_MEM

System Log Message	Unable to allocate memory for L2TP flow for tunnel <i>tunnel-id</i> , session <i>session-id</i>
Description	The Layer 2 Tunneling Protocol (L2TP) could not allocate the memory it needed to create a flow for the indicated tunnel and session.
Type	Error: An error occurred
Severity	error
Facility	LOG_PFE

ASP_L2TP_OBJ_CAC_FAIL

System Log Message	Unable to allocate object-cache memory for flow (unit <i>unit-id</i> , tunnel <i>tunnel-id</i> , session <i>session-id</i>)
Description	The Layer 2 Tunneling Protocol (L2TP) could not allocate memory from an object cache for the flow defined by the indicated unit, tunnel, and session.
Type	Error: An error occurred
Severity	error
Facility	LOG_PFE

ASP_L2TP_STATS_BULK_QUERY_FAILED

System Log Message	Number of queries (<i>num-queries</i>) in statistics request exceeded limit (<i>max-queries</i>)
Description	The Layer 2 Tunneling Protocol (L2TP) did not process an interprocess communication (IPC) request for statistics because it included the indicated the number of queries, which exceeds the limit as indicated.
Type	Error: An error occurred
Severity	error
Facility	LOG_PFE

ASP_L2TP_STATS_VERSION_INVALID

System Log Message	Invalid version <i>received-value</i> on statistics request (expected <i>expected-value</i>)
---------------------------	---

Description The Layer 2 Tunneling Protocol process (l2tpd) received a request for statistics with the indicated version, which is not the indicated, supported version.

Type Error: An error occurred

Severity error

Facility LOG_PFE

ASP_L2TP_TUN_GRP_ADD_FAIL_ALLOC

System Log Message Unable to add tunnel group for service set *service-set*: could not allocate ID

Description The Layer 2 Tunneling Protocol (L2TP) could not add a tunnel group for the indicated service set because it could not allocate an internal ID.

Type Error: An error occurred

Severity error

Facility LOG_PFE

ASP_L2TP_TUN_GRP_ADD_FAIL_EXISTS

System Log Message Unable to add tunnel group *group-id*: it already exists

Description The Layer 2 Tunneling Protocol (L2TP) could not add a tunnel group with the indicated ID because it already existed.

Type Error: An error occurred

Severity error

Facility LOG_PFE

ASP_L2TP_TUN_GRP_CHG_FAIL_ALLOC

System Log Message Unable to change tunnel group for service set *service-set*: could not allocate ID

Description The Layer 2 Tunneling Protocol (L2TP) could not change a tunnel group for the indicated service set because it could not allocate an internal ID.

Type Error: An error occurred

Severity error

Facility LOG_PFE

ASP_L2TP_TUN_GRP_CHG_FAIL_INVLD

System Log Message Unable to change tunnel group *group-id*: ID is invalid

Description The Layer 2 Tunneling Protocol (L2TP) could not change the tunnel group with the indicated internal ID, because the ID is invalid.

Type Error: An error occurred

Severity error

Facility LOG_PFE

ASP_L2TP_TUN_GRP_DEL_FAIL_INVLD

System Log Message Unable to delete tunnel group *group-id*: ID is invalid

Description The Layer 2 Tunneling Protocol (L2TP) could not delete the tunnel group with the indicated internal ID, because the ID is invalid.

Type Error: An error occurred

Severity error

Facility LOG_PFE

ASP_NAT_OUTOF_ADDRESSES

System Log Message natpool *nat-pool-name* is out of addresses

Description Network Address Translation (NAT) services could not allocate an address from the indicated NAT pool, because no addresses were available.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_PFE

ASP_NAT_OUTOF_PORTS

System Log Message natpool *nat-pool-name* is out of ports

Description Network Address Translation (NAT) services could not allocate a port from the indicated NAT pool, because no ports were available.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_PFE

ASP_NAT_POOL_RELEASE

System Log Message natpool release *address:port[count]*

Description Network Address Translation (NAT) services made the indicated number of ports available in the pool for the indicated address, starting at the indicated port number.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_PFE

ASP_NAT_RULE_MATCH

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name) application: application, source-interface-nameseparator source-address:source-port ->*

*destination-address**destination-port*, *event-type* rule-set: *rule-set-name*, rule: *rule-name*, term: *term-name*

Description A packet matched the indicated term in the indicated Network Address Translation (NAT) rule. If the rule belongs to a rule set, the rule set name is also displayed. The matching packet contained the indicated information about its protocol (numerical identifier and name), application, source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error

Severity info

Facility LOG_PFE

ASP_PGCP_IPC_MSG_WRITE_FAILED

System Log Message Unable to write IPC message (type *message-type*, subtype *message-subtype*): status code *status*

Description The Packet Gateway Control Protocol (PGCP) client on the MultiServices Physical Interface Card (PIC) could not write an interprocess communication (IPC) message to the end of its pipe.

Type Error: An error occurred

Severity error

Facility LOG_PFE

ASP_PGCP_IPC_PIPE_WRITE_FAILED

System Log Message Unable to write IPC message (type *message-type*, subtype *message-subtype*) to pipe: status code *status*

Description The Packet Gateway Control Protocol (PGCP) client on the MultiServices Physical Interface Card (PIC) could not write the contents of its interprocess communication (IPC) pipe to the socket layer.

Type Error: An error occurred

Severity error

Facility LOG_PFE

ASP_SFW_ALG_LEVEL_ADJUSTED

System Log Message ALG *sfw-application-name* specified by stateful firewall or CoS rule was reduced to *nat-application-name*, because twice NAT does not support ALG *application*

Description A twice Network Address Translation (NAT) rule is applied to the same source or destination addresses as a stateful firewall or class-of-service (CoS) rule that applies an application-level gateway (ALG) other than Internet Control Message Protocol (ICMP) or traceroute. The configuration is invalid, because only those ALGs are supported in combination with twice NAT. The ALG configured in the stateful firewall or CoS rule was ignored, and only the application configured in the twice-NAT rule was applied. The

adaptive services software accomplished this internally by adjusting the indicated ALG value (which is not supported with twice NAT) to the indicated supported value.

Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_PFE
Action	Change the configuration so that twice-NAT rules (defined at the [edit services nat] hierarchy level) are not applied to the same source or destination addresses as rules defined at the [edit services stateful-firewall] or [edit services cos] hierarchy level that include ALGs other than the supported ones.

ASP_SFW_ALG_PROMOTION_FAILED

System Log Message	ALG promotion failed. Stateful firewall application <i>sfw-application-name</i> conflicts with NAT application <i>nat-application-name</i> or conflicts with QoS application; request creation of discard flow
Description	A matching application-level gateway protocol (ALG) was found from both the indicated stateful firewall rule and either the indicated Network Address Translation (NAT) rule or a quality-of-service (QoS) rule, but the two ALGs were not at the same level.
Type	Event: This message reports an event, not an error
Severity	critical
Facility	LOG_PFE
Action	Resolve the conflicting application-protocol matching conditions in the rules at the [edit services stateful-firewall] hierarchy level and either the [edit services cos] (for QoS rules) or [edit services nat] (for NAT rules) hierarchy level.

ASP_SFW_APP_MSG_TOO_LONG

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The stateful firewall discarded the Transmission Control Protocol (TCP) packet with the indicated characteristics, because the packet was so large that it exhausted memory resources. The packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_PFE

Action Delete active flows to forcibly free memory, or wait for the system to reclaim memory. Consider creating more service sets among which resources can be divided. Otherwise, contact your technical support representative.

ASP_SFW_CHANGE_INACTIVITY_TIMER

System Log Message change global inactivity timer to *value1* open timeout to *value2*

Description The global inactivity timer and the open timeout were set to the indicated values.

Type Event: This message reports an event, not an error

Severity critical

Facility LOG_PFE

ASP_SFW_CREATE_ACCEPT_FLOW

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name) application: application, source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type nat-information softwire-information*

Description The packet with the indicated characteristics matched a stateful firewall rule that has the 'accept' action, and the stateful firewall created a flow. If the flow requires Network Address Translation (NAT) services, NAT information appears at the end of the message. The matching packet contained the indicated information about its protocol (numerical identifier and name), application, source (logical interface name, IP address, and port number), and destination (IP address and port number), and if relevant, Softwire source and destination IP addresses

Type Event: This message reports an event, not an error

Severity info

Facility LOG_PFE

ASP_SFW_CREATE_DISCARD_FLOW

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name) application: application, source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type*

Description The packet with the indicated characteristics matched a stateful firewall rule that has the 'discard' action, and the stateful firewall created a discard flow. The matching packet contained the indicated information about its protocol (numerical identifier and name), application, source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_PFE

ASP_SFW_CREATE_REJECT_FLOW

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name) application: application, source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The packet with the indicated characteristics matched a stateful firewall rule that has the 'reject' action, and the stateful firewall created a reject flow. The matching packet contained the indicated information about its protocol (numerical identifier and name), application, source (logical interface name, IP address, and port number), and destination (IP address and port number).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_PFE

ASP_SFW_DELETE_FLOW

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name) application: application, source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type nat-information software-information</i>
Description	The flow with the indicated characteristics was removed from the system. If the flow required Network Address Translation (NAT) services, NAT information appears at the end of the message. The flow indicated information about its protocol (numerical identifier and name), application, source (logical interface name, IP address, and port number), destination (IP address and port number), and if relevant, Softwire source and destination IP addresses.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_PFE

ASP_SFW_FTP_ACTIVE_ACCEPT

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name) application: application, source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type nat-information</i>
Description	When the stateful firewall receives PORT/EPRT commands in the control channel, it creates a flow in anticipation of an FTP data connection from client to server. The packet with the indicated characteristics matched such a flow. If the flow requires Network Address Translation (NAT) services, NAT information appears at the end of the message. The matching packet contained the indicated information about its protocol (numerical identifier and name), application, source (logical interface name, IP address, and port number), and destination (IP address and port number).
Type	Event: This message reports an event, not an error
Severity	notice

Facility LOG_PFE

ASP_SFW_FTP_PASSIVE_ACCEPT

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name) application: application, source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type nat-information*

Description When the stateful firewall receives PASV/EPSV commands in the control channel, it creates a flow in anticipation of an FTP data connection from server to client. The packet with the indicated characteristics matched such a flow. If the flow requires Network Address Translation (NAT) services, NAT information appears at the end of the message. The matching packet contained the indicated information about its protocol (numerical identifier and name), application, source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_PFE

ASP_SFW_ICMP_ERROR_DROP

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type*

Description The stateful firewall discarded the Internet Control Message Protocol (ICMP) error packet with the indicated characteristics, because the packet did not belong to an existing flow. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_PFE

ASP_SFW_ICMP_HEADER_LEN_ERROR

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type*

Description The stateful firewall discarded the Internet Control Message Protocol (ICMP) packet with the indicated characteristics, because the length field in the packet header was shorter than the minimum 8 bytes required for an ICMP packet. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error

Severity notice
Facility LOG_PFE

ASP_SFW_ICMP_PACKET_ERROR_LENGTH

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name),
source-interface-nameseparatorsource-address:source-port ->
destination-addressdestination-port, event-type*

Description The stateful firewall discarded the Internet Control Message Protocol (ICMP) error packet with the indicated characteristics, because the packet contained fewer than 48 bytes of data, or more than 576. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_PFE

ASP_SFW_IP_FRAG_ASSEMBLY_TIMEOUT

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name),
source-interface-nameseparatorsource-address:source-port ->
destination-addressdestination-port, event-type*

Description The stateful firewall discarded the packet with the indicated characteristics and all related IP fragments it had previously received, because all fragments did not arrive within the four-second reassembly timeout period. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_PFE

ASP_SFW_IP_FRAG_OVERLAP

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name),
source-interface-nameseparatorsource-address:source-port ->
destination-addressdestination-port, event-type*

Description The stateful firewall discarded the packet with the indicated characteristics and all related IP fragments it had previously received, because the contents of two fragments overlapped. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error
Severity notice

Facility LOG_PFE

ASP_SFW_IP_OPTION_DROP_PACKET

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type*

Description The stateful firewall discarded the packet with the indicated characteristics, because the packet contained nonconfigured IP option types. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_PFE

ASP_SFW_IP_PACKET_CHECKSUM_ERROR

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type*

Description The stateful firewall discarded the packet with the indicated characteristics, because the packet checksum was incorrect. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_PFE

ASP_SFW_IP_PACKET_DST_BAD

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type*

Description The stateful firewall discarded the packet with the indicated characteristics, because the packet destination address was either a multicast address or was in the range reserved for experimental use (248.0.0.0 through 255.255.255.254). The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_PFE

ASP_SFW_IP_PACKET_FRAG_LEN_INV

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The stateful firewall discarded the packet with the indicated characteristics and all related IP fragments it had previously received, because the length of a fragment was invalid. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_PFE

ASP_SFW_IP_PACKET_INCORRECT_LEN

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The stateful firewall discarded the IP packet with the indicated characteristics, because the packet length was invalid. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_PFE

ASP_SFW_IP_PACKET_LAND_ATTACK

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The stateful firewall discarded the IP packet with the indicated characteristics, because the source and destination address for the packet were the same (referred to as a land attack). The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_PFE

ASP_SFW_IP_PACKET_NOT_VERSION_4

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The stateful firewall discarded the IP packet with the indicated characteristics, because the packet version was not IP version 4 (IPv4). The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_PFE

ASP_SFW_IP_PACKET_PROTOCOL_ERROR

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The stateful firewall discarded the IP packet with the indicated characteristics, because the packet used an invalid protocol. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_PFE

ASP_SFW_IP_PACKET_SRC_BAD

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The stateful firewall discarded the packet with the indicated characteristics, because the packet source address was one of the following: (1) a multicast address (2) a broadcast address (3) in the range 127.0.0.0 through 127.255.255.255 (4) in the range 248.0.0.0 through 255.255.255.254, which is reserved for experimental use. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_PFE

ASP_SFW_IP_PACKET_TOO_LONG

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The stateful firewall discarded the IP packet with the indicated characteristics, because the packet contained more than 64 kilobytes (KB) of data (referred to as a ping-of-death attack). The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_PFE

ASP_SFW_IP_PACKET_TOO_SHORT

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The stateful firewall discarded the IP packet with the indicated characteristics, because the packet did not contain the minimum amount of data required. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_PFE

ASP_SFW_IP_PACKET_TTL_ERROR

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The stateful firewall discarded the IP packet with the indicated characteristics, because the packet had a time-to-live (TTL) value of 0 (zero). The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_PFE

ASP_SFW_NEW_POLICY

System Log Message	install new configuration
Description	A new stateful firewall policy was installed.
Type	Event: This message reports an event, not an error
Severity	critical
Facility	LOG_PFE

ASP_SFW_NO_IP_PACKET

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The stateful firewall received the packet with the indicated characteristics, which was not an IP packet. The packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_PFE

ASP_SFW_NO_POLICY

System Log Message	<i>source-address -> destination-address</i> No policy
Description	The stateful firewall received packets with the indicated source and destination addresses. There was no matching policy for the traffic.
Type	Event: This message reports an event, not an error
Severity	critical
Facility	LOG_PFE

ASP_SFW_NO_RULE_DROP

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The stateful firewall discarded the packet with the indicated characteristics, because the packet did not match and stateful firewall rules. In this case, the default action is to discard the packet. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).
Type	Event: This message reports an event, not an error

Severity notice
Facility LOG_PFE

ASP_SFW_PING_DUPLICATED_SEQNO

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name),
source-interface-nameseparatorsource-address:source-port ->
destination-addressdestination-port, event-type*

Description The stateful firewall discarded the Internet Control Message Protocol (ICMP) echo request packet with the indicated characteristics, because packet's sequence number was the same as in a previous packet. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_PFE

ASP_SFW_PING_MISMATCHED_SEQNO

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name),
source-interface-nameseparatorsource-address:source-port ->
destination-addressdestination-port, event-type*

Description The stateful firewall discarded the Internet Control Message Protocol (ICMP) echo reply packet with the indicated characteristics, because the firewall had not previously received an echo request packet with the same sequence number. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_PFE

ASP_SFW_PING_OUTOF_SEQNO_CACHE

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name),
source-interface-nameseparatorsource-address:source-port ->
destination-addressdestination-port, event-type*

Description The stateful firewall discarded the Internet Control Message Protocol (ICMP) echo request packet with the indicated characteristics, because it had not received echo replies for an excessive number of previously received echo requests. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error

Severity notice
Facility LOG_PFE

ASP_SFW_POLICY_REJECT

System Log Message reject configuration because *reason*

Description A newly installed stateful firewall policy was rejected for the indicated reason.

Type Event: This message reports an event, not an error

Severity critical

Facility LOG_PFE

ASP_SFW_RULE_ACCEPT

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name) application: application, source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type rule-set: rule-set-name, rule: rule-name, term: term-name*

Description The packet with the indicated characteristics matched the indicated term in the indicated stateful firewall rule, which has an 'accept' action. If the rule belongs to a rule set, the rule set name is also displayed. The stateful firewall accepted the flow to which the packet belongs. The matching packet contained the indicated information about its protocol (numerical identifier and name), application, source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error

Severity info

Facility LOG_PFE

ASP_SFW_RULE_DISCARD

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name) application: application, source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type rule-set: rule-set-name, rule: rule-name, term: term-name*

Description The packet with the indicated characteristics matched the indicated term in the indicated stateful firewall rule, which has a 'discard' action. If the rule belongs to a rule set, the rule set name is also displayed. The stateful firewall discarded the packet. The matching packet contained the indicated information about its protocol (numerical identifier and name), application, source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_PFE

ASP_SFW_RULE_REJECT

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name) application: application, source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type rule-set: rule-set-name, rule: rule-name, term: term-name</i>
Description	The packet with the indicated characteristics matched the indicated term in the indicated stateful firewall rule, which has a 'reject' action. If the rule belongs to a rule set, the rule set name is also displayed. If the packet used the User Datagram Protocol (UDP), the stateful firewall generated an Internet Control Message Protocol (ICMP) error message. If the packet used the Transmission Control Protocol (TCP), the stateful firewall generated an RST packet. The matching packet contained the indicated information about its protocol (numerical identifier and name), application, source (logical interface name, IP address, and port number), and destination (IP address and port number).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_PFE

ASP_SFW_SYN_DEFENSE

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The stateful firewall discarded the packet with the indicated characteristics, because the Transmission Control Protocol (TCP) handshake that is used to establish a session did not complete quickly enough. The time limit is set by the 'open-timeout' statement at the [edit interfaces <services-interface> services-options] hierarchy level or is four seconds by default. The event was reported to intrusion detection services (IDS) and can cause IDS to activate SYN cookie protection. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_PFE
Cause	Possible causes for the handshake failure include the following: (1) sequence numbers did not match in a SYN packet and a previous SYN packet (the second packet was not a retransmission) (2) sequence numbers did not match in a SYN/ACK packet and a previous SYN packet (3) either or both a SYN/ACK packet and an ACK packet did not arrive at the firewall within the time limit.

ASP_SFW_TCP_BAD_SYN_COOKIE_RESP

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The stateful firewall discarded the Transmission Control Protocol (TCP) ACK packet with the indicated characteristics, either because it is the first packet in a session, or because its sequence number did not match the sequence number in the SYN/ACK packet that the firewall previously generated for the session. The firewall generates SYN/ACK packets when SYN cookie protection is activated. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_PFE

ASP_SFW_TCP_FLAGS_ERROR

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The stateful firewall discarded the Transmission Control Protocol (TCP) packet with the indicated characteristics, because the flags in the packet were set in one of the following combinations: (1) FIN and RST (2) SYN and one or more of FIN, RST, and URG. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_PFE

ASP_SFW_TCP_HEADER_LEN_ERROR

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The stateful firewall discarded the Transmission Control Protocol (TCP) packet with the indicated characteristics, because the length field in the packet header was shorter than the minimum 20 bytes required for a TCP packet. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_PFE

ASP_SFW_TCP_NON_SYN_FIRST_PACKET

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type*

Description The stateful firewall discarded the Transmission Control Protocol (TCP) packet with the indicated characteristics, because it was the first packet in the TCP session but the SYN flag was not set. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_PFE

ASP_SFW_TCP_PORT_ZERO

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type*

Description The stateful firewall discarded the Transmission Control Protocol (TCP) packet with the indicated characteristics, because the source or destination port specified in the packet was zero (0). The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_PFE

ASP_SFW_TCP_RECONSTRUCT_DROP

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type*

Description The stateful firewall discarded the Transmission Control Protocol (TCP) packet with the indicated characteristics, because the session to which the packet belongs violated TCP standards. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error

Severity	notice
Facility	LOG_PFE
Cause	Possible causes include the following: (1) the amount of previously received but unacknowledged data exceeded the TCP window (2) there were sequence number errors (gaps in the sequence or packets with overlapping numbers).

ASP_SFW_TCP_SCAN

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The stateful firewall received a Transmission Control Protocol (TCP) RST packet from a server, indicating that the server rejected a connection attempt directed to the indicated destination address and port. The event was reported to intrusion detection services (IDS) and can cause IDS to activate SYN cookie protection. The RST packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_PFE

ASP_SFW_TCP_SEQNO_AND_FLAGS_ZERO

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The stateful firewall discarded the Transmission Control Protocol (TCP) packet with the indicated characteristics, because the packet's sequence number was 0 (zero) and no flags were set. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_PFE

ASP_SFW_TCP_SEQNO_ZERO_FLAGS_SET

System Log Message	<i>syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type</i>
Description	The stateful firewall discarded the Transmission Control Protocol (TCP) packet with the indicated characteristics, because the packet's sequence number was 0 (zero) and one or more of the FIN, PSH, and RST flags were set. The discarded packet contained the

indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_PFE

ASP_SFW_UDP_HEADER_LEN_ERROR

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type*

Description The stateful firewall discarded the User Datagram Protocol (UDP) packet with the indicated characteristics, because the length field in the packet header was shorter than the minimum 8 bytes required for an UDP packet. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_PFE

ASP_SFW_UDP_PORT_ZERO

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type*

Description The stateful firewall discarded the User Datagram Protocol (UDP) packet with the indicated characteristics, because the source or destination port specified in the packet was zero (0). The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_PFE

ASP_SFW_UDP_SCAN

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type*

Description The stateful firewall received an Internet Control Message Protocol (ICMP) error message from a server running at the indicated destination address and User Datagram Protocol

(UDP) port. The error packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_PFE

ASP_SFW_VERY_BAD_PACKET

System Log Message *syslog-prefix error-code: proto protocol-id (protocol-name), source-interface-nameseparatorsource-address:source-port -> destination-addressdestination-port, event-type*

Description The stateful firewall discarded the packet with the indicated characteristics, because the packet was malformed. The discarded packet contained the indicated information about its protocol (numerical identifier and name), source (logical interface name, IP address, and port number), and destination (IP address and port number).

Type Event: This message reports an event, not an error
Severity critical
Facility LOG_PFE

ASP_SVC_SET_MAX_FLOWS_EXCEEDED

System Log Message Number of flows (currently *current-flows*) exceeded configured limit (*maximum-value*) *count* times in previous 60 seconds

Description A flow was not created for a service and service set, because the current number of flows for all supported services exceeded the limit configured with the 'max-flows' statement at the [edit services service-set <service-set-name>] hierarchy level. The message appears once per minute and reports the number of times in the previous 60 seconds that the system noted the excessive number of flows.

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_PFE

CHAPTER 11

AUDITD System Log Messages

This chapter describes messages with the **AUDITD** prefix. They are generated by the audit process (auditd), which notifies the RADIUS accounting server of user activity on the routing platform, such as login, logout, and execution of command-line interface (CLI) commands.

AUDITD_RADIUS_AV_ERROR

System Log Message	Unable to create <i>type</i> record: <i>error-message</i>
Description	The audit process (auditd) experienced the indicated error when building RADIUS attribute-value (AV) pairs for the indicated type of accounting request, which can be a login or logout event, or a command issued in the CLI.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

AUDITD_RADIUS_OPEN_FAILED

System Log Message	<i>function-name</i> : unable to create RADIUS object handle (<i>error-message</i>)
Description	The audit process (auditd) could not create a RADIUS object handle, which it uses for various RADIUS operations.
Type	Error: An error occurred
Severity	emergency
Facility	LOG_DAEMON

AUDITD_RADIUS_REQ_CREATE_FAILED

System Log Message	Unable to create RADIUS request: <i>error-message</i>
Description	The audit process (auditd) could not create a RADIUS accounting request for the indicated reason.
Type	Error: An error occurred
Severity	error

Facility LOG_DAEMON

AUDITD_RADIUS_REQ_DROPPED

System Log Message Discarded Accounting-Request message; no RADIUS server responded

Description The audit process (auditd) gathers information about system accounting events from other system processes and sends the information to RADIUS servers in an Accounting-Request message. The process repeatedly sent a message to all configured RADIUS servers without receiving a response, so it discarded the message.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause The RADIUS accounting servers are not correctly configured or are unreachable, or the server applications are not responding.

AUDITD_RADIUS_REQ_SEND_ERROR

System Log Message *function-name: error-message*

Description The audit process (auditd) experienced the indicated error when it requested accounting information from a RADIUS server.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause An internal software failure occurred.

Action Contact your technical support representative.

AUDITD_RADIUS_REQ_TIMED_OUT

System Log Message Retransmitted request to RADIUS server *radius-server*

Description The audit process (auditd) gathers information about system accounting events from other system processes and sends the information to RADIUS servers in an Accounting-Request message. After failing to receive a response from the indicated server, auditd waited for a timeout period and resent the message.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause The RADIUS server is not responding. Possible reasons include (a) the server machine is down, too busy, or unreachable (b) the server application is down or too busy (c) the shared RADIUS secret sent by auditd does not match the secret on the server.

AUDITD_RADIUS_SERVER_ADD_ERROR

System Log Message	Unable to add RADIUS server <i>radius-server: error-message</i>
Description	The audit process (auditd) read the RADIUS accounting server configuration, but could not add the indicated server to the internal structure used to track servers.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

AUDITD_SOCKET_FAILURE

System Log Message	<i>function-name: unable to operation socket (error-message)</i>
Description	The audit process (auditd) listens on a Transmission Control Protocol (TCP) socket for system accounting events reported by other processes on the routing platform. The indicated socket operation failed with the indicated error.
Type	Error: An error occurred
Severity	emergency
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

CHAPTER 12

AUTHD System Log Messages

This chapter describes messages with the AUTHD prefix. They are generated by the generic authentication service process (authd) which is a security service that verifies an identity that is claimed by or for a system entity.

AUTHD_AUTH_CREATE_FAILED

System Log Message	Unable to allocate authentication handle: <i>error-message</i>
Description	The generic authentication service process (authd) could not allocate an authentication object for the indicated reason.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

AUTHD_RADIUS_GETHOSTNAME_FAILED

System Log Message	Unable to obtain hostname for outgoing RADIUS message: <i>error-message</i>
Description	The generic authentication service process (authd) could not obtain a hostname for an outgoing RADIUS message.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

AUTHD_SERVER_INIT_BIND_FAIL

System Log Message	Unable to bind to socket <i>file-descriptor: error-message</i> (errno error-code)
Description	The generic authentication service process (authd) could not bind the server to the address specified.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

AUTHD_SERVER_INIT_LISTEN_FAIL

System Log Message	Unable to listen on socket <i>file-descriptor: error-message</i> (errno error-code)
Description	The generic authentication service process (authd) could not initialize listening on the server for the indicated socket.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

CHAPTER 13

AUTOCONF System Log Messages

This chapter describes messages with the **AUTOCONF** prefix. They are generated by the auto-configuration process (autoconfd).

AUTOCONF_AUTHENTICATE_LICENSE

System Log Message	Authentication failed due to license error. Total license failures <i>count</i>
Description	The auto-configuration process (autoconfd) failed to authenticate the clients because there were no licenses or an insufficient number of licenses. The indicated number of license failures occurred and the clients were denied access and configuration.
Type	Error: An error occurred
Severity	alert
Facility	LOG_DAEMON
Action	Add or update the license for authentication

CHAPTER 14

AUTOD System Log Messages

This chapter describes messages with the **AUTOD** prefix. They are generated by the autoinstallation process (autod), which controls the initialization of J Series Services Routers.

AUTOD_BIND_FAILURE

System Log Message	Unable to bind address to socket: <i>error-message</i>
Description	The autoinstallation process (autod) received the indicated error when it tried to bind a socket to an address.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

AUTOD_HOSTNAME_EXPANSION_FAILURE

System Log Message	Unable to expand compressed DNS domain name: <i>error-message</i>
Description	The autoinstallation process (autod) received the indicated error when it tried to expand a compressed Domain Name System (DNS) domain name.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

AUTOD_RECV_FAILURE

System Log Message	Unable to receive on socket: <i>error-message</i>
Description	The autoinstallation process (autod) received the indicated error when it tried to receive data on a socket.
Type	Error: An error occurred

Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

AUTOD_RES_MKQUERY_FAILURE

System Log Message	DNS query failed: <i>error-message</i>
Description	The autoinstallation process (autod) received the indicated error when it made a Domain Name System (DNS) query.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

AUTOD_SEND_FAILURE

System Log Message	Unable to send on socket: <i>error-message</i>
Description	The autoinstallation process (autod) received the indicated error when it tried to send data on a socket.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

AUTOD_SOCKET_CREATE_FAILURE

System Log Message	Unable to create socket: <i>error-message</i>
Description	The autoinstallation process (autod) received the indicated error when it tried to create a socket.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHAPTER 15

AV System Log Messages

This chapter describes messages with the **AV** prefix. They are generated by the antivirus scanning process (avd).

AV_HUGE_FILE_DROPPED_MT

System Log Message	AntiVirus: Content from <i>source-address:source-port</i> to <i>destination-address:destination-port</i> <i>filename</i> was dropped because maximum content size was exceeded.
Description	The antivirus scanner dropped the received traffic without scanning because the file size exceeds the maximum content limit; see product Release Notes for the maximum content size supported on a device
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_PFE

AV_HUGE_FILE_NOT_SCANNED_MT

System Log Message	AntiVirus: Content from <i>source-address:source-port</i> to <i>destination-address:destination-port</i> <i>filename</i> was not scanned because maximum content size was exceeded.
Description	The antivirus scanner passed the received traffic without scanning because the file size exceeds the maximum content limit; see product Release Notes for the maximum content size supported on a device
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_PFE

AV_MANY_MSGS_DROPPED_MT

System Log Message	AntiVirus: Content from <i>source-address:source-port</i> to <i>destination-address:destination-port</i> <i>filename</i> dropped because the maximum number of concurrent messages exceeded.
Description	The antivirus scanner dropped the received traffic because the maximum number of concurrent messages to scan is exceeded
Type	Event: This message reports an event, not an error

Severity warning
Facility LOG_PFE

AV_MANY_MSGS_NOT_SCANNED_MT

System Log Message AntiVirus: Content from *source-address:source-port* to *destination-address:destination-port filename* was not scanned because the maximum number of concurrent messages are exceeded.

Description The antivirus scanner passed the received traffic without scanning because the maximum number of concurrent messages to scan is exceeded

Type Event: This message reports an event, not an error
Severity warning
Facility LOG_PFE

AV_PATTERN_GET_FAILED

System Log Message AntiVirus: cannot retrieve pattern *error-message* file due to *error-code (status-code)*.

Description The device was unable to access or retrieve an antivirus pattern file from a server, identified by IP address and port number, through HTTP. The error code provides information you need to get help from Juniper Networks technical support

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_FIREWALL
Cause Unable to retrieve an antivirus pattern file from the server
Action Contact Juniper Networks technical support

AV_PATTERN_KEY_EXPIRED

System Log Message AntiVirus: Attempt to *time* failed due to *date*, please renew to receive updates.

Description The internal antivirus scanner was unsuccessful in downloading the antivirus pattern file, because the AV license key has been expired

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_FIREWALL
Cause Download the antivirus pattern file while antivirus license key has been expired
Action Renew the antivirus license key

AV_PATTERN_KL_CHECK_FAILED

System Log Message	AntiVirus: db file signature mismatch: <i>error-message</i> .
Description	The device is unable to use Kaspersky's pattern file. The error message provides information you need to give Juniper Networks technical support
Type	Event: This message reports an event, not an error
Severity	critical
Facility	LOG_FIREWALL
Cause	The device is unable to use Kaspersky's pattern file
Action	Contact Juniper Networks technical support

AV_PATTERN_TOO_BIG

System Log Message	AntiVirus: The pattern file specified in server is too large(<i>file-size</i> bytes)
Description	The pattern file size specified in the server initialization file (server.ini) exceeds the maximum prescribed limit
Type	Event: This message reports an event, not an error
Severity	alert
Facility	LOG_FIREWALL
Cause	The pattern file size specified in the server initialization file exceeds the limit
Action	Contact Juniper Networks technical support

AV_PATTERN_UPDATED

System Log Message	AntiVirus: Pattern file updated. Version: <i>version</i> ; size: <i>file-size</i> bytes
Description	The internal antivirus scanner successfully updated the pattern file and may have changed the size of the file in the process
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_FIREWALL
Cause	The internal antivirus scanner successfully updated the antivirus pattern file
Action	No recommended action

AV_PATTERN_WRITE_FS_FAILED

System Log Message	AntiVirus: db file save failed: <i>error-code</i>
---------------------------	---

Description	The device is unable to save contents of an antivirus pattern file to the file system
Type	Event: This message reports an event, not an error
Severity	critical
Facility	LOG_FIREWALL
Cause	The device is unable to save contents of an antivirus pattern file to the file system
Action	Contact Juniper Networks technical support

AV_SCANNER_DROP_FILE_MT

System Log Message	AntiVirus: Content from <i>source-address:source-port</i> to <i>destination-address:destination-port</i> <i>filename</i> was dropped because scan-engine error or constraint with code <i>error-code</i> for <i>error-message</i> .
Description	The antivirus scanner dropped the received traffic because of an internal error
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_PFE

AV_SCANNER_ERROR_SKIPPED_MT

System Log Message	AntiVirus: Content from <i>source-address:source-port</i> to <i>destination-address:destination-port</i> <i>filename</i> was not scanned because scan-engine error or constraint with code <i>error-code</i> for <i>error-message</i> .
Description	The antivirus scanner passed the received traffic because of an internal error
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_PFE

AV_SCANNER_READY

System Log Message	AntiVirus:The scan engine is ready.
Description	The antivirus scan engine is ready to scan the traffic
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_FIREWALL
Cause	The antivirus scan engine is ready
Action	No recommended action

AV_VIRUS_DETECTED_MT

System Log Message	AntiVirus: Virus detected: from <i>source-address:source-port</i> to <i>destination-address:destination-port</i> <i>source-zone source-zone-name filename</i> file <i>temporary-filename</i> virus <i>name</i> URL: http://www.viruslist.com/en/search?VN=url
Description	The antivirus scanner has detected a virus; the log will show source and destination port and IP, source zone, contaminated file, virus name and URL link with virus description
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_PFE

CHAPTER 16

BFDD System Log Messages

This chapter describes messages with the **BFDD** prefix. They are generated by the Bidirectional Forwarding Detection protocol process (bfdd), which detects failures in the bidirectional path between two routing platforms.

BFDD_MIRROR_ERROR

System Log Message	Unable to establish BFD mirror connection between Routing Engines: <i>error-message</i>
Description	The Bidirectional Forwarding Detection process (bfdd) could not establish the mirror connection (which supports nonstop routing) between the master and backup Routing Engines.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Cause	The master and backup Routing Engines are running incompatible versions of the Junos OS.
Action	Update the Junos OS to compatible versions on the master and backup Routing Engines.

BFDD_MIRROR_VERSION_MISMATCH

System Log Message	Versions of BFD mirror software on Routing Engines are incompatible: <i>error-message</i>
Description	While trying to establish the mirror connection (which supports nonstop routing) between the master and backup Routing Engines, the Bidirectional Forwarding Detection process (bfdd) determined that the versions of Junos OS on the Routing Engines were incompatible.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Action	Update the Junos OS to compatible versions on the master and backup Routing Engines.

BFDD_READ_ERROR

System Log Message	Read error on <i>pipe-type</i> pipe: <i>reason (error-message)</i>
Description	The Bidirectional Forwarding Detection process (bfd) could not read the message available on the indicated type of pipe.
Type	Error: An error occurred
Severity	info
Facility	LOG_DAEMON
Action	Contact your technical support representative.

BFDD_TRAP_MHOP_STATE_DOWN

System Log Message	local discriminator: <i>session-id</i> , new state: <i>state</i> , peer addr: <i>pip-interface</i>
Description	The state changed to 'down' or 'admin down' for the indicated Bidirectional Forwarding Detection process (bfd) session.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

BFDD_TRAP_MHOP_STATE_UP

System Log Message	local discriminator: <i>session-id</i> , new state: <i>state</i> , peer addr: <i>pip-interface</i>
Description	The state changed to 'up' for the indicated Bidirectional Forwarding Detection process (bfd) session.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

BFDD_TRAP_SHOP_STATE_DOWN

System Log Message	local discriminator: <i>session-id</i> , new state: <i>state</i> , interface: <i>pip-interface</i> , peer addr: <i>remote-peer</i>
Description	The state changed to 'down' or 'admin down' for the indicated Bidirectional Forwarding Detection process (bfd) session.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

BFDD_TRAP_SHOP_STATE_UP

System Log Message	local discriminator: <i>session-id</i> , new state: <i>state</i> , interface: <i>pip-interface</i> , peer addr: <i>remote-peer</i>
Description	The state changed to 'up' for the indicated Bidirectional Forwarding Detection process (bfd) session.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

BFDD_TRAP_STATE_DOWN

System Log Message	local discriminator: <i>session-id</i> , new state: <i>state</i>
Description	The state changed to 'down' or 'admin down' for the indicated Bidirectional Forwarding Detection process (bfd) session.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

BFDD_TRAP_STATE_UP

System Log Message	local discriminator: <i>session-id</i> , new state: <i>state</i>
Description	The state changed to 'up' for the indicated Bidirectional Forwarding Detection process (bfd) session.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

BFDD_WRITE_ERROR

System Log Message	<i>function-name</i> : write error on <i>pipe-type</i> pipe (<i>error-message</i>)
Description	The Bidirectional Forwarding Detection process (bfd) could not write a message to the indicated type of pipe.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHAPTER 17

BOOTPD System Log Messages

This chapter describes messages with the **BOOTPD** prefix. They are generated by the boot parameter process (tnp.bootpd), which provides the appropriate boot string to hardware components as they initialize.

BOOTPD_ARG_ERR

System Log Message	Ignoring unknown option <i>-option</i>
Description	The indicated option was provided on the 'tnp.bootpd' command line and is invalid. The boot parameter process (tnp.bootpd) initialized but ignored the invalid option.
Type	Error: An error occurred
Severity	warning
Facility	ANY
Action	Remove the invalid option from the 'tnp.bootpd' command line.

BOOTPD_BAD_ID

System Log Message	Unexpected ID 0x <i>assembly-id</i>
Description	As each hardware component on the routing platform initializes, it requests a boot string from the boot parameter process (tnp.bootpd). The boot strings are defined in the configuration file tnp.bootpd. A request failed because it included the indicated assembly ID, for which there is no definition in the file.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	ANY

BOOTPD_BOOTSTRING

System Log Message	Boot string: <i>boot-string</i>
Description	As each hardware component on the routing platform initializes, it requests a boot string from the boot parameter process (tnp.bootpd). tnp.bootpd responded with the indicated boot string.

Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

BOOTPD_CONFIG_ERR

System Log Message	Problems with configuration file ' <i>filename</i> ', using defaults
Description	The boot parameter process (tnp.bootpd) could not read the indicated configuration file, so it initialized using default settings defined at compile time.
Type	Error: An error occurred
Severity	error
Facility	ANY
Action	Correct the configuration file.

BOOTPD_CONF_OPEN

System Log Message	Unable to open configuration file ' <i>filename</i> '
Description	The boot parameter process (tnp.bootpd) could not open the indicated configuration file, so it initialized using default settings defined at compile time.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	ANY
Action	Contact your technical support representative.

BOOTPD_DUP_PIC_SLOT

System Log Message	Duplicate default value defined for PIC <i>pic-slot</i> in FPC <i>fpc-slot</i>
Description	As each hardware component on the routing platform initializes, it requests a boot string from the boot parameter process (tnp.bootpd). The boot strings are defined in the configuration file for tnp.bootpd. There was more than one definition in the file for the indicated Physical Interface Card (PIC) slot in the indicated Flexible PIC Concentrator (FPC), so tnp.bootpd used the first definition it found.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	ANY
Action	Remove the extra definitions from the configuration file.

BOOTPD_DUP_REV

System Log Message	Duplicate revision: <i>major-version.minor-version</i>
Description	As each hardware component on the routing platform initializes, it requests a boot string from the boot parameter process (tnp.bootpd). The boot strings are defined in the configuration file for tnp.bootpd. There was more than one definition in the file for the indicated revision of a component, so tnp.bootpd used the first definition it found.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	ANY
Action	Remove the extra definitions from the configuration file.

BOOTPD_DUP_SLOT

System Log Message	Duplicate slot default: <i>slot</i>
Description	As each hardware component on the routing platform initializes, it requests a boot string from the boot parameter process (tnp.bootpd). The boot strings are defined in the configuration file for tnp.bootpd. There was more than one definition in the file for the indicated slot (combination of component assembly ID and revision), so tnp.bootpd used the first definition it found.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	ANY
Action	Remove the extra definitions from the configuration file.

BOOTPD_HWDB_ERROR

System Log Message	Operation in chassis hardware database failed: <i>error-message</i>
Description	The boot parameter process (tnp.bootpd) could not complete an operation in the hardware database maintained by the chassis process (chassisd), for the indicated reason.
Type	Error: An error occurred
Severity	error
Facility	ANY

BOOTPD_MODEL_CHK

System Log Message	Unexpected ID <i>Oxidentifier</i> for model <i>model</i>
---------------------------	--

Description	As each hardware component on the routing platform initializes, it requests a boot string from the boot parameter process (tnp.bootpd). A request failed because it included the indicated assembly ID, which is inconsistent with the routing platform's model number.
Type	Error: An error occurred
Severity	warning
Facility	ANY
Action	Contact your technical support representative.

BOOTPD_MODEL_ERR

System Log Message	Unsupported model <i>model</i> , assuming M40 defaults
Description	As each hardware component on the routing platform initializes, it requests a boot string from the boot parameter process (tnp.bootpd). The boot strings are defined in the configuration file for tnp.bootpd. A request included a model number for which there was no definition in the configuration file, so tnp.bootpd provided the boot string appropriate for an M40 router.
Type	Error: An error occurred
Severity	warning
Facility	ANY
Action	Contact your technical support representative.

BOOTPD_NEW_CONF

System Log Message	New configuration installed
Description	The boot parameter process (tnp.bootpd) loaded a new configuration file.
Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

BOOTPD_NO_BOOTSTRING

System Log Message	No boot string found for type <i>board-type major-version.minor-version command-type</i>
Description	As each hardware component on the routing platform initializes, it requests a boot string from the boot parameter process (tnp.bootpd). The boot strings are defined in the configuration file for tnp.bootpd. The file did not include a boot string for the hardware component with the indicated characteristics.
Type	Error: An error occurred
Severity	warning
Facility	ANY

Action Contact your technical support representative.

BOOTPD_NO_CONFIG

System Log Message No configuration file '*filename*', using defaults

Description The boot parameter process (tnp.bootpd) could not open the indicated configuration file, so it initialized using default settings defined at compile time.

Type Event: This message reports an event, not an error

Severity notice

Facility ANY

BOOTPD_PARSE_ERR

System Log Message *filename: return-value* parse errors on SIGHUP

Description There was an error in the configuration file for the boot parameter process (tnp.bootpd), so it initialized using default settings defined at compile time.

Type Error: An error occurred

Severity error

Facility ANY

Action Correct the configuration file.

BOOTPD_REPARSE

System Log Message Reparsing configuration file '*filename*'

Description The boot parameter process (tnp.bootpd) reparsed the indicated configuration file.

Type Event: This message reports an event, not an error

Severity info

Facility ANY

BOOTPD_SELECT_ERR

System Log Message *select: error-message*

Description The boot parameter process (tnp.bootpd) issued the select() system call, which returned the indicated error message.

Type Error: An error occurred

Severity warning

Facility ANY

Action Contact your technical support representative.

BOOTPD_TIMEOUT

System Log Message	Timeout <i>duration</i> unreasonable
Description	The indicated timeout value was specified for the -t argument on the 'tnp.bootpd' command line, or no value was provided. The value was not acceptable, so the boot parameter process (tnp.bootpd) initialized using the default value of 30 seconds.
Type	Error: An error occurred
Severity	warning
Facility	ANY
Action	Provide an acceptable value for the -t argument; acceptable values are '1' (second) and larger.

CHAPTER 18

CFMD System Log Messages

This chapter describes messages with the **CFMD** prefix. They are generated by the connectivity-fault management (CFM) process (cfmd), which supports Operation, Administration, and Maintenance (OAM) functions that are defined in the Institute of Electrical and Electronics Engineers (IEEE) 802.1ag standard for Ethernet interfaces.

CFMD_CCM_DEFECT_CROSS_CONNECT

System Log Message	CFM defect: <i>error-message</i>
Description	A connectivity-fault management (CFM) maintenance endpoint (MEP) received a continuity check message (CCM) that had an incorrect maintenance association (MA) ID or a maintenance domain (MD) level lower than that of the MEP, each of which indicates a cross-connect error.
Type	Event: This message reports an event, not an error
Severity	error
Facility	ANY
Cause	The configuration is invalid.
Action	Check whether the configured MD name, format, and level, or the MA name or format, is different from the remote endpoint.

CFMD_CCM_DEFECT_ERROR

System Log Message	CFM defect: <i>error-message</i>
Description	A connectivity-fault management (CFM) maintenance endpoint (MEP) received a continuity check message (CCM) with an incorrect transmission interval or MEP ID, which indicates a configuration error.
Type	Event: This message reports an event, not an error
Severity	error
Facility	ANY
Cause	The configuration is invalid.

Action Verify that the configured continuity-check transmission interval does not differ from the remote endpoint, and that the configured MEP ID is valid.

CFMD_CCM_DEFECT_MAC_STATUS

System Log Message CFM defect: *error-message*

Description A connectivity-fault management (CFM) maintenance endpoint (MEP) received a continuity check message (CCM) that contained a 'Port Status' or 'Interface Status' type, length, value (TLV), which indicate a failed bridge port or aggregated port.

Type Event: This message reports an event, not an error

Severity error

Facility ANY

CFMD_CCM_DEFECT_NONE

System Log Message CFM defect: *error-message*

Description No defect was detected.

Type Event: This message reports an event, not an error

Severity error

Facility ANY

CFMD_CCM_DEFECT_RDI

System Log Message CFM defect: *error-message*

Description A connectivity-fault management (CFM) maintenance endpoint (MEP) received a continuity check message (CCM) that had the 'Remote Defect Indication' (RDI) bit set, which indicates that not all configured MEPs are returning CCMs to the transmitting MEP.

Type Event: This message reports an event, not an error

Severity error

Facility ANY

CFMD_CCM_DEFECT_RMEP

System Log Message CFM defect: *error-message*

Description A connectivity-fault management (CFM) maintenance endpoint (MEP) did not receive three consecutive continuity check message (CCM)s from one of the other MEPs in its maintenance association (MA), which indicates a MEP failure or network failure.

Type Event: This message reports an event, not an error

Severity error

Facility ANY

CFMD_CCM_DEFECT_UNKNOWN

System Log Message	CFM defect: <i>error-message</i>
Description	An unknown defect was detected.
Type	Event: This message reports an event, not an error
Severity	error
Facility	ANY

CFMD_PARSE_BAD_SWITCH

System Log Message	<i>executable-name</i> : invalid switch: <i>option</i>
Description	The enterprise switching process (cfmd) terminated because of an invalid switch.
Type	Error: An error occurred
Severity	error
Facility	ANY
Action	Examine the messages that immediately follow this message in the system log for information about possible causes.
Cause	An internal software failure occurred.

CFMD_PARSE_CMD_ARG

System Log Message	<i>executable-name</i> : missing argument for switch: <i>option</i>
Description	The enterprise switching process (cfmd) terminated because of an internal error.
Type	Error: An error occurred
Severity	error
Facility	ANY
Action	Examine the messages that immediately follow this message in the system log for information about possible causes.
Cause	An internal software failure occurred.

CFMD_PARSE_CMD_EXTRA

System Log Message	<i>executable-name</i> : extraneous information on command line: <i>option</i>
Description	The enterprise switching process (cfmd) terminated because of an internal error.
Type	Error: An error occurred
Severity	error

Facility	ANY
Action	Examine the messages that immediately follow this message in the system log for information about possible causes.
Cause	An internal software failure occurred.

CFMD_PARSE_USAGE

System Log Message	Usage: <i>executable-name</i> [-c] [-C] [-n] [-N] [-t[flags]] [-f config-file] [trace-file]
Description	The enterprise switching process (cfmd) terminated because of an internal error.
Type	Error: An error occurred
Severity	error
Facility	ANY
Action	Examine the messages that immediately follow this message in the system log for information about possible causes.
Cause	An internal software failure occurred.

CFMD_PPM_READ_ERROR

System Log Message	Read error on pipe from ppmfd: <i>reason (error-message)</i>
Description	The connectivity fault management process (cfmd) could not read a message available on the read pipe from the periodic packet management process (ppmd).
Type	Error: An error occurred
Severity	error
Facility	ANY
Action	Contact your technical support representative.

CFMD_PPM_WRITE_ERROR

System Log Message	<i>function-name</i> : write error on pipe to ppmfd (<i>error-message</i>)
Description	The connectivity fault management process (cfmd) could not write a message on the pipe to the periodic packet management process (ppmd).
Type	Error: An error occurred
Severity	error
Facility	ANY
Action	Contact your technical support representative.

CHAPTER 19

CHASSISD System Log Messages

This chapter describes messages with the **CHASSISD** prefix. They are generated by the chassis process (chassisd), which controls hardware components on the routing platform.

CHASSISD_ANTICF_PIM_CHECK_FAILED

System Log Message	PIM <i>pim-slot</i> failed anti-counterfeit check
Description	The indicated Physical Interface Module (PIM) failed the anti-counterfeit check performed by the chassis process (chassisd).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_ANTICF_RE_CHECK_FAILED

System Log Message	Routing Engine failed anti-counterfeit check
Description	The Routing Engine failed the anti-counterfeit check performed by the chassis process (chassisd).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_ANTICF_RE_ROM_READ_FAIL

System Log Message	Unable to read serial number from anti-counterfeit device for Routing Engine
Description	The chassis process (chassisd) could not read the serial number recorded in the ROM of the anti-counterfeit device for the Routing Engine.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_ANTICF_RE_SHA_READ_FAIL

System Log Message	Unable to read SHA output from anti-counterfeit device for Routing Engine
Description	The chassis process (chassisd) could not read Secure Hash Algorithm (SHA) information from the anti-counterfeit device for the Routing Engine.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_ANTICF_ROM_READ_FAILED

System Log Message	Unable to read serial number from anti-counterfeit device for PIM <i>pim-slot</i>
Description	The chassis process (chassisd) could not read the serial number recorded in the ROM of the anti-counterfeit device for the indicated Physical Interface Module.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_ANTICF_SHA_READ_FAILED

System Log Message	Unable to read SHA output from anti-counterfeit device for PIM <i>pim-slot</i>
Description	The chassis process (chassisd) could not read Secure Hash Algorithm (SHA) information from the anti-counterfeit device for the indicated Physical Interface Module (PIM).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_ARGUMENT_ERROR

System Log Message	Unknown option <i>option</i>
Description	The indicated option, provided on the 'chassisd' command line, is invalid. The chassis process (chassisd) initialized but ignored the invalid option.
Type	Error: An error occurred
Severity	error

Facility LOG_DAEMON
Action Contact your technical support representative.

CHASSISD_BLOWERS_SPEED

System Log Message Fans and impellers are now running at normal speed
Description The fans (and impellers, if applicable) were running at the normal speed.
Type Event: This message reports an event, not an error
Severity notice
Facility LOG_DAEMON

CHASSISD_BLOWERS_SPEED_FULL

System Log Message Fans and impellers being set to full speed [*reason*]
Description For the indicated reason, the chassis process (chassisd) increased the speed of fans (and impellers, if applicable) to the maximum.
Type Event: This message reports an event, not an error
Severity notice
Facility LOG_DAEMON

CHASSISD_BLOWERS_SPEED_MEDIUM

System Log Message Fans and impellers being set to intermediate speed
Description The chassis process (chassisd) increased the speed of fans (and impellers, if applicable) to the intermediate level because of a temperature increase in the chassis.
Type Event: This message reports an event, not an error
Severity notice
Facility LOG_DAEMON

CHASSISD_BUS_DEVICE_OPEN_FAILURE

System Log Message Unable to open '*bus-type*' bus device, error *error-message* (*error-code*)
Description The chassis process (chassisd) could not open the indicated bus device for the indicated reason.
Type Error: An error occurred
Severity error
Facility LOG_DAEMON
Action Contact your technical support representative.

CHASSISD_CB_CLOCK_CHECKSUM

System Log Message	Clock module on M120 CB had configuration data checksum error
Description	The chassis process (chassisd) detected a checksum error for the clock module on an M120 Control Board (CB).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_CB_MASTER_BP_IGNORED

System Log Message	Press of online/offline button ignored for master <i>fru-name fru-slot</i>
Description	The online/offline button for the indicated control board was pressed, but the chassis process (chassisd) ignored the request. The control board for M40e and M160 routers is the Miscellaneous Control Subsystem (MCS). The control board for M320, T320, and T640 routing platforms is the Control Board (CB).
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON
Cause	The control board was acting as master.
Action	Switch mastership to the other control board before taking the control board offline.

CHASSISD_CB_READ

System Log Message	Error reading midplane ID EEPROM, errno <i>error-code</i>
Description	The chassis process (chassisd) could not read the EEPROM on the midplane.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_CB_RE_ONLINE_BP_IGNORED

System Log Message	Unable to take <i>fru-name fru-slot</i> offline because paired Routing Engine is online
Description	The online/offline button for the indicated control board was pressed, but the chassis process (chassisd) ignored the request. The control board for M40e and M160 routers is the Miscellaneous Control Subsystem (MCS). The control board for M320, T320, and T640 routing platforms is the Control Board (CB).

Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON
Cause	The Routing Engine paired with the indicated control board is still online.
Action	Take the Routing Engine offline before taking the control board offline.

CHASSISD_CFEB_POWER_FAILURE

System Log Message	<i>function-name: unable to turn state power for CFEB cfeb-slot</i>
Description	The chassis process (chassisd) could not turn on or turn off the power to the indicated Compact Forwarding Engine Board (CFEB).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_CLEAR_CONFIG_ERROR

System Log Message	<i>function-name: status</i>
Description	The chassis process (chassisd) encountered an error while trying to clear the state information associated with a copy of the management process (mgd) that it spawned to commit the rescue configuration. The commit operation succeeded or failed as indicated.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

CHASSISD_CLOCK_FAILURE

System Log Message	<i>function-name: fru-name error-message</i>
Description	The chassis process (chassisd) determined that the indicated clock source failed in the indicated way.
Type	Error: An error occurred
Severity	error

Facility LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_CLOCK_NOTICE

System Log Message *fru-name: message*

Description The clock-synchronization status of the indicated component (field-replaceable unit, or FRU) changed as indicated.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

CHASSISD_CLOCK_RESET_FAIL

System Log Message Zarlink module on Taz Base Board is not coming up after reset

Description The chassis process (chassisd) detected an error in the state of clock module.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHASSISD_CMB_READBACK_ERROR

System Log Message Readback error from chassis management bus for *fru-name fru-slot* ([*0xaddress*, *0xoffset*] -> *0xerror-code*)

Description The chassis process (chassisd) could not read back information from the Chassis Management Bus (CMB) about the indicated component (field-replaceable unit, or FRU).

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause The probable cause is hardware error.

Action Contact your technical support representative.

CHASSISD_COMMAND_ACK_ERROR

System Log Message Error occurred when *fru-name fru-slot* reported its online status: *error-message* (error code *error-code*)

Description The chassis process requested that the indicated component (field-replaceable unit, or FRU) confirm that it was online. The indicated error occurred when the FRU sent its response. In the normal case, the chassis process performed any additional action necessary to guarantee that the FRU came online.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_COMMAND_ACK_SFM_ERROR

System Log Message	<i>function-name: SFM sfm-slot did not acknowledge FPC fpc-slot: error error-message (code error-code)</i>
Description	The chassis process (chassisd) requires an acknowledgment from each Switching and Forwarding Module (SFM) before it registers a Flexible PIC Controller (FPC) as online. The acknowledgment message from the indicated SFM failed for the indicated FPC.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_CONCAT_MODE_ERROR

System Log Message	Cannot set no-concatenated mode for FPC <i>fpc-slot</i> PIC <i>pic-slot</i>
Description	The chassis process (chassisd) could not set channelized mode for the indicated SONET/SDH PIC. Channelized mode is configured by including the no-concatenate statement at the [edit chassis fpc 'slot' pic 'slot'] hierarchy level.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

CHASSISD_CONFIG_ACCESS_ERROR

System Log Message	<i>function-name: error-message</i>
Description	The chassis process (chassisd) experienced the indicated problem while attempting to parse the configuration database.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

CHASSISD_CONFIG_CHANGE_IFDEV_DEL

System Log Message	Deleting <i>argument1 interface-typesdev-numberargument2</i> due to configuration change
Description	The chassis process (chassisd) deleted the indicated interface devices due to a change in the configuration.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

CHASSISD_CONFIG_INIT_ERROR

System Log Message	Unable to parse configuration; using defaults
Description	The chassis process (chassisd) could not parse the configuration and used default values while initializing.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_CONFIG_WARNING

System Log Message	<i>function-name: warning-message, FPC fpc-slot PIC pic-slot</i>
Description	The configuration that was specified for the indicated PIC is invalid for that type of PIC.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

CHASSISD_DEVICE_OPEN_ERROR

System Log Message	Unable to open <i>device-name</i> device file (errno <i>error-code</i>)
Description	The chassis process (chassisd) could not open the device file for the indicated device.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_EXEC_ERROR

System Log Message	<i>function-name: error-message</i>
---------------------------	-------------------------------------

Description	While trying to commit the rescue configuration, the chassis process (chassisd) encountered an error.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

CHASSISD_EXISTS

System Log Message	chassisd already running; exiting
Description	The chassis process (chassisd) exited because it discovered that another chassisd process is already running.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

CHASSISD_EXISTS_TERM_OTHER

System Log Message	Killing existing chassisd and exiting
Description	The chassis process (chassisd) discovered that another chassisd process is already running. It terminated the other process and exited.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

CHASSISD_FAN_FAILURE

System Log Message	<i>fru-name</i> in slot <i>fru-slot</i> failed
Description	The indicated fan or impeller failed. The chassis process (chassisd) raised an alarm and increased the speed of the remaining fans (and impellers, if applicable) to full speed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FASIC_CONFIG_COMPLETE

System Log Message	Fchip: configuration already completed
Description	The chassis process (chassisd) detected an attempt to configure an F chip on a Control Board (CB) when configuration was already complete.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_FASIC_FTOKEN_ERROR

System Log Message	Fchip (CB <i>control-board-slot</i> , ID <i>fchip-id</i>): ftoken overflow/underflow set (<i>data</i>) at <i>address</i>
Description	The chassis process (chassisd) detected an underflow or overflow error on the indicated F chip on the indicated Control Board (CB).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FASIC_FTOKEN_INIT_ERROR

System Log Message	Fchip (CB <i>control-board-slot</i> , ID <i>fchip-id</i>): f8chip_ftoken_init() stuck in ftoken loop, <i>addr=address</i> , <i>data=data</i>
Description	The chassis process (chassisd) encountered an error while initializing memory at the indicated address for the indicated F chip on the indicated Control Board (CB).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FASIC_HSL_CONFIG_ERROR

System Log Message	Fchip (CB <i>control-board-slot</i> , ID <i>fchip-id</i>): HSL configuration failed (error <i>error-message</i>)
Description	The chassis process (chassisd) could not configure high speed links (HSL) for the indicated F chip on the indicated Control Board (CB).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_FASIC_HSL_LINK_ERROR

System Log Message	Fchip (CB <i>control-board-slot</i> , ID <i>fchip-id</i>): link <i>link-id</i> failed because of <i>error-message</i>
Description	The chassis process (chassisd) detected an error for the indicated high speed link (HSL) for the indicated F chip on the indicated Control Board (CB).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FASIC_INIT_ERROR

System Log Message	Fchips were not configured yet
Description	The chassis process (chassisd) detected that F chips were not yet initialized on the Control Board (CB).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_FASIC_INPUT_DROP

System Log Message	Fchip (CB <i>control-board-slot</i> , ID <i>fchip-id</i>): dropped <i>drop-rate</i> cells per second coming from Packet Forwarding Engine <i>pfe</i> on FPC <i>fpc-slot</i>
Description	The Packet Forwarding Engine divides packets into smaller units called cells for more efficient processing. As the indicated F chip on the indicated Control Board (CB) processed data that was received from the indicated Packet Forwarding Engine on the indicated Flexible PIC Concentrator (FPC), it dropped the indicated number of cells per second.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FASIC_OUTPUT_DROP

System Log Message	Fchip (CB <i>control-board-slot</i> , ID <i>fchip-id</i>): dropped <i>drop-rate</i> cells per second destined for Packet Forwarding Engine <i>pfe</i> on FPC <i>fpc-slot</i>
Description	The Packet Forwarding Engine divides packets into smaller units called cells for more efficient processing. As the indicated F chip on the indicated Control Board (CB) processed data before sending it to the indicated Packet Forwarding Engine on the indicated Flexible

Port Concentrator (FPC) for outgoing transmission, it dropped the indicated number of cells per second.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FASIC_PIO_READ_ERROR

System Log Message Fchip (CB *control-board-slot*, ID *fchip-id*): read error in *function-name()* for link#*link-id* at address *address* in register *register*

Description The indicated routine failed with a read error at the indicated address and register for the indicated F chip and link on the indicated Control Board (CB).

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_FASIC_PIO_WRITE_ERROR

System Log Message Fchip (CB *control-board-slot*, ID *fchip-id*): write error in *function-name()* for link#*link-id* at address *address* in register *register*

Description The indicated routine failed with a write error at the indicated address and register for the indicated F chip and link on the indicated Control Board (CB).

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_FASIC_PLL_ERROR

System Log Message Fchip (CB *control-board-slot*, ID *fchip-id*): unable to lock PLL

Description The chassis process (chassisd) could not lock a phased-lock loop (PLL) for the indicated F chip on the indicated Control Board (CB).

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FASIC_RESET_ERROR

System Log Message	Fchip (CB <i>control-board-slot</i> , ID <i>fchip-id</i>): reset failed
Description	The chassis process (chassisd) could not reset the indicated F chip on the indicated Control Board (CB).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FASIC_SRAM_ERROR

System Log Message	Fchip (CB <i>control-board-slot</i> , ID <i>fchip-id</i>): SRAM fuse did not initialize
Description	The chassis process (chassisd) detected that static RAM (SRAM) did not initialize properly for the indicated F chip on the indicated Control Board (CB).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_FASIC_VERSION_ERROR

System Log Message	Fchip (CB <i>control-board-slot</i> , ID <i>fchip-id</i>): part number <i>part-number</i> and version <i>version</i> were invalid
Description	The indicated part number and version detected for the indicated F chip on the indicated Control Board (CB) were not valid values.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_FCHIP_CONFIG_COMPLETE

System Log Message	Fchip: configuration already completed
Description	The chassis process (chassisd) detected an attempt to configure an F chip when configuration was already complete.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_FCHIP_CONFIG_MD_ERROR

System Log Message	Fchip <i>fchip-id</i> : invalid number of Md chips (<i>count</i>) for Packet Forwarding Engine <i>pfe</i> on FPC <i>fpc-slot</i>
Description	The chassis process (chassisd) detected an invalid number of Md chips for the indicated F chip, Packet Forwarding Engine and Flexible PIC Concentrator (FPC).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_FCHIP_CONFIG_RATE_ERROR

System Log Message	Fchip <i>fchip-id</i> : unable to set rate limit on port <i>port</i>
Description	The chassis process (chassisd) could not set the rate limit for the indicated F chip and port.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_FCHIP_CONFIG_READ_ERROR

System Log Message	Fchip <i>fchip-id</i> : unable to read configuration register
Description	The chassis process (chassisd) could not read a configuration register on the indicated F chip.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_FCHIP_FTOKEN_ERROR

System Log Message	Fchip <i>fchip-id</i> : Ftoken overflow/underflow set (<i>data</i>) at <i>address</i>
Description	The chassis process (chassisd) detected an underflow or overflow error on the indicated F chip.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FCHIP_FTOKEN_INIT_ERROR

System Log Message	Fchip <i>fchip-id</i> : fchip_ftoken_init() stuck in ftoken loop, addr= <i>address</i> , data= <i>data</i>
Description	The chassis process (chassisd) encountered an error while initializing memory at the indicated address for the indicated F chip.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FCHIP_HSR_ERROR

System Log Message	Fchip high-speed receiver (HSR) error: <i>error-message</i>
Description	The chassis process (chassisd) detected an error in the high-speed receiver (HSR) subsystem for the F chip with the indicated characteristics.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_FCHIP_HSR_INIT_ERROR

System Log Message	HSR: No vectors supplied
Description	The chassis process (chassisd) could not initialize the high-speed receiver (HSR) subsystem for an F chip.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_FCHIP_HSR_INIT_LINK_ERR

System Log Message	Fchip <i>fchip-id</i> : unable to initialize HSR link <i>link-id</i>
Description	The chassis process (chassisd) could not initialize the indicated high-speed receiver (HSR) link for the indicated F chip.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_FCHIP_HSR_RESET_ERROR

System Log Message	Fchip <i>fchip-id</i> : hsr_reset error in fchip_init() on link <i>link-id</i>
---------------------------	--

Description A high-speed receiver (HSR) reset error occurred during initialization of the indicated F chip and link.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHASSISD_FCHIP_HST_ERROR

System Log Message Fchip high-speed transmitter (HST) error: *error-message*

Description The chassis process (chassisd) detected an error in the high-speed transmitter (HST) subsystem for the F chip with the indicated characteristics.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHASSISD_FCHIP_HST_INIT_ERROR

System Log Message HST: No vectors supplied

Description The chassis process (chassisd) could not initialize the high-speed transmitter (HST) subsystem for an F chip.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHASSISD_FCHIP_HST_INIT_LINK_ERR

System Log Message Fchip *fchip-id*: unable to initialize HST link *link-id*

Description The chassis process (chassisd) could not initialize the indicated high-speed transmitter (HST) link for the indicated F chip.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHASSISD_FCHIP_HST_RESET_ERROR

System Log Message Fchip *fchip-id*: hst_reset error in fchip_init() on link *link-id*

Description A high-speed transmitter (HST) reset error occurred during initialization of the indicated F chip and link.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHASSISD_FCHIP_INIT_ERROR

System Log Message Fchips were not configured yet

Description The chassis process (chassisd) detected that F chips were not yet initialized.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHASSISD_FCHIP_LINK_ERROR

System Log Message SIBsib-slot_F0: *link-type* link *link-id* was bad

Description The chassis process (chassisd) detected an error for the indicated high-speed receiver (HSR) or high-speed transmitter (HST) link for an F chip on the indicated Switch Interface Board (SIB).

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_FCHIP_MONITOR_ERROR

System Log Message F chip module was invalid

Description The chassis process (chassisd) detected an invalid F-chip module while enabling or disabling the monitoring of F-chip functional blocks.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_FCHIP_PIO_READ_ERROR

System Log Message Fchip *fchip-id*: read error in *function-name()* for link#*link-id*, at address *address* in register *register*

Description The indicated routine failed with a read error at the indicated address and register for the indicated F chip and link.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHASSISD_FCHIP_PIO_WRITE_ERROR

System Log Message Fchip *fchip-id*: write error in *function-name*() for link#*link-id*, at address *address* in register *register*

Description The indicated routine failed with a write error at the indicated address and register for the indicated F chip and link.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHASSISD_FCHIP_POLL_ERROR

System Log Message Fchip *fchip-id*: *link-type* *link-id* poll returned error *error-code*

Description An error with the indicated error number occurred during polling of the indicated high-speed receiver (HSR) or high-speed transmitter (HST) link for the indicated F chip.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_FCHIP_RATE_ERROR

System Log Message Fchip *fchip-id*: per-port rate limit was not enabled

Description The chassis process (chassisd) detected that per-port rate limiting was not enabled when it attempted to set the rate limit on an individual port for the indicated F chip.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_FCHIP_SIB_NOT_STARTED

System Log Message Unable to start *fru-name* *fru-slot* because F chips were not initialized

Description The indicated Switch Interface Board (SIB) did not start because the F chips on it were not initialized.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON
Action Contact your technical support representative.

CHASSISD_FCHIP_VERSION_ERROR

System Log Message F chip *fchip-id*: part number (*part-number*) and version (*version*) were invalid
Description The indicated part number and version detected for the indicated F chip were not valid values.
Type Error: An error occurred
Severity error
Facility LOG_DAEMON

CHASSISD_FEB_REVERSION

System Log Message Reversion from FEB *fru-slot* to FEB *slot*
Description The chassis daemon (chassisd) reverted to the indicated FEB from the specified FEB.
Type Event: This message reports an event, not an error
Severity error
Facility LOG_DAEMON

CHASSISD_FEB_SWITCHOVER

System Log Message Switchover from FEB *fru-slot* to FEB *slot*
Description The chassis daemon (chassisd) switched to the indicated FEB from the specified FEB.
Type Event: This message reports an event, not an error
Severity error
Facility LOG_DAEMON

CHASSISD_FHSR_READ_REG_ERROR

System Log Message Fchip: fhsr_read() failed at address *address*
Description The high-speed receiver (HSR) read routine failed at the indicated address on an F-chip register.
Type Error: An error occurred
Severity error
Facility LOG_DAEMON
Action Contact your technical support representative.

CHASSISD_FHSR_WRITE_REG_ERROR

System Log Message	Fchip: fhsr_write() of value <i>value</i> failed at address <i>address</i>
Description	The high-speed receiver (HSR) write routine could not record the indicated value at the indicated address on an F-chip register.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_FHST_READ_REG_ERROR

System Log Message	Fchip: fhst_read() failed at address <i>address</i>
Description	The high-speed transmitter (HST) read routine failed at the indicated address on an F-chip register.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FHST_WRITE_REG_ERROR

System Log Message	Fchip: fhst_write() of value <i>value</i> failed at address <i>address</i>
Description	The high-speed transmitter (HST) write routine could not record the indicated value at the indicated address on an F-chip register.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_FILE_OPEN

System Log Message	File open: <i>filename</i> , error: <i>error-code</i> -- <i>error-message</i>
Description	The chassis process (chassisd) could not open the indicated file for the indicated reason.
Type	Error: An error occurred
Severity	critical
Facility	LOG_DAEMON

CHASSISD_FILE_STAT

System Log Message	File stat: <i>filename</i> , error: <i>error-code</i> -- <i>error-message</i>
---------------------------	---

Description The chassis process (chassisd) could not open the indicated file because it could not obtain its status.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHASSISD_FM_BAD_STATE

System Log Message *function-name: unexpected state statetype for SIB#sib-slot*

Description The indicated function failed because it encountered the indicated type of unexpected internal state with respect to the indicated Switch Interface Board (SIB).

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_FM_ERROR

System Log Message *function-name: error-message (SIB#sib-slot, Packet Forwarding Engine pfe on FPC fpc-slot)*

Description During execution of the indicated fabric management routine, the indicated error occurred between the indicated Switch Interface Board (SIB) and the indicated Packet Forwarding Engine on the indicated Flexible PIC Concentrator (FPC).

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_FM_ERROR_CLOS_F13_HSR

System Log Message FM: *error-message* errors occurred on link from F2-f2-sib_SFfrom-fchip_s-port to F13SIBto-sfc-sib_SF3_to-fchip_d-port on plane sib-plane

Description In a Tx-Plus routing matrix, packets traverse both electrical and optical media as they travel between the Switch Interface Boards (SIBs) in the T1600 routing nodes (called ST-SIB-Ls) and the SIBs in the TX Matrix Plus platform (called F13SIBs and F2S-SIBs). The chassis process (chassisd) on the SFC routing node detected an error in the electrical path between the indicated port on the indicated F2SIB and F13SIB on the indicated plane.

Type Error: An error occurred

Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FM_ERROR_CLOS_F13_HST

System Log Message	FM: <i>error-message</i> errors occurred on link from F13SIB <i>from-sfc-sib_SF1_from-fchip_s-port</i> to F2- <i>f2-sib_SFto-fchip_d-port</i> on plane <i>sib-plane</i>
Description	In a Tx-Plus routing matrix, packets traverse both electrical and optical media as they travel between the Switch Interface Boards (SIBs) in the T1600 routing nodes (called ST-SIB-Ls) and the SIBs in the TX Matrix Plus platform (called F13SIBs and F2S-SIBs). The chassis process (chassisd) on the SFC routing node detected an error in the transmit electrical path between the indicated port on the indicated F13SIB and F2SIB on the indicated plane.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FM_ERROR_CLOS_F2_HSR

System Log Message	FM: <i>error-message</i> errors occurred on link from F13SIB <i>from-sfc-sib_SF1_from-fchip_s-port</i> to <i>f2-sib_SFto-fchip_d-port</i> on plane <i>sib-plane</i>
Description	In a Tx-Plus routing matrix, packets traverse both electrical and optical media as they travel between the Switch Interface Boards (SIBs) in the T1600 routing nodes (called ST-SIB-Ls) and the SIBs in the TX Matrix Plus platform (called F13SIBs and F2S-SIBs). The chassis process (chassisd) on the SFC routing node detected an error in the electrical path between the indicated port on the indicated F2SIB and F13SIB on the indicated plane.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FM_ERROR_CLOS_F2_HST

System Log Message	FM: <i>error-message</i> errors occurred on link from <i>f2-sib_SFfrom-fchip_s-port</i> to F13SIB <i>to-sfc-sib_SF1_to-fchip_d-port</i> on plane <i>sib-plane</i>
Description	In a Tx-Plus routing matrix, packets traverse both electrical and optical media as they travel between the Switch Interface Boards (SIBs) in the T1600 routing nodes (called ST-SIB-Ls) and the SIBs in the TX Matrix Plus platform (called F13SIBs and F2S-SIBs).

The chassis process (chassisd) on the SFC routing node detected an error in the transmit electrical path between the indicated port on the indicated F2SIB and F13SIB on the indicated plane.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON
Action Contact your technical support representative.

CHASSISD_FM_ERROR_F13_FB_HSR_TXP

System Log Message *error-message errors on LCClcc_FPCfpc-slot_pfe link via ST_SIB_Lfrom-lcc-sib_FBfiber-bundle to F13SIBto-sfc-sib*

Description In a Tx-Plus routing matrix, packets traverse both electrical and optical media as they travel between the Switch Interface Boards (SIBs) in the T1600 routing nodes (called ST-SIB-Ls) and the SIBs in the TX Matrix Plus platform (called F13SIBs and F2S-SIBs). The chassis process (chassisd) on the routing node that houses the indicated F13SIB detected an error in the electrical path between the indicated ports on the F13SIB and the indicated ST-SIB-L on the indicated LCC.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON
Action Contact your technical support representative.

CHASSISD_FM_ERROR_F13_FB_RX_VC

System Log Message *error-message on F13SIBfrom-sfc-sib_FBfiber-bundle VCSEL vcse Channel vcse-channel connected from LCC lcc SIB_L to-lcc-sib*

Description In a Tx-Plus routing matrix, packets traverse both electrical and optical media as they travel between the Switch Interface Boards (SIBs) in the T1600 routing nodes (called ST-SIB-Ls) and the SIBs in the TX Matrix Plus platform (called F13SIBs and F2S-SIBs). The chassis process (chassisd) on the routing node that houses the indicated F13SIB detected the indicated error as packets that were traveling in the in the optical media from the indicated ST-SIB-L on the indicated LCC.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON
Action Contact your technical support representative.

CHASSISD_FM_ERROR_F13_FB_TXP

System Log Message	<i>F13SIBsib-slot_FB_fiber-bundle LCC lcc ST_SIB_Lto-lcc-sib is error-message</i>
Description	In a Tx-Plus routing matrix, the fiber-optic cable between each Switch Interface Board in a T1600 routing node (called a ST-SIB-L) must connect to a specific SIB port on the TX-Plus Matrix platform (called a F13SIB). The cable connected at the indicated F13SIB had the indicated error.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FM_ERROR_F13_FB_TX_VC

System Log Message	<i>error-message on F13SIBfrom-sfc-sib_FBfiber-bundle VCSEL vcsel Channel vcsel-channel connected to LCC lcc SIB_L to-lcc-sib</i>
Description	In a Tx-Plus routing matrix, packets traverse both electrical and optical media as they travel between the Switch Interface Boards (SIBs) in the T1600 routing nodes (called ST-SIB-Ls) and the SIBs in the TX Matrix Plus platform (called F13SIBs and F2S-SIBs). The chassis process (chassisd) on the routing node that houses the indicated F13SIB detected the indicated error as packets that were traveling in the indicated direction were translated between electrical and optical media.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FM_ERROR_F13_VC_PWR

System Log Message	<i>FM: High power difference at F13SIBfrom-sfc-sib_FBfiber-bundle VCSEL vcsel Channel vcsel-channel connected to LCC lcc SIB_Lsib-slot</i>
Description	In a Tx-Plus routing matrix, packets traverse both electrical and optical media as they travel between the Switch Interface Boards (SIBs) in the T1600 routing nodes (called ST-SIB-Ls) and the SIBs in the TX Matrix Plus platform (called F13SIBs and F2S-SIBs). The chassis process (chassisd) on the SFC routing node that houses the indicated F13SIB detected higher than configured receive power difference levels on the indicated fiber-bundles connected to the indicated LCC ST-SIB-L.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_FM_ERROR_SIB_L_FB_HSR

System Log Message	FM: HSR error occurred on link from SIB-S port <i>F(s-row,s-port)</i> to SIB-L# <i>sib-slot</i> port <i>F(l-row,l-port)</i>
Description	In a routing matrix, packets traverse both electrical and optical media as they travel between the Switch Interface Boards (SIBs) in the T640 routing nodes (called SIB-Ls) and the SIBs in the TX Matrix platform (called SIB-Ss). The chassis process (chassisd) on the routing node that houses the indicated SIB-L detected an error in the electrical path between the indicated ports on the SIB-L and the corresponding SIB-S.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FM_ERROR_SIB_L_FB_RX_VC

System Log Message	<i>error-message</i> on LCC <i>lcc</i> SIB_L <i>from-lcc-sib_FB</i> fiber-bundle VCSEL <i>vcsel</i> Channel <i>vcsel-channel</i> connected to F13SIB <i>to-sfc-sib</i>
Description	In a Tx-Plus routing matrix, packets traverse both electrical and optical media as they travel between the Switch Interface Boards (SIBs) in the T1600 routing nodes (called ST-SIB-Ls) and the SIBs in the TX Matrix Plus platform (called F13SIBs and F2S-SIBs). The chassis process (chassisd) on the routing node that houses the indicated ST-SIB-L detected the indicated error as packets that were traveling in the optical media.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FM_ERROR_SIB_L_FB_SMF

System Log Message	FM: <i>error-message</i> error occurred on link <i>to-from-sib</i> SIB-L# <i>sib-slot</i> <i>to-from-scc</i> SCC
Description	In a routing matrix, packets traverse both electrical and optical media as they travel between the Switch Interface Boards (SIBs) in the TX Matrix platform (the switch-card chassis, or SCC) and the SIBs in the T640 routing nodes (called SIB-Ls). The chassis process (chassisd) on the routing node that houses the indicated SIB-L detected the indicated error as packets that were traveling in the indicated direction were translated between electrical and optical media.
Type	Error: An error occurred
Severity	error

Facility LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_FM_ERROR_SIB_L_FB_TXP

System Log Message LCC *lcc* ST-SIB-L:*sib-slot* Fiber-bundle:*fiber-bundle* is *error-message*

Description In a Tx-Plus routing matrix, the fiber-optic cable between each Switch Interface Board in a T1600 routing node (called a ST-SIB-L) must connect to a specific SIB port on the TX-Plus Matrix platform (called a F13SIB). The cable connected at the indicated ST-SIB-L had the indicated error.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_FM_ERROR_SIB_L_FB_TX_VC

System Log Message *error-message* on LCC *lcc* SIB_L*from-lcc-sib_FB*fiber-bundle VCSEL *vcsel* Channel *vcsel-channel* connected to F13SIB*to-sfc-sib*

Description In a Tx-Plus routing matrix, packets traverse both electrical and optical media as they travel between the Switch Interface Boards (SIBs) in the T1600 routing nodes (called ST-SIB-Ls) and the SIBs in the TX Matrix Plus platform (called F13SIBs and F2S-SIBs). The chassis process (chassisd) on the routing node that houses the indicated ST-SIB-L detected the indicated error as packets that were traveling in the indicated direction were translated between electrical and optical media.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_FM_ERROR_SIB_L_HSR_PFE

System Log Message FM: *error-message* on LCC:*lcc* FPC*fpc-slot_pfe* link to ST-SIB-L*to-lcc-sib_fchip-id*

Description In a Tx-Plus routing matrix, packets traverse both electrical and optical media as they travel between the Switch Interface Boards (SIBs) in the T1600 routing nodes (called ST-SIB-Ls) and the SIBs in the TX Matrix Plus platform (called F13SIBs and F2S-SIBs). The chassis process (chassisd) on the routing node that houses the indicated ST-SIB-L detected an error in the electrical path between the indicated ST-SIB-L and the indicated PFE on the FPC.

Type Error: An error occurred

Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FM_ERROR_SIB_L_HSR_TXP

System Log Message	FM: <i>error-message</i> on LCC:lcc FPCfpc-slot_pfe link connected by ST-SIB-Lfrom-lcc-sib_fchip-id_s-port_FBfiber-bundle to F13SIBto-sfc-sib
Description	In a Tx-Plus routing matrix, packets traverse both electrical and optical media as they travel between the Switch Interface Boards (SIBs) in the T1600 routing nodes (called ST-SIB-Ls) and the SIBs in the TX Matrix Plus platform (called F13SIBs and F2S-SIBs). The chassis process (chassisd) on the routing node that houses the indicated ST-SIB-L detected an error in the electrical path between the indicated ports on the SIB-L and the corresponding F13SIB.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FM_ERROR_SIB_L_MISMATCH

System Log Message	FM: fiber cable from SIB-L#sib-slot possibly connected to wrong SIB-S
Description	In a routing matrix, the fiber-optic cable between each Switch Interface Board in a T640 routing node (called a SIB-L) must connect to a specific SIB port on the TX Matrix platform (called a SIB-S). The cable originating at the indicated SIB-L was possibly plugged into the wrong SIB-S port or wrong SIB-S.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FM_ERROR_SIB_L_VC_PWR

System Log Message	FM: High power difference at LCC lcc SIB_Lsib-slot_FBfiber-bundle VCSEL vcsel Channel vcsel-channel connected to F13SIBfrom-sfc-sib
Description	In a Tx-Plus routing matrix, packets traverse both electrical and optical media as they travel between the Switch Interface Boards (SIBs) in the T1600 routing nodes (called ST-SIB-Ls) and the SIBs in the TX Matrix Plus platform (called F13SIBs and F2S-SIBs). The chassis process (chassisd) on the routing node that houses the indicated ST-SIB-L detected higher than configured receive power levels on the indicated fiber-bundles connected to the indicated LCC ST-SIB-L.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FM_ERROR_SIB_S_FB_HSR

System Log Message	FM: HSR error occurred on link from LCC <i>lcc</i> SIB-L port F(<i>l-row,l-port</i>) to SIB-S# <i>sib-slot</i> port F(<i>s-row,s-port</i>)
Description	In a routing matrix, packets traverse both electrical and optical media as they travel between the Switch Interface Boards (SIBs) in the TX Matrix platform (called SIB-Ss) and the SIBs in the T640 routing nodes (called SIB-Ls). The chassis process (chassisd) on the TX Matrix platform detected an error in the electrical path between the indicated port on the indicated SIB-S and the indicated port on a SIB-L installed in the indicated routing node (line-card chassis, or LCC).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FM_ERROR_SIB_S_FB_SMF

System Log Message	FM: <i>error-message</i> error occurred on link <i>to-from-sib-s</i> SIB-S# <i>sib-slot</i> <i>to-from-lcc</i> LCC <i>lcc</i>
Description	In a routing matrix, packets traverse both electrical and optical media as they travel between the Switch Interface Boards (SIBs) in the TX Matrix platform (called SIB-Ss) and the SIBs in the T640 routing nodes (line-card chassis, or LCCs). The chassis process (chassisd) on the TX Matrix platform detected the indicated error as packets that were traveling to or from the indicated LCC were translated between electrical and optical media.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FM_FABRIC_DOWN

System Log Message	All fabric planes in the system have gone down after interfaces have been created. If no fabric planes come online in two minutes, FPCs will be rebooted.
Description	The chassis process detected all the fabric planes went down after interfaces were created and the router is not capable of carrying traffic coming in through the interfaces.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FM_MEMORY_ERROR

System Log Message	<i>function-name</i> : unable to allocate memory; <i>error-message</i>
Description	The chassis process (chassisd) could not allocate memory for a fabric operation.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FM_SIB_ERROR

System Log Message	Fabric management error for SIB <i>sib-slot</i> : <i>error-message</i>
Description	The chassis process (chassisd) detected the indicated type of error on the indicated Switch Interface Board (SIB) and performed the indicated action.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FM_SIB_FPC_TYPE_ERROR

System Log Message	SIB <i>sib-slot</i> does not support features required for FPC Type 4
Description	The indicated Switch Interface Board (SIB) does not support features required by the Flexible PIC Concentrator (FPC) Type 4.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FPC_FABRIC_DOWN_REBOOT

System Log Message	FPC <i>fpc-slot</i> has been rebooted to delete its interfaces as all fabric planes are down.
---------------------------	---

Description The chassis process (chassisd) rebooted the FPC to bring the FPC's interfaces down because the router is incapable of forwarding traffic due to all fabric planes being down.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_FPC_NOT_FOUND

System Log Message *function-name*: unable to find FPC for PIC attachment operation

Description The chassis process (chassisd) attempted to bring a PIC online, but could not find the Flexible PIC Concentrator (FPC) that houses it.

Type Error: An error occurred

Severity warning

Facility LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_FPC_PIC_DETECT_TIMEOUT

System Log Message *function-name*: PIC detection on FPC *fpc-slot* timed out

Description The chassis process (chassisd) expects to receive notification within a timeout period that each Flexible PIC Concentrator (FPC) has attached the PICs that it houses. It did not receive notification from the indicated FPC.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_FPC_TYPE_SIB_TYPE_ERROR

System Log Message Installed SIB type (SIB-I8-F16) does not support features required by FPC *fpc-slot*

Description The indicated Flexible PIC Concentrator (FPC) is Type 4, which is not supported by Switch Interface Board (SIB) type SIB-I8-F16.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_FRU_ALREADY_OFFLINE

System Log Message	<i>fru-name fru-slot</i> already offline
Description	The chassis process (chassisd) received a request to take the indicated component (field-replaceable unit, or FRU) offline, but the FRU was already offline.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON

CHASSISD_FRU_ALREADY_ONLINE

System Log Message	Received request to bring <i>fru-name fru-slot</i> online; it was already online
Description	The chassis process (chassisd) received a request to bring the indicated component (field-replaceable unit, or FRU) online, but the FRU was already online.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

CHASSISD_FRU_EVENT

System Log Message	<i>function-name: state fru-name fru-slot</i>
Description	The state of the indicated component (field-replaceable unit, or FRU) changed as indicated.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

CHASSISD_FRU_INVALID_SLOT

System Log Message	FRU <i>fru-name</i> is not supported in current slot
Description	The chassis process (chassisd) detected that the indicated hardware component (field-replaceable unit, or FRU) was inserted in a slot that is not valid for that component type.
Type	Error: An error occurred
Severity	critical
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FRU_IO_ERROR

System Log Message	<i>function-name: fru-name operation error: reason (error-message)</i>
Description	The chassis process (chassisd) could not perform the indicated I/O operation on the indicated component (field-replaceable unit, or FRU).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FRU_IO_OFFSET_ERROR

System Log Message	<i>function-name: fru-name operation error: reason 0xoffset (error-message)</i>
Description	The chassis process (chassisd) could not perform the indicated I/O operation at the indicated byte offset.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_FRU_IPC_WRITE_ERROR

System Log Message	<i>function-name: FRU fru-name, errno error-code, error-message</i>
Description	The chassis process (chassisd) could not send an interprocess communication (IPC) message to the indicated component (field-replaceable unit, or FRU) because of the indicated error.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON

CHASSISD_FRU_OFFLINE_FAILED

System Log Message	Unable to take <i>fru-name fru-slot</i> offline because FRU sequencer is active: <i>reason</i>
Description	The chassis process (chassisd) could not take the indicated component (field-replaceable unit, or FRU) offline for the indicated reason.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

CHASSISD_FRU_OFFLINE_NOTICE

System Log Message	Taking <i>fru-name fru-slot</i> offline: <i>reason</i>
Description	The chassis process (chassisd) took the indicated component (field-replaceable unit, or FRU) offline for the indicated reason.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

CHASSISD_FRU_OFFLINE_TIMEOUT

System Log Message	Offline request timed out; <i>fru-name fru-slot</i> restarted
Description	The indicated component (field-replaceable unit, or FRU) did not go offline within the time period that is normally sufficient for synchronized shutdown. After generating this message, the chassis process (chassisd) tried several times to take the FRU offline and powered it down if all attempts failed.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

CHASSISD_FRU_ONLINE_TIMEOUT

System Log Message	<i>function-name</i> : attempt to bring <i>fru-name fru-slot</i> online timed out
Description	The indicated component (field-replaceable unit, or FRU) did not come online within the time that is normally sufficient. After generating this message, the chassis process (chassisd) tried to bring the FRU online several more times. If all attempts failed, the chassisd process raised an alarm and left the FRU offline.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON

CHASSISD_FRU_STEP_ERROR

System Log Message	<i>fru-name fru-slot</i> at step <i>step-number</i>
Description	The power-on sequence for the indicated component (field-replaceable unit, or FRU) failed at the indicated point.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_FRU_UNRESPONSIVE

System Log Message	Error for <i>fru-name fru-slot</i> : <i>error-message</i> ; <i>action</i>
Description	The chassis process (chassisd) tried to bring the indicated component (field-replaceable unit, or FRU) online, but the attempt failed in the indicated way. As a result, the chassisd process performed the indicated action.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON

CHASSISD_FRU_UNRESPONSIVE_RETRY

System Log Message	Attempt <i>count</i> to power on <i>fru-name fru-slot</i> timed out; restarted it
Description	The chassis process (chassisd) tried the indicated number of times to bring the indicated component (field-replaceable unit, or FRU) online, but the attempts failed. In another attempt to bring the FRU online, the chassisd process issued the restart command for the FRU.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON

CHASSISD_FRU_UNSUPPORTED

System Log Message	chassisd invalidated support for <i>fru-name fru-slot</i>
Description	The chassis process (chassisd) invalidated support for the indicated component (field-replaceable unit, or FRU) during initialization.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON

CHASSISD_FRU_VERSION_MISMATCH

System Log Message	<i>component</i> version mismatch for <i>fru-name</i> -- expected <i>expected-value</i> , got <i>received-value</i>
Description	The chassis process (chassisd) verifies that it supports the revision level or version of a component (field-replaceable unit, or FRU). The revision level for the indicated FRU was unsupported or otherwise invalid.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON
Action	Upgrade the FRU.

CHASSISD_GASIC_ID_ERROR

System Log Message	Fchip: invalid SIB slot
Description	A routine tried to determine the identifier for an application-specific integrated circuit (ASIC) on a Switch Interface Board (SIB). The attempt failed, because the supplied SIB slot number was invalid.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_GBUS_NOT_READY

System Log Message	<i>function-name: fru-name</i> not ready for power up (RTIME_PWR_COND = 0x <i>value</i>)
Description	The GBUS was not ready when the chassis process (chassisd) first tried to power it on, and the power-up operation timed out.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	The probable cause is hardware error.
Action	Contact your technical support representative.

CHASSISD_GBUS_READBACK_ERROR

System Log Message	Readback error from GBUS for <i>fru-name fru-slot</i> ([0x <i>gbus-address</i> , 0x <i>gbus-registers</i>] -> 0x <i>return-value</i>)
Description	There was an error when the chassis process (chassisd) tried to read back information from the GBUS on the indicated component (field-replaceable unit, or FRU).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	The probable cause is hardware error.
Action	Contact your technical support representative.

CHASSISD_GBUS_RESET_EVENT

System Log Message	<i>fru-name#fru-slot - command</i>
---------------------------	------------------------------------

Description The chassis process (chassisd) reset the GBUS for the indicated component (field-replaceable unit, or FRU). This is a normal part of startup.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

CHASSISD_GBUS_SANITY_ERROR

System Log Message *function-name: fru-name fru-slot -- management bus failed sanity test*

Description The chassis process (chassisd) checks its management GBUS with a set of test operations when it is started. The tests failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_GENERIC_ERROR

System Log Message *function-name: error-message*

Description The chassis process (chassisd) detected the indicated error.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Perform any corrective actions mentioned in the error message.

CHASSISD_GENERIC_WARNING

System Log Message *function-name: error-message*

Description The chassis process (chassisd) generated the indicated warning message.

Type Error: An error occurred

Severity notice

Facility LOG_DAEMON

CHASSISD_GETTIMEOFDAY

System Log Message Unexpected error from gettimeofday: *error-code -- error-message*

Description The chassis process (chassisd) could not obtain the time of day because of the indicated error.

Type Error: An error occurred
Severity warning
Facility LOG_DAEMON

CHASSISD_GRES_UNSUPP_PIC

System Log Message Unable to enable graceful Routing Engine switchover; PIC does not support it
Description The chassis process (chassisd) could not enable graceful Routing Engine switchover because an installed PIC does not support it.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

CHASSISD_HIGH_TEMP_CONDITION

System Log Message Chassis temperature over *temperature* degrees C (*message*)
Description The temperature of one or more components (field-replaceable units, or FRUs) exceeded the indicated temperature, which is the lower of two thresholds. The fans (and impellers, if applicable) were in the indicated state. The chassis process (chassisd) increased the speed of all functioning fans and impellers to full speed.

Type Event: This message reports an event, not an error
Severity warning
Facility LOG_DAEMON
Action Increase cooling in the area around the chassis.

CHASSISD_HOST_TEMP_READ

System Log Message Error reading host temperature sensor
Description The chassis process (chassisd) could not read the temperature sensors on the routing platform.

Type Error: An error occurred
Severity notice
Facility LOG_DAEMON

CHASSISD_HSR_CONFIG_READ_ERROR

System Log Message *function-name*: unable to read configuration for HSR *identifier*
Description The indicated function could not read the configuration for the indicated high-speed receiver (HSR).

Type Error: An error occurred

Severity error
Facility LOG_DAEMON

CHASSISD_HSR_CONFIG_WRITE_ERROR

System Log Message *function-name*: unable to write configuration for HSR *identifier*

Description The indicated routine could not write to the configuration for the indicated high-speed receiver (HSR).

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHASSISD_HSR_ELEMENTS_ERROR

System Log Message Provided number of HSR elements (*count*) was invalid

Description The indicated routine for processing a certain number of high-speed receiver (HSR) elements failed, because the supplied number of elements was invalid.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHASSISD_HSR_FIFO_ERROR

System Log Message *function-name*: FIFO read failed for HSR *identifier*

Description A first in, first out (FIFO) read error occurred during execution of the indicated routine on the indicated high-speed receiver (HSR).

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHASSISD_I2CS_READBACK_ERROR

System Log Message Readback error from I2C slave for *fru-name fru-slot* ([*0xi2cs-address*, *0xoffset*] -> *0xerror-code*)

Description The chassis process (chassisd) could not read back information from the I2C slave (I2CS) about the indicated component (field-replaceable unit, or FRU).

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause The probable cause is hardware error.

Action Contact your technical support representative.

CHASSISD_I2C_BAD_IDEEPROM_FORMAT

System Log Message Invalid IDEEPROM format for *fru-name*

Description The chassis process (chassisd) determined that the ID EEPROM format specified for the indicated type of hardware component (field-replaceable unit, or FRU) is not valid for it.

Type Error: An error occurred

Severity critical

Facility LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_I2C_FIC_PRESENCE_READ

System Log Message *function-name: fru-name* unable to get presence masks (*error-message*)

Description The chassis process (chassisd) could not read I2C data with presence information about the indicated component (field-replaceable unit, or FRU).

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_I2C_GENERIC_ERROR

System Log Message *function-name: error-message*

Description The indicated error occurred during an I2C access library operation.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_I2C_INVALID_ASSEMBLY_ID

System Log Message 'Ox*assembly-id*' is invalid value for *fru-name* assembly ID

Description The assembly ID for the indicated component (field-replaceable unit, or FRU) was not valid for its type.

Type Error: An error occurred

Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_I2C_IOCTL_FAILURE

System Log Message	<i>function-name: operation</i> ioctl failure for group <i>group-id</i> at address <i>0xaddress</i> (<i>errno error-code</i>)
Description	The chassis process (chassisd) could not perform the indicated ioctl() operation on the I2C data for the indicated component (field-replaceable unit, or FRU).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_I2C_IO_FAILURE

System Log Message	<i>function-name: fru-name</i> operation failed for group <i>group-id</i> at address <i>0xaddress</i>
Description	The chassis process (chassisd) could not perform the indicated I/O operation on the I2C data for the indicated component (field-replaceable unit, or FRU).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_I2C_MIDPLANE_CORRUPT

System Log Message	Corruption on midplane ID EEPROM (ID: <i>0xassembly-id</i> , MAC address: <i>0xmac-address</i> , <i>0xversion</i>)
Description	The chassis process (chassisd) found corrupted information when it tried to verify the parameters of the midplane's I2C ID EEPROM.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_I2C_RANGE_ERROR

System Log Message	<i>function-name:</i> requested offset was out of range (offset <i>offset</i> + nbytes <i>count</i> > 256)
---------------------------	--

Description	The indicated offset, which is greater than 256, was specified in a read request for an I2C device.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	No I2C device uses or has storage above an offset of 256.
Action	Contact your technical support representative.

CHASSISD_I2C_READ_ERROR

System Log Message	<i>function-name</i> : read error for group <i>group-id</i> at address <i>0xaddress</i> , offset <i>offset</i>
Description	The chassis process (chassisd) could not read I2C data from the indicated device.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_I2C_WRITE_ERROR

System Log Message	<i>function-name</i> : write error for group <i>group-id</i> at address <i>0xaddress</i> , offset <i>offset</i>
Description	The chassis process (chassisd) could not write I2C data to the indicated device.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_IDEEPROM_READ_ERROR

System Log Message	Unable to read <i>fru-name</i> ID EEPROM
Description	The chassis process (chassisd) could not read the I2C ID EEPROM of the indicated component (field-replaceable unit, or FRU).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_IFDEV_CREATE_FAILURE

System Log Message	<i>function-name</i> : unable to create interface device for <i>interface-name</i> (<i>error-message</i>)
Description	The chassis process (chassisd) creates initial interface devices for newly installed PICs and pseudodevices. It could not create a device for the indicated PIC or pseudodevice.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	Necessary resources might have been unavailable.
Action	Contact your technical support representative.

CHASSISD_IFDEV_CREATE_NOTICE

System Log Message	<i>function-name</i> : created <i>device-name</i> for <i>interface-name</i>
Description	The chassis process (chassisd) created the initial interface device for the indicated newly installed PIC or pseudodevice.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

CHASSISD_IFDEV_DETACH_ALL_PSEUDO

System Log Message	ifdev_detach(pseudo devices: all)
Description	The chassis process (chassisd) detached the interface devices for all pseudodevices.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

CHASSISD_IFDEV_DETACH_FPC

System Log Message	ifdev_detach_fpc(<i>fpc-slot</i>)
Description	The chassis process (chassisd) detached the interface devices for all PICs installed in the indicated Flexible PIC Concentrator (FPC).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

CHASSISD_IFDEV_DETACH_PIC

System Log Message	<code>ifdev_detach_pic(<i>fpc-slot/pic-slot</i>)</code>
Description	The chassis process (chassisd) detached the interface devices for the indicated PIC.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

CHASSISD_IFDEV_DETACH_PSEUDO

System Log Message	<code>ifdev_detach(pseudo devices: porttype <i>port-type</i>, sdev=<i>sdev-number</i>, edev=<i>edev-number</i>)</code>
Description	The chassis process (chassisd) detached the interface devices for the indicated pseudodevices.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

CHASSISD_IFDEV_DETACH_TLV_ERROR

System Log Message	<code>ifdev_detach: rtslib_ifdm_change_tlvs failed for slot <i>fpc-slot</i> dev idx <i>device-id</i> <i>error-message</i></code>
Description	The chassis process (chassisd) asked the kernel to remove the indicated interface from the kernel interface table. The request failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_IFDEV_GETBYNAME_NOTICE

System Log Message	<code><i>function-name</i>: ifdm get_by_name failed for <i>interface-type</i> interface device <i>interface-name</i> (<i>error-message</i>)</code>
Description	The chassis process (chassisd) failed to find the indicated interface device, even though it just created it.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	There was a problem with interface state creation.
Action	Contact your technical support representative.

CHASSISD_IFDEV_GET_BY_INDEX_FAIL

System Log Message	<i>function-name: rtslib_ifdm_get_by_index failed: error-code - error-message</i>
Description	The chassis process (chassisd) could not obtain information about an interface device.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_IFDEV_GET_BY_NAME_FAIL

System Log Message	Unable to retrieve information for interface device <i>interface-name: error-message</i>
Description	The chassis process (chassisd) could not obtain information about the indicated interface device.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_IFDEV_NO_MEMORY

System Log Message	<i>function-name: unable to allocate memory for interface-type interface</i>
Description	The chassis process (chassisd) could not allocate memory when creating an interface device for the indicated interface type.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	Resources on the system are extremely limited.
Action	Eliminate the resource limitations and restart the PIC that houses the interface for which the interface device could not be created.

CHASSISD_IFDEV_RETRY_NOTICE

System Log Message	<i>function-name: attempt count to add interface device interface-name failed (error-message)</i>
Description	The chassis process (chassisd) tried the indicated number of times to create the indicated interface device, but the attempts failed. After generating this message, the chassisd process waited a while for resources to free up and tried again.
Type	Event: This message reports an event, not an error
Severity	warning

Facility LOG_DAEMON

Cause Necessary resources might have been unavailable. They should become available soon.

CHASSISD_IFDEV_RTSLIB_FAILURE

System Log Message *function-name: library-function-name failed (error-message)*

Description The chassis process (chassisd) could not create an interface device because an error occurred during the indicated call to the routing socket library.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_IOCTL_FAILURE

System Log Message *function-name: reason for fru-name (error-message)*

Description The chassis process (chassisd) could not perform the indicated ioctl() operation on the indicated component (field-replaceable unit, or FRU).

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_IPC_ANNOUNCE_TIMEOUT

System Log Message *function-name: no ack received from fru-type for fru-name fru-slot state change (Oxsent-mask, acks Oxack-mask)*

Description The chassis process (chassisd) notified the indicated components (field-replaceable units, or FRUs) that the component in the indicated slot was changing state. It did not receive the expected acknowledgment.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_IPC_CONNECTION_DROPPED

System Log Message Dropped IPC connection for *fru-name fru-slot*

Description	The chassis process (chassisd) dropped its interprocess communication (IPC) connection to the indicated component (field-replaceable unit, or FRU).
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

CHASSISD_IPC_DAEMON_WRITE_ERROR

System Log Message	pipe_write failure for <i>connection-id</i> ; connection error: <i>error-message</i> (errno <i>error-code</i>)
Description	The chassis process (chassisd) could not write to a socket, because of the indicated error. The socket is for a connection to another process that runs on the Routing Engine and helps manage the chassis.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_IPC_ERROR

System Log Message	<i>function-name</i> : <i>error-message</i>
Description	An error occurred when the chassis process (chassisd) received an interprocess communication (IPC) message.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_IPC_FLUSH_ERROR

System Log Message	<i>function-name</i> : flush operation failed for <i>fru-name</i> <i>fru-slot</i>
Description	The chassis process (chassisd) could not write to a socket that it was using to communicate with the indicated component (field-replaceable unit, or FRU).
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_IPC_MSG_DROPPED

System Log Message	Dropping message from connection queue: type = <i>message-type</i> , subtype = <i>message-subtype</i>
Description	The chassis process (chassisd) dropped an interprocess communication (IPC) message because the message queue had already reached maximum capacity.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	The connection to a component (field-replaceable unit, or FRU) no longer exists, so the chassisd process cannot send all messages immediately as it usually does.
Action	Contact your technical support representative.

CHASSISD_IPC_MSG_ERROR

System Log Message	<i>function-name</i> : error code <i>error-code</i> , type <i>message-type</i> , subtype <i>message-subtype</i> , opcode <i>message-opcode</i>
Description	The chassis process (chassisd) detected an error in an interprocess communication (IPC) message with the indicated characteristics.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_IPC_MSG_FRU_NOT_FOUND

System Log Message	<i>function-name</i> : unable to locate FRU for message with type <i>message-type</i> , subtype <i>message-subtype</i> , opcode <i>message-opcode</i>
Description	The chassis process (chassisd) could not locate a component (field-replaceable unit, or FRU) to handle the interprocess communication (IPC) message with the indicated characteristics that it received. The message was ignored.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_IPC_MSG_QFULL_ERROR

System Log Message	Dropping message from connection queue: type = <i>message-type</i> , subtype = <i>message-subtype</i>
Description	The chassis process (chassisd) had to discard a message because the queue of messages waiting for a connection was already full.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_IPC_MSG_UNHANDLED

System Log Message	<i>function-name</i> : unable to handle <i>fru-name</i> message with type <i>message-type</i> , subtype <i>message-subtype</i> , length <i>length</i> , opcode <i>message-opcode</i> , error <i>error-code</i>
Description	The chassis process (chassisd) received an interprocess communication (IPC) message about the indicated FRU. The message had the indicated characteristics. The chassisd process could not handle the message.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_IPC_UNEXPECTED_MSG

System Log Message	<i>function-name</i> : invalid message received: <i>message</i> (message type <i>message-type</i> , subtype <i>message-subtype</i>)
Description	The chassis process (chassisd) received a unexpected message with the indicated characteristics.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_IPC_UNEXPECTED_RECV

System Log Message	Received unexpected message from <i>connection-id</i> : type = <i>message-type</i> , subtype = <i>message-subtype</i>
Description	The chassis process (chassisd) received an unexpected message from a peer connection.
Type	Error: An error occurred

Severity error
Facility LOG_DAEMON

CHASSISD_IPC_WRITE_ERROR

System Log Message *function-name*: pipe_write failure for SCC connection with error *error-code* (*error-message*)

Description A line-card chassis in a routing matrix attempted to send data to the TX Matrix platform (switch-card chassis, or SCC) over a pipe. The attempt failed with the indicated error.

Type Error: An error occurred

Severity warning

Facility LOG_DAEMON

CHASSISD_IPC_WRITE_ERR_NO_PIPE

System Log Message FRU has no connection pipe *function-name* *fru-name*

Description The chassis process (chassisd) could not send a message to the indicated component (field-replaceable unit, or FRU) because the interprocess communication (IPC) pipe to the FRU no longer existed.

Type Error: An error occurred

Severity warning

Facility LOG_DAEMON

CHASSISD_IPC_WRITE_ERR_NULL_ARGS

System Log Message FRU has no connection arguments *function-name* *fru-name*

Description The chassis process (chassisd) could not send a message to the indicated component (field-replaceable unit, or FRU) because one or more required parameters had a null value.

Type Error: An error occurred

Severity warning

Facility LOG_DAEMON

CHASSISD_ISSU_BLOB_ERROR

System Log Message *fru-name*: *error-message*

Description The chassisd process (chassisd) detected the indicated error while handling blobs (opaque information) for the indicated field replaceable unit (fru). The blobs are used by the fru to store state information across in service software upgrade(issu) reboot.

Type Error: An error occurred

Severity notice

Facility LOG_DAEMON

CHASSISD_ISSU_DAEMON_ERROR

System Log Message	Daemon [<i>process-name</i>] state:< <i>state</i> > error:< <i>error-message</i> >
Description	The chassisd process (chassisd) encountered the indicated error in the indicated in service software upgrade (issu) state for the indicated daemon.
Type	Error: An error occurred
Severity	notice
Facility	LOG_DAEMON

CHASSISD_ISSU_ERROR

System Log Message	<i>action error-code(error-message)</i>
Description	The chassisd process (chassisd) encountered the indicated error for the indicated in service software upgrade process (issu) action.
Type	Error: An error occurred
Severity	notice
Facility	LOG_DAEMON

CHASSISD_ISSU_FRU_ERROR

System Log Message	<i>fru-name: state:[state] error-message</i>
Description	The chassisd process (chassisd) encountered the indicated error during the in service software upgrade for the indicated field replaceable unit (fru).
Type	Error: An error occurred
Severity	notice
Facility	LOG_DAEMON

CHASSISD_ISSU_FRU_IPC_ERROR

System Log Message	<i>fru-name: state:[state] error:[message] reason:[error-message]</i>
Description	The chassisd process (chassisd) detected the indicated error for the indicated field replaceable unit (fru) during in service software upgrade (issu).
Type	Error: An error occurred
Severity	notice
Facility	LOG_DAEMON

CHASSISD_JTREE_ERROR

System Log Message	jtree terminate operation returned <i>error-code</i>
Description	The chassis process (chassisd) received the indicated error when executing the Junos system call that terminates the jtree.

Type Event: This message reports an event, not an error
Severity warning
Facility LOG_DAEMON

CHASSISD_LCC_RELEASE_MASTERSHIP

System Log Message Backup Routing Engine became master, because JUNOS version of former master did not match SCC master

Description The chassis process (chassisd) running on the master Routing Engine on a T640 routing node (line-card chassis, or LCC, in a routing matrix) relinquished mastership to the backup Routing Engine in the LCC.

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_DAEMON

Cause The version of the Junos OS on the master Routing Engine did not match the version on the TX Matrix platform's master Routing Engine. The version on the backup Routing Engine did match the TX Matrix platform.

CHASSISD_LOST_MASTERSHIP

System Log Message Routing Engine lost mastership; exiting

Description The chassis process (chassisd) running on the master Routing Engine exited, because mastership switched to the other Routing Engine.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON
Action Contact your technical support representative.

CHASSISD_MAC_ADDRESS_AE_ERROR

System Log Message chassisd MAC address allocation error for *aedvice-id*

Description The chassis process (chassisd) could not obtain a media access control (MAC) address for the indicated aggregated Ethernet interface because of an internal error.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

CHASSISD_MAC_ADDRESS_CBP_ERROR

System Log Message chassisd MAC address allocation error for CBP

Description The chassis process (chassisd) could not obtain a media access control (MAC) address for a customer backbone port because of an internal error.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHASSISD_MAC_ADDRESS_ERROR

System Log Message chassisd MAC address allocation exceed error for FPC *fpc-slot*, PIC *pic-slot*, port *port*

Description The chassis process (chassisd) could not obtain a media access control (MAC) address for the indicated interface because of an internal error.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHASSISD_MAC_ADDRESS_FABRIC_ERR

System Log Message Unable to allocate MAC address for fabric interface *device-id*

Description The chassis process (chassisd) could not obtain a media access control (MAC) address for the indicated fabric interface because of an internal error.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHASSISD_MAC_ADDRESS_IRB_ERROR

System Log Message chassisd MAC address allocation error for IRB

Description The chassis process (chassisd) could not obtain a media access control (MAC) address for an integrated routing and bridging interface because of an internal error.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHASSISD_MAC_ADDRESS_PIP_ERROR

System Log Message chassisd MAC address allocation error for PIP

Description The chassis process (chassisd) could not obtain a media access control (MAC) address for a provider instance port because of an internal error.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHASSISD_MAC_ADDRESS_SWFAB_ERR

System Log Message Unable to allocate MAC address for swfabric interface *device-id*

Description The chassis process (chassisd) could not obtain a media access control (MAC) address for the indicated swfabric interface because of an internal error.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHASSISD_MAC_ADDRESS_VLAN_ERROR

System Log Message chassisd MAC address allocation error for VLAN

Description The chassis process (chassisd) could not obtain a media access control (MAC) address for a vlan interface because of an internal error.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHASSISD_MAC_DEFAULT

System Log Message Using default MAC address base

Description The chassis process (chassisd) used the default base media access control (MAC) address.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

CHASSISD_MALLOC_FAILURE

System Log Message *function-name*: chassisd malloc failed, aborting

Description The chassis process (chassisd) could not allocate memory. The chassisd process tried to continue functioning, but the lack of memory usually causes the process to fail. An administrator needs to restart it at some point.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_MASTER_PCG_REMOVED

System Log Message	Master PCG (slot <i>pcg-slot</i>) removed; powering down Packet Forwarding Engine complex
Description	The master Packet Forwarding Engine Clock Generator (PCG) was removed. The PCG provides the system clock for all application-specific integrated circuits (ASICs) in the routing platform, so packet forwarding halts until the Packet Forwarding Engine is restarted and a PCG is functioning as master.
Type	Error: An error occurred
Severity	critical
Facility	LOG_DAEMON

CHASSISD_MASTER_SCG_REMOVED

System Log Message	Master SCG (slot <i>fru-slot</i>) removed; powering it down
Description	The master SONET Clock Generator (SCG) was removed. The SCG provides the clock for SONET/SDH interface timing, so those interfaces might drop packets and experience other errors until a new clock source is established.
Type	Error: An error occurred
Severity	critical
Facility	LOG_DAEMON

CHASSISD_MBUS_ERROR

System Log Message	<i>fru-name fru-slot</i> : management bus failed sanity test
Description	Startup tests on the indicated FRU's management bus failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_MCHASSIS_SWITCH_WARNING

System Log Message	CB settings on <i>chassis-type old-index</i> changed: switch is now ' <i>value</i> ', chassis index is now <i>0xnew-index</i>
Description	A toggle switch on the back of the Control Board on each platform in a routing matrix is set to 'M' (multichassis) on the T640 routing nodes and to 'S' (single-chassis) on the TX Matrix platform. On a T640 routing node, the adjacent dial is set to the node's index number in the routing matrix (0 through 3); on the TX Matrix platform it is set to 0. The setting of the toggle switch, the dial, or both, changed to the indicated values on the indicated platform. The new settings take effect when the routing matrix next reboots.

Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Action	If the changes were accidental, return the toggle and dial to the correct settings before the next reboot. If the changes were intended, disconnect and move the cables on the TX Matrix platform Switch Interface Board (SIB) to the row that corresponds to the T640 routing node's new index number.

CHASSISD_MCS_INTR_ERROR

System Log Message	Received SIGUSR2 without any interrupts pending
Description	The chassis process (chassisd) received the indicated interrupt signal. The signal normally indicates that an event on the Miscellaneous Control Subsystem (MCS) requires servicing. However, the chassisd process did not find such an event pending. This error does not usually cause component failure.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_MGR_CONNECT

System Log Message	<i>function-name</i> evSelectFD: initial pipe create aborted (errno <i>error-code</i>)
Description	The chassis process (chassisd) could not to open a pipe for interprocess communication (IPC) to a component (field-replaceable unit, or FRU).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_MIC_OFFLINE_NOTICE

System Log Message	Taking MIC <i>mic-slot</i> in FPC <i>fpc-slot</i> offline: <i>reason</i>
Description	The chassis process (chassisd) took the indicated MIC offline, for the indicated reason.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

CHASSISD_MULTILINK_BUNDLES_ERROR

System Log Message	Unable to set multilink Frame Relay UNI NNI bundles for PIC <i>pic-slot</i> in FPC <i>fpc-slot</i>
Description	The chassis process (chassisd) could not create multilink Frame Relay user-to-network interface and network-to-network interface (MLFR UNI NNI [FRF.16]) bundles for the indicated PIC.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_NO_PCGS

System Log Message	No PCG <i>status</i>
Description	The chassis process (chassisd) could not find an operational Packet Forwarding Engine Clock Generator (PCG). Packet forwarding is halted until a PCG becomes operational.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_NO_SCGS

System Log Message	No SCG <i>state</i>
Description	The chassis process (chassisd) could not find an operational SONET Clock Generator (SCG). To continue functioning correctly, SONET/SDH interfaces that use an SCG as their clock source must find another source.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_OFFLINE_NOTICE

System Log Message	Routing Engine offline: <i>message</i>
Description	The chassis process (chassisd) took the Routing Engine offline.
Type	Event: This message reports an event, not an error

Severity critical
Facility LOG_DAEMON

CHASSISD_OID_GEN_FAILED

System Log Message Unable to generate OID: *oid (error-message)*

Description The chassis process (chassisd) could not generate an object identifier (OID) for the indicated object.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_OVER_TEMP_CONDITION

System Log Message Chassis temperature over *temperature* degrees C (*message*); routing platform will shutdown in *duration* seconds if condition persists

Description The temperature of one or more components (field-replaceable units, or FRUs) exceeded the indicated temperature, which is the upper of two thresholds. The fans (and impellers, if applicable) were in the indicated state. If the temperature does not go below the threshold within four minutes after the chassis process (chassisd) detects this condition, the chassisd process shuts down the routing platform. When this message was logged, the indicated number of seconds remained before shutdown.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Increase cooling in the area around the chassis.

CHASSISD_OVER_TEMP_SHUTDOWN_TIME

System Log Message Chassis temperature above *temperature* degrees C *description* (> *duration* seconds); powering down all FRUs

Description The chassis process (chassisd) shut down the routing platform because the temperature of one or more components exceeded the indicated threshold temperature for the indicated amount of time. Continued operation at the excessive temperature could damage the routing platform.

Type Error: An error occurred

Severity critical

Facility LOG_DAEMON

Action Increase cooling in the area around the chassis.

CHASSISD_PARSE_COMPLETE

System Log Message	Using new configuration
Description	The chassis process (chassisd) successfully parsed its configuration file.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

CHASSISD_PCI_ERROR

System Log Message	<i>function-name: error-message</i>
Description	While performing an operation on the PCI bus, the chassis process (chassisd) encountered the indicated error.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	A software or a hardware problem occurred.
Action	Contact your technical support representative.

CHASSISD_PEER_UNCONNECTED

System Log Message	<i>function-name: peer not connected</i>
Description	The chassis process (chassisd) processed a packet for a peer with an invalid or missing connection.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON
Cause	In most cases, this error is caused by peers transitioning up and down unexpectedly. The error is usually transient and nonfatal.

CHASSISD_PEM_BREAKER_TRIP

System Log Message	Circuit breaker tripped for power supply <i>pem-slot</i>
Description	The circuit breaker was tripped for the indicated power entry module (PEM).
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

Action Turn on the affected PEM manually.

CHASSISD_PEM_IMPROPER

System Log Message Power supply *pem-slot* improper for platform

Description Old PEM is not supported in this platform.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Replace old PEM with proper newer PEM

CHASSISD_PEM_INPUT_BAD

System Log Message *error-message* for power supply *pem-slot* (status bits: *0xstatus-code*); check circuit breaker

Description The chassis process (chassisd) detected the indicated error condition for the indicated power entry module (PEM).

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

Action Check the status of the circuit breaker and the input connections.

CHASSISD_PEM_NOT_SUFFICIENT

System Log Message Unable to power up FPC *fpc-slot*, because no three-input 240-A power supply is installed

Description On the T1600 router, the T1600-FPC4 ES Flexible PIC Concentrator (FPC) requires that at least one three-input 240-A power supply be installed. The chassis process (chassisd) did not power on the T1600-FPC4 ES in the indicated slot because the required power supply is not installed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Install at least one three-input 240-A power supply.

CHASSISD_PEM_OVERLOAD

System Log Message Overload condition for power supply *pem-slot* (status bits: *0xstatus-code*);

Description The indicated power entry module (PEM) reported an output voltage overload condition.

Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	There might have been excessive load on the PEM.

CHASSISD_PEM_TEMPERATURE

System Log Message	Temperature check bit set for power supply <i>pem-slot</i> ; airflow might be inadequate
Description	The chassis process (chassisd) detected that the 'temperature check bit' was set in the status bit mask for the indicated power entry module (PEM).
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	The PEM might have exceeded its temperature threshold, possibly because the airflow through it was inadequate.

CHASSISD_PEM_VOLTAGE

System Log Message	Power supply <i>pem-slot</i> reports problem; check output voltage
Description	The indicated power entry module (PEM) reported a problem with its output voltage.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	There might have been excessive load on the PEM.

CHASSISD_PIC_CMD_GIVEUP

System Log Message	<i>function-name</i> : attempt <i>fpc-slot</i> to bring PIC <i>pic-slot</i> in FPC <i>count</i> online timed out; stopped trying
Description	The chassis process (chassisd) tried the indicated number of times to bring the indicated PIC online, but stopped trying after all attempts failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_PIC_CMD_TIMEOUT

System Log Message	<i>function-name</i> : attempt to bring PIC <i>pic-slot</i> in FPC <i>fpc-slot</i> online timed out
Description	The chassis process (chassisd) tried to bring the indicated PIC online. The attempt took longer than the standard time allotted for that operation.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_PIC_CONFIG_CONFLICT

System Log Message	<i>fpc pic-slot</i> pic <i>fpc-slot</i> port mirror instance <i>instance</i> will be applied to both the PICs
Description	The PIC configuration will be applied to all PICs on the FPC.
Type	Event: This message reports an event, not an error
Severity	unknown
Facility	LOG_DAEMON

CHASSISD_PIC_CONFIG_ERROR

System Log Message	Unable to create interface devices during attachment of PIC <i>pic-slot</i> in FPC <i>fpc-slot</i> : graceful switchover not supported
Description	The chassis process (chassisd) did not create an interface device for the indicated PIC because graceful switchover was enabled but is not supported in combination with that PIC type. A PIC must have an interface device to come online, so it remained offline.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Remove the PIC or upgrade the Junos OS.

CHASSISD_PIC_HWERROR

System Log Message	PIC <i>pic-slot</i> in FPC <i>fpc-slot</i> (PIC type <i>pic-type</i> , version <i>version</i>) had hardware error
Description	The indicated PIC experienced a hardware error. The chassis process (chassisd) did not bring the PIC online.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_PIC_OFFLINE_NOTICE

System Log Message Taking PIC *pic-slot* in FPC *fpc-slot* offline: *reason*

Description The chassis process (chassisd) took the indicated PIC offline, for the indicated reason.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

CHASSISD_PIC_OID_GEN_FAILED

System Log Message Unable to generate OID for PIC: *pic-name* (*error-message*)

Description The chassis process (chassisd) could not generate an object identifier (OID) for the indicated Physical Interface Card (PIC).

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_PIC_OID_UNKNOWN

System Log Message Unable to find OID for PIC: *i2c-id*

Description The chassis process (chassisd) could not determine the object identifier (OID) for the PIC with the indicated identifier.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_PIC_RESET_ON_SWITCHOVER

System Log Message PIC *pic-slot* in FPC *fpc-slot* (type *pic-type*, version *version*) will be reset on switchover

Description The chassis process (chassisd) noted that the PIC with the indicated characteristics needs to be reset when a graceful switchover occurs.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

CHASSISD_PIC_SPEED_INVALID

System Log Message	Set speed for <i>so-fpc-slot/pic-slot/port</i> to <i>default-value</i> because configured value <i>current-value</i> is invalid
Description	The chassis process (chassisd) set the speed for the indicated PIC to the indicated value, because the configured value is either higher than the maximum valid value or lower than the minimum valid value.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Reconfigure the PIC with a valid speed.

CHASSISD_PIC_VERSION_ERROR

System Log Message	Hardware version (<i>pic-slot</i>) of PIC <i>fpc-slot</i> in FPC <i>pic-type</i> (PIC type <i>version</i>) is not supported
Description	The chassis process (chassisd) did not bring the indicated PIC online, because its hardware version is not supported.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Cause	The PIC requires a hardware upgrade.
Action	Contact your technical support representative.

CHASSISD_PIDFILE_OPEN

System Log Message	Unable to open PID file ' <i>filename</i> ': <i>errno error-code</i>
Description	The chassis process (chassisd) could not open the file where it stores its process ID (PID).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	The chassisd process might have detected that another chassisd process was running and tried to read the file so that it could use the PID recorded there when terminating the other process.

CHASSISD_PIPE_WRITE_ERROR

System Log Message	Pipe write error: <i>error-message</i>
---------------------------	--

Description	The chassis process (chassisd) experienced a fatal error while writing to a pipe.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	There was no reader for the pipe.

CHASSISD_POWER_CHECK

System Log Message	<i>fru-name fru-slot</i> not powering up
Description	The chassis process (chassisd) could not power up the indicated component (field-replaceable unit, or FRU), because the FRU did not respond.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_POWER_EVENT

System Log Message	Unable to turn off power to <i>fru-name fru-slot</i> ; a stand-alone test jumper might be installed
Description	The chassis process (chassisd) could not turn off power to the indicated component (field-replaceable unit, or FRU).
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	A common reason is that a standalone test jumper is installed.

CHASSISD_POWER_RATINGS_EXCEEDED

System Log Message	PIM/module in slot <i>fru-slot</i> left offline to avoid exceeding chassis power ratings
Description	The chassis process (chassisd) did not bring online the component (field-replaceable unit, or FRU) in the indicated slot, because doing so causes the total power demand of components in the chassis to exceed the chassis' power ratings. On a J-series Services Router, the component is a Physical Interface Module (PIM) or other module that installs in a PIM slot.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_PSD_RELEASE_MASTERSHIP

System Log Message	Backup Routing Engine became master, because JUNOS version of former master did not match RSD master
Description	The chassis process (chassisd) running on the master Routing Engine on a System-Domain routing node relinquished mastership to the backup Routing Engine in the PSD.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON
Cause	The version of the Junos OS on the master Routing Engine did not match the version on the RSD platform's master Routing Engine. The version on the backup Routing Engine did match the RSD platform.

CHASSISD_PSU_ERROR

System Log Message	<i>error-message</i> power supply <i>pem-slot</i> (status bits: <i>0xstatus-code</i>); status failure
Description	The chassis process (chassisd) detected the indicated error condition for the indicated power supply unit (PSU).
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

CHASSISD_PSU_FAN_FAIL

System Log Message	Fan Fail for power supply <i>pem-slot</i>
Description	PSU Fan fail bit is set in the status for the indicated power supply unit (PSU)
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON

CHASSISD_PSU_INPUT_BAD

System Log Message	<i>error-message</i> power supply <i>pem-slot</i> (status bits: <i>0xstatus-code</i>); Input failure
Description	The chassis process (chassisd) detected the input voltage/warning fault condition for the indicated power supply unit (PSU).
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Action	Check the status of the input connections.

CHASSISD_PSU_OVERLOAD

System Log Message	Overload condition for power supply <i>pem-slot</i> (status bits: <i>0xstatus-code</i>);
Description	The indicated power supply unit (PSU) reported an output voltage overload condition.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	There might have been excessive load on the PSU.

CHASSISD_PSU_TEMPERATURE

System Log Message	Temperature check bit set for power supply <i>pem-slot</i> ; airflow might be inadequate
Description	The chassis process (chassisd) detected that the 'temperature check bit' was set in the status bit mask for the indicated power supply unit (PSU).
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	The PSU might have exceeded its temperature threshold, possibly because the airflow through it was inadequate.

CHASSISD_PSU_VOLTAGE

System Log Message	Power supply <i>pem-slot</i> reports problem; check output voltage
Description	The indicated power supply unit (PSU) reported a problem with its output voltage.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	There might have been excessive load on the PSU.

CHASSISD_RANGE_CHECK

System Log Message	<i>function-name</i> : '0xvalue' is invalid value for <i>object-name</i> (out of range)
Description	The indicated value was outside the valid range of values for the indicated object.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_RECONNECT_SUCCESSFUL

System Log Message Successfully reconnected on soft restart

Description The chassis process (chassisd) successfully reconnected with each Packet Forwarding Engine after a soft restart.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

CHASSISD_RELEASE_MASTERSHIP

System Log Message Release mastership notification

Description The chassis process (chassisd) running on the master Routing Engine received a request to release mastership.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

Cause The Routing Engine was probably rebooting and graceful Routing Engine switchover is configured.

CHASSISD_RE_CONSOLE_FE_STORM

System Log Message Console device encountering framing error storm on Routing Engine *routing-engine-slot* (possibly a bad console cable)

Description At least one console device on the Routing Engine has encountered excessive framing errors. This can be indicative of a bad cable connected to the device (especially true in the case of a serial console port.)

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHASSISD_RE_INIT_INVALID_RE_SLOT

System Log Message re_init: re *routing-engine-slot*, out of range

Description The chassis process (chassisd) could not initialize a Routing Engine because the slot number specified for it was invalid.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHASSISD_RE_OVER_TEMP_CONDITION

System Log Message Routing Engine *routing-engine-slot* temperature (*temperature* C) over *threshold* degrees C

Description The temperature of the indicated Routing Engine exceeded the indicated temperature, which is the upper of two thresholds.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Increase cooling in the area around the chassis.

CHASSISD_RE_OVER_TEMP_SHUTDOWN

System Log Message Routing Engine *routing-engine-slot* temperature above *threshold* degrees C for too long; *action*

Description The chassis process (chassisd) performed the indicated action because the temperature of the indicated Routing Engine exceeded the maximum threshold for more than four minutes. Continued operation at the excessive temperature could damage routing platform components.

Type Error: An error occurred

Severity critical

Facility LOG_DAEMON

Action Increase cooling in the area around the chassis.

CHASSISD_RE_OVER_TEMP_WARNING

System Log Message Routing Engine *routing-engine-slot* temperature (*temperature* C) over *threshold* degrees C, *component* will shutdown in *duration* seconds if condition persists

Description The temperature of the indicated Routing Engine exceeded the indicated temperature, which is the upper of two thresholds. If the temperature does not go below the threshold within four minutes after the chassis process (chassisd) detects this condition, the chassisd process shuts down the indicated component. When this message was logged, the indicated number of seconds remained before shutdown.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Increase cooling in the area around the chassis.

CHASSISD_RE_WARM_TEMP_CONDITION

System Log Message	Routing Engine <i>routing-engine-slot</i> temperature (<i>temperature C</i>) is above warm temperature limit (<i>threshold C</i>)
Description	The temperature of the indicated Routing Engine exceeded the indicated temperature, which is the lower of two thresholds.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON
Action	Increase cooling in the area around the chassis.

CHASSISD_ROOT_MOUNT_ERROR

System Log Message	Unable to determine the mount point for root directory: <i>error-message</i>
Description	The chassis process (chassisd) could not determine the mount point for the root file system.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_RTS_SEQ_ERROR

System Log Message	ifmsg sequence gap <i>expected-value - received-value</i>
Description	The chassis process (chassisd) received a routing socket message out of order.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	A routing socket message was lost because of excessive load or lack of memory.

CHASSISD_SBOARD_VERSION_MISMATCH

System Log Message	Version mismatch: chassisd message version <i>expected-value fru-name</i> message version <i>received-value</i> local IPC version <i>local-ipc-version</i> remote IPC version <i>remote-ipc-version</i>
Description	The chassis process (chassisd) verifies that it supports the revision level or version of a component (field-replaceable unit, or FRU). The revision level for the indicated FRU was unsupported or otherwise invalid.
Type	Error: An error occurred
Severity	error

Facility LOG_DAEMON

Cause Either a previous software upgrade did not complete successfully, or the chassisd process or FRU did not restart after a successful software upgrade.

Action Upgrade the software and reboot the routing platform.

CHASSISD_SENSOR_RANGE_NOTICE

System Log Message *fru-name fru-slot* temperature is *temperature* degrees C, which is outside operating range

Description The temperature sensor on the indicated component (field-replaceable unit, or FRU) reported the indicated temperature, which is outside the acceptable operating range.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

Cause Some sensors generate erroneous readings when a FRU starts up. When this happens, the chassis process (chassisd) rereads the sensor at a later time.

CHASSISD_SERIAL_ID

System Log Message Serial ID read error: *error-code* -- *error-message*

Description The chassis process (chassisd) could not obtain the Routing Engine's serial number from the kernel because of the indicated error.

Type Error: An error occurred

Severity warning

Facility LOG_DAEMON

CHASSISD_SFM_MODE_ERROR

System Log Message *function-name: error-message*

Description The chassis process could not configure a requested operational mode for a Switching and Forwarding Module (SFM), for the indicated reason.

Type Error: An error occurred

Severity info

Facility LOG_DAEMON

Cause Possible reasons include (a) the requested mode is available only with certain versions of an application-specific integrated circuit (ASIC) (b) not all SFMs are online as required by the requested mode (c) cross-connect mode cannot be configured if an OC-192c Physical Interface Card (PIC) is installed.

CHASSISD_SFM_NOT_ONLINE

System Log Message	<i>function-name: SFM sfm-slot</i> not online
Description	The indicated Switching and Forwarding Module (SFM) was offline.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_SHUTDOWN_NOTICE

System Log Message	Shutdown reason: <i>reason</i>
Description	Although the chassis process (chassisd) normally does not exit or shut down except when the Routing Engine reboots, it shut down for the indicated reason.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

CHASSISD_SIB_INVALID_SLOT

System Log Message	<i>fru-name</i> in invalid slot <i>slot</i>
Description	The chassis process (chassisd) detected the presence of the switch interface board (SIB) in an invalid slot. The SIB remains offline.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_SIGPIPE

System Log Message	SIGPIPE received
Description	The chassis process (chassisd) received a signal indicating that its attempt to write to a pipe failed because the reader (which could be another process or thread) did not exist.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON
Cause	The entity at the other end of the pipe exited or closed the connection.

CHASSISD_SMB_ERROR

System Log Message	<i>smb_read: fpga download not complete: val return-value, action</i>
Description	The system management bus (SMB) could not download field-programmable gate array (FPGA) information and returned the indicated status code. The chassis process (chassisd) took the indicated action.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_SMB_INVALID_PS

System Log Message	<i>function-name: invalid power supply status code (0xstatus-code)</i>
Description	The chassis process (chassisd) could not set the status (enabled or disabled) for a power supply, because it received the indicated power supply status code, which is invalid.
Type	Error: An error occurred
Severity	critical
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_SMB_IOCTL_FAILURE

System Log Message	<i>function-name: 'operation' ioctl failed on system management bus (address 0xmemory-address, cmd 0xcommand)</i>
Description	The indicated ioctl() operation failed at the indicated address on the system management bus (SMB).
Type	Error: An error occurred
Severity	critical
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_SMB_READ_FAILURE

System Log Message	<i>function-name: read() failed on system management bus (address 0xmemory-address)</i>
Description	A read() operation failed at the indicated address on the system management bus (SMB).
Type	Error: An error occurred
Severity	critical
Facility	LOG_DAEMON

Action Contact your technical support representative.

CHASSISD_SNMP_TRAP1

System Log Message	SNMP trap generated: <i>trap (argument1 value1)</i>
Description	The chassisd process (chassisd) generated the indicated simple network management protocol (snmp) trap with the indicated value.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

CHASSISD_SNMP_TRAP10

System Log Message	SNMP trap generated: <i>trap (argument1 value1, argument2 value2, argument3 value3, argument4 value4, argument5 value5, argument6 value6, argument7 value7, argument8 value8, argument9 value9, argument10 value10)</i>
Description	The chassis process (chassisd) generated a Simple Network Management Protocol (SNMP) trap with the ten indicated argument-value pairs.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

CHASSISD_SNMP_TRAP6

System Log Message	SNMP trap generated: <i>trap (argument1 value1, argument2 value2, argument3 value3, argument4 value4, argument5 value5, argument6 value6)</i>
Description	The chassis process (chassisd) generated a Simple Network Management Protocol (SNMP) trap with the six indicated argument-value pairs.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

CHASSISD_SNMP_TRAP7

System Log Message	SNMP trap generated: <i>trap (argument1 value1, argument2 value2, argument3 value3, argument4 value4, argument5 value5, argument6 value6, argument7 value7)</i>
Description	The chassis process (chassisd) generated a Simple Network Management Protocol (SNMP) trap with the seven indicated argument-value pairs.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

CHASSISD_SPI_IOCTL_FAILURE

System Log Message	<i>function-name: reason 0xaddress, error error-message</i>
Description	The chassis process (chassisd) could not perform the indicated ioctl() operation on the indicated register of the spi device.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_SPMB_RESTART

System Log Message	SPMB <i>slot</i> restarted
Description	The indicated Switch Processor Mezzanine Board (SPMB) restarted.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

CHASSISD_SPMB_RESTART_TIMEOUT

System Log Message	Attempt <i>count</i> to restart SPMB <i>slot</i> timed out; <i>action</i>
Description	The chassis process (chassisd) tried the indicated number of times to bring the indicated Switch Processor Mezzanine Board (SPMB) online. The chassisd process performed the indicated action as a result of the failure.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON

CHASSISD_SSB_FAILOVERS

System Log Message	<i>fru-name</i> failover occurred <i>count</i> times
Description	The indicated packet-switching component or control board failed over to a redundant neighbor the indicated number of times, which exceeds the maximum limit.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	There is probably a system error.

Action Contact your technical support representative.

CHASSISD_STANDALONE_FPC_NOTICE

System Log Message chassisd running in standalone FPC mode *mode*

Description The chassis process (chassisd) was running in the indicated standalone Flexible PIC Concentrator (FPC) mode. This message was logged in case the administrator wants it to run in a different mode.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

CHASSISD_SYSCTL_ERROR

System Log Message *function-name: sysctl-error* error from *sysctl-function-name: error-message* (errno *error-code*)

Description The chassis process (chassisd) received the indicated error from the indicated sysctl() operation.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHASSISD_TEMP_HOT_NOTICE

System Log Message *fru-name* temperature of *temperature* degrees C is above limit (*threshold* degrees)

Description The temperature of the chassis, or of the indicated component (field-replaceable unit, or FRU), exceeded the lower of two thresholds. The chassis process (chassisd) increased the speed of all functioning fans (and impellers, if applicable) to full speed. If the temperature did not decrease below the threshold within 4 minutes after this message was logged, the chassisd process shut down the routing platform.

Type Event: This message reports an event, not an error

Severity error

Facility LOG_DAEMON

Action Increase cooling in the area around the chassis.

CHASSISD_TEMP_SENSOR_FAILURE

System Log Message *function-name: unable to read temperature sensor for fru-name*

Description The temperature sensor for the indicated component (field-replaceable unit, or FRU) either did not respond to a request from the chassis process (chassisd) for a temperature reading or sent a value that is outside the normal operating range.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_TERM_SIGNAL

System Log Message	Received SIGTERM request, shutting down
Description	The chassis process (chassisd) received the SIGTERM signal, indicating that it should terminate. It began the procedure for clean shutdown and exit, but possibly restarted automatically after exiting.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

CHASSISD_TIMER_CLR_ERR

System Log Message	<i>function-name: message</i>
Description	The chassis process (chassisd) could not clear the state of the timer it had set to track the timeout period for an event.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHASSISD_TIMER_ERR

System Log Message	Unable to schedule timeout for <i>description</i>
Description	The chassis process (chassisd) could not start a timer to track the timeout period for the indicated event. The seriousness of this error depends on the event.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_TIMER_VAL_ERR

System Log Message	Null timer ID
Description	The chassis process (chassisd) started a timer to track the timeout period for an event. The timer returned a null identifier, so the chassisd process could not clear the timer.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

CHASSISD_UNEXPECTED_EXIT

System Log Message evMainLoop returned *return-value* (*errno error-code*)
Description The chassis process (chassisd) exited unexpectedly and reported the indicated error.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

CHASSISD_UNEXPECTED_VALUE

System Log Message *function-name*: '*value*' is invalid value for *object-name*
Description The indicated value was specified for the indicated object in a message received by the chassis process (chassisd). The value is invalid for that type of object.

Type Error: An error occurred
Severity warning
Facility LOG_DAEMON
Action Contact your technical support representative.

CHASSISD_UNSUPPORTED_FPC

System Log Message FPC with I2C ID of *0xi2c-id* is not supported
Description A Flexible PIC Concentrator (FPC) of the indicated type was installed in the routing platform. The software does not support that FPC type on this platform.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON
Action Contact your technical support representative.

CHASSISD_UNSUPPORTED_MODEL

System Log Message Model *model* unsupported with this version of chassisd
Description The version of the chassis process (chassisd) software that is installed on the routing platform does not support this type of chassis.

Type Error: An error occurred

Severity	warning
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_UNSUPPORTED_PIC

System Log Message	PIC <i>pic-slot</i> in FPC <i>fpc-slot</i> (type <i>pic-type</i> , version <i>version</i>) is not supported
Description	The indicated PIC is either not supported on this routing platform or is not supported by the installed version of the chassis process (chassisd) software. The chassisd process did not bring the PIC online.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_UNSUPPORTED_PIC_MODE

System Log Message	Application mode <i>mode</i> is not supported for PIC <i>pic-slot</i> in FPC <i>fpc-slot</i>
Description	The indicated PIC does not support the indicated application mode configured for it.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Action	Check which application modes are supported for the PIC.

CHASSISD_UNSUPPORTED_SIB

System Log Message	SIB with assembly ID <i>assembly-id</i> is not supported
Description	The chassis process (chassisd) detected the presence of a new Switch Interface Board (SIB) with the indicated assembly ID. The SIB remains offline, because it is not a supported type.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_VERSION_MISMATCH

System Log Message	Version mismatch: chassisd message version <i>expected-value fru-name fru-slot</i> message version <i>received-value</i> local IPC version <i>local-ipc-version</i> remote IPC version <i>remote-ipc-version</i>
Description	As a component (field-replaceable unit, or FRU) comes online, the chassis process (chassisd) verifies that the FRU's revision level or version is supported. The revision level of the indicated FRU was unsupported or otherwise invalid.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	Either a previous software upgrade did not complete successfully, or the chassisd process or FRU did not restart after a successful software upgrade.
Action	Upgrade the software and reboot the routing platform.

CHASSISD_VOLTAGE_READ_FAILED

System Log Message	Unable to read voltage from <i>fru-name</i> (group <i>group-id</i> , address <i>address</i> , channel <i>voltage-channel</i>)
Description	The chassis process (chassisd) could not read voltage data from the indicated component (field-replaceable unit, or FRU).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHASSISD_VOLTAGE_SENSOR_INIT

System Log Message	Unable to initialize voltage sensor for <i>fru-name</i> (group <i>group-id</i> , address <i>address</i>)
Description	The chassis process (chassisd) could not initialize the voltage sensor for the indicated component (field-replaceable unit, for FRU).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHAPTER 20

CHASSISM System Log Messages

This chapter describes messages with the **CHASSISM** prefix. They are generated by the chassis manager process (chassism), which controls hardware components on the routing platform.

CHASSISM_SYSTEM

System Log Message	<i>reason: error-message</i>
Description	A system call made by this process failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	It is possible that the kernel lacked the resources to fulfill the request.

CHAPTER 21

CONTENT System Log Messages

This chapter describes messages with the **CONTENT** prefix. They are generated by the content filtering process (contentd) which filters certain types of traffic based on the type, file extension, and protocol command. The content filter controls file transfers across the gateway by checking traffic against configured filter lists.

CONTENT_FILTERING_BLOCKED_MT

System Log Message	Content Filtering: <i>argument (profile-name)</i> from <i>source-address</i> is <i>action</i> due to <i>reason</i>
Description	The transaction is blocked due to content filtering setting
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_PFE
Cause	The transaction is in content filtering's block list
Action	Check the transaction to make sure it is not a false positive

CHAPTER 22

COSD System Log Messages

This chapter describes messages with the **COSD** prefix. They are generated by the class-of-service (CoS) process (cosd), which enables the routing platform to provide different levels of service to applications based on packet classifications.

COSD_AGGR_CONFIG_INVALID

System Log Message	Error: Cannot have config <i>error-message interface-name</i>
Description	The class-of-service (CoS) process (cosd) did not apply the config on this interface because it was not valid in this case
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	One possible cause is if any Class-of-Service is configured on an interface which is a part of an aggregated interface
Action	Remove or change the config from/on the interface.

COSD_CHASSIS_SCHED_MAP_INVALID

System Log Message	Chassis scheduler map incorrectly applied to interface <i>interface-name: error-message</i>
Description	The class-of-service (CoS) process (cosd) did not apply a chassis scheduler map to the indicated interface, because the configuration used to apply the scheduler map was invalid.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	One possible cause is that the chassis scheduler map is applied to a specific interface. For most interface types, a scheduler map must be applied to all interfaces on the PIC; therefore, a wildcard must be used to specify the interfaces. One exception to this rule is the Gigabit Ethernet IQ PIC.

Action Correct the configuration used to apply the chassis scheduler map to the interface.

COSD_CLASSIFIER_NO_SUPPORT_LSI

System Log Message	Cannot support classifier type <i>classifier-type</i> on lsi interface <i>interface-name</i>
Description	The Differentiated Services code point (DSCP) classifier and the 802.1p classifier are only supported on I-Chip based Flexible PIC Concentrators (FPCs).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Remove the DSCP or the 802.1p classifier configuration from the routing instance

COSD_CLASS_8021P_UNSUPPORTED

System Log Message	ieee-802.1 classifier is not valid on interface <i>interface-name</i>
Description	The IEEE 802.1p classifier is not supported on the indicated interface.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Action	Remove the 802.1p classifier configuration from the interface, or configure an interface encapsulation type that supports 802.1p classifiers.

COSD_CONF_OPEN_FAILURE

System Log Message	Unable to open: <i>filename</i> , using default CoS forwarding classes, do 'commit full' in cli to avoid this message
Description	The class-of-service (CoS) process (cosd) could not read configuration data.
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	All of the following: mgd -l fails after upgrade (cosd.conf does not exist and is not created because of the mgd -l failure), the first commit is 'commit' and not 'commit full' (cosd.conf will not commit is 'commit' and not 'commit full' (cosd.conf will not automatically be created), [class-of-service forwarding-classes] does not exist (the file cosd.conf will not get exported with plain 'commit')
Action	Do a 'commit full'

COSD_DB_OPEN_FAILED

System Log Message	Unable to open configuration database: <i>error-message(name)</i>
Description	The class-of-service (CoS) process (cosd) could not read configuration data for the indicated reason.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	The specified database does not exist
Action	Contact your technical support representative.

COSD_EXACT_RATE_UNSUPP_INTERFACE

System Log Message	Unable to apply scheduler map <i>scheduler-map</i> to interface <i>interface-name</i> because it does not support exact-rate transmission
Description	The class-of-service (CoS) process (cosd) did not apply the indicated scheduler map to the indicated interface, because a scheduler named in the scheduler map specifies exact transmission rate. The interface is housed on a type of PIC that does not support exact transmission rate, such as an IQ2 PIC. In terms of configuration, the 'exact' statement is included in the scheduler definition at the [edit class-of-service schedulers <scheduler-name> transmit-rate (<rate> percent <percentage>)] hierarchy level. The scheduler is included in the scheduler map that is applied to the interface.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Remove the 'exact' statement from the scheduler in the scheduler map applied to the interface.

COSD_EXACT_RATE_UNSUPP_SESSION

System Log Message	Unable to apply CoS to L2TP session <i>session-id</i> , because scheduler map <i>scheduler-map</i> specifies exact rate transmission
Description	The class-of-service (CoS) process (cosd) did not apply CoS settings to the indicated Layer 2 Tunneling Protocol (L2TP) session, because the scheduler map specified by the RADIUS server for the session is configured for exact transmission rate. Exact transmission rate is not supported for L2TP sessions on the type of PIC that houses the interface, such as an IQ2 PIC. In terms of configuration, the 'exact' statement is included in a scheduler definition at the [edit class-of-service schedulers <scheduler-name> transmit-rate (<rate> percent <percentage>)] hierarchy level. The scheduler is included in a scheduler map that is associated with a traffic control profile. The traffic control profile is named

by an attribute in the RADIUS server's configuration file, which makes the profile apply to the session.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Remove the 'exact' statement from the scheduler in the scheduler map applied to the session.

COSD_FRAGMENTATION_MAP_CONFLICT

System Log Message Interface *compression-device* matches wildcard *wildcard-interface-name*, but fragmentation map *fragmentation-map* was not applied because interface is compression device for link interface *link-interface-name*

Description The indicated fragmentation map is normally applied to interfaces that match the indicated wildcard. The class-of-service (CoS) process (cosd) did not apply the fragmentation map to the indicated interface, even though it matches the wildcard, because the interface is acting as a compression device for the indicated link interface.

Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Action	Correct the configuration of the fragmentation map.

COSD_HIGH_PRIO_QUEUES_INTERFACE

System Log Message Unable to apply scheduler map *scheduler-map* to interface *interface-name*, because multiple schedulers in map have "high," "medium-high," or "strict-high" priority

Description The class-of-service (CoS) process (cosd) did not apply the indicated scheduler map to the indicated interface, because the map includes more than one scheduler that has high, medium-high, or strict-high priority. For interfaces that are housed by certain PICs, such as an IQ2 PIC, the scheduler map can include only one scheduler that specifies one of those three priority levels. In terms of configuration, the 'priority' statement at the [edit class-of-service schedulers <scheduler-name>] hierarchy level has the value 'high, ' 'medium-high, ' or 'strict-high' for more than one of the schedulers in the map.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Correct the configuration so that the scheduler map includes only one scheduler with high, medium-high, or strict-high priority.

COSD_HIGH_PRIO_QUEUES_SESSION

System Log Message	Unable to apply CoS to L2TP session <i>session-id</i> , because multiple schedulers in scheduler map <i>scheduler-map</i> have "high," "medium-high," or "strict-high" priority
Description	The class-of-service (CoS) process (cosd) did not apply CoS settings to the indicated Layer 2 Tunneling Protocol (L2TP) session, because the scheduler map specified by the RADIUS server for the session includes more than one scheduler that has high, medium-high, or strict-high priority. For interfaces that are housed by certain PICs, such as an IQ2 PIC, the scheduler map can include only one scheduler that specifies one of those three priority levels. In terms of configuration, the 'priority' statement at the [edit class-of-service schedulers <scheduler-name>] hierarchy level has the value 'high,' 'medium-high,' or 'strict-high' for more than one of the schedulers in the map. The map is associated with a traffic control profile that is named by an attribute in the RADIUS server's configuration file, which makes the profile apply to the session.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Correct the configuration so that the scheduler map includes only one scheduler with high, medium-high, or strict-high priority.

COSD_IFD_OUTPUT_SHAPING_RATE_ERR

System Log Message	Traffic shaping not supported on interface device <i>interface-name</i>
Description	The class-of-service (CoS) process (cosd) did not apply the shaping rate that is configured for the indicated interface.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	Shaping rate is valid only for interfaces housed by IQ and IQ2 PICs, and the interface is on a different type of PIC.
Action	Remove the shaping rate configuration from the interface.

COSD_IFD_SHAPER_ERR

System Log Message	port shaper not allowed on interface <i>interface-name</i>
Description	The non-queuing dense port concentrators (DPCs) did not support the specified shaping rate.
Type	Error: An error occurred
Severity	error

Facility	LOG_DAEMON
Cause	The port shaper was not supported on the non-queuing DPCs.
Action	Remove the shaping rate configuration from the interface.

COSD_INTERFACE_NO_MEDIA

System Log Message	Unable to obtain media information for interface <i>interface-name</i>
Description	The message sent by the kernel for the indicated interface did not include required media information.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

COSD_L2TP_COS_NOT_CONFIGURED

System Log Message	Unable to apply CoS to L2TP session <i>session-id</i> because session-aware CoS is not enabled for interface <i>interface-name</i>
Description	The class-of-service (CoS) process (cosd) did not apply CoS settings to the indicated Layer 2 Tunneling Protocol (L2TP) session on the indicated interface, because the interface is not configured to support session-aware CoS for L2TP. In terms of configuration, the 'per-session-scheduler' statement is not included at the [edit interfaces <interface-name> unit <logical-unit-number>] hierarchy level.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Include the 'per-session-scheduler' statement in the configuration for the interface.

COSD_L2TP_COS_NOT_SUPPORTED

System Log Message	Unable to apply CoS to L2TP session <i>session-id</i> on interface <i>interface-name</i> : it does not support CoS
Description	The class-of-service (CoS) process (cosd) did not apply CoS settings to the indicated Layer 2 Tunneling Protocol (L2TP) session on the indicated interface. The interface is configured to support session-aware CoS for L2TP, but is not on a PIC that supports that feature, such as an IQ2 PIC. In terms of configuration, the 'per-session-scheduler' statement is included at the [edit interfaces <interface-name> unit <logical-unit-number>] hierarchy level.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Determine whether the interface is on an PIC that supports session-aware CoS; if not, remove the 'per-session-scheduler' statement.

COSD_L2TP_SHAPING_NOT_CONFIGURED

System Log Message Unable to apply CoS to L2TP session *session-id* because session-aware shaping is not enabled for interface *interface-name*

Description The class-of-service (CoS) process (cosd) did not apply CoS settings to the indicated Layer 2 Tunneling Protocol (L2TP) session on the indicated interface, because session-aware traffic shaping for L2TP is not configured on the PIC that houses the interface. In terms of configuration, the 'session-shaping' statement is not included at the [edit chassis fpc <slot-number> pic <pic-number> traffic-manager mode] hierarchy level.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Include the 'session-shaping' statement in the configuration for the PIC.

COSD_LARGE_DELAY_BUFFER_INVALID

System Log Message Error for interface *interface-name* *error-message*

Description The class-of-service (CoS) process (cosd) did not apply the large delay buffer setting that is configured for the indicated interface.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	The interface is not housed on one of the PIC types that support large delay buffer.
Action	Remove the large delay buffer configuration from the interface.

COSD_MALLOC_FAILED

System Log Message malloc failed: *error-message*

Description The class-of-service (CoS) process (cosd) could not dynamically allocate memory for the indicated reason.

Type	Error: An error occurred
-------------	--------------------------

Severity	error
Facility	LOG_DAEMON
Cause	A software bug caused a memory leak or the Routing Engine did not have sufficient memory.
Action	Contact your technical support representative.

COSD_MPLS_DSCP_CLASS_NO_SUPPORT

System Log Message	Cannot support MPLS DSCP classifier on ifl <i>interface-name</i>
Description	The MPLS Differentiated Services code point (DSCP) classifier is only supported on I-Chip based Flexible PIC Concentrators (FPCs). It is not supported on Q2 PICs.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Remove the MPLS DSCP classifier configuration from the logical interface.

COSD_MULTILINK_CLASS_CONFLICT

System Log Message	Fragmentation map <i>fragmentation-map</i> for wildcard <i>wildcard-interface-name</i> specified multilink class <i>class-name</i> for queue <i>queue-number</i> on interface <i>interface-name</i> , which exceeds configured limit of <i>limit</i>
Description	The indicated fragmentation map is normally applied to interfaces that match the indicated wildcard, and specifies the indicated multilink class setting for queues on those interfaces. The class-of-service (CoS) process (cosd) did not apply the fragmentation map to the indicated interface, even though it matches the wildcard, because the setting in the map exceeds the indicated class limit, which is configured on the interface itself.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Action	Correct the configuration so that the multilink class setting in the fragmentation map does not exceed the class limit for the interface.

COSD_NULL_INPUT_ARGUMENT

System Log Message	NULL input argument : <i>error-message</i>
Description	The pointer that was passed to this function was NULL.
Type	Error: An error occurred
Severity	error

Facility LOG_DAEMON

Action Contact your technical support representative.

COSD_OUT_OF_DEDICATED_QUEUES

System Log Message Queue usage count for interface *interface-name* is at *percentage-value* percent

Description The class-of-service (CoS) process (cosd) is running out of dedicated queues.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

COSD_RATE_LIMIT_INVALID

System Log Message Unable to apply scheduler map *scheduler-map* to interface *interface-name*. *description*.

Description The class-of-service (CoS) process (cosd) did not apply the indicated scheduler map to the indicated interface, because the number of rate limited queues in the scheduler map exceeded the limit supported by this interface or the priority is not supported. The interface is housed in a type of PIC that does not support the number of configured rate limited queues or the priority is not supported. In terms of configuration, the 'rate-limit' statement is included in the scheduler definition at the [edit class-of-service schedulers <scheduler-name> transmit-rate <rate> | percent <percentage>] hierarchy level. The scheduler is included in the scheduler map applied to the interface.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Either limit the number of rate-limited schedulers in this scheduler map to the allowed maximum for this PIC and interface type or check the allowed priority for rate-limited queues

COSD_RATE_LIMIT_NOT_SUPPORTED

System Log Message Unable to apply scheduler map *scheduler-map* to interface *interface-name* because it does not support rate limiting

Description The class-of-service (CoS) process (cosd) did not apply the indicated scheduler map to the indicated interface, because a scheduler named in the scheduler map is configured for rate limiting. The interface is housed in a type of PIC that does not support rate limiting. In terms of configuration, the 'rate-limit' statement is included in the scheduler definition at the [edit class-of-service schedulers <scheduler-name> transmit-rate <rate> | percent <percentage>] hierarchy level. The scheduler is included in the scheduler map applied to the interface.

Type Error: An error occurred

Severity	error
Facility	LOG_DAEMON
Action	Remove the 'rate-limit' statement from the scheduler in the scheduler map applied to the interface.

COSD_REWRITE_RULE_LIMIT_EXCEEDED

System Log Message	Number of rewrite rules applied to interface <i>interface-name</i> exceeds limit (<i>maximum-value</i>)
Description	The class-of-service (CoS) process (cosd) determined that the number of rewrite rules applied to the indicated interface exceeds the indicated limit for the interface. In terms of configuration, too many rewrite rules are included at the [edit class-of-service interfaces <interface-name> unit <logical-unit-number> rewrite-rules] hierarchy level.
Type	Error: An error occurred
Severity	error
Facility	ANY
Action	Remove rewrite rules from the configuration for the interface.

COSD_RL_IFL_NEEDS_SHAPING

System Log Message	"rate-limit" configured in <i>scheduler-map</i> , but ifl <i>interface-name</i> does not have output shaper configured. It will use the ifd-shaping rate/ifd-transmit rate for implementation of rate-limit.
Description	The 'rate-limit' statement is configured in one or more schedulers that are part of the indicated scheduler map. In order to apply this scheduler map to the indicated interface, output shaping rate should be configured on the interface. Since no output shaping rate is configured, the transmit rate or shaping rate of the parent interface will be used instead.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Action	Configure output shaping rate for the indicated interface

COSD_SCHEDULER_MAP_CONFLICT

System Log Message	Forwarding classes " <i>first-forwarding-class</i> " and " <i>second-forwarding-class</i> " in scheduler map <i>scheduler-map</i> both map to queue <i>queue-number</i>
Description	Both of the indicated forwarding classes, which are defined in the indicated scheduler map, map to the same indicated queue. The double mapping is invalid.
Type	Error: An error occurred
Severity	error

Facility LOG_DAEMON
Action Map only one forwarding class to the queue.

COSD_SCHED_AVG_CONST_UNSUPPORTED

System Log Message Averaging constant not supported on interface *interface-name*. Value set in scheduler-map *scheduler-map* (scheduler *name*) will be ignored.

Description Configuring averaging constant is not supported on the indicated interface. Value set in the indicated scheduler will be ignored.

Type Error: An error occurred

Severity warning

Facility LOG_DAEMON

Action Remove the averaging-constant configuration from the indicated scheduler.

COSD_SCHED_MAP_GROUP_CONFLICT

System Log Message Interface *interface-name* cannot be bound to scheduler-map *scheduler-map*. It will be bound to default scheduler-map

Description Interfaces belonging to a group cannot be bound to different scheduler maps. They will be bound to the default scheduler map.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Map only one scheduler map to all the interfaces of a group.

COSD_SHAPER_GROUP_CONFLICT

System Log Message Interface *interface-name* cannot be bound to configured shaping-rate. It will be bound to default rate

Description Interfaces belonging to a group cannot be bound to different shaping rates. They will be bound to default shaping rate.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Map only one shaping rate to all interfaces of a group.

COSD_STREAM_IFD_CREATE_FAILURE

System Log Message Unable to create special master interface device for *interface-name*

Description	The class-of-service (CoS) process (cosd) could not create the indicated internal interface device, which it needs for application of a chassis scheduler map.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

COSD_TIMER_ERROR

System Log Message	Unable to set retry timer for rtsock write operation: <i>error-message</i>
Description	The class-of-service (CoS) process (cosd) used a routine from the rtsock library to write to the kernel, but the kernel did not accept the request. The cosd process could not set the retry timer for the request, for the indicated reason.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

COSD_TRICOLOR_ALWAYS_ON

System Log Message	tri-color is always enabled in this platform. There is no need to explicitly set it.
Description	Tri-color marking is always enabled on this platform. There is no need to explicitly set it.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Action	Remove the 'tri-color' configuration statement

COSD_TRICOLOR_NOT_SUPPORTED

System Log Message	Unable to apply scheduler <i>scheduler-map</i> to interface <i>interface-name</i> , because it does not support tricolor marking
Description	The class-of-service (CoS) process (cosd) did not apply the indicated scheduler map to the indicated interface, because a scheduler included in the map specifies a packet loss priority (PLP) that is supported only with tricolor marking (TCM). The interface does not support TCM, either because TCM is not enabled or the interface is on a router that

does not support TCM. In terms of configuration, the value 'medium-high' or 'medium-low' is specified for the 'loss-priority' statement in a scheduler definition at the [edit class-of-service schedulers <scheduler-name> drop-profile-map] hierarchy level. The scheduler is included in the scheduler map applied to the interface, but the 'tri-color' statement is either not included at the [edit class-of-service] hierarchy level, or is not supported.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Change the value of the 'loss-priority' statement in the scheduler or include the 'tri-color' statement to enable TCM on the router.

COSD_TX_QUEUE_RATES_TOO_HIGH

System Log Message	Unable to apply scheduler map <i>scheduler-map</i> to interface <i>interface-name</i> : sum of scheduler transmission rates exceeds interface shaping or transmission rate
Description	The class-of-service (CoS) process (cosd) did not apply the indicated scheduler map to the indicated interface, because the sum of the queue transmission rates defined in the schedulers in the scheduler map exceeds the shaping or transmission rate for the interface. In terms of configuration, the 'transmit-rate' statement is specified for each scheduler at the [edit class-of-service schedulers <scheduler-name>] hierarchy level. The sum of the configured transmission rates exceeds the transmission or shaping rate of the interface.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Decrease the value of one or more 'transmit-rate' statements so that the sum is less than the interface transmission or shaping rate.

COSD_UNKNOWN_CLASSIFIER

System Log Message	classifier type <i>classifier-type</i> is invalid
Description	The class-of-service (CoS) process (cosd) did not recognize the indicated classifier type from the rtsock library.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

COSD_UNKNOWN_REWRITE

System Log Message	rtsock rewrite type <i>type</i> is invalid
Description	The class-of-service (CoS) process (cosd) did not recognize the indicated rewrite type from the rtsock library.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

COSD_UNKNOWN_TRANSLATION_TABLE

System Log Message	rtsock translation table type <i>translation-table-type</i> is invalid
Description	The class-of-service (CoS) process (cosd) did not recognize the indicated translation table type from the rtsock library.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

CHAPTER 23

DCBX System Log Messages

This chapter describes messages with the **DCBX** prefix. They are generated by the interface process (lldpd), which is a discovery and capability exchange protocol to discover peers and exchange information.

DCBX_VERSION

System Log Message	IF <i>interface-name</i> : DCBX TLV version 1.0 received
Description	Ignoring the received Data Center Bridging Protocol (DCBX) packet because it is an old version, version 1.0.
Type	Error: An error occurred
Severity	info
Facility	LOG_DAEMON
Cause	The software on the Host Bus Adapter (HBA) is not up-to-date.

CHAPTER 24

DCD System Log Messages

This chapter describes messages with the **DCD** prefix. They are generated by the interface process (dcd), which controls the physical interface devices and logical interfaces in the routing platform.

DCD_GRE_CONFIG_INVALID

System Log Message	Either tunnel key or clear-dont-fragment-bit must be configured for this GRE tunnel (<i>interface-name</i>), to enable post fragmentation
Description	This interface needs either the tunnel key or the clear-dont-fragment-bit to be configured along with allow-fragmentation
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Configure either the tunnel key or clear-dont-fragment-bit for this tunnel

DCD_MALLOC_FAILED_INIT

System Log Message	Memory allocation failed during initialization for configuration load
Description	The interface process (dcd) could not dynamically allocate memory in preparation for loading a configuration.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	A software bug caused a memory leak, or the routing platform had insufficient memory.
Action	Contact your technical support representative.

DCD_PARSE_CFG_WARNING

System Log Message	<i>configuration-statement : warning-message</i>
Description	The interface-control process (dcd) found a discrepant configuration

Type	Error: An error occurred
Severity	warning
Facility	ANY
Cause	This is a warning message and the current configuration has a few discrepancies to be addressed.
Action	Contact your technical support representative.

DCD_PARSE_EMERGENCY

System Log Message	dcd_config: errors while parsing configuration file
Description	The interface process (dcd) encountered an unhandled internal state while parsing the configuration database.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	There might be a bug in the dcd process' parser.
Action	Contact your technical support representative.

DCD_PARSE_ERROR_CLOCK

System Log Message	PIC housing interface <i>interface-name</i> does not support clocking as configured
Description	The 'clocking' statement is included at the [edit interfaces] hierarchy level for the indicated interface, but is not supported by the 10-Gigabit Ethernet IQ2 Physical Interface Card (PIC).
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Action	Remove the 'clocking' statement from the configuration for the interface.

DCD_PARSE_ERROR_HIER_SCHEDULER

System Log Message	<i>interface-name</i> : PIC or encapsulation type does not support 'hierarchical-scheduler' statement
Description	The 'hierarchical-scheduler' statement is included at the [edit interfaces] hierarchy level for the indicated interface, but is not supported either by the PIC or the configured type of encapsulation.
Type	Error: An error occurred

Severity	warning
Facility	LOG_DAEMON
Action	Remove the 'hierarchical-scheduler' statement from the configuration for the interface.

DCD_PARSE_ERROR_IFLSET

System Log Message	Interface <i>interface-name</i> does not support 'interface-set' statement
Description	The 'interface-set' statement is included at the [edit interfaces] hierarchy level for the indicated interface, but is not supported by the interface.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Action	Remove the 'interface-set' statement from the configuration for the interface.

DCD_PARSE_ERROR_MAX_HIER_LEVELS

System Log Message	<i>interface-name</i> : PIC or encapsulation type does not support 'maximum-hierarchy-levels' statement
Description	The 'hierarchical-scheduler maximum-hierarchy-levels' statement is included at the [edit interfaces] hierarchy level for the indicated interface, but is not supported either by the PIC or the configured type of encapsulation.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Action	Remove the 'hierarchical-scheduler maximum-hierarchy-levels' statement from the configuration for the interface.

DCD_PARSE_ERROR_SCHEDULER

System Log Message	<i>interface-name</i> : PIC or encapsulation type does not support 'per-unit-scheduler' or 'shared-scheduler' statement
Description	The 'per-unit-scheduler' or 'shared-scheduler' statement is included at the [edit interfaces] hierarchy level for the indicated interface, but is not supported either by the PIC or the configured type of encapsulation.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Action	Remove the 'per-unit-scheduler' or 'shared-scheduler' statement from the configuration for the interface.

DCD_PARSE_ERROR_SCHEDULER_LIMIT

System Log Message	<i>interface-name</i> : exceeds the allowed limit (<i>maximum-value</i>) of 'per-unit-scheduler' interface statement for PIC= <i>pic-slot</i> on FPC= <i>fpc-slot</i>
Description	The 'per-unit-scheduler' statement is enabled on more interfaces than what this PIC would support.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Action	Remove the 'per-unit-scheduler' statement from the configuration for the interface.

DCD_PARSE_ERROR_VLAN_TAGGING

System Log Message	<i>interface-name</i> : PIC type does not support flexible-vlan-tagging statement
Description	The 'flexible-vlan-tagging' statement is included at the [edit interfaces] hierarchy level for the indicated interface, but is not supported by the Physical Interface Card (PIC) that houses the interface.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Action	Remove the 'flexible-vlan-tagging' statement from the configuration for the interface.

DCD_PARSE_ERR_INCOMPATIBLE_CFG

System Log Message	<i>configuration-statement</i> : Incompatible configuration detected : <i>warning-message</i>
Description	The interface process (dcd) found a configuration which will not be supported in future releases.
Type	Error: An error occurred
Severity	warning
Facility	ANY
Cause	This is a warning and the configuration will not be supported in future release.
Action	Contact your technical support representative.

DCD_PARSE_MINI_EMERGENCY

System Log Message	dcd_mini_config: errors while parsing configuration overlay
Description	The interface process (dcd) encountered an unhandled internal state during interface parsing.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	There might be a bug in the dcd process' parser.
Action	Contact your technical support representative.

DCD_PARSE_STATE_EMERGENCY

System Log Message	An unhandled state was encountered during interface parsing
Description	The interface process (dcd) encountered an unhandled internal state during interface parsing.
Type	Error: An error occurred
Severity	emergency
Facility	LOG_DAEMON
Cause	There might be a bug in the dcd process' parser.
Action	Contact your technical support representative.

CHAPTER 25

DFCD System Log Messages

This chapter describes messages with the **DFCD** prefix. They are generated by the dynamic flow control process (dfcd), which monitors packet flows using dynamically alterable filtering criteria.

DFCD_FTAP_PIC_UNSUPPORTED

System Log Message	PIC housing interface <i>interface-name</i> does not support flow-tap service
Description	The Physical Interface Card (PIC) that houses the indicated interface does not support flow-tap service.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

DFCD_GENCFG_MALLOC_FAILED

System Log Message	GENCFG mem alloc failed !!!
Description	The dynamic flow capture process (dfcd) could not allocate memory for gencfg message.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

DFCD_GENCFG_WRITE_FAILED

System Log Message	GENCFG write failed for Reason: <i>error-message</i> (<i>error-code</i>)
Description	The dynamic flow capture process (dfcd) could not send gencfg message, for the indicated reason.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

DFCD_LINH_MALLOC_FAILED

System Log Message	GENCFG mem alloc failed !!!
Description	The dynamic flow capture process (dfcd) could not allocate memory for linh message.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

DFCD_LI_NEXT_HOP_ADD_FAILED

System Log Message	Unable to add li next hop for subscriber interface: <i>error-message (error-code)</i>
Description	The dynamic flow capture process (dfcd) could not add a subscriber li next hop, for the indicated reason.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

DFCD_NEXT_HOP_ADD_FAILED

System Log Message	Unable to add service next hop: <i>error-message (error-code)</i>
Description	The dynamic flow capture process (dfcd) could not add a service next hop, for the indicated reason.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

DFCD_NEXT_HOP_DELETE_FAILED

System Log Message	Unable to delete service next hop: <i>error-message (error-code)</i>
Description	The dynamic flow capture process (dfcd) could not delete a service next hop, for the indicated reason.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

DFCD_SAMPLE_CLASS_ADD_FAILED

System Log Message	Unable to add sample class: <i>error-message (error-code)</i>
Description	The dynamic flow capture process (dfcd) could not add a sample class, for the indicated reason.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

DFCD_SAMPLE_CLASS_DELETE_FAILED

System Log Message Unable to delete sample class: *error-message (error-code)*

Description The dynamic flow capture process (dfcd) could not delete a sample class, for the indicated reason.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

CHAPTER 26

DFWD System Log Messages

This chapter describes messages with the **DFWD** prefix. They are generated by the firewall process (dfwd), which manages compilation and downloading of Junos firewall filters.

DFWD_MALLOC_FAILED_INIT

System Log Message	Memory allocation failed during initialization for configuration load
Description	The firewall process (dfwd) could not dynamically allocate memory in preparation for loading a configuration.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	A software bug caused a memory leak, or the routing platform had insufficient memory.
Action	Contact your technical support representative.

DFWD_PARSE_FILTER_EMERGENCY

System Log Message	dfwd encountered errors while parsing filter index file
Description	The firewall process (dfwd) encountered an unhandled internal state while parsing a filter index file.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	There might be a bug in the parser.
Action	Contact your technical support representative.

DFWD_PARSE_STATE_EMERGENCY

System Log Message	dfwd encountered unhandled state while parsing interface
---------------------------	--

Description	The firewall process (dfwd) encountered an unhandled internal state while parsing an interface.
Type	Error: An error occurred
Severity	emergency
Facility	LOG_DAEMON
Cause	There might be a bug in the parser.
Action	Contact your technical support representative.

DFWD_POLICER_LIMIT_EXCEEDED

System Log Message Number of interface policers configured is exceeding maximum allowed *total-count*.

Description	The firewall process (dfwd) detected that number of interface policers configured is exceeding maximum allowed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Reduce the number of interface policers to within allowed limit.

CHAPTER 27

DH System Log Messages

This chapter describes messages with the **DH** prefix. They are generated by the Dynamic Host Configuration Protocol (DHCP) server process (dhcpcd) for J Series Services Routers, which automatically allocates network IP addresses and delivers configuration settings to client hosts in a Transmission Control Protocol (TCP)/IP network.

DH_SVC_AUTHENTICATE_LICENSE

System Log Message	Authentication failed due to license error. Total license failures <i>count</i>
Description	The Dynamic Host Configuration Protocol (DHCP) services process (dhcp-service) failed to authenticate the clients because there were no licenses or an insufficient number of licenses. The indicated number of license failures occurred and the clients were denied access and configuration.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Add or update license for authentication

DH_SVC_BIND_FAILURE

System Log Message	bind() to port <i>port</i> failed: <i>error-message</i>
Description	The Dynamic Host Configuration Protocol (DHCP) services process (dhcp-service) received the indicated error when it tried to bind a socket to the indicated local port.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

DH_SVC_RECVMSG_FAILURE

System Log Message	Exiting due to too many recvmsg() failures
---------------------------	--

Description	The Dynamic Host Configuration Protocol (DHCP) services process (dhcp-service) could not receive data from the network, which it needs to do during normal operation.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

DH_SVC_RTsock_FAILURE

System Log Message	Error with rtsock: <i>error-message</i>
Description	The Dynamic Host Configuration Protocol (DHCP) services process (dhcp-service) experienced the indicated error with a routing socket.
Type	Error: An error occurred
Severity	info
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

DH_SVC_SENDMSG_FAILURE

System Log Message	sendmsg() from <i>source-address</i> to port <i>destination-port</i> at <i>destination-address</i> via interface <i>interface-name</i> and routing instance <i>routing-instance</i> failed: <i>error-message</i>
Description	The Dynamic Host Configuration Protocol (DHCP) services process (dhcp-service) could not send data from the indicated source (address, interface, and routing instance) to the indicated destination (port and address), which it needs to do during normal operation.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

DH_SVC_SENDMSG_NOINT_FAILURE

System Log Message	sendmsg() from <i>source-address</i> to port <i>destination-port</i> at <i>destination-address</i> via routing instance <i>routing-instance</i> failed: <i>error-message</i>
Description	The Dynamic Host Configuration Protocol (DHCP) services process (dhcp-service) could not send data from the indicated source (address and routing instance) to the indicated destination (port and address), which it needs to do during normal operation.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

DH_SVC_SETSOCKOPT_FAILURE

System Log Message	setsockopt(<i>socket-option</i>) failed: <i>error-message</i>
Description	The Dynamic Host Configuration Protocol (DHCP) services process (dhcp-service) could not set the indicated socket option.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

DH_SVC_SOCKET_FAILURE

System Log Message	socket(<i>arguments</i>) failed: <i>error-message</i>
Description	The Dynamic Host Configuration Protocol (DHCP) services process (dhcp-service) could not create a socket.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHAPTER 28

DHCPD System Log Messages

This chapter describes messages with the **DHCPD** prefix. They are generated by the Dynamic Host Configuration Protocol (DHCP) server process (dhcpcd) for J Series Services Routers, which automatically allocates network IP addresses and delivers configuration settings to client hosts in a Transmission Control Protocol (TCP)/IP network.

DHCPD_BIND_FAILURE

System Log Message	bind() to port <i>port</i> failed: <i>error-message</i>
Description	The Dynamic Host Configuration Protocol server process (dhcpcd) received the indicated error when it tried to bind a socket to the indicated local port.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH
Action	Contact your technical support representative.

DHCPD_DEGRADED_MODE

System Log Message	Running in degraded mode because of <i>reason</i> : <i>error-message</i>
Description	The Dynamic Host Configuration Protocol server process (dhcpcd) began running in degraded mode because the indicated unrecoverable error occurred.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH
Cause	There might be a problem with the lease cache directory used to store persistent lease information.
Action	Contact your technical support representative.

DHCPD_MEMORY_ALLOCATION_FAILURE

System Log Message	Unable to allocate memory for <i>object-name</i> : <i>error-message</i>
---------------------------	---

Description The Dynamic Host Configuration Protocol server process (dhcpcd) could not allocate memory from the heap for the indicated object.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

Action Contact your technical support representative.

DHCPD_OVERLAY_CONFIG_FAILURE

System Log Message Unable to open overlay configuration: *error-message*

Description The Dynamic Host Configuration Protocol server process (dhcpcd) could not open an overlay configuration file for parsing.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

Action Contact your technical support representative.

DHCPD_OVERLAY_PARSE_FAILURE

System Log Message Unable to parse overlay configuration because of *count* syntax errors

Description The Dynamic Host Configuration Protocol server process (dhcpcd) could not parse its overlay configuration because the configuration contained the indicated number of syntax errors.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

Cause An internal software failure occurred.

Action Contact your technical support representative.

DHCPD_RECVMSG_FAILURE

System Log Message Exiting due to too many recvmsg() failures

Description The Dynamic Host Configuration Protocol server process (dhcpcd) could not receive data from the network, which it needs to do during normal operation.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

Action Contact your technical support representative.

DHCPD_RT SOCK_FAILURE

System Log Message Error with rtsock: *error-message*

Description The Dynamic Host Configuration Protocol server process (dhcpcd) experienced the indicated error with a routing socket.

Type Error: An error occurred

Severity info

Facility LOG_AUTH

Cause An internal software failure occurred.

Action Contact your technical support representative.

DHCPD_SENDMSG_FAILURE

System Log Message sendmsg() from *source-address* to port *destination-port* at *destination-address* via interface *interface-name* and routing instance *routing-instance* failed: *error-message*

Description The Dynamic Host Configuration Protocol server process (dhcpcd) could not send data from the indicated source (address, interface, and routing instance) to the indicated destination (port and address), which it needs to do during normal operation.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

Action Contact your technical support representative.

DHCPD_SENDMSG_NOINT_FAILURE

System Log Message sendmsg() from *source-address* to port *destination-port* at *destination-address* via routing instance *routing-instance* failed: *error-message*

Description The Dynamic Host Configuration Protocol server process (dhcpcd) could not send data from the indicated source (address and routing instance) to the indicated destination (port and address), which it needs to do during normal operation.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

Action Contact your technical support representative.

DHCPD_SETSOCKOPT_FAILURE

System Log Message	setsockopt(<i>socket-option</i>) failed: <i>error-message</i>
Description	The Dynamic Host Configuration Protocol server process (dhcpcd) could not set the indicated socket option.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH
Action	Contact your technical support representative.

DHCPD_SOCKET_FAILURE

System Log Message	socket(<i>arguments</i>) failed: <i>error-message</i>
Description	The Dynamic Host Configuration Protocol server process (dhcpcd) could not create a socket.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH
Action	Contact your technical support representative.

CHAPTER 29

DYNAMIC System Log Messages

This chapter describes messages with the **DYNAMIC** prefix. They are generated by the Access Manager client which is used in the dynamic VPN feature. The dynamic VPN feature further simplifies remote access by enabling users to establish Internet Protocol Security (IPsec) VPN tunnels without having to manually configure VPN settings on their PCs or laptops. Instead, authenticated users can simply download the Access Manager Web client to their computers. This Layer 3 remote access client uses client-side configuration settings that it receives from the server to create and manage a secure end-to-site VPN tunnel to the server.

DYNAMIC_VPN_AUTH_CONNECT_FAIL

System Log Message	Unable to connect to fwauthd on socket <i>file-descriptor: error-message</i>
Description	The connection manager authentication process could not connect to fwauthd daemon on the indicated socket.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_AUTH

DYNAMIC_VPN_AUTH_FAIL

System Log Message	Username/password and token are <i>username</i>
Description	The connection manager authentication process was unable to authenticate the indicated user/token
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_AUTH

DYNAMIC_VPN_AUTH_INVALID

System Log Message	<i>type username</i> is invalid
Description	The connection manager authentication failed due to invalid user/token
Type	Event: This message reports an event, not an error

Severity error
Facility LOG_AUTH

DYNAMIC_VPN_AUTH_MUL_CONN

System Log Message Connection exists for *type username* at *client-name client-id*

Description Connection already existed for this user

Type Event: This message reports an event, not an error
Severity error
Facility LOG_AUTH

DYNAMIC_VPN_AUTH_NO_CONFIG

System Log Message Authentication failed for *type username* due to unavailable client config

Description The connection manager authentication process was unable to obtain client config for the indicated user/token

Type Event: This message reports an event, not an error
Severity error
Facility LOG_AUTH

DYNAMIC_VPN_AUTH_NO_LICENSE

System Log Message Authentication failed for *type username* due to unavailable license

Description The connection manager authentication process was unable to obtain license for the indicated user/token

Type Event: This message reports an event, not an error
Severity error
Facility LOG_AUTH

DYNAMIC_VPN_AUTH_OK

System Log Message *type username* with *client-name client-id* authenticated successfully.

Description The connection manager authentication process was able to authenticate the indicated user/token successfully

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_AUTH

DYNAMIC_VPN_CLIENT_CONFIG_WRITE

System Log Message Client VPN config is saved in file *filename* for user *username*

Description Connection manager writes client VPN config to file before sending to client.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_AUTH

DYNAMIC_VPN_CONN_DEL_NOTIFY

System Log Message Connection manager receives SA deleted notification for ike-id *gateway-id*

Description Connection manager receives SA deleted notification from IKED.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_AUTH

DYNAMIC_VPN_CONN_DEL_REQUEST

System Log Message Connection manager receives delete request from the client for user *username* ike-id *gateway-id*

Description Connection manager receives connection delete request from the client.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_AUTH

DYNAMIC_VPN_CONN_EST_NOTIFY

System Log Message Connection manager receives SA established notification for ike-id *gateway-id*

Description Connection manager receives SA established notification from IKED.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_AUTH

DYNAMIC_VPN_INIT_SUCCESSFUL

System Log Message Connection manager initialization succeeded.

Description Connection manager is initialized successfully.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_AUTH

DYNAMIC_VPN_LICENSE_ASSIGNED

System Log Message	Dynamic VPN license granted, license <i>limit</i> free, <i>count</i> overdrafted, <i>current-value</i> used
Description	The Access Manager client has successfully acquired a license and is permitted to connect to the device.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_FIREWALL

DYNAMIC_VPN_LICENSE_CHECK_FAILED

System Log Message	Dynamic VPN license check failed for user <i>username</i>
Description	No Access Manager license is available at the moment.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

DYNAMIC_VPN_LICENSE_CHECK_OK

System Log Message	Dynamic VPN license check succeed for user <i>username</i>
Description	Preliminary check on Access Manager license is successful for the given user.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_AUTH

DYNAMIC_VPN_LICENSE_EXHAUSTED

System Log Message	Dynamic VPN license denied, no available license
Description	The device is out of Access Manager licenses. Connection request from the Access Manager client is denied.
Type	Error: An error occurred
Severity	error
Facility	LOG_FIREWALL

DYNAMIC_VPN_LICENSE_FREED

System Log Message	Dynamic VPN license returned, license <i>limit</i> free, <i>count</i> overdrafted, <i>current-value</i> used
Description	The Access Manager client has disconnected and returned its license.
Type	Event: This message reports an event, not an error

Severity info
Facility LOG_FIREWALL

DYNAMIC_VPN_LICENSE_FREE_FAILED

System Log Message Server failed to free an Access Manager for *username*
Description The Access Manager client attempt to return a license has failed.

Type Event: This message reports an event, not an error
Severity error
Facility LOG_AUTH

DYNAMIC_VPN_LICENSE_FREE_OK

System Log Message Server successfully freed an Access Manager license for *username*
Description The Access Manager client successfully returned a license.

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_AUTH

DYNAMIC_VPN_LICENSE_GET_FAILED

System Log Message Server failed to get an Access Manager license for *username*
Description No Access Manager license is available at the moment.

Type Event: This message reports an event, not an error
Severity error
Facility LOG_AUTH

DYNAMIC_VPN_LICENSE_GET_OK

System Log Message Server successfully got an Access Manager license for *username*
Description The Access Manager client successfully obtained a license.

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_AUTH

DYNAMIC_VPN_LICENSE_INSTALLED

System Log Message Dynamic VPN license *name* installed, license *limit* total, *count* free
Description An Access Manager license was installed successfully on this device.

Type Event: This message reports an event, not an error

Severity info
Facility LOG_FIREWALL

DYNAMIC_VPN_LICENSE_REQUIRED

System Log Message Dynamic VPN license denied, no license installed

Description Requested operation requires an Access Manager license to be installed on this device.

Type Error: An error occurred

Severity error

Facility LOG_FIREWALL

DYNAMIC_VPN_LICENSE_UNINSTALLED

System Log Message Dynamic VPN license *name* deleted, license *limit* total, *count* free

Description An Access Manager license is removed from this device.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_FIREWALL

CHAPTER 30

ESPTASK System Log Messages

This chapter describes messages with the **ESPTASK** prefix.

ESPTASK_PARSE_BAD_SWITCH

System Log Message	<i>executable-name: invalid switch: option</i>
Description	This process terminated because of an invalid option.
Type	Error: An error occurred
Severity	error
Facility	ANY
Action	Examine the messages that immediately follow this message in the system log for information about possible causes.
Cause	An internal software failure occurred.

ESPTASK_PARSE_CMD_ARG

System Log Message	<i>executable-name: missing argument for switch: option</i>
Description	This process terminated because of an internal error.
Type	Error: An error occurred
Severity	error
Facility	ANY
Action	Examine the messages that immediately follow this message in the system log for information about possible causes.
Cause	An internal software failure occurred.

ESPTASK_PARSE_CMD_EXTRA

System Log Message	<i>executable-name: extraneous information on command line: option</i>
Description	This process terminated because of an invalid option.

Type	Error: An error occurred
Severity	error
Facility	ANY
Action	Examine the messages that immediately follow this message in the system log for information about possible causes.
Cause	An internal software failure occurred.

ESPTASK_PARSE_USAGE

System Log Message	Usage: <i>executable-name</i> [-c] [-C] [-n] [-N] [-t[flags]] [-f config-file] [trace-file]
Description	This process terminated because of an invalid option.
Type	Error: An error occurred
Severity	error
Facility	ANY
Action	Examine the messages that immediately follow this message in the system log for information about possible causes.
Cause	An internal software failure occurred.

CHAPTER 31

ESWD System Log Messages

This chapter describes messages with the **ESWD** prefix. They are generated by the ethernet bridging process (eswd).

ESWD_BPDU_BLOCK_ERROR_DISABLED

System Log Message	<i>interface-name</i> : bpdu-block disabled port
Description	This condition occurs when bpdu-block error condition is detected.
Type	Error: An error occurred
Severity	alert
Facility	LOG_DAEMON

ESWD_BPDU_BLOCK_ERROR_ENABLED

System Log Message	<i>interface-name</i> : bpdu-block enabled port
Description	This condition occurs when bpdu-block error condition is cleared.
Type	Error: An error occurred
Severity	alert
Facility	LOG_DAEMON

ESWD_DAI_FAILED

System Log Message	<i>count type</i> received, interface <i>interface-name</i> [index <i>interface-device-index</i>], vlan <i>vlan-name</i> [index <i>vlan-id</i>], sender ip/mac <i>sender-address/mac1</i> , receiver ip/mac <i>destination-address/mac2</i>
Description	The ARP request/response received on this port cannot be linked to any of the IPs assigned by DHCP.
Type	Error: An error occurred
Severity	alert
Facility	LOG_DAEMON

ESWD_DHCP_UNTRUSTED

System Log Message	<i>count</i> untrusted <i>type</i> received, interface <i>interface-name</i> [index <i>interface-device-index</i>], vlan <i>vlan-name</i> [index <i>vlan-id</i>], server ip/mac <i>source-address/mac1</i> , offer ip/client mac <i>client-address/mac2</i>
Description	DHCP server packets are being received on a port which was not meant to receive server traffic.
Type	Error: An error occurred
Severity	alert
Facility	LOG_DAEMON

ESWD_INVALID_MAC_ADDRESS

System Log Message	Invalid MAC address <i>mac-addresse</i> received on <i>interface-name</i>
Description	Received a MAC address that is not in the configured valid MAC addresses for this interface.
Type	Error: An error occurred
Severity	alert
Facility	LOG_DAEMON
Cause	MAC address recieved is not configured as a valid MAC address for this interface.

ESWD_MAC_LIMIT_ALERT

System Log Message	MAC limit is less than the current number of MACs for the interface. You might want to remove some of the MACs for interface <i>interface-name</i> using `clear ethernet-switching table' command
Description	Log message alerting user to clear the MACs because the number of MACs learned on an interface exceeds the mac limit
Type	Error: An error occurred
Severity	alert
Facility	LOG_DAEMON

ESWD_MAC_LIMIT_BLOCK

System Log Message	MAC limit (<i>limit</i>) exceeded at <i>interface-name</i> : shutting down the interface
Description	Interface was blocked because the number of MAC addresses learned on an interface has exceeded the user configured limit.
Type	Error: An error occurred
Severity	alert

Facility LOG_DAEMON

Cause More learning requests were received by the system than the user configured.

ESWD_MAC_LIMIT_DROP

System Log Message MAC limit (*limit*) exceeded at *interface-name*: dropping the packet

Description Learning request was dropped because the number of MAC addresses learned on an interface has reached the user configured limit.

Type Error: An error occurred

Severity alert

Facility LOG_DAEMON

Cause More learning requests were received by the system than the user configured.

ESWD_MAC_LIMIT_EXCEEDED

System Log Message MAC limit (*limit*) exceeded at *interface-name*

Description Number of MAC addresses learned on an interface has exceeded the user configured limit.

Type Error: An error occurred

Severity alert

Facility LOG_DAEMON

Cause More learning requests were received by the system than the user configured.

ESWD_MAC_MOVE_LIMIT_BLOCK

System Log Message MAC move limit (*limit*) exceeded at *vlan-name* for MAC address *mac-addresse*; shutting down interface *interface-name*

Description Data traffic on interface was halted because the number of times that a MAC addresses moved to a different interface exceeded the user-configured limit.

Type Error: An error occurred

Severity alert

Facility LOG_DAEMON

Cause A MAC address moved to a different interface more times per second than the user configured.

ESWD_MAC_MOVE_LIMIT_DROP

System Log Message MAC move limit (*limit*) exceeded at *vlan-name* for MAC address *mac-addresse*; dropping the packet on interface *interface-name*

Description	Learning request was dropped because the number of times a MAC address moved to a different interface exceeded the user-configured limit.
Type	Error: An error occurred
Severity	alert
Facility	LOG_DAEMON
Cause	A MAC address moved to a different interface more times per second than the user configured.

ESWD_MAC_MOVE_LIMIT_EXCEEDED

System Log Message	MAC move limit (<i>limit</i>) exceeded at <i>vlan-name</i> for MAC address <i>mac-addresse</i> on interface <i>interface-name</i>
Description	The number of times that a MAC address moved to a different interface within a VLAN exceeded the user-configured limit.
Type	Error: An error occurred
Severity	alert
Facility	LOG_DAEMON
Cause	A MAC address moved to a different interface more times per second than the user configured.

ESWD_MIRROR_ERROR

System Log Message	Mirror version on other Routing Engine is incompatible: <i>error-message</i>
Description	The indicated error occurred when the layer2 control protocol process (l2cpd) tried to establish the nonstop routing mirror connection between the master and standby Routing Engines.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Cause	The master and standby Routing Engines are running incompatible versions of the JUNOS software.
Action	Update the JUNOS software on the master Routing Engine, standby Routing Engine, or both, so that they are running compatible versions.

ESWD_MIRROR_VERSION_MISMATCH

System Log Message	Mirror versions on Routing Engines are incompatible: <i>mastermaster-is-local</i> has version <i>master-version</i> , <i>standbystandby-is-local</i> has version <i>standby-version</i>
---------------------------	---

Description	While trying to establish the nonstop routing mirror connection between the master and standby Routing Engines, the layer2 control protocol process (l2cpd) determined that the version of the nonstop routing mirror software on the Routing Engines did not match.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Cause	The master and standby Routing Engines are running incompatible versions of the JUNOS software.
Action	Update the JUNOS software on the master Routing Engine, standby Routing Engine, or both, so that they are running compatible versions.

ESWD_MODULE_SHUTDOWN_FAILURE

System Log Message	ESWD: <i>error-message</i> Module shutdown failed
Description	While deleting the instance of logical-switch, RST/MST Module shutdown failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

ESWD_PPM_READ_ERROR

System Log Message	Read error on pipe from pppmd: <i>reason (error-message)</i>
Description	The ethernet bridging process (eswd) could not read a message available on the read pipe from the periodic packet management process (ppmd).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

ESWD_PPM_WRITE_ERROR

System Log Message	<i>function-name</i> : write error on pipe to pppmd (<i>error-message</i>)
Description	The ethernet bridging process (eswd) could not write a message on the pipe to the periodic packet management process (ppmd).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

Action Contact your technical support representative.

ESWD_STP_BASE_MAC_ERROR

System Log Message Failed to get *error-message*. All modules will remain disabled.

Description This condition occurs when STP cannot derive the base MAC address of the system.

Type Error: An error occurred

Severity alert

Facility LOG_DAEMON

ESWD_STP_LOOP_PROTECT_CLEARED

System Log Message *interface-name*: loop protect cleared for instance *instance-id*

Description This condition occurs when STP loop protect condition is cleared.

Type Error: An error occurred

Severity alert

Facility LOG_DAEMON

ESWD_STP_LOOP_PROTECT_IN_EFFECT

System Log Message *interface-name*: loop protect in effect for instance *instance-id*

Description This condition occurs when STP loop protect condition occurs.

Type Error: An error occurred

Severity alert

Facility LOG_DAEMON

ESWD_STP_ROOT_PROTECT_CLEARED

System Log Message *interface-name*: root protect cleared for instance *instance-id*

Description This condition occurs when STP root protect condition is cleared.

Type Error: An error occurred

Severity alert

Facility LOG_DAEMON

ESWD_STP_ROOT_PROTECT_IN_EFFECT

System Log Message *interface-name*: root protect in effect for instance *instance-id*

Description This condition occurs when STP root protect condition occurs.

Type Error: An error occurred

Severity alert
Facility LOG_DAEMON

ESWD_ST_CTL_BW_INFO

System Log Message *interface-name*: configured storm control speed *level* is greater than interface speed *bandwidth*. Storm control will be set to the latter

Description Log message to alert the user to the bandwidth setting limits.

Type Error: An error occurred
Severity alert
Facility LOG_DAEMON

ESWD_ST_CTL_ERROR_DISABLED

System Log Message *interface-name*: storm control disabled port

Description This condition occurs when storm control error condition is detected.

Type Error: An error occurred
Severity alert
Facility LOG_DAEMON

ESWD_ST_CTL_ERROR_ENABLED

System Log Message *interface-name*: storm control enabled port

Description This condition occurs when storm-control error condition is cleared.

Type Error: An error occurred
Severity alert
Facility LOG_DAEMON

ESWD_ST_CTL_ERROR_IN_EFFECT

System Log Message *interface-name*: storm control in effect on the port

Description This condition occurs when a storm control error condition is detected.

Type Error: An error occurred
Severity alert
Facility LOG_DAEMON

ESWD_ST_CTL_INFO

System Log Message *interface-name*: storm control will default to 80 percent of link speed

Description Log message to alert the user to the storm control setting.

Type Error: An error occurred
Severity alert
Facility LOG_DAEMON

ESWD_SYSTEM_CALL_FAILED

System Log Message *reason: error-message*

Description A system call made by enterprise switching process (eswd) failed.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON
Cause It is possible that the kernel lacked the resources to fulfill the request.

CHAPTER 32

EVENTD System Log Messages

This chapter describes messages with the **EVENTD** prefix. They are generated by the event policy process (eventd), which performs configured actions in response to events on a routing platform that trigger system log messages.

EVENTD_ACK_FAILED

System Log Message	Unable to send acknowledgment: <i>error-message</i>
Description	Junos processes can request that the event processing process (eventd) notify them when a specific event occurs. The eventd process could not send an acknowledgment for a registration request, for the indicated reason.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

EVENTD_ALARM_CLEAR

System Log Message	User <i>username</i> cleared alarm: " <i>timestamp: message</i> "
Description	An administrator has acknowledged and cleared a security alarm.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

EVENTD_ALARM_FILE

System Log Message	Could not open the eventd alarm file ' <i>filename</i> ' for writing
Description	The event processing process (eventd) could not open the alarm statistics file for writing.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

EVENTD_COMMAND_SUBSTITUTE_ERROR

System Log Message	Variable substitution failed for command ' <i>command</i> '
Description	The event processing process (eventd) can be configured to execute a Junos command-line interface (CLI) command when a specified event occurs. The command can include one or more variables (such as an interface name), which the eventd process replaces with actual values related to the event when it issues the command. Variable substitution failed for the indicated command.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.

EVENTD_ESCRIPT_EXECUTION

System Log Message	Trying to execute the script ' <i>filename</i> ' from ' <i>directory-name</i> '
Description	The event process (eventd) executing the configured event script from the specified location.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

EVENTD_ESCRIPT_NOT_CONFIGURED

System Log Message	Trying to execute the non configured script ' <i>filename</i> ' from ' <i>directory-name</i> '
Description	The event process (eventd) executing the non configured event script from the specified location.
Type	Error: An error occurred
Severity	info
Facility	LOG_DAEMON

EVENTD_EVENT_SEND_FAILED

System Log Message	Unable to send event notification: <i>error-message</i>
Description	Junos processes can request that the event processing process (eventd) notify them when a specific event occurs. The eventd process could not send an event notification for the indicated reason.
Type	Error: An error occurred
Severity	error

Facility LOG_DAEMON

EVENTD_FORK_ERR

System Log Message Unable to fork: *error-message*

Description The event processing process (eventd) could not create a child process for executing policies.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

EVENTD_PIPE_CREATION_FAILED

System Log Message Unable to create pipe: *error-message*

Description The event processing process (eventd) could not create a pipe for interprocess communication.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

EVENTD_POLICY_ACTION_FAILED

System Log Message Unable to execute '*action*' action in policy *policy-name*

Description The event processing process (eventd) could not perform the indicated action, which is specified by the indicated policy.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

EVENTD_POLICY_LIMIT_EXCEEDED

System Log Message Unable to execute policy '*policy-name*' because current number of policies (*count*) exceeds system limit (*limit*)

Description The event processing process (eventd) could not execute the indicated policy, because the indicated number of currently executing policies exceeded the indicated maximum defined by the system.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

EVENTD_POLICY_UPLOAD_FAILED

System Log Message	Unable to upload file ' <i>filename</i> ' to destination ' <i>destination-name</i> ' for policy ' <i>policy-name</i> '
Description	The event processing process (eventd) could not upload the indicated file to the indicated destination.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

EVENTD_POPEN_FAIL

System Log Message	Error <i>error-code</i> in invoking command ' <i>command</i> '
Description	A call to the popen() function failed when the event processing process (eventd) invoked the indicated command.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

EVENTD_READ_ERROR

System Log Message	recvmsg() failed: <i>error-message</i>
Description	The event processing process (eventd) could not read an event sent to it, for the indicated reason.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

EVENTD_REGEX_INVALID

System Log Message	Invalid regular expression ' <i>regular-expression</i> ' provided for attribute value
Description	The event processing process (eventd) received a request that included the indicated regular expression as the value for an attribute. The regular expression is not valid.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

EVENTD_REG_VERSION_MISMATCH

System Log Message	Registration version <i>expected-value</i> did not match expected version (<i>received-value</i>)
---------------------------	---

Description The event processing process (eventd) received a registration request with the indicated version indicator, which does not match the indicated version expected by the eventd process.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

EVENTD_ROTATE_COMMAND_FAILED

System Log Message Command '*command*' failed during rotation of file '*filename*': *error-message*

Description The event processing process (eventd) invoked the indicated command while attempting to rotate the indicated file. The command failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

EVENTD_ROTATE_FORK_EXCEEDED

System Log Message Unable to fork: too many child processes

Description The event processing process (eventd) could not create a child process for rotating files because adding another child would have made the number of children exceed the limit.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

EVENTD_ROTATE_FORK_FAILED

System Log Message Unable to fork: *error-message*

Description The event processing process (eventd) could not create a child process for rotating files, for the indicated reason.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

EVENTD_SCRIPT_CHECKSUM_MISMATCH

System Log Message *checksum* checksum value does not match for script *filename*

Description Current checksum value of the script does not match with the checksum configured under [event-options event-script] hierarchy. As a result any event-policy configured inside the script will not be read

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

EVENTD_SET_PROCESS_PRIV_FAILED

System Log Message Unable to set process privilege level to that of user '*username*': *error-message*

Description In preparation for executing an action defined in a policy, the event processing process (eventd) tried to change its privilege level to that of the indicated Junos user. The attempt failed. It made the attempt because the user-name statement is included at one of several possible levels under the [edit event-options policy <policy-name> then] hierarchy level.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

EVENTD_SET_TIMER_FAILED

System Log Message evSetTimer failed: *error-message*

Description The event processing process (eventd) starts a timer whenever an internal event needs to be generated. It could not activate the timer for the indicated reason.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

EVENTD_SYSLOG_FWD_FAILED

System Log Message Unable to forward syslog message to PSD (*psd-id*), errno: *error-code*

Description The event processing process (eventd) encountered a system error when forwarding a syslog message to indicated protected system domain (PSD).

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

EVENTD_TEST_ALARM

System Log Message This is test alarm *argument1* of *argument2*

Description This is an alarm test for the eventd alarm infrastructure.

Type Event: This message reports an event, not an error
Severity notice

Facility LOG_DAEMON

EVENTD_TRANSFER_COMMAND_FAILED

System Log Message Command '*error-code*' failed during transfer of file '*command*': *filename*

Description The event processing process (eventd) invoked the indicated command while attempting to transfer the indicated file. The command failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

EVENTD_TRANSFER_FORK_EXCEEDED

System Log Message Unable to fork: too many child processes

Description The event processing process (eventd) could not create a child process for transferring files, because adding another child would have made the number of children exceed the limit.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

EVENTD_TRANSFER_FORK_FAILED

System Log Message Unable to fork: *error-message*

Description The event processing process (eventd) could not create a child process for transferring files, for the indicated reason.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

EVENTD_VERSION_MISMATCH

System Log Message Event version *expected-value* did not match expected version (*received-value*)

Description The event processing process (eventd) received an event with the indicated version indicator, which does not match the indicated version expected by the eventd process.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

EVENTD_XML_FILENAME_INVALID

System Log Message XML syntax of output filename was invalid

Description	An event script created an output file and wrote the filename to standard output (stdout) with Extensible Markup Language (XML) tagging like the following: <event-script-output-filename>output-file.tgz</event-script-output-filename>. The event processing process read the output filename and determined that its XML syntax was invalid.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHAPTER 33

FC System Log Messages

This chapter describes messages with the **FC** prefix. They are generated by the Fibre Channel process (*fcd*) which connects servers to disks and tape devices in a storage area network.

FC_FABRIC_CREATED

System Log Message	Fabric <i>fc-fabric-name</i> fabric-id <i>fc-fabric-id</i> fabric-type <i>fc-fabric-type</i> created
Description	Fibre channel fabric is created.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

FC_FABRIC_DELETED

System Log Message	Fabric <i>fc-fabric-name</i> fabric-id <i>fc-fabric-id</i> fabric-type <i>fc-fabric-type</i> deleted
Description	Fibre channel fabric is deleted.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

FC_FABRIC_WWN_ASSIGNED

System Log Message	Fabric <i>fc-fabric-name</i> fabric-wwn <i>wwn</i> is set
Description	Fabric_WWN has been set for a fibre channel fabric.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

FC_FABRIC_WWN_CLEARED

System Log Message	Fabric <i>fc-fabric-name</i> fabric-wwn is cleared
---------------------------	--

Description Fabric_WWN is cleared for a fibre channel fabric.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

FC_FLOGI_VN_PORT_LOGIN_FAILED

System Log Message Fabric *fc-fabric-name* interface *interface-name* enode-mac *enode-mac-address* wwn *wwn* - *reason*

Description FIP FLOGI/FDISC from the end node has failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

FC_LOGICAL_INTERFACE_CREATED

System Log Message Fabric *fc-fabric-name* interface *interface-name* created

Description Fibre channel logical interface is created.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

FC_LOGICAL_INTERFACE_DELETED

System Log Message Fabric *fc-fabric-name* interface *interface-name* deleted

Description Fibre channel logical interface is deleted.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

FC_LOGICAL_INTERFACE_ISOLATED

System Log Message Fabric *fc-fabric-name* interface *interface-name* reason - *reason*

Description Fibre channel logical interface is isolated.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause Protocol error or repeated failure must have occurred.

Action Check physical connection and reason code for isolation.

Action Interface disable followed by enable might clear this problem.

FC_PROXY_NP_PORT_LB_ADDED

System Log Message Fabric *fc-fabric-name* NP_Port *interface-name* added to fabric load balance list

Description NP_Port is added to the fabric load balance list.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

FC_PROXY_NP_PORT_LB_REMOVED

System Log Message Fabric *fc-fabric-name* NP_Port *interface-name* removed from fabric load balance list

Description NP_Port is removed from the fabric load balance list.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

FC_PROXY_NP_PORT_LOGIN_ABORTED

System Log Message Fabric *fc-fabric-name* NP_Port *interface-name* login aborted

Description Login from NP_Port has aborted.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause It is possible that the NP_Port or fibre channel switch is experiencing timeouts.

FC_PROXY_NP_PORT_LOGIN_FAILED

System Log Message Fabric *fc-fabric-name* NP_Port *interface-name* login failed - *error-message*

Description Login from NP_Port has failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause NP_Port login is rejected by the fibre channel switch.

Action Check fibre channel switch configuration.

FC_PROXY_NP_PORT_LOGOUT

System Log Message Fabric *fc-fabric-name* NP_Port *interface-name* logged out by core switch

Description NP_Port is logged out from the fabric port.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

FC_PROXY_NP_PORT_NPIV_FAILED

System Log Message Fabric *fc-fabric-name* NP_Port *interface-name* attached fabric port does not support NPIV

Description Fabric port on the fibre channel switch does not support NPIV.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

FC_PROXY_NP_PORT_OFFLINE

System Log Message Fabric *fc-fabric-name* NP_Port *interface-name* is offline

Description Proxy NP_Port is down.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

FC_PROXY_NP_PORT_ONLINE

System Log Message Fabric *fc-fabric-name* NP_Port *interface-name* fcid: *fcid* online

Description Login from NP_Port is completed.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

FC_PROXY_VN_PORT_LOGIN_ABORTED

System Log Message Fabric *fc-fabric-name* NP_Port *interface-name* FDISC is aborted for wwn *wwn*

Description FLOGI or FDISC from the VN_port (end node) is aborted.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause It is possible that the NP_Port or fibre channel switch is experiencing timeouts.

FC_PROXY_VN_PORT_LOGIN_FAILED

System Log Message Fabric *fc-fabric-name* NP_Port *interface-name* FDISC rejected for wwn *wwn* - *error-message*

Description FLOGI or FDISC from the VN_Port (end node) has failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause VN_Port login is rejected by the fibre channel switch.

CHAPTER 34

FCD System Log Messages

This chapter describes messages with the **FCD** prefix. They are generated by the Fibre Channel process (fcd) which connects servers to disks and tape devices in a storage area network.

FCD_SYS_CALL_FAILED

System Log Message	<i>reason: error-message</i>
Description	A system call made by the fibre channel process (fcd) failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	It is possible that the kernel did not have enough resources to fulfill the request.

CHAPTER 35

FCOE System Log Messages

This chapter describes messages with the **FCOE** prefix. They are generated by the Fibre Channel process (fcd) which connects servers to disks and tape devices in a storage area network.

FCOE_LOGICAL_INTERFACE_CREATED

System Log Message	Fabric <i>fc-fabric-name</i> interface <i>interface-name</i> mac <i>mac-address</i> created
Description	Fibre channel over Ethernet logical interface is created.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

FCOE_LOGICAL_INTERFACE_DELETED

System Log Message	Fabric <i>fc-fabric-name</i> interface <i>interface-name</i> mac <i>mac-address</i> deleted
Description	Fibre channel over Ethernet logical interface is deleted.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

FCOE_LOGICAL_INTERFACE_ISOLATED

System Log Message	Fabric <i>fc-fabric-name</i> interface <i>interface-name</i> mac <i>mac-address</i> reason - <i>reason</i>
Description	Fibre channel over Ethernet logical interface is isolated.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	Protocol error or repeated failure must have occurred.
Action	Check physical connection and reason code for isolation.

Action Interface disable followed by enable might clear this problem.

CHAPTER 36

FIP System Log Messages

This chapter describes messages with the **FIP** prefix. They are generated by the Fibre Channel process (fcd) which connects servers to disks and tape devices in a storage area network.

FIP_ENODE_CLEARED

System Log Message	Fabric <i>fc-fabric-name</i> interface <i>interface-name</i> enode-mac <i>enode-mac-address</i>
Description	FIP end node is removed from a fibre channel fabric.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

FIP_ENODE_FKA_TIMER_EXPIRED

System Log Message	Fabric <i>fc-fabric-name</i> interface <i>interface-name</i> enode-mac <i>enode-mac-address</i> keepalive timer expired
Description	FIP end node keepalive timer expired.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

FIP_ENODE_LEARNED

System Log Message	Fabric <i>fc-fabric-name</i> interface <i>interface-name</i> enode-mac <i>enode-mac-address</i>
Description	FIP End node is learnt on a fibre channel fabric.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

FIP_MAX_FCOE_FILTERS_REACHED

System Log Message	Maximum number of allowed FCoE filters (<i>slot</i>) reached for this slot <i>maximum-value</i>
---------------------------	---

Description Maximum number of allowed FCoE filters reached.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

FIP_MAX_SESSIONS_REACHED

System Log Message Maximum number of allowed FIP sessions (*slot*) reached for this slot *maximum-value*

Description Maximum number of allowed FIP sessions reached.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

FIP_PROTOCOL_STARTED

System Log Message Fabric *fc-fabric-name* interface *interface-name* fcf-mac *mac-address* FIP protocol started

Description FIP protocol is started on an interface.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

FIP_PROTOCOL_STOPPED

System Log Message Fabric *fc-fabric-name* interface *interface-name* fcf-mac *mac-address* FIP protocol stopped

Description FIP protocol is stopped on an interface.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

FIP_VN_PORT_FKA_TIMER_EXPIRED

System Log Message Fabric *fc-fabric-name* interface *interface-name* enode-mac *enode-mac-address* wwn *wwn* vn-mac *vn-mac-address*

Description VN_Port keepalive timer expired.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

FIP_VN_PORT_LOGIN_FAILED

System Log Message	Fabric <i>fc-fabric-name</i> interface <i>interface-name</i> enode-mac <i>enode-mac-address</i> wwn <i>wwn</i> - <i>reason</i>
Description	FIP FLOGI/FDISC from the end node has failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	VN_Port login is rejected. Its possible that the maximum session limit has reached.
Action	Check the number of sessions on the end node or the number of sessions on the gateway

FIP_VN_PORT_SESSION_CLEARED

System Log Message	Fabric <i>fc-fabric-name</i> interface <i>interface-name</i> enode-mac <i>enode-mac-address</i> wwn <i>wwn</i> vn-mac <i>vn-mac-address</i> fcid <i>fcid</i>
Description	VN_Port login session is terminated.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

FIP_VN_PORT_SESSION_CREATED

System Log Message	Fabric <i>fc-fabric-name</i> interface <i>interface-name</i> enode-mac <i>enode-mac-address</i> wwn <i>wwn</i> vn-mac <i>vn-mac-address</i> fcid <i>fcid</i>
Description	FIP FLOGI/FDISC from the end node is completed.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

FLOW System Log Messages

This chapter describes messages with the **FLOW** prefix. They are generated by the process that handles flows on routers running the Junos OS with enhanced services.

FLOW_HIGH_WATERMARK_TRIGGERED

System Log Message	Number of sessions <i>current-flows</i> exceeded the high watermark <i>limit</i> . Early aging triggered.
Description	Early aging of sessions is triggered when the number of concurrent session entries in the session table exceeds the configured high watermark. When the number of concurrent sessions drops below the configured low watermark, the router stops aggressively aging out sessions. This message notifies you that the session high watermark has been exceeded and aggressive aging of sessions has begun.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_PFE

FLOW_IP_ACTION

System Log Message	Flow IP action detected attack attempt: <i>source-address/source-port --> destination-address/destination-port</i> from interface <i>interface-name</i> , from zone <i>source-zone-name</i> , action <i>action</i> .
Description	Flow IP action notification is generated when a new connection matches security flow IP action filter that has been setup to log or has ip-notify action
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_PFE

FLOW_LOW_WATERMARK_TRIGGERED

System Log Message	Number of sessions <i>current-flows</i> dropped below the low watermark <i>limit</i> . Early aging stopped.
Description	Early aging of sessions is triggered when the number of concurrent session entries in the session table exceeds the configured high watermark. When the number of concurrent sessions drops below the configured low watermark, the router stops aggressively aging

out sessions. This message notifies you that the number of concurrent sessions has dropped below the configured low watermark, and that aggressive aging of sessions has stopped.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_PFE

CHAPTER 38

FPCLOGIN System Log Messages

This chapter describes messages with the **FPCLOGIN** prefix. They are generated by the Flexible PIC Concentrator (FPC) login process (pimlogin), which provides direct login access to Physical Interface Modules (PIMs).

FPCLOGIN_ADDRESS_GET_FAILED

System Log Message	Unable to determine IP address of TGM in slot <i>slot</i>
Description	A user tried to log in to the Physical Interface Module (PIM) in the indicated slot on a Flexible PIC Concentrator (FPC). In response, the FPC login process (pimlogin) tried to determine the PIM's IP address. It could not do so, and the login attempt failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

FPCLOGIN_IPC_RECEIVE_FAILED

System Log Message	Unable to receive IPC message from <i>process-name</i>
Description	The Flexible PIC Concentrator (FPC) login process (pimlogin) could not process an interprocess communication (IPC) message from the indicated other process. The 'wxd' process is the WX Physical Interface Module process.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

FPCLOGIN_IPC_SEND_FAILED

System Log Message	Unable to send IPC message to <i>process-name</i>
Description	The Flexible PIC Concentrator (FPC) login process (pimlogin) could not send an interprocess communication (IPC) message to the indicated other process. The 'wxd' process is the WX Physical Interface Module process (wxd).
Type	Error: An error occurred

Severity error
Facility LOG_DAEMON

FPCLOGIN_LOGIN_FAILED

System Log Message fpclogin failed: *error-message*

Description A user tried to log in to a Physical Interface Module (PIM). The attempt failed for the indicated reason.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

FPCLOGIN_MESSAGE_INVALID

System Log Message Message from *process-name* *error-message*

Description The message that the Flexible PIC Concentrator (FPC) login process (pimlogin) received from the indicated other process was invalid in the indicated way. The 'wxd' process is the WX Physical Interface Module process (wxd).

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

FPCLOGIN_SOCKET_OPERATION_FAILED

System Log Message Unable to complete '*error-message*' operation

Description The Flexible PIC Concentrator (FPC) login process (pimlogin) could not perform the indicated operation on a routing socket.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHAPTER 39

FSAD System Log Messages

This chapter describes messages with the **FSAD** prefix. They are generated by the File System Access process (fsad), which provides Trivial FTP (TFTP) support for file transfer between services PICs and other routing platform components.

FSAD_CONFIG_ERROR

System Log Message	Reason: <i>reason</i>
Description	The configuration file for the File System Access process (fsad) might contain an error.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

FSAD_CONNTIMEDOUT

System Log Message	Connection timed out to the client (<i>connection-type</i> , <i>ip-address</i>) having request type <i>port</i>
Description	The File System Access process (fsad) flushed all state information about the timed-out connection.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON

FSAD_DIR_CREATE

System Log Message	Failed to create directory <i>directory-name</i> : <i>error-message</i>
Description	The File System Access process (fsad) could not create the indicated directory.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

FSAD_DIR_STAT

System Log Message	<i>function-name: stat()</i> failed for pathname <i>pathname: reason</i>
Description	The File System Access process (fsad) received a request for a nonexistent file or directory.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	The path does not exist.
Action	Make sure the path specified in the request is valid.

FSAD_FAILED

System Log Message	In <i>enclosing-function-name: function-name()</i> returned: <i>reason</i>
Description	An internal error occurred inside a function in the File System Access process (fsad).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

FSAD_FILE_FAILED

System Log Message	<i>enclosing-function-name: function-name</i> failed for file ' <i>filename</i> ' with error message <i>reason</i>
Description	An internal error occurred while the File System Access process (fsad) was performing a file operation.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

FSAD_FILE_REMOVE

System Log Message	Unable to remove file ' <i>filename</i> ': <i>reason</i>
---------------------------	--

Description	The File System Access process (fsad) could not remove the indicated file for the indicated reason.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	The file to be removed does not exist or its permissions do not allow the operation.
Action	Make sure that the file exists and that its permissions allow it to be deleted.

FSAD_FILE_RENAME

System Log Message	Unable to rename file ' <i>source-filename</i> ' to ' <i>destination-filename</i> ': <i>reason</i>
Description	The File System Access process (fsad) could not rename the indicated file for the indicated reason.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	Either the source file does not exist, or one or both of the source and destination pathnames are incorrect.
Action	Make sure the source and destination paths exist and that the rename operation is allowed.

FSAD_FILE_STAT

System Log Message	<i>function-name</i> : stat() failed for file pathname <i>pathname</i> : <i>reason</i>
Description	The File System Access process (fsad) received a request for a nonexistent file.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	The file path does not exist.
Action	Make sure the path specified in the request is valid.

FSAD_FILE_SYNC

System Log Message	Unable to sync file ' <i>filename</i> ': <i>reason</i>
---------------------------	--

Description When closing a file, the File System Access process (fsad) executes the sync() system call to ensure that any changes to the file are committed to disk. This operation failed for the indicated file.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

FSAD_FLOWC_IPC_PAYLOAD_SIZE

System Log Message Received flowc IPC message with incorrect length: message type *message-type*, subtype *message-subtype*, opcode *operation-code*, length *length* (expected length *expected-value*)

Description The File System Access process (fsad) received a flow collector IPC message in which the payload length was incorrect.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

FSAD_FLOWC_IPC_SUBTYPE

System Log Message Received flowc IPC message with incorrect subtype: message type *message-type*, subtype *message-subtype*, opcode *operation-code*, length *length*

Description The File System Access process (fsad) received a flow collector IPC message in which the subtype field was incorrect.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

FSAD_FLOWC_IPC_TYPE

System Log Message Received flowc IPC message with incorrect type: message type *message-type*, subtype *message-subtype*, opcode *operation-code*, length *length*

Description The File System Access process (fsad) received a flow collector IPC message in which the type field was incorrect.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

FSAD_FLOWC_IPC_VERSION

System Log Message Received flowc IPC message with incorrect version *received-value* (expected version *expected-value*)

Description The File System Access process (fsad) received a flow collector IPC message in which the version field was incorrect.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

FSAD_FLOWC_SERVICE_INACTIVE

System Log Message *reason*

Description The File System Access process (fsad) received a request for the Flow Collector Transfer Log Archive service, which is not currently active.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

FSAD_FREE_SPACE_LOG

System Log Message Unable to move temporary file *temporary-filename* (size *file-size* KB) to log file *log-filename* because free disk space (*count* KB) is insufficient

Description The File System Access process (fsad) could not move the CDR temporary file of the indicated size to the log file, because it is larger than the amount of free disk space.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

FSAD_FREE_SPACE_TMP

System Log Message Unable to write CDR batch output to file *temporary-filename* because free disk space (*count* KB) is insufficient

Description The File System Access process (fsad) could not write CDR batch output to the indicated temporary file, because the amount of free disk space was insufficient.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

FSAD_FS_STAT

System Log Message statfs() failed for pathname *pathname*: *reason*

Description The File System Access process (fsad) encountered an error in getting filesystem statistics.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

FSAD_GEN_IPC_PAYLOAD_SIZE

System Log Message Received IPC message with incorrect length: message type *message-type*, subtype *message-subtype*, opcode *operation-code*, length *length* (expected length *expected-value*)

Description The File System Access process (fsad) received an IPC message in which the payload length was incorrect.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

FSAD_GEN_IPC_SUBTYPE

System Log Message Received IPC message with incorrect subtype: message type *message-type*, subtype *message-subtype*, opcode *operation-code*, length *length*

Description The File System Access process (fsad) received an IPC message in which the subtype field was incorrect.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

FSAD_GEN_IPC_TYPE

System Log Message Received IPC message with incorrect type: message type *message-type*, subtype *message-subtype*, opcode *operation-code*, length *length*

Description The File System Access process (fsad) received an IPC message in which the type field was incorrect.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

FSAD_GEN_IPC_VERSION

System Log Message Received generic IPC message with incorrect version *received-value* (expected version *expected-value*)

Description The File System Access process (fsad) received an IPC message in which the version field was incorrect.

Type	Error: An error occurred
-------------	--------------------------

Severity error
Facility LOG_DAEMON

FSAD_GEN_SERVICE_INACTIVE

System Log Message Received IPC message for inactive service *service-name*

Description The File System Access process (fsad) received an IPC message for a service that is currently not active.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

FSAD_GEN_SERVICE_INIT_FAILED

System Log Message Failed to initialize service *service-name*

Description The File System Access process (fsad) could not initialize the indicated service.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

FSAD_MAXCONN

System Log Message Upper limit reached in fsad for handling connections

Description The File System Access process (fsad) stopped accepting new connections because it reached an internal limit for handling connections.

Type Event: This message reports an event, not an error

Severity error

Facility LOG_DAEMON

FSAD_MEMORYALLOC_FAILED

System Log Message *allocation-function-name* failed in the function *function-name* (*line-number*)

Description The File System Access process (fsad) could not allocate memory. The system might be running low on memory.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause An internal software failure occurred.

Action Contact your technical support representative.

FSAD_NOT_ROOT

System Log Message	Must be run as root
Description	The user who attempted to start the File System Access process (fsad) was not the root user.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

FSAD_PARENT_DIRECTORY

System Log Message	<i>directory-name</i> : invalid directory: <i>message</i>
Description	The parent directory specified in the request for a file was not valid.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Make sure the path specified in the request is valid.

FSAD_PATH_IS_DIRECTORY

System Log Message	File path cannot be a directory (<i>pathname</i>)
Description	The File System Access process (fsad) received a request on a directory instead of a regular file.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	The file path points to a directory.
Action	Make sure the path points to a regular file.

FSAD_PATH_IS_NOT_DIRECTORY

System Log Message	invalid path ' <i>pathname</i> ' : not a directory : <i>action</i>
Description	The File System Access process (fsad) received a request for a pathname that was not a directory.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

FSAD_PATH_IS_SPECIAL

System Log Message	Not a regular file (<i>pathname</i>)
Description	The File System Access process (fsad) received a request for a pathname that points to a nonregular file.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Make sure the path points to a regular file.

FSAD_RECVERROR

System Log Message	fsad received error <i>message</i> from client having request type <i>connection-type</i> at (<i>ip-address</i> , <i>port</i>)
Description	The File System Access process (fsad) received a packet with the indicated error message from the other end of a connection.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

FSAD_RENAME

System Log Message	<i>function-name</i> : failed to rename temporary file <i>filename</i> to <i>new-filename</i> : <i>reason</i>
Description	The File System Access process (fsad) could not rename the indicated temporary file for the indicated reason.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

FSAD_TERMINATED_CONNECTION

System Log Message	Open file ' <i>filename</i> ' closed due to process shutdown
Description	The File System Access process (fsad) terminated a connection, stored the connection's (unwritten) data to disk, and purged it from its data structures.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

FSAD_TRACEOPEN_FAILED

System Log Message	Open operation on trace file ' <i>pathname</i> ' returned error <i>error-message</i>
Description	The File System Access process (fsad) failed to open the indicated trace file.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

FSAD_USAGE

System Log Message	Incorrect usage, <i>message</i>
Description	The File System Access process (fsad) displayed its usage statement.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON
Cause	The fsad process was invoked with incorrect command-line arguments.
Action	Check the usage and invoke the fsad process with the correct command-line arguments.

CHAPTER 40

FUD System Log Messages

This chapter describes messages with the **FUD** prefix. They are generated by the UDP forwarding process (fud), which forwards UDP (User Datagram Protocol) packets from a network to a server for services that run over UDP.

FUD_ARGUMENT_FAILURE

System Log Message	Unknown option " <i>option</i> "
Description	One or more options provided on the 'fud' command line were invalid. The UDP forwarding process (fud) initialized but ignored the invalid options.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Reissue the 'fud' command with the correct options.

FUD_BAD_SERVER_ADDR_FAILURE

System Log Message	Destination address of <i>destination-address</i> is invalid
Description	One or more server addresses configured for the UDP forwarding process (fud) were invalid.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Reconfigure the fud process with valid server addresses.

FUD_BIND_FAILURE

System Log Message	bind(port <i>port</i>) failed: <i>error-message</i>
Description	The UDP forwarding process (fud) received the indicated error when it tried to bind a socket to a local address.
Type	Error: An error occurred

Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

FUD_DAEMON_FAILURE

System Log Message	Unable to run in the background as daemon: <i>error-message</i>
Description	The UDP forwarding process (fud) could not create a version of itself to run in the background as a daemon.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

FUD_MEMORY_ALLOCATION_FAILURE

System Log Message	Unable to allocate <i>count</i> bytes of memory: <i>error-message</i>
Description	The UDP forwarding process (fud) could not allocate the indicated amount of memory from the heap.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

FUD_PERMISSION_FAILURE

System Log Message	<i>program-name</i> must be run as root
Description	The user who attempted to start the UDP forwarding process (fud) was not the root user, so the process did not start.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Become the root user before issuing the 'fud' command.

FUD_PIDLOCK_FAILURE

System Log Message	Unable to lock PID file; another <i>program-name</i> was running
---------------------------	--

Description	The UDP Forwarding process (fud) attempted to lock the file that records its process ID (PID), which serves to prevent multiple instances of the fud process from running simultaneously. The attempt failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	Another instance of the fud process is running.
Action	Check whether another fud process is running, and stop it if appropriate.

FUD_PIDUPDATE_FAILURE

System Log Message	Unable to update PID file for <i>program-name</i>
Description	The UDP Forwarding process (fud) attempted to update the file that records its process ID (PID), which serves to prevent multiple instances of the fud process from running simultaneously. The attempt failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	Another instance of the fud process is running.
Action	Check whether another fud process is running, and stop it if appropriate.

FUD_RECVMSG_FAILURE

System Log Message	Exiting because of repeated recvmsg() failures
Description	The UDP Forwarding process (fud) could not receive data from the network, which it needs to do during normal operation.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

FUD_RTsock_WRITE_FAILURE

System Log Message	Unable to write to routing socket: <i>error-message</i>
Description	The UDP Forwarding process (fud) could not write to its routing socket for the indicated reason.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

FUD_SENDSMSG_FAILURE

System Log Message	<code>sendmsg()</code> to <i>destination-address</i> port <i>port</i> on interface <i>interface-name</i> <i>rt_inst</i> <i>routing-instance</i> failed: <i>error-message</i>
Description	The UDP Forwarding process (fud) could not send data to the indicated destination port and address via the indicated interface and routing instance, which it needs to do during normal operation.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

FUD_SENDSMSG_NOINT_FAILURE

System Log Message	<code>sendmsg()</code> to <i>destination-address</i> port <i>port</i> <i>rt_inst</i> <i>routing-instance</i> failed: <i>error-message</i>
Description	The UDP Forwarding process (fud) could not send data to the indicated destination port and address via the indicated routing instance, which it needs to do during normal operation.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

FUD_SETSOCKOPT_FAILURE

System Log Message	<code>setsockopt(arguments)</code> failed: <i>error-message</i>
Description	The UDP Forwarding process (fud) could not set the indicated socket option.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

FUD_SOCKET_FAILURE

System Log Message	socket(<i>arguments</i>) failed: <i>error-message</i>
Description	The UDP Forwarding process (fud) could not create a socket.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHAPTER 41

FWAUTH System Log Messages

This chapter describes messages with the **FWAUTH** prefix. They are generated by the process that authenticates users when they initiate a connection across a firewall.

FWAUTH_FTP_LONG_PASSWORD

System Log Message	Authentication for user <i>username</i> at <i>client-address</i> was denied (long password).
Description	The length of the password must not exceed 128 characters.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_PFE

FWAUTH_FTP_LONG_USERNAME

System Log Message	Authentication for user <i>username</i> at <i>client-address</i> was denied (long username).
Description	The length of the username must not exceed 64 characters.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_PFE

FWAUTH_FTP_USER_AUTH_ACCEPTED

System Log Message	User <i>username</i> of group <i>group-name</i> at <i>client-address</i> is accepted.
Description	The authenticated user can start accessing protected resources.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_PFE

FWAUTH_FTP_USER_AUTH_FAIL

System Log Message	User <i>username</i> at <i>client-address</i> is rejected.
Description	User authentication failed because the username or password was invalid.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_PFE

FWAUTH_HTTP_USER_AUTH_ACCEPTED

System Log Message User *username* of group *group-name* at *client-address* is accepted.
Description The authenticated user can start accessing protected resources.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_PFE

FWAUTH_HTTP_USER_AUTH_FAIL

System Log Message User *username* at *client-address* is rejected.
Description User authentication failed because the username or password was invalid.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_PFE

FWAUTH_TELNET_LONG_PASSWORD

System Log Message Authentication for user *username* at *client-address* was denied (long password).
Description The length of the password must not exceed 128 characters.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_PFE

FWAUTH_TELNET_LONG_USERNAME

System Log Message Authentication for user *username* at *client-address* was denied (long username).
Description The length of username must not exceed 64 characters.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_PFE

FWAUTH_TELNET_USER_AUTH_ACCEPTED

System Log Message User *username* of group *group-name* at *client-address* is accepted.
Description The authenticated user can start accessing protected resources

Type Event: This message reports an event, not an error
Severity info
Facility LOG_PFE

FWAUTH_TELNET_USER_AUTH_FAIL

System Log Message User *username* at *client-address* is rejected.
Description User authentication failed because the username or password was invalid.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_PFE

FWAUTH_WEBAUTH_FAIL

System Log Message WebAuth user *username* at *client-address* is rejected/timed out.
Description The provided user credentials are not valid.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_PFE

FWAUTH_WEBAUTH_SUCCESS

System Log Message WebAuth user *username* of group *group-name* at *client-address* is accepted.
Description The authenticated user can start accessing protected resources.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_PFE

CHAPTER 42

GPRSD System Log Messages

This chapter describes messages with the **GPRSD** prefix. They are generated by the general packet radio service process (gprsd) that integrates with existing GSM networks and offers mobile subscribers with packet switched data services access to corporate networks and the Internet.

GPRSD_MEMORY_ALLOC_FAILED

System Log Message	Unable to allocate <i>count</i> bytes of memory
Description	The general packet radio service daemon process (gprsd) could not allocate the indicated number of bytes of memory.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	It is possible that system memory is exhausted.
Action	Increase the amount of RAM in the Routing Engine.

GPRSD_RESTART_CCFG_READ_FAILED

System Log Message	Subcomponent could not read configuration database
Description	As the general packet radio service daemon process (gprsd) restarted, one or more of its subcomponents could not read its configuration information from the configuration database. The gprsd process restarted regardless without affecting routing performance.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHAPTER 43

HNCACHED System Log Messages

This chapter describes messages with the HNCACHED prefix. They are generated by the hostname-caching process (hncached) which stores hostnames in a temporary storage area in order to be able to retrieve them faster.

HNCACHED_HOST_ADDRESS_CHANGED

System Log Message	Detected change in IP addresses for host: <i>hostname</i>
Description	The hostname-caching process (hostname-cached) detected that the set of IP addresses for the specified hostname changed
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

HNCACHED_NAME_RESOLUTION_FAILURE

System Log Message	Failed to resolve hostname: <i>hostname</i> (<i>error-message</i>)
Description	The hostname-caching process (hostname-cached) failed to resolve the specified hostname for indicated reason
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	1)If the hostname used in config is incorrect, fix it. 2) Ensure that the configured name-server is reachabe and is working.

CHAPTER 44

ICCPD System Log Messages

This chapter describes messages with the **ICCPD** prefix. They are generated by the interchassis communication process (iccpd).

ICCPD_ASSERT_SOFT

System Log Message	Soft assertion failed at line <i>line-number</i> in file ' <i>source-filename</i> ' with error " <i>message</i> ", but iccpd with PID <i>pid</i> continued running
Description	The source code for the interchassis communication process (iccpd) includes internal self-consistency checks. As the iccpd process with the indicated process ID (PID) executed the binary compiled from the indicated source file, a check failed at the indicated line number in the file. The iccpd process created a diagnostic core file for analysis by technical support personnel and continued to run.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Examine the messages that immediately follow this message in the system log for information about possible causes. Contact a technical support representative, and be ready to provide the list of messages and the diagnostic core file, if requested.

ICCPD_OPEN_ERROR

System Log Message	<i>error-message</i> : open error on pipe
Description	The interchassis communication process (iccpd) could not initialize.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

ICCPD_READ_ERROR

System Log Message	Read error on pipe from <i>client-name</i> : <i>reason</i> (<i>error-message</i>)
Description	The interchassis communication process (iccpd) could not read a message on a pipe for the indicated client.
Type	Error: An error occurred
Severity	info
Facility	LOG_DAEMON
Action	Contact your technical support representative.

ICCPD_WRITE_ERROR

System Log Message	write error on pipe to <i>client-name</i> :
Description	The interchassis communication process (iccpd) could not write a message on a pipe for the indicated client.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

IDP System Log Messages

This chapter describes messages with the **IDP** prefix. They are generated by the Intrusion Detection and Prevention (IDP) process which enforces various attack detection and prevention techniques on network traffic.

IDP_APPDDOS_APP_ATTACK_EVENT

System Log Message	DDOS Attack at <i>timestamp</i> on <i>ddos-application-name</i> , < <i>source-zone-name:source-interface-name:source-address:source-port</i> >:< <i>destination-zone-name:destination-interface-name:destination-address:destination-port</i> > for <i>protocol-name</i> protocol and service <i>service-name</i> by rule <i>rule-name</i> of rulebase <i>rulebase-name</i> in policy <i>policy-name</i> . attack: repeats <i>repeat-count</i> action <i>action</i> threat-severity <i>threat-severity</i> , connection-hit-rate <i>connection-hit-rate</i> , context-name <i>context-name</i> , hit-rate <i>context-hit-rate</i> , value-hit-rate <i>context-value-hit-rate</i> time-scope <i>time-scope</i> time-count <i>time-count</i> time-period <i>time-period</i> secs, context value: <i>context-value</i>
Description	The application-level distributed denial-of-service (AppDDoS) attack occurred when the number of client transactions exceeded the user-configured connection, context and time binding thresholds
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_PFE

IDP_APPDDOS_APP_STATE_EVENT

System Log Message	DDOS Application threshold crossed at <i>timestamp</i> on <i>ddos-application-name</i> , < <i>destination-zone-name:destination-interface-name:destination-address:destination-port</i> > for <i>protocol-name</i> protocol and service <i>service-name</i> in rule <i>rule-name</i> of rulebase <i>rulebase-name</i> in policy <i>policy-name</i> . repeats <i>repeat-count</i> message: <i>message</i> context-value: <i>context-value</i>
Description	The application-level distributed denial-of-service (AppDDoS) state transition occurred when the number of application transactions exceeded the user-configured connection or context thresholds
Type	Event: This message reports an event, not an error
Severity	info

Facility LOG_PFE

IDP_ATTACK_LOG_EVENT

System Log Message IDP: at *timestamp*, *message-type* Attack log
<*source-address:source-port->destination-address:destination-port*> for *protocol-name*
protocol and service *service-name* application *application-name* by rule *rule-name* of
rulebase *rulebase-name* in policy *policy-name*. attack: repeat=*repeat-count*, action=*action*,
threat-severity=*threat-severity*, name=*attack-name*, NAT
<*nat-source-address:nat-source-port->nat-destination-address:nat-destination-port*>,
time-elapsed=*elapsed-time*, inbytes=*inbound-bytes*, outbytes=*outbound-bytes*,
inpackets=*inbound-packets*, outpackets=*outbound-packets*,
intf:*source-zone-name:source-interface-name->destination-zone-name:destination-interface-name*,
packet-log-id: *packet-log-id* and misc-message *message*

Description IDP Attack log generated for attack

Type Event: This message reports an event, not an error

Severity info

Facility LOG_PFE

IDP_COMMIT_COMPLETED

System Log Message IDP policy commit is complete.

Description IDP policy commit has completed. Policy compile and load however may have been a
success or failure.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_AUTH

IDP_COMMIT_FAILED

System Log Message IDP policy commit failed. Exiting from compilation.

Description There was an error while trying to commit the active policy in IDPD. Device will continue
running the current IDP policy.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

IDP_DAEMON_INIT_FAILED

System Log Message Aborting...A failure was encountered;*error-message*

Description An attempt to start IDP policy daemon failed because an error was encountered during
initialization.

Type Error: An error occurred
Severity error
Facility LOG_AUTH

IDP_IGNORED_IPV6_ADDRESSES

System Log Message IDP ignores IPv6 addresses for the '*rulebase-name*'
Description IDP IPv6 support is not enabled for the rulebase.

Type Event: This message reports an event, not an error
Severity warning
Facility LOG_AUTH

IDP_INTERNAL_ERROR

System Log Message Encountered an error(*error-message*)
Description IDP daemon encountered an internal error

Type Error: An error occurred
Severity error
Facility LOG_AUTH

IDP_POLICY_COMPILATION_FAILED

System Log Message IDP compilation of policy[*idp-policy*] failed : [*reason*]
Description IDP policy compiler encountered an error while compiling or packaging the policy. Device will continue running the existing IDP policy

Type Event: This message reports an event, not an error
Severity error
Facility LOG_AUTH

IDP_POLICY_LOAD_FAILED

System Log Message IDP policy loading failed ;policy[*idp-policy*] ,detector[*idp-detector*] ,failure detail[*reason*]
Description A compiled and optimized IDP policy could not be loaded into IDP engine. Device will continue running the existing IDP policy.

Type Error: An error occurred
Severity error
Facility LOG_AUTH

IDP_POLICY_LOAD_SUCCEEDED

System Log Message IDP policy[*idp-policy*] and detector[*idp-detector*] loaded successfully(*message*).

Description A compiled and optimized IDP policy was loaded successfully into the IDP engine. All subsequent sessions will be processed as per this new IDP policy.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_AUTH

IDP_POLICY_UNLOAD_FAILED

System Log Message Failed to unload IDP policy. reason: *reason*.

Description A running IDP policy could not be unloaded from IDP engine. Device will continue running the IDP policy.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

IDP_POLICY_UNLOAD_SUCCEEDED

System Log Message IDP policy unloaded successfully.

Description A running IDP policy was unloaded successfully from the IDP engine.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_AUTH

IDP_SCHEDULEDUPDATE_START_FAILED

System Log Message Failed to start scheduled update(*error:error-message*)

Description The scheduled IDP security package update failed to start. Device will try it again at the next scheduled time

Type Error: An error occurred

Severity error

Facility LOG_AUTH

IDP_SCHEDULED_UPDATE_STARTED

System Log Message Scheduled update has started(at *timestamp*)

Description The scheduled IDP security package update has started.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_AUTH

IDP_SECURITY_INSTALL_RESULT

System Log Message	security package install result(<i>status</i>)
Description	IDP background process has returned the security package install result
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_AUTH

IDP_SESSION_LOG_EVENT

System Log Message	IDP: at <i>timestamp</i> , <i>event-name</i> .
Description	IDP session threshold crossing event
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_PFE

IDP_SIGNATURE_LICENSE_EXPIRED

System Log Message	IDP Signagure update license(ID= <i>feature-id</i>) has expired
Description	IDP signature update license key has expired. Signature update may not work any more.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_AUTH

CHAPTER 46

JADE System Log Messages

This chapter describes messages with the **JADE** prefix. They are generated by the Junos XML protocol authentication process (*jade*), which authenticates and checks authorization of client applications using the Junos XML management protocol.

JADE_ATTRIBUTES_TOO_LONG

System Log Message	Attribute number or length in client <i>junoscript</i> tag was too large
Description	The JUNOScript client passed too many attributes in the initial <junoscript> tag, or the attributes were too long.
Type	Error: An error occurred
Severity	error
Facility	ANY

JADE_AUTH_FAILURE

System Log Message	Authentication failed for user ' <i>username</i> ' : <i>error-message</i>
Description	The username or password supplied by the client was incorrect.
Type	Error: An error occurred
Severity	notice
Facility	ANY

JADE_AUTH_SUCCESS

System Log Message	Authentication succeeded for user ' <i>username</i> '
Description	The jade authentication process authenticated the indicated user.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	ANY

JADE_EXEC_ERROR

System Log Message	CLI xml-mode exec error: <i>error-message</i>
---------------------------	---

Description The JUNOScript authentication process (jade) could not start because of an internal error.

Type Error: An error occurred

Severity error

Facility ANY

JADE_PAM_ERROR

System Log Message PAM error: *error-message*

Description The JUNOScript authentication process (jade) could not process the credentials supplied by the client.

Type Error: An error occurred

Severity error

Facility ANY

JADE_PAM_NO_LOCAL_USER

System Log Message Unable to get local username from PAM: *error-message*

Description The JUNOScript authentication process (jade) could not obtain a local username while processing the credentials supplied by the client.

Type Error: An error occurred

Severity error

Facility ANY

JADE_SOCKET_ERROR

System Log Message Socket operation '*operation*' failed: *error-message*

Description The indicated socket operation, initiated by the JUNOScript authentication process (jade), failed for the indicated reason.

Type Error: An error occurred

Severity error

Facility ANY

JCS System Log Messages

This chapter describes messages with the JCS prefix. They are generated by the Juniper Control System (jcsd) process which provides the user interface to the control processes for the management modules and switch modules in the JCS 1200 platform.

JCS_BBD_LOAD_FAILURE

System Log Message	Blade <i>slot</i> load BBD failure: <i>error-message</i>
Description	The JCS process (jcsd) could not load blade bay data for the specified blade.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

JCS_BBD_LOCAL_MISMATCH

System Log Message	Blade <i>slot</i> BBD <i>error-message</i> mismatch (<i>expected-value</i> != <i>received-value</i>)
Description	The blade bay data retrieved for the specified blade does not match the data loaded during the reboot process. This error usually indicates that blade bay data in the JCS Management Module was changed since the last reboot.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

JCS_BBD_NOT_FOUND

System Log Message	Blade <i>slot</i> bay data not found
Description	Blade bay data was not found for the specified blade.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

JCS_BBD_NOT_VALID

System Log Message	Blade <i>slot</i> BBD is invalid
Description	The blade bay data for the specified blade is invalid.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

JCS_BBD_PARSE_ERROR

System Log Message	Blade <i>slot</i> bay data parse error - <i>error-message</i>
Description	The blade bay data for the specified blade did not parse correctly.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

JCS_BBD_PEER_MISMATCH

System Log Message	Peer blade <i>slot</i> BBD <i>error-message</i> mismatch (<i>expected-value</i> != <i>received-value</i>)
Description	The blade bay data retrieved for the specified peer blade does not match the data retrieved for the local blade. This error indicates that blade bay data in the JCS Management Module was not configured properly.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

JCS_BBD_SYSTEM_CONFLICT

System Log Message	Local BBD <i>error-message</i> (<i>value</i>) conflicts with blade <i>slot</i>
Description	The blade bay data retrieved for the local blade conflicts with another blade in the JCS. This error indicates that blade bay data in the JCS Management Module was not configured properly.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

JCS_EXT_LINK_STATE

System Log Message	Switch <i>slot</i> EXT link state is <i>state</i>
Description	The JCS process (jcsd) detects a change of state for the external link of the indicated switch module.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_DAEMON

JCS_INVALID_BANDWIDTH_ERROR

System Log Message Invalid bandwidth percent (*value*)
Description The specified switch bandwidth is invalid. The bandwidth is defined as a percentage between 1 and 100.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

JCS_KERNEL_RSD_LINK_DOWN

System Log Message Kernel RSD link is DOWN (*error-message*)
Description The JCS process (jcsd) has disabled kernel RSD communication for the specified reason.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

JCS_KERNEL_RSD_LINK_ENABLED

System Log Message Kernel RSD link is ENABLED (*error-message*)
Description The JCS process (jcsd) has verified the blade bay data and enabled kernel RSD communication.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_DAEMON

JCS_MM_COMMUNICATION_ERROR

System Log Message MM communication error (*error-message*)
Description The JCS process (jcsd) could not send an SNMP request to the Management Module because of the indicated error.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

JCS_MM_COMMUNICATION_OK

System Log Message	MM communication is OK
Description	The JCS process (jcsd) has established a communication link with the Management Module.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

JCS_PEER_BLADE_STATE

System Log Message	Peer blade <i>slot</i> is <i>state</i>
Description	The JCS process (jcsd) detects a change of state for the indicated blade.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

JCS_READ_BANDWIDTH_ERROR

System Log Message	Read bandwidth error (<i>error-code</i>)
Description	The indicated error occurred when attempting to read the current switch bandwidth.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

JCS_READ_BBD_ERROR

System Log Message	Read blade bay data (<i>error=error-code</i>)
Description	The indicated error occurred when attempting to read the current blade bay data via a sysctl call.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

JCS_RSD_LINK_STATE

System Log Message	Switch <i>slot</i> RSD link state is <i>state</i>
Description	The JCS process (jcsd) detects a change of state for the RSD link of the indicated switch module.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_DAEMON

JCS_SWITCH_BANDWIDTH_CONFIG

System Log Message Switch *slot* bandwidth *value1* percent (*value2* Kbps)
Description The indicated JCS Switch Module has changed the bandwidth configuration to the specified value.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_DAEMON

JCS_SWITCH_COMMUNICATION_ERROR

System Log Message Switch *slot* communication error (*error-message*)
Description The JCS process (jcsd) could not send an SNMP request to the indicated Switch Module because of the indicated error.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

JCS_SWITCH_COMMUNICATION_OK

System Log Message Switch *slot* communication is OK
Description The JCS process (jcsd) has established a communication link with the indicated Switch Module.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_DAEMON

CHAPTER 48

JDIAMETERD System Log Messages

This chapter describes messages with the **JDIAMETERD** prefix. They are generated by the `jdiameter` process (`jdiameterd`). `Jdiameter` is an open source software implementation of the Diameter Base Protocol that is written in Java.

JDIAMETERD_FUNC_HSHAKE_FAIL

System Log Message	Application <i>diameter-function</i> cannot generate handshake, disconnecting
Description	The Diameter process(<code>jdiameterd</code>) failed to generate handshake message to the process that implements the Diameter-function. The connection was closed so that a new connection with full resynchronization could be established.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

JDIAMETERD_FUNC_LOCACCEPT_NFOUND

System Log Message	Path <i>pathname</i> does not match any application
Description	The Diameter process(<code>jdiameterd</code>) rejected a RE function side connection because there is no matching diameter-function.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

JDIAMETERD_FUNC_NSCK_LISTEN_FAIL

System Log Message	Unable to listen on internal-ip
Description	The Diameter process(<code>jdiameterd</code>) is unable to listen on the internal ip socket for function side connections.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

JDIAMETERD_FUNC_OUT_OF_SYNC

System Log Message	Application <i>diameter-function</i> is out of sync, disconnecting
Description	The Diameter process (jdiameterd) was out of sync with the process that implements the Diameter function. The connection was closed so that a new connection with full resynchronization could be established.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

JDIAMETERD_FUNC_PICACCEPT_NFOUND

System Log Message	Port <i>remote-port</i> does not match any application
Description	The Diameter process(jdiameterd) rejected a PIC function side connection because there is no matching diameter-function.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

JDIAMETERD_FUNC_TOO_MANY_BADE2ES

System Log Message	Application <i>diameter-function</i> has too many bad end-to-end-ids, disconnecting
Description	A daemon impelenting diameter function, sent too many messages with bad end-to-end-ids the connection will be closed, so a new connection with full resynchronization could be established.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

JDIAMETERD_FUNC_USCK_LISTEN_FAIL

System Log Message	Unable to listen on <i>pathname</i>
Description	The Diameter process(jdiameterd) is unable to listen on the unix socket for function side connections.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHAPTER 49

JIVED System Log Messages

This chapter describes messages with the **JIVED** prefix. They are generated by the mag-service process (jived).

JIVED_ALREADY_RUNNING

System Log Message	Another copy of this program is running
Description	Another instance of the mag-service process (jived) is already running. Only one instance can run at a time.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

JIVED_EVLIB_FUNC_FAILED

System Log Message	<i>function-name: event-function-name: reason</i>
Description	A function in the event library used by the mag-service process (jived) failed with the indicated error.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.

JIVED_INITIATE_CONN_FAILED

System Log Message	<i>function-name: aborting, failed to connect to mgd.</i>
Description	The mag-service process (jived) failed to initiate the connection to RE.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

Cause An internal software failure occurred.

JIVED_INIT_FAILED

System Log Message *error-message: reason*

Description The mag-service process (jived) failed to initialize.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

JIVED_NOT_ROOT

System Log Message JIVED must run as root

Description The mag-service process (jived) must be run with root privileges.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause jived being run without root privilege

JIVED_PIDFILE_LOCK_FAILED

System Log Message Unable to lock pid file

Description The mag-service process (jived) failed to lock the file that records its process ID (PID). The lock file is used to prevent multiple instances of the jived process from running simultaneously.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause Another instance of the jived process is already running.

JIVED_PIDFILE_UPDATE_FAILED

System Log Message can not update process PID file: *reason*

Description The mag-service process (jived) failed to update the file that records its process ID (PID). The lock file is used to prevent multiple instances of the jived process from running simultaneously.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON
Cause An internal software failure occurred.

JIVED_SNMP_SEND_TRAP_FAILED

System Log Message *error-message: trap*
Description The mag-service process (jived) failed in the attempt to send an SNMP trap
Type Error: An error occurred
Severity error
Facility LOG_DAEMON

CHAPTER 50

JPTSPD System Log Messages

This chapter describes messages with the **JPTSPD** prefix. They are generated by the packet-triggered subscriber process (jptspd) which creates and manages packet-triggered subscriber interfaces. A packet-triggered subscriber interface is created when the router receives a packet with an IP source address that does not match any entries in the demultiplexer table. When the router detects an unmatched packet, it generates a trigger event that determines whether to create a dynamic subscriber interface or configure an existing interface.

JPTSPD_INIT_FAILURE

System Log Message	JPTSPD failed to initialize
Description	The packet triggered subscriber process (jptspd) initialization failed.
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	One possible cause is that the system is out of memory.
Action	Contact your technical support representative.

JPTSPD_OUT_OF_MEMORY

System Log Message	Out of memory
Description	The packet triggered subscriber process (jptspd) could not dynamically allocate memory.
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	A software bug caused a memory leak, or too many subscriber and service sessions.
Action	Contact your technical support representative.

JPTSPD_PIC_CONNECTED

System Log Message	JPTSPD connected to pic <i>pic-name</i>
Description	The packet triggered subscriber process (jptspd) connected to a PIC.
Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

JPTSPD_PIC_DISCONNECTED

System Log Message	JPTSPD disconnected to pic <i>pic-name reason</i>
Description	The packet triggered subscriber process (jptspd) disconnected to a PIC.
Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

JPTSPD_SRC_FAST_SYNC_ABORT

System Log Message	JPTSPD fast synchronization was aborted <i>partition-name</i>
Description	The packet triggered subscriber process (jptspd) aborted fast synchronization with SRC.
Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY
Cause	One possible cause is that the connection between jptspd and SRC is down.

JPTSPD_SRC_FAST_SYNC_DONE

System Log Message	JPTSPD fast synchronization was done <i>partition-name</i>
Description	The packet triggered subscriber process (jptspd) finished fast synchronization with SRC.
Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

JPTSPD_SRC_FAST_SYNC_START

System Log Message	JPTSPD fast synchronization started <i>partition-name</i>
Description	The packet triggered subscriber process (jptspd) started fast synchronization with SRC.
Type	Event: This message reports an event, not an error

Severity info

Facility ANY

JPTSPD_SRC_FULL_SYNC_ABORT

System Log Message JPTSPD full synchronization was aborted *partition-name*

Description The packet triggered subscriber process (jptspd) aborted full synchronization with SRC.

Type Event: This message reports an event, not an error

Severity info

Facility ANY

Cause One possible cause is that the connection between jptspd and SRC is down.

JPTSPD_SRC_FULL_SYNC_DONE

System Log Message JPTSPD full synchronization was done *partition-name*

Description The packet triggered subscriber process (jptspd) finished full synchronization with SRC.

Type Event: This message reports an event, not an error

Severity info

Facility ANY

JPTSPD_SRC_FULL_SYNC_START

System Log Message JPTSPD full synchronization started *partition-name*

Description The packet triggered subscriber process (jptspd) started full synchronization with SRC.

Type Event: This message reports an event, not an error

Severity info

Facility ANY

CHAPTER 51

JSRPD System Log Messages

This chapter describes messages with the **JSRPD** prefix. They are generated by the Juniper Services Redundancy Protocol (jsrpd) process, which controls chassis clustering.

JSRPD_DAEMONIZE_FAILED

System Log Message	Aborting, unable to run in the background as a daemon: <i>error-message</i>
Description	The Juniper Services Redundancy Protocol process (JSRPD) failed to create a version of itself to run in the background.
Type	Error: An error occurred
Severity	emergency
Facility	LOG_DAEMON

JSRPD_DUPLICATE

System Log Message	Another copy of this program is running
Description	The Juniper Services Redundancy Protocol process (JSRPD) detected that another version of itself is already running.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

JSRPD_NODE_STATE_CHANGE

System Log Message	Node <i>chassis-id</i> state due to <i>reason</i>
Description	The Juniper Services Redundancy Protocol process (JSRPD) detected an event, such as failover, that caused the state of the chassis cluster node to change due to the reason indicated in the log.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON

Cause A link failure occurred and the secondary node is disabled.

Cause The secondary node has recovered from link failure and is being rebooted to recover from the disabled state.

Action Contact your technical support representative.

JSRPD_NOT_ROOT

System Log Message Must be run as root

Description The Juniper Services Redundancy Protocol process (JSRPD) can be instantiated only by the user with root privileges.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

JSRPD_PID_FILE_LOCK

System Log Message Unable to lock PID file: *error-message*

Description The Juniper Services Redundancy Protocol process (JSRPD) failed to lock the PID file, which serves to prevent multiple instances of the process from running simultaneously.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

JSRPD_PID_FILE_UPDATE

System Log Message Unable to update process PID file: *error-message*

Description The Juniper Services Redundancy Protocol process (JSRPD) failed to update the PID file, which serves to prevent multiple instances of the process from running simultaneously.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

JSRPD_REDUNDANCY_MODE_CHANGE

System Log Message Redundancy mode change will not be effective until all nodes in the cluster are rebooted simultaneously

Description The Juniper Services Redundancy Protocol process (JSRPD) detected a change in chassis cluster redundancy mode. The new mode is not effective until all nodes in the cluster are rebooted.

Type Error: An error occurred
Severity warning
Facility LOG_DAEMON

JSRPD_REDUNDANCY_MODE_MISMATCH

System Log Message Change in HA redundancy mode detected..please reboot all nodes in the cluster simultaneously!!

Description The Juniper Services Redundancy Protocol process (JSRPD) detected a change in the chassis cluster redundancy mode configuration and detected that only some (not all) of the nodes rebooted. The new mode is not effective until all nodes in the cluster are rebooted.

Type Error: An error occurred
Severity warning
Facility LOG_DAEMON

JSRPD_RG_STATE_CHANGE

System Log Message Redundancy-group *rg-id* transitioned from '*old-state*' to '*new-state*' state due to *reason*

Description The Juniper Services Redundancy Protocol process (JSRPD) detected an event that caused the state of the chassis cluster redundancy group to change due to the reason indicated in the log.

Type Event: This message reports an event, not an error
Severity alert
Facility LOG_DAEMON

JSRPD_SET_CS_MON_FAILURE

System Log Message Cold-sync Monitor failed for redundancy-group *rg-id*

Description The Juniper Services Redundancy Protocol process (JSRPD) detected cold-sync monitoring failure for a redundancy group.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

JSRPD_SET_INTF_MON_FAILURE

System Log Message Interface Monitor failed for redundancy-group *rg-id*

Description The Juniper Services Redundancy Protocol process (JSRPD) detected interface monitoring failure for a redundancy group.

Type Error: An error occurred

Severity error
Facility LOG_DAEMON

JSRPD_SET_IP_MON_FAILURE

System Log Message IP Monitor failed for redundancy-group *rg-id*

Description The Juniper Services Redundancy Protocol process (JSRPD) detected IP address monitoring failure for a redundancy group.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

JSRPD_SET_NPC_MON_FAILURE

System Log Message NPC Monitor failed for redundancy-group *rg-id*

Description The Juniper Services Redundancy Protocol process (JSRPD) detected Network Processing Card (NPC) monitoring failure for a redundancy group.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

JSRPD_SET_OTHER_INTF_MON_FAIL

System Log Message Interface Monitor failed on other node for redundancy-group *rg-id*

Description The Juniper Services Redundancy Protocol process (JSRPD) detected interface monitoring failure on the other node for a redundancy group.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

JSRPD_SET_SPU_MON_FAILURE

System Log Message SPU Monitor failed for redundancy-group *rg-id*

Description The Juniper Services Redundancy Protocol process (JSRPD) detected Services Processing Unit (SPU) monitoring failure for a redundancy group.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

JSRPD_SOCKET_CREATION_FAILURE

System Log Message Socket creation (server) failed unexpectedly *error-message*.

Description The Juniper Services Redundancy Protocol process (JSRPD) failed to create a socket.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

JSRPD_SOCKET_LISTEN_FAILURE

System Log Message Socket listen (server) failed unexpectedly. *error-message*

Description The Juniper Services Redundancy Protocol process (JSRPD) failed to listen on a socket.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

JSRPD_SOCKET_RECV_HB_FAILURE

System Log Message Socket reception of heartbeat from failed unexpectedly *error-message*.

Description The Juniper Services Redundancy Protocol process (JSRPD) failed to receive heartbeat.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

JSRPD_UNSET_CS_MON_FAILURE

System Log Message Cold-sync Monitor failure recovered for redundancy-group *rg-id*

Description The Juniper Services Redundancy Protocol process (JSRPD) detected that the previous cold-sync monitoring failure no longer exists for a redundancy group.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

JSRPD_UNSET_INTF_MON_FAILURE

System Log Message Interface Monitor failure recovered for redundancy-group *rg-id*

Description The Juniper Services Redundancy Protocol process (JSRPD) detected that the previous interface monitoring failure no longer exists for a redundancy group.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

JSRPD_UNSET_IP_MON_FAILURE

System Log Message	IP Monitor failure recovered for redundancy-group <i>rg-id</i>
Description	The Juniper Services Redundancy Protocol process (JSRPD) detected that the previous IP address monitoring failure no longer exists for a redundancy group.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

JSRPD_UNSET_NPC_MON_FAILURE

System Log Message	NPC Monitor failure recovered for redundancy-group <i>rg-id</i>
Description	The Juniper Services Redundancy Protocol process (JSRPD) detected that the previous Network Processing Card (NPC) monitoring failure no longer exists for a redundancy group.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

JSRPD_UNSET_OTHER_INTF_MON_FAIL

System Log Message	Interface Monitor failure recovered on other node for redundancy-group <i>rg-id</i>
Description	The Juniper Services Redundancy Protocol process (JSRPD)\ detected that the previous interface monitoring failure on the other node no longer exists for a redundancy group.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

JSRPD_UNSET_SPU_MON_FAILURE

System Log Message	SPU Monitor failure recovered for redundancy-group <i>rg-id</i>
Description	The Juniper Services Redundancy Protocol process (JSRPD) detected that the previous Services Processing Unit (SPU) monitoring failure no longer exists for a redundancy group.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

JSRPD_USAGE

System Log Message	Usage: jsrpd [-C] [-N] [-X] [-d debug-level] [-l] [-v]
---------------------------	--

Description The Juniper Services Redundancy Protocol process (JSRPD) was invoked with incorrect options.

Type Event: This message reports an event, not an error

Severity error

Facility LOG_DAEMON

CHAPTER 52

KMD System Log Messages

This chapter describes messages with the **KMD** prefix. They are generated by the key management process (kmd), which provides IP Security (IPSec) authentication services for encryption PICs.

KMD_CFG_IF_ID_POOL_NOT_FOUND

System Log Message	Unable to allocate logical interface for IPSec interface from pool <i>pool-name</i> : pool not found
Description	The key management process (kmd) maintains pools of logical interfaces for assignment to IP Security (IPSec) interfaces. It could not allocate a logical interface, because it could not access the indicated pool.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

KMD_CFG_IF_ID_POOL_NO_ENTRY

System Log Message	Unable to return logical interface <i>interface-name.interface-unit</i> to pool <i>pool-name</i> : no entry in pool for interface
Description	The key management process (kmd) maintains pools of logical interfaces for assignment to IP Security (IPSec) interfaces. It could not return the indicated logical interface to the indicated pool, because there was no entry for the interface in the pool.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

KMD_CFG_IF_ID_POOL_NO_INTERFACE

System Log Message	Unable to allocate logical interface for IPSec interface from pool <i>pool-name</i> : no interfaces available
Description	The key management process (kmd) maintains pools of logical interfaces for assignment to IP Security (IPSec) interfaces. It could not allocate a logical interface, because none were available in the indicated pool.

Type Error: An error occurred
Severity error
Facility LOG_AUTH

KMD_CFG_IF_ID_POOL_RETURN_FAILED

System Log Message Unable to return logical interface to pool *pool-name*: pool not found

Description The key management process (kmd) maintains pools of logical interfaces for assignment to IP Security (IPSec) interfaces. It could not return a logical interface to the indicated pool, because it could not access the pool.

Type Error: An error occurred
Severity error
Facility LOG_AUTH

KMD_DPD_FAILOVER_MANUAL_TUNNEL

System Log Message Tunnel *tunnel-name* did not fail over: it is manual type

Description An IP Security (IPSec) tunnel normally fails over to its backup when the key management process (kmd) detects a dead peer. Failover was not attempted for the indicated tunnel, which is configured as a manual type and so does not support failover.

Type Error: An error occurred
Severity error
Facility LOG_AUTH

KMD_DPD_FAILOVER_MAX_ATTEMPTS

System Log Message Number of failover attempts exceeded limit *count* for tunnel *tunnel-name*

Description An IP Security (IPSec) tunnel fails over to its backup when the key management process (kmd) detects a dead peer. The key management process (kmd) stopped making failover attempts for the indicated tunnel, because the number of attempts exceeded the indicated limit configured for Internet Key Exchange (IKE) Phase 1 negotiations.

Type Error: An error occurred
Severity error
Facility LOG_AUTH

Cause Failover attempts can fail repeatedly if both the primary and backup peers are unreachable during the failover.

KMD_DPD_FAILOVER_NO_ACTIVE_PEER

System Log Message Tunnel *tunnel-name* did not fail over: no active peer configured

Description An IP Security (IPSec) tunnel normally fails over to its backup when the key management process (kmd) detects a dead peer. Failover was not attempted because the configuration for the indicated tunnel does not include information about an active peer.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_DPD_FAILOVER_NO_BACKUP_PEER

System Log Message Tunnel *tunnel-name* did not fail over: no backup peer configured

Description An IP Security (IPSec) tunnel normally fails over to its backup when the key management process (kmd) detects a dead peer. A failover attempt failed when the kmd process found that the configuration for the indicated tunnel does not include information about a backup peer.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_DPD_FAILOVER_NO_TUNNEL_CFG

System Log Message Tunnel did not fail over: tunnel configuration not found

Description An IP Security (IPSec) tunnel normally fails over to its backup when the key management process (kmd) detects a dead peer. Failover was not attempted because there was no configuration information for the tunnel.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_DPD_IKE_SERVER_NOT_FOUND

System Log Message Unable to send DPD reply to remote peer *remote-address:remote-port*: no IKE server instance for local peer *local-address:local-port*

Description The key management process (kmd) could not retrieve the Internet Key Exchange (IKE) server instance referenced by the indicated local peer (address and port), so it could not reply to the indicated remote peer (address and port) from the local peer.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_DPD_INVALID_ADDRESS

System Log Message Unable to send DPD reply: local peer *local-address*; remote peer *remote-address*

Description One of the indicated peer addresses (local or remote) was invalid, so the key management process (kmd) could not send a dead peer detection (DPD) reply to the remote peer.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_DPD_INVALID_SEQUENCE_NUMBER

System Log Message Unable to send DPD reply: remote peer *remote-address:remote-port* provided invalid zero sequence number to local peer *local-address:local-port*

Description The indicated remote peer (address and port) provided a zero sequence number, which is invalid, to the indicated local peer (address and port). As a result, the key management process (kmd) could not send a dead peer detection (DPD) reply to the remote peer.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_DPD_NO_LOCAL_ADDRESS

System Log Message Unable to send DPD hello message from local peer *local-address/local-port*: address not found in instance *service-set*

Description The indicated service set did not include an entry for the indicated local peer (address and port), so the key management process (kmd) could not send a dead peer detection (DPD) hello message from that peer.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_DPD_REMOTE_ADDRESS_CHANGED

System Log Message Remote peer address for tunnel *tunnel-name* changed from *old-address* to *new-address*

Description The remote peer address in the configuration for the indicated tunnel changed to a new value as indicated.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_AUTH

KMD_DPD_REMOTE_PEER_NOT_FOUND

System Log Message Unable to send DPD reply: DPD entry for remote peer *remote-address:remote-port* not found in IKE server instance *service-set*

Description The Internet Key Exchange (IKE) server instance for the indicated service set did not include an entry for the indicated remote peer (address and port), so the key management process (kmd) could not send a dead peer detection (DPD) reply.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_DPD_UNEXPECTED_IKE_STATUS

System Log Message DPD reply to remote peer *remote-address:remote-port* failed with unexpected status *status* for IKE server instance *ike-instance*

Description A dead peer detection (DPD) reply sent to the indicated remote peer (address and port) failed and returned the indicated Internet Key Exchange (IKE) status code for the indicated IKE instance.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_PM_AUTH_ALGORITHM_INVALID

System Log Message Invalid authentication algorithm *auth-algorithm-id* negotiated in transform *transform-id* for use by *protocol-name* in tunnel *tunnel-name*

Description During Internet Key Exchange (IKE) Phase 2 negotiation of the indicated transform, the indicated authentication algorithm was chosen to be used by the indicated protocol (Authentication Header [AH] or Encapsulating Security Payload [ESP]) for the indicated tunnel. The algorithm is not a valid value, so the associated security association (SA) was not established.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_PM_DUPLICATE_LIFE_DURATION

System Log Message Duplicate SA life duration value given in Quick Mode notification from *remote-address:remote-port*

Description The IKE Quick Mode notification message from the indicated remote gateway and remote port contains duplicate value for life duration. Hence Quick Mode notification payload is dropped.

Type Error: An error occurred

Severity error

Facility LOG_SYSLOG

KMD_PM_DYNAMIC_SA_INSTALL_FAILED

System Log Message	Unable to install dynamic SA for tunnel <i>tunnel-name</i>
Description	Installation of a dynamic security association (SA) failed for the indicated tunnel during Internet Key Exchange (IKE) Phase 2.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

KMD_PM_ENCRYPTION_INVALID

System Log Message	Invalid encryption algorithm negotiated in transform <i>transform-id</i> for use by ESP in tunnel <i>tunnel-name</i>
Description	During Internet Key Exchange (IKE) Phase 2 negotiation of the indicated transform, an encryption algorithm was chosen to be used by the Encapsulating Security Payload (ESP) protocol for the indicated tunnel. The algorithm is not a valid value, so the associated security association (SA) was not installed to the data path.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

KMD_PM_IKE_SERVER_LOOKUP_FAILED

System Log Message	No IKE server to connect Phase-1 to <i>remote-peer</i>
Description	The IKE Phase-1 negotiation with indicated remote gateway address failed because there is no corresponding IKE server running locally.
Type	Error: An error occurred
Severity	error
Facility	LOG_SYSLOG

KMD_PM_IKE_SERVER_NOT_FOUND

System Log Message	Failed to connect to <i>remote-address:remote-port</i> as there is no IKE server context available in instance <i>service-set</i>
Description	There is no local IKE server context in the indicated service set, hence failed to send the SPI delete notification request.
Type	Error: An error occurred
Severity	error
Facility	LOG_SYSLOG

KMD_PM_IKE_SRV_NOT_FOUND_CREATE

System Log Message	Local peer <i>local-address:local-port</i> could not inform remote peer <i>remote-address:remote-port</i> of SA creation failure: IKE server not found
Description	The key management process (kmd) could not connect to the indicated remote peer (address and port), because it could not locate a Internet Key Exchange (IKE) server for the indicated local peer (address and port). As a result, it could not notify the remote peer that a security association (SA) was not created.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

KMD_PM_IKE_SRV_NOT_FOUND_DELETE

System Log Message	Unable to notify remote peer <i>remote-address:remote-port</i> that SPI was deleted: no IKE server for service set <i>service-set</i>
Description	The indicated service set did not have a local Internet Key Exchange (IKE) server context for the indicated remote peer (address and port). As a result, notification about deletion of a security parameter index (SPI) was not sent.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

KMD_PM_ILLEGAL_REMOTE_GW_ID

System Log Message	Aborting Phase-1 negotiation. Cannot initiate negotiation with invalid Phase-1 remote <i>remote-peer</i> in instance: <i>service-set</i>
Description	The specified remote gateway identity is neither an IPv4 address nor an IPv6 address. Hence Phase-1 negotiation can not be started
Type	Error: An error occurred
Severity	error
Facility	LOG_SYSLOG

KMD_PM_INCONSISTENT_P2_IDS

System Log Message	Inconsistent phase-2 (IPsec) identities, local : initiator = <i>local-initiator</i> responder = <i>local-responder</i> remote : initiator = <i>remote-initiator</i> responder = <i>remote-responder</i>
Description	Initiator and responder identities at the local end are inconsistent with the remote peer's identities. Quick Mode negotiation is aborted.
Type	Error: An error occurred
Severity	error

Facility LOG_SYSLOG

KMD_PM_INVALID_LIFE_TYPE

System Log Message Invalid life type *units-type* found in the Quick Mode notification from *remote-address:remote-port*

Description The IKE Quick Mode notification message from the indicated remote gateway and remote port contains invalid life type. Second and Kilobytes are the only supported life types currently. Hence Quick Mode notification payload is dropped.

Type Error: An error occurred

Severity error

Facility LOG_SYSLOG

KMD_PM_KEY_NOT_SUPPORTED

System Log Message Key type *type* not supported

Description The key management process (kmd) retrieved a key of the indicated type during Internet Key Exchange (IKE) Phase 1. The key type is not one of the supported types, which are public/private and preshared.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_PM_LIFETIME_DUPLICATE

System Log Message Phase 2 lifetime notification message from remote peer *remote-address:remote-port* specified duplicate duration

Description During Internet Key Exchange (IKE) Phase 2 negotiation, the indicated remote peer (address and port) sent a lifetime notification message that specified a duplicate value for the security association (SA) lifetime duration. As a result, the key management process (kmd) discarded the notification message.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_PM_LIFETIME_LENGTH_UNEQUAL

System Log Message Phase 2 lifetime notification message from remote peer *remote-address:remote-port* had unequal payload length

Description During Internet Key Exchange (IKE) Phase 2 negotiation, the indicated remote peer (address and port) sent a lifetime notification message with an unequal payload length. As a result, the key management process (kmd) discarded the notification message.

Type Error: An error occurred
Severity error
Facility LOG_AUTH

KMD_PM_LIFETIME_NO_DURATION

System Log Message Phase 2 lifetime notification message from remote peer *remote-address:remote-port* did not define duration

Description During Internet Key Exchange (IKE) Phase 2 negotiation, the indicated remote peer (address and port) sent a lifetime notification message that did not specify a duration for the security association (SA) lifetime. As a result, the key management process (kmd) discarded the notification message.

Type Error: An error occurred
Severity error
Facility LOG_AUTH

KMD_PM_LIFETIME_TYPE_UNDEFINED

System Log Message Phase 2 lifetime notification message from remote peer *remote-address:remote-port* did not specify life type

Description During Internet Key Exchange (IKE) Phase 2 negotiation, the indicated remote peer (address and port) sent a lifetime notification message that did not specify a life type, making it impossible to determine the lifetime duration for the corresponding security association (SA). As a result, the key management process (kmd) discarded the notification message.

Type Error: An error occurred
Severity error
Facility LOG_AUTH

KMD_PM_LIFETIME_UNITS_INVALID

System Log Message Phase 2 lifetime notification message from remote peer *remote-address:remote-port* specified invalid units type *units-type*

Description During Internet Key Exchange (IKE) Phase 2 negotiation, the indicated remote peer (address and port) sent a lifetime notification message that specified the indicated type of units for the security association (SA) lifetime. The type is invalid (the acceptable units are seconds and kilobytes). As a result, the key management process (kmd) discarded the notification message.

Type Error: An error occurred
Severity error
Facility LOG_AUTH

KMD_PM_NEW_GROUP_UNSUPPORTED

System Log Message	New Group mode not supported
Description	Internet Key Exchange (IKE) New Group mode is not supported, so an attempt to start New Group negotiation failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

KMD_PM_NO_LIFETIME

System Log Message	Duplicate life time payloads present in the notification from <i>remote-address:remote-port</i> . Dropping the notification.
Description	The IKE Quick Mode notification message from the indicated remote gateway and remote port contains two life type fields and there is no life duration field. Quick Mode notification is being dropped since it has insufficient information about life duration.
Type	Error: An error occurred
Severity	error
Facility	LOG_SYSLOG

KMD_PM_NO_LIFE_TYPE

System Log Message	Quick mode notification from <i>remote-address:remote-port</i> contains lifetime duration without corresponding SA lifetime payload.
Description	The IKE Quick Mode notification message from the indicated remote gateway and remote port does not contain life type, hence existing life duration cannot be interpreted to be of a particular life type. Quick Mode notification payload is dropped.
Type	Error: An error occurred
Severity	error
Facility	LOG_SYSLOG

KMD_PM_NO_PROPOSAL_FOR_PHASE1

System Log Message	Aborting Phase-1negotiation. No proposal found to initiate negotiation between local: <i>local-peer</i> and remote <i>remote-peer</i> in instance: <i>service-set</i>
Description	It is not possible to start the Phase-1 negotiation to the indicated remote gateway because there is no proposal present.
Type	Error: An error occurred
Severity	error
Facility	LOG_SYSLOG

KMD_PM_NO_SPD_PHASE1_FUNC_PTR

System Log Message	Phase-1 SPD handler is not registered in instance: <i>service-set</i>
Description	Phase-1 negotiation can not be initiated as initialization function failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_SYSLOG

KMD_PM_P1_POLICY_LOOKUP_FAILURE

System Log Message	Policy lookup for Phase-1 [<i>negotiation-role</i>] failed for p1_local= <i>local-peer</i> p1_remote= <i>remote-peer</i>
Description	The IKE Phase-1 negotiation with the indicated remote gateway address failed because there is no IKE policy configured for use against the indicated remote gateway.
Type	Error: An error occurred
Severity	error
Facility	LOG_SYSLOG

KMD_PM_P2_POLICY_LOOKUP_FAILURE

System Log Message	Policy lookup for Phase-2 [<i>negotiation-role</i>] failed for p1_local= <i>local-peer</i> p1_remote= <i>remote-peer</i> p2_local= <i>local-prefix</i> p2_remote= <i>remote-prefix</i>
Description	The IKE Phase-2 negotiation with the indicated remote gateway address failed because the traffic selectors proposed by the remote gateway address do not match any of the policies configured for the indicated local gateway address. The proposed traffic selectors are indicated by the Phase-2 local and remote IP prefixes.
Type	Error: An error occurred
Severity	error
Facility	LOG_SYSLOG

KMD_PM_PHASE1_GROUP_UNREADABLE

System Log Message	Unable to read group attributes from IKE Phase 1 proposal
Description	The key management process (kmd) could not read the information in an Internet Key Exchange (IKE) Phase 1 proposal about the Diffie-Hellman (DH) group to use.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

KMD_PM_PHASE1_GROUP_UNSPECIFIED

System Log Message	Used DH group 1 because Phase 1 proposal did not specify group
Description	The key management process (kmd) assigned Diffie-Hellman (DH) group 1 to an Internet Key Exchange (IKE) Phase 1 proposal because no group was specified.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_AUTH

KMD_PM_PHASE1_IKE_SRV_NOT_FOUND

System Log Message	Unable to perform Phase 1 negotiation with remote peer <i>remote-peer</i> : no local IKE server
Description	The key management process (kmd) could not locate an Internet Key Exchange (IKE) server for the local peer. As a result, IKE Phase 1 negotiation failed with the indicated remote peer.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

KMD_PM_PHASE1_NO_IDENTITYIES

System Log Message	Unable to begin Phase 1 negotiation for local peer <i>service-set</i> and remote peer <i>local-peer</i> in instance <i>remote-peer</i>
Description	Internet Key Exchange (IKE) Phase 1 negotiation did not begin, because either the local peer or remote peer was undefined for the indicated service set.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

KMD_PM_PHASE1_NO_SPD_HANDLER

System Log Message	No Phase 1 SPD handler registered for service set <i>service-set</i>
Description	A security policy database (SPD) handler is not registered for the indicated service set. As a result, Internet Key Exchange (IKE) Phase 1 negotiation did not begin.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

KMD_PM_PHASE1_POLICY_LOOKUP_FAIL

System Log Message	Unable to retrieve Phase 1 policy from <i>negotiation-role</i> (local peer <i>local-peer</i> , remote peer <i>remote-peer</i>)
Description	The key management process (kmd) could not retrieve a policy from the indicated participant to use during Internet Key Exchange (IKE) Phase 1 negotiation between the indicated local and remote peers.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

KMD_PM_PHASE1_POLICY_NOT_FOUND

System Log Message	Unable to find policy for Phase 1 negotiation between local peer <i>local-peer</i> and remote peer <i>remote-peer</i> in service set <i>service-set</i>
Description	The key management process (kmd) could not retrieve a policy for Internet Key Exchange (IKE) Phase 1 negotiation between the indicated local and remote peers in the indicated service set. As a result, Phase 1 did not begin.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

KMD_PM_PHASE1_POLICY_SEARCH_FAIL

System Log Message	No ike-policy found for ike-access-profile: <i>access-profile</i> , instance: <i>service-set</i>
Description	The key management process (kmd) could not retrieve the Phase 1 policy referenced by the indicated Internet Key Exchange (IKE) access profile for the indicated dynamic-endpoint service set.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

KMD_PM_PHASE1_PROTO_INVALID

System Log Message	Phase 1 transform specified invalid protocol <i>received-value</i> instead of SSH_IKE_PROTOCOL_ISAKMP (<i>expected-value</i>)
Description	The indicated protocol in a transform negotiated during Internet Key Exchange (IKE) Phase 1 is not a valid value. The only valid value is the Internet Security Association and Key Management Protocol (ISAKMP). The key management process (kmd) rejected the transform.
Type	Error: An error occurred

Severity error
Facility LOG_AUTH

KMD_PM_PHASE1_PROTO_NOT_ISAKMP

System Log Message Protocol in IKE Phase 1 proposal was not ISAKMP as expected

Description The protocol in an Internet Key Exchange (IKE) Phase 1 proposal was not the expected value, which is the Internet Security Association and Key Management Protocol (ISAKMP).

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_PM_PHASE1_PROTO_TWICE

System Log Message Phase 1 transform included protocol *protocol-id* twice

Description A transform negotiated during Internet Key Exchange (IKE) Phase 1 specified the indicated protocol twice, which is invalid. The key management process (kmd) rejected the transform.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_PM_PHASE1_TXFORM_INCOMPLETE

System Log Message Phase 1 transform was missing mandatory attributes

Description A transform negotiated during Internet Key Exchange (IKE) Phase 1 did not include values for all attributes. One or more the following was missing: the authentication algorithm, encryption algorithm, or Diffie-Hellman group. The key management process (kmd) rejected the transform.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_PM_PHASE1_TXFORM_INVALID

System Log Message Phase 1 transform specified invalid transform ID *received-value* instead of *expected-value*

Description The indicated identifier for a transform negotiated during Internet Key Exchange (IKE) Phase 1 is not the indicated expected value. The key management process (kmd) rejected the transform.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_PM_PHASE2_IDENTITY_MISMATCH

System Log Message Phase 2 identities did not match: local initiator *local-initiator*, responder *local-responder*; remote initiator *remote-initiator*, responder *remote-responder*

Description The indicated initiator and responder identities defined by the local peer did not match the indicated identities defined by the remote peer. The key management process (kmd) canceled Internet Key Exchange (IKE) Phase 2 negotiation.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_PM_PHASE2_NOTIF_UNKNOWN

System Log Message Unknown Phase 2 notification *notification-name* (type *notification-type*, size *length* bytes) from *remote-address:remote-port* for protocol *protocol-id* (SPI(*size*)=*data*)

Description The indicated Internet Key Exchange (IKE) Phase 2 notification message from the indicated remote peer (address and port) is a type that the key management process (kmd) does not support. As a result, the kmd process discarded the message and Phase 2 negotiation failed.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_PM_PHASE2_POLICY_LOOKUP_FAIL

System Log Message Unable to retrieve policy for Phase 2 from *negotiation-role* (Phase 1 local peer *local-peer*, remote peer *remote-peer*; Phase 2 local peer *local-prefix*, remote peer *remote-prefix*)

Description The key management process (kmd) could not retrieve a policy from the indicated participant to use during Internet Key Exchange (IKE) Phase 2 negotiation for the indicated local and remote peers. The traffic selectors proposed by the remote peer (represented by the indicated Phase 2 IP prefixes) do not match any local peer policies.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_PM_PHASE2_SELECTOR_UNDEFINED

System Log Message Unable to start Phase 2: No traffic-selector addresses defined for SA *sa-name*

Description The configuration for the indicated security association (SA) did not include the information about local and remote traffic selectors required for Internet Key Exchange (IKE) Phase 2, so that phase did not begin.

Type Error: An error occurred
Severity error
Facility LOG_AUTH

KMD_PM_PROPOSAL_NO_AUTH

System Log Message AH proposal did not define authentication algorithm

Description An Internet Key Exchange (IKE) Phase 2 proposal did not define the authentication algorithm for the Authentication Header (AH) protocol to use. The key management process (kmd) rejected the proposal.

Type Error: An error occurred
Severity error
Facility LOG_AUTH

KMD_PM_PROPOSAL_NO_ENCRYPTION

System Log Message ESP proposal did not define encryption algorithm

Description An Internet Key Exchange (IKE) Phase 2 proposal did not define the encryption algorithm for the Encapsulating Security Payload (ESP) protocol to use. The key management process (kmd) rejected the proposal.

Type Error: An error occurred
Severity error
Facility LOG_AUTH

KMD_PM_PROPOSAL_NO_KEY_LENGTH

System Log Message Phase 2 proposal did not specify length for variable key-length cipher *cipher*

Description An Internet Key Exchange (IKE) Phase 2 proposal did not define the key length for the indicated variable-length cipher. As a result, the key management process (kmd) rejected the proposal.

Type Error: An error occurred
Severity error
Facility LOG_AUTH

KMD_PM_PROPOSAL_NULL_ESP

System Log Message ESP was negotiated with null encryption and authentication

Description Encapsulating Security Payload (ESP) was negotiated as the protocol During Internet Key Exchange (IKE) Phase 2, but no values were negotiated for the authentication and encryption algorithms. As a result, the key management process (kmd) rejected the transform.

Type Error: An error occurred
Severity error
Facility LOG_AUTH

KMD_PM_PROPOSAL_PROTOCOL_INVALID

System Log Message Protocol *protocol-id* in Phase 2 proposal was invalid (was not AH or ESP)

Description An Internet Key Exchange (IKE) Phase 2 proposal specified the indicated protocol, which is invalid. The acceptable protocols are Authentication Header (AH) and Encapsulating Security Payload (ESP). The key management process (kmd) rejected the proposal.

Type Error: An error occurred
Severity error
Facility LOG_AUTH

KMD_PM_PROTO_INVALID

System Log Message Invalid protocol *protocol-id* was negotiated for SA *sa-name*

Description During Internet Key Exchange (IKE) Phase 2, the indicated protocol was chosen for the indicated security association (SA). It is not a valid value, so the SA was not established.

Type Error: An error occurred
Severity error
Facility LOG_AUTH

KMD_PM_PROTO_IPCOMP_UNSUPPORTED

System Log Message Unsupported IPComp protocol was negotiated for SA *sa-name*

Description During Internet Key Exchange (IKE) Phase 2, the IP Payload Compression Protocol (IPComp) was chosen for the indicated security association (SA). IPComp is not supported, so the SA was not established.

Type Error: An error occurred
Severity error
Facility LOG_AUTH

KMD_PM_PROTO_ISAKMP_RESV_UNSUPP

System Log Message Unsupported protocol ISAKMP or RESERVED was negotiated for SA *sa-name*

Description During Internet Key Exchange (IKE) Phase 2, either Internet Security Association and Key Management Protocol (ISAKMP) or the value RESERVED was chosen as the protocol for the indicated security association (SA). They are not supported values, so the SA was not established.

Type Error: An error occurred

Severity error
Facility LOG_AUTH

KMD_PM_PROTO_NOT_NEGOTIATED

System Log Message No protocol negotiated for SA *sa-name*

Description While verifying the results of Internet Key Exchange (IKE) Phase 2, the key management process (kmd) determined that no protocol was negotiated for the indicated security association (SA). The SA was not established.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_PM_REMOTE_PEER_INVALID

System Log Message Phase 1 negotiation failed: remote address *remote-peer* in instance *service-set* is invalid

Description Internet Key Exchange (IKE) Phase 1 negotiation failed because the indicated remote peer address in the indicated service set is not a valid IP version 4 (IPv4) or IP version 6 (IPv6) address.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_PM_SA_CFG_NOT_FOUND

System Log Message Unable to install negotiated Phase 2 values: SA *sa-name* configuration not found

Description The key management process (kmd) could not retrieve configuration information for the indicated security association (SA), and so could not record the values that were negotiated for the SA during Internet Key Exchange (IKE) Phase 2. The SA was not established.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_PM_SA_DELETE_REJECT

System Log Message Rejected SA deletion request for service set *service-set*: SPI size (*size*) is not 4 (local peer *local-address:local-port*, remote peer *remote-address:remote-port*)

Description The key management process (kmd) discarded a message that requested deletion of a security association (SA) between the indicated local peer (address and port) and remote peer (address and port), because the indicated size of the associated Security Parameter Index (SPI) was not as expected. As a result, the SA was not deleted.

Type Error: An error occurred
Severity error
Facility LOG_AUTH

KMD_PM_SA_INDEX_GEN_FAILED

System Log Message Unable to generate pair index for SA *sa-name* in service set *service-set*

Description The key management process (kmd) could not generate a pair index for the indicated security association (SA) in the indicated service set. The kmd process canceled Internet Key Exchange (IKE) Phase 2 negotiation.

Type Error: An error occurred
Severity error
Facility LOG_AUTH

KMD_PM_SA_PEER_ABSENT

System Log Message No active peer found in tunnel configuration block *sa-name*

Description Failed to find active peer information in the tunnel configuration block. Hence unable to send SA delete notifications to the peer.

Type Error: An error occurred
Severity error
Facility LOG_SYSLOG

KMD_PM_SA_PEER_NOT_FOUND

System Log Message Unable to find active peer for SA *sa-name*

Description The key management process (kmd) could not retrieve information about an active peer from the configuration for the indicated security association (SA). As a result, it could not notify peers that an SA was deleted.

Type Error: An error occurred
Severity error
Facility LOG_AUTH

KMD_PM_SPI_DELETE_REJECT

System Log Message IKE Phase-2 delete:In instance *service-set* rejecting request to delete SPI size *sizeu* != 4 Local gateway *local-address:local-port*, Remote gateway *remote-address:remote-port*

Description The SPI size in the delete notification is invalid. Hence delete request is rejected. Quick Mode notification payload is dropped.

Type Error: An error occurred
Severity error

Facility LOG_SYSLOG

KMD_PM_UNEQUAL_PAYLOAD_LENGTH

System Log Message Inconsistent payload lengths in Quick Mode responder life time notification from *remote-address:remote-port*

Description IKE Quick Mode notification is dropped because of unequal payload length received in the message.

Type Error: An error occurred

Severity error

Facility LOG_SYSLOG

KMD_PM_UNINITIALISE_ERROR

System Log Message Invalid policy manager handle to uninitialized *service-set*

Description Failed to uninitialized the Policy manager object while deleting the indicated service set.

Type Error: An error occurred

Severity error

Facility LOG_SYSLOG

KMD_PM_UNINITIALIZE_FAILED

System Log Message Unable to uninitialized service set *service-set*: invalid policy manager handle

Description The key management process could not delete the indicated service set, because lack of a valid handle prevented the kmd process from uninitialized the policy manager object for the service set.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_PM_UNKNOWN_P1_IDENTITIES

System Log Message Failed to initiate the Phase-1 negotiation for local:*local-peer* and remote:*remote-peer* in instance:*service-set*

Description Phase-1 negotiation can not be started because either the local gateway identity or the remote gateway identity is unknown.

Type Error: An error occurred

Severity error

Facility LOG_SYSLOG

KMD_PM_UNKNOWN_PHASE2_ENTITIES

System Log Message	No Phase-2 entities present in tunnel configuration block <i>sa-name</i>
Description	Unable to initiate Phase-2 negotiation because of unknown local and remote traffic selectors in the indicated security association configuration block. For Adaptive Service PIC, the security association configuratin block refers to the tunnel configured under a service set with a given rule name and term name.
Type	Error: An error occurred
Severity	error
Facility	LOG_SYSLOG

KMD_PM_UNKNOWN_QM_NOTIFICATION

System Log Message	Unknown Quick mode notification <i>notification-name (notification-type) (size length)bytes</i> from <i>remote-address:remote-port</i> for protocol= <i>protocol-idd spi(sizeu)=data</i>
Description	The notification message sent by the indicated remote gateway and remote port is not recognized. Hence Quick Mode notification payload is dropped.
Type	Error: An error occurred
Severity	error
Facility	LOG_SYSLOG

KMD_PM_UNSUPPORTED_KEY

System Log Message	Key type = <i>type</i> , not supported
Description	The specified key type is unsupported. Public/Private and Pre-shared key are the only types supported presently.
Type	Error: An error occurred
Severity	error
Facility	LOG_SYSLOG

KMD_PM_UNSUPPORTED_MODE

System Log Message	New group mode not supported currently
Description	The IKE New Group mode negotiations failed, because this is not a supported feature currently.
Type	Error: An error occurred
Severity	error
Facility	LOG_SYSLOG

KMD_SNMP_EXTRA_RESPONSE

System Log Message	PIC <i>pic-slot</i> sent additional response after reply to SNMP query: <i>error-message</i>
Description	The indicated PIC sent an additional unexpected message after it responded to a request from the key management process (kmd) for Simple Network Management Protocol (SNMP) statistics about IP Security (IPSec) security associations (SAs). As a result, the kmd process discarded the initial response.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

KMD_SNMP_FATAL_ERROR

System Log Message	Fatal SNMP error occurred: <i>error-message</i>
Description	The key management process (kmd) could not retrieve Simple Network Management Protocol (SNMP) statistics about IP Security (IPSec) security associations (SAs), because the indicated fatal SNMP error occurred.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

KMD_SNMP_IKE_SERVER_NOT_FOUND

System Log Message	Unable to fulfill SNMP request: could not fetch IKE server context for service set <i>service-set</i>
Description	The key management process (kmd) could not retrieve the Internet Key Exchange (IKE) server context for the indicated service set. As a result, it could not process a request for Simple Network Management Protocol (SNMP) statistics.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

KMD_SNMP_MALLOC_FAILED

System Log Message	Unable to allocate memory for reply buffer; SNMP query to PIC <i>pic-slot</i> failed
Description	The key management process (kmd) could not allocate memory for the buffer it uses to store Simple Network Management Protocol (SNMP) statistics about IP Security (IPSec) security associations (SAs). As a result, it could not retrieve statistics from the indicated PIC.
Type	Error: An error occurred
Severity	error

Facility LOG_AUTH

KMD_SNMP_PIC_CONNECTION_FAILED

System Log Message Unable to connect to PIC *pic-slot*; SNMP query failed

Description The key management process (kmd) could not open a connection to the indicated PIC. As a result, it could not retrieve Simple Network Management Protocol (SNMP) statistics about IP Security (IPSec) security associations (SAs).

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_SNMP_PIC_NO_RESPONSE

System Log Message PIC *pic-slot* did not respond to SNMP query: *error-message*

Description The indicated PIC did not respond to a request from the key management process (kmd) for Simple Network Management Protocol (SNMP) statistics about IP Security (IPSec) security associations (SAs).

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_SNMP_PIC_SLOT_NOT_FOUND

System Log Message Unable to retrieve slot information for PIC *pic-slot*; SNMP query failed

Description The key management process (kmd) could not retrieve information about the slot housing the indicated PIC. As a result, it could not retrieve Simple Network Management Protocol (SNMP) statistics about IP Security (IPSec) security associations (SAs) from the PIC.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

KMD_VPN_DFBIT_STATUS_MSG

System Log Message The DF-BIT for VPN *vpn-name* has been set to *argument*.

Description VPN DF bit status has been set.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

KMD_VPN_DOWN_ALARM_USER

System Log Message	VPN <i>vpn-name</i> from <i>remote-address</i> is down.
Description	Notification to user that VPN monitor detects IPSec SA is down.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

KMD_VPN_UP_ALARM_USER

System Log Message	VPN <i>vpn-name</i> from <i>remote-address</i> is up.
Description	Notification to user that VPN monitor detects IPSec SA is up.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

CHAPTER 53

L2ALD System Log Messages

This chapter describes messages with the **L2ALD** prefix. They are generated by the Layer 2 address learning process (l2ald), which supports the dynamic acquisition of information about media access control (MAC) addresses in a Layer 2 bridge environment.

L2ALD_BD_NAME_RESTRICTION

System Log Message	Reserved character '/' is not allowed as part of bridge-domain(<i>bridge-domain</i>) name. Any firewall filter applied to this bridge-domain might fail to work.
Description	Firewall filter will not work for the restricted bridge-domain name.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Action	Contact your technical support representative.

L2ALD_DUPLICATE_RBEB_MAC

System Log Message	Duplicate RBEB mac has been detected (<i>mac-address</i>). LE already exists with pbbn_id : <i>pbbn-id</i> . Rejecting LE create with pbbn_id : <i>new-pbbn-id</i>
Description	The l2 learning process (l2ald) already has this particular BEB mac existing for a different PBBN ID.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

L2ALD_GENCFG_OP_FAILED

System Log Message	Unable to complete gencfg operation <i>operation</i> (major <i>type</i> , minor <i>subtype</i>): <i>error-message</i>
Description	The Layer 2 address learning process (l2ald) could not send Layer 2 forwarding-related information to the Packet Forwarding Engines, because the indicated operation failed during configuration generation.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

L2ALD_IPC_MESSAGE_ERROR

System Log Message	Message (type <i>message-type</i> , subtype <i>message-subtype</i> , opcode <i>message-opcode</i>) received with error <i>error-message</i>
Description	The Layer 2 address learning process (l2ald) detected an error in an interprocess communication (IPC) message with the indicated characteristics.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

L2ALD_IPC_MESSAGE_INVALID

System Log Message	Invalid message received (message type <i>message</i> , subtype <i>message-type</i>): <i>message-subtype</i>
Description	The Layer 2 address learning process (l2ald) received a message with the indicated characteristics. The message was invalid for the indicated reason.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

L2ALD_IPC_MESSAGE_SEND_FAILED

System Log Message	Unable to send IPC message to <i>peer-name identifier</i>
Description	The Layer 2 address learning process (l2ald) could not send an interprocess communication (IPC) message to the indicated Layer 2 peer.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Action	Contact your technical support representative.

L2ALD_IPC_PIPE_WRITE_ERROR

System Log Message	Unable to write on pipe: <i>error-message</i>
Description	The Layer 2 address learning process (l2ald) could not write to an interprocess communication (IPC) pipe for the indicated reason.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	One possible reason is that there was no reader for the pipe.
Action	Contact your technical support representative.

L2ALD_MAC_LIMIT_REACHED_BD

System Log Message	Limit on learned MAC addresses reached for routing instance ' <i>routing-instance</i> ', domain ' <i>bridge-domain:vlan-id</i> '; current count is <i>count</i>
Description	The Layer 2 address learning process (l2ald) stopped adding addresses to the MAC address table that were learned by interfaces in the indicated bridging domain, because the indicated count of learned addresses exceeds the configured or default limit for the bridge-domain.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON
Action	Increase the limit on addresses learned by interfaces in the bridge domain, by increasing the value of the 'interface-mac-limit' statement at the [edit routing-instances <routing-instance-name> bridge-domains <bridge-domain-name> bridge-options] hierarchy level.

L2ALD_MAC_LIMIT_REACHED_GLOBAL

System Log Message	Global limit on learned MAC addresses reached; current count is <i>count</i>
Description	The Layer 2 address learning process (l2ald) stopped adding addresses to the MAC address table, because the indicated count of learned addresses exceeds the limit for the router.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON

Action Increase the limit on addresses learned by the interfaces on the router by increasing the value of the 'global-mac-limit' statement at the [edit protocols l2-learning] hierarchy level.

L2ALD_MAC_LIMIT_REACHED_IF

System Log Message Limit on learned MAC addresses reached for *interface-name*; current count is *count*

Description The Layer 2 address learning process (l2ald) stopped adding addresses to the MAC address table that were learned by the indicated interface, because the indicated count of learned addresses exceeds the limit configured for the interface.

Type Event: This message reports an event, not an error

Severity error

Facility LOG_DAEMON

Action Increase the limit on addresses learned by the interface by increasing the value of the 'interface-mac-limit' statement at the appropriate location under the [edit routing-instances <routing-instance-name> bridge-domains <bridge-domain-name> bridge-options] or the [edit routing-instances <routing-instance-name> protocols vpls] hierarchy level.

L2ALD_MAC_LIMIT_REACHED_IFBD

System Log Message Limit on learned MAC addresses reached for *interface-name*; current count is *count*

Description The Layer 2 address learning process (l2ald) stopped adding addresses to the MAC address table that were learned by the indicated interface:vlan-id, because the indicated count of learned addresses exceeds the limit configured for the interface:vlan-id.

Type Event: This message reports an event, not an error

Severity error

Facility LOG_DAEMON

Action Increase the limit on addresses learned by the interface by increasing the value of the 'interface-mac-limit' statement at the appropriate location under the [edit routing-instances <routing-instance-name> bridge-domains <bridge-domain-name> bridge-options] or the [edit routing-instances <routing-instance-name> protocols vpls] hierarchy level.

L2ALD_MAC_LIMIT_REACHED_RTT

System Log Message Limit on learned MAC addresses reached for routing instance '*routing-instance*'; current count is *count*

Description The Layer 2 address learning process (l2ald) stopped adding addresses to the MAC address table that were learned by interfaces in the indicated routing instance, because the indicated count of learned addresses exceeds the configured or default limit for the routing instance.

Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON
Action	Increase the limit on addresses learned by interfaces in the routing-instance, by increasing the value of the 'interface-mac-limit' statement at the [edit routing-instances <routing-instance-name> protocol l2-learning] or the [edit routing-instances <routing-instance-name> protocols vpls] hierarchy level.

L2ALD_MAC_LIMIT_RESET_BD

System Log Message Resumed adding MAC addresses learned from routing instance '*routing-instance*', domain '*bridge-domain:vlan-id*'; current count is *count*

Description The Layer 2 address learning process (l2ald) resumed adding addresses to the MAC address table that were learned by interfaces in the indicated bridging domain, because the indicated count of learned addresses no longer exceeds the limit configured for the domain.

Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON
Cause	The probable reason that the count of addresses went below the limit is that addresses in the table reached the age limit and were removed.

L2ALD_MAC_LIMIT_RESET_GLOBAL

System Log Message Resumed adding MAC addresses for router; current count is *count*

Description The Layer 2 address learning process (l2ald) resumed adding addresses to the MAC address table, because the indicated count of learned addresses no longer exceeds the configured limit.

Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON
Cause	The probable reason that the count of addresses went below the limit is that addresses in the table reached the age limit and were removed.

L2ALD_MAC_LIMIT_RESET_IF

System Log Message Resumed adding MAC addresses learned by *interface-name*; current count is *count*

Description The Layer 2 address learning process (l2ald) resumed adding addresses to the MAC address table that were learned by the indicated interface, because the indicated count of learned addresses no longer exceeds the limit configured for the interface.

Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON
Cause	The probable reason that the count of addresses went below the limit is that addresses in the table reached the age limit and were removed.

L2ALD_MAC_LIMIT_RESET_RTT

System Log Message Resumed adding MAC addresses learned from routing instance '*routing-instance*'; current count is *count*

Description The Layer 2 address learning process (l2ald) resumed adding addresses to the MAC address table that were learned by interfaces in the indicated bridging domain, because the indicated count of learned addresses no longer exceeds the limit configured for the instance.

Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON
Cause	The probable reason that the count of addresses went below the limit is that addresses in the table reached the age limit and were removed.

L2ALD_MAC_MOVE_NOTIFICATION

System Log Message MAC Moves detected in the system

Description When the same MAC address is learned on a different interface, or on the same interface but a different unit number, it is considered a MAC move. When this happens frequently for a specific time duration, a notification is sent

Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	The probable reason for mac moves is the loops in the topology or some kind of misconfiguration.

L2ALD_MALLOC_FAILED

System Log Message Unable to allocate memory: *error-message*

Description The Layer 2 address learning process (l2ald) could not allocate memory while creating a data structure.

Type	Error: An error occurred
Severity	error

Facility LOG_DAEMON
Action Contact your technical support representative.

L2ALD_MANAGER_CONNECT

System Log Message Unable to create pipe to Layer 2 address-learning manager: *error-message*

Description The Layer 2 address learning process (l2ald) could not open a pipe for interprocess communication (IPC) with a Layer 2 address-learning manager process.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

L2ALD_NAME_LENGTH_IF_DEVICE

System Log Message Unable to add interface device *interface-name*; name exceeds limit of *length* characters

Description The Layer 2 address learning process (l2ald) did not add an entry for the indicated interface device to the interface table, because its name exceeds the indicated limit on the number of characters.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

L2ALD_NAME_LENGTH_IF_FAMILY

System Log Message Unable to add interface family *interface-family*; name exceeds limit of *length* characters

Description The Layer 2 address learning process (l2ald) did not add an entry for the indicated interface family to the interface table, because its name exceeds the indicated limit on the number of characters.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

L2ALD_NAME_LENGTH_IF_LOGICAL

System Log Message Unable to add logical interface *interface-name*; name exceeds limit of *length* characters

Description	The Layer 2 address learning process (l2ald) did not add an entry for the indicated logical interface to the interface table, because its name exceeds the indicated limit on the number of characters.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

L2ALD_PBBN_IFL_REVA

System Log Message	Unable to initialize Provider Backbone Bridging on interface <i>interface-name</i> . It is present on a Rev A card.
Description	The Layer 2 address learning process (l2ald) could not initialize the interface for the provider backbone bridging (PBB) feature because the interface was on a revision A card.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Cause	Revision A cards do not support provider backbone bridging (PBB) features.
Action	Contact your technical support representative.

L2ALD_PBBN_REINSTATE_IFBDS

System Log Message	Hardware VCs are being restored for data packet.They were de-programmed because <i>interface-name</i> had an interface on a Rev A card.
Description	The Layer 2 address learning process (l2ald) reinstated certain hardware circuits to resume data traffic. The circuits were brought down because the provider backbone bridging (PBB) feature had discovered that one of the interfaces was on a revision A card.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Cause	The interface is no longer present on the revision A card.
Action	Contact your technical support representative.

L2ALD_PBBN_RETRACT_IFBDS

System Log Message	Provider Backbone Bridging feature detected on interface <i>interface-name</i> on a Rev A card. VCs are being de-programmed.
---------------------------	--

Description	The Layer 2 address learning process (l2ald) retracted certain hardware circuits to block data traffic. The circuits were brought down because the provider backbone bridging (PBB) feature had discovered that one of the interfaces was on a revision A card.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Cause	An interface was discovered on the revision A card. Revision A cards do not support provider backbone bridging (PBB) features.
Action	Contact your technical support representative.

L2ALD_PIP_IFD_READ_RETRY

System Log Message	Retry count exceeded trying to read <i>pip-interface</i> from the kernel. Retry count is <i>retry-count</i>
Description	The Layer 2 address learning process (l2ald) could not read the provide-in-provider interface (pip0) interface from the kernel.
Type	Error: An error occurred
Severity	critical
Facility	LOG_DAEMON
Cause	The chassis process may have been too slow in creating the interface.
Action	Contact your technical support representative.

CHAPTER 54

L2CPD System Log Messages

This chapter describes messages with the **L2CPD** prefix. They are generated by the Layer 2 Control Protocol process (l2cpd), which supports the transmission of control messages for Layer 2 spanning tree protocols in a Layer 2 bridge environment.

L2CPD_ASSERT

System Log Message	Assertion failed for <i>executable-name</i> (PID <i>pid</i>) at line <i>line-number</i> in file ' <i>source-filename</i> ': <i>message</i>
Description	The source code for the Layer 2 Control Protocol process (l2cpd) includes internal self-consistency tests. The l2cpd process with the indicated executable name and process ID (PID) terminated because the indicated test failed at the indicated line number in the indicated source file. The process created a diagnostic core file for analysis by technical support personnel.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	Messages that immediately follow this message in the system log might provide information about possible causes.
Action	Contact a technical support representative, and be ready to provide the list of messages and the diagnostic core file, if requested.

L2CPD_ASSERT_SOFT

System Log Message	Assertion failed for <i>executable-name</i> (PID <i>pid</i>) at line <i>line-number</i> in file ' <i>source-filename</i> ' (<i>message</i>); process continued running
Description	The source code for the Layer 2 Control Protocol process (l2cpd) includes internal self-consistency tests. The l2cpd process with the indicated executable name and process ID (PID) terminated because the indicated type of check failed at the indicated line number in the indicated source file. The process continued to run, but created a diagnostic core file for analysis by technical support personnel.
Type	Error: An error occurred

Severity	error
Facility	LOG_DAEMON
Cause	Messages that immediately follow this message in the system log might provide information about possible causes.
Action	Contact a technical support representative, and be ready to provide the list of messages and the diagnostic core file, if requested.

L2CPD_EXIT

System Log Message	<i>l2cpd</i> process with PID <i>pid</i> exited (was using executable <i>executable-name</i> , version <i>version</i> built by <i>builder</i> on <i>date</i>); caller was <i>address</i>
Description	The Layer 2 Control Protocol process (<i>l2cpd</i>) exited. The process had the indicated process ID (PID) and was using an executable with the indicated name, version, and other characteristics.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON
Cause	Either a system resource was unavailable, the <i>l2cpd</i> process could not interpret an error, or the indicated user (referred to as a 'caller') terminated the process.

L2CPD_KERNEL_VERSION

System Log Message	Kernel version (<i>kernel-version</i>) of routing sockets was not required version (<i>l2cpd-version</i>)
Description	The Layer 2 Control Protocol process (<i>l2cpd</i>) determined that the indicated version of routing sockets, which the kernel supports, is not the version that it requires.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Upgrade the kernel package.

L2CPD_KERNEL_VERSION_OLD

System Log Message	Kernel version (<i>kernel-version</i>) of routing socket message type <i>message-type</i> is older than the required version (<i>l2cpd-version</i>)
Description	The Layer 2 Control Protocol process (<i>l2cpd</i>) determined that the kernel supports an indicated older version of the indicated routing socket message type than it requires.
Type	Error: An error occurred
Severity	error

Facility LOG_DAEMON
Action Upgrade the kernel package.

L2CPD_KERNEL_VERSION_UNSUPP

System Log Message Kernel version of routing socket message type '*message-type*' was not required version (*l2cpd-version*)

Description The Layer 2 Control Protocol process (l2cpd) determined that the kernel does not support the version of the indicated routing socket message type that it requires.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Upgrade the kernel package.

L2CPD_MEMORY_EXCESSIVE

System Log Message Using *size* KB of memory, *percentage-value* percent of available

Description The Layer 2 Control Protocol process (l2cpd) was using the indicated amount and percentage of Routing Engine memory, which is considered excessive.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause Either the l2cpd process is leaking memory or the use of system resources is excessive. Possible causes include misconfigured routing filters or a very complex configured network topology.

Action Increase the amount of RAM in the Routing Engine.

L2CPD_MGMT_TIMEOUT

System Log Message Peer *peer-name* timed out

Description The Layer 2 Control Protocol process (l2cpd) did not receive input from the indicated management peer within the timeout period.

Type Error: An error occurred

Severity warning

Facility LOG_DAEMON

Cause Messages that immediately follow this message in the system log might provide information about possible causes.

L2CPD_MIRROR_ERROR

System Log Message	Unable to establish mirror connection between Routing Engines: <i>error-message</i>
Description	The Layer 2 Control Protocol process (l2cpd) could not establish the mirror connection (which supports nonstop routing) between the master and backup Routing Engines.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Cause	The master and backup Routing Engines are running incompatible versions of the Junos OS.
Action	Update the Junos OS to compatible versions on the master and backup Routing Engines.

L2CPD_MIRROR_VERSION_MISMATCH

System Log Message	Versions of mirror software on Routing Engines are incompatible: <i>error-message</i>
Description	While trying to establish the mirror connection (which supports nonstop routing) between the master and backup Routing Engines, the Layer 2 Control Protocol process (l2cpd) determined that the versions of Junos OS on the Routing Engines were incompatible.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Action	Update the Junos OS to compatible versions on the master and backup Routing Engines.

L2CPD_PPM_READ_ERROR

System Log Message	Read error on pipe from ppmd: <i>reason (error-message)</i>
Description	The Layer 2 Control Protocol process (l2cpd) could not read a message available on the read pipe from the periodic packet management process (ppmd).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

L2CPD_PPM_WRITE_ERROR

System Log Message	<i>function-name</i> : write error on pipe to ppmd (<i>error-message</i>)
Description	The Layer 2 Control Protocol process (l2cpd) could not write a message on the pipe to the periodic packet management process (ppmd).

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

L2CPD_RUNTIME_MODULE

System Log Message	<i>function-name</i> : runtime was excessive (<i>time</i>) during <i>action</i> of <i>module</i>
Description	The indicated operation on the indicated submodule of the Layer 2 Control Protocol process (l2cpd) ran uninterrupted for the indicated period of time, which is considered excessive.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	The message was logged because task accounting is enabled. The function might be implemented inefficiently.

L2CPD_RUNTIME_OPERATION

System Log Message	<i>function-name</i> : runtime was excessive (<i>time</i>) during <i>action</i> of <i>module</i>
Description	The indicated operation on the indicated submodule of the Layer 2 Control Protocol process (l2cpd) ran uninterrupted for the indicated period of time, which is considered excessive.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	The message was logged because task accounting is enabled. The function might be implemented inefficiently.

L2CPD_RUNTIME_TASK

System Log Message	<i>function-name</i> : runtime was excessive (<i>total-time</i> [<i>user-time</i> user, <i>system-time</i> system]) doing <i>action</i>
Description	While performing the indicated operation, the indicated function in the Layer 2 Control Protocol process (l2cpd) ran uninterrupted for the indicated period of time (the sum of the indicated user and system times), which is considered excessive.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

Cause The message was logged because task accounting is enabled. The function might be implemented inefficiently.

L2CPD_RUNTIME_TOTAL

System Log Message *function-name: runtime was excessive (total of *time* in *count* callbacks) after *action* of *module**

Description After the indicated operation on the indicated submodule of the Layer 2 Control Protocol process (l2cpd), several functions ran uninterrupted in the indicated number of callbacks for the indicated period of time, which is considered excessive.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

Cause The message was logged because task accounting is enabled. The function might be implemented inefficiently.

L2CPD_TASK_BEGIN

System Log Message l2cpd process started (version *l2cpd-version* built on *date* by *builder*)

Description The Layer 2 Control Protocol process (l2cpd) started. It was assigned the indicated process ID (PID) and was using an executable with the indicated name, version, and build date.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

L2CPD_TASK_CHILD_KILLED

System Log Message Child process '*task-name*' terminated by SIG*signal-name* *core-dump-status*

Description While a child process of the Layer 2 Control Protocol process (l2cpd) was performing the indicated operation, it terminated in response to the indicated signal.

Type Event: This message reports an event, not an error

Severity error

Facility LOG_DAEMON

L2CPD_TASK_CHILD_STOPPED

System Log Message Child process '*task-name*' stopped by SIG*signal-name*

Description While a child process of the Layer 2 Control Protocol process (l2cpd) was performing the indicated operation, it stopped in response to the indicated signal.

Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON

L2CPD_TASK_FORK

System Log Message	Unable to fork <i>task-name: error-message</i>
Description	The Layer 2 Control Protocol process (l2cpd) could not create the indicated child process.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

L2CPD_TASK_GETWD

System Log Message	getwd() failed for <i>error-message</i>
Description	The Layer 2 Control Protocol process (l2cpd) invoked the getwd() system call, which failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	It is possible that the kernel lacked the resources needed to fulfill the request. The l2cpd process continued operating.

L2CPD_TASK_MASTERSHIP

System Log Message	Assumed mastership
Description	The Layer 2 Control Protocol process (l2cpd) became active when the Routing Engine on which it was running assumed mastership.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

L2CPD_TASK_NO_REINIT

System Log Message	Unable to reinitialize
Description	The Layer 2 Control Protocol process (l2cpd) did not reinitialize as requested, because it was running in a state that did not allow reconfiguration.
Type	Error: An error occurred
Severity	error

Facility LOG_DAEMON

L2CPD_TASK_PID_CLOSE

System Log Message Unable to close and remove PID file *filename: error-message*

Description The Layer 2 Control Protocol process (l2cpd) could not close and remove the file that records its process ID (PID), which serves to prevent multiple instances of the l2cpd process from running simultaneously.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

L2CPD_TASK_PID_LOCK

System Log Message flock(*filename*, LOCK_EX): *error-message*

Description The Layer 2 Control Protocol process (l2cpd) could not lock the file that records its process ID (PID), which serves to prevent multiple instances of the l2cpd process from running simultaneously.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

L2CPD_TASK_PID_WRITE

System Log Message Unable to write to PID file *filename: error-message*

Description The Layer 2 Control Protocol process (l2cpd) could not write to the file that records its process ID (PID), which serves to prevent multiple instances of the l2cpd process from running simultaneously.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

L2CPD_TASK_REINIT

System Log Message Reinitialized

Description The Layer 2 Control Protocol process (l2cpd) reinitialized.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

L2CPD_TASK_SIGNAL_IGNORE

System Log Message	Unable to register SIG <i>signal-name</i> to be ignored: <i>error-message</i>
Description	The Layer 2 Control Protocol process (l2cpd) informed the kernel that it wished to ignore the indicated signal, but the kernel did not process the request.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

L2CPD_TERMINATE_ACTIVE

System Log Message	Exited with active tasks: <i>task-name</i>
Description	After receiving multiple termination requests, the Layer 2 Control Protocol process (l2cpd) exited without performing the indicated cleanup tasks.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

L2CPD_TERMINATE_SIGNAL

System Log Message	Exited after receiving termination signal <i>signal-name</i>
Description	In response to the indicated termination request, the Layer 2 Control Protocol process (l2cpd) terminated adjacencies with neighbors and shut down.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

L2CPD_TRACE_FAILED

System Log Message	Unable to write to trace file <i>filename</i>
Description	The Layer 2 Control Protocol process (l2cpd) could not write to the indicated trace file, and stopped attempting to do so. The next commit of the configuration database will reenables tracing.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON

L2CPD_XSTP_SHUTDOWN_FAILED

System Log Message	Unable to shut down <i>error-message</i> module
---------------------------	---

Description The Layer 2 Control Protocol process (l2cpd) could not shut down the indicated Rapid Spanning Tree Protocol (RSTP) or Multiple Spanning Tree Protocol (MSTP) module.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHAPTER 55

L2TPD System Log Messages

This chapter describes messages with the **L2TPD** prefix. They are generated by the Layer 2 Tunneling Protocol (L2TP) process (l2tpd), which provides services that enable tunneling of Point-to-Point Protocol (PPP) sessions across a Layer 3 IP network.

L2TPD_COS_PROFILE_ADD

System Log Message	Unable to add CoS profile <i>profile-name</i> (L2TP tunnel <i>tunnel-id</i> , session <i>session-id</i>): <i>error-message</i>
Description	The Layer 2 Tunneling Protocol process (l2tpd) could not add the indicated class-of-service (CoS) profile to the indicated session on the indicated tunnel, which is associated with a user.
Type	Error: An error occurred
Severity	error
Facility	LOG_NEWS
Action	Remove the CoS profile from the RADIUS database or contact your technical support representative.

L2TPD_COS_PROFILE_DELETE

System Log Message	Unable to delete CoS profile (L2TP tunnel <i>tunnel-id</i> , session <i>session-id</i>): <i>error-message</i>
Description	The Layer 2 Tunneling Protocol process (l2tpd) could not delete a class-of-service (CoS) profile from the indicated session on the indicated tunnel, which is associated with a user.
Type	Error: An error occurred
Severity	error
Facility	LOG_NEWS
Action	Remove the CoS profile from the RADIUS database or contact your technical support representative.

L2TPD_DB_ADD_FAILED

System Log Message	Unable to add node for <i>node-name</i> to internal database
Description	The Layer 2 Tunneling Protocol process (l2tpd) maintains a copy of the Junos configuration database in memory. It could not add the indicated node to the in-memory database.
Type	Error: An error occurred
Severity	error
Facility	LOG_NEWS

L2TPD_DB_DELETE_FAILED

System Log Message	Unable to delete node for <i>node-name</i> from internal database
Description	The Layer 2 Tunneling Protocol process (l2tpd) maintains a copy of the Junos configuration database in memory. It could not delete the indicated node to the in-memory database.
Type	Error: An error occurred
Severity	error
Facility	LOG_NEWS

L2TPD_DB_INIT_FAILED

System Log Message	Unable to initialize root node <i>object-name</i> in internal database: <i>error-message</i>
Description	The Layer 2 Tunneling Protocol process (l2tpd) maintains a copy of the Junos configuration database in memory. It could not initialize the root node for the indicated object in the in-memory database.
Type	Error: An error occurred
Severity	error
Facility	LOG_NEWS

L2TPD_DB_TUN_GRP_ALLOC_FAILED

System Log Message	Unable to allocate memory for tunnel group
Description	The Layer 2 Tunneling Protocol process (l2tpd) could not allocate memory for the data structure used to record tunnel group information.
Type	Error: An error occurred
Severity	error
Facility	LOG_NEWS

L2TPD_DEFAULT_PROTO_CREATE_FAIL

System Log Message	Unable to create default L2TP module
Description	The Layer 2 Tunneling Protocol process (l2tpd) could not create a default L2TP module.
Type	Error: An error occurred
Severity	error
Facility	LOG_NEWS

L2TPD_EVLIB_CREATE_FAILED

System Log Message	Unable to create event context: <i>error-message</i>
Description	The Layer 2 Tunneling Protocol process (l2tpd) could not create a context for handling asynchronous events.
Type	Error: An error occurred
Severity	emergency
Facility	LOG_NEWS

L2TPD_EVLIB_FD_DEREGISTER_FAILED

System Log Message	Unable to deregister file descriptor: not registered
Description	The Layer 2 Tunneling Protocol process (l2tpd) could not deregister a file descriptor, because it did not exist.
Type	Error: An error occurred
Severity	error
Facility	LOG_NEWS

L2TPD_EVLIB_FD_DESELECT_FAILED

System Log Message	Unable to deselect file descriptor: <i>error-message</i>
Description	The Layer 2 Tunneling Protocol process (l2tpd) could not deselect a file descriptor.
Type	Error: An error occurred
Severity	error
Facility	LOG_NEWS

L2TPD_EVLIB_FD_NOT_REGISTERED

System Log Message	No file descriptor registered
Description	The Layer 2 Tunneling Protocol process (l2tpd) could not find a registered file descriptor while attempting to set an event mask.

Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_EVLIB_FD_SELECT_FAILED

System Log Message Unable to select file descriptor for events *event-id: error-message*
Description The Layer 2 Tunneling Protocol process (l2tpd) could not select the file descriptor for the indicated events.
Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_EVLIB_TIMER_CLEAR_FAILED

System Log Message Unable to clear event timer: *error-message*
Description The Layer 2 Tunneling Protocol process (l2tpd) could not clear an event timer for the indicated reason.
Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_EVLIB_TIMER_SET_FAILED

System Log Message Unable to set event timer: *error-message*
Description The Layer 2 Tunneling Protocol process (l2tpd) could not set an event timer for the indicated reason.
Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_FILTER_FILE_OPEN_FAILED

System Log Message Unable to open file *filename*
Description The Layer 2 Tunneling Protocol process (l2tpd) could not open the indicated filter file.
Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_GLOBAL_CFG_ADD_FAILED

System Log Message	Unable to add global configuration for PIC <i>pic-slot</i> (errno <i>error-code</i>)
Description	The Layer 2 Tunneling Protocol process (l2tpd) could not add the global configuration for the indicated PIC.
Type	Error: An error occurred
Severity	error
Facility	LOG_NEWS

L2TPD_GLOBAL_CFG_CHANGE_FAILED

System Log Message	Unable to change global configuration for PIC <i>pic-slot</i> (errno <i>error-code</i>)
Description	The Layer 2 Tunneling Protocol process (l2tpd) could not change the global configuration for the indicated PIC.
Type	Error: An error occurred
Severity	error
Facility	LOG_NEWS

L2TPD_GLOBAL_CFG_DELETE_FAILED

System Log Message	Unable to delete global configuration for PIC <i>pic-slot</i> (errno <i>error-code</i>)
Description	The Layer 2 Tunneling Protocol process (l2tpd) could not delete the global configuration for the indicated PIC.
Type	Error: An error occurred
Severity	error
Facility	LOG_NEWS

L2TPD_IFD_ADD_FAILED

System Log Message	<i>function-name</i> : unable to add interface device <i>interface-name</i>
Description	The Layer 2 Tunneling Protocol process (l2tpd) maintains a copy of the Junos configuration database in memory. It could not add the indicated interface device to the in-memory database.
Type	Error: An error occurred
Severity	error
Facility	LOG_NEWS

L2TPD_IFD_DELETE_FAILED

System Log Message	<i>function-name</i> : unable to delete interface device <i>interface-name</i>
---------------------------	--

Description The Layer 2 Tunneling Protocol process (l2tpd) maintains a copy of the Junos configuration database in memory. It could not delete the indicated interface device from the in-memory database.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_IFD_MSG_REGISTER_FAILED

System Log Message Unable to register message handler for interface device: *error-message*

Description The Layer 2 Tunneling Protocol process (l2tpd) could not register an interface device message handler.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_IFD_ROOT_ALLOC_FAILED

System Log Message Unable to allocate memory for interface device root node: *error-message*

Description The Layer 2 Tunneling Protocol process (l2tpd) maintains a copy of the Junos configuration database in memory. It could not allocate memory in the in-memory database for the root node for an interface device.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_IFL_ADD_FAILED

System Log Message *function-name*: unable to add interface *interface-name*

Description The Layer 2 Tunneling Protocol process (l2tpd) maintains a copy of the Junos configuration database in memory. It could not add the indicated logical interface to the in-memory database.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_IFL_DELETE_FAILED

System Log Message *function-name*: unable to delete interface *interface-name*

Description The Layer 2 Tunneling Protocol process (l2tpd) maintains a copy of the Junos configuration database in memory. It could not delete the indicated logical interface from the in-memory database.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_IFL_MSG_REGISTER_FAILED

System Log Message Unable to register message handler for interface: *error-message*

Description The Layer 2 Tunneling Protocol process (l2tpd) could not register a logical interface message handler.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_IFL_NOT_FOUND

System Log Message Unable to find logical interface (L2TP tunnel *tunnel-id*, session *session-id*)

Description The Layer 2 Tunneling Protocol process (l2tpd) could not retrieve a logical interface in the indicated tunnel and session.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_IFL_ROOT_ALLOC_FAILED

System Log Message Unable to allocate memory for interface root node: *error-message*

Description The Layer 2 Tunneling Protocol process (l2tpd) maintains a copy of the Junos configuration database in memory. It could not allocate memory in the in-memory database for the root node for a logical interface.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_INSTANCE_CREATE_FAILED

System Log Message Unable to create L2TP instance *tunnel-group*

Description The Layer 2 Tunneling Protocol process (l2tpd) could not create an L2TP instance for the indicated tunnel group.

Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_INSTANCE_RESTART_FAILED

System Log Message Unable to trigger restart of L2TP instance *tunnel-group*
Description The Layer 2 Tunneling Protocol process (l2tpd) could not restart the L2TP instance for the indicated tunnel group.

Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_INTERFACE_ID_NOT_FOUND

System Log Message Unable to find interface ID *interface-name*
Description The Layer 2 Tunneling Protocol process (l2tpd) could not find the indicated interface ID in the copy of the Junos configuration database that it maintains in memory.

Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_MESSAGE_REGISTER_FAILED

System Log Message Unable to register L2TP message handler: *error-message*
Description The Layer 2 Tunneling Protocol process (l2tpd) could not register an L2TP message handler.

Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_MLPPP_BUNDLE_ALLOC_FAILED

System Log Message Unable to allocate MLPPP bundle
Description The Layer 2 Tunneling Protocol process (l2tpd) could not allocate memory for a multilink Point-to-Point Protocol (MLPPP) bundle.

Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_MLPPP_BUNDLE_CREATE_FAILED

System Log Message	Unable to create MLPPP bundle (L2TP tunnel <i>tunnel-id</i> , session <i>session-id</i>)
Description	The Layer 2 Tunneling Protocol process (l2tpd) could not create a multilink Point-to-Point Protocol (MLPPP) bundle in the indicated tunnel and session.
Type	Error: An error occurred
Severity	error
Facility	LOG_NEWS

L2TPD_MLPPP_BUNDLE_INVALID_ID

System Log Message	MLPPP bundle ID was invalid
Description	The identifier assigned to a multilink Point-to-Point Protocol (MLPPP) bundle was invalid.
Type	Error: An error occurred
Severity	error
Facility	LOG_NEWS

L2TPD_MLPPP_COPY_CFG_FAILED

System Log Message	Unable to copy MLPPP configuration (L2TP tunnel <i>tunnel-id</i> , session <i>session-id</i>)
Description	The Layer 2 Tunneling Protocol process (l2tpd) could not copy the multilink Point-to-Point Protocol (MLPPP) configuration for the indicated tunnel and session.
Type	Error: An error occurred
Severity	error
Facility	LOG_NEWS

L2TPD_MLPPP_ID_ALLOC_FAILED

System Log Message	Unable to allocate MLPPP ID map
Description	The Layer 2 Tunneling Protocol process (l2tpd) could not allocate memory for a multilink Point-to-Point Protocol (MLPPP) identifier map data structure.
Type	Error: An error occurred
Severity	error
Facility	LOG_NEWS

L2TPD_MLPPP_ID_BITMAP_ALLOC_FAIL

System Log Message	Unable to allocate bitmap field for MLPPP ID map
Description	The Layer 2 Tunneling Protocol process (l2tpd) could not allocate memory for a bitmap field in a multilink Point-to-Point Protocol (MLPPP) identifier map data structure.

Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_MLPPP_ID_NODE_ADD_FAILED

System Log Message Unable to add node for bundle *bundle* to MLPPP ID map

Description The Layer 2 Tunneling Protocol process (l2tpd) could not add a node for the indicated multilink Point-to-Point Protocol (MLPPP) bundle to an MLPPP identifier map data structure.

Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_MLPPP_ID_ROOT_ALLOC_FAILED

System Log Message Unable to allocate root node for MLPPP ID map

Description The Layer 2 Tunneling Protocol process (l2tpd) could not allocate the root note for a multilink Point-to-Point Protocol (MLPPP) identifier map data structure.

Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_MLPPP_LINK_CREATE_FAILED

System Log Message Unable to create MLPPP bundle links (L2TP tunnel *tunnel-id*, session *session-id*)

Description The Layer 2 Tunneling Protocol process (l2tpd) could not create multilink Point-to-Point Protocol (MLPPP) bundle links for the indicated tunnel and session.

Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_MLPPP_LINK_MAX_EXCEEDED

System Log Message Unable to add link: maximum number of sessions exceeded for MLPPP bundle *bundle* (L2TP tunnel *tunnel-id*, session *session-id*)

Description The Layer 2 Tunneling Protocol process (l2tpd) could not add a link for the indicated multilink Point-to-Point Protocol (MLPPP) bundle in the indicated tunnel and session, because the maximum number of links was exceeded.

Type Error: An error occurred
Severity error

Facility LOG_NEWS

L2TPD_MLPPP_POOL_ADDRESS_FAILED

System Log Message Unable to assign pool address for MLPPP bundle *bundle* (L2TP tunnel *tunnel-id*, session *session-id*)

Description The Layer 2 Tunneling Protocol process (l2tpd) could not assign a pool address for the indicated multilink Point-to-Point Protocol (MLPPP) bundle in the indicated tunnel and session.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_MLPPP_SESSION_CREATE_FAIL

System Log Message Unable to create MLPPP session (L2TP tunnel *tunnel-id*, session *session-id*)

Description The Layer 2 Tunneling Protocol process (l2tpd) could not create a multilink Point-to-Point Protocol (MLPPP) session for the indicated tunnel and session.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_MLPPP_SESSION_DELETE_FAIL

System Log Message Unable to delete session for MLPPP bundle *bundle* (L2TP tunnel *tunnel-id*, session *session-id*, errno *error-code*)

Description The Layer 2 Tunneling Protocol process (l2tpd) could not delete the session configuration for the indicated multilink Point-to-Point Protocol (MLPPP) bundle in the indicated tunnel and session.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_MLPPP_SPEED_MISMATCH

System Log Message Unable to add link: speed differs for bundle *bundle* (L2TP tunnel *tunnel-id*, session *session-id*)

Description The Layer 2 Tunneling Protocol process (l2tpd) could not add a link for the indicated multilink Point-to-Point Protocol (MLPPP) bundle in the indicated tunnel and session, because the bundle speed does not match.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_NH_DELETE_FAILED

System Log Message Unable to delete next hop *next-hop*

Description The Layer 2 Tunneling Protocol process (l2tpd) could not delete the indicated next hop.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_POLICER_ADD_FAILED

System Log Message Unable to add policer *filter-name* (L2TP tunnel *tunnel-id*, session *session-id*): *error-message*

Description The Layer 2 Tunneling Protocol process (l2tpd) could not add the indicated policer to the indicated session on the indicated tunnel, which is associated with a user.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

Action Remove the policer from the RADIUS database or contact your technical support representative.

L2TPD_POLICER_PROFILE_DEL_FAILED

System Log Message Unable to delete policer profile (L2TP tunnel *tunnel-id*, session *session-id*): *error-message*

Description The Layer 2 Tunneling Protocol process (l2tpd) could not delete a policer profile from the indicated session on the indicated tunnel, which is associated with a user.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

Action Remove the policer profile from the RADIUS database or contact your technical support representative.

L2TPD_POOL_ADDRESS_FAILED

System Log Message Unable to assign pool address (L2TP tunnel *tunnel-id*, session *session-id*)

Description The Layer 2 Tunneling Protocol process (l2tpd) could not assign a pool address in the indicated tunnel and session.

Type Error: An error occurred

Severity error
Facility LOG_NEWS

L2TPD_POOL_ASSIGN_ADDRESS_FAILED

System Log Message Unable to assign L2TP pool address: pool *pool-name* is invalid or has no free addresses

Description The Layer 2 Tunneling Protocol process (l2tpd) could not assign an address from the indicated address pool, either because the pool was invalid or had no free addresses.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_PPP_ROUTE_ADD_FAILED

System Log Message Unable to add PPP peer route (L2TP tunnel *tunnel-id*, session *session-id*)

Description The Layer 2 Tunneling Protocol process (l2tpd) maintains a copy of the Junos configuration database in memory. It could not add information about a Point-to-Point Protocol (PPP) peer route to the in-memory configuration for the indicated tunnel and session.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_PPP_ROUTE_DELETE_FAILED

System Log Message Unable to remove PPP peer route (L2TP tunnel *tunnel-id*, session *session-id*)

Description The Layer 2 Tunneling Protocol process (l2tpd) maintains a copy of the Junos configuration database in memory. It could not delete information about a Point-to-Point Protocol (PPP) peer route from the in-memory configuration for the indicated tunnel and session.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_PROFILE_NOT_FOUND

System Log Message Profile *profile-name* not found

Description The Layer 2 Tunneling Protocol process (l2tpd) could not locate an access profile from the configuration in order to find radius servers to authenticate.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_PROFILE_NO_RADIUS_SERVERS

System Log Message Can't find radius servers for profile '*profile-name*

Description The Layer 2 Tunneling Protocol process (l2tpd) could not locate any radius servers for the configured access profile.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_RADIUS_ACCT_PORT_ZERO

System Log Message RADIUS server accounting port is zero

Description The Layer 2 Tunneling Protocol process (l2tpd) determined that the RADIUS server accounting port is zero, which is not a valid value.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_RADIUS_GETHOSTNAME_FAILED

System Log Message Unable to obtain hostname for outgoing RADIUS message: *error-message*

Description The Layer 2 Tunneling Protocol process (l2tpd) could not obtain a hostname for an outgoing RADIUS message.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_RADIUS_RT_INST_ENOENT

System Log Message Ignoring RADIUS server *radius-server*: routing instance *routing-instance* did not exist

Description The Layer 2 Tunneling Protocol process (l2tpd) did not use the indicated RADIUS server because the indicated routing instance specified for the server did not exist.

Type Error: An error occurred

Severity notice

Facility LOG_NEWS

L2TPD_RADIUS_RT_INST_NOT_FOUND

System Log Message Ignoring RADIUS server *radius-server*: unable to retrieve routing instance *routing-instance* (*error-message*)

Description The Layer 2 Tunneling Protocol process (l2tpd) did not use the indicated RADIUS server because it could not retrieve the indicated routing instance specified for the server.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_RADIUS_SERVER_NOT_FOUND

System Log Message Unable to find RADIUS server (tunnel *tunnel-id*, session *session-id*)

Description The Layer 2 Tunneling Protocol process (l2tpd) could not locate a RADIUS server during Point-to-Point Protocol (PPP) authentication of the indicated tunnel and session.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_RADIUS_SRC_ADDR_BIND_FAIL

System Log Message Ignoring RADIUS server *radius-server*: unable to bind to source address *source-address* (*error-message*)

Description The Layer 2 Tunneling Protocol process (l2tpd) did not use the indicated RADIUS server because it could not bind to the indicated source address.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_RADIUS_SRC_ADDR_ENOENT

System Log Message Ignoring RADIUS server *radius-server*: source address *source-address* did not exist

Description The Layer 2 Tunneling Protocol process (l2tpd) did not use the indicated RADIUS server because the indicated source address did not exist in the routing instance for the server.

Type Error: An error occurred

Severity notice

Facility LOG_NEWS

L2TPD_RPD_ASYNC_UNREG_FAILED

System Log Message Unable to unregister with rpd (*return-value*)

Description The Layer 2 Tunneling Protocol process (l2tpd) could not unregister asynchronously with the routing protocol process (rpd).

Type Error: An error occurred

Severity error
Facility LOG_NEWS

L2TPD_RPD_ROUTE_ADD_CB_FAILED

System Log Message Unable to add route *address/prefix-length* asynchronously (gateway *gateway-id* [*gateway-name*], L2TP tunnel *tunnel-id*, session *session-id*): *error-code*

Description The Layer 2 Tunneling Protocol process (l2tpd) could not add a route on an asynchronous callback for the indicated address and prefix, gateway, tunnel, and session.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_RPD_ROUTE_ADD_FAILED

System Log Message Unable to add route *address/prefix-length* (gateway *gateway-id* [*gateway-name*], L2TP tunnel *tunnel-id*, session *session-id*): *error-message* (*error-code*)

Description The Layer 2 Tunneling Protocol process (l2tpd) could not add a route for the indicated address and prefix, gateway, tunnel, and session.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_RPD_ROUTE_DELETE_CB_FAILED

System Log Message Unable to delete route *address/prefix-length* asynchronously (gateway *gateway-id* [*gateway-name*], L2TP tunnel *tunnel-id*, session *session-id*): *error-code*

Description The Layer 2 Tunneling Protocol process (l2tpd) could not delete a route on an asynchronous callback for the indicated address and prefix, gateway, tunnel, and session.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_RPD_ROUTE_DELETE_FAILED

System Log Message Unable to delete route *address/prefix-length* (gateway *gateway-id* [*gateway-name*], L2TP tunnel *tunnel-id*, session *session-id*): *error-message* (*error-code*)

Description The Layer 2 Tunneling Protocol process (l2tpd) could not delete a route for the indicated address and prefix, gateway, tunnel, and session.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_RPD_ROUTE_PREFIX_TOO_LONG

System Log Message Unable to add route *address/prefix-length*: prefix too long (L2TP tunnel *tunnel-id*, session *session-id*)

Description The Layer 2 Tunneling Protocol process (l2tpd) could not add a route for the indicated address and prefix, tunnel, and session.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_RPD_SESS_CREATE_FAILED

System Log Message Unable to establish session with rpd (*error-code*)

Description The Layer 2 Tunneling Protocol process (l2tpd) could not establish a session with the routing protocol process (rpd).

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_RPD_SESS_HANDLE_ALLOC_FAIL

System Log Message Unable to allocate session handle for rpd connection: *error-message* (*error-code*)

Description The Layer 2 Tunneling Protocol process (l2tpd) could not allocate a session handle while attempting to initialize a connection to the routing protocol process (rpd).

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_RPD_SOCKET_ALLOC_FAILED

System Log Message Unable to allocate socket address for rpd connection

Description The Layer 2 Tunneling Protocol process (l2tpd) could not allocate a socket address structure while attempting to initialize a connection to the routing protocol process (rpd).

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_RPD_TBL_LOCATE_BY_NAME

System Log Message Unable to locate rpd table by name: *error-message* (*error-code*)

Description The Layer 2 Tunneling Protocol process (l2tpd) attempted to retrieve a routing protocol process table by providing the table name. The attempt failed.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_RPD_TBL_LOCATE_FAILED

System Log Message Unable to locate table *table-name* for *identifier* (*return-value*)

Description The Layer 2 Tunneling Protocol process (l2tpd) could not retrieve the indicated routing protocol process table.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_RPD_VERSION_MISMATCH

System Log Message Versions of rpd and librpd did not match; not retrying

Description The Layer 2 Tunneling Protocol process (l2tpd) determined that the versions of the routing protocol process (rpd) and routing protocol library (librpd) were different. It halted its attempt to connect to the rpd process.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_RTSLIB_ASYNC_OPEN_FAILED

System Log Message Unable to open asynchronous routing socket connection

Description The Layer 2 Tunneling Protocol process (l2tpd) could not open a routing socket connection asynchronously. It uses the connection to communicate with the Junos operating system kernel.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_RTSLIB_OPEN_FAILED

System Log Message Unable to open routing socket connection

Description The Layer 2 Tunneling Protocol process (l2tpd) could not open a routing socket connection, which it uses to communicate with the Junos operating system kernel.

Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_SERVER_START_FAILED

System Log Message Startup of L2TP server failed
Description The Layer 2 Tunneling Protocol (L2TP) server did not start.

Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_SERVICE_NH_ADD_FAILED

System Log Message Unable to add service next hop (L2TP tunnel *tunnel-id*, session *session-id*): *error-message* (*error-code*)
Description The Layer 2 Tunneling Protocol process (l2tpd) maintains a copy of the Junos configuration database in memory. It could not add information about a service next hop to the in-memory configuration for the indicated tunnel and session.

Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_SERVICE_NH_DELETE_FAILED

System Log Message Unable to remove service next hop *next-hop* (VRF *vrf*, L2TP tunnel *tunnel-id*, session *session-id*)
Description The Layer 2 Tunneling Protocol process (l2tpd) maintains a copy of the Junos configuration database in memory. It could not remove information about the indicated service next hop from the in-memory configuration for the indicated tunnel and session.

Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_SESSION_CFG_ADD_ERROR

System Log Message Unable to add L2TP tunnel *tunnel-id*, session *session-id* to PIC configuration (*errno error-code*)
Description The Layer 2 Tunneling Protocol process (l2tpd) maintains a copy of the Junos configuration database in memory. It could not add information about the indicated session and tunnel to the in-memory configuration for the PIC.

Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_SESSION_CFG_ADD_FAILED

System Log Message Unable to add L2TP tunnel *tunnel-id*, session *session-id* to PIC configuration
Description The Layer 2 Tunneling Protocol process (l2tpd) maintains a copy of the Junos configuration database in memory. It could not add information about the indicated session and tunnel to the in-memory configuration for the PIC.

Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_SESSION_CFG_DELETE_FAILED

System Log Message Unable to remove L2TP tunnel *tunnel-id*, session *session-id* from PIC configuration
Description The Layer 2 Tunneling Protocol process (l2tpd) maintains a copy of the Junos configuration database in memory. It could not remove information about the indicated session and tunnel from the in-memory configuration for the PIC.

Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_SESSION_DELETE_FAILED

System Log Message Unable to delete session (L2TP tunnel *tunnel-id*, session *session-id*, errno *error-code*)
Description The Layer 2 Tunneling Protocol process (l2tpd) could not delete information about the indicated tunnel and session.

Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_SESSION_IFF_NOT_FOUND

System Log Message Unable to find family structure for interface *interface-name* (L2TP tunnel *tunnel-id*, session *session-id*)
Description The Layer 2 Tunneling Protocol process (l2tpd) could not retrieve the interface family structure for the indicated logical interface index in the indicated tunnel and session.

Type Error: An error occurred
Severity error

Facility LOG_NEWS

L2TPD_SESSION_IFL_ADD_FAILED

System Log Message *function-name*: unable to assign session *session-id* to interface *interface-name*

Description The Layer 2 Tunneling Protocol process (l2tpd) could not associate the indicated session with the indicated logical interface.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_SESSION_IFL_ALLOC_FAILED

System Log Message *function-name*: unable to allocate memory for session *session-id*, interface *interface-name*

Description The Layer 2 Tunneling Protocol process (l2tpd) could not allocate memory for the indicated session to be associated with the indicated logical interface.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_SESSION_IFL_CLI_TREE_ALLOC

System Log Message Unable to allocate memory for session tree for interface *interface-name*

Description The Layer 2 Tunneling Protocol process (l2tpd) maintains a copy of the Junos configuration database in memory. It could not allocate memory for a command-line interface (CLI)-specific session tree structure for the indicated logical interface.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_SESSION_IFL_DELETED

System Log Message *function-name*: interface *interface-name* is deleted

Description The Layer 2 Tunneling Protocol process (l2tpd) detected that the configuration information for the indicated logical interface was deleted for a session.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_SESSION_IFL_DELETE_FAILED

System Log Message *function-name*: unable to delete session *identifier* from interface *interface-name*

Description The Layer 2 Tunneling Protocol process (l2tpd) could not delete information about a session from the configuration information for a logical interface.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_SESSION_IFL_GET_FAILED

System Log Message *function-name: unable to find interface interface-name*

Description The Layer 2 Tunneling Protocol process (l2tpd) could not retrieve configuration information about the indicated logical interface, to which it was going to add session information.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_SESSION_IFL_NOT_EQUAL

System Log Message *function-name: interface interface-name not equal*

Description The Layer 2 Tunneling Protocol process (l2tpd) could not add a session for the indicated logical interface.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_SESSION_IFL_NOT_FOUND

System Log Message Unable to find interface *interface-name* (L2TP tunnel *tunnel-id*, session *session-id*)

Description The Layer 2 Tunneling Protocol process (l2tpd) could not find the indicated logical interface corresponding to the indicated tunnel and session.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_SESSION_IFL_OCCUPIED

System Log Message *function-name: interface interface-name already has associated session (value1/value2)*

Description The Layer 2 Tunneling Protocol process (l2tpd) determined that the indicated logical interface already had an associated session.

Type Error: An error occurred

Severity error
Facility LOG_NEWS

L2TPD_SESSION_IFL_REMOVE_FAILED

System Log Message Unable to remove L2TP tunnel *tunnel-id*, session *session-id* from logical interface (errno *error-code*)

Description The Layer 2 Tunneling Protocol process (l2tpd) could not remove information about the indicated tunnel and session from the record it maintains for a logical interface.

Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_SESSION_INVALID_PEER_IP

System Log Message Invalid peer address *peer-address* in IPCP UP (L2TP tunnel *tunnel-id*, session *session-id*); closing session

Description The Layer 2 Tunneling Protocol process (l2tpd) received an IP Control Protocol (IPCP) 'UP' message for the indicated tunnel and session that included the indicated IP address for a peer. The address was invalid, and the l2tpd process started closing down the session.

Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_SESSION_ROUTE_ADD_FAILED

System Log Message Unable to add PPP route (L2TP tunnel *tunnel-id*, session *session-id*, errno *error-code*)

Description The Layer 2 Tunneling Protocol process (l2tpd) could not add a Point-to-Point Protocol (PPP) route for the indicated tunnel and session.

Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_SESSION_RT_TBL_NOT_FOUND

System Log Message Unable to find route table *table-id* for interface *interface-name* (L2TP tunnel *tunnel-id*, session *session-id*)

Description The Layer 2 Tunneling Protocol process (l2tpd) could not retrieve the indicated routing table associated with the indicated logical interface in the indicated tunnel and session.

Type Error: An error occurred

Severity error
Facility LOG_NEWS

L2TPD_SESSION_TUNNEL_ID_MISMATCH

System Log Message Tunnel ID *tunnel-id* in message does not match L2TP tunnel *l2tp-tunnel-id*, session *session-id*

Description The Layer 2 Tunneling Protocol process (l2tpd) received a message with the indicated tunnel identifier, which did not match the identifier stored for the indicated tunnel and session.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_SETSOCKOPT_FAILED

System Log Message setsockopt() failed *operation: error-message*

Description The Layer 2 Tunneling Protocol process (l2tpd) could not set socket options during the indicated operation.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_SET_ASYNC_CONTEXT

System Log Message Unable to set asynchronous context (*errno error-code*)

Description The Layer 2 Tunneling Protocol process (l2tpd) could not set asynchronous context for a routing socket connection, which it uses to communicate with the Junos operating system kernel.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_SHOW_MULTILINK

System Log Message Detail level *level* is not supported by 'show services l2tp multilink' command

Description The 'show services l2tp multilink' command was issued with the indicated option to specify the amount of information to return, but the command does not support that option.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_SHOW_SESSION

System Log Message Detail level *level* is not supported by 'show services l2tp session' command

Description The 'show services l2tp session' command was issued with the indicated option to specify the amount of information to return, but the command does not support that option.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_SHOW_TUNNEL

System Log Message Detail level *level* is not supported by 'show services l2tp tunnel' command

Description The 'show services l2tp tunnel' command was issued with the indicated option to specify the amount of information to return, but the command does not support that option.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_SOCKET_FAILED

System Log Message socket() failed *operation: error-message*

Description The Layer 2 Tunneling Protocol process (l2tpd) could not open socket during the indicated operation.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_SUBUNIT_ROUTE_ALLOC_FAILED

System Log Message Unable to allocate L2TP route (tunnel *tunnel-id*, session *session-id*)

Description The Layer 2 Tunneling Protocol process (l2tpd) could not allocate a subunit route record for the indicated tunnel and session.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_TRACE_FILE_OPEN_FAILED

System Log Message Unable to open trace file: *error-message*

Description The Layer 2 Tunneling Protocol process (l2tpd) could not open its trace file.

Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_TUNNEL_CFG_ADD_FAILED

System Log Message Unable to add L2TP tunnel *tunnel-id* to PIC configuration (errno *error-code*)
Description The Layer 2 Tunneling Protocol process (l2tpd) maintains a copy of the Junos configuration database in memory. It could not add information about the indicated tunnel to the in-memory configuration for the PIC.

Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_TUNNEL_CFG_ADD_INV_ADDR

System Log Message Unable to add L2TP tunnel *tunnel-id* to PIC configuration: address invalid
Description The Layer 2 Tunneling Protocol process (l2tpd) maintains a copy of the Junos configuration database in memory. It could not add information about the indicated tunnel to the in-memory configuration for the PIC, because the local or remote address provided for the tunnel was invalid.

Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_TUNNEL_CFG_DELETE_FAILED

System Log Message Unable to remove L2TP tunnel *tunnel-id* from PIC configuration
Description The Layer 2 Tunneling Protocol process (l2tpd) maintains a copy of the Junos configuration database in memory. It could not remove information about the indicated tunnel from the in-memory configuration for the PIC.

Type Error: An error occurred
Severity error
Facility LOG_NEWS

L2TPD_TUNNEL_DELETE_FAILED

System Log Message Unable to delete L2TP tunnel *tunnel-id* (errno *error-code*)
Description The Layer 2 Tunneling Protocol process (l2tpd) could not delete information about the indicated tunnel.

Type Error: An error occurred

Severity error
Facility LOG_NEWS

L2TPD_TUNNEL_DEST_IF_LOOKUP_FAIL

System Log Message Unable to find destination interface for L2TP tunnel *tunnel-id* remote address: *error-message*

Description The Layer 2 Tunneling Protocol process (l2tpd) tried to use route lookup to determine which local logical interface to use to reach the remote end of the indicated tunnel. The attempt failed.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_TUNNEL_GROUP_ADD_FAILED

System Log Message Unable to create L2TP tunnel group

Description The Layer 2 Tunneling Protocol process (l2tpd) could not create a tunnel group.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_TUNNEL_GROUP_CFG_ADD_FAIL

System Log Message Unable to add tunnel group *tunnel-group* (service set *service-set*) to configuration for PIC *pic-slot*: *error-message*

Description The Layer 2 Tunneling Protocol process (l2tpd) maintains a copy of the Junos configuration database in memory. It could not add information about the indicated tunnel group and service set to the in-memory configuration for the indicated PIC.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_TUNNEL_GROUP_CFG_DEL_FAIL

System Log Message Unable to delete tunnel group *tunnel-group* (service set *service-set*): *error-code*

Description The Layer 2 Tunneling Protocol process (l2tpd) could not delete information about the indicated tunnel group and service set.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_TUNNEL_GROUP_CREATE_FAILED

System Log Message	Unable to create L2TP module for tunnel group <i>address</i>
Description	The Layer 2 Tunneling Protocol process (l2tpd) could not create the indicated protocol tunnel group.
Type	Error: An error occurred
Severity	error
Facility	LOG_NEWS

L2TPD_TUNNEL_GROUP_DELETE_FAILED

System Log Message	Unable to delete L2TP tunnel group <i>tunnel-group-id</i> (errno <i>error-code</i>)
Description	The Layer 2 Tunneling Protocol process (l2tpd) could not delete information about the indicated tunnel group.
Type	Error: An error occurred
Severity	error
Facility	LOG_NEWS

L2TPD_TUNNEL_GROUP_IDX_MISMATCH

System Log Message	Tunnel group index <i>index1</i> in message does not match index <i>index2</i> stored for L2TP tunnel <i>tunnel-id</i>
Description	The Layer 2 Tunneling Protocol process (l2tpd) received a message with the indicated tunnel group index, which did not match the indicated group tunnel index stored for the indicated tunnel.
Type	Error: An error occurred
Severity	error
Facility	LOG_NEWS

L2TPD_TUNNEL_GROUP_RESTART_FAIL

System Log Message	Unable to restart L2TP module for tunnel group
Description	The Layer 2 Tunneling Protocol process (l2tpd) could not restart a protocol tunnel group.
Type	Error: An error occurred
Severity	error
Facility	LOG_NEWS

L2TPD_USER_AUTHN_NOT_FOUND

System Log Message	Unable to find user profile <i>username</i> during PPP authentication
---------------------------	---

Description The Layer 2 Tunneling Protocol process (l2tpd) could not retrieve the user profile for the indicated username, which it needs for Point-to-Point Protocol (PPP) authentication of a session.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_USER_AUTHN_ORDER_UNKNOWN

System Log Message Unknown authentication order *authentication-order* (tunnel *tunnel-id*, session *session-id*)

Description The Layer 2 Tunneling Protocol process (l2tpd) did not recognize the indicated authentication order, which was specified for Point-to-Point (PPP) authentication of the indicated tunnel and session.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

L2TPD_USER_AUTHN_PWD_NOT_FOUND

System Log Message Unable to retrieve password during PPP authentication of user *username*

Description The Layer 2 Tunneling Protocol process (l2tpd) could not retrieve the password for the indicated username, which it needs for Point-to-Point Protocol (PPP) authentication of a session.

Type Error: An error occurred

Severity error

Facility LOG_NEWS

CHAPTER 56

LACPD System Log Messages

This chapter describes messages with the **LACPD** prefix. They are generated by the Link Aggregation Control Protocol (LACPD) process (lacpd), which supports LACP functions for aggregated Ethernet interfaces.

LACPD_MEMORY_ALLOCATION_FAILED

System Log Message	Unable to allocate memory for interface <i>interface-name</i>
Description	The Link Aggregation Control Protocol process (lacpd) could not allocate memory for the indicated interface.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHAPTER 57

LFMD System Log Messages

This chapter describes messages with the **LFMD** prefix. They are generated by the link-fault management process (lfmd), which supports Operation, Administration, and Maintenance (OAM) functions that are defined in the Institute of Electrical and Electronics Engineers (IEEE) 802.3ah standard for Ethernet interfaces.

LFMD_RT SOCK_OPEN_FAILED

System Log Message	Unable to open synchronous routing socket: <i>error-message</i>
Description	The Ethernet Operation, Administration and Management link-fault management process (lfmd) could not open a routing socket to create a connection.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

LIBESPTASK System Log Messages

This chapter describes messages with the LIBESPTASK prefix.

LIBESPTASK_SNMP_CONN_PROG

System Log Message	<i>function-name: error-message</i>
Description	The indicated error occurred while the process using libesptask was connecting to the Simple Network Management Protocol (SNMP) master agent.
Type	Error: An error occurred
Severity	info
Facility	ANY

LIBESPTASK_SNMP_CONN_QUIT

System Log Message	<i>function-name: unable to connect to SNMP agent (pathname): error-message</i>
Description	The process using libesptask could not connect to the indicated Simple Network Management Protocol (SNMP) master agent.
Type	Error: An error occurred
Severity	error
Facility	ANY

LIBESPTASK_SNMP_CONN_RETRY

System Log Message	<i>function-name: reattempting connection to SNMP agent (pathname): error-message</i>
Description	The process using libesptask tried again to connect to the indicated Simple Network Management Protocol (SNMP) master agent after a connection attempt failed.
Type	Error: An error occurred
Severity	error
Facility	ANY

LIBESPTASK_SNMP_INVALID_SOCKET

System Log Message	<i>function-name: socket file-descriptor is invalid</i>
---------------------------	---

Description The process using libesptask could not send a message to a Simple Network Management Protocol (SNMP) master agent because the indicated socket is invalid.

Type Error: An error occurred

Severity error

Facility ANY

LIBESPTASK_SNMP_SOCKOPT_BLOCK

System Log Message *function-name*: unable to set nonblocking option

Description The process using libesptask could not set a socket to nonblocking mode after connecting to the Simple Network Management Protocol (SNMP) master agent.

Type Error: An error occurred

Severity error

Facility ANY

LIBESPTASK_SNMP_SOCKOPT_RECVBUF

System Log Message *function-name*: unable to set recvbuf option

Description The process using libesptask could not set the size of the kernel receive buffer, which allows it to accept the largest possible packet from the Simple Network Management Protocol (SNMP) master agent.

Type Error: An error occurred

Severity error

Facility ANY

LIBESPTASK_SNMP_SOCKOPT_SENDBUF

System Log Message *function-name*: unable to set sendbf option

Description The process using libesptask could not set the size of the kernel send buffer, which allows it to send the largest possible packet to the Simple Network Management Protocol (SNMP) master agent.

Type Error: An error occurred

Severity error

Facility ANY

CHAPTER 59

LIBJNX System Log Messages

This chapter describes messages with the **LIBJNX** prefix. They are generated by processes that call routines in the libjuniper library, which includes routines for creating and managing child processes, parsing machine and interface addresses, tracing, file I/O, and other functions.

LIBJNX_AUDIT_ERROR

System Log Message	<i>function-name: error-message</i>
Description	A JUNOS process could not notify the audit process (auditd) about user activity related to system accounting, because of an interprocess communication (IPC) error.
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	Possible reasons include (a) auditd was not running (b) auditd was still initializing after a restart (c) there was a socket error.
Action	Contact your technical support representative.

LIBJNX_COMPRESS_EXEC_FAILED

System Log Message	Unable to compress file ' <i>filename</i> ' using <i>program-name: error-message</i>
Description	A JUNOS process tried to use the indicated utility to create a compressed version of the indicated old system log file. The attempt failed for the indicated reason.
Type	Error: An error occurred
Severity	info
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

LIBJNX_DEFAULT_IP_ADDR_NOT_SET

System Log Message	Unable to retrieve system default IP address: not set in kernel (<i>error-message</i>)
Description	A JUNOS process could not retrieve the system default IP address from the kernel, because the address is not defined there.
Type	Error: An error occurred
Severity	critical
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

LIBJNX_EVLIB_FAILURE

System Log Message	<i>function-name: error-message</i>
Description	A JUNOS process called the indicated function in the event library. The function failed for the indicated reason.
Type	Error: An error occurred
Severity	emergency
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

LIBJNX_EXEC_EXITED

System Log Message	Command stopped: PID <i>pid</i> , signal= <i>'return-value'</i> <i>core-dump-status</i> , command ' <i>command</i> '
Description	A JUNOS process created a child process to execute the indicated command for it. The child process stopped unexpectedly.
Type	Error: An error occurred
Severity	notice
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

LIBJNX_EXEC_FAILED

System Log Message	Child exec failed for command ' <i>command</i> ': <i>error-message</i>
---------------------------	--

Description	A JUNOS process called the <code>exec()</code> system call while creating a child process to execute the indicated command for it. The system call failed.
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

LIBJNX_EXEC_PIPE

System Log Message	Unable to create pipes for command ' <i>command</i> ': <i>error-message</i>
Description	A JUNOS process created a child process to execute the indicated command for it. Its attempt to create pipes for communication with the child failed.
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

LIBJNX_EXEC_SINGALED

System Log Message	Command received signal: PID <i>pid</i> , signal <i>signal-name</i> core-dump-status, command ' <i>command</i> '
Description	A JUNOS process created a child process to execute the indicated command for it. The child process received the indicated signal and exited.
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

LIBJNX_EXEC_WEXIT

System Log Message	Command exited: PID <i>pid</i> , status <i>return-value</i> core-dump-status, command ' <i>command</i> '
Description	A JUNOS process created a child process to execute the indicated command for it. The child process exited abnormally with the indicated exit code.

Type	Error: An error occurred
Severity	notice
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

LIBJNX_FILE_COPY_FAILED

System Log Message	Failed to copy from <i>source-filename</i> to <i>destination-filename</i>
Description	A JUNOS process could not copy the indicated source file to the indicated destination name or location.
Type	Error: An error occurred
Severity	error
Facility	ANY

LIBJNX_FILE_SYSTEM_FAIL

System Log Message	<i>pathname: error-message</i>
Description	A JUNOS process could not obtain status information for the indicated file system.
Type	Event: This message reports an event, not an error
Severity	error
Facility	ANY

LIBJNX_FILE_SYSTEM_SPACE

System Log Message	Not enough space left on device <i>pathname</i>
Description	A JUNOS process found that the indicated file system did not have the free space needed for storing temporary files.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	ANY

LIBJNX_INVALID_CHASSIS_ID

System Log Message	<i>function-name: invalid chassis ID chassis-id</i>
Description	A JUNOS process could not determine the hostname for the master Routing Engine on a routing node in a routing matrix, because the indicated chassis ID provided for the routing platform was invalid.
Type	Error: An error occurred

Severity error

Facility ANY

LIBJNX_INVALID_RE_SLOT_ID

System Log Message *function-name: invalid Routing Engine slot ID routing-engine-slot*

Description A JUNOS process could not determine the hostname for a Routing Engine, because the indicated Routing Engine slot ID was invalid.

Type Error: An error occurred

Severity error

Facility ANY

LIBJNX_INVALID_XML_DATA

System Log Message Invalid XML data '\data'

Description The XML parser closed its session with a client application because the indicated XML data sent by the client was invalid.

Type Error: An error occurred

Severity error

Facility ANY

LIBJNX_PRIV_LOWER_FAILED

System Log Message Unable to lower privilege level: *error-message*

Description A JUNOS process attempted to revert its effective user ID to the original user. The attempt failed.

Type Error: An error occurred

Severity error

Facility ANY

Cause An internal software failure occurred.

Action Contact your technical support representative.

LIBJNX_PRIV_RAISE_FAILED

System Log Message Unable to raise privilege level: *error-message*

Description A JUNOS process attempted to set its effective user ID to the root user. The attempt failed.

Type Error: An error occurred

Severity error

Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

LIBJNX_REPLICATE_RCP_ERROR

System Log Message	<i>operation: operational-status</i>
Description	The rcp command failed during replication.
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

LIBJNX_REPLICATE_RCP_EXEC_FAILED

System Log Message	rcp failed: <i>error-message</i>
Description	A JUNOS process created a child process to copy a file to the other Routing Engine. The copy operation failed.
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

LIBJNX_SNMP_ENGINE_FILE_FAILURE

System Log Message	<i>function-name: operation: operation filename: error-message</i>
Description	A JUNOS process could not perform the indicated operation on the indicated SNMP engine data file.
Type	Error: An error occurred
Severity	critical
Facility	ANY
Cause	An internal software failure occurred.

Action Contact your technical support representative.

LIBJNX_SNMP_ENGINE_SCAN_FAILURE

System Log Message *function-name: fscanf : filename scanning: data Error: error-message*

Description A JUNOS process could not perform the scan operation on the indicated SNMP engine data file.

Type Error: An error occurred

Severity critical

Facility ANY

Cause An internal software failure occurred.

Action Contact your technical support representative.

LIBJNX_SOCKET_FAILURE

System Log Message *operation: error-message*

Description Various system processes use Transmission Control Protocol (TCP), User Datagram Protocol (UDP), and Reliable Data Protocol (RDP) sockets. The indicated socket operation failed for the indicated reason.

Type Error: An error occurred

Severity emergency

Facility ANY

Cause An internal software failure occurred.

Action Contact your technical support representative.

LIBJNX_XML_DECODE_FAILED

System Log Message Invalid XML encoding '*data*', skipping to ';'.

Description The XML parser ignored the indicated XML data sent by a client application, because the XML encoding of the data was invalid. The parser skipped ahead to the likely endpoint for the invalid data.

Type Error: An error occurred

Severity error

Facility ANY

Cause A possible cause is improper escaping of character constants in the data stream.

Action Contact your technical support representative.

CHAPTER 60

LIBJSNMP System Log Messages

This chapter describes messages with the **LIBJSNMP** prefix. They are generated by the `libjsnmp` process.

LIBJSNMP_CTX_FAILURE

System Log Message	<code>snmp_ms_trap_api</code> return <i>argument</i>
Description	Sub-agents SNMP context either too long or of zero size
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

LIBJSNMP_IPC_ERROR

System Log Message	<i>argument: sock:port</i> (type: <i>port-type</i>)
Description	Error in SNMP related IPC messages size mismatch, corruption or memory failure
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

LIBJSNMP_IPC_READ_ERROR

System Log Message	Unable to read <i>inbound-bytes</i> bytes: <i>sock: port</i> (type: <i>port-type</i>)
Description	Error in reading IPC messages during SNMP related messaging

Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

LIBJSNMP_MTHD_API_UNKNOWN_TYPE

System Log Message	unknown oev type: <i>tag-type</i>
Description	Internal error - Unknown SNMP object indexing type
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

LIBJSNMP_NS_LOG_CRIT

System Log Message	CRIT: <i>argument</i>
Description	Logs for SNMP critical message
Type	Error: An error occurred
Severity	critical
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

LIBJSNMP_NS_LOG_EMERG

System Log Message	EMERG: <i>argument</i>
Description	SNMP errors with LOG_EMERG as severity
Type	Error: An error occurred
Severity	emergency
Facility	ANY
Cause	An internal software failure occurred.

Action Contact your technical support representative.

LIBSNMP_NS_LOG_ERR

System Log Message ERR: *argument*

Description SNMP errors with LOG_ERR as severity

Type Error: An error occurred

Severity error

Facility ANY

Cause An internal software failure occurred.

Action Contact your technical support representative.

LIBSNMP_OID_GEN_FAILED

System Log Message Unable to generate OID: *object-name (system-error-message)*

Description Unable to translate SNMP object string to OID

Type Error: An error occurred

Severity error

Facility ANY

Cause An internal software failure occurred.

Action Contact your technical support representative.

LIBSNMP_READ_LEN_ERR

System Log Message error *error-code* reading routing socket

Description Failure while reading rtsocket for SNMP related operation

Type Error: An error occurred

Severity error

Facility ANY

Cause An internal software failure occurred.

Action Contact your technical support representative.

LIBSNMP_RTMSIZE_MISMATCH_ERR

System Log Message routing socket msg size *argument* of *argument1* (call buf = *argument2*)

Description Error in message length while reading rtsocket for SNMP related operation

Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

LIBJSNMP_SMS_HDR_ERR

System Log Message	problem with hdr size (<i>record-size</i>) or msg size (<i>size</i>)
Description	Discrepancy in sub-agent message length and header size
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

LIBJSNMP_SMS_MSG_ERR

System Log Message	received <i>received-value</i> bytes, expected <i>expected-value</i> bytes
Description	Various discrepancies in sub-agent message lengths. SNMP Message errors
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

LIBJSNMP_SOCKET_OPEN_ERR

System Log Message	routing socket open error <i>argument</i>
Description	Failure in opening routing socket
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	An internal software failure occurred.

Action Contact your technical support representative.

LIBSNMP_SOCKET_VER_MISMATCH

System Log Message routing socket version mismatch

Description Routing socket version mismatch between kernel and application

Type Error: An error occurred

Severity error

Facility ANY

Cause An internal software failure occurred.

Action Contact your technical support representative.

LIBSNMP_TRAP_API_FAILURE

System Log Message *function-name: Trap API: argument argument1*

Description Misc. error while creating SNMP traps

Type Error: An error occurred

Severity error

Facility ANY

Cause An internal software failure occurred.

Action Contact your technical support representative.

LIBSNMP_TRAP_UTILS_ERR

System Log Message unknown trap object: *object-name*

Description Trying to send invalid object as varbind while creating SNMP traps

Type Error: An error occurred

Severity error

Facility ANY

Cause An internal software failure occurred.

Action Contact your technical support representative.

CHAPTER 61

LIBMSRPC System Log Messages

This chapter describes messages with the **LIBMSRPC** prefix. They are generated by the mspinfo process, which is responsible for RPC communication between the Routing Engine (RE) and the Multiservices PICs.

LIBMSRPC_CLIENT_INIT_FAILED

System Log Message	Can't create msrpc client: <i>error-message</i>
Description	A JUNOS process (mspinfo) could not establish initialization of the RPC client.
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	Possible reasons: process is out of memory
Action	Contact your technical support representative.

LIBMSRPC_CLIENT_KCOM_FAILED

System Log Message	Can't initialize kcom for msrpc client: <i>error-message</i>
Description	A JUNOS process (mspinfo) could not establish initialization of the kcom subsystem.
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	Possible reasons: can't initialize kcom services.
Action	Contact your technical support representative.

LIBMSRPC_CLIENT_KCOM_NO_IF

System Log Message	No active extension-provider interfaces
---------------------------	---

Description	A JUNOS process (mspinfo) could not find any configured and active extension-provider interfaces.
Type	Error: An error occurred
Severity	notice
Facility	ANY
Cause	Possible reasons: can't initialize kcom services.
Action	Contact your technical support representative.

LIBMSRPC_CLIENT_NO_CONNECTION

System Log Message	Failed connecting <i>fpc=fpc-slot, pic=pic-slot</i>
Description	Remote execution of the command given from the RE to the PIC failed, can not connect to the PIC.
Type	Error: An error occurred
Severity	notice
Facility	ANY
Cause	Possible reasons: a)PIC appears online but is not responding b)msrpc server is not running on the PIC.
Action	Contact your technical support representative.

LIBMSRPC_CLIENT_NO_REPLY

System Log Message	Error executing " <i>command</i> ": no reply from the PIC
Description	Remote execution of the command given from the RE to the PIC failed, no reply from the PIC.
Type	Error: An error occurred
Severity	notice
Facility	ANY
Cause	Possible reasons: a)wrong command b)insufficient permissions c)wrong arguments d)PIC appears online but is not responding e)msrpc server is not running on the PIC.
Action	Contact your technical support representative.

LIBMSRPC_CLIENT_PIC_DOWN

System Log Message	Interface <i>interface-name</i> is down
Description	Remote execution of the command given from the RE to the PIC failed, the PIC is down.

Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	Possible reasons: the given PIC is not responding and/or is offline.
Action	Contact your technical support representative.

LIBMSRPC_CLIENT_WRONG_OUTPUT

System Log Message	Error executing " <i>command</i> ": output length exceeds <i>correct-length</i> characters
Description	Remote execution of the command given from the RE to the PIC failed, PIC returned unexpected output.
Type	Error: An error occurred
Severity	notice
Facility	ANY
Cause	Possible reasons: a)wrong command b)wrong arguments.
Action	Contact your technical support representative.

CHAPTER 62

LICENSE System Log Messages

This chapter describes messages with the **LICENSE** prefix. They are generated by processes that call routines in the liblicense library, which provide software license management functions on a routing platform.

LICENSE_CONNECT_FAILURE

System Log Message	Connection could not be set up: <i>error-message</i>
Description	The indicated error occurred because a connection to the license-check process was not established.
Type	Error: An error occurred
Severity	error
Facility	ANY

LICENSE_CONN_TO_LI_CHECK_FAILURE

System Log Message	Process could not connect to license-check in <i>maximum-value</i> tries; giving up
Description	The indicated process failed to connect to the license-check process after the indicated maximum tries.
Type	Error: An error occurred
Severity	error
Facility	ANY

LICENSE_CONN_TO_LI_CHECK_SUCCESS

System Log Message	Connected to license-check
Description	The indicated process successfully connected to the license-check process.
Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

LICENSE_EXPIRED

System Log Message	License for feature <i>feature-name(feature-id)</i> expired
Description	The time-based license for the indicated feature expired. The feature remains inactive until a new license is installed.
Type	Event: This message reports an event, not an error
Severity	alert
Facility	LOG_DAEMON

LICENSE_EXPIRED_KEY_DELETED

System Log Message	License key " <i>filename</i> " has expired.
Description	The indicated license-key has been removed from the file-system.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	ANY

LICENSE_GRACE_PERIOD_APPROACHING

System Log Message	License grace period for feature <i>feature-name(feature-id)</i> will expire in <i>time</i>
Description	The indicated amount of time remained before the license grace period for the indicated feature would expire. If a new license was not installed within that time, the feature became inactive.
Type	Event: This message reports an event, not an error
Severity	alert
Facility	LOG_DAEMON

LICENSE_GRACE_PERIOD_EXCEEDED

System Log Message	License grace period for feature <i>feature-name(feature-id)</i> will expire in <i>time</i> (limit = <i>maximum-value</i>)
Description	The grace period for a scale license is about to expire. Unless the scale license is upgraded, the license will scale back to the licensed limit once the grace period expires.
Type	Event: This message reports an event, not an error
Severity	alert
Facility	LOG_DAEMON

LICENSE_GRACE_PERIOD_EXPIRED

System Log Message	License grace period for feature <i>feature-name(feature-id)</i> has expired
---------------------------	--

Description The grace period for a licensable feature has expired. Strict license enforcement will remain active until a new license is installed.

Type Event: This message reports an event, not an error

Severity alert

Facility LOG_DAEMON

LICENSE_LIST_MANAGEMENT

System Log Message Error occurred for feature *feature-name*: *error-message* (system error: *system-error-message*)

Description The management process (mgd) could not complete a license management command related to the indicated feature. If a system error is reported, it caused the problem.

Type Error: An error occurred

Severity error

Facility ANY

LICENSE_NEARING_EXPIRY

System Log Message License for feature *feature-name*(*feature-id*) expires in *time*

Description At the time this message was logged, the indicated amount of time remained before the time-based license for the indicated feature would expire. If a new license was not installed within that time, the feature became inactive.

Type Event: This message reports an event, not an error

Severity alert

Facility LOG_DAEMON

LICENSE_READ_ERROR

System Log Message recvmsg() failed:*error-message*

Description The indicated process failed to read an event sent to it, for the indicated reason.

Type Error: An error occurred

Severity error

Facility ANY

LICENSE_REG_ERROR

System Log Message Registration request failed: *current-value*

Description The license registration request failed. A request needs to be resent to the license-check process.

Type Error: An error occurred

Severity error

Facility ANY

LICENSE_SIGNATURE_VERIFY_FAILED

System Log Message Signature verification failed: *error-message*

Description The management process (mgd) could not verify a license because the license's signature was invalid.

Type Error: An error occurred

Severity error

Facility ANY

LICENSE_UNKNOWN_RESPONSE_TYPE

System Log Message unknown message type received: *current-value*

Description An unknown response type was received from the license-check process.

Type Error: An error occurred

Severity error

Facility ANY

LICENSE_VERIFICATION_FILE_ERROR

System Log Message License verification failed for file '*error-message*': *filename* (system error: *system-error-message*)

Description The management process (mgd) could not verify the indicated license file because of the indicated internal file-handling error.

Type Error: An error occurred

Severity error

Facility ANY

CHAPTER 63

LLDPD System Log Messages

This chapter describes messages with the **LLDPD** prefix. They are generated by the link layer discovery protocol process (lldpd) which is used by EX-series switches to learn and distribute device information on network links. The information allows the switch to quickly identify a variety of devices, including IP telephones, resulting in a LAN that interoperates smoothly and efficiently.

LLDPD_SYSTEM

System Log Message *reason: error-message*

Description A system call made by the Link Layer Discovery Protocol process (LLDPD) failed.

Type Error: An error occurred

Severity error

Facility LOG_KERN

Cause It is possible that the kernel lacked the resources to fulfill the request. LLDPD will recover.

CHAPTER 64

LOGIN System Log Messages

This chapter describes messages with the **LOGIN** prefix. They are generated by the login process (login), which performs authentication for Telnet sessions.

LOGIN_ABORTED

System Log Message	Client aborted login
Description	A login attempt was cancelled, either by the remote user or in response to a signal.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_AUTH

LOGIN_FAILED

System Log Message	Login failed for user <i>username</i> from host <i>hostname</i>
Description	A login attempt failed for the indicated username.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_AUTH

LOGIN_FAILED_LIMIT

System Log Message	Specified number of login failures (<i>limit</i>) for user ' <i>username</i> ' reached from ' <i>remote-address</i> '
Description	Several login attempts failed for the indicated username.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_AUTH

LOGIN_FAILED_SET_CONTEXT

System Log Message	Failed to set context for user <i>username</i>
---------------------------	--

Description The login process (login) could not set login context properties for the indicated user and cancelled the authentication attempt.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

LOGIN_FAILED_SET_LOGIN

System Log Message Failed to set login ID for user *username*: *error-message*

Description The login process (login) could not assume the user ID of the indicated user and cancelled the authentication attempt.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

LOGIN_HOSTNAME_UNRESOLVED

System Log Message Unable to resolve hostname *hostname*: *error-message*

Description The login process (login) could not resolve the indicated remote hostname for the indicated reason.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

Cause An internal software failure occurred.

LOGIN_INFORMATION

System Log Message User *username* logged in from host *hostname* on device *tty-name*

Description The indicated username was authenticated and logged into the shell specified for it in the password file.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_AUTH

LOGIN_MALFORMED_USER

System Log Message Invalid username: *username*

Description The indicated username was invalid.

Type Event: This message reports an event, not an error

Severity info
Facility LOG_AUTH

LOGIN_PAM_AUTHENTICATION_ERROR

System Log Message Failed password for user *username*
Description The login process (login) could not authenticate the indicated user via PAM.
Type Event: This message reports an event, not an error
Severity error
Facility LOG_AUTH

LOGIN_PAM_ERROR

System Log Message Failure while authenticating user *username: error-message*
Description The PAM authentication process failed for the indicated username, for the indicated reason.
Type Error: An error occurred
Severity error
Facility LOG_AUTH

LOGIN_PAM_MAX_RETRIES

System Log Message Too many retries while authenticating user *username*
Description The number of failed PAM authentication attempts for the indicated user exceeded the maximum limit.
Type Error: An error occurred
Severity error
Facility LOG_AUTH

LOGIN_PAM_STOP

System Log Message Failed to end PAM session: *error-message*
Description The login process (login) could not end the PAM authentication session, for the indicated reason.
Type Error: An error occurred
Severity error
Facility LOG_AUTH

LOGIN_PAM_USER_UNKNOWN

System Log Message Attempt to authenticate unknown user *username*

Description The login process (login) failed to authenticate the indicated user via PAM because the username was unknown.

Type Event: This message reports an event, not an error

Severity error

Facility LOG_AUTH

LOGIN_PASSWORD_EXPIRED

System Log Message Forcing change of expired password for user *username*

Description The password provided for the indicated username was expired and the user was prompted to set a new one.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_AUTH

LOGIN_REFUSED

System Log Message Login of user *username* from host *hostname* on device *tty-name* was refused: *reason*

Description A login attempt for the indicated username was rejected for the indicated reason.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_AUTH

LOGIN_ROOT

System Log Message User *username* logged in as root from host *hostname* on device *tty-name*

Description The indicated username was authenticated as a superuser and logged into the shell specified for the root user in the password file.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_AUTH

LOGIN_TIMED_OUT

System Log Message Login attempt timed out after *duration* seconds

Description A login attempt failed to complete in the maximum time allowed.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_AUTH

CHAPTER 65

LPDFD System Log Messages

This chapter describes messages with the **LPDFD** prefix. They are generated by the local policy decision function process (lpdfd). A policy decision function is a component in the IP multimedia subsystem that controls traffic entering the packet-switched network by allocating or denying IP bearer resources.

LPDFD_DYN_PDB_OPEN_FAILED

System Log Message	Failed to open profile database: <i>error-message</i>
Description	The local policy decision function process (lpdfd) failed to open the profile database.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

LPDFD_DYN_REGISTER_FAILED

System Log Message	Dynamic config register failed: <i>error-message</i>
Description	The local policy decision function process (lpdfd) failed to register with the dynamic configuration subsystem.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

LPDFD_PCONN_SERVER

System Log Message	<i>argument</i> : Cannot retrieve peer info for session. Error: <i>error-message</i>
Description	The local policy decision function process (lpdfd) pconn server failed to initialize
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHAPTER 66

LRMUX System Log Messages

This chapter describes messages with the **LRMUX** prefix. They are generated by the logical router multiplexer process (lrmuxd), which manages the multiple instances of the routing protocols process (rpd) on a machine running logical routers.

LRMUX_FAILED_EXEC

System Log Message	Failed to exec <i>command</i>
Description	The Logical System Multiplexer process (lrmuxd) issued the exec() system call to start a routing process (rpd) to check the validity of the configuration. The system call failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

LRMUX_LRPD_PID_LOCK

System Log Message	Lock not found on PID file <i>filename</i>
Description	The Logical System Multiplexer process (lrmuxd) could not find a lock for a logical system.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	A logical system process (rpd) died.

LRMUX_LRPD_PID_OPEN

System Log Message	Unable to open PID file <i>filename</i>
Description	The Logical System Multiplexer process (lrmuxd) could not open the indicated PID lock file for a logical system process (rpd).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

LRMUX_LRPD_SEND_HUP

System Log Message	Unable to send signal to PID <i>pid</i>
Description	The Logical System Multiplexer process (lrmuxd) could not forward a SIGHUP signal to a logical system process (rpd).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

LRMUX_PID_LOCK

System Log Message	Unable to lock PID file ' <i>filename</i> '
Description	The Logical System Multiplexer process (lrmuxd) attempted to lock the file that records its process ID (PID), which serves to prevent multiple instances of the lrmuxd process from running simultaneously. The attempt failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHAPTER 67

MCSN System Log Messages

This chapter describes messages with the **MCSN** prefix. They are generated by the multicast snooping process (mcsnoopd), which enables a Layer 2 device to examine the content of Layer 3 packets to determine which actions to perform.

MCSN_ABORT

System Log Message	abort <i>executable-name</i> [<i>pid</i>] version <i>version</i> built by <i>builder</i> on <i>date</i> : <i>error-message</i>
Description	The multicast snooping process (mcsnoopd) terminated because of an internal error.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Examine the messages that immediately follow this message in the system log for information about possible causes.
Cause	An internal software failure occurred.

MCSN_ACTIVE_TERMINATE

System Log Message	Exiting with active tasks: <i>task-name</i>
Description	After receiving multiple termination requests, the multicast snooping process (mcsnoopd) exited without performing the indicated cleanup tasks.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

MCSN_ASSERT

System Log Message	Assertion failed <i>executable-name</i> [<i>pid</i>]: file " <i>source-filename</i> ", line <i>line-number</i> : " <i>message</i> "
Description	The source code for the multicast snooping process (mcsnoopd) includes internal self-consistency checks. A check failed at the indicated line number in the indicated source file, causing the instance of mcsnoopd that was using the indicated binary and

had the indicated process ID (PID) to terminate. The process created a diagnostic core dump for analysis by technical support personnel.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Examine the messages that immediately follow this message in the system log for information about possible causes. Contact a technical support representative, and be ready to provide the list of messages and the diagnostic core dump, if requested.

MCSN_ASSERT_SOFT

System Log Message	Soft assertion failed <i>executable-name</i> [<i>pid</i>]: file " <i>source-filename</i> ", line <i>line-number</i> : " <i>message</i> ", daemon continued running
Description	The source code for the multicast snooping process (mcsnoopd) includes internal self-consistency checks. A check failed at the indicated line number in the indicated source file, but the instance of mcsnoopd that was using the indicated binary and had the indicated process ID (PID) continued running. The process created a diagnostic core dump for analysis by technical support personnel.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Examine the messages that immediately follow this message in the system log for information about possible causes. Contact a technical support representative, and be ready to provide the list of messages and the diagnostic core dump, if requested.

MCSN_EXIT

System Log Message	Exit <i>executable-name</i> [<i>pid</i>] version <i>version</i> built by <i>builder</i> on <i>date</i> , caller <i>address</i>
Description	The multicast snooping process (mcsnoopd) exited, either in response to a user request or because of a system error.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON
Cause	A system resource was unavailable, mcsnoopd did not understand an error, or a user terminated the process.

Action Examine the messages that immediately follow this message in the system log for information about possible causes.

MCSN_SCHED_CALLBACK_LONGRUNTIME

System Log Message *function-name: excessive runtime time during action of module*

Description The indicated submodule of the multicast snooping process (mcsnoopd) ran uninterrupted for the indicated period of time, which is considered excessive.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

Cause The duration was noted because task accounting is enabled. The function might be implemented inefficiently.

MCSN_SCHED_CUMULATIVE_LONGRUNTIME

System Log Message *function-name: excessive runtime (total of time in count callbacks) after action of module*

Description Several submodules of the multicast snooping process (mcsnoopd) ran uninterrupted for the indicated period of time, which is considered excessive.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

Cause The duration was noted because task accounting is enabled. The function might be implemented inefficiently.

MCSN_SIGNAL_TERMINATE

System Log Message *signal-name* termination signal received

Description In response to the indicated termination request, the multicast snooping process (mcsnoopd) terminated adjacencies with neighbors and shut down.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

MCSN_START

System Log Message *Start executable-name[pid] version version built date*

Description The multicast snooping process (mcsnoopd) started.

Type Event: This message reports an event, not an error

Severity info
Facility LOG_DAEMON

MCSN_SYSTEM

System Log Message *reason: error-message*

Description A system call made by the multicast snooping process (mcsnoopd) failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause It is possible that the kernel lacked the resources to fulfill the request. The mcsnoopd process will recover.

MCSN_TASK_BEGIN

System Log Message Commencing routing updates, version *mcsnoopd-version*, built *date* by *builder*

Description The multicast snooping process (mcsnoopd) started.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

MCSN_TASK_CHILDKILLED

System Log Message *task-name* terminated by SIG*signal-name**core-dump-status*

Description While a child process of the multicast snooping process (mcsnoopd) was performing the indicated operation, it terminated in response to the indicated signal.

Type Event: This message reports an event, not an error

Severity error

Facility LOG_DAEMON

MCSN_TASK_CHILDSTOPPED

System Log Message *task-name* stopped by SIG*signal-name*

Description While a child process of the multicast snooping process (mcsnoopd) was performing the indicated operation, it stopped in response to the indicated signal.

Type Event: This message reports an event, not an error

Severity error

Facility LOG_DAEMON

MCSN_TASK_FORK

System Log Message	Unable to fork <i>task-name: error-message</i>
Description	The multicast snooping process failed to create the indicated child process.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

MCSN_TASK_GETWD

System Log Message	getwd: <i>error-message</i>
Description	The getwd() system call made by the multicast snooping process (mcsnoopd) failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	It is possible that the kernel lacked the resources to fulfill the request. The mcsnoopd process will recover.

MCSN_TASK_MASTERSHIP

System Log Message	Assuming mastership
Description	The multicast snooping process (mcsnoopd) became active when the Routing Engine on which it was running assumed mastership.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

MCSN_TASK_NOREINIT

System Log Message	Reinitialization not possible
Description	The multicast snooping process (mcsnoopd) failed to reinitialize as requested, because it was running in a state that did not allow reconfiguration.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

MCSN_TASK_REINIT

System Log Message	Reinitializing
---------------------------	----------------

Description The multicast snooping process (mcsnoopd) reinitialized.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

MCSN_TASK_SIGNALIGNORE

System Log Message sigaction(SIG*signal-name*): *error-message*

Description The multicast snooping process (mcsnoopd) informed the kernel that it wished to ignore the indicated signal, but the kernel failed to process the request.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

CHAPTER 68

MCSNOOPD System Log Messages

This chapter describes messages with the **MCSNOOPD** prefix. They are generated by the multicast snooping process (mcsnoopd), which enables a Layer 2 device to examine the content of Layer 3 packets to determine which actions to perform.

MCSNOOPD_MGMT_TIMEOUT

System Log Message	Connection to management peer <i>process-name</i> timed out waiting for input
Description	The connection between the snooping process (mcsnoopd) and the indicated management process (mgd) timed out before input arrived from the mgd process.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON

CHAPTER 69

MIB2D System Log Messages

This chapter describes messages with the **MIB2D** prefix. They are generated by the Management Information Base II (MIB II) process (mib2d), which services requests for information gathered and reported by the Simple Network Management Protocol (SNMP).

MIB2D_ATM_ERROR

System Log Message	<i>function-name: error-message</i>
Description	The MIB II process (mib2d) could not process ATM-related information.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

MIB2D_CONFIG_CHECK_FAILED

System Log Message	<i>function-name: configuration database has errors</i>
Description	The portion of the candidate configuration related to the MIB II process (mib2d) was checked for validity during a 'commit' operation. The check failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	The configuration was invalid.
Action	Correct the invalid portion of the configuration as described in the error message on the console.

MIB2D_FILE_OPEN_FAILURE

System Log Message	Unable to open file ' <i>filename</i> ': <i>error-message</i>
---------------------------	---

Description The MIB II process (mib2d) could not open the indicated file.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause An internal software failure occurred.

Action Contact your technical support representative.

MIB2D_IFD_IFDINDEX_FAILURE

System Log Message Ifd index assigned to *interface-name* changed from *old-value* to *new-value*, removing old interface

Description There was a change to the ifd Index assigned to the indicated existing interface.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause An internal software failure occurred.

Action Contact your technical support representative.

MIB2D_IFD_IFINDEX_FAILURE

System Log Message SNMP index assigned to *interface-name* changed from *old-value* to *new-value*

Description There was a change to the SNMP ifIndex assigned to the indicated existing interface.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause An internal software failure occurred.

Action Contact your technical support representative.

MIB2D_IFL_IFINDEX_FAILURE

System Log Message SNMP index assigned to *interface-name.interface-unit* changed from *old-value* to *new-value*

Description There was a change to the SNMP ifIndex assigned to the indicated existing interface.

Type Error: An error occurred

Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

MIB2D_IF_FLAPPING_MISSING

System Log Message	<i>function-name</i> : interface flapping missing: ifname(<i>interface-name</i>) old if_anydown_flaps(<i>old-value</i>) if_anydown_flaps(<i>new-value</i>)
Description	The MIB II process (mib2d) is blocked on the kernel for synchronous message. If there is an interface flap (down and then back up again) in the time mib2d is blocked in the kernel, mib2d will miss asynchronous messages from the kernel about state changes.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

MIB2D_KVM_FAILURE

System Log Message	<i>function-name</i> : <i>reason</i> : <i>error-message</i>
Description	A call to the indicated function in the kernel virtual memory library failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

MIB2D_PMON_OVERLOAD_CLEARED_TRAP

System Log Message	Overload name: <i>overload-name</i> , interface: <i>interface-name</i>
Description	The MIB II process (mib2d) generated a jnxPMonOverloadCleared trap when it detected the clearing of an overload condition on the indicated monitoring services interface.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

MIB2D_PMON_OVERLOAD_SET_TRAP

System Log Message	Overload name: <i>overload-name</i> , interface: <i>interface-name</i>
---------------------------	--

Description The MIB II process (mib2d) generated a jnxPMonOverloadSet trap when it detected an overload condition on the indicated monitoring services interface.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

MIB2D_RTSLIB_READ_FAILURE

System Log Message *function-name: failed in operation object-name: index (error-message)*

Description A call to the indicated function in the routing socket library failed during the indicated operation on the indicated object.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause An internal software failure occurred.

Action Contact your technical support representative.

MIB2D_RTSLIB_SEQ_MISMATCH

System Log Message *function-name: sequence mismatch (expected-value, received-value), resyncing*

Description The indicated function in the routing socket library detected a sequence number mismatch. The MIB II process (mib2d) will resynchronize its data with the Junos kernel.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

MIB2D_SNMP_INDEX_ASSIGN

System Log Message *function-name: reason snmpid(snmp-interface-index)
ifname(interface-name.interface-unit)*

Description MIB2D can not assign snmp index for each interface.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause An internal software failure occurred.

Action Contact your technical support representative.

MIB2D_SNMP_INDEX_DUPLICATE

System Log Message	<i>function-name: duplicate snmpid(snmp-interface-index) old ifname(interface-name.interface-unit) new ifname(new-interface-name.kernel-interface-unit)</i>
Description	The SNMP index for first interface name was assigned the same SNMP index as second interface name.
Type	Error: An error occurred
Severity	emergency
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

MIB2D_SNMP_INDEX_UPDATE_STAT

System Log Message	<i>function-name reason filename</i>
Description	MIB2D can not get the status of SNMP index file
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

MIB2D_SNMP_INDEX_WRITE

System Log Message	<i>function-name: reason filename</i>
Description	MIB2D can not write into a file containing all the indices
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

MIB2D_SYSCTL_FAILURE

System Log Message	<i>function-name: sysctl type failed: error-message</i>
---------------------------	---

Description A request to the Junos kernel for system data failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause An internal software failure occurred.

Action Contact your technical support representative.

MIB2D_TRAP_HEADER_FAILURE

System Log Message *function-name: trap_request_header failed*

Description The MIB II process (mib2d) could not allocate a trap header.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause The Routing Engine is low on memory.

Action Contact your technical support representative.

MIB2D_TRAP_SEND_FAILURE

System Log Message *function-name: trap_request_send: error-message*

Description The MIB II process (mib2d) could not send a trap header.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause An internal software failure occurred.

Action Contact your technical support representative.

CHAPTER 70

MPLS_OAM System Log Messages

This chapter describes messages with the **MPLS_OAM** prefix. They are generated by the Multiprotocol Label Switching (MPLS) Operation, Administration, and Maintenance (OAM) process (mplsoamd), which supports traceroute operations for LDP label-switched paths (LSPs).

MPLS_OAM_FANOUT_LIMIT_REACHED

System Log Message	<i>fec-address</i> : traceroute fanout limit was reached
Description	The traceroute fanout limit was reached.
Type	Error: An error occurred
Severity	info
Facility	LOG_DAEMON
Action	Raise the traceroute fanout limit parameter.

MPLS_OAM_INVALID_SOURCE_ADDRESS

System Log Message	<i>fec-address</i> : source address <i>ip-address</i> is invalid
Description	The traceroute utility is configured to use an invalid source address.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Configure traceroute to use a valid source address.

MPLS_OAM_PATH_LIMIT_REACHED

System Log Message	<i>fec-address</i> : traceroute path limit was reached
Description	The traceroute path limit was reached.
Type	Error: An error occurred
Severity	info

Facility LOG_DAEMON
Action Raise the traceroute path limit parameter.

MPLS_OAM_SEND_FAILED

System Log Message *fec-address: unable to send probe (error-message)*

Description The Multiprotocol Label Switching (MPLS) Operation, Administration, and Maintenance (OAM) process (mplsoamd) could not send a traceroute probe packet.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

MPLS_OAM_SOCKET_OPEN_FAILED

System Log Message *fec-address: unable to open socket (error-message)*

Description The Multiprotocol Label Switching (MPLS) Operation, Administration, and Maintenance (OAM) process (mplsoamd) could not open a socket to initiate a traceroute operation.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

MPLS_OAM_SOCKET_SELECT_FAILED

System Log Message *fec-address: unable to select socket (error-message)*

Description The Multiprotocol Label Switching (MPLS) Operation, Administration, and Maintenance (OAM) process (mplsoamd) could not select a socket to initiate a traceroute operation.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

MPLS_OAM_TRACEROUTE_INTERRUPTED

System Log Message *fec-address: topology update interrupted traceroute*

Description A traceroute operation was interrupted by a topology change.

Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON
Action	Wait for the next scheduled traceroute operation.

MPLS_OAM_TTL_EXPIRED

System Log Message	<i>fec-address</i> : traceroute TTL limit was reached
Description	The time-to-live (TTL) limit for the traceroute utility was reached.
Type	Error: An error occurred
Severity	info
Facility	LOG_DAEMON
Action	Raise the traceroute TTL limit parameter.

MPLS_OAM_UNREACHABLE

System Log Message	<i>fec-address</i> : traceroute encountered unreachable node
Description	The traceroute utility encountered a node that does not have a computable destination address. The Multiprotocol Label Switching (MPLS) Operation, Administration, and Maintenance (OAM) process (mplsoamd) therefore could not send a probe to the node.
Type	Error: An error occurred
Severity	info
Facility	LOG_DAEMON
Action	Contact your technical support representative.

CHAPTER 71

NEXTHOP System Log Messages

This chapter describes messages with the **NEXTHOP** prefix. They are generated by the process that decides the next hop.

NEXTHOP_COMPONENTS_LIMIT_REACHED

System Log Message	Limit on components reached for flood next hop for routing instance ' <i>routing-instance</i> '
Description	The limit on the number of logical interfaces for a next hop was reached for the indicated routing instance and bridging domain. Only a subset of new interfaces were added to the next hop.
Type	Event: This message reports an event, not an error
Severity	error
Facility	ANY

CHAPTER 72

NSD System Log Messages

This chapter describes messages with the **NSD** prefix. They are generated by the network security process (nsd), which manages firewall configuration on routers running Junos OS with enhanced services.

NSD_MEMORY_ALLOC_FAILED

System Log Message	Unable to allocate <i>count</i> bytes of memory
Description	The network security process (nsd) could not allocate the indicated number of bytes of memory.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	It is possible that system memory is exhausted.
Action	Increase the amount of RAM in the Routing Engine.

NSD_RESTART_COMP_CFG_READ_FAILED

System Log Message	Subcomponent could not read configuration database
Description	As the network security process (nsd) restarted, one or more of its subcomponents could not read its configuration information from configuration database. The nsd process restarted anyway, and routing performance was not affected.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

NSD_SEC_NODE_COMP_SYNC_FAILED

System Log Message	One or more subcomponents could not sync their state on backup RE
Description	One or more subcomponents of the network security process (nsd) failed to synchronize their state when the nsd restarted on secondary mode.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

CHAPTER 73

NSTRACED System Log Messages

This chapter describes messages with the **NSTRACED** prefix. They are generated by the USP trace process (nstraced).

NSTRACED_MEMORY_ALLOC_FAILED

System Log Message	Unable to allocate <i>count</i> bytes of memory
Description	The USP trace process (nstraced) could not allocate the indicated number of bytes of memory.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	System memory was exhausted.
Action	Increase the amount of RAM in the Routing Engine.

NSTRACED_RESTART_CFG_READ_FAILED

System Log Message	Subcomponent could not read configuration database
Description	When the USP trace process (nstraced) restarted, it could not read its configuration information from the configuration database.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

PFE System Log Messages

This chapter describes messages with the **PFE** prefix. They are generated by the Packet Forwarding Engine controller, which manages packet forwarding functions.

PFE_ANALYZER_CFG_FAILED

System Log Message	Error in Analyzer <i>error-message</i> for index = <i>index</i> error-code = <i>error-code</i>
Description	The configuration analyzer terminated because an error occurred during the configuration.
Type	Error: An error occurred
Severity	error
Facility	ANY

PFE_ANALYZER_SHIM_CFG_FAILED

System Log Message	Error in Analyzer <i>error-message</i> for index = <i>index</i> error-code = <i>error-code</i>
Description	The configuration analyzer terminated because an error occurred while the chip was being programmed.
Type	Error: An error occurred
Severity	error
Facility	ANY

PFE_ANALYZER_TABLE_WRITE_FAILED

System Log Message	<i>index</i> Could not create analyzer <i>error-message</i> table
Description	The logical interfaces (ifl) index failed to configure the analyzer because of an error.
Type	Error: An error occurred
Severity	error
Facility	ANY

PFE_ANALYZER_TASK_FAILED

System Log Message	Following task failed : <i>error-message</i>
---------------------------	--

Description The task analyzer terminated because an error occurred during the task.

Type Error: An error occurred

Severity error

Facility ANY

PFE_CBF_UNSUPPORTED

System Log Message Internet Processor I does not support CoS-based forwarding

Description The Internet Processor I application-specific integrated circuit (ASIC) does not support class-of-service (CoS)-based forwarding (CBF).

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

PFE_COS_B2_ONE_CLASS

System Log Message COSMAN: classifier *classifier-id-new* for ifl *index* replaces classifier *classifier-id-old* still used

Description Only one classifier can be active on a B2-based FPC at any given time.

Type Error: An error occurred

Severity error

Facility ANY

PFE_COS_B2_UNSUPPORTED

System Log Message COSMAN: B2 FPC cannot support classifier type *classifier-type-name*

Description B2-based FPCs can only handle IP precedence classifiers. They do not support any other classifier.

Type Error: An error occurred

Severity error

Facility ANY

PFE_FW_DELETE_MISMATCH_ERR

System Log Message Instance mismatch for type (*installed-firewall-name* != *deleted-firewall-name*) ifl *logical-interface-index* family *protocol-family*

Description Before a firewall is deleted, it is sanity checked against what is installed in the forwarding topology. A mismatch was detected between the firewall to be deleted and the forwarding topology, and the delete operation was canceled.

Type Error: An error occurred

Severity error
Facility LOG_PFE

PFE_FW_IF_DIALER_ERR

System Log Message DFW: output *type (firewall-name)* on ifl *logical-interface-index* rejected, invalid interface

Description Firewalls that use the ipsec-sa action to forward traffic to an IP Security (IPSec) security association (SA) cannot be configured on the ES Physical Interface Card (PIC) that services the SA. That configuration creates traffic loops within the router and was probably unintended. The problematic filter was automatically removed from the indicated interface.

Type Error: An error occurred
Severity error
Facility LOG_PFE

PFE_FW_IF_INPUT_ERR

System Log Message DFW: input *type (firewall-name)* on ifl *logical-interface-index* rejected, invalid interface

Description Firewalls that use the ipsec-sa action to forward traffic to an IP Security (IPSec) security association (SA) cannot be configured on the ES Physical Interface Card (PIC) that services the SA. That configuration creates traffic loops within the router and was probably unintended. The problematic firewall was automatically removed from the indicated interface.

Type Error: An error occurred
Severity error
Facility LOG_PFE

PFE_FW_IF_OUTPUT_ERR

System Log Message DFW: output *type (firewall-name)* on ifl *logical-interface-index* rejected, invalid interface

Description Firewalls that use the ipsec-sa action to forward traffic to an IP Security (IPSec) security association (SA) cannot be configured on the ES Physical Interface Card (PIC) that services the SA. That configuration creates traffic loops within the router and was probably unintended. The problematic firewall was automatically removed from the indicated interface.

Type Error: An error occurred
Severity error
Facility LOG_PFE

PFE_FW_PSF_DELETE_MISMATCH_ERR

System Log Message Instance mismatch for *type (installed-firewall-name != deleted-firewall-name)* hardware label *index* family *protocol-family*

Description Before a postservice firewall is deleted, it is sanity checked against what is installed in the forwarding topology. A mismatch was detected between the firewall to be deleted and the forwarding topology, and the delete operation was canceled.

Type Error: An error occurred

Severity error

Facility LOG_PFE

PFE_FW_SYSLOG_ETH

System Log Message FW: *interface-name action destination-address source-address protocol-name (count packets)*

Description An Ethernet frame matched against a stateless firewall filter with the indicated 'syslog' action (A = Accept, D = Discard, R = Reject).

Type Event: This message reports an event, not an error

Severity info

Facility ANY

PFE_FW_SYSLOG_IP

System Log Message FW: *interface-name action protocol-name source-address destination-address source-port-or-type destination-port-or-code (count packets)*

Description An IP packet matched against a stateless firewall filter with the indicated 'syslog' action (A = Accept, D = Discard, R = Reject).

Type Event: This message reports an event, not an error

Severity info

Facility ANY

PFE_FW_SYSLOG_IP6_GEN

System Log Message FW: *interface-name action protocol-name source-address destination-address (count packets)*

Description An IP version 6 (IPv6) packet matched against a stateless firewall filter with the indicated 'syslog' action (A = Accept, D = Discard, R = Reject).

Type Event: This message reports an event, not an error

Severity info

Facility ANY

PFE_FW_SYSLOG_IP6_ICMP

System Log Message FW: *interface-name action protocol-name source-address destination-address type type code error-code (count packets)*

Description An IP version 6 (IPv6) Internet Control Message Protocol (ICMP) packet matched against a stateless firewall filter with the indicated 'syslog' action (A = Accept, D = Discard, R = Reject).

Type Event: This message reports an event, not an error

Severity info

Facility ANY

PFE_FW_SYSLOG_IP6_TCP_UDP

System Log Message FW: *interface-name* *action* *protocol-name* *source-address* *destination-address* sport:*source-port* dport:*destination-port* (*count* packets)

Description An IP version 6 (IPv6) Transmission Control Protocol/User Datagram Protocol (TCP/UDP) packet matched against a stateless firewall filter with the indicated 'syslog' action (A = Accept, D = Discard, R = Reject).

Type Event: This message reports an event, not an error

Severity info

Facility ANY

PFE_MGCP_MEM_INIT_FAILED

System Log Message Failed to create memory pool for *error-message*

Description Failed to initialize the MGCP memory pool.

Type Error: An error occurred

Severity error

Facility LOG_PFE

PFE_MGCP_REG_HDL_FAIL

System Log Message Failed to register *object-name* handle

Description Failed to register the handler with the external module.

Type Error: An error occurred

Severity error

Facility LOG_PFE

PFE_NH_RESOLVE_THROTTLED

System Log Message Next-hop resolution requests from interface *logical-interface-index* throttled

Description The Packet Forwarding Engine throttled next-hop resolution requests from the indicated interface, because the high number of requests might constitute an attempted denial-of-service (DoS) attack. Examples of events that generate next-hop resolution requests include an attempt to forward a packet without an Address Resolution Protocol

(ARP) entry and receiving a multicast data packet with no matching route. Normally, the Packet Forwarding Engine forwards the requests to the Routing Engine.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_PFE

PFE_SCCP_ADD_PORT_FAIL

System Log Message Failed to add SCCP ALG port to application definition table
Description Failed to add the SCCP port to the application definition table.

Type Error: An error occurred
Severity error
Facility LOG_PFE

PFE_SCCP_DEL_PORT_FAIL

System Log Message Failed to remove SCCP ALG port from application definition table
Description Failed to delete the SCCP port from application definition table.

Type Error: An error occurred
Severity error
Facility LOG_PFE

PFE_SCCP_REG_NAT_VEC_FAIL

System Log Message Failed to add SCCP ALG vector to flow module
Description Failed to register the SCCP vector with the flow module.

Type Error: An error occurred
Severity error
Facility LOG_PFE

PFE_SCCP_REG_RM_FAIL

System Log Message Failed to register SCCP client to Resource Manager
Description Failed to register the SCCP Resource Manager client.

Type Error: An error occurred
Severity error
Facility LOG_PFE

PFE_SCCP_REG_VSIP_FAIL

System Log Message	Failed to register SCCP client to VoIP State IP port
Description	Failed to register the SCCP client to VoIP State IP port.
Type	Error: An error occurred
Severity	error
Facility	LOG_PFE

PFE_SCCP_RM_CLIENTID_FAIL

System Log Message	Failed to get SCCP Resource Manager client identifier
Description	Failed to get the SCCP Resource Manager client identifier.
Type	Error: An error occurred
Severity	error
Facility	LOG_PFE

PFE_SCREEN_MT_CFG_ERROR

System Log Message	failed to <i>operation</i> the screen config due to <i>error-message</i>
Description	failed to change the configuration of screen module
Type	Error: An error occurred
Severity	error
Facility	LOG_PFE

PFE_SCREEN_MT_CFG_EVENT

System Log Message	[<i>operation</i>]: screen name - <i>context-name</i>
Description	configuration of screen module is changed
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_PFE

PFE_SCREEN_MT_ZONE_BINDING_ERROR

System Log Message	screen <i>index1</i> failed to apply to zone <i>index2</i> due to <i>reason</i>
Description	Failed to bind the screen to the zone.
Type	Error: An error occurred
Severity	error

Facility LOG_PFE

PFE_SIP_ADD_PORT_FAIL

System Log Message Failed to add SIP ALG port to application definition table

Description Failed to add the SIP port to the application definition table.

Type Error: An error occurred

Severity error

Facility LOG_PFE

PFE_SIP_DEL_PORT_FAIL

System Log Message Failed to delete SIP ALG port from application definition table

Description Failed to remove the SIP port from the application definition table.

Type Error: An error occurred

Severity error

Facility LOG_PFE

PFE_SIP_MEM_INIT_FAILED

System Log Message Failed to create memory pool for *object-name*

Description Failed to create a memory pool for SIP.

Type Error: An error occurred

Severity error

Facility LOG_PFE

PFE_SIP_REG_HDL_FAIL

System Log Message Failed to register *object-name* handle

Description Failed to register the handler with the external module.

Type Error: An error occurred

Severity error

Facility LOG_PFE

CHAPTER 75

PFED System Log Messages

This chapter describes messages with the **PFED** prefix. They are generated by the Packet Forwarding Engine process, which gathers and reports Packet Forwarding Engine statistics.

PFED_NOTIFICATION_STATS_FAILED

System Log Message	Unable to retrieve notification statistics
Description	The Packet Forwarding Engine process (pfed) could not retrieve Packet Forwarding Engine notification statistics.
Type	Error: An error occurred
Severity	warning
Facility	LOG_PFE

CHAPTER 76

PGCPD System Log Messages

This chapter describes messages with the **PGCPD** prefix. They are generated by the pgcpd process. This process decodes Packet Gateway Control Protocol (PGCP) messages that virtual packet gateways (VPG) receive from the packet gateway controller (PGC) and translates these messages to interprocess communication (IPC) messages.

PGCPD_SHUTDOWN

System Log Message	The pgcpd process shut down
Description	The packet gateway control process (pgcpd) state was shut down.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

PGCPD_STARTUP

System Log Message	The pgcpd process just started up
Description	The packet gateway control process (pgcpd) just started up
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

PGCPD_SWITCH_OVER

System Log Message	switch over
Description	Switch over from active to backup Routing Engine
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

CHAPTER 77

PING System Log Messages

This chapter describes messages with the **PING** prefix. They are generated by the ping command, which tests whether a remote machine is accessible across the network.

PING_EGRESS_JITTER_THRESH_EXCEED

System Log Message	pingCtlOwnerIndex = <i>test-owner</i> , pingCtlTestName = <i>test-name</i>
Description	The jitter for the egress trip time exceeded the configured threshold during the indicated test conducted by the indicated user.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

PING_EGRESS_STDDEV_THRESH_EXCEED

System Log Message	pingCtlOwnerIndex = <i>test-owner</i> , pingCtlTestName = <i>test-name</i>
Description	The standard deviation of the egress trip time exceeded the configured threshold during the indicated test conducted by the indicated user.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

PING_EGRESS_THRESHOLD_EXCEEDED

System Log Message	pingCtlOwnerIndex = <i>test-owner</i> , pingCtlTestName = <i>test-name</i>
Description	The egress trip time measured for a probe exceeded the configured threshold during the indicated test conducted by the indicated user.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

PING_INGRESS_JTR_THRESH_EXCEED

System Log Message	pingCtlOwnerIndex = <i>test-owner</i> , pingCtlTestName = <i>test-name</i>
Description	The jitter for the ingress trip time exceeded the configured threshold during the indicated test conducted by the indicated user.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

PING_INGRESS_STDDV_THRESH_EXCEED

System Log Message	pingCtlOwnerIndex = <i>test-owner</i> , pingCtlTestName = <i>test-name</i>
Description	The standard deviation of the ingress trip time exceeded the configured threshold during the indicated test conducted by the indicated user.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

PING_INGRESS_THRESHOLD_EXCEEDED

System Log Message	pingCtlOwnerIndex = <i>test-owner</i> , pingCtlTestName = <i>test-name</i>
Description	The ingress trip time measured for a probe exceeded the configured threshold during the indicated test conducted by the indicated user.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

PING_PROBE_FAILED

System Log Message	pingCtlOwnerIndex = <i>test-owner</i> , pingCtlTestName = <i>test-name</i>
Description	The number of successive probe failures exceeded the pingCtlTrapProbeFailureFilter threshold.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

PING_RTT_JTR_THRESH_EXCEED

System Log Message	pingCtlOwnerIndex = <i>test-owner</i> , pingCtlTestName = <i>test-name</i>
Description	The jitter for the round trip time exceeded the configured threshold during the indicated test conducted by the indicated user.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_DAEMON

PING_RTT_STDDV_THRESH_EXCEED

System Log Message pingCtlOwnerIndex = *test-owner*, pingCtlTestName = *test-name*
Description The standard deviation of the round trip time exceeded the configured threshold during the indicated test conducted by the indicated user.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_DAEMON

PING_RTT_THRESHOLD_EXCEEDED

System Log Message pingCtlOwnerIndex = *test-owner*, pingCtlTestName = *test-name*
Description The round trip time measured for a probe exceeded the configured threshold during the indicated test conducted by the indicated user.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_DAEMON

PING_TEST_COMPLETED

System Log Message pingCtlOwnerIndex = *test-owner*, pingCtlTestName = *test-name*
Description All probes were sent and the number of failed probes was less than the pingCtlTrapTestFailureFilter threshold.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_DAEMON

PING_TEST_FAILED

System Log Message pingCtlOwnerIndex = *test-owner*, pingCtlTestName = *test-name*
Description All probes were sent but the number of failed probes equaled or exceeded the pingCtlTrapTestFailureFilter threshold.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_DAEMON

PING_UNKNOWN_THRESH_TYPE_EXCEED

System Log Message	pingCtlOwnerIndex = <i>test-owner</i> , pingCtlTestName = <i>test-name</i>
Description	An unknown type of threshold event was reported during the indicated test conducted by the indicated user.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

CHAPTER 78

PPMD System Log Messages

This chapter describes messages with the **PPMD** prefix. They are generated by the periodic packet management process (ppmd), which maintains routing protocol adjacencies for the routing protocol process (rpd).

PPMD_ASSERT_SOFT

System Log Message	Soft assertion failed at line <i>line-number</i> in file ' <i>source-filename</i> ' with error " <i>message</i> ", but ppmdd with PID <i>pid</i> continued running
Description	The source code for the periodic package management process (ppmd) includes internal self-consistency checks. As the ppmdd process with the indicated process ID (PID) executed the binary compiled from the indicated source file, a check failed at the indicated line number in the file. The ppmdd process created a diagnostic core file for analysis by technical support personnel and continued to run.
Type	Error: An error occurred
Severity	error
Facility	LOG_NEWS
Cause	An internal software failure occurred.
Action	Examine the messages that immediately follow this message in the system log for information about possible causes. Contact a technical support representative, and be ready to provide the list of messages and the diagnostic core file, if requested.

PPMD_OPEN_ERROR

System Log Message	<i>function-name</i> : open error on pipe to <i>protocol-name</i> (<i>error-message</i>)
Description	The periodic packet management process (ppmd) could not initialize the indicated protocol.
Type	Error: An error occurred
Severity	error
Facility	LOG_NEWS
Action	Contact your technical support representative.

PPMD_READ_ERROR

System Log Message	Read error on pipe from <i>protocol-name</i> : <i>reason</i> (<i>error-message</i>)
Description	The periodic packet management process (ppmd) could not read a message on a pipe for the indicated protocol.
Type	Error: An error occurred
Severity	info
Facility	LOG_NEWS
Action	Contact your technical support representative.

PPMD_WRITE_ERROR

System Log Message	<i>function-name</i> : write error on pipe to <i>protocol-name</i> (<i>error-message</i>)
Description	The periodic packet management process (ppmd) could not write a message on a pipe for the indicated protocol.
Type	Error: An error occurred
Severity	error
Facility	LOG_NEWS
Action	Contact your technical support representative.

CHAPTER 79

PPPD System Log Messages

This chapter describes messages with the **PPPD** prefix. They are generated by the Point-to-Point Protocol (PPP) process (pppd), which processes packets that use PPP.

PPPD_AUTH_CREATE_FAILED

System Log Message	Unable to allocate authentication handle: <i>error-message</i>
Description	The Point-to-Point Protocol process (pppd) could not allocate an authentication object, for the indicated reason.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

PPPD_CHAP_AUTH_IN_PROGRESS

System Log Message	Interface <i>interface-name</i> received response ' <i>operation</i> ' with CHAP ID <i>message-id</i> , but was still authenticating previous response
Description	The Point-to-Point Protocol process (pppd) received another Challenge Handshake Authentication Protocol (CHAP) response from a peer while authenticating a previous CHAP response sent by that peer. The peer is resending CHAP responses faster than the pppd process can process them.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

PPPD_CHAP_GETHOSTNAME_FAILED

System Log Message	<i>interface-name</i> : Unable to obtain hostname for outgoing CHAP message: <i>error-message</i>
Description	The Point-to-Point Protocol process (pppd) could not obtain the hostname needed to fill in the 'Name' field in an outgoing CHAP packet.
Type	Error: An error occurred
Severity	error

Facility LOG_AUTH

PPPD_CHAP_INVALID_IDENTIFIER

System Log Message Interface *interface-name* received '*operation*' message with CHAP ID *message-id* instead of expected ID *expected-value*

Description The Point-to-Point Protocol process (pppd) received a Challenge Handshake Authentication Protocol (CHAP) message from a peer that included the indicated message identifier, which did not match the indicated expected value.

Type Error: An error occurred

Severity info

Facility LOG_AUTH

PPPD_CHAP_INVALID_OPCODE

System Log Message *interface-name*: received invalid operation code *operation* (type *operation-code*, CHAP ID *message-id*)

Description The Point-to-Point Protocol process (pppd) received a Challenge Handshake Authentication Protocol (CHAP) message that included the indicated operation code, which is invalid.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

PPPD_CHAP_LOCAL_NAME_UNAVAILABLE

System Log Message Unable to determine value for 'Name' in outgoing CHAP packet

Description The Point-to-Point Protocol process (pppd) could not determine the value needed to fill in the 'Name' field in an outgoing Challenge Handshake Authentication Protocol (CHAP) packet, because either the local name was not specified or pppd could not determine the hostname.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

PPPD_CHAP_OPERATION_UNEXPECTED

System Log Message *interface-name*: unexpected operation type *operation* (CHAP ID *message-id*)

Description The Challenge Handshake Authentication Protocol (CHAP) message with the indicated identifier had the indicated operation type, which the Point-to-Point Protocol process (pppd) did not expect.

Type Error: An error occurred

Severity info
Facility LOG_AUTH

PPPD_CHAP_REPLAY_ATTACK_DETECTED

System Log Message *interface-name*: received operation with CHAP ID *message-id*, which is identical to an outstanding challenge. Peer is trying to exhort response value.

Description During an exchange of authentication messages, a peer responded to a challenge message from the Point-to-Point Protocol process (pppd) by returning the same message. The pppd process did not respond to the peer, because doing so would provide the answer to the original challenge. The peer must provide the answer on its own for authentication to succeed.

Type Error: An error occurred
Severity error
Facility LOG_AUTH

PPPD_EVLIB_CREATE_FAILURE

System Log Message Unable to create event context: *error-message*

Description The Point-to-Point Protocol process (pppd) could not create a context for handling asynchronous events, for the indicated reason.

Type Error: An error occurred
Severity error
Facility LOG_AUTH

PPPD_LOCAL_CREATE_FAILED

System Log Message Unable to allocate LOCAL module handle: *error-message*

Description The Point-to-Point Protocol process (pppd) attempted to allocate a locally configured 'password' authentication module as part of its authentication sequence. The allocation failed.

Type Error: An error occurred
Severity error
Facility LOG_AUTH

PPPD_MEMORY_ALLOCATION_FAILURE

System Log Message Unable to allocate memory for object *object-name*: *error-message*

Description The Point-to-Point Protocol process (pppd) could not allocate memory from the heap for the indicated object.

Type Error: An error occurred

Severity	error
Facility	LOG_AUTH
Action	Contact your technical support representative.

PPPD_PAP_GETHOSTNAME_FAILED

System Log Message	Unable to obtain hostname for PAP message sent from interface <i>interface-name</i> : <i>error-message</i>
Description	The Point-to-Point Protocol process (pppd) could not obtain the hostname it needed to fill in the 'Name' field in an outgoing Password Authentication Protocol (PAP) packet sent from the indicated interface.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

PPPD_PAP_INVALID_IDENTIFIER

System Log Message	Interface <i>interface-name</i> received ' <i>operation</i> ' message with PAP ID <i>message-id</i> instead of expected ID <i>expected-value</i>
Description	The Point-to-Point Protocol process (pppd) received a Password Authentication Protocol (PAP) message from a peer that included the indicated identifier, which did not match the indicated expected value.
Type	Error: An error occurred
Severity	info
Facility	LOG_AUTH

PPPD_PAP_INVALID_OPCODE

System Log Message	Interface <i>interface-name</i> received ' <i>operation</i> ' message with PAP ID <i>message-id</i> and invalid operation code <i>operation-code</i>
Description	The Point-to-Point Protocol process (pppd) received a Password Authentication Protocol (PAP) message from a peer that included the indicated operation code, which is invalid.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

PPPD_PAP_LOCAL_PASSWORD_UNAVAIL

System Log Message	Unable to determine value for 'Password' in outgoing PAP packet
Description	The Point-to-Point Protocol process (pppd) could not determine the value to write in the 'Password' field in an outgoing Password Authentication Protocol (PAP) packet.

Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH
Cause	The local password was not defined for the local hostname.

PPPD_PAP_OPERATION_UNEXPECTED

System Log Message	<i>interface-name</i> : unexpected operation type <i>operation</i> (PAP ID <i>message-id</i>)
Description	The Point-to-Point Protocol process (pppd) received a Password Authentication Protocol (PAP) message with the indicated identifier and operation type. The operation type was not valid.
Type	Error: An error occurred
Severity	info
Facility	LOG_AUTH

PPPD_POOL_ADDRESSES_EXHAUSTED

System Log Message	No addresses available in pool " <i>pool-name</i> " to assign to remote peer on interface <i>interface-name</i>
Description	The Point-to-Point Protocol process (pppd) could not assign an address from the indicated address pool to the remote peer on the indicated interface, because there were no more addresses available in the pool.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH
Action	Increase the number of addresses in the address pool.

PPPD_RADIUS_ADD_SERVER_FAILED

System Log Message	Unable to add RADIUS server <i>radius-server</i> for profile <i>access-profile</i> : <i>error-message</i>
Description	The Point-to-Point Protocol process (pppd) could not add the indicated RADIUS server for the indicated access profile.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

PPPD_RADIUS_ALLOC_PASSWD_FAILED

System Log Message	Unable to allocate RADIUS password of size <i>size</i> : <i>error-message</i>
---------------------------	---

Description The Point-to-Point Protocol process (pppd) could not allocate space for a temporary Challenge Handshake Authentication Protocol (CHAP) RADIUS password of the indicated size.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

PPPD_RADIUS_CREATE_FAILED

System Log Message Unable to allocate RADIUS module handle: *error-message*

Description The Point-to-Point Protocol process (pppd) attempted to allocate a RADIUS authentication module as part of its authentication sequence. The allocation failed.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

PPPD_RADIUS_CREATE_REQ_FAILED

System Log Message Unable to create RADIUS access request message: *error-message*

Description The Point-to-Point Protocol process (pppd) could not create an access request message to send to the RADIUS server.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

PPPD_RADIUS_GETHOSTNAME_FAILED

System Log Message Unable to obtain hostname for outgoing RADIUS message: *error-message*

Description The Point-to-Point Protocol process (pppd) could not obtain the hostname it needed to fill in the PPP_IDENTIFIER field in an outgoing RADIUS message.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

PPPD_RADIUS_MESSAGE_UNEXPECTED

System Log Message Unknown response from RADIUS server: *return-value*

Description The RADIUS authentication module for the Point-to-Point Protocol process (pppd) received a message from the RADIUS server that it could not process.

Type Error: An error occurred

Severity error
Facility LOG_AUTH

PPPD_RADIUS_NO_VALID_SERVERS

System Log Message Unable to find valid RADIUS server for profile *access-profile*

Description The Point-to-Point Protocol process (pppd) could not access a valid RADIUS server to use for the indicated access profile.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

PPPD_RADIUS_OPEN_FAILED

System Log Message rad_auth_open failed: *error-message*

Description The Point-to-Point Protocol process (pppd) could not create a RADIUS object handle, which it uses to communicate with the RADIUS server.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

PPPD_RADIUS_ROUTE_INST_ENOENT

System Log Message Ignored RADIUS server *radius-server* for profile *access-profile* because routing instance *routing-instance* did not exist

Description The indicated routing instance, which the Point-to-Point Protocol process (pppd) uses for routing of RADIUS packets, was not defined.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_AUTH

Cause The process of adding the required routing instance was still in progress when the message was logged.

Action None required. Authentication with the indicated RADIUS server is automatically reattempted, and can succeed when the interface exists.

CHAPTER 80

PROFILER System Log Messages

This chapter describes messages with the **PROFILER** prefix. They are generated by the profiler service process (profilerd) which captures accurate and granular detail of the traffic pattern over a specific time period. The profiler process provides details on the threats are encountered by the network as well as details about the mix of application traffic.

PROFILER_RECONFIGURE_SIGHUP

System Log Message	SIGHUP - re-reading configuration
Description	In response to a SIGHUP signal, the profiler service process (profilerd) read its configuration from the configuration database
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

CHAPTER 81

RDD System Log Messages

This chapter describes messages with the **RDD** prefix. They are generated by the redundant interfaces process (rdd), which manages redundant interfaces when they are configured on Adaptive Services PICs.

RDD_EVLIB_CREATE_FAILURE

System Log Message	evCreate failed (<i>error-message</i>)
Description	The redundant interfaces process (rdd) could not create a context used for handling all asynchronous events (such as timers and message availability).
Type	Error: An error occurred
Severity	emergency
Facility	LOG_DAEMON

RDD_IFDEV_ADD_FAILURE

System Log Message	<i>function-name</i> : unable to add interface device <i>interface-name</i> (<i>error-message</i>)
Description	The redundant interfaces process (rdd) could not create an interface device because an error occurred during the indicated call to the routing socket library.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RDD_IFDEV_DELETE_FAILURE

System Log Message	<i>function-name</i> : rtslib delete operation failed for interface device <i>interface-name</i> (<i>error-message</i>)
Description	The redundant interfaces process (rdd) could not delete an interface device because an error occurred during the indicated call to the routing socket library.
Type	Error: An error occurred

Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RDD_IFDEV_GET_FAILURE

System Log Message	<i>function-name</i> : rtslib get operation failed for interface device <i>interface-name</i> (<i>error-message</i>)
Description	The redundant interfaces process (rdd) could not get an interface device because an error occurred during the indicated call to the routing socket library.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RDD_IFDEV_INCOMPATIBLE_REVERT

System Log Message	<i>function-name</i> : did not revert <i>rsp-interface-name</i> back to primary interface <i>primary-interface-name</i> ; PIC is incompatible with secondary
Description	The redundant interfaces process (rdd) tried to migrate service processing for the indicated redundant interface from the secondary interface back to the indicated primary interface. The attempt failed because the Adaptive Services (AS) PICs that house the primary and secondary interfaces are not compatible.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RDD_IFDEV_INCOMPATIBLE_SWITCH

System Log Message	Unable to switch <i>rsp-interface-name</i> to secondary interface <i>secondary-interface-name</i> ; PIC is incompatible with primary
Description	The redundant interfaces process (rdd) tried to migrate service processing for the indicated redundant interface from the primary interface to the indicated secondary interface. The attempt failed because the Adaptive Services (AS) PICs that house the primary and secondary interfaces are not compatible.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RDD_IFDEV_RETRY_NOTICE

System Log Message	<i>function-name</i> : repeated attempt to add interface device <i>interface-name</i> failed (<i>error-message</i>)
Description	The redundant interfaces process (rdd) tried repeatedly to create the indicated interface device, but the attempts failed. After generating this message, rdd waited a while for resources to free up and tried again.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	Necessary resources might have been unavailable. They should become available soon.

RDD_NEW_INTERFACE_STATE

System Log Message	Event <i>event-name</i> changed state of interface <i>interface-name</i> from ' <i>old-state</i> ' to ' <i>new-state</i> '
Description	The indicated event on the indicated redundant interface changed the interface state as indicated.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

RMOPD System Log Messages

This chapter describes messages with the **RMOPD** prefix. They are generated by the Simple Network Management Protocol (SNMP) remote operations process (rmopd), which services SNMP requests for execution of ping and traceroute operations.

RMOPD_ADDRESS_MULTICAST_INVALID

System Log Message	Multicast address is not allowed
Description	When a Simple Network Management Protocol (SNMP) client requests a remote operation, it can specify the addresses of the source and target hosts for the operation. A request failed because the client specified a multicast address for either or both the source and target hosts.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RMOPD_ADDRESS_SOURCE_INVALID

System Log Message	Source address invalid: <i>error-message</i>
Description	When a Simple Network Management Protocol (SNMP) client requests a remote operation, it can specify the address to use as the source host for the operation, along with the corresponding address type (such as IP version 4 [IPv4]). Either the specified address was invalid because it did not match the specified address type, or the address could not be resolved.
Type	Error: An error occurred
Severity	notice
Facility	LOG_DAEMON

RMOPD_ADDRESS_STRING_FAILURE

System Log Message	Unable to convert numeric address to string: <i>error-message</i>
Description	The remote Simple Network Management Protocol (SNMP) operations process (rmopd) could not convert a numeric host address to the corresponding hostname text string.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RMOPD_ADDRESS_TARGET_INVALID

System Log Message rmop_util_set_address status message: *error-message*

Description When a Simple Network Management Protocol (SNMP) client requests a remote operation, it must specify the address of the target host along with the corresponding address type (such as IP version 4 [IPv4]). Either the specified address was invalid because it did not match the specified address type, or the address could not be resolved.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RMOPD_ICMP_ADDR_TYPE_UNSUPPORTED

System Log Message Only IPv4 source address is supported

Description When a Simple Network Management Protocol (SNMP) client requests a remote operation, it can specify the address type (such as IP version 4 [IPv4]) of the source and target hosts for the operation. The client specified an unsupported address type.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RMOPD_IFINDEX_NOT_ACTIVE

System Log Message ifindex: *snmp-interface-index*

Description When a Simple Network Management Protocol (SNMP) client requests a remote operation, it can specify which interface to use as the source host address, identifying it by either its numerical index or its name. The indicated index was invalid because it represents an inactive interface.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RMOPD_IFINDEX_NO_INFO

System Log Message No information for *snmp-interface-index*, message: *error-message*

Description When a Simple Network Management Protocol (SNMP) client requests a remote operation, it can specify which interface to use as the source host address, identifying it

by either its numerical index or its name. The SNMP remote operations process (rmopd) could not find any information about the interface with the indicated index.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RMOPD_IFNAME_NOT_ACTIVE

System Log Message ifname: *interface-name*

Description When a Simple Network Management Protocol (SNMP) client requests a remote operation, it can specify which interface to use as the source host address, identifying it by either its numerical index or its name. The indicated name was invalid because it represents an inactive interface.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RMOPD_IFNAME_NO_INFO

System Log Message No information for *interface-name*, message: *error-message*

Description When a Simple Network Management Protocol (SNMP) client requests a remote operation, it can specify which interface to use as the source host address, identifying it by either its numerical index or its name. The SNMP remote operations process (rmopd) could not find any information about the interface with the indicated name.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RMOPD_ROUTING_INSTANCE_NO_INFO

System Log Message No information for routing instance *routing-instance*: *error-message*

Description The indicated routing instance does not exist, so the Simple Network Management Protocol (SNMP) remote operations process (rmopd) could not retrieve information about it.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RMOPD_TRACEROUTE_ERROR

System Log Message Message: *error-message*

Description The traceroute application reported the indicated error message to the Simple Network Management Protocol (SNMP) remote operations process (rmopd).

Type Error: An error occurred

Severity notice

Facility LOG_DAEMON

CHAPTER 83

RPD System Log Messages

This chapter describes messages with the **RPD** prefix. They are generated by the routing protocol process (rpd) which controls the routing protocols that run on the router. This process starts all the configured routing protocols and handles all the routing messages. It maintains one or more routing tables, which consolidate the routing information learned from all routing protocols. From this routing information, the routing protocol process determines the active routes to network destinations and installs these routes into the Routing Engine's forwarding table. Finally, it implements routing policy, which allows you to control the routing information that is transferred between the routing protocols and the routing table.



NOTE: When an interface goes down, individual **RPD_IGMP_LEAVE** and **RPD_MLD_LEAVE** messages are no longer generated per group or per host. Instead, a single message (such as **RPD_IGMP_ALL_SUBSCRIBERS_DELETED**) is generated for the interface.

RPD_ABORT

System Log Message	abort <i>executable-name</i> [<i>pid</i>] version <i>version</i> built by <i>builder</i> on <i>date</i> : <i>error-message</i>
Description	The routing protocol process (rpd) terminated because of an internal error.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Examine the messages that immediately follow this message in the system log for information about possible causes.
Cause	An internal software failure occurred.

RPD_ACTIVE_TERMINATE

System Log Message	Exiting with active tasks: <i>task-name</i>
Description	After receiving multiple termination requests, the routing protocol process (rpd) exited without performing the indicated cleanup tasks.

Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_AMT_CFG_ADDR_FMLY_INVALID

System Log Message	Valid address family information is required
Description	An invalid address family value was encountered while parsing AMT configuration.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	ANY
Action	Modify the configuration statement to use a valid value.

RPD_AMT_CFG_ANYCAST_INVALID

System Log Message	An invalid anycast-prefix is configured
Description	An invalid anycast prefix was encountered while parsing AMT configuration.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	ANY
Action	Modify the configuration statement to use a valid value.

RPD_AMT_CFG_LOC_ADDR_INVALID

System Log Message	An invalid local-address is configured
Description	An invalid local address was encountered while parsing AMT configuration.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	ANY
Action	Modify the configuration statemetn to use a valid value.

RPD_AMT_CFG_PREFIX_LEN_SHORT

System Log Message	Prefix length <i>prefix-length</i> is too short for prefix <i>route-prefix</i>
Description	The prefix length for the indicated prefix is too short and it has a non-zero host portion. Excess host bits will be ignored.
Type	Event: This message reports an event, not an error

Severity warning

Facility ANY

RPD_AMT_CFG_RELAY_INVALID

System Log Message Invalid relay information is configured

Description Invalid relay configuration was encountered while parsing AMT configuration.

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

Action Modify the configuration statement to use a valid value.

RPD_AMT_RELAY_DISCOVERY

System Log Message AMT relay discovery message from gateway *destination-address* port *destination-port* at *time*

Description AMT relay discovery event.

Type Event: This message reports an event, not an error

Severity info

Facility ANY

RPD_AMT_TUNNEL_CREATE

System Log Message Tunnel created between gateway *destination-address* port *destination-port* relay *source-address* port *source-port* on interface *interface-name* at *time*

Description AMT tunnel create event.

Type Event: This message reports an event, not an error

Severity info

Facility ANY

RPD_AMT_TUNNEL_DELETE

System Log Message Tunnel deleted between gateway *destination-address* port *destination-port* relay *source-address* port *source-port* on interface *interface-name* at *time*

Description AMT tunnel delete event.

Type Event: This message reports an event, not an error

Severity info

Facility ANY

RPD_ASSERT

System Log Message	Assertion failed <i>executable-name</i> [<i>pid</i>]: file " <i>source-filename</i> ", line <i>line-number</i> : " <i>message</i> "
Description	The source code for the routing protocol process (rpd) includes internal self-consistency checks. A check failed at the indicated line number in the indicated source file, causing the instance of rpd that was using the indicated binary and had the indicated process ID (PID) to terminate. The process created a diagnostic core dump for analysis by technical support personnel.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Examine the messages that immediately follow this message in the system log for information about possible causes. Contact a technical support representative, and be ready to provide the list of messages and the diagnostic core dump, if requested.

RPD_ASSERT_SOFT

System Log Message	Soft assertion failed <i>executable-name</i> [<i>pid</i>]: file " <i>source-filename</i> ", line <i>line-number</i> : " <i>message</i> ", daemon continued running
Description	The source code for the routing protocol process (rpd) includes internal self-consistency checks. A check failed at the indicated line number in the indicated source file, but the instance of rpd that was using the indicated binary and had the indicated process ID (PID) continued running. The process created a diagnostic core dump for analysis by technical support personnel.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Examine the messages that immediately follow this message in the system log for information about possible causes. Contact a technical support representative, and be ready to provide the list of messages and the diagnostic core dump, if requested.

RPD_BFD_READ_ERROR

System Log Message	Read error on pipe from bfdd: <i>reason</i> (<i>error-message</i>)
Description	The routing protocol process (rpd) could not read a message available on the read pipe from the Bidirectional Forwarding Detection process (bfdd).

Type	Error: An error occurred
Severity	info
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_BFD_WRITE_ERROR

System Log Message	<i>function-name</i> : write error on pipe to bfdd (<i>error-message</i>)
Description	The routing protocol process (rpd) could not write a message on the pipe to the Bidirectional Forwarding Detection process (bfdd).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_BGP_CFG_ADDR_INVALID

System Log Message	Invalid <i>argument</i> address <i>ip-address</i>
Description	An invalid local or neighbor address was encountered while parsing BGP configuration.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	ANY
Action	Modify the configuration statement to use a valid value.

RPD_BGP_CFG_LOCAL_ASNUM_WARN

System Log Message	local as-number cannot be set to confederation as-number <i>data-id</i> , statement ignored
Description	Local autonomous-system number cannot be set to the confederation autonomous-system number. Statement will be ignored.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	ANY

RPD_BGP_NEIGHBOR_STATE_CHANGED

System Log Message	BGP peer <i>peer-name</i> changed state from <i>old-state</i> to <i>new-state</i> (event <i>event-type</i>)
Description	During BGP negotiation with the local router, the state of the indicated BGP neighbor (peer) changed as indicated. The ESTABLISHED state is the final state in the neighbor negotiation.

Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

RPD_CFG_TRACE_FILE_MISSING

System Log Message	No file specified under traceoptions hierarchy
Description	The routing protocol process (rpd) could not find the 'file' statement under a traceoptions hierarchy. This would prevent it from performing tracing.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	ANY

RPD_DYN_CFG_BUSY_SIGNAL_FAILED

System Log Message	Dynamic config <i>action</i> busy signal failed: <i>error-message</i>
Description	The routing protocol process (rpd) failed to notify the dynamic configuration clients about its availability to process the dynamic configuration requests.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_DYN_CFG_GET_PROFILE_FAILED

System Log Message	Get dynamic profiles failed: <i>error-code</i>
Description	The routing protocol process (rpd) tried to load a profile from the database and failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_DYN_CFG_GET_PROF_NAME_FAILED

System Log Message	Get profile name for session <i>client-session-id</i> failed: <i>error-code</i>
Description	The routing protocol process (rpd) tried to get the profile name from the session snapshot and failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

Action Contact your technical support representative.

RPD_DYN_CFG_GET_SES_STATE_FAILED

System Log Message Get session state for session *client-session-id* failed: *error-code*

Description The routing protocol process (rpd) failed to get the session state from the session snapshot.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

RPD_DYN_CFG_GET_SES_TYPE_FAILED

System Log Message Get session type for session *client-session-id* failed: *error-code*

Description The routing protocol process (rpd) tried to get the session type from the session snapshot and failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

RPD_DYN_CFG_GET_SNAPSHOT_FAILED

System Log Message Get session id *client-session-id* snapshot failed: *error-code*

Description The routing protocol process (rpd) tried to load client session data from the database and failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_DYN_CFG_PDB_CLOSE_FAILED

System Log Message Failed to close profile database: *error-code*

Description The routing protocol process (rpd) tried to close the profile database and failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_DYN_CFG_PDB_OPEN_FAILED

System Log Message	Failed to open profile database: <i>error-code</i>
Description	The routing protocol process (rpd) tried to open the profile database and failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_DYN_CFG_PROCESSING_FAILED

System Log Message	Module <i>module</i> failed to process dynamic configuration
Description	The routing protocol process (rpd) tried to process dynamic configuration and failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_DYN_CFG_REGISTER_FAILED

System Log Message	Dynamic config registration failed: <i>error-message</i>
Description	The routing protocol process (rpd) tried to register with the dynamic configuration subsystem and failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_DYN_CFG_REQUEST_ACK_FAILED

System Log Message	Failed to ack request <i>data-id</i> : <i>error-code</i>
Description	The routing protocol process (rpd) tried to acknowledge a dynamic configuration request and failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_DYN_CFG_RESPONSE_SLOW

System Log Message	Dynamic config response for session id <i>client-session-id</i> took <i>system-seconds</i> seconds
Description	The routing protocol process (rpd) is responding slowly to dynamic config requests.
Type	Error: An error occurred

Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_DYN_CFG_SCHEMA_OPEN_FAILED

System Log Message	Could not open configuration schema: <i>error-message</i>
Description	The routing protocol process (rpd) tried to open the configuration schema and failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_DYN_CFG_SDB_CLOSE_FAILED

System Log Message	Failed to close session database: <i>error-code</i>
Description	The routing protocol process (rpd) tried to close the session database and failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_DYN_CFG_SDB_OPEN_FAILED

System Log Message	Failed to open session database: <i>error-code</i>
Description	The routing protocol process (rpd) tried to open the session database and failed.
Type	Error: An error occurred
Severity	info
Facility	LOG_DAEMON

RPD_DYN_CFG_SES_RECOVERY_FAILED

System Log Message	Recovery of session <i>client-session-id</i> failed
Description	The routing protocol process (rpd) tried to recover a session and failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_DYN_CFG_SET_CONTEXT_FAILED

System Log Message	Set dynamic config context for profile <i>profile-name</i> session <i>client-session-id</i> failed
Description	The routing protocol process (rpd) tried to set up the dynamic configuration context and failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_ESIS_ADJDOWN

System Log Message	ES-IS lost <i>adjacency-type</i> adjacency to <i>neighbor-nsap-netn</i> on <i>interface-name</i> , reason: <i>reason</i>
Description	An ES-IS adjacency with the indicated neighboring router was terminated. The local router no longer exchanges routing information with, or directs traffic to, the neighboring router.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON
Cause	The communication path to the neighboring router was disrupted, a protocol error occurred, or the neighboring router was powered down.

RPD_ESIS_ADJUP

System Log Message	ES-IS new <i>adjacency-type</i> adjacency to <i>neighbor-nsap-netn</i> on <i>interface-name</i>
Description	An ES-IS adjacency was established with the indicated neighboring router. The local router can now exchange information with it.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

RPD_EXIT

System Log Message	Exit <i>executable-name</i> [<i>pid</i>] version <i>version</i> built by <i>builder</i> on <i>date</i> , caller <i>address</i>
Description	The routing protocol process (rpd) exited, either in response to a user request or because of a system error.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

Cause A system resource was unavailable, rpd did not understand an error, or a user terminated the process.

Action Examine the messages that immediately follow this message in the system log for information about possible causes.

RPD_IFD_INDEXCOLLISION

System Log Message Physical interface collision -- same name, different index (new *new-interface-name new-index* old *old-interface-name old-value*)

Description The routing protocol process (rpd) received a message from the kernel in which the numerical index associated with the indicated interface name differed from the index-to-name mapping maintained by rpd.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause It is possible that rpd discarded some interface messages from the kernel without processing them because it received more messages than it could handle. It will recover.

RPD_IFD_NAMECOLLISION

System Log Message Physical interface collision -- different name, same index (new *new-interface-name new-index*, old *old-interface-name old-value*)

Description The routing protocol process (rpd) received a message from the kernel in which the name associated with the indicated numerical interface index differed from the name-to-index mapping maintained by rpd.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause It is possible that rpd discarded some interface messages from the kernel without processing them because it received more messages than it could handle. It will recover.

RPD_IFL_INDEXCOLLISION

System Log Message Logical interface collision -- same name, different index (new *new-interface-name new-index* old *old-interface-name old-value*)

Description The routing protocol process (rpd) received a message from the kernel in which the numerical index associated with the indicated interface name differed from the index-to-name mapping maintained by rpd.

Type Error: An error occurred

Severity	error
Facility	LOG_DAEMON
Cause	It is possible that rpd discarded some interface messages from the kernel without processing them because it received more messages than it could handle. It will recover.

RPD_IFL_NAMECOLLISION

System Log Message	Logical interface collision -- different name, same index (new <i>new-interface-name new-index</i> , old <i>old-interface-name old-value</i>)
Description	The routing protocol process (rpd) received a message from the kernel in which the name associated with the indicated numerical interface index differed from the name-to-index mapping maintained by rpd.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	It is possible that rpd discarded some interface messages from the kernel without processing them because it received more messages than it could handle. It will recover.

RPD_IGMP_ACCOUNTING_OFF

System Log Message	<i>interface-name time</i>
Description	Internet Group Management Protocol (IGMP) accounting for the indicated interface was disabled at the indicated time.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

RPD_IGMP_ACCOUNTING_ON

System Log Message	<i>interface-name time</i>
Description	Internet Group Management Protocol (IGMP) accounting for the indicated interface was enabled at the indicated time.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

RPD_IGMP_ALL_SUBSCRIBERS_DELETED

System Log Message	All IGMP subscribers on interface <i>interface-name</i> deleted at <i>time</i> because the interface is down
Description	All IGMP subscribers have been deleted because the interface is down.

Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

RPD_IGMP_CFG_CREATE_ENTRY_FAILED

System Log Message	Could not create entry for <i>entry</i> .
Description	Internet Group Management Protocol (IGMP) failed to create the indicated configuration entry. The configuration request failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_IGMP_CFG_GROUP_OUT_OF_RANGE

System Log Message	The combination of group-count <i>count</i> and group-increment <i>ip-address</i> causes some of the groups out of range.
Description	The configuration request failed because the indicated configuration object contained a group that is out of range.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Modify configuration statement to use a valid value.

RPD_IGMP_CFG_INVALID_VALUE

System Log Message	The <i>object-name</i> configuration object <i>identifier</i> field has an invalid value of <i>value</i>
Description	The configuration request failed because the indicated configuration object contained the indicated invalid value.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Modify configuration statement to use a valid value.

RPD_IGMP_CFG_SOURCE_OUT_OF_RANGE

System Log Message	The combination of source-count <i>count</i> and source-increment <i>ip-address</i> causes some of the sources out of range.
---------------------------	--

Description	The configuration request failed because the indicated configuration object contained a source that is out of range.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Modify configuration statement to use a valid value.

RPD_IGMP_DYN_CFG_ALREADY_BOUND

System Log Message	Dynamic configuration session id <i>client-session-id</i> for interface <i>interface-name</i> is already bound to interface <i>old-interface-name</i> .
Description	The indicated dynamic configuration session id is already bound to another interface. The dynamic configuration instantiation request was rejected.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Unbind session id from existing interface.

RPD_IGMP_DYN_CFG_INVALID_STMT

System Log Message	Invalid dynamic configuration statement: <i>configuration-statement</i>
Description	The indicated dynamic configuration statement was invalid. The dynamic configuration instantiation request was rejected.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Remove the unsupported configuration statement.

RPD_IGMP_DYN_CFG_SES_ID_ADD_FAIL

System Log Message	Failed to add dynamic configuration session id <i>client-session-id</i> to interface <i>interface-name</i> .
Description	Failed to associate the indicated dynamic configuration session id to specified interface. The dynamic configuration instantiation request was rejected.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

Action Contact your technical support representative.

RPD_IGMP_DYN_CFG_SES_ID_MISMATCH

System Log Message Dynamic configuration entry for interface *interface-name* with session id *client-session-id* found an existing entry with a different session id of *client-session-id-1*.

Description The dynamic configuration instantiation request matched an existing dynamic configuration block that had a different session id. The dynamic configuration instantiation request was rejected.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

RPD_IGMP_JOIN

System Log Message Listener *source-address* sent a join to *destination-address* for group *group-address* source *sender-address* on interface *interface-name* at *time*

Description IGMP join event.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_IGMP_LEAVE

System Log Message Listener *source-address* sent a leave to *destination-address* for group *group-address* source *sender-address* on interface *interface-name* at *time*

Description IGMP leave event.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_IGMP_MEMBERSHIP_TIMEOUT

System Log Message Membership timeout for listener *source-address* for group *group-address* source *sender-address* on interface *interface-name* at *time*

Description IGMP group membership timeout.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_IGMP_ROUTER_VERSION_MISMATCH

System Log Message IGMP version mismatch on *interface-name*. Local version: *local-version* Remote version: *remote-version*

Description The IGMP version running on the local router does not match the one received in the query

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

RPD_ISIS_ADJDOWN

System Log Message IS-IS lost *Lisis-level* adjacency to *neighbor-system-ids* on *interface-name*, reason: *reason*

Description An IS-IS adjacency with the indicated neighboring router was terminated. The local router no longer exchanges routing information with, or directs traffic to, the neighboring router.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

Cause The communication path to the neighboring router was disrupted, a protocol error occurred, or the neighboring router was powered down.

RPD_ISIS_ADJUP

System Log Message IS-IS new *Lisis-level* adjacency to *neighbor-system-ids* on *interface-name*

Description An IS-IS adjacency was established with the indicated neighboring router. The local router can now exchange information with it.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_ISIS_ADJUPNOIP

System Log Message IS-IS new *Lisis-level* adjacency to *neighbor-system-ids* on *interface-name* without an address

Description An IS-IS adjacency was established with the indicated neighboring router, which is not configured for IS-IS for IP.

Type Event: This message reports an event, not an error

Severity notice

Facility	LOG_DAEMON
Cause	The neighboring router is misconfigured: it is enabled for IS-IS but not for exchange of IP route information.
Action	Configure the neighboring router for IS-IS with IP, or remove it from the IS-IS mesh.

RPD_ISIS_LDP_SYNC

System Log Message	IS-IS interface <i>interface-name</i> advertised with infinite metric for <i>duration</i> seconds already due to loss of synchronization with LDP
Description	The IS-IS protocol lost synchronization with the Label Distribution Protocol (LDP) on the indicated interface. As a consequence, it began advertising an infinite metric for the interface and has been doing so for the indicated number of seconds.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Action	Determine why LDP lost synchronization with IS-IS.

RPD_ISIS_LSPCKSUM

System Log Message	IS-IS <i>Lisis-level</i> LSP checksum error, interface <i>interface-name</i> , LSP id <i>lspl</i> , sequence <i>sequence-number</i> , checksum <i>checksum</i> , lifetime <i>duration</i>
Description	The indicated IS-IS informational link-state PDU (LSP) failed an internal checksum validity test, implying that it was corrupted.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Cause	The packet was corrupted in transit between the neighboring IS-IS router and this router, or memory on one of the routers was corrupted.
Action	None, unless a large number of these messages appear in the system log file. The corrupted LSP is silently discarded.

RPD_ISIS_NO_ROUTERID

System Log Message	IS-IS instance does not have a valid router ID
Description	The IS-IS instance did not have a valid router ID.
Type	Error: An error occurred
Severity	alert

Facility LOG_DAEMON

Cause When a router ID is not explicitly configured for an instance, IPv4 addresses configured under the instance are considered in the selection of the router ID. In this case, the instance did not have a router ID configured and no IPv4 addresses were configured.

Action Either configure a router ID by including the 'routing-instance' statement under the instance, or configure an IPv4 address by including the 'family inet' statement under one of the interfaces of the instance. You can also configure both.

RPD_ISIS_OVERLOAD

System Log Message IS-IS database overload

Description The IS-IS link-state database is full and no additional memory can be allocated for it.

Type Error: An error occurred

Severity alert

Facility LOG_DAEMON

Cause No additional memory is available for storing IS-IS link-state information. Either system resources are exhausted or a software error occurred (such as a memory leak in the routing protocol process [rpd]). In the former case, IS-IS might be carrying too much information, or the router configuration includes too many features that use large amounts of system memory.

Action Perform one or more of the following actions: (1) Check for unusually high memory usage by the IS-IS task or rpd, (2) Unconfigure features that use large amounts of memory, (3) Add more memory to the Routing Engine, (4) Carry fewer IS-IS routes.

RPD_KRT_CCC_IFL_MODIFY

System Log Message *error-code, error-message*

Description The routing protocol process (rpd) attempted to modify the state for a logical interface that is related to circuit cross-connect (CCC), but the request failed.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

Cause It is possible that the kernel lacked the resources to fulfill the request. The rpd process will recover.

RPD_KRT_DELETED_RTT

System Log Message *task-name: received deleted routing table from the kernel for family address-family-type table ID table-id*

Description The routing protocol process (rpd) received a message from the kernel that referred to a routing table that no longer exists.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_KRT_IFA_GENERATION

System Log Message ifa generation mismatch -- rpd *rpd-generation* kernel *kernel-generation*

Description The routing protocol process (rpd) received a message from the kernel in which the interface address associated with the indicated numerical index differed from the address-to-index mapping maintained by rpd.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

Cause It is possible that rpd discarded some interface messages from the kernel without processing them because it received more messages than it could handle. It will recover.

RPD_KRT_IFDCHANGE

System Log Message *task-name* CHANGE for ifd *interface-device-index address/prefix-length* failed, error "*error-message*"

Description The routing protocol process (rpd) sent a request to the kernel to change the state of the indicated interface. The request failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause It is possible that the kernel lacked the resources to fulfill the request. The rpd process will recover.

RPD_KRT_IFDEST_GET

System Log Message *task-name* IFDEST GET for ifd *rpd-interface-name* failed, error "*error-message*"

Description The routing protocol process (rpd) requested state information about the indicated interface from the kernel. The request failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause It is possible that the kernel lacked the resources to fulfill the request. The rpd process will recover.

RPD_KRT_IFDGET

System Log Message *task-name* GET index for ifd *interface-name* failed, error "*error-message*"

Description The routing protocol process (rpd) requested state information about the indicated interface from the kernel. The request failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause It is possible that the kernel lacked the resources to fulfill the request. The rpd process will recover.

RPD_KRT_IFD_CELL_RELAY_INV_MODE

System Log Message Invalid mode (*mode*) specified for interface device *interface-name*; defaulting to port mode

Description The routing protocol process (rpd) received a message from the kernel that specified the cell-relay encapsulation for the indicated physical interface, but the specified cell-relay mode (port, or trunk user-to-network interface [UNI], or trunk network-to-network interface [NNI]) was invalid.

Type Error: An error occurred

Severity notice

Facility LOG_DAEMON

RPD_KRT_IFD_CELL_RELAY_NO_MODE

System Log Message No mode specified for interface device *interface-name*; defaulting to port mode

Description The routing protocol process (rpd) received a message from the kernel that specified the cell-relay encapsulation for the indicated physical interface, but not the cell-relay mode.

Type Error: An error occurred

Severity notice

Facility LOG_DAEMON

RPD_KRT_IFD_GENERATION

System Log Message ifd *interface-device-index* generation mismatch -- rpd *rpd-generation* kernel *kernel-generation*

Description	The routing protocol process (rpd) received a message from the kernel in which the physical interface associated with the indicated numerical index differed from the interface-to-index mapping maintained by rpd.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON
Cause	It is possible that rpd discarded some interface messages from the kernel without processing them because it received more messages than it could handle. It will recover.

RPD_KRT_IFL_CELL_RELAY_INV_MODE

System Log Message	Invalid mode (<i>mode</i>) specified for logical interface <i>interface-name</i> ; defaulting to port mode
Description	The routing protocol process (rpd) received a message from the kernel that specified the cell-relay encapsulation for the indicated logical interface, but the specified cell-relay mode (port, virtual-circuit, or virtual-path) was invalid.
Type	Error: An error occurred
Severity	notice
Facility	LOG_DAEMON

RPD_KRT_IFL_CELL_RELAY_NO_MODE

System Log Message	No mode specified for logical interface <i>interface-name</i> ; defaulting to port mode
Description	The routing protocol process (rpd) received a message from the kernel that specified the cell-relay encapsulation for the indicated logical interface but not the cell-relay mode.
Type	Error: An error occurred
Severity	notice
Facility	LOG_DAEMON

RPD_KRT_IFL_GENERATION

System Log Message	ifl <i>logical-interface-index</i> generation mismatch -- rpd <i>rpd-interface-name</i> <i>rpd-generation</i> kernel <i>kernel-interface-name.kernel-interface-unit</i> <i>kernel-generation</i>
Description	The routing protocol process (rpd) received a message from the kernel in which the logical interface associated with the indicated numerical index differed from the interface-to-index mapping maintained by rpd.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

Cause It is possible that rpd discarded some interface messages from the kernel without processing them because it received more messages than it could handle. It will recover.

RPD_KRT_KERNEL_BAD_ROUTE

System Log Message *task-name: lost interface-hierarchy logical-interface-index for route route-prefix*

Description As it restarted, the routing protocol process (rpd) could not process a route obtained from the kernel because the route contained references to objects that are no longer valid.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

Cause rpd did not recognize some elements in the route message, such as the logical interface index or an address family.

Action rpd can probably solve the problem, but check the entry for the indicated route prefix in the forwarding table. If the prefix's route and forwarding table entry are inconsistent, contact a technical support representative for instructions.

RPD_KRT_NEXTHOP_OVERFLOW

System Log Message *type route-prefix: number of next hops (count) exceeded the maximum allowed (maximum-value) -- truncating*

Description The number of next hops for the indicated route exceeded the indicated limit for a single route add operation.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause An indexed next hop can use multiple forwarding next hops per forwarding class. It is possible to have more next hops per route than can be carried in a single message. This requires that next hops be reused across forwarding classes, which is not recommended.

Action Eliminate common next hops across forwarding classes, thereby reducing the total number of next hops that must be specified.

RPD_KRT_NOIFD

System Log Message No device *interface-device-index* for interface *logical-interface-index* (*interface-name*)

Description The routing protocol process (rpd) received a message from the kernel that associated the indicated physical interface device and logical interface. The rpd process has no record of the device.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	It is possible that rpd discarded some interface messages from the kernel without processing them because it received more messages than it could handle. It will recover.

RPD_KRT_VERSION

System Log Message	Routing socket version mismatch (kernel <i>kernel-version</i> != rpd <i>rpd-version</i>) -- kernel upgrade required
Description	The routing protocol process (rpd) discovered that the kernel does not support the version of routing sockets it requires.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	The kernel version is older than the rpd version.
Action	Upgrade the kernel package.

RPD_KRT_VERSIONNONE

System Log Message	Routing socket message type <i>message-type</i> 's version is not supported by kernel, expected <i>rpd-version</i> -- kernel upgrade required
Description	The routing protocol process (rpd) discovered that the kernel does not support the routing socket message types that it requires.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	The kernel version is older than the rpd version.
Action	Upgrade the kernel package.

RPD_KRT_VERSIONOLD

System Log Message	Routing socket message type <i>message-type</i> 's version is older than expected (<i>kernel-version</i> < <i>rpd-version</i>) -- consider upgrading the kernel
Description	The routing protocol process (rpd) discovered that the kernel uses an older version of routing socket message types than it does.
Type	Error: An error occurred

Severity	error
Facility	LOG_DAEMON
Cause	The kernel version is older than the rpd version.
Action	Upgrade the kernel package.

RPD_KRT_VPLS_IFL_MODIFY

System Log Message	Unable to modify VPLS-related state: <i>error-code</i> (<i>errno error-message</i>)
Description	The routing protocol process (rpd) attempted to modify the state for a logical interface that is related to virtual private LAN service (VPLS), but the request failed.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON
Cause	It is possible that the kernel lacked the resources to fulfill the request. The rpd process will recover.

RPD_L2VPN_LABEL_ALLOC_FAILED

System Log Message	Unable to allocate <i>label-type</i> labels for site <i>name</i> with ID <i>identifier</i> in instance <i>vpn-name</i>
Description	The routing protocol process (rpd) could not allocate labels of the indicated type for the indicated site (name and ID) in the indicated virtual private network (VPN) virtual circuit (VC), because the resulting number of labels would have exceeded the limit.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_L2VPN_REMOTE_SITE_COLLISION

System Log Message	Two remote PEs (RDs <i>route-discriminator</i> and <i>route-discriminator2</i>) have the same site ID (<i>identifier</i>) in VPN <i>vpn-name</i>
Description	The routing protocol process (rpd) for the indicated virtual private network (VPN) received an advertisement from a remote provider edge (PE) router with the first indicated route discriminator, but the associated site ID also belongs to a remote site with the second route discriminator.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

RPD_L2VPN_SITE_COLLISION

System Log Message	Same site ID <i>identifier</i> configured on remote PE (RD <i>route-discriminator</i>) and local PE in VPN <i>vpn-name</i> (non-multihomed site <i>name</i>)
Description	The routing protocol process (rpd) for the indicated virtual private network (VPN) received an advertisement from a remote provider edge (PE) router, but the associated site ID belongs to a local site.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON

RPD_LAYER2_VC_BFD_DOWN

System Log Message	BFD session for Layer 2 VC <i>vc-name</i> went down
Description	The routing protocol process (rpd) determined that the Bidirectional Forwarding Detection (BFD) protocol session for the indicated Layer 2 virtual private network (VPN) virtual circuit (VC) terminated.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_LAYER2_VC_BFD_UP

System Log Message	BFD session for Layer 2 VC <i>vc-name</i> came up
Description	The routing protocol process (rpd) determined that the Bidirectional Forwarding Detection (BFD) protocol session for the the indicated Layer 2 virtual private network (VPN) virtual circuit (VC) came up.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_LAYER2_VC_DOWN

System Log Message	State of Layer 2 VC <i>vc-name</i> changed from UP to <i>state</i>
Description	The state of the indicated Layer 2 virtual private network (VPN) virtual circuit (VC) changed as indicated (to either down or deleted).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_LAYER2_VC_PING_DOWN

System Log Message	Ping failure for Layer 2 VC <i>vc-name</i>
Description	The routing protocol process (rpd) determined that the Ping for the indicated Layer 2 virtual private network (VPN) virtual circuit (VC) failed.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_LAYER2_VC_UP

System Log Message	State of Layer 2 VC <i>vc-name</i> changed to UP
Description	The state of the indicated Layer 2 virtual private network (VPN) virtual circuit (VC) changed to up.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

RPD_LDP_BFD_DOWN

System Log Message	LDP BFD session for FEC <i>fec-address</i> went down
Description	The routing protocol process (rpd) determined that the Label Distribution Protocol (LDP) Bidirectional Forwarding Detection (BFD) protocol session for the indicated forwarding equivalence class (FEC) terminated.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_LDP_BFD_DOWN_TRACEROUTE_FAIL

System Log Message	LDP BFD sessions for FEC <i>fec-address</i> going down due to traceroute failure
Description	The routing protocol process (rpd) determined that the Label Distribution Protocol (LDP) Bidirectional Forwarding Detection (BFD) protocol session for the indicated forwarding equivalence class (FEC) was terminated due to traceroute failure.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_LDP_BFD_UP

System Log Message	LDP BFD session for FEC <i>fec-address</i> came up
---------------------------	--

Description The routing protocol process (rpd) determined that the Label Distribution Protocol (LDP) Bidirectional Forwarding Detection (BFD) protocol session for the indicated forwarding equivalence class (FEC) came up.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

RPD_LDP_GR_CFG_IGNORED

System Log Message LDP needs *duration* seconds for restart. Instance restart-duration is *time-period* seconds only. Graceful restart will not be attempted

Description Instance restart-duration is less than that needed by LDP to finish graceful-restart. LDP GR will not be attempted.

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

Action Modify the instance restart-duration and ldp GR configurations.

RPD_LDP_INTF_BLOCKED

System Log Message Duplicate session ID detected from *neighbor-address*, interface *interface-name*, blocking interface

Description Label Distribution Protocol (LDP) operations were blocked on the indicated interface because the same session ID was detected across multiple interfaces but per-interface transport addresses are in use.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

RPD_LDP_INTF_UNBLOCKED

System Log Message LDP interface *interface-name* is now unblocked

Description The indicated interface returned to the normal Label Distribution Protocol (LDP) operational state. It was previously blocked because the routing protocol process (rpd) noticed that a duplicate session ID was being used.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

RPD_LDP_NBRDOWN

System Log Message	LDP neighbor <i>neighbor-addressi (interface-name)</i> is down
Description	A Label Distribution Protocol (LDP) adjacency was terminated because the indicated neighbor stopped communicating. If the adjacency was the only one with this neighbor, the routing protocol process (rpd) terminated the associated LDP session.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_LDP_NBRUP

System Log Message	LDP neighbor <i>neighbor-addressi (interface-name)</i> is up
Description	A Label Distribution Protocol (LDP) adjacency with the indicated neighbor became active. The routing protocol process (rpd) established an LDP session with the neighbor if one did not already exist.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

RPD_LDP_PING_DOWN

System Log Message	LDP LSP ping failure for FEC <i>fec-address</i>
Description	The routing protocol process (rpd) determined that LSP ping returned error for the indicated forwarding equivalence class (FEC) of Label Distribution Protocol (LDP).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_LDP_SESSIONDOWN

System Log Message	LDP session <i>neighbor-addressi</i> is down, reason: <i>reason</i>
Description	The routing protocol process (rpd) terminated a Label Distribution Protocol (LDP) session with the indicated neighbor and deleted all labels exchanged during the session.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_LDP_SESSIONUP

System Log Message	LDP session <i>neighbor-addressi</i> is up
---------------------------	--

Description The routing protocol process (rpd) established a Label Distribution Protocol (LDP) session with the indicated neighbor. The routers began exchanging labels.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_LMP_ALLOC_ACK

System Log Message Unknown context in ALLOC_ACK message

Description The routing protocol process (rpd) received a label allocation acknowledgment that contained invalid context.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_LMP_ALLOC_REQUEST_TIMEOUT

System Log Message Allocation request timeout for context *Oxaddress*, client request ID *Oxrequest-id*

Description The label allocation request with the indicated client request ID and for the indicated context timed out before completion.

Type Event: This message reports an event, not an error

Severity error

Facility LOG_DAEMON

RPD_LMP_CONTROL_CHANNEL

System Log Message *operation* operation failed: control channel *logical-interface-index* unknown

Description The routing protocol process (rpd) received a message that specified the indicated type of operation on the indicated control channel. The channel does not exist.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_LMP_NO_CALLBACK

System Log Message No function callback for label removed event

Description The routing protocol process (rpd) could not notify a client that a label was removed, because there was no function callback for the removal event.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_LMP_NO_MEMORY

System Log Message *function-name: malloc() failed (error-message, errno error-code)*

Description The routing protocol process (rpd) could not allocate memory.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause An internal software failure occurred.

RPD_LMP_NO_PEER

System Log Message Peer *peer-id* not found for TE link *link-name* (index *link-id*)

Description The routing protocol process (rpd) could not locate the indicated peer while processing a TE LINK message for the traffic-engineering link with the indicated name and index.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_LMP_PEER

System Log Message *operation* operation failed: peer *peer-name* (index *peer-id*) *reason*

Description The routing protocol process (rpd) could not perform the indicated operation for the peer with the indicated name and index, for the indicated reason.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_LMP_PEER_IFL

System Log Message *operation* operation failed because *reason* for peer *peer-name* (index *peer-id*): *error-message* (errno *error-code*)

Description The routing protocol process (rpd) could not perform the indicated operation for the peer with the indicated name and index, for the indicated reason.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_LMP_PEER_INDEX

System Log Message	No more peer indexes
Description	No more peer indexes were available for allocation.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON

RPD_LMP_RESOURCE

System Log Message	<i>operation</i> operation failed: resource <i>resource</i> (type <i>type</i> , index <i>index</i>) <i>reason</i>
Description	The routing protocol process (rpd) could not perform the indicated operation for the resource with the indicated name, type, and index, for the indicated reason.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_LMP_RESOURCE_NO_LINK

System Log Message	TE link <i>link-id</i> not found for resource <i>resource</i> (type <i>type</i> , index <i>index</i>)
Description	The routing protocol process (rpd) could not locate the indicated traffic-engineering link for the resource with the indicated name, type, and index.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_LMP_SEND

System Log Message	<i>function-name</i> : handling write exception (<i>error-message</i> , errno <i>error-code</i>)
Description	The routing protocol process (rpd) could not send a message to the Label Management Protocol (LMP) process (lmpd).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_LMP_SEND_ALLOCATION_MESSAGE

System Log Message	Unable to send allocation message: <i>error-message</i> (<i>error-code</i>)
Description	The routing protocol process (rpd) could not send an allocation message.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_LMP_SYSFAIL

System Log Message Unable to start *type* timer

Description The routing protocol process (rpd) discovered that the Label Management Protocol (LMP) process (lmpd) was not running. The rpd process attempted to start the indicated type of timer for restarting the lmpd process or reestablishing a connection to it, but the attempt failed.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.

Action Examine the messages that immediately follow this message in the system log for information about possible reasons that lmpd failed.

RPD_LMP_TE_LINK

System Log Message *operation* operation failed: TE link *link-name* (index *index*) *reason*

Description The routing protocol process (rpd) could not perform the indicated operation for the traffic-engineering link with the indicated name and index, for the indicated reason.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_LMP_TE_LINK_INDEX

System Log Message No more TE-link indexes

Description No more traffic-engineering link indexes were available for allocation.

Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON

RPD_LMP_UNEXPECTED_OPCODE

System Log Message *message-type* message had unexpected operation code *operation-code*

Description The routing protocol process (rpd) received the indicated type of message, which had the indicated invalid operation code.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RPD_LOCK_FLOCKED

System Log Message Unable to obtain a lock on *filename*, is another copy of rpd running?

Description The routing protocol process (rpd) could not obtain the mutual exclusion lock that prevents more than one instance of rpd from running simultaneously. The system terminated the indicated process.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON
Cause Another rpd process is running.
Action Use the 'show system process' command to verify that another rpd is running.

RPD_LOCK_LOCKED

System Log Message Unable to obtain a lock on *filename, program-name[pid]* is still running

Description The routing protocol process (rpd) could not obtain the mutual exclusion lock that prevents more than one instance of rpd from running simultaneously. The system terminated this instance of rpd.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON
Cause Another rpd is running.
Action Use the 'show system process' command to verify that another rpd is running.

RPD_MC_CFG_CREATE_ENTRY_FAILED

System Log Message Could not create entry for *entry*.

Description The multicast configuration request failed because the routing protocol process (rpd) failed to create the specified configuration entry.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON
Action Contact your technical support representative.

RPD_MC_CFG_FWDCACHE_CONFLICT

System Log Message	Multicast forwarding-cache: reuse value must be less than or equal to suppress value
Description	Multicast forwarding-cache reuse value is configured greater than the suppress value. Reuse value must be less than or equal to the suppress value.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	ANY

RPD_MC_CFG_PREFIX_LEN_SHORT

System Log Message	Multicast <i>argument</i> : prefix length <i>prefix-length</i> is too short for prefix <i>route-prefix</i> , ignoring excess host bits
Description	The prefix length for the indicated prefix is too short and it has a non-zero host portion. Excess host bits will be ignored.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	ANY

RPD_MC_COSD_WRITE_ERROR

System Log Message	Unable to write to pipe to COS process: (<i>error-message</i>)
Description	The routing protocol process (rpd) could not write a message on the write pipe to the Class Of Service process (cosd).
Type	Error: An error occurred
Severity	info
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_MC_DESIGNATED_PE_CHANGE

System Log Message	Designated forwarder changed to <i>ip-address</i> for backup-pe-group <i>group-name</i> in <i>routing-instance</i> instance
Description	The routing protocol daemon (rpd) assigned the indicated Provider Edge (PE) as the new designated forwarder of the indicated routing instance for the indicated backup-pe-group.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_MC_DYN_CFG_ALREADY_BOUND

System Log Message	Dynamic configuration session id <i>client-session-id</i> for interface <i>interface-name</i> is already bound to interface <i>old-interface-name</i> .
Description	The dynamic configuration instantiation request was rejected because the specified dynamic configuration session ID was already bound to another interface.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Unbind the session ID from the existing interface.

RPD_MC_DYN_CFG_SES_ID_ADD_FAIL

System Log Message	Failed to add dynamic configuration session id <i>client-session-id</i> to interface <i>interface-name</i> .
Description	The dynamic configuration instantiation request was rejected because the routing protocol process failed to associate the specified dynamic configuration session ID with the specified interface.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_MC_DYN_CFG_SES_ID_MISMATCH

System Log Message	Dynamic configuration entry for interface <i>interface-name</i> with session id <i>client-session-id</i> found an existing entry with a different session id of <i>client-session-id-1</i> .
Description	The dynamic configuration instantiation request was rejected because the request matched an existing dynamic configuration block that had a different session ID.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_MC_LOCAL_DESIGNATED_PE

System Log Message	Local PE is now the designated forwarder for backup-pe-group <i>group-name</i> in <i>routing-instance</i> instance
---------------------------	--

Description The routing protocol daemon (rpd) selected the local Provider Edge (PE) as the designated forwarder of the indicated routing instance for the indicated backup-pe-group.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

RPD_MC_OIF_REJECT

System Log Message Interface *interface-name* is rejected due to lack of bw

Description When multicast bandwidth admission control is applied, an interface may not be put into the downstream interface list for a forwarding cache if the interface does not have enough bandwidth for the flow, even when a multicast protocol determines that there are local/downstream receivers.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_MC_OIF_RE_ADMIT

System Log Message Interface *interface-name* is re-admitted with newly available bw

Description The indicated downstream interface that was previously rejected was readmitted for the flow because there was newly available bandwidth on the interface.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_MGMT_TIMEOUT

System Log Message Connection to management peer *process-name* timed out waiting for input

Description The connection between the routing protocol process (rpd) and the indicated management process (mgd) timed out before input arrived from the mgd process.

Type Error: An error occurred

Severity warning

Facility LOG_DAEMON

RPD_MIRROR_ERROR

System Log Message Unable to establish mirror connection between Routing Engines: *error-message*

Description The routing protocol process (rpd) could not establish the mirror connection (which supports nonstop routing) between the master and backup Routing Engines.

Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Cause	The master and backup Routing Engines are running incompatible versions of the Junos OS.
Action	Update the Junos OS to compatible versions on the master and backup Routing Engines.

RPD_MIRROR_VERSION_MISMATCH

System Log Message	Versions of mirror software on Routing Engines are incompatible: <i>error-message</i>
Description	While trying to establish the mirror connection between the master and backup Routing Engines (which supports nonstop routing), the routing protocol process (rpd) determined that the versions of Junos OS on the Routing Engines were incompatible.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Action	Update the Junos OS to compatible versions on the master and backup Routing Engines.

RPD_MLD_ACCOUNTING_OFF

System Log Message	<i>interface-name time</i>
Description	The Multicast Listener Discovery (MLD) accounting for the indicated interface was disabled at the indicated time.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

RPD_MLD_ACCOUNTING_ON

System Log Message	<i>interface-name time</i>
Description	The Multicast Listener Discovery (MLD) accounting for the indicated interface was enabled at the indicated time.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

RPD_MLD_ALL_SUBSCRIBERS_DELETED

System Log Message	All MLD subscribers on interface <i>interface-name</i> deleted at <i>time</i> because the interface is down
Description	All MLD subscribers have been deleted because the interface is down.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

RPD_MLD_CFG_CREATE_ENTRY_FAILED

System Log Message	Could not create entry for <i>entry</i> .
Description	MLD failed to create the indicated configuration entry. The configuration request failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_MLD_CFG_GROUP_OUT_OF_RANGE

System Log Message	The combination of group-count <i>count</i> and group-increment <i>ip-address</i> causes some of the groups out of range.
Description	The configuration request failed because the indicated configuration object contained a group that is out of range.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Modify configuration statement to use a valid value.

RPD_MLD_CFG_INVALID_VALUE

System Log Message	The <i>object-name</i> configuration object <i>identifier</i> field has an invalid value of <i>value</i>
Description	The configuration request failed because the indicated configuration object contained the indicated invalid value.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

Action Modify configuration statement to use a valid value.

RPD_MLD_CFG_SOURCE_OUT_OF_RANGE

System Log Message The combination of source-count *count* and source-increment *ip-address* causes some of the sources out of range.

Description The configuration request failed because the indicated configuration object contained a source that is out of range.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Modify configuration statement to use a valid value.

RPD_MLD_DYN_CFG_ALREADY_BOUND

System Log Message Dynamic configuration session id *client-session-id* for interface *interface-name* is already bound to interface *old-interface-name*.

Description The indicated dynamic configuration session id is already bound to another interface. The dynamic configuration instantiation request was rejected.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Unbind session id from existing interface.

RPD_MLD_DYN_CFG_INVALID_STMT

System Log Message Invalid dynamic configuration statement: *configuration-statement*

Description The indicated dynamic configuration statement was invalid. The dynamic configuration instantiation request was rejected.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Remove the unsupported configuration statement.

RPD_MLD_DYN_CFG_SES_ID_ADD_FAIL

System Log Message Failed to add dynamic configuration session id *client-session-id* to interface *interface-name*.

Description Failed to associate the indicated dynamic configuration session id to specified interface. The dynamic configuration instantiation request was rejected.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_MLD_DYN_CFG_SES_ID_MISMATCH

System Log Message Dynamic configuration entry for interface *interface-name* with session id *client-session-id* found an existing entry with a different session id of *client-session-id-1*.

Description The dynamic configuration instantiation request matched an existing dynamic configuration block that had a different session id. The dynamic configuration instantiation request was rejected.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

RPD_MLD_JOIN

System Log Message Listener *source-address* sent a join to *destination-address* for group *group-address* source *sender-address* on interface *interface-name* at *time*

Description MLD join event.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_MLD_LEAVE

System Log Message Listener *source-address* sent a leave to *destination-address* for group *group-address* source *sender-address* on interface *interface-name* at *time*

Description MLD leave event.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_MLD_MEMBERSHIP_TIMEOUT

System Log Message Membership timeout for listener *source-address* for group *group-address* source *sender-address* on interface *interface-name* at *time*

Description	MLD group membership timeout.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

RPD_MLD_ROUTER_VERSION_MISMATCH

System Log Message	MLD version mismatch on <i>interface-name</i> . Local version: <i>local-version</i> Remote version: <i>remote-version</i>
Description	The MLD version running on the local router does not match the one received in the query
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

RPD_MPLS_INTERFACE_ROUTE_ERROR

System Log Message	Unable to add route in table <i>table-name</i> for label <i>mpls-label</i> pointing to <i>interface-name</i>
Description	There was a failure in adding a Multiprotocol Label Switching (MPLS) route pointing to an interface
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_MPLS_INTF_MAX_LABELS_ERROR

System Log Message	Maximum labels exceeded - failed to stack additional label to nexthop on interface <i>interface-name</i>
Description	There was a failure in stacking additional label to a nexthop which already has maximum number of labels allowed for the interface
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_MPLS_LSP_AUTOBW_NOTICE

System Log Message	mpls LSP <i>lsp-name</i> Autobw already in progress, ignoring new trigger
Description	The auto-bandwidth adjustment for the indicated Multiprotocol Label Switching (MPLS) label-switched path (LSP) already in progress, ignoring new trigger.
Type	Event: This message reports an event, not an error
Severity	notice

Facility LOG_DAEMON

RPD_MPLS_LSP_BANDWIDTH_CHANGE

System Log Message MPLS LSP *lsp-name* bandwidth changed, lsp bandwidth *bandwidth* bps

Description The bandwidth associated with the indicated Multiprotocol Label Switching (MPLS) label-switched path (LSP) changed.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

RPD_MPLS_LSP_CHANGE

System Log Message MPLS LSP *lsp-name* change on *path-type(pathname)* Route *lsp-rro* lsp bandwidth *bandwidth* bps

Description The indicated Multiprotocol Label Switching (MPLS) label-switched path (LSP) was rerouted and its Record Route Object (RRO) changed.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

RPD_MPLS_LSP_DOWN

System Log Message MPLS LSP *lsp-name* down on *path-type(pathname)*

Description The indicated Multiprotocol Label Switching (MPLS) label-switched path (LSP) went down and could not be used to send traffic.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

RPD_MPLS_LSP_SWITCH

System Log Message MPLS LSP *lsp-name* switch from *old-path-type(old-pathname)* to *new-path-type(new-pathname)*, Route *lsp-rro*: *reason* lsp bandwidth *bandwidth* bps

Description The indicated Multiprotocol Label Switching (MPLS) label-switched path (LSP) switched from primary path to secondary path or vice versa.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

RPD_MPLS_LSP_UP

System Log Message	MPLS LSP <i>lsp-name</i> up on <i>path-type(pathname)</i> Route <i>lsp-rrr</i> lsp bandwidth <i>bandwidth</i> bps
Description	The indicated Multiprotocol Label Switching (MPLS) label-switched path (LSP) came up and could be used to send traffic.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

RPD_MPLS_OAM_LSP_PING_REPLY_ERR

System Log Message	Received ping reply with an error: <i>error-code</i> .
Description	Received a LSP ping reply with an error code, for the ping request sent. If any failure action is configured, the failure action will get executed
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON

RPD_MPLS_OAM_PING_REPLY_TIMEOUT

System Log Message	LSP ping reply timed out
Description	LSP ping timed out waiting for a reply. If any failure action is configured, the failure action will get executed
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON

RPD_MPLS_OAM_READ_ERROR

System Log Message	Unable to read from pipe to MPLS OAM process: <i>reason (error-message)</i>
Description	The routing protocol process (rpd) could not read a message available on the read pipe from the MPLS Operation, Administration, and Maintenance process (mplsoamd).
Type	Error: An error occurred
Severity	info
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_MPLS_OAM_WRITE_ERROR

System Log Message	Unable to write to pipe to MPLS OAM process: (<i>error-message</i>)
Description	The routing protocol process (rpd) could not write a message on the write pipe to the MPLS Operation, Administration, and Maintenance process (mplsoamd).
Type	Error: An error occurred
Severity	info
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_MPLS_PATH_BANDWIDTH_CHANGE

System Log Message	MPLS path <i>pathname</i> (lsp <i>lsp-name</i>) bandwidth changed, path bandwidth <i>bandwidth</i> bps
Description	The bandwidth associated with the indicated Multiprotocol Label Switching (MPLS) path changed.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

RPD_MPLS_PATH_BFD_DOWN

System Log Message	BFD session for MPLS path <i>pathname</i> went down on LSP <i>lsp-name</i>
Description	The routing protocol process (rpd) determined that the Bidirectional Forwarding Detection (BFD) protocol session for the indicated Multiprotocol Label Switching (MPLS) path terminated on the indicated label-switched path (LSP).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_MPLS_PATH_BFD_UP

System Log Message	BFD session for MPLS path <i>pathname</i> came up on LSP <i>lsp-name</i>
Description	The routing protocol process (rpd) determined that the Bidirectional Forwarding Detection (BFD) protocol session for the the indicated Multiprotocol Label Switching (MPLS) path came up on the indicated label-switched path (LSP).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_MPLS_PATH_BW_NOT_AVAILABLE

System Log Message	Unable to satisfy bandwidth configured for MPLS path <i>pathname</i> on LSP <i>lsp-name</i>
Description	The bandwidth setting for the indicated Multiprotocol Label Switching (MPLS) path and label-switched path (LSP) was changed recently, but attempts to apply the new setting failed. The LSP continued to use the previous amount of bandwidth.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Action	Determine the reason that the bandwidth could not change and make the necessary changes to the software configuration, hardware configuration, or both.

RPD_MPLS_PATH_DOWN

System Log Message	MPLS path <i>pathname</i> down on LSP <i>lsp-name</i>
Description	The indicated Multiprotocol Label Switching (MPLS) path went down on the indicated label-switched path (LSP).
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

RPD_MPLS_PATH_PING_DOWN

System Log Message	LSP ping failure occurred for MPLS path <i>pathname</i> on LSP <i>lsp-name</i>
Description	The routing protocol process (rpd) determined that the LSP ping returned error for the indicated Multiprotocol Label Switching (MPLS) path terminated on the indicated label-switched path (LSP).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_MPLS_PATH_UP

System Log Message	MPLS path <i>pathname</i> up on LSP <i>lsp-name</i> path bandwidth <i>bandwidth</i> bps
Description	The indicated Multiprotocol Label Switching (MPLS) path came up on the indicated label-switched path (LSP).
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

RPD_MPLS_TABLE_ROUTE_ERROR

System Log Message	Unable to add route in table <i>table-name</i> for label <i>mpls-label</i> pointing to <i>next-table-name</i>
Description	There was a failure in adding a Multiprotocol Label Switching (MPLS) route pointing to another MPLS routing table
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_MSDP_CFG_SA_LIMITS_CONFLICT

System Log Message	Threshold value <i>threshold</i> must be less than or equal to maximum value <i>maximum-value</i> . Setting threshold to maximum
Description	The MSDP active-source-limit threshold is either undefined or exceeds the maximum value. Threshold will be set to maximum.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	ANY
Action	Consider modifying the MSDP active-source-limit configurations.

RPD_MSDP_CFG_SRC_INVALID

System Log Message	<i>argument</i> is an invalid source address
Description	The indicated MSDP source is configured with an invalid address
Type	Event: This message reports an event, not an error
Severity	warning
Facility	ANY
Action	Modify the configuration statement to use a valid value.

RPD_MSDP_PEER_DOWN

System Log Message	MSDP peer <i>peer-address</i> peer-group <i>peer-group</i> out of Established state
Description	The indicated MSDP peer left the Established state. The routing protocol process (rpd) deleted all active sources learned from the peer and will no longer send 'Source Active' messages to it.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_MSDP_PEER_UP

System Log Message MSDP peer *peer-address* peer-group *peer-group* into Established state

Description The indicated MSDP peer entered the Established state.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_MSDP_SRC_ACTIVE_OVER_LIMIT

System Log Message Number of MSDP source-active messages about *originator* exceeded configured limit *message*

Description The number of MSDP source-active messages received from the indicated instance, peer, or source exceeded the configured limit. All source-active messages are discarded until the limit is no longer exceeded. During periods when the event reported by this message occurs frequently, the routing protocol process (rpd) does not log every occurrence. In this case, the repetitions field in the message indicates how many times the event occurred since the rpd process previously logged this message.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

RPD_MSDP_SRC_ACTIVE_OVER_THRESH

System Log Message Number of MSDP source-active messages about *originator* exceeded configured threshold *message*

Description The number of MSDP source-active messages received from the indicated instance, peer, or source exceeded the configured threshold. Until the threshold is no longer exceeded, a random early discard (RED) profile is applied to incoming messages so that only some of them are accepted. During periods when the event reported by this message occurs frequently, the routing protocol process (rpd) does not log every occurrence. In this case, the repetitions field in the message indicates how many times the event occurred since the rpd process previously logged this message.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

RPD_MSDP_SRC_ACTIVE_UNDER_LIMIT

System Log Message Number of MSDP source-active messages about *originator* no longer exceeded configured limit *message*

Description The number of MSDP source-active messages received from the indicated instance, peer, or source no longer exceeded the configured limit. Active-source messages are no longer discarded automatically. During periods when the event reported by this message occurs frequently, the routing protocol process (rpd) does not log every occurrence. In this case, the repetitions field in the message indicates how many times the event occurred since the rpd process previously logged this message.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

RPD_MSDP_SRC_ACTIVE_UNDER_THRESH

System Log Message Number of MSDP source-active messages about *originator* no longer exceeded configured threshold *message*

Description The number of MSDP source-active messages received from the indicated instance, peer, or source no longer exceeded the configured threshold. A random early discard (RED) profile is no longer applied to incoming messages. During periods when the event reported by this message occurs frequently, the routing protocol process (rpd) does not log every occurrence. In this case, the repetitions field in the message indicates how many times the event occurred since the rpd process previously logged this message.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

RPD_MVPN_CFG_PREFIX_LEN_SHORT

System Log Message MVPN *argument*: prefix length *prefix-length* is too short for prefix *route-prefix*, ignoring excess host bits

Description The prefix length for MVPN source or group object is too short and the indicated prefix has a non-zero host portion. Excess host bits will be ignored.

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

RPD_OSPF_CFGNBR_P2P

System Log Message Ignored configured neighbors on point-to-point realm *realm-name* interface *interface-name* area *area-id*

Description For point-to-point interfaces, OSPF neighbors are learned by using hello messages, so the implicit configuration of neighbors was ignored for the indicated point-to-point interface.

Type Error: An error occurred

Severity	warning
Facility	LOG_DAEMON
Action	Remove the neighbor configuration for the indicated interface.

RPD_OSPF_IF_COST_CHANGE

System Log Message	Interface <i>interface-name</i> (<i>interface-address</i>) area <i>area-idi</i> : cost changed <i>cost</i> -> <i>metric</i>
Description	OSPF interface cost changed due to change in interface bandwidth
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

RPD_OSPF_LDP_SYNC

System Log Message	OSPF realm <i>realm-name</i> interface <i>interface-name</i> area <i>area-idi</i> advertised with infinite metric for <i>duration</i> seconds already due to loss of synchronization with LDP
Description	The OSPF protocol lost synchronization with the Label Distribution Protocol (LDP) on the indicated interface. As a consequence, it began advertising an infinite metric for the interface and has been doing so for the indicated number of seconds.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Action	Determine why LDP lost synchronization with OSPF.

RPD_OSPF_LSA_MAXIMUM_EXCEEDED

System Log Message	OSPF realm <i>realm-name</i> number of non-local LSAs exceeded maximum limit
Description	The number of non self-generated LSAs exceeded maximum limit specified for database protection in the indicated realm. Consequently, all non self-generated LSA were deleted and all neighbors were killed. The router will not send any OSPF hellos and will ignore any incoming OSPF packets till ignore-time has elapsed.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_OSPF_LSA_WARNING_EXCEEDED

System Log Message	OSPF realm <i>realm-name</i> number of non-local LSAs exceeded warning limit
Description	The number of non self-generated LSAs exceeded warning limit specified for database protection in the indicated realm.

Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_OSPF_NBRDOWN

System Log Message	OSPF neighbor <i>neighbor-address</i> (realm <i>realm-name</i> interface <i>interface-name</i> area <i>area-idi</i>) state changed from <i>old-state</i> to <i>new-state</i> due to <i>event-name</i> (event reason: <i>reason</i>)
Description	An OSPF adjacency with the indicated neighboring router was terminated. The local router no longer exchanges routing information with, or directs traffic to, the neighboring router.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_OSPF_NBRUP

System Log Message	OSPF neighbor <i>neighbor-address</i> (realm <i>realm-name</i> interface <i>interface-name</i> area <i>area-idi</i>) state changed from <i>old-state</i> to <i>new-state</i> due to <i>event-name</i> (event reason: <i>reason</i>)
Description	An OSPF adjacency was established with the indicated neighboring router. The local router can now exchange information with it.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

RPD_OSPF_OVERLOAD

System Log Message	OSPF instance <i>instance</i> topology <i>topology</i> is going into overload state: number of export prefixes (<i>count</i>) exceeded maximum allowed (<i>maximum-value</i>)
Description	The indicated topology in the indicated OSPF instance became overloaded and will remain in that state until an administrator intervenes.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Cause	The number of export prefixes exceeded the configured limit.
Action	Unconfigure or modify export policies that inject a large number of routes.

RPD_OSPF_TOPO_IF_COST_CHANGE

System Log Message	Interface <i>interface-name</i> (<i>interface-address</i>) area <i>area-idi</i> topology <i>topology</i> : cost changed <i>cost</i> -> <i>metric</i>
---------------------------	--

Description OSPF topology interface cost changed due to change in interface bandwidth

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_OS_MEMHIGH

System Log Message Using *size* KB of memory, *percentage-value* percent of available

Description The routing protocol process (rpd) is using the indicated amount and percentage of Routing Engine memory, which is considered excessive.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause Either rpd is leaking memory or the use of system resources is excessive, perhaps because routing filters are misconfigured or the configured network topology is very complex.

Action Increase the amount of RAM in the Routing Engine.

RPD_PARSE_BAD_LR_NAME

System Log Message *executable-name*: logical system name "*logical-system-name*" exceeds *count* characters

Description The indicated logical system name exceeds the indicated maximum number of characters.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Assign a shorter name.

RPD_PARSE_BAD_OPTION

System Log Message *executable-name*: command-line option *option* is invalid

Description The command line used to start the indicated process included the indicated option, which is invalid. The process did not start.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Reissue the command without the invalid option.

RPD_PARSE_CMD_ARG

System Log Message	<i>executable-name</i> : missing required argument for command-line option <i>option</i>
Description	The command line used to start the indicated process did not include the argument required by the indicated option. The process did not start.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Reissue the command and include the required argument.

RPD_PARSE_CMD_DUPLICATE

System Log Message	<i>executable-name</i> : command-line option <i>option</i> is a duplicate
Description	The command line used to start the indicated process included the indicated duplicate option. The process did not start.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Reissue the command without the duplicate option.

RPD_PARSE_CMD_EXTRA

System Log Message	<i>executable-name</i> : command-line option <i>option</i> is extraneous
Description	The command line used to start the indicated process included the indicated option, which is extraneous. The process did not start.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Reissue the command and omit the extraneous option.

RPD_PIM_NBRDOWN

System Log Message	Instance <i>routing-instance</i> : PIM neighbor <i>neighbor-address</i> (<i>interface-name</i>) removed due to: <i>reason</i>
Description	The routing protocol process (rpd) declared the indicated PIM neighbor inactive.
Type	Event: This message reports an event, not an error
Severity	notice

Facility LOG_DAEMON

RPD_PIM_NBRUP

System Log Message Instance *routing-instance*: PIM new neighbor *neighbor-address* interface *interface-name*

Description The routing protocol process (rpd) discovered the indicated new PIM neighbor on the indicated interface.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_PLCY_CFG_COMMUNITY_FAIL

System Log Message Failed to parse community string under policy-options: *error-message*

Description The routing protocol process (rpd) encountered a non-catastrophic error in bgp community member string while parsing policy-options.

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

RPD_PLCY_CFG_FWDCLASS_OVERRIDDEN

System Log Message *argument* supersedes forwarding-class under policy-statement *policy-name*

Description During configuration parsing, a destination-class or source-class statement overrode the forwarding-class statement.

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

RPD_PLCY_CFG_IFALL_NOMATCH

System Log Message The interface 'all' statement under policy-statement *policy-name* will not match anything

Description Interface 'all' does not have any special meaning under the policy-options hierarchy unlike under various other hierarchies

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

RPD_PLCY_CFG_NH_NETMASK

System Log Message Netmask ignored for next hop: *argument*.

Description A netmask was specified with the indicated next hop. The netmask is ignored. In a future release, a next hop address with netmask may generate a configuration error

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

RPD_PLCY_CFG_PARSE_GEN_FAIL

System Log Message Policy warning: *error-message*

Description A conflict was detected while parsing the policy-options configuration hierarchy

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

RPD_PLCY_CFG_PREFIX_LEN_SHORT

System Log Message prefix length *prefix-length* is too short for prefix *route-prefix* under policy-statement *policy-name*, ignoring excess host bits

Description The prefix length for the indicated prefix is too short and it has a non-zero host portion. Excess host bits will be ignored.

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

RPD_PPM_READ_ERROR

System Log Message Read error on pipe from ppmd: *reason (error-message)*

Description The routing protocol process (rpd) could not read a message available on the read pipe from the periodic packet management process (ppmd).

Type Error: An error occurred

Severity info

Facility LOG_DAEMON

Action Contact your technical support representative.

RPD_PPM_WRITE_ERROR

System Log Message *function-name*: write error on pipe to ppmd (*error-message*)

Description The routing protocol process (rpd) could not write a message on the pipe to the periodic packet management process (ppmd).

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_RA_CFG_CREATE_ENTRY_FAILED

System Log Message	Could not create entry for <i>entry</i> .
Description	The configuration request failed because the IPv6 routing advertisements failed to create the indicate configuration entry.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_RA_CFG_INVALID_VALUE

System Log Message	The <i>object-name</i> configuration object <i>identifier</i> field has an invalid value of <i>value</i>
Description	The configuration request failed because the configuration object contained the indicated invalid value.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Change the value in the configuration statement to a valid one.

RPD_RA_DYN_CFG_ALREADY_BOUND

System Log Message	Dynamic configuration session id <i>client-session-id</i> for interface <i>interface-name</i> is already bound to interface <i>old-interface-name</i> .
Description	The dynamic configuration instantiation request was rejected because the indicated session ID was already bound to another interface.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Unbind session id from existing interface.

RPD_RA_DYN_CFG_INVALID_STMT

System Log Message	Invalid dynamic configuration statement: <i>configuration-statement</i>
Description	The dynamic configuration instantiation request was rejected because the indicated dynamic configuration statement was invalid.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Remove the unsupported configuration statement.

RPD_RA_DYN_CFG_SES_ID_ADD_FAIL

System Log Message	Failed to add dynamic configuration session id <i>client-session-id</i> to interface <i>interface-name</i> .
Description	The dynamic configuration instantiation request was rejected because it failed to associate the indicated session ID with the specified interface.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_RA_DYN_CFG_SES_ID_MISMATCH

System Log Message	Dynamic configuration entry for interface <i>interface-name</i> with session id <i>client-session-id</i> found an existing entry with a different session id of <i>client-session-id-1</i> .
Description	The dynamic configuration instantiation request was rejected because it matched an existing dynamic configuration block that had a different session ID.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_RDISC_CKSUM

System Log Message	Bad checksum for router solicitation from <i>source-address</i> to <i>destination-address</i>
Description	The routing protocol process (rpd) ignored a router discovery solicitation message from the indicated address because the checksum in the message's ICMP header was invalid.
Type	Event: This message reports an event, not an error

Severity	warning
Facility	LOG_DAEMON
Cause	The solicitation message was incorrectly generated or damaged in transit.
Action	Examine the host that generated the solicitation message.

RPD_RDISC_NOMULTI

System Log Message	Ignoring interface <i>interface-address</i> on <i>interface-name</i> -- multicast not available
Description	The indicated interface was configured for router discovery, but does not support IP multicast operations as required. The routing protocol process (rpd) did not enable router discovery on the interface.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Action	Do not configure router discovery on the interface.

RPD_RDISC_NORECVIF

System Log Message	Unable to locate interface for router solicitation from <i>source-address</i> to <i>destination-address</i>
Description	The routing protocol process (rpd) ignored a router discovery solicitation message from the indicated router because the router's IP address does not share the IP prefix of the local router. The local router is not a candidate for the indicated router because they are not on the same network.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	Although the indicated router seems to be locally attached, no interfaces on the local router are configured to handle its IP address. Either the indicated router is configured with the wrong IP address, or the local router is not correctly configured for the network that the indicated router is using.
Action	Ignore this message if it indicates the desired configuration, or reconfigure one or both routers to share a common network.

RPD_RDISC_SOLICITADDR

System Log Message	Expected multicast (<i>expected-address</i>) for router solicitation from <i>source-address</i> to <i>destination-address</i>
---------------------------	---

Description	A router discovery solicitation message received from the indicated address was not sent to the expected multicast address for all routers.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Action	Examine the configuration of the router that generated the router discovery solicitation message.

RPD_RDISC_SOLICITICMP

System Log Message	Nonzero ICMP code (<i>value</i>) for router solicitation from <i>source-address</i> to <i>destination-address</i>
Description	The routing protocol process (rpd) ignored a router discovery solicitation message from the indicated router because the ICMP code in the message header was nonzero.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	The solicitation message was incorrectly generated.
Action	Examine the host that generated the solicitation message.

RPD_RDISC_SOLICITLEN

System Log Message	Insufficient length (<i>length</i>) for router solicitation from <i>source-address</i> to <i>destination-address</i>
Description	The routing protocol process (rpd) ignored a router discovery solicitation message from the indicated router, because the indicated message length is too short.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	The solicitation message was incorrectly generated.
Action	Examine the host that generated the solicitation message.

RPD_RIP_AUTH_REQUEST

System Log Message	Request with invalid authentication from <i>source-address</i> (<i>interface-name</i>)
Description	The routing protocol process (rpd) ignored an RIP request because the request authentication failed.

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_DAEMON

RPD_RIP_AUTH_UPDATE

System Log Message Update with invalid authentication from *source-address (interface-name)*
Description The routing protocol process (rpd) ignored a RIP update because authentication of the update failed.
Type Event: This message reports an event, not an error
Severity notice
Facility LOG_DAEMON

RPD_RIP_JOIN_BROADCAST

System Log Message Unable to get broadcast address on *interface-name*; using the all-ones address
Description RIP cannot run on the indicated interface because the routing protocol process (rpd) could not obtain the broadcast address on the interface as required for running RIP version 1 or version 2 in compatibility mode.
Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RPD_RIP_JOIN_MULTICAST

System Log Message Unable to join multicast group on *interface-name: error-message*
Description RIP cannot run on the indicated interface, because the routing protocol process (rpd) could not join the RIP multicast group as required for RIP version 2 multicast updates.
Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RPD_RSVP_BACKUP_DOWN

System Log Message Backup for protecting LSP *lsp-name* down, using bypass *bypass-lsp-name* reason
Description When link protection is enabled, a backup label-switched path (LSP) is needed to maintain a protected LSP's control-plane connectivity when topology failures are detected. The backup LSP for the indicated protected LSP failed. The failure can cause traffic loss because the protected LSP tears down when there is no backup. If the reason for the backup failure can be determined, it is reported in the message.
Type Event: This message reports an event, not an error

Severity warning
Facility LOG_DAEMON

RPD_RSVP_BYPASS_DOWN

System Log Message RSVP bypass *bypass-lsp-name* for protecting interface *interface-name* went down *reason*

Description The indicated RSVP link-protection bypass, which was protecting the indicated interface, was terminated. If the reason for the termination can be determined, it is reported in the message.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

RPD_RSVP_BYPASS_UP

System Log Message RSVP bypass *bypass-lsp-name* for protecting interface *interface-name* came up

Description The indicated RSVP link-protection bypass was established to protect the indicated interface.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

RPD_RSVP_COS_CFG_WARN

System Log Message RSVP: Error while checking the existence of [edit class-of-service]: *error-message*

Description RSVP detected an error while parsing configurations under the CoS hierarchy. RSVP CoS configurations will be ignored.

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

RPD_RSVP_LSP_SWITCH

System Log Message RSVP LSP *lsp-name* switched to backup; using bypass LSP *bypass-lsp-name*, route *lsp-rro*

Description RSVP detected a failure downstream for the indicated label-switched path (LSP) and switched it to a backup using the indicated bypass LSP.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

Cause The downstream interface or router for the LSP went down.

RPD_RSVP_MAXIMUM_SESSIONS

System Log Message RSVP maximum session limit of *limit* reached

Description The routing protocol process (rpd) could not set up an RSVP session because the indicated limit on the number of sessions was reached.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

RPD_RSVP_NBRDOWN

System Log Message RSVP neighbor *neighbor-address* down on interface *interface-name*, *reason*

Description The RSVP neighbor to the indicated address was terminated.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

Cause The communication path to the neighboring router was disrupted, a protocol error occurred, or the neighboring router was powered down.

RPD_RSVP_NBRUP

System Log Message RSVP neighbor *neighbor-address* up on interface *interface-name*

Description An RSVP neighbor was established to the indicated address.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

RPD_RT_CFG_BR_CONFLICT

System Log Message static route: *route-prefix* is also configured as backup-router destination, turn on retain flag to ensure proper functionality

Description A conflict occurred between the system backup router configuration and the indicated static route.

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

Action Add the retain flag to the static route

RPD_RT_CFG_CREATE_ENTRY_FAILED

System Log Message	Could not create entry <i>entry</i>
Description	RT failed to create the indicated configuration entry. The configuration request failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_RT_CFG_INVALID_VALUE

System Log Message	The <i>object-name</i> configuration object <i>identifier</i> field has an invalid value of <i>value</i>
Description	The configuration request failed because the indicated configuration object contained the indicated invalid value.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Modify configuration statement to use a valid value.

RPD_RT_CFG_TABLE_NON_MATCHING

System Log Message	Routing-table <i>table-name</i> under routing-instance <i>instance</i> associated with session-id <i>session-id</i> does not match the instance
Description	The dynamic config request with a specific session id and routing-instance cannot be completed because a routing-table where routes should be added does not match the instance
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_RT_DUPLICATE_RD

System Log Message	routing-instance <i>routing-instance</i> has duplicate route-distinguisher <i>route-discriminator</i> as routing-instance <i>existing-routing-instance</i>
Description	The route-distinguisher assigned to this routing instance has already been assigned to another routing instance (as indicated).
Type	Error: An error occurred
Severity	error

Facility LOG_DAEMON

RPD_RT_DYN_CFG_INST_NOT_FOUND

System Log Message Routing-instance *instance* associated with session-id *session-id* not found

Description The dynamic-config request for a specific session id and routing-instance cannot be completed because the instance was not found

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_RT_DYN_CFG_TABLE_NOT_FOUND

System Log Message Routing-table *table-name* under routing-instance *instance* associated with session-id *session-id* not found

Description The dynamic config request with a specific session id and routing-instance cannot be completed because a routing table where routes should be added was not found

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_RT_ERROR

System Log Message *rt_event_event-name*: fatal state error

Description A route in the routing table was found to be in an unrecoverable error state.

Type Error: An error occurred

Severity critical

Facility LOG_DAEMON

RPD_RT_IFUP

System Log Message UP route for interface *interface-name* index *logical-interface-index* *address/prefix-length*

Description The interface route for the indicated interface and prefix changed state from down to up, becoming available for routing.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

RPD_RT_INST_CFG_RESERVED_NAME

System Log Message The routing-instance name *instance* is reserved and cannot be used

Description The routing-instances configuration was rejected by rpd because of a reserved routing-instance name was used

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_RT_INST_IMPORT_PLCY_WARNING

System Log Message Instance *routing-instance: command*routing-options instance-import]error-message

Description The policy configured for instance-import in the indicated instance needs modification to become operational.

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

RPD_RT_PATH_LIMIT_BELOW

System Log Message Number of paths (*count*) in table *table-name* is now less than the configured maximum (*limit*)

Description The number of paths in the indicated routing table previously equaled or exceeded the indicated limit, but went down to the indicated number, which is below the limit.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

RPD_RT_PATH_LIMIT_REACHED

System Log Message Number of paths (*count*) in table *table-name* status configured maximum (*limit*)

Description The indicated total number of paths in the indicated routing table equaled or exceeded the indicated configured limit. Attempts to add some types of path to the table fail while this condition holds, but the path count can exceed the limit if paths are forcibly added (for example, for static routes). This message first appears in the log when the limit is reached and repeats periodically until the number of paths goes below the limit.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_RT_PATH_LIMIT_WARNING

System Log Message Number of paths (*count*) in table *table-name* reached warning threshold (*threshold* percent of configured maximum *limit*)

Description The indicated total number of paths in the indicated routing table reached the threshold for a warning. The threshold is the indicated percentage of the indicated configured limit on the number of paths.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

RPD_RT_PREFIX_LIMIT_BELOW

System Log Message Number of prefixes (*prefix-count*) in table *table-name* is now less than the configured maximum (*limit*)

Description The number of prefixes in the indicated routing table previously equaled or exceeded the indicated limit, but went down to the indicated number, which is below the limit.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

RPD_RT_PREFIX_LIMIT_REACHED

System Log Message Number of prefixes (*prefix-count*) in table *table-name status* configured maximum (*limit*)

Description The indicated total number of prefixes in the indicated routing table equaled or exceeded the indicated configured limit. Attempts to add some types of prefix to the table fail while this condition holds, but the prefix count can exceed the limit if prefixes are forcibly added (for example, for static routes). This message first appears in the log when the limit is reached and repeats periodically until the number of prefixes goes below the limit.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_RT_PREFIX_LIMIT_WARNING

System Log Message Number of prefixes (*prefix-count*) in table *table-name* reached warning threshold (*threshold* percent of configured maximum *limit*)

Description The indicated total number of prefixes in the indicated routing table reached the threshold for a warning. The threshold is the indicated percentage of the indicated configured limit on the number of prefixes.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

RPD_RT_SHOWMODE

System Log Message	invalid display mode (<i>mode</i>)
Description	The indicated display mode was specified in a 'show route' command and is unsupported.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_RT_TAG_ID_ALLOC_FAILED

System Log Message	Unable to allocate <i>object-name</i> for routing instance <i>instance</i>
Description	The routing protocol process (rpd) could not allocate either labels or subunits (as indicated) for the indicated routing instance, because the result number of objects would have exceeded the limit.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_SCHED_CALLBACK_LONGRUNTIME

System Log Message	<i>function-name</i> : excessive runtime <i>time</i> during <i>action</i> of <i>module</i>
Description	The indicated submodule of the routing protocol process (rpd) ran uninterrupted for the indicated period of time, which is considered excessive.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	The duration was noted because task accounting is enabled. The function might be implemented inefficiently.

RPD_SCHED_CUMULATIVE_LONGRUNTIME

System Log Message	<i>function-name</i> : excessive runtime (total of <i>time</i> in <i>count</i> callbacks) after <i>action</i> of <i>module</i>
Description	Several submodules of the routing protocol process (rpd) ran uninterrupted for the indicated period of time, which is considered excessive.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	The duration was noted because task accounting is enabled. The function might be implemented inefficiently.

RPD_SCHED_MODULE_LONGRUNTIME

System Log Message	<i>function-name: excessive runtime time during action of module</i>
Description	Several submodules of the routing protocol process (rpd) ran uninterrupted for the indicated period of time, which is considered excessive.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	The duration was noted because task accounting is enabled. The function might be implemented inefficiently.

RPD_SCHED_TASK_LONGRUNTIME

System Log Message	<i>function-name ran for total-time (user-time user, system-time system) doing action</i>
Description	A task callback within the routing protocol process (rpd) ran uninterrupted for the indicated period of time, which is considered excessive.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	The duration was noted because task accounting is enabled. The function might be implemented inefficiently.

RPD_SIGNAL_TERMINATE

System Log Message	<i>signal-name</i> termination signal received
Description	In response to the indicated termination request, the routing protocol process (rpd) terminated adjacencies with neighbors and shut down.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_SNMP_CONN_PROG

System Log Message	<i>function-name: error-message</i>
Description	The indicated error occurred while the routing protocol process (rpd) was connecting to the Simple Network Management Protocol (SNMP) master agent.
Type	Error: An error occurred
Severity	info

Facility LOG_DAEMON

RPD_SNMP_CONN_QUIT

System Log Message *function-name: unable to connect to SNMP agent (pathname): error-message*

Description The routing protocol process (rpd) could not connect to the indicated Simple Network Management Protocol (SNMP) master agent.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_SNMP_CONN_RETRY

System Log Message *function-name: reattempting connection to SNMP agent (pathname): error-message*

Description The routing protocol process (rpd) tried again to connect to the indicated Simple Network Management Protocol (SNMP) master agent after a connection attempt failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_SNMP_INVALID_SOCKET

System Log Message *function-name: socket file-descriptor is invalid*

Description The routing protocol process (rpd) could not send a message to a Simple Network Management Protocol (SNMP) master agent because the indicated socket is invalid.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_SNMP_SOCKOPT_BLOCK

System Log Message *function-name: unable to set nonblocking option*

Description The routing protocol process (rpd) could not set a socket to nonblocking mode after connecting to the Simple Network Management Protocol (SNMP) master agent.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_SNMP_SOCKOPT_RECVBUF

System Log Message *function-name: unable to set recvbuf option*

Description The routing protocol process (rpd) could not set the size of the kernel receive buffer, which allows it to accept the largest possible packet from the Simple Network Management Protocol (SNMP) master agent.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_SNMP_SOCKET_OPT_SENDBUF

System Log Message *function-name: unable to set sendbf option*

Description The routing protocol process (rpd) could not set the size of the kernel send buffer, which allows it to send the largest possible packet to the Simple Network Management Protocol (SNMP) master agent.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_START

System Log Message Start *executable-name*[*pid*] version *version* built *date*

Description The routing protocol process (rpd) started.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_SYSTEM

System Log Message *reason: error-message*

Description A system call made by the routing protocol process (rpd) failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause It is possible that the kernel lacked the resources to fulfill the request. The rpd process will recover.

RPD_TASK_BEGIN

System Log Message Commencing routing updates, version *rpd-version*, built *date* by *builder*

Description The routing protocol process (rpd) started.

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_DAEMON

RPD_TASK_CHILDKILLED

System Log Message *task-name* terminated by SIG*signal-name**core-dump-status*
Description While a child process of the routing protocol process (rpd) was performing the indicated operation, it terminated in response to the indicated signal.

Type Event: This message reports an event, not an error
Severity error
Facility LOG_DAEMON

RPD_TASK_CHILDSTOPPED

System Log Message *task-name* stopped by SIG*signal-name*
Description While a child process of the routing protocol process (rpd) was performing the indicated operation, it stopped in response to the indicated signal.

Type Event: This message reports an event, not an error
Severity error
Facility LOG_DAEMON

RPD_TASK_DYN_REINIT

System Log Message Dynamic reconfiguration in process
Description The routing protocol process (rpd) reinitialized.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_DAEMON

RPD_TASK_FORK

System Log Message Unable to fork *task-name*: *error-message*
Description The routing protocol process failed to create the indicated child process.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RPD_TASK_GETWD

System Log Message *getwd*: *error-message*

Description	The getwd() system call made by the routing protocol process (rpd) failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	It is possible that the kernel lacked the resources to fulfill the request. The rpd process will recover.

RPD_TASK_MASTERSHIP

System Log Message	Assuming mastership
Description	The routing protocol process (rpd) became active when the Routing Engine on which it was running assumed mastership.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

RPD_TASK_NOREINIT

System Log Message	Reinitialization not possible
Description	The routing protocol process (rpd) failed to reinitialize as requested, because it was running in a state that did not allow reconfiguration.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_TASK_PIDCLOSED

System Log Message	Unable to close and remove <i>filename: error-message</i>
Description	The routing protocol process (rpd) tried to close and remove the file that records its process ID (PID), which serves to prevent multiple instances of rpd from running simultaneously. The attempt failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_TASK_PIDFLOCK

System Log Message	flock(<i>filename</i> , LOCK_EX): <i>error-message</i>
---------------------------	---

Description The routing protocol process (rpd) issued the flock() system call on the file that records its process ID (PID), which serves to prevent multiple instances of rpd from running simultaneously. The system call failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_TASK_PIDWRITE

System Log Message Unable to write to fd *filename*: *error-message*

Description The routing protocol process (rpd) tried to write to the file that records its process ID (PID), which serves to prevent multiple instances of rpd from running simultaneously. The attempt failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_TASK_REINIT

System Log Message Reinitializing

Description The routing protocol process (rpd) reinitialized.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_TASK_SIGNALIGNORE

System Log Message sigaction(SIG*signal-name*): *error-message*

Description The routing protocol process (rpd) informed the kernel that it wished to ignore the indicated signal, but the kernel failed to process the request.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_TRACE_FAILED

System Log Message Unable to write to trace file *filename*

Description The routing protocol process (rpd) could not write to the indicated trace file, and stopped attempting to do so. The next commit of the configuration database will reenables tracing.

Type Event: This message reports an event, not an error

Severity error
Facility LOG_DAEMON

RPD_VPLS_INTF_NOT_IN_SITE

System Log Message Some interfaces of instance *instance* are not configured under its single site

Description Some interfaces of the indicated vpls instance have not been configured under the sole site of the instance.

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

Action Configure all interfaces of the instace under its single site.

RPD_ABORT

System Log Message abort *executable-name*[*pid*] version *version* built by *builder* on *date*: *error-message*

Description The routing protocol process (rpd) terminated because of an internal error.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Examine the messages that immediately follow this message in the system log for information about possible causes.

Cause An internal software failure occurred.

RPD_ACTIVE_TERMINATE

System Log Message Exiting with active tasks: *task-name*

Description After receiving multiple termination requests, the routing protocol process (rpd) exited without performing the indicated cleanup tasks.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

RPD_AMT_CFG_ADDR_FMLY_INVALID

System Log Message Valid address family information is required

Description An invalid address family value was encountered while parsing AMT configuration.

Type Event: This message reports an event, not an error

Severity	warning
Facility	ANY
Action	Modify the configuration statement to use a valid value.

RPD_AMT_CFG_ANYCAST_INVALID

System Log Message	An invalid anycast-prefix is configured
Description	An invalid anycast prefix was encountered while parsing AMT configuration.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	ANY
Action	Modify the configuration statement to use a valid value.

RPD_AMT_CFG_ANYCAST_MCAST

System Log Message	Anycast-prefix <i>route-prefix</i> cannot be a multicast address
Description	A multicast address cannot be configured as the anycast-prefix
Type	Event: This message reports an event, not an error
Severity	warning
Facility	ANY
Action	Modify the configuration statement to use a valid value.

RPD_AMT_CFG_LOC_ADDR_INVALID

System Log Message	An invalid local-address is configured
Description	An invalid local address was encountered while parsing AMT configuration.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	ANY
Action	Modify the configuration statement to use a valid value.

RPD_AMT_CFG_LOC_ADDR_MCAST

System Log Message	Local-address <i>route-prefix</i> cannot be a multicast address
Description	A multicast address cannot be configured as the local-address.
Type	Event: This message reports an event, not an error

Severity	warning
Facility	ANY
Action	Modify the configuration statement to use a valid value.

RPD_AMT_CFG_PREFIX_LEN_SHORT

System Log Message	Prefix length <i>prefix-length</i> is too short for prefix <i>route-prefix</i>
Description	The prefix length for the indicated prefix is too short and it has a non-zero host portion. Excess host bits will be ignored.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	ANY

RPD_AMT_CFG_RELAY_INVALID

System Log Message	Invalid relay information is configured
Description	Invalid relay configuration was encountered while parsing AMT configuration.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	ANY
Action	Modify the configuration statement to use a valid value.

RPD_AMT_RELAY_DISCOVERY

System Log Message	AMT relay discovery message from gateway <i>destination-address</i> port <i>destination-port</i> at <i>time</i>
Description	AMT relay discovery event.
Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

RPD_AMT_TUNNEL_CREATE

System Log Message	Tunnel created between gateway <i>destination-address</i> port <i>destination-port</i> relay <i>source-address</i> port <i>source-port</i> on interface <i>interface-name</i> at <i>time</i>
Description	AMT tunnel create event.
Type	Event: This message reports an event, not an error
Severity	info

Facility ANY

RPD_AMT_TUNNEL_DELETE

System Log Message Tunnel deleted between gateway *destination-address* port *destination-port* relay *source-address* port *source-port* on interface *interface-name* at *time*

Description AMT tunnel delete event.

Type Event: This message reports an event, not an error

Severity info

Facility ANY

RPD_ASSERT

System Log Message Assertion failed *executable-name*[*pid*]: file "*source-filename*", line *line-number*: "*message*"

Description The source code for the routing protocol process (rpd) includes internal self-consistency checks. A check failed at the indicated line number in the indicated source file, causing the instance of rpd that was using the indicated binary and had the indicated process ID (PID) to terminate. The process created a diagnostic core dump for analysis by technical support personnel.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause An internal software failure occurred.

Action Examine the messages that immediately follow this message in the system log for information about possible causes. Contact a technical support representative, and be ready to provide the list of messages and the diagnostic core dump, if requested.

RPD_ASSERT_SOFT

System Log Message Soft assertion failed *executable-name*[*pid*]: file "*source-filename*", line *line-number*: "*message*", daemon continued running

Description The source code for the routing protocol process (rpd) includes internal self-consistency checks. A check failed at the indicated line number in the indicated source file, but the instance of rpd that was using the indicated binary and had the indicated process ID (PID) continued running. The process created a diagnostic core dump for analysis by technical support personnel.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause An internal software failure occurred.

Action Examine the messages that immediately follow this message in the system log for information about possible causes. Contact a technical support representative, and be ready to provide the list of messages and the diagnostic core dump, if requested.

RPD_BFD_READ_ERROR

System Log Message Read error on pipe from bfdd: *reason (error-message)*

Description The routing protocol process (rpd) could not read a message available on the read pipe from the Bidirectional Forwarding Detection process (bfdd).

Type Error: An error occurred

Severity info

Facility LOG_DAEMON

Action Contact your technical support representative.

RPD_BFD_WRITE_ERROR

System Log Message *function-name*: write error on pipe to bfdd (*error-message*)

Description The routing protocol process (rpd) could not write a message on the pipe to the Bidirectional Forwarding Detection process (bfdd).

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

RPD_BGP_CFG_ADDR_INVALID

System Log Message Invalid *argument* address *ip-address*

Description An invalid local or neighbor address was encountered while parsing BGP configuration.

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

Action Modify the configuration statement to use a valid value.

RPD_BGP_CFG_LOCAL_ASNUM_WARN

System Log Message local as-number cannot be set to confederation as-number *data-id*, statement ignored

Description Local autonomous-system number cannot be set to the confederation autonomous-system number. Statement will be ignored.

Type	Event: This message reports an event, not an error
Severity	warning
Facility	ANY

RPD_BGP_NEIGHBOR_STATE_CHANGED

System Log Message	BGP peer <i>peer-name</i> changed state from <i>old-state</i> to <i>new-state</i> (event <i>event-type</i>)
Description	During BGP negotiation with the local router, the state of the indicated BGP neighbor (peer) changed as indicated. The ESTABLISHED state is the final state in the neighbor negotiation.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

RPD_CFG_TRACE_FILE_MISSING

System Log Message	No file specified under traceoptions hierarchy
Description	The routing protocol process (rpd) could not find the 'file' statement under a traceoptions hierarchy. This would prevent it from performing tracing.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	ANY

RPD_DYN_CFG_BUSY_SIGNAL_FAILED

System Log Message	Dynamic config <i>action</i> busy signal failed: <i>error-message</i>
Description	The routing protocol process (rpd) failed to notify the dynamic configuration clients about its availability to process the dynamic configuration requests.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_DYN_CFG_GET_PROFILE_FAILED

System Log Message	Get dynamic profiles failed: <i>error-code</i>
Description	The routing protocol process (rpd) tried to load a profile from the database and failed.
Type	Error: An error occurred
Severity	error

Facility LOG_DAEMON

RPD_DYN_CFG_GET_PROF_NAME_FAILED

System Log Message Get profile name for session *client-session-id* failed: *error-code*

Description The routing protocol process (rpd) tried to get the profile name from the session snapshot and failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

RPD_DYN_CFG_GET_SES_STATE_FAILED

System Log Message Get session state for session *client-session-id* failed: *error-code*

Description The routing protocol process (rpd) failed to get the session state from the session snapshot.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

RPD_DYN_CFG_GET_SES_TYPE_FAILED

System Log Message Get session type for session *client-session-id* failed: *error-code*

Description The routing protocol process (rpd) tried to get the session type from the session snapshot and failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

RPD_DYN_CFG_GET_SNAPSHOT_FAILED

System Log Message Get session id *client-session-id* snapshot failed: *error-code*

Description The routing protocol process (rpd) tried to load client session data from the database and failed.

Type Error: An error occurred

Severity error
Facility LOG_DAEMON

RPD_DYN_CFG_PDB_CLOSE_FAILED

System Log Message Failed to close profile database: *error-code*
Description The routing protocol process (rpd) tried to close the profile database and failed.
Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RPD_DYN_CFG_PDB_OPEN_FAILED

System Log Message Failed to open profile database: *error-code*
Description The routing protocol process (rpd) tried to open the profile database and failed.
Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RPD_DYN_CFG_PROCESSING_FAILED

System Log Message Module *module* failed to process dynamic configuration
Description The routing protocol process (rpd) tried to process dynamic configuration and failed.
Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RPD_DYN_CFG_REGISTER_FAILED

System Log Message Dynamic config registration failed: *error-message*
Description The routing protocol process (rpd) tried to register with the dynamic configuration subsystem and failed.
Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RPD_DYN_CFG_REQUEST_ACK_FAILED

System Log Message Failed to ack request *data-id*: *error-code*
Description The routing protocol process (rpd) tried to acknowledge a dynamic configuration request and failed.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RPD_DYN_CFG_RESPONSE_SLOW

System Log Message Dynamic config response for session id *client-session-id* took *system-seconds* seconds
Description The routing protocol process (rpd) is responding slowly to dynamic config requests.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON
Action Contact your technical support representative.

RPD_DYN_CFG_SCHEMA_OPEN_FAILED

System Log Message Could not open configuration schema: *error-message*
Description The routing protocol process (rpd) tried to open the configuration schema and failed.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RPD_DYN_CFG_SDB_CLOSE_FAILED

System Log Message Failed to close session database: *error-code*
Description The routing protocol process (rpd) tried to close the session database and failed.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RPD_DYN_CFG_SDB_OPEN_FAILED

System Log Message Failed to open session database: *error-code*
Description The routing protocol process (rpd) tried to open the session database and failed.

Type Error: An error occurred
Severity info
Facility LOG_DAEMON

RPD_DYN_CFG_SES_RECOVERY_FAILED

System Log Message Recovery of session *client-session-id* failed

Description The routing protocol process (rpd) tried to recover a session and failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

RPD_DYN_CFG_SET_CONTEXT_FAILED

System Log Message Set dynamic config context for profile *profile-name* session *client-session-id* failed

Description The routing protocol process (rpd) tried to set up the dynamic configuration context and failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_ESIS_ADJDOWN

System Log Message ES-IS lost *adjacency-type* adjacency to *neighbor-nsap-netn* on *interface-name*, reason: *reason*

Description An ES-IS adjacency with the indicated neighboring router was terminated. The local router no longer exchanges routing information with, or directs traffic to, the neighboring router.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

Cause The communication path to the neighboring router was disrupted, a protocol error occurred, or the neighboring router was powered down.

RPD_ESIS_ADJUP

System Log Message ES-IS new *adjacency-type* adjacency to *neighbor-nsap-netn* on *interface-name*

Description An ES-IS adjacency was established with the indicated neighboring router. The local router can now exchange information with it.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_EXIT

System Log Message	Exit <i>executable-name</i> [<i>pid</i>] version <i>version</i> built by <i>builder</i> on <i>date</i> , caller <i>address</i>
Description	The routing protocol process (rpd) exited, either in response to a user request or because of a system error.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON
Cause	A system resource was unavailable, rpd did not understand an error, or a user terminated the process.
Action	Examine the messages that immediately follow this message in the system log for information about possible causes.

RPD_IFD_INDEXCOLLISION

System Log Message	Physical interface collision -- same name, different index (new <i>new-interface-name new-index</i> old <i>old-interface-name old-value</i>)
Description	The routing protocol process (rpd) received a message from the kernel in which the numerical index associated with the indicated interface name differed from the index-to-name mapping maintained by rpd.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	It is possible that rpd discarded some interface messages from the kernel without processing them because it received more messages than it could handle. It will recover.

RPD_IFD_NAMECOLLISION

System Log Message	Physical interface collision -- different name, same index (new <i>new-interface-name new-index</i> , old <i>old-interface-name old-value</i>)
Description	The routing protocol process (rpd) received a message from the kernel in which the name associated with the indicated numerical interface index differed from the name-to-index mapping maintained by rpd.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	It is possible that rpd discarded some interface messages from the kernel without processing them because it received more messages than it could handle. It will recover.

RPD_IFL_INDEXCOLLISION

System Log Message	Logical interface collision -- same name, different index (new <i>new-interface-name new-index</i> old <i>old-interface-name old-value</i>)
Description	The routing protocol process (rpd) received a message from the kernel in which the numerical index associated with the indicated interface name differed from the index-to-name mapping maintained by rpd.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	It is possible that rpd discarded some interface messages from the kernel without processing them because it received more messages than it could handle. It will recover.

RPD_IFL_NAMECOLLISION

System Log Message	Logical interface collision -- different name, same index (new <i>new-interface-name new-index</i> , old <i>old-interface-name old-value</i>)
Description	The routing protocol process (rpd) received a message from the kernel in which the name associated with the indicated numerical interface index differed from the name-to-index mapping maintained by rpd.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	It is possible that rpd discarded some interface messages from the kernel without processing them because it received more messages than it could handle. It will recover.

RPD_IGMP_ACCOUNTING_OFF

System Log Message	<i>interface-name time</i>
Description	Internet Group Management Protocol (IGMP) accounting for the indicated interface was disabled at the indicated time.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

RPD_IGMP_ACCOUNTING_ON

System Log Message	<i>interface-name time</i>
Description	Internet Group Management Protocol (IGMP) accounting for the indicated interface was enabled at the indicated time.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_DAEMON

RPD_IGMP_ALL_SUBSCRIBERS_DELETED

System Log Message All IGMP subscribers on interface *interface-name* deleted at *time* because the interface is down

Description All IGMP subscribers have been deleted because the interface is down.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_DAEMON

RPD_IGMP_CFG_CREATE_ENTRY_FAILED

System Log Message Could not create entry for *entry*.

Description Internet Group Management Protocol (IGMP) failed to create the indicated configuration entry. The configuration request failed.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON
Action Contact your technical support representative.

RPD_IGMP_CFG_GROUP_OUT_OF_RANGE

System Log Message The combination of group-count *count* and group-increment *ip-address* causes some of the groups out of range.

Description The configuration request failed because the indicated configuration object contained a group that is out of range.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON
Action Modify configuration statement to use a valid value.

RPD_IGMP_CFG_INVALID_VALUE

System Log Message The *object-name* configuration object *identifier* field has an invalid value of *value*

Description The configuration request failed because the indicated configuration object contained the indicated invalid value.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Modify configuration statement to use a valid value.

RPD_IGMP_CFG_SOURCE_OUT_OF_RANGE

System Log Message The combination of source-count *count* and source-increment *ip-address* causes some of the sources out of range.

Description The configuration request failed because the indicated configuration object contained a source that is out of range.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Modify configuration statement to use a valid value.

RPD_IGMP_DYN_CFG_ALREADY_BOUND

System Log Message Dynamic configuration session id *client-session-id* for interface *interface-name* is already bound to interface *old-interface-name*.

Description The indicated dynamic configuration session id is already bound to another interface. The dynamic configuration instantiation request was rejected.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Unbind session id from existing interface.

RPD_IGMP_DYN_CFG_INVALID_STMT

System Log Message Invalid dynamic configuration statement: *configuration-statement*

Description The indicated dynamic configuration statement was invalid. The dynamic configuration instantiation request was rejected.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Remove the unsupported configuration statement.

RPD_IGMP_DYN_CFG_SES_ID_ADD_FAIL

System Log Message	Failed to add dynamic configuration session id <i>client-session-id</i> to interface <i>interface-name</i> .
Description	Failed to associate the indicated dynamic configuration session id to specified interface. The dynamic configuration instantiation request was rejected.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_IGMP_DYN_CFG_SES_ID_MISMATCH

System Log Message	Dynamic configuration entry for interface <i>interface-name</i> with session id <i>client-session-id</i> found an existing entry with a different session id of <i>client-session-id-1</i> .
Description	The dynamic configuration instantiation request matched an existing dynamic configuration block that had a different session id. The dynamic configuration instantiation request was rejected.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_IGMP_JOIN

System Log Message	Listener <i>source-address</i> sent a join to <i>destination-address</i> for group <i>group-address</i> source <i>sender-address</i> on interface <i>interface-name</i> at <i>time</i>
Description	IGMP join event.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

RPD_IGMP_LEAVE

System Log Message	Listener <i>source-address</i> sent a leave to <i>destination-address</i> for group <i>group-address</i> source <i>sender-address</i> on interface <i>interface-name</i> at <i>time</i>
Description	IGMP leave event.
Type	Event: This message reports an event, not an error

Severity info
Facility LOG_DAEMON

RPD_IGMP_MEMBERSHIP_TIMEOUT

System Log Message Membership timeout for listener *source-address* for group *group-address* source *sender-address* on interface *interface-name* at time

Description IGMP group membership timeout.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_DAEMON

RPD_IGMP_ROUTER_VERSION_MISMATCH

System Log Message IGMP version mismatch on *interface-name*. Local version: *local-version* Remote version: *remote-version*

Description The IGMP version running on the local router does not match the one received in the query

Type Event: This message reports an event, not an error
Severity warning
Facility LOG_DAEMON

RPD_ISIS_ADJDOWN

System Log Message IS-IS lost *Lisis-level* adjacency to *neighbor-system-ids* on *interface-name*, reason: *reason*

Description An IS-IS adjacency with the indicated neighboring router was terminated. The local router no longer exchanges routing information with, or directs traffic to, the neighboring router.

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_DAEMON

Cause The communication path to the neighboring router was disrupted, a protocol error occurred, or the neighboring router was powered down.

RPD_ISIS_ADJUP

System Log Message IS-IS new *Lisis-level* adjacency to *neighbor-system-ids* on *interface-name*

Description An IS-IS adjacency was established with the indicated neighboring router. The local router can now exchange information with it.

Type Event: This message reports an event, not an error
Severity info

Facility LOG_DAEMON

RPD_ISIS_ADJUPNOIP

System Log Message IS-IS new *Lisis-level* adjacency to *neighbor-system-ids* on *interface-name* without an address

Description An IS-IS adjacency was established with the indicated neighboring router, which is not configured for IS-IS for IP.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

Cause The neighboring router is misconfigured: it is enabled for IS-IS but not for exchange of IP route information.

Action Configure the neighboring router for IS-IS with IP, or remove it from the IS-IS mesh.

RPD_ISIS_LDP_SYNC

System Log Message IS-IS interface *interface-name* advertised with infinite metric for *duration* seconds already due to loss of synchronization with LDP

Description The IS-IS protocol lost synchronization with the Label Distribution Protocol (LDP) on the indicated interface. As a consequence, it began advertising an infinite metric for the interface and has been doing so for the indicated number of seconds.

Type Error: An error occurred

Severity warning

Facility LOG_DAEMON

Action Determine why LDP lost synchronization with IS-IS.

RPD_ISIS_LSPCKSUM

System Log Message IS-IS *Lisis-level* LSP checksum error, interface *interface-name*, LSP id *lspl*, sequence *sequence-number*, checksum *checksum*, lifetime *duration*

Description The indicated IS-IS informational link-state PDU (LSP) failed an internal checksum validity test, implying that it was corrupted.

Type Error: An error occurred

Severity warning

Facility LOG_DAEMON

Cause The packet was corrupted in transit between the neighboring IS-IS router and this router, or memory on one of the routers was corrupted.

Action None, unless a large number of these messages appear in the system log file. The corrupted LSP is silently discarded.

RPD_ISIS_NO_ROUTERID

System Log Message IS-IS instance does not have a valid router ID

Description The IS-IS instance did not have a valid router ID.

Type Error: An error occurred

Severity alert

Facility LOG_DAEMON

Cause When a router ID is not explicitly configured for an instance, IPv4 addresses configured under the instance are considered in the selection of the router ID. In this case, the instance did not have a router ID configured and no IPv4 addresses were configured.

Action Either configure a router ID by including the 'routing-instance' statement under the instance, or configure an IPv4 address by including the 'family inet' statement under one of the interfaces of the instance. You can also configure both.

RPD_ISIS_OVERLOAD

System Log Message IS-IS database overload

Description The IS-IS link-state database is full and no additional memory can be allocated for it.

Type Error: An error occurred

Severity alert

Facility LOG_DAEMON

Cause No additional memory is available for storing IS-IS link-state information. Either system resources are exhausted or a software error occurred (such as a memory leak in the routing protocol process [rpd]). In the former case, IS-IS might be carrying too much information, or the router configuration includes too many features that use large amounts of system memory.

Action Perform one or more of the following actions: (1) Check for unusually high memory usage by the IS-IS task or rpd, (2) Unconfigure features that use large amounts of memory, (3) Add more memory to the Routing Engine, (4) Carry fewer IS-IS routes.

RPD_KRT_CCC_IFL_MODIFY

System Log Message *error-code, error-message*

Description The routing protocol process (rpd) attempted to modify the state for a logical interface that is related to circuit cross-connect (CCC), but the request failed.

Type Event: This message reports an event, not an error

Severity	info
Facility	LOG_DAEMON
Cause	It is possible that the kernel lacked the resources to fulfill the request. The rpd process will recover.

RPD_KRT_DELETED_RTT

System Log Message	<i>task-name</i> : received deleted routing table from the kernel for family <i>address-family-type</i> table ID <i>table-id</i>
Description	The routing protocol process (rpd) received a message from the kernel that referred to a routing table that no longer exists.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_KRT_IFA_GENERATION

System Log Message	ifa generation mismatch -- rpd <i>rpd-generation</i> kernel <i>kernel-generation</i>
Description	The routing protocol process (rpd) received a message from the kernel in which the interface address associated with the indicated numerical index differed from the address-to-index mapping maintained by rpd.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON
Cause	It is possible that rpd discarded some interface messages from the kernel without processing them because it received more messages than it could handle. It will recover.

RPD_KRT_IFDCHANGE

System Log Message	<i>task-name</i> CHANGE for ifd <i>interface-device-index</i> <i>address/prefix-length</i> failed, error " <i>error-message</i> "
Description	The routing protocol process (rpd) sent a request to the kernel to change the state of the indicated interface. The request failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	It is possible that the kernel lacked the resources to fulfill the request. The rpd process will recover.

RPD_KRT_IFDEST_GET

System Log Message	<i>task-name</i> IFDEST GET for ifd <i>rpd-interface-name</i> failed, error " <i>error-message</i> "
Description	The routing protocol process (rpd) requested state information about the indicated interface from the kernel. The request failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	It is possible that the kernel lacked the resources to fulfill the request. The rpd process will recover.

RPD_KRT_IFDGET

System Log Message	<i>task-name</i> GET index for ifd <i>interface-name</i> failed, error " <i>error-message</i> "
Description	The routing protocol process (rpd) requested state information about the indicated interface from the kernel. The request failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	It is possible that the kernel lacked the resources to fulfill the request. The rpd process will recover.

RPD_KRT_IFD_CELL_RELAY_INV_MODE

System Log Message	Invalid mode (<i>mode</i>) specified for interface device <i>interface-name</i> ; defaulting to port mode
Description	The routing protocol process (rpd) received a message from the kernel that specified the cell-relay encapsulation for the indicated physical interface, but the specified cell-relay mode (port, or trunk user-to-network interface [UNI], or trunk network-to-network interface [NNI]) was invalid.
Type	Error: An error occurred
Severity	notice
Facility	LOG_DAEMON

RPD_KRT_IFD_CELL_RELAY_NO_MODE

System Log Message	No mode specified for interface device <i>interface-name</i> ; defaulting to port mode
Description	The routing protocol process (rpd) received a message from the kernel that specified the cell-relay encapsulation for the indicated physical interface, but not the cell-relay mode.

Type	Error: An error occurred
Severity	notice
Facility	LOG_DAEMON

RPD_KRT_IFD_GENERATION

System Log Message *ifd interface-device-index generation mismatch -- rpd rpd-generation kernel kernel-generation*

Description The routing protocol process (rpd) received a message from the kernel in which the physical interface associated with the indicated numerical index differed from the interface-to-index mapping maintained by rpd.

Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

Cause It is possible that rpd discarded some interface messages from the kernel without processing them because it received more messages than it could handle. It will recover.

RPD_KRT_IFL_CELL_RELAY_INV_MODE

System Log Message Invalid mode (*mode*) specified for logical interface *interface-name*; defaulting to port mode

Description The routing protocol process (rpd) received a message from the kernel that specified the cell-relay encapsulation for the indicated logical interface, but the specified cell-relay mode (port, virtual-circuit, or virtual-path) was invalid.

Type	Error: An error occurred
Severity	notice
Facility	LOG_DAEMON

RPD_KRT_IFL_CELL_RELAY_NO_MODE

System Log Message No mode specified for logical interface *interface-name*; defaulting to port mode

Description The routing protocol process (rpd) received a message from the kernel that specified the cell-relay encapsulation for the indicated logical interface but not the cell-relay mode.

Type	Error: An error occurred
Severity	notice
Facility	LOG_DAEMON

RPD_KRT_IFL_GENERATION

System Log Message *ifl logical-interface-index generation mismatch -- rpd rpd-interface-name rpd-generation kernel kernel-interface-name.kernel-interface-unit kernel-generation*

Description	The routing protocol process (rpd) received a message from the kernel in which the logical interface associated with the indicated numerical index differed from the interface-to-index mapping maintained by rpd.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON
Cause	It is possible that rpd discarded some interface messages from the kernel without processing them because it received more messages than it could handle. It will recover.

RPD_KRT_KERNEL_BAD_ROUTE

System Log Message	<i>task-name: lost interface-hierarchy logical-interface-index for route route-prefix</i>
Description	As it restarted, the routing protocol process (rpd) could not process a route obtained from the kernel because the route contained references to objects that are no longer valid.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	rpd did not recognize some elements in the route message, such as the logical interface index or an address family.
Action	rpd can probably solve the problem, but check the entry for the indicated route prefix in the forwarding table. If the prefix's route and forwarding table entry are inconsistent, contact a technical support representative for instructions.

RPD_KRT_NEXTHOP_OVERFLOW

System Log Message	<i>type route-prefix: number of next hops (count) exceeded the maximum allowed (maximum-value) -- truncating</i>
Description	The number of next hops for the indicated route exceeded the indicated limit for a single route add operation.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An indexed next hop can use multiple forwarding next hops per forwarding class. It is possible to have more next hops per route than can be carried in a single message. This requires that next hops be reused across forwarding classes, which is not recommended.
Action	Eliminate common next hops across forwarding classes, thereby reducing the total number of next hops that must be specified.

RPD_KRT_NOIFD

System Log Message	No device <i>interface-device-index</i> for interface <i>logical-interface-index</i> (<i>interface-name</i>)
Description	The routing protocol process (rpd) received a message from the kernel that associated the indicated physical interface device and logical interface. The rpd process has no record of the device.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	It is possible that rpd discarded some interface messages from the kernel without processing them because it received more messages than it could handle. It will recover.

RPD_KRT_VERSION

System Log Message	Routing socket version mismatch (kernel <i>kernel-version</i> != rpd <i>rpd-version</i>) -- kernel upgrade required
Description	The routing protocol process (rpd) discovered that the kernel does not support the version of routing sockets it requires.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	The kernel version is older than the rpd version.
Action	Upgrade the kernel package.

RPD_KRT_VERSIONNONE

System Log Message	Routing socket message type <i>message-type</i> 's version is not supported by kernel, expected <i>rpd-version</i> -- kernel upgrade required
Description	The routing protocol process (rpd) discovered that the kernel does not support the routing socket message types that it requires.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	The kernel version is older than the rpd version.
Action	Upgrade the kernel package.

RPD_KRT_VERSIONOLD

System Log Message	Routing socket message type <i>message-type</i> 's version is older than expected (<i>kernel-version</i> < <i>rpd-version</i>) -- consider upgrading the kernel
Description	The routing protocol process (rpd) discovered that the kernel uses an older version of routing socket message types than it does.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	The kernel version is older than the rpd version.
Action	Upgrade the kernel package.

RPD_KRT_VPLS_IFL_MODIFY

System Log Message	Unable to modify VPLS-related state: <i>error-code</i> (errno <i>error-message</i>)
Description	The routing protocol process (rpd) attempted to modify the state for a logical interface that is related to virtual private LAN service (VPLS), but the request failed.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON
Cause	It is possible that the kernel lacked the resources to fulfill the request. The rpd process will recover.

RPD_L2VPN_LABEL_ALLOC_FAILED

System Log Message	Unable to allocate <i>label-type</i> labels for site <i>name</i> with ID <i>identifier</i> in instance <i>vpn-name</i>
Description	The routing protocol process (rpd) could not allocate labels of the indicated type for the indicated site (name and ID) in the indicated virtual private network (VPN) virtual circuit (VC), because the resulting number of labels would have exceeded the limit.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_L2VPN_REMOTE_SITE_COLLISION

System Log Message	Two remote PEs (RDs <i>route-discriminator</i> and <i>route-discriminator2</i>) have the same site ID (<i>identifier</i>) in VPN <i>vpn-name</i>
Description	The routing protocol process (rpd) for the indicated virtual private network (VPN) received an advertisement from a remote provider edge (PE) router with the first indicated route

discriminator, but the associated site ID also belongs to a remote site with the second route discriminator.

Type Event: This message reports an event, not an error
Severity warning
Facility LOG_DAEMON

RPD_L2VPN_SITE_COLLISION

System Log Message Same site ID *identifier* configured on remote PE (RD *route-discriminator*) and local PE in VPN *vpn-name* (non-multihomed site *name*)

Description The routing protocol process (rpd) for the indicated virtual private network (VPN) received an advertisement from a remote provider edge (PE) router, but the associated site ID belongs to a local site.

Type Event: This message reports an event, not an error
Severity error
Facility LOG_DAEMON

RPD_LAYER2_VC_BFD_DOWN

System Log Message BFD session for Layer 2 VC *vc-name* went down

Description The routing protocol process (rpd) determined that the Bidirectional Forwarding Detection (BFD) protocol session for the indicated Layer 2 virtual private network (VPN) virtual circuit (VC) terminated.

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_DAEMON

RPD_LAYER2_VC_BFD_UP

System Log Message BFD session for Layer 2 VC *vc-name* came up

Description The routing protocol process (rpd) determined that the Bidirectional Forwarding Detection (BFD) protocol session for the the indicated Layer 2 virtual private network (VPN) virtual circuit (VC) came up.

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_DAEMON

RPD_LAYER2_VC_DOWN

System Log Message State of Layer 2 VC *vc-name* changed from UP to *state*

Description The state of the indicated Layer 2 virtual private network (VPN) virtual circuit (VC) changed as indicated (to either down or deleted).

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

RPD_LAYER2_VC_PING_DOWN

System Log Message Ping failure for Layer 2 VC *vc-name*

Description The routing protocol process (rpd) determined that the Ping for the indicated Layer 2 virtual private network (VPN) virtual circuit (VC) failed.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

RPD_LAYER2_VC_UP

System Log Message State of Layer 2 VC *vc-name* changed to UP

Description The state of the indicated Layer 2 virtual private network (VPN) virtual circuit (VC) changed to up.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_LDP_BFD_DOWN

System Log Message LDP BFD session for FEC *fec-address* went down

Description The routing protocol process (rpd) determined that the Label Distribution Protocol (LDP) Bidirectional Forwarding Detection (BFD) protocol session for the indicated forwarding equivalence class (FEC) terminated.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

RPD_LDP_BFD_DOWN_TRACEROUTE_FAIL

System Log Message LDP BFD sessions for FEC *fec-address* going down due to traceroute failure

Description The routing protocol process (rpd) determined that the Label Distribution Protocol (LDP) Bidirectional Forwarding Detection (BFD) protocol session for the indicated forwarding equivalence class (FEC) was terminated due to traceroute failure.

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_DAEMON

RPD_LDP_BFD_UP

System Log Message LDP BFD session for FEC *fec-address* came up

Description The routing protocol process (rpd) determined that the Label Distribution Protocol (LDP) Bidirectional Forwarding Detection (BFD) protocol session for the indicated forwarding equivalence class (FEC) came up.

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_DAEMON

RPD_LDP_GR_CFG_IGNORED

System Log Message LDP needs *duration* seconds for restart. Instance restart-duration is *time-period* seconds only. Graceful restart will not be attempted

Description Instance restart-duration is less than that needed by LDP to finish graceful-restart. LDP GR will not be attempted.

Type Event: This message reports an event, not an error
Severity warning
Facility ANY
Action Modify the instance restart-duration and ldp GR configurations.

RPD_LDP_INTF_BLOCKED

System Log Message Duplicate session ID detected from *neighbor-address*i, interface *interface-name*, blocking interface

Description Label Distribution Protocol (LDP) operations were blocked on the indicated interface because the same session ID was detected across multiple interfaces but per-interface transport addresses are in use.

Type Event: This message reports an event, not an error
Severity warning
Facility LOG_DAEMON

RPD_LDP_INTF_UNBLOCKED

System Log Message LDP interface *interface-name* is now unblocked

Description The indicated interface returned to the normal Label Distribution Protocol (LDP) operational state. It was previously blocked because the routing protocol process (rpd) noticed that a duplicate session ID was being used.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

RPD_LDP_NBRDOWN

System Log Message LDP neighbor *neighbor-addressi (interface-name)* is down

Description A Label Distribution Protocol (LDP) adjacency was terminated because the indicated neighbor stopped communicating. If the adjacency was the only one with this neighbor, the routing protocol process (rpd) terminated the associated LDP session.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

RPD_LDP_NBRUP

System Log Message LDP neighbor *neighbor-addressi (interface-name)* is up

Description A Label Distribution Protocol (LDP) adjacency with the indicated neighbor became active. The routing protocol process (rpd) established an LDP session with the neighbor if one did not already exist.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_LDP_PING_DOWN

System Log Message LDP LSP ping failure for FEC *fec-address*

Description The routing protocol process (rpd) determined that LSP ping returned error for the indicated forwarding equivalence class (FEC) of Label Distribution Protocol (LDP).

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

RPD_LDP_SESSIONDOWN

System Log Message LDP session *neighbor-addressi* is down, reason: *reason*

Description The routing protocol process (rpd) terminated a Label Distribution Protocol (LDP) session with the indicated neighbor and deleted all labels exchanged during the session.

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_DAEMON

RPD_LDP_SESSIONUP

System Log Message LDP session *neighbor-address* is up
Description The routing protocol process (rpd) established a Label Distribution Protocol (LDP) session with the indicated neighbor. The routers began exchanging labels.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_DAEMON

RPD_LMP_ALLOC_ACK

System Log Message Unknown context in ALLOC_ACK message
Description The routing protocol process (rpd) received a label allocation acknowledgment that contained invalid context.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RPD_LMP_ALLOC_REQUEST_TIMEOUT

System Log Message Allocation request timeout for context *0xaddress*, client request ID *0xrequest-id*
Description The label allocation request with the indicated client request ID and for the indicated context timed out before completion.

Type Event: This message reports an event, not an error
Severity error
Facility LOG_DAEMON

RPD_LMP_CONTROL_CHANNEL

System Log Message *operation* operation failed: control channel *logical-interface-index* unknown
Description The routing protocol process (rpd) received a message that specified the indicated type of operation on the indicated control channel. The channel does not exist.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RPD_LMP_NO_CALLBACK

System Log Message	No function callback for label removed event
Description	The routing protocol process (rpd) could not notify a client that a label was removed, because there was no function callback for the removal event.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_LMP_NO_MEMORY

System Log Message	<i>function-name</i> : malloc() failed (<i>error-message</i> , <i>errno error-code</i>)
Description	The routing protocol process (rpd) could not allocate memory.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.

RPD_LMP_NO_PEER

System Log Message	Peer <i>peer-id</i> not found for TE link <i>link-name</i> (index <i>link-id</i>)
Description	The routing protocol process (rpd) could not locate the indicated peer while processing a TE LINK message for the traffic-engineering link with the indicated name and index.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_LMP_PEER

System Log Message	<i>operation</i> operation failed: peer <i>peer-name</i> (index <i>peer-id</i>) <i>reason</i>
Description	The routing protocol process (rpd) could not perform the indicated operation for the peer with the indicated name and index, for the indicated reason.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_LMP_PEER_IFL

System Log Message	<i>operation</i> operation failed because <i>reason</i> for peer <i>peer-name</i> (index <i>peer-id</i>): <i>error-message</i> (<i>errno error-code</i>)
---------------------------	---

Description The routing protocol process (rpd) could not perform the indicated operation for the peer with the indicated name and index, for the indicated reason.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_LMP_PEER_INDEX

System Log Message No more peer indexes

Description No more peer indexes were available for allocation.

Type Event: This message reports an event, not an error

Severity error

Facility LOG_DAEMON

RPD_LMP_RESOURCE

System Log Message *operation* operation failed: resource *resource* (type *type*, index *index*) *reason*

Description The routing protocol process (rpd) could not perform the indicated operation for the resource with the indicated name, type, and index, for the indicated reason.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_LMP_RESOURCE_NO_LINK

System Log Message TE link *link-id* not found for resource *resource* (type *type*, index *index*)

Description The routing protocol process (rpd) could not locate the indicated traffic-engineering link for the resource with the indicated name, type, and index.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_LMP_SEND

System Log Message *function-name*: handling write exception (*error-message*, errno *error-code*)

Description The routing protocol process (rpd) could not send a message to the Label Management Protocol (LMP) process (lmpd).

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_LMP_SEND_ALLOCATION_MESSAGE

System Log Message Unable to send allocation message: *error-message (error-code)*

Description The routing protocol process (rpd) could not send an allocation message.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_LMP_SYSFAIL

System Log Message Unable to start *type* timer

Description The routing protocol process (rpd) discovered that the Label Management Protocol (LMP) process (lmpd) was not running. The rpd process attempted to start the indicated type of timer for restarting the lmpd process or reestablishing a connection to it, but the attempt failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause An internal software failure occurred.

Action Examine the messages that immediately follow this message in the system log for information about possible reasons that lmpd failed.

RPD_LMP_TE_LINK

System Log Message *operation* operation failed: TE link *link-name* (index *index*) *reason*

Description The routing protocol process (rpd) could not perform the indicated operation for the traffic-engineering link with the indicated name and index, for the indicated reason.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_LMP_TE_LINK_INDEX

System Log Message No more TE-link indexes

Description No more traffic-engineering link indexes were available for allocation.

Type Event: This message reports an event, not an error

Severity error

Facility LOG_DAEMON

RPD_LMP_UNEXPECTED_OPCODE

System Log Message *message-type* message had unexpected operation code *operation-code*

Description The routing protocol process (rpd) received the indicated type of message, which had the indicated invalid operation code.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_LOCK_FLOCKED

System Log Message Unable to obtain a lock on *filename*, is another copy of rpd running?

Description The routing protocol process (rpd) could not obtain the mutual exclusion lock that prevents more than one instance of rpd from running simultaneously. The system terminated the indicated process.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause Another rpd process is running.

Action Use the 'show system process' command to verify that another rpd is running.

RPD_LOCK_LOCKED

System Log Message Unable to obtain a lock on *filename*, *program-name*[*pid*] is still running

Description The routing protocol process (rpd) could not obtain the mutual exclusion lock that prevents more than one instance of rpd from running simultaneously. The system terminated this instance of rpd.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause Another rpd is running.

Action Use the 'show system process' command to verify that another rpd is running.

RPD_MC_CFG_CREATE_ENTRY_FAILED

System Log Message Could not create entry for *entry*.

Description The multicast configuration request failed because the routing protocol process (rpd) failed to create the specified configuration entry.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

RPD_MC_CFG_FWDCACHE_CONFLICT

System Log Message Multicast forwarding-cache: reuse value must be less than or equal to suppress value

Description Multicast forwarding-cache reuse value is configured greater than the suppress value. Reuse value must be less than or equal to the suppress value.

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

RPD_MC_CFG_PREFIX_LEN_SHORT

System Log Message Multicast *argument*: prefix length *prefix-length* is too short for prefix *route-prefix*, ignoring excess host bits

Description The prefix length for the indicated prefix is too short and it has a non-zero host portion. Excess host bits will be ignored.

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

RPD_MC_COSD_WRITE_ERROR

System Log Message Unable to write to pipe to COS process: (*error-message*)

Description The routing protocol process (rpd) could not write a message on the write pipe to the Class Of Service process (cosd).

Type Error: An error occurred

Severity info

Facility LOG_DAEMON

Action Contact your technical support representative.

RPD_MC_DESIGNATED_PE_CHANGE

System Log Message	Designated forwarder changed to <i>ip-address</i> for backup-pe-group <i>group-name</i> in <i>routing-instance</i> instance
Description	The routing protocol daemon (rpd) assigned the indicated Provider Edge (PE) as the new designated forwarder of the indicated routing instance for the indicated backup-pe-group.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_MC_DYN_CFG_ALREADY_BOUND

System Log Message	Dynamic configuration session id <i>client-session-id</i> for interface <i>interface-name</i> is already bound to interface <i>old-interface-name</i> .
Description	The dynamic configuration instantiation request was rejected because the specified dynamic configuration session ID was already bound to another interface.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Unbind the session ID from the existing interface.

RPD_MC_DYN_CFG_SES_ID_ADD_FAIL

System Log Message	Failed to add dynamic configuration session id <i>client-session-id</i> to interface <i>interface-name</i> .
Description	The dynamic configuration instantiation request was rejected because the routing protocol process failed to associate the specified dynamic configuration session ID with the specified interface.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_MC_DYN_CFG_SES_ID_MISMATCH

System Log Message	Dynamic configuration entry for interface <i>interface-name</i> with session id <i>client-session-id</i> found an existing entry with a different session id of <i>client-session-id-1</i> .
Description	The dynamic configuration instantiation request was rejected because the request matched an existing dynamic configuration block that had a different session ID.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_MC_LOCAL_DESIGNATED_PE

System Log Message	Local PE is now the designated forwarder for backup-pe-group <i>group-name</i> in <i>routing-instance</i> instance
Description	The routing protocol daemon (rpd) selected the local Provider Edge (PE) as the designated forwarder of the indicated routing instance for the indicated backup-pe-group.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_MC_OIF_REJECT

System Log Message	Interface <i>interface-name</i> is rejected due to lack of bw
Description	When multicast bandwidth admission control is applied, an interface may not be put into the downstream interface list for a forwarding cache if the interface does not have enough bandwidth for the flow, even when a multicast protocol determines that there are local/downstream receivers.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

RPD_MC_OIF_RE_ADMIT

System Log Message	Interface <i>interface-name</i> is re-admitted with newly available bw
Description	The indicated downstream interface that was previously rejected was readmitted for the flow because there was newly available bandwidth on the interface.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

RPD_MGMT_TIMEOUT

System Log Message	Connection to management peer <i>process-name</i> timed out waiting for input
Description	The connection between the routing protocol process (rpd) and the indicated management process (mgd) timed out before input arrived from the mgd process.

Type Error: An error occurred
Severity warning
Facility LOG_DAEMON

RPD_MIRROR_ERROR

System Log Message Unable to establish mirror connection between Routing Engines: *error-message*

Description The routing protocol process (rpd) could not establish the mirror connection (which supports nonstop routing) between the master and backup Routing Engines.

Type Error: An error occurred
Severity warning
Facility LOG_DAEMON

Cause The master and backup Routing Engines are running incompatible versions of the Junos OS .

Action Update the Junos OS to compatible versions on the master and backup Routing Engines.

RPD_MIRROR_VERSION_MISMATCH

System Log Message Versions of mirror software on Routing Engines are incompatible: *error-message*

Description While trying to establish the mirror connection between the master and backup Routing Engines (which supports nonstop routing), the routing protocol process (rpd) determined that the versions of Junos OS on the Routing Engines were incompatible.

Type Error: An error occurred
Severity warning
Facility LOG_DAEMON

Action Update the Junos OS to compatible versions on the master and backup Routing Engines.

RPD_MLD_ACCOUNTING_OFF

System Log Message *interface-name time*

Description The Multicast Listener Discovery (MLD) accounting for the indicated interface was disabled at the indicated time.

Type Event: This message reports an event, not an error
Severity info
Facility LOG_DAEMON

RPD_MLD_ACCOUNTING_ON

System Log Message *interface-name time*

Description The Multicast Listener Discovery (MLD) accounting for the indicated interface was enabled at the indicated time.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_MLD_ALL_SUBSCRIBERS_DELETED

System Log Message All MLD subscribers on interface *interface-name* deleted at *time* because the interface is down

Description All MLD subscribers have been deleted because the interface is down.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_MLD_CFG_CREATE_ENTRY_FAILED

System Log Message Could not create entry for *entry*.

Description MLD failed to create the indicated configuration entry. The configuration request failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

RPD_MLD_CFG_GROUP_OUT_OF_RANGE

System Log Message The combination of group-count *count* and group-increment *ip-address* causes some of the groups out of range.

Description The configuration request failed because the indicated configuration object contained a group that is out of range.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Modify configuration statement to use a valid value.

RPD_MLD_CFG_INVALID_VALUE

System Log Message The *object-name* configuration object *identifier* field has an invalid value of *value*

Description	The configuration request failed because the indicated configuration object contained the indicated invalid value.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Modify configuration statement to use a valid value.

RPD_MLD_CFG_SOURCE_OUT_OF_RANGE

System Log Message	The combination of source-count <i>count</i> and source-increment <i>ip-address</i> causes some of the sources out of range.
Description	The configuration request failed because the indicated configuration object contained a source that is out of range.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Modify configuration statement to use a valid value.

RPD_MLD_DYN_CFG_ALREADY_BOUND

System Log Message	Dynamic configuration session id <i>client-session-id</i> for interface <i>interface-name</i> is already bound to interface <i>old-interface-name</i> .
Description	The indicated dynamic configuration session id is already bound to another interface. The dynamic configuration instantiation request was rejected.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Unbind session id from existing interface.

RPD_MLD_DYN_CFG_INVALID_STMT

System Log Message	Invalid dynamic configuration statement: <i>configuration-statement</i>
Description	The indicated dynamic configuration statement was invalid. The dynamic configuration instantiation request was rejected.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

Action Remove the unsupported configuration statement.

RPD_MLD_DYN_CFG_SES_ID_ADD_FAIL

System Log Message Failed to add dynamic configuration session id *client-session-id* to interface *interface-name*.

Description Failed to associate the indicated dynamic configuration session id to specified interface. The dynamic configuration instantiation request was rejected.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_MLD_DYN_CFG_SES_ID_MISMATCH

System Log Message Dynamic configuration entry for interface *interface-name* with session id *client-session-id* found an existing entry with a different session id of *client-session-id-1*.

Description The dynamic configuration instantiation request matched an existing dynamic configuration block that had a different session id. The dynamic configuration instantiation request was rejected.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Contact your technical support representative.

RPD_MLD_JOIN

System Log Message Listener *source-address* sent a join to *destination-address* for group *group-address* source *sender-address* on interface *interface-name* at *time*

Description MLD join event.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_MLD_LEAVE

System Log Message Listener *source-address* sent a leave to *destination-address* for group *group-address* source *sender-address* on interface *interface-name* at *time*

Description MLD leave event.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_MLD_MEMBERSHIP_TIMEOUT

System Log Message Membership timeout for listener *source-address* for group *group-address* source *sender-address* on interface *interface-name* at time

Description MLD group membership timeout.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_MLD_ROUTER_VERSION_MISMATCH

System Log Message MLD version mismatch on *interface-name*. Local version: *local-version* Remote version: *remote-version*

Description The MLD version running on the local router does not match the one received in the query

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

RPD_MPLS_INTERFACE_ROUTE_ERROR

System Log Message Unable to add route in table *table-name* for label *mpls-label* pointing to *interface-name*

Description There was a failure in adding a Multiprotocol Label Switching (MPLS) route pointing to an interface

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

RPD_MPLS_INTF_MAX_LABELS_ERROR

System Log Message Maximum labels exceeded - failed to stack additional label to nexthop on interface *interface-name*

Description There was a failure in stacking additional label to a nexthop which already has maximum number of labels allowed for the interface

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_MPLS_LSP_AUTOBW_NOTICE

System Log Message mpls LSP *lsp-name* Autobw already in progress, ignoring new trigger

Description The auto-bandwidth adjustment for the indicated Multiprotocol Label Switching (MPLS) label-switched path (LSP) already in progress, ignoring new trigger.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

RPD_MPLS_LSP_BANDWIDTH_CHANGE

System Log Message MPLS LSP *lsp-name* bandwidth changed, lsp bandwidth *bandwidth* bps

Description The bandwidth associated with the indicated Multiprotocol Label Switching (MPLS) label-switched path (LSP) changed.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

RPD_MPLS_LSP_CHANGE

System Log Message MPLS LSP *lsp-name* change on *path-type(pathname)* Route *lsp-rrr* lsp bandwidth *bandwidth* bps

Description The indicated Multiprotocol Label Switching (MPLS) label-switched path (LSP) was rerouted and its Record Route Object (RRO) changed.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

RPD_MPLS_LSP_DOWN

System Log Message MPLS LSP *lsp-name* down on *path-type(pathname)*

Description The indicated Multiprotocol Label Switching (MPLS) label-switched path (LSP) went down and could not be used to send traffic.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

RPD_MPLS_LSP_SWITCH

System Log Message MPLS LSP *lsp-name* switch from *old-path-type(old-pathname)* to *new-path-type(new-pathname)*, Route *lsp-rrr*: *reason* lsp bandwidth *bandwidth* bps

Description The indicated Multiprotocol Label Switching (MPLS) label-switched path (LSP) switched from primary path to secondary path or vice versa.

Type Event: This message reports an event, not an error
Severity warning
Facility LOG_DAEMON

RPD_MPLS_LSP_UP

System Log Message MPLS LSP *lsp-name* up on *path-type(pathname)* Route *lsp-rro* lsp bandwidth *bandwidth* bps

Description The indicated Multiprotocol Label Switching (MPLS) label-switched path (LSP) came up and could be used to send traffic.

Type Event: This message reports an event, not an error
Severity warning
Facility LOG_DAEMON

RPD_MPLS_OAM_LSP_PING_REPLY_ERR

System Log Message Received ping reply with an error: *error-code*.

Description Received a LSP ping reply with an error code, for the ping request sent. If any failure action is configured, the failure action will get executed

Type Event: This message reports an event, not an error
Severity error
Facility LOG_DAEMON

RPD_MPLS_OAM_PING_REPLY_TIMEOUT

System Log Message LSP ping reply timed out

Description LSP ping timed out waiting for a reply. If any failure action is configured, the failure action will get executed

Type Event: This message reports an event, not an error
Severity error
Facility LOG_DAEMON

RPD_MPLS_OAM_READ_ERROR

System Log Message Unable to read from pipe to MPLS OAM process: *reason (error-message)*

Description The routing protocol process (rpd) could not read a message available on the read pipe from the MPLS Operation, Administration, and Maintenance process (mplsoamd).

Type Error: An error occurred
Severity info
Facility LOG_DAEMON

Action Contact your technical support representative.

RPD_MPLS_OAM_WRITE_ERROR

System Log Message Unable to write to pipe to MPLS OAM process: (*error-message*)

Description The routing protocol process (rpd) could not write a message on the write pipe to the MPLS Operation, Administration, and Maintenance process (mplsoamd).

Type Error: An error occurred

Severity info

Facility LOG_DAEMON

Action Contact your technical support representative.

RPD_MPLS_PATH_BANDWIDTH_CHANGE

System Log Message MPLS path *pathname* (lsp *lsp-name*) bandwidth changed, path bandwidth *bandwidth* bps

Description The bandwidth associated with the indicated Multiprotocol Label Switching (MPLS) path changed.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

RPD_MPLS_PATH_BFD_DOWN

System Log Message BFD session for MPLS path *pathname* went down on LSP *lsp-name*

Description The routing protocol process (rpd) determined that the Bidirectional Forwarding Detection (BFD) protocol session for the indicated Multiprotocol Label Switching (MPLS) path terminated on the indicated label-switched path (LSP).

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

RPD_MPLS_PATH_BFD_UP

System Log Message BFD session for MPLS path *pathname* came up on LSP *lsp-name*

Description The routing protocol process (rpd) determined that the Bidirectional Forwarding Detection (BFD) protocol session for the the indicated Multiprotocol Label Switching (MPLS) path came up on the indicated label-switched path (LSP).

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

RPD_MPLS_PATH_BW_NOT_AVAILABLE

System Log Message Unable to satisfy bandwidth configured for MPLS path *pathname* on LSP *lsp-name*

Description The bandwidth setting for the indicated Multiprotocol Label Switching (MPLS) path and label-switched path (LSP) was changed recently, but attempts to apply the new setting failed. The LSP continued to use the previous amount of bandwidth.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

Action Determine the reason that the bandwidth could not change and make the necessary changes to the software configuration, hardware configuration, or both.

RPD_MPLS_PATH_DOWN

System Log Message MPLS path *pathname* down on LSP *lsp-name*

Description The indicated Multiprotocol Label Switching (MPLS) path went down on the indicated label-switched path (LSP).

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

RPD_MPLS_PATH_PING_DOWN

System Log Message LSP ping failure occurred for MPLS path *pathname* on LSP *lsp-name*

Description The routing protocol process (rpd) determined that the LSP ping returned error for the indicated Multiprotocol Label Switching (MPLS) path terminated on the indicated label-switched path (LSP).

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

RPD_MPLS_PATH_UP

System Log Message MPLS path *pathname* up on LSP *lsp-name* path bandwidth *bandwidth* bps

Description The indicated Multiprotocol Label Switching (MPLS) path came up on the indicated label-switched path (LSP).

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

RPD_MPLS_TABLE_ROUTE_ERROR

System Log Message Unable to add route in table *table-name* for label *mpls-label* pointing to *next-table-name*

Description There was a failure in adding a Multiprotocol Label Switching (MPLS) route pointing to another MPLS routing table

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

RPD_MSDP_CFG_SA_LIMITS_CONFLICT

System Log Message Threshold value *threshold* must be less than or equal to maximum value *maximum-value*. Setting threshold to maximum

Description The MSDP active-source-limit threshold is either undefined or exceeds the maximum value. Threshold will be set to maximum.

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

Action Consider modifying the MSDP active-source-limit configurations.

RPD_MSDP_CFG_SRC_INVALID

System Log Message *argument* is an invalid source address

Description The indicated MSDP source is configured with an invalid address

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

Action Modify the configuration statement to use a valid value.

RPD_MSDP_PEER_DOWN

System Log Message MSDP peer *peer-address* peer-group *peer-group* out of Established state

Description The indicated MSDP peer left the Established state. The routing protocol process (rpd) deleted all active sources learned from the peer and will no longer send 'Source Active' messages to it.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

RPD_MSDP_PEER_UP

System Log Message MSDP peer *peer-address* peer-group *peer-group* into Established state

Description The indicated MSDP peer entered the Established state.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_MSDP_SRC_ACTIVE_OVER_LIMIT

System Log Message Number of MSDP source-active messages about *originator* exceeded configured limit *message*

Description The number of MSDP source-active messages received from the indicated instance, peer, or source exceeded the configured limit. All source-active messages are discarded until the limit is no longer exceeded. During periods when the event reported by this message occurs frequently, the routing protocol process (rpd) does not log every occurrence. In this case, the repetitions field in the message indicates how many times the event occurred since the rpd process previously logged this message.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

RPD_MSDP_SRC_ACTIVE_OVER_THRESH

System Log Message Number of MSDP source-active messages about *originator* exceeded configured threshold *message*

Description The number of MSDP source-active messages received from the indicated instance, peer, or source exceeded the configured threshold. Until the threshold is no longer exceeded, a random early discard (RED) profile is applied to incoming messages so that only some of them are accepted. During periods when the event reported by this message occurs frequently, the routing protocol process (rpd) does not log every occurrence. In this case, the repetitions field in the message indicates how many times the event occurred since the rpd process previously logged this message.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

RPD_MSDP_SRC_ACTIVE_UNDER_LIMIT

System Log Message Number of MSDP source-active messages about *originator* no longer exceeded configured limit *message*

Description The number of MSDP source-active messages received from the indicated instance, peer, or source no longer exceeded the configured limit. Active-source messages are no longer discarded automatically. During periods when the event reported by this message occurs frequently, the routing protocol process (rpd) does not log every occurrence. In this case, the repetitions field in the message indicates how many times the event occurred since the rpd process previously logged this message.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

RPD_MSDP_SRC_ACTIVE_UNDER_THRESH

System Log Message Number of MSDP source-active messages about *originator* no longer exceeded configured threshold *message*

Description The number of MSDP source-active messages received from the indicated instance, peer, or source no longer exceeded the configured threshold. A random early discard (RED) profile is no longer applied to incoming messages. During periods when the event reported by this message occurs frequently, the routing protocol process (rpd) does not log every occurrence. In this case, the repetitions field in the message indicates how many times the event occurred since the rpd process previously logged this message.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_DAEMON

RPD_MVPN_CFG_PREFIX_LEN_SHORT

System Log Message MVPN *argument*: prefix length *prefix-length* is too short for prefix *route-prefix*, ignoring excess host bits

Description The prefix length for MVPN source or group object is too short and the indicated prefix has a non-zero host portion. Excess host bits will be ignored.

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

RPD_OSPF_CFGNBR_P2P

System Log Message Ignored configured neighbors on point-to-point realm *realm-name* interface *interface-name* area *area-id*

Description For point-to-point interfaces, OSPF neighbors are learned by using hello messages, so the implicit configuration of neighbors was ignored for the indicated point-to-point interface.

Type Error: An error occurred

Severity	warning
Facility	LOG_DAEMON
Action	Remove the neighbor configuration for the indicated interface.

RPD_OSPF_IF_COST_CHANGE

System Log Message	Interface <i>interface-name</i> (<i>interface-address</i>) area <i>area-idi</i> : cost changed <i>cost</i> -> <i>metric</i>
Description	OSPF interface cost changed due to change in interface bandwidth
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

RPD_OSPF_LDP_SYNC

System Log Message	OSPF realm <i>realm-name</i> interface <i>interface-name</i> area <i>area-idi</i> advertised with infinite metric for <i>duration</i> seconds already due to loss of synchronization with LDP
Description	The OSPF protocol lost synchronization with the Label Distribution Protocol (LDP) on the indicated interface. As a consequence, it began advertising an infinite metric for the interface and has been doing so for the indicated number of seconds.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Action	Determine why LDP lost synchronization with OSPF.

RPD_OSPF_LSA_MAXIMUM_EXCEEDED

System Log Message	OSPF realm <i>realm-name</i> number of non-local LSAs exceeded maximum limit
Description	The number of non self-generated LSAs exceeded maximum limit specified for database protection in the indicated realm. Consequently, all non self-generated LSA were deleted and all neighbors were killed. The router will not send any OSPF hellos and will ignore any incoming OSPF packets till ignore-time has elapsed.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_OSPF_LSA_WARNING_EXCEEDED

System Log Message	OSPF realm <i>realm-name</i> number of non-local LSAs exceeded warning limit
Description	The number of non self-generated LSAs exceeded warning limit specified for database protection in the indicated realm.

Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_OSPF_NBRDOWN

System Log Message	OSPF neighbor <i>neighbor-address</i> (realm <i>realm-name</i> interface <i>interface-name</i> area <i>area-idi</i>) state changed from <i>old-state</i> to <i>new-state</i> due to <i>event-name</i> (event reason: <i>reason</i>)
Description	An OSPF adjacency with the indicated neighboring router was terminated. The local router no longer exchanges routing information with, or directs traffic to, the neighboring router.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_OSPF_NBRUP

System Log Message	OSPF neighbor <i>neighbor-address</i> (realm <i>realm-name</i> interface <i>interface-name</i> area <i>area-idi</i>) state changed from <i>old-state</i> to <i>new-state</i> due to <i>event-name</i> (event reason: <i>reason</i>)
Description	An OSPF adjacency was established with the indicated neighboring router. The local router can now exchange information with it.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

RPD_OSPF_OVERLOAD

System Log Message	OSPF instance <i>instance</i> topology <i>topology</i> is going into overload state: number of export prefixes (<i>count</i>) exceeded maximum allowed (<i>maximum-value</i>)
Description	The indicated topology in the indicated OSPF instance became overloaded and will remain in that state until an administrator intervenes.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Cause	The number of export prefixes exceeded the configured limit.
Action	Unconfigure or modify export policies that inject a large number of routes.

RPD_OSPF_TOPO_IF_COST_CHANGE

System Log Message	Interface <i>interface-name</i> (<i>interface-address</i>) area <i>area-idi</i> topology <i>topology</i> : cost changed <i>cost</i> -> <i>metric</i>
---------------------------	--

Description OSPF topology interface cost changed due to change in interface bandwidth

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_OS_MEMHIGH

System Log Message Using *size* KB of memory, *percentage-value* percent of available

Description The routing protocol process (rpd) is using the indicated amount and percentage of Routing Engine memory, which is considered excessive.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause Either rpd is leaking memory or the use of system resources is excessive, perhaps because routing filters are misconfigured or the configured network topology is very complex.

Action Increase the amount of RAM in the Routing Engine.

RPD_PARSE_BAD_LR_NAME

System Log Message *executable-name*: logical system name "*logical-system-name*" exceeds *count* characters

Description The indicated logical system name exceeds the indicated maximum number of characters.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Assign a shorter name.

RPD_PARSE_BAD_OPTION

System Log Message *executable-name*: command-line option *option* is invalid

Description The command line used to start the indicated process included the indicated option, which is invalid. The process did not start.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Action Reissue the command without the invalid option.

RPD_PARSE_CMD_ARG

System Log Message	<i>executable-name</i> : missing required argument for command-line option <i>option</i>
Description	The command line used to start the indicated process did not include the argument required by the indicated option. The process did not start.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Reissue the command and include the required argument.

RPD_PARSE_CMD_DUPLICATE

System Log Message	<i>executable-name</i> : command-line option <i>option</i> is a duplicate
Description	The command line used to start the indicated process included the indicated duplicate option. The process did not start.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Reissue the command without the duplicate option.

RPD_PARSE_CMD_EXTRA

System Log Message	<i>executable-name</i> : command-line option <i>option</i> is extraneous
Description	The command line used to start the indicated process included the indicated option, which is extraneous. The process did not start.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Reissue the command and omit the extraneous option.

RPD_PIM_NBRDOWN

System Log Message	Instance <i>routing-instance</i> : PIM neighbor <i>neighbor-address</i> (<i>interface-name</i>) removed due to: <i>reason</i>
Description	The routing protocol process (rpd) declared the indicated PIM neighbor inactive.
Type	Event: This message reports an event, not an error
Severity	notice

Facility LOG_DAEMON

RPD_PIM_NBRUP

System Log Message Instance *routing-instance*: PIM new neighbor *neighbor-address* interface *interface-name*

Description The routing protocol process (rpd) discovered the indicated new PIM neighbor on the indicated interface.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_PLCY_CFG_COMMUNITY_FAIL

System Log Message Failed to parse community string under policy-options: *error-message*

Description The routing protocol process (rpd) encountered a non-catastrophic error in bgp community member string while parsing policy-options.

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

RPD_PLCY_CFG_FWDCLASS_OVERRIDDEN

System Log Message *argument* supersedes forwarding-class under policy-statement *policy-name*

Description During configuration parsing, a destination-class or source-class statement overrode the forwarding-class statement.

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

RPD_PLCY_CFG_IFALL_NOMATCH

System Log Message The interface 'all' statement under policy-statement *policy-name* will not match anything

Description Interface 'all' does not have any special meaning under the policy-options hierarchy unlike under various other hierarchies

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

RPD_PLCY_CFG_NH_NETMASK

System Log Message Netmask ignored for next hop: *argument*.

Description A netmask was specified with the indicated next hop. The netmask is ignored. In a future release, a next hop address with netmask may generate a configuration error

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

RPD_PLCY_CFG_PARSE_GEN_FAIL

System Log Message Policy warning: *error-message*

Description A conflict was detected while parsing the policy-options configuration hierarchy

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

RPD_PLCY_CFG_PREFIX_LEN_SHORT

System Log Message prefix length *prefix-length* is too short for prefix *route-prefix* under policy-statement *policy-name*, ignoring excess host bits

Description The prefix length for the indicated prefix is too short and it has a non-zero host portion. Excess host bits will be ignored.

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

RPD_PPM_READ_ERROR

System Log Message Read error on pipe from ppmd: *reason (error-message)*

Description The routing protocol process (rpd) could not read a message available on the read pipe from the periodic packet management process (ppmd).

Type Error: An error occurred

Severity info

Facility LOG_DAEMON

Action Contact your technical support representative.

RPD_PPM_WRITE_ERROR

System Log Message *function-name*: write error on pipe to ppmd (*error-message*)

Description The routing protocol process (rpd) could not write a message on the pipe to the periodic packet management process (ppmd).

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_RA_CFG_CREATE_ENTRY_FAILED

System Log Message	Could not create entry for <i>entry</i> .
Description	The configuration request failed because the IPv6 routing advertisements failed to create the indicate configuration entry.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_RA_CFG_INVALID_VALUE

System Log Message	The <i>object-name</i> configuration object <i>identifier</i> field has an invalid value of <i>value</i>
Description	The configuration request failed because the configuration object contained the indicated invalid value.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Change the value in the configuration statement to a valid one.

RPD_RA_DYN_CFG_ALREADY_BOUND

System Log Message	Dynamic configuration session id <i>client-session-id</i> for interface <i>interface-name</i> is already bound to interface <i>old-interface-name</i> .
Description	The dynamic configuration instantiation request was rejected because the indicated session ID was already bound to another interface.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Unbind session id from existing interface.

RPD_RA_DYN_CFG_INVALID_STMT

System Log Message	Invalid dynamic configuration statement: <i>configuration-statement</i>
Description	The dynamic configuration instantiation request was rejected because the indicated dynamic configuration statement was invalid.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Remove the unsupported configuration statement.

RPD_RA_DYN_CFG_SES_ID_ADD_FAIL

System Log Message	Failed to add dynamic configuration session id <i>client-session-id</i> to interface <i>interface-name</i> .
Description	The dynamic configuration instantiation request was rejected because it failed to associate the indicated session ID with the specified interface.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_RA_DYN_CFG_SES_ID_MISMATCH

System Log Message	Dynamic configuration entry for interface <i>interface-name</i> with session id <i>client-session-id</i> found an existing entry with a different session id of <i>client-session-id-1</i> .
Description	The dynamic configuration instantiation request was rejected because it matched an existing dynamic configuration block that had a different session ID.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_RDISC_CKSUM

System Log Message	Bad checksum for router solicitation from <i>source-address</i> to <i>destination-address</i>
Description	The routing protocol process (rpd) ignored a router discovery solicitation message from the indicated address because the checksum in the message's ICMP header was invalid.
Type	Event: This message reports an event, not an error

Severity	warning
Facility	LOG_DAEMON
Cause	The solicitation message was incorrectly generated or damaged in transit.
Action	Examine the host that generated the solicitation message.

RPD_RDISC_NOMULTI

System Log Message	Ignoring interface <i>interface-address</i> on <i>interface-name</i> -- multicast not available
Description	The indicated interface was configured for router discovery, but does not support IP multicast operations as required. The routing protocol process (rpd) did not enable router discovery on the interface.
Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Action	Do not configure router discovery on the interface.

RPD_RDISC_NORECVIF

System Log Message	Unable to locate interface for router solicitation from <i>source-address</i> to <i>destination-address</i>
Description	The routing protocol process (rpd) ignored a router discovery solicitation message from the indicated router because the router's IP address does not share the IP prefix of the local router. The local router is not a candidate for the indicated router because they are not on the same network.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	Although the indicated router seems to be locally attached, no interfaces on the local router are configured to handle its IP address. Either the indicated router is configured with the wrong IP address, or the local router is not correctly configured for the network that the indicated router is using.
Action	Ignore this message if it indicates the desired configuration, or reconfigure one or both routers to share a common network.

RPD_RDISC_SOLICITADDR

System Log Message	Expected multicast (<i>expected-address</i>) for router solicitation from <i>source-address</i> to <i>destination-address</i>
---------------------------	---

Description	A router discovery solicitation message received from the indicated address was not sent to the expected multicast address for all routers.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Action	Examine the configuration of the router that generated the router discovery solicitation message.

RPD_RDISC_SOLICITICMP

System Log Message	Nonzero ICMP code (<i>value</i>) for router solicitation from <i>source-address</i> to <i>destination-address</i>
Description	The routing protocol process (rpd) ignored a router discovery solicitation message from the indicated router because the ICMP code in the message header was nonzero.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	The solicitation message was incorrectly generated.
Action	Examine the host that generated the solicitation message.

RPD_RDISC_SOLICITLEN

System Log Message	Insufficient length (<i>length</i>) for router solicitation from <i>source-address</i> to <i>destination-address</i>
Description	The routing protocol process (rpd) ignored a router discovery solicitation message from the indicated router, because the indicated message length is too short.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	The solicitation message was incorrectly generated.
Action	Examine the host that generated the solicitation message.

RPD_RIP_AUTH_ACK

System Log Message	Ack with invalid authentication from <i>source-address</i> (<i>interface-name</i>)
Description	The routing protocol process (rpd) ignored an RIP ack because the ack authentication failed.

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_DAEMON

RPD_RIP_AUTH_REQUEST

System Log Message Request with invalid authentication from *source-address (interface-name)*
Description The routing protocol process (rpd) ignored an RIP request because the request authentication failed.
Type Event: This message reports an event, not an error
Severity notice
Facility LOG_DAEMON

RPD_RIP_AUTH_UPDATE

System Log Message Update with invalid authentication from *source-address (interface-name)*
Description The routing protocol process (rpd) ignored a RIP update because authentication of the update failed.
Type Event: This message reports an event, not an error
Severity notice
Facility LOG_DAEMON

RPD_RIP_JOIN_BROADCAST

System Log Message Unable to get broadcast address on *interface-name*; using the all-ones address
Description RIP cannot run on the indicated interface because the routing protocol process (rpd) could not obtain the broadcast address on the interface as required for running RIP version 1 or version 2 in compatibility mode.
Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RPD_RIP_JOIN_MULTICAST

System Log Message Unable to join multicast group on *interface-name: error-message*
Description RIP cannot run on the indicated interface, because the routing protocol process (rpd) could not join the RIP multicast group as required for RIP version 2 multicast updates.
Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RPD_RSVP_BACKUP_DOWN

System Log Message	Backup for protecting LSP <i>lsp-name</i> down, using bypass <i>bypass-lsp-name</i> reason
Description	When link protection is enabled, a backup label-switched path (LSP) is needed to maintain a protected LSP's control-plane connectivity when topology failures are detected. The backup LSP for the indicated protected LSP failed. The failure can cause traffic loss because the protected LSP tears down when there is no backup. If the reason for the backup failure can be determined, it is reported in the message.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

RPD_RSVP_BYPASS_DOWN

System Log Message	RSVP bypass <i>bypass-lsp-name</i> for protecting interface <i>interface-name</i> went down reason
Description	The indicated RSVP link-protection bypass, which was protecting the indicated interface, was terminated. If the reason for the termination can be determined, it is reported in the message.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

RPD_RSVP_BYPASS_UP

System Log Message	RSVP bypass <i>bypass-lsp-name</i> for protecting interface <i>interface-name</i> came up
Description	The indicated RSVP link-protection bypass was established to protect the indicated interface.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

RPD_RSVP_COS_CFG_WARN

System Log Message	RSVP: Error while checking the existence of [edit class-of-service]: <i>error-message</i>
Description	RSVP detected an error while parsing configurations under the CoS hierarchy. RSVP CoS configurations will be ignored.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	ANY

RPD_RSVP_LSP_SWITCH

System Log Message	RSVP LSP <i>lsp-name</i> switched to backup; using bypass LSP <i>bypass-lsp-name</i> , route <i>lsp-rro</i>
Description	RSVP detected a failure downstream for the indicated label-switched path (LSP) and switched it to a backup using the indicated bypass LSP.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	The downstream interface or router for the LSP went down.

RPD_RSVP_MAXIMUM_SESSIONS

System Log Message	RSVP maximum session limit of <i>limit</i> reached
Description	The routing protocol process (rpd) could not set up an RSVP session because the indicated limit on the number of sessions was reached.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

RPD_RSVP_NBRDOWN

System Log Message	RSVP neighbor <i>neighbor-address</i> down on interface <i>interface-name</i> , <i>reason</i>
Description	The RSVP neighbor to the indicated address was terminated.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	The communication path to the neighboring router was disrupted, a protocol error occurred, or the neighboring router was powered down.

RPD_RSVP_NBRUP

System Log Message	RSVP neighbor <i>neighbor-address</i> up on interface <i>interface-name</i>
Description	An RSVP neighbor was established to the indicated address.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

RPD_RT_CFG_BR_CONFLICT

System Log Message	static route: <i>route-prefix</i> is also configured as backup-router destination, turn on retain flag to ensure proper functionality
Description	A conflict occurred between the system backup router configuration and the indicated static route.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	ANY
Action	Add the retain flag to the static route

RPD_RT_CFG_CREATE_ENTRY_FAILED

System Log Message	Could not create entry <i>entry</i>
Description	RT failed to create the indicated configuration entry. The configuration request failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

RPD_RT_CFG_INVALID_VALUE

System Log Message	The <i>object-name</i> configuration object <i>identifier</i> field has an invalid value of <i>value</i>
Description	The configuration request failed because the indicated configuration object contained the indicated invalid value.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Modify configuration statement to use a valid value.

RPD_RT_CFG_TABLE_NON_MATCHING

System Log Message	Routing-table <i>table-name</i> under routing-instance <i>instance</i> associated with session-id <i>session-id</i> does not match the instance
Description	The dynamic config request with a specific session id and routing-instance cannot be completed because a routing-table where routes should be added does not match the instance
Type	Error: An error occurred

Severity error
Facility LOG_DAEMON

RPD_RT_DUPLICATE_RD

System Log Message routing-instance *routing-instance* has duplicate route-distinguisher *route-discriminator* as routing-instance *existing-routing-instance*

Description The route-distinguisher assigned to this routing instance has already been assigned to another routing instance (as indicated).

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RPD_RT_DYN_CFG_INST_NOT_FOUND

System Log Message Routing-instance *instance* associated with session-id *session-id* not found

Description The dynamic-config request for a specific session id and routing instance cannot be completed because the instance was not found

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RPD_RT_DYN_CFG_TABLE_NOT_FOUND

System Log Message Routing-table *table-name* under routing-instance *instance* associated with session-id *session-id* not found

Description The dynamic config request with a specific session id and routing-instance cannot be completed because a routing table where routes should be added was not found

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RPD_RT_ERROR

System Log Message *rt_event_event-name*: fatal state error

Description A route in the routing table was found to be in an unrecoverable error state.

Type Error: An error occurred
Severity critical
Facility LOG_DAEMON

RPD_RT_IFUP

System Log Message	UP route for interface <i>interface-name</i> index <i>logical-interface-index</i> <i>address/prefix-length</i>
Description	The interface route for the indicated interface and prefix changed state from down to up, becoming available for routing.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

RPD_RT_INST_CFG_RESERVED_NAME

System Log Message	The routing-instance name <i>instance</i> is reserved and cannot be used
Description	The routing-instances configuration was rejected by rpd because of a reserved routing-instance name was used
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_RT_INST_IMPORT_PLCY_WARNING

System Log Message	Instance <i>routing-instance: command</i> routing-options instance-import]error-message
Description	The policy configured for instance-import in the indicated instance needs modification to become operational.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	ANY

RPD_RT_PATH_LIMIT_BELOW

System Log Message	Number of paths (<i>count</i>) in table <i>table-name</i> is now less than the configured maximum (<i>limit</i>)
Description	The number of paths in the indicated routing table previously equaled or exceeded the indicated limit, but went down to the indicated number, which is below the limit.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

RPD_RT_PATH_LIMIT_REACHED

System Log Message	Number of paths (<i>count</i>) in table <i>table-name</i> status configured maximum (<i>limit</i>)
---------------------------	--

Description	The indicated total number of paths in the indicated routing table equaled or exceeded the indicated configured limit. Attempts to add some types of path to the table fail while this condition holds, but the path count can exceed the limit if paths are forcibly added (for example, for static routes). This message first appears in the log when the limit is reached and repeats periodically until the number of paths goes below the limit.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_RT_PATH_LIMIT_WARNING

System Log Message	Number of paths (<i>count</i>) in table <i>table-name</i> reached warning threshold (<i>threshold</i> percent of configured maximum <i>limit</i>)
Description	The indicated total number of paths in the indicated routing table reached the threshold for a warning. The threshold is the indicated percentage of the indicated configured limit on the number of paths.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

RPD_RT_PREFIX_LIMIT_BELOW

System Log Message	Number of prefixes (<i>prefix-count</i>) in table <i>table-name</i> is now less than the configured maximum (<i>limit</i>)
Description	The number of prefixes in the indicated routing table previously equaled or exceeded the indicated limit, but went down to the indicated number, which is below the limit.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

RPD_RT_PREFIX_LIMIT_REACHED

System Log Message	Number of prefixes (<i>prefix-count</i>) in table <i>table-name</i> status configured maximum (<i>limit</i>)
Description	The indicated total number of prefixes in the indicated routing table equaled or exceeded the indicated configured limit. Attempts to add some types of prefix to the table fail while this condition holds, but the prefix count can exceed the limit if prefixes are forcibly added (for example, for static routes). This message first appears in the log when the limit is reached and repeats periodically until the number of prefixes goes below the limit.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_RT_PREFIX_LIMIT_WARNING

System Log Message	Number of prefixes (<i>prefix-count</i>) in table <i>table-name</i> reached warning threshold (<i>threshold</i> percent of configured maximum <i>limit</i>)
Description	The indicated total number of prefixes in the indicated routing table reached the threshold for a warning. The threshold is the indicated percentage of the indicated configured limit on the number of prefixes.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

RPD_RT_SHOWMODE

System Log Message	invalid display mode (<i>mode</i>)
Description	The indicated display mode was specified in a 'show route' command and is unsupported.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_RT_TAG_ID_ALLOC_FAILED

System Log Message	Unable to allocate <i>object-name</i> for routing instance <i>instance</i>
Description	The routing protocol process (rpd) could not allocate either labels or subunits (as indicated) for the indicated routing instance, because the result number of objects would have exceeded the limit.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_SCHED_CALLBACK_LONGRUNTIME

System Log Message	<i>function-name</i> : excessive runtime <i>time</i> during <i>action</i> of <i>module</i>
Description	The indicated submodule of the routing protocol process (rpd) ran uninterrupted for the indicated period of time, which is considered excessive.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	The duration was noted because task accounting is enabled. The function might be implemented inefficiently.

RPD_SCHED_CUMULATIVE_LONGRUNTIME

System Log Message	<i>function-name</i> : excessive runtime (total of <i>time</i> in <i>count</i> callbacks) after <i>action</i> of <i>module</i>
Description	Several submodules of the routing protocol process (rpd) ran uninterrupted for the indicated period of time, which is considered excessive.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	The duration was noted because task accounting is enabled. The function might be implemented inefficiently.

RPD_SCHED_MODULE_LONGRUNTIME

System Log Message	<i>function-name</i> : excessive runtime <i>time</i> during <i>action</i> of <i>module</i>
Description	Several submodules of the routing protocol process (rpd) ran uninterrupted for the indicated period of time, which is considered excessive.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	The duration was noted because task accounting is enabled. The function might be implemented inefficiently.

RPD_SCHED_TASK_LONGRUNTIME

System Log Message	<i>function-name</i> ran for <i>total-time</i> (<i>user-time</i> user, <i>system-time</i> system) doing <i>action</i>
Description	A task callback within the routing protocol process (rpd) ran uninterrupted for the indicated period of time, which is considered excessive.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON
Cause	The duration was noted because task accounting is enabled. The function might be implemented inefficiently.

RPD_SIGNAL_TERMINATE

System Log Message	<i>signal-name</i> termination signal received
Description	In response to the indicated termination request, the routing protocol process (rpd) terminated adjacencies with neighbors and shut down.

Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_SNMP_CONN_PROG

System Log Message *function-name: error-message*

Description The indicated error occurred while the routing protocol process (rpd) was connecting to the Simple Network Management Protocol (SNMP) master agent.

Type	Error: An error occurred
Severity	info
Facility	LOG_DAEMON

RPD_SNMP_CONN_QUIT

System Log Message *function-name: unable to connect to SNMP agent (pathname): error-message*

Description The routing protocol process (rpd) could not connect to the indicated Simple Network Management Protocol (SNMP) master agent.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_SNMP_CONN_RETRY

System Log Message *function-name: reattempting connection to SNMP agent (pathname): error-message*

Description The routing protocol process (rpd) tried again to connect to the indicated Simple Network Management Protocol (SNMP) master agent after a connection attempt failed.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_SNMP_INVALID_SOCKET

System Log Message *function-name: socket file-descriptor is invalid*

Description The routing protocol process (rpd) could not send a message to a Simple Network Management Protocol (SNMP) master agent because the indicated socket is invalid.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_SNMP_SOCKET_BLOCK

System Log Message	<i>function-name</i> : unable to set nonblocking option
Description	The routing protocol process (rpd) could not set a socket to nonblocking mode after connecting to the Simple Network Management Protocol (SNMP) master agent.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_SNMP_SOCKET_RECVBUF

System Log Message	<i>function-name</i> : unable to set recvbuf option
Description	The routing protocol process (rpd) could not set the size of the kernel receive buffer, which allows it to accept the largest possible packet from the Simple Network Management Protocol (SNMP) master agent.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_SNMP_SOCKET_SENDBUF

System Log Message	<i>function-name</i> : unable to set sendbf option
Description	The routing protocol process (rpd) could not set the size of the kernel send buffer, which allows it to send the largest possible packet to the Simple Network Management Protocol (SNMP) master agent.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_START

System Log Message	Start <i>executable-name</i> [<i>pid</i>] version <i>version</i> built <i>date</i>
Description	The routing protocol process (rpd) started.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

RPD_SYSTEM

System Log Message	<i>reason</i> : <i>error-message</i>
Description	A system call made by the routing protocol process (rpd) failed.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	It is possible that the kernel lacked the resources to fulfill the request. The rpd process will recover.

RPD_TASK_BEGIN

System Log Message Commencing routing updates, version *rpdc-version*, built *date* by *builder*

Description The routing protocol process (rpd) started.

Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

RPD_TASK_CHILDKILLED

System Log Message *task-name* terminated by SIG*signal-name**core-dump-status*

Description While a child process of the routing protocol process (rpd) was performing the indicated operation, it terminated in response to the indicated signal.

Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON

RPD_TASK_CHILDSTOPPED

System Log Message *task-name* stopped by SIG*signal-name*

Description While a child process of the routing protocol process (rpd) was performing the indicated operation, it stopped in response to the indicated signal.

Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON

RPD_TASK_DYN_REINIT

System Log Message Dynamic reconfiguration in process

Description The routing protocol process (rpd) reinitialized.

Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

RPD_TASK_FORK

System Log Message	Unable to fork <i>task-name: error-message</i>
Description	The routing protocol process failed to create the indicated child process.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_TASK_GETWD

System Log Message	getwd: <i>error-message</i>
Description	The getwd() system call made by the routing protocol process (rpd) failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	It is possible that the kernel lacked the resources to fulfill the request. The rpd process will recover.

RPD_TASK_MASTERSHIP

System Log Message	Assuming mastership
Description	The routing protocol process (rpd) became active when the Routing Engine on which it was running assumed mastership.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

RPD_TASK_NOREINIT

System Log Message	Reinitialization not possible
Description	The routing protocol process (rpd) failed to reinitialize as requested, because it was running in a state that did not allow reconfiguration.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RPD_TASK_PIDCLOSED

System Log Message	Unable to close and remove <i>filename: error-message</i>
---------------------------	---

Description The routing protocol process (rpd) tried to close and remove the file that records its process ID (PID), which serves to prevent multiple instances of rpd from running simultaneously. The attempt failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_TASK_PIDFLOCK

System Log Message flock(*filename*, LOCK_EX): *error-message*

Description The routing protocol process (rpd) issued the flock() system call on the file that records its process ID (PID), which serves to prevent multiple instances of rpd from running simultaneously. The system call failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_TASK_PIDWRITE

System Log Message Unable to write to fd *filename*: *error-message*

Description The routing protocol process (rpd) tried to write to the file that records its process ID (PID), which serves to prevent multiple instances of rpd from running simultaneously. The attempt failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

RPD_TASK_REINIT

System Log Message Reinitializing

Description The routing protocol process (rpd) reinitialized.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

RPD_TASK_SIGNALIGNORE

System Log Message sigaction(SIG*signal-name*): *error-message*

Description The routing protocol process (rpd) informed the kernel that it wished to ignore the indicated signal, but the kernel failed to process the request.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

RPD_TRACE_FAILED

System Log Message Unable to write to trace file *filename*

Description The routing protocol process (rpd) could not write to the indicated trace file, and stopped attempting to do so. The next commit of the configuration database will reenables tracing.

Type Event: This message reports an event, not an error
Severity error
Facility LOG_DAEMON

RPD_VPLS_INTF_NOT_IN_SITE

System Log Message Some interfaces of instance *instance* are not configured under its single site

Description Some interfaces of the indicated vpls instance have not been configured under the sole site of the instance.

Type Event: This message reports an event, not an error
Severity warning
Facility ANY
Action Configure all interfaces of the instance under its single site.

CHAPTER 84

RT System Log Messages

This chapter describes messages with the **RT** prefix. They are generated on routers running the Junos OS with enhanced services by the Packet Forwarding Engine as it processes packets for security control in real time.

RT_FLOW_SESSION_CLOSE

System Log Message	<i>session closed reason: source-address/source-port->destination-address/destination-port service-name nat-source-address/nat-source-port->nat-destination-address/nat-destination-port src-nat-rule-name dst-nat-rule-name protocol-id policy-name source-zone-name destination-zone-name session-id-32 packets-from-client(bytes-from-client) packets-from-server(bytes-from-server) elapsed-time application nested-application username(roles) packet-incoming-interface</i>
Description	A security session was closed.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_PFE

RT_FLOW_SESSION_CREATE

System Log Message	<i>session created source-address/source-port->destination-address/destination-port service-name nat-source-address/nat-source-port->nat-destination-address/nat-destination-port src-nat-rule-name dst-nat-rule-name protocol-id policy-name source-zone-name destination-zone-name session-id-32 username(roles) packet-incoming-interface</i>
Description	A security session was created.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_PFE

RT_FLOW_SESSION_DENY

System Log Message	<i>session denied source-address/source-port->destination-address/destination-port service-name protocol-id icmp-type policy-name source-zone-name</i>
---------------------------	---

*destination-zone-name application nested-application username(roles)
packet-incoming-interface*

Description A security session was not permitted by policy.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_PFE

RT_GTP_BAD_LICENSE

System Log Message GTP invalid license (*gtpP memory-address*)

Description The GPRS tunneling protocol (GTP) is not enabled. The user needs to enable GTP to solve this problem.

Type Error: An error occurred

Severity error

Facility LOG_PFE

RT_GTP_DEL_TUNNEL_VO

System Log Message Delete tunnel for VO *gtp-array-index* (tid *gtp-mobile-id1gtp-mobile-id2*), in *gtp-tunnel-in-count* out *gtp-tunnel-out-count*, duration: *duration* seconds

Description A GPRS tunneling protocol (GTP) version 0 tunnel was deleted.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_PFE

RT_GTP_DEL_TUNNEL_V1

System Log Message Delete tunnel V1 *gtp-array-index* (SGSN teid *gtp-teid*), in *gtp-tunnel-in-count* out *gtp-tunnel-out-count*, duration: *duration* seconds

Description A GPRS tunneling protocol (GTP) version 1 tunnel was deleted.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_PFE

RT_GTP_PKT_APN_IE

System Log Message APN IE: *name*

Description Displays the contents of the Access Point Name (APN) information element carried in the GPRS tunneling protocol (GTP) message.

Type Event: This message reports an event, not an error

Severity info
Facility LOG_PFE

RT_GTP_PKT_DESCRIPTION_CHARGING

System Log Message GTP *source-address* -> *destination-address* charging *vmajor-version*

Description Displays the GPRS tunneling protocol (GTP) packet description for a GTP charging message. The description includes the source and destination address and version.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_PFE

RT_GTP_PKT_DESCRIPTION_VO

System Log Message GTP *source-address* -> *destination-address* TID *gtp-mobile-id1gtp-mobile-id2* (index *gtp-array-index*)

Description Displays the GPRS tunneling protocol (GTP) packet description for a GTP version 0 message. The description includes the source and destination address, 64-bit tunnel ID, and index.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_PFE

RT_GTP_PKT_DESCRIPTION_V1

System Log Message GTP *source-address* -> *destination-address* TeID *xgtp-teid* (index *gtp-array-index*)

Description Displays the GPRS tunneling protocol (GTP) packet description for a GTP version 1 message. The description includes the source and destination address, tunnel endpoint ID, and index.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_PFE

RT_GTP_PKT_ENDUSER_ADDR_IE_IPV4

System Log Message EndUserAddr IE: *ip-address*

Description Displays the contents of the IPv4 End User Address information element carried in the GPRS tunneling protocol (GTP) message. The content includes the end user IP address.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_PFE

RT_GTP_PKT_GSNADDR_IE

System Log Message	GSNaddr IE: <i>ip-address</i>
Description	Displays the contents of the GPRS Support Node (GSN) Address information element carried in the GPRS tunneling protocol (GTP) message. The content includes the GSN IP address.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_PFE

RT_GTP_PKT_IMSI_IE

System Log Message	IMSI IE: <i>gtp-mobile-id1gtp-mobile-id2</i>
Description	Displays the contents of the International Mobile Subscriber Identity (IMSI) information element carried in the GPRS tunneling protocol (GTP) message. The content includes the lower and higher halves of the GTP mobile ID.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_PFE

RT_GTP_PKT_MSISDN_IE

System Log Message	MSISdn IE: <i>gtp-isdn-number</i>
Description	Displays the contents of the MS International PSTN/ISDN Number (MSISDN) information element carried in the GPRS tunneling protocol (GTP) message. The content includes the ISDN number.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_PFE

RT_GTP_PKT_RESULT

System Log Message	*** <i>message</i>
Description	Displays the GPRS tunneling protocol (GTP) packet process result, providing information about whether the packet is passed or dropped.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_PFE

RT_GTP_SANITY_EXTENSION_HEADER

System Log Message	*** GTP-DROP <i>message-type</i> (sanity): wrong extension header
Description	The GPRS tunneling protocol (GTP) packet has an incorrect extension header and the packet will be dropped.
Type	Error: An error occurred
Severity	error
Facility	LOG_PFE

RT_GTP_SYSTEM_ERROR

System Log Message	*** GTP-DROP <i>message-type</i> : bad system status (<i>error-code</i>)
Description	The GPRS tunneling protocol (GTP) packet was dropped due to a firewall system error, as indicated by the error code.
Type	Error: An error occurred
Severity	error
Facility	LOG_PFE

RT_H323_NAT_COOKIE_NOT_FOUND

System Log Message	<i>object-name</i> cannot find cookie from session
Description	Failed to find the H.323 NAT cookie.
Type	Error: An error occurred
Severity	error
Facility	LOG_PFE

RT_IPSEC_BAD_SPI

System Log Message	IPSec tunnel on int <i>interface-name</i> with tunnel ID <i>Oxtunnel-id</i> received a packet with a bad SPI. <i>source-address->destination-address/length, type, SPI Oindex, SEQ Osequence-number</i> .
Description	Received IPSec packet with bad SPI
Type	Error: An error occurred
Severity	error
Facility	LOG_PFE

RT_IPSEC_REPLAY

System Log Message	Replay packet detected on IPSec tunnel on <i>interface-name</i> with tunnel ID <i>Oxtunnel-id</i> ! From <i>source-address</i> to <i>destination-address/length, type, SPI Oindex, SEQ Osequence-number</i> .
---------------------------	---

Description Received IPSec replay packet

Type Error: An error occurred

Severity error

Facility LOG_PFE

RT_MGCP_CALL_LIMIT_EXCEED

System Log Message Exceed maximum call *max active call numbermaximum-value*

Description The maximum MGCP active call limit has been exceeded.

Type Error: An error occurred

Severity error

Facility LOG_PFE

RT_MGCP_DECODE_FAIL

System Log Message Failed to decode MGCP packet

Description Failed to decode MGCP message.

Type Error: An error occurred

Severity error

Facility LOG_PFE

RT_MGCP_MEM_ALLOC_FAILED

System Log Message Failed to allocate memory for *object-name*

Description Failed to allocate memory for the MGCP objects.

Type Error: An error occurred

Severity error

Facility LOG_PFE

RT_MGCP_REG_NAT_VEC_FAIL

System Log Message Failed to add MGCP *object-name* to flow module

Description Failed to register the MGCP ALG vector with the flow module.

Type Error: An error occurred

Severity error

Facility LOG_PFE

RT_MGCP_REG_RM_FAIL

System Log Message Failed to register MGCP ALG with Resource Manager

Description Failed to register the MGCP Resource Manager client.

Type Error: An error occurred

Severity error

Facility LOG_PFE

RT_MGCP_REM_NAT_VEC_FAIL

System Log Message Failed to remove MGCP *object-name* from flow module

Description Failed to remove the MGCP ALG vector from the flow module.

Type Error: An error occurred

Severity error

Facility LOG_PFE

RT_MGCP_RM_CLIENTID_FAIL

System Log Message MGCP ALG Resource Manager client registration failed

Description Failed to obtain the MGCP Resource Manager client identifier.

Type Error: An error occurred

Severity error

Facility LOG_PFE

RT_MGCP_UNREG_BY_RM

System Log Message MGCP ALG client has been unregistered by Resource Manager

Description The Resource Manager has unregistered the MGCP Resource Manager client.

Type Error: An error occurred

Severity error

Facility LOG_PFE

RT_SCCP_CALL_LIMIT_EXCEED

System Log Message Failed to create SCCP ALG call, call limit *maximum-value* exceeded

Description The maximum SCCP call limit has been exceeded.

Type Error: An error occurred

Severity error

Facility LOG_PFE

RT_SCCP_CALL_RATE_EXCEED

System Log Message The SCCP active call rate limit *maximum-value* has been exceeded

Description The SCCP active call rate limit has been exceeded.

Type Error: An error occurred

Severity error

Facility LOG_PFE

RT_SCCP_DECODE_FAIL

System Log Message Failed to decode SCCP packet from *source-address->destination-address*

Description Failed to decode SCCP packet.

Type Error: An error occurred

Severity error

Facility LOG_PFE

RT_SCCP_NAT_COOKIE_NOT_FOUND

System Log Message Failed to find SCCP ALG cookie from session

Description Failed to find SCCP NAT cookie.

Type Error: An error occurred

Severity error

Facility LOG_PFE

RT_SCCP_REM_NAT_VEC_FAIL

System Log Message Failed to remove SCCP ALG vector from flow module

Description Failed to remove the SCCP ALG vector from the flow module.

Type Error: An error occurred

Severity error

Facility LOG_PFE

RT_SCCP_UNREG_RM_FAIL

System Log Message Failed to unregister SCCP client from Resource Manager when the ALG was unregistered

Description Failed to unregister SCCP client from Resource Manager when the ALG was unregistered.

Type Error: An error occurred

Severity error

Facility LOG_PFE

RT_SCREEN_ICMP

System Log Message *attack-name* source: *source-address*, destination: *destination-address*, zone name: *source-zone-name*, interface name: *interface-name*, action: *action*

Description ICMP attack category

Type Event: This message reports an event, not an error

Severity error

Facility LOG_PFE

RT_SCREEN_IP

System Log Message *attack-name* source: *source-address*, destination: *destination-address*, protocol-id: *protocol-id*, zone name: *source-zone-name*, interface name: *interface-name*, action: *action*

Description IP attack category

Type Event: This message reports an event, not an error

Severity error

Facility LOG_PFE

RT_SCREEN_SESSION_LIMIT

System Log Message *attack-name* message: *ip-address*, zone name: *source-zone-name*, interface name: *interface-name*, action: *action*

Description Session limit category

Type Event: This message reports an event, not an error

Severity error

Facility LOG_PFE

RT_SCREEN_TCP

System Log Message *attack-name* source: *source-address:source-port*, destination: *destination-address:destination-port*, zone name: *source-zone-name*, interface name: *interface-name*, action: *action*

Description TCP attack category

Type Event: This message reports an event, not an error

Severity error

Facility LOG_PFE

RT_SCREEN_TCP_DST_IP

System Log Message *attack-name* destination: *destination-address*, zone name: *source-zone-name*, interface name: *interface-name*, action: *action*

Description	TCP destination IP attack category
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_PFE

RT_SCREEN_TCP_SRC_IP

System Log Message	<i>attack-name</i> source: <i>source-address</i> , zone name: <i>source-zone-name</i> , interface name: <i>interface-name</i> , action: <i>action</i>
Description	TCP source IP attack category
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_PFE

RT_SCREEN_UDP

System Log Message	<i>attack-name</i> source: <i>source-address:source-port</i> , destination: <i>destination-address:destination-port</i> , zone name: <i>source-zone-name</i> , interface name: <i>interface-name</i> , action: <i>action</i>
Description	UDP attack category
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_PFE

RT_SCTP_LOG_INFO

System Log Message	***SCTP configuration: <i>message</i>
Description	SCTP log info.
Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

RT_SCTP_PKT_INFO

System Log Message	***SCTP (type <i>message-type</i> <i>source-address/source-port</i> -> <i>destination-address/destination-port</i>) <i>message</i>
Description	SCTP packet info.
Type	Event: This message reports an event, not an error
Severity	info

Facility ANY

RT_SIP_MEM_ALLOC_FAILED

System Log Message Failed to allocate memory for *object-name*

Description Failed to allocate memory from the memory pool.

Type Error: An error occurred

Severity error

Facility LOG_PFE

CHAPTER 85

RTLOG System Log Messages

This chapter describes messages with the **RTLOG** prefix. They are generated on routers running the Junos OS with enhanced services by the system log module of the Packet Forwarding Engine as it processes packets for security control in real time.

RTLOG_JLOG_TEST

System Log Message	JLOG test OK, jlog_handle= <i>current-value</i>
Description	Test JSF Log plugin registration.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_PFE

RTLOG_UTP_TCP_SYN_FLOOD

System Log Message	source: <i>source-address-source-port</i> , destination: <i>destination-address-destination-port</i> , zone name: <i>filter-name</i> , interface name: <i>interface-name</i>
Description	Security LOG UTP fake TCP SYN flood attack.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_PFE

CHAPTER 86

RTLOGD System Log Messages

This chapter describes messages with the **RTLOGD** prefix. They are generated by the system log utility for real-time processing of packets for security control (rtlogd) on routers running the Junos OS with enhanced services.

RTLOGD_LOG_BIND_ERROR

System Log Message	Failed to bind socket to PFE: <i>error-message</i>
Description	Junos JSR log daemon receives JSR log from a JSR log forwarder. The JSR log daemon failed to connect to the forwarder.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

RTLOGD_LOG_READ_ERROR

System Log Message	Failed to read from PFE: <i>error-message</i>
Description	Junos JSR log daemon relays JSR logs from the dataplane to the system event daemon for logging. The JSR log daemon fails to read JSR logs for the indicated reason.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHAPTER 87

RTPERF System Log Messages

This chapter describes messages with the **RTPERF** prefix. They are related to performance logs for the data plane.

RTPERF_CPU_THRESHOLD_EXCEEDED

System Log Message	FPC <i>fpc-slot</i> PIC <i>pic-slot</i> CPU utilization exceeds threshold, current value= <i>current-value</i>
Description	PFE cpu threshold exceeded
Type	Event: This message reports an event, not an error
Severity	critical
Facility	LOG_PFE

RTPERF_CPU_USAGE_OK

System Log Message	FPC <i>fpc-slot</i> PIC <i>pic-slot</i> CPU utilization returns to normal, current value= <i>current-value</i>
Description	PFE cpu usage okay
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_PFE

CHAPTER 88

SAVAL System Log Messages

This chapter describes messages with the SAVAL prefix. They are generated by the MAC SA Validate system (jsavald) process.

SAVAL_RT SOCK_FAILURE

System Log Message	Error with rtsock: <i>error-message</i>
Description	The MAC SA Validate system process (jsavald) experienced the indicated error with a routing socket.
Type	Error: An error occurred
Severity	info
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

CHAPTER 89

SDXD System Log Messages

This chapter describes messages with the **SDX** prefix. They are generated by the Session and Resource Control (SRC) process (sdx), which provides a user interface for deploying Internet services.

SDXD_BEEP_FIN_FAIL

System Log Message	Graceful close of BEEP session failed
Description	The Session and Resource Control (SRC) process (sdx) could not send a request to the SRC server to close a Blocks Extensible Exchange Protocol (BEEP) session. It sends this request when the session becomes unconfigured.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON
Cause	The usual cause is that the session was already partially or completely closed.
Action	None required. The sdx process recovers automatically in this situation.

SDXD_BEEP_INIT_FAIL

System Log Message	BEEP initialization failed
Description	The Session and Resource Control (SRC) process (sdx) could not initialize the Blocks Extensible Exchange Protocol (BEEP), which it uses to connect to an SRC server.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure might have occurred.

SDXD_CHANNEL_START_FAIL

System Log Message	Notification channel could not be started (<i>error-code</i>): <i>message</i>
---------------------------	---

Description	The indicated Blocks Extensible Exchange Protocol (BEEP) channel could not be started for the indicated reason.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON
Cause	The usual cause is an abnormal operation, which might be described in the system log message.

SDXD_CONNECT_FAIL

System Log Message	Connection to SDX server failed: <i>message</i>
Description	The Session and Resource Control (SRC) process (sxdx) could not connect to an SRC server for the indicated reason.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON
Cause	There was a network problem or the server was not running.

SDXD_DAEMONIZE_FAIL

System Log Message	Aborting, unable to run in the background as a daemon: <i>error-message</i>
Description	The Service Deployment System process (sxdx) could not create a version of itself to run in the background as a daemon.
Type	Error: An error occurred
Severity	emergency
Facility	LOG_DAEMON

SDXD_EVLIB_FAILURE

System Log Message	<i>function-name: error-message</i>
Description	The Service Deployment System process (sxdx) called the indicated function in the event library. The function failed with the indicated error.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.

SDXD_KEEPAIVES_MISSED

System Log Message	No server keepalives received for three intervals
Description	The Session and Resource Control (SRC) process (sxdx) and SRC server exchange keepalive messages at regular intervals. The process did not receive a keepalive from the server for three consecutive keepalive intervals. In this case, it closes the session and tries to connect to another SRC server.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

SDXD_KEEPAIVE_SEND_FAIL

System Log Message	Unable to send keepalive
Description	The Session and Resource Control (SRC) process (sxdx) could not send a keepalive message to the SRC server, which it does periodically to maintain its connection to the server.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON
Cause	There might have been a network problem.

SDXD_MGMT_SOCKET_IO

System Log Message	management daemon I/O failure: <i>reason</i>
Description	The Service Deployment System process (sxdx) could not read from or write to the management socket that it uses to communicate with the Junos management process (mgd).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	The mgd process might have exited abnormally.

SDXD_OUT_OF_MEMORY

System Log Message	Insufficient memory during <i>operation</i>
Description	The Service Deployment System (sxdx) attempted to allocate memory for an internal object during the indicated operation. The attempt failed.
Type	Error: An error occurred

Severity error
Facility LOG_DAEMON

SDXD_PID_FILE_UPDATE

System Log Message Unable to update process PID file: *error-message*

Description The Service Deployment System process (sdx) attempted to update the file that records its process ID (PID), which serves to prevent multiple instances of sdx from running simultaneously. The attempt failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

SDXD_SOCKET_FAILURE

System Log Message *operation* failed: *error-message*

Description The Service Deployment System process (sdx) uses Transmission Control Protocol (TCP) sockets for communication with the SRC server. The indicated operation, which might be for socket creation or binding to a local address, failed with the indicated error.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause An internal software failure occurred.

Action Contact your technical support representative.

CHAPTER 90

SFW System Log Messages

This chapter describes messages with the **SFW** prefix.

SFW_LOG_FUNCTION

System Log Message	Function: <i>service-set</i>
Description	Function:
Type	Error: An error occurred
Severity	error
Facility	ANY

CHAPTER 91

SMTPD System Log Messages

This chapter describes messages with the **SMTPD** prefix. They are generated by smtp client process (smtpd).

SMTPD_DROP_MAIL_PAYLOAD

System Log Message	Dropped mail to user: <i>error-message</i> . Send failed or queued reached max
Description	The smtp client process (smtpd) attempted to send the mail payload to the configured gateway mail server failed due to one of the following reasons: network connection failure, error in the payload, or sent failed after retries. The mail is dropped.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON

SMTPD_NO_CONFIGURED_SERVER

System Log Message	Unable to send mail to <i>error-message</i> . Configure server with relay
Description	The smtp client process (smtpd) is unable to send mail payload. A gateway server must be configured. This server must allow relaying.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON

CHAPTER 92

SNMP System Log Messages

This chapter describes messages with the **SNMP** prefix. They are generated by two kinds of processes:

- Processes that perform SNMP operations, such as the MIB II process (mib2d) and the SNMP agent process (snmpd). Those processes also generate messages with prefixes that match their names, as described in “MIB2D System Log Messages” on page 373 and “SNMPD System Log Messages” on page 513.
- Processes that are instrumented to generate system log messages when they send SNMP traps. The SNMP remote operations process (rmopd) is one such process. It also generates messages with the RMOPD_ prefix, which are described in “RMOPD System Log Messages” on page 419.

SNMP_GET_ERROR1

System Log Message	<i>function-name operation failed for object-name: index1 index1 (error-message)</i>
Description	An SNMP Get or GetNext request failed for the indicated object, which has the indicated index.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

SNMP_GET_ERROR2

System Log Message	<i>function-name operation failed for object-name: index1 index1 index2 index2 (error-message)</i>
Description	An SNMP Get or GetNext request failed for the indicated object, which has the indicated indexes.
Type	Error: An error occurred

Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

SNMP_GET_ERROR3

System Log Message	<i>function-name operation failed for object-name: index1 index1 index2 index2 index3 index3 (error-message)</i>
Description	An SNMP Get or GetNext request failed for the indicated object, which has the indicated indexes.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

SNMP_GET_ERROR4

System Log Message	<i>function-name operation failed for object-name: index1 index1 index2 index2 index3 index3 index4 index4 (error-message)</i>
Description	An SNMP Get or GetNext request failed for the indicated object, which has the indicated indexes.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

SNMP_RTSLIB_FAILURE

System Log Message	<i>function-name: reason: error-message</i>
Description	A call to the indicated function in the routing socket library failed with the indicated error.
Type	Error: An error occurred
Severity	emergency

Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

SNMP_TRAP_LINK_DOWN

System Log Message	ifIndex <i>snmp-interface-index</i> , ifAdminStatus <i>admin-status</i> , ifOperStatus <i>operational-status</i> , ifName <i>interface-name</i>
Description	The SNMP agent process (snmpd) generated a linkDown trap because the indicated interface changed state to 'down'.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_DAEMON

SNMP_TRAP_LINK_UP

System Log Message	ifIndex <i>snmp-interface-index</i> , ifAdminStatus <i>admin-status</i> , ifOperStatus <i>operational-status</i> , ifName <i>interface-name</i>
Description	The SNMP agent process (snmpd) generated a linkUp trap because the indicated interface changed state to 'up'.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

SNMP_TRAP_TRACERT_PATH_CHANGE

System Log Message	traceRouteCtlOwnerIndex = <i>test-owner</i> , traceRouteCtlTestName = <i>test-name</i>
Description	The Simple Network Management Protocol (SNMP) remote operations process (rmopd) generated a traceRoutePathChange trap because two probes with the same time-to-live (TTL) value returned with different IP addresses.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

SNMP_TRAP_TRACERT_TEST_COMPLETED

System Log Message	traceRouteCtlOwnerIndex = <i>test-owner</i> , traceRouteCtlTestName = <i>test-name</i>
Description	The Simple Network Management Protocol (SNMP) remote operations process (rmopd) generated a tracerouteTestCompleted trap because the test completed and the full path to the target was determined.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

SNMP_TRAP_TRACERT_TEST_FAILED

System Log Message traceRouteCtlOwnerIndex = *test-owner*, traceRouteCtlTestName = *test-name*

Description The Simple Network Management Protocol (SNMP) remote operations process (rmopd) generated a tracerouteTestFailed trap because the test completed and the full path to the target was not determined.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

CHAPTER 93

SNMPD System Log Messages

This chapter describes messages with the **SNMPD** prefix. They are generated by the Simple Network Management Protocol (SNMP) agent process (snmpd), which responds to SNMP requests. As necessary, it passes the requests to subagent processes running on its machine and forwards the traps they generate to the SNMP manager.

SNMPD_AUTH_FAILURE

System Log Message	<i>function-name: message from source-address to destination-address (index1)</i>
Description	The indicated function failed because the authorization check failed for the interface, Simple Network Management Protocol (SNMP) community, or user making the request.
Type	Error: An error occurred
Severity	notice
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

SNMPD_AUTH_PRIVILEGES_EXCEEDED

System Log Message	<i>function-name: source-address: request exceeded community privileges</i>
Description	The indicated function failed because the Simple Network Management Protocol (SNMP) community making the access request did not have the required privileges.
Type	Error: An error occurred
Severity	notice
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

SNMPD_AUTH_RESTRICTED_ADDRESS

System Log Message	<i>function-name</i> : request from address <i>source-address</i> not allowed
Description	The indicated function failed because access requests from the indicated source address are not allowed.
Type	Error: An error occurred
Severity	notice
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

SNMPD_AUTH_WRONG_PDU_TYPE

System Log Message	<i>function-name</i> : <i>source-address</i> : unauthorized SNMP PDU type: <i>pdu-type</i>
Description	The indicated function failed because the indicated type of protocol data unit (PDU) is not supported.
Type	Error: An error occurred
Severity	notice
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

SNMPD_BIND_INFO

System Log Message	Source address for trap socket was set to <i>bind-address</i>
Description	The source address for the indicated type of socket used by the Simple Network Management Protocol (SNMP) agent process (snmpd) was set to the indicated address.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON
Cause	An administrator changed the Junos configuration for the process or for an interface.
Cause	The online/offline state changed for a PIC. This can also cause the address to become newly available or unavailable.

SNMPD_CONFIG_ERROR

System Log Message	Configuration database has errors
Description	The Simple Network Management Protocol (SNMP) agent process (snmpd) detected an error in the SNMP configuration database.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

SNMPD_CONTEXT_ERROR

System Log Message	<i>function-name: error in operation context context-name</i>
Description	The indicated operation (addition or deletion) failed during configuration of the indicated Simple Network Management Protocol (SNMP) context.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

SNMPD_FILE_FAILURE

System Log Message	<i>function-name: fopen filename: error-message</i>
Description	The Simple Network Management Protocol (SNMP) agent process (snmpd) could not access the indicated file.
Type	Error: An error occurred
Severity	emergency
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

SNMPD_GROUP_ERROR

System Log Message	<i>function-name: error in operation group: 'group-id' user 'username' model 'model'</i>
Description	The indicated operation (creation, installation, or deletion) failed during configuration of the indicated group.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

SNMPD_HEALTH_MON_THRESH_CROSS

System Log Message	<i>syslog-subtagdelimiterevent-name</i>
Description	A system parameter monitored by the self-monitoring feature crossed a rising or falling threshold.
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_DAEMON
Cause	System resources were being consumed.

SNMPD_INIT_FAILED

System Log Message	snmpd initialization failure: <i>error-message</i>
Description	Initialization of the Simple Network Management Protocol (SNMP) agent process (snmpd) failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

SNMPD_LIBJUNIPER_FAILURE

System Log Message	<i>function-name: system_default_inaddr: error-message</i>
Description	The indicated function from the Juniper Networks Simple Network Management Protocol (SNMP) library failed and returned the indicated error to the SNMP agent process (snmpd).
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

Cause An internal software failure occurred.

Action Contact your technical support representative.

SNMPD_RADIX_FAILURE

System Log Message *function-name: radix_add failed: error-message*

Description The Simple Network Management Protocol (SNMP) agent process (snmpd) uses radix trees to store valid client prefixes, which are used to determine authorization for requests from users and communities. It could not create a new entry in a radix tree.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause An internal software failure occurred.

Action Contact your technical support representative.

SNMPD_RECEIVE_FAILURE

System Log Message *function-name: receive message failure: error-message*

Description The indicated error occurred while the Simple Network Management Protocol (SNMP) agent process (snmpd) was receiving either a protocol data unit (PDU) from the User Datagram Protocol (UDP) or a message from a subagent.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause An internal software failure occurred.

Action Contact your technical support representative.

SNMPD_RMONFILE_FAILURE

System Log Message *function-name: operation: operation filename: error-message*

Description The indicated operation failed on the indicated remote monitoring (RMON) data file.

Type Error: An error occurred

Severity critical

Facility LOG_DAEMON

Cause An internal software failure occurred.

Action Contact your technical support representative.

SNMPD_RMON_COOKIE

System Log Message *function-name*: Null cookie

Description An invalid data pointer was returned when the remote monitoring (RMON) asynchronous completion handler performed an RMON alarm operation.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause An internal software failure occurred.

Action Contact your technical support representative.

SNMPD_RMON_EVENTLOG

System Log Message *syslog-subtagdelimitermessage*

Description The indicated remote monitoring (RMON) event completed.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

SNMPD_RMON_MIBERROR

System Log Message *function-name*: internal Get request error: *description*, alarm *alarm-id*, error *error-message*, variable: *name* (*oid*)

Description A Get request for a monitored object instance failed during initialization of the indicated remote monitoring (RMON) alarm.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause An internal software failure occurred.

Action Contact your technical support representative.

SNMPD_RTSLIB_ASYNC_EVENT

System Log Message *function-name*: sequence mismatch (*expected-value*, *received-value*), resyncing

Description A notification from the kernel to the Simple Network Management Protocol (SNMP) agent process (snmpd) was lost.

Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON

SNMPD_SEND_FAILURE

System Log Message *function-name: send type (index1) failure: error-message*

Description The Simple Network Management Protocol (SNMP) agent process (snmpd) could not send either a protocol data unit (PDU) to the User Datagram Protocol (UDP) or a message to a subagent.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

SNMPD_SET_FAILED

System Log Message *Snmp set failed: error-message*

Description Configuration data was changed using an Simple Network Management Protocol (SNMP) Set request, but the SNMP agent process (snmpd) could not save the changes to the configuration database.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

SNMPD_SMOID_GEN_FAILURE

System Log Message *Unable to generate OID from product-name (error-message)*

Description The Simple Network Management Protocol (SNMP) agent process (snmpd) could not generate a value for the self-monitoring object identifier (OID) of the indicated product.

Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.

Action Contact your technical support representative.

SNMPD_SOCKET_FAILURE

System Log Message *function-name: socket failure: reason (error-message)*

Description The Simple Network Management Protocol (SNMP) agent process (snmpd) uses sockets for communication with subagents. A socket operation, such as creation or removal, failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause An internal software failure occurred.

Action Contact your technical support representative.

SNMPD_SOCKET_FATAL_FAILURE

System Log Message *function-name: socket failure: reason (error-message)*

Description The Simple Network Management Protocol (SNMP) agent process (snmpd) uses sockets for communication with subagents. The process exited after a socket operation, such as creation or removal, failed.

Type Error: An error occurred

Severity emergency

Facility LOG_DAEMON

Cause An internal software failure occurred.

Action Contact your technical support representative.

SNMPD_SYSLIB_FAILURE

System Log Message *function-name: system function 'system-function-name' failed: error-message*

Description The indicated function from the Simple Network Management Protocol (SNMP) system library failed and returned the indicated error to the SNMP agent process (snmpd).

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause An internal software failure occurred.

Action Contact your technical support representative.

SNMPD_SYSOID_FAILURE

System Log Message	Unable to determine sysObjectID from internal model: <i>model</i>
Description	The Simple Network Management Protocol (SNMP) agent process (snmpd) could not determine the value of the sysObjectID object.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

SNMPD_SYSOID_GEN_FAILURE

System Log Message	Unable to generate OID for product <i>product-name</i> (<i>error-message</i>)
Description	The Simple Network Management Protocol (SNMP) agent process (snmpd) could not generate a value for the sysObjectID object for the indicated product.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

SNMPD_THROTTLE_QUEUE_DRAINED

System Log Message	<i>function-name</i> : cleared all throttled traps
Description	The queue of throttled traps was cleared.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

SNMPD_TRAP_COLD_START

System Log Message	<i>function-name</i> : SNMP trap: cold start
Description	The Simple Network Management Protocol (SNMP) agent process (snmpd) generated a cold-start trap when the entire Routing Engine (including the snmpd process) initialized.
Type	Event: This message reports an event, not an error

Severity critical
Facility LOG_DAEMON

SNMPD_TRAP_GEN_FAILURE

System Log Message *function-name: SNMP trap error: trap-message (error-message)*

Description The Simple Network Management Protocol (SNMP) agent process (snmpd) could not generate a trap.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause An internal software failure occurred.

Action Contact your technical support representative.

SNMPD_TRAP_INVALID_DATA

System Log Message *function-name: SNMP trap error: invalid message (value) received*

Description The Simple Network Management Protocol (SNMP) agent process (snmpd) received a trap message from a subagent that contained an invalid variable binding (varbind) type.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause An internal software failure occurred.

Action Contact your technical support representative.

SNMPD_TRAP_QUEUED

System Log Message Adding trap to *trap-destination* to *queue-name* queue, *size* traps in queue

Description A trap was queued for later transmission.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_DAEMON

Cause Possible causes include the following: (a) the system is not completely initialized, (b) a route does not exist, or (c) traps are being throttled.

SNMPD_TRAP_QUEUE_DRAINED

System Log Message	<i>function-name</i> : traps queued to <i>trap-destination</i> sent successfully
Description	The queued traps for the indicated destination were successfully sent.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

SNMPD_TRAP_QUEUE_MAX_ATTEMPTS

System Log Message	<i>function-name</i> : after <i>count</i> attempts, deleting <i>trap-count</i> traps queued to <i>trap-destination</i>
Description	The number of attempts to send traps to the indicated destination exceeded the configured maximum. The traps still waiting to be sent were discarded.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Action	Contact your technical support representative.

SNMPD_TRAP_QUEUE_MAX_SIZE

System Log Message	<i>function-name</i> : maximum queue size exceeded (<i>size</i>), discarding trap to <i>trap-destination</i> from <i>queue-name</i> queue
Description	The number of traps in the trap queue exceeded the configured maximum. The traps still waiting to be sent were discarded.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

SNMPD_TRAP_THROTTLED

System Log Message	<i>function-name</i> : traps throttled after <i>count</i> traps
Description	The number of traps waiting for transmission exceeded the configured maximum, so the remaining traps were throttled.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

SNMPD_TRAP_WARM_START

System Log Message	<i>function-name</i> : SNMP trap: warm start
---------------------------	--

Description The Simple Network Management Protocol (SNMP) agent process (snmpd) generated a warm-start trap when it initialized (other Routing Engine processes were already active).

Type Event: This message reports an event, not an error

Severity error

Facility LOG_DAEMON

SNMPD_USER_ERROR

System Log Message *function-name: error in action user 'username' auth 'authentication-type' priv 'privilege-type'*

Description The indicated operation (creation, installation, or deletion) failed during configuration of the indicated user.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause An internal software failure occurred.

Action Contact your technical support representative.

SPD System Log Messages

This chapter describes messages with the **SPD** prefix. They are generated by the adaptive services process (spd), which provides the user interface for management and configuration of Adaptive Services PICs.

SPD_CONFIGURATION_COMPILE

System Log Message	Compilation of configuration rule <i>rule-name</i> term <i>index</i> failed: <i>reason</i>
Description	The adaptive services process (spd) could not compile a configured object, such as a rule or rule term.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

SPD_CONN_FATAL_FAILURE

System Log Message	Connection attempt failed with fatal error: <i>error-message</i>
Description	The adaptive services process (spd) attempted to open a connection to an Adaptive Services PIC, to gather information requested in a Simple Network Management Protocol (SNMP) query. The attempt failed with the indicated fatal error.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

SPD_CONN_NO_REPLY

System Log Message	<i>function-name</i> : no reply from <i>interface-name</i> (<i>error-message</i>)
Description	The adaptive services process (spd) did not receive a reply from the indicated interface on an Adaptive Services PIC for information requested in a Simple Network Management Protocol (SNMP) query.
Type	Error: An error occurred
Severity	error

Facility LOG_DAEMON

SPD_CONN_OPEN_FAILURE

System Log Message *function-name: unable to open connection to interface-name (error-message)*

Description The adaptive services process (spd) attempted to open a connection to the indicated interface on an Adaptive Services PIC, to gather information requested in a Simple Network Management Protocol (SNMP) query. The attempt failed for the indicated reason.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

SPD_CONN_SEND_FAILURE

System Log Message *function-name: unable to send query to interface-name (error-message)*

Description The adaptive services process (spd) attempted to send a request for information, needed for a Simple Network Management Protocol (SNMP) query, to the indicated interface on an Adaptive Services PIC. The attempt failed for the indicated reason.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

SPD_CONN_UNEXPECTED_MSG

System Log Message *function-name: unexpected response received from interface-name (error-message)*

Description The adaptive services process (spd) sent a request for information, needed for a Simple Network Management Protocol (SNMP) query, to the indicated interface on an Adaptive Services PIC. It received an unexpected response.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

SPD_DAEMONIZE_FAILED

System Log Message Aborting, unable to run in the background as a daemon: *error-message*

Description The adaptive services process (spd) could not create a version of itself to run in the background as a daemon.

Type Error: An error occurred

Severity emergency

Facility LOG_DAEMON

SPD_DB_IF_ADD_FAILURE

System Log Message	Unable to add database entry for <i>interface-name: error-message</i>
Description	The adaptive services process (spd) uses an internal database to store information needed to reply to Simple Network Management Protocol (SNMP) queries. It could not add an entry to the database for the indicated interface on an Adaptive Services PIC.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

SPD_DB_IF_ALLOC_FAILURE

System Log Message	Unable to allocate database entry for <i>interface-name: error-message</i>
Description	The adaptive services process (spd) uses an internal database to store information needed to reply to Simple Network Management Protocol (SNMP) queries. It could not allocate an entry in the database for the indicated interface on an Adaptive Services PIC.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

SPD_DB_SVC_SET_ADD_FAILURE

System Log Message	Unable to add database entry for <i>service-set: error-message</i>
Description	The adaptive services process (spd) uses an internal database to store information needed to reply to Simple Network Management Protocol (SNMP) queries. It could not add an entry to the database for the indicated service set.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

SPD_DB_SVC_SET_ALLOC_FAILURE

System Log Message	Unable to allocate database entry for <i>service-set: error-message</i>
Description	The adaptive services process (spd) uses an internal database to store information needed to reply to Simple Network Management Protocol (SNMP) queries. It could not allocate an entry in the database for the indicated service set.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

SPD_DUPLICATE

System Log Message	Another copy of this program is running
Description	An attempt to start the adaptive services process (spd) failed because an instance of the process is already running.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

SPD_EVLIB_CREATE_FAILURE

System Log Message	evCreate failed with: <i>error-message</i>
Description	The adaptive services process (spd) could not create a context used for handling all asynchronous events (such as timers and message availability).
Type	Error: An error occurred
Severity	emergency
Facility	LOG_DAEMON

SPD_EVLIB_EXIT_FAILURE

System Log Message	evMainLoop return value: <i>return-value</i> , error: <i>error-message</i>
Description	The adaptive services process (spd) returned from an event loop, which it should never do.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

SPD_GEN_NUM_FAIL

System Log Message	Initialization of generation number failed, <i>error-message</i>
Description	The adaptive services process (spd) attempted to initialize the generation-number for the service sets. However, the memory allocation failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

SPD_NOT_ROOT

System Log Message	Must be run as root
Description	The user who attempted to start the adaptive services process (spd) was not the root user.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

SPD_OUT_OF_MEMORY

System Log Message Insufficient memory for operation *operation*
Description The adaptive services process (spd) attempted to allocate memory for an internal object. The attempt failed.
Type Error: An error occurred
Severity error
Facility LOG_DAEMON

SPD_PID_FILE_LOCK

System Log Message Unable to lock PID file: *error-message*
Description The adaptive services process (spd) attempted to lock the file that records its process ID (PID), which serves to prevent multiple instances of spd from running simultaneously. The attempt failed.
Type Error: An error occurred
Severity error
Facility LOG_DAEMON

SPD_PID_FILE_UPDATE

System Log Message Unable to update process PID file: *error-message*
Description The adaptive services process (spd) attempted to update the file that records its process ID (PID), which serves to prevent multiple instances of spd from running simultaneously. The attempt failed.
Type Error: An error occurred
Severity error
Facility LOG_DAEMON

SPD_SERVICE_NEXT_HOP_ADD_FAILED

System Log Message Unable to add service next hop: *error-message (error-code)*
Description The adaptive services process (spd) could not add a service next hop for the indicated reason.
Type Error: An error occurred
Severity error

Facility LOG_DAEMON

SPD_SERVICE_NEXT_HOP_DEL_FAILED

System Log Message Unable to delete service next hop: *error-message (error-code)*

Description The adaptive services process (spd) could not delete a service next hop for the indicated reason.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

SPD_TRAP_OID_GEN_FAILED

System Log Message Unable to generate OID for *identifier (error-message)*

Description The adaptive services process (spd) could not generate the indicated object identifier (OID) for a Simple Network Management Protocol (SNMP) trap notification.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

SPD_TRAP_REQUEST_FAILURE

System Log Message *function-name: type* request failed: *error-message*

Description The adaptive services process (spd) made the indicated type of request to the application programming interface (API) for generating Simple Network Management Protocol (SNMP) traps, but did not receive the expected result.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

SPD_USAGE

System Log Message Usage: spd [-N] [-v] [-d debug-level]

Description The adaptive services process (spd) displayed the syntax statement for the 'spd' command because the command was invoked incorrectly.

Type Event: This message reports an event, not an error

Severity error

Facility LOG_DAEMON

CHAPTER 95

SSH System Log Messages

This chapter describes messages with the **SSH** prefix. They are generated by the ssh-relay process (ssh).

SSH_FIPS_SELFTEST_EXECUTED

System Log Message	FIPS RNG and HASH function selftests executed successfully.
Description	FIPS selftests were executed successfully after key generation.
Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

SSH_KEYGEN_SELFTEST_DSA

System Log Message	FIPS RNG and DSA selftests executed successfully.
Description	FIPS RNG and DSA selftests were executed successfully after key generation.
Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

SSH_KEYGEN_SELFTEST_RSA

System Log Message	FIPS RNG and RSA selftests executed successfully.
Description	FIPS RNG and RSA selftests were executed successfully after key generation.
Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

SSH_RELAY_CONNECT_ERROR

System Log Message	Unable to connect to <i>service-name</i> server: <i>error-message</i>
Description	The 'ssh-relay' program could not connect to the server process for the indicated service.

Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	The server process is not running or has not enabled the service.

SSH_RELAY_SERVER_ERROR

System Log Message	SSH relay error for <i>service-name</i> service: <i>error-message</i>
Description	The indicated error occurred when a JUNOS process tried to establish secure shell (SSH) relay during initialization of the indicated service.
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

SSH_RELAY_USAGE

System Log Message	Usage: ssh-relay -s <i>service-name</i>
Description	The syntax statement for the 'ssh-relay' command was displayed because the command was invoked with one or more incorrect options, or without necessary options.
Type	Error: An error occurred
Severity	error
Facility	ANY

SSHD System Log Messages

This chapter describes messages with the SSHD prefix. They are generated by the secure shell process (sshd) which grants you access to specified shell accounts.

SSHD_FIPS_SELFTEST_EXECUTED

System Log Message	FIPS RNG and HASH function selftests executed successfully.
Description	FIPS selftests were executed successfully after key generation.
Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

SSHD_LOGIN_FAILED_LIMIT

System Log Message	Specified number of login failures (<i>limit</i>) for user ' <i>username</i> ' reached from ' <i>remote-address</i> '
Description	Several login attempts failed for the indicated username.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	ANY

CHAPTER 97

TASK System Log Messages

This chapter describes messages with the **TASK** prefix.

TASK_ABORT

System Log Message	abort <i>executable-name</i> [<i>pid</i>] version <i>version</i> built by <i>builder</i> on <i>date</i> : <i>error-message</i>
Description	The control protocol process terminated because of an internal error.
Type	Error: An error occurred
Severity	error
Facility	ANY
Action	Examine the messages that immediately follow this message in the system log for information about possible causes.
Cause	An internal software failure occurred.

TASK_ACTIVE_TERMINATE

System Log Message	Exiting with active tasks: <i>task-name</i>
Description	After receiving multiple termination requests, the control protocol process exited without performing the indicated cleanup tasks.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	ANY

TASK_ASSERT

System Log Message	Assertion failed <i>executable-name</i> [<i>pid</i>]: file " <i>source-filename</i> ", line <i>line-number</i> : " <i>message</i> "
Description	The source code for this process includes internal self-consistency checks. The process terminated because a check failed, creating a diagnostic core dump for analysis by technical support personnel and noting the number of the line in the source file where the check failed.
Type	Error: An error occurred

Severity	error
Facility	ANY
Cause	An internal software failure occurred.
Action	Examine the messages that immediately follow this message in the system log for information about possible causes. Contact a technical support representative, and be ready to provide the list of messages and the diagnostic core dump, if requested.

TASK_ASSERT_SOFT

System Log Message	Soft assertion failed <i>executable-name</i> [<i>pid</i>]: file " <i>source-filename</i> ", line <i>line-number</i> : " <i>message</i> ", daemon continued running
Description	The source code for the process includes internal self-consistency checks. A check failed but the process continued running. It created a diagnostic core dump for analysis by technical support personnel and noted the number of the line in the source file where the check failed.
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	An internal software failure occurred.
Action	Examine the messages that immediately follow this message in the system log for information about possible causes. Contact a technical support representative, and be ready to provide the list of messages and the diagnostic core dump, if requested.

TASK_EXIT

System Log Message	Exit <i>executable-name</i> [<i>pid</i>] version <i>version</i> built by <i>builder</i> on <i>date</i> , caller <i>address</i>
Description	The process exited, either in response to a user request or because of a system error.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	ANY
Cause	A system resource was unavailable, an unexpected error occurred, or a user terminated the process.
Action	Examine the messages that immediately follow this message in the system log for information about possible causes.

TASK_LOCK_FLOCKED

System Log Message	Unable to obtain a lock on <i>filename</i> , is another copy of the process running?
---------------------------	--

Description The process could not obtain the mutual exclusion lock that prevents more than one instance from running simultaneously. The system terminated the indicated process.

Type Error: An error occurred

Severity error

Facility ANY

Cause Another process is running.

Action Use the 'show system process' command to verify that another process is running.

TASK_LOCK_LOCKED

System Log Message Unable to obtain a lock on *filename, program-name[pid]* is still running

Description The process could not obtain the mutual exclusion lock that prevents more than one instance from running simultaneously. The system terminated this instance.

Type Error: An error occurred

Severity error

Facility ANY

Cause Another process is running.

Action Use the 'show system process' command to verify that another process is running.

TASK_MGMT_TIMEOUT

System Log Message peer *peer-name* timed out waiting for input

Description Daemon timed out waiting for management input.

Type Error: An error occurred

Severity warning

Facility ANY

Action Examine the messages that immediately follow this message in the system log for information about possible causes.

Cause An internal software failure occurred.

TASK_OS_MEMHIGH

System Log Message Using *size* KB of memory, *percentage-value* percent of available

Description The process is using the indicated amount and percentage of Routing Engine memory, which is considered excessive.

Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	Either the process is leaking memory or the use of system resources is excessive.
Action	Increase the amount of RAM in the Routing Engine.

TASK_SCHED_CALLBACK_LONGRUNTIME

System Log Message	<i>function-name: excessive runtime time during action of module</i>
Description	The indicated submodule of this process ran uninterrupted for the indicated period of time, which is considered excessive.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	ANY
Cause	The duration was noted because task accounting is enabled. The function might be implemented inefficiently.

TASK_SCHED_CUMULATIVE_RUNTIME

System Log Message	<i>function-name: excessive runtime (total of time in count callbacks) after action of module</i>
Description	Several submodules of this process ran uninterrupted for the indicated period of time, which is considered excessive.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	ANY
Cause	The duration was noted because task accounting is enabled. The function might be implemented inefficiently.

TASK_SCHED_MODULE_LONGRUNTIME

System Log Message	<i>function-name: excessive runtime time during action of module</i>
Description	Several submodules of this process ran uninterrupted for the indicated period of time, which is considered excessive.
Type	Event: This message reports an event, not an error
Severity	warning
Facility	ANY

Cause The duration was noted because task accounting is enabled. The function might be implemented inefficiently.

TASK_SCHED_TASK_LONGRUNTIME

System Log Message *function-name* ran for *total-time* (*user-time* user, *system-time* system) doing *action*

Description A task callback within this process ran uninterrupted for the indicated period of time, which is considered excessive.

Type Event: This message reports an event, not an error

Severity warning

Facility ANY

Cause The duration was noted because task accounting is enabled. The function might be implemented inefficiently.

TASK_SIGNAL_TERMINATE

System Log Message termination signal no- *signal-name* received

Description In response to the indicated termination request, the process terminated and shut down.

Type Event: This message reports an event, not an error

Severity notice

Facility ANY

TASK_START

System Log Message Start *executable-name*[*pid*] version *version* built *date*

Description Process started.

Type Event: This message reports an event, not an error

Severity info

Facility ANY

TASK_SYSTEM

System Log Message *reason: error-message*

Description A system call made by this process failed.

Type Error: An error occurred

Severity error

Facility ANY

Cause It is possible that the kernel lacked the resources to fulfill the request.

TASK_TASK_BEGIN

System Log Message	Commencing virtual chassis control daemon, version <i>process-version</i> , built <i>date</i> by <i>builder</i>
Description	The process started.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	ANY

TASK_TASK_CHILDKILLED

System Log Message	<i>task-name</i> terminated by SIG <i>signal-name</i> <i>core-dump-status</i>
Description	While a child process was performing the indicated operation, it terminated in response to the indicated signal.
Type	Event: This message reports an event, not an error
Severity	error
Facility	ANY

TASK_TASK_CHILDSTOPPED

System Log Message	<i>task-name</i> stopped by SIG <i>signal-name</i>
Description	While a child process was performing the indicated operation, it stopped in response to the indicated signal.
Type	Event: This message reports an event, not an error
Severity	error
Facility	ANY

TASK_TASK_FORK

System Log Message	Unable to fork <i>task-name</i> : <i>error-message</i>
Description	This process failed to create the indicated child process.
Type	Error: An error occurred
Severity	error
Facility	ANY

TASK_TASK_GETWD

System Log Message	<i>getwd: error-message</i>
Description	The <i>getwd()</i> system call failed.
Type	Error: An error occurred

Severity	error
Facility	ANY
Cause	It is possible that the kernel lacked the resources to fulfill the request.

TASK_TASK_NOREINIT

System Log Message	Reinitialization not possible
Description	This process (VCCPD) failed to reinitialize as requested, because it was running in a state that did not allow reconfiguration.
Type	Error: An error occurred
Severity	error
Facility	ANY

TASK_TASK_PIDCLOSED

System Log Message	Unable to close and remove <i>filename: error-message</i>
Description	This process tried to close and remove the file that records its process ID (PID), which serves to prevent multiple instances from running simultaneously. The attempt failed.
Type	Error: An error occurred
Severity	error
Facility	ANY

TASK_TASK_PIDFLOCK

System Log Message	<code>flock(filename, LOCK_EX): error-message</code>
Description	This process issued the flock() system call on the file that records its process ID (PID), which serves to prevent multiple instances from running simultaneously. The system call failed.
Type	Error: An error occurred
Severity	error
Facility	ANY

TASK_TASK_PIDWRITE

System Log Message	Unable to write <i>filename: error-message</i>
Description	This process tried to write to the file that records its process ID (PID), which serves to prevent multiple instances from running simultaneously. The attempt failed.
Type	Error: An error occurred
Severity	error
Facility	ANY

TASK_TASK_REINIT

System Log Message	Reinitializing
Description	This process reinitialized.
Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

TASK_TASK_SIGNALIGNORE

System Log Message	sigaction(SIG <i>signal-name</i>): <i>error-message</i>
Description	This process informed the kernel that it wished to ignore the indicated signal, but the kernel failed to process the request.
Type	Error: An error occurred
Severity	error
Facility	ANY

TASK_TRACE_FAILED

System Log Message	Unable to write to trace file <i>filename</i>
Description	This process could not write to the indicated trace file, and stopped attempting to do so. The next commit of the configuration database will reenble tracing.
Type	Event: This message reports an event, not an error
Severity	error
Facility	ANY

CHAPTER 98

TFTPD System Log Messages

This chapter describes messages with the **TFTPD** prefix. They are generated by the Trivial FTP (TFTP) process (tnp.tftpd), which services requests from hardware components for the configuration files that they use during initialization.

TFTPD_AF_ERR

System Log Message	Unexpected address family <i>address-family-type</i>
Description	As each hardware component on the routing platform initializes, it requests its configuration file from the TFTP process (tnp.tftpd). The tnp.tftpd process exited because an incoming packet had the indicated, unexpected value in its address family (sockaddr) field.
Type	Error: An error occurred
Severity	error
Facility	ANY

TFTPD_BIND_ERR

System Log Message	bind: <i>error-message</i>
Description	Binding of a socket to an address failed due to a system error.
Type	Error: An error occurred
Severity	error
Facility	ANY

TFTPD_CONNECT_ERR

System Log Message	connect: <i>error-message</i>
Description	Connection of a socket to an address failed due to a system error.
Type	Error: An error occurred
Severity	error
Facility	ANY

TFTPD_CONNECT_INFO

System Log Message	TFTP operation from address <i>address</i> port <i>port</i> file <i>filename</i>
Description	As each hardware component on the routing platform initializes, it requests its configuration file from the TFTP process (tnp.tftpd). The process established a connection with the indicated characteristics: kind of operation (read or write), address and port connected to, and name of file transferred.
Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

TFTPD_CREATE_ERR

System Log Message	check_space <i>error-message</i>
Description	The TFTP process (tnp.tftpd) could not create a core dump file.
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	There is probably not enough free space in the file system where tnp.tftpd tried to create the file.

TFTPD_FIO_ERR

System Log Message	ioctl(FIONBIO): <i>error-message</i>
Description	The TFTP process (tnp.tftpd) could not set the standard input to be nonblocking.
Type	Error: An error occurred
Severity	error
Facility	ANY

TFTPD_FORK_ERR

System Log Message	fork: <i>error-message</i>
Description	As each hardware component on the routing platform initializes, it requests its configuration file from the TFTP process (tnp.tftpd). To service multiple clients simultaneously, tnp.tftpd calls the fork() system call to make a copy of itself for each request. The system call returned the indicated error.
Type	Error: An error occurred
Severity	error
Facility	ANY

TFTPD_NAK_ERR

System Log Message	<i>nak error error-code, error-message</i>
Description	The TFTP process (tnp.tftpd) sent a negative acknowledgment to a client because of the indicated error condition.
Type	Error: An error occurred
Severity	warning
Facility	ANY

TFTPD_OPEN_ERR

System Log Message	Unable to open file ' <i>filename</i> ', error: <i>error-message</i>
Description	The TFTP process (tnp.tftpd) could not open the indicated file because of the indicated error.
Type	Error: An error occurred
Severity	warning
Facility	ANY

TFTPD_RECVCOMPLETE_INFO

System Log Message	Received <i>count</i> blocks of <i>block-size</i> size for file ' <i>filename</i> '
Description	The TFTP process (tnp.tftpd) received the last portion of a transmitted file. This message records the number of blocks received, the block size used, and the name of the file to which the data was written.
Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

TFTPD_RECVFROM_ERR

System Log Message	<i>recvfrom: error-message</i>
Description	The TFTP process (tnp.tftpd) issued the <code>recvfrom()</code> system call when attempting to receive data from the network. The system call failed.
Type	Error: An error occurred
Severity	error
Facility	ANY

TFTPD_RECV_ERR

System Log Message	<i>recv: error-message</i>
Description	The TFTP process (tnp.tftpd) could not receive data from the network.

Type	Error: An error occurred
Severity	error
Facility	ANY

TFTPD_SENDCOMPLETE_INFO

System Log Message	Sent <i>count</i> blocks of <i>block-size</i> and 1 block of <i>size</i> for file ' <i>filename</i> '
Description	The TFTP process (tnp.tftpd) successfully sent a file. This message records the number of blocks sent, the block size used, the size of the last block, and the name of the source file.
Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

TFTPD_SEND_ERR

System Log Message	send: <i>error-message</i>
Description	The TFTP process (tnp.tftpd) could not send data.
Type	Error: An error occurred
Severity	error
Facility	ANY

TFTPD_SOCKET_ERR

System Log Message	socket: <i>error-message</i>
Description	The TFTP process (tnp.tftpd) could not open a socket for data transmission or reception.
Type	Error: An error occurred
Severity	error
Facility	ANY

TFTPD_STATFS_ERR

System Log Message	statfs <i>filename</i> , error: <i>error-message</i>
Description	The TFTP process (tnp.tftpd) issued the statfs() system call to obtain the status of the file system into which it needed to write a crash file. The system call failed with the indicated error.
Type	Error: An error occurred
Severity	error
Facility	ANY

CHAPTER 99

UFDD System Log Messages

This chapter describes messages with the **UFDD** prefix. They are generated by the Junos OS command-line interface (CLI) and management process (mgd), which together form the Junos user interface that accepts and processes input from users and client applications.

UFDD_SYSTEM_CALL_FAILED

System Log Message *reason: error-message*

Description A system call made by the uplink failure detection process (ufdd) failed.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

Cause It is possible that the kernel lacked the resources to fulfill the request.

CHAPTER 100

UI System Log Messages

This chapter describes messages with the **UI** prefix. They are generated by the Junos OS command-line interface (CLI) and management process (mgd), which together form the Junos user interface that accepts and processes input from users and client applications.

UI_AUTH_EVENT

System Log Message	Authenticated user ' <i>username</i> ' at permission level ' <i>authentication-level</i> '
Description	The management process (mgd) authenticated the indicated user.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_AUTH

UI_AUTH_INVALID_CHALLENGE

System Log Message	Received invalid authentication challenge for user ' <i>username</i> ': <i>response</i>
Description	When a user logs onto the routing platform and attempts to authenticate, the CLI and management process (mgd) use a challenge-and-response system to limit the exposure of sensitive information such as passwords and keys. The format of the challenge generated by mgd was incorrect.
Type	Error: An error occurred
Severity	error
Facility	LOG_USER
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

UI_BOOTTIME_FAILED

System Log Message	Unable to fetch boot time: <i>error-message</i>
Description	The management process (mgd) could not retrieve the system boot time from the kernel.

Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

UI_CFG_AUDIT_NEW

System Log Message	User ' <i>username</i> ' action: <i>pathname new-name</i>
Description	The indicated user created a new configuration object by copying or renaming an existing object as indicated.
Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

UI_CFG_AUDIT_OTHER

System Log Message	User ' <i>username</i> ' action: <i>pathname delimitervalue</i>
Description	The indicated user deleted, activated, or deactivated a configuration object, as indicated. The JUNOS configuration log facility logged the change.
Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

UI_CFG_AUDIT_SET

System Log Message	User ' <i>username</i> ' action: <i>pathname delimiterdata -> "value"</i>
Description	The indicated user set a value for a configuration object, as indicated.
Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

UI_CFG_AUDIT_SET_SECRET

System Log Message	User ' <i>username</i> ' action: <i>pathname</i>
Description	The indicated user set a value for a configuration object, as indicated. For security, the actual value (which might be an authentication key or password, for example) is not recorded.
Type	Event: This message reports an event, not an error

Severity info
Facility ANY

UI_CHILD_ARGS_EXCEEDED

System Log Message Too many arguments for child process '*command*'

Description The management process (mgd) invokes some commands on behalf of users. It supplied more arguments than the command's syntax statement specifies.

Type Error: An error occurred

Severity error

Facility ANY

Cause An internal software failure occurred.

Action Contact your technical support representative.

UI_CHILD_CHANGE_USER

System Log Message Unable to switch to local user: *username*

Description The management process (mgd) invokes some commands on behalf of users. Its attempt to adopt the UID of the indicated user failed.

Type Error: An error occurred

Severity error

Facility ANY

Cause An internal software failure occurred.

Action Contact your technical support representative.

UI_CHILD_EXEC

System Log Message Child exec failed for command '*command*': *error-message*

Description The management process (mgd) invoked the exec() system call while creating a child processes to execute the indicated command on its behalf. The system call failed.

Type Error: An error occurred

Severity error

Facility ANY

Cause An internal software failure occurred.

Action Contact your technical support representative.

UI_CHILD_EXITED

System Log Message	Child exited: PID <i>pid</i> , status <i>return-value</i> <i>core-dump-status</i> , command ' <i>command</i> '
Description	The management process (mgd) created a child process to execute the indicated command for it. The child process exited unexpectedly with the indicated status code.
Type	Error: An error occurred
Severity	notice
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

UI_CHILD_FOPEN

System Log Message	Unable to append to log ' <i>filename</i> ': <i>error-message</i>
Description	The management process (mgd) attempted to save the output from a command in the indicated log file, but could not open the file.
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

UI_CHILD_OUTPUT

System Log Message	Child output: <i>message</i>
Description	The management process (mgd) spawned a child process that output some messages that were requested to be hidden but which need to be logged for informational purposes.
Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

UI_CHILD_PIPE_FAILED

System Log Message	Unable to create pipe for command ' <i>command</i> ': <i>error-message</i>
Description	The management process (mgd) created a child process to execute the indicated command for it. Its attempt to create pipes for communication with the child process failed.

Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

UI_CHILD_STOPPED

System Log Message	Child stopped: PID <i>pid</i> , signal= <i>signal-name</i> core-dump-status, command=' <i>command</i> ')
Description	The management process (mgd) created a child process to execute the indicated command for it. The child process received the indicated signal and stopped.
Type	Error: An error occurred
Severity	notice
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

UI_CHILD_WAITPID

System Log Message	waitpid failed: PID <i>pid</i> , rc <i>return-value</i> , status <i>status-code</i> : <i>error-message</i>
Description	The management process (mgd) created a child process to execute a command for it. It could not wait for the child process to finish.
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

UI_CMDLINE_READ_LINE

System Log Message	User ' <i>username</i> ', command ' <i>command</i> '
Description	The indicated user typed the indicated command at the CLI prompt and pressed the Enter key, sending the command string to the management process (mgd).
Type	Event: This message reports an event, not an error
Severity	info

Facility LOG_AUTH

UI_CMD_AUTH_REGEX_INVALID

System Log Message Invalid '*allow-deny*' command authorization regular expression '*regular-expression*': *error-message*

Description An operation that attempted to set command or configuration authorization included the indicated regular expression. The operation failed because the expression syntax was invalid.

Type Error: An error occurred

Severity error

Facility ANY

Action Correct any errors in the regular expression.

UI_COMMIT

System Log Message User '*username*' requested '*command*' operation (comment: *message*)

Description The indicated user requested the indicated type of commit operation on the candidate configuration and added the indicated comment. The 'commit' operation applies to the local Routing Engine and the 'commit synchronize' operation to both Routing Engines.

Type Event: This message reports an event, not an error

Severity notice

Facility ANY

UI_COMMIT_AT_ABORT

System Log Message *reason*, will try again

Description An attempt to complete a pending commit operation was cancelled for the indicated reason.

Type Error: An error occurred

Severity error

Facility ANY

UI_COMMIT_AT_COMPLETED

System Log Message 'commit at' was successful

Description Changes to the candidate configuration were activated at the time scheduled by a 'commit at' operation.

Type Event: This message reports an event, not an error

Severity notice

Facility ANY

UI_COMMIT_AT_FAILED

System Log Message *reason*, scheduled commit cleared

Description A 'commit at' operation did not complete, for the indicated reason.

Type Error: An error occurred

Severity error

Facility ANY

UI_COMMIT_COMPRESS_FAILED

System Log Message Unable to compress file '*filename*'

Description As part of committing a new configuration, the management process (mgd) compresses and saves a copy of the configuration. mgd saved the configuration file in regular format because it could not compress it.

Type Error: An error occurred

Severity error

Facility ANY

Cause The Routing Engine is low on resources.

Cause An internal software failure occurred.

Action Contact your technical support representative.

UI_COMMIT_CONFIRMED_REMINDER

System Log Message 'commit confirmed' must be confirmed within *duration* minutes

Description A 'commit confirmed' operation has activated the candidate configuration temporarily. If the commit is not confirmed within the indicated number of minutes (for example, by the command-line interface (CLI) 'commit' command), the management process (mgd) will roll back to the previous configuration.

Type Event: This message reports an event, not an error

Severity notice

Facility ANY

UI_COMMIT_EMPTY_CONTAINER

System Log Message Skipped empty object '*node-name*'

Description Some container objects are marked for automatic removal from the configuration hierarchy if they are empty when the user who created them changes to the top ([edit]) level of the hierarchy or exits configuration mode. While committing the candidate

configuration, the management process (mgd) encountered such an object that was empty but not removed.

Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY
Cause	When the commit operation began, the user who created the new container object had not populated it and was in configuration mode but not at the top level of the hierarchy.
Action	Populate or remove the empty object before committing the configuration. The user who created the object can remove it by exiting configuration mode or issuing the 'top' command to move to the top level of the hierarchy.

UI_COMMIT_NOT_CONFIRMED

System Log Message Commit was not confirmed; *message*

Description The 'commit confirmed' operation commits a configuration but requires confirmation within a defined number of minutes for the commit to become permanent. If the commit is not confirmed (by the 'commit' command, for example), the management process (mgd) automatically rolls back to the previously committed configuration. The automatic rollback restores management access to the routing platform in case an error in the configuration blocks access.

Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_AUTH

UI_COMMIT_PREV_CNF_SAVED

System Log Message Previously committed configuration saved to *filename*

Description In case automatic rollback of unconfirmed commit fails, previously committed configuration is saved up for further inspection.

Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_AUTH

Cause The cause of the problem might be recorded in messages that precede this message in the system log.

UI_COMMIT_PROGRESS

System Log Message Commit operation in progress: *message*

Description As it performed a commit operation, the management process (mgd) recorded its execution of the indicated step.

Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

UI_COMMIT_ROLLBACK_FAILED

System Log Message Automatic rollback failed

Description The 'commit confirmed' operation commits a configuration but requires confirmation within a defined number of minutes for the commit to become permanent. If the commit is not confirmed (by the 'commit' command, for example), the management process (mgd) automatically rolls back to the previously committed configuration. The 'commit confirmed' operation was not confirmed, but mgd could not roll back the configuration. The configuration might be in an indeterminate state.

Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH
Cause	The cause of the problem might be recorded in messages that precede this message in the system log.

UI_COMMIT_SYNC_FORCE

System Log Message All logins to local configuration database were terminated because forced 'commit synchronize' operation was invoked on other Routing Engine

Description The 'commit synchronize force' command was issued on the other Routing Engine on the router. All login sessions in the local configuration database were terminated and the configuration from the other Routing Engine was committed on the local Routing Engine.

Type	Event: This message reports an event, not an error
Severity	notice
Facility	ANY

UI_CONFIGURATION_ERROR

System Log Message Process: *process-name*, path: *pathname*, statement: *configuration-statement*, *error-message*

Description The indicated process found a problem in its configuration.

Type	Error: An error occurred
Severity	error
Facility	ANY

UI_CONFIGURATION_WARNING

System Log Message	Process: <i>process-name</i> , path: <i>pathname</i> , statement: <i>configuration-statement</i> , <i>warning-message</i>
Description	The indicated process found a problem in its configuration.
Type	Error: An error occurred
Severity	warning
Facility	ANY

UI_DAEMON_ACCEPT_FAILED

System Log Message	<i>connection-type</i> socket connection accept failed: <i>error-message</i>
Description	The management process (mgd) did not accept an incoming connection request.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

UI_DAEMON_FORK_FAILED

System Log Message	Unable to create session child: <i>error-message</i>
Description	The management process (mgd) invokes the fork() system call to create a copy of itself for each CLI session. The system call failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

UI_DAEMON_SELECT_FAILED

System Log Message	select failed: <i>error-message</i>
Description	The management process (mgd) uses the select() system call to listen for incoming connection requests on a socket. The system call failed.
Type	Error: An error occurred

Severity	error
Facility	LOG_AUTH
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

UI_DAEMON_SOCKET_FAILED

System Log Message	<i>connection-type</i> socket create failed: <i>error-message</i>
Description	The management process (mgd) uses sockets to communicate with other Junos OS processes running on the routing platform. It could not allocate a socket.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH
Cause	System resources are exhausted.
Action	Contact your technical support representative.

UI_DBASE_ACCESS_FAILED

System Log Message	Unable to reaccess configuration database file ' <i>filename</i> ', address <i>address</i> , size <i>size</i> : <i>reason</i>
Description	To increase the size of the configuration database, the management process (mgd) must unmap the database from its address space, change the database size, and remap the database. The remapping operation failed.
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

UI_DBASE_CHECKOUT_FAILED

System Log Message	Database ' <i>filename</i> ' is out of data and needs to be rebuilt
Description	When the routing platform boots, the management process (mgd) checks the configuration database for internal consistency. It found one or more inconsistencies.
Type	Event: This message reports an event, not an error
Severity	alert

Facility	ANY
Cause	mgd restarted after new JUNOS software was installed.
Action	None; mgd will rebuild the database.

UI_DBASE_EXTEND_FAILED

System Log Message	Unable to extend configuration database file ' <i>filename</i> ' to size <i>requested-size</i> : <i>reason</i>
Description	The management process (mgd) could not increase the configuration database to the indicated size.
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	The hard disk is defective or is not installed in the routing platform.
Action	Repair or replace the hard disk.
Cause	There is insufficient disk space on the /var partition on the hard disk.
Action	Delete user files from the /var/homes directory to increase the available disk space.

UI_DBASE_LOGIN_EVENT

System Log Message	User ' <i>username</i> ' entering configuration mode
Description	The indicated user entered configuration mode (logged into the configuration database).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	ANY

UI_DBASE_LOGOUT_EVENT

System Log Message	User ' <i>username</i> ' exiting configuration mode
Description	The indicated user exited configuration mode (logged out of the configuration database).
Type	Event: This message reports an event, not an error
Severity	notice
Facility	ANY

UI_DBASE_MISMATCH_EXTENT

System Log Message	Database header extent mismatch for file ' <i>filename</i> ': expecting <i>expected-value</i> , got <i>received-value</i>
---------------------------	---

Description	The header in the configuration database records the highest address allocated in the database. The management process (mgd) discovered that the highest address actually allocated in the database does not match the header value.
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	The database file is corrupted.
Action	Contact your technical support representative.

UI_DBASE_MISMATCH_MAJOR

System Log Message	Database header major version number mismatch for file ' <i>filename</i> ': expecting <i>expected-value</i> , got <i>received-value</i>
Description	For compatibility, the version number recorded in the header of the configuration database must match the version of JUNOS software running on the routing platform. The management process (mgd) discovered that the major parts (for example, '5' in '5.x') of the version numbers do not match.
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	A recent software upgrade did not complete successfully.
Action	Issue the 'show version' command to check the JUNOS version. If necessary, issue the 'request system reboot' command to reboot the routing platform and complete the software installation.
Cause	The database file is corrupted.
Action	Contact your technical support representative.

UI_DBASE_MISMATCH_MINOR

System Log Message	Database header minor version number mismatch for file ' <i>filename</i> ': expecting <i>expected-value</i> , got <i>received-value</i>
Description	For compatibility, the version number recorded in the header of the configuration database must match the version of JUNOS software running on the routing platform. The management process (mgd) discovered that the minor parts (for example, '2' in 'x.2') of the version numbers do not match.
Type	Error: An error occurred

Severity	error
Facility	ANY
Cause	A recent software upgrade did not complete successfully.
Action	Issue the 'show version' command to check the JUNOS version. If necessary, issue the 'request system reboot' command to reboot the routing platform and complete the software installation.
Cause	The database file is corrupted.
Action	Contact your technical support representative.

UI_DBASE_MISMATCH_SEQUENCE

System Log Message	Database header sequence numbers mismatch for file ' <i>filename</i> '. If a package has just been added or deleted, please verify and commit the configuration.
Description	The header of the configuration database records the version number of the configuration schema (possible set of statements) used when the database was created. To prevent corruption, all JUNOS processes that access the database must use the same schema. The management process (mgd) discovered that the version number for the JUNOS software installed on the routing platform does not match the header value.
Type	Error: An error occurred
Severity	warning
Facility	ANY
Cause	A recent software upgrade did not complete successfully.
Action	Issue the 'show version' command to check the JUNOS version. If necessary, issue the 'request system reboot' command to reboot the routing platform and complete the software installation.
Cause	The database file is corrupted.
Action	Contact your technical support representative.

UI_DBASE_MISMATCH_SIZE

System Log Message	Database header size mismatch for file ' <i>filename</i> ': expecting <i>expected-value</i> x, got <i>received-value</i>
Description	The header of the configuration database records the database size. The management process (mgd) discovered that the size of the actual database file does not match the header value.
Type	Error: An error occurred

Severity	error
Facility	ANY
Cause	The database file is corrupted.
Action	Contact your technical support representative.

UI_DBASE_OPEN_FAILED

System Log Message	Database open failed for file ' <i>filename</i> ': <i>reason</i>
Description	The management process (mgd) could not open the indicated configuration database file.
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	The database file does not exist.
Action	Select a different filename or create a new configuration.
Cause	The /config directory does not have sufficient space for a new database.
Action	Remove files from the /config directory to make more space available.

UI_DBASE_REBUILD_FAILED

System Log Message	<i>modeusername</i> rebuild of the database ' <i>filename</i> ' failed
Description	The management process (mgd) could not rebuild the configuration database file.
Type	Error: An error occurred
Severity	alert
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

UI_DBASE_REBUILD_SCHEMA_FAILED

System Log Message	Automatic rebuild of the database failed
Description	The management process (mgd) could not rebuild the schema for the configuration database.
Type	Error: An error occurred

Severity	alert
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

UI_DBASE_REBUILD_STARTED

System Log Message	<i>modeusername</i> rebuild/rollback of the database ' <i>filename</i> ' started
Description	The management process (mgd) began to rebuild the configuration database file or its schema because that object was not current. The operation will complete shortly.
Type	Event: This message reports an event, not an error
Severity	alert
Facility	ANY

UI_DBASE_RECREATE

System Log Message	User ' <i>username</i> ' attempting database re-creation
Description	The management process (mgd) discovered that the version of JUNOS software running on the routing platform does not match the version of the current configuration database. In response to a prompt from mgd, the indicated user initiated a rebuilding of the database.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	ANY

UI_DBASE_REOPEN_FAILED

System Log Message	Reopen of the database failed
Description	After rebuilding the schema file for the configuration database, the management process (mgd) closes the file and reopens it in read-only mode to prevent corruption. It could not reopen the file.
Type	Error: An error occurred
Severity	alert
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

UI_DUPLICATE_UID

System Log Message	Users <i>username1</i> and <i>username2</i> have the same UID <i>uid</i>
---------------------------	--

Description The JUNOS software allows multiple user login accounts to share the same UID. This message was logged in case site policy dictates that users should not share UIDs.

Type Event: This message reports an event, not an error

Severity notice

Facility ANY

Action Assign different UIDs to the affected users.

UI_FACTORY_OPERATION

System Log Message Committing factory default configuration because CONFIG button was pressed and held

Description The management process (mgd) began a commit operation to activate the factory default configuration, because the CONFIG button on the chassis was pressed and held for 15 seconds or more.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_AUTH

UI_INITIALSETUP_OPERATION

System Log Message Committing EZsetup configuration as EZsetup option is chosen

Description The management process (mgd) began a commit operation to activate the pre initial setup configuration, because the initial-setup option was selected from the LCD Menu.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_AUTH

UI_INVALID_REMOTE_PERMISSION

System Log Message invalid permissions from authorization server: *permission-name*

Description RADIUS and TACACS+ authorization servers use Juniper Networks vendor-specific attributes (VSAs) to specify user permissions. A VSA included the indicated permission name, which is invalid.

Type Error: An error occurred

Severity error

Facility ANY

UI_JUNOSCRIPT_CMD

System Log Message User '*username*' used JUNOScript client to run command '*command*'

Description The indicated user ran the indicated command using the JUNOS XML management protocol.

Type Event: This message reports an event, not an error

Severity info

Facility LOG_AUTH

UI_JUNOSCRIPT_ERROR

System Log Message JUNOScript error: *error-message*

Description The management process (mgd) normally sends an error message to the JUNOS CLI or JUNOScript API client in an <xnm:error> tag. It could not send the tag, so it sent the indicated error message in an XML comment instead.

Type Error: An error occurred

Severity warning

Facility ANY

UI_LCC_NO_MASTER

System Log Message No master Routing Engine defined for LCC/cc

Description By default, the Junos OS installed on the TX Matrix platform in a routing matrix is automatically copied to and installed on all T640 routing nodes in the routing matrix. The software was not installed on the indicated T640 routing node (line-card chassis, or LCC), because the management process (mgd) on the TX Matrix platform could not determine which Routing Engine on the LCC was the master.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

Action Resolve the mastership situation on the T640 routing node and install the software on its Routing Engines.

UI_LOAD_EVENT

System Log Message User '*username*' is performing a '*operation*'

Description The indicated user requested the indicated operation ('rollback, ' or 'load' or one of its variants) on the configuration database. The existing configuration database was deleted and a new database was created based on a text file.

Type Event: This message reports an event, not an error

Severity notice

Facility ANY

UI_LOAD_JUNOS_DEFAULT_FILE_EVENT

System Log Message	Loading the default config from <i>pathname</i>
Description	The system is loading junos default configuration from file.
Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

UI_LOGIN_EVENT

System Log Message	User ' <i>username</i> ' login, class ' <i>class-name</i> ' <i>local-peer[pid]</i> , ssh-connection ' <i>ssh-connection</i> ', client-mode ' <i>client-mode</i> '
Description	The indicated user started a JUNOS CLI session.
Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

UI_LOGOUT_EVENT

System Log Message	User ' <i>username</i> ' logout
Description	The indicated user exited from a JUNOS CLI session.
Type	Event: This message reports an event, not an error
Severity	info
Facility	ANY

UI_LOST_CONN

System Log Message	Lost connection to daemon ' <i>process-name</i> '
Description	The management process (mgd) uses sockets to communicate with other JUNOS software processes. The socket it was using for the indicated process closed prematurely.
Type	Error: An error occurred
Severity	error
Facility	ANY
Cause	An internal software failure occurred.
Action	Contact your technical support representative.

UI_MASTERSHIP_EVENT

System Log Message	<i>mastership-event card-name</i> mastership by ' <i>username</i> '
---------------------------	---

Description Some redundant routing platform components use a master/standby system in which the master component is active and the standby is inactive but ready to assume mastership. The indicated user performed the indicated operation to modify component mastership.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_AUTH

UI_MOTD_PROPAGATE_ERROR

System Log Message Unable to propagate login announcement (motd) to *pathname*

Description The management process (mgd) could not create or write to the indicated file, which was the intended location for the message of the day (MOTD) configured at the [edit system login announcement] hierarchy level.

Type Error: An error occurred

Severity error

Facility ANY

UI_NETCONF_CMD

System Log Message User '*username*' used NETCONF client to run command '*command*'

Description The indicated user ran the indicated command using the NETCONF application programming interface (API).

Type Event: This message reports an event, not an error

Severity info

Facility LOG_AUTH

UI_NETCONF_ERROR

System Log Message NETCONF error: *error-message*

Description The management process (mgd) normally sends error messages to the NETCONF client in the <rpc-error> tag element. It could not send that tag element, and instead sent the indicated error message in an XML comment.

Type Error: An error occurred

Severity warning

Facility ANY

UI_PARSE_JUNOSCRIPT_ATTRIBUTES

System Log Message Error parsing attributes in client *junoscript* tag

Description The management process (mgd) encountered an error and exited while attempting to parse the XML attributes in the <junoscript> tag submitted by a client application.

Type Error: An error occurred

Severity error

Facility LOG_AUTH

UI_READ_FAILED

System Log Message read failed for peer *peer-name*: *error-message*

Description The management process (mgd) uses the read() system call to access data sent by other JUNOS processes running on the routing platform (referred to as its peers). The system call failed for the indicated process.

Type Error: An error occurred

Severity error

Facility ANY

Cause An internal software failure occurred.

Action Contact your technical support representative.

UI_READ_TIMEOUT

System Log Message Timeout on read of peer '*peer-name*'

Description When communicating with other JUNOS processes running on the routing platform (referred to as peers), the management process (mgd) waits only a defined period for responses to arrive. The timeout period passed for the indicated process.

Type Event: This message reports an event, not an error

Severity notice

Facility ANY

UI_REBOOT_EVENT

System Log Message System *halt-reboot* by '*username*'

Description The indicated software process restarted as requested by the indicated user.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_AUTH

UI_RESCUE_OPERATION

System Log Message Committing rescue configuration because CONFIG button was pressed

Description The management process (mgd) began a commit operation to activate the rescue configuration, because the CONFIG button on the chassis was pressed.

Type Event: This message reports an event, not an error

Severity notice

Facility LOG_AUTH

UI_RESTART_EVENT

System Log Message User '*username*' restarting daemon '*process-name*'*description*

Description The indicated software process restarted as requested by the indicated user.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_AUTH

UI_SCHEMA_CHECKOUT_FAILED

System Log Message Schema is out of date and needs to be rebuilt

Description The JUNOS user interface schema file records all CLI commands and configuration statements available in the JUNOS software. While initializing, the new management process (mgd) determined that the schema's sequence number means that the schema is incompatible with the JUNOS software installed on the routing platform.

Type Error: An error occurred

Severity alert

Facility ANY

Cause The schema is out of date.

Action None; mgd will rebuild the schema based on the current JUNOS version.

UI_SCHEMA_MISMATCH_MAJOR

System Log Message Schema major version mismatch for package *package-name* (*expected-value* vs. *received-value*)

Description The JUNOS user interface schema file records all CLI commands and configuration statements available in the JUNOS software. While initializing, the management process (mgd) discovered that the major part (for example, '5' in '5.x') of the schema version number does not match the major version number of the JUNOS software installed on the routing platform. The mismatch could lead to corruption of the configuration database.

Type Error: An error occurred

Severity error

Facility ANY

Cause The schema is incompatible with the installed JUNOS software.

Action None; mgd will rebuild the schema based on the current JUNOS version.

Cause An internal software failure occurred.

Action Contact your technical support representative.

UI_SCHEMA_MISMATCH_SEQUENCE

System Log Message Schema header sequence numbers mismatch for package *package-name*

Description The JUNOS user interface schema file records all CLI commands and configuration statements available in the JUNOS software. Schema sequence numbers serve as a checksum of the configuration data schema and ensure that the software used to access the database understands the data. The value in the database file did not match the expected value.

Type Error: An error occurred

Severity error

Facility ANY

Cause The JUNOS software installation did not succeed, possibly because of an internal software error.

Action Contact your technical support representative.

UI_SCHEMA_SEQUENCE_ERROR

System Log Message Schema sequence number mismatch

Description The JUNOS user interface schema file records all CLI commands and configuration statements available in the JUNOS software. The management process (mgd) rebuilds the schema as necessary to be compatible with the JUNOS software installed on the routing platform. A sequence number in the schema acts as a checksum that represents its content and format. A JUNOS process attempted to access the schema but determined that the schema's sequence number means that it is incompatible with the process.

Type Error: An error occurred

Severity alert

Facility ANY

Cause An internal software failure occurred.

Action Contact your technical support representative.

UI_TACPLUS_ERROR

System Log Message	TACACS+ failure: <i>error-message</i>
Description	The management process (mgd) failed to send a record to TACACS+.
Type	Error: An error occurred
Severity	notice
Facility	LOG_AUTH

UI_VERSION_FAILED

System Log Message	Unable to fetch system version: <i>error-message</i>
Description	The management process (mgd) could not retrieve version information from the kernel.
Type	Error: An error occurred
Severity	error
Facility	ANY
Action	Contact your technical support representative.

UI_WRITE_RECONNECT

System Log Message	Re-establishing connection to peer ' <i>peer-name</i> '
Description	The management process (mgd) reconnected to the indicated JUNOS process running on the routing platform.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	ANY

UTMD System Log Messages

This chapter describes messages with the **UTMD** prefix. They are generated by the unified threat management process (utmd) which protects the network from all types of attack.

UTMD_MALLOC_FAILURE

System Log Message	Out of memory. Unable to malloc <i>error-message</i> bytes
Description	The example process (utmd) could not allocate memory for a resource possibly due to lack of memory
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

UTMD_SSAMLIB_FAILURE

System Log Message	ssamlib call returned error : <i>error-message</i>
Description	The example process (utmd) encountered an error while calling a function or from a callback of the ssamlib library.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

CHAPTER 102

VCCPD System Log Messages

This chapter describes messages with the **VCCPD** prefix. They are generated by the virtual chassis control protocol (vccpd) process which exchanges link-state advertisement based discovery messages between all the packet forwarding engines (PFE) through the virtual chassis ports (VCP).

VCCPD_KNL_VERSION

System Log Message	Routing socket version mismatch (kernel <i>kernel-version</i> != vccpd <i>version</i>) -- kernel upgrade required
Description	The virtual chassis control protocol process (VCCPD) discovered that the kernel does not support the version of routing sockets it requires.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	The kernel version is older than the VCCPD version.
Action	Upgrade the kernel package.

VCCPD_KNL_VERSIONNONE

System Log Message	Routing socket message type <i>message-type</i> 's version is not supported by kernel, expected <i>version</i> -- kernel upgrade required
Description	The virtual chassis control protocol process (VCCPD) discovered that the kernel does not support the routing socket message types that it requires.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	The kernel version is older than the VCCPD version.
Action	Upgrade the kernel package.

VCCPD_KNL_VERSIONOLD

System Log Message	Routing socket message type <i>message-type</i> 's version is older than expected (<i>kernel-version</i> < <i>version</i>) -- consider upgrading the kernel
Description	The virtual chassis control protocol process (VCCPD) discovered that the kernel uses an older version of routing socket message types than it does.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	The kernel version is older than the VCCPD version.
Action	Upgrade the kernel package.

VCCPD_PROTOCOL_ADJDOWN

System Log Message	Lost adjacency to <i>neighbor-system-ids</i> on <i>interface-name</i> ,
Description	A virtual chassis adjacency with the indicated neighboring switch was terminated. The local switch no longer exchanges information with the neighboring switch.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_DAEMON
Cause	The communication path to the neighboring switch was disrupted, a protocol error occurred, or the neighboring switch was powered down.

VCCPD_PROTOCOL_ADJUP

System Log Message	New adjacency to <i>neighbor-system-ids</i> on <i>interface-name</i>
Description	A virtual chassis adjacency was established with the indicated neighboring switch. The local switch can now exchange information with it.
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_DAEMON

VCCPD_PROTOCOL_LSPCKSUM

System Log Message	LSP checksum error, interface <i>interface-name</i> , LSP id <i>lspl</i> , sequence <i>sequence-number</i> , checksum <i>checksum</i> , lifetime <i>duration</i>
Description	The indicated vccpd link-state PDU (LSP) failed an internal checksum validity test, implying that it was corrupted.

Type	Error: An error occurred
Severity	warning
Facility	LOG_DAEMON
Cause	The packet was corrupted in transit between the neighboring switch and this switch, or memory on one of the switches was corrupted.
Action	None, unless a large number of these messages appear in the system log file. The corrupted LSP is purged from the virtual chassis and sent again by the originator.

VCCPD_PROTOCOL_OVERLOAD

System Log Message	vccpd database overload
Description	The vccpd link-state database is full and no additional memory can be allocated for it.
Type	Error: An error occurred
Severity	alert
Facility	LOG_DAEMON
Cause	No additional memory is available for storing vccpd link-state information. Either system resources are exhausted or a software error occurred (such as a memory leak).
Action	Perform one or more of the following actions: (1) Check for unusually high memory usage by vccpd, (2) Add more memory to the switch.

VCCPD_SYSTEM

System Log Message	<i>reason: error-message</i>
Description	A system call made by this process failed.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON
Cause	It is possible that the kernel lacked the resources to fulfill the request.

CHAPTER 103

VRRPD System Log Messages

This chapter describes messages with the **VRRPD** prefix. They are generated by the Virtual Router Redundancy Protocol (VRRP) process (vrrpd), which provides the user interface for management of VRRP groups.

VRRPD_ADVERT_TIME_MISMATCH

System Log Message	Packet received by <i>interface-name</i> for VRRP group <i>vrrp-group-id</i> had advertisement time <i>received-value</i> ms instead of required <i>expected-value</i> ms
Description	A Virtual Routing Redundancy Protocol (VRRP) advertisement packet received by the indicated interface for the indicated VRRP group specified an advertisement-timer value different from the value configured for the interface and group. The advertisement interval must be the same on all routing platforms in the VRRP group. For VRRP with IPv4, the value is set by the 'advertise-interval <seconds>' or 'fast-interval <milliseconds>' statement at the [edit interfaces <interface-name> unit <logical-unit-number> family inet address <address> vrrp-group <group-number>] hierarchy level. For VRRP with IPv6, the value is set by the 'inet6-advertise-interval <seconds>' or 'fast-interval <milliseconds>' statement at the [edit interfaces <interface-name> unit <logical-unit-number> family inet6 address <address> vrrp-inet6-group <group-number>] hierarchy level.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

VRRPD_AUTH_INFO_INVALID

System Log Message	VRRP ad packet from <i>ip-address</i> received by interface <i>interface-name.interface-unit</i> for group <i>vrrp-group-id</i> was invalid: <i>error-message</i>
Description	The Virtual Routing Redundancy Protocol (VRRP) advertisement packet sent from the indicated IP address and received by the VRRP process (vrrpd) for the indicated group at the indicated address contained invalid authentication information. The message 'invalid-authentication-type' means that the packet specifies an authentication type that is not defined in RFC 2338, Virtual Router Redundancy Protocol. The message 'authentication-type-mismatch' means that the packet specifies an authentication type different from the type used by the interface that received the packet. The message

'authentication-key-mismatch' means that the authentication key in the packet is incorrect.

Type Error: An error occurred
Severity warning
Facility LOG_DAEMON

VRRPD_GET_TRAP_HEADER_FAILED

System Log Message Request for trap signature header failed

Description The Virtual Routing Redundancy Protocol (VRRP) process requested the signature header for an SNMP trap. The request failed.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON
Cause An internal software failure occurred.

VRRPD_LINK_LOCAL_ADD_MISMATCH

System Log Message Link-Local Address Mismatch: *received-value expected-value*

Description The indicated interface received a Virtual Routing Redundancy protocol (VRRP) packet for the indicated VRRP group in which the link-local address was different from the one configured for the group and interface

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

VRRPD_MISSING_VIP

System Log Message Packet received by *interface-name* for VRRP group *vrrp-group-id* did not include required virtual IP address *ip-address*

Description The indicated interface received a Virtual Routing Redundancy protocol (VRRP) packet for the indicated VRRP group in which the list of virtual IP addresses did not include the indicated address. For VRRP with IPv4, the list is defined by the 'virtual-address [<addresses>]' statement at the [edit interfaces <interface-name> unit <logical-unit-number> family inet address <address> vrrp-group <group-number>] hierarchy level. For VRRP with IPv6, the list is defined by the 'virtual-inet6-address [<addresses>]' statement at the [edit interfaces <interface-name> unit <logical-unit-number> family inet6 address <address> vrrp-inet6-group <group-number>] hierarchy level.

Type Error: An error occurred

Severity error
Facility LOG_DAEMON

VRRPD_NEW_BACKUP

System Log Message Interface *interface-name.interface-unit* (local address *interface-address*) became VRRP backup for group *vrrp-group-id*

Description The indicated interface became the Virtual Routing Redundancy Protocol (VRRP) backup for the indicated VRRP group. The VRRP process (vrrpd) stopped sending VRRP advertisements for the virtual IP address on the interface that corresponds to the group.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

VRRPD_NEW_MASTER

System Log Message Interface *interface-name.interface-unit* (local address *interface-address*) became VRRP master for group *vrrp-group-id*

Description The indicated interface became the Virtual Routing Redundancy Protocol (VRRP) master for the indicated VRRP group. The VRRP process (vrrpd) started sending VRRP advertisements for the virtual IP address on the interface that corresponds to the group.

Type Event: This message reports an event, not an error

Severity warning

Facility LOG_DAEMON

VRRPD_VIP_COUNT_MISMATCH

System Log Message Packet received by *interface-name* for VRRP group *vrrp-group-id* had *received-value* virtual IP addresses instead of required *expected-value*

Description The indicated interface received a Virtual Routing Redundancy Protocol (VRRP) packet for the indicated VRRP group in which the number of virtual IP addresses was different from the number of addresses configured for the group and interface. The list of addresses must be the same on all routing platforms in a VRRP group. For VRRP with IPv4, the list is defined by the 'virtual-address [<addresses>]' statement at the [edit interfaces <interface-name> unit <logical-unit-number> family inet address <address> vrrp-group <group-number>] hierarchy level. For VRRP with IPv6, the list is defined by the 'virtual-inet6-address [<addresses>]' statement at the [edit interfaces <interface-name> unit <logical-unit-number> family inet6 address <address> vrrp-inet6-group <group-number>] hierarchy level.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

VSYSD System Log Messages

This chapter describes messages with the **VSYSD** prefix. They are generated by the virtual system process (vsysd) process which controls virtual systems.

VSYSD_INIT_FAILED

System Log Message	Unable to find root virtual system
Description	The virtual system process (vsysd) did not initialize, because it could not find the root virtual system.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

WEB System Log Messages

This chapter describes messages with the **WEB** prefix. They are generated by the Hypertext Transfer Protocol process (httpd), which provides a graphical user interface (GUI) for monitoring and configuring J Series Services Routers.

WEB_AUTH_FAIL

System Log Message	Unable to authenticate httpd client (username <i>username</i>)
Description	The checklogin authentication process could not authenticate the indicated user.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_AUTH

WEB_AUTH_SUCCESS

System Log Message	Authenticated httpd client (username <i>username</i>)
Description	The checklogin authentication process authenticated the indicated user.
Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_AUTH

WEB_AUTH_TIME_EXCEEDED

System Log Message	Login attempt exceeded maximum processing time
Description	The checklogin process halted a login attempt because it took longer than the maximum processing time allowed.
Type	Error: An error occurred
Severity	error
Facility	LOG_AUTH

WEB_CERT_FILE_NOT_FOUND

System Log Message	Could not find certificate file ' <i>filename</i> ', disabling HTTPS
---------------------------	--

Description http-gk could not open the configured HTTPS certificate for reading.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

WEB_CHILD_STATE

System Log Message Unable to retrieve child state: *error-message*

Description The Web management process (httpd) could not retrieve state information for a child process that had exited, for the indicated reason.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

WEB_CONFIG_OPEN_ERROR

System Log Message Could not open '*filename*' for writing

Description httpd-gk could not open the web server configuration file for writing.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

WEB_CONFIG_WRITE_ERROR

System Log Message Could not write '*filename*' configuration. Disk full?

Description httpd-gk could not write the web server configuration file to disk.

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

WEB_COULDNT_START_HTTPD

System Log Message Could not fork httpd process!

Description The Web management gatekeeper process (httpd-gk) could not start the web management process (httpd).

Type Error: An error occurred

Severity error

Facility LOG_DAEMON

WEB_EVENTLIB_INIT

System Log Message	Unable to initialize event library: <i>error-message</i>
Description	The Web management gatekeeper process (httpd-gk) attempted to initialize the event library during startup. The attempt failed for the indicated reason.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

WEB_KEYPAIR_FILE_NOT_FOUND

System Log Message	Could not find key pair file ' <i>filename</i> ', disabling HTTPS
Description	http-gk could not open the configured HTTPS key pair file for reading.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

WEB_MGD_BIND_ERROR

System Log Message	Could not bind mgd listener socket: <i>error-message</i>
Description	The web management process could not open the MGD listening socket.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

WEB_MGD_CHMOD_ERROR

System Log Message	Could not chmod mgd listener socket
Description	The web management process could not change the MGD listening socket to proper file permissions.
Type	Error: An error occurred
Severity	error
Facility	LOG_DAEMON

WEB_MGD_CONNECT_ERROR

System Log Message	Could not connect to mgd management socket
Description	The web management process could not connect to the MGD management socket.
Type	Error: An error occurred

Severity error
Facility LOG_DAEMON

WEB_MGD_FCNTL_ERROR

System Log Message Could not set incoming mgd request to nonblocking
Description The web management process could not set the MGD listening socket to nonblocking.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

WEB_MGD_LISTEN_ERROR

System Log Message Could not listen mgd listener socket: *error-message*
Description The web management process could not open the MGD listening socket.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

WEB_MGD_RECVMSG_PEEK_ERROR

System Log Message Could not peek recvmsg() mgd connection
Description The web management process could not peek the incoming MGD request.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

WEB_MGD_SOCKET_ERROR

System Log Message Could not create mgd listener socket
Description The web management process could not open the MGD listening socket.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

WEB_PIDFILE_LOCK

System Log Message Unable to lock PID file *pathname: error-message*
Description The Web management gatekeeper process (httpd-gk) attempted to lock the indicated file, which records its process ID (PID). The file serves to prevent multiple instances of httpd-gk from running simultaneously. The attempt failed for the indicated reason.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

WEB_PIDFILE_UPDATE

System Log Message Unable to update PID file *pathname: error-message*

Description The Web management gatekeeper process (httpd-gk) attempted to update the indicated file, which records the process ID (PID) of the running httpd-gk process. The file serves to prevent multiple instances of httpd-gk from running simultaneously. The attempt failed for the indicated reason.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

Cause The most common reason is that another httpd-gk process was already running.

WEB_UNAME_FAILED

System Log Message Unable to retrieve system hostname: *error-message*

Description The Web management gatekeeper process (httpd-gk) attempted to retrieve and store the local hostname, which it shares with its remote clients. The attempt failed for the indicated reason.

Type Error: An error occurred
Severity error
Facility LOG_DAEMON

WEB_WEBAUTH_AUTH_FAIL

System Log Message Web-authentication of user *username* with fwauthd failed

Description The web-authentication authentication process was unable to authenticate the indicated user

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_DAEMON

WEB_WEBAUTH_AUTH_OK

System Log Message Web-authentication of user *username* with fwauthd successful

Description The web-authentication authentication process was able to authenticate the indicated user successfully

Type Event: This message reports an event, not an error
Severity notice
Facility LOG_DAEMON

WEB_WEBAUTH_CONNECT_FAIL

System Log Message Unable to connect to fwauthd on socket *file-descriptor: error-message*

Description The web-authentication authentication process could not connect to fwauthd daemon on the indicated socket

Type Event: This message reports an event, not an error
Severity error
Facility LOG_DAEMON

CHAPTER 106

WEBFILTER System Log Messages

This chapter describes messages with the **WEBFILTER** prefix. They are generated by the web filtering process (webfilter) which allows you to manage Internet usage by preventing access to inappropriate web content.

WEBFILTER_CACHE_NOT_ENABLED

System Log Message	Failed to enable the web-filtering category cache
Description	Failed to enable the category cache for web-filtering
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_FIREWALL
Cause	Temporarily out of system memory
Action	No recommended action

WEBFILTER_INTERNAL_ERROR

System Log Message	Error encountered: <i>error-message</i>
Description	An error is encountered in a periodical task or during a server update
Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_FIREWALL
Cause	An error is encountered in a periodical task or during a server update
Action	No recommended action

WEBFILTER_REQUEST_NOT_CHECKED

System Log Message	Error encountered: server down, failed to check request <i>error-message</i>
Description	Web-filtering failed to check a web request,

Type	Event: This message reports an event, not an error
Severity	error
Facility	LOG_FIREWALL
Cause	Failed to talk to web server, temporary out of system memory or internal error
Action	No recommended action

WEBFILTER_SERVER_CONNECTED

System Log Message Successfully connected to webfilter server *name*

Description Client successfully connected to web server

Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_FIREWALL
Cause	Successfully connected to web server
Action	No recommended action

WEBFILTER_SERVER_DISCONNECTED

System Log Message Webfilter: server *name* disconnected

Description A socket error is encountered upon connecting to a web server

Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_FIREWALL
Cause	A socket error is encountered upon connecting to a web server
Action	No recommended action

WEBFILTER_SERVER_ERROR

System Log Message WebFilter: An error is received from server *name* (0xstatus-code): *error-message*

Description An error status is received from web server

Type	Event: This message reports an event, not an error
Severity	notice
Facility	LOG_FIREWALL
Cause	An error status is received from web server

WEBFILTER_URL_BLOCKED

System Log Message	WebFilter: ACTION="URL Blocked" <i>source-address(source-port)->destination-address(destination-port) CATEGORY="name"</i> <i>REASON="error-message" PROFILE="profile-name" URL=object-name OBJ=pathname</i>
Description	A web request is blocked
Type	Event: This message reports an event, not an error
Severity	warning
Facility	LOG_FIREWALL
Cause	A web request is blocked
Action	No recommended action

WEBFILTER_URL_PERMITTED

System Log Message	WebFilter: ACTION="URL Permitted" <i>source-address(source-port)->destination-address(destination-port) CATEGORY="name"</i> <i>REASON="error-message" PROFILE="profile-name" URL=object-name OBJ=pathname</i>
Description	A web request is permitted
Type	Event: This message reports an event, not an error
Severity	info
Facility	LOG_FIREWALL
Cause	A web request is permitted
Action	No recommended action

PART 3

Index

- Index on page 793

Index

Symbols

!	regular expression operator system logging.....	23
#	comments in configuration statements.....	lxix
\$	regular expression operator system logging.....	23
()	regular expression operator system logging.....	23
(), in syntax descriptions.....		lxix
*	regular expression operator system logging.....	23
+	regular expression operator system logging.....	23
.	regular expression operator system logging.....	23
< >, in syntax descriptions.....		lxix
?	regular expression operator system logging.....	23
[]	regular expression operator system logging.....	23
[], in configuration statements.....		lxix
^	regular expression operator system logging.....	23
{ }, in configuration statements.....		lxix
	regular expression operator system logging.....	23
(pipe), in syntax descriptions.....		lxix

A

ACCT system log messages.....	57
-------------------------------	----

ALARMD system log messages.....	61
alert (system logging severity level 1).....	20
alert (system logging severity level).....	10
ANCPD system log messages.....	67
ANTISPAM system log messages.....	69
any (system logging facility).....	9
any (system logging severity level).....	10
APPID system log messages.....	71
APPIDD system log messages.....	73
APPPXY system log messages.....	75
APTRACK system log messages.....	77
archive statement usage guidelines.....	17
ASP system log messages.....	79
AUDITD system log messages.....	109
AUTHD system log messages.....	113
authorization (system logging facility) Facilities for the facility-override Statement.....	9
AUTOCONFD system log messages.....	115
AV system log messages.....	119

B

BFDD system log messages.....	125
BOOTPD system log messages.....	129
braces, in configuration statements.....	lxix
brackets angle, in syntax descriptions..... square, in configuration statements.....	lxix
brief statement system logging usage guidelines.....	11

C

CFMD system log messages.....	135
change-log (system logging facility).....	9
CHASSISD system log messages.....	139
CHASSISM system log messages.....	219
comments, in configuration statements.....	lxix
Common Criteria system logging.....	7
conflict-log (system logging facility).....	9

console statement	
system logging	
usage guidelines.....	12
CONTENT system log messages.....	221
conventions	
text and syntax.....	lxviii
COSD system log messages.....	223
critical (system logging severity level 2).....	20
critical (system logging severity level).....	10
curly braces, in configuration statements.....	lxix
customer support.....	lxx
contacting JTAC.....	lxx

D

daemon (system logging facility).....	9
option to facility-override statement.....	15
DCBX system log messages.....	237
DCD system log messages.....	239
debug (system logging severity level 7).....	20
dfc (system logging facility).....	9
DFCD system log messages.....	245
DFWD system log messages.....	249
DH system log messages.....	251
DHCPD system log messages.....	255
documentation	
comments on.....	lxx
DYNAMIC system log messages.....	259

E

emergency (system logging severity level 0).....	20
emergency (system logging severity level).....	10
error (system logging severity level 3).....	20
error (system logging severity level).....	10
ESPTASK system log messages.....	265
ESWD system log messages.....	267
EVENTD system log messages.....	275
explicit-priority statement	
usage guidelines	
routing matrix.....	32
single-chassis system.....	18

F

facilities (system logging)	
alternative for remote machine.....	15
default for remote machine.....	14
for local machine.....	9
mapping of codes to names.....	19

facility-override statement	
system logging	
usage guidelines.....	14
FC system log messages.....	283
FCD system log messages.....	289
FCOE system log messages.....	291
file statement	
system logging	
usage guidelines.....	10, 17
files	
system log messages, archiving.....	17
FIP system log messages.....	293
firewall (system logging facility).....	9
FLOW system log messages.....	297
font conventions.....	lxviii
FPCLOGIN system log messages.....	299
FSAD system log messages.....	301
ftp (system logging facility).....	9
option to facility-override statement.....	15
FUD system log messages.....	311
FWAUTH system log messages.....	317

G

GPRSD system log messages.....	321
--------------------------------	-----

H

help syslog command	
usage guidelines.....	48
HNCACHED system log messages.....	323
host statement	
system logging	
usage guidelines for routing matrix.....	33
usage guidelines for single-chassis	
system.....	12

I

ICCPD system log messages.....	325
icons defined, notice.....	lxviii
IDP system log messages.....	327
info (system logging severity level 6).....	20
info (system logging severity level).....	10
interactive-commands (system logging facility).....	9

J

JADE system log messages.....	333
JCS system log messages.....	335
JDIAMETERD system log messages.....	341
JIVED system log messages.....	343
JPTSPD system log messages.....	347

JSRPD system log messages.....351
 Junos-FIPS
 system logging.....7

K

kernel (system logging facility).....9
 option to facility-override statement.....15

L

L2ALD system log messages.....383
 L2CPD system log messages.....393
 L2TPD system log messages.....403
 LACPD system log messages.....433
 LFMD system log messages.....435
 LIBESPTASK system log messages.....437
 LIBJNX system log messages.....439
 LIBJSNMP system log messages.....447
 LIBMSRPC system log messages.....453
 LICENSE system log messages.....457
 LLDPD system log messages.....461
 local[0-7] (options to facility-override
 statement).....15
 log-prefix statement
 system logging
 usage guidelines.....16
 LOGIN system log messages.....463
 LPDFD system log messages.....467
 LRMUX system log messages.....469

M

manuals
 comments on.....lxx
 match statement
 usage guidelines.....22
 MCSN system log messages.....471
 MCSNOOPD system log messages.....477
 MIB2D system log messages.....479
 MPLS_OAM system log messages.....485

N

NEXTHOP system log messages.....489
 no-world-readable statement
 system logging
 usage guidelines.....17
 none (system logging severity level).....10
 notice (system logging severity level 5).....20
 notice (system logging severity level).....10
 notice icons defined.....lxviii
 NSD system log messages.....491

NSTRACED system log messages.....493

O

operators, regular expression
 system logging.....23
 other-routing-engine option to host statement
 usage guidelines
 routing matrix.....33
 single-chassis system.....12

P

parentheses, in syntax descriptions.....lxix
 pfe (system logging facility).....9
 PFE system log messages.....495
 PFED system log messages.....503
 PGCPD system log messages.....505
 PING system log messages.....507
 PPMD system log messages.....511
 PPPD system log messages.....513
 priorities
 system logging, including in log message
 for routing matrix.....32
 for single-chassis system.....18
 PROFILER system log messages.....521

R

RDD system log messages.....523
 regular expression operators
 system logging.....23
 RMOPD system log messages.....527
 routing matrix
 system logging.....27
 RPD system log messages.....531
 RT system log messages.....677
 RTLOG system log messages.....689
 RTLOGD system log messages.....691

S

SAVAL system log messages.....695
 scc-master option to host statement
 usage guidelines.....28
 SDXD system log messages.....697
 severity levels for system logging.....20
 SFW system log messages.....701
 size statement
 system logging
 usage guidelines.....17
 SMTPD system log messages.....703
 SNMP system log messages.....705

SNMPD system log messages.....	709
source-address statement	
system logging	
usage guidelines for routing matrix.....	33
usage guidelines for single-chassis	
system.....	13
SPD system log messages.....	721
SSH system log messages.....	727
SSHD system log messages.....	729
structured-data statement	
usage guidelines.....	11
support, technical See technical support	
syntax conventions.....	lxviii
system logging	
Common Criteria.....	7
configuration statements.....	4
defaults.....	4
different on each node in routing matrix.....	34
disabling.....	24
examples.....	24
facilities	
alternative for remote machine.....	15
default for remote machine.....	14
for local machine.....	9
facilities	
mapping of codes to names.....	19
files, archiving.....	17
forwarding messages in routing matrix.....	28
Junos-FIPS.....	7
message descriptions	
displaying.....	48
fields in.....	48
messages, displaying	
generated by Junos process.....	42
generated by service on PIC.....	43
structured-data format.....	37
regular expression filtering.....	22
regular expression operators.....	23
routing matrix.....	27
severity levels.....	20
single-chassis system.....	7
timestamp, modifying.....	21
system processes	
usage guidelines.....	4

T

TASK system log messages.....	731
technical support	
contacting JTAC.....	lxx

TFTPD system log messages.....	739
time-format statement	
usage guidelines.....	21
TX Matrix platform	
system logging.....	27

U

UFDD system log messages.....	743
UI system log messages.....	745
user (system logging facility).....	9
option to facility-override statement.....	15
user statement	
system logging	
usage guidelines.....	12
UTMD system log messages.....	769

V

VCCPD system log messages.....	771
VRRPD system log messages.....	775
VSYS system log messages.....	779

W

warning (system logging severity level 4).....	20
warning (system logging severity level).....	10
WEB system log messages.....	781
WEBFILTER system log messages.....	787
world-readable statement	
system logging	
usage guidelines.....	17