JUNIPER NETWORKS

Junos® OS

Subscriber-Aware and Application-Aware Traffic Treatment Feature Guide

Modified: 2018-12-03

Copyright © 2018, Juniper Networks, Inc.

Juniper Networks, Inc.
1133 Innovation Way
Sunnyvale, California 94089
USA
408-745-2000
www.juniper.net

Juniper Networks, the Juniper Networks logo, Juniper, and Junos are registered trademarks of Juniper Networks, Inc. in the United States and other countries. All other trademarks, service marks, registered marks, or registered service marks are the property of their respective owners.

Juniper Networks assumes no responsibility for any inaccuracies in this document. Juniper Networks reserves the right to change, modify, transfer, or otherwise revise this publication without notice.

Junos® OS Subscriber-Aware and Application-Aware Traffic Treatment Feature Guide
Copyright © 2018 Juniper Networks, Inc. All rights reserved.

The information in this document is current as of the date on the title page.

YEAR 2000 NOTICE

Juniper Networks hardware and software products are Year 2000 compliant. Junos OS has no known time-related limitations through the year 2038. However, the NTP application is known to have some difficulty in the year 2036.

END USER LICENSE AGREEMENT

The Juniper Networks product that is the subject of this technical documentation consists of (or is intended for use with) Juniper Networks software. Use of such software is subject to the terms and conditions of the End User License Agreement ("EULA") posted at https://support.juniper.net/support/eula/. By downloading, installing or using such software, you agree to the terms and conditions of that EULA.

Table of Contents

About the Documentation xxiii
Documentation and Release Notes xxiii
Using the Examples in This Manual xxiii
Merging a Full Example xxiv
Merging a Snippet xxiv
Documentation Conventions xxv
Documentation Feedback xxvii
Requesting Technical Support xxvii
Self-Help Online Tools and Resources xxviii
Opening a Case with JTAC xxviii

Part 1 Subscriber-Aware and Application-Aware Traffic Treatment Overview

Chapter 1 **Subscriber-Aware and Application-Aware Traffic Treatment Overview 3**

Subscriber-Aware and Application-Aware Traffic Treatment Overview 3
Introduction 3
Access-Independent Subscriber Traffic Treatment 4
Subscriber Identification Methods 4
Application Identification 5
Policy Control Methods 5
Subscriber-Aware Data Session Logging and Reporting 5
Usage Monitoring 5
Configuring Subscriber-Aware and Application-Aware Traffic Treatment Overview 6

Part 2 Applying Subscriber-Aware and Application-Aware Policies and Services

Chapter 2 **Configuring the Service PIC, Session PIC, and TDF Gateway 11**

TDF Gateway Service PICs and Session PICs for Subscriber-Aware Traffic Treatment 11
TDF Gateway 11
Service and Session PICs 11
Redundancy for Service PICs and Session PICs 13
Configuring Service PICs and Session PICs Overview 13
Preconfigured Groups for Service PICs and for Session PICs Overview 14
Configuring a Services Interface for a Session PIC or Service PIC 16
Configuring a TDF Gateway 16

Copyright © 2018, Juniper Networks, Inc.

Making Predefined Groups Available for Session PIC and Service PIC Configuration . . . 17
Configuring Service PICs . . . 18
Configuring Session PICs . . . 19
Configuring Tracing for TDF Gateway . . . 19

Chapter 3 Configuring Application Identification . . . 23

Application Identification Overview . . . 23
Downloading and Installing Predefined Junos OS Application Signature Packages . . . 24
Configuring Custom Application Signatures . . . 25
Uninstalling a Predefined Junos OS Application Signature Package . . . 31

Chapter 4 Configuring HTTP Header Enrichment . . . 33

Junos Web Aware HTTP Header Enrichment Overview . . . 33
Configuring HTTP Header Enrichment Overview . . . 33
Configuring Tag Rules . . . 35
Configuring HCM Profiles and Assigning Tag Rules . . . 40

Chapter 5 Configuring Policy and Charging Enforcement . . . 43

Understanding Junos Subscriber Aware Policy and Charging Enforcement Function (PCEF) . . . 44
Static Policy Control . . . 44
Dynamic Policy Control . . . 45
RADIUS Server Policy Control . . . 45
Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment . . . 47
Understanding Service Data Flow Filters . . . 47
Understanding Application Filters . . . 48
Understanding PCC Action Profiles . . . 48
Understanding How Subscriber-Aware Policy and Charging Control Rules Are Provisioned Dynamically by a PCRF . . . 49
Policy Decisions . . . 49
Supported Operations . . . 50
Methods for Provisioning PCC Rules . . . 50
Understanding How Subscriber-Aware Policy and Charging Control Rules Are Provisioned Statically . . . 52
Understanding How a RADIUS Server Controls Policy and Charging Control Rules . . . 53
Rule Activation When TDF Session Begins . . . 53
Rule Activation and Deactivation When RADIUS Server Sends Request . . . 53
Supported Attributes in RADIUS Messages . . . 54
Understanding PCEF Profiles . . . 56
Understanding Network Elements . . . 57
Load Balancing Within Network Elements . . . 57
Server Priority . . . 57
Dead Server Detection . . . 57
Maximum Pending Requests for a Network Element . . . 58

Copyright © 2018, Juniper Networks, Inc.

Understanding AAA Profiles . . . 58
Network Elements . . . 58
RADIUS Attributes That Carry Rulebase Names for Activation and Deactivation . . . 58
Understanding Static Time-of-Day PCC Rule Activation and Deactivation . . . 59
Understanding Usage Monitoring for TDF Subscribers . . . 59
Tracked Resource Identification . . . 60
Threshold Configuration . . . 60
Messages and AVPs That Are Used . . . 60
Configuring Dynamic Policy Control by PCRF . . . 61
Configuring Static Policy Control . . . 62
Configuring Policy Control by RADIUS Servers . . . 63
Configuring Service Data Flow Filters . . . 64
Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware . . . 67
Configuring Policy and Charging Control Rules . . . 70
Configuring a Policy and Charging Control Rulebase . . . 73
Configuring RADIUS Servers . . . 74
Configuring RADIUS Network Elements . . . 77
Configuring an AAA Profile . . . 78
Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Dynamic Policies . . . 80
Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Static Policies . . . 81
Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Policies That a RADIUS Server Controls . . . 82
Configuration of Static Time-of-Day PCC Rule Activation and Deactivation Overview . . . 83
Configuring the NTP Server . . . 84
Configuring Static Time-of-Day PCC Rule Activation and Deactivation in a Junos OS Subscriber Aware PCEF Profile . . . 84
Configuring TDF Subscriber Usage Monitoring for Traffic That Matches Predefined PCC Rules . . . 85

Chapter 6 **Configuring TDF Subscribers . . . 87**

IP-Based and IFL-Based TDF Subscribers Overview . . . 88
IP-Based Subscribers . . . 88
IFL-Based Subscribers . . . 88
IP-Based Subscriber Setup Overview . . . 88
Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain . . . 89
Understanding Source IP Filtering with Address Pools in TDF Domains for IP-Based Subscribers . . . 90
Understanding Selection of Properties for an IP-Based TDF Subscriber . . . 90
Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber . . . 92
Snooping RADIUS Accounting Requests for IP-Based Subscribers Overview . . . 94
Understanding IFL-Based Subscriber Setup . . . 95

Copyright © 2018, Juniper Networks, Inc.

Understanding the Definition of a Set of IFL-Based Subscriber Properties with a TDF Domain . . . 96
Configuring IP-Based TDF Subscriber Setup When MX Series Router Is a RADIUS Server . . . 97
Configuring IP-Based TDF Subscriber Setup When Accounting Requests Are Snooped . . . 98
Configuring Address Pools for Source-IP Filtering of IP-Based Subscribers . . . 99
Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain . . 100
Configuring the TDF Domain Name and AAA Parameters . . . 101
Configuring Address Filtering . . . 103
Configuring Subscriber Services and Policies . . . 103
Configuring Access Interfaces . . . 104
Configuring Session Controls . . . 104
Configuring Default Policy . . . 105
Configuring RADIUS Clients That Send Accounting Requests for IP-Based Subscribers . . . 106
Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers . . . 107
Configuring the Term Name . . . 108
Configuring Match Conditions for the RADIUS Client . . . 108
Configuring Match Conditions for Snoop Segments . . . 108
Configuring Match Conditions for Predefined AVPs . . . 109
Configuring Match Conditions for Custom AVP Attributes . . . 110
Configuring the TDF Domain to Select . . . 112
Configuring the PCEF Profile to Select . . . 112
Configuring Snooping of RADIUS Accounting Requests for IP-Based Subscribers . . . 113
Configuring IFL-Based TDF Subscriber Setup . . . 116
Configuring IFL-Based TDF Subscribers and Properties with a TDF Domain . . . 117
Configuring the TDF Domain Name and Type . . . 117
Configuring IFL-Based Subscribers . . . 118
Configuring Address Filtering . . . 118
Configuring Subscriber Services and Policies . . . 118
Configuring Session Controls . . . 119
Configuring a TDF Logical Interface . . . 120
Configuring TDF Interface to Access Interface Associations in VRFs . . . 120

Chapter 7 Configuring Services . . . 123

Overview of Applying Services to Subscribers . . . 123
Applying Services to Subscriber-Aware Traffic with a Service Set . . . 124

Chapter 8 Configuring Diameter . . . 127

Diameter Profiles Overview . . . 127
Juniper Networks Diameter AVPs for Subscriber Aware Policy Control . . . 128
Configuring Diameter Overview . . . 129
Configuring Diameter Profiles . . . 130
Configuring Diameter Bindings . . . 131
Configuring Diameter Network Elements . . . 132
Configuring Diameter AVPs for Gx Applications . . . 133
Configuring Diameter Peers . . . 134

Copyright © 2018, Juniper Networks, Inc.

Configuring the Diameter Transport . . . 136
Configuring Advertisements in Diameter Messages . . . 137
Configuring Parameters for Diameter Applications . . . 138
Configuring the Origin Attributes of the Diameter Instance . . . 138

Part 3 Configuring Reporting for Subscriber-Aware Data Sessions

Chapter 9 Configuring Reporting . . . 141

Logging and Reporting Function for Subscribers . . . 141
Log and Report Control . . . 141
Templates . . . 142
HTTP Transaction Logging . . . 146
Log Dictionary for Template Types . . . 146
Configuring Logging and Reporting for Junos OS Subscriber Aware . . . 152
Configuring an LRF Profile for Subscribers . . . 152
Configuring the LRF Profile Name . . . 153
Configuring Policy-Based Logging . . . 153
(Optional) Configuring HTTP Transaction Logging . . . 153
Configuring Collectors . . . 154
Configuring Templates . . . 155
Configuring Logging and Reporting Rules . . . 156
Assigning an LRF Profile to Subscribers . . . 157
Configuring the Activation of an LRF Rule by a PCC Rule . . . 160

Part 4 Modifying Subscriber-Aware Configuration

Chapter 10 Modifying Subscriber-Aware Configuration in Maintenance Mode . . . 165

Maintenance Mode Overview for Subscriber Aware Policy Enforcement . . . 166
Changing Address Attributes in the Address Pool . . . 167
Deleting an Address Pool . . . 168
Changing AMS Interface Parameters on a TDF Gateway . . . 169
Modifying a TDF Domain . . . 172
Modifying the TDF Interface of a TDF Domain . . . 174
Deleting a TDF Domain . . . 175
Changing a TDF Interface . . . 177
Deleting a TDF Interface . . . 178
Changing TDF Gateway Parameters with Maintenance Mode . . . 180
Changing PCEF Profiles, PCC Rules, PCC Rulebases, Diameter Profiles, Flow Descriptions, and PCC Action Profiles . . . 182
Changing PCEF Profiles, PCC Rules, PCC Rulebases, Diameter Profiles, Flow Descriptions, and PCC Action Profiles with the TDF Domain in Maintenance Mode . . . 183
Changing PCEF Profiles, PCC Rules, PCC Rulebases, Diameter Profiles, Flow Descriptions, and PCC Action Profiles with the TDF Gateway in Maintenance Mode . . . 184
Deleting a PCEF Profile . . . 186
Deleting a PCEF Profile with the TDF Domain in Maintenance Mode . . . 186
Deleting a PCEF Profile with the Gateway in Maintenance Mode . . . 188
Changing Static Time-of-Day Settings for PCC Rules . . . 190

Copyright © 2018, Juniper Networks, Inc.

Deleting a Services PIC 191
Deleting a Session PIC 193

Part 5 Monitoring and Troubleshooting

Chapter 11 Monitoring and Troubleshooting 199

Configuring Tracing for PCEF Operations 199
Configuring Call-Rate Statistics Collection 200

Part 6 Configuration Statements and Operational Commands

Chapter 12 Configuration Statements 205

3gpp-imsi 213
aaa clients (TDF) 214
aaa-policy-control (PCEF Profile) 215
aaa-profile (PCEF Profile) 216
access-interfaces (IFL Subscriber) 217
access-interfaces (IP Subscriber) 218
accounting (AAA Profile) 219
accounting (RADIUS Client) 220
accounting-port (RADIUS Server) 221
accounting-secret (RADIUS Server) 222
activation-attribute (AAA Profile) 223
address (Diameter Peer) 224
address (LRF Profile) 224
address (RADIUS Clients) 225
address (RADIUS Server) 225
address-mapping (Application Identification) 226
address-pools 227
allow-dynamic-requests (RADIUS Server) 228
alt-name (Application Identification) 228
application (Application Identification) 229
application-groups (PCC Rules) 231
application-identification (Application Identification) 232
application-identification-profile (Service Set) 233
applications (Diameter) 234
applications (PCC Rules) 235
attribute 236
attributes (Diameter Gx Profiles) 238
authentication (AAA Profile) 239
burst-size (Default Local Policy) 240
burst-size (TDF Domain) 241
cac (TDF Gateway) 242
cacheable (Application Identification) 242
call-rate-statistics 243
called-station-id 244
calling-station-id 245
chain-order (Application Identification) 246
check-bytes (Application Identification) 246

Copyright © 2018, Juniper Networks, Inc.

class . . . 247
client . . . 248
clients . . . 249
coa-accounting (AAA Profile) . . . 250
code . . . 251
code (AAA Profile) . . . 252
code (Application Identification) . . . 253
collector (LRF Profile) . . . 254
collector (LRF Rule) . . . 255
compatibility (Application Identification) . . . 255
connect-actively . . . 256
constant . . . 257
context (Application Identification) . . . 258
count (HTTP Header Enrichment) . . . 259
cpu (TDF Gateway) . . . 260
deactivation-attribute (AAA Profile) . . . 261
dead-criteria-retries (RADIUS Server) . . . 262
default-local-policy . . . 263
default-pool (Address Pools) . . . 264
description (Application Identification) . . . 264
destination (Application Identification) . . . 265
destination (LRF Profile) . . . 265
destination-address (HTTP Header Enrichment) . . . 266
destination-address-range (HTTP Header Enrichment) . . . 267
destination-ip-address (RADIUS Snoop Segment) . . . 268
destination-port (RADIUS Snoop Segment) . . . 269
destination-port-range (HTTP Header Enrichment) . . . 270
destination-ports (HTTP Header Enrichment) . . . 271
destination-prefix-list (HTTP Header Enrichment) . . . 272
diameter (Subsciber Aware Policy Control) . . . 273
diameter (TDF Gateway) . . . 275
diameter-profile (PCEF Profile) . . . 276
direction (Application Identification) . . . 277
direction (Service Data Flow Filters) . . . 278
disconnect-peer-timeout . . . 279
domain (TDF Domain Selection) . . . 280
domain-selection . . . 281
domains . . . 285
dynamic-policy-control . . . 288
dynamic-requests-secret (RADIUS Server) . . . 289
encrypt (HTTP Header Enrichment) . . . 290
equals . . . 291
exclude (Diameter Gx Profiles) . . . 292
external-assigned (Address Pools) . . . 293
family (Address Pools) . . . 294
family (Exclude Prefix) . . . 295
family (TDF Interface) . . . 296
flow-action . . . 297
flow-descriptions . . . 298

Copyright © 2018, Juniper Networks, Inc.

flows (PCC Rules) . . . 300
format . . . 301
format (LRF Profile) . . . 303
forwarding-class (PCC Action Profiles) . . . 304
firmware-revision . . . 305
framed-ip-address . . . 306
framed-ipv6-prefix . . . 307
from (HTTP Header Enrichment) . . . 308
from (PCC Rules) . . . 309
from (TDF Domain Selection) . . . 310
function (Diameter Network Element) . . . 313
gate-status . . . 314
greater-than . . . 315
gx-profile . . . 316
has-prefix . . . 317
has-suffix . . . 318
hcm (HTTP Header Enrichment) . . . 319
hcm-profile (HTTP Header Enrichment) . . . 320
hcm-profile (PCC Action Profiles) . . . 321
host (Diameter Origin) . . . 322
http-log-multiple-transactions (LRF Profile) . . . 322
icmp-mapping (Application Identification) . . . 323
id-components . . . 324
idle-timeout . . . 325
ifl-subscriber . . . 326
immediate-accounting-response . . . 327
include (Diameter Gx Profiles) . . . 328
incoming-queue . . . 329
inet (TDF Subscriber Address) . . . 330
inet (TDF Subscriber Exclude Prefix) . . . 331
inet6 (TDF Subscriber Address) . . . 332
inet6 (TDF Subscriber Exclude Prefix) . . . 333
integer . . . 334
interface (Services PIC) . . . 335
interface (Session PICs) . . . 336
interface-service (Services Interfaces) . . . 337
ip-protocol-mapping (Application Identification) . . . 338
ip-subscriber . . . 339
ipv4-address (Steering Path) . . . 340
ipv4-mask (HTTP Header Enrichment) . . . 341
ipv4-or-value (HTTP Header Enrichment) . . . 342
ipv6-address (Steering Path) . . . 343
ipv6-mask (HTTP Header Enrichment) . . . 344
ipv6-or-value (HTTP Header Enrichment) . . . 345
keep-existing-steering . . . 346
less-than . . . 347
local-port-range . . . 348
local-ports . . . 350
logging-rule (PCC Action Profile) . . . 351

Copyright © 2018, Juniper Networks, Inc.

lrf-profile (Service Set) . . . 352
matches . . . 353
maximum-bit-rate (Default Local Policy) . . . 355
maximum-bit-rate (PCC Action Profiles) . . . 356
maximum-bit-rate (TDF Domain) . . . 357
maximum-pending-reqs-limit . . . 358
maximum-pending-requests (Diameter) . . . 359
maximum-sessions (TDF Gateway) . . . 359
maximum-subscribers . . . 360
maximum-sessions-trap-percentage (TDF Gateway) . . . 361
member (Application Identification) . . . 362
memory (TDF Gateway) . . . 363
mif (TDF Interface) . . . 364
monitoring-key (PCC Action Profile) . . . 365
mtu (TDF Interface) . . . 365
nas-ip-address . . . 366
nat-rule-sets (Service Set) . . . 367
nat-rules . . . 367
network-element (AAA Profile) . . . 368
network-element (Diameter Base Protocol) . . . 369
network-element (Subscriber Aware Policy Control) . . . 370
network-elements (RADIUS) . . . 371
network (Address Pools) . . . 372
network (TDF Domain) . . . 373
no-send-to-ue . . . 374
order (Application Identification) . . . 375
order-priority (Application Identification) . . . 376
origin (Diameter Base Protocol) . . . 377
outgoing-queue . . . 378
over (Application Identification) . . . 379
path (Steering) . . . 380
pattern (Application Identification) . . . 381
pattern (Class Attribute) . . . 382
pcc-action-profile (PCC Rules) . . . 383
pcc-action-profiles . . . 384
pcc-rule . . . 386
pcc-rulebases (PCEF) . . . 387
pcc-rulebases (PCEF Profile) . . . 388
pcc-rules (PCEF) . . . 390
pcc-rules (PCEF Profile) . . . 391
pcc-time-of-day-profiles . . . 393
pcef . . . 394
pcef-profile (Service Set) . . . 396
pcef-profile (TDF Domain) . . . 397
pcef-profile (TDF Domain Selection) . . . 398
peer (Diameter Base Protocol) . . . 399
peer (Diameter Network Element) . . . 400
pending-queue-watermark . . . 401
pending-queue-watermark-abate . . . 402

Copyright © 2018, Juniper Networks, Inc.

policy-based-logging (LRF Profile) . . . 403
pool (TDF Domain) . . . 404
port (LRF Profile) . . . 405
port (RADIUS Server) . . . 405
port-range (Application Identification) . . . 406
prefer-framed-ip-address (RADIUS Clients) . . . 407
prefer-framed-ipv6-prefix (RADIUS Clients) . . . 408
priority (Diameter Network Element) . . . 408
priority (RADIUS Network Elements) . . . 409
product-name . . . 410
profile (HTTP Header Enrichment) . . . 411
profile (LRF) . . . 412
profile (Services Application Identification) . . . 413
profile (HCM placeholder) . . . 414
profile (Services PCEF) . . . 414
profiles (AAA) . . . 415
profiles (PCEF) . . . 416
protocol (Application Identification) . . . 418
protocol (Flow Descriptions) . . . 419
realm (Diameter Origin) . . . 420
redirect (PCC Action Profiles) . . . 421
regex (Class Attribute) . . . 422
remote-address . . . 423
remote-port-range . . . 424
remote-ports . . . 426
report (LRF Rule) . . . 427
request-cache-timeout (RADIUS Snoop Segment) . . . 428
request-timeout . . . 429
response-cache-timeout (RADIUS Client) . . . 430
retry (RADIUS Server) . . . 431
revert-interval (RADIUS Server) . . . 432
routing-instance (PCC Action Profiles) . . . 433
rule (HTTP Header Enrichment for Tag Rule Set) . . . 434
rule (LRF) . . . 435
rule-activation-time . . . 436
rule-deactivation-time . . . 437
secret (RADIUS Client) . . . 438
secret (RADIUS Server) . . . 438
server (RADIUS Network Elements) . . . 439
servers (RADIUS) . . . 440
service-mode . . . 441
service-pics . . . 442
service-set (Subscriber-Aware) . . . 443
service-set (TDF Interface) . . . 444
session-pics . . . 445
session-pics (Diameter) . . . 446
shared-secret (RADIUS Snoop Segment) . . . 447
snoop-segment (TDF Domain Selection) . . . 448
snoop-segments (RADIUS) . . . 449

Copyright © 2018, Juniper Networks, Inc.

snoop-segments (TDF Gateway) . . . 450
source (Application Identification) . . . 451
source-address (LRF Profile) . . . 451
source-interface . . . 452
source-interface (RADIUS Server) . . . 453
source-interface (RADIUS Snoop Segment) . . . 454
source-ip-address (RADIUS Snoop Segment) . . . 455
static-policy-control . . . 456
steering . . . 458
string . . . 459
subscriber-address . . . 460
subscriber-awareness (Service Set Options) . . . 461
subscriber-exclude-prefix . . . 462
subscriber-type (TDF Domain) . . . 463
subscription-id . . . 464
subscription-id-options . . . 465
subscription-id-type (Class Attribute) . . . 466
tag (HTTP Header Enrichment) . . . 467
tag-attribute (HTTP Header Enrichment) . . . 468
tag-attribute (HTTP Header Enrichment Tag Rule) . . . 469
tag-header (HTTP Header Enrichment) . . . 470
tag-operation (HTTP Header Enrichment) . . . 471
tag-rule (Profiles for HTTP Header Enrichment) . . . 472
tag-rule (HTTP Header Enrichment) . . . 473
tag-rules (Service Set) . . . 474
tag-rule-set (HTTP Header Enrichment) . . . 475
tag-rule-sets (Service Set) . . . 476
tag-separator (HTTP Header Enrichment) . . . 476
tag-value (HTTP Header Enrichment) . . . 477
tags (Application Identification) . . . 478
targets . . . 479
tdf (Unified Edge) . . . 480
tdf-interface . . . 481
template (LRF Profile) . . . 482
template (LRF Rule) . . . 483
template-tx-interval (LRF Profile) . . . 484
template-type (LRF Profile) . . . 485
term (HTTP Header Enrichment) . . . 487
term (TDF Domain Selection) . . . 489
then (HTTP Header Enrichment) . . . 493
then (LRF rule) . . . 494
then (PCC Rules) . . . 495
then (TDF Domain Selection) . . . 496
time . . . 497
time-limit (LRF Rule) . . . 498
timeout (Diameter Network Element) . . . 499
timeout (RADIUS Server) . . . 500
traceoptions (Diameter Base Protocol) . . . 501
traceoptions (PCEF) . . . 503

Copyright © 2018, Juniper Networks, Inc.

traceoptions (TDF Gateway) . . . 505
trigger-type (LRF Profile) . . . 507
type (Application Identification) . . . 508
type (ICMP Mapping for Application Identification) . . . 508
unit (TDF Interface) . . . 509
url . . . 510
use-class (Class Attribute) . . . 511
user-name . . . 512
user-password (PCEF Profile) . . . 513
v4address . . . 514
v6address . . . 515
v6prefix . . . 516
vendor-id . . . 517
vendor-id (AAA Profile) . . . 518
vendor-support . . . 519
volume-limit (LRF Rule) . . . 520
watchdog-timeout . . . 521

Chapter 13 Operational Commands . . . 523

clear services application-identification application-system-cache . . . 526
clear services application-identification statistics . . . 527
clear services lrf collector statistics . . . 529
clear services lrf statistics . . . 530
clear unified-edge tdf aaa radius client statistics . . . 531
clear unified-edge tdf aaa radius network-element statistics . . . 532
clear unified-edge tdf aaa radius server statistics . . . 533
clear unified-edge tdf aaa radius snoop-segment statistics . . . 534
clear unified-edge tdf aaa statistics . . . 535
clear unified-edge tdf address-assignment pool . . . 536
clear unified-edge tdf address-assignment statistics . . . 537
clear unified-edge tdf call-admission-control statistics . . . 538
clear unified-edge tdf diameter network-element statistics . . . 539
clear unified-edge tdf diameter pcc-gx statistics . . . 540
clear unified-edge tdf diameter peer statistics . . . 541
clear unified-edge tdf statistics . . . 542
clear unified-edge tdf subscribers . . . 543
clear unified-edge tdf subscribers peer . . . 545
request interface load-balancing revert (Aggregated Multiservices) . . . 546
request interface load-balancing switchover (Aggregated Multiservices) . . . 547
request services application-identification application . . . 548
request services application-identification download . . . 550
request services application-identification download status . . . 551
request services application-identification group . . . 552
request services application-identification install . . . 554
request services application-identification install status . . . 555
request services application-identification proto-bundle-status . . . 556
request services application-identification uninstall . . . 557
request services application-identification uninstall status . . . 558
request unified-edge tdf call-trace clear . . . 559

Copyright © 2018, Juniper Networks, Inc.

request unified-edge tdf call-trace show 560
request unified-edge tdf call-trace start 563
request unified-edge tdf call-trace stop 565
show interfaces anchor-group (Aggregated Packet Forwarding Engine) 567
show interfaces load-balancing (Aggregated Multiservices) 570
show services application-identification application 574
show services application-identification application-system-cache 580
show services application-identification counter 584
show services application-identification group 587
show services application-identification statistics application-groups 591
show services application-identification statistics applications 593
show services application-identification status 595
show services application-identification version 598
show services ha detail 599
show services hcm statistics 601
show services hcm pic-statistics 603
show services lrf collector statistics 607
show services lrf rule statistics 609
show services lrf statistics 611
show services lrf template 612
show services traffic-detection-function hcm statistics 614
show services traffic-detection-function sessions 617
show unified-edge tdf aaa radius client statistics 620
show unified-edge tdf aaa radius client status 626
show unified-edge tdf aaa radius network-element statistics 628
show unified-edge tdf aaa radius server statistics 631
show unified-edge tdf aaa radius server status 635
show unified-edge tdf aaa radius snoop-segment statistics 638
show unified-edge tdf aaa statistics 642
show unified-edge tdf address-assignment pool 649
show unified-edge tdf address-assignment service-mode 653
show unified-edge tdf address-assignment statistics 655
show unified-edge tdf call-admission-control statistics 657
show unified-edge tdf call-rate statistics 660
show unified-edge tdf diameter network-element statistics 662
show unified-edge tdf diameter network-element status 665
show unified-edge tdf diameter pcc-gx statistics 667
show unified-edge tdf diameter peer statistics 672
show unified-edge tdf diameter peer status 677
show unified-edge tdf domain service-mode 681
show unified-edge tdf domain statistics 683
show unified-edge tdf resource-manager clients 688
show unified-edge tdf service-mode 690
show unified-edge tdf statistics 692
show unified-edge tdf status 699
show unified-edge tdf subscribers 703
show unified-edge tdf system interfaces 717
show unified-edge tdf system interfaces service-mode 719

Copyright © 2018, Juniper Networks, Inc.

Copyright © 2018, Juniper Networks, Inc.

List of Figures

Part 1 Subscriber-Aware and Application-Aware Traffic Treatment Overview

Chapter 1 **Subscriber-Aware and Application-Aware Traffic Treatment Overview . . . 3**

Figure 1: Subscriber-Aware Policy Enforcement on the MX Series . . . 4

Part 2 Applying Subscriber-Aware and Application-Aware Policies and Services

Chapter 2 **Configuring the Service PIC, Session PIC, and TDF Gateway . . . 11**

Figure 2: Service PIC and Session PIC Overview . . . 12

Chapter 5 **Configuring Policy and Charging Enforcement . . . 43**

Figure 3: Static Policy Control . . . 44
Figure 4: Dynamic Policy Control . . . 45
Figure 5: RADIUS Server Policy Control . . . 46
Figure 6: Message Flow for Pull Mode During TDF Subscriber Creation . . . 51
Figure 7: Message Flow for Pull Mode After PCEF Event Trigger . . . 51
Figure 8: Message Flow for Push Mode . . . 52
Figure 9: RADIUS Server Message Flow When TDF Session Begins . . . 53
Figure 10: Message Flow When RADIUS Server Sends Request . . . 54

Chapter 6 **Configuring TDF Subscribers . . . 87**

Figure 11: IP-Based Subscriber Setup Process . . . 91

Chapter 7 **Configuring Services . . . 123**

Figure 12: Subscriber-Aware Service Set Relationships . . . 123

Part 3 Configuring Reporting for Subscriber-Aware Data Sessions

Chapter 9 **Configuring Reporting . . . 141**

Figure 13: HTTP Transaction Logging . . . 146

Copyright © 2018, Juniper Networks, Inc.

Copyright © 2018, Juniper Networks, Inc.

List of Tables

About the Documentation xxiii

Table 1: Notice Icons xxv
Table 2: Text and Syntax Conventions xxvi

Part 2 Applying Subscriber-Aware and Application-Aware Policies and Services

Chapter 2 Configuring the Service PIC, Session PIC, and TDF Gateway 11

Table 3: Trace Flags 20

Chapter 5 Configuring Policy and Charging Enforcement 43

Table 4: Attributes Supported in Access-Request Messages 54
Table 5: Attributes Supported in Access-Accept Messages 55
Table 6: Attributes Supported in CoA Messages 56

Chapter 6 Configuring TDF Subscribers 87

Table 7: Options for id-components of Subscription-Id 102

Chapter 8 Configuring Diameter 127

Table 8: Juniper Networks Diameter AVPs for Subscriber Policy Control 128
Table 9: Diameter AVP Exclusions for Gx Applications 133
Table 10: Diameter AVP Inclusions for Gx Applications 134

Part 3 Configuring Reporting for Subscriber-Aware Data Sessions

Chapter 9 Configuring Reporting 141

Table 11: Logging Dictionary for Template Types 147

Part 5 Monitoring and Troubleshooting

Chapter 11 Monitoring and Troubleshooting 199

Table 12: Trace Flags 200

Part 6 Configuration Statements and Operational Commands

Chapter 12 Configuration Statements 205

Table 13: Regular Expression Operators for the matches Statement 354

Chapter 13 Operational Commands 523

Table 14: request unified-edge tdf call-trace show Output Fields 560
Table 15: request unified-edge tdf call-trace start Output Fields 564
Table 16: request unified-edge tdf call-trace stop Output Fields 565
Table 17: show interfaces anchor-group Output Fields 567

Copyright © 2018, Juniper Networks, Inc.

Table 18: Aggregated Multiservices show interfaces load-balancing Output Fields . . . 570
Table 19: show services application-identification application Output Fields . . . 574
Table 20: show services application-identification application-system-cache Output Fields . . . 580
Table 21: show services application-identification counter Output Fields . . . 584
Table 22: show services application-identification group Output Fields . . . 587
Table 23: show services application-identification statistics application-groups Output Fields . . . 591
Table 24: show services application-identification statistics applications Output Fields . . . 593
Table 25: show services application-identification status Output Fields . . . 595
Table 26: show services ha detail Output Fields . . . 599
Table 27: show services hcm statistics Output Fields . . . 601
Table 28: show services hcm pic-statistics Output Fields . . . 603
Table 29: show services lrf collector statistics Output Fields . . . 607
Table 30: show services lrf rule statistics Output Fields . . . 609
Table 31: show services lrf statistics Output Fields . . . 611
Table 32: show services traffic-detection-function hcm statistics Output Fields . . . 614
Table 33: show services traffic-detection-function sessions Output Fields . . . 617
Table 34: show unified-edge tdf aaa radius client statistics Output Fields . . . 620
Table 35: show unified-edge tdf aaa radius client status Output Fields . . . 626
Table 36: show unified-edge tdf aaa radius network-element statistics Output Fields . . . 629
Table 37: show unified-edge tdf aaa radius server statistics Output Fields . . . 632
Table 38: show unified-edge tdf aaa radius server status Output Fields . . . 635
Table 39: show unified-edge tdf aaa radius snoop-segment statistics Output Fields . . . 639
Table 40: show unified-edge tdf aaa statistics Output Fields . . . 643
Table 41: show unified-edge tdf address-assignment pool Output Fields . . . 650
Table 42: show unified-edge tdf address-assignment service-mode Output Fields . . . 653
Table 43: show unified-edge tdf address-assignment statistics Output Fields . . . 655
Table 44: show unified-edge tdf call-admission-control statistics Output Fields . . . 658
Table 45: show unified-edge tdf call-rate statistics Output Fields . . . 660
Table 46: show unified-edge tdf diameter network-element statistics Output Fields . . . 663
Table 47: show unified-edge tdf diameter network-element status Output Fields . . . 665
Table 48: show unified-edge tdf diameter pcc-gx statistics Output Fields . . . 667
Table 49: show unified-edge tdf diameter peer statistics Output Fields . . . 673
Table 50: show unified-edge tdf diameter peer status Output Fields . . . 677
Table 51: show unified-edge tdf domain service-mode Output Fields . . . 681
Table 52: show unified-edge tdf domain statistics Output Fields . . . 683
Table 53: show unified-edge tdf resource-manager clients Output Fields . . . 688
Table 54: show unified-edge tdf service-mode Output Fields . . . 690

Copyright © 2018, Juniper Networks, Inc.

Table 55: show unified-edge tdf statistics Output Fields 692
Table 56: show unified-edge tdf status Output Fields 700
Table 57: show unified-edge tdf subscribers Output Fields 704
Table 58: show unified-edge tdf system interfaces Output Fields 717
Table 59: show unified-edge tdf system interfaces service-mode Output Fields 719

Copyright © 2018, Juniper Networks, Inc.

Copyright © 2018, Juniper Networks, Inc.

About the Documentation

- Documentation and Release Notes on page xxiii
- Using the Examples in This Manual on page xxiii
- Documentation Conventions on page xxv
- Documentation Feedback on page xxvii
- Requesting Technical Support on page xxvii

Documentation and Release Notes

To obtain the most current version of all Juniper Networks® technical documentation, see the product documentation page on the Juniper Networks website at https://www.juniper.net/documentation/.

If the information in the latest release notes differs from the information in the documentation, follow the product Release Notes.

Juniper Networks Books publishes books by Juniper Networks engineers and subject matter experts. These books go beyond the technical documentation to explore the nuances of network architecture, deployment, and administration. The current list can be viewed at https://www.juniper.net/books.

Using the Examples in This Manual

If you want to use the examples in this manual, you can use the **load merge** or the **load merge relative** command. These commands cause the software to merge the incoming configuration into the current candidate configuration. The example does not become active until you commit the candidate configuration.

If the example configuration contains the top level of the hierarchy (or multiple hierarchies), the example is a *full example*. In this case, use the **load merge** command.

If the example configuration does not start at the top level of the hierarchy, the example is a *snippet*. In this case, use the **load merge relative** command. These procedures are described in the following sections.

Copyright © 2018, Juniper Networks, Inc.

Merging a Full Example

To merge a full example, follow these steps:

1. From the HTML or PDF version of the manual, copy a configuration example into a text file, save the file with a name, and copy the file to a directory on your routing platform.

   For example, copy the following configuration to a file and name the file **ex-script.conf**. Copy the **ex-script.conf** file to the **/var/tmp** directory on your routing platform.

   ```
   system {
     scripts {
       commit {
         file ex-script.xsl;
       }
     }
   }
   interfaces {
     fxp0 {
       disable;
       unit 0 {
         family inet {
           address 10.0.0.1/24;
         }
       }
     }
   }
   ```

2. Merge the contents of the file into your routing platform configuration by issuing the **load merge** configuration mode command:

   ```
   [edit]
   user@host# load merge /var/tmp/ex-script.conf
   load complete
   ```

Merging a Snippet

To merge a snippet, follow these steps:

1. From the HTML or PDF version of the manual, copy a configuration snippet into a text file, save the file with a name, and copy the file to a directory on your routing platform.

   For example, copy the following snippet to a file and name the file **ex-script-snippet.conf**. Copy the **ex-script-snippet.conf** file to the **/var/tmp** directory on your routing platform.

   ```
   commit {
     file ex-script-snippet.xsl; }
   ```


Copyright © 2018, Juniper Networks, Inc.

2. Move to the hierarchy level that is relevant for this snippet by issuing the following configuration mode command:

```
[edit]
user@host# edit system scripts
[edit system scripts]
```

3. Merge the contents of the file into your routing platform configuration by issuing the **load merge relative** configuration mode command:

```
[edit system scripts]
user@host# load merge relative /var/tmp/ex-script-snippet.conf
load complete
```

For more information about the **load** command, see CLI Explorer.

Documentation Conventions

Table 1 on page xxv defines notice icons used in this guide.

Table 1: Notice Icons

Icon	Meaning	Description
	Informational note	Indicates important features or instructions.
	Caution	Indicates a situation that might result in loss of data or hardware damage.
	Warning	Alerts you to the risk of personal injury or death.
	Laser warning	Alerts you to the risk of personal injury from a laser.
	Tip	Indicates helpful information.
	Best practice	Alerts you to a recommended use or implementation.

Table 2 on page xxvi defines the text and syntax conventions used in this guide.

Copyright © 2018, Juniper Networks, Inc.

Table 2: Text and Syntax Conventions

Convention	Description	Examples
Bold text like this	Represents text that you type.	To enter configuration mode, type the **configure** command: user@host> **configure**
`Fixed-width text like this`	Represents output that appears on the terminal screen.	`user@host>` **show chassis alarms** `No alarms currently active`
Italic text like this	• Introduces or emphasizes important new terms. • Identifies guide names. • Identifies RFC and Internet draft titles.	• A policy *term* is a named structure that defines match conditions and actions. • *Junos OS CLI User Guide* • RFC 1997, *BGP Communities Attribute*
Italic text like this	Represents variables (options for which you substitute a value) in commands or configuration statements.	Configure the machine's domain name: [edit] root@# **set system domain-name** *domain-name*
Text like this	Represents names of configuration statements, commands, files, and directories; configuration hierarchy levels; or labels on routing platform components.	• To configure a stub area, include the **stub** statement at the **[edit protocols ospf area area-id]** hierarchy level. • The console port is labeled **CONSOLE**.
< > (angle brackets)	Encloses optional keywords or variables.	**stub <default-metric** *metric***>;**
| (pipe symbol)	Indicates a choice between the mutually exclusive keywords or variables on either side of the symbol. The set of choices is often enclosed in parentheses for clarity.	**broadcast | multicast** **(*string1* | *string2* | *string3*)**
# (pound sign)	Indicates a comment specified on the same line as the configuration statement to which it applies.	**rsvp { # Required for dynamic MPLS only**
[ ] (square brackets)	Encloses a variable for which you can substitute one or more values.	**community name members [** ***community-ids*** **]**

Indention and braces ({ })	Identifies a level in the configuration hierarchy.	[edit]
		routing-options {
		  static {
		  route default {
		  nexthop *address*;
		  retain;
		  }
		  }
		}

; (semicolon)	Identifies a leaf statement at a configuration hierarchy level.	

Copyright © 2018, Juniper Networks, Inc.

Table 2: Text and Syntax Conventions (continued)

Convention	Description	Examples
GUI Conventions		
Bold text like this	Represents graphical user interface (GUI) items you click or select.	• In the Logical Interfaces box, select **All Interfaces**. • To cancel the configuration, click **Cancel**.
> (bold right angle bracket)	Separates levels in a hierarchy of menu selections.	In the configuration editor hierarchy, select **Protocols>Ospf**.

Documentation Feedback

We encourage you to provide feedback so that we can improve our documentation. You can use either of the following methods:

- Online feedback system—Click TechLibrary Feedback, on the lower right of any page on the Juniper Networks TechLibrary site, and do one of the following:



  - Click the thumbs-up icon if the information on the page was helpful to you.
  - Click the thumbs-down icon if the information on the page was not helpful to you or if you have suggestions for improvement, and use the pop-up form to provide feedback.

- E-mail—Send your comments to **techpubs-comments@juniper.net**. Include the document or topic name, URL or page number, and software version (if applicable).

Requesting Technical Support

Technical product support is available through the Juniper Networks Technical Assistance Center (JTAC). If you are a customer with an active J-Care or Partner Support Service support contract, or are covered under warranty, and need post-sales technical support, you can access our tools and resources online or open a case with JTAC.

- JTAC policies—For a complete understanding of our JTAC procedures and policies, review the *JTAC User Guide* located at https://www.juniper.net/us/en/local/pdf/resource-guides/7100059-en.pdf.
- Product warranties—For product warranty information, visit https://www.juniper.net/support/warranty/.

Copyright © 2018, Juniper Networks, Inc.

- JTAC hours of operation—The JTAC centers have resources available 24 hours a day, 7 days a week, 365 days a year.

Self-Help Online Tools and Resources

For quick and easy problem resolution, Juniper Networks has designed an online self-service portal called the Customer Support Center (CSC) that provides you with the following features:

- Find CSC offerings: https://www.juniper.net/customers/support/
- Search for known bugs: https://prsearch.juniper.net/
- Find product documentation: https://www.juniper.net/documentation/
- Find solutions and answer questions using our Knowledge Base: https://kb.juniper.net/
- Download the latest versions of software and review release notes: https://www.juniper.net/customers/csc/software/
- Search technical bulletins for relevant hardware and software notifications: https://kb.juniper.net/InfoCenter/
- Join and participate in the Juniper Networks Community Forum: https://www.juniper.net/company/communities/
- Open a case online in the CSC Case Management tool: https://www.juniper.net/cm/

To verify service entitlement by product serial number, use our Serial Number Entitlement (SNE) Tool: https://entitlementsearch.juniper.net/entitlementsearch/

Opening a Case with JTAC

You can open a case with JTAC on the Web or by telephone.

- Use the Case Management tool in the CSC at https://www.juniper.net/cm/.
- Call 1-888-314-JTAC (1-888-314-5822 toll-free in the USA, Canada, and Mexico).

For international or direct-dial options in countries without toll-free numbers, see https://www.juniper.net/support/requesting-support.html.

Copyright © 2018, Juniper Networks, Inc.

PART 1

Subscriber-Aware and Application-Aware Traffic Treatment Overview

- Subscriber-Aware and Application-Aware Traffic Treatment Overview on page 3

Copyright © 2018, Juniper Networks, Inc.

Copyright © 2018, Juniper Networks, Inc.

CHAPTER 1

Subscriber-Aware and Application-Aware Traffic Treatment Overview

- Subscriber-Aware and Application-Aware Traffic Treatment Overview on page 3
- Configuring Subscriber-Aware and Application-Aware Traffic Treatment Overview on page 6

Subscriber-Aware and Application-Aware Traffic Treatment Overview

This topic contains an overview of subscriber-aware and application-aware traffic treatment.

- Introduction on page 3
- Access-Independent Subscriber Traffic Treatment on page 4
- Subscriber Identification Methods on page 4
- Application Identification on page 5
- Policy Control Methods on page 5
- Subscriber-Aware Data Session Logging and Reporting on page 5
- Usage Monitoring on page 5

Introduction

Junos Subscriber Aware identifies the mobile or fixed-line subscriber associated with a data session, and enforces traffic treatment based on policies assigned to the subscriber. This permits highly customizable differentiated services for subscribers. A subscriber policy can be based on Layer 7 application information for the IP flow (for example, YouTube) or can be based on Layer 3/Layer 4 information for the IP flow (for example, the source and destination IP address). Junos Subscriber Aware resides on an MX Series router.

Subscriber-aware policies can specify the following actions:

- Redirecting HTTP traffic to another URL or IP address
- Forwarding packets to a routing instance so that packets are directed to external service chains (predefined sequence of services)
- Setting the forwarding class

Copyright © 2018, Juniper Networks, Inc.

- Setting the maximum bit rate
- Performing HTTP header enrichment (provided by Junos Web Aware, which resides on the same MX Series router as Junos Subscriber Aware)
- Setting the gating status to blocked or allowed

Subscriber-aware policies can also specify the time of day that the policies are in effect.

Access-Independent Subscriber Traffic Treatment

Subscriber identification for both mobile access and wireline access provides a unified experience for the subscriber, regardless of the connection method.

Junos Subscriber Aware resides on an MX Series router that is located between the gateway of the access network and the public network and network services, as shown in Figure 1 on page 4. Subscribers may be controlled by a broadband network gateway (BNG) in a wireline access network, by a gateway GPRS support node (GGSN) in a 2G or 3G network architecture, or by a Packet Data Network Gateway (PGW) in a 4G/LTE network architecture.

Figure 1: Subscriber-Aware Policy Enforcement on the MX Series



Subscriber Identification Methods

You can use the following methods to identify subscribers:

- IP-based—Processes a RADIUS accounting start request to identify the subscriber. An IP-based subscriber session is for one unique user IP address.
- IFL-based—Requires you to configure a subscriber name and specify a set of MX Series router access interfaces for the subscriber. Junos Subscriber Aware assigns all data sessions received on those interfaces to the configured subscriber.

Copyright © 2018, Juniper Networks, Inc.

Application Identification

Layer 7 application identification is provided by Junos Application Aware, which performs deep packet inspection (DPI) to determine whether the subscriber's data packets match an application signature. When an application is identified, the appropriate subscriber policy is applied to the packets. Juniper Networks provides a set of predefined application signatures that you can download and that are periodically updated. You can also configure your own custom application signatures.

Junos Subscriber Aware and Junos Application Aware reside on the same MX Series router, allowing policy control on a single platform.

Policy Control Methods

Subscriber-aware policies can be controlled dynamically by a policy and charging rules function (PCRF) server, can be activated by a RADIUS server, or can be under static control.

Under dynamic control, a PCRF either sends policies to the MX Series router or activates predefined policies that you configured on the MX Series router. Dynamic policy control is provided by Junos Policy Control, which resides on the same MX Series router as Junos Subscriber Aware.

Under RADIUS server control, the RADIUS server controls the activation of your predefined polices but does not send policies to the MX Series router.

Under static control, your predefined policies are not controlled by a PCRF or RADIUS server.

Subscriber-Aware Data Session Logging and Reporting

Junos Subscriber Aware can log data for subscriber-aware data sessions and send that data in an IPFIX format to an external log collector. These logs can include subscriber information, application information, HTTP metadata, data volume, time-of-day information, and source and destination details. You can then use the external collector, which is not a Juniper Networks product, to perform analytics that provide you with insights about subscriber and application usage, enabling you to create packages and policies that increase revenue.

Usage Monitoring

For subscriber data sessions that are under the dynamic policy control of a PCRF, Junos Subscriber Aware can monitor the volume of traffic or amount of time the subscriber uses during a session, and send reports to the PCRF. The PCRF can use this information to adjust the policies for a subscriber.

Related Documentation

- Configuring Subscriber-Aware and Application-Aware Traffic Treatment Overview on page 6

Copyright © 2018, Juniper Networks, Inc.

Configuring Subscriber-Aware and Application-Aware Traffic Treatment Overview

To configure subscriber-aware and application-aware traffic treatment:

1. Configure service PICs and session PICs.

   See "Configuring Service PICs and Session PICs Overview" on page 13.

2. (Optional) Identify Layer 7 applications.

   a. Install application signature packages.

      See "Downloading and Installing Predefined Junos OS Application Signature Packages" on page 24.

   b. Configure custom application signatures.

      See "Configuring Custom Application Signatures" on page 25.

3. (Optional) Configure HTTP header enrichment.

   See "Configuring HTTP Header Enrichment Overview" on page 33.

4. Configure a policy enforcement method.

   - For dynamic policy control, see "Configuring Dynamic Policy Control by PCRF" on page 61.
   - For static policy control, see "Configuring Static Policy Control" on page 62.
   - For RADIUS server policy control, see "Configuring Policy Control by RADIUS Servers" on page 63.

5. Configure the policy enforcement for an IP-based subscriber. An IP-based subscriber session handles traffic for one unique user IP address.

   - If the MX Series router is identified as a RADIUS server for the access gateway, see "Configuring IP-Based TDF Subscriber Setup When MX Series Router Is a RADIUS Server" on page 97
   - If the MX Series router is not identifed as a RADIUS server for the access gateway, see "Configuring IP-Based TDF Subscriber Setup When Accounting Requests Are Snooped" on page 98

6. Configure the policy enforcement for an IFL-based subscriber. An IFL-based subscriber session handles all the traffic received on a specific set of interfaces.

   See "Configuring IFL-Based TDF Subscriber Setup" on page 116.

7. Apply services to a subscriber.

   See "Applying Services to Subscriber-Aware Traffic with a Service Set" on page 124.

8. (Optional) If you configured dynamic policy control, configure Diameter.

 Copyright © 2018, Juniper Networks, Inc.

See "Configuring Diameter Overview" on page 129.

Related Documentation

- Subscriber-Aware and Application-Aware Traffic Treatment Overview on page 3

Copyright © 2018, Juniper Networks, Inc.

Copyright © 2018, Juniper Networks, Inc.

PART 2

Applying Subscriber-Aware and Application-Aware Policies and Services

- Configuring the Service PIC, Session PIC, and TDF Gateway on page 11
- Configuring Application Identification on page 23
- Configuring HTTP Header Enrichment on page 33
- Configuring Policy and Charging Enforcement on page 43
- Configuring TDF Subscribers on page 87
- Configuring Services on page 123
- Configuring Diameter on page 127

Copyright © 2018, Juniper Networks, Inc.

 Copyright © 2018, Juniper Networks, Inc.

CHAPTER 2

Configuring the Service PIC, Session PIC, and TDF Gateway

- TDF Gateway Service PICs and Session PICs for Subscriber-Aware Traffic Treatment on page 11
- Configuring Service PICs and Session PICs Overview on page 13
- Preconfigured Groups for Service PICs and for Session PICs Overview on page 14
- Configuring a Services Interface for a Session PIC or Service PIC on page 16
- Configuring a TDF Gateway on page 16
- Making Predefined Groups Available for Session PIC and Service PIC Configuration on page 17
- Configuring Service PICs on page 18
- Configuring Session PICs on page 19
- Configuring Tracing for TDF Gateway on page 19

TDF Gateway Service PICs and Session PICs for Subscriber-Aware Traffic Treatment

You must configure at least one TDF gateway, one service PIC, and one session PIC to operate subscriber-aware traffic treatment. Each service PIC and session PIC is configured on an MS-MPC, and assigned to a TDF gateway.

- TDF Gateway on page 11
- Service and Session PICs on page 11
- Redundancy for Service PICs and Session PICs on page 13

TDF Gateway

The traffic detection function (TDF) gateway on the MX Series router establishes a context and framework for configuring subscriber-aware services. You assign service PICs and session PICs to the TDF gateway, and specify the call admission control (CAC) parameters for subscriber sessions.

Service and Session PICs

A service PIC provides subscriber-aware policy enforcement and traffic redirection (*steering*) that is application-aware. Traffic steering refers to the capability to direct or

Copyright © 2018, Juniper Networks, Inc.

traverse traffic from a specified source to an endpoint or the adjacent network element in a routing path. The service PIC is configured with software plugins to perform the configured or requested services, which include the policy and charging enforcement function (PCEF), application detection and control, HTTP header enrichment, HTTP redirect, and network address translation.

The service PIC also stores the policy and charging control (PCC) rules that it enforces, and holds the subscriber records and rules that are sent from the session PIC.

The subscriber's assigned TDF logical interface (mif) and the service set that is applied to the mif determine the service PIC to which a packet is sent. See "IP-Based Subscriber Setup Overview" on page 88.

A session PIC supports access subscriber session setup and management, enabling the steering of subscriber traffic to the correct services PIC. The session PIC also sets up a session with the policy and charging rules function (PCRF) so it can receive subscriber PCC rules from the PCRF and send application-start messages to the PCRF.

Figure 2 on page 12 shows an overview of a service PIC and a session PIC and their functions.

Figure 2: Service PIC and Session PIC Overview



Copyright © 2018, Juniper Networks, Inc.

Redundancy for Service PICs and Session PICs

You can configure a service PIC or a session PIC as an individual PIC or with a backup for redundancy. You can configure redundancy by including the interfaces for the primary and the backup PICs in an aggregated multiservices (AMS) interface .

You can configure a session PIC with 1:1 redundancy — a primary session PIC has one backup PIC that does not back up any other session PICs.

You can configure service PICs with N:1 redundancy — multiple service PICs can share the same backup MS-PIC.

In addition to the redundancy configuration, each PIC that is a primary or backup needs to be configured as a session PIC or service PIC at the **[edit unified-edge gateways tdf *gateway-name* system]** hierarchy level.

Related Documentation

- Configuring a TDF Gateway on page 16
- Configuring Session PICs on page 19
- Configuring Service PICs on page 18
- *Configuring Aggregated Multiservices Interfaces*

Configuring Service PICs and Session PICs Overview

You must configure at least one service PIC and one session PIC under a TDF gateway. The service PIC provides subscriber-aware services, such as the policy and charging enforcement function (PCEF), application detection and control, and HTTP header enrichment. The session PIC supports access subscriber sessions, policy and charging rules function (PCRF) sessions, and PCEF library installation from the PCRF.

You can configure service PICs and session PICs on MS-MPCs, and you can configure them either as a member of a redundant group by using an aggregated multiservices (AMS) interface or as a standalone service PIC or session PIC.

To configure service and session PICs:

1. Configure the TDF gateway.

   See "Configuring a TDF Gateway" on page 16.

2. If you want any of the service or session PICs to be members of redundant groups, configure an aggregated multiservices (AMS) interface for each group.

   See *Configuring Aggregated Multiservices Interfaces*.

3. If you want any of the service or session PICs not to be members of redundant groups, configure a services interface.

   See "Configuring a Services Interface for a Session PIC or Service PIC" on page 16.

Copyright © 2018, Juniper Networks, Inc.

4. Install predefined groups that are needed for configuration of the service PICs and session PICs.

   See "Making Predefined Groups Available for Session PIC and Service PIC Configuration" on page 17.

5. Configure each service PIC.

   See "Configuring Service PICs" on page 18.

6. Configure each session PIC.

   See "Configuring Session PICs" on page 19.

Related Documentation

- TDF Gateway Service PICs and Session PICs for Subscriber-Aware Traffic Treatment on page 11
- Preconfigured Groups for Service PICs and for Session PICs Overview on page 14

Preconfigured Groups for Service PICs and for Session PICs Overview

To simplify configuration, Junos Subscriber Aware software includes predefined configuration groups that include the parameters for stable operation of session PICs and service PICs. These groups are included in the **/etc/config/tdf-defaults.conf** file, which you load and then merge with your configuration. Next, you apply the appropriate group to each session PIC and service PIC configuration as follows:

- For each session PIC, apply the **tdf-session-xlp** group.
- For each service PIC that requires application identification but not HTTP header enrichment, apply the **tdf-services-xlp-dpi** group.
- For each service PIC that requires both application identification and HTTP header enrichment, configure the **tdf-services-xlp-dpi-with-hcm** group.

The predefined **tdf-session-xlp** group contains the following statements:

```
[edit groups]
tdf-session-xlp {
   chassis {
      fpc <*> {
         pic <*> {
            adaptive-services {
               service-package {
                  extension-provider {
                     boot-os embedded-junos64;
                     package jservices-mobile;
                  }
               }
            }
         }
      }
   }
```


Copyright © 2018, Juniper Networks, Inc.

```
  }
}
```

The predefined **tdf-services-xlp-dpi** group contains the following statements:

```
[edit groups]
tdf-services-xlp-dpi {
  chassis {
    fpc <*> {
      pic <*> {
        adaptive-services {
          service-package {
            extension-provider {
              boot-os embedded-junos64;
              package jservices-mss;
              package jservices-jdpi;
              package jservices-pcef;
            }
          }
        }
      }
    }
  }
}
```

The predefined **tdf-services-xlp-dpi-with-hcm** group contains the following statements:

```
[edit groups]
tdf-services-xlp-dpi-with-hcm {
  chassis {
    fpc <*> {
      pic <*> {
        adaptive-services {
          service-package {
            extension-provider {
              boot-os embedded-junos64;
              package jservices-mss;
              package jservices-jdpi;
              package jservices-pcef;
              package jservices-hcm;
              package jservices-crypto-base;
            }
          }
        }
      }
    }
  }
}
```

Related Documentation

- Making Predefined Groups Available for Session PIC and Service PIC Configuration on page 17
- Configuring Session PICs on page 19

- Configuring Service PICs on page 18

Configuring a Services Interface for a Session PIC or Service PIC

If a service PIC or a session PIC is not part of a redundant group (the service interface is not part of an aggregated multiservices interface), you must configure a services interface on the MS-MPC for the service PIC.

- Configure the services interface.

```
[edit]
user@host# set interfaces ms-fpc/pic/0 unit logical-unit-number family family address
    address
```

Related Documentation

- *Configuring Aggregated Multiservices Interfaces*
- Configuring Service PICs on page 18
- Configuring Session PICs on page 19
- TDF Gateway Service PICs and Session PICs for Subscriber-Aware Traffic Treatment on page 11

Configuring a TDF Gateway

To run Junos Subscriber Aware, you must configure a traffic detection function (TDF) gateway on the MX Series router. The TDF gateway establishes a context and framework for configuring subscriber-aware services for subscriber data that is accessing the network through the MX Series router. You also specify the call admission control (CAC) parameters for the TDF gateway.

To configure the TDF gateway:

1. Configure a name for the TDF gateway.

```
[edit unified-edge gateways]
user@host# set tdf gateway-name
```

2. Configure the threshold for the maximum amount of CPU that the TDF gateway can use as a percentage from 1 through 90.

```
[edit unified-edge gateways tdf gateway-name]
user@host# set cac cpu cpu-pct
```

   If the amount of CPU that the TDF gateway uses reaches the threshold, the SNMP trap **jnxScgSMCPUThreshHigh** is generated.

3. Configure the maximum number of TDF subscriber sessions that can be running, expressed in thousands of sessions.

Copyright © 2018, Juniper Networks, Inc.

```
[edit unified-edge gateways tdf gateway-name]
user@host# set cac maximum-sessions max-sessions
```

You can configure from 10 through 5000 sessions.

4. Configure the trap threshold for the number of TDF subscriber sessions as a percentage of the maximum number of sessions.

```
[edit unified-edge gateways tdf gateway-name]
user@host# set cac maximum-sessions-trap-percentage max-sessions-pct
```

If the number of subscriber sessions reaches the threshold, the SNMP trap **jnxScgSMSessionThreshHigh** is generated.

5. Configure the threshold for the maximum amount of memory that the TDF gateway can use, as a percentage from 1 through 90.

```
[edit unified-edge gateways tdf gateway-name]
user@host# set cac memory memory-pct
```

If the amount of memory that the TDF gateway uses reaches the threshold, the SNMP trap **jnxScgSMMemoryThreshHigh** is generated.

Related Documentation

- Configuring Service PICs on page 18
- Configuring Session PICs on page 19

Making Predefined Groups Available for Session PIC and Service PIC Configuration

You must make the predefined session PIC and service PIC groups available in your configuration. These groups are used when you configure the session PICs and the service PICs.

To make the predefined groups available in your configuration:

- Load and merge the **tdf-defaults.conf** file.

```
[edit]
user@host# load merge /etc/config/tdf-defaults.conf
```

Related Documentation

- Configuring Service PICs on page 18
- Configuring Session PICs on page 19
- TDF Gateway Service PICs and Session PICs for Subscriber-Aware Traffic Treatment on page 11

Copyright © 2018, Juniper Networks, Inc.

Configuring Service PICs

An MS-MPC must have a service interface configured as a service PIC in order to provide subscriber-aware services, such as the policy and charging enforcement function (PCEF), application detection and control, or HTTP header enrichment. Repeat this procedure for each service interface that you want to serve as a service PIC.

Before you begin to configure a service PIC:

- Make sure that you installed the predefined groups.
- If the service PIC is not part of a redundant group, make sure that you have configured the service interface on the MS-MPC.
- If the service PIC is to function as a member of a redundant group, make sure that you have configured an aggregated multiservices (AMS) interface with the service interface as a member interface.

To configure a service PIC:

1. Add the MS-MPC service interface to the list of service PICs.

   ```
   [edit unified-edge gateways tdf gateway-name system]
   user@host# set service-pics interface interface-name
   ```

   where *interface-name* is ams*n* if you have redundancy configured and is ms-*fpc/pic/*0 if you do not have redundancy configured.

2. Perform one of the following actions:

   - If application identification is required but not HTTP header enrichment, configure the **tdf-services-xlp-dpi** group to run on the PIC.

     ```
     [edit chassis]
     user@host# set fpc slot-number pic pic-number apply-groups tdf-services-xlp-dpi
     ```

   - If both application identification and HTTP header enrichment are required, configure the **tdf-services-xlp-dpi-with-hcm** group to run on the PIC.

     ```
     [edit chassis]
     user@host# set fpc slot-number pic pic-number apply-groups
       tdf-services-xlp-dpi-with-hcm
     ```

Related Documentation

- Configuring a Services Interface for a Session PIC or Service PIC on page 16
- *Configuring Aggregated Multiservices Interfaces*
- Making Predefined Groups Available for Session PIC and Service PIC Configuration on page 17
- TDF Gateway Service PICs and Session PICs for Subscriber-Aware Traffic Treatment on page 11

Copyright © 2018, Juniper Networks, Inc.

Configuring Session PICs

An MS-MPC must have a service interface configured as a session PIC in order to support access subscriber sessions, policy and charging rules function (PCRF) sessions, and PCEF library installation from the PCRF. Repeat this procedure for each service interface that you want to serve as a session PIC.

Before you begin to configure a session PIC:

- Make sure that you have installed the predefined groups.
- If the session PIC is not part of a redundant group, make sure that you have configured the service interface on the MS-MPC.
- If the session PIC is to function as a member of a redundant group, make sure that you have configured an aggregated multiservices (AMS) interface with the service interface as a member interface.

To configure a session PIC:

1. Add the MS-MPC service interface to the list of session PICs.

   ```
   [edit unified-edge gateways tdf gateway-name system]
   user@host# set session-pics interface interface-name
   ```

   where *interface-name* is ams*n* if you have redundancy configured and is ms-*fpc/pic/*0 if you do not have redundancy configured.

2. Configure the **tdf-session-xlp** group to run on the PIC.

   ```
   [edit chassis]
   user@host# set fpc slot-number pic pic-number apply-groups tdf-session-xlp
   ```

Related Documentation

- Making Predefined Groups Available for Session PIC and Service PIC Configuration on page 17
- Configuring a Services Interface for a Session PIC or Service PIC on page 16
- *Configuring Aggregated Multiservices Interfaces*
- TDF Gateway Service PICs and Session PICs for Subscriber-Aware Traffic Treatment on page 11

Configuring Tracing for TDF Gateway

To configure tracing operations for the TDF gateway:

1. Specify that you want to configure tracing options for the TDF gateway.

   ```
   [edit unified-edge gateways tdf gateway-name]
   ```

Copyright © 2018, Juniper Networks, Inc.

```
user@host# edit traceoptions
```

2. Configure the name of the file used for the trace output.

```
[edit unified-edge gateways tdf gateway-name traceoptions]
user@host# set file file-name
```

3. (Optional) Configure the maximum size of each trace file.

```
[edit unified-edge gateways tdf gateway-name traceoptions]
user@host# set file file-name size size
```

4. (Optional) Configure the maximum number of trace files.

```
[edit unified-edge gateways tdf gateway-name traceoptions]
user@host# set file file-name files number
```

5. (Optional) Configure the read permissions for the log file.

```
[edit unified-edge gateways tdf gateway-name traceoptions]
user@host# set file file-name (no-world-readable | world-readable)
```

6. (Optional) Disable remote tracing capabilities.

```
[edit unified-edge gateways tdf gateway-name traceoptions]
user@host# set no-remote-trace
```

7. Configure flags to filter the operations to be logged.

```
[edit unified-edge gateways tdf gateway-name traceoptions]
user@host# set flag flag
```

Table 3 on page 20 describes the flags that you can include.

Table 3: Trace Flags

Flag	Description
all	Trace all operations.
bulkjob	Trace events that are handled by bulk jobs in order to prevent system overload.
config	Trace configuration events.
cos-cac	Trace class of service (CoS) and call admission control (CAC) events.
ctxt	Trace user equipment, Packet Data Network (PDN), or bearer context events.

Copyright © 2018, Juniper Networks, Inc.

Table 3: Trace Flags (continued)

Flag	Description
fsm	Trace mobile subscriber finite state machine (FSM) events.
gtpu	Trace GPRS tunneling protocol, user plane (GTP-U) events.
ha	Trace high availability events.
init	Trace initialization events.
pfem	Trace Packet Forwarding Engine Manager events.
stats	Trace **stats** events. This flag is used internally by Juniper Networks engineers.
waitq	Trace **waitq** events. This flag is used internally by Juniper Networks engineers.

8. Configure the level of tracing.

```
[edit unified-edge gateways tdf gateway-name traceoptions]
user@host# set level (all | critical | error | info | notice | verbose | warning)
```

Related Documentation

- traceoptions on page 505

Copyright © 2018, Juniper Networks, Inc.

 Copyright © 2018, Juniper Networks, Inc.

CHAPTER 3

Configuring Application Identification

- Application Identification Overview on page 23
- Downloading and Installing Predefined Junos OS Application Signature Packages on page 24
- Configuring Custom Application Signatures on page 25
- Uninstalling a Predefined Junos OS Application Signature Package on page 31

Application Identification Overview

Junos Application Aware is an infrastructure plug-in on MS-MPC service PICs that provides information to clients about application protocol bundles based on deep packet inspection (DPI) of application signatures. These clients can be any of the plug-ins on the MX Series router service chain, such as traffic detection function (TDF), that request application classification data. Starting in Junos OS Release 16.1R4 and then in Junos OS Release 17.2R1, application identification is available in Junos OS Broadband Subscriber Management.

In application identification, you can apply application signatures as follows:

- **Predefined signatures**—Junos Application Aware comes with a bundle of predefined, preinstalled application signatures, but we recommend that you download and install the latest version of predefined signatures. As new sets of signatures are supported, they are compiled and made available for you to download.
- **Custom application signatures**—For any application signatures that are not predefined, you can create custom signatures for HTTP, SSL, and stream signature contexts and install them for application identification. After you have configured and committed custom signatures, they are serialized and merged with the predefined application signatures. You can specify the following types of custom application signatures:

Copyright © 2018, Juniper Networks, Inc.

- **Address based**—You can define an application identification based on a specific IP address, or port, or both where a source IP address, destination IP address, or both are used for a known application in a customer's network. This is useful, for example, when a Session Initiation Protocol (SIP) server initiates a session from its well known port, 5060. The customer can put the SIP server IP address and port 5060 as source IP/port for the SIP application. This method provides efficiency and accuracy of application identification for customer's network.
- **Internet Control Message Protocol (ICMP) based**—Application identification based on types of ICMP messages.
- **IP protocol based**—Application identification based on IP protocol. TCP, UDP, and ICMP are not supported for this method of signature creation.
- **Pattern-matching signatures**—Application based on pattern matching combined with Layer 7 protocol identification.

Release History Table

Release	Description
16.1R4	Starting in Junos OS Release 16.1R4 and then in Junos OS Release 17.2R1, application identification is available in Junos OS Broadband Subscriber Management.

Related Documentation

- Configuring Custom Application Signatures on page 25
- Downloading and Installing Predefined Junos OS Application Signature Packages on page 24

Downloading and Installing Predefined Junos OS Application Signature Packages

To download, install, and verify the installation of predefined Junos OS application signature packages:

1. Configure the URL for the application signature packages server.

```
[edit services application-identification]
user@host# set download url https://services.netscreen.com/cgi-bin/index.cgi
```

2. Download the application signature package.
   - To download the latest signature package, enter the following command:

```
user@host> request services application-identification download
```

   - To download a specific, known signature package, include the version number:

```
user@host> request services application-identification download version
  version-number
```


Copyright © 2018, Juniper Networks, Inc.

3. Confirm the successful download of the package.

```
user@host> request services application-identification download status
```

```
Downloading application package succeed.
```

4. Install the application signature package.

```
user@host> request services application-identification install
```

5. Confirm the successful installation of the application signature package.

```
user@host> request services application-identification install status
```

```
Compiling application signatures of package version.
```

or

```
Install application package succeed
```

Related Documentation

- Uninstalling a Predefined Junos OS Application Signature Package on page 31
- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25

Configuring Custom Application Signatures

You can configure custom application definitions using custom signatures. These definitions enable identification of protocol bundles through deep packet inspection (DPI) for use by interested services in the service chain.

Before you configure custom application signatures, ensure that **jservices-jdpi** is configured on all required interfaces of your MS-MPC. To review how to configure the package on your MS-MPC:

- For Junos OS Subscriber Aware, see "Preconfigured Groups for Service PICs and for Session PICs Overview" on page 14.
- For Junos OS Broadband Subscriber Management, see *Installing Services Packages for Subscriber Management Application-Aware Policy Management*.

To configure one or more custom application signatures:

1. Specify a name for the application.

```
[edit services application-identification]
user@host# edit application application-name
```

Copyright © 2018, Juniper Networks, Inc.

For example:

```
[edit services application-identification]
user@host# edit application my:http
```

2. Specify a description for the application.

```
[edit services application-identification application application-name]
user@host# set description description
```

For example:

```
[edit services application-identification application my:http]
user@host# set description "Test application"
```

3. Specify an alternative name for the application.

```
[edit services application-identification application application-name]
user@host# set alt-name alt-name
```

For example:

```
[edit services application-identification application my:http]
user@host# set alt-name my:http-app
```

4. Enable saving of the application system cache (ASC).

```
[edit services application-identification application my:http]
user@host# set cacheable
```

5. Specify the name of the Junos OS release for compatibility.

```
[edit services application-identification application application-name]
user@host# set compatibility junos-compatibility-version
```

For example:

```
[edit services application-identification application my:http]
user@host# set compatibility 17.1
```

6. Specify any desired application tags, consisting of a user-defined name and value.

```
[edit services application-identification application application-name]
user@host# set tags tag-name tag-value
```

For example:

```
[edit services application-identification application my:http]
user@host# set tags traffic-type video-stream
```


Copyright © 2018, Juniper Networks, Inc.

7. Specify one or more address-based signatures.

   a. Specify a source IP address.

      ```
      [edit services application-identification application application-name]
      user@host# set address-mapping name source ip ip-address-prefix
      ```

      For example:

      ```
      [edit services application-identification application my:http]
      user@host# set address-mapping addr1 source ip 192.0.2.7/24
      ```

   b. Specify a destination IP address.

      ```
      [edit services application-identification application application-name]
      user@host# set address-mapping name destination ip ip-address-prefix
      ```

      For example:

      ```
      [edit services application-identification application my:http]
      user@host# set address-mapping addr1 destination ip 198.51.100.6/32
      ```

   c. Specify the sequential order for using this signature.

      ```
      [edit services application-identification application application-name]
      user@host# set address-mapping name order order
      ```

      For example:

      ```
      [edit services application-identification application my:http]
      user@host# set address-mapping addr1 order 1
      ```

   d. Specify the priority for using this signature instead of using any matched predefined signatures.

      ```
      [edit services application-identification application application-name]
      user@host# set address-mapping name order-priority (high | low)
      ```

      For example:

      ```
      [edit services application-identification application my:http]
      user@host# set address-mapping addr1 order-priority high
      ```

8. Specify an ICMP-based signature.

   a. Specify ICMP type and code.

      ```
      [edit services application-identification application application-name]
      user@host# set icmp-mapping type icmp-type code icmp-code
      ```

      For example:

      ```
      [edit services application-identification application my:http]
      ```

Copyright © 2018, Juniper Networks, Inc.

```
user@host# set icmp-mapping type 33 code 34
```

b. Specify the sequential order for using this signature.

```
[edit services application-identification application application-name]
user@host# set icmp-mapping order order
```

For example:

```
[edit services application-identification application my:http]
user@host# set icmp-mapping order 2
```

c. Specify the priority for using this signature instead of using any matched predefined signatures.

```
[edit services application-identification application application-name]
user@host# set icmp-mapping order-priority (high | low)
```

For example:

```
[edit services application-identification application my:http]
user@host# set icmp-mapping order-priority high
```

9. Specify an IP protocol-based signature.

a. Specify the IP protocol by protocol number.

```
[edit services application-identification application application-name]
user@host# set ip-protocol-mapping protocol protocol-number
```

For example:

```
[edit services application-identification application my:http]
user@host# set ip-protocol-mapping protocol 103
```

b. Specify the sequential order for using this signature.

```
[edit services application-identification application application-name]
user@host# set ip-protocol-mapping order order
```

For example:

```
[edit services application-identification application my:http]
user@host# set ip-protocol-mapping order 3
```

c. Specify the priority for using this signature instead of using any matched predefined signatures.

```
[edit services application-identification application application-name]
user@host# set ip-protocol-mapping order-priority (high | low)
```

For example:

Copyright © 2018, Juniper Networks, Inc.

```
[edit services application-identification application my:http]
user@host# set ip-protocol-mapping order-priority high
```

10. Specify one or more Layer 4 and Layer 7 signatures using pattern matching in conjunction with a Layer 4 protocol.

    a. Specify a name for the Layer 4 Layer 7 signature.

    ```
    [edit services application-identification application application-name]
    user@host# edit over l4-l7-signature-name
    ```

    For example:

    ```
    [edit services application-identification application my:http]
    user@host# edit over myl3l7
    ```

    b. Specify the sequential order for using this signature.

    ```
    [edit services application-identification application application-name over
      l4-l7-signature-name]
    user@host# set order order
    ```

    For example:

    ```
    [edit services application-identification application my:http over myl3l7]
    user@host# set order 1
    ```

    c. Specify the priority for using this signature instead of using any matched predefined signatures.

    ```
    [edit services application-identification application application-name over
      l4-l7-signature-name]
    user@host# set order-priority (high | low)
    ```

    For example:

    ```
    [edit services application-identification application my:http over myl3l7]
    user@host# set order-priority high
    ```

    d. Specify the protocol.

    ```
    [edit services application-identification application application-name over
      l4-l7-signature-name]
    user@host# set protocol (http | ssl | tcp | udp)
    ```

    For example:

    ```
    [edit services application-identification application my:http over myl3l7]
    user@host# set protocol http
    ```

    e. (Optional) Specify that members are to be matched in order.

    ```
    [edit services application-identification application application-name over
      l4-l7-signature-name]
    ```

Copyright © 2018, Juniper Networks, Inc.

```
user@host# set chain-order
```

f. Specify a member. You can repeat this step to define up to four members.

```
[edit services application-identification application application-name over
  l4-l7-signature-name]
user@host# edit member member-name
```

For example:

```
[edit services application-identification application my:http over myl3l7]
user@host# edit member m01
```

g. Specify the member's identifying pattern.

```
[edit services application-identification application application-name over
  l4-l7-signature-name member member-name]
user@host# set pattern pattern
```

For example:

```
[edit services application-identification application my:http over myl3l7 member
  m01]
user@host# set pattern "www\.facebook\.net"
```

h. Specify the direction of flows to which pattern matching is applied.

```
[edit services application-identification application application-name over
  l4-l7-signature-name member member-name]
user@host# set direction (any | client-to-server | server-to-client)
```

For example:

```
[edit services application-identification application my:http over myl3l7 member
  m01]
user@host# set direction any
```

11. Specify the number of check-bytes. This option applies to TCP and UDP only.

```
[edit services application-identification application application-name over
  l4-l7-signature-name member member-name]
user@host# set check-bytes max-bytes-to-check
```

For example:

```
[edit services application-identification application my:http over myl3l7 member m01]
user@host# set check-bytes 5000
```

12. Specify the order to be used if conflicts occur during the application classification. In such a case, the application with lowest order is classified.

Copyright © 2018, Juniper Networks, Inc.

```
[edit services application-identification application application-name over
  l4-l7-signature-name member member-name]
user@host# set order order
```

For example:

```
[edit services application-identification application my:http over myl3l7 member m01]
user@host# set order 1
```

13. Specify the priority to define the order of precedence of custom signatures over other signatures. A value of **high** indicates highest precedence and **low** indicates lowest precedence.

```
[edit services application-identification application application-name over
  l4-l7-signature-name member member-name]
user@host# set order-priority (high | low)
```

For example:

```
[edit services application-identification application my:http over myl3l7 member m01]
user@host# set order-priority high
```

Related Documentation

- Application Identification Overview on page 23

Uninstalling a Predefined Junos OS Application Signature Package

To uninstall the current application signature package:

- Enter the uninstall command.

```
user@host> request service application-identification uninstall
```

Related Documentation

- Downloading and Installing Predefined Junos OS Application Signature Packages on page 24

Copyright © 2018, Juniper Networks, Inc.

 Copyright © 2018, Juniper Networks, Inc.

CHAPTER 4

Configuring HTTP Header Enrichment

- Junos Web Aware HTTP Header Enrichment Overview on page 33
- Configuring HTTP Header Enrichment Overview on page 33
- Configuring Tag Rules on page 35
- Configuring HCM Profiles and Assigning Tag Rules on page 40

Junos Web Aware HTTP Header Enrichment Overview

Subscribers accessing Web-based services often need to have content added to the HTTP headers sent back and forth as part of the client-server exchange. You can use Junos Web Aware to configure HTTP header enrichment on the MX Series router. Junos Web Aware allows tag insertions. In addition to the International Mobile Subscriber Identity (IMSI) and mobile station ISDN (MSISDN) tags, you can specify tags for International Mobile Station Equipment Identity (IMEI), TDF gateway IP address, and Subscriber IP address.

For example, this feature can add the last line to this sequence of HTTP headers:

```
GET /256k.html HTTP/1.1
Host: 10.45.45.2
Accept */*
Accept-Language: en-us
Accept-Encoding: gzip, deflate
User-Agent: Mozilla/4.0 (compatible; MSIE 6.0; Windows NT 5.1; NET CLR 1.1.4322
name: value
X-MSISDN: <MSISDN #>
```

You can also use HTTP header enrichment to replace a byte of the IPv4 or IPV6 user address in the HTTP header with a value you specify.

Related Documentation

- Configuring HTTP Header Enrichment Overview on page 33
- hcm on page 319

Configuring HTTP Header Enrichment Overview

You configure HTTP header enrichment by configuring tag rules and an HCM profile that points to specific tag rules. Tag rules identify the HTTP enrichment actions to take when

Copyright © 2018, Juniper Networks, Inc.

the conditions in the tag rule are matched. For subscriber traffic under static policy control, a tag rule is used if it is included in the HCM profile specified in a PCC rule that the traffic matches. For subscribers under dynamic policy control, a message from the PCRF identifies the configured HCM profile to use for HTTP header enrichment.

If you change the configuration of tag rules during an existing subscriber data session, the changes do not impact the existing session. The configuration changes are used by any new subscriber data sessions.

To configure HTTP header enrichment for a subscriber:

1. Configure one or more tag rules to specify the HTTP header enrichment actions.

   See "Configuring Tag Rules" on page 35.

2. Configure an HCM profile and assign tag rules to it.

   See "Configuring HCM Profiles and Assigning Tag Rules" on page 40.

3. (For subscribers under static policy control) Assign the HCM profile to a PCC action profile.

   See "Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware" on page 67.

4. (For subscribers under static policy control) Configure a PCC rule that includes the PCC action profile.

   See "Configuring Policy and Charging Control Rules" on page 70.

5. Enable HTTP enrichment for a subscriber's service set.

   See "Applying Services to Subscriber-Aware Traffic with a Service Set" on page 124.

Related Documentation

- Junos Web Aware HTTP Header Enrichment Overview on page 33.

Copyright © 2018, Juniper Networks, Inc.

Configuring Tag Rules

Tag rules include one or more **term** statements that identify the HTTP enrichment actions to take when the conditions in the **term** are matched. You must configure at least one **tag** in the **then** clause of a **term**, and you can configure multiple tags.

Terms are evaluated in the order they are configured. If a data packet matches all the criteria in the **from** statement in a **term**, then the actions specified in the **then** statement of the **term** are applied. If the **from** statement does not identify any criteria, then all traffic matches. After a data packet matches a term, further terms are not evaluated. If no terms match, then the HTTP header is not enriched.

To configure a tag rule:

1. Configure the list of tag attributes that may be used in tag rules.

   ```
   [edit services hcm]
   user@host# set tag-attribute tag-attr-name
   ```

   The tag attributes currently supported are **apn**, **ggsnipv4**, **ggsnipv6**, **imei**, **imsi**, **ipv4addr**, **ipv6addr**, and **msisdn**. To configure multiple tag attributes, include them in square brackets ([ ]).

   For example:

   ```
   [edit services hcm]
   user@host# set tag-attribute [msisdn apn]
   ```

2. Configure a name for the tag rule.

   ```
   [edit services hcm]
   user@host# set tag-rule rule-name
   ```

   For example:

   ```
   [edit services hcm]
   user@host# set tag-rule rule1
   ```

3. Configure a term for the tag rule.

   ```
   [edit services hcm set tag-rule rule-name]
   user@host# set term term-number
   ```

   NOTE: The term argument must have a numeric value.

   For example:

   ```
   [edit services hcm set tag-rule rule1]
   ```

Copyright © 2018, Juniper Networks, Inc.

```
user@host# set term 1
```

4. (Optional) Specify the prefix that the HTTP request destination IP address must match.

   ```
   [edit services hcm tag-rule rule-name term term-number from]
   user@host# set destination-address prefix
   ```

   For example:

   ```
   [edit services hcm tag-rule rule1 term 1 from]
   user@host# set destination-address 192.0.2.0/24
   ```

   You can also specify the type of address to match:

   ```
   [edit services hcm tag-rule rule-name term term-number from]
   user@host# set destination-address (any-ipv4 | any-ipv6 | any-unicast)
   ```

   You can specify multiple prefixes or address types by including the **destination-address** statement multiple times.

5. (Optional) Specify an IP address range that the HTTP request destination IP address must match.

   ```
   [edit services hcm tag-rule rule-name term term-number from]
   user@host# set destination-address-range low address high address
   ```

   For example:

   ```
   [edit services hcm tag-rule rule1 term 1 from]
   user@host# set destination-address-range low 10.10.10.1 high 10.10.10.255
   ```

   You can specify multiple address ranges by including the **destination-address-range** statement multiple times.

6. (Optional) Specify the destination prefix list that the HTTP request destination IP address must match. The prefix list must already be defined at the **[edit policy-options prefix-list]** hierarchy level.

   ```
   [edit services hcm tag-rule rule-name term term-number from]
   user@host# set destination-prefix-list prefix-name
   ```

   For example:

   ```
   [edit services hcm tag-rule rule1 term 1 from]
   user@host# set destination-prefix-list customer1
   ```

   You can specify multiple prefix lists by including the **destination-prefix-list** statement multiple times.

Copyright © 2018, Juniper Networks, Inc.

7. (Optional) Specify any addresses that you want to exclude from matching the HTTP request destination IP address with the **except** statement. To exclude addresses, you must also configure addresses that do match in a **destination-address**, **destination-address-range**, or **destination-prefix-list** statement at the **[edit services hcm tag-rule *rule-name* term *term-number* from]** hierarchy level.

   For example:

   ```
   [edit services hcm tag-rule rule1 term 1 from]
   user@host# set destination-address-range low 10.10.10.1 high 10.10.10.255
   user@host# set destination-address 10.10.10.9/32 except
   ```

   This matches all the addresses in the destination range except 10.10.10.9.

   You can use **except** in the following statements at the **[edit services hcm tag-rule *rule-name* term *term-number* from]** hierarchy level:

   ```
   destination-address {
     any-ipv4 except;
     any-ipv6 except;
     any-unicast except;
     prefix except;
   }
   destination-address-range {
     high address low address except;
   }
   destination-prefix-list {
     prefix-name except;
   }
   ```

8. (Optional) Specify a port range that the HTTP request destination port number must match.

   ```
   [edit services hcm tag-rule rule-name term term-number from]
   user@host# set destination-port-range high port-number low port-number
   ```

   You can specify multiple port ranges by including the **destination-port-range** statement multiple times.

   NOTE: If you do not specify any ports or port ranges to match, then all ports are matched.

9. (Optional) Specify the HTTP request destination port number that must be matched.

   ```
   [edit services hcm tag-rule rule-name term term-number from]
   user@host# set destination-ports value
   ```

   You can specify multiple ports by including the **destination-ports** statement multiple times.

Copyright © 2018, Juniper Networks, Inc.

10. (Optional) Specify that you want to apply all HTTP header enrichment actions specified in the **then** statement of the tag rule to all HTTP requests by not including any matching conditions in the **from** statement. You must include a **from** statement in each **term** of a tag rule.

    ```
    [edit services hcm tag-rule rule-name term term-number ]
    user@host# set from
    ```

    For example:

    ```
    [edit services hcm tag-rule rule2 term 1]
    user@host# set from
    [edit services hcm tag-rule rule2 term 1]
    user@host# set then count
    ```

11. Configure a name for a tag.

    ```
    [edit services hcm tag-rule rule-name term term-number then]
    user@host# set tag tag-name
    ```

    For example:

    ```
    [edit services hcm tag-rule rule1 term 1 then]
    user@host# set tag msisdn-tag
    ```

12. Configure the tag header that the tag applies to the HTTP header.

    ```
    [edit services hcm tag-rule rule-name term term-number then tag tag-name]
    user@host# set tag-header header
    ```

    For example:

    ```
    [edit services hcm tag-rule rule1 term 1 then tag msisdn-tag]
    user@host# set tag-header X_MSISDN
    ```

    You can configure a maximum of 16 unique tag headers.

    The *header* values cannot be **accept**, **accept-charset**, **accept-encoding**, **accept-language**, **authorization**, **expect**, **host**, **if-match**, **if-modified-since**, **if-none-match**, **if-range**, **if-unmodified-since**, **max-forwards**, **proxy-authorization**, **referer**, **user-agent**, or **x-moz**. These header values are reserved; you cannot configure them.

13. Specify the tag attribute that the tag applies to the HTTP header. To specify multiple attributes at one time, include the attributes in square brackets ([]).

    ```
    [edit services hcm tag-rule rule-name term term-number then tag tag-name]
    user@host# set tag-attribute [tag-attr-name]
    ```


Copyright © 2018, Juniper Networks, Inc.

NOTE: The tag attribute must be listed in the tag attributes configured in Step 1.

For example:

```
[edit services hcm tag-rule rule1 term 1 then tag msisdn-tag]
user@host# set tag-attribute msisdn
```

14. Specify the separator that the tag uses in the HTTP header.

```
[edit services hcm tag-rule rule-name term term-number then tag tag-name]
user@host# set tag-separator separator
```

For example:

```
[edit services hcm tag-rule rule1 term 1 then tag msisdn-tag]
user@host# set tag-separator /
```

15. (Optional) Specify a hash method and prefix key for the insertion of the tag in the HTTP header.

```
[edit services hcm tag-rule rule-name term term-number then tag tag-name encrypt]
user@host# set hash algorithm prefix hash-prefix
```

Currently, only the **md5** hash method is supported.

For example:

```
[edit services hcm tag-rule rule1 term 1 then tag msisdn-tag encrypt]
user@host# set hash md5 prefix gatewaykey1
```

16. (Optional) Enable the collection of statistics for HTTP header enrichment for the tag rule.

```
[edit services hcm tag-rule rule-name term term-number then
user@host# set count
```

17. (Optional) Configure how the tag replaces a byte of the IPv4 or IPv6 user address with a different value in the HTTP header.

```
[edit services hcm tag-rule rule-name term term-number then tag tag-name]
user@host# set (ipv4-mask ipv4-mask | ipv6-mask ipv6-mask) (ipv4-or-value
  ipv4-or-value | ipv6-or-value ipv6-or-value)
```

To identify the byte you want to replace, enter **255** for IPv4 or **ff** for IPv6 in the corresponding byte of the **ipv4-mask** or **ipv6-mask** and enter zero in the other bytes.

Copyright © 2018, Juniper Networks, Inc.

To specify the new value for that byte, enter the value in the corresponding byte of the **ipv4-or-value** or the **ipv6-or-value** and enter zero in the other bytes.

For example, the following replaces the first byte of the IPv4 user address with the value 168:

```
[edit services hcm tag-rule tag1 term term1 then tag subscip4]
user@host# set ipv4-mask 255.0.0.0 ipv4-or-value 168.0.0.0
```

18. If you want to configure more tags for the **then** statement in the term, repeat Step 11 through Step 17.

19. If you want to configure another **term** statement for the tag rule, repeat Step 3 through Step 18.

Related Documentation

- Configuring HTTP Header Enrichment Overview on page 33
- Configuring HCM Profiles and Assigning Tag Rules on page 40
- Junos Web Aware HTTP Header Enrichment Overview on page 33

Configuring HCM Profiles and Assigning Tag Rules

The HCM profile for a subscriber specifies the tag rules to apply to a subscriber's traffic. Tag rules identify the HTTP enrichment actions to take when the conditions in the tag rule are matched. You can have a maximum of 100 HCM profiles.

For subscriber-aware traffic under static policy control, a tag rule is used if it is included in the HCM profile specified in a PCC rule that the traffic matches. For subscriber-aware traffic under dynamic policy control, a message from the PCRF identifies the configured HCM profile and tag rules to use for HTTP header enrichment.

To configure an HCM profile:

1. Configure the HCM profile name.

```
[edit services hcm]
user@host# set profile profile-name
```

For example:

```
[edit services hcm]
user@host# set profile hcm1
```

2. Assign a tag rule to the HCM profile.

```
[edit services hcm profile profile-name]
user@host# set tag-rule rule-name
```

For example:

Copyright © 2018, Juniper Networks, Inc.

```
[edit services hcm profile hcm1]
user@host# set tag-rule rule1
```

Related Documentation

- Configuring HTTP Header Enrichment Overview on page 33
- Configuring Tag Rules on page 35
- Junos Web Aware HTTP Header Enrichment Overview on page 33
- Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware on page 67

Copyright © 2018, Juniper Networks, Inc.

Copyright © 2018, Juniper Networks, Inc.

CHAPTER 5

Configuring Policy and Charging Enforcement

- Understanding Junos Subscriber Aware Policy and Charging Enforcement Function (PCEF) on page 44
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- Understanding How Subscriber-Aware Policy and Charging Control Rules Are Provisioned Dynamically by a PCRF on page 49
- Understanding How Subscriber-Aware Policy and Charging Control Rules Are Provisioned Statically on page 52
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53
- Understanding PCEF Profiles on page 56
- Understanding Network Elements on page 57
- Understanding AAA Profiles on page 58
- Understanding Static Time-of-Day PCC Rule Activation and Deactivation on page 59
- Understanding Usage Monitoring for TDF Subscribers on page 59
- Configuring Dynamic Policy Control by PCRF on page 61
- Configuring Static Policy Control on page 62
- Configuring Policy Control by RADIUS Servers on page 63
- Configuring Service Data Flow Filters on page 64
- Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware on page 67
- Configuring Policy and Charging Control Rules on page 70
- Configuring a Policy and Charging Control Rulebase on page 73
- Configuring RADIUS Servers on page 74
- Configuring RADIUS Network Elements on page 77
- Configuring an AAA Profile on page 78
- Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Dynamic Policies on page 80

Copyright © 2018, Juniper Networks, Inc.

- Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Static Policies on page 81
- Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Policies That a RADIUS Server Controls on page 82
- Configuration of Static Time-of-Day PCC Rule Activation and Deactivation Overview on page 83
- Configuring the NTP Server on page 84
- Configuring Static Time-of-Day PCC Rule Activation and Deactivation in a Junos OS Subscriber Aware PCEF Profile on page 84
- Configuring TDF Subscriber Usage Monitoring for Traffic That Matches Predefined PCC Rules on page 85

Understanding Junos Subscriber Aware Policy and Charging Enforcement Function (PCEF)

The policy and charging enforcement function (PCEF) of Junos Subscriber Aware enforces policy and charging control (PCC) rules for the treatment of a subscriber's packets. A PCC rule is installed on, and enforced by, the PCEF. The PCC rules can be under static control, under dynamic control of the policy and charging rules function (PCRF), or under activation/deactivation control of a RADIUS server, depending on the PCEF profile that is assigned to a subscriber.

- Static Policy Control on page 44
- Dynamic Policy Control on page 45
- RADIUS Server Policy Control on page 45

Static Policy Control

For static policies, the PCEF enforces PCC rules you predefined on the MX Series router with no interaction from the PCRF or a RADIUS server, as shown in Figure 3 on page 44.

Figure 3: Static Policy Control



Copyright © 2018, Juniper Networks, Inc.

Dynamic Policy Control

For dynamic policies, the PCEF acts upon messages received from the PCRF. The PCRF is the central entity that makes policy and charging decisions based on input from different sources, such as mobile operator configuration, user subscription information, and services information. The PCC rules are either provisioned by the PCRF and sent to the PCEF over the Gx interface using Diameter AVPs, or predefined on the MX Series router and activated by a Diameter message from the PCRF. The PCEF also provides the PCRF with subscriber and access information. See Figure 4 on page 45.

When PCC rules are under dynamic control, the PCEF gives precedence to rules sent by the PCRF over rules that are predefined on the PCEF.

Figure 4: Dynamic Policy Control



RADIUS Server Policy Control

For polices under control of a RADIUS server, a RADIUS server activates and deactivates policy and PCC rules that you have predefined on the MX Series router, as shown in Figure 5 on page 46.

Copyright © 2018, Juniper Networks, Inc.

Figure 5: RADIUS Server Policy Control



Related Documentation

- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- Understanding How Subscriber-Aware Policy and Charging Control Rules Are Provisioned Dynamically by a PCRF on page 49
- Understanding How Subscriber-Aware Policy and Charging Control Rules Are Provisioned Statically on page 52
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment

You can configure policy and charging control (PCC) rules to define the treatment to apply to specific service data flows or to packets associated with specific applications. A PCC rule is applicable to a subscriber's traffic if the rule is in the subscriber's PCEF profile.

These predefined PCC rules contain a **from** clause that identifies the service data flows or applications, and a **then** clause that specifies the PCC action profile that identifies the treatment to apply.

A predefined PCC rule can be used in three ways:

- When PCC rules are under static control, predefined rules are the only rules used. The provisioning of PCC rules involves no interaction from the policy and charging rules function (PCRF) or a RADIUS server.
- When PCC rules are under dynamic control, a predefined PCC rule must be activated by the PCRF. (With dynamic control, PCC rules can also be sent from the PCRF.)
- When PCC rules are under RADIUS server control, a predefined PCC rule must be activated by the RADIUS server.

This topic includes the following sections:

- Understanding Service Data Flow Filters on page 47
- Understanding Application Filters on page 48
- Understanding PCC Action Profiles on page 48

Understanding Service Data Flow Filters

Service data flow (SDF) filters (flow identifiers) are specified in the **from** clause of a PCC rule to identify IP packets belonging to a particular Layer 3 or Layer 4 service data flow. If the IP packet matches the SDF filter in a PCC rule, the treatment specified in the PCC action profile in the **then** clause of the rule is applied.

To configure Layer 3 or Layer 4 SDF filters, you specify one or more of the following parameters:

- Source IP address
- Destination IP address
- Source port
- Destination port
- Layer 4 protocol (UDP or TCP)

Copyright © 2018, Juniper Networks, Inc.

Understanding Application Filters

Applications or application groups are specified in the **from** clause of a PCC rule to identify IP packets belonging to a specific application. If the IP packet is for an application identified in a PCC rule, the treatment specified in the PCC action profile in the **then** clause of the rule is applied.

To configure application-aware PCC rules, you can specify one or more of the following parameters:

- application—Specifies the name of an application. This can be a Layer 7 protocol (for example, HTTP) or a particular application running on a Layer 7 protocol, such as Facebook and Yahoo Messenger.
- application-group—Specifies the name of an application group, which can be used to process a number of applications or subgroups at the same time.

NOTE: **Application-aware PCC rules that reference specified applications can include wildcard or specific Layer-3 SDF filters, Layer-4 SDF filters, or both.**

Understanding PCC Action Profiles

A PCC rule configuration includes an action profile in the **then** clause that defines the treatment to apply to a service data flow or to a packet belonging to an application identified in the **from** clause of the rule. You can configure a PCC action profile that is used in one or more PCC rules to provide the following functionality:

- HTTP redirection—Specifies HTTP redirection to a URL. You can use this action only for PCC rules that match only HTTP-based applications and all flows.
- HTTP Steering path—Specifies an IPv4 or IPv6 address for steering HTTP packets. You can use this action only for PCC rules that match only HTTP-based applications and all flows.

NOTE: **A single PCC rule can support either HTTP redirection or HTTP steering path, but not both.**

- Steering with a routing instance—Specifies a routing instance for steering of packets to a third-party server to apply services or to a local or external service chain. You can configure different routing instances for traffic from the subscriber (uplink) and traffic to the subscriber (downlink).
- Keep existing steering—Specifies that steering attributes configured in a PCC action profile that a PCC rule applies to a data flow session when it begins will continue to be applied to the data flow when the PCC rule match conditions are modified, deleted, or added to.
- Forwarding class—Specifies the forwarding class that you want assigned to the packet.

Copyright © 2018, Juniper Networks, Inc.

- Maximum bit rate—Specifies the maximum bit rate for uplink and for downlink traffic.
- HCM profile—Specifies the profile that identifies the HTTP header enrichment rules to apply. You can use this action only for PCC rules that match only HTTP-based applications and all flows.
- Gating status—Specifies whether to block or to forward IP packets.

Related Documentation

- Understanding Junos Subscriber Aware Policy and Charging Enforcement Function (PCEF) on page 44
- Understanding How Subscriber-Aware Policy and Charging Control Rules Are Provisioned Dynamically by a PCRF on page 49
- Understanding How Subscriber-Aware Policy and Charging Control Rules Are Provisioned Statically on page 52
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53
- Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware on page 67
- Configuring Service Data Flow Filters on page 64
- Configuring Policy and Charging Control Rules on page 70
- Application Identification Overview on page 23

Understanding How Subscriber-Aware Policy and Charging Control Rules Are Provisioned Dynamically by a PCRF

With dynamic policy control, the policy and charging rules function (PCRF) controls the provisioning of policy and charging control (PCC) rules on the Junos Subscriber Aware PCEF for a subscriber. Dynamic policy control is enabled when a dynamic-policy-control policy and charging enforcement function (PCEF) profile is assigned to a subscriber. Dynamic policy control requires Junos Policy Control.

This topic includes the following sections:

- Policy Decisions on page 49
- Supported Operations on page 50
- Methods for Provisioning PCC Rules on page 50

Policy Decisions

The PCRF is central in making policy and charging control decisions and can install, activate, modify, or deactivate a PCC rule on the PCEF at any time. The PCRF can make its policy and charging control decisions based on different sources, including:

Copyright © 2018, Juniper Networks, Inc.

- Subscription information for the user equipment that is received from the subscription profile repository (SPR)
- Operator configuration in the PCRF
- Information from the access network about the access technology
- Information from the PCEF, such as the name of the application that the subscriber is using

The Gx interface is used to send PCC rule provisioning information from the PCRF to the PCEF, and to provide notification of traffic-plane events from the PCEF to the PCRF.

Supported Operations

Junos Subscriber Aware and Junos Policy Control support the following operations with the PCRF:

- Install or modify rules—The PCRF sends the **Charging-Rule-Install** AVP to install a PCC rule that is not already installed or modify an existing rule on the PCEF.
- Remove rules—The PCRF sends the **Charging-Rule-Remove** AVP to remove a PCC rule that is already installed.
- Activate rules—The PCRF sends the **Rule-Activation-Time** AVP to indicate the time at which to activate the rule, and it is contained within the **Charging-Rule-Install** AVP. This operation results in a single activation of the rule, not a recurring activation schedule.
- Deactivate rules—The PCRF sends the **Rule-Deactivation-Time** AVP to indicate the time at which to deactivate the rule, and it is contained within the **Charging-Rule-Install** AVP. This operation results in a single deactivation of the rule, not a recurring deactivation schedule.
- PCEF session revalidation—The PCRF sends the **Revalidation-Time** AVP along with the **Event-Trigger** AVP with the value **REVALIDATION_TIMEOUT** to indicate the time at which the PCEF must request PCEF session revalidation from the PCRF. When the specified time is reached, the PCEF sends an event trigger with the value **REVALIDATION_TIMEOUT** to request PCEF session revalidation.
- Report application start or stop—The PCEF sends an event trigger when it detects the start or stop of an application.

The containers for the PCC rules are named **Charging-Rule-Definition**. Multiple **Charging-Rule-Definition** containers can be sent within a **Charging-Rule-Install** or **Charging-Rule-Remove**, each of which is applied per subscriber.

If a time zone is configured on the router, the activation and deactivation settings apply to the configured time zone and are adjusted for transitions to and from daylight saving time.

Methods for Provisioning PCC Rules

The PCRF uses one of the following procedures to specify the PCC rules that the PCEF applies:

Copyright © 2018, Juniper Networks, Inc.

- Pull mode during TDF subscriber creation—Applies when the MX Series gateway receives a request for a new TDF subscriber. The PCEF sends a credit control request initial (CCR-I) message to the PCRF with information about the subscriber. The PCRF downloads PCC rules to the PCEF in a credit control answer initial (CCA-I) message, which may also include any activation and deactivation times that apply to the rules and the time at which the PCEF must re-request PCC rules from the PCRF. Figure 6 on page 51 shows the message flow for a pull procedure during TDF subscriber creation.

Figure 6: Message Flow for Pull Mode During TDF Subscriber Creation



- Pull mode after PCEF event trigger—Applies when the PCEF sends an event trigger to the PCRF. This can occur when the MX Series router detects a new application start or stop or when the revalidation time has occurred. The PCEF sends a credit control request update (CCR-U) message along with the appropriate event trigger to the PCRF. The PCRF might download new rules to the PCEF in a credit control answer update (CCA-U) message, which may also include any activation and deactivation times that apply to the rules and the time at which the PCEF must re-request PCC rules from the PCRF. Figure 7 on page 51 shows the message flow for a pull procedure after a PCEF event trigger.

Figure 7: Message Flow for Pull Mode After PCEF Event Trigger



Copyright © 2018, Juniper Networks, Inc.

- Push mode—Applies when the PCRF provisions PCC rules without obtaining a request from the PCEF. The PCRF sends the PCC rules in a re-authorization request (RAR) to the PCEF based on information sent to the PCRF through the Rx interface or in response to a trigger within the PCRF. The RAR may also include any activation and deactivation times that apply to the rules and the time at which the PCEF must re-request PCC rules from the PCRF. The PCRF includes these PCC rules in an RAR message because the PCC rules were not requested by the PCEF, and no credit control request (CCR) or credit control answer (CCA) messages are triggered by the RAR. The PCEF responds with a re-authorization answer (RAA) message. Figure 8 on page 52 shows the message flow for a push procedure.

Figure 8: Message Flow for Push Mode



Related Documentation

- Understanding Junos Subscriber Aware Policy and Charging Enforcement Function (PCEF) on page 44
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- Configuring Dynamic Policy Control by PCRF on page 61

Understanding How Subscriber-Aware Policy and Charging Control Rules Are Provisioned Statically

Static policy control is enabled when a static-policy-control policy and charging enforcement function (PCEF) profile is assigned to a subscriber. The policy and charging control (PCC) rules that you configure on the MX Series router and assign to the PCEF profile are active, and are *not* controlled by the policy and charging rules function (PCRF) or RADIUS server.

Related Documentation

- Understanding Junos Subscriber Aware Policy and Charging Enforcement Function (PCEF) on page 44
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- Configuring Static Policy Control on page 62

Copyright © 2018, Juniper Networks, Inc.

Understanding How a RADIUS Server Controls Policy and Charging Control Rules

Policy control by a RADIUS server takes place when an aaa-policy-control policy and charging enforcement function (PCEF) profile is assigned to a subscriber. A RADIUS server activates and deactivates policy and charging control (PCC) rules that you have configured on the MX Series router and assigned to the PCEF profile. A network element, which is a load-balanced group of RADIUS servers, is assigned to the subscriber.

This topic includes the following sections:

- Rule Activation When TDF Session Begins on page 53
- Rule Activation and Deactivation When RADIUS Server Sends Request on page 53
- Supported Attributes in RADIUS Messages on page 54

Rule Activation When TDF Session Begins

When the traffic detection function (TDF) subscriber session begins, the Junos Subscriber Aware PCEF sends an access request to the RADIUS server. This is shown in Figure 9 on page 53. This access request includes the subscriber username, IP address, and other relevant AVP information that Subscriber Aware received from the broadband network gateway or Packet Data Network Gateway during the subscriber session setup.

The RADIUS server responds to the PCEF with an access-accept message, which contains the names of the rulebases to activate. You can configure the AVP that carries the name of a rulebase to be activated; by default the PCEF looks for a rulebase name in the ERX-Service-Activate Juniper vendor-specific attributes (VSA).

Figure 9: RADIUS Server Message Flow When TDF Session Begins



Rule Activation and Deactivation When RADIUS Server Sends Request

The RADIUS server can initiate the activation or deactivation of rulebases by sending a change of authorization (CoA) request to the PCEF, as shown in Figure 10 on page 54. You can configure the AVP that carries the name of a rulebase to be activated; by default the PCEF looks for a rulebase name in the ERX-Service-Activate Juniper VSA. You can

Copyright © 2018, Juniper Networks, Inc.

also configure the AVP that carries the name of a rulebase to be deactivated; by default the PCEF looks for a rulebase name in the ERX-Service-Deactivate Juniper VSA.

The PCEF responds to the CoA request by sending a CoA Ack to the RADIUS server.

Figure 10: Message Flow When RADIUS Server Sends Request



Supported Attributes in RADIUS Messages

The following tables list the RADIUS attributes, 3GPP VSAs, and Juniper Networks VSAs that are supported in the RADIUS messages between the MX Series router and a RADIUS server.

Table 4 on page 54 lists the RADIUS attributes and 3GPP VSAs that are supported in the access-request messages sent to the RADIUS server.

Table 4: Attributes Supported in Access-Request Messages

Attribute Number	Attribute Name	Description	Content
1	User-Name	Username for the TDF subscriber if it is provided in the RADIUS accounting request received from the Packet Data Network Gateway (PGW) or broadband network gateway (BNG). This is a RADIUS IETF attribute.	String
2	User-Password	User password configured in the subscriber's PCEF profile. This is a RADIUS IETF attribute.	String
4	NAS-IP-Address	IPv4 address of the MX Series router for communication with the RADIUS server. This is a RADIUS IETF attribute.	IPv4 address

Copyright © 2018, Juniper Networks, Inc.

Table 4: Attributes Supported in Access-Request Messages (continued)

Attribute Number	Attribute Name	Description	Content
8	Framed-IP-Address	IPv4 address for the TDF subscriber if it is provided in the RADIUS accounting request received from the PGW or BNG. This is a RADIUS IETF attribute.	IPv4 address
31	Calling-Station-ID	Identifier for the mobile station of the TDF subscriber if it is provided in the RADIUS accounting request received from the PGW or BNG. This is a RADIUS IETF attribute.	MSISDN in international format, UTF-8 encoded decimal characters
32	NAS-Identifier	Identifier of the NAS originating the request. This is a RADIUS IETF attribute.	String
44	Acct-Session-ID	User Session identifier generated by Subscriber Aware for the TDF subscriber. This is a RADIUS IETF attribute.	UTF-8 encoded string
97	Framed-IPv6-Prefix	IPv6 prefix for the TDF subscriber if it is provided in the RADIUS accounting request received from the PGW or BNG. This is a RADIUS IETF attribute.	Value indicating the prefix, as specified in RFC 3162
26/10415/1 (3GPP type 1)	3GPP-IMSI	IMSI for the TDF subscriber if it is provided in the RADIUS accounting request received from the PGW or BNG. This is a 3GPP VSA.	UTF-8 encoded string

Table 5 on page 55 lists the VSAs that are supported in the Access-Accept messages sent from the RADIUS server to the PCEF.

Table 5: Attributes Supported in Access-Accept Messages

Attribute Number	Attribute Name	Description	Content
26-65	ERX-Service-Activate	Specifies a PCC rulebase to activate for the subscriber. Tagged VSA, which supports 8 tags (1-8). This is a Juniper Networks VSA and is the default VSA for carrying rulebase activations; you can also specify a different AVP code and vendor ID.	string: *rulebase-name*

Table 6 on page 56 lists the VSAs that are supported in the CoA messages sent from the RADIUS server to the PCEF.

Copyright © 2018, Juniper Networks, Inc.

Table 6: Attributes Supported in CoA Messages

Attribute Number	Attribute Name	Description	Content
26-65	ERX-Service-Activate	Specifies a PCC rulebase to activate for the subscriber. Tagged VSA, which supports 8 tags (1-8). This is a Juniper Networks VSA and is the default VSA for carrying rulebase activations; you can also specify a different AVP code and vendor ID.	string: *rulebase-name*
26-66	ERX-Service-Deactivate	Specifies a PCC rulebase to deactivate for the subscriber. This is a Juniper Networks VSA and is the default VSA for carrying rulebase deactivations; you can also specify a different AVP code and vendor ID.	string: *rulebase-name*

Related Documentation

- Understanding Junos Subscriber Aware Policy and Charging Enforcement Function (PCEF) on page 44
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- Configuring Policy Control by RADIUS Servers on page 63

Understanding PCEF Profiles

A policy and charging enforcement function (PCEF) profile defines whether policy and charging control (PCC) rules for a subscriber are under static control, under dynamic control of the policy and charging rules function, or under activation/deactivation control of a RADIUS server by using the **static-policy-control**, **dynamic-policy-control**, or **aaa-policy-control** statement, respectively, in the PCEF profile configuration. The PCEF profile also identifies the predefined PCC rules and rulebases that the subscriber can use, and assigns a precedence value to each predefined rule. A subscriber is assigned a PCEF profile during the TDF subscriber session setup. See "Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber" on page 92.

A PCEF profile with dynamic policy control requires a Diameter Gx profile, which provides network access information for the Diameter application.

A PCEF profile with RADIUS server control requires an AAA profile, which provides the policy control attributes for RADIUS servers.

Related Documentation

- Understanding Junos Subscriber Aware Policy and Charging Enforcement Function (PCEF) on page 44
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47

Copyright © 2018, Juniper Networks, Inc.

- Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Dynamic Policies on page 80
- Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Static Policies on page 81
- Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Policies That a RADIUS Server Controls on page 82
- Understanding Static Time-of-Day PCC Rule Activation and Deactivation on page 59

Understanding Network Elements

A network element is a load-balanced group of RADIUS servers providing policy management for TDF subscribers.

Network elements are specified in the AAA profile that is applied to a policy and charging enforcement function (PCEF) profile. A subscriber is assigned to a PCEF profile.

- Load Balancing Within Network Elements on page 57
- Server Priority on page 57
- Dead Server Detection on page 57
- Maximum Pending Requests for a Network Element on page 58

Load Balancing Within Network Elements

The Junos Subscriber Aware PCEF distributes requests to RADIUS servers across the servers in the network element.

Server Priority

Within a network element, a RADIUS server can be assigned a priority of 1 through 16, with 1 being the highest priority. You can have multiple servers with the same priority in a network element. All access requests are load balanced among the highest priority servers. If all the servers with the highest priority in the network element fail, then requests are load balanced among servers with the next highest priority level.

Dead Server Detection

To determine whether a RADIUS server in a network element has failed, the PCEF keeps track of how often requests sent to a server time out and must be retransmitted. If the number of times that requests need to be retransmitted reaches a configured limit within a configured time interval, PCEF marks the server as **dead** and starts sending requests to the next available server in the network element with the same priority.

At the same time, the PCEF starts a timer for the RADIUS server. After this timer expires, the PCEF marks the dead server as alive again, and includes it in the rotation for sending RADIUS messages.

Copyright © 2018, Juniper Networks, Inc.

Maximum Pending Requests for a Network Element

You can configure the maximum number of requests that can be queued to the network element. When the pending request queue is full, any additional requests are dropped.

You can also configure a high and a low watermark that are percentages of the maximum number of requests that can be queued. If the number of pending requests reaches this high watermark, a **flow control on** message is generated. When the number of pending requests then falls below the low watermark, a **flow control off** message is generated.

Related Documentation

- Configuring RADIUS Network Elements on page 77
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Understanding AAA Profiles

An AAA profile is a collection of attributes to specify how the Junos Subscriber Aware PCEF interacts with RADIUS servers that control the activation and deactivation of policy and charging control (PCC) rules. An AAA profile is assigned to a subscriber's policy and charging enforcement function (PCEF) profile, which specifies the PCC rulebases for the subscriber.

- Network Elements on page 58
- RADIUS Attributes That Carry Rulebase Names for Activation and Deactivation on page 58

Network Elements

In the AAA profile, you specify a network element (load-balanced RADIUS server group) to be used for authorization of policy control. If the RADIUS servers in a Network Element cannot initiate a change of authorization (CoA) request without an accounting record, then the AAA profile must specify the network element for accounting as well as for authorization, and the AAA profile must enable CoA accounting.

RADIUS Attributes That Carry Rulebase Names for Activation and Deactivation

You can specify the RADIUS AVPs that carry the PCC rulebase names for activation or deactivation. By default, the PCC rulebase name for activations is carried in the ERX-Service-Activate Juniper vendor-specific attributes (VSA). By default, the PCC rulebase name for deactivations is carried in the ERX-Service-Deactivate Juniper VSA.

Related Documentation

- Configuring an AAA Profile on page 78
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

Understanding Static Time-of-Day PCC Rule Activation and Deactivation

With static time-of-day policy and charging control (PCC) rules activation and deactivation, you can specify a schedule for activating and deactivating PCC rules or rulebases within a static PCEF profile. The rule or rulebase activation and deactivation settings take effect for subscribers assigned to that static PCEF profile.

The activation and deactivation settings can consist of the time of day, the day, and the month of the year. The day can be expressed as a day of the week, as a numbered day of the month, or as the last day of the current month. If a day is not specified, then the rule activation and deactivation occurs daily at the specified times. If you configure a day of the month, you can also configure a month of the year.

If a day is not specified and the deactivation time of day setting is earlier than the activation time of day setting, then a rule is deactivated the day after it is activated.

If a time zone is configured on the router, the time-of-day settings apply to the configured time zone and are adjusted for transitions to and from daylight saving time.

You cannot use static time-of-day settings for dynamic PCC rules.

Related Documentation

- Configuration of Static Time-of-Day PCC Rule Activation and Deactivation Overview on page 83
- Configuring the NTP Server on page 84
- Configuring Static Time-of-Day PCC Rule Activation and Deactivation in a Junos OS Subscriber Aware PCEF Profile on page 84
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47

Understanding Usage Monitoring for TDF Subscribers

For TDF subscribers that are assigned to a dynamic policy and charging enforcement function (PCEF) profile, you can monitor the subscriber use during a session as a volume of traffic, an amount of time, or both, and send reports to the policy and charging rules function (PCRF) when a threshold is exceeded or when the PCRF requests a report. Data volume and the amount of time used can be tracked for individual or multiple data flows or applications that appear in specific policy and charging control (PCC) rules, or for the entire subscriber session.

This topic includes the following sections:

- Tracked Resource Identification on page 60
- Threshold Configuration on page 60
- Messages and AVPs That Are Used on page 60

Copyright © 2018, Juniper Networks, Inc.

Tracked Resource Identification

Data usage for a subscriber session is tracked through an object called a monitoring key, which the PCRF configures. Traffic for a particular data flow, application, or combination of data flows and applications can be tracked as a data set by assigning a monitoring key to the PCC rules that identify those flows or applications. For predefined PCC rules, you specify the monitoring key with the PCC rule's action profile. For dynamic PCC rules, the PCRF specifies the monitoring key for a rule.

Data usage can also be tracked for the entire TDF subscriber session by configuring the monitoring key level as SESSION.

Threshold Configuration

The PCRF specifies a threshold for reporting data usage when it configures a monitoring key. The threshold can be a combination of uplink volume, downlink volume, total volume, and time used. The MX Series router reports the usage information to the PCRF when this limit is exceeded, and resets the volume to zero.

Messages and AVPs That Are Used

The PCRF must first request usage monitoring by sending the Event-Trigger AVP with the value USAGE_REPORT. This request can be sent to the MX Series router in a CCA-I, CCA-U, or RAR message.

The PCRF configures a monitoring key by sending a Usage Monitoring Information (UMI) AVP that includes the following in a CCA-I, CCA-U, or RAR message to the MX Series router:

- Monitoring-key AVP, which is the identifier.
- Granted-Service-Unit AVP, which specifies the volume threshold, time threshold, or both.
- Usage-Monitoring-Level AVP, which indicates whether the monitoring key applies to the entire subscriber session or to particular PCC/ePCC rules.

The PCRF requests usage monitoring for traffic that matches a PCC rule's data flows or applications by sending the following in a CCA-I, CCA-U, or RAR message to the MX Series router:

- Charging-Rule-Definition AVP, which identifies the rule.
- UMI AVP that includes the Monitoring-key AVP, which identifies the monitoring key to which the rule is associated.

The MX Series router reports usage to the PCRF by sending a UMI AVP that includes the following in a CCR-U message:

- Monitoring-key AVP, which is the identifier.
- Used-Service-Unit AVP, which gives a combination of uplink volume, downlink volume, total volume, and time used.

Copyright © 2018, Juniper Networks, Inc.

The PCRF can request a usage report, regardless of whether the threshold is reached, by sending a UMI AVP that includes the following in a CCA-U or RAR message:

- Monitoring-key AVP, which is the identifier.
- Usage-Monitoring-Report AVP, which is set to the value USAGE_MONITORING_REPORT_REQUIRED (0).

The PCRF requests that usage monitoring be disabled for a monitoring key by sending a UMI AVP that includes the following in a CCA-U or RAR message:

- Monitoring-key AVP, which is the identifier.
- Usage-Monitoring-Support, which is set to the value USAGE_MONITORING_DISABLED (0).

Related Documentation

- IP-Based Subscriber Setup Overview on page 88
- Configuring TDF Subscriber Usage Monitoring for Traffic That Matches Predefined PCC Rules on page 85
- Understanding How Subscriber-Aware Policy and Charging Control Rules Are Provisioned Dynamically by a PCRF on page 49

Configuring Dynamic Policy Control by PCRF

You can configure policy management that is dynamically controlled by the policy and charging rules function (PCRF), which can both provision policy and charging control (PCC) rules on the MX Series router and activate PCC rules that are predefined on the MX Series router.

To configure policy management that is dynamically controlled by a PCRF:

1. (Optional) Configure any flow identifiers to be used in PCC rules.

   See "Configuring Service Data Flow Filters" on page 64.

2. (Optional) Configure any custom applications to be used in PCC rules.

   See "Configuring Custom Application Signatures" on page 25.

3. (Optional) Configure the PCC action profiles to be used in PCC rules.

   See "Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware" on page 67

4. (Optional) Configure PCC rules.

   See "Configuring Policy and Charging Control Rules" on page 70.

5. (Optional) Configure PCC rulebases.

Copyright © 2018, Juniper Networks, Inc.

See "Configuring a Policy and Charging Control Rulebase" on page 73.

6. Configure a Diameter Gx profile.

   See "Configuring Diameter Profiles" on page 130.

7. Configure a dynamic PCEF profile.

   See "Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Dynamic Policies" on page 80

8. (Optional) Configure an NTP server if you want the PCRF to send activation, deactivation, or revalidation times.

   See "Configuring the NTP Server" on page 84.

Related Documentation

- Understanding Junos Subscriber Aware Policy and Charging Enforcement Function (PCEF) on page 44
- Understanding How Subscriber-Aware Policy and Charging Control Rules Are Provisioned Dynamically by a PCRF on page 49

Configuring Static Policy Control

You can configure static policy management that is controlled entirely by predefined policy and charging control (PCC) rules that you have configured on the MX Series router.

To configure static policy control:

1. Configure any flow identifiers to be used in PCC rules.

   See "Configuring Service Data Flow Filters" on page 64.

2. Configure any custom applications to be used in PCC rules.

   See "Configuring Custom Application Signatures" on page 25.

3. Configure the PCC action profiles to be used in PCC rules.

   See "Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware" on page 67

4. Configure PCC rules.

   See "Configuring Policy and Charging Control Rules" on page 70.

5. (Optional) Configure PCC rulebases.

 Copyright © 2018, Juniper Networks, Inc.

See "Configuring a Policy and Charging Control Rulebase" on page 73.

6. Configure a policy and charging enforcement function (PCEF) profile for static policy control.

   See "Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Static Policies" on page 81

Related Documentation

- Understanding Junos Subscriber Aware Policy and Charging Enforcement Function (PCEF) on page 44
- Understanding How Subscriber-Aware Policy and Charging Control Rules Are Provisioned Statically on page 52

Configuring Policy Control by RADIUS Servers

You can configure policy management that is controlled by RADIUS servers. A RADIUS server activates and deactivates policy and charging control (PCC) rules that have been configured on the MX Series router.

To configure policy management that is controlled by RADIUS servers:

1. Configure any flow identifiers to be used in PCC rules.

   See "Configuring Service Data Flow Filters" on page 64.

2. Configure any custom applications to be used in PCC rules.

   See "Configuring Custom Application Signatures" on page 25.

3. Configure the PCC action profiles to be used in PCC rules.

   See "Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware" on page 67

4. Configure PCC rules.

   See "Configuring Policy and Charging Control Rules" on page 70.

5. Configure PCC rulebases.

   See "Configuring a Policy and Charging Control Rulebase" on page 73.

6. Configure RADIUS servers.

   See "Configuring RADIUS Servers" on page 74.

7. Configure RADIUS network elements.

   See "Configuring RADIUS Network Elements" on page 77.

Copyright © 2018, Juniper Networks, Inc.

8. Configure an AAA profile.

   See "Configuring an AAA Profile" on page 78.

9. Configure a policy and charging enforcement function (PCEF) profile for policy control by a RADIUS server.

   See "Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Policies That a RADIUS Server Controls" on page 82

Related Documentation

- Understanding Junos Subscriber Aware Policy and Charging Enforcement Function (PCEF) on page 44
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Configuring Service Data Flow Filters

A service data flow (SDF) filter is specified as a matching condition in the **from** clause of a policy and charging control (PCC) rule. Each SDF filter can have one or more flows associated with it; each flow is a five-tuple match.

NOTE: If you configure an SDF filter without specifying a remote address, port, port range, or protocol , then the SDF filter matches IP packets that have any value configured for the corresponding attribute. If you configure an SDF filter, you must configure at least one of the following attributes: direction, local port or local port range, protocol, remote address, or remote port or remote port range.

You can configure SDF filters for Junos OS Subscriber Aware or for Junos OS Broadband Subscriber Management, but you use a different CLI hierarchy level for each product.

- If you are using Junos OS Subscriber Aware, configure SDF filters at the **[edit unified-edge pcef]** hierarchy level.
- If you are using Junos OS Broadband Subscriber Management, configure SDF filters at the **[edit services pcef]** hierarchy level.

To configure Layer 3 and Layer 4 SDF filters:

1. Specify a name for the SDF filter.

   For Junos OS Subscriber Aware:

   ```
   [edit unified-edge pcef]
   user@host# set flow-descriptions flow-identifier
   ```

   For Junos OS Broadband Subscriber Management:

Copyright © 2018, Juniper Networks, Inc.

```
[edit services pcef]
user@host# set flow-descriptions flow-identifier
```

2. Specify the flow direction for the SDF filter.

NOTE: If you do not specify a flow direction, then the SDF filter is applied in both the uplink and downlink directions.

For Junos OS Subscriber Aware:

```
[edit unified-edge pcef flow-descriptions flow-identifier]
user@host# set direction (uplink | downlink | both)
```

For Junos OS Broadband Subscriber Management:

```
[edit services pcef flow-descriptions flow-identifier]
user@host# set direction (uplink | downlink | both)
```

3. Specify a remote address (IPv4 or IPv6) for the SDF filter:

NOTE: You can specify an IPv4 subnet or an IPv6 subnet but not both.

- Specify an IPv4 address for the SDF filter.

  For Junos OS Subscriber Aware:

  ```
  [edit unified-edge pcef flow-descriptions flow-identifier]
  user@host# set remote-address ipv4-address ipv4-address
  ```

  For Junos OS Broadband Subscriber Management:

  ```
  [edit services pcef flow-descriptions flow-identifier]
  user@host# set remote-address ipv4-address ipv4-address
  ```

- Specify an IPv6 address for the SDF filter.

  For Junos OS Subscriber Aware:

  ```
  [edit unified-edge pcef flow-descriptions flow-identifier]
  user@host# set remote-address ipv6-address ipv6-address
  ```

  For Junos OS Broadband Subscriber Management:

  ```
  [edit services pcef flow-descriptions flow-identifier]
  user@host# set remote-address ipv6-address ipv6-address
  ```

4. Specify a protocol (using the standard protocol number) for the SDF filter.

   For Junos OS Subscriber Aware:

Copyright © 2018, Juniper Networks, Inc.

```
[edit unified-edge pcef flow-descriptions flow-identifier]
user@host# set protocol number
```

For Junos OS Broadband Subscriber Management:

```
[edit services pcef flow-descriptions flow-identifier]
user@host# set protocol number
```

5. Specify a local port or a list of port numbers for the SDF filter. To specify a list of port numbers (up to a maximum of three), enclose the port numbers in square brackets ([]).

   NOTE: You can configure a local port or local port range but not both in the same SDF filter.

   For Junos OS Subscriber Aware:

   ```
   edit unified-edge pcef flow-descriptions flow-identifier]
   user@host# set local-ports number
   ```

   For Junos OS Broadband Subscriber Management:

   ```
   edit services pcef flow-descriptions flow-identifier]
   user@host# set local-ports number
   ```

6. Specify a local port range for the SDF filter.

   For Junos OS Subscriber Aware:

   ```
   [edit unified-edge pcef flow-descriptions flow-identifier]
   user@host# set local-port-range low low-value high high-value
   ```

   For Junos OS Broadband Subscriber Management:

   ```
   [edit services pcef flow-descriptions flow-identifier]
   user@host# set local-port-range low low-value high high-value
   ```

7. Specify a remote port or list of remote ports for the SDF filter. To specify a list of port numbers (up to a maximum of three), enclose the port numbers in square brackets ([]).

   NOTE: You can configure a remote port or remote port range but not both in the same SDF filter.

   For Junos OS Subscriber Aware:

   ```
   [edit unified-edge pcef flow-descriptions flow-identifier]
   ```


Copyright © 2018, Juniper Networks, Inc.

```
user@host# set remote-ports number
```

For Junos OS Broadband Subscriber Management:

```
[edit services pcef flow-descriptions flow-identifier]
user@host# set remote-ports number
```

8. Specify a remote port range for the SDF filter.

   For Junos OS Subscriber Aware:

   ```
   [edit unified-edge pcef flow-descriptions flow-identifier]
   user@host# set remote-port-range low low-value high high-value
   ```

   For Junos OS Broadband Subscriber Management:

   ```
   [edit services pcef flow-descriptions flow-identifier]
   user@host# set remote-port-range low low-value high high-value
   ```

Related Documentation

- *Configuring Application-Aware Policy Control for Subscriber Management*
- *Understanding Application-Aware Policy Control for Subscriber Management*
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- Configuring Policy and Charging Control Rules on page 70

Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware

A PCC action profile defines the treatment to be applied to specific service data flows or to packets associated with specific applications. A PCC action profile is specified in the **then** clause of a PCC rule.

NOTE: To make a change to a PCC action profile, you must be in maintenance mode. (See "Changing PCEF Profiles, PCC Rules, PCC Rulebases, Diameter Profiles, Flow Descriptions, and PCC Action Profiles" on page 182).

To configure PCC action profiles:

1. Specify a name for the PCC action profile.

   ```
   [edit unified-edge pcef]
   user@host# edit pcc-action-profiles profile-name
   ```

2. Configure the maximum bit rate for uplink and downlink subscriber traffic.

   ```
   [edit unified-edge pcef pcc-action-profiles profile-name]
   ```

Copyright © 2018, Juniper Networks, Inc.

```
user@host# set maximum-bit-rate uplink mbr-uplink-value downlink
  mbr-downlink-value
```

The range is 0 through 6144000 Kbps.

3. Configure HTTP redirection to a URL.

```
[edit unified-edge pcef pcc-action-profiles profile-name redirect]
user@host# set url url-name
```

NOTE: A PCC action profile that includes HTTP redirection can only be used in PCC rules that match only HTTP-based applications and all flows.

4. Configure the steering of traffic to a third-party server for applying services or to a service chain with one of the following methods:

   - Specify the IP address of the third-party server for HTTP traffic.

```
[edit unified-edge pcef pcc-action-profiles profile-name steering path]
user@host# set (ipv4-address ipv4-address | set ipv6-address ipv6-address)
```

NOTE: A PCC action profile that includes a steering path can only be used in PCC rules that match only HTTP-based applications and all flows.

   - Specify the routing instance to use to reach the third-party server or service chain.

```
[edit unified-edge pcef pcc-action-profiles profile-name steering]
user@host# set routing-instance downlink downlink-vrf-name uplink uplink-vrf-name
```

   The downlink routing instance is applied to traffic going to the access side, and the uplink routing instance is applied to traffic being sent from the access side.

5. Specify that steering attributes configured in a PCC action profile that a PCC rule applies to a data flow session when it begins will continue to be applied to the data flow when the PCC rule match conditions are modified, deleted, or added to.

```
[edit unified-edge pcef pcc-action-profiles profile-name steering]
user@host# set keep-existing-steering
```

6. Specify the HCM profile that you want to use for determining which HTTP header enrichment rules are applied.

```
[edit unified-edge pcef pcc-action-profiles profile-name]
user@host# set hcm-profile hcm-profile-name
```


Copyright © 2018, Juniper Networks, Inc.

NOTE: A PCC action profile that includes an HCM profile can only be used in PCC rules that match only HTTP-based applications and all flows.

7. Specify the forwarding class that you want packets to be assigned.

```
[edit unified-edge pcef pcc-action-profiles profile-name]
user@host# set forwarding-class class-name
```

8. Configure the gating status by enabling or disabling the forwarding of packets.

```
[edit unified-edge pcef pcc-action-profiles profile-name]
user@host# set gate-status (disable-both | downlink | uplink | uplink-downlink)
```

Related Documentation

- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- Configuring Policy and Charging Control Rules on page 70
- Configuring TDF Subscriber Usage Monitoring for Traffic That Matches Predefined PCC Rules on page 85

Copyright © 2018, Juniper Networks, Inc.

Configuring Policy and Charging Control Rules

A policy and charging control (PCC) rule defines the treatment to be applied to packets associated with specific applications or to specific service data flows.

You can configure PCC rules for Junos OS Subscriber Aware or for Junos OS Broadband Subscriber Management, but you use a different CLI hierarchy level for each product.

- If you are using Junos OS Subscriber Aware, configure PCC rules at the **[edit unified-edge pcef]** hierarchy level.
- If you are using Junos OS Broadband Subscriber Management, configure PCC rules at the **[edit services pcef]** hierarchy level.

NOTE: If you are using Junos OS Subscriber Aware, you must be in maintenance mode to make a change to a PCC rule. (See "Changing PCEF Profiles, PCC Rules, PCC Rulebases, Diameter Profiles, Flow Descriptions, and PCC Action Profiles" on page 182).

NOTE: If you are using Junos OS Broadband Subscriber Management, you cannot change a PCC rule while it is being used by a subscriber. To modify the rule, you must log off the subscribers that are using the rule.

Before you configure PCC rules, you must do the following:

- Configure the service data flow (SDF) filters that the PCC rules reference.
- Configure the application groups and any custom applications that you want to reference in application-aware PCC rules.
- Configure the PCC action profiles that the PCC rules reference.

NOTE: When specifying application-aware PCC rules in a PCEF profile, you must also configure a default Layer 3 or Layer 4 wildcard PCC rule to ensure that the default charging characteristics are applied to unmatched subscriber traffic without dropping that traffic. For example, the default Layer 3 or Layer 4 wildcard PCC rule prevents traffic based on DNS queries from being dropped. In addition, the policy (PCEF profile) that includes application-aware PCC rules must also include a wildcard Layer 3 or Layer 4 PCC rule at a lower precedence.

To configure PCC rules:

1. Specify a name for the PCC rule.

   For Junos OS Subscriber Aware:

Copyright © 2018, Juniper Networks, Inc.

```
[edit unified-edge pcef]
user@host# edit pcc-rules rule-name
```

For Junos OS Broadband Subscriber Management:

```
[edit services pcef]
user@host# edit pcc-rules rule-name
```

2. In a **from** statement, specify an SDF filter to use Layer 3 or Layer 4 match conditions for filtering subscriber traffic.

   For Junos OS Subscriber Aware:

   ```
   [edit unified-edge pcef pcc-rules rule-name]
   user@host# set from flows flow-identifier
   ```

   For Junos OS Broadband Subscriber Management:

   ```
   [edit services pcef pcc-rules rule-name]
   user@host# set from flows flow-identifier
   ```

   If you do not want to filter subscriber traffic based on SDF filters, use the **any** option.

   For Junos OS Subscriber Aware:

   ```
   [edit unified-edge pcef pcc-rules rule-name]
   user@host# set from flows any
   ```

   For Junos OS Broadband Subscriber Management:

   ```
   [edit services pcef pcc-rules rule-name]
   user@host# set from flows any
   ```

3. (Optional) Specify an application as a match condition for filtering subscriber traffic.

   For Junos OS Subscriber Aware:

   ```
   [edit unified-edge pcef pcc-rules rule-name]
   user@host# set from applications application-name
   ```

   For Junos OS Broadband Subscriber Management:

   ```
   [edit services pcef pcc-rules rule-name]
   user@host# set from applications application-name
   ```

4. (Optional) Specify multiple applications instead of specifying each application separately by specifying an application group as a match condition for filtering subscriber traffic.

   For Junos OS Subscriber Aware:

```
[edit unified-edge pcef pcc-rules rule-name]
user@host# set from application-groups application-group-name
```

For Junos OS Broadband Subscriber Management:

```
[edit services pcef pcc-rules rule-name]
user@host# set from application-groups application-group-name
```

5. Specify the PCC rules action profile that defines the treatment to be applied to specific service data flows or to packets associated with specific applications.

NOTE: You can use PCC action profiles with HTTP redirection or HCM profiles only in PCC rules that match only HTTP-based applications and any flows.

For Junos OS Subscriber Aware:

```
[edit unified-edge pcef pcc-rules rule-name]
user@host# set then pcc-action-profile profile-name
```

For Junos OS Broadband Subscriber Management:

```
[edit services pcef pcc-rules rule-name]
user@host# set then pcc-action-profile profile-name
```

Related Documentation

- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- *Understanding Application-Aware Policy Control for Subscriber Management*
- Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware on page 67
- *Configuring Policy and Charging Control Action Profiles for Subscriber Management*
- Configuring Service Data Flow Filters on page 64
- Configuring Custom Application Signatures on page 25

Copyright © 2018, Juniper Networks, Inc.

Configuring a Policy and Charging Control Rulebase

A policy and charging control (PCC) rulebase contains a set of PCC rules. Each rule specified in the PCC rulebase is assigned a precedence to designate the priority in which PCC rules are evaluated for selection in a policy and charging enforcement function (PCEF) profile.

You can configure PCC rulebases for Junos OS Subscriber Aware or for Junos OS Broadband Subscriber Management, but you use a different CLI hierarchy level for each product.

- If you are using Junos OS Subscriber Aware, configure PCC rulebases at the **[edit unified-edge pcef]** hierarchy level.
- If you are using Junos OS Broadband Subscriber Management, configure PCC rulebases at the **[edit services pcef]** hierarchy level.

NOTE: If you are using Junos OS Subscriber Aware, you must be in maintenance mode to make a change to a PCC rulebase. (See "Changing PCEF Profiles, PCC Rules, PCC Rulebases, Diameter Profiles, Flow Descriptions, and PCC Action Profiles" on page 182).

NOTE: If you are using Junos OS Broadband Subscriber Management, you cannot change a PCC rulebase while it is being used by a subscriber. To modify the rulebase, you must log off the subscribers that are using the rule.

Before you configure a PCC rulebase, you must do the following:

- Configure service data flow filters.
- Configure PCC action profiles.
- Configure PCC rules.

To configure a PCC rulebase:

1. Specify a name for the rulebase.

   For Junos OS Subscriber Aware:

   ```
   [edit unified-edge pcef ]
   user@host# edit pcc-rulebases rulebase-name
   ```

   For Junos OS Broadband Subscriber Management:

   ```
   [edit services pcef ]
   user@host# edit pcc-rulebases rulebase-name
   ```

Copyright © 2018, Juniper Networks, Inc.

2. Specify the PCC rules that the rulebase references and a precedence value (1 through 65,535) for each rule.

   NOTE:
   - The same rule can be configured in different rulebases and can have a different precedence.
   - The precedence assigned must be unique among the configured PCC rules.
   - A lower precedence value indicates a higher precedence. For example, if a PCC rulebase has two PCC rules with precedence 5 and 10 respectively, the PCC rule with precedence 5 is evaluated first.

   For Junos OS Subscriber Aware:

   ```
   [edit unified-edge pcef pcc-rulebases rulebase-name]
   user@host# set pcc-rule rule-name precedence number
   user@host# set pcc-rule rule-name precedence number
   user@host# set pcc-rule rule-name precedence number
   ```

   For Junos OS Broadband Subscriber Management:

   ```
   [edit services pcef pcc-rulebases rulebase-name]
   user@host# set pcc-rule rule-name precedence number
   user@host# set pcc-rule rule-name precedence number
   user@host# set pcc-rule rule-name precedence number
   ```

Related Documentation

- Configuring Policy and Charging Control Rules on page 70
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- *Understanding Application-Aware Policy Control for Subscriber Management*
- Understanding Junos Subscriber Aware Policy and Charging Enforcement Function (PCEF) on page 44

Configuring RADIUS Servers

You must configure RADIUS servers before you can configure a RADIUS network element. A network element is a load-balanced group of RADIUS servers providing policy management for TDF subscribers.

To configure a RADIUS server:

1. Configure a name for the RADIUS server.

   ```
   [edit access radius]
   user@host# set servers name
   ```


Copyright © 2018, Juniper Networks, Inc.

2. Specify the IP address of the RADIUS server.

```
[edit access radius servers name]
user@host# set address server-address
```

3. Configure an interface and IPv4 address to specify the source for RADIUS requests. The MX Series router sends RADIUS requests to the RADIUS server using this source address.

```
[edit access radius servers name]
user@host# set source-interface interface [ipv4-address address]
```

4. Configure a shared secret (password) to be used by the MX Series router and the RADIUS server.

```
[edit access radius servers name]
user@host# set secret password
```

5. Configure the port number to which the RADIUS requests are sent.

```
[edit access radius servers name]
user@host# set port port-number
```

6. Specify the RADIUS server port number to which the MX Series router sends RADIUS accounting-start and accounting-stop requests. RADIUS accounting-start and accounting-stop requests are used when the RADIUS server is not able to initiate a change of authorization (CoA) request without an accounting record.

```
[edit access radius servers name]
user@host# set accounting-port port-number
```

7. Configure the secret password to be used when sending accounting-start requests to the RADIUS server if the accounting secret password is different from the authentication secret password. RADIUS accounting-start requests are used when the RADIUS server is not able to initiate a CoA request without an accounting record.

```
[edit access radius servers name]
user@host# set accounting-secret password
```

8. Configure the number of attempts to contact the RADIUS server that the MX Series router is allowed to make when it does not receive a response to its initial request. You can specify from 1 through 10 retries. The default is 3.

```
[edit access radius servers name]
user@host# set retry attempts
```

Copyright © 2018, Juniper Networks, Inc.

9. Configure the amount of time that the MX Series router waits to receive a response from a RADIUS server before retrying a request. By default, the MX Series router waits 3 seconds. You can configure the timeout to be from 1 through 90 seconds.

```
[edit access radius servers name]
user@host# set timeout seconds
```

10. Allow dynamic requests from the RADIUS server so that CoA requests can be received.

```
[edit access radius servers name]
user@host# set allow-dynamic-requests
```

11. Configure the secret password to be used for CoA requests from the RADIUS server.

```
[edit access radius servers name]
user@host# set dynamic-requests-secret password
```

12. Configure a limit to the number of request retries within a specified time interval that the MX Series router can send to the RADIUS server. If the number of retries reaches this limit, the RADIUS server is marked as dead, and the MX Series router begins to send requests to other RADIUS servers in the network element.

```
[edit access radius servers name]
user@host# set dead-criteria-retries retry-number interval seconds
```

13. Configure the amount of time that must pass after a RADIUS server is first marked dead until it is marked as alive by the MX Series router. When the MX Series router marks the RADIUS server as alive, it can again send requests to the RADIUS server.

```
[edit access radius servers name]
user@host# set revert-interval seconds
```

Related Documentation

- Understanding Network Elements on page 57
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

Configuring RADIUS Network Elements

A network element is a load-balanced group of RADIUS servers providing policy management for TDF subscribers.

Before you configure a network element, you must do the following:

- Configure the RADIUS servers that are to be part of the network element.

To configure a network element:

1. Specify a name for the network element.

   ```
   [edit access radius]
   user@host# set network-elements name
   ```

2. Specify the RADIUS servers that make up the network element.

   ```
   [edit access radius network-elements name]
   user@host# set server name
   ```

3. Assign each server in the network element a priority from 1 through 16 (1 is the highest priority). You can have multiple servers with the same priority in a network element. All access requests are load balanced among the highest priority servers. If all the servers with the highest priority in the network element fail, then requests are load balanced among servers with the next highest priority level.

   ```
   [edit access radius network-elements name server name]
   user@host# set priority priority
   ```

4. Configure the maximum number of requests that can be queued to the network element. When the pending-request queue is full, any additional requests are dropped.

   ```
   [edit access radius network-elements name]
   user@host# set maximum-pending-reqs-limit number
   ```

5. Configure the pending-request queue high watermark for the network element. This is a percentage of the maximum number of requests that can be queued to the network element, which is configured in the **maximum-pending-reqs-limit** *number* statement. When the queue size reaches the high watermark, a **flow control on** message is generated.

   ```
   [edit access radius network-elements name]
   user@host# set pending-queue-watermark watermark
   ```

6. Configure the pending-request queue low watermark for the network element. This is a percentage of the maximum size of the pending-request queue, which is configured

Copyright © 2018, Juniper Networks, Inc.

in the **maximum-pending-reqs-limit** *watermark* statement. When the number of pending requests drops below this low watermark value after having exceeded the high watermark, a **flow control off** message is generated.

```
[edit access radius network-elements name]
user@host# set pending-queue-watermark-abate abate-watermark
```

Related Documentation

- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53
- Understanding Network Elements on page 57
- Configuring RADIUS Servers on page 74

Configuring an AAA Profile

An AAA profile is a collection of attributes to specify how the MX Series router interacts with RADIUS servers that control the activation and deactivation of policy and charging control (PCC) rules.

Before you configure an AAA profile, you must do the following:

- Configure the network elements that are to be included in the AAA profile.

To configure an AAA profile:

1. Configure a name for the AAA profile.

   ```
   [edit unified-edge aaa]
   user@host# set profiles aaa-profile-name
   ```

2. Specify the network element providing policy management for TDF subscribers.

   ```
   [edit unified-edge aaa profiles aaa-profile-name radius authentication]
   user@host# set network-element network-element-name
   ```

3. If the RADIUS servers in the network element providing policy management for TDF subscribers cannot initiate a change of authorization (CoA) request without an accounting record, specify that the network element is used for accounting.

   ```
   [edit unified-edge aaa profiles aaa-profile-name radius accounting]
   user@host# set network-element network-element-name
   ```

4. If the RADIUS servers in the network element providing policy management for TDF subscribers cannot initiate a CoA request without an accounting record, enable the initiation of a RADIUS accounting start from the MX Series router to the RADIUS servers.

Copyright © 2018, Juniper Networks, Inc.

```
[edit unified-edge aaa profiles aaa-profile-name radius policy]
user@host# set coa-accounting enable
```

5. Configure the RADIUS attribute that you want to carry the PCC rulebase name for rulebase activations from the RADIUS policy server to the MX Series router. By default, the rulebase name is carried in the ERX-Service-Activate Juniper vendor-specific attribute (VSA).

   a. Specify the numeric value for the RADIUS AVP.

   ```
   [edit unified-edge aaa profiles aaa-profile-name radius policy activation-attribute]
   user@host# set code numeric-code
   ```

   b. If the RADIUS AVP is vendor-specific, specify the vendor identification.

   ```
   [edit unified-edge aaa profiles aaa-profile-name radius policy activation-attribute]
   user@host# set vendor-id vendor-id
   ```

6. Configure the RADIUS attribute that you want to carry the PCC rulebase name for rulebase deactivations from the RADIUS policy server to the MX Series router. By default, the rulebase name is carried in the ERX-Service-Deactivate Juniper VSA.

   a. Specify the numeric value for the RADIUS AVP.

   ```
   [edit unified-edge aaa profiles aaa-profile-name radius policy deactivation-attribute]
   user@host# set code numeric-code
   ```

   b. If the RADIUS AVP is vendor-specific, specify the vendor identification.

   ```
   [edit unified-edge aaa profiles aaa-profile-name radius policy deactivation-attribute]
   user@host# set vendor-id vendor-id
   ```

Related Documentation

- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53
- Understanding AAA Profiles on page 58
- Configuring RADIUS Network Elements on page 77

Copyright © 2018, Juniper Networks, Inc.

Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Dynamic Policies

When a policy and charging enforcement function (PCEF) profile is configured with dynamic policy control, the policy and charging rules function (PCRF) can both provision policy and charging control (PCC) rules and activate PCC rules that are predefined on the Junos Subscriber Aware PCEF.

Before you configure a PCEF profile for dynamic policies, you must do the following:

- Configure a Diameter Gx profile.
- (Optional) Configure service data flow (SDF) filters.
- (Optional) Configure a PCC action profile.
- (Optional) Configure PCC rules, PCC rulebases, or both.

NOTE: You can add PCC rules or PCC rulebases to a dynamic PCEF profile without being in maintenance mode. To make other changes to a dynamic PCEF profile, you must be in maintenance mode.

NOTE: When a PCEF profile includes application-aware PCC rules, you must also include a default Layer 3 or Layer 4 wildcard PCC rule to ensure that the default charging characteristics are applied to unmatched subscriber traffic without dropping that traffic. For example, the default Layer 3 or Layer 4 wildcard PCC rule prevents traffic based on DNS queries from being dropped. In addition, the PCEF profile that includes application-aware PCC rules must also include a wildcard Layer 3 or Layer 4 PCC rule at a lower precedence.

To configure a PCEF profile for dynamic policies:

1. Specify a name for the PCEF profile.

```
[edit unified-edge pcef]
user@host# edit profiles profile-name
```

2. Specify one or more PCC rules and a precedence for each rule for dynamic policy control. A lower precedence value indicates a higher precedence.

```
[edit unified-edge pcef profiles profile-name]
user@host# set dynamic-policy-control pcc-rules rule-name precedence number
```

NOTE: If the profile includes application-aware PCC rules, you must also include a wildcard Layer 3 or Layer 4 PCC rule at a lower precedence.

Copyright © 2018, Juniper Networks, Inc.

3. Specify one or more PCC rulebases for dynamic policy control.

```
[edit unified-edge pcef profiles profile-name]
user@host# set dynamic-policy-control pcc-rulebases rulebase-name
```

NOTE: Make sure that the PCC rules and PCC rulebases configured in a PCEF profile do not overlap.

4. Specify a Diameter Gx profile.

```
[edit unified-edge pcef profiles profile-name dynamic-policy-control]
user@host# set diameter-profile gx-profile-name
```

Related Documentation

- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- Understanding Junos Subscriber Aware Policy and Charging Enforcement Function (PCEF) on page 44
- Configuring Policy and Charging Control Rules on page 70
- Configuring a Policy and Charging Control Rulebase on page 73

Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Static Policies

A policy and charging enforcement function (PCEF) profile configured for static policy control specifies that policy and charging control (PCC) rules are provisioned by the Junos Subscriber Aware PCEF with no interaction from the policy and charging rules function (PCRF).

NOTE: To make a change to a static PCEF profile, you must be in maintenance mode. (See "Changing PCEF Profiles, PCC Rules, PCC Rulebases, Diameter Profiles, Flow Descriptions, and PCC Action Profiles" on page 182).

Before you configure a PCEF profile for static policies, you must do the following:

- Configure service data flow filters for PCC rules.
- Configure PCC action profiles for PCC rules.
- Configure PCC rules.
- (Optional) Configure PCC rulebases.

To configure a PCEF profile for static policies:

1. Specify a name for the PCEF profile.

Copyright © 2018, Juniper Networks, Inc.

```
[edit unified-edge pcef]
user@host# edit profiles profile-name
```

2. Specify one or more PCC rules and a precedence for each rule for static policy control. A lower precedence value indicates a higher precedence.

```
[edit unified-edge pcef profiles profile-name]
user@host# set static-policy-control pcc-rules rule-name precedence number
```

3. Specify one or more PCC rule bases for static policy control.

```
[edit unified-edge pcef profiles profile-name]
user@host# set static-policy-control pcc-rulebases rulebase-name
```

Related Documentation

- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- Understanding Junos Subscriber Aware Policy and Charging Enforcement Function (PCEF) on page 44
- Configuring Policy and Charging Control Rules on page 70
- Configuring a Policy and Charging Control Rulebase on page 73
- Understanding Static Time-of-Day PCC Rule Activation and Deactivation on page 59

Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Policies That a RADIUS Server Controls

A policy and charging enforcement function (PCEF) profile configured for policy control by a RADIUS server specifies that the RADIUS server activates and deactivates policy and charging control (PCC) rulebases that you have predefined on the MX Series router.

Before you configure a PCEF profile for policies controlled by a RADIUS server, you must do the following:

- Configure PCC rulebases.
- Configure an AAA profile.

To configure a PCEF profile for policies controlled by a RADIUS server:

1. Specify a name for the PCEF profile.

```
[edit unified-edge pcef]
user@host# edit profiles profile-name
```

2. Specify one or more PCC rule bases for policy control by a RADIUS server.

Copyright © 2018, Juniper Networks, Inc.

```
[edit unified-edge pcef profiles profile-name]
user@host# set aaa-policy-control pcc-rulebases rulebase-name
```

3. Specify the AAA profile that identifies the RADIUS server policy control parameters.

```
[edit unified-edge pcef profiles profile-name]
user@host# set aaa-policy-control aaa-profile aaa-profile-name
```

4. Configure the user password for subscribers assigned to this PCEF profile.

```
[edit unified-edge pcef profiles profile-name]
user@host# set aaa-policy-control user-password password
```

Related Documentation

- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- Understanding Junos Subscriber Aware Policy and Charging Enforcement Function (PCEF) on page 44
- Configuring Policy and Charging Control Rules on page 70
- Configuring a Policy and Charging Control Rulebase on page 73
- Configuring an AAA Profile on page 78

Configuration of Static Time-of-Day PCC Rule Activation and Deactivation Overview

You configure static time-of-day PCC rule activation and deactivation to specify when a rule or rulebase within a static PCEF profile is active.

To configure static time-of-day PCC rules activation and deactivation:

1. Configure an NTP server.

   See "Configuring the NTP Server" on page 84.

2. Configure the activation and deactivation settings and apply them to a rule or rulebase.

   See "Configuring Static Time-of-Day PCC Rule Activation and Deactivation in a Junos OS Subscriber Aware PCEF Profile" on page 84

Related Documentation

- Understanding Static Time-of-Day PCC Rule Activation and Deactivation on page 59

Copyright © 2018, Juniper Networks, Inc.

Configuring the NTP Server

Before you use the static or dynamic time-of-day functionality for PCC rules, you must configure an NTP server.

To configure the NTP server:

1. Specify the IP address of the NTP server.

```
[edit system]
user@host# set ntp server ip-address
```

2. Enable the NTP process on the router.

```
[edit system]
user@host# set processes ntp enable
```

Related Documentation

- Configuring Static Time-of-Day PCC Rule Activation and Deactivation in a Junos OS Subscriber Aware PCEF Profile on page 84
- Understanding Static Time-of-Day PCC Rule Activation and Deactivation on page 59

Configuring Static Time-of-Day PCC Rule Activation and Deactivation in a Junos OS Subscriber Aware PCEF Profile

You configure static time-of-day PCC rule activation and deactivation to specify when to activate or deactivate a rule or rulebase within a static PCEF profile.

Before you configure static time-of-day PCC rule activation and deactivation, configure the NTP server.

To configure static time-of-day PCC rule or rulebase activation and deactivation within a PCEF profile:

1. Specify a name for a time-of-day profile.

```
[edit unified-edge pcef]
user@host# set pcc-time-of-day-profiles profile-name
```

2. Specify the activation time in the time-of-day profile.

```
[edit unified-edge pcef pcc-time-of-day-profiles profile-name]
user@host# set rule-activation-time <day-of-week | day-of-month month> <hour:min>
```

You can specify the time of day, the day, and the month of the year. The day can be expressed as the day of the month (**DAY1** through **DAY31** or **Last-day-of-month**) or the day of the week (for example, **MONDAY**). If you specify the day of the month, you

Copyright © 2018, Juniper Networks, Inc.

can also specify the month of the year. If a time zone is configured on the router, the time-of-day settings apply to the configured time zone.

3. Specify the deactivation time in the time-of-day profile. Use the same combination of options that you used in Step 2.

```
[edit unified-edge pcef pcc-time-of-day-profiles profile-name]
user@host# set rule-deactivation-time <day-of-week | day-of-month month>
   <hour:min>
```

If a day is not specified and the deactivation time of day setting is earlier than the activation time of day setting, then a rule is deactivated the day after it is activated.

4. Within a static PCEF profile, apply the time-of-day profile to individual rules or rulebases.

```
[edit unified-edge pcef profiles profile-name static-policy-control]
user@host# set pcc-rules rule-name precedence number time-of-day-profile
   profile-name
user@host# set pcc-rulebases rulebase-name time-of-day-profile profile-name
```

Those rules or rulebases use the activation and deactivation settings for subscribers assigned to the PCEF profile.

Related Documentation

- Understanding Static Time-of-Day PCC Rule Activation and Deactivation on page 59
- Configuring the NTP Server on page 84
- Understanding PCEF Profiles on page 56

Configuring TDF Subscriber Usage Monitoring for Traffic That Matches Predefined PCC Rules

You can configure usage monitoring of TDF subscriber traffic that matches particular data flows or applications that are identified in a predefined PCC rule by identifying the appropriate monitoring key in the **pcc-action-profile** of the PCC rule. This monitoring key controls usage reporting for all the predefined PCC rules that use this **pcc-action-profile**.

To configure usage monitoring for a predefined PCC rule:

- For the **pcc-action-profile** that is used in the predefined PCC rule, specify the monitoring key that controls reporting:

```
[edit unified-edge pcef pcc-action-profiles profile-name]
user@host# set monitoring-key key_string
```

Related Documentation

- Understanding Usage Monitoring for TDF Subscribers on page 59

Copyright © 2018, Juniper Networks, Inc.

- Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware on page 67

 Copyright © 2018, Juniper Networks, Inc.

CHAPTER 6

Configuring TDF Subscribers

- IP-Based and IFL-Based TDF Subscribers Overview on page 88
- IP-Based Subscriber Setup Overview on page 88
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- Understanding Source IP Filtering with Address Pools in TDF Domains for IP-Based Subscribers on page 90
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- Snooping RADIUS Accounting Requests for IP-Based Subscribers Overview on page 94
- Understanding IFL-Based Subscriber Setup on page 95
- Understanding the Definition of a Set of IFL-Based Subscriber Properties with a TDF Domain on page 96
- Configuring IP-Based TDF Subscriber Setup When MX Series Router Is a RADIUS Server on page 97
- Configuring IP-Based TDF Subscriber Setup When Accounting Requests Are Snooped on page 98
- Configuring Address Pools for Source-IP Filtering of IP-Based Subscribers on page 99
- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Configuring RADIUS Clients That Send Accounting Requests for IP-Based Subscribers on page 106
- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Configuring Snooping of RADIUS Accounting Requests for IP-Based Subscribers on page 113
- Configuring IFL-Based TDF Subscriber Setup on page 116
- Configuring IFL-Based TDF Subscribers and Properties with a TDF Domain on page 117
- Configuring a TDF Logical Interface on page 120
- Configuring TDF Interface to Access Interface Associations in VRFs on page 120

Copyright © 2018, Juniper Networks, Inc.

IP-Based and IFL-Based TDF Subscribers Overview

Junos Subscriber Aware implements the Third-Generation Partnership Project (3GPP) traffic detection function (TDF), enabling subscriber-aware policy enforcement and traffic steering that is application-aware. Before a user's data traffic can undergo TDF processing, a TDF subscriber session must be set up.

You can configure two types of TDF subscribers:

- IP-Based Subscribers on page 88
- IFL-Based Subscribers on page 88

IP-Based Subscribers

IP-based subscriber sessions are initiated when Junos Subscriber Aware processes a RADIUS accounting start request for a potential subscriber from a gateway GPRS support node (GGSN), Packet Data Network Gateway (PGW), or broadband network gateway (BNG). An IP-based subscriber session is for one unique user IP address.

IFL-Based Subscribers

IFL-based subscriber sessions are initiated when you configure the TDF subscriber and assign it a set of interfaces. All traffic that the MX Series router receives on those interfaces shares the same IFL-based subscriber session.

Related Documentation

- IP-Based Subscriber Setup Overview on page 88
- Understanding IFL-Based Subscriber Setup on page 95

IP-Based Subscriber Setup Overview

Junos Subscriber Aware initiates an IP-based subscriber session when it receives a RADIUS accounting request from a gateway GPRS support node (GGSN), Packet Data Network Gateway (PGW), or broadband network gateway (BNG). An individual subscriber session is created for each unique source IP address.

The MX Series router can receive a RADIUS accounting request in two ways:

- When the MX Series router is identified as a RADIUS server for the GGSN, PGW, or BNG, you configure the GGSN, PGW, or BNG as a RADIUS client of the MX Series router. The RADIUS client sends the accounting request to a designated interface and IP address on the MX Series router, which sends it to the subscriber processing module.
- When the GGSN, PGW, or BNG does not treat the MX Series router as a RADIUS server, you configure a filter called a *snoop segment*. Junos OS examines RADIUS accounting requests that pass through the MX Series router to determine whether they match the filter, which is known as *snooping*. When an accounting request matches the filter, Junos OS copies the request and sends it to the subscriber processing module.

Copyright © 2018, Juniper Networks, Inc.

You specify how an IP-based subscriber session is created and how a subscriber's traffic is processed by configuring TDF domains and PCEF profiles, and configuring a selection process for applying them to subscribers. The selection process identifies the attribute-value pair (AVP) values in the RADIUS accounting start request that must be matched to select a particular TDF domain or PCEF profile.

Related Documentation

- IP-Based and IFL-Based TDF Subscribers Overview on page 88
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- Snooping RADIUS Accounting Requests for IP-Based Subscribers Overview on page 94

Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain

A traffic detection function (TDF) domain identifies a set of properties for creating a TDF IP-based subscriber session and specifying how TDF subscriber traffic is processed. You can create several TDF domains if you have multiple categories of subscribers. You configure a selection process to assign IP-based subscribers to a TDF domain. Multiple subscribers can be assigned to the same TDF domain.

IP-based TDF domains include the following information:

- An IP-based type of subscriber.
- The TDF logical interface (mif) that handles the subscriber traffic. A TDF interface is distinct from other types of interfaces and is used to associate a TDF domain's subscribers with an access interface in a virtual routing and forwarding table (VRF). The TDF logical interface also identifies the TDF service set that is applied to the traffic.
- (Optional) The PCEF profile that must be applied to the TDF subscriber. The PCEF profile specifies how to apply policy and charging rules to the TDF subscriber traffic. If the TDF domain does not specify a PCEF profile, you must configure a PCEF profile selection process in addtion to the TDF domain selection process.
- Source IP addresses for uplink traffic and destination IP addresses for downlink traffic that you do *not* want to undergo TDF processing.
- Idle timeout and maximum number of subscribers for the TDF domain.
- Source IP addresses for users who can become TDF subscribers, using address pools.
- (Not applicable to snooped messages) The enabling or disabling of an immediate RADIUS response message from the MX Series router to the accounting start message received from a gateway GPRS support node (GGSN), Packet Data Network Gateway (PGW), or broadband network gateway (BNG) RADIUS client.

Copyright © 2018, Juniper Networks, Inc.

- The method for constructing the Subscription-Id for the Diameter credit control request (CCR) message that is sent from the TDF to the PCRF for a TDF subscriber.
- The local policy (drop/forward packets, maximum bit rate, burst size) to apply to the subscriber packets entering the access interface of the TDF domain if a TDF subscriber session does not exist.
- One or more interfaces that face the access network and can carry traffic for the TDF subscriber.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- IP-Based Subscriber Setup Overview on page 88
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92

Understanding Source IP Filtering with Address Pools in TDF Domains for IP-Based Subscribers

The TDF domain that is assigned to an IP-based subscriber can identify a set of source IP addresses of packets that need to undergo TDF processing. These sets of IP addresses are configured using address pools. Address pools can then be added to a TDF domain.

Address pools contain a set of IP addresses specified by network prefixes. You can configure more than one set of addresses in an address pool. You can configure address pools to contain IPv4 addresses or IPv6 addresses, but not both.

You can configure an address pool as a default pool, and a TDF domain uses the default address pool when an address pool is not explicitly specified for the TDF domain.

Related Documentation

- Configuring Address Pools for Source-IP Filtering of IP-Based Subscribers on page 99

Understanding Selection of Properties for an IP-Based TDF Subscriber

When the MX Series router receives a RADIUS accounting start request from the access network's gateway GPRS support node (GGSN), Packet Data Network Gateway (PGW), or broadband network gateway (BNG) for an IP-based subscriber, it needs to select the properties to apply to a subscriber by selecting a traffic detection function (TDF) domain before setting up a TDF subscriber session. The domain-selection configuration identifies the values that various AVPs (such as the 3GPP IMSI or the IPv4 address) in the RADIUS request must match to select a particular TDF domain. For RADIUS requests that were snooped, the domain-selection configuration can identify the snoop segment that matched the request.

The domain-selection configuration includes one or more **term** statements, each of which includes **from** statements that must all be matched, and a **then** statement that identifies the name of the TDF domain. When a term matches, further terms are not evaluated if

Copyright © 2018, Juniper Networks, Inc.

a PCEF profile is specified in either the selected TDF domain or in the **then** statement. If a PCEF profile is not specified in either the selected TDF domain or in the **then** statement, further terms are evaluated to find a PCEF profile for the subscriber.

If no TDF domain is selected, then the TDF subscriber session is not set up.

Before you can configure the TDF domain selection, you must configure a TDF gateway, the TDF domains, and the RADIUS client.

The match conditions for TDF domain selection include:

- (Not applicable to snooped messages) The RADIUS client (GGSN, PGW, or BNG) that is sending the accounting start request
- Values for called-station-id, calling-station-id, class, framed-ip-address, framed-ipv6-prefix, 3gpp-imsi, nas-ip-address, or user-name AVPs
- Values for other AVPs you identify

Figure 11 on page 91 shows an overview of the IP-based subscriber setup process.

Figure 11: IP-Based Subscriber Setup Process



Related Documentation

- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based and IFL-Based TDF Subscribers Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

- IP-Based Subscriber Setup Overview on page 88
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107

Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber

As part of the traffic detection function (TDF) subscriber session creation, the subscriber is assigned a policy and charging enforcement function (PCEF) profile, which specifies how policy and charging control (PCC) rules are defined on the TDF.

If every IP-based subscriber assigned to a TDF domain can share the same PCEF profile, then the PCEF profile can be specified within the TDF domain, under the **[edit unified-edge gateways tdf *gateway-name* domains]** hierarchy level. (For IFL-based subscribers, the PCEF profile *must* be specified within the TDF domain.)

If all of the IP-based subscribers assigned to the same TDF domain cannot share the same PCEF profile, the TDF domain does not specify a PCEF profile, and the PCEF profile selection must be configured under the **[edit unified-edge gateways tdf *gateway-name* domain-selection term]** hierarchy level. The **domain-selection term** consists of a **from** and a **then** statement.

The **from** statement identifies the match conditions for the subscriber. This includes the RADIUS client (GGSN, PGW, or BNG) that is sending the accounting start request for the subscriber and the values for particular AVPs in the message.

The **then** statement identifies the PCEF profile to assign to the subscriber. The **then** statement can also include the name of the TDF domain to assign to the subscriber. If the **then** statement only includes the PCEF profile, then another **domain-selection term** must assign a TDF domain to the subscriber.

When both a PCEF profile and a TDF domain are assigned to a subscriber in a **domain-selection term** statement, that PCEF profile is used even if the TDF domain specifies another PCEF profile.

Example: The TDF domain **domain1** specifies a PCEF profile. The **domain-selection term** does not need to specify a PCEF profile.

```
[edit unified-edge gateways tdf tdf1]
domain-selection {
   term 1 {
      from {
         client {
            client1;
         }
         user-name matches carrierA
      }
      then {
```


Copyright © 2018, Juniper Networks, Inc.

```
        domain domain1;
      }
    }
}
```

Example: The TDF domain **domain2** does not specify a PCEF profile. A **domain-selection term** must specify a PCEF profile. In this example, the PCEF profile is specified in the same term as the TDF domain.

```
[edit unified-edge gateways tdf tdf1]
domain-selection {
  term 1 {
    from {
      framed-ip-address equals 192.0.2.1/32
    }
    then {
      domain domain2;
      pcef-profile pcef3;
    }
  }
}
```

Example: The TDF domain **domain2** does not specify a PCEF profile. A **domain-selection term** must specify a PCEF profile. In this example, only the first term selects the TDF domain, so other terms must be added to select the PCEF profile.

```
[edit unified-edge gateways tdf tdf1]
domain-selection {
  term 1 {
    from {
      client {
        client2;
      }
      user-name matches carrierB
    }
    then {
      domain domain2;
    }
  }
  term 2 {
    from {
      framed-ip-address equals 192.0.2.1/32
    }
    then {
      pcef-profile pcef3;
    }
  }
  term 3{
    from {
      framed-ip-address equals 198.51.100.2/32
    }
    then {
      pcef-profile pcef4;
```

Copyright © 2018, Juniper Networks, Inc.

```
    }
  }
}
```

Related Documentation

- IP-Based and IFL-Based TDF Subscribers Overview on page 88
- IP-Based Subscriber Setup Overview on page 88
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107

Snooping RADIUS Accounting Requests for IP-Based Subscribers Overview

When the gateway GPRS support node (GGSN), Packet Data Network Gateway (PGW), or broadband network gateway (BNG) does not identify the MX Series router as a RADIUS server, RADIUS accounting requests are not sent to a particular MX Series router IP address and interface configured for RADIUS messages. In this situation, you can configure the MX Series router to actively examine RADIUS accounting requests that pass through the MX Series router. This process is known as *snooping*. Junos OS identifies accounting requests that match a filter you configure, copies those requests, and sends them to the subscriber processing module.

To configure snooping, you configure filters called *snoop segments*. You can include the following conditions in a snoop segment:

- Destination IP address of the accounting request
- Shared secret between the accounting request sender and the MX Series router
- (Optional) Destination port of the accounting request
- (Optional) MX Series router interface that receives the accounting request
- (Optional) Source IP address of accounting requests from a GGSN, PGW, or BNG

You can also configure the length of time to cache the accounting request that was snooped. Any duplicate request that is received by the MX Series router within this time is dropped.

You can configure multiple snoop segments.

Related Documentation

- IP-Based Subscriber Setup Overview on page 88
- Configuring IP-Based TDF Subscriber Setup When Accounting Requests Are Snooped on page 98
- Configuring Snooping of RADIUS Accounting Requests for IP-Based Subscribers on page 113

Copyright © 2018, Juniper Networks, Inc.

Understanding IFL-Based Subscriber Setup

You use the CLI to configure an IFL-based subscriber for a particular interface or set of access interfaces. All user traffic that uses these interfaces belongs to the same subscriber session. The IFL-based subscriber session becomes active when at least one of its access interfaces is up.

You can specify the following types of interfaces:

- Physical Layer 3 Ethernet interface
- Layer 3 Aggregated Ethernet interface
- Integrated routing and bridging (IRB) interface
- IRB that contains Ether-channel and physical interface members
- Logical Tunnel interface

You specify how an IFL-based subscriber's traffic is processed by configuring the properties of the TDF domain in which the IFL-based subscriber is configured, which includes a pointer to the PCEF profile to assign to the subscriber.

When an IFL-based subscriber session is created, it is anchored on a session PIC based on a round-robin selection process. If a stand-alone session PIC goes down and any IFL-based subscribers are anchored on that PIC, Junos OS re-anchors a subscriber onto another session PIC.

An IFL-based subscriber session is deleted in the following situations:

- All of the subscriber's access interfaces are down. When at least one interface comes back up, the subscriber session is restored.
- Subscriber is removed from the configuration with the CLI.
- Subscriber is set to deactivate with the CLI.
- Subscriber is cleared with the CLI. You can later restore the subscriber by using the revert option with the clear command. (See **clear unified-edge tdf subscribers**.)

Related Documentation

- IP-Based and IFL-Based TDF Subscribers Overview on page 88
- Understanding the Definition of a Set of IFL-Based Subscriber Properties with a TDF Domain on page 96

Copyright © 2018, Juniper Networks, Inc.

Understanding the Definition of a Set of IFL-Based Subscriber Properties with a TDF Domain

A traffic detection function (TDF) domain identifies a set of properties for the IFL-based subscribers configured in the TDF domain. You can create several TDF domains if you have multiple categories of subscribers. Multiple subscribers can be assigned to the same TDF domain.

TDF domains include the following information:

- Logical interface-based type of subscriber.
- Name of each subscriber.
- Interfaces that belong to a subscriber. An interface can belong to only one subscriber.
- The TDF logical interface (mif) that handles the subscriber traffic. A TDF interface is distinct from other types of interfaces and is used to associate a TDF domain's subscribers with an access interface in a virtual routing and forwarding table (VRF). The TDF logical interface also identifies the TDF service set that is applied to the traffic.
- The PCEF profile that must be applied to the TDF subscriber. The PCEF profile specifies how to apply policy and charging rules to the TDF subscriber traffic.
- Source IP addresses for uplink traffic and destination IP addresses for downlink traffic you do not want to undergo TDF processing.

Related Documentation

- Configuring IFL-Based TDF Subscribers and Properties with a TDF Domain on page 117
- Understanding IFL-Based Subscriber Setup on page 95

Copyright © 2018, Juniper Networks, Inc.

Configuring IP-Based TDF Subscriber Setup When MX Series Router Is a RADIUS Server

This task describes how to configure IP-based TDF subscriber setup when the gateway GPRS support node (GGSN), Packet Data Network Gateway (PGW), or broadband network gateway (BNG) identifies the MX Series router as a RADIUS server. An IP-based TDF subscriber is defined by the AVP values in the RADIUS accounting request received.

Before you configure the subscriber setup, you must do the following:

- Configure the access interfaces on the MX Series router chassis.
- Configure the PCEF profile.
- Configure the interface and IP address that you want to receive RADIUS requests on the MX Series router.
- Configure a TDF gateway.

To configure IP-based subscriber setup when the MX Series router acts as a RADIUS server:

1. Configure the TDF interfaces that can be used by TDF subscribers.

   See "Configuring a TDF Logical Interface" on page 120.

2. Associate the TDF interface to an access interface in a VRF routing instance.

   See "Configuring TDF Interface to Access Interface Associations in VRFs" on page 120.

3. Configure sets of source IP addresses that TDF domains can use to accept traffic.

   See "Configuring Address Pools for Source-IP Filtering of IP-Based Subscribers" on page 99.

4. Configure TDF domains that can be assigned to subscribers.

   See "Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain" on page 100.

5. Configure RADIUS clients that can send the subscriber accounting requests.

   See "Configuring RADIUS Clients That Send Accounting Requests for IP-Based Subscribers" on page 106.

6. Configure how Junos OS selects TDF domains and PCEF profiles for subscribers.

   See "Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers" on page 107.

Related Documentation

- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

Configuring IP-Based TDF Subscriber Setup When Accounting Requests Are Snooped

This task describes how to configure IP-based TDF subscriber setup when the gateway GPRS support node (GGSN), Packet Data Network Gateway (PGW), or broadband network gateway (BNG) does not identify the MX Series router as a RADIUS server.

Before you configure the subscriber setup, you must do the following:

- Configure the PCEF profile.
- Configure a TDF gateway.

To configure IP-based subscriber setup when the MX Series router *does not* act as a RADIUS server:

1. Configure the TDF interfaces that can be used by TDF subscribers.

   See "Configuring a TDF Logical Interface" on page 120.

2. Associate the TDF interface to an access interface.

   See "Configuring TDF Interface to Access Interface Associations in VRFs" on page 120.

3. Configure sets of source IP addresses that TDF domains can use to accept traffic.

   See "Configuring Address Pools for Source-IP Filtering of IP-Based Subscribers" on page 99.

4. Configure TDF domains that can be assigned to subscribers.

   See "Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain" on page 100.

5. Configure the snooping filters that examine RADIUS accounting requests.

   See "Configuring Snooping of RADIUS Accounting Requests for IP-Based Subscribers" on page 113.

6. Configure how Junos OS selects TDF domains and PCEF profiles for subscribers.

   See "Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers" on page 107.

Related Documentation

- IP-Based Subscriber Setup Overview on page 88
- Snooping RADIUS Accounting Requests for IP-Based Subscribers Overview on page 94

Copyright © 2018, Juniper Networks, Inc.

Configuring Address Pools for Source-IP Filtering of IP-Based Subscribers

Address pools identify a set of IP addresses that a TDF domain for IP-based subscribers uses to determine which packets undergo TDF processing.

To configure address pools:

1. Specify a name for the address pool.

```
[edit access address-assignment]
user@host# set address-pools name
```

   The pool name can contain letters, numbers, and hyphens (-) and can be up to 63 characters long.

2. Specify the protocol family (**inet** for IPv4 addresses and **inet6** for IPv6 addresses) for the address pool.

```
[edit access address-assignment]
user@host# set address-pools name family (inet | inet6)
```

   For example, to configure an address pool named *mbg-pool1* with IPv4 addresses:

```
[edit access address-assignment]
user@host# set address-pools mbg-pool1 family inet
```

3. Specify the network prefix for the address pool for the configured protocol family.

```
[edit access address-assignment]
user@host# set address-pools name family (inet | inet6) network [network-prefix]
  external-assigned
```

NOTE: A address pool must have at least one network prefix configured. You can configure more than one network prefix by including the **network** statement multiple times.

The **external-assigned** statement is required.

   For example, to configure an address pool with network prefixes 10.100.0.0/16 and 192.168.0.0/16:

```
[edit access address-assignment]
user@host# set address-pools mbg-pool1 family inet network 10.100.0.0/16
  external-assigned
user@host# set address-pools mbg-pool1 family inet network 192.168.0.0/16
  external-assigned
```

4. (Optional) Specify that the address pool is the default pool.

Copyright © 2018, Juniper Networks, Inc.

A TDF domain uses the default address pool to specify the source addresses of packets that undergo TDF processing when an address pool is not specified for the TDF domain.

```
[edit access address-assignment]
user@host# set address-pools name default-pool
```

Related Documentation

- Understanding Source IP Filtering with Address Pools in TDF Domains for IP-Based Subscribers on page 90
- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- IP-Based Subscriber Setup Overview on page 88

Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain

You define a set of properties for processing IP-based subscriber traffic and for setting up the subscriber session by configuring a TDF domain. You can create multiple TDF domains.

A potential IP-based subscriber is assigned to a TDF domain through a TDF domain-selection process that you configure in another topic.

Before you begin to create a TDF domain for IP-based subscribers, make sure that you have done the following:

- Configured the TDF interface (mif-) that the TDF domain uses.
- Configured the access-facing interfaces that the TDF domain uses.
- Configured a VRF routing instance that includes the TDF interface and the access-facing interfaces.
- Configured the PCEF profile if the TDF domain specifies one.
- Configured the address pool that contains source IP addresses of packets that are excluded from TDF processing for the TDF domain.

To configure a TDF domain for IP-based subscribers:

1. Configuring the TDF Domain Name and AAA Parameters on page 101
2. Configuring Address Filtering on page 103
3. Configuring Subscriber Services and Policies on page 103
4. Configuring Access Interfaces on page 104
5. Configuring Session Controls on page 104
6. Configuring Default Policy on page 105

Copyright © 2018, Juniper Networks, Inc.

Configuring the TDF Domain Name and AAA Parameters

To configure the TDF domain name and the AAA parameters that are used by the TDF domain to create TDF IP-based subscriber sessions:

1. Specify a name for the TDF domain. The name can be from 1 through 50 characters long.

   ```
   [edit unified-edge gateways tdf gateway-name]
   user@host# set domains domain-name
   ```

2. (Optional) Configure the TDF domain for IP-based subscribers.

   ```
   [edit unified-edge gateways tdf gateway-name domains domain-name]
   user@host# set subscriber-type ip
   ```

   You may omit this step because the default **subscriber-type** for TDF domains is **ip**.

3. Specify one or more methods for constructing the Subscription-Id for the Diameter credit control request (CCR) message that is sent from the TDF to the PCRF for subscribers belonging to the TDF domain.

   a. Specify the type of information to use for the Subscription-Id.

      You can specify multiple types, and the order of preference matches the order in which you enter the types. Table 7 on page 102 describes the types.

      ```
      [edit unified-edge gateways tdf gateway-name domains domain-name ip-subscriber]
      user@host# set subscription-id subscription-id-options entry-name id-components
        [use-class | use-imsi | use-msisdn | use-nai | use-nas-port | use-nas-port-id |
        use-realm | use-username]
      ```

      You can specify multiple methods by including the *entry-name* variable multiple times.

   b. If you selected **use-class** in Step a, you can also configure a regular expression to parse the Class attribute contents, specify characters to insert between the resulting regular expression groups, and specify the subscription ID type.

      ```
      [edit unified-edge gateways tdf gateway-name domains domain-name ip-subscriber
        subscription-id]
      user@host# set use-class regex "value"
      user@host# set use-class pattern "pattern"
      user@host# set use-class subscription-id-type (imsi | msisdn | nai | private | sip-uri)
      ```

      where *value* is a regular expression and *pattern* indicates the characters to insert between regular expression groups, which are identified with **\n** for a group number.

      For example, the following configuration generates **" 000118191129|ALICE:DRAV3:"** out of **" 000118191129#000118191129#ALICE:DRAV3:#7168#nflat#ADSL##"** and sets the type to IMSI:

Copyright © 2018, Juniper Networks, Inc.

```
[edit unified-edge gateways tdf TDF1 domains domain1 ip-subscriber subscription-id
  ]
user@host# set use-class regex "[^#]*#\([^#]*\)\#\([^#]*\)"
user@host# set use-class pattern "\1|\2"
user@host# set use-class subscription-id-type imsi
```

c. Specify a constant string for the Subscription-Id-Data value.

This constant value is used if none of the **subscription-id-options** methods can be used. In such a case, the Subscription-Id-Type is END_USER_PRIVATE.

```
[edit unified-edge gateways tdf gateway-name domains domain-name ip-subscriber]
user@host# set subscription-id constant value
```

Table 7: Options for id-components of Subscription-Id

Option	Subscription-Id Type	Subscription-Id Data
use-class	Configurable	Entire Class attribute by default. Class attribute value can be parsed with **regex** option under the **[edit unified-edge gateways tdf *gateway-name* domains *domain-name* subscription-id use-class]** hierarchy.
use-imsi	END_USER_IMSI	3GPP-IMSI
use-msisdn	END_USER_E164	Calling-Station-Id
use-nai	END_USER_NAI	User-Name
use-nas-port	END_USER_PRIVATE	NAS-Port
use-nas-port-id	END_USER_PRIVATE	NAS-Port-Id
use-realm	END_USER_PRIVATE	Realm portion of the User-Name in NAI format
use-username	END_USER_PRIVATE	Username portion of the User-Name in NAI format

4. (Not applicable to snooped messages) Enable or disable the sending of an immediate RADIUS response message to the accounting start message received from a gateway GPRS support node (GGSN), Packet Data Network Gateway (PGW), or broadband network gateway (BNG) RADIUS client (disabled is the default).

   If the option is disabled, the response is sent after the TDF subscriber session creation is complete.

```
[edit unified-edge gateways tdf gateway-name domains domain-name ip-subscriber]
user@host# set immediate-accounting-response (enabled | disabled)
```


Copyright © 2018, Juniper Networks, Inc.

Configuring Address Filtering

To restrict the traffic that undergoes TDF processing for the TDF domain by identifying source IP addresses for uplink traffic and destination IP addresses for downlink traffic:

1. Identify the network prefix of source and destination IP addresses for packets that *do not* undergo TDF processing. Specify **inet** for IPv4 prefixes and **inet6** for IPv6 prefixes.

   ```
   [edit unified-edge gateways tdf gateway-name domains domain-name]
   user@host# set subscriber-exclude-prefix family (inet | inet6) network address
     net-mask
   ```

2. Identify the address pool that contains source and destination IP addresses of packets that undergo TDF processing. Specify **inet** for IPv4 prefixes and **inet6** for IPv6 prefixes.

   ```
   [edit unified-edge gateways tdf gateway-name domains domain-name ip-subscriber ]
   user@host# set subscriber-address (inet | inet6) pool pool-name
   ```

   NOTE: The address pool must be configured at the **[edit access address-assignment]** hierarchy level.

Configuring Subscriber Services and Policies

To configure the services and policies for IP-based subscribers that belong to the TDF domain:

1. Identify the TDF interface for the TDF domain.

   The TDF domain uses the service set that is applied to this TDF interface.

   ```
   [edit unified-edge gateways tdf gateway-name domains domain-name]
   user@host# set tdf-interface mif.number
   ```

   NOTE: The TDF interface (mif) must have been previously configured at the **[edit interfaces]** hierarchy level.

2. (Optional) Identify the PCEF profile that the TDF domain uses to apply policies.

   If you do not identify a PCEF profile, then the PCEF profile must be assigned under the **[edit unified-edge gateways tdf *gateway-name* domain-selection term]** hierarchy.

   ```
   [edit unified-edge gateways tdf gateway-name domains domain-name]
   user@host# set pcef-profile name
   ```

Copyright © 2018, Juniper Networks, Inc.

NOTE: The PCEF profile must have been previously configured at the **[unified-edge pcef]** hierarchy level.

Configuring Access Interfaces

To configure the interfaces that face the access network and carry traffic to and from the IP-based subscribers that belong to the TDF domain:

- Specify at least one interface. You can specify multiple interfaces.

```
[edit unified-edge gateways tdf gateway-name domains domain-name ip-subscriber]
user@host# set access-interfaces interface-name
```

Configuring Session Controls

To configure the TDF session controls for subscribers that belong to the TDF domain:

1. Configure the idle timeout (in minutes) for the TDF subscriber session. The range is 0 through 300.

```
[edit unified-edge gateways tdf gateway-name domains domain-name ip-subscriber]
user@host# set idle-timeout idle-timeout
```

2. Configure the default TDF subscriber maximum bit rate (MBR) for uplink and downlink traffic.

   Uplink traffic originates from the subscriber towards the public data network (PDN), and downlink traffic comes from the PDN and is destined for the subscriber. The range is 0 through 6,144,000 Kbps.

```
[edit unified-edge gateways tdf gateway-name domains domain-name]
user@host# set maximum-bit-rate uplink mbr-uplink-value downlink
  mbr-downlink-value
```

3. Configure the default TDF subscriber allowed burst size for uplink and downlink traffic.

   Uplink traffic originates from the subscriber towards the public data network (PDN), and downlink traffic comes from the PDN and is destined for the subscriber. The range is 1500 through 1,500,000,000 bytes.

```
[edit unified-edge gateways tdf gateway-name domains domain-name]
user@host# set burst-size uplink uplink-burst-size downlink downlink-burst-size
```

4. Configure the maximum number of subscriber sessions allowed (in thousands) for the TDF domain. The range is 100 thousands through 5000 thousands.

```
[edit unified-edge gateways tdf gateway-name domains domain-name ip-subscriber]
```


Copyright © 2018, Juniper Networks, Inc.

```
user@host# set maximum-subscribers number
```

Configuring Default Policy

To configure the default local policy for handling subscriber traffic entering the access interface of the TDF domain if a TDF subscriber session does not exist:

1. Configure the flow action to take on the subscriber's traffic.

   ```
   [edit unified-edge gateways tdf gateway-name domains domain-name ip-subscriber]
   user@host# set default-local-policy flow-action (drop | forward)
   ```

2. Configure the maximum bit rate for the subscriber's traffic.

   ```
   [edit unified-edge gateways tdf gateway-name domains domain-name ip-subscriber]
   user@host# set default-local-policy maximum-bit-rate uplink mbr-uplink-value
     downlink mbr-downlink-value
   ```

   Uplink traffic originates from the subscriber towards the public data network (PDN); downlink traffic comes from the PDN and is destined for the subscriber. The range is 0 through 6144000 Kbps.

3. Configure the allowed burst size for the subscriber's traffic.

   ```
   [edit unified-edge gateways tdf gateway-name domains domain-name ip-subscriber]
   user@host# set default-local-policy burst-size uplink uplink-burst-size downlink
     downlink-burst-size
   ```

   Uplink traffic originates from the subscriber towards the public data network (PDN); downlink traffic comes from the PDN and is destined for the subscriber. The range is 1500 through 1,500,000,000 bytes.

Related Documentation

- IP-Based and IFL-Based TDF Subscribers Overview on page 88
- IP-Based Subscriber Setup Overview on page 88
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- Configuring Address Pools for Source-IP Filtering of IP-Based Subscribers on page 99
- Understanding PCEF Profiles on page 56
- Configuring a Services Interface for a Session PIC or Service PIC on page 16

Copyright © 2018, Juniper Networks, Inc.

Configuring RADIUS Clients That Send Accounting Requests for IP-Based Subscribers

You specify an MX Series router RADIUS client for each gateway GPRS support node (GGSN), Packet Data Network Gateway (PGW), or broadband network gateway (BNG) that sends IP-based subscriber session requests and identifies the MX Series router as a RADIUS server. This task is not used for snooped accounting requests.

Before you begin to configure a RADIUS client, make sure that you have configured the interface and IP address that you want to receive RADIUS requests on the MX Series router.

To configure the RADIUS clients:

1. Configure the name of the RADIUS client.

   ```
   [edit access radius]
   user@host# set clients client-name
   ```

2. Specify the IP address from which the RADIUS client sends the RADIUS requests.

   ```
   [edit access radius]
   user@host# set clients client-name address client-address
   ```

3. Specify the MX Series router interface and IPv4 address that receive RADIUS requests from the GGSN, PGW, or BNG.

   ```
   [edit access radius]
   user@host# set clients client-name source-interface interface ipv4-address address
   ```

4. Configure a shared secret to be used by the MX Series router and the RADIUS client for accounting.

   ```
   [edit access radius]
   user@host# set clients client-name accounting secret password
   ```

5. (Optional) Specify that the framed-ip-address is used for subscriber creation when both the framed-route and framed-ip-address attributes are in the RADIUS accounting request from the RADIUS client. The framed-ip-netmask is also used for subscriber creation if it is in the request.

   ```
   [edit access radius]
   user@host# set clients client-name prefer-framed-ip-address
   ```

   By default, the framed-route attribute is used for subscriber creation when both the framed-route and framed-ip-address attributes are in the RADIUS accounting request.

Copyright © 2018, Juniper Networks, Inc.

6. (Optional) Specify that the framed-ipv6-prefix is used for subscriber creation when both the delegated-ipv6-prefix and framed-ipv6-prefix attributes are in the RADIUS accounting request from the RADIUS client.

   ```
   [edit access radius]
   user@host# set clients client-name prefer-framed-ipv6-prefix
   ```

   By default, the delegated-ipv6-prefix attribute is used for subscriber creation when both the delegated-ipv6-prefix and framed-ipv6-prefix attributes are in the RADIUS accounting request.

7. Configure the duration, in seconds, that the RADIUS response messages (sent for request messages) are stored in the MX Series router response cache before they time out.

   ```
   [edit access radius]
   user@host# set clients client-name accounting response-cache-timeout seconds
   ```

8. Enable the RADIUS client for a specific TDF gateway.

   ```
   [edit unified-edge gateways tdf gateway-name]
   user@host# set aaa clients client-name
   ```

   Use the *client-name* that you configured in Step 1.

Related Documentation

- IP-Based Subscriber Setup Overview on page 88

Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers

You must configure the criteria that Junos OS uses to select a TDF domain for an IP-based subscriber, which determines how the subscriber session is set up and how the subscriber traffic is treated. (The domain-selection process does not apply to IFL-based subscribers, who are automatically assigned to the TDF domain in which they are configured.) You configure a **term** to identify conditions that must be matched in the incoming RADIUS request in order to select a particular TDF domain.

You configure the selection of the policy-control properties by selecting a PCEF profile. The PCEF profile can be identified in the selected TDF domain, or you can independently configure the criteria for the selection of a PCEF profile.

Before you begin to configure TDF domain or PCEF profile selection, make sure that you have done the following:

- Configured a TDF gateway.
- Configured the TDF domains.

Copyright © 2018, Juniper Networks, Inc.

- Configured the PCEF profiles.
- Configured the RADIUS client.

To configure a term for TDF domain or PCEF profile selection, perform the following tasks and repeat this process for each term you want to configure:

1. Configuring the Term Name on page 108
2. Configuring Match Conditions for the RADIUS Client on page 108
3. Configuring Match Conditions for Snoop Segments on page 108
4. Configuring Match Conditions for Predefined AVPs on page 109
5. Configuring Match Conditions for Custom AVP Attributes on page 110
6. Configuring the TDF Domain to Select on page 112
7. Configuring the PCEF Profile to Select on page 112

Configuring the Term Name

To configure the name for the **term** that contains the **from** statements and the **then** statement:

- Configure a term name that is 1 through 50 characters in length.

```
[edit unified-edge gateways tdf gateway-name domain-selection]
user@host# set term term-name
```

Configuring Match Conditions for the RADIUS Client

Before you begin to configure a match condition for a RADIUS client, you must ensure that you have configured the RADIUS client at the **[edit access radius clients]** hierarchy level, and specified it as the **aaa-client** at the **[edit unified-edge gateways tdf *gateway-name*]** hierarchy level.

To configure a match condition for the RADIUS client that sent the incoming RADIUS request:

- Specify the client.

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name]
user@host# set from client client-name
```

Configuring Match Conditions for Snoop Segments

For RADIUS requests that were snooped, the domain-selection configuration can identify the snoop segment that matched the request.

To configure a match condition for the snoop segment:

- Specify the snoop segment.

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name]
```


Copyright © 2018, Juniper Networks, Inc.

```
user@host# set from snoop-segment snoop-segment-name
```

Configuring Match Conditions for Predefined AVPs

To configure match conditions for the called-station-id, calling-station-id, class, framed-ip-address, framed-ipv6-prefix, 3gpp-imsi, nas-ip-address, or user-name AVP in the incoming RADIUS request from the subscriber:

1. Configure any called-station-id match condition.

   ```
   [edit unified-edge gateways tdf gateway-name domain-selection term term-name]
   user@host# set from called-station-id (equals | matches) value
   ```

   Use **equals** to specify a value the called-station-id must equal or use **matches** to specify a regular expression the called-station-id must match.

2. Configure any calling-station-id match condition.

   ```
   [edit unified-edge gateways tdf gateway-name domain-selection term term-name]
   user@host# set from calling-station-id equals value
   ```

   or

   ```
   [edit unified-edge gateways tdf gateway-name domain-selection term term-name]
   user@host# set from calling-station-id matches value
   ```

   Use **equals** to specify a value the calling-station-id must equal or use **matches** to specify a regular expression the calling-station-id must match.

3. Configure any class match condition.

   ```
   [edit unified-edge gateways tdf gateway-name domain-selection term term-name]
   user@host# set from class (equals | has-prefix | has-suffix | matches) value
   ```

   Use **equals** to specify a value the class must equal, use **has-prefix** to specify the prefix that the class must have, use **has-suffix** to specify the suffix that the class must have, or use **matches** to specify a regular expression the class must match.

4. Configure any framed-ip-address match condition.

   ```
   [edit unified-edge gateways tdf gateway-name domain-selection term term-name]
   user@host# set from framed-ip-address equals value
   ```

5. Configure any framed-ipv6-prefix match condition.

   ```
   [edit unified-edge gateways tdf gateway-name domain-selection term term-name]
   user@host# set from framed-ipv6-prefix equals value
   ```

6. Configure any 3gpp-imsi match condition.

Copyright © 2018, Juniper Networks, Inc.

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name]
user@host# set from 3gpp-imsi (equals | has-prefix | has-suffix | matches) value
```

Use **equals** to specify a value the 3gpp-imsi must equal, use **has-prefix** to specify the prefix that the 3gpp-imsi must have, use **has-suffix** to specify the suffix that the 3gpp-imsi must have, or use **matches** to specify a regular expression the 3gpp-imsi must match.

7. Configure any nas-ip-address match condition.

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name]
user@host# set from nas-ip-address equals value
```

8. Configure any user-name match condition.

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name]
user@host# set from user-name (equals | has-prefix | has-suffix | matches) value
```

Use **equals** to specify a value the user-name must equal, use **has-prefix** to specify the prefix that the user-name must have, use **has-suffix** to specify the suffix that the user-name must have, or use **matches** to specify a regular expression the user-name must match.

Configuring Match Conditions for Custom AVP Attributes

To configure match conditions for up to five custom AVP attributes (other than the called-station-id, calling-station-id, class, framed-ip-address, framed-ipv6-prefix, 3gpp-imsi, nas-ip-address, or user-name) in the incoming RADIUS request from the subscriber:

1. Configure an attribute name that is 1 through 50 characters in length.

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name]
user@host# set from attribute name
```

2. Configure any match condition for the custom attribute's AVP code.

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  attribute name]
user@host# set code numeric-code
```

3. Configure any match condition for the custom attribute's vendor-id.

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  attribute name]
user@host# set vendor-id vendor-id
```

4. Configure any match condition for custom attribute data in integer format.

Copyright © 2018, Juniper Networks, Inc.

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  attribute name]
user@host# set format integer (equals | greater-than | less-than) value
```

5. Configure any match condition for custom attribute data in string format.

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  attribute name]
user@host# set format string (equals | has-prefix | has-suffix | matches) value
```

   Use **equals** to specify a value the string must equal, use **has-prefix** to specify the prefix that the string must have, use **has-suffix** to specify the suffix that the string must have, or use **matches** to specify a regular expression the string must match.

6. Configure any match condition for custom attribute data in time format.

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  attribute name]
user@host# set format time (equals | greater-than | less-than) value
```

7. Configure any match condition for custom attribute data in IPv4 address format.

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  attribute name]
user@host# set format v4address equals value
```

8. Configure any match condition for custom attribute data in IPv6 address format.

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  attribute name]
user@host# set format v6address equals value
```

9. Configure any match condition for custom attribute data in IPv6 address prefix format.

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  attribute name]
user@host# set format v6prefix equals value
```

Copyright © 2018, Juniper Networks, Inc.

Configuring the TDF Domain to Select

To specify the TDF domain to select when the **from** conditions in the **term** have been matched:

- Specify the TDF domain name.

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name]
user@host# set then domain tdf-domain-name
```

Configuring the PCEF Profile to Select

If a particular TDF domain does not specify a PCEF profile or you want different members of the same TDF domain to have different PCEF profiles, you must specify the PCEF profile under the **[edit unified-edge gateways tdf *gateway-name* domain-selection]** hierarchy level.

To specify the PCEF profile to select when the **from** conditions in the **term** have been matched, use one of the following methods:

- Specify the PCEF profile name in the same **term** statement that specifies the TDF domain.

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name]
user@host# set from {...}
user@host# set then domain tdf-domain-name
user@host# set then pcef-profile pcef-profile-name
```

- Specify the PCEF profile name in a different **term** statement.

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name]
user@host# set from {...}
user@host# set then pcef-profile pcef-profile-name
```

Related Documentation

- IP-Based and IFL-Based TDF Subscribers Overview on page 88
- IP-Based Subscriber Setup Overview on page 88
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Configuring a TDF Gateway on page 16
- Configuring RADIUS Clients That Send Accounting Requests for IP-Based Subscribers on page 106

Copyright © 2018, Juniper Networks, Inc.

Configuring Snooping of RADIUS Accounting Requests for IP-Based Subscribers

Copyright © 2018, Juniper Networks, Inc.

If a gateway GPRS support node (GGSN), Packet Data Network Gateway (PGW), or broadband network gateway (BNG) does not treat the MX Series router as a RADIUS server, Junos OS must actively snoop RADIUS accounting requests from that gateway to set up TDF subscriber sessions. Snooping uses a filter called a *snoop segment* to identify the requests to send to the subscriber management module.

To configure snooping of RADIUS accounting requests:

1. Configure a name for the snoop segment.

   ```
   [edit access radius]
   user@host# set snoop-segments snoop-segment-name
   ```

   For example:

   ```
   [edit access radius]
   user@host# set snoop-segments 123
   ```

2. Specify the destination IP address of accounting requests to snoop.

   ```
   [edit access radius snoop-segments snoop-segment-name]
   user@host# set destination-ip-address destination-address
   ```

   For example:

   ```
   [edit access radius snoop-segments 123]
   user@host# set destination-ip-address 10.102.30.102
   ```

3. (Optional) Specify the destination port of accounting requests to snoop.

   ```
   [edit access radius snoop-segments snoop-segment-name]
   user@host# set destination-port destination-port
   ```

   For example:

   ```
   [edit access radius snoop-segments 123]
   user@host# set destination-port 52000
   ```

   If this statement is not included, the destination port is set to 1813.

4. (Optional) Specify the source IP address of accounting requests from a GGSN, PGW, or BNG to snoop.

   ```
   [edit access radius snoop-segments snoop-segment-name]
   user@host# set source-ip-address source-address
   ```

   For example:

   ```
   [edit access radius snoop-segments 123]
   user@host# set source-ip-address 10.11.11.11
   ```


Copyright © 2018, Juniper Networks, Inc.

If the source IP address is not included, snooping of accounting requests is not restricted by their source.

5. Specify the MX Series router interface on which the accounting requests to be snooped are received.

```
[edit access radius snoop-segments snoop-segment-name]
user@host# set source-interface source-interface
```

For example:

```
[edit access radius snoop-segments 123]
user@host# set source-interface ge-0/0/0.0
```

If the source interface is not included, snooping of accounting requests is not restricted by the interface that receives the request.

6. Specify the shared secret for the MX Series router and the accounting request sender.

```
[edit access radius snoop-segments snoop-segment-name]
user@host# set shared-secret secret
```

For example:

```
[edit access radius snoop-segments 123]
user@host# set shared-secret juniper
```

If the shared secrets do not match, the subscriber session is not set up.

7. (Optional) Configure the number of seconds to cache the accounting request that was snooped. If the same request is received by the MX Series router within this time, it is considered a duplicate request and is dropped.

```
[edit access radius snoop-segments snoop-segment-name]
user@host# set request-cache-timeout timeout
```

For example:

```
[edit access radius snoop-segments 123]
user@host# set request-cache-timeout 4
```

8. Repeat Steps 1 through 7 to configure additional snoop segments.

Copyright © 2018, Juniper Networks, Inc.

9. Assign one or more snoop segments to the TDF gateway.

```
[edit unified-edge gateways tdf gateway-name aaa]
user@host# set snoop-segments [snoop-segment-name]
```

For example, the following configures **gateway1** to snoop accounting requests destined for the RADIUS server 10.102.30.102 on port 52000 that originate from IP address 10.11.11.11 and are received on interface ge-0/0/0.0:

```
[edit unified-edge gateways tdf gateway1 aaa]
user@host# set snoop-segments 123
```

Related Documentation

- Snooping RADIUS Accounting Requests for IP-Based Subscribers Overview on page 94
- Configuring IP-Based TDF Subscriber Setup When Accounting Requests Are Snooped on page 98
- IP-Based Subscriber Setup Overview on page 88

Configuring IFL-Based TDF Subscriber Setup

This task describes how to configure IFL-based TDF subscriber setup.

Before you configure the subscriber setup, you must do the following:

- Configure the interfaces on the MX Series router chassis.
- Configure the PCEF profile.
- Configure a TDF gateway.

To configure IFL-based subscriber setup:

1. Configure the TDF interfaces that TDF subscribers can use.

   See "Configuring a TDF Logical Interface" on page 120.

2. Associate the TDF interface to an access interface in a VRF routing instance.

   See "Configuring TDF Interface to Access Interface Associations in VRFs" on page 120.

3. Configure the IFL-based subscribers.

   See "Configuring IFL-Based TDF Subscribers and Properties with a TDF Domain" on page 117.

Related Documentation

- Understanding IFL-Based Subscriber Setup on page 95

Copyright © 2018, Juniper Networks, Inc.

Configuring IFL-Based TDF Subscribers and Properties with a TDF Domain

You configure one or more IFL-based TDF subscribers and a set of properties for processing the traffic for those subscribers by configuring a TDF domain. You can create multiple TDF domains.

Before you begin to create a TDF domain for IFL-based subscribers, make sure that you have done the following tasks:

- Configured the TDF interface (mif-) that the TDF domain uses.
- Configured the interfaces that the TDF domain uses.
- Configured a VRF routing instance that includes the TDF interface and the interfaces that the TDF domain uses.
- Configured the PCEF profile that the TDF domain uses.

To configure a TDF domain for IFL-based subscribers, perform the following:

1. Configuring the TDF Domain Name and Type on page 117
2. Configuring IFL-Based Subscribers on page 118
3. Configuring Address Filtering on page 118
4. Configuring Subscriber Services and Policies on page 118
5. Configuring Session Controls on page 119

Configuring the TDF Domain Name and Type

To configure the TDF domain name and type:

1. Specify a name for the TDF domain. The name can be from 1 through 50 characters long.

   ```
   [edit unified-edge gateways tdf gateway-name]
   user@host# set domains domain-name
   ```

   For example:

   ```
   [edit unified-edge gateways tdf TDF1]
   user@host# set domains ifl-1
   ```

2. Configure the subscriber type for IFL-based subscribers.

   ```
   [edit unified-edge gateways tdf gateway-name domains domain-name]
   user@host# set subscriber-type ifl
   ```

Copyright © 2018, Juniper Networks, Inc.

Configuring IFL-Based Subscribers

To configure IFL-based subscribers:

1. Configure the name for a subscriber.

   ```
   [edit unified-edge gateways tdf gateway-name domains domain-name]
   user@host# set ifl-subscriber subscriber-name
   ```

   For example:

   ```
   [edit unified-edge gateways tdf TDF1 domains ifl-1]
   user@host# set ifl-subscriber ifl-sub1
   ```

2. Configure one or more interfaces for the subscriber.

   ```
   [edit unified-edge gateways tdf gateway-name domains domain-name ifl-subscriber
     subscriber-name]
   user@host# set access-interfaces [interface-name]
   ```

   For example:

   ```
   [edit unified-edge gateways tdf TDF1 domains ifl-1 ifl-subscriber ifl-sub1]
   user@host# set access-interfaces ae0.736
   ```

   You can assign only one IFL-based subscriber to an interface.

3. Repeat Step 1 and Step 2 for each IFL-based subscriber you want to configure in the TDF domain.

Configuring Address Filtering

To restrict the traffic that undergoes TDF processing for the TDF domain by identifying source IP addresses for uplink traffic and destination IP addresses for downlink traffic:

- Identify the network prefix of source and destination IP addresses for packets that *do not* undergo TDF processing. Specify **inet** for IPv4 prefixes and **inet6** for IPv6 prefixes.

  ```
  [edit unified-edge gateways tdf gateway-name domains domain-name]
  user@host# set subscriber-exclude-prefix family (inet | inet6) network address
    net-mask
  ```

Configuring Subscriber Services and Policies

To configure the services and policies for IFL-based subscribers that belong to the TDF domain:

1. Identify the TDF interface for the TDF domain.

   The TDF domain uses the service set that is applied to this TDF interface.

Copyright © 2018, Juniper Networks, Inc.

```
[edit unified-edge gateways tdf gateway-name domains domain-name]
user@host# set tdf-interface mif.number
```

NOTE: The TDF interface (mif) must have been previously configured at the **[edit interfaces]** hierarchy level.

2. Identify the PCEF profile that the TDF domain uses to apply policies.

```
[edit unified-edge gateways tdf gateway-name domains domain-name]
user@host# set pcef-profile name
```

NOTE: The PCEF profile must have been previously configured at the **[unified-edge pcef]** hierarchy level.

Configuring Session Controls

To configure the TDF session controls for subscribers that belong to the TDF domain:

1. Configure the default TDF subscriber maximum bit rate (MBR) for uplink and downlink traffic.

   Uplink traffic originates from the subscriber towards the public data network (PDN), and downlink traffic comes from the PDN and is destined for the subscriber. The range is 0 through 6,144,000 Kbps.

```
[edit unified-edge gateways tdf gateway-name domains domain-name]
user@host# set maximum-bit-rate uplink mbr-uplink-value downlink
  mbr-downlink-value
```

2. Configure the default TDF subscriber allowed burst size for uplink and downlink traffic.

   Uplink traffic originates from the subscriber towards the public data network (PDN), and downlink traffic comes from the PDN and is destined for the subscriber. The range is 1500 through 1,500,000,000 bytes.

```
[edit unified-edge gateways tdf gateway-name domains domain-name]
user@host# set burst-size uplink uplink-burst-size downlink downlink-burst-size
```

Related Documentation

- Understanding IFL-Based Subscriber Setup on page 95
- Understanding the Definition of a Set of IFL-Based Subscriber Properties with a TDF Domain on page 96
- Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Dynamic Policies on page 80
- Configuring a Services Interface for a Session PIC or Service PIC on page 16

Copyright © 2018, Juniper Networks, Inc.

Configuring a TDF Logical Interface

A TDF logical interface is distinct from other types of interfaces and is used to associate a TDF domain's subscribers with an access interface in a virtual routing and forwarding (VRF) table and with a TDF service set. You need to configure one TDF interface logical interface (unit) for every TDF domain.

To configure a TDF interface, you configure one or more logical interfaces (units) for the interface:

1. Configure a TDF logical interface. Repeat this step for each TDF domain.

```
[edit interfaces]
user@host# set mif unit interface-unit-number family family-name
```

2. (Optional) Configure the maximum transmission unit (MTU) size for the TDF logical interface.

```
[edit interfaces]
user@host# set mtu mtu-size
```

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Configuring IFL-Based TDF Subscribers and Properties with a TDF Domain on page 117
- Configuring TDF Interface to Access Interface Associations in VRFs on page 120
- Applying Services to Subscriber-Aware Traffic with a Service Set on page 124

Configuring TDF Interface to Access Interface Associations in VRFs

Junos associates TDF interfaces (mif) with access interfaces. You must configure a virtual routing and forwarding (VRF) table for each TDF domain. The VRF must include the TDF interface and one or more access interfaces for the TDF domain.

Before you begin, make sure that you have done the following:

- Configured the access interfaces on the MX Series router chassis.
- Configured the TDF interfaces.

To configure a TDF interface-to-access port mapping in a VRF, specify the VRF and place both the TDF interface (unit) and the physical access interface unit in the same VRF.

- Configure the VRF routing instance.

```
[edit routing-instances]
user@host# set routing-instance interface mif.n
user@host# set routing-instance interface interface-name
```


Copyright © 2018, Juniper Networks, Inc.

Related Documentation

- Configuring a TDF Logical Interface on page 120
- Applying Services to Subscriber-Aware Traffic with a Service Set on page 124

Copyright © 2018, Juniper Networks, Inc.

Copyright © 2018, Juniper Networks, Inc.

CHAPTER 7

Configuring Services

- Overview of Applying Services to Subscribers on page 123
- Applying Services to Subscriber-Aware Traffic with a Service Set on page 124

Overview of Applying Services to Subscribers

Subscriber-aware services are enabled for the subscribers belonging to a specific TDF domain by creating a subscriber-aware service set. This service set is applied to the TDF domain's TDF interface (mif). These services are carried out on the service PIC that is identified by the service interface in the service set.

Subscriber-aware services are applied to a subscriber's traffic based on policy and control (PCC) rules. The PCC rules are either under local control, under PCRF dynamic control, or under activation and deactivation control by a RADIUS server, depending on the PCEF profile for the TDF domain.

You may also apply network address translation (NAT) services independently of the PCC rules by specifying NAT rules in the service set.

Figure 12 on page 123 shows the relationships among subscriber-aware service sets and other configured objects.

Figure 12: Subscriber-Aware Service Set Relationships



Related Documentation

- Applying Services to Subscriber-Aware Traffic with a Service Set on page 124
- Understanding Junos Subscriber Aware Policy and Charging Enforcement Function (PCEF) on page 44

Copyright © 2018, Juniper Networks, Inc.

Applying Services to Subscriber-Aware Traffic with a Service Set

Junos OS supports subscriber-aware services for the subscribers belonging to a particular TDF domain through the configuration of a subscriber-aware service set. The service set is assigned to the TDF domain's TDF interface (mif).

Before you configure the service set, complete the following tasks:

- Configure the service PIC for the service set.
- Configure the TDF interface (mif).
- Configure the PCEF profile at the **[edit unified-edge pcef]** hierarchy level.
- Configure any NAT rules or rule sets that you want to apply.

To configure the subscriber-aware services for a TDF domain's subscribers:

1. Configure a PCEF profile at the [**services**] hierarchy level by specifying a name for the PCEF profile. This profile is a placeholder profile with no configuration options, but it must be created.

   ```
   [edit services]
   user@host# set pcef profile pcef-profile-name
   ```

2. Configure an application identification profile by specifying a name for the profile. This profile is a placeholder profile with no configuration options, but it must be created.

   ```
   [edit services application-identification]
   user@host# set profile app-id-profile-name
   ```

3. Configure an HTTP header enrichment profile by specifying a name for the profile. This profile is a placeholder profile with no configuration options, but it must be created.

   ```
   [edit services hcm]
   user@host# set profile hcm-profile-name
   ```

4. Define a subscriber-aware service set.

   ```
   [edit services]
   user@host# set service-set service-set-name service-set-options subscriber-awareness
   ```

5. Enable PCEF services for the service set. Use the profile name that you configured in Step 1.

   ```
   [edit services service-set service-set-name]
   user@host# set pcef-profile pcef-profile-name
   ```


Copyright © 2018, Juniper Networks, Inc.

6. Enable application identification for the service set. Use the profile name that you configured in Step 2.

```
[edit services service-set service-set-name]
user@host# set application-identification-profile app-id-profile-name
```

7. Enable HTTP header enrichment for the service set. Use the profile name that you configured in Step 3.

```
[edit services service-set service-set-name]
user@host# set hcm-profile hcm-profile-name
```

8. Specify NAT rules or rule-sets for the service set.

```
[edit services service-set service-set-name]
user@host# set ([nat-rules rule-name] | nat-rule-sets rule-set-name)
```

9. Specify the services PIC interface on which the services are performed.

```
[edit services service-set service-set-name]
user@host# set interface-service service-interface interface-name
```

The *interface-name* is ams*n* if you have redundancy configured and is ms-*fpc/pci*/0 if you do not have redundancy configured.

10. Apply the service set to the TDF interface (mif) that is part of the TDF domain.

```
[edit interfaces mif unit number family family service]
user@host# set input service-set service-set-name
user@host# set output service-set service-set-name
```

NOTE: The output service set for the mif is not used by the MX Series router, but it must be configured so that the configuration commit does not fail.

Related Documentation

- Configuring Service PICs on page 18
- Configuring a TDF Logical Interface on page 120
- Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Dynamic Policies on page 80
- Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Static Policies on page 81

Copyright © 2018, Juniper Networks, Inc.

Copyright © 2018, Juniper Networks, Inc.

CHAPTER 8

Configuring Diameter

- Diameter Profiles Overview on page 127
- Juniper Networks Diameter AVPs for Subscriber Aware Policy Control on page 128
- Configuring Diameter Overview on page 129
- Configuring Diameter Profiles on page 130
- Configuring Diameter Bindings on page 131
- Configuring Diameter Network Elements on page 132
- Configuring Diameter AVPs for Gx Applications on page 133
- Configuring Diameter Peers on page 134
- Configuring the Diameter Transport on page 136
- Configuring Advertisements in Diameter Messages on page 137
- Configuring Parameters for Diameter Applications on page 138
- Configuring the Origin Attributes of the Diameter Instance on page 138

Diameter Profiles Overview

The Diameter profile provides network access information for the Diameter application. The Diameter profile specifies prioritized targets, or endpoints, for particular applications. The target specifies the destination realm, network element, and priority associated with the target.

Target selection is based on priority. A lower number has a higher priority. For load balancing, targets have the same priority.

From the prioritized list of targets for a Diameter profile, the target is selected as follows:

- The target with the highest priority (lowest number) is selected.
- In the event of a tie, where the priority is the same, target selection alternates among the peers with the same priority.

Copyright © 2018, Juniper Networks, Inc.

NOTE: Failover handling depends on what enables the policy for the application. Switching between targets based on priority, such as failing over between primary and secondary online charging servers, only occurs if the failover handling policy enables it.

After you configure the Diameter profiles, the Diameter applications can reference them. For example, when configuring transport profiles for online charging, you can associate the configured Diameter profile with the transport profile to interact with the online charging server. Similarly, when configuring profiles for provisioning Policy Charging and Control application rules, you can associate the configured Diameter profile with the policy and charging enforcement function (PCEF) profile to interact with the policy and charging rules function (PCRF).

Related Documentation

- Configuring Diameter Profiles on page 130

Juniper Networks Diameter AVPs for Subscriber Aware Policy Control

Diameter conveys information by including various attribute-value pairs (AVPs) in Diameter messages.

Table 8 on page 128 lists the AVPs for subscriber policy control.

Table 8: Juniper Networks Diameter AVPs for Subscriber Policy Control

Attribute Number	Diameter AVP	Description	Type
1100	TDF-Application-Instance-Identifier-Base	Identifies the application-group.	UTF8String
1101	Service-Chaining-Information	Provides service chaining information for dynamic steering of packets.	UTF8String
1102	LRF-Profile-Name	Provides the name of the logging and reporting framework (LRF) profile.	UTF8String
1103	HCM-Profile-Name	Provides the name of the HTTP content module.	UTF8String
1104	Forwarding-Class-Name	Provides the forwarding class name on the router.	UTF8String
1105	Redirect-VRF	Specifies whether redirection is supported. If the application flows support redirection, Redirect-VRF specifies the redirect address and address type.	UTF8String
1106	Requested-Burstsize-UL	Provides the uplink burst size specified in a QoS policy.	Integer32

Copyright © 2018, Juniper Networks, Inc.

Table 8: Juniper Networks Diameter AVPs for Subscriber Policy Control (continued)

Attribute Number	Diameter AVP	Description	Type
1107	Requested-Burstsize-DL	Provides the downlink burst size specified in a QoS policy.	Integer32
1108	Steering-Information	Specifies an optional grouped AVP that contains Steering-Uplink-VRF, Steering-Downlink-VRF, and Steering-IP-Address.	Grouped
1109	Steering-Uplink-VRF	Provides the address of uplink destination for packets if dynamic steering is supported.	UTF8String
1110	Steering-Downlink-VRF	Provides the address of downlink destination for packets if dynamic steering is supported.	UTF8String
1111	Steering-IP-Address	Identifies the IP address for HTTP redirect.	Address

Configuring Diameter Overview

If you are using a PCRF to dynamically control subscriber-aware policies, you must configure Diameter.

To configure Diameter for PCRF-controlled subscriber-aware policies:

1. Configure the remote peer to which the MX Series router sends Diameter messages.

   See "Configuring Diameter Peers" on page 134.

2. Identify the session PIC and PIC interfaces for a Diameter network element.

   See "Configuring Diameter Bindings" on page 131.

3. Configure the peers in a Diameter network element.

   See "Configuring Diameter Network Elements" on page 132.

4. Configure network access information in a Diameter profile.

   See "Configuring Diameter Profiles" on page 130.

5. (Optional) Specify the Diameter attribute-value pairs (AVPs) to include and exclude in the credit control request (CCR) messages.

   See "Configuring Diameter AVPs for Gx Applications" on page 133.

6. Configure the Diameter transport.

   See "Configuring the Diameter Transport" on page 136.

Copyright © 2018, Juniper Networks, Inc.

7. Configure the information to be advertised in Diameter messages.

   See "Configuring Advertisements in Diameter Messages" on page 137.

8. Configure the maximum number of pending requests for a Diameter application.

   See "Configuring Parameters for Diameter Applications" on page 138.

9. Configure the endpoint node that originates Diameter messages.

   See "Configuring the Origin Attributes of the Diameter Instance" on page 138.

Related Documentation

- Diameter Profiles Overview on page 127

Configuring Diameter Profiles

The Diameter profile provides network access information for the Diameter application.

NOTE: To make a change to a Diameter profile, you must be in maintenance mode. (See "Changing PCEF Profiles, PCC Rules, PCC Rulebases, Diameter Profiles, Flow Descriptions, and PCC Action Profiles" on page 182).

To configure the Diameter profile:

1. Create the Diameter profile for the Gx application (**gx-profile**).

   ```
   [edit]
   user@host# set unified-edge diameter-profiles gx-profile profile-name
   ```

2. Set up the target for the profile.

   ```
   [edit unified-edge diameter-profiles gx-profile profile-name]
   user@host# set targets target-name
   ```

3. Specify the destination realm associated with the target.

   ```
   [edit unified-edge diameter-profiles gx-profile profile-name targets target-name]
   user@host# set destination-realm realm-name
   ```

4. Specify the priority associated with the target.

   The prioritization determines failover or load-balancing behavior. For load balancing, configure the targets with the same priority.

   ```
   [edit unified-edge diameter-profiles gx-profile profile-name targets target-name]
   user@host# set priority priority-value
   ```


Copyright © 2018, Juniper Networks, Inc.

5. Specify the network element associated with the target.

```
[edit unified-edge diameter-profiles gx-profile profile-name targets target-name]
user@host# set network-element element-name
```

6. (Optional) Specify the destination host associated with the target.

```
[edit unified-edge diameter-profiles gx-profile profile-name targets target-name]
user@host# set destination-host hostname
```

Related Documentation

- Diameter Profiles Overview on page 127
- Configuring Diameter Bindings on page 131
- Configuring Diameter Network Elements on page 132
- Configuring Diameter AVPs for Gx Applications on page 133
- Configuring Diameter Peers on page 134
- Configuring the Diameter Transport on page 136
- Configuring Advertisements in Diameter Messages on page 137
- Configuring Parameters for Diameter Applications on page 138
- Configuring the Origin Attributes of the Diameter Instance on page 138
- gx-profile on page 316
- diameter on page 275
- diameter on page 273

Configuring Diameter Bindings

You can configure a Diameter network element to run on a specific session PIC. You can organize other session PICs in a group around the selected session PIC on which the configured network element runs. When organized in a group, the selected session PIC can send and receive messages for other session PICs in the group. By default, every Diameter network element runs on every session PIC.

NOTE: If you want to set up Diameter bindings for session PICs on the broadband gateway, contact Juniper Networks Professional Services for assistance.

To configure the Diameter binding for network elements:

1. Configure the network element used for the Diameter binding on the broadband gateway.

```
[edit]
```

Copyright © 2018, Juniper Networks, Inc.

```
user@host# set unified-edge tdf gateway gateway-name diameter network-element
  element-name
```

2. Specify the session PICs group that serves the network element.

```
[edit unified-edge tdf gateway gateway-name diameter network-element element-name]
user@host# set session-pics group group-name
```

3. Specify the session PIC interfaces in this group that serve the network element. The interface must be a multiservices interface.

```
[edit unified-edge tdf gateway gateway-name diameter network-element element-name
  session-pics group group-name]
user@host# set session-pic ams number
user@host# set session-pic ms-fpc/pic/port
```

Related Documentation

- Configuring Diameter Profiles on page 130

Configuring Diameter Network Elements

A Diameter network element consists of associated functions and a list of prioritized peers. The functions associate a Diameter application with the network element. The prioritization determines failover or load-balancing behavior for peer selection.

Before you configure Diameter network elements, perform the following task:

- Define the Diameter peers. See "Configuring Diameter Peers" on page 134.

To configure a Diameter network element:

1. Specify the name of the network element.

```
[edit access diameter]
user@host# set network-element element-name
```

2. Associate one or more functions with the network element.

   All functions are associated by default.

```
[edit access diameter network-element element-name]
user@host# set function function-name
```

3. Associate a Diameter peer with the network element and set the priority for the peer.

   Peers with the lower priority number have the higher priority for peer selection. Peers with the same priority are load-balancing peers so the peer selection alternates between the two peers.

Copyright © 2018, Juniper Networks, Inc.

```
[edit access diameter network-element element-name]
user@host# set peer peer-name priority priority-value
```

4. (Optional) Associate a Diameter peer with the network element and set the amount of time to wait for a response from this peer before retransmitting the request to another peer. The default is 4 seconds.

```
[edit access diameter network-element element-name]
user@host# set peer peer-name timeout seconds
```

Related Documentation

- Configuring Diameter Profiles on page 130

Configuring Diameter AVPs for Gx Applications

You can exclude Diameter attribute-value pairs (AVPs) from or include in the credit control request (CCR) messages between the MX Series router and the policy and charging rules function (PCRF) server.

NOTE: The configuration of the Diameter AVPs for dynamic PCEF policies is optional.

To configure Diameter AVPs for Gx applications:

1. Specify the name of the Diameter Gx profile for which you are configuring the Diameter AVPs.

```
[edit]
user@host# edit unified-edge diameter-profiles gx-profile profile-name
```

The Diameter Gx profile name can contain letters, numbers, and hyphens (-) and can be up to 128 characters long.

2. Specify the optional AVPs to be excluded from the CCR messages between the MX Series router and the PCRF. By default, all AVPs are included in the CCR messages.

```
[edit unified-edge diameter-profiles gx-profile profile-name]
user@host# set attributes exclude [attribute]
```

You can specify more than one AVP in a single line.

Table 9 on page 133 describes the AVPs that you can exclude from CCR messages.

Table 9: Diameter AVP Exclusions for Gx Applications

AVP	Information in AVP
an-gw-address	AN-GW-Address AVP, which contains the IP addresses of the access node gateway.

Copyright © 2018, Juniper Networks, Inc.

Table 9: Diameter AVP Exclusions for Gx Applications (continued)

AVP	Information in AVP
default-eps-bearer-qos	Default-EPS-Bearer-QoS AVP.
packet-filter-information	Packet-Filter-Information AVP.
packet-filter-operation	Packet-Filter-Operation AVP.
rat-type	RAT-Type AVP.

3. Specify the optional AVPs to be included in the CCR messages between the MX Series router and the PCRF. By default, all AVPs are included in the CCR messages.

```
[edit unified-edge diameter-profiles gx-profile profile-name]
user@host# set attributes include [attribute]
```

You can specify more than one AVP in a single line.

Table 10 on page 134 describes the AVPs that you can included in CCR messages.

Table 10: Diameter AVP Inclusions for Gx Applications

AVP	Information in AVP
gx-capability-list	Gx-capability-list AVP.
rule-suggestion	Rule-suggestion AVP.

Related Documentation

- Configuring Diameter Profiles on page 130

Configuring Diameter Peers

You can configure the remote peers to which Diameter sends messages. Port 3868 is used for active connections to peers by default.

To configure a remote peer for a Diameter instance:

1. Specify the name of the Diameter peer.

```
[edit access diameter]
user@host# set peer peer-name
```

2. Specify the address of the Diameter peer.

```
[edit access diameter peer peer-name]
user@host# set address ip-address
```


Copyright © 2018, Juniper Networks, Inc.

3. Specify the transport that Diameter uses for active connections to the peer.

```
[edit access diameter peer peer-name]
user@host# set connect-actively transport transport-name
```

4. (Optional) Specify the port that Diameter uses for active connections to the peer. The default is port 3868.

```
[edit access diameter peer peer-name]
user@host# set connect-actively port port-number
```

5. (Optional) Specify the time to wait for connection acknowledgment from the peer. The default is 10 seconds.

```
[edit access diameter peer peer-name]
user@host# set connect-actively timeout seconds
```

6. (Optional) Specify the time to wait before trying to reconnect to a peer after receiving a Disconnect-Peer-Request message with the DO_NOT_WANT_TO_TALK_TO_YOU value for the Disconnect-Cause AVP. If you do not set a value, no reconnection attempt is made.

```
[edit access diameter peer peer-name]
user@host# set connect-actively repeat-timeout seconds
```

7. (Optional) Specify the time to wait for a Capabilities-Exchange-Answer message from the peer. The default is 10 seconds.

```
[edit access diameter peer peer-name]
user@host# set connect-actively capabilities-exchange-timeout seconds
```

8. (Optional) Specify the time to wait between connection attempts for this peer. The default is 30 seconds.

```
[edit access diameter peer peer-name]
user@host# set connect-actively retry-timeout seconds
```

9. (Optional) Specify the time to wait for a Device-Watchdog-Answer message from the peer. The default is 30 seconds.

```
[edit access diameter peer peer-name]
user@host# set watchdog-timeout seconds
```

10. (Optional) Specify the time to wait in the Closing state while disconnecting this peer. The default is 10 seconds.

Copyright © 2018, Juniper Networks, Inc.

```
[edit access diameter peer peer-name]
user@host# set disconnect-peer-timeout seconds
```

11. (Optional) Specify the size of the incoming queue for the peer. The default is 6000. You can specify a smaller value if you want to throttle the peer.

```
[edit access diameter peer peer-name]
user@host# set incoming-queue size size
```

12. (Optional) Specify the size of the outgoing queue for the peer. The default is 6000. You can specify a smaller value if you want to throttle the peer.

```
[edit access diameter peer peer-name]
user@host# set outgoing-queue size size
```

13. (Optional) Specify the high watermark of the outgoing queue for the peer.

    The default is 80 percent. If the queue size reaches the high watermark, the peer is marked unavailable, any new messages to the Diameter network element are not sent to this peer, and the SNMP trap **Diameter_PeerOutQHiWMarkNotif** is generated.

```
[edit access diameter peer peer-name]
user@host# set outgoing-queue high-watermark high-watermark
```

14. (Optional) Specify the low watermark of the outgoing queue for the peer.

    The default is 60 percent. If the queue size descends to the low watermark after reaching the high watermark, the peer becomes available and the SNMP trap **Diameter_PeerLowQHiWMarkNotif** is generated.

```
[edit access diameter peer peer-name]
user@host# set outgoing-queue low-watermark low-watermark
```

Related Documentation

- Configuring Diameter Profiles on page 130

Configuring the Diameter Transport

You can configure one or more transports for a Diameter instance to set the source IP address for the local connection, and optionally configure a routing instance context. The routing instance for the transport connection must match that for the peer, or a configuration error is reported. Multiple peers can share the same transport.

To configure a transport for a Diameter instance:

1. Configure the transport name.

```
[edit access diameter]
```


Copyright © 2018, Juniper Networks, Inc.

```
user@host# set transport transport-name
```

2. Configure the source IP address for the Diameter local transport connection.

```
[edit access diameter transport transport-name]
user@host# set address ip-address
```

3. (Optional) Configure a routing instance, to which the address is bound, for the transport.

```
[edit access diameter transport transport-name]
user@host# set routing-instance routing-instance
```

Related Documentation

- Configuring Diameter Profiles on page 130

Configuring Advertisements in Diameter Messages

You can configure information advertised in the Capabilities-Exchange-Request or Capabilities-Exchange-Answer messages. This information includes firmware revision, product name, and vendor identification.

To configure the advertisements:

1. (Optional) Specify the value for the Firmware-Revision AVP that is advertised. 0 is the default.

```
[edit access diameter]
user@host# set firmware-revision firmware-revision
```

2. (Optional) Specify the value of the Product-Name AVP that is advertised. Juniper Diameter Client is the default.

```
[edit access diameter]
user@host# set product-name name
```

3. (Optional) Specify the value of the Vendor-Id AVP that is advertised. 2636 is the default.

```
[edit access diameter]
user@host# set vendor-id vendor-id
```

Related Documentation

- Configuring Diameter Profiles on page 130

Copyright © 2018, Juniper Networks, Inc.

Configuring Parameters for Diameter Applications

You can configure parameters for Diameter applications, including the maximum number of pending requests.

To configure the parameters for the Diameter application:

1. Specify the Gx application (**pcc-gx**), for which you want to configure parameters.

```
[edit access diameter]
user@host# set applications pcc-gx
```

2. (Optional) Specify the maximum number of pending requests for the Diameter application. The default is 20,000.

```
[edit access diameter applications pcc-gx]
user@host# set maximum-pending-requests requests
```

Related Documentation

- Configuring Diameter Profiles on page 130

Configuring the Origin Attributes of the Diameter Instance

You can configure the identifying characteristics of the endpoint node that originates Diameter messages for the Diameter instance. The hostname is supplied as the value for the Origin-Host prefix. The realm is supplied as the value for the Origin-Realm attribute-value pair (AVP).

To configure the origin attributes:

1. Specify the Origin-Host prefix that originates the Diameter message.

```
[edit access diameter origin]
user@host# set host hostname
```

2. Specify the realm of the host that originates the Diameter message.

```
[edit access diameter origin]
user@host# set realm realm-name
```

Related Documentation

- Configuring Diameter Profiles on page 130

Copyright © 2018, Juniper Networks, Inc.

PART 3

Configuring Reporting for Subscriber-Aware Data Sessions

- Configuring Reporting on page 141

Copyright © 2018, Juniper Networks, Inc.

Copyright © 2018, Juniper Networks, Inc.

CHAPTER 9

Configuring Reporting

- Logging and Reporting Function for Subscribers on page 141
- Log Dictionary for Template Types on page 146
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152
- Configuring an LRF Profile for Subscribers on page 152
- Assigning an LRF Profile to Subscribers on page 157
- Configuring the Activation of an LRF Rule by a PCC Rule on page 160

Logging and Reporting Function for Subscribers

The logging and reporting function (LRF) enables you to log data for subscriber application-aware policy control sessions and send that data in an IPFIX format to an external log collector using UDP-based transport. These data session logs can include subscriber information, application information, HTTP metadata, data volume, time-of-day information, and source and destination details. Starting in Junos OS Release 16.1R4 and then in Junos OS Release 17.2R1, LRF is available in Junos OS Broadband Subscriber Management.

The external collector, which is not a Juniper Networks product, may then use this data to perform analytics that provide you with insights about subscriber and application usage, allowing you to create packages and policies that increase revenue.

- Log and Report Control on page 141
- Templates on page 142
- HTTP Transaction Logging on page 146

Log and Report Control

A subscriber's data sessions are logged and sent to collectors based on an LRF profile that you configure and associate with the subscriber.

The LRF profile includes:

- Templates—Specify the type of data that you want sent and the trigger that causes data to be sent. You can configure a maximum of 16 templates in an LRF profile.
- Collectors—Identify the destination to send data to. You can configure a maximum of eight collectors in an LRF profile.

Copyright © 2018, Juniper Networks, Inc.

- LRF rules—Specify the template and collector to use and, if applicable, a data volume limit that triggers the sending of data. An LRF rule's actions are performed when the matching conditions in a static PCC rule that references the LRF rule are met. You can configure a maximum of 32 LRF rules in an LRF profile.

To associate the LRF profile with a subscriber:

- For Junos OS Subscriber Aware, assign the LRF profile to the subscriber-aware TDF service set that belongs to the TDF interface (mif) in the subscriber's TDF domain.
- For Junos OS Broadband Subscriber Management, assign the LRF profile to the service set that is configured for application-aware policy control.

Templates

You specify the data fields in a template by configuring one or more types for the template; for example, HTTP and IPv4. Each type represents a set of fields, and the template you configure includes fields from all the types you configure. The template is sent to the collector when you configure it, and is re-sent at a configurable interval. The template types that you can select and the fields that are included by each type are:

- Device Data—Contains data fields specific to the device collecting the logging feed:
  - DPI Engine Version
  - IP address of TDF gateway (in IPv4 format)
- DNS—Contains the DNS response time data field.
- Flow ID—Contains the Flow ID data field.

  When HTTP multiple transaction logging is enabled, FlowID is an implicit type that gets included with the HTTP template. When the consolidated session log is generated at the time of SESSION_CLOSE, LRF includes the FlowID that can be used to correlate with the HTTP transaction log records.
- HTTP—Contains data fields for the HTTP metadata from header fields:
  - User Agent
  - Content Length - Request
  - HTTP Response Code
  - Language
  - Host
  - Location
  - Http Method
  - Referer (HTTP)
  - MIME type
  - Time to First Byte
- IFL subscriber—Contains data fields specific to IFL-based subscribers:

Copyright © 2018, Juniper Networks, Inc.

- Subscriber Name
- IFL Name

- IPFlow—Contains data fields for the uplink and downlink octets and bytes. When a data record for volume limit is exported, these IPFlow statistics in the record are the actual data received after the last volume limit was reported in that data session and *not* cumulative data.
  - Uplink Octets
  - Downlink Octets
  - Uplink Packets
  - Downlink Packets
  - Ip Protocol—Protocol ID from IP header; for example, 17 (UDP), 6 (TCP).
  - Record Reason—A value of **1** for the session close and a value of **2** for volume-limit.
- IPFlow Extended—Contains data fields for the service set name, routing instance, and payload timestamps. The initiator of the very first packet of a session is the client and the responder is the server.
  - Service-Set-Name
  - Routing-Instance
- IPFlow TCP—Contains data fields for TCP-related timestamps:
  - Retransmitted TCP packets uplink
  - Retransmitted TCP packets downlink
  - TCP flow creation timestamp
- IPFlow TCP Timestamp—Contains IBM-specific data fields for TCP-related timestamps:
  - Smooth RTT uplink
  - Smooth RTT downlink
  - Client setup time
  - Server Setup time
  - First Client Payload timestamp
  - Upload time
  - First Server Payload timestamp
  - Download time
  - Acknowledged volumes uplink
  - Acknowledged volumes downlink

  To use the IPFlow TCP Timestamp template when configuring an LRF profile, identify the template as vendor specific to avoid a commit warning. See "Configuring an LRF Profile for Subscribers" on page 152.

Copyright © 2018, Juniper Networks, Inc.

- IPFlow Timestamp—Contains data fields for the flow start and end timestamps:
  - Flow Start Time—For TCP, the flow start time is when the SYN packet is received. For UDP, it is when the first packet is sent.
  - Flow End Time
- IPv4—Contains data fields for the basic source and destination IPv4 information:
  - Source IPv4 Address
  - Destination IPv4 Address
- IPv4 Extended—Contains data fields for the elements of IPv4 extended fields:
  - IPv4 TOS / Class of Service
  - IPv4 Source Mask
  - IPv4 Destination Mask
  - IPv4 Next Hop
- IPv6—Contains data fields for the basic source and destination IPv6 information:
  - Source IPv6 Address
  - Destination IPv6 Address
- IPv6 Extended—Contains data fields for the elements of IPv6 extended fields:
  - IPv6 Source Mask
  - IPv6 Destination Mask
  - IPv6 Next Hop
  - Traffic Class
- L7 Application—Contains data fields for the Layer 7 application:
  - Application Protocol—Application data protocol below the classified application name; for example, **http** or **ssl**.
  - Application Name—Application name; for example, **junos:facebook** or **junos:Netflix**.
  - Host—HTTP header host when application protocol is **http**, SSL common name when application protocol is **ssl**, DNS name when application protocol is **dns**.
- Mobile Subscriber—Contains data fields specific to mobile subscribers:
  - IMSI
  - MSISDN
  - IMEI
  - RAT-type
  - ULI
  - RADIUS Called Station ID

Copyright © 2018, Juniper Networks, Inc.

- PCC—Contains the PCC rule name data field.
- Status Code Distribution—Contains data fields for the HTTP or DNS status codes:
  - Status code 1
  - Status code 2
  - Status code 3
  - Status code 4
  - Status code 5
  - Num Instances 1
  - Num Instances 2
  - Num Instances 3
  - Num Instances 4
  - Num Instances 5
- Subscriber Data—Contains data fields for Generic Subscriber information that can be included with wireless (mobile) subscribers or wireline subscribers:
  - NAS_IP_ADDR
  - Subscriber Type—1 for IP-based subscriber, 2 for IFL-based subscriber.
  - Subscriber IP Address
  - Subscriber VRF
  - NAS Port ID
  - Accounting-Session-Id
  - Class
  - NAS Port Type
- Transport Layer—Contains data fields for the transport layer:
  - Source Transport Port
  - Destination Transport Port
- Video—Contains data fields for video traffic:
  - Bitrate
  - Duration
- Wireline Subscriber—Contains the UserName data field for wireline subscribers. This is the same as RADIUS Called Station ID.

The template that is specified in an LRF rule determines the set of data fields that are included when data is sent to a collector. The data message includes a pointer to the template ID so that the collector can correlate the data contents with the data field lengths and types.

Copyright © 2018, Juniper Networks, Inc.

In a template, you also specify the type of trigger that determines when to send data to the collector. This trigger type can be a data volume limit, a time limit, or the closing of a data session (UDP sessions are considered closed after 60 seconds of inactivity; TCP sessions are considered closed when a FIN, FIN-ACK, or RST is received).

HTTP Transaction Logging

You may enable HTTP transaction logging in an LRF profile. This causes each HTTP transaction in a TCP session to be separately logged and sent to the collector, as shown in Figure 13 on page 146. This option is only relevant when the template being used includes HTTP in the template type.

By default, HTTP transaction logging is disabled, and the HTTP transaction records for a TCP session are sent together as one group of records.

Figure 13: HTTP Transaction Logging



Release History Table

Release	Description
16.1R4	Starting in Junos OS Release 16.1R4 and then in Junos OS Release 17.2R1, LRF is available in Junos OS Broadband Subscriber Management.

Related Documentation

- Log Dictionary for Template Types on page 146
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152
- *Configuring Logging and Reporting for Subscriber Management*

Log Dictionary for Template Types

Table 11 on page 147 shows the logging dictionary of the template types that LRF supports. The log fields are a mix of IETF standard fields and fields that Juniper Networks defined. The IPFIX convention for vendor-defined fields is an enterprise bit set to **1** and an enterprise ID set to the vendor-ID. (The Juniper Networks vendor-ID is 2636.) An IETF standard field has an enterprise bit set to **0** and no value for the enterprise ID.

Copyright © 2018, Juniper Networks, Inc.

Table 11: Logging Dictionary for Template Types

Template Type	Field Name	Enterprise Bit/ID	Information Element Identifier	Data Type	Data Length (bytes)
Device Data	DPI Engine Version	1/2636	503	string	32
	IP address of TDF gateway.	1/2636	502	ipv4Address	4
DNS	DNS response time	1/2636	876	dateTimeMilliseconds	8
Flow ID	Flow ID	1/2636	107	unsigned32	4
HTTP	User Agent	1/2636	152	string	32
	Content Length - Request	1/2636	154	unsigned32	4
	HTTP Response Code	1/2636	155	unsigned16	2
	Language	1/2636	156	string	16
	Host	1/2636	157	string	64
	Location	1/2636	158	string	64
	Http Method	1/2636	159	string	8
	Referer(HTTP)	1/2636	160	string	64
	MIME type	1/2636	161	string	32
	Http URI	1/2636	163	string	255
	Time to First Byte	1/2636	181	dateTimeMilliseconds	8
IFL Subscriber	Subscriber Name	1/2636	511	string	16
	IFL Name	1/2636	512	string	16

Copyright © 2018, Juniper Networks, Inc.

Table 11: Logging Dictionary for Template Types (continued)

Template Type	Field Name	Enterprise Bit/ID	Information Element Identifier	Data Type	Data Length (bytes)
IPFlow	Uplink Octets	1/2636	103	unsigned32	4
	Downlink Octets	1/2636	104	unsigned32	4
	Uplink Packets	1/2636	105	unsigned32	4
	Downlink Packets	1/2636	106	unsigned32	4
	Ip Protocol	0	4	unsigned8	1
	Record Reason	1/2636	112	unsigned8	1
IPFlow Extended	Service-Set-Name	1/2636	520	string	16
	Routing-Instance	1/2636	521	string	16

Copyright © 2018, Juniper Networks, Inc.

Table 11: Logging Dictionary for Template Types (continued)

Template Type	Field Name	Enterprise Bit/ID	Information Element Identifier	Data Type	Data Length (bytes)
IPFlow TCP Timestamp	Retransmitted TCP packets uplink	1/2636	115	unsigned32	4
	Retransmitted TCP packets downlink	1/2636	116	unsigned32	4
	Smooth RTT uplink	1/2636	117	dateTimeMilliseconds	8
	Smooth RTT downlink	1/2636	118	dateTimeMilliseconds	8
	Client setup Time	1/2636	119	dateTimeMilliseconds	8
	Server Setup time	1/2636	120	dateTimeMilliseconds	8
	TCP flow creation timestamp	1/2636	121	dateTimeMilliseconds	8
	First Client Payload TS	1/2636	108	dateTimeMilliseconds	8
	Upload time	1/2636	113	dateTimeMilliseconds	8
	First Server Payload TS	1/2636	110	dateTimeMilliseconds	8
	Download time	1/2636	114	dateTimeMilliseconds	8
	Acknowledged volumes uplink	1/2636	122	unsigned64	8
	Acknowledged volumes downlink	1/2636	123	unsigned64	8
IPFlow Timestamp	Flow Start Time	1/2636	101	dateTimeMilliseconds	8
	Flow End Time	1/2636	102	dateTimeMilliseconds	8
IPv4	Source IPv4 Address	0	8	ipv4Address	4
	Destination IPv4 Address	0	12	ipv4Address	4

Copyright © 2018, Juniper Networks, Inc.

Table 11: Logging Dictionary for Template Types (continued)

Template Type	Field Name	Enterprise Bit/ID	Information Element Identifier	Data Type	Data Length (bytes)
IPv4 Extended	IPv4 TOS/Class of Service	0	5	unsigned8	1
	IPv4 Source Mask	0	9	unsigned8	1
	IPv4 Destination Mask	0	13	unsigned8	1
	IPv4 Next Hop	0	15	ipv4Address	4
IPv6	Source IPv6 Address	0	27	ipv6Address	16
	Destination IPv6 Address	0	28	ipv6Address	16
IPv6 Extended	IPv6 Source Mask	0	29	unsigned8	1
	IPv6 Destination Mask	0	30	unsigned8	1
	IPv6 Next hop	0	62	ipv6Address	16
	Traffic Class	1/2636	126	unsigned8	1
L7 Application	Application Protocol	1/2636	151	string	32
	Application Name	1/2636	170	string	32
	Host	1/2636	157	string	64
Mobile Subscriber	IMSI	1/2636	504	string	16
	MSISDN	1/2636	505	string	16
	IMEI	1/2636	506	string	16
	RAT-type	1/2636	507	unsigned8	1
	ULI	1/2636	508	string	13
	RADIUS Called Station ID	1/2636	509	string	32
PCC	PCC rule name	1/2636	901	string	64

Copyright © 2018, Juniper Networks, Inc.

Table 11: Logging Dictionary for Template Types (continued)

Template Type	Field Name	Enterprise Bit/ID	Information Element Identifier	Data Type	Data Length (bytes)
Status Code Distribution	Status code 1	1/2636	171	unsigned16	2
	Status code 2	1/2636	172	unsigned16	2
	Status code 3	1/2636	173	unsigned16	2
	Status code 4	1/2636	174	unsigned16	2
	Status code 5	1/2636	175	unsigned16	2
	Num Instances 1	1/2636	176	unsigned16	2
	Num Instances 2	1/2636	177	unsigned16	2
	Num Instances 3	1/2636	178	unsigned16	2
	Num Instances 4	1/2636	179	unsigned16	2
	Num Instances 5	1/2636	180	unsigned16	2
Subscriber Data	NAS_IP_ADDR	1/2636	519	ipv4Address	4
	Subscriber Type	1/2636	515	unsigned8	1
	Subscriber IP address	1/2636	516	ipv4Address	4
	Subscriber VRF	1/2636	517	unsigned32	4
	NAS Port ID	1/2636	518	string	32
	Accounting-Session-Id	1/2636	514	string	32
	Class	1/2636	522	String	32
	NAS Port Type	1/2636	523	unsigned32	4
Transport Layer	Source Transport Port	0	7	unsigned16	2
	Destination Transport Port	0	11	unsigned16	2
Video	Bitrate	1/2636	851	unsigned32	2
	Duration	1/2636	852	unsigned32	4

Copyright © 2018, Juniper Networks, Inc.

Table 11: Logging Dictionary for Template Types (continued)

Template Type	Field Name	Enterprise Bit/ID	Information Element Identifier	Data Type	Data Length (bytes)
Wireline Subscriber	UserName	1/2636	513	string	32

Configuring Logging and Reporting for Junos OS Subscriber Aware

To configure logging and reporting for traffic belonging to a set of subscribers, you configure LRF rules, collectors, and templates in an LRF profile; assign that LRF profile to the TDF service set associated with the subscribers' TDF domain; and assign each LRF rule to a PCC rule to activate it.

Before you begin to configure logging and reporting, you must:

- Configure the TDF domain for the subscriber.
- Configure the subscriber-aware service set for those subscribers.

To configure logging and reporting:

1. Configure an LRF profile to specify a set of logging and reporting parameters, which includes data templates, collectors, and LRF rules.

   See "Configuring an LRF Profile for Subscribers" on page 152.

2. Assign the LRF profile to a set of subscribers.

   See "Assigning an LRF Profile to Subscribers" on page 157.

3. Configure activation of an LRF rule with a static PCC rule.

   See "Configuring the Activation of an LRF Rule by a PCC Rule" on page 160.

Related Documentation

- Logging and Reporting Function for Subscribers on page 141

Configuring an LRF Profile for Subscribers

Configure an LRF profile to specify a set of logging and reporting parameters, which includes data templates, collectors, and LRF rules.

To configure an LRF profile:

1. Configuring the LRF Profile Name on page 153
2. Configuring Policy-Based Logging on page 153
3. (Optional) Configuring HTTP Transaction Logging on page 153
4. Configuring Collectors on page 154

Copyright © 2018, Juniper Networks, Inc.

5. Configuring Templates on page 155
6. Configuring Logging and Reporting Rules on page 156

Configuring the LRF Profile Name

An LRF profile is identified by a name, which you later specify in the service set for the subscribers.

- Configure a name for the LRF profile.

```
[edit services lrf]
user@host# set profile profile-name
```

For example:

```
[edit services lrf]
user@host# set profile lrf_profile1
```

Configuring Policy-Based Logging

Policy-based logging causes the LRF rules to be activated by PCC rules in a static PCEF profile.

- Configure policy-based logging in the LRF profile.

```
[edit services lrf profile profile-name]
user@host# set policy-based-logging
```

For example:

```
[edit services lrf profile lrf_profile1]
user@host# set policy-based-logging
```

(Optional) Configuring HTTP Transaction Logging

Configure HTTP transaction logging if you want the HTTP metadata generated and sent separately for each transaction of a data session. This option is only relevant if the template specified in an LRF rule includes **http** in the **template-type**.

- Configure HTTP transaction logging in the LRF profile.

```
[edit services lrf profile profile-name]
user@host# set http-log-multiple-transactions
```

For example:

```
[edit services lrf profile lrf_profile1]
user@host# set http-log-multiple-transactions
```

Copyright © 2018, Juniper Networks, Inc.

Configuring Collectors

Configure one or more collectors that you want to receive logging and reporting data when an LRF rule is activated. You can configure up to eight collectors for an LRF profile. For each collector:

1. Configure a name for the collector.

   ```
   [edit services lrf profile profile-name]
   user@host# set collector collector-name
   ```

   For example:

   ```
   [edit services lrf profile lrf_profile1]
   user@host# set collector collector1
   ```

2. Specify the destination IP address of the collector.

   ```
   [edit services lrf profile profile-name collector collector-name destination]
   user@host# set address collector-address
   ```

   For example:

   ```
   [edit services lrf profile lrf_profile1 collector collector1 destination]
   user@host# set address 192.0.2.5
   ```

3. Specify the destination port of the collector.

   ```
   [edit services lrf profile profile-name collector collector-name destination]
   user@host# set port collector-port-number
   ```

   For example:

   ```
   [edit services lrf profile lrf_profile1 collector collector1 destination]
   user@host# set port 4739
   ```

4. Configure the source address to be used when exporting data to the collector.

   ```
   [edit services lrf profile profile-name collector collector-name]
   user@host# set source-address source-address
   ```

   For example:

   ```
   [edit services lrf profile lrf_profile1 collector collector1]
   user@host# set source-address 10.1.1.1
   ```


Copyright © 2018, Juniper Networks, Inc.

Configuring Templates

Configure one or more templates, each of which specifies a set of data to be transmitted when an LRF rule is activated. You can configure up to 16 templates for an LRF profile. For each template:

1. Configure a name for the template.

   ```
   [edit services lrf profile profile-name]
   user@host# set template template-name
   ```

   For example:

   ```
   [edit services lrf profile lrf_profile1]
   user@host# set template template1
   ```

2. Configure a format for the template. Only the IPFIX format is supported for this release.

   ```
   [edit services lrf profile profile-name template template-name]
   user@host# set format ipfix
   ```

   For example:

   ```
   [edit services lrf profile lrf_profile1 template template1]
   user@host# set format ipfix
   ```

3. Configure the template types, which specify the data fields to include. You must configure at least one type, and you can configure multiple types.

   ```
   [edit services lrf profile profile-name template template-name]
   user@host# set template-type template-type
   ```

   For example:

   ```
   [edit services lrf profile lrf_profile1 template template1]
   user@host# set template-type http ipv4
   ```

   This example results in a template that includes fields from both the HTTP and IPv4 templates.

4. If you used the **ipflow-tcp-ts** template type, identify it as an IBM template to avoid a commit warning.

   ```
   [edit services lrf profile profile-name]
   user@host# set vendor-support ibm
   ```

5. Configure the interval, in seconds, at which you want the template to be retransmitted to the collector. The interval can be from 10 through 600, and the default is 60.

Copyright © 2018, Juniper Networks, Inc.

```
[edit services lrf profile profile-name template template-name]
user@host# set template-tx-interval tx-time
```

For example:

```
[edit services lrf profile lrf_profile1 template template1]
user@host# set template-tx-interval 100
```

6. Configure the type of trigger that causes the generation of data records and transmission to the collector. You can specify the trigger type as either the closing of the data session (default) or a data volume limit. The data volume limit value is specified within an LRF rule.

```
[edit services lrf profile profile-name template template-name]
user@host# set trigger-type (session-close | volume)
```

For example:

```
[edit services lrf profile lrf_profile1 template template1]
user@host# set trigger-type volume
```

Configuring Logging and Reporting Rules

Configure one or more LRF rules, which control how data sessions are logged and reported. You can configure up to 32 LRF rules for an LRF profile. For each LRF rule:

1. Configure a name for the LRF rule.

```
[edit services lrf profile profile-name]
user@host# set rule lrf-rule-name
```

For example:

```
[edit services lrf profile lrf_profile1]
user@host# set rule rule1
```

You cannot use the same LRF rule name in multiple LRF profiles.

2. Specify the collector that you want to receive the data if this rule is matched.

```
[edit services lrf profile profile-name rule lrf-rule-name ]
user@host# set then report collector collector-name
```

For example:

```
[edit services lrf profile lrf_profile1 rule rule1]
user@host# set then report collector collector1
```

3. Specify the template that identifies the type of data to report if this rule is matched.

Copyright © 2018, Juniper Networks, Inc.

```
[edit services lrf profile profile-name rule lrf-rule-name]
user@host# set then report template template-name
```

For example:

```
[edit services lrf profile lrf_profile1 rule rule1]
user@host# set then report template template1
```

4. If you specified **volume** for the template's trigger type in Step 6 of "Configuring Templates" on page 155, configure the data volume limit to be used for reporting by this rule.

   ```
   [edit services lrf profile profile-name rule lrf-rule-name]
   user@host# set then report volume-limit volume
   ```

   The data volume, in megabytes, can be from 1 through 1024.

   For example:

   ```
   [edit services lrf profile lrf_profile1 rule rule1]
   user@host# set then report volume-limit 4
   ```

5. If you specified **time** for the template's trigger type in Step 6 of "Configuring Templates" on page 155, configure the time limit to be used for reporting by this rule.

   ```
   [edit services lrf profile profile-name rule lrf-rule-name]
   user@host# set then report time-limit time-interval
   ```

   The time limit, in seconds, can be from 60 through 1800. The default is 300.

   For example:

   ```
   [edit services lrf profile lrf_profile1 rule rule1]
   user@host# set then report time-limit 360
   ```

Related Documentation

- Logging and Reporting Function for Subscribers on page 141
- *Applying Logging and Reporting Configuration to a Subscriber Management Service Set*
- Configuring the Activation of an LRF Rule by a PCC Rule on page 160
- Configuring Custom Application Signatures on page 25

Assigning an LRF Profile to Subscribers

Before you can assign an LRF profile to a set of subscribers, you must:

- Configure the LRF profile.
- Configure the TDF interface (mif).

Copyright © 2018, Juniper Networks, Inc.

- Configure the TDF domain for the set of subscribers.
- Configure the service set for the TDF domain's TDF interface (mif).

Assign the LRF profile to a set of subscribers to apply the profile's logging and reporting configuration to the subscribers' traffic. You accomplish this by assigning the LRF profile to the subscriber-aware TDF service set associated with the TDF interface (mif) in the subscribers' TDF domain.

To assign an LRF profile to subscribers:

1. Identify the mif interface in the subscribers' TDF domain.

   ```
   [edit unified-edge gateways tdf]
   user@host# show domains domain-name
   ```

   For example:

   ```
   [edit unified-edge gateways tdf]
   user@host# show domains domain1
   ```

   ```
   pcef-profile pcef-prof-static;
   tdf-interface mif.0;
   access-interfaces {
       ge-1/0/1.0;
   }
   ...
   ```

2. Identify the service set or sets assigned to the mif interface.

   ```
   [edit interfaces]
   user@host# show mif.number
   ```

   For example:

   ```
   [edit interfaces]
   user@host# show mif.0
   ```

   ```
   family inet {
       service {
           input {
               service-set sset1;
           }
           output {
               service-set sset1;
           }
       }
   }
   ```

3. Assign the LRF profile to the service set or sets.

   ```
   [edit services service-set service-set-name]
   user@host# set lrf-profile profile-name
   ```


Copyright © 2018, Juniper Networks, Inc.

For example:

```
[edit services service-set sset1]
user@host# set lrf-profile lrf_profile1
```

Related Documentation

- Logging and Reporting Function for Subscribers on page 141
- Configuring an LRF Profile for Subscribers on page 152
- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Applying Services to Subscriber-Aware Traffic with a Service Set on page 124
- Configuring a TDF Logical Interface on page 120

Copyright © 2018, Juniper Networks, Inc.

Configuring the Activation of an LRF Rule by a PCC Rule

NOTE: If you are using Junos OS Subscriber Aware, you must be in maintenance mode to make a change to a PCC action profile. (See "Changing PCEF Profiles, PCC Rules, PCC Rulebases, Diameter Profiles, Flow Descriptions, and PCC Action Profiles" on page 182).

NOTE: If you are using Junos OS Broadband Subscriber Management, you cannot make a change to a PCC action profile that is being used by subscribers. To modify the PCC action profile, you must first log off the subscribers that are using the PCC action profile.

Before you configure activation of an LRF rule by a PCC rule, you must:

- Configure the LRF rule in an LRF profile.
- Configure policy-based logging in the LRF profile.
- Configure the PCC rule.

In this release, you must use a PCC rule's matching conditions to activate an LRF rule, which controls how data sessions are logged and reported. You identify the LRF rule in the PCC rule's action profile.

You can configure a PCC rule to activate an LRF rule for Junos OS Subscriber Aware or for Junos OS Broadband Subscriber Management, but you use a different CLI hierarchy level for each product.

- If you are using Junos OS Subscriber Aware, configure PCC rules at the **[edit unified-edge pcef]** hierarchy level.
- If you are using Junos OS Broadband Subscriber Management, configure PCC rules at the **[edit services pcef]** hierarchy level.

To configure a PCC rule to activate an LRF rule:

1. Identify the PCC action profile that is used in the PCC rule.

   For Junos OS Subscriber Aware:

   ```
   [edit unified-edge pcef]
   user@host# show pcc-rules rule-name
   ```

   For Junos OS Broadband Subscriber Management:

   ```
   [edit services pcef]
   user@host# show pcc-rules rule-name
   ```

   For example:

Copyright © 2018, Juniper Networks, Inc.

For Junos OS Subscriber Aware:

```
[edit unified-edge pcef]
user@host# show pcc-rules all-traffic
```

```
from {
    flows {
        all;
    }
}
then {
    pcc-action-profile all-traffic-action;
}
```

For Junos OS Broadband Subscriber Management:

```
[edit services pcef]
user@host# show pcc-rules all-traffic
```

```
from {
    flows {
        all;
    }
}
then {
    pcc-action-profile all-traffic-action;
}
```

2. Assign the LRF rule to the PCC action profile.

   For Junos OS Subscriber Aware:

   ```
   [edit unified-edge pcef pcc-action-profiles profile-name]
   user@host# set logging-rule lrf-rule-name
   ```

   For Junos OS Broadband Subscriber Management:

   ```
   [edit services pcef pcc-action-profiles profile-name]
   user@host# set logging-rule lrf-rule-name
   ```

   For example:

   For Junos OS Subscriber Aware:

   ```
   [edit unified-edge pcef pcc-action-profiles all-traffic-action]
   user@host# set logging-rule rule1
   ```

   For Junos OS Broadband Subscriber Management:

   ```
   [edit services pcef pcc-action-profiles all-traffic-action]
   user@host# set logging-rule rule1
   ```

Copyright © 2018, Juniper Networks, Inc.

Related Documentation

- Logging and Reporting Function for Subscribers on page 141
- Configuring an LRF Profile for Subscribers on page 152
- Configuring Policy and Charging Control Rules on page 70

Copyright © 2018, Juniper Networks, Inc.

PART 4

Modifying Subscriber-Aware Configuration

- Modifying Subscriber-Aware Configuration in Maintenance Mode on page 165

Copyright © 2018, Juniper Networks, Inc.

Copyright © 2018, Juniper Networks, Inc.

CHAPTER 10

Modifying Subscriber-Aware Configuration in Maintenance Mode

- Maintenance Mode Overview for Subscriber Aware Policy Enforcement on page 166
- Changing Address Attributes in the Address Pool on page 167
- Deleting an Address Pool on page 168
- Changing AMS Interface Parameters on a TDF Gateway on page 169
- Modifying a TDF Domain on page 172
- Modifying the TDF Interface of a TDF Domain on page 174
- Deleting a TDF Domain on page 175
- Changing a TDF Interface on page 177
- Deleting a TDF Interface on page 178
- Changing TDF Gateway Parameters with Maintenance Mode on page 180
- Changing PCEF Profiles, PCC Rules, PCC Rulebases, Diameter Profiles, Flow Descriptions, and PCC Action Profiles on page 182
- Deleting a PCEF Profile on page 186
- Changing Static Time-of-Day Settings for PCC Rules on page 190
- Deleting a Services PIC on page 191
- Deleting a Session PIC on page 193

Copyright © 2018, Juniper Networks, Inc.

Maintenance Mode Overview for Subscriber Aware Policy Enforcement

With Junos OS maintenance mode, you can take certain network functionality offline to perform specific maintenance tasks without disrupting service. When the traffic detection function (TDF) domains, TDF gateways, TDF subscribers, TDF interfaces, subscriber polices, or service PICs need maintenance, entering maintenance mode prevents these subscriber services elements from accepting new requests. You have the option of allowing all existing services to complete, or clear them. When ready, you can proceed with critical maintenance functions with a minimum of service disruption. Subscribers who attempt to access a gateway that is in maintenance mode receive a message that the service is not supported.

If you want to perform any of the following operations, you must do so in maintenance mode:

- Delete or modify the addresses of certain TDF (mif) interfaces
- Delete or change the type of a TDF domain
- Change TDF interface configuration parameters
- Change a TDF interface for a TDF domain
- Change a static time-of-day profile
- Delete or modify a policy and charging enforcement function (PCEF) profile (However, maintenance mode is not required to add PCC rules or rulebases to a dynamic PCEF profile.)
- Delete or modify a PCC rule
- Delete or modify a PCC rulebase
- Delete or modify a Diameter profile
- Delete or modify a flow description
- Delete an address pool or modify its parameters

You can perform all other maintenance tasks outside of maintenance mode.

The maintenance mode procedures listed do not include adding elements. New elements carry no traffic and thus do not need to be gracefully halted. However, you can create new network elements in maintenance mode as an environment in which to test configurations before deploying them.

Related Documentation

- Changing a TDF Interface on page 177
- Deleting a TDF Interface on page 178
- Changing Address Attributes in the Address Pool on page 167
- Modifying a TDF Domain on page 172
- Deleting a TDF Domain on page 175
- Deleting a Session PIC on page 193

Copyright © 2018, Juniper Networks, Inc.

- Deleting a Services PIC on page 191
- Changing AMS Interface Parameters on a TDF Gateway on page 169
- Changing TDF Gateway Parameters with Maintenance Mode on page 180

Changing Address Attributes in the Address Pool

This procedure describes how to place an address pool of a virtual routing and forwarding (VRF) instance in maintenance mode, allow all existing sessions using this pool to gracefully terminate, and then delete or modify pool attributes (for example, change address ranges in a pool).

To change address attributes in the address pool:

1. From configuration mode, activate maintenance mode for an address pool.

   ```
   [edit]
   user@host# set routing-instance vrf-name access address-assignment address-pools
     juniper-pool service-mode maintenance
   user@host# commit
   ```

2. Verify that all subscriber sessions have ended.

   ```
   user@host# run show unified-edge tdf address-assignment pool brief
   ```

   The service mode shows **Maintenance – Active Phase** if all the sessions are cleared. The service mode shows **Maintenance – In Phase** if some sessions are active. The service mode shows **Maintenance – Out Phase** if maintenance mode is not configured (that is, it is in operational mode).

3. (Optional) Terminate existing sessions using the **clear** command.

   ```
   [edit]
   user@host# run clear unified-edge tdf subscribers routing-instance juniper-vrf
   ```

   When the subscriber count is zero and all sessions have terminated, the service mode status indicates **Maintenance – Active phase**. In this state, you can modify address pool attributes and commit changes.

4. Make changes to the pool.

5. Verify that changes were properly saved.

   ```
   [edit]
   user@host# run show configuration routing-instance access address-assignment
     address-pools pool-name detail
   ```

Copyright © 2018, Juniper Networks, Inc.

NOTE: These modifications, if made outside of active maintenance mode, fail.

6. Exit maintenance mode to return to normal operational mode.

```
[edit]
user@host# delete routing-instance juniper-vrf  access address-assignment
   address-pools pool-name service-mode
```

7. Return the gateway to operational state.

```
[edit]
user@host# run show unified-edge tdf gateway service-mode
```

Related Documentation

- Maintenance Mode Overview for Subscriber Aware Policy Enforcement on page 166
- Deleting an Address Pool on page 168

Deleting an Address Pool

This procedure describes how to delete an address pool. You must first halt new sessions from being started and verify that no active sessions remain. The steps are similar to those described in "Changing Address Attributes in the Address Pool" on page 167.

To delete an address from an address pool:

1. From configuration mode, activate maintenance mode for an address pool.

```
[edit]
user@host# set routing-instance juniper-vrf access address-assignment address-pools
   pool-name service-mode maintenance
user@host# commit
```

2. Verify that all subscriber sessions have ended.

```
[edit]
user@host# run show unified-edge tdf address-assignment pool brief
```

   The service mode shows **Maintenance – Active Phase** if all the sessions are cleared. The service mode shows **Maintenance – In Phase** if some sessions are active. The service mode shows **Maintenance – Out Phase** if maintenance mode is not configured (that is, it is in operational mode).

3. (Optional) Terminate sessions that are using an address pool using the **clear** command.

Copyright © 2018, Juniper Networks, Inc.

```
[edit]
user@host#  run clear unified-edge tdf subscribers routing-instance juniper-vrf
```

When the subscriber count is zero and all sessions have terminated, the service mode status indicates **Maintenance – Active phase**. In this state, you can modify pool attributes and commit changes.

4. When the subscriber count is zero and all sessions have ended, modify address pool attributes and commit changes.

NOTE: These modifications, if made outside of active maintenance mode, fail.

5. Delete the address pool and commit the change.

```
[edit]
user@host# delete routing-instance juniper-vrf access address-assignment
   address-pools juniper-pool
user@host# commit
```

6. Verify that the address pool has been deleted (that is, it is not listed in the output).

```
[edit]
user@host# run show configuration routing-instance juniper-vrf access
   address-assignment address-pools juniper-pool
```

Related Documentation

- Maintenance Mode Overview for Subscriber Aware Policy Enforcement on page 166
- Changing Address Attributes in the Address Pool on page 167

Changing AMS Interface Parameters on a TDF Gateway

This procedure shows how to change the parameters for an aggregated multiservices (AMS) interface on a TDF gateway using maintenance mode at the **[edit interfaces]** hierarchy level. If an AMS interface is configured under a gateway's session PICs or services PICs, and you change any load-balancing options such as membership of AMS interfaces (mams), then the AMS interface must be in maintenance mode.

Before you change AMS parameters using maintenance mode:

- Make sure that this change has been coordinated with affected groups and users.

To configure maintenance mode and AMS parameter change:

1. Verify the current status of maintenance mode for the AMS.

Copyright © 2018, Juniper Networks, Inc.

```
[edit]
user@host> show unified-edge tdf gateway-name system interfaces service-mode
```

The **service-mode** option displays the information details about maintenance mode as well as status.

```
Maintenance Mode
   MM Active Phase - System is ready to accept configuration changes for
all
                  attributes of this object and its sub-hierarchies.
   MM In/Out Phase - System is ready to accept configuration changes only
for
                  non-maintenance mode attributes of this object and
                  its sub-hierarchies.

Interface Name  Gateway Name  Service Mode
ms-1/0/0   SCG1    Operational
ms-1/1/0   SCG1    Operational
ms-2/0/0   SCG1    Operational
ms-2/1/0   SCG1    Operational
pfe-0/0/0   SCG1    Operational
pfe-0/1/0   SCG1    Operational
pfe-0/2/0   SCG1    Operational
pfe-0/3/0   SCG1    Operational
ams1    SCG1    Operational
```

2. From configuration mode, show the current configuration for the AMS interface.

```
user@host# show interfaces interface-name
load-balancing-options {
  member-interface mams-4/1/0;
  member-interface mams-5/1/0;
  member-failure-options {
    redistribute-all-traffic {
      enable-rejoin;
    }
  }
  high-availability-options {
    many-to-one {
      preferred-backup mams-5/1/0;
    }
  }
}
unit 1 {
  family inet;
}
unit 2 {
  family inet;
}
```

3. On the gateway, place the interface in maintenance mode.

```
[edit]
```


Copyright © 2018, Juniper Networks, Inc.

```
user@host# set unified-edge tdf gateway-name system interface interface-name
  service-mode maintenance
user@host# commit
```

4. Verify that the AMS interface is in active maintenance mode where configuration changes are accepted for this object and all of its subhierarchies, after you commit the configuration.

```
user@host> show unified-edge tdf gateway-name system interfaces service-mode
```

```
Maintenance Mode
   MM Active Phase - System is ready to accept configuration changes for
all
                  attributes of this object and its sub-hierarchies.
   MM In/Out Phase - System is ready to accept configuration changes only
for
                  non-maintenance mode attributes of this object and
                  its sub-hierarchies.

Interface Name  Gateway Name  Service Mode
ms-1/0/0   SCG1    Operational
ms-1/1/0   SCG1    Operational
ms-2/0/0   SCG1    Operational
ms-2/1/0   SCG1    Operational
pfe-0/0/0   SCG1    Operational
pfe-0/1/0   SCG1    Operational
pfe-0/2/0   SCG1    Operational
pfe-0/3/0   SCG1    Operational
ams1    SCG1    Maintenance - Active Phase
```

NOTE: All subscribers serviced by the AMS interface must go to zero. You can wait for these conditions to be met, or use the clear command for the interface (or gateway) to force these conditions.

5. Delete or change AMS member interfaces and parameters.

```
user@host> show unified-edge tdf gateway-name system interfaces service-mode
[edit unified-edge]
user@host# delete unified-edge tdf gateway-name system interface interface-name
  load-balancing-options member-interface mams-interface-name
[edit interfaces]
user@host# set interfaces interface-name load-balancing-options member-interface
  mams-interface-name
user@host# delete interfaces interface-name load-balancing-options
  high-availability-options many-to-one preferred-backup mams-interface-name
user@host# set interfaces interface-name load-balancing-options
  high-availability-options many-to-one preferred-backup mams-interface-name
```

6. Exit maintenance mode and commit the changes.

Copyright © 2018, Juniper Networks, Inc.

```
user@host# delete unified-edge tdf gateway-name system interface interface-name
   service-mode maintenance
user@host# commit
```

Related Documentation

- Maintenance Mode Overview for Subscriber Aware Policy Enforcement on page 166
- Deleting a Session PIC on page 193
- Deleting a Services PIC on page 191
- Changing TDF Gateway Parameters with Maintenance Mode on page 180

Modifying a TDF Domain

This procedure describes how to use maintenance mode to modify a TDF domain. Options include modifying such parameters as TDF domain, mobile-interface, address filtering, AAA parameters, session characteristics, and access interfaces. You must first halt new sessions from being started and verify that there are no active sessions remaining.

To change a TDF domain for a group of subscribers that belong to that domain:

1. From configuration mode, activate maintenance mode for an TDF domain.

   ```
   [edit]
   user@host# set unified-edge gateways tdf gateway-name domains domain-name
      service-mode maintenance
   user@host# commit
   ```

2. Verify that the TDF domain is in maintenance mode.

   ```
   [edit]
   user@host# run show unified-edge tdf domains service-mode
   ```

   This command displays the service-mode status for all the TDF domains. You can verify the status for the specific TDF domain and take action accordingly.

   The service mode for the TDF domain shows **Maintenance – Active Phase** if all the sessions using this TDF domain are cleared. The service mode for the TDF domain shows **Maintenance - In Phase** if some sessions are actively using this TDF domain.

3. Verify that no subscribers are active on the TDF domain.

   ```
   [edit]
   user@host# run show unified-edge tdf subscribers | match domain-name
   ```

4. (Optional) Terminate sessions on a TDF domain using the **clear** command.

   ```
   [edit]
   ```


Copyright © 2018, Juniper Networks, Inc.

```
user@host# run clear unified-edge tdf subscribers domain domain-name gateway
  gateway-name
```

5. When the subscriber count is zero and all sessions have ended, make and commit changes to the TDF domain in active maintenance mode.

   NOTE: These modifications must be made in active maintenance mode or they fail.

6. Modify the TDF domain and commit the changes.

7. Exit maintenance mode and commit the changes.

```
[edit]
user@host# delete unified-edge gateways tdf gateway-name domains domain-name
  service-mode
user@host# commit
```

8. Verify that changes were properly committed.

```
[edit]
user@host# run show configuration unified-edge gateways tdf gateway-name
  tdf-services domains  domain-name
```

   The command output displays the configuration changes you made to the TDF domain.

9. Return the gateway to operational state.

```
[edit]
user@host# run show unified-edge tdf gateway service-mode
```

NOTE: Although maintenance mode does not explicitly include AAA options, certain AAA changes require you to place affected TDF domains in maintenance mode first. These changes include changing an AAA profile name and changing authorization or accounting elements. If you attempt to make AAA changes that affect a TDF domain that is not in maintenance mode, you are prompted to place the appropriate TDF domain into maintenance mode before proceeding with AAA profile name or element changes.

Related Documentation

- Maintenance Mode Overview for Subscriber Aware Policy Enforcement on page 166
- Modifying the TDF Interface of a TDF Domain on page 174

Copyright © 2018, Juniper Networks, Inc.

- Deleting a TDF Domain on page 175
- Changing TDF Gateway Parameters with Maintenance Mode on page 180

Modifying the TDF Interface of a TDF Domain

This procedure describes how to use maintenance mode to modify attributes of the TDF interface for a TDF domain. You must first halt new sessions from being started and verify that no active sessions remain.

To configure the mobile interface of a TDF domain:

1. From configuration mode, activate maintenance mode for the TDF domain using the mobile interface to be modified.

   ```
   [edit]
   user@host# set unified-edge gateways tdf gateway-name domains  domain-name
     service-mode maintenance
   user@host# commit
   ```

2. Verify that the TDF domain of this mobile interface is in maintenance mode.

   ```
   [edit]
   user@host# run show unified-edge tdf domain service-mode
   ```

   From the gateway hierarchy, the service mode for the gateway shows **Maintenance – Active Phase** if all the sessions using this TDF domain are cleared. The service mode for the gateway shows **Maintenance – In Phase** if some sessions are actively using this TDF domain. The service mode for the TDF domain shows **Maintenance – Out Phase** if maintenance mode is not configured (that is, it is in operational mode).

   You cannot make and commit changes to a mobile interface unless the TDF domain to which it is attached is in maintenance mode.

3. Verify that no subscribers are active on the TDF domain.

   ```
   [edit]
   user@host# run show unified-edge tdf subscribers | match domain-name
   ```

4. (Optional) Terminate sessions that are using an address pool using the **clear** command.

   ```
   [edit]
   user@host# run clear unified-edge tdf subscribers domain domain-name gateway
     gateway-name
   ```

5. When the subscriber count is zero and all sessions have ended, make and commit changes to the TDF domain interface in active maintenance mode.

Copyright © 2018, Juniper Networks, Inc.

NOTE: These modifications must be made in active maintenance mode or they fail.

6. Modify the interface.

7. Exit maintenance mode and commit the changes.

```
[edit]
user@host# delete unified-edge gateways tdf gateway-name domain domain-name
  service-mode
user@host# commit
```

8. Verify that changes were properly committed.

```
[edit]
user@host# run show configuration unified-edge gateways tdf gateway-name domain
  domain-name
```

9. Return the gateway to operational state.

```
[edit]
user@host# run show unified-edge tdf service-mode
```

Related Documentation

- Maintenance Mode Overview for Subscriber Aware Policy Enforcement on page 166
- Deleting a TDF Domain on page 175
- Changing TDF Gateway Parameters with Maintenance Mode on page 180

Deleting a TDF Domain

This procedure describes how to use maintenance mode to delete a TDF domain. You must first halt new sessions from being started and verify that there no active sessions remain.

To delete a TDF domain name:

1. From configuration mode, activate maintenance mode for a TDF domain.

```
[edit]
user@host# set unified-edge gateways tdf gateway-name domains domain-name
  service-mode maintenance
user@host#  commit
```

2. Verify that the TDF domain is in maintenance mode.

Copyright © 2018, Juniper Networks, Inc.

```
[edit]
user@host# run show unified-edge tdf domains service-mode
```

The service mode shows **Maintenance – Active Phase** if all the sessions are cleared. The service mode shows **Maintenance – In Phase** if some sessions are active. The service mode shows **Maintenance – Out Phase** if maintenance mode is not configured (that is, it is in operational mode).

3. Verify that no subscribers are active on the TDF domain.

```
user@host# run show unified-edge tdf domain domain-name gateway gateway-name
```

4. (Optional) Terminate sessions that are using a TDF domain using the **clear** command.

```
user@host#  run clear unified-edge tdf subscribers domain domain-name gateway
  gateway-name
```

5. When the subscriber count is zero and all sessions have ended, delete the TDF domain in active maintenance mode.

NOTE: These modifications must be made in active maintenance mode or they fail.

6. Delete the TDF domain and commit the changes.

```
user@host# delete unified-edge gateways tdf  gateway-name tdf-services domains
  domain-name
user@host# commit
```

7. Verify that changes were properly committed by showing the configuration for the entire unified edge to make sure the TDF domain is deleted.

```
[edit]
user@host# run show configuration unified-edge gateways tdf gateway-name domain
  domain-name
```

8. Return the gateway to the operational state.

```
[edit]
user@host# run show unified-edge tdf gateway service-mode
```

Related Documentation

- Maintenance Mode Overview for Subscriber Aware Policy Enforcement on page 166
- Modifying the TDF Interface of a TDF Domain on page 174

Copyright © 2018, Juniper Networks, Inc.

- Changing TDF Gateway Parameters with Maintenance Mode on page 180

Changing a TDF Interface

This procedure describes how to use maintenance mode to halt new sessions from being started and to verify that no active sessions remain before making changes to a TDF interface address.

1. From configuration mode, activate maintenance mode for a gateway.

```
[edit]
user@host# set unified-edge gateways tdf gateway-name service-mode maintenance
user@host# commit
```

2. Verify that the TDF gateway is in maintenance mode.

```
[edit]
user@host# run show unified-edge tdf gateway service-mode
```

From the gateway hierarchy, the service mode for the TDF gateway shows **Maintenance – Active Phase** if all the sessions using this pool are cleared. The service mode for the gateway shows **Maintenance – In Phase** if some sessions are actively using this pool.

3. Verify that no subscribers are active on this gateway.

```
[edit]
user@host# run show unified-edge tdf subscribers gateway gateway-name
```

NOTE: If a large number of subscribers use this gateway, the preceding command can be process intensive, in which case you can use the following command to show the active contexts across all of the gateway instances:

```
[edit]
user@host# run show unified-edge tdf status
```

4. (Optional) Terminate sessions that are using the gateway using the following **clear** command:

```
[edit]
user@host# run clear unified-edge tdf subscribers gateway gateway-name
```

CAUTION: This clear command deletes all of the existing subscribers on the gateway. Only issue these commands if you intend to disconnect service to all these subscribers.

Copyright © 2018, Juniper Networks, Inc.

5. When the subscriber count is zero, and all sessions have ended, modify the TDF interface in active maintenance mode.

```
[edit]
user@host# set unified-edge gateways tdf gateway-name domains domain-name
user@host# commit
```

NOTE: These modifications must be made in active maintenance mode or they fail.

6. Verify that changes were properly committed.

```
[edit]
user@host# run show configuration unified-edge tdf gateway  gateway-name
```

7. Exit maintenance mode and commit the changes.

```
[edit]
user@host# delete unified-edge gateways tdf gateway-name gateway gateway-name
   service-mode
user@host# commit
```

8. Return the gateway to operational state.

```
[edit]
user@host# run show unified-edge tdf gateway service-mode
```

Related Documentation

- Maintenance Mode Overview for Subscriber Aware Policy Enforcement on page 166
- Changing TDF Gateway Parameters with Maintenance Mode on page 180
- Deleting a TDF Interface on page 178

Deleting a TDF Interface

This procedure describes how to use maintenance mode to delete a TDF interface. You must first halt new sessions from being started and verify that no active sessions are remaining.

You can use maintenance mode to remove any of the TDF interfaces.

You can also enter maintenance mode to delete control and data portions of these interface configurations.

1. From configuration mode, activate maintenance mode for a gateway.

```
[edit]
```


Copyright © 2018, Juniper Networks, Inc.

```
user@host# set unified-edge gateways tdf gateway-name service-mode maintenance
user@host# commit
```

2. Verify that the TDF gateway is in maintenance mode.

```
[edit]
user@host# run show unified-edge tdf gateway service-mode
```

From the gateway hierarchy, the service mode for the gateway shows **Maintenance – Active Phase** if all the sessions using this pool are cleared. The service mode for the gateway shows **Maintenance – In Phase** if some sessions are actively using this pool. The service mode for the gateway shows **Maintenance – Out Phase** if maintenance mode is not configured (that is, the gateway is in operational mode).

3. Verify that no subscribers are active on this gateway.

```
[edit]
user@host# run show unified-edge tdf subscriber gateway gateway-name
```

4. (Optional) Terminate sessions that are using the gateway and clear CDRs using the following **clear** command.

```
[edit]
user@host# run clear unified-edge tdf subscribers gateway  gateway-name
```

5. When the subscriber count is zero, and all sessions have ended, delete the TDF interface in active maintenance mode.

NOTE: These modifications must be made in active maintenance mode or they fail.

6. Delete the TDF interface.

```
[edit]
user@host# delete unified-edge gateways tdf gateway-name domains domain-name
  tdf-interface mif  interface-name
```

7. Exit maintenance mode and commit the changes.

```
user@host# delete unified-edge gateways tdf gateway-name gateway gateway-name
  service-mode
user@host# commit
```

8. Verify that changes were properly committed.

Copyright © 2018, Juniper Networks, Inc.

```
user@host# run show configuration unified-edge tdf gateway gateway-name
```

Related Documentation

- Maintenance Mode Overview for Subscriber Aware Policy Enforcement on page 166
- Changing TDF Gateway Parameters with Maintenance Mode on page 180
- Changing a TDF Interface on page 177

Changing TDF Gateway Parameters with Maintenance Mode

This procedure shows how to change the parameters for a TDF gateway using maintenance mode at the **[edit unified-edge gateways tdf *gateway-name*]** hierarchy level.

The gateway must be in maintenance mode to change:

- Maximum number of sessions
- Maximum amount of memory and CPU utilization.

Before you change these gateway parameters using maintenance mode:

- Make sure that this change has been coordinated with affected groups and users.
- Make sure that this change is applied to the correct gateway type and name.

To configure maintenance mode for a gateway parameter change:

1. Verify the current status of maintenance mode for the gateway.

   Under normal operating conditions, the service mode is **Operational** (that is, not in maintenance mode).

   ```
   user@host> show unified-edge tdf gateway-name service-mode
   ```

   The **service-mode** option displays the information details about maintenance mode as well as status.

   ```
   Maintenance Mode
      MM Active Phase - System is ready to accept configuration changes for
   all
                     attributes of this object and its sub-hierarchies.
      MM In/Out Phase - System is ready to accept configuration changes only
   for
                     non-maintenance mode attributes of this object and
                     its sub-hierarchies.

   Gateway Name  Service Mode

   <gateway-name> Operational
   ```

2. From configuration mode, place the gateway in maintenance mode.

Copyright © 2018, Juniper Networks, Inc.

```
[edit]
user@host# set unified-edge tdf gateway-name service-mode maintenance
user@host# commit
```

3. Verify that the gateway is in active maintenance mode where configuration changes are accepted for this object.

```
[edit]
user@host> show unified-edge tdf gateway-name service-mode
```

The **service-mode** option displays the information details about maintenance mode as well as status.

```
Maintenance Mode
   MM Active Phase - System is ready to accept configuration changes for
all
                  attributes of this object and its sub-hierarchies.
   MM In/Out Phase - System is ready to accept configuration changes only
for
                  non-maintenance mode attributes of this object and
                  its sub-hierarchies.

Gateway Name  Service Mode

<gateway-name> Maintenance - Active Phase
```

NOTE: All subscribers serviced by the gateway must go to zero. You can wait for these conditions to be met, or use the clear command for the gateway to force these conditions.

4. Configure the threshold for the maximum amount of CPU that the TDF gateway can use as a percentage from 1 through 90.

```
[edit unified-edge gateways tdf gateway-name]
user@host# set cac cpu cpu-pct
```

5. Configure the maximum number of TDF subscriber sessions that may be running, expressed in thousands of sessions.

```
[edit unified-edge gateways tdf gateway-name]
user@host# set cac maximum-sessions max-sessions
```

6. Configure the threshold for the maximum amount of memory that the TDF gateway can use as a percentage from 1 through 90.

```
[edit unified-edge gateways tdf gateway-name]
user@host# set cac memory memory-pct
```

Copyright © 2018, Juniper Networks, Inc.

7. Exit maintenance mode and commit the changes.

```
[edit]
user@host# delete unified-edge tdf gateway-name service-mode maintenance
user@host# commit
```

Related Documentation

- Maintenance Mode Overview for Subscriber Aware Policy Enforcement on page 166
- Changing AMS Interface Parameters on a TDF Gateway on page 169
- Deleting a Session PIC on page 193
- Deleting a Services PIC on page 191

Changing PCEF Profiles, PCC Rules, PCC Rulebases, Diameter Profiles, Flow Descriptions, and PCC Action Profiles

These procedures show how to enter maintenance mode to halt new sessions from being started and verify that no sessions remain on either the gateway or TDF domain before making changes to the following:

- PCEF profiles (However, maintenance mode is not required to add PCC rules or rulebases to a dynamic PCEF profile.)
- PCC rules
- PCC rulebases
- Diameter profiles
- Flow descriptions
- PCC action profiles

NOTE: Even when a PCEF profile is not associated with a TDF domain or a TDF domain-selection term, configuration changes or deletion of the PCEF profile and any referenced objects of the profile require you to activate maintenance mode for the TDF gateway.

- Changing PCEF Profiles, PCC Rules, PCC Rulebases, Diameter Profiles, Flow Descriptions, and PCC Action Profiles with the TDF Domain in Maintenance Mode on page 183
- Changing PCEF Profiles, PCC Rules, PCC Rulebases, Diameter Profiles, Flow Descriptions, and PCC Action Profiles with the TDF Gateway in Maintenance Mode on page 184

Copyright © 2018, Juniper Networks, Inc.

Changing PCEF Profiles, PCC Rules, PCC Rulebases, Diameter Profiles, Flow Descriptions, and PCC Action Profiles with the TDF Domain in Maintenance Mode

This procedure shows operators how to enter maintenance mode to halt new sessions from being started and to verify that no sessions remain on the TDF domain before making changes to PCEF profiles, PCC rules, PCC rulebases, Diameter profiles, flow descriptions, and PCC action profiles for a TDF domain.

To activate maintenance mode for the TDF domain and make changes:

1. From configuration mode, activate maintenance mode for the TDF domain.

```
[edit]
user@host# set unified-edge gateways tdf gateway-name domain domain-name
   service-mode maintenance
user@host# commit
```

2. Verify that the TDF domain is in maintenance mode.

```
[edit]
user@host# run show unified-edge tdf domain service-mode
```

   The service mode for the TDF domain shows **Maintenance–Active Phase** if all the sessions using this TDF domain are cleared. The service mode for the TDF domain shows **Maintenance - In Phase** if some sessions are actively using this TDF domain.

3. Verify that no subscribers are active on the TDF domain.

```
[edit]
user@host# run show unified-edge tdf subscribers | match domain-name
```

4. (Optional) Terminate any remaining sessions on the TDF domain by using the **clear** command.

```
[edit]
user@host# run clear unified-edge tdf subscribers | match domain-name
```

5. Verify that the TDF domain is in Active Phase.

```
[edit]
user@host# run show unified-edge tdf domain service-mode
```

6. Make the configuration changes and commit the changes.

7. Exit maintenance mode.

```
[edit]
```

Copyright © 2018, Juniper Networks, Inc.

```
user@host# delete unified-edge gateways tdf gateway-name domain domain-name
  service-mode
user@host# commit
```

8. Verify that changes were properly committed.

   - To view a PCEF profile configuration:

     ```
     [edit]
     user@host# run show configuration unified-edge pcef profiles profile-name
     ```

   - To view a PCC rulebase configuration:

     ```
     [edit]
     user@host# run show configuration unified-edge pcef pcc-rulebases rulebase-name
     ```

   - To view a PCC rules configuration:

     ```
     [edit]
     user@host# run show configuration unified-edge pcef pcc-rules rule-name
     ```

   - To view a flow description configuration:

     ```
     [edit]
     user@host# run show configuration unified-edge pcef flow-description flow-identifier
     ```

   - To view a PCC action profile configuration:

     ```
     [edit]
     user@host# run show configuration unified-edge pcef pcc-action-profiles
       profile-name
     ```

9. Return the gateway to operational state.

   ```
   [edit]
   user@host# run show unified-edge tdf gateway service-mode
   ```

Changing PCEF Profiles, PCC Rules, PCC Rulebases, Diameter Profiles, Flow Descriptions, and PCC Action Profiles with the TDF Gateway in Maintenance Mode

This procedure shows how to enter maintenance mode to halt new sessions from being started and to verify that no sessions remain on the TDF gateway before making changes to PCEF profiles, PCC rules, PCC rulebases, Diameter profiles, flow descriptions, and PCC action profiles across multiple TDF domains on the gateway.

To activate maintenance mode for the gateway and make changes:

1. From configuration mode, activate maintenance mode for the gateway.

   ```
   [edit]
   user@host# set unified-edge gateways tdf gateway-name service-mode maintenance
   user@host# commit
   ```


Copyright © 2018, Juniper Networks, Inc.

2. Verify that the TDF gateway is in maintenance mode.

```
[edit]
user@host# run show unified-edge tdf service-mode
```

   From the gateway hierarchy, the service mode shows **Maintenance—Active Phase** if all the sessions are cleared. The service mode shows **Maintenance—In Phase** if some sessions are active. The service mode shows **Maintenance—Out Phase** if maintenance mode is not configured, and the gateway is in operational mode.

3. Make the configuration changes.

   You can modify a PCEF profile by making changes to the PCC rules, PCC rulebases, or flow identifiers that the PCEF profile references or by specifying a different PCC rule, rule precedence, PCC rulebase, or Diameter profile in the PCEF profile.

4. Exit maintenance mode and commit the changes.

```
[edit]
user@host# delete unified-edge gateways tdf gateway-name service-mode
user@host# commit
```

5. Verify that changes were properly committed.

   - To view a PCEF profile configuration:

```
[edit]
user@host# run show configuration unified-edge pcef profiles profile-name
```

   - To view a PCC rulebase configuration:

```
[edit]
user@host# run show configuration unified-edge pcef pcc-rulebases rulebase-name
```

   - To view a PCC rules configuration:

```
[edit]
user@host# run show configuration unified-edge pcef pcc-rules rule-name
```

   - To view a flow description configuration:

```
[edit]
user@host# run show configuration unified-edge pcef flow-description flow-identifier
```

   - To view a PCC action profile configuration:

```
[edit]
user@host# run show configuration unified-edge pcef pcc-action-profiles
   profile-name
```

6. Return the gateway to operational state.

Copyright © 2018, Juniper Networks, Inc.

```
[edit]
user@host# run show unified-edge tdf gateway service-mode
```

See Also

- Maintenance Mode Overview for Subscriber Aware Policy Enforcement on page 166
- Deleting a PCEF Profile on page 186
- Changing PCEF Profiles, PCC Rules, PCC Rulebases, Diameter Profiles, Flow Descriptions, and PCC Action Profiles on page 182

Deleting a PCEF Profile

These procedures show how to enter maintenance mode to halt new sessions from being started and verify that no sessions remain on the TDF domain or gateway before removing a policy and charging enforcement function (PCEF) profile from the TDF domain or service-selection profile configurations.

NOTE: Regardless of whether a PCEF profile is associated within a TDF domain or not, or whether a PCEF profile is associated with a TDF domain-selection term or not, configuration changes and deletion of a PCEF profile (and other referenced objects of the profile) require that the TDF gateway be placed in maintenance mode. However, you need not activate maintenance mode for the gateway if you are adding a new PCEF profile.

- Deleting a PCEF Profile with the TDF Domain in Maintenance Mode on page 186
- Deleting a PCEF Profile with the Gateway in Maintenance Mode on page 188

Deleting a PCEF Profile with the TDF Domain in Maintenance Mode

This procedure shows how to enter maintenance mode to halt new sessions from being started and to verify that there are no sessions remaining on the TDF domain before removing a PCEF profile configuration that a TDF domain or service-selection profile references.

To activate maintenance mode for the TDF domain and make changes to a PCEF profile:

1. From configuration mode, activate maintenance mode for the TDF domain that references the PCEF profile.

```
[edit]
user@host# set unified-edge gateways tdf gateway-name domains domain-name
   service-mode maintenance
user@host# commit
```

2. Verify that the TDF domain is in maintenance mode.

```
[edit]
```


Copyright © 2018, Juniper Networks, Inc.

```
user@host# run show unified-edge tdf domain service-mode
```

The service mode for the TDF domain shows **Maintenance—Active Phase** if all the sessions using this TDF domain are cleared. The service mode for the TDF domain shows **Maintenance—In Phase** if some sessions are actively using this TDF domain.

3. Verify that no subscribers are active on the TDF domain.

```
[edit]
user@host# run show unified-edge tdf subscribers | match domain-name
```

4. (Optional) Terminate any remaining sessions on the TDF domain.

```
[edit]
user@host# run clear unified-edge tdf subscribers domain domain-name
```

5. Verify that the TDF domain is in an active phase.

```
[edit]
user@host# run show unified-edge tdf domain service-mode
```

6. In the TDF domain or service-selection profile configuration, remove the referenced PCEF profile and commit the changes.

```
user@host# delete unified-edge gateways tdf gateway-name domains domain-name
  pcef-profile pcef-profile-name
```

```
user@host# delete unified-edge gateways tdf gateway-name domain-selection term
  term-name then pcef-profile pcef-profile-name
```

7. Verify that the changes were properly committed by showing the configuration for the entire TDF domain or service-selection profile to make sure the PCEF profile is deleted.

   - To view a PCEF profile configuration:

     ```
     [edit]
     user@host# run show configuration unified-edge pcef profiles profile-name
     ```

   - To view a PCC rulebase configuration:

     ```
     [edit]
     user@host# run show configuration unified-edge pcef pcc-rulebases rulebase-name
     ```

   - To view a PCC rules configuration:

     ```
     [edit]
     user@host# run show configuration unified-edge pcef pcc-rules rule-name
     ```

Copyright © 2018, Juniper Networks, Inc.

- To view a flow description configuration:

```
[edit]
user@host# run show configuration unified-edge pcef flow-description flow-identifier
```

- To view a PCC action profile configuration:

```
[edit]
user@host# run show configuration unified-edge pcef pcc-action-profiles
  profile-name
```

8. (Optional) If the PCEF profile is not used in other TDF domain or service-selection profile configurations, you can delete the PCEF profile configuration and commit the changes.

```
[edit]
user@host# delete unified-edge gateways tdf gateway-name domains domain-name
  service-mode
user@host# commit
```

9. Exit maintenance mode.

```
[edit]
user@host# delete unified-edge gateways tdf gateway-name service-mode
user@host# commit
```

10. Return the gateway to operational state.

```
user@host# run show unified-edge tdf gateway service-mode
```

Deleting a PCEF Profile with the Gateway in Maintenance Mode

This procedure shows how to enter maintenance mode to halt new sessions from being started and to verify that no sessions remain on the TDF gateway before deleting PCEF profiles that are referenced by one or more TDF domains on a gateway.

To activate maintenance mode for the gateway and make changes to a PCEF profile:

1. From configuration mode, activate maintenance mode for the gateway.

```
[edit]
user@host# set unified-edge gateways tdf gateway-name service-mode maintenance
user@host# commit
```

2. Verify that the TDF gateway is in maintenance mode.

```
[edit]
user@host# run show unified-edge tdf service-mode
```


Copyright © 2018, Juniper Networks, Inc.

From the gateway hierarchy, the service mode shows **Maintenance—Active Phase** if all the sessions are cleared. The service mode shows **Maintenance—In Phase** if some sessions are active. The service mode shows **Maintenance—Out Phase** if maintenance mode is not configured, and the gateway is in operational mode.

3. Verify that no subscribers are active on the gateway.

```
[edit]
user@host# run show unified-edge tdf subscribers gateway gateway-name
```

4. (Optional) Terminate any remaining sessions on the gateway.

```
[edit]
user@host# run clear unified-edge tdf subscribers gateway gateway-name
```

5. Verify that the gateway is in an active phase.

```
[edit]
user@host# run show unified-edge tdf gateway service-mode
```

6. For each applicable TDF domain, delete the PCEF profile from the TDF domain configuration and commit the changes.

```
user@host# delete unified-edge gateways tdf gateway-name domains domain-name
   pcef-profile pcef-profile-name
user@host# commit
```

7. Verify that the changes were properly committed by showing the configuration for each TDF domain to make sure the PCEF profile is deleted.

   - To view a PCEF profile configuration:

     ```
     [edit]
     user@host# run show configuration unified-edge pcef profiles profile-name
     ```

   - To view a PCC rulebase configuration:

     ```
     [edit]
     user@host# run show configuration unified-edge pcef pcc-rulebases rulebase-name
     ```

   - To view a PCC rules configuration:

     ```
     [edit]
     user@host# run show configuration unified-edge pcef pcc-rules rule-name
     ```

   - To view a flow description configuration:

     ```
     [edit]
     user@host# run show configuration unified-edge pcef flow-description flow-identifier
     ```

Copyright © 2018, Juniper Networks, Inc.

- To view a PCC action profile configuration:

```
[edit]
user@host# run show configuration unified-edge pcef pcc-action-profiles
  profile-name
```

8. Exit maintenance mode.

```
[edit]
user@host# delete unified-edge gateways tdf gateway-name service-mode
user@host# commit
```

9. Return the gateway to operational state.

```
[edit]
user@host# run show unified-edge tdf gateway service-mode
```

See Also

- Maintenance Mode Overview for Subscriber Aware Policy Enforcement on page 166
- Changing PCEF Profiles, PCC Rules, PCC Rulebases, Diameter Profiles, Flow Descriptions, and PCC Action Profiles on page 182

Changing Static Time-of-Day Settings for PCC Rules

This procedure shows how to enter maintenance mode to make changes to static time-of-day activation and deactivation settings or to apply those settings to PCC rules and rulebases.

To make changes to the static time-of-day activation and deactivation configuration:

1. From configuration mode, activate maintenance mode for the gateway.

```
[edit unified-edge gateways]
user@host# set tdf gateway-name service-mode maintenance
user@host# commit
```

2. Verify that the gateway is in maintenance mode.

```
[edit unified-edge gateways]
user@host# run show unified-edge tdf service-mode
```

The service mode shows **Maintenance—Active Phase** if all the sessions are cleared. The service mode shows **Maintenance—In Phase** if some sessions are active. The service mode shows **Maintenance—Out Phase** if maintenance mode is not configured, and the gateway is in operational mode.

3. Modify the time-of-day profile settings, the assignment of time-of-day profiles to rules and rulebases within a PCEF profile, or both, and commit the changes. See

Copyright © 2018, Juniper Networks, Inc.

"Configuring Static Time-of-Day PCC Rule Activation and Deactivation in a Junos OS Subscriber Aware PCEF Profile" on page 84.

4. Exit maintenance mode.

```
[edit unified-edge gateways]
user@host# delete tdf gateway-name service-mode
user@host# commit
```

5. Verify that changes were properly committed.

   - To view a PCEF profile configuration:

```
[edit]
user@host# run show configuration unified-edge pcef profiles profile-name
```

   - To view a time-of-day profile configuration:

```
[edit]
user@host# run show configuration unified-edge pcef pcc-time-of-day-profiles
  profile-name
```

Related Documentation

- Maintenance Mode Overview for Subscriber Aware Policy Enforcement on page 166

Deleting a Services PIC

This procedure shows how to delete a services PIC using maintenance mode at the **[edit unified-edge gateways tdf *gateway-name* system session-pics interface]** hierarchy level. The services PIC can be an aggregated multiservices (AMS) interface. Services PICs perform packet-related services on a broadband gateway.

Before you delete a services PIC using maintenance mode:

- Make sure that this change has been coordinated with affected groups and users.

To configure maintenance mode and services PIC deletion:

1. Verify the current status of maintenance mode for this services PIC.

```
user@host> show unified-edge tdf gateway-name system interfaces service-mode
```

   The **service-mode** option displays the information details about maintenance mode as well as status.

```
Maintenance Mode
   MM Active Phase - System is ready to accept configuration changes for
all
                  attributes of this object and its sub-hierarchies.
   MM In/Out Phase - System is ready to accept configuration changes only
```

Copyright © 2018, Juniper Networks, Inc.

```
for
                  non-maintenance mode attributes of this object and
                  its sub-hierarchies.

Interface Name  Gateway Name  Service Mode
ms-1/0/0   SCG1    Operational
ms-1/1/0   SCG1    Operational
ms-2/0/0   SCG1    Operational
ms-2/1/0   SCG1    Operational
pfe-0/0/0   SCG1    Operational
pfe-0/1/0   SCG1    Operational
pfe-0/2/0   SCG1    Operational
pfe-0/3/0   SCG1    Operational
ams1    SCG1    Operational
```

2. From configuration mode, place the interface in maintenance mode.

```
[edit]
user@host# set unified-edge gateways tdf gateway-name system session-pics interface
  interface-name service-mode maintenance
user@host# commit
```

3. Verify that the services PIC is in active maintenance mode where configuration changes are accepted for this object and all of its subhierarchies.

```
[edit]
user@host> show unified-edge tdf gateway-name system interfaces service-mode
```

```
Maintenance Mode
   MM Active Phase - System is ready to accept configuration changes for
all
                  attributes of this object and its sub-hierarchies.
   MM In/Out Phase - System is ready to accept configuration changes only
for
                  non-maintenance mode attributes of this object and
                  its sub-hierarchies.

Interface Name  Gateway Name  Service Mode
ms-1/0/0   SCG1    Operational
ms-1/1/0   SCG1    Operational
ms-2/0/0   SCG1    Maintenance - Active Phase
ms-2/1/0   SCG1    Operational
pfe-0/0/0   SCG1    Operational
pfe-0/1/0   SCG1    Operational
pfe-0/2/0   SCG1    Operational
pfe-0/3/0   SCG1    Operational
ams1    SCG1    Operational
```

NOTE: All subscribers serviced by the services PIC must go to zero. You can wait for these conditions to be met, or use the clear command for the interface (or gateway) to force these conditions.

Copyright © 2018, Juniper Networks, Inc.

4. Delete the services PIC, exit maintenance mode, and commit the changes.

NOTE: Deletion of a services PIC automatically exits maintenance mode for the deleted PIC.

```
[edit]
user@host# delete unified-edge gateways tdf gateway-name system interface
  interface-name
user@host# commit
```

Related Documentation

- Maintenance Mode Overview for Subscriber Aware Policy Enforcement on page 166
- Deleting a Session PIC on page 193
- Changing AMS Interface Parameters on a TDF Gateway on page 169
- Changing TDF Gateway Parameters with Maintenance Mode on page 180

Deleting a Session PIC

This procedure shows how to delete a session PIC using maintenance mode at the **[edit unified-edge gateways tdf *gateway-name* system session-pics interface]** hierarchy level. The session PIC can be an aggregated multiservices (AMS) interface. Session PICs process control plane messages on a broadband gateway.

Before you delete a session PIC using maintenance mode:

- Make sure that this change has been coordinated with affected groups and users.

To configure maintenance mode and session PIC deletion:

1. Verify the current status of maintenance mode for this session PIC.

```
user@host> show unified-edge tdf gateway-name system interfaces service-mode
```

The **service-mode** option displays the information details about maintenance mode as well as status.

```
Maintenance Mode
   MM Active Phase - System is ready to accept configuration changes for
all
                  attributes of this object and its sub-hierarchies.
   MM In/Out Phase - System is ready to accept configuration changes only
for
                  non-maintenance mode attributes of this object and
                  its sub-hierarchies.

Interface Name  Gateway Name  Service Mode
ms-1/0/0   SCG1    Operational
ms-1/1/0   SCG1    Operational
```

Copyright © 2018, Juniper Networks, Inc.

```
ms-2/0/0   SCG1    Operational
ms-2/1/0   SCG1    Operational
pfe-0/0/0   SCG1    Operational
pfe-0/1/0   SCG1    Operational
pfe-0/2/0   SCG1    Operational
pfe-0/3/0   SCG1    Operational
ams1    SCG1    Operational
```

2. From configuration mode on the TDF gateway, place the interface in maintenance mode.

```
[edit]
user@host# set unified-edge gateways tdf gateway-name system session-pics interface
  interface-name service-mode maintenance
user@host# commit
```

3. Verify that the session PIC is in active maintenance mode where configuration changes are accepted for this object and all of its subhierarchies.

```
user@host> show unified-edge tdf gateway-name system interfaces service-mode
```

```
Maintenance Mode
   MM Active Phase - System is ready to accept configuration changes for
all
                  attributes of this object and its sub-hierarchies.
   MM In/Out Phase - System is ready to accept configuration changes only
for
                  non-maintenance mode attributes of this object and
                  its sub-hierarchies.

Interface Name  Gateway Name  Service Mode
ms-1/0/0   SCG1    Operational
ms-1/1/0   SCG1    Maintenance - Active Phase
ms-2/0/0   SCG1    Operational
ms-2/1/0   SCG1    Operational
pfe-0/0/0   SCG1    Operational
pfe-0/1/0   SCG1    Operational
pfe-0/2/0   SCG1    Operational
pfe-0/3/0   SCG1    Operational
ams1    SCG1    Operational
```

NOTE: All subscribers serviced by the session PIC must go to zero. You can wait for these conditions to be met, or use the clear command for the interface (or gateway) to force these conditions.

4. Delete the session PIC.

```
[edit]
user@host# delete unified-edge gateways tdf gateway-name system interface
  interface-name
```


Copyright © 2018, Juniper Networks, Inc.

5. Exit maintenance mode after committing the changes.

NOTE: Deletion of a session PIC automatically exits maintenance mode for the deleted PIC.

```
[edit]
user@host# commit
```

Related Documentation

- Maintenance Mode Overview for Subscriber Aware Policy Enforcement on page 166
- Deleting a Services PIC on page 191
- Changing AMS Interface Parameters on a TDF Gateway on page 169
- Changing TDF Gateway Parameters with Maintenance Mode on page 180

Copyright © 2018, Juniper Networks, Inc.

Copyright © 2018, Juniper Networks, Inc.

PART 5

Monitoring and Troubleshooting

- Monitoring and Troubleshooting on page 199

Copyright © 2018, Juniper Networks, Inc.

Copyright © 2018, Juniper Networks, Inc.

CHAPTER 11

Monitoring and Troubleshooting

- Configuring Tracing for PCEF Operations on page 199
- Configuring Call-Rate Statistics Collection on page 200

Configuring Tracing for PCEF Operations

To configure tracing operations for the policy and charging enforcement function (PCEF):

1. Specify that you want to configure tracing options for PCEF.

```
[edit unified-edge pcef]
user@host# edit traceoptions
```

2. (Optional) Configure the name of the file used for the trace output.

```
[edit unified-edge pcef traceoptions]
user@host# set file file-name
```

3. (Optional) Configure the maximum size of each trace file.

```
[edit unified-edge pcef traceoptions]
user@host# set file size size
```

4. (Optional) Configure the maximum number of trace files.

```
[edit unified-edge pcef traceoptions]
user@host# set file files number
```

5. (Optional) Configure the read permissions for the log file.

```
[edit unified-edge pcef traceoptions]
user@host# set file (no-world-readable | world-readable)
```

6. (Optional) Configure flags to filter the operations to be logged.

```
[edit unified-edge pcef traceoptions]
```

Copyright © 2018, Juniper Networks, Inc.

```
user@host# set flag flag
```

Table 12 on page 200 describes the flags that you can include.

Table 12: Trace Flags

Flag	Description
all	Trace all operations.
config	Trace configuration events.
debug	Trace the debug internal events.
fsm	Trace finite state machine events.
general	Trace general events that do not fit in any specific traces.
high-availability	Trace high availability events.
init	Trace initialization events.
tftmgr	Trace traffic flow manager events.

7. (Optional) Configure the level of tracing.

```
[edit unified-edge pcef traceoptions]
user@host# set level (all | critical | error | info | notice | verbose | warning)
```

Related Documentation

- traceoptions on page 503

Configuring Call-Rate Statistics Collection

You can configure the collection of statistics for the rate of calls for a TDF gateway and for a TDF domain. You configure the length of the interval for statistics collection and the number of call-records to keep.

To configure call-rate statistics collection for the TDF gateway or TDF domain:

1. Configure the length of the interval for statistics collection:
   - For a TDF gateway:

     ```
     [edit unified-edge gateways tdf gateway-name]
     user@host# set call-rate-statistics interval minutes
     ```

   - For a TDF domain:

     ```
     [edit unified-edge gateways tdf gateway-name domains domain-name]
     ```


Copyright © 2018, Juniper Networks, Inc.

```
user@host# set call-rate-statistics interval minutes
```

2. Configure the number of call-rate records to save.

   - For a TDF gateway:

     ```
     [edit unified-edge gateways tdf gateway-name]
     user@host# set call-rate-statistics history records
     ```

   - For a TDF domain:

     ```
     [edit unified-edge gateways tdf gateway-name domains domain-name]
     user@host# set call-rate-statistics history records
     ```

   When the number of call-rate records equals the **history** value and a new record is received, the oldest record is replaced by the new record.

Related Documentation

- show unified-edge tdf call-rate statistics on page 660

Copyright © 2018, Juniper Networks, Inc.

 Copyright © 2018, Juniper Networks, Inc.

PART 6

Configuration Statements and Operational Commands

- Configuration Statements on page 205
- Operational Commands on page 523

Copyright © 2018, Juniper Networks, Inc.

Copyright © 2018, Juniper Networks, Inc.

CHAPTER 12

Configuration Statements

- 3gpp-imsi on page 213
- aaa clients (TDF) on page 214
- aaa-policy-control (PCEF Profile) on page 215
- aaa-profile (PCEF Profile) on page 216
- access-interfaces (IFL Subscriber) on page 217
- access-interfaces (IP Subscriber) on page 218
- accounting (AAA Profile) on page 219
- accounting (RADIUS Client) on page 220
- accounting-port (RADIUS Server) on page 221
- accounting-secret (RADIUS Server) on page 222
- activation-attribute (AAA Profile) on page 223
- address (Diameter Peer) on page 224
- address (LRF Profile) on page 224
- address (RADIUS Clients) on page 225
- address (RADIUS Server) on page 225
- address-mapping (Application Identification) on page 226
- address-pools on page 227
- allow-dynamic-requests (RADIUS Server) on page 228
- alt-name (Application Identification) on page 228
- application (Application Identification) on page 229
- application-groups (PCC Rules) on page 231
- application-identification (Application Identification) on page 232
- application-identification-profile (Service Set) on page 233
- applications (Diameter) on page 234
- applications (PCC Rules) on page 235
- attribute on page 236
- attributes (Diameter Gx Profiles) on page 238
- authentication (AAA Profile) on page 239

Copyright © 2018, Juniper Networks, Inc.

- burst-size (Default Local Policy) on page 240
- burst-size (TDF Domain) on page 241
- cac (TDF Gateway) on page 242
- cacheable (Application Identification) on page 242
- call-rate-statistics on page 243
- called-station-id on page 244
- calling-station-id on page 245
- chain-order (Application Identification) on page 246
- check-bytes (Application Identification) on page 246
- class on page 247
- client on page 248
- clients on page 249
- coa-accounting (AAA Profile) on page 250
- code on page 251
- code (AAA Profile) on page 252
- code (Application Identification) on page 253
- collector (LRF Profile) on page 254
- collector (LRF Rule) on page 255
- compatibility (Application Identification) on page 255
- connect-actively on page 256
- constant on page 257
- context (Application Identification) on page 258
- count (HTTP Header Enrichment) on page 259
- cpu (TDF Gateway) on page 260
- deactivation-attribute (AAA Profile) on page 261
- dead-criteria-retries (RADIUS Server) on page 262
- default-local-policy on page 263
- default-pool (Address Pools) on page 264
- description (Application Identification) on page 264
- destination (Application Identification) on page 265
- destination (LRF Profile) on page 265
- destination-address (HTTP Header Enrichment) on page 266
- destination-address-range (HTTP Header Enrichment) on page 267
- destination-ip-address (RADIUS Snoop Segment) on page 268
- destination-port (RADIUS Snoop Segment) on page 269
- destination-port-range (HTTP Header Enrichment) on page 270
- destination-ports (HTTP Header Enrichment) on page 271

Copyright © 2018, Juniper Networks, Inc.

- destination-prefix-list (HTTP Header Enrichment) on page 272
- diameter (Subsciber Aware Policy Control) on page 273
- diameter (TDF Gateway) on page 275
- diameter-profile (PCEF Profile) on page 276
- direction (Application Identification) on page 277
- direction (Service Data Flow Filters) on page 278
- disconnect-peer-timeout on page 279
- domain (TDF Domain Selection) on page 280
- domain-selection on page 281
- domains on page 285
- dynamic-policy-control on page 288
- dynamic-requests-secret (RADIUS Server) on page 289
- encrypt (HTTP Header Enrichment) on page 290
- equals on page 291
- exclude (Diameter Gx Profiles) on page 292
- external-assigned (Address Pools) on page 293
- family (Address Pools) on page 294
- family (Exclude Prefix) on page 295
- family (TDF Interface) on page 296
- flow-action on page 297
- flow-descriptions on page 298
- flows (PCC Rules) on page 300
- format on page 301
- format (LRF Profile) on page 303
- forwarding-class (PCC Action Profiles) on page 304
- firmware-revision on page 305
- framed-ip-address on page 306
- framed-ipv6-prefix on page 307
- from (HTTP Header Enrichment) on page 308
- from (PCC Rules) on page 309
- from (TDF Domain Selection) on page 310
- function (Diameter Network Element) on page 313
- gate-status on page 314
- greater-than on page 315
- gx-profile on page 316
- has-prefix on page 317
- has-suffix on page 318

Copyright © 2018, Juniper Networks, Inc.

- hcm (HTTP Header Enrichment) on page 319
- hcm-profile (HTTP Header Enrichment) on page 320
- hcm-profile (PCC Action Profiles) on page 321
- host (Diameter Origin) on page 322
- http-log-multiple-transactions (LRF Profile) on page 322
- icmp-mapping (Application Identification) on page 323
- id-components on page 324
- idle-timeout on page 325
- ifl-subscriber on page 326
- immediate-accounting-response on page 327
- include (Diameter Gx Profiles) on page 328
- incoming-queue on page 329
- inet (TDF Subscriber Address) on page 330
- inet (TDF Subscriber Exclude Prefix) on page 331
- inet6 (TDF Subscriber Address) on page 332
- inet6 (TDF Subscriber Exclude Prefix) on page 333
- integer on page 334
- interface (Services PIC) on page 335
- interface (Session PICs) on page 336
- interface-service (Services Interfaces) on page 337
- ip-protocol-mapping (Application Identification) on page 338
- ip-subscriber on page 339
- ipv4-address (Steering Path) on page 340
- ipv4-mask (HTTP Header Enrichment) on page 341
- ipv4-or-value (HTTP Header Enrichment) on page 342
- ipv6-address (Steering Path) on page 343
- ipv6-mask (HTTP Header Enrichment) on page 344
- ipv6-or-value (HTTP Header Enrichment) on page 345
- keep-existing-steering on page 346
- less-than on page 347
- local-port-range on page 348
- local-ports on page 350
- logging-rule (PCC Action Profile) on page 351
- lrf-profile (Service Set) on page 352
- matches on page 353
- maximum-bit-rate (Default Local Policy) on page 355
- maximum-bit-rate (PCC Action Profiles) on page 356

 Copyright © 2018, Juniper Networks, Inc.

- maximum-bit-rate (TDF Domain) on page 357
- maximum-pending-reqs-limit on page 358
- maximum-pending-requests (Diameter) on page 359
- maximum-sessions (TDF Gateway) on page 359
- maximum-subscribers on page 360
- maximum-sessions-trap-percentage (TDF Gateway) on page 361
- member (Application Identification) on page 362
- memory (TDF Gateway) on page 363
- mif (TDF Interface) on page 364
- monitoring-key (PCC Action Profile) on page 365
- mtu (TDF Interface) on page 365
- nas-ip-address on page 366
- nat-rule-sets (Service Set) on page 367
- nat-rules on page 367
- network-element (AAA Profile) on page 368
- network-element (Diameter Base Protocol) on page 369
- network-element (Subscriber Aware Policy Control) on page 370
- network-elements (RADIUS) on page 371
- network (Address Pools) on page 372
- network (TDF Domain) on page 373
- no-send-to-ue on page 374
- order (Application Identification) on page 375
- order-priority (Application Identification) on page 376
- origin (Diameter Base Protocol) on page 377
- outgoing-queue on page 378
- over (Application Identification) on page 379
- path (Steering) on page 380
- pattern (Application Identification) on page 381
- pattern (Class Attribute) on page 382
- pcc-action-profile (PCC Rules) on page 383
- pcc-action-profiles on page 384
- pcc-rule on page 386
- pcc-rulebases (PCEF) on page 387
- pcc-rulebases (PCEF Profile) on page 388
- pcc-rules (PCEF) on page 390
- pcc-rules (PCEF Profile) on page 391
- pcc-time-of-day-profiles on page 393

Copyright © 2018, Juniper Networks, Inc.

- pcef on page 394
- pcef-profile (Service Set) on page 396
- pcef-profile (TDF Domain) on page 397
- pcef-profile (TDF Domain Selection) on page 398
- peer (Diameter Base Protocol) on page 399
- peer (Diameter Network Element) on page 400
- pending-queue-watermark on page 401
- pending-queue-watermark-abate on page 402
- policy-based-logging (LRF Profile) on page 403
- pool (TDF Domain) on page 404
- port (LRF Profile) on page 405
- port (RADIUS Server) on page 405
- port-range (Application Identification) on page 406
- prefer-framed-ip-address (RADIUS Clients) on page 407
- prefer-framed-ipv6-prefix (RADIUS Clients) on page 408
- priority (Diameter Network Element) on page 408
- priority (RADIUS Network Elements) on page 409
- product-name on page 410
- profile (HTTP Header Enrichment) on page 411
- profile (LRF) on page 412
- profile (Services Application Identification) on page 413
- profile (HCM placeholder) on page 414
- profile (Services PCEF) on page 414
- profiles (AAA) on page 415
- profiles (PCEF) on page 416
- protocol (Application Identification) on page 418
- protocol (Flow Descriptions) on page 419
- realm (Diameter Origin) on page 420
- redirect (PCC Action Profiles) on page 421
- regex (Class Attribute) on page 422
- remote-address on page 423
- remote-port-range on page 424
- remote-ports on page 426
- report (LRF Rule) on page 427
- request-cache-timeout (RADIUS Snoop Segment) on page 428
- request-timeout on page 429
- response-cache-timeout (RADIUS Client) on page 430

 Copyright © 2018, Juniper Networks, Inc.

- retry (RADIUS Server) on page 431
- revert-interval (RADIUS Server) on page 432
- routing-instance (PCC Action Profiles) on page 433
- rule (HTTP Header Enrichment for Tag Rule Set) on page 434
- rule (LRF) on page 435
- rule-activation-time on page 436
- rule-deactivation-time on page 437
- secret (RADIUS Client) on page 438
- secret (RADIUS Server) on page 438
- server (RADIUS Network Elements) on page 439
- servers (RADIUS) on page 440
- service-mode on page 441
- service-pics on page 442
- service-set (Subscriber-Aware) on page 443
- service-set (TDF Interface) on page 444
- session-pics on page 445
- session-pics (Diameter) on page 446
- shared-secret (RADIUS Snoop Segment) on page 447
- snoop-segment (TDF Domain Selection) on page 448
- snoop-segments (RADIUS) on page 449
- snoop-segments (TDF Gateway) on page 450
- source (Application Identification) on page 451
- source-address (LRF Profile) on page 451
- source-interface on page 452
- source-interface (RADIUS Server) on page 453
- source-interface (RADIUS Snoop Segment) on page 454
- source-ip-address (RADIUS Snoop Segment) on page 455
- static-policy-control on page 456
- steering on page 458
- string on page 459
- subscriber-address on page 460
- subscriber-awareness (Service Set Options) on page 461
- subscriber-exclude-prefix on page 462
- subscriber-type (TDF Domain) on page 463
- subscription-id on page 464
- subscription-id-options on page 465
- subscription-id-type (Class Attribute) on page 466

Copyright © 2018, Juniper Networks, Inc.

- tag (HTTP Header Enrichment) on page 467
- tag-attribute (HTTP Header Enrichment) on page 468
- tag-attribute (HTTP Header Enrichment Tag Rule) on page 469
- tag-header (HTTP Header Enrichment) on page 470
- tag-operation (HTTP Header Enrichment) on page 471
- tag-rule (Profiles for HTTP Header Enrichment) on page 472
- tag-rule (HTTP Header Enrichment) on page 473
- tag-rules (Service Set) on page 474
- tag-rule-set (HTTP Header Enrichment) on page 475
- tag-rule-sets (Service Set) on page 476
- tag-separator (HTTP Header Enrichment) on page 476
- tag-value (HTTP Header Enrichment) on page 477
- tags (Application Identification) on page 478
- targets on page 479
- tdf (Unified Edge) on page 480
- tdf-interface on page 481
- template (LRF Profile) on page 482
- template (LRF Rule) on page 483
- template-tx-interval (LRF Profile) on page 484
- template-type (LRF Profile) on page 485
- term (HTTP Header Enrichment) on page 487
- term (TDF Domain Selection) on page 489
- then (HTTP Header Enrichment) on page 493
- then (LRF rule) on page 494
- then (PCC Rules) on page 495
- then (TDF Domain Selection) on page 496
- time on page 497
- time-limit (LRF Rule) on page 498
- timeout (Diameter Network Element) on page 499
- timeout (RADIUS Server) on page 500
- traceoptions (Diameter Base Protocol) on page 501
- traceoptions (PCEF) on page 503
- traceoptions (TDF Gateway) on page 505
- trigger-type (LRF Profile) on page 507
- type (Application Identification) on page 508
- type (ICMP Mapping for Application Identification) on page 508
- unit (TDF Interface) on page 509

 Copyright © 2018, Juniper Networks, Inc.

- url on page 510
- use-class (Class Attribute) on page 511
- user-name on page 512
- user-password (PCEF Profile) on page 513
- v4address on page 514
- v6address on page 515
- v6prefix on page 516
- vendor-id on page 517
- vendor-id (AAA Profile) on page 518
- vendor-support on page 519
- volume-limit (LRF Rule) on page 520
- watchdog-timeout on page 521

3gpp-imsi

Syntax

```
3gpp-imsi {
  equals value;
  has-prefix value;
  has-suffix value;
  matches value;
}
```

Hierarchy Level

[edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* from]

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the RADIUS AVP 3GPP-IMSI for the incoming RADIUS request from the subscriber.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

aaa clients (TDF)

Syntax

```
aaa {
  clients client-name;
  apply-groups [group-names];
  apply-groups-except [group-names];
}
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name]
```

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the GGSN, PGW, or BNG RADIUS clients that can send RADIUS requests to a TDF gateway.

Options

client-name—RADIUS client name that was previously configured at the **[edit access radius clients]** hierarchy level.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring RADIUS Clients That Send Accounting Requests for IP-Based Subscribers on page 106
- Configuring a TDF Gateway on page 16

Copyright © 2018, Juniper Networks, Inc.

aaa-policy-control (PCEF Profile)

Syntax

```
aaa-policy-control {
  aaa-profile aaa-profile-name;
  pcc-rulebases [rulebase-name];
  user-password password;
}
```

Hierarchy Level

[edit unified-edge pcef profiles *profile-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure RADIUS-server-controlled policy management for a policy and charging enforcement function (PCEF) profile.

Options

The remaining statements are explained separately.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Policies That a RADIUS Server Controls on page 82
- Configuring an AAA Profile on page 78

Copyright © 2018, Juniper Networks, Inc.

aaa-profile (PCEF Profile)

Syntax aaa-profile *aaa-profile-name*;

Hierarchy Level [edit unified-edge pcef profiles *profile-name* aaa-policy-control]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the AAA profile that identifies the RADIUS server policy control parameters for the policy and charging enforcement function (PCEF) profile. The AAA profile must already be defined at the **[edit unified-edge aaa]** hierarchy level.

Options ***aaa-profile-name***—Name of the AAA profile.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Policies That a RADIUS Server Controls on page 82
- Configuring an AAA Profile on page 78

Copyright © 2018, Juniper Networks, Inc.

access-interfaces (IFL Subscriber)

Syntax

```
access-interfaces [interface-name];
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domains domain-name ifl-subscriber
  subscriber-name]
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify one or more interfaces that carry traffic for the subscriber.

Options ***interface-name***—Name of the interface. You can assign only one IFL-based subscriber to an interface. You can specify the following types of interfaces:

- Physical Layer 3 Ethernet interface
- Layer 3 Aggregated Ethernet interface
- IRB interface
- IRB that contains Ether-channel and physical interface members
- Logical Tunnel interface

NOTE: The interfaces and the TDF interface (mif) in the TDF domain must be included in the same VRF routing instance.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring IFL-Based TDF Subscribers and Properties with a TDF Domain on page 117
- Understanding the Definition of a Set of IFL-Based Subscriber Properties with a TDF Domain on page 96

Copyright © 2018, Juniper Networks, Inc.

access-interfaces (IP Subscriber)

Syntax access-interfaces [*interface-name*];

Hierarchy Level [edit unified-edge gateways tdf *gateway-name* domains *domain-name* ip-subscriber]

Release Information Statement introduced in Junos OS Release 16.1 on MX Series.

Description Specify at least one interface that faces the access network and that carries traffic for the TDF domain for IP-based subscribers. You can specify multiple interfaces by including the **access-interfaces** statement multiple times.

Options ***interface-name***—Name of the interface.

NOTE: The access-facing interface and the TDF interface (mif) in the TDF domain must be included in the same VRF routing instance.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

accounting (AAA Profile)

Syntax

```
accounting {
  network-element network-element-name;
}
```

Hierarchy Level

[edit unified-edge aaa profiles *aaa-profile-name* radius]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Specify the network element providing policy management for TDF subscribers. The network element must already be defined at the **[edit access radius]** hierarchy level. This statement is required if the RADIUS servers cannot initiate a CoA request without an accounting record.

The remaining statement is explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring an AAA Profile on page 78
- Understanding AAA Profiles on page 58
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

accounting (RADIUS Client)

Syntax

```
accounting {
  secret password;
  response-cache-timeout seconds;
}
```

Hierarchy Level

[edit access radius clients *client-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Specify a shared secret and response cache timeout to be used by the MX Series router and the RADIUS client for accounting.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring RADIUS Clients That Send Accounting Requests for IP-Based Subscribers on page 106

Copyright © 2018, Juniper Networks, Inc.

accounting-port (RADIUS Server)

Syntax accounting-port *port-number*;

Hierarchy Level [edit access radius servers *name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the RADIUS server port number to which the MX Series router sends RADIUS accounting-start and accounting-stop requests. RADIUS accounting-start and accounting-stop requests are used when the RADIUS server is not able to initiate a change of authorization request without an accounting record.

Options ***port-number***—Port number to which the RADIUS requests are sent.

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring RADIUS Servers on page 74
- Understanding Network Elements on page 57
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

accounting-secret (RADIUS Server)

Syntax accounting-secret *password*;

Hierarchy Level [edit access radius servers *name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the secret password to be used when sending accounting-start requests to the RADIUS server if the accounting secret password is different from the authentication secret password. RADIUS accounting-start requests are used when the RADIUS server is not able to initiate a change of authorization request without an accounting record.

Default Use the same password that is used for authentication requests.

Options ***password***—Password for accounting requests.

Range: 1 through 64 characters

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring RADIUS Servers on page 74
- Understanding Network Elements on page 57
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

activation-attribute (AAA Profile)

Syntax

```
activation-attribute {
  <code numeric-code;>
  <vendor-id vendor-id;>
}
```

Hierarchy Level

[edit unified-edge aaa profiles *aaa-profile-name* radius policy]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure the RADIUS attribute that you want to carry the PCC rulebase name for rulebase activations from the RADIUS policy server to the MX Series router. By default, the rulebase name is carried in the ERX-Service-Activate Juniper vendor-specific attribute.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring an AAA Profile on page 78
- Understanding AAA Profiles on page 58
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

address (Diameter Peer)

Syntax address *ip-address*;

Hierarchy Level [edit access diameter peer *peer-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the IP address for the Diameter remote peer.

Options ***address***—IP address for the Diameter peer.

Required Privilege Level admin—To view this statement in the configuration.
admin-control—To add this statement to the configuration.

Related Documentation
- diameter on page 273

address (LRF Profile)

Syntax address *collector-address*;

Hierarchy Level [edit services lrf profile *profile-name* collector *collector-name* destination]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the destination IP address of the collector.

Options ***collector-address***—IP address of the collector.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation
- Configuring an LRF Profile for Subscribers on page 152
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152

Copyright © 2018, Juniper Networks, Inc.

address (RADIUS Clients)

Syntax address *client-address*;

Hierarchy Level [edit access radius clients *client-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the address from which the GGSN, PGW, or BNG RADIUS client sends the RADIUS requests.

Options ***client-address***—IP address of the PGW client.

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation
- Configuring RADIUS Clients That Send Accounting Requests for IP-Based Subscribers on page 106

address (RADIUS Server)

Syntax address *server-address*;

Hierarchy Level [edit access radius servers *name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the address of the RADIUS server.

Options ***server-address***—IP address for the RADIUS server.

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation
- Configuring RADIUS Servers on page 74
- Understanding Network Elements on page 57
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

address-mapping (Application Identification)

Syntax

```
address-mapping name {
  destination {
    ip ip-address-prefix;
  }
  source {
    ip ip-address-prefix;
  }
  order order;
  order-priority (high | low);
  }
}
```

Hierarchy Level

[edit services application-identification *application application-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Define an application signature based on the source or destination IP address.

The remaining statements are explained separately. Search for a statement in CLI Explorer or click a linked statement in the Syntax section for details.

Options

name—Name given to the application associated with the source or destination IP address.

Required Privilege Level

view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation

- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25

Copyright © 2018, Juniper Networks, Inc.

address-pools

Syntax

```
address-pools {
  name {
    default-pool;
    family (inet | inet6) {
      network {
        [network-prefix] {
          external-assigned;
        }
      }
    }
    service-mode service-mode-options;
  }
}
```

Hierarchy Level

[edit access address-assignment]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure the address pools that the TDF domains use to specify the source IP addresses of packets to undergo TDF processing.

Options

name—Name of the address pool.

Range: 1 through 63 alphanumeric characters

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Understanding Source IP Filtering with Address Pools in TDF Domains for IP-Based Subscribers on page 90
- Configuring Address Pools for Source-IP Filtering of IP-Based Subscribers on page 99
- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100

Copyright © 2018, Juniper Networks, Inc.

allow-dynamic-requests (RADIUS Server)

Syntax allow-dynamic-requests;

Hierarchy Level [edit access radius servers *name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Allow dynamic requests from the RADIUS server so that change of authorization requests can be received.

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring RADIUS Servers on page 74
- Understanding Network Elements on page 57
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

alt-name (Application Identification)

Syntax alt-name *alt-name*

Hierarchy Level [edit services application-identification application *application-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Provide an alternate name for the application.

Options ***alt-name***—Alternate name for the application.

Range: 1 through 255 characters

Required Privilege Level view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation

- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25

Copyright © 2018, Juniper Networks, Inc.

application (Application Identification)

Syntax

```
application application-name <description description> {
  address-mapping name {
    destination {
      ip ip-address-prefix;
    }
    source {
      ip ip-address-prefix;
    }
    order order;
    order-priority (high | low);
    }
  }
  alt-name alt-name;
  cacheable;
  compatibility junos-compatibility-version;
  description description;
  icmp-mapping {
    code icmp-code;
    order order;
    order-priority (high | low);
    type icmp-type;
  }
  ip-protocol-mapping {
    order order;
    order-priority (high | low);
    protocol protocol-number
  }
  over l4-l7-signature-name {
    chain-order
    member member-name {
      check-bytes max-bytes-to-check;
      context context;
      pattern pattern;
      direction direction;
    }
    order order;
    order-priority (high | low);
    port-range {
      tcp [port-range];
      udp [port-range];
    }
    protocol (http | ssl | tcp | udp);
  }
  tags tag-value;
  type type;
}
```

Hierarchy Level

```
[edit services application-identification]
```

Copyright © 2018, Juniper Networks, Inc.

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure identification of an application for which one or more custom signatures are defined.

Options

application-name—Name of the application for which one or more custom signatures has been defined.

description—(Optional) Textual description of the application for which mappings are provided.

The remaining statements are explained separately. Search for a statement in CLI Explorer or click a linked statement in the Syntax section for details.

Required Privilege Level

view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation

- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25

Copyright © 2018, Juniper Networks, Inc.

application-groups (PCC Rules)

Syntax

```
application-groups [application-group-name];
```

Hierarchy Level

```
[edit unified-edge pcef pcc-rules rule-name from],
[edit services pcef pcc-rules rule-name from]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef pcc-rules *rule-name* from]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description

Specify one or more application groups to define the match criteria for the policy and charging control (PCC) rule. You can specify a maximum of 10 application groups in a PCC rule.

NOTE: You must also include the **flows** statement. If you do not want to filter subscriber traffic based on service data flow filters, use **flows any**.

If you are using Junos OS Subscriber Aware, specify the name of the application group at the **[edit unified-edge pcef pcc-rules *rule-name* from]** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, specify the name of the application group at the **[edit services pcef pcc-rules *rule-name* from]** hierarchy level.

Options

application-group-name—Name of an application group that is used to detect IP packet flows.

Range: 1 through 63 characters.

NOTE: The referenced application groups must have been previously configured in the **[edit services application-identification]** hierarchy level.

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring Policy and Charging Control Rules on page 70

Copyright © 2018, Juniper Networks, Inc.

application-identification (Application Identification)

Syntax

```
application-identification {
  application application-name <description description> {
    address-mapping name {
      destination {
        ip ip-address-prefix;
      }
      source {
        ip ip-address-prefix;
      }
      order order;
      order-priority (high | low);
      }
    }
    alt-name alt-name;
    cacheable;
    compatibility junos-compatibility-version;
    description description;
    icmp-mapping {
      code icmp-code;
      order order;
      order-priority (high | low);
      type icmp-type;
    }
    ip-protocol-mapping {
      order order;
      order-priority (high | low);
      protocol protocol-number
    }
    over l4-l7-signature-name {
      chain-order
      member member-name {
        check-bytes max-bytes-to-check;
        context context;
        pattern pattern;
        direction direction;
      }
      order order;
      order-priority (high | low);
      port-range {
        tcp [port-range];
        udp [port-range];
      }
      protocol (http | ssl | tcp | udp);
    }
    tags tag-value;
    type type;
  }
}
```

Hierarchy Level

```
[edit services]
```


Copyright © 2018, Juniper Networks, Inc.

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure application identification options to identify the application as it passes through the device.

The remaining statements are explained separately. Search for a statement in CLI Explorer or click a linked statement in the Syntax section for details.

Required Privilege Level view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation
- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25

application-identification-profile (Service Set)

Syntax
```
application-identification-profile app-id-profile-name;
```

Hierarchy Level
```
[edit services service-set service-set-name]
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the dummy application identification profile that you configured at the **[edit services application-identification profile]** hierarchy level. This profile is a placeholder profile with no configuration options, but it must be specified to enable application identification functionality on the services plane.

Options ***app-id-profile-name***—Name of the application identification profile.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation
- Applying Services to Subscriber-Aware Traffic with a Service Set on page 124
- *Identifying the Service Interface That Handles Subscriber Management Application-Aware Policy Control*

Copyright © 2018, Juniper Networks, Inc.

applications (Diameter)

Syntax

```
applications {
  pcc-gx {
    maximum-pending-requests requests;
  }
}
```

Hierarchy Level

[edit access diameter]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure the parameters for Diameter applications. Specify the Diameter application for which you are configuring the parameters. The Gx application (**pcc-gx**) is currently supported.

Options

pcc-gx—Use the parameters for the Gx application.

The remaining statement is explained separately. See CLI Explorer.

Required Privilege Level

access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- diameter on page 273

Copyright © 2018, Juniper Networks, Inc.

applications (PCC Rules)

Syntax

```
applications [application-name];
```

Hierarchy Level

```
[edit unified-edge pcef pcc-rules rule-name from],
[edit services pcef pcc-rules rule-name from]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef pcc-rules *rule-name* from]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description

Specify one or more applications to define the match criteria for the policy and charging control (PCC) rule. You can specify a maximum of 10 applications in a PCC rule.

NOTE: **You must also include the flows statement. If you do not want to filter subscriber traffic based on service data flow filters, use flows any.**

If you are using Junos OS Subscriber Aware, specify the name of the applications at the **[edit unified-edge pcef pcc-rules *rule-name* from]** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, specify the name of the applications at the **[edit services pcef pcc-rules *rule-name* from]** hierarchy level.

Options

application-name—Name of one or more applications that is used to detect IP packet flows.

Range: 1 through 63 characters.

NOTE: **The referenced application must have been previously configured in the [edit services application-identification] hierarchy level.**

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring Policy and Charging Control Rules on page 70

Copyright © 2018, Juniper Networks, Inc.

attribute

Syntax

```
attribute name {
  apply-groups [group-names];
  apply-groups-except [group-names];
  code numeric-code;
  vendor-id vendor-id;
  format {
    integer {
      apply-groups [group-names];
      apply-groups-except [group-names];
      equals {
        apply-groups [group-names];
        apply-groups-except [group-names];
        value;
      }
      greater-than value;
      less-than value;
    }
    string {
      apply-groups [group-names];
      apply-groups-except [group-names];
      equals {
        apply-groups [group-names];
        apply-groups-except [group-names];
        value;
      }
      has-prefix{
        apply-groups [group-names];
        apply-groups-except [group-names];
        value;
      }
      has-suffix {
        apply-groups [group-names];
        apply-groups-except [group-names];
        value;
      }
      matches {
        apply-groups [group-names];
        apply-groups-except [group-names];
        value;
      }
    }
    time {
      apply-groups [group-names];
      apply-groups-except [group-names];
      equals {
        apply-groups [group-names];
        apply-groups-except [group-names];
        value;
      }
      greater-than value;
      less-than value;
```


Copyright © 2018, Juniper Networks, Inc.

```
    }
    v4address {
      apply-groups [group-names];
      apply-groups-except [group-names];
      equals {
        apply-groups [group-names];
        apply-groups-except [group-names];
        value;
      }
    }
    v6address {
      apply-groups [group-names];
      apply-groups-except [group-names];
      equals {
        apply-groups [group-names];
        apply-groups-except [group-names];
        value;
      }
    }
    v6prefix {
      apply-groups [group-names];
      apply-groups-except [group-names];
      equals {
        apply-groups [group-names];
        apply-groups-except [group-names];
        value;
      }
    }
  }
}
```

Hierarchy Level [edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* from]

Release Information Statement introduced in Junos OS Release 16.1 on MX Series.

Description Specify a custom RADIUS attribute for the incoming RADIUS request from the subscriber. You can configure up to five attributes.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

Options *name*—Name for the attribute.

Range: 1 through 50 alphanumeric characters. Allowed characters are [a-z, A-Z, 0-9]

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Copyright © 2018, Juniper Networks, Inc.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

attributes (Diameter Gx Profiles)

Syntax

```
attributes {
  exclude {
    an-gw-address;
    default-eps-bearer-qos;
    packet-filter-information;
    packet-filter-operation;
    rat-type;
  }
  include {
    gx-capability-list;
    rule-suggestion;
  }
}
```

Hierarchy Level

[edit unified-edge diameter-profiles gx-profile *profile-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure attribute-value pairs (AVPs) that are excluded from or included in the credit control request (CCR) messages between the MX Series router and the policy and charging enforcement function (PCEF).

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- gx-profile on page 316

Copyright © 2018, Juniper Networks, Inc.

authentication (AAA Profile)

Syntax

```
authentication {
  network-element network-element-name;
}
```

Hierarchy Level

[edit unified-edge aaa profiles *aaa-profile-name* radius]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Specify the network element providing policy management for TDF subscribers. The network element must already be defined at the **[edit access radius]** hierarchy level.

The remaining statement is explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring an AAA Profile on page 78
- Understanding AAA Profiles on page 58
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

burst-size (Default Local Policy)

Syntax

```
burst-size uplink uplink-burst-size downlink downlink-burst-size;
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domains domain-name ip-subscriber
  default-local-policy]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Specify the allowed burst size for a subscriber's uplink and downlink traffic during the TDF IP-based subscriber creation process. Uplink traffic originates from the subscriber towards the public data network (PDN), and downlink traffic comes from the PDN and is destined for the subscriber.

Options

uplink-burst-size—Burst size value for the uplink direction.

Range: 1500 through 1,500,000,000 bytes.

downlink-burst-size—Burst size value for the downlink direction.

Range: 1500 through 1,500,000,000 bytes

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

burst-size (TDF Domain)

Syntax

```
burst-size {
  apply-groups [group-names];
  apply-groups-except [group-names];
  downlink downlink-burst-size;
  uplink uplink-burst-size ;
}
```

Hierarchy Level

[edit unified-edge gateways tdf *gateway-name* domains *domain-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure the TDF domain's default TDF subscriber allowed burst size for uplink and downlink traffic. Uplink traffic originates from the subscriber towards the public data network (PDN), and downlink traffic comes from the PDN and is destined for the subscriber.

Options

downlink-burst-size—Burst size value for the downlink direction.

Range: 1500 through 1,500,000,000 bytes.

uplink-burst-size—Burst size value for the uplink direction.

Range: 1500 through 1,500,000,000 bytes.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Configuring IFL-Based TDF Subscribers and Properties with a TDF Domain on page 117
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based and IFL-Based TDF Subscribers Overview on page 88
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

cac (TDF Gateway)

Syntax

```
cac {
  cpu cpu-pct;
  maximum-sessions max-sessions;
  maximum-sessions-trap-percentage max-sessions-pct;
  memory memory-pct;
}
```

Hierarchy Level

[edit unified-edge gateways tdf *gateway-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure the call admissions control (CAC) parameters for the TDF gateway.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a TDF Gateway on page 16

cacheable (Application Identification)

Syntax

```
cacheable
```

Hierarchy Level

[edit services application-identification application *application-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Enable the application system cache (ASC), which saves the mapping between an application type and the corresponding destination IP address, destination port, protocol type, and service. The ASC is disabled by default.

Required Privilege Level

view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation

- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25

Copyright © 2018, Juniper Networks, Inc.

call-rate-statistics

Syntax

```
call-rate-statistics {
   history records;
   interval minutes;
}
```

Hierarchy Level

[edit unified-edge gateways tdf *gateway-name*],
[edit unified-edge gateways tdf *gateway-name* domains *domain-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure call rate statistics for a TDF gateway or a TDF domain.

Options

records—Number of call-rate statistics records to save. When the number of call-rate records equals this value and a new record is received, the oldest record is replaced by the new record.

minutes—Length of statistics collection interval.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge—To add this statement to the configuration.

Related Documentation

- Configuring Call-Rate Statistics Collection on page 200

Copyright © 2018, Juniper Networks, Inc.

called-station-id

Syntax

```
called-station-id {
  equals value;
  matches value;
}
```

Hierarchy Level

[edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* from]

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the RADIUS AVP called station ID for the incoming RADIUS request from the IP-based subscriber.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

calling-station-id

Syntax

```
calling-station-id {
  equals value;
  matches value;
}
```

Hierarchy Level

[edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* from]

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the RADIUS AVP calling station ID for the incoming RADIUS request from the IP-based subscriber.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

chain-order (Application Identification)

Syntax
```
chain-order;
```

Hierarchy Level
```
[edit services application-identification application application-name over]
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Read members in order. By default, chain ordering is turned off. If there is only one member, this option is ignored.

Required Privilege Level view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation
- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25

check-bytes (Application Identification)

Syntax
```
check-bytes max-bytes-to-check;
```

Hierarchy Level
```
[edit services application-identification application application-name over member]
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the maximum number of bytes to be inspected. This statement applies to TCP and UDP protocols for stream context. It is not considered for other protocols and contexts.

Options ***max-bytes-to-check***—Number of bytes to be inspected.

Range: 1 through 5000

Default: Not configured

Required Privilege Level view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation
- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25

Copyright © 2018, Juniper Networks, Inc.

class

Syntax

```
class {
  equals value;
  has-prefix value;
  has-suffix value;
  matches value;
}
```

Hierarchy Level

[edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* from]

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the RADIUS AVP class for the incoming RADIUS request from the IP-based subscriber.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

client

Syntax client *client-name*;

Hierarchy Level [edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* from]

Release Information Statement introduced in Junos OS Release 16.1 on MX Series.

Description Specify the RADIUS client for the incoming RADIUS request from an IP-based subscriber.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

Options ***client-name***—Name of the RADIUS client.

NOTE: The RADIUS client must have been previously configured at the **[edit access radius]** hierarchy level, and specified as the **aaa-client** at the **[edit unified-edge gateways tdf *gateway-name*]** hierarchy level.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88
- Configuring RADIUS Clients That Send Accounting Requests for IP-Based Subscribers on page 106

Copyright © 2018, Juniper Networks, Inc.

clients

Syntax

```
clients client-name {
  accounting {
    secret password;
    response-cache-timeout seconds;
  }
  address client-address;
  <prefer-framed-ip-address>
  <prefer-framed-ipv6-prefix>
  source-interface interface ipv4-address address;
}
```

Hierarchy Level

```
[edit access radius]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure a RADIUS client for each GGSN, PGW, or BNG that sends subscriber session requests to the MX Series router and identifies it as a RADIUS server.

Options

client-name—Name for the client.

Range: 1 through 50 alphanumeric characters. Allowed characters are a-z, A-Z, 0-9.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring RADIUS Clients That Send Accounting Requests for IP-Based Subscribers on page 106

Copyright © 2018, Juniper Networks, Inc.

coa-accounting (AAA Profile)

Syntax coa-accounting (enable | disable);

Hierarchy Level [edit unified-edge aaa profiles *aaa-profile-name* radius policy]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Enable or disable the initiation of a RADIUS accounting start from the MX Series router to the RADIUS server. Enabling this feature is required if the RADIUS server cannot initiate a change of authorization request without an accounting record. Specifying **enable** does not cause the MX Series router to report any billing information.

Options

enable—Initiate a RADIUS accounting start from the MX Series Router to the RADIUS server.

disable—Do not initiate a RADIUS accounting start from the MX Series Router to the RADIUS server.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring an AAA Profile on page 78
- Understanding AAA Profiles on page 58
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

code

Syntax

```
code numeric-code;
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  attribute name]
```

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the custom attribute's AVP code for the incoming RADIUS request from the subscriber.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

Options

numeric-code—Numeric value for the code.

Range: 0 through 255.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

code (AAA Profile)

Syntax code *numeric-code*;

Hierarchy Level [edit unified-edge aaa profiles *aaa-profile-name* radius policy activation-attribute],
[edit unified-edge aaa profiles *aaa-profile-name* radius policy deactivation-attribute]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the RADIUS attributes that you want to carry the PCC rulebase name for rulebase activations and deactivations from the RADIUS policy server to the MX Series router. By default, the rulebase name is carried in the ERX-Service-Activate Juniper vendor-specific attribute (VSA) for activations and in the ERX-Service-Deactivate Juniper VSA for deactivations.

Options ***numeric-code***—Numeric value for the RADIUS AVP.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring an AAA Profile on page 78
- Understanding AAA Profiles on page 58
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

code (Application Identification)

Syntax code *icmp-code*;

Hierarchy Level [edit services application-identification application *application-name* icmp-mapping]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Match the specified ICMP code to create a custom application signature.

Options ***value***—Numeric value for the ICMP code.

Range: 0 through 254

Required Privilege Level view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation

- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25

Copyright © 2018, Juniper Networks, Inc.

collector (LRF Profile)

Syntax

```
collector collector-name {
  destination {
    address collector-address;
    port collector-port-number;
  }
  source-address source-address;
}
```

Hierarchy Level

```
[edit services lrf profile profile-name]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure a collector that receives logging and reporting data. This collector can be specified in LRF rules.

Options

collector-name—Name for the collector.

Range: Up to 32 characters.

The remaining statements are explained separately. Search for a statement in CLI Explorer or click a linked statement in the Syntax section for details.

Required Privilege Level

interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring an LRF Profile for Subscribers on page 152
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152
- *Configuring Logging and Reporting for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

collector (LRF Rule)

Syntax collector *collector-name*;

Hierarchy Level [edit services lrf profile *profile-name* rule *lrf-rule-name* then report]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the collector that receives the data if the LRF rule is matched.

Options ***collector-name***—Name of the collector that receives the data. The referenced collector must already be defined at the **[edit services lrf profile *profile-name*]** hierarchy level.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring an LRF Profile for Subscribers on page 152
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152
- *Configuring Logging and Reporting for Subscriber Management*

compatibility (Application Identification)

Syntax compatibility *junos-compatibility-version*;

Hierarchy Level [edit services application-identification application *application-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the Junos OS release for compatibility.

Options ***junos-compatibility-version***—Name of the Junos OS software release compatibility version, such as 17.1.

Required Privilege Level view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation

- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25

Copyright © 2018, Juniper Networks, Inc.

connect-actively

Syntax

```
connect-actively {
  <capabilities-exchange-timeout seconds>;
  <port port-number>;
  <repeat-timeout seconds>;
  <retry-timeout seconds>;
  <timeout seconds>;
  transport transport-name;
}
```

Hierarchy Level

[edit access diameter peer *peer-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Define the destination port and transport connection used to establish active connections to the Diameter peer.

Options

capabilities-exchange-timeout *seconds*—(Optional) Use the specified amount of time to wait for a Capabilities-Exchange-Answer message.

Range: 1 through 65,535 seconds

Default: 10 seconds

port *port-number*—(Optional) Use the specified destination TCP port.

Default: 3868

repeat-timeout *seconds*—(Optional) Use the specified amount of time to wait before attempting to reconnect to this peer after receiving the DO_NOT_WANT_TO_TALK_TO_YOU value for the Disconnect-Cause AVP in the Disconnect-Peer-Request message. A value of zero means that there is no attempt to reconnect to the peer.

Range: 0 through 65,535 seconds

Default: 0

retry-timeout *seconds*—(Optional) Use the specified amount of time to wait between connection attempts for this peer.

Range: 1 through 65,535 seconds

Default: 30 seconds

timeout *seconds*—(Optional) Use the specified amount of time to wait for connection acknowledgement for this peer.

Range: 1 through 65,535 seconds

Default: 10 seconds

transport *transport-name*—Use the specified name of the transport layer connection.

Copyright © 2018, Juniper Networks, Inc.

NOTE: The specified transport must already be configured at the **[edit access diameter transport]** hierarchy level.

Required Privilege Level
access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation
- diameter on page 273

constant

Syntax
```
constant value;
```

Hierarchy Level
```
[edit unified-edge gateways tdf gateway-name domains domain-name ip-subscriber
  subscription-id]
```

Release Information
Statement introduced in Junos OS Release 16.1 on MX Series.

Description
Specify a constant string for the Subscription-Id-Data value for IP-based subscribers. This constant value is used if none of the **subscription-id-options** methods can be used. In such a case, the Subscription-Id-Type is END_USER_PRIVATE.

Options
value—String that is used for the Subscription-Id-Data value.

Required Privilege Level
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation
- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

context (Application Identification)

Syntax context *context*;

Hierarchy Level [edit services application-identification application *application-name* over member]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Define a predefined service-specific context as an additional matching criterion for application identification.

Options ***context***—One of the following predefined contexts:

- **http-get-url-parsed-param-parsed**—Decoded, normalized GET URL in an HTTP request and the decoded CGI parameters, if any.
- **http-header-content-type**—Content-Type header in an HTTP transaction.
- **http-header-cookie**—Cookie header in an HTTP transaction.
- **http-header-host**—Host header in an HTTP request.
- **http-header-user-agent**—User-agent header in an HTTP transaction.
- **http-post-url-parsed-param-parsed**—Decoded, normalized POST URL in an HTTP request and the decoded CGI parameters, if any.
- **http-post-variable-parsed**—Decoded POST URL or form data variables.
- **http-url-parsed**—Decoded, normalized URL in an HTTP request.
- **http-url-parsed-param-parsed**—Decoded, normalized URL in an HTTP request and the decoded CGI parameters, if any.
- **ssl-server-name**—Server name in the TLS server name extension or in the SSL server certificate.
- **stream**— TCP or UDP stream data.

Required Privilege Level view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation

- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25

 Copyright © 2018, Juniper Networks, Inc.

count (HTTP Header Enrichment)

Syntax

```
count;
```

Hierarchy Level

[edit services hcm tag-rule *rule-name* term *term-number* then]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Enable the collection of statistics for HTTP header enrichment for the tag rule term. The collection of statistics for a term is disabled by default.

Required Privilege Level

interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring HTTP Header Enrichment Overview on page 33
- Configuring Tag Rules on page 35
- Configuring HCM Profiles and Assigning Tag Rules on page 40
- Junos Web Aware HTTP Header Enrichment Overview on page 33.
- **show services hcm statistics on page 601**

Copyright © 2018, Juniper Networks, Inc.

cpu (TDF Gateway)

Syntax cpu *cpu-pct*;

Hierarchy Level [edit unified-edge gateways tdf *gateway-name* cac]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the threshold for the maximum amount of CPU that the TDF gateway can use. If the amount of CPU that the TDF gateway uses reaches the threshold, the SNMP trap **jnxScgSMCPUThreshHigh** is generated.

Options ***cpu-pct***—Maximum percentage of CPU.

Range: 1 through 90.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a TDF Gateway on page 16

 Copyright © 2018, Juniper Networks, Inc.

deactivation-attribute (AAA Profile)

Syntax

```
deactivation-attribute {
  <code numeric-code;>
  <vendor-id vendor-id;>
}
```

Hierarchy Level

[edit unified-edge aaa profiles *aaa-profile-name* radius policy]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure the RADIUS attribute that you want to carry the PCC rulebase name for rulebase deactivations from the RADIUS policy server to the MX Series router. By default, the rulebase name is carried in the ERX-Service-Deactivate Juniper vendor-specific attribute.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring an AAA Profile on page 78
- Understanding AAA Profiles on page 58
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

dead-criteria-retries (RADIUS Server)

Syntax dead-criteria-retries *retry-number* interval *seconds*;

Hierarchy Level [edit access radius servers *name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure a limit to the number of times the MX Series router can resend a request to the RADIUS server when no response from the RADIUS server is received. If the number of retries reaches this limit, the RADIUS server is marked as dead, and the MX Series router begins to send requests to other RADIUS servers in the network element.

Default The dead server detection function is disabled.

Options ***retry-number***—Number of retries.

Range: 10 through 65535

seconds—Time interval in seconds.

Range: 5 through 300

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring RADIUS Servers on page 74
- Understanding Network Elements on page 57
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

default-local-policy

Syntax

```
default-local-policy {
  apply-groups [group-names];
  apply-groups-except [group-names];
  flow-action (drop | forward);
  maximum-bit-rate uplink mbr-uplink-value downlink mbr-downlink-value;
  burst-size uplink uplink-burst-size downlink downlink-burst-size;
}
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domains domain-name ip-subscriber]
```

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the default local policy, which is applied to the IP-based subscriber's data packets entering the access interface of the TDF domain when a TDF subscriber session does not exist.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

default-pool (Address Pools)

Syntax default-pool;

Hierarchy Level [edit access address-assignment address-pools *name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the address pool as a default pool. A TDF domain uses the default address pool to specify the source IP addresses of packets that undergo TDF processing when an address pool is not specified for the TDF domain.

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Understanding Source IP Filtering with Address Pools in TDF Domains for IP-Based Subscribers on page 90
- Configuring Address Pools for Source-IP Filtering of IP-Based Subscribers on page 99
- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100

description (Application Identification)

Syntax description *description*

Hierarchy Level [edit services application-identification application *application-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Provide a description of the application.

Options ***description***—Textual description of the application.

Range: 1 through 255 characters

Required Privilege Level view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation

- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25

Copyright © 2018, Juniper Networks, Inc.

destination (Application Identification)

Syntax

```
destination ip ip-address-prefix;
```

Hierarchy Level

```
[edit services application-identification application application-name address-mapping]
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the destination IP address for address mapping-based application identification.

Options ***ip-address-prefix***—IP address and prefix for matching.

Required Privilege Level view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation

- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25

destination (LRF Profile)

Syntax

```
destination {
  address collector-address;
  port collector-port-number;
}
```

Hierarchy Level

```
[edit services lrf profile profile-name collector collector-name]
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the destination IP address and port number of the collector.

The remaining statements are explained separately. Search for a statement in CLI Explorer or click a linked statement in the Syntax section for details.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring an LRF Profile for Subscribers on page 152
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152
- *Configuring Logging and Reporting for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

destination-address (HTTP Header Enrichment)

Syntax

```
destination-address {
  (any-ipv4 | any-ipv4 except);
  (any-ipv6 | any-ipv6 except);
  (any-unicast | any-unicast except);
  (prefix | prefix except);
}
```

Hierarchy Level

```
[edit services hcm tag-rule rule-name term term-number from]
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the prefix or address type that the HTTP request destination IP address must match. You can specify multiple prefixes or address types by including the **destination-address** statement multiple times.

After this criterion and the other match criteria specified for the **term** are matched, the HTTP header enrichment actions specified for the **term** are applied to the HTTP traffic.

Options

any-ipv4—Match any IPv4 address.

any-ipv4 except—Exclude IPv4 addresses from addresses that are in a **destination-address**, **destination-address-range**, or **destination-prefix-list** statement configured at the **[edit services hcm tag-rule *rule-name* term *term-number* from]** hierarchy level. You cannot use **except** without also configuring addresses that do match.

any-ipv6—Match any IPv6 address.

any-ipv6 except—Exclude IPv6 addresses from addresses that are in a **destination-address**, **destination-address-range**, or **destination-prefix-list** statement configured at the **[edit services hcm tag-rule *rule-name* term *term-number* from]** hierarchy level. You cannot use **except** without also configuring addresses that do match.

any-unicast—Match any IPv4 unicast address. This option does not match any IPv6 addresses.

any-unicast except—Exclude IPv4 unicast addresses from addresses that are in a **destination-address**, **destination-address-range**, or **destination-prefix-list** statement configured at the **[edit services hcm tag-rule *rule-name* term *term-number* from]** hierarchy level. You cannot use **except** without also configuring IPv4 addresses that do match.

prefix—IP prefix for the addresses that are matched.

Copyright © 2018, Juniper Networks, Inc.

***prefix* except**—Exclude the specified IP prefixes from addresses that are in a **destination-address**, **destination-address-range**, or **destination-prefix-list** statement configured at the **[edit services hcm tag-rule *rule-name* term *term-number* from]** hierarchy level. You cannot use **except** without also configuring addresses that do match.

Required Privilege Level
interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation
- Configuring HTTP Header Enrichment Overview on page 33
- hcm on page 319

destination-address-range (HTTP Header Enrichment)

Syntax

```
destination-address-range {
  high address low address <except>;
}
```

Hierarchy Level

```
[edit services hcm tag-rule rule-name term term-number from]
```

Release Information
Statement introduced in Junos OS Release 17.1 on MX Series.

Description
Specify an IP address range that the HTTP request destination IP address must match. You can specify multiple address ranges by including the **destination-address-range** statement multiple times.

After this criterion and the other match criteria specified for the **term** are matched, the HTTP header enrichment actions specified for the **term** are applied to the HTTP traffic.

Options
except—(Optional) Exclude addresses in the specified address range from addresses that are in a **destination-address**, **destination-address-range**, or **destination-prefix-list** statement configured at the **[edit services hcm tag-rule *rule-name* term *term-number* from]** hierarchy level. You cannot use **except** without also configuring addresses that do match.

high *address*—Upper limit of the address range.

low *address*—Lower limit of the address range.

Required Privilege Level
interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation
- Configuring HTTP Header Enrichment Overview on page 33
- hcm on page 319

Copyright © 2018, Juniper Networks, Inc.

destination-ip-address (RADIUS Snoop Segment)

Syntax destination-ip-address *destination-address*;

Hierarchy Level [edit access radius snoop-segments *segment-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the destination IP address for accounting messages to snoop.

Options ***destination-address***—Destination IPv4 address of accounting messages.

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring Snooping of RADIUS Accounting Requests for IP-Based Subscribers on page 113
- Snooping RADIUS Accounting Requests for IP-Based Subscribers Overview on page 94
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

destination-port (RADIUS Snoop Segment)

Syntax destination-port *destination-port*;

Hierarchy Level [edit access radius snoop-segments *segment-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the destination port for accounting messages to snoop.

Options ***destination-port***—Destination port of accounting messages.

Default: 1813

Range: 1 through 65,535

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring Snooping of RADIUS Accounting Requests for IP-Based Subscribers on page 113
- Snooping RADIUS Accounting Requests for IP-Based Subscribers Overview on page 94
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

destination-port-range (HTTP Header Enrichment)

Syntax

```
destination-port-range {
   high port-number low port-number;
}
```

Hierarchy Level

[edit services hcm tag-rule *rule-name* term *term-number* from]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Specify a port range that the HTTP request destination port number must match. You can specify multiple port ranges by including the **destination-port-range** statement multiple times.

After this criterion and the other match criteria specified for the **term** are matched, the HTTP header enrichment actions specified for the **term** are applied to the HTTP traffic.

Options

high *port-number*—Upper limit of the port range.

low *port-number*—Lower limit of the port range.

Required Privilege Level

interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring HTTP Header Enrichment Overview on page 33
- hcm on page 319

Copyright © 2018, Juniper Networks, Inc.

destination-ports (HTTP Header Enrichment)

Syntax destination-ports *value*;

Hierarchy Level [edit services hcm tag-rule *rule-name* term *term-number* from]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the HTTP request destination port number that must be matched. You can specify multiple ports by including the **destination-ports** statement multiple times.

After this criterion and the other match criteria specified for the **term** are matched, the HTTP header enrichment actions specified for the **term** are applied to the HTTP traffic.

Options *value*—Port number.
Range: 0 through 65,535

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring HTTP Header Enrichment Overview on page 33
- hcm on page 319

Copyright © 2018, Juniper Networks, Inc.

destination-prefix-list (HTTP Header Enrichment)

Syntax

```
destination-prefix-list {
  (prefix-name | prefix-name except);
}
```

Hierarchy Level

[edit services hcm tag-rule *rule-name* term *term-number* from]

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the destination prefix list that the HTTP request destination IP address must match. You can specify multiple prefix lists by including the **destination-prefix-list** statement multiple times.

After this criterion and the other match criteria specified for the **term** are matched, the HTTP header enrichment actions specified for the **term** are applied to the HTTP traffic.

Options

prefix-name—Name of the prefix list.

NOTE: **The prefix list must already be defined at the [edit policy-options prefix-list] hierarchy level.**

***prefix-name* except**—Exclude addresses that are in the specified prefix list from addresses that are in the **destination-address** or **destination-address-range** statement configured at the **[edit services hcm tag-rule *rule-name* term *term-number* from]** hierarchy level. You cannot use **except** without also configuring addresses that do match.

Required Privilege Level

interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring HTTP Header Enrichment Overview on page 33
- hcm on page 319

Copyright © 2018, Juniper Networks, Inc.

diameter (Subsciber Aware Policy Control)

Syntax

```
diameter {
  applications {
    pcc-gx {
      <maximum-pending-requests requests>;
    }
  }
  <firmware-revision version>;
  network-element element-name {
    function function-name;
    peer peer-name {
      priority priority-value;
      <timeout seconds>;
    }
  }
  origin {
    host hostname;
    realm realm-name;
  }
  peer peer-name {
    address ip-address;
    connect-actively {
      <capabilities-exchange-timeout seconds>;
      <port port-number>;
      <repeat-timeout seconds>;
      <retry-timeout seconds>;
      <timeout seconds>;
      transport transport-name;
    }
    <disconnect-peer-timeout seconds>;
    <incoming-queue> {
      size size;
    }
    <outgoing-queue> {
      <high-watermark high-watermark>;
      <low-watermark low-watermark>;
      size size;
    }
    <watchdog-timeout seconds>;
  }
<product-name product-name>;
  traceoptions {
    file diameter;
    flag flag;
    level all;
    peer {
      peer-name;
    }
  }
```

Hierarchy Level [edit access]

Copyright © 2018, Juniper Networks, Inc.

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the Diameter base protocol parameters for subscriber-aware dynamic policycontrol, so that Diameter applications can connect to remote peers. The Diameter base protocol configuration includes configuration of the endpoint origin, the transport layer connection, the remote peers, and the network elements.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring Diameter Profiles on page 130

 Copyright © 2018, Juniper Networks, Inc.

diameter (TDF Gateway)

Syntax

```
diameter {
  network-element {
    element-name {
      session-pics {
        group {
          group-name {
            [session-pic interface-name];
          }
        }
      }
    }
  }
}
```

Hierarchy Level

```
[edit unified-edge tdf gateway-name]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure the Diameter protocol parameters associated with Diameter bindings for this TDF gateway.

NOTE: If you want to set up Diameter bindings for session PICs on the TDF gateway, contact Juniper Networks Professional Services for assistance.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Diameter Profiles on page 130

Copyright © 2018, Juniper Networks, Inc.

diameter-profile (PCEF Profile)

Syntax diameter-profile *gx-profile-name*;

Hierarchy Level [edit unified-edge pcef profiles *profile-name* dynamic-policy-control],
[edit services pcef profiles *profile-name* dynamic-policy-control]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef profiles *profile-name* dynamic-policy-control]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 18.2R1 on MX Series.

Description Specify the Diameter Gx profile to use for the PCEF dynamic policy control profile. A PCEF profile with dynamic policy control must reference a defined Diameter Gx profile.

If you are using Junos OS Broadband Subscriber Management, specify the Diameter Gx profile at the **[edit services pcef profiles *profile-name* dynamic-policy-control]** hierarchy level.

If you are using Junos OS Subscriber Aware, specify the Diameter Gx profile at the **[edit unified-edge pcef profiles *profile-name* dynamic-policy-control]** hierarchy level.

Options ***gx-profile-name***—Name of the Diameter Gx profile to use with this dynamic policy control profile.

Required Privilege Level For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.
For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- *Configuring a Policy and Charging Enforcement Function Profile for Subscriber Management*
- Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Dynamic Policies on page 80

 Copyright © 2018, Juniper Networks, Inc.

direction (Application Identification)

Syntax

```
direction (any | client-to-server | server-to-client);
```

Hierarchy Level

```
[edit services application-identification application application-name over member]
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the connection direction of the packets to which to apply pattern matching.

Options

any—Apply pattern matching to packets flowing in any direction.

client-to-server—Apply pattern matching only to packets flowing from client to server.

server-to-client—Apply pattern matching only to packets flowing from server to client.

Required Privilege Level

view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation

- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25

Copyright © 2018, Juniper Networks, Inc.

direction (Service Data Flow Filters)

Syntax

```
direction (uplink | downlink | both);
```

Hierarchy Level

[edit unified-edge pcef flow-descriptions *flow-identifier*],
[edit services pcef flow-descriptions *flow-identifier*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef flow-descriptions *flow-identifier*]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description

Specify the direction in which service data flow (SDF) filters will detect service flow IP packets.

If you are using Junos OS Subscriber Aware, specify the direction at the **[edit unified-edge pcef flow-descriptions *flow-identifier*]** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, specify the direction at the **[edit services pcef flow-descriptions *flow-identifier*]** hierarchy level.

Default

If you do not configure the **direction** statement, the default direction is **both**.

Options

uplink—SDF filters are applied in the uplink direction.

downlink—SDF filters are applied in the downlink direction.

both—SDF filters are applied in both the uplink and downlink directions.

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring Service Data Flow Filters on page 64
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- *Understanding Application-Aware Policy Control for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

disconnect-peer-timeout

Syntax disconnect-peer-timeout *seconds*;

Hierarchy Level [edit access diameter peer *peer-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the amount of time to wait in the Closing state while disconnecting this peer.

Options ***seconds***—Amount of time to wait in the Closing state.

Range: 1 through 65,535 seconds

Default: 10 seconds

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- diameter on page 273

Copyright © 2018, Juniper Networks, Inc.

domain (TDF Domain Selection)

Syntax domain *tdf-domain-name*;

Hierarchy Level [edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* then]

Release Information Statement introduced in Junos OS Release 16.1 on MX Series.

Description Specify the TDF domain to be selected when the criteria specified in the domain selection statement are matched.

NOTE: This statement is required even if you have not specified any match criteria.

Options ***tdf-domain-name***—Name of the TDF domain to use.

NOTE: The TDF domain must have been previously configured at the **[edit unified-edge gateways tdf *gateway-name* domains]** hierarchy level.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

domain-selection

Syntax

```
domain-selection {
  apply-groups [group-names];
  apply-groups-except [group-names];
  term term-name {
    from {
      3gpp-imsi {
        equals value;
        has-prefix value;
        has-suffix value;
        matches value;
      }
      attribute name {
        code numeric-code;
        vendor-id vendor-id;
        format {
          integer {
            apply-groups [group-names];
            apply-groups-except [group-names];
            equals {
              apply-groups [group-names];
              apply-groups-except [group-names];
              value;
            }
            greater-than value;
            less-than value;
          }
          string {
            apply-groups [group-names];
            apply-groups-except [group-names];
            equals {
              apply-groups [group-names];
              apply-groups-except [group-names];
              value;
            }
            has-prefix {
              apply-groups [group-names];
              apply-groups-except [group-names];
              value;
            }
            has-suffix {
              apply-groups [group-names];
              apply-groups-except [group-names];
              value;
            }
            matches {
              apply-groups [group-names];
              apply-groups-except [group-names];
              value;
            }
          }
          time {
```

Copyright © 2018, Juniper Networks, Inc.

```
            apply-groups [group-names];
            apply-groups-except [group-names];
            equals {
              apply-groups [group-names];
              apply-groups-except [group-names];
              value;
            }
            greater-than value;
            less-than value;
          }
          v4address {
            apply-groups [group-names];
            apply-groups-except [group-names];
            equals {
              apply-groups [group-names];
              apply-groups-except [group-names];
              value;
            }
          }
          v6address {
            apply-groups [group-names];
            apply-groups-except [group-names];
            equals {
              apply-groups [group-names];
              apply-groups-except [group-names];
              value;
            }
          }
          v6prefix {
            apply-groups [group-names];
            apply-groups-except [group-names];
            equals {
              apply-groups [group-names];
              apply-groups-except [group-names];
              value;
            }
          }
        }
      }
      called-station-id {
        equals value;
        matches value;
      }
      calling-station-id {
        equals value;
        matches value;
      }
      class {
        equals value;
        has-prefix value;
        has-suffix value;
        matches value;
      }
      client client-name;
      framed-ip-address {
```


Copyright © 2018, Juniper Networks, Inc.

```
        equals value;
      }
      framed-ipv6-prefix {
        equals value;
      }
      nas-ip-address {
        equals value;
      }
      snoop-segment snoop-segment-name;
      user-name {
        equals value;
        has-prefix value;
        has-suffix value;
        matches value;
      }
    }
    then {
      domain tdf-domain-name;
      pcef-profile pcef-profile-name;
    }
  }
}
```

Hierarchy Level [edit unified-edge gateways tdf *gateway-name*]

Release Information Statement introduced in Junos OS Release 16.1 on MX Series.

Copyright © 2018, Juniper Networks, Inc.

Description Specify the TDF domain to be used for an IP-based subscriber. You can configure multiple terms under **domain-selection**, and each term is applied in the order in which it is configured. You can specify multiple match conditions within a term and all of the conditions have to match. If the incoming RADIUS request from the subscriber matches the criteria in a term, then the TDF domain specified in the **then** statement of the term is used to create the TDF subscriber.

You can also specify a PCEF profile for an IP-based subscriber. This is required if the TDF domain selected for a subscriber does not specify a PCEF profile or you want to allow different members of the same TDF domain to have different PCEF profiles.

After a term matches and a TDF domain is selected, further terms are not evaluated if the PCEF profile is specified in either the **then** statement or in the selected TDF domain. If a PCEF profile is not specified in either the **then** statement or in the selected TDF domain, further terms are evaluated to find a PCEF profile for the subscriber.

If no TDF domain is selected for a subscriber, then a TDF subscriber session is not created.

NOTE: **The TDF domain must have been previously configured at the [edit unified-edge gateways tdf *gateway-name* domains] hierarchy level.**

The PCEF profile must have been previously configured at the [edit unified-edge pcef] hierarchy level.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92

Copyright © 2018, Juniper Networks, Inc.

domains

Syntax

```
domains domain-name {
  apply-groups [group-names];
  apply-groups-except [group-names];
  burst-size {
    apply-groups [group-names];
    apply-groups-except [group-names];
    downlink downlink-burst-size;
    uplink uplink-burst-size ;
  }
  ifl-subscriber [subscriber-name] {
    access-interfaces [interface-name];
    apply-groups [group-names];
    apply-groups-except [group-names];
  }
  ip-subscriber {
    access-interfaces [interface-name];
    apply-groups [group-names];
    apply-groups-except [group-names];
    default-local-policy {
      flow-action (drop | forward);
      maximum-bit-rate {
        uplink mbr-uplink-value ;
        downlink mbr-downlink-value;
      }
      burst-size {
        uplink uplink-burst-size;
        downlink downlink-burst-size;
      }
    }
    idle-timeout idle-timout;
    immediate-accounting-response (enabled | disabled);
    maximum-subscribers number;
    subscriber-address {
      apply-groups [group-names];
      apply-groups-except [group-names];
      inet {
        apply-groups [group-names];
        apply-groups-except [group-names];
        pool pool-name;
      }
      inet6 {
        apply-groups [group-names];
        apply-groups-except [group-names];
        pool pool-name;
      }
    }
    subscription-id {
      apply-groups [group-names];
      apply-groups-except [group-names];
      constant ;
      subscription-id-options {
```

Copyright © 2018, Juniper Networks, Inc.

```
        entry-name {
          id-components {
            use-imsi;
            use-msisdn;
            use-nai;
            use-username;
            use-realm;
            use-nas-port;
            use-nas-port-id;
          }
        }
      }
    }
  }
  maximum-bit-rate {
    apply-groups [group-names];
    apply-groups-except [group-names];
    downlink mbr-downlink-value;
    uplink mbr-uplink-value;
  }
  pcef-profile name;
  service-mode service-mode-options;
  subscriber-exclude-prefix {
    apply-groups [group-names];
    apply-groups-except [group-names];
    family {
      inet {
        apply-groups [group-names];
        apply-groups-except [group-names];
        network address net-mask;
      }
      inet6 {
        apply-groups [group-names];
        apply-groups-except [group-names];
        network address net-mask;
      }
    }
  }
  subscriber-type (ip | ifl);
  tdf-interface mif.number;
}
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name]
```

Release Information Statement introduced in Junos OS Release 16.1 on MX Series.

Description Configure a TDF domain, which specifies a set of properties for creating TDF subscriber sessions and for handling subscriber traffic.

Copyright © 2018, Juniper Networks, Inc.

Options

domain-name—Name of the TDF domain.

Range: 1 through 50 alphanumeric characters.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Configuring IFL-Based TDF Subscribers and Properties with a TDF Domain on page 117
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- Understanding the Definition of a Set of IFL-Based Subscriber Properties with a TDF Domain on page 96

Copyright © 2018, Juniper Networks, Inc.

dynamic-policy-control

Syntax

```
dynamic-policy-control {
  pcc-rules {
    [rule-name number];
  }
  pcc-rulebases {
    [rulebase-name];
  }
  diameter-profile gx-profile-name;
}
```

Hierarchy Level

[edit unified-edge pcef profiles *profile-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure the dynamic policy control for the PCC rules, PCC rulebases, or both in a PCEF profile. You can configure a maximum of 32 PCC rules in a PCEF profile. There is no limit to the number of PCC rulebases you can configure in a PCEF profile.

NOTE: If you configure the **dynamic-policy-control** statement for a PCEF profile, you cannot configure the **static-policy-control** statement in the same profile.

The remaining statements are explained separately.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Dynamic Policies on page 80
- Understanding How Subscriber-Aware Policy and Charging Control Rules Are Provisioned Dynamically by a PCRF on page 49

Copyright © 2018, Juniper Networks, Inc.

dynamic-requests-secret (RADIUS Server)

Syntax dynamic-requests-secret *password*;

Hierarchy Level [edit access radius servers *name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the secret password to be used for change of authorization requests from the RADIUS server.

Default Use the same password that is used for authentication requests.

Options ***password***—Password for dynamic requests.

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring RADIUS Servers on page 74
- Understanding Network Elements on page 57
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

encrypt (HTTP Header Enrichment)

Syntax

```
encrypt {
  hash algorithm;
  prefix hash-prefix;
}
```

Hierarchy Level

[edit services hcm tag-rule *rule-name* term *term-number* then tag *tag-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Specify the transform to be applied to the header for the HTTP header enrichment so that you can add subscriber attributes in a way that is obscured from the user.

NOTE: If you include this statement, then you also must configure **hash** and **prefix** statements.

Options

hash *algorithm*—Use the specified hashing algorithm. Currently, only **md5** is supported.

prefix *hash-prefix*—Use the specified prefix key (up to 63 alphanumeric characters). The prefix key is concatenated with the specified tag attribute and hashed. The resulting hash value is then inserted into the HTTP header.

Required Privilege Level

interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring HTTP Header Enrichment Overview on page 33
- Configuring Tag Rules on page 35
- Configuring HCM Profiles and Assigning Tag Rules on page 40
- Junos Web Aware HTTP Header Enrichment Overview on page 33.

Copyright © 2018, Juniper Networks, Inc.

equals

Syntax

```
equals {
  apply-groups [group-names];
  apply-groups-except [group-names];
  value;
}
```

Hierarchy Level

[edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* from called-station-id],
[edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* from calling-station-id],
[edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* from class],
[edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* from framed-ip-address],
[edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* from framed-ipv6-prefix],
[edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* from 3gpp-imsi],
[edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* from nas-ip-address],
[edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* from attribute *name* format integer],
[edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* from attribute *name* format string],
[edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* from attribute *name* format time],
[edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* from attribute *name* format v4address],
[edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* from attribute *name* format v6address],
[edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* from attribute *name* format v6prefix]

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the value that the RADIUS attribute must equal.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

Options

value—Value that the RADIUS attribute must equal.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Copyright © 2018, Juniper Networks, Inc.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

exclude (Diameter Gx Profiles)

Syntax

```
exclude {
  an-gw-address;
  default-eps-bearer-qos;
  packet-filter-information;
  packet-filter-operation;
  rat-type;
}
```

Hierarchy Level

[edit unified-edge diameter-profiles gx-profile *profile-name* attributes]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure the attribute-value pairs (AVPs) to be excluded from the credit control request (CCR) messages between the MX Series router and the policy and charging enforcement function (PCEF).

Options

an-gw-address—Exclude the AN-GW-Address AVP.

default-eps-bearer-qos—Exclude the Default-EPS-Bearer-QoS AVP.

packet-filter-information—Exclude the Packet-Filter-Information AVP.

packet-filter-operation—Exclude the Packet-Filter-Operation AVP.

rat-type—Exclude the RAT-Type AVP.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- gx-profile on page 316

Copyright © 2018, Juniper Networks, Inc.

external-assigned (Address Pools)

Syntax

```
external-assigned;
```

Hierarchy Level

[edit access address-assignment address-pools *name* family inet network *network-prefix*],
[edit access address-assignment address-pools *name* family inet6 network *network-prefix*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Assign addresses in network prefixes statically.

Required Privilege Level

access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Understanding Source IP Filtering with Address Pools in TDF Domains for IP-Based Subscribers on page 90
- Configuring Address Pools for Source-IP Filtering of IP-Based Subscribers on page 99

Copyright © 2018, Juniper Networks, Inc.

family (Address Pools)

Syntax

```
family (inet | inet6) {
  network {
    [network-prefix] {
      external-assigned;
    }
  }
}
```

Hierarchy Level

[edit access address-assignment address-pools *name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Specify the protocol family information for the address pool. Address pools must have either **inet** (IPv4) or **inet6** (IPv6) configured.

NOTE: A address pool can have either inet (IPv4) or inet6 (IPv6) configured, but not both.

Options

inet—IP version 4 (IPv4) suite.

inet6—IP version 6 (IPv6) suite.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Understanding Source IP Filtering with Address Pools in TDF Domains for IP-Based Subscribers on page 90
- Configuring Address Pools for Source-IP Filtering of IP-Based Subscribers on page 99

Copyright © 2018, Juniper Networks, Inc.

family (Exclude Prefix)

Syntax

```
family {
  inet {
    apply-groups [group-names];
    apply-groups-except [group-names];
    network address net-mask;
  }
  inet6 {
    apply-groups [group-names];
    apply-groups-except [group-names];
    network address net-mask;
  }
}
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domains domain-name
  subscriber-exclude-prefix]
```

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the IP version for the network prefix of source IP addresses for uplink packets and destination IP addresses for downlink packets that must not undergo TDF processing.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Configuring IFL-Based TDF Subscribers and Properties with a TDF Domain on page 117
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based and IFL-Based TDF Subscribers Overview on page 88
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

family (TDF Interface)

Syntax family *family-name*;

Hierarchy Level [edit interfaces mif unit *interface-unit-number*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the protocol family information for the TDF logical interface.

Options ***family-name***—Protocol family. The following options are supported:

- **inet**—IP version 4 suite.
- **inet6**—IP version 6 suite.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring a TDF Logical Interface on page 120

Copyright © 2018, Juniper Networks, Inc.

flow-action

Syntax

```
flow-action (drop | forward)
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domains domain-name ip-subscriber
  default-local-policy]
```

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the action to take on a subscriber's data packets entering the access interface of the TDF domain when a TDF IP-based subscriber session does not exist.

Options

drop—Drop the subscriber's packets.

forward—Forward the subscriber's packets.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

flow-descriptions

Syntax

```
flow-descriptions flow-identifier {
  direction (uplink | downlink | both);
  local-port-range {
    low lower-boundary high upper-boundary;
  }
  local-ports number;
  no-send-to-ue;
  protocol protocol-number;
  remote-address (ipv4-address ipv4-address | ipv6-address ipv6-address);
  remote-port-range {
    low lower-boundary high upper-boundary;
  }
  remote-ports number;
}
```

Hierarchy Level

[edit unified-edge pcef],
[edit services pcef]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description

Specify a service data flow (SDF) filter (flow identifier) that includes one or more filtering parameters (address, protocol, and port) to identify the subscriber traffic that you want the SDF filter to detect. SDF filters are specified in a PCC rule to identify the Layer 3 or Layer 4 IP packet flows that you want to receive a particular treatment.

NOTE: A PCC rule must include at least one SDF filter and can include a maximum of 15 SDF filters.

If you are using Junos OS Subscriber Aware, specify the name of the SDF filter at the **[edit unified-edge pcef]** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, specify the name of the SDF filter at the **[edit services pcef]** hierarchy level.

Options

flow-identifier—Name of the SDF filter.

Range: 1 through 63 characters.

The remaining statements are explained separately. Search for a statement in CLI Explorer or click a linked statement in the Syntax section for details.

Copyright © 2018, Juniper Networks, Inc.

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring Service Data Flow Filters on page 64
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- *Understanding Application-Aware Policy Control for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

flows (PCC Rules)

Syntax

```
flows ([flow-identifier] | any);
```

Hierarchy Level

```
[edit unified-edge pcef pcc-rules rule-name from],
[edit services pcef pcc-rules rule-name from]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef pcc-rules *rule-name* from]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description

Specify the service data flow (SDF) filters (flow identifiers) that define the match criteria for the policy and charging control (PCC) rule. You can configure a maximum of 15 SDF filters. You must include the **flows** statement in a PCC rule. If you do not want to filter subscriber traffic based on SDF filters, use the **any** option.

If you are using Junos OS Subscriber Aware, specify the name of the SDF filter at the **[edit unified-edge pcef pcc-rules *rule-name* from]** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, specify the name of the SDF filter at the **[edit services pcef pcc-rules *rule-name* from]** hierarchy level.

Options

flow-identifier—Name of an SDF filter that is used to detect IP packet flows. You can configure a maximum of 15 SDF filters. The referenced SDF filters must be configured.
Range: 1 through 63 characters.

any—All IP packet flows.

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring Policy and Charging Control Rules on page 70
- Configuring Service Data Flow Filters on page 64

Copyright © 2018, Juniper Networks, Inc.

format

Syntax

```
format {
  integer {
    apply-groups [group-names];
    apply-groups-except [group-names];
    equals {
      apply-groups [group-names];
      apply-groups-except [group-names];
      value;
    }
    greater-than value;
    less-than value;
  }
  string {
    apply-groups [group-names];
    apply-groups-except [group-names];
    equals {
      apply-groups [group-names];
      apply-groups-except [group-names];
      value;
    }
    has-prefix{
      apply-groups [group-names];
      apply-groups-except [group-names];
      value;
    }
    has-suffix {
      apply-groups [group-names];
      apply-groups-except [group-names];
      value;
    }
    matches {
      apply-groups [group-names];
      apply-groups-except [group-names];
      value;
    }
  }
  time {
    apply-groups [group-names];
    apply-groups-except [group-names];
    equals {
      apply-groups [group-names];
      apply-groups-except [group-names];
      value;
    }
    greater-than value;
    less-than value;
  }
  v4address {
    apply-groups [group-names];
    apply-groups-except [group-names];
    equals {
```

Copyright © 2018, Juniper Networks, Inc.

```
      apply-groups [group-names];
      apply-groups-except [group-names];
      value;
    }
  }
  v6address {
    apply-groups [group-names];
    apply-groups-except [group-names];
    equals {
      apply-groups [group-names];
      apply-groups-except [group-names];
      value;
    }
  }
  v6prefix {
    apply-groups [group-names];
    apply-groups-except [group-names];
    equals {
      apply-groups [group-names];
      apply-groups-except [group-names];
      value;
    }
  }
}
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  attribute name]
```

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the custom AVP attribute's format and value to match for the incoming RADIUS request from the IP-based subscriber.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

format (LRF Profile)

Syntax format ipfix;

Hierarchy Level [edit services lrf profile *profile-name* template *template-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure a format for the template. Only the IPFIX format is supported for this release.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring an LRF Profile for Subscribers on page 152
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152
- *Configuring Logging and Reporting for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

forwarding-class (PCC Action Profiles)

Syntax

```
forwarding-class class-name;
```

Hierarchy Level

```
[edit unified-edge pcef pcc-action-profiles profile-name],
[edit services pcef pcc-action-profiles profile-name]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef pcc-action-profiles *profile-name*]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description

Specify the forwarding class to which packets must be assigned.

If you are using Junos OS Subscriber Aware, specify the forwarding class at the **[edit unified-edge pcef pcc-action-profiles *profile-name*]** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, specify the forwarding class at the **[edit services pcef pcc-action-profiles *profile-name*]** hierarchy level.

Options

class-name—Name of the forwarding class.

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware on page 67
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- *Understanding Application-Aware Policy Control for Subscriber Management*
- *Configuring Policy and Charging Control Action Profiles for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

firmware-revision

Syntax firmware-revision *firmware-revision*;

Hierarchy Level [edit access diameter]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the firmware revision that is advertised in the Capabilities-Exchange-Request or Capabilities-Exchange-Answer message.

Options ***firmware-revision***—Number of the firmware revision that is the advertised value of the Firmware-Revision AVP.

Default: 0

Range: 0 through 4294967295

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- diameter on page 273

Copyright © 2018, Juniper Networks, Inc.

framed-ip-address

Syntax

```
framed-ip-address {
  equals value;
}
```

Hierarchy Level

[edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* from]

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the RADIUS AVP Framed-IP-Address (IPv4) for the incoming RADIUS request from the subscriber.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

The remaining statement is explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

framed-ipv6-prefix

Syntax

```
framed-ipv6-prefix {
  equals value;
}
```

Hierarchy Level

[edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* from]

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the RADIUS AVP Framed-IPv6-Prefix for the incoming RADIUS request from the subscriber.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

The remaining statement is explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

from (HTTP Header Enrichment)

Syntax

```
from {
  destination-address {
    (any-ipv4 | any-ipv4 except);
    (any-ipv6 | any-ipv6 except);
    (any-unicast | any-unicast except);
    (prefix | prefix except);
  }
  destination-address-range {
    high address low address <except>;
  }
  destination-port-range {
    high port-number low port-number;
  }
  destination-ports value;
  destination-prefix-list {
    (prefix-name | prefix-name except);
  }
}
```

Hierarchy Level

```
[edit services hcm tag-rule rule-name term term-number]
```

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the match criteria for the term in the tag rule. If all the conditions specified in the match criteria are met, then the HTTP header enrichment actions specified in the **then** statement are applied.

If you want the HTTP header enrichment actions specified in the **then** statement to be applied to all HTTP requests, do not include any matching conditions with the **from** statement.

NOTE: You must include a **from** statement in a tag rule.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring HTTP Header Enrichment Overview on page 33
- hcm on page 319

Copyright © 2018, Juniper Networks, Inc.

from (PCC Rules)

Syntax

```
from {
  <application-groups [application-group-name]>;
  <applications [application-name]>;
  flows ([flow-identifier] | any);
}
```

Hierarchy Level

[edit unified-edge pcef pcc-rules *rule-name*],
[edit services pcef pcc-rules *rule-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef pcc-rules *rule-name*]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description

Specify the match criteria for the policy and charging control (PCC) rules. Any referenced SDF filter, application, or application group in the **from** statement must be configured.

If you are using Junos OS Subscriber Aware, specify the match criteria at the **[edit unified-edge pcef pcc-rules *rule-name*]** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, specify the match criteria at the **[edit services pcef pcc-rules *rule-name*]** hierarchy level.

NOTE: You must include the **flows** statement. If you do not want to filter subscriber traffic based on service data flow (SDF) filters, use **flows any**.

The remaining statements are explained separately. Search for a statement in CLI Explorer or click a linked statement in the Syntax section for details.

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring Policy and Charging Control Rules on page 70

from (TDF Domain Selection)

Syntax

```
from {
  apply-groups [group-names];
  apply-groups-except [group-names];
  3gpp-imsi {
    equals value;
    has-prefix value;
    has-suffix value;
    matches value;
  }
  attribute name {
    code numeric-code;
    vendor-id vendor-id;
    format {
      integer {
        apply-groups [group-names];
        apply-groups-except [group-names];
        equals {
          apply-groups [group-names];
          apply-groups-except [group-names];
          value;
        }
        greater-than value;
        less-than value;
      }
      string {
        apply-groups [group-names];
        apply-groups-except [group-names];
        equals {
          apply-groups [group-names];
          apply-groups-except [group-names];
          value;
        }
        has-prefix{
          apply-groups [group-names];
          apply-groups-except [group-names];
          value;
        }
        has-suffix {
          apply-groups [group-names];
          apply-groups-except [group-names];
          value;
        }
        matches {
          apply-groups [group-names];
          apply-groups-except [group-names];
          value;
        }
      }
      time {
        apply-groups [group-names];
        apply-groups-except [group-names];
```


Copyright © 2018, Juniper Networks, Inc.

```
        equals {
          apply-groups [group-names];
          apply-groups-except [group-names];
          value;
        }
        greater-than value;
        less-than value;
      }
      v4address {
        apply-groups [group-names];
        apply-groups-except [group-names];
        equals {
          apply-groups [group-names];
          apply-groups-except [group-names];
          value;
        }
      }
      v6address {
        apply-groups [group-names];
        apply-groups-except [group-names];
        equals {
          apply-groups [group-names];
          apply-groups-except [group-names];
          value;
        }
      }
      v6prefix {
        apply-groups [group-names];
        apply-groups-except [group-names];
        equals {
          apply-groups [group-names];
          apply-groups-except [group-names];
          value;
        }
      }
    }
  }
  called-station-id {
    equals value;
    matches value;
  }
  calling-station-id {
    equals value;
    matches value;
  }
  class {
    equals value;
    has-prefix value;
    has-suffix value;
    matches value;
  }
  client client-name;
  framed-ip-address {
    equals value;
  }
```

```
framed-ipv6-prefix {
  equals value;
}
nas-ip-address {
  equals value;
}
snoop-segment snoop-segment-name;
user-name {
  equals value;
  has-prefix value;
  has-suffix value;
  matches value;
 }
}
```

Hierarchy Level [edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name*]

Release Information Statement introduced in Junos OS Release 16.1 on MX Series.

Description Specify the match criteria for the TDF domain selection or PCEF profile selection term.

NOTE: For any term, the subscriber must match all the match conditions specified in a from statement. If you do not configure the from statement, then all subscribers are considered a match.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

function (Diameter Network Element)

Syntax function *function-name*;

Hierarchy Level [edit access diameter network-element *element-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the function associated with a Diameter network element.

Options ***function-name***—Function associated with the network element.

Functions currently supported:

- Policy charging and control (**pcc-gx**).
- Diameter credit-control application are the functions currently supported.

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- diameter on page 273

Copyright © 2018, Juniper Networks, Inc.

gate-status

Syntax

```
gate-status (uplink | downlink | uplink-downlink | disable-both);
```

Hierarchy Level

[edit unified-edge pcef pcc-action-profiles *profile-name*],
[edit services pcef pcc-action-profiles *profile-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef pcc-action-profiles *profile-name*]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description

Configure the gate status in a PCC action profile to enable or disable the forwarding of service flow packets. The gate status determines whether the uplink and downlink gates are opened or closed.

If you are using Junos OS Subscriber Aware, configure the gate status at the **[edit unified-edge pcef pcc-action-profiles *profile-name*]** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, configure the gate status at the **[edit services pcef pcc-action-profiles *profile-name*]** hierarchy level.

Default

By default, if this statement is not configured, forwarding of service data flow packets is enabled in both the uplink and downlink directions.

Options

disable-both—Disable forwarding of service data flow packets in the uplink and downlink directions.

downlink—Enable forwarding of service data flow packets in the downlink direction.

uplink-downlink—Enable forwarding of service data flow packets in the uplink and downlink directions.

uplink—Enable forwarding of service data flow packets in the uplink direction.

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware on page 67

Copyright © 2018, Juniper Networks, Inc.

- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- *Configuring Policy and Charging Control Action Profiles for Subscriber Management*
- *Understanding Application-Aware Policy Control for Subscriber Management*

greater-than

Syntax

```
greater-than value;
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  attribute name format integer],
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  attribute name format time]
```

Release Information Statement introduced in Junos OS Release 16.1 on MX Series.

Description Specify a value for the custom AVP attribute above which the incoming RADIUS request from the subscriber must match.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

Options ***value***—Value that the attribute must be greater than.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

gx-profile

Syntax

```
gx-profile profile-name {
  <attributes> {
    exclude {
      an-gw-address;
      default-eps-bearer-qos;
      packet-filter-information;
      packet-filter-operation;
      rat-type;
    }
    include {
      gx-capability-list;
      rule-suggestion;
    }
  }
  <request-timeout seconds>;
  targets {
    target-name {
      <destination-host hostname>;
      destination-realm realm-name;
      network-element element-name;
      priority priority-value;
    }
  }
}
```

Hierarchy Level

```
[edit unified-edge diameter-profiles]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure the Diameter profile used for Gx applications.

Options

profile-name—Name of the Diameter profile.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Diameter Profiles Overview on page 127

Copyright © 2018, Juniper Networks, Inc.

has-prefix

Syntax

```
has-prefix {
  apply-groups [group-names];
  apply-groups-except [group-names];
  value;
}
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  class],
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  3gpp-imsi],
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  attribute name format string]
```

Release Information Statement introduced in Junos OS Release 16.1 on MX Series.

Description Specify the prefix that the attribute must have.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

Options *value*—Prefix string.

Range: 1 through 254 alphanumeric characters.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

has-suffix

Syntax

```
has-suffix {
  apply-groups [group-names];
  apply-groups-except [group-names];
  value;
}
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  class],
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  3gpp-imsi],
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  attribute name format string]
```

Release Information Statement introduced in Junos OS Release 16.1 on MX Series.

Description Specify the suffix that the attribute must have.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

Options ***value***—Suffix string.

Range: 1 through 254 alphanumeric characters.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

hcm (HTTP Header Enrichment)

Syntax

```
hcm {
  tag-attribute [tag-attr-name];
  tag-rule rule-name {
    term term-number {
      from {
        destination-address {
          (any-ipv4 | any-ipv4 except);
          (any-ipv6 | any-ipv6 except);
          (any-unicast | any-unicast except);
          (prefix | prefix except);
        }
        destination-address-range {
          high address low address <except>;
        }
        destination-port-range {
          high port-number low port-number;
        }
        destination-ports value;
        destination-prefix-list {
          (prefix-name | prefix-name except);
        }
      }
      then {
        count;
        tag tag-name {
          encrypt {
            hash algorithm;
            prefix hash-prefix;
          }
          ipv4-mask ipv4-mask;
          ipv6-mask ipv6-mask;
          ipv4-or-value ipv4-or-value;
          ipv6-or-value ipv6-or-value;
          tag-attribute tag-attr-name;
          tag-header header;
          tag-separator separator;
        }
      }
    }
  }
  tag-rule-set rule-set-name {
    [rule rule-name];
  }
  profile profile-name {
    tag rule rule-name;
  }
}
```

Hierarchy Level

```
[edit services]
```

Copyright © 2018, Juniper Networks, Inc.

Release Information Statement introduced in Junos OS Release 16.1 on MX Series.

Description Configure the parameters required to support subscriber-aware HTTP header enrichment.

You can add content to the HTTP headers sent back and forth as part of the client-server exchange for subscribers accessing Web-based services. You configure HTTP header enrichment as a service for a subscriber.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation
- Configuring HTTP Header Enrichment Overview on page 33

hcm-profile (HTTP Header Enrichment)

Syntax
```
hcm-profile hcm-profile-name;
```

Hierarchy Level
```
[edit services service-set]
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the HTTP header enrichment profile that was configured at the **[edit services hcm]** hierarchy level. This placeholder profile has no configuration options, but it must be specified to enable HTTP header enrichment functionality on the services plane.

Options ***hcm-profile-name***—Name of the HCM profile.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation
- Configuring HTTP Header Enrichment Overview on page 33
- hcm on page 319

Copyright © 2018, Juniper Networks, Inc.

hcm-profile (PCC Action Profiles)

Syntax hcm-profile *hcm-profile-name*;

Hierarchy Level [edit unified-edge pcef pcc-action-profiles *profile-name*]

Release Information Statement introduced in Junos OS Release 16.1 on MX Series.

Description Specify the HCM profile that you want a PCC action profile to use for determining which HTTP header enrichment rules to apply.

NOTE: This PCC action profile can be used in a PCC rule that only includes **applications** or **application-groups** statements in the **from** statement, and these statements must identify HTTP-based applications. The HCM profile must have been previously configured at the **[edit services hcm]** hierarchy level.

Options ***hcm-profile-name***—Name of the HCM profile.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware on page 67
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47

Copyright © 2018, Juniper Networks, Inc.

host (Diameter Origin)

Syntax host *hostname*;

Hierarchy Level [edit access diameter origin]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the name of the host that originates the Diameter message.

Options ***hostname***—Name of the message origin host. Supplied as the value of the Origin-Host AVP for all messages sent by the Diameter instance.

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation
- diameter on page 273

http-log-multiple-transactions (LRF Profile)

Syntax http-log-multiple-transactions;

Hierarchy Level [edit services lrf profile *profile-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure HTTP transaction logging to generate and send HTTP metadata for each transaction of a data session. This option is only relevant if the template specified in an LRF rule includes **http** in the **template-type**.

By default, HTTP transaction logging is disabled, and the HTTP transaction records for a TCP session are sent together as one group of records.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation
- Configuring an LRF Profile for Subscribers on page 152
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152
- *Configuring Logging and Reporting for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

icmp-mapping (Application Identification)

Syntax

```
icmp-mapping {
  code icmp-code;
  order order;
  order-priority (high | low);
  type icmp-type;
}
```

Hierarchy Level

[edit services application-identification application *application-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Match Internet Control Message Protocol (ICMP) messages identified by unique code and type. This classification is intended to identify and differentiate various types of ICMP messages.

The remaining statements are explained separately. Search for a statement in CLI Explorer or click a linked statement in the Syntax section for details.

Required Privilege Level

view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation

- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25

Copyright © 2018, Juniper Networks, Inc.

id-components

Syntax

```
id-components {
  use-class;
  use-imsi;
  use-msisdn;
  use-nai;
  use-nas-port;
  use-nas-port-id;
  use-realm;
  use-username;
}
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domains domain-name ip-subscriber
  subscription-id subscription-id-options entry-name]
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify a method for constructing the Subscription-Id for the Diameter credit control request (CCR) message that is sent from the TDF to the PCRF for IP-based subscribers belonging to the TDF domain. You may specify more than one option, and the order of preference matches the order in which the options appear.

Options

use-class—Subscription-Id-Type is configurable and the Subscription-Id-Data is the entire Class attribute value by default. You can configure a regular expression to parse the Class attribute contents, specify characters to insert between the resulting regular expression groups, and specify the subscription ID type with the **use-class** options under the **[edit unified-edge gateways tdf *gateway-name* domains *domain-name* subscription-id]** hierarchy.

use-imsi—Subscription-Id-Type is END_USER_IMSI and the Subscription-Id-Data is the 3GPP-IMSI.

use-msisdn—Subscription-Id-Type is END_USER_E164 and the Subscription-Id-Data is the Calling-Station-Id.

use-nai—Subscription-Id-Type is END_USER_NAI and the Subscription-Id-Data is the entire User-Name.

use-nas-port—Subscription-Id-Type is END_USER_PRIVATE and the Subscription-Id-Data is the NAS-Port.

use-nas-port-id—Subscription-Id-Type is END_USER_PRIVATE and the Subscription-Id-Data is the NAS-Port-Id.

use-realm—Subscription-Id-Type is END_USER_PRIVATE and the Subscription-Id-Data is the realm portion of User-Name in NAI format.

Copyright © 2018, Juniper Networks, Inc.

use-username—Subscription-Id-Type is END_USER_PRIVATE and the Subscription-Id-Data is the user name portion of User-Name in NAI format.

Required Privilege Level
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation
- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89

idle-timeout

Syntax
```
idle-timeout idle-timeout;
```

Hierarchy Level
```
[edit unified-edge gateways tdf gateway-name domains domain-name ip-subscriber]
```

Release Information
Statement introduced in Junos OS Release 16.1 on MX Series.

Description
Configure the idle timeout for the TDF IP-based subscriber session. The idle timeout is the duration that the subscriber session waits to receive a data packet before timing out. After the idle timeout expires, the TDF takes down the session. Setting the idle timeout ensures that if no data is being sent for the duration specified, then the session can be taken down, and the TDF's resources can be freed.

Options
idle-timeout—Number of minutes after which the TDF subscriber session times out.
Range: 0 through 300.

Required Privilege Level
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation
- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

ifl-subscriber

Syntax

```
ifl-subscriber [subscriber-name] {
  access-interfaces [interface-name];
  apply-groups [group-names];
  apply-groups-except [group-names];
}
```

Hierarchy Level

[edit unified-edge gateways tdf *gateway-name* domains *domain-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Specify the name of the IFL-based subscriber for traffic that is carried on a particular interface or interfaces. You can configure up to 32 IFL-based subscribers in a TDF domain.

To configure a subscriber name, you must have set the **subscriber-type** to **ifl** at the **[edit unified-edge gateway tdf *gateway-name* domains *domain-name*]** hierarchy.

Options

subscriber-name—Name of the subscriber. You can configure up to 32 IFL-based subscribers in a TDF domain.

Range: Up to 63 bytes.

The remaining statements are described separately.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring IFL-Based TDF Subscribers and Properties with a TDF Domain on page 117
- Understanding the Definition of a Set of IFL-Based Subscriber Properties with a TDF Domain on page 96

Copyright © 2018, Juniper Networks, Inc.

immediate-accounting-response

Syntax immediate-accounting-response (enabled | disabled);

Hierarchy Level [edit unified-edge gateways tdf *gateway-name* domains *domain-name* ip-subscriber]

Release Information Statement introduced in Junos OS Release 16.1 on MX Series.

Description Enable or disable the sending of an immediate RADIUS response message to the accounting start message received from a GGSN, PGW, or BNG RADIUS client.

Default If you do not specify an option, **disabled** is the default.

Options **enabled**—Enable immediate response.

disabled—Disable immediate response. The response is sent after TDF subscriber creation is complete.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

include (Diameter Gx Profiles)

Syntax

```
include {
  gx-capability-list;
  rule-suggestion;
}
```

Hierarchy Level

[edit unified-edge diameter-profiles gx-profile *profile-name* attributes]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure the attribute-value pairs (AVPs) to be included in the credit control request (CCR) messages between the MX Series router and the policy and charging enforcement function (PCEF).

Options

gx-capability-list—Include the Gx-Capability list AVP.

rule-suggestion—Include the Rule-suggestion AVP.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- gx-profile on page 316

Copyright © 2018, Juniper Networks, Inc.

incoming-queue

Syntax

```
incoming-queue {
  size size;
}
```

Hierarchy Level

[edit access diameter peer *peer-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure the incoming queue properties of this peer.

Options

size *size*—Size of the queue. The default is 6000.

Range: 1 through 65,535 packets

Required Privilege Level

access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- diameter on page 273

Copyright © 2018, Juniper Networks, Inc.

inet (TDF Subscriber Address)

Syntax

```
inet {
  apply-groups [group-names];
  apply-groups-except [group-names];
  pool pool-name;
}
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domains domain-name ip-subscriber
  subscriber-address]
```

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify IP version 4 (IPv4) for the address pool that contains the source IP addresses for IP-based subscriber packets that undergo TDF processing.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

inet (TDF Subscriber Exclude Prefix)

Syntax

```
inet {
  network address mask;
}
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domains domain-name
  subscriber-exclude-prefix family]
```

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify IP version 4 (IPv4) for the network prefix of source IP addresses for uplink packets and destination IP addresses for downlink packets that do not undergo TDF processing.

The remaining statement is explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Configuring IFL-Based TDF Subscribers and Properties with a TDF Domain on page 117
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based and IFL-Based TDF Subscribers Overview on page 88
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

inet6 (TDF Subscriber Address)

Syntax

```
inet6 {
  apply-groups [group-names];
  apply-groups-except [group-names];
  pool pool-name;
}
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domains domain-name ip-subscriber
  subscriber-address]
```

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify IP version 6 (IPv6) for the address pool that contains the source IP addresses for IP-based subscriber packets that undergo TDF processing.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

inet6 (TDF Subscriber Exclude Prefix)

Syntax

```
inet6 {
  network address mask;
}
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domains domain-name
  subscriber-exclude-prefix family]
```

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify IP version 6 (IPv6) for the network prefix of source IP addresses for uplink packets and destination IP addresses for downlink packets that do not undergo TDF processing.

The remaining statement is explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Configuring IFL-Based TDF Subscribers and Properties with a TDF Domain on page 117
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based and IFL-Based TDF Subscribers Overview on page 88
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

integer

Syntax

```
integer {
  apply-groups [group-names];
  apply-groups-except [group-names];
  equals value;
  greater-than value;
  less-than value;
}
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  attribute name format]
```

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the custom AVP attribute's format as an integer and the value to match for the incoming RADIUS request from the IP-based subscriber.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

interface (Services PIC)

Syntax [interface *interface-name*];

Hierarchy Level [edit unified-edge gateways tdf *gateway-name* system service-pics]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify one or more of the MS-MPC service interfaces that represent the service PICs used for anchoring subscriber-aware services in the MX Series router. The following conditions are applicable to the services PIC interfaces configured here:

- If an aggregated multiservices interface (ams) is specified in this statement, the ams must already be defined at the **[edit interfaces]** hierarchy level.
- The PIC must have the **jservices-hcm**, **jservices-mss**, **jservices-jdpi**, **jservices-pcef**, and **jservices-crypto-base** packages configured at the **[edit chassis fpc *slot-number* pic *pic-number* adaptive-services service-package extension-provider]** hierarchy level.
- The appropriate services group configuration must be applied to the PIC:
  - For each service PIC that requires application identification but not HTTP header enrichment, apply the **tdf-services-xlp-dpi** group.
  - For each service PIC that requires both application identification and HTTP header enrichment, configure the **tdf-services-xlp-dpi-with-hcm** group.
- If an MS-MPC service interface is a member of an AMS, then that member interface cannot be specified here. For example, if mams-2/0/0 is a member interface of ams0, then ms-2/0/0/ cannot be directly specified here.

NOTE: If an AMS (for example ams0) is used for the services PIC, then load balancing is performed to distribute subscriber-aware services among the member interfaces. Otherwise, load balancing is not performed.

Options ***interface-name***—Name of the interface representing the services PIC.

Syntax: The interface must be a valid multiservices interface (ams*n* or ms-*a*/*b*/0, where *n* is the ams number, *a* is the Flexible PIC Concentrator [FPC] slot number, and *b* is the PIC slot number); for example, ams0 or ms-1/0/0.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Copyright © 2018, Juniper Networks, Inc.

Related Documentation

- Configuring Service PICs on page 18
- TDF Gateway Service PICs and Session PICs for Subscriber-Aware Traffic Treatment on page 11

interface (Session PICs)

Syntax

```
[interface interface-name];
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name system session-pics]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Specify one or more of the MS-MPC service interfaces that represent the session PICs used for the control plane in the TDF gateway. The following conditions are applicable to the session PIC interfaces configured here:

- If an aggregated multiservices interface (ams) is specified in this statement, the ams must already be defined at the **[edit interfaces]** hierarchy level.
- The **tdf-session-xlp** group configuration must be applied to the PIC.
- The session PIC must have the **jservices-mobile** package configured at the **[edit chassis fpc slot-number pic pic-number adaptive-services service-package extension-provider]** hierarchy level.
- If a session PIC interface is a member of an AMS, then that member interface cannot be specified here. For example, if mams-2/0/0 is a member interface of ams0, then ms-2/0/0/ cannot be directly specified here.

Options

interface-name—Name of the interface representing the services PIC.

Syntax: The interface must be a valid multiservices interface (ams*n* or ms-*a*/*b*/0, where *n* is the ams number, *a* is the Flexible PIC Concentrator [FPC] slot number, and *b* is the PIC slot number); for example, ams0 or ms-1/0/0.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Session PICs on page 19
- TDF Gateway Service PICs and Session PICs for Subscriber-Aware Traffic Treatment on page 11

Copyright © 2018, Juniper Networks, Inc.

interface-service (Services Interfaces)

Syntax

```
interface-service {
  load-balancing-options {
    hash-keys {
      egress-key (destination-ip | source-ip);
      ingress-key (destination-ip | source-ip);
    }
  }
  service-interface name;
}
```

Hierarchy Level

```
[edit services service-set service-set-name]
```

Release Information Statement introduced before Junos OS Release 7.4.

Description Specify the device name for the interface service Physical Interface Card (PIC).

Options **service-interface *name***—Name of the service device associated with the interface-wide service set.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- *Configuring Service Sets to be Applied to Services Interfaces*

Copyright © 2018, Juniper Networks, Inc.

ip-protocol-mapping (Application Identification)

Syntax

```
ip-protocol-mapping {
  order order;
  order-priority (high | low);
  protocol (http | ssl | tcp | udp)
}
```

Hierarchy Level

[edit services application-identification application *application-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

For IP traffic, identify an application by matching the IP protocol. This parameter is used to identify an application based on IP and is intended only for IP traffic.

Options

protocol-number—Industry-standard numeric protocol value.

Range: 0 through 254

You can find a complete list of industry standard protocol numbers at the IANA website.

The remaining statements are explained separately. Search for a statement in CLI Explorer or click a linked statement in the Syntax section for details.

Required Privilege Level

view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation

- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25

Copyright © 2018, Juniper Networks, Inc.

ip-subscriber

Syntax

```
ip-subscriber {
  access-interfaces interface-name [interface-name];
  apply-groups [group-names];
  apply-groups-except [group-names];
  default-local-policy {
    flow-action (drop | forward);
    maximum-bit-rate {
      uplink mbr-uplink-value ;
      downlink mbr-downlink-value;
    }
    burst-size {
      uplink uplink-burst-size;
      downlink downlink-burst-size;
    }
  }
  idle-timeout idle-timout;
  immediate-accounting-response (enabled | disabled);
  maximum-subscribers number;
  subscriber-address {
    apply-groups [group-names];
    apply-groups-except [group-names];
    inet {
      apply-groups [group-names];
      apply-groups-except [group-names];
      pool pool-name;
    }
    inet6 {
      apply-groups [group-names];
      apply-groups-except [group-names];
      pool pool-name;
    }
  }
  subscription-id {
    apply-groups [group-names];
    apply-groups-except [group-names];
    constant ;
    subscription-id-options {
      entry-name {
        id-components {
          use-imsi;
          use-msisdn;
          use-nai;
          use-username;
          use-realm;
          use-nas-port;
          use-nas-port-id;
        }
      }
    }
  }
}
```

Copyright © 2018, Juniper Networks, Inc.

Hierarchy Level [edit unified-edge gateways tdf *gateway-name* domains *domain-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure TDF domain features that are unique to IP-based subscribers.

The remaining statements are described separately.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation
- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based Subscriber Setup Overview on page 88

ipv4-address (Steering Path)

Syntax ipv4-address *ipv4-address*;

Hierarchy Level [edit unified-edge pcef pcc-action-profiles *profile-name* steering path]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the IPv4 address of a third-party server to which the PCC action profile steers HTTP traffic for applying services. If you configure this, the PCC action profile can only be used in PCC rules that match only HTTP-based applications and all flows.

Options **ipv4-address *ipv4-address*** —Use the specified IPv4 address of the server.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation
- Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware on page 67
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47

Copyright © 2018, Juniper Networks, Inc.

ipv4-mask (HTTP Header Enrichment)

Syntax ipv4-mask *ipv4-mask*;

Hierarchy Level [edit services hcm tag-rule *rule-name* term *term-number* then tag *tag-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the IPv4 mask to identify a byte of the IPv4 subscriber address that you want to modify in the HTTP header. You must also set the **ipv4-or-value** statement at the **[edit services hcm tag-rule *rule-name* term *term-number* then tag *tag-name*]** hierarchy level to specify the new value you want to put in the byte.

Options ***ipv4-mask***—IPv4 mask. Specify **255** in the byte you want to modify and specify **0** in the bytes that you *do not* want to modify.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- ipv4-or-value on page 342
- Configuring HTTP Header Enrichment Overview on page 33
- Configuring Tag Rules on page 35
- Configuring HCM Profiles and Assigning Tag Rules on page 40
- Junos Web Aware HTTP Header Enrichment Overview on page 33.

Copyright © 2018, Juniper Networks, Inc.

ipv4-or-value (HTTP Header Enrichment)

Syntax ipv4-or-value *ipv4-or-value*;

Hierarchy Level [edit services hcm tag-rule *rule-name* term *term-number* then tag *tag-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the new IPv4 value for the byte you want to modify in the IPv4 subscriber address in the HTTP header. You must also set the **ipv4-mask** statement at the **[edit services hcm tag-rule *rule-name* term *term-number* then tag *tag-name*]** hierarchy level to clear the existing byte value.

Options ***ipv4-or-value***—IPv4 value. Specify the new value in the byte you are modifying and specify 0 in all other bytes.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- ipv4-mask on page 341
- Configuring HTTP Header Enrichment Overview on page 33
- Configuring Tag Rules on page 35
- Configuring HCM Profiles and Assigning Tag Rules on page 40
- Junos Web Aware HTTP Header Enrichment Overview on page 33.

Copyright © 2018, Juniper Networks, Inc.

ipv6-address (Steering Path)

Syntax ipv6-address *ipv6-address*;

Hierarchy Level [edit unified-edge pcef pcc-action-profiles *profile-name* steering path]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the IPv6 address of a third-party server to which the PCC action profile steers HTTP traffic for applying services. If you configure this, the PCC action profile can only be used in PCC rules that match only HTTP-based applications and all flows.

Options **ipv6-address *ipv6-address*** —Use the specified IPv6 address of the server.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware on page 67
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47

Copyright © 2018, Juniper Networks, Inc.

ipv6-mask (HTTP Header Enrichment)

Syntax ipv6-mask *ipv6-mask*;

Hierarchy Level [edit services hcm tag-rule *rule-name* term *term-number* then tag *tag-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the IPv6 mask to identify a byte of the IPv6 subscriber address that you want to modify in the HTTP header. You must also set the **ipv6-or-value** statement at the **[edit services hcm tag-rule *rule-name* term *term-number* then tag *tag-name*]** hierarchy level to specify the new value you want to put in the byte.

Options ***ipv6-mask***—IPv6 mask. Specify **ff** in the byte you want to modify and specify **0** in the bytes that you *do not* want to modify.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- ipv6-or-value on page 345
- Configuring HTTP Header Enrichment Overview on page 33
- Configuring Tag Rules on page 35
- Configuring HCM Profiles and Assigning Tag Rules on page 40
- Junos Web Aware HTTP Header Enrichment Overview on page 33.

Copyright © 2018, Juniper Networks, Inc.

ipv6-or-value (HTTP Header Enrichment)

Syntax ipv6-or-value *ipv6-or-value*;

Hierarchy Level [edit services hcm tag-rule *rule-name* term *term-number* then tag *tag-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the new IPv6 value for the byte you want to modify in the IPv6 subscriber address in the HTTP header. You must also set the **ipv6-mask** statement at the **[edit services hcm tag-rule *rule-name* term *term-number* then tag *tag-name*]** hierarchy level to clear the existing byte value.

Options ***ipv6-or-value***—IPv6 value. Specify the new value in the byte you are modifying and specify 0 in all other bytes.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- ipv6-mask on page 344
- Configuring HTTP Header Enrichment Overview on page 33
- Configuring Tag Rules on page 35
- Configuring HCM Profiles and Assigning Tag Rules on page 40
- Junos Web Aware HTTP Header Enrichment Overview on page 33.

Copyright © 2018, Juniper Networks, Inc.

keep-existing-steering

Syntax keep-existing-steering;

Hierarchy Level [edit unified-edge pcef pcc-action-profiles *profile-name* steering]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify that steering attributes configured in a PCC action profile that a PCC rule applies to a data flow session when it begins will continue to be applied to the data flow when the PCC rule match conditions are modified, deleted, or added to.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware on page 67
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47

Copyright © 2018, Juniper Networks, Inc.

less-than

Syntax

```
less-than value;
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  attribute name format integer],
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  attribute name format time]
```

Release Information Statement introduced in Junos OS Release 16.1 on MX Series.

Description Specify a value for the custom AVP attribute below which the incoming RADIUS request from the subscriber must match.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

Options ***value***—Value that the attribute must be less than.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

local-port-range

Syntax

```
local-port-range {
  low low-value;
  high high-value;
}
```

Hierarchy Level

[edit unified-edge pcef flow-descriptions *flow-identifier*],
[edit services pcef flow-descriptions *flow-identifier*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef flow-descriptions *flow-identifier*]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description

Specify the port range to identify the subscriber traffic that you want the service data flow (SDF) filter to detect.

NOTE: You can specify either **local-port-range** or a list of ports with **local-ports**, but not both.

If you are using Junos OS Subscriber Aware, specify the port range at the **[edit unified-edge pcef flow-descriptions *flow-identifier*]** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, specify the port range at the **[edit services pcef flow-descriptions *flow-identifier*]** hierarchy level.

Default

If the **local-port-range** statement is not configured, the default is any range of local ports.

Options

low-value— Lower boundary for the port range.

Range: 1 through 65,535

high-value — Upper boundary for the port range.

Range: 1 through 65,535

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Copyright © 2018, Juniper Networks, Inc.

Related Documentation

- Configuring Service Data Flow Filters on page 64
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- *Understanding Application-Aware Policy Control for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

local-ports

Syntax local-ports [*number*];

Hierarchy Level [edit unified-edge pcef flow-description *flow-identifier*],
[edit services pcef flow-description *flow-identifier*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef flow-description *flow-identifier*]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description Specify a port number or list of port numbers to identify the subscriber traffic that you want the service data flow (SDF) filter to detect.

NOTE: You can specify either a list of ports or a port range, but not both.

If you are using Junos OS Subscriber Aware, specify the port numbers at the **[edit unified-edge pcef flow-description *flow-identifier*]** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, specify the port numbers at the **[edit services pcef flow-description *flow-identifier*]** hierarchy level.

Default If the **local-ports** statement is not configured, the default is any local ports.

Options ***number***—Number of a port or list of port numbers. You can specify a maximum of three port numbers (separated by a space) in a list.

Range: 1 through 65,535

Required Privilege Level For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring Service Data Flow Filters on page 64
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- *Understanding Application-Aware Policy Control for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

logging-rule (PCC Action Profile)

Syntax

```
logging-rule lrf-rule-name;
```

Hierarchy Level

```
[edit unified-edge pcef pcc-action-profiles profile-name],
[edit services pcef pcc-action-profiles profile-name]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef pcc-action-profiles *profile-name*]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description

Assign the LRF rule to the PCC action profile of a static PCC rule. When the matching conditions in the PCC rule are met, the LRF rule is activated.

If you are using Junos OS Subscriber Aware, specify the name of the LRF rule at the **[edit unified-edge pcef pcc-action-profiles *profile-name*]** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, specify the name of the LRF rule at the **[edit services pcef pcc-action-profiles *profile-name*]** hierarchy level.

Options

lrf-rule-name—LRF rule name. The referenced LRF rule must be configured in an LRF profile.

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring the Activation of an LRF Rule by a PCC Rule on page 160
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152
- *Configuring Logging and Reporting for Subscriber Management*
- Configuring an LRF Profile for Subscribers on page 152

Copyright © 2018, Juniper Networks, Inc.

lrf-profile (Service Set)

Syntax lrf-profile *profile-name*;

Hierarchy Level [edit services service-set *service-set-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Assign the LRF profile to the service set that is that is configured for application-aware policy control.

Options ***profile-name***—LRF profile name. The referenced LRF profile must be configured.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Assigning an LRF Profile to Subscribers on page 157
- Configuring an LRF Profile for Subscribers on page 152
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152
- *Applying Logging and Reporting Configuration to a Subscriber Management Service Set*
- *Configuring Logging and Reporting for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

matches

Syntax

```
matches {
  apply-groups [group-names];
  apply-groups-except [group-names];
  value;
}
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  called-station-id],
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  calling-station-id],
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  class],
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  3gpp-imsi],
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  attribute name format string]
```

Release Information Statement introduced in Junos OS Release 16.1 on MX Series.

Description Specify the regular expression that the attribute must match.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

Copyright © 2018, Juniper Networks, Inc.

Table 13: Regular Expression Operators for the matches Statement

Operator	Matches
. (period)	One instance of any character except the space.
* (asterisk)	Zero or more instances of the immediately preceding term.
+ (plus sign)	One or more instances of the immediately preceding term.
? (question mark)	Zero or one instance of the immediately preceding term.
| (pipe)	One of the terms that appears on either side of the pipe operator.
! (exclamation point)	Any string except the one specified by the expression when the exclamation point appears at the start of the expression. Use of the exclamation point is specific to Junos OS.
^ (caret)	Start of a line when the caret appears outside square brackets. One instance of any character that does not follow it within square brackets when the caret is the first character inside square brackets.
$ (dollar sign)	End of a line.
[ ] (paired square brackets)	One instance of one of the enclosed alphanumeric characters. To indicate a range of characters, use a hyphen (-) to separate the beginning and ending characters of the range. For example, [a-z0-9] matches any letter or number.
( ) (paired parentheses)	One instance of the evaluated value of the enclosed term. Parentheses are used to indicate the order of evaluation in the regular expression.

Options

value—Regular expression to match.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

maximum-bit-rate (Default Local Policy)

Syntax

```
maximum-bit-rate uplink mbr-uplink-value downlink mbr-downlink-value;
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domains domain-name ip-subscriber
  default-local-policy]
```

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Configure the maximum bit rate (MBR) for a subscriber's uplink and downlink traffic entering or exiting the access interface of the TDF domain when a TDF IP-based subscriber session does not exist. Uplink traffic originates from the subscriber towards the public data network (PDN), and downlink traffic comes from the PDN and is destined for the subscriber.

Options

mbr-uplink-value—MBR value for the uplink direction.

Range: 0 through 6144000 Kbps.

mbr-downlink-value—MBR value for the downlink direction.

Range: 0 through 6144000 Kbps.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

maximum-bit-rate (PCC Action Profiles)

Syntax maximum-bit-rate uplink *mbr-uplink-value* downlink *mbr-downlink-value*;

Hierarchy Level [edit unified-edge pcef pcc-action-profiles *profile-name*],
[edit services pcef pcc-action-profiles *profile-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef pcc-action-profiles *profile-name*** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description Specify the maximum bit rate (MBR) that you want a PCC action profile to use for uplink and downlink traffic.

If you are using Junos OS Subscriber Aware, specify the MBR at the **[edit unified-edge pcef pcc-action-profiles *profile-name*** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, specify the MBR at the **[edit services pcef pcc-action-profiles *profile-name*** hierarchy level.

Default If you configure the **maximum-bit-rate** statement but do not specify MBR values for **uplink** and **downlink**, the default value is 0.

Options ***mbr-uplink-value***—MBR value for the uplink direction.

Range: 1 through 6144000 Kbps.

mbr-downlink-value—MBR value for the downlink direction.

Range: 1 through 6144000 Kbps.

Required Privilege Level For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware on page 67
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- *Configuring Policy and Charging Control Action Profiles for Subscriber Management*
- *Understanding Application-Aware Policy Control for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

maximum-bit-rate (TDF Domain)

Syntax

```
maximum-bit-rate {
  apply-groups [group-names];
  apply-groups-except [group-names];
  downlink mbr-downlink-value;
  uplink mbr-uplink-value;
}
```

Hierarchy Level

[edit unified-edge gateways tdf *gateway-name* domains *domain-name*]

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Configure the TDF domain's default TDF subscriber maximum bit rate (MBR) for uplink and downlink traffic. Uplink traffic originates from the subscriber towards the public data network (PDN), and downlink traffic comes from the PDN and is destined for the subscriber.

Options

mbr-downlink-value—MBR value for the downlink direction.

Range: 0 through 1,048,000 Kbps.

mbr-uplink-value—MBR value for the uplink direction.

Range: 0 through 6,144,000 Kbps.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Configuring IFL-Based TDF Subscribers and Properties with a TDF Domain on page 117
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based and IFL-Based TDF Subscribers Overview on page 88
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

maximum-pending-reqs-limit

Syntax maximum-pending-reqs-limit *number*;

Hierarchy Level [edit access radius network-element *name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the maximum number of requests that can be queued to the network element. When the pending-request queue is full, any additional requests are dropped.

Options ***number***—Maximum number of pending requests.

Range: 512 through 8192

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring RADIUS Network Elements on page 77
- Understanding Network Elements on page 57
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

maximum-pending-requests (Diameter)

Syntax maximum-pending-requests *requests*;

Hierarchy Level [edit access diameter applications pcc-gx]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the maximum number of pending requests parameter for the Diameter application.

Options ***requests***—Maximum number of pending requests.

Range: 1000 through 65,535

Default: 20,000

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- diameter on page 273

maximum-sessions (TDF Gateway)

Syntax maximum-sessions *max-sessions*;

Hierarchy Level [edit unified-edge gateways tdf *gateway-name* cac]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the maximum number of TDF subscriber sessions that may be running.

Options ***max-sessions***—Maximum number of TDF subscriber sessions, expressed in thousands.

Range: 10 thousands through 5000 thousands

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a TDF Gateway on page 16

Copyright © 2018, Juniper Networks, Inc.

maximum-subscribers

Syntax maximum-subscribers *number*;

Hierarchy Level [edit unified-edge gateways tdf *gateway-name* domains *domain-name* ip-subscriber]

Release Information Statement introduced in Junos OS Release 16.1 on MX Series.

Description Specify the maximum number of IP-based subscriber sessions that the TDF domain can support.

Options ***number***—Maximum number of subscriber sessions allowed.

Range: 100 thousands through 5000 thousands.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

maximum-sessions-trap-percentage (TDF Gateway)

Syntax maximum-sessions-trap-percentage *max-sessions-pct*;

Hierarchy Level [edit unified-edge gateways tdf *gateway-name* cac]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the trap threshold for the number of TDF subscriber sessions as a percentage of the maximum number of sessions (**maximum-sessions**) that was configured at the **[edit unified-edge gateways tdf *gateway-name* cac]** hierarchy level. If the number of subscriber sessions reaches the threshold, the SNMP trap **jnxScgSMSessionThreshHigh** is generated.

Options ***max-sessions-pct***—Percentage of the maximum number of TDF subscriber sessions.

Range: 1 through 90

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a TDF Gateway on page 16

member (Application Identification)

Syntax

```
[member member-name];
```

Hierarchy Level

```
[edit services application-identification application application-name over]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Define a member name for a custom application definition. Custom definitions can contain multiple members that define attributes for an application. You can define a maximum of four member names.

Options

member-name—Name of a member for a custom application definition. You can define a maximum of four member names.

Required Privilege Level

view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation

- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25
- Application Identification Overview on page 23Application Identification Overview on page 23

Copyright © 2018, Juniper Networks, Inc.

memory (TDF Gateway)

Syntax memory *memory-pct*;

Hierarchy Level [edit unified-edge gateways tdf *gateway-name* cac]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the threshold for the maximum amount of memory that the TDF gateway may use. If the amount of memory that the TDF gateway uses reaches the threshold, the SNMP trap **jnxScgSMMemoryThreshHigh** is generated.

Options ***memory-pct***—Maximum percentage of memory that can be used.

Range: 1 through 90.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a TDF Gateway on page 16

Copyright © 2018, Juniper Networks, Inc.

mif (TDF Interface)

Syntax

```
mif {
  mtu;
  unit interface-unit-number {
    family family-name {
      service {
        input service-set;
        output service-set;
      }
    }
  }
}
```

Hierarchy Level

[edit interfaces]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure the TDF interfaces for the TDF domains. A TDF interface is distinct from other types of interfaces and is used to associate a TDF domain's subscribers with an access interface in a virtual routing and forwarding table (VRF). You need to configure one TDF interface logical interface (unit) for every TDF domain.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring a TDF Logical Interface on page 120

Copyright © 2018, Juniper Networks, Inc.

monitoring-key (PCC Action Profile)

Syntax monitoring-key *key_string*

Hierarchy Level [edit unified-edge pcef pcc-action-profiles *profile-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the monitoring key that controls TDF subscriber usage monitoring for traffic that matches the data flows or applications identified in the predefined PCC rules containing the PCC action profile. The monitoring key is defined by the PCRF.

Options ***key_string***—Identifier for the monitoring key.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation
- Configuring TDF Subscriber Usage Monitoring for Traffic That Matches Predefined PCC Rules on page 85
- Understanding Usage Monitoring for TDF Subscribers on page 59

mtu (TDF Interface)

Syntax mtu *mtu-size*;

Hierarchy Level [edit interfaces mif]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the maximum transmission unit (MTU) size for the TDF interface.

Options ***mtu-size***—MTU size.

Range: 256 through 9192 bytes

Default: 500 bytes (inet, inet6, and ISO families), 1448 bytes (MPLS)

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation
- Configuring a TDF Logical Interface on page 120

Copyright © 2018, Juniper Networks, Inc.

nas-ip-address

Syntax

```
nas-ip-address {
  equals value;
}
```

Hierarchy Level

[edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* from]

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the RADIUS AVP NAS-IP-Address for the incoming RADIUS request from the subscriber.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

The remaining statement is explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

nat-rule-sets (Service Set)

Syntax nat-rule-sets *rule-set-name*;

Hierarchy Level [edit services service-set *service-set-name*]

Release Information Statement introduced before Junos OS Release 7.4.

Description Specify the Network Address Translation (NAT) rule set included in the service set. You can configure only one NAT rule set. If you specify a NAT rule set, you cannot specify a NAT rule.

Options ***rule-set-name***—Name of the NAT rule set.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation
- Applying Services to Subscriber-Aware Traffic with a Service Set on page 124

nat-rules

Syntax (nat-rules *rule-name* | nat-rule-sets *rule-set-name*);

Hierarchy Level [edit services service-set *service-set-name*]

Release Information Statement introduced before Junos OS Release 7.4.

Description Specify the Network Address Translation (NAT) rules or rule set included in this service set. You can configure multiple rules, but only one rule set for each service.

Options ***rule-name***—Identifier for the collection of terms that constitute this rule.

rule-set-name—Identifier for the set of rules to be included.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation
- *Configuring Service Rules*
- Applying Services to Subscriber-Aware Traffic with a Service Set on page 124

Copyright © 2018, Juniper Networks, Inc.

network-element (AAA Profile)

Syntax network-element *network-element-name*;

Hierarchy Level [edit unified-edge aaa profiles *aaa-profile-name* radius authentication],
[edit unified-edge aaa profiles *aaa-profile-name* radius accounting]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the network element providing policy management for TDF subscribers. The network element must already be defined at the **[edit access radius]** hierarchy level.

Options ***network-element-name***—Name of the network element.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring an AAA Profile on page 78
- Understanding AAA Profiles on page 58
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53
- Configuring RADIUS Network Elements on page 77

Copyright © 2018, Juniper Networks, Inc.

network-element (Diameter Base Protocol)

Syntax

```
network-element element-name {
  function function-name;
  peer peer-name {
    priority priority-value;
    <timeout seconds>;
  }
}
```

Hierarchy Level

```
[edit access diameter]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure the Diameter network element, which is similar to a peer group that provides function-specific features including failover and load balancing. Specify the associated function that the network element supports. You can prioritize the peers to support failover or load balancing.

Default

By default, all network elements are available on every session PIC unless Diameter bindings are configured.

Options

element-name—Name of the network element.

Range: Up to 32 alphanumeric characters

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- diameter on page 273

Copyright © 2018, Juniper Networks, Inc.

network-element (Subscriber Aware Policy Control)

Syntax

```
network-element {
  element-name {
    session-pics {
      group {
        group-name {
          [session-pic interface-name];
        }
      }
    }
  }
}
```

Hierarchy Level

[edit unified-edge tdf *gateway-name* diameter]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure the Diameter network element associated with Diameter bindings for this TDF gateway.

NOTE: If you want to set up Diameter bindings for session PICs on the TDF gateway, contact Juniper Networks Professional Services for assistance.

Options

element-name—Name of the network element.

Range: Up to 32 alphanumeric characters

NOTE: The specified network element must already be configured on the TDF gateway at the **[edit access diameter network-element]** hierarchy level.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- diameter on page 275

Copyright © 2018, Juniper Networks, Inc.

network-elements (RADIUS)

Syntax

```
network-elements name {
  server name {
    priority priority;
  }
  maximum-pending-reqs-limit number;
  pending-queue-watermark watermark;
  pending-queue-watermark-abate abate-watermark;
}
```

Hierarchy Level

```
[edit access radius]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure a network element, which is a load-balanced group of RADIUS servers providing policy management for TDF subscribers.

Options

name—Name of the network element.

Range: Up to 31 alphanumeric characters.

The remaining statements are described separately.

Required Privilege Level

access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring RADIUS Network Elements on page 77
- Understanding Network Elements on page 57
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

network (Address Pools)

Syntax

```
network {
  [network-prefix] {
    external-assigned;
  }
}
```

Hierarchy Level

[edit access address-assignment address-pools *name* family inet],
[edit access address-assignment address-pools *name* family inet6]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Specify the network prefix for the address pool for IPv4 or IPv6 addresses.

NOTE: At least one network prefix must be configured but you can configure more than one prefix.

Options

network-prefix—Network prefix (IPv4 or IPv6).

The remaining statement is explained separately. See CLI Explorer.

Required Privilege Level

access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Understanding Source IP Filtering with Address Pools in TDF Domains for IP-Based Subscribers on page 90
- Configuring Address Pools for Source-IP Filtering of IP-Based Subscribers on page 99

Copyright © 2018, Juniper Networks, Inc.

network (TDF Domain)

Syntax

```
network address net-mask;
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domains domain-name
  subscriber-exclude-prefix family inet],
[edit unified-edge gateways tdf gateway-name domains domain-name
  subscriber-exclude-prefix family inet6]
```

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the network prefix of source IP addresses for uplink packets and destination IP addresses for downlink packets that do not undergo TDF processing.

Options

address—Network address for the network prefix to exclude.

net-mask—Netmask for the network prefix.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Configuring IFL-Based TDF Subscribers and Properties with a TDF Domain on page 117
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based and IFL-Based TDF Subscribers Overview on page 88
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

no-send-to-ue

Syntax no-send-to-ue;

Hierarchy Level [edit unified-edge pcef flow-description *flow-identifier*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify that signaling information about the service data flow (SDF) filter is not sent to the user equipment.

Default By default, if this statement is not configured, signaling information about the SDF filter is sent to the user equipment.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Service Data Flow Filters on page 64
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47

Copyright © 2018, Juniper Networks, Inc.

order (Application Identification)

Syntax

order *order;*

Hierarchy Level

[edit services application-identification application *name* address-mapping *name*],
[edit services application-identification application *application-name* icmp-mapping],
[edit services application-identification application *application-name* ip-protocol-mapping],
[edit services application-identification application *application-name* over]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Define application matching priority. For address configurations, the order number resolves the conflict when multiple address entries are matched for a specific session. The lower number has a higher priority.

Options

order—Order sequence number. This value is mandatory and must be unique.

Default: 0

Range: 0 through 65,535

Required Privilege Level

view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation

- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25
- Application Identification Overview on page 23Application Identification Overview on page 23

Copyright © 2018, Juniper Networks, Inc.

order-priority (Application Identification)

Syntax

```
order-priority (high | low)
```

Hierarchy Level

[edit services application-identification application *application-name* address-mapping *name*],
[edit services application-identification application *application-name* icmp-mapping],
[edit services application-identification application *application-name* ip-protocol-mapping],
[edit services application-identification application *application-name* over]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Defiine the priority of signatures when both a custom signature and predefined signature apply to a protocol bundle.

Options

high—Custom signatures have priority over predefined signatures.

low—Predefined signatures have priority over custom signatures.

Default: high

Required Privilege Level

view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation

- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25
- Application Identification Overview on page 23Application Identification Overview on page 23

Copyright © 2018, Juniper Networks, Inc.

origin (Diameter Base Protocol)

Syntax

```
origin {
  host hostname;
  realm realm-name;
}
```

Hierarchy Level

[edit access diameter]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Specify values of the Origin-Realm AVP and the Origin-Host AVP used in all messages sent by the Diameter instance. These values must be unique for each session PIC.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- diameter on page 273

Copyright © 2018, Juniper Networks, Inc.

outgoing-queue

Syntax

```
outgoing-queue {
  <high-watermark high-watermark>;
  <low-watermark low-watermark>;
  size size;
}
```

Hierarchy Level

```
[edit access diameter peer peer-name]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure the outgoing queue properties for this peer. When the queue size reaches the high watermark, the peer is marked unavailable, any new messages to the Diameter network element are not sent to this peer, and the SNMP trap **Diameter_PeerOutQHiWMarkNotif** is generated. When the queue size descends below the low watermark after reaching the high watermark, the peer becomes available and the SNMP trap **Diameter_PeerLowQHiWMarkNotif** is generated.

Options

high-watermark *high-watermark*—(Optional) Use the specified high watermark for this peer.

Range: 1 through 100 percent

Default: 80

low-watermark *low-watermark*—(Optional) Use the specified low watermark for this peer.

Range: 1 through 100 percent

Default: 60

size *size*—Use the specified size of the queue. The default is 6000.

Range: 1 through 65,535 packets

Required Privilege Level

access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring Diameter Peers on page 134
- diameter on page 273

Copyright © 2018, Juniper Networks, Inc.

over (Application Identification)

Syntax

```
over l4-l7-signature-name {
  chain-order
  member member-name {
    check-bytes max-bytes-to-check;
    context context;
    pattern pattern;
    direction (any | client-to-server | server-to-client);
  }
  order order;
  order-priority (high | low);
  port-range {
    tcp [port-range];
    udp [port-range];
  }
  protocol (http | ssl | tcp | udp);
}
```

Hierarchy Level

```
[edit services application-identification application application-name]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure a custom signature based on Layer 7 custom signatures that are further differentiated by the Layer 4 protocol type. Users can define their own signatures for deep packet inspection (DPI) that do not exist in the predefined signature database.

Options

l4-l7-signature-name—Name of the signature used for DPI.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation

- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25
- Application Identification Overview on page 23Application Identification Overview on page 23

Copyright © 2018, Juniper Networks, Inc.

path (Steering)

Syntax

```
path {
  ipv4-address ipv4-address;
  ipv6-address ipv6-address;
}
```

Hierarchy Level

[edit unified-edge pcef pcc-action-profiles *profile-name* steering]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Specify the IP address of a third-party server to which the PCC action profile steers HTTP traffic for applying services. If you configure this, the PCC action profile can only be used in PCC rules that match only HTTP-based applications and all flows.

The remaining statements are explained separately.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware on page 67
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47

Copyright © 2018, Juniper Networks, Inc.

pattern (Application Identification)

Syntax pattern *pattern*;

Hierarchy Level [edit services application-identification application *application-name* over member]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Define an attack pattern to be detected.

Options ***pattern***—User-defined pattern of attack to match, using a regular expression.

Required Privilege Level view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation

- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25
- Application Identification Overview on page 23Application Identification Overview on page 23

Copyright © 2018, Juniper Networks, Inc.

pattern (Class Attribute)

Syntax

```
pattern “pattern”;
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domains domain-name subscription-id
  use-class]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure characters to insert between the resulting regular expression groups that are generated from parsing the Class attribute contents of the accounting request from the BNG, PGW, or GGSN. Regular expression groups are identified with **\n** for a group number.

Options

pattern—Characters to insert between regular expression groups. A regular expression group number “n” is identified as **\n**.

For example, the following configuration generates **" 000118191129|ALICE:DRAV3:"** out of **" 000118191129#000118191129#ALICE:DRAV3:#7168#nflat#ADSL##"**:

```
[edit unified-edge gateways tdf TDF1 domains domain1 subscription-id]
user@host# set use-class regex "[^#]*#\([^#]*\)\#\([^#]*\)"
user@host# set use-class pattern "\1|\2"
```

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100

Copyright © 2018, Juniper Networks, Inc.

pcc-action-profile (PCC Rules)

Syntax

```
pcc-action-profile profile-name;
```

Hierarchy Level

```
[edit unified-edge pcef pcc-rules rules-name then],
[edit services pcef pcc-rules rules-name then]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef pcc-rules *rules-name* then]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description

Specify the name of the action profile to include in a policy and charging control (PCC) rule configuration. The action profile defines the treatment to be applied to specific service data flows or to packets associated with specific applications.

If you are using Junos OS Subscriber Aware, specify the name of the action profile at the **[edit unified-edge pcef pcc-rules *rules-name* then]** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, specify the name of the action profile at the **[edit services pcef pcc-rules *rules-name* then]** hierarchy level.

Options

profile-name—Name of the PCC action profile that the PCC rule references. The referenced action profile must be configured.

Range: 1 through 63 characters.

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring Policy and Charging Control Rules on page 70
- Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware on page 67
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- *Configuring Policy and Charging Control Action Profiles for Subscriber Management*
- *Understanding Application-Aware Policy Control for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

pcc-action-profiles

Syntax

```
pcc-action-profiles profile-name {
  forwarding-class class-name;
  gate-status (uplink | downlink | uplink-downlink | disable-both);
  hcm-profile hcm-profile-name;
  logging-rule lrf-rule-name;
  maximum-bit-rate uplink mbr-uplink-value downlink mbr-downlink-value;
  monitoring-key key_string;
  redirect {
    url url-name;
  }
  steering {
    keep-existing-steering;
    path {
      ipv4-address ipv4-address;
      ipv6-address ipv6-address;
    }
    routing-instance {
      downlink downlink-vrf-name;
      uplink uplink-vrf-name;
    }
  }
}
```

Hierarchy Level

[edit unified-edge pcef],
[edit services pcef]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description

Configure a PCC action profile. A PCC action profile defines the treatment to be applied to specific service data flows or to packets associated with specific applications. A PCC action profile is specified in the **then** clause of a PCC rule.

If you are using Junos OS Subscriber Aware, configure the PCC action profile at the **[edit unified-edge pcef]** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, configure the PCC action profile at the **[edit services pcef]** hierarchy level. The following options are not applicable to subscriber management:

- **hcm-profile**
- **steering path** and its options

Options

profile-name—Name of the PCC action profile.

Range: 1 through 63 characters.

Copyright © 2018, Juniper Networks, Inc.

The remaining statements are explained separately. Search for a statement in CLI Explorer or click a linked statement in the Syntax section for details.

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware on page 67
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- Configuring TDF Subscriber Usage Monitoring for Traffic That Matches Predefined PCC Rules on page 85
- *Configuring Policy and Charging Control Action Profiles for Subscriber Management*
- *Understanding Application-Aware Policy Control for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

pcc-rule

Syntax

[pcc-rule *rule-name* precedence *number*];

Hierarchy Level

[edit unified-edge pcef pcc-rule-bases *rulebase-name*],
[edit services pcef pcc-rule-bases *rulebase-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef pcc-rule-bases *rulebase-name*]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description

Specify one or more policy and charging control (PCC) rules and the rules precedence in a PCC rulebase.

If you are using Junos OS Subscriber Aware, configure the PCC rules at the **[edit unified-edge pcef pcc-rule-bases *rulebase-name*]** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, configure the PCC rules at the **[edit services pcef pcc-rule-bases *rulebase-name*]** hierarchy level.

Options

rule-name—Name of the PCC rule. The referenced PCC rule must be configured.

Range: 1 through 63 characters.

number—Precedence value assigned to the PCC rule. The precedence assigned must be unique among the configured PCC rules.

Range: 1 through 65,535

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring a Policy and Charging Control Rulebase on page 73
- Configuring Policy and Charging Control Rules on page 70

Copyright © 2018, Juniper Networks, Inc.

pcc-rulebases (PCEF)

Syntax

```
pcc-rulebases rulebase-name {
  [pcc-rule rule-name precedence number];
}
```

Hierarchy Level

```
[edit unified-edge pcef],
[edit services pcef]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description

Configure a policy and charging control (PCC) rulebase. You can specify from 1 through 4000 rules in a rulebase.

If you are using Junos OS Subscriber Aware, configure the PCC rulebase at the **[edit unified-edge pcef]** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, configure the PCC rulebase at the **[edit services pcef]** hierarchy level.

Options

rulebase-name—Name of the PCC rulebase.

Range: 1 through 63 characters.

The remaining statements are explained separately. Search for a statement in CLI Explorer or click a linked statement in the Syntax section for details.

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring a Policy and Charging Control Rulebase on page 73

Copyright © 2018, Juniper Networks, Inc.

pcc-rulebases (PCEF Profile)

Syntax

```
[pcc-rulebases rulebase-name <time-of-day-profile profile-name>];
```

Hierarchy Level

```
[edit unified-edge pcef profiles profile-name aaa-policy-control],
[edit unified-edge pcef profiles profile-name dynamic-policy-control],
[edit unified-edge pcef profiles profile-name static-policy-control],
[edit services pcef profiles profile-name static-policy-control],
[edit services pcef profiles profile-name dynamic-policy-control]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef profiles *profile-name* static-policy-control]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.
Support at the **[edit services pcef profiles *profile-name* dynamic-policy-control]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 18.2R1 on MX Series.

Description

Specify a policy and charging control (PCC) rulebase for a policy control profile.

If you are using Junos OS Subscriber Aware, specify the PCC rulebase at the **[edit unified-edge pcef profiles *profile-name* (aaa-policy-control | dynamic-policy-control | static-policy-control)** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, specify the PCC rulebase at the **[edit services pcef profiles *profile-name* (static-policy-control | dynamic-policy-control)]** hierarchy level.

Options

rulebase-name—Name of the PCC rulebase. The referenced PCC rulebase must be configured.

time-of-day-profile *profile-name*—(Optional; only applies to rulebases in static PCEF profiles for Junos OS Subscriber Aware) Use the specified name of the time-of-day profile to apply to the PCC rulebase. The referenced profile must already be defined at the **[edit unified-edge pcef]** hierarchy level. The time-of-day profile specifies the time of day, day of the week, or day of the month to activate or deactivate the PCC rulebase for subscribers assigned to the PCEF profile.

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Copyright © 2018, Juniper Networks, Inc.

Related Documentation

- Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Dynamic Policies on page 80
- Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Static Policies on page 81
- Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Policies That a RADIUS Server Controls on page 82
- Configuring Static Time-of-Day PCC Rule Activation and Deactivation in a Junos OS Subscriber Aware PCEF Profile on page 84
- Configuring a Policy and Charging Control Rulebase on page 73
- *Configuring a Policy and Charging Enforcement Function Profile for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

pcc-rules (PCEF)

Syntax

```
pcc-rules rule-name {
  from {
    <application-groups [application-group-name]>;
    <applications [application-name]>;
    flows ([flow-identifier | any)];
  }
  then {
    pcc-action-profile profile-name;
  }
}
```

Hierarchy Level

[edit unified-edge pcef],
[edit services pcef]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description

Configure the PCC rules. A PCC rule identifies the subscriber IP packets that are associated with a service data flow (SDF) or application and defines the treatment to be applied to the packets.

If you are using Junos OS Subscriber Aware, configure the PCC rule at the **[edit unified-edge pcef]** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, configure the PCC rule at the **[edit services pcef]** hierarchy level.

Options

rule-name—Name of the PCC rule.

Range: 1 through 63 characters.

The remaining statements are explained separately. Search for a statement in CLI Explorer or click a linked statement in the Syntax section for details.

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring Policy and Charging Control Rules on page 70
- Configuring TDF Subscriber Usage Monitoring for Traffic That Matches Predefined PCC Rules on page 85

Copyright © 2018, Juniper Networks, Inc.

pcc-rules (PCEF Profile)

Syntax

```
pcc-rules [rule-name precedence number <time-of-day-profile profile-name>];
```

Hierarchy Level

```
[edit unified-edge pcef profiles profile-name aaa-policy-control],
[edit unified-edge pcef profiles profile-name dynamic-policy-control],
[edit unified-edge pcef profiles profile-name static-policy-control],
[edit services pcef profiles profile-name static-policy-control],
[edit services pcef profiles profile-name dynamic-policy-control]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef profiles *profile-name* static-policy-control]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.
Support at the **[edit services pcef profiles *profile-name* dynamic-policy-control]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 18.2R1 on MX Series.

Description

Specify the policy and charging control (PCC) rules for a policy and charging enforcement function (PCEF) profile and assign a precedence to each PCC rule. You can configure up to 32 PCC rules in a PCEF profile.

If you are using Junos OS Subscriber Aware, specify the PCC rules at the **[edit unified-edge pcef profiles *profile-name* (aaa-policy-control | dynamic-policy-control | static-policy-control)** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, specify the PCC rules at the **[edit services pcef profiles *profile-name* (static-policy-control | dynamic-policy-control)]** hierarchy level.

Options

rule-name—Name of the PCC rule. The referenced PCC rule must be configured.

precedence *number*—Use the specified precedence value assigned to a PCC rule. A lower precedence value indicates a higher precedence.

Range: 1 through 65,535

time-of-day-profile *profile-name*—(Optional; only applies to rules in static PCEF profiles for Junos OS Subscriber Aware) Use the specified name of the time-of-day profile to apply to the PCC rule. The referenced profile must already be defined at the **[edit unified-edge pcef]** hierarchy level. The time-of-day profile specifies the time of day, day of the week, or day of the month to activate or deactivate the PCC rule for subscribers assigned to the PCEF profile.

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Copyright © 2018, Juniper Networks, Inc.

For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Dynamic Policies on page 80
- Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Static Policies on page 81
- Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Policies That a RADIUS Server Controls on page 82
- Configuring Static Time-of-Day PCC Rule Activation and Deactivation in a Junos OS Subscriber Aware PCEF Profile on page 84
- *Configuring a Policy and Charging Enforcement Function Profile for Subscriber Management*
- Configuring Policy and Charging Control Rules on page 70

Copyright © 2018, Juniper Networks, Inc.

pcc-time-of-day-profiles

Syntax

```
pcc-time-of-day-profiles profile-name {
  rule-activation-time {
    <day-of-week | day-of-month month>;
    <hour:min>;
  }
  rule-deactivation-time {
    <day-of-week | day-of-month month>;
    <hour:min>;
  }
}
```

Hierarchy Level

```
[edit unified-edge pcef]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure a PCC time-of-day profile to specify the time of day, day of the week, or day of the month to activate and deactivate a PCC rule or rulebase. A PCC time-of-day profile is applied to a PCC rule or PCC rulebase within a static PCEF profile. If a time zone is configured on the router, the time-of-day settings apply to the configured time zone.

Options

profile-name—Name of the PCC time-of-day profile.

Range: 1 through 63 characters.

The remaining statements are explained separately.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Static Time-of-Day PCC Rule Activation and Deactivation in a Junos OS Subscriber Aware PCEF Profile on page 84
- Understanding Static Time-of-Day PCC Rule Activation and Deactivation on page 59

Copyright © 2018, Juniper Networks, Inc.

pcef

Syntax

```
pcef {
  flow-descriptions flow-identifier {
    direction (uplink | downlink | both);
    local-port-range {
      low low-value high high-value;
    }
    local-ports number;
    no-send-to-ue;
    protocol number;
    remote-address (ipv4-address ipv4-address | ipv6-address ipv6-address);
    remote-port-range {
      low low-value high high-value;
    }
    remote-ports number;
  }
  pcc-action-profiles profile-name {
    forwarding-class class-name;
    gate-status (uplink | downlink | uplink-downlink | disable-both);
    hcm-profile hcm-profile-name;
    logging-rule lrf-rule-name;
    maximum-bit-rate uplink mbr-uplink-value downlink mbr-downlink-value;
    monitoring-key key_string;
    redirect {
      url url-name;
    }
    steering {
      keep-existing-steering;
      path {
        ipv4-address ipv4-address;
        ipv6-address ipv6-address;
      }
      routing-instance {
        downlink downlink-vrf-name;
        uplink uplink-vrf-name;
      }
    }
  }
  pcc-rulebases rulebase-name {
    [pcc-rule rule-name precedence number];
  }
  pcc-rules rule-name {
    from {
      <application-groups [application-group-name]>;
      <applications [application-name]>;
      flows ([flow-identifier ] | any);
    }
    then {
      pcc-action-profile profile-name;
    }
  }
  pcc-time-of-day-profiles profile-name {
```


Copyright © 2018, Juniper Networks, Inc.

```
    rule-activation-time {
      <day-of-week | day-of-month month>;
      <hour:min>;
    }
    rule-deactivation-time {
      <day-of-week | day-of-month month>;
      <hour:min>;
    }
  }
  profiles profile-name {
    aaa-policy-control {
      aaa-profile aaa-profile-name;
      pcc-rulebases [rulebase-name];
      user-password password;
    }
    dynamic-policy-control {
      pcc-rules {
        [rule-name number];
      }
      pcc-rulebases {
        [rulebase-name];
      }
      diameter-profile gx-profile-name;
    }
    static-policy-control {
      pcc-rules {
        [rule-name precedence number <time-of-day-profile profile-name>];
      }
      pcc-rulebases {
        [rulebase-name <time-of-day-profile profile-name>];
      }
    }
  }
}
```

Hierarchy Level [edit unified-edge]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Set up the overall policy and control enforcement function (PCEF) configuration.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Understanding Junos Subscriber Aware Policy and Charging Enforcement Function (PCEF) on page 44
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47

Copyright © 2018, Juniper Networks, Inc.

pcef-profile (Service Set)

Syntax pcef-profile *pcef-profile-name*;

Hierarchy Level [edit services service-set *service-set-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the dummy PCEF profile that you configured at the **[edit services pcef]** hierarchy level. This profile is a placeholder profile with no configuration options, but it must be specified to enable PCEF functionality on the services plane.

Options ***pcef-profile-name***—Name of the PCEF profile.

Required Privilege Level
For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Applying Services to Subscriber-Aware Traffic with a Service Set on page 124
- *Identifying the Service Interface That Handles Subscriber Management Application-Aware Policy Control*
- *Configuring a Policy and Charging Enforcement Function Profile for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

pcef-profile (TDF Domain)

Syntax pcef-profile *name*;

Hierarchy Level [edit unified-edge gateways tdf *gateway-name* domains *domain-name*]

Release Information Statement introduced in Junos OS Release 16.1 on MX Series.

Description Specify the policy and charging enforcement function (PCEF) profile to be applied to subscribers in the TDF domain. This is required for IFL-based subscribers, and optional for IP-based subscribers. If you do not identify a PCEF profile, then the PCEF profile must be assigned under the **[edit unified-edge gateways tdf *gateway-name* domain-selection term]** hierarchy level.

Options ***name***—Name of the PCEF profile.

NOTE: **The PCEF profile must have been previously configured at the [edit unified-edge pcef] hierarchy level.**

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Configuring IFL-Based TDF Subscribers and Properties with a TDF Domain on page 117
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based and IFL-Based TDF Subscribers Overview on page 88
- IP-Based Subscriber Setup Overview on page 88
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- Understanding PCEF Profiles on page 56

Copyright © 2018, Juniper Networks, Inc.

pcef-profile (TDF Domain Selection)

Syntax

```
pcef-profile pcef-profile-name;
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name then]
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the policy and charging enforcement function (PCEF) profile to be selected for the IP-based TDF subscriber when the criteria specified in the **domain-selection term *term-name* from** statement are matched. This PCEF profile is required if the TDF domain selected for a subscriber does not specify a PCEF profile or you want to allow different members of the same TDF domain to have different PCEF profiles.

Options ***pcef-profile-name***—Name of the PCEF profile.

NOTE: The PCEF profile must have been previously configured at the **[edit unified-edge pcef]** hierarchy level.

Required Privilege Level
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

peer (Diameter Base Protocol)

Syntax

```
peer peer-name {
  address ip-address;
  connect-actively {
    <capabilities-exchange-timeout seconds>;
    <port port-number>;
    <repeat-timeout seconds>;
    <retry-timeout seconds>;
    <timeout seconds>;
    transport transport-name;
  }
  <disconnect-peer-timeout seconds>;
  <incoming-queue> {
    size size;
  }
  <outgoing-queue> {
    <high-watermark high-watermark>;
    <low-watermark low-watermark>;
    size size;
  }
  <watchdog-timeout seconds>;
}
```

Hierarchy Level

```
[edit access diameter]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure a remote peer for the Diameter instance. You can configure up to 31 peers.

Options

peer-name—Name of the peer.

Range: 1 through 32 alphanumeric characters

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- diameter on page 273

Copyright © 2018, Juniper Networks, Inc.

peer (Diameter Network Element)

Syntax

```
peer peer-name {
  priority priority-value;
  <timeout seconds>;
}
```

Hierarchy Level

[edit access diameter network-element *element-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Define and prioritize a peer associated with a Diameter network element. You must prioritize the associated peer by including the **priority** statement.

Options

peer-name—Name of the peer.

Range: 1 through 32 alphanumeric characters

NOTE: **The specified peer must already be configured at the [edit access diameter peer] hierarchy level.**

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- diameter on page 273

Copyright © 2018, Juniper Networks, Inc.

pending-queue-watermark

Syntax pending-queue-watermark *watermark*;

Hierarchy Level [edit access radius network-element *name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the pending-request queue high watermark for the network element. This is a percentage of the maximum number of requests that can be queued to the network element, which is configured in the **maximum-pending-reqs-limit *number*** statement at the **[edit access radius network-element *name*]** hierarchy level. When the queue size reaches the high watermark, a **flow control on** message is generated.

Options ***watermark***—High watermark for the network element pending request queue.

Range: 1 through 100 percent.

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring RADIUS Network Elements on page 77
- Understanding Network Elements on page 57
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

pending-queue-watermark-abate

Syntax pending-queue-watermark-abate *abate-watermark*;

Hierarchy Level [edit access radius network-element *name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the low watermark of the pending-request queue for the network element. This is a percentage of the maximum size of the pending-request queue, which is configured in the **maximum-pending-reqs-limit *watermark*** statement at the **[edit access radius network-element *name*]** hierarchy level. When the number of pending requests drops below this low watermark value after having exceeded the high watermark configured in the **pending-queue-watermark *watermark*** statement, a **flow control off** message is generated.

Options ***abate-watermark***—Low watermark for the network element pending request queue.

Range: 1 through 100 percent.

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring RADIUS Network Elements on page 77
- Understanding Network Elements on page 57
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

policy-based-logging (LRF Profile)

Syntax

```
policy-based-logging;
```

Hierarchy Level

```
[edit services lrf profile profile-name]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure policy-based logging, which causes the LRF rules to be activated by PCC rules.

Required Privilege Level

interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring an LRF Profile for Subscribers on page 152
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152
- *Configuring Logging and Reporting for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

pool (TDF Domain)

Syntax

```
pool pool-name;
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domains domain-name ip-subscriber
  subscriber-address (inet | inet6)]
```

Release Information Statement introduced in Junos OS Release 16.1 on MX Series.

Description Specify the address pool that contains the source IP addresses for IP-based subscriber packets that undergo TDF processing.

You can specify only one address pool.

Options ***pool-name***—Name of the address pool.

NOTE: The address pool must have been previously configured at the **[edit access address-assignment]** hierarchy level.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Address Pools for Source-IP Filtering of IP-Based Subscribers on page 99
- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Understanding Source IP Filtering with Address Pools in TDF Domains for IP-Based Subscribers on page 90
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89

Copyright © 2018, Juniper Networks, Inc.

port (LRF Profile)

Syntax port *collector-port-number*;

Hierarchy Level [edit services lrf profile *profile-name* collector *collector-name* destination]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the destination port of the collector.

Options ***collector-port-number***—Port number for the destination address of the collector.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring an LRF Profile for Subscribers on page 152
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152
- *Configuring Logging and Reporting for Subscriber Management*

port (RADIUS Server)

Syntax port *port-number*;

Hierarchy Level [edit access radius servers *name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the port number to which the RADIUS requests are sent.

Options ***port-number***—Port number to which the RADIUS requests are sent.

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring RADIUS Servers on page 74
- Understanding Network Elements on page 57
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

port-range (Application Identification)

Syntax

```
port-range {
  tcp [port-range];
  udp [port-range];
}
```

Hierarchy Level

[edit services application-identification application *application-name* over]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Define TCP or UDP port number range.

Options

port-range—Numeric port ranges. The format for numeric port ranges is in the format *minimum-value–maximum-value*.

Required Privilege Level

view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation

- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25
- Application Identification Overview on page 23Application Identification Overview on page 23

Copyright © 2018, Juniper Networks, Inc.

prefer-framed-ip-address (RADIUS Clients)

Syntax

```
prefer-framed-ip-address;
```

Hierarchy Level

[edit access radius clients *client-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Specify that the framed-ip-address is used for subscriber creation when both the framed-route and framed-ip-address attributes are in the RADIUS accounting request from the RADIUS client. The framed-ip-netmask is also used for subscriber creation if it is in the request.

By default, the framed-route attribute is used for subscriber creation when both the framed-route and framed-ip-address attributes are in the RADIUS accounting request.

Required Privilege Level

access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring RADIUS Clients That Send Accounting Requests for IP-Based Subscribers on page 106

Copyright © 2018, Juniper Networks, Inc.

prefer-framed-ipv6-prefix (RADIUS Clients)

Syntax prefer-framed-ipv6-prefix;

Hierarchy Level [edit access radius clients *client-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify that the framed-ipv6-prefix is used for subscriber creation when both the delegated-ipv6-prefix and framed-ipv6-prefix attributes are in the RADIUS accounting request from the RADIUS client.

By default, the delegated-ipv6-prefix attribute is used for subscriber creation when both the delegated-ipv6-prefix and framed-ipv6-prefix attributes are in the RADIUS accounting request.

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation
- Configuring RADIUS Clients That Send Accounting Requests for IP-Based Subscribers on page 106

priority (Diameter Network Element)

Syntax priority *priority-value*;

Hierarchy Level [edit access diameter network-element *element-name* peer *peer-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Set the priority for a peer within a Diameter network element. A peer with a lower number has a higher priority. For load balancing, configure the peers with the same priority.

Options ***priority-value***—Priority for the peer within the network element.

Range: 1 through 65,535

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation
- diameter on page 273

Copyright © 2018, Juniper Networks, Inc.

priority (RADIUS Network Elements)

Syntax priority *priority*;

Hierarchy Level [edit access radius network-element *name* server *name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure a priority for each RADIUS server in the network element. You can have multiple servers with the same priority in a network element. All access requests are load balanced among the highest priority servers. If all the servers with the highest priority in the network element fail, then requests are load balanced among servers with the next highest priority level.

Options ***priority***—Relative priority for a RADIUS server.

Range: 1 through 16.

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring RADIUS Network Elements on page 77
- Understanding Network Elements on page 57
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

product-name

Syntax product-name *name*;

Hierarchy Level [edit access diameter]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the product name that is advertised in the Capabilities-Exchange-Request or Capabilities-Exchange-Answer message.

Options ***name***—Name of product that is the advertised value of the Product-Name AVP.
Default: Juniper Diameter Client

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation
- diameter on page 273

 Copyright © 2018, Juniper Networks, Inc.

profile (HTTP Header Enrichment)

Syntax

```
profile profile-name {
  tag rule rule-name;
}
```

Hierarchy Level

[edit services hcm]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure an HCM profile, which points to one or more tag rules that Junos OS uses to enrich HTTP headers with the appropriate tags. You can configure a maximum of 100 HCM profiles.

For subscriber traffic under static policy control, a tag rule is used if it is included in the HCM profile specified in a PCC rule that the traffic matches. For subscribers under dynamic policy control, a message from the PCRF identifies the configured HCM profile and tag rules to use for HTTP header enrichment.

Options

profile-name—Name of the HCM profile.

The remaining statement is explained separately. See CLI Explorer.

Required Privilege Level

interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring HTTP Header Enrichment Overview on page 33
- Configuring HCM Profiles and Assigning Tag Rules on page 40

Copyright © 2018, Juniper Networks, Inc.

profile (LRF)

Syntax

```
profile profile-name {
  collector collector-name {
    destination {
      address collector-address;
      port collector-port-number;
    }
    source-address source-address;
  }
  http-log-multiple-transactions;
  policy-based-logging;
  rule lrf-rule-name {
    then {
      report {
        collector collector-name;
        template template-name;
        volume-limit volume;
      }
    }
  }
  template template-name {
    format ipfix;
    template-tx-interval tx-time;
    template-type template-type;
    trigger-type (session-close | time | volume);
  }
  vendor-support ibm;
}
```

Hierarchy Level

```
[edit services lrf]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
vendor-support option introduced in Junos OS Release 17.2.

Description

Configure an LRF profile to specify a set of logging and reporting parameters, which includes data templates, collectors, and LRF rules.

For Junos OS Subscriber Aware, you can then assign an LRF profile to a subscriber by assigning the profile to the TDF service set associated with the subscriber's TDF domain.

For Junos OS Broadband Subscriber Management, you can then assign the LRF profile to the service set that is configured for application-aware policy control.

Options

profile-name—Name of the LRF profile.

Range: Up to 63 characters.

The remaining statements are explained separately. Search for a statement in CLI Explorer or click a linked statement in the Syntax section for details.

Copyright © 2018, Juniper Networks, Inc.

Required Privilege Level
interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation
- Configuring an LRF Profile for Subscribers on page 152
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152
- *Configuring Logging and Reporting for Subscriber Management*
- Logging and Reporting Function for Subscribers on page 141

profile (Services Application Identification)

Syntax
```
profile app-id-profile-name;
```

Hierarchy Level
```
[edit services application-identification]
```

Release Information
Statement introduced in Junos OS Release 17.1 on MX Series.

Description
Configure an application identification profile. This profile is a placeholder profile with no configuration options, but it must be created to enable application identification functionality on the services plane.

Options
app-id-profile-name—Name of the application identification profile.

Required Privilege Level
interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation
- Applying Services to Subscriber-Aware Traffic with a Service Set on page 124

Copyright © 2018, Juniper Networks, Inc.

profile (HCM placeholder)

Syntax profile *hcm-profile-name*;

Hierarchy Level [edit services hcm]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure an HTTP header enrichment profile that is a placeholder profile with no configuration options; this profile is specified in the configuration of a subscriber-aware service set to enable HTTP header enrichment functionality on the services plane.

Options ***hcm-profile-name***—Name of the HTTP header enrichment profile.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Applying Services to Subscriber-Aware Traffic with a Service Set on page 124

profile (Services PCEF)

Syntax profile *pcef-profile-name*;

Hierarchy Level [edit services pcef]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure a policy and charging enforcement function (PCEF) profile that is a placeholder profile with no configuration options. This profile must be created to enable PCEF functionality on the services plane. You apply this placeholder profile to the subscriber-aware service set.

Options ***pcef-profile-name***—Name of the PCEF profile.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Applying Services to Subscriber-Aware Traffic with a Service Set on page 124
- *Identifying the Service Interface That Handles Subscriber Management Application-Aware Policy Control*

Copyright © 2018, Juniper Networks, Inc.

profiles (AAA)

Syntax

```
profiles aaa-profile-name {
  radius {
    accounting {
      network-element network-element-name;
    }
    authentication {
      network-element network-element-name;
    }
    policy {
      activation-attribute {
        <code numeric-code;>
        <vendor-id vendor-id;>
      }
      deactivation-attribute {
        <code numeric-code;>
        <vendor-id vendor-id;>
      }
      coa-accounting (enable | disable);
    }
  }
}
```

Hierarchy Level

```
[edit unified-edge aaa]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure a profile of the policy control attributes for RADIUS servers. This profile is used by the policy and charging enforcement function (PCEF) profile.

Options

aaa-profile-name—Name of the AAA profile.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring an AAA Profile on page 78
- Understanding AAA Profiles on page 58
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

profiles (PCEF)

Syntax

```
profiles profile-name {
  aaa-policy-control {
    aaa-profile aaa-profile-name;
    pcc-rulebases [rulebase-name <time-of-day-profile profile-name>];
    user-password password;
  }
  dynamic-policy-control {
    pcc-rules {
      [rule-name precedence number <time-of-day-profile profile-name>];
    }
    pcc-rulebases {
      [rulebase-name <time-of-day-profile profile-name>];
    }
    diameter-profile gx-profile-name;
  }
  static-policy-control {
    pcc-rules {
      [rule-name precedence number <time-of-day-profile profile-name>];
    }
    pcc-rulebases {
      [rulebase-name <time-of-day-profile profile-name>];
    }
  }
```

Hierarchy Level

```
[edit unified-edge pcef],
[edit services pcef]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description

Set up the overall policy and charging enforcement function (PCEF) configuration that can be applied to subscribers.

NOTE: You can configure only one of the following statements in a PCEF profile: **aaa-policy-control**, **static-policy-control**, or **dynamic-policy-control**.

You can configure a maximum of 32 policy and charging control (PCC) rules in a PCEF profile. There is no limit to the number of PCC rulebases you can configure in a PCEF profile.

If you are using Junos OS Subscriber Aware, configure the PCEF profile at the **[edit unified-edge pcef]** hierarchy level. You then assign this profile to the subscriber's TDF domain or to the domain selection configuration.

Copyright © 2018, Juniper Networks, Inc.

If you are using Junos OS Broadband Subscriber Management, configure the PCEF profile at the **[edit services pcef]** hierarchy level. The **static-policy-control** option is applicable to PCC rule activation through a dynamic profile, and you assign the PCEF profile to the dynamic profile. Starting in Junos OS Release 18.2R1, the **dynamic-policy-control** option is also available and is applicable to direct rule activation by a policy and charging rules function (PCRF) server; you assign the PCEF profile to the access profile. The **aaa-policy-control** option is not applicable to subscriber management.

Options

profile-name—Name of the PCEF profile.

Range: 1 through 63 characters.

The remaining statements are explained separately. Search for a statement in CLI Explorer or click a linked statement in the Syntax section for details.

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Dynamic Policies on page 80
- Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Static Policies on page 81
- Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Policies That a RADIUS Server Controls on page 82
- *Configuring a Policy and Charging Enforcement Function Profile for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

protocol (Application Identification)

Syntax

```
protocol (http | ssl | tcp | udp);
```

Hierarchy Level

```
[edit services application-identification application application-name over]
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Identify the protocol bundles to be monitored to classify applications.

Options

http—Use the HTTP protocol .

ssl—Use the SSL protocol.

tcp—Use the TCP protocol.

udp—Use the UDP protocol.

Required Privilege Level

view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation

- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25

Copyright © 2018, Juniper Networks, Inc.

protocol (Flow Descriptions)

Syntax

```
protocol number;
```

Hierarchy Level

```
[edit unified-edge pcef flow-description flow-identifier],
[edit services pcef flow-description flow-identifier]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef flow-description *flow-identifier*]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description

Specify a protocol type to identify the subscriber traffic that you want the service data flow (SDF) filter to detect. If you specify the **protocol** statement, you must specify a protocol number.

If you are using Junos OS Subscriber Aware, specify the protocol type at the **[edit unified-edge pcef flow-description *flow-identifier*]** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, specify the protocol type at the **[edit services pcef flow-description *flow-identifier*]** hierarchy level.

Default

If you do not specify the **protocol** statement, the default is any protocol.

Options

number—Number that specifies the IP protocol type.
Range: 1 through 255

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring Service Data Flow Filters on page 64
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- *Understanding Application-Aware Policy Control for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

realm (Diameter Origin)

Syntax realm *realm-name*;

Hierarchy Level [edit access diameter origin]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the realm of the host that originates the Diameter message.

Options ***realm-name***—Name of the message origin realm. Supplied as the value of Origin-Realm AVP for all messages sent by the Diameter instance.

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- diameter on page 273

Copyright © 2018, Juniper Networks, Inc.

redirect (PCC Action Profiles)

Syntax

```
redirect {
  url url-name;
}
```

Hierarchy Level

[edit unified-edge pcef pcc-action-profiles *profile-name*],
[edit services pcef pcc-action-profiles *profile-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef pcc-action-profiles *profile-name*]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description

Specify HTTP redirection to a URL. If you configure this, the PCC action profile can only be used in PCC rules that match only HTTP-based applications and all flows.

If you are using Junos OS Subscriber Aware, specify the redirection at the **[edit unified-edge pcef pcc-action-profiles *profile-name*]** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, specify the redirection at the **[edit services pcef pcc-action-profiles *profile-name*]** hierarchy level.

The remaining statements are explained separately. Search for a statement in CLI Explorer or click a linked statement in the Syntax section for details.

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware on page 67
- *Configuring Policy and Charging Control Action Profiles for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

regex (Class Attribute)

Syntax

```
regex “value”;
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domains domain-name subscription-id
  use-class]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure a regular expression to parse the Class attribute contents of the accounting request from the BNG, PGW, or GGSN.

Options

value—Regular expression that parses the contents of the Class attribute.

For example, the following configuration generates **" 000118191129ALICE:DRAV3:"** out of **" 000118191129#000118191129#ALICE:DRAV3:#7168#nflat#ADSL##"**:

```
[edit unified-edge gateways tdf TDF1 domains domain1 subscription-id ]
user@host# set use-class regex "[^#]*#\([^#]*\)\#\([^#]*\)"
```

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100

Copyright © 2018, Juniper Networks, Inc.

remote-address

Syntax

```
remote-address (ipv4-address ipv4-address | ipv6-address ipv6-address);
```

Hierarchy Level

```
[edit unified-edge pcef flow-descriptions flow-identifier],
[edit services pcef flow-descriptions flow-identifier]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef flow-descriptions *flow-identifier*]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description

Specify a remote IP address for the service data flow (SDF) filter.

If you are using Junos OS Subscriber Aware, specify the remote IP address at the **[edit unified-edge pcef flow-descriptions *flow-identifier*]** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, specify the remote IP address at the **[edit services pcef flow-descriptions *flow-identifier*]** hierarchy level.

Options

ipv4-address—IPv4 address.

ipv6-address—IPv6 address.

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring Service Data Flow Filters on page 64
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- *Understanding Application-Aware Policy Control for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

remote-port-range

Syntax

```
remote-port-range {
  low low-value;
  high high-value;
}
```

Hierarchy Level

[edit unified-edge pcef flow-descriptions *flow-identifier*],
[edit services pcef flow-descriptions *flow-identifier*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef flow-descriptions *flow-identifier*]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description

Specify the remote port range to identify the subscriber traffic that you want the service data flow (SDF) filter to detect.

If you are using Junos OS Subscriber Aware, specify the remote port range at the **[edit unified-edge pcef flow-descriptions *flow-identifier*]** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, specify the remote port range at the **[edit services pcef flow-descriptions *flow-identifier*]** hierarchy level.

NOTE: You can specify either a remote port range or a list of remote ports, but not both.

Default

If you configure neither the **remote-port-range** nor the **remote-ports** statement, the default is any remote port.

Options

high-value—Upper boundary for the remote port range.

Range: 1 through 65,535

low-value—Lower boundary for the remote port range.

Range: 1 through 65,535

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Copyright © 2018, Juniper Networks, Inc.

Related Documentation

- Configuring Service Data Flow Filters on page 64
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- *Understanding Application-Aware Policy Control for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

remote-ports

Syntax remote-ports [*number*];

Hierarchy Level [edit unified-edge pcef flow-description *flow-identifier*],
[edit services pcef flow-description *flow-identifier*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef flow-descriptions *flow-identifier*]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description Specify a remote port or list of remote ports to identify the subscriber traffic that you want the service data flow (SDF) filter to detect.

If you are using Junos OS Subscriber Aware, specify the remote ports at the **[edit unified-edge pcef flow-descriptions *flow-identifier*]** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, specify the remote ports at the **[edit services pcef flow-descriptions *flow-identifier*]** hierarchy level.

NOTE: **You can specify either a list of remote ports or a remote port range, but not both.**

Default If you configure neither the **remote-ports** nor the **remote-port-range** statement, the default is any remote port.

Options ***number***—Port number or list of port numbers. You can specify a maximum of three port numbers in a list.

Range: 1 through 65,535

Required Privilege Level For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring Service Data Flow Filters on page 64
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47

Copyright © 2018, Juniper Networks, Inc.

- *Understanding Application-Aware Policy Control for Subscriber Management*

report (LRF Rule)

Syntax

```
report {
  collector collector-name;
  template template-name;
  time-limit time-interval;
  volume-limit volume;
}
```

Hierarchy Level

[edit services lrf profile *profile-name* rule *lrf-rule-name* then]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure the actions to take if the LRF rule is matched.

The remaining statements are explained separately. Search for a statement in CLI Explorer or click a linked statement in the Syntax section for details.

Required Privilege Level

interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring an LRF Profile for Subscribers on page 152
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152
- *Configuring Logging and Reporting for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

request-cache-timeout (RADIUS Snoop Segment)

Syntax request-cache-timeout *timeout*;

Hierarchy Level [edit access radius snoop-segments *segment-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the length of time to cache the accounting request that was snooped. If the same request is received by the MX Series router within this time, the duplicate request is dropped.

Options ***timeout***—Length of time, in seconds.

Range: 1 through 30

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring Snooping of RADIUS Accounting Requests for IP-Based Subscribers on page 113
- Snooping RADIUS Accounting Requests for IP-Based Subscribers Overview on page 94
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

request-timeout

Syntax request-timeout *seconds*;

Hierarchy Level [edit unified-edge diameter-profiles gx-profile *profile-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the time to wait for a response from the server.

Options ***seconds***—Length of timeout interval.

Range: 0 through 65,535 seconds.

NOTE: 0 seconds indicates that the request timeout is not be enabled.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- gx-profile on page 316

Copyright © 2018, Juniper Networks, Inc.

response-cache-timeout (RADIUS Client)

Syntax response-cache-timeout *seconds*;

Hierarchy Level [edit access radius clients *client-name* accounting]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the timeout for the RADIUS response cache. This timeout indicates how long to store the RADIUS response messages (sent for request messages) in the MX Series router response cache.

Options ***seconds***—Length of timeout interval.

Range: 5 through 20 seconds

Default: 15 seconds

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring RADIUS Clients That Send Accounting Requests for IP-Based Subscribers on page 106

 Copyright © 2018, Juniper Networks, Inc.

retry (RADIUS Server)

Syntax retry *attempts*;

Hierarchy Level [edit access radius servers *name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure a limit to the number of times the MX Series router can resend a request to the RADIUS server when no response from the RADIUS server is received. If the number of retries reaches this limit, the RADIUS server is marked as dead, and the MX Series router begins to send requests to other RADIUS servers in the network element.

Options ***attempts***—Number of attempts allowed.

Range: 1 through 10

Default: 3

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring RADIUS Servers on page 74
- Understanding Network Elements on page 57
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

revert-interval (RADIUS Server)

Syntax revert-interval *seconds*;

Hierarchy Level [edit access radius servers *name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the amount of time that must pass after a RADIUS server is first marked dead until it is marked as alive by Junos OS. When Junos OS marks the RADIUS server as alive, it can again send requests to the RADIUS server.

Options ***seconds***—Number of seconds after which a dead server is marked active.

Range: 0 through 4,294,967,295

Default: 300 seconds

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring RADIUS Servers on page 74
- Understanding Network Elements on page 57
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

routing-instance (PCC Action Profiles)

Syntax

```
routing-instance {
  downlink downlink-vrf-name;
  uplink uplink-vrf-name;
}
```

Hierarchy Level

[edit unified-edge pcef pcc-action-profiles *profile-name* steering],
[edit services pcef pcc-action-profiles *profile-name* steering]

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.
Support at the **[edit services pcef pcc-action-profiles *profile-name* steering]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description

Specify the routing instance that a PCC action profile uses for steering traffic.

Options

downlink *downlink-vrf-name*—Use the specified name of the routing instance for downlink traffic (to the access side) or the predefined dynamic interface variable .

uplink *uplink-vrf-name*—Use the specified name of the routing instance for uplink traffic (from the access side).

NOTE: **The routing instances must have been previously configured.**

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware on page 67
- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- *Configuring Policy and Charging Control Action Profiles for Subscriber Management*
- *Understanding Application-Aware Policy Control for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

rule (HTTP Header Enrichment for Tag Rule Set)

Syntax rule *rule-name*;

Hierarchy Level [edit services hcm tag-rule-set]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the tag rule that you want to be a part of the tag rule set.

NOTE: **The tag rule must already be defined at the [edit services hcm] hierarchy level.**

Options ***rule-name***—Name of the tag rule.

To specify multiple tag rules, include the **rule** statement multiple times.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring HTTP Header Enrichment Overview on page 33
- hcm on page 319

Copyright © 2018, Juniper Networks, Inc.

rule (LRF)

Syntax

```
rule lrf-rule-name {
  then {
    report {
      collector collector-name;
      template template-name;
      time-limit time-interval;
      volume-limit volume;
    }
  }
}
```

Hierarchy Level

[edit services lrf profile *profile-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure an LRF rule, which controls how data sessions are logged and reported. In this release, the matching conditions for an LRF rule are identified in a static PCC rule, not in the LRF rule.

Options

lrf-rule-name—Name of the LRF rule.

Range: Up to 63 characters.

The remaining statements are explained separately. Search for a statement in CLI Explorer or click a linked statement in the Syntax section for details.

Required Privilege Level

interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring an LRF Profile for Subscribers on page 152
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152
- *Configuring Logging and Reporting for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

rule-activation-time

Syntax

```
rule-activation-time {
  <day-of-week | day-of-month month>;
  <hour:min>;
}
```

Hierarchy Level

[edit unified-edge pcef pcc-time-of-day-profiles *profile-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Specify the time of day, day of the week or day of the month, or month of the year to activate a PCC rule or rulebase. You can specify the time of day, the day, or both. If you specify the day of the month, you can also specify the month of the year, which results in the yearly activation of the rule or rulebase. Use the same combination of options in the **rule-deactivation-time** statement. If a time zone is configured on the router, the time-of-day settings apply to the configured time zone.

If a day is not specified and the activation time of day setting is later than the deactivation time of day setting, then a rule is deactivated the day after it is activated.

Options

day-of-week—(Optional) Day of the week on which to activate a PCC rule or rulebase.

day-of-month—(Optional) Day of the month on which to activate a PCC rule or rulebase.
Syntax: DAY*n*, where *n* can be from 1 through 31, or **Last-day-of-month**, which depends on the current month.

month—(Optional) Month of the year in which to activate a PCC rule or rulebase.

hour—(Optional) Hour at which to activate a PCC rule or rulebase as a two-digit number from 00 through 23.

min—(Optional) Minute at which to activate a PCC rule or rulebase as a two-digit number from 00 through 59.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Static Time-of-Day PCC Rule Activation and Deactivation in a Junos OS Subscriber Aware PCEF Profile on page 84
- Understanding Static Time-of-Day PCC Rule Activation and Deactivation on page 59

Copyright © 2018, Juniper Networks, Inc.

rule-deactivation-time

Syntax

```
rule-deactivation-time {
  <day-of-week | day-of-month month>;
  <hour:min>;
}
```

Hierarchy Level

[edit unified-edge pcef pcc-time-of-day-profiles *profile-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Specify the time of day, day of the week or day of the month, or month of the year to deactivate a PCC rule or rulebase. You can specify the time of day, the day, or both. If you specify the day of the month, you can also specify the month of the year, which results in the yearly deactivation of the rule or rulebase. Use the same combination of options as in the **rule-activation-time** statement. If a time zone is configured on the router, the time-of-day settings apply to the configured time zone.

If a day is not specified and the deactivation time of day setting is earlier than the activation time of day setting, then a rule is deactivated the day after it is activated.

Options

day-of-week—(Optional) Day of the week on which to deactivate a PCC rule or rulebase.

day-of-month—(Optional) Day of the month on which to deactivate a PCC rule or rulebase.

Syntax: DAY*n*, where *n* can be from 1 through 31, or **Last-day-of-month**, which depends on the current month.

month—(Optional) Month of the year in which to deactivate a PCC rule or rulebase.

hour—(Optional) Hour at which to deactivate a PCC rule or rulebase as a two-digit number from 00 through 23.

min—(Optional) Minute at which to deactivate a PCC rule or rulebase as a two-digit number from 00 through 59.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Static Time-of-Day PCC Rule Activation and Deactivation in a Junos OS Subscriber Aware PCEF Profile on page 84
- Understanding Static Time-of-Day PCC Rule Activation and Deactivation on page 59

Copyright © 2018, Juniper Networks, Inc.

secret (RADIUS Client)

Syntax secret *password*;

Hierarchy Level [edit access radius clients *client-name* accounting]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify a shared secret to be used by the MX Series router and the RADIUS client for accounting.

Options ***password***—Shared secret to use ; it can include spaces if the character string is enclosed in quotation marks. Maximum length is 256 characters.

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring RADIUS Clients That Send Accounting Requests for IP-Based Subscribers on page 106

secret (RADIUS Server)

Syntax secret *password*;

Hierarchy Level [edit access radius servers *name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure a shared secret to be used by the MX Series router and the RADIUS server.

Options ***password***—Shared secret to use.

Range: 1 through 64 characters

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring RADIUS Servers on page 74
- Understanding Network Elements on page 57
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

server (RADIUS Network Elements)

Syntax

```
server name {
  priority priority;
}
```

Hierarchy Level

[edit access radius network-element *name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure a RADIUS server for the network element, which is a load-balanced group of RADIUS servers providing policy management for TDF subscribers. The RADIUS server must already be defined at the **[edit access radius]** hierarchy level. You can configure multiple RADIUS servers under a network element.

Options

name—Name of the RADIUS server.

The remaining statement is described separately.

Required Privilege Level

access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring RADIUS Network Elements on page 77
- Understanding Network Elements on page 57
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53
- Configuring RADIUS Servers on page 74

Copyright © 2018, Juniper Networks, Inc.

servers (RADIUS)

Syntax

```
servers name {
  accounting-port port-number;
  accounting-secret password;
  address server-address;
  allow-dynamic-requests;
  dead-criteria-retries retry-number interval seconds;
  dynamic-requests-secret password;
  port port-number;
  retry attempts;
  revert-interval seconds;
  secret password;
  source-interface interface [ipv4-address address];
  timeout seconds;
}
```

Hierarchy Level

```
[edit access radius]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure a RADIUS server that provides policy management for TDF subscribers.

Options

name—Name of the RADIUS server.

Range: 1 through 32 characters

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring RADIUS Servers on page 74
- Understanding Network Elements on page 57
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

service-mode

Syntax service-mode *service-mode-options*;

Hierarchy Level [edit routing-instance *vrf-name* access address-assignment address-pools *juniper-pool*],
[edit unified-edge gateways tdf *gateway-name*],
[edit unified-edge gateways tdf *gateway-name* domains *domain-name*],
[edit unified-edge tdf *gateway-name* system interface *interface-name*],
[unified-edge gateways tdf *gateway-name* system session-pics interface *interface-name*]

Release Information Statement introduced in Junos OS Release 16.1 on MX Series.

Description Set maintenance mode for a network element so that you can carry out maintenance tasks such as deleting or modifying the element, for example, an address pool.

When in the maintenance mode active phase, you can modify all the valid attributes on the network element. In other cases, you can modify only the non-maintenance mode attributes.

The following network elements must be in maintenance mode before you can modify or delete them:

- Address pools
- AMS interfaces
- PCEF profiles
- Session PICs
- Service PICs
- Static time-of-day settings
- TDF domains
- TDF interfaces
- TDF gateways

Options ***service-mode-options***—Type of the service mode. Currently, only **maintenance** mode is supported.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation
- Maintenance Mode Overview for Subscriber Aware Policy Enforcement on page 166

Copyright © 2018, Juniper Networks, Inc.

service-pics

Syntax

```
service-pics {
  [interface interface-name];
}
```

Hierarchy Level

[edit unified-edge gateways tdf *gateway-name* system]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Specify the service interfaces that represent the service PICs used for anchoring subscriber-aware services in the TDF Gateway.

The remaining statement is explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Service PICs on page 18
- TDF Gateway Service PICs and Session PICs for Subscriber-Aware Traffic Treatment on page 11

Copyright © 2018, Juniper Networks, Inc.

service-set (Subscriber-Aware)

Syntax

```
service-set service-set-name {
  service-set-options {
    subscriber-awareness;
  }
  lrf-profile profile-name;
  pcef-profile pcef-profile-name;
  application-identification-profile app-id-profile-name;
  hcm profilehcm-profile--name;
  nat-rules rule-name;
  nat-rule-sets rule-set-name;
  disable-replication-capability;
  }
  interface-service {
    service-interface interface-name;
  }
}
```

Hierarchy Level

```
[edit services]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure subscriber-aware services by creating a subscriber-aware service set to be applied to a TDF interface.

Options

service-set-name—Name of the service set.

The remaining statements are explained separately.

Required Privilege Level

interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Applying Services to Subscriber-Aware Traffic with a Service Set on page 124
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152

Copyright © 2018, Juniper Networks, Inc.

service-set (TDF Interface)

Syntax

```
service-set service-set-name;
```

Hierarchy Level

```
[edit interfaces mif unit number family inet service input],
[edit interfaces mif unit number family inet service output]
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Apply the service set to the service input and output of the TDF interface (mif) that is part of a TDF domain.

The output service set for the mif is not used by the MX Series router, but it must be configured so that the configuration commit does not fail.

Options ***service-set-name***—Name of the service set that is being applied to the TDF interface.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Applying Services to Subscriber-Aware Traffic with a Service Set on page 124

Copyright © 2018, Juniper Networks, Inc.

session-pics

Syntax

```
session-pics {
  [interface interface-name];
}
```

Hierarchy Level

[edit unified-edge gateways tdf *gateway-name* system]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Specify the service interfaces that represent the session PICs used for the control plane in the TDF gateway.

The remaining statement is explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Session PICs on page 19
- TDF Gateway Service PICs and Session PICs for Subscriber-Aware Traffic Treatment on page 11

Copyright © 2018, Juniper Networks, Inc.

session-pics (Diameter)

Syntax

```
session-pics {
  group {
    group-name {
      [session-pic interface-name];
    }
  }
}
```

Hierarchy Level

[edit unified-edge tdf *gateway-name* diameter network-element *element-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure the session PICs that are serving this Diameter network element for Diameter bindings on this TDF gateway.

NOTE: If you want to set up Diameter bindings for session PICs on the TDF gateway, contact Juniper Networks Professional Services for assistance.

Options

group-name—Name of the session PIC group that is serving the Diameter network element.

interface-name—Name of interface representing session PIC.

Syntax: The interface must be a valid multiservices interface (ams or ms-*a*/*b*/0, where *a* is the Flexible PIC Concentrator [FPC] slot number and *b* is the PIC slot number); for example, ams0, ams1, or ms-1/0/0.

NOTE: The specified interface for the session PIC must already be configured for this TDF gateway.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- diameter on page 275

Copyright © 2018, Juniper Networks, Inc.

shared-secret (RADIUS Snoop Segment)

Syntax shared-secret *secret*;

Hierarchy Level [edit access radius snoop-segments *segment-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure a shared secret to be used by the MX Series router and the RADIUS client. If the shared secrets do not match, the subscriber session is not set up.

Options ***secret***—Shared secret. The maximum length is 64 characters.

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring Snooping of RADIUS Accounting Requests for IP-Based Subscribers on page 113
- Snooping RADIUS Accounting Requests for IP-Based Subscribers Overview on page 94
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

snoop-segment (TDF Domain Selection)

Syntax snoop-segment *snoop-segment-name*;

Hierarchy Level [edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* from]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the snoop segment that matches the RADIUS request.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

Options ***snoop-segment-name***—Name of the snoop segment.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88
- Configuring Snooping of RADIUS Accounting Requests for IP-Based Subscribers on page 113

Copyright © 2018, Juniper Networks, Inc.

snoop-segments (RADIUS)

Syntax

```
snoop-segments snoop-segment-name {
  destination-ip-address destination-address;
  <destination-port destination-port;>
  <request-cache-timeout timeout;>
  shared-secret secret;
  source-interface source-interface;
  <source-ip-address source-address;>
}
```

Hierarchy Level

```
[edit access radius]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Specify which accounting messages to snoop. You must specify at least the destination IP address for the accounting messages, the shared secret, and the source interface.

Options

snoop-segment-name—Name for the snoop segment. The maximum length is 32 characters.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring Snooping of RADIUS Accounting Requests for IP-Based Subscribers on page 113
- Snooping RADIUS Accounting Requests for IP-Based Subscribers Overview on page 94
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

snoop-segments (TDF Gateway)

Syntax snoop-segments [*snoop-segment-name*];

Hierarchy Level [edit unified-edge gateways tdf *gateway-name* aaa]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify one or more snoop segments that control RADIUS accounting request snooping for the TDF gateway. The snoop segments must already be configured at the **[edit access radius]** hierarchy level.

Options ***snoop-segment-name***—Name of a snoop segment.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Snooping of RADIUS Accounting Requests for IP-Based Subscribers on page 113
- Snooping RADIUS Accounting Requests for IP-Based Subscribers Overview on page 94
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

source (Application Identification)

Syntax source ip *ip-address-prefix*;

Hierarchy Level [edit services application-identification application *application-name* address-mapping]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the source IP address for address mapping-based application identification.

Options ***ip-address-prefix***—IP address and prefix for matching.

Required Privilege Level view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation

- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25
- Application Identification Overview on page 23

source-address (LRF Profile)

Syntax source-address *source-address*;

Hierarchy Level [edit services lrf profile *profile-name* collector *collector-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the source address to be used when exporting data to the collector.

Options ***source-address***—IP address to be used as the source address.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring an LRF Profile for Subscribers on page 152
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152
- *Configuring Logging and Reporting for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

source-interface

Syntax source-interface *interface* ipv4-address *address*;

Hierarchy Level [edit access radius clients *client-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the MX Series router interface and IPv4 address that receive RADIUS requests from the GGSN, PGW, or BNG RADIUS client.

Options ***interface***—Name of the interface.

address—IPv4 address on the MX Series router.

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring RADIUS Clients That Send Accounting Requests for IP-Based Subscribers on page 106

 Copyright © 2018, Juniper Networks, Inc.

source-interface (RADIUS Server)

Syntax source-interface *interface* [ipv4-address *address*];

Hierarchy Level [edit access radius servers *name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the source interface and one or more IPv4 addresses on the MX Series router that receive RADIUS requests from which the RADIUS requests are sent to the RADIUS server.

Options ***interface***—Source interface that sends the RADIUS requests.

address—Source IPv4 address that sends the RADIUS requests. You can specify multiple source IPv4 addresses.

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring RADIUS Servers on page 74
- Understanding Network Elements on page 57
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

source-interface (RADIUS Snoop Segment)

Syntax source-interface *source-interface*;

Hierarchy Level [edit access radius snoop-segments *segment-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the interface of the MX Series router that receives accounting packets from the access network to be snooped.

Options ***source-interface***—Name of the interface.

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring Snooping of RADIUS Accounting Requests for IP-Based Subscribers on page 113
- Snooping RADIUS Accounting Requests for IP-Based Subscribers Overview on page 94
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

source-ip-address (RADIUS Snoop Segment)

Syntax

```
source-ip-address source-address;
```

Hierarchy Level

```
[edit access radius snoop-segments segment-name]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Specify the source IP address of accounting requests from a GGSN, PGW, or BNG to snoop. If you do not enter a source IP address, accounting requests from any IP address can be snooped.

Options

source-address—Source IPv4 address.

Required Privilege Level

access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring Snooping of RADIUS Accounting Requests for IP-Based Subscribers on page 113
- Snooping RADIUS Accounting Requests for IP-Based Subscribers Overview on page 94
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

static-policy-control

Syntax

```
static-policy-control {
  pcc-rules {
    [rule-name precedence number <time-of-day-profile profile-name>];
  }
  pcc-rulebases {
    [rulebase-name <time-of-day-profile profile-name>];
  }
}
```

Hierarchy Level

[edit unified-edge pcef profiles *profile-name*],
[edit services pcef profiles *profile-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef profiles *profile-name*]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description

Configure static policy control for the policy and charging control (PCC) rules or PCC rulebase in a policy and charging enforcement function (PCEF) profile. You can configure a maximum of 32 PCC rules in a PCEF profile. There is no limit to the number of PCC rulebases you can configure in a PCEF profile.

NOTE: For Junos OS Subscriber Aware, you can configure only one of the following statements in a PCEF profile: **aaa-policy-control**, **static-policy-control**, or **dynamic-policy-control**. For Junos OS Subscriber Management, you can configure only **static-policy-control**.

If you are using Junos OS Subscriber Aware, configure static policy control at the **[edit unified-edge pcef profiles *profile-name*]** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, configure static policy control at the **[edit services pcef profiles *profile-name*]** hierarchy level.

The remaining statements are explained separately. Search for a statement in CLI Explorer or click a linked statement in the Syntax section for details.

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Copyright © 2018, Juniper Networks, Inc.

Related Documentation

- Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Static Policies on page 81
- *Configuring a Policy and Charging Enforcement Function Profile for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

steering

Syntax

```
steering {
  keep-existing-steering;
  path {
    ipv4-address ipv4-address;
    ipv6-address ipv6-address;
  }
  routing-instance {
    downlink downlink-vrf-name;
    uplink uplink-vrf-name;
  }
}
```

Hierarchy Level

[edit unified-edge pcef pcc-action-profiles *profile-name*],
[edit services pcef pcc-action-profiles *profile-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef pcc-action-profiles *profile-name*]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description

Specify the method that a PCC action profile uses for steering traffic

If you are using Junos OS Subscriber Aware, configure steering at the **[edit unified-edge pcef pcc-action-profiles *profile-name*]** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, configure the PCC action profile at the **[edit services pcef pcc-action-profiles *profile-name*]** hierarchy level. The following options are not applicable to subscriber management:

- **path**
- **keep-existing-steering** and its options

The remaining statements are explained separately. Search for a statement in CLI Explorer or click a linked statement in the Syntax section for details.

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware on page 67

Copyright © 2018, Juniper Networks, Inc.

- Understanding Predefined Policy and Charging Control Rules for Subscriber-Aware Traffic Treatment on page 47
- *Configuring Policy and Charging Control Action Profiles for Subscriber Management*
- *Understanding Application-Aware Policy Control for Subscriber Management*

string

Syntax

```
string {
  apply-groups [group-names];
  apply-groups-except [group-names];
  equals;
  has-prefix;
  has-suffix;
  matches;
}
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  attribute name format]
```

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the custom AVP attribute's format as a string and the value to match for the incoming RADIUS request from the IP-based subscriber.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

subscriber-address

Syntax

```
subscriber-address {
  apply-groups [group-names];
  apply-groups-except [group-names];
  inet {
    apply-groups [group-names];
    apply-groups-except [group-names];
    pool pool-name;
  }
  inet6 {
    apply-groups [group-names];
    apply-groups-except [group-names];
    pool pool-name;
  }
}
```

Hierarchy Level

[edit unified-edge gateways tdf *gateway-name* domains *domain-name* ip-subscriber]

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the address pool that contains the source IP addresses for IP-based subscriber packets that can undergo TDF processing.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

subscriber-awareness (Service Set Options)

Syntax

```
subscriber-awareness;
```

Hierarchy Level

```
[edit services service-set service-set-name service-set-options]
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Enable subscriber awareness on the service set.

Default If you do not include the **subscriber-awareness** statement, then subscriber-aware services cannot be provided.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Applying Services to Subscriber-Aware Traffic with a Service Set on page 124

Copyright © 2018, Juniper Networks, Inc.

subscriber-exclude-prefix

Syntax

```
subscriber-exclude-prefix {
  apply-groups [group-names];
  apply-groups-except [group-names];
  family {
    inet {
      apply-groups [group-names];
      apply-groups-except [group-names];
      network address net-mask;
    }
    inet6 {
      apply-groups [group-names];
      apply-groups-except [group-names];
      network address net-mask;
    }
  }
}
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domains domain-name]
```

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the network prefix of source IP addresses for uplink packets and destination IP addresses for downlink packets that do not undergo TDF processing.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Configuring IFL-Based TDF Subscribers and Properties with a TDF Domain on page 117
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based and IFL-Based TDF Subscribers Overview on page 88
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

subscriber-type (TDF Domain)

Syntax

```
subscriber-type (ip | ifl);
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domains domain-name]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure the type of subscriber that this domain is applied to — an IP-based subscriber or an IFL-based (interface-based) subscriber. If you do not include this statement, **subscriber-type ip** is used.

Options

ip—(Default) Apply the TDF domain to IP-based subscribers, for which a RADIUS accounting request is sent to the MX Series router. An individual subscriber session is created for each unique source IP address.

ifl—Apply the TDF domain to IFL-based subscribers, which are defined by a set of interfaces. One subscriber session is created for all traffic that is received on those interfaces.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Configuring IFL-Based TDF Subscribers and Properties with a TDF Domain on page 117
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- Understanding the Definition of a Set of IFL-Based Subscriber Properties with a TDF Domain on page 96

Copyright © 2018, Juniper Networks, Inc.

subscription-id

Syntax

```
subscription-id {
  apply-groups [group-names];
  apply-groups-except [group-names];
  constant value;
  subscription-id-options {
    entry-name {
      id-components {
        use-class;
        use-imsi;
        use-msisdn;
        use-nai;
        use-nas-port;
        use-nas-port-id;
        use-realm;
        use-username;
      }
    }
  }
  use-class {
    regex "value";
    pattern "pattern";
    subscription-id-type (imsi | msisdn | nai | private | sip-uri);
  }
}
```

Hierarchy Level

[edit unified-edge gateways tdf *gateway-name* domains *domain-name* ip-subscriber]

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify how the Subscription-Id is constructed for the Diameter credit control request (CCR) message that is sent from the TDF to the PCRF for IP-based subscribers belonging to the TDF domain.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

subscription-id-options

Syntax

```
subscription-id-options {
  [entry-name] {
    id-components {
      use-class;
      use-imsi;
      use-msisdn;
      use-nai;
      use-nas-port;
      use-nas-port-id;
      use-realm;
      use-username;
    }
  }
}
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domains domain-name ip-subscriber
  subscription-id]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Specify a method for constructing the Subscription-Id for the RADIUS credit control request (CCR) message that is sent from the TDF to the PCRF for IP-based subscribers belonging to the TDF domain. To specify multiple methods, include the *entry-name* option multiple times.

Options

entry-name—Identifier for the Subscription-Id construction method.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

subscription-id-type (Class Attribute)

Syntax

```
subscription-id-type (imsi | msisdn | nai | private | sip-uri);
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domains domain-name subscription-id
  use-class]
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the subscription ID type when the Class attribute is used for the subscription ID.

Options

imsi—Use the IMSI subscriber type.

msisdn—Use the MSISDN (E164) subscriber type.

nai—Use the NAI subscriber type.

private—Use the Private subscriber type.

sip-uri—Use the SIP URI name subscriber type.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100

Copyright © 2018, Juniper Networks, Inc.

tag (HTTP Header Enrichment)

Syntax

```
tag tag-name {
  encrypt {
    hash algorithm;
    prefix hash-prefix;
  }
  ipv4-mask ipv4-mask;
  ipv6-mask ipv6-mask;
  ipv4-or-value ipv4-or-value;
  ipv6-or-value ipv6-or-value;
  tag-attribute tag-attr-name;
  tag-header header;
  tag-separator separator;
}
```

Hierarchy Level

[edit services hcm tag-rule *rule-name* term *term-number* then]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure the tags to be applied to the HTTP headers. If you configure a tag, you must include the **tag-header** statement.

Options

tag-name—Name of the tag.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring HTTP Header Enrichment Overview on page 33
- Configuring Tag Rules on page 35
- Configuring HCM Profiles and Assigning Tag Rules on page 40
- Junos Web Aware HTTP Header Enrichment Overview on page 33.

Copyright © 2018, Juniper Networks, Inc.

tag-attribute (HTTP Header Enrichment)

Syntax tag-attribute [*tag-attr-name*];

Hierarchy Level [edit services hcm]

Release Information Statement introduced in Junos OS Release 16.1 on MX Series.

Description Specify one or more tag attributes that can be used in tag rules for HTTP header enrichment.

These attributes are stored in the subscriber database for subscribers. After these attributes are configured, they can be used in the tag rules. HTTP tag rules can be configured to choose one or more of these attributes to insert in the HTTP header.

Options *tag-attr-name*—Tag attribute. To specify multiple attributes at one time, include the attributes in square brackets ([]). The supported attributes are **apn**, **ggsnipv4**, **ggsnipv6**, **imei**, **imsi**, **ipv4addr**, **ipv6addr**, and **msisdn**.

Range: 1 through 63 alphanumeric characters

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring HTTP Header Enrichment Overview on page 33
- Configuring Tag Rules on page 35
- Junos Web Aware HTTP Header Enrichment Overview on page 33.

Copyright © 2018, Juniper Networks, Inc.

tag-attribute (HTTP Header Enrichment Tag Rule)

Syntax tag-attribute [*tag-attr-name*];

Hierarchy Level [edit services hcm tag-rule *rule-name* term *term-number* then tag *tag-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify one or more tag attributes (for the tag header and separator) to insert into the HTTP header.

NOTE: **The tag attribute specified here must already be defined at the [edit services hcm] hierarchy level.**

Options *tag-attr-name*—Tag attribute. To specify multiple attributes at one time, include the attributes in square brackets ([]). The supported attributes are **apn**, **ggsnipv4**, **ggsnipv6**, **imei**, **imsi**, **ipv4addr**, **ipv6addr**, and **msisdn**.

Range: 1 through 63 alphanumeric characters

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring HTTP Header Enrichment Overview on page 33
- Configuring Tag Rules on page 35

Copyright © 2018, Juniper Networks, Inc.

tag-header (HTTP Header Enrichment)

Syntax tag-header *header*;

Hierarchy Level [edit services hcm tag-rule *rule-name* term *term-number* then tag *tag-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the tag header for the tag to be inserted into the HTTP header. This is a required configuration.

You can configure a total of 16 unique tag headers for all the tag rules you configure.

Options *header*—Tag header.

Values: You *cannot* use the following values: **accept**, **accept-charset**, **accept-encoding**, **accept-language**, **authorization**, **expect**, **host**, **if-match**, **if-modified-since**, **if-none-match**, **if-range**, **if-unmodified-since**, **max-forwards**, **proxy-authorization**, **referer**, **user-agent**, or **x-moz**. These header values are reserved; you cannot configure them.

Range: 1 through 63 alphanumeric characters

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring HTTP Header Enrichment Overview on page 33
- Configuring Tag Rules on page 35
- Configuring HCM Profiles and Assigning Tag Rules on page 40
- Junos Web Aware HTTP Header Enrichment Overview on page 33.

Copyright © 2018, Juniper Networks, Inc.

tag-operation (HTTP Header Enrichment)

Syntax tag-operation (add | delete | modify);

Hierarchy Level [edit services hcm tag-rule *rule-name* term *term-name* then tag *tag-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the operation to be performed on the specified tag of the tag rule set.

NOTE: The tag rule must already be defined at the **[edit services hcm]** hierarchy level.

Options

add—Add the specified tag with previously existing tag in the tag rule set.

delete—Delete the specified tag from the tag rule set.

modify—Modify the existing tag in the tag rule set.

Required Privilege Level

interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring HTTP Header Enrichment Overview on page 33
- hcm on page 319

Copyright © 2018, Juniper Networks, Inc.

tag-rule (Profiles for HTTP Header Enrichment)

Syntax tag-rule *rule-name*;

Hierarchy Level [edit services hcm profile *profile-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the tag rule to be associated with the HCM profile.

NOTE: **The tag rule specified here must already be defined at the [edit services hcm] hierarchy level.**

Options ***rule-name***—Name of the tag rule.

Range: 1 through 63 alphanumeric characters

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring HTTP Header Enrichment Overview on page 33
- Configuring HCM Profiles and Assigning Tag Rules on page 40

Copyright © 2018, Juniper Networks, Inc.

tag-rule (HTTP Header Enrichment)

Syntax

```
tag-rule rule-name {
  term term-number {
    from {
      destination-address {
        (any-ipv4 | any-ipv4 except);
        (any-ipv6 | any-ipv6 except);
        (any-unicast | any-unicast except);
        (prefix | prefix except);
      }
      destination-address-range {
        high address low address <except>;
      }
      destination-port-range {
        high port-number low port-number;
      }
      destination-ports value;
      destination-prefix-list {
        (prefix-name | prefix-name except);
      }
    }
    then {
      count;
      tag tag-name {
        encrypt {
          hash algorithm;
          prefix hash-prefix;
        }
        ipv4-mask ipv4-mask;
        ipv6-mask ipv6-mask;
        ipv4-or-value ipv4-or-value;
        ipv6-or-value ipv6-or-value;
        tag-attribute tag-attr-name;
        tag-header header;
        tag-separator separator;
      }
    }
  }
}
```

Hierarchy Level

```
[edit services hcm]
```

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Configure the tag rules that enrich HTTP headers with the appropriate tags.

You must configure at least one term for a tag rule, but you can configure multiple terms. Terms are evaluated in the order they are configured. If a data packet matches all the criteria in the **from** statement in any of the terms, then the actions specified in the **then** statement are applied. If the **from** statement does not identify any criteria, then all traffic

Copyright © 2018, Juniper Networks, Inc.

matches. After a term matches a data packet, further terms are not evaluated. If no terms match, then the HTTP header is not enriched.

For subscriber traffic under static policy control, a tag rule is used if it is included in the HCM profile specified in a PCC rule that the traffic matches. For subscribers under dynamic policy control, a message from the PCRF identifies the configured HCM profile and tag rules to use for HTTP header enrichment.

Options *rule-name*—Name of the tag rule.

Range: 1 through 63 alphanumeric characters

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring HTTP Header Enrichment Overview on page 33
- Configuring Tag Rules on page 35
- Configuring HCM Profiles and Assigning Tag Rules on page 40
- Junos Web Aware HTTP Header Enrichment Overview on page 33.

tag-rules (Service Set)

Syntax

```
[tag-rules rule-name;]
```

Hierarchy Level

```
[edit services service-set service-set-name]
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify one or more HTTP header enrichment tag rules to include in the service set. You can configure multiple tag rules. If you specify any tag rules, you cannot specify a tag rule set.

Options *rule-name*—Name of the tag rule.

Range: 1 through 63 alphanumeric characters

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Applying Services to Subscriber-Aware Traffic with a Service Set on page 124
- Configuring HTTP Header Enrichment Overview on page 33

Copyright © 2018, Juniper Networks, Inc.

tag-rule-set (HTTP Header Enrichment)

Syntax

```
tag-rule-set rule-set-name {
  [rule rule-name];
}
```

Hierarchy Level

```
[edit services hcm]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure the tag rule set for HTTP header enrichment so that you can group multiple configured tag rules into one tag rule set.

Options

rule-set-name—Name of the tag rule set.

The remaining statement is explained separately. See CLI Explorer.

Required Privilege Level

interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring HTTP Header Enrichment Overview on page 33
- hcm on page 319

Copyright © 2018, Juniper Networks, Inc.

tag-rule-sets (Service Set)

Syntax tag-rule-sets *rule-set-name*;

Hierarchy Level [edit services service-set *service-set-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the HTTP header enrichment tag rule set included in the service set. You can configure only one tag rule set. If you specify a tag rule set, you cannot specify a tag rule.

Options ***rule-set-name***—Name of the tag rule set.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation
- Applying Services to Subscriber-Aware Traffic with a Service Set on page 124
- Configuring HTTP Header Enrichment Overview on page 33

tag-separator (HTTP Header Enrichment)

Syntax tag-separator *separator*;

Hierarchy Level [edit services hcm tag-rule *rule-name* term *term-number* then tag *tag-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the tag separator for the tag to be inserted into the HTTP header.

Options ***separator***—Tag separator. You may use a forward slash (/) or pipe (|).
Default: / (forward slash)

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation
- Configuring HTTP Header Enrichment Overview on page 33
- Configuring Tag Rules on page 35
- Configuring HCM Profiles and Assigning Tag Rules on page 40
- Junos Web Aware HTTP Header Enrichment Overview on page 33.

Copyright © 2018, Juniper Networks, Inc.

tag-value (HTTP Header Enrichment)

Syntax tag-value *value*;

Hierarchy Level [edit services hcm tag-rule then tag]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the tag value for the specified tag name.

NOTE: The tag rule must already be defined at the [edit services hcm] hierarchy level.

Options ***value***—String of up to 16 alphanumeric characters

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring HTTP Header Enrichment Overview on page 33
- hcm on page 319

Copyright © 2018, Juniper Networks, Inc.

tags (Application Identification)

Syntax tags *tag-name tag-value*;

Hierarchy Level [edit services application-identification application *application-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify an application tag that provides general information about the application, such as associated risk factors, technology, and the type of traffic. The tag consists of a user-defined name and value.

Options ***tag-name***—Name for the tag, which is a textual string.

tag-value—Value for the tag.

Required Privilege Level view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation

- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25
- Application Identification Overview on page 23Application Identification Overview on page 23

Copyright © 2018, Juniper Networks, Inc.

targets

Syntax

```
targets {
  target-name {
    <destination-host hostname>;
    destination-realm realm-name;
    network-element element-name;
    priority priority-value;
  }
}
```

Hierarchy Level [edit unified-edge diameter-profiles gx-profile *profile-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the targets for this Diameter profile.

Options ***target-name***—Name of the target.

destination-host *hostname*—(Optional) Use the name of the destination host associated with this target.

destination-realm *realm-name*—Use the name of the destination realm associated with this target.

network-element *element-name*—Use the name of the network element.

NOTE: The Diameter network element must be previously configured at the **[edit access diameter network-element]** hierarchy level.

Range: 1 through 32 characters

priority *priority-value*—Use the specified priority for the target within the Diameter profile. A value with a lower number has a higher priority. For load balancing, configure the targets with the same priority.

NOTE: Failover handling depends on how the policy for the application is configured. For example, switching between the primary and secondary online charging servers set with the appropriate priority can occur only when the failover handling policy is configured to do so.

Range: 1 through 65,535

Copyright © 2018, Juniper Networks, Inc.

Required Privilege Level
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation
- gx-profile on page 316

tdf (Unified Edge)

Syntax
```
tdf gateway-name;
```

Hierarchy Level
```
[edit unified-edge gateways]
```

Release Information
Statement introduced in Junos OS Release 17.1 on MX Series.

Description
Specify the name to be used for the traffic detection function (TDF) gateway.

Options
gateway-name—Name of the gateway.
Range: 1 through 16 characters.

Required Privilege Level
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation
- TDF Gateway Service PICs and Session PICs for Subscriber-Aware Traffic Treatment on page 11

Copyright © 2018, Juniper Networks, Inc.

tdf-interface

Syntax tdf-interface mif.*number*;

Hierarchy Level [edit unified-edge gateways tdf *gateway-name* domains *domain-name*]

Release Information Statement introduced in Junos OS Release 16.1 on MX Series.

Description Specify the TDF interface that the TDF domain uses. A TDF interface is different from other types of interfaces, and is associated with the TDF service set that is used for the TDF subscriber.

NOTE: The TDF interface must have been previously configured at the [edit interfaces] hierarchy level.

The TDF interface and the access-facing interfaces in the TDF domain must be included in the same VRF routing instance.

Options **mif.*number***—Use the specified TDF interface unit number.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100
- Understanding the Definition of a Set of IP-Based Subscriber Properties with a TDF Domain on page 89
- IP-Based Subscriber Setup Overview on page 88
- Configuring TDF Interface to Access Interface Associations in VRFs on page 120
- Configuring TDF Interface to Access Interface Associations in VRFs on page 120
- Configuring a TDF Logical Interface on page 120

Copyright © 2018, Juniper Networks, Inc.

template (LRF Profile)

Syntax

```
template template-name {
  format ipfix;
  template-tx-interval tx-time;
  template-type template-type;
  trigger-type (session-close | volume);
}
```

Hierarchy Level

```
[edit services lrf profile profile-name]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure a template, which specifies a set of data to be transmitted. This template can be specified in LRF rules.

Options

template-name—Name for the template.

Range: Up to 32 characters.

The remaining statements are explained separately. Search for a statement in CLI Explorer or click a linked statement in the Syntax section for details.

Required Privilege Level

interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring an LRF Profile for Subscribers on page 152
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152
- *Configuring Logging and Reporting for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

template (LRF Rule)

Syntax template *template-name*;

Hierarchy Level [edit services lrf profile *profile-name* rule *lrf-rule-name* then report]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the template that identifies the type of data to report if the LRF rule is matched.

Options ***template-name***—Name of the template that is used. The referenced template must be configured.

Range: Up to 32 characters.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring an LRF Profile for Subscribers on page 152
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152
- *Configuring Logging and Reporting for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

template-tx-interval (LRF Profile)

Syntax template-tx-interval *tx-time*;

Hierarchy Level [edit services lrf profile *profile-name* template *template-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the interval at which to retransmit the template to the collector.

Options ***tx-time***—Time interval in seconds.

Default: 60

Range: 10 through 600

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring an LRF Profile for Subscribers on page 152
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152
- *Configuring Logging and Reporting for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

template-type (LRF Profile)

Syntax template-type *template-type*;

Hierarchy Level [edit services lrf profile *profile-name* template *template-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the template types for the template, which specify the data fields to include. You must configure at least one type, and you can configure multiple types.

Options ***template-type***—Template type. You must configure at least one of the following types, and you can configure multiple types:

- **device-data**—Use data fields specific to the device collecting the logging feed.
- **dns**—Use the DNS response time data field.
- **flow-id**—Use the Flow ID data field.
- **http**—Use data fields for the HTTP metadata from header fields.
- **ifl-subscriber**—Use data fields specific to interface-based subscribers.
- **ipflow**—Use data fields for the uplink and downlink octets and bytes.
- **ipflow-extended**—Use data fields for the service set name, routing instance, and payload timestamps.
- **ipflow-tcp**—Use data fields for TCP-related timestamps.
- **ipflow-tcp-ts**—Use IBM-specific data fields for TCP-related timestamps.When configuring a **ipflow-tcp-ts** template, configure **vendor-support ibm** at the **[edit services lrf profile *profile-name*]** hierarchy level to avoid a commit warning.
- **ipflow-ts**—Use data fields for the flow start and end timestamps.
- **ipv4**—Use data fields for the basic source and destination IPv4 information.
- **ipv4-extended**—Use data fields for the elements of IPv4 extended fields.
- **ipv6**—Use data fields for the basic source and destination IPv6 information.
- **ipv6-extended**—Use data fields for the elements of IPv6 extended fields.
- **l7-app**—Use data fields for the Layer 7 application.
- **mobile-subscriber**—Use data fields specific to mobile subscribers.
- **pcc**—Use the PCC rule name data field.
- **status-code-dist**—Use data fields for the HTTP or DNS status codes.
- **subscriber-data**—Use data fields for Generic Subscriber information that can be included with wireless (mobile) subscribers or wireline subscribers.

Copyright © 2018, Juniper Networks, Inc.

- **transport-layer**—Use data fields for the transport layer.
- **video**—Use data fields for video traffic.
- **wireline-subscriber**—Use the UserName data field for wireline subscribers.

Required Privilege Level

interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring an LRF Profile for Subscribers on page 152
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152
- *Configuring Logging and Reporting for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

term (HTTP Header Enrichment)

Syntax

```
term term-number {
  from {
    destination-address {
      (any-ipv4 | any-ipv4 except);
      (any-ipv6 | any-ipv6 except);
      (any-unicast | any-unicast except);
      (prefix | prefix except);
    }
    destination-address-range {
      high address low address <except>;
    }
    destination-port-range {
      high port-number low port-number;
    }
    destination-ports value;
    destination-prefix-list {
      (prefix-name | prefix-name except);
    }
  }
  then {
    count;
    tag tag-name {
      encrypt {
        hash algorithm;
        prefix hash-prefix;
      }
      ipv4-mask ipv4-mask;
      ipv6-mask ipv6-mask;
      ipv4-or-value ipv4-or-value;
      ipv6-or-value ipv6-or-value;
      tag-attribute tag-attr-name;
      tag-header header;
      tag-separator separator;
    }
  }
}
```

Hierarchy Level

```
[edit services hcm tag-rule rule-name]
```

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Configure a term in a tag rule, which is used to enrich HTTP headers with the appropriate tags. You must configure at least one term for a tag rule, but you can configure multiple terms. Terms are evaluated in the order they are configured. If a data packet matches all the criteria in the **from** statement in any of the terms, then the actions specified in the **then** statement are applied. If the **from** statement does not identify any criteria, then all traffic matches. After a term matches a data packet, further terms are not evaluated. If no terms match, then the HTTP header is not enriched.

Copyright © 2018, Juniper Networks, Inc.

For subscriber traffic under static policy control, a tag rule is used if it is included in the HCM profile specified in a PCC rule that the traffic matches. For subscribers under dynamic policy control, a message from the PCRF identifies the configured HCM profile and tag rules to use for HTTP header enrichment.

Options

term-number—Number for the term.

Range: 1 through 32,767

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring HTTP Header Enrichment Overview on page 33
- Configuring Tag Rules on page 35
- Configuring HCM Profiles and Assigning Tag Rules on page 40
- Junos Web Aware HTTP Header Enrichment Overview on page 33.

Copyright © 2018, Juniper Networks, Inc.

term (TDF Domain Selection)

Syntax

```
term term-name {
  apply-groups [group-names];
  apply-groups-except [group-names];
  from {
    3gpp-imsi {
      equals value;
      has-prefix value;
      has-suffix value;
      matches value;
    }
    attribute name {
      code numeric-code;
      vendor-id vendor-id;
      format {
        integer {
          apply-groups [group-names];
          apply-groups-except [group-names];
          equals {
            apply-groups [group-names];
            apply-groups-except [group-names];
            value;
          }
          greater-than value;
          less-than value;
        }
        string {
          apply-groups [group-names];
          apply-groups-except [group-names];
          equals {
            apply-groups [group-names];
            apply-groups-except [group-names];
            value;
          }
          has-prefix{
            apply-groups [group-names];
            apply-groups-except [group-names];
            value;
          }
          has-suffix {
            apply-groups [group-names];
            apply-groups-except [group-names];
            value;
          }
          matches {
            apply-groups [group-names];
            apply-groups-except [group-names];
            value;
          }
        }
        time {
          apply-groups [group-names];
```

Copyright © 2018, Juniper Networks, Inc.

```
        apply-groups-except [group-names];
        equals {
          apply-groups [group-names];
          apply-groups-except [group-names];
          value;
        }
        greater-than value;
        less-than value;
      }
      v4address {
        apply-groups [group-names];
        apply-groups-except [group-names];
        equals {
          apply-groups [group-names];
          apply-groups-except [group-names];
          value;
        }
      }
      v6address {
        apply-groups [group-names];
        apply-groups-except [group-names];
        equals {
          apply-groups [group-names];
          apply-groups-except [group-names];
          value;
        }
      }
      v6prefix {
        apply-groups [group-names];
        apply-groups-except [group-names];
        equals {
          apply-groups [group-names];
          apply-groups-except [group-names];
          value;
        }
      }
    }
  }
  called-station-id {
    equals value;
    matches value;
  }
  calling-station-id {
    equals value;
    matches value;
  }
  class {
    equals value;
    has-prefix value;
    has-suffix value;
    matches value;
  }
  client client-name;
  framed-ip-address {
    equals value;
```


Copyright © 2018, Juniper Networks, Inc.

```
    }
    framed-ipv6-prefix {
      equals value;
    }
    nas-ip-address {
      equals value;
    }
    snoop-segment snoop-segment-name;
    user-name {
      equals value;
      has-prefix value;
      has-suffix value;
      matches value;
    }
  }
  then {
    domain tdf-domain-name;
    pcef-profile pcef-profile-name;
  }
}
```

Hierarchy Level [edit unified-edge gateways tdf *gateway-name* domain-selection]

Release Information Statement introduced in Junos OS Release 16.1 on MX Series.

Copyright © 2018, Juniper Networks, Inc.

Description Configure a term that can be used to select the TDF domain for an IP-based subscriber. You can configure multiple terms (up to 10 terms) for the TDF domain selection, and each term is applied in the order in which it is configured. You can specify multiple match conditions within the **from** statement of a term, and all of the conditions have to match. If the incoming RADIUS request from the subscriber matches the criteria in a term, then the TDF domain specified in the **then** statement of the term is used to create the TDF subscriber session.

A term can also be used to select a PCEF profile for a an IP-based subscriber. Setting up a term so that it is used to select a profile is required if the TDF domain selected for a subscriber does not specify a PCEF profile or you want to allow different members of the same TDF domain to have different PCEF profiles.

After a term matches and a TDF domain is selected, further terms are not evaluated when the PCEF profile is specified in either the **then** statement or in the selected TDF domain. If a PCEF profile is not specified in either the **then** statement or in the selected TDF domain, further terms are evaluated to find a PCEF profile for the subscriber.

If no TDF domain is selected for a subscriber, then a TDF subscriber session is not created.

NOTE: The TDF domain must have been previously configured at the **[edit unified-edge gateways tdf *gateway-name* domains]** hierarchy level.

The PCEF profile must have been previously configured at the **[edit unified-edge pcef]** hierarchy level.

Options ***term-name***—Identifier for the term.

Range: 1 through 50 alphanumeric characters.

The remaining statements are explained separately. See CLI Explorer.

NOTE: You must configure at least one term.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

then (HTTP Header Enrichment)

Syntax

```
then {
  count;
  tag tag-name {
    encrypt {
      hash algorithm;
      prefix hash-prefix;
    }
    ipv4-mask ipv4-mask;
    ipv6-mask ipv6-mask;
    ipv4-or-value ipv4-or-value;
    ipv6-or-value ipv6-or-value;
    tag-attribute tag-attr-name;
    tag-header header;
    tag-separator separator;
  }
}
```

Hierarchy Level

```
[edit services hcm tag-rule rule-name term term-number]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Specify the actions to be taken if the criteria for the tag rule are matched. For subscribers under static policy control, the matching conditions for a tag rule are determined by the PCC rule that uses the HCM profile specifying the tag rule. For subscribers under dynamic policy control, a message from the PCRF identifies the configured HCM profile to use for HTTP header enrichment.

NOTE: You must configure this statement and include at least one action to be taken for the tag rule term.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring HTTP Header Enrichment Overview on page 33
- Configuring Tag Rules on page 35
- Configuring HCM Profiles and Assigning Tag Rules on page 40
- Junos Web Aware HTTP Header Enrichment Overview on page 33.

Copyright © 2018, Juniper Networks, Inc.

then (LRF rule)

Syntax

```
then {
  report {
    collector collector-name;
    template template-name;
    time-limit time-interval;
    volume-limit volume;
  }
}
```

Hierarchy Level

[edit services lrf profile *profile-name* rule *lrf-rule-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure the actions to take if the LRF rule is matched.

The remaining statements are explained separately. Search for a statement in CLI Explorer or click a linked statement in the Syntax section for details.

Required Privilege Level

interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring an LRF Profile for Subscribers on page 152
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152
- *Configuring Logging and Reporting for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

then (PCC Rules)

Syntax

```
then {
  pcc-action-profile profile-name;
}
```

Hierarchy Level

[edit unified-edge pcef pcc-rules *rule-name*],
[edit services pcef pcc-rules *rule-name*]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef pcc-rules *rule-name*]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description

Specify the policy and charging control (PCC) action profile for a PCC rule. The PCC action profile specifies the actions to apply to subscriber traffic that matches any of the **from** statements in the PCC rule. A PCC rule configuration must include the **then** statement and a PCC action profile. The referenced PCC action profile must be configured.

If you are using Junos OS Subscriber Aware, specify the name of the PCC action profile at the **[edit unified-edge pcef pcc-rules *rule-name*]** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, specify the name of the PCC action profile at the **[edit services pcef pcc-rules *rule-name*]** hierarchy level.

The remaining statements are explained separately. Search for a statement in CLI Explorer or click a linked statement in the Syntax section for details.

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring Policy and Charging Control Rules on page 70
- Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware on page 67
- *Configuring Policy and Charging Control Action Profiles for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

then (TDF Domain Selection)

Syntax

```
then {
  domain tdf-domain-name;
  pcef-profile pcef-profile-name;
}
```

Hierarchy Level

[edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name*]

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the TDF domain or the PCEF profile to be selected when the criteria specified in the domain selection statement match.

NOTE: This statement is required even if you have not specified any match criteria. The TDF domain must have been previously configured at the **[edit unified-edge gateways tdf *gateway-name* domains]** hierarchy level.

The PCEF profile must have been previously configured at the **[edit unified-edge pcef]** hierarchy level.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

time

Syntax

```
time {
  apply-groups [group-names];
  apply-groups-except [group-names];
  equals {
    apply-groups [group-names];
    apply-groups-except [group-names];
    value;
  }
  greater-than value;
  less-than value;
}
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  attribute name format]
```

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the custom AVP attribute's format as time and the value to match for the incoming RADIUS request from the IP-based subscriber.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

time-limit (LRF Rule)

Syntax time-limit *time-interval*;

Hierarchy Level [edit services lrf profile *profile-name* rule *lrf-rule-name* then report]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the time limit to be used for reporting. The template that the LRF rule is using must have **trigger-type time** configured.

Options ***time-interval***—The time limit in seconds.

Range: 60 through 1800

Default: 300

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring an LRF Profile for Subscribers on page 152
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152

Copyright © 2018, Juniper Networks, Inc.

timeout (Diameter Network Element)

Syntax timeout *seconds*;

Hierarchy Level [edit access diameter network-element *element-name* peer *peer-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the amount of time to wait for a response from this peer before transmitting the request to another peer.

Options ***seconds***—Amount of time to wait before transmitting the request.

Range: 1 through 100 seconds

Default: 4 seconds

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- diameter on page 273

Copyright © 2018, Juniper Networks, Inc.

timeout (RADIUS Server)

Syntax timeout *seconds*;

Hierarchy Level [edit access radius servers *name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the amount of time that the MX Series router waits to receive a response from a RADIUS server before retrying the request.

Options ***seconds***—Number of seconds to wait.

Range: 1 through 90

Default: 3

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- Configuring RADIUS Servers on page 74
- Understanding Network Elements on page 57
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

traceoptions (Diameter Base Protocol)

Syntax

```
traceoptions {
  file filename <files number> <match regular-expression > <size maximum-file-size>
    <world-readable | no-world-readable>;
  flag flag;
  level (all | error | info | notice | verbose | warning);
  no-remote-trace;
  <peer peer-name>;
}
```

Hierarchy Level

```
[edit access diameter]
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Define tracing options for Diameter peers.

Options

file *filename*—Use the specified file to receive the output of the tracing operation. Enclose the filename within quotation marks. All files are placed in the directory **/var/log**.

files *number*—(Optional) Create the specified maximum number of trace files before overwriting the oldest one. If you specify a maximum number of files, you also must specify a maximum file size with the **size** option.

Range: 2 through 1000

Default: 3 files

flag *flag*—Use the specified tracing operation. To specify more than one tracing operation, include multiple **flag** statements. You can include the following flags:

- **all**—Trace all operations.
- **receive**—Trace received packets.
- **receive-detail**—Trace received packets in detail.
- **send**—Trace transmitted packets.
- **send-detail**—Trace transmitted packets in detail.
- **state**—Trace Diameter peer state changes.
- **timeout**—Trace timeout events.

level—Use the specified level of tracing. You can specify any of the following levels:

- **all**—Match all levels.
- **error**—Match error conditions.
- **info**—Match informational messages.

Copyright © 2018, Juniper Networks, Inc.

- **notice**—Match notice messages about conditions requiring special handling.
- **verbose**—Match verbose messages.
- **warning**—Match warning messages.

match *regular-expression*—(Optional) Refine the output to include lines that contain the specified regular expression.

no-remote-trace—Disable remote tracing.

no-world-readable—(Optional) Disable unrestricted file access.

peer *peer-name*—(Optional) Trace packets sent to or received from the specified peer. The specified peer must be defined at the **[edit access diameter peer]** hierarchy level.

size *maximum-file-size*—(Optional) Use the specified maximum size of each trace file. By default, the number entered is treated as bytes. Alternatively, you can include a suffix to the number to indicate kilobytes (KB), megabytes (MB), or gigabytes (GB). If you specify a maximum file size, you also must specify a maximum number of trace files with the **files** option.

Syntax: ***size*k** to specify KB, ***size*m** to specify MB, or ***size*g** to specify GB

Range: 10240 through 1073741824

Default: 128 KB

world-readable—(Optional) Enable unrestricted file access.

Required Privilege Level

trace—To view this statement in the configuration.
trace-control—To add this statement to the configuration.

Related Documentation

- diameter on page 273

Copyright © 2018, Juniper Networks, Inc.

traceoptions (PCEF)

Syntax

```
traceoptions {
  file file-name <files number> <no-word-readable | world-readable> <size size>;
  flag flag;
  level (all | critical | error | info | notice | verbose | warning);
  no-remote-trace;
}
```

Hierarchy Level

```
[edit unified-edge pcef]
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify tracing options for policy and charging enforcement functions (PCEF).

Options

file *file-name*—Use the specified name of the file to receive the output of the tracing operation.

files *number*—(Optional) Use the specified maximum number of trace files. When a trace file named trace-file reaches its maximum size, it is renamed trace-file.0, then trace-file.1, and so on, until the maximum number of trace files is reached. Then the oldest trace file is overwritten.

Range: 2 through 1000

Default: 3 files

flag *flag*—Specify which operations are to be traced. To specify more than one operation, include multiple flag statements.

BEST PRACTICE: You might want to enable traceoptions only when you want to debug specific charging operations. Enabling the traceoption flags might have an impact on the system performance.

- **all**—Trace all operations.
- **config**—Trace configuration events.
- **debug**—Trace debug internal events.
- **fsm**—Trace finite state machine events.
- **general**—Trace general events that do not fit in any specific traces.
- **high-availability**—Trace high-availability events.
- **init**—Trace initialization events.
- **tftmgr**—Trace tftmgr events.

Copyright © 2018, Juniper Networks, Inc.

level—Use the specified level of tracing. You can specify any of the following levels:

- **all**—Match all levels.
- **critical**—Match critical conditions.
- **error**—Match error conditions.
- **info**—Match informational messages
- **notice**—Match conditions that must be handled specially.
- **verbose**—Match verbose messages.
- **warning**—Match warning messages.

no-remote-trace—(Optional) Disable remote tracing.

no-world-readable—(Optional) Disable unrestricted file access.

size *size*—(Optional) Use the specified maximum size of each trace file, in kilobytes (KB) or megabytes (MB). When a trace file named trace-file reaches this size, it is renamed trace-file.0. When the trace-file again reaches its maximum size, trace-file.0 is renamed trace-file.1 and trace-file is renamed trace-file.0. This renaming scheme continues until the maximum number of trace files is reached. Then, the oldest trace file is overwritten. If you specify a maximum number of files, you must also specify a maximum file size with the size option.

Syntax: *xk* to specify KB, *xm* to specify MB, or *xg* to specify GB.

Range: 10,240 through 1,073,741,824 bytes

Default: 128 KB

word-readable—(Optional) Enable unrestricted file access.

Required Privilege Level

trace and unified-edge—To view this statement in the configuration.
trace-control and unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Tracing for PCEF Operations on page 199

Copyright © 2018, Juniper Networks, Inc.

traceoptions (TDF Gateway)

Syntax

```
traceoptions {
  file file-name <files number> <no-word-readable | world-readable> <size size>;
  flag flag;
  level (all | critical | error | info | notice | verbose | warning);
  no-remote-trace;
}
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name]
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify tracing options for the TDF gateway.

Options

file *file-name*—Use the specified name of the file to receive the output of the tracing operation.

files *number*—(Optional) Use the specified maximum number of trace files. When a trace file named trace-file reaches its maximum size, it is renamed trace-file.0, then trace-file.1, and so on, until the maximum number of trace files is reached. Then the oldest trace file is overwritten.

Range: 2 through 1000 files

Default: 3 files

flag *flag*—Specify which operations are to be traced. To specify more than one operation, include multiple flag statements.

- **all**—Trace everything.
- **bulkjob**—Trace events that are handled by bulk jobs in order to prevent system overload.
- **config**—Trace configuration events.
- **cos-cac**—Trace class of service (CoS) and call admission control (CAC) events.
- **ctxt**—Trace user equipment, Packet Data Network (PDN), or bearer context events.
- **fsm**—Trace mobile subscriber finite state machine (FSM) events.
- **gtpu**—Trace GPRS tunneling protocol, user plane (GTP-U) events.
- **ha**—Trace high availability events.
- **init**—Trace initialization events.
- **pfem**—Trace Packet Forwarding Engine Manager events.
- **stats**—Trace **stats** events. This flag is used internally by Juniper Networks engineers.

Copyright © 2018, Juniper Networks, Inc.

- **waitq**—Trace **waitq** events. This flag is used internally by Juniper Networks engineers.

level—Use the specified level of tracing. You can specify any of the following levels:

- **all**—Match all levels.
- **critical**—Match critical conditions.
- **error**—Match error conditions.
- **info**—Match informational messages
- **notice**—Match conditions that must be handled specially.
- **verbose**—Match verbose messages.
- **warning**—Match warning messages.

no-remote-trace—(Optional) Disable remote tracing.

no-world-readable—(Optional) Disable unrestricted file access.

size *size*—(Optional) Use the specified maximum size of each trace file, in kilobytes (KB) or megabytes (MB). When a trace file named trace-file reaches this size, it is renamed trace-file.0. When the trace-file again reaches its maximum size, trace-file.0 is renamed trace-file.1 and trace-file is renamed trace-file.0. This renaming scheme continues until the maximum number of trace files is reached. Then, the oldest trace file is overwritten. If you specify a maximum number of files, you must also specify a maximum file size with the size option.

Syntax: *xk* to specify KB, *xm* to specify MB, or *xg* to specify GB.

Range: 10,240 through 1,073,741,824 bytes.

Default: 128 KB

word-readable—(Optional) Enable unrestricted file access.

Required Privilege Level

trace and unified-edge—To view this statement in the configuration.
trace-control and unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Tracing for TDF Gateway on page 19

Copyright © 2018, Juniper Networks, Inc.

trigger-type (LRF Profile)

Syntax

```
trigger-type (session-close | volume);
```

Hierarchy Level

```
[edit services lrf profile profile-name template template-name]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure the type of trigger that causes the generation of data records and transmission to the collector. You can only configure one type of trigger.

Default

If you do not include the **trigger-type** statement, the default trigger is **session-close**.

Options

session-close—Use the closing of the data session to cause the generation of data records and transmission to the collector.

volume—Use a data volume limit to cause the generation of data records and transmission to the collector. The data volume limit value is configured in the LRF rule.

Required Privilege Level

interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring an LRF Profile for Subscribers on page 152
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152
- *Configuring Logging and Reporting for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

type (Application Identification)

Syntax type *type*;

Hierarchy Level [edit services application-identification application *application-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Specify the type of application, such as FTP or HTTP.

Options ***type***—Type of application such as FTP or HTTP.

Required Privilege Level view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation
- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25

type (ICMP Mapping for Application Identification)

Syntax type *icmp-type*;

Hierarchy Level [edit services application-identification application *application-name* icmp-mapping]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Match an ICMP type value to create a custom application signature.

Options ***value***—ICMP code value.
Range: 0 through 254

Required Privilege Level view-level—To view this statement in the configuration.
control-level—To add this statement to the configuration.

Related Documentation
- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25

Copyright © 2018, Juniper Networks, Inc.

unit (TDF Interface)

Syntax

```
unit interface-unit-number {
  family family-name;
}
```

Hierarchy Level

[edit interfaces mif]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure the logical interface on the TDF interface. You must configure a logical interface to be able to use the TDF interface.

Options

interface-unit-number—Number of the logical unit.

Range: 0 through 16,384

The remaining statement is explained separately. See CLI Explorer.

Required Privilege Level

interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring a TDF Logical Interface on page 120

Copyright © 2018, Juniper Networks, Inc.

url

Syntax

```
url url-name;
```

Hierarchy Level

```
[edit unified-edge pcef pcc-action-profiles profile-name redirect],
[edit services pcef pcc-action-profiles profile-name redirect]
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
Support at the **[edit services pcef pcc-action-profiles *profile-name* redirect]** hierarchy level introduced for Junos OS Broadband Subscriber Management in Junos OS Release 17.2 on MX Series.

Description

Specify the URL name that you want a PCC action profile to use for performing HTTP redirection. If you configure this, the PCC action profile can only be used in PCC rules that match only HTTP-based applications and all flows.

If you are using Junos OS Subscriber Aware, specify the URL name at the **[edit unified-edge pcef pcc-action-profiles *profile-name* redirect]** hierarchy level.

If you are using Junos OS Broadband Subscriber Management, specify the URL name at the **[edit services pcef pcc-action-profiles *profile-name* redirect]** hierarchy level.

Options

url-name—URL for the HTTP redirect.

Required Privilege Level

For Junos OS Subscriber Aware:
unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.
For Junos OS Broadband Subscriber Management:
services—To view this statement in the configuration.
services–control—To add this statement to the configuration.

Related Documentation

- Configuring Policy and Charging Control Action Profiles For Junos OS Subscriber Aware on page 67
- *Configuring Policy and Charging Control Action Profiles for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

use-class (Class Attribute)

Syntax

```
use-class {
  regex "value";
  pattern "pattern";
  subscription-id-type (imsi | msisdn | nai | private | sip-uri);
}
```

Hierarchy Level

[edit unified-edge gateways tdf *gateway-name* domains *domain-name* subscription-id]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure a regular expression to parse the Class attribute contents, specify characters to insert between the resulting regular expression groups, and specify the subscription ID type if you configured **subscription-id-options** *entry-name* **use-class** under **[edit unified-edge gateways tdf** *gateway-name* **domains** *domain-name* **subscription-id]**.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Set of IP-Based TDF Subscriber Properties with a TDF Domain on page 100

Copyright © 2018, Juniper Networks, Inc.

user-name

Syntax

```
user-name {
  equals value;
  has-prefix value;
  has-suffix value;
  matches value;
}
```

Hierarchy Level

[edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* from]

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the RADIUS AVP User-Name for the incoming RADIUS request from the subscriber.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

user-password (PCEF Profile)

Syntax user-password *password*;

Hierarchy Level [edit unified-edge pcef profiles *profile-name* aaa-policy-control]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the user password for subscribers assigned to the parent PCEF profile.

Options ***password***—Password for access requests to the RADIUS server.

Range: 1 through 32 characters

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring a Policy and Charging Enforcement Function Profile for Junos OS Subscriber Aware Policies That a RADIUS Server Controls on page 82
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

v4address

Syntax

```
v4address {
  apply-groups [group-names];
  apply-groups-except [group-names];
  equals;
}
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  attribute name format]
```

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the custom AVP attribute's format as an IPv4 address and the value to match for the incoming RADIUS request from the IP-based subscriber.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

v6address

Syntax

```
v6address {
  apply-groups [group-names];
  apply-groups-except [group-names];
  equals;
}
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  attribute name format]
```

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the custom AVP attribute's format as an IPv6 address and the value to match for the incoming RADIUS request from the IP-based subscriber.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

v6prefix

Syntax

```
v6prefix {
  apply-groups [group-names];
  apply-groups-except [group-names];
  equals;
}
```

Hierarchy Level

```
[edit unified-edge gateways tdf gateway-name domain-selection term term-name from
  attribute name format]
```

Release Information

Statement introduced in Junos OS Release 16.1 on MX Series.

Description

Specify the custom AVP attribute's format as an IPv6 address prefix and the value to match for the incoming RADIUS request from the IP-based subscriber.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

The remaining statements are explained separately. See CLI Explorer.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

vendor-id

Syntax vendor-id *vendor-id*;

Hierarchy Level [edit unified-edge gateways tdf *gateway-name* domain-selection term *term-name* from attribute *name*]

Release Information Statement introduced in Junos OS Release 16.1 on MX Series.

Description Specify the custom attribute's AVP vendor identification number for the incoming RADIUS request from the subscriber.

After this criterion and the other match criteria specified for the TDF domain or PCEF profile selection term are matched, the specified TDF domain or PCEF profile is selected.

Options ***vendor-id***—AVP vendor identification number.

Range: 0 through 65,534.

Required Privilege Level unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring Assignment of TDF Subscriber Properties and Policy-Control Properties to IP-Based Subscribers on page 107
- Understanding Selection of Properties for an IP-Based TDF Subscriber on page 90
- Understanding Selection of Policy-Control Properties for an IP-based TDF Subscriber on page 92
- IP-Based Subscriber Setup Overview on page 88

Copyright © 2018, Juniper Networks, Inc.

vendor-id (AAA Profile)

Syntax

vendor-id *vendor-id*;

Hierarchy Level

[edit unified-edge aaa profiles *aaa-profile-name* radius policy activation-attribute],
[edit unified-edge aaa profiles *aaa-profile-name* radius policy deactivation-attribute]

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Configure the vendor identification when a vendor-specific RADIUS attribute is used to carry the policy and charging control (PCC) rulebase name for rulebase activations or deactivations. By default, the rulebase name is carried in the ERX-Service-Activate Juniper vendor-specific attribute (VSA) for activations and in the ERX-Service-Deactivate Juniper VSA for deactivations.

Options

vendor-id—Vendor identification number for the RADIUS AVP.

Required Privilege Level

unified-edge—To view this statement in the configuration.
unified-edge-control—To add this statement to the configuration.

Related Documentation

- Configuring an AAA Profile on page 78
- Understanding AAA Profiles on page 58
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

Copyright © 2018, Juniper Networks, Inc.

vendor-support

Syntax

```
vendor-support ibm;
```

Hierarchy Level

```
[edit services lrf profile profile-name]
```

Release Information

Statement introduced in Junos OS Release 17.2 on MX Series.

Description

Configure support for any vendor-specific template types. Currently, the only vendor-specific template type is **ipflow-tcp-ts**, for which you configure **vendor-specific ibm**.

If you do not configure **vendor-specific ibm**, a warning appears when you commit the configuration.

Required Privilege Level

interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring an LRF Profile for Subscribers on page 152
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152
- *Configuring Logging and Reporting for Subscriber Management*
- Logging and Reporting Function for Subscribers on page 141

Copyright © 2018, Juniper Networks, Inc.

volume-limit (LRF Rule)

Syntax volume-limit *volume*;

Hierarchy Level [edit services lrf profile *profile-name* rule *lrf-rule-name* then report]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the data volume limit to be used for reporting. The template that the LRF rule is using must have **trigger-type volume** configured.

Options ***volume***—Data volume, in megabytes.

Range: 1 through 1024

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Documentation

- Configuring an LRF Profile for Subscribers on page 152
- Configuring Logging and Reporting for Junos OS Subscriber Aware on page 152
- *Configuring Logging and Reporting for Subscriber Management*

Copyright © 2018, Juniper Networks, Inc.

watchdog-timeout

Syntax watchdog-timeout *seconds*;

Hierarchy Level [edit access diameter peer *peer-name*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Configure the amount of time to wait for a Device-Watchdog-Answer message.

Options ***seconds***—Amount of time to wait.

Range: 1 through 65,535 seconds

Default: 30 seconds

Required Privilege Level access—To view this statement in the configuration.
access-control—To add this statement to the configuration.

Related Documentation

- diameter on page 273

Copyright © 2018, Juniper Networks, Inc.

Copyright © 2018, Juniper Networks, Inc.

CHAPTER 13

Operational Commands

- clear services application-identification application-system-cache
- clear services application-identification statistics
- clear services lrf collector statistics
- clear services lrf statistics
- clear unified-edge tdf aaa radius client statistics
- clear unified-edge tdf aaa radius network-element statistics
- clear unified-edge tdf aaa radius server statistics
- clear unified-edge tdf aaa radius snoop-segment statistics
- clear unified-edge tdf aaa statistics
- clear unified-edge tdf address-assignment pool
- clear unified-edge tdf address-assignment statistics
- clear unified-edge tdf call-admission-control statistics
- clear unified-edge tdf diameter network-element statistics
- clear unified-edge tdf diameter pcc-gx statistics
- clear unified-edge tdf diameter peer statistics
- clear unified-edge tdf statistics
- clear unified-edge tdf subscribers
- clear unified-edge tdf subscribers peer
- request interface load-balancing revert (Aggregated Multiservices)
- request interface load-balancing switchover (Aggregated Multiservices)
- request services application-identification application
- request services application-identification download
- request services application-identification download status
- request services application-identification group
- request services application-identification install
- request services application-identification install status
- request services application-identification proto-bundle-status
- request services application-identification uninstall

Copyright © 2018, Juniper Networks, Inc.

- request services application-identification uninstall status
- request unified-edge tdf call-trace clear
- request unified-edge tdf call-trace show
- request unified-edge tdf call-trace start
- request unified-edge tdf call-trace stop
- show interfaces anchor-group (Aggregated Packet Forwarding Engine)
- show interfaces load-balancing (Aggregated Multiservices)
- show services application-identification application
- show services application-identification application-system-cache
- show services application-identification counter
- show services application-identification group
- show services application-identification statistics application-groups
- show services application-identification statistics applications
- show services application-identification status
- show services application-identification version
- show services ha detail
- show services hcm statistics
- show services hcm pic-statistics
- show services lrf collector statistics
- show services lrf rule statistics
- show services lrf statistics
- show services lrf template
- show services traffic-detection-function hcm statistics
- show services traffic-detection-function sessions
- show unified-edge tdf aaa radius client statistics
- show unified-edge tdf aaa radius client status
- show unified-edge tdf aaa radius network-element statistics
- show unified-edge tdf aaa radius server statistics
- show unified-edge tdf aaa radius server status
- show unified-edge tdf aaa radius snoop-segment statistics
- show unified-edge tdf aaa statistics
- show unified-edge tdf address-assignment pool
- show unified-edge tdf address-assignment service-mode
- show unified-edge tdf address-assignment statistics
- show unified-edge tdf call-admission-control statistics
- show unified-edge tdf call-rate statistics
- show unified-edge tdf diameter network-element statistics

Copyright © 2018, Juniper Networks, Inc.

- show unified-edge tdf diameter network-element status
- show unified-edge tdf diameter pcc-gx statistics
- show unified-edge tdf diameter peer statistics
- show unified-edge tdf diameter peer status
- show unified-edge tdf domain service-mode
- show unified-edge tdf domain statistics
- show unified-edge tdf resource-manager clients
- show unified-edge tdf service-mode
- show unified-edge tdf statistics
- show unified-edge tdf status
- show unified-edge tdf subscribers
- show unified-edge tdf system interfaces
- show unified-edge tdf system interfaces service-mode

Copyright © 2018, Juniper Networks, Inc.

clear services application-identification application-system-cache

Syntax

```
clear services application-identification application-system-cache
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Clear entries from the application system cache.

Options This command has no options.

Required Privilege Level clear

Related Documentation

- show services application-identification application-system-cache on page 580

List of Sample Output clear services application-identification application-system-cache on page 526

Output Fields When you enter this command, you are provided no feedback on the status of your request.

Sample Output

clear services application-identification application-system-cache

```
user@host> clear services application-identification application-system-cache
```


Copyright © 2018, Juniper Networks, Inc.

clear services application-identification statistics

Syntax

```
clear services application-identification statistics
cumulative
interval
logical-system
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.
The **logical-system** option is introduced in Junos OS Release 18.3R1 on SRX Series.

Description

Clears all Junos OS application statistics such as cumulative, interval, applications, and application groups.

Options

cumulative— Clears the cumulative application statistics.

interval— Clears the application interval statistics. Interval statistics are displayed in Top-N format, such that the first application group displayed has the largest byte count. If this parameter is not specified, then the default is 1, which is the current interval.

logical-system— Name of the logical system.

Required Privilege Level

clear

Related Documentation

- show services application-identification statistics applications on page 593
- show services application-identification statistics application-groups on page 591

List of Sample Output

clear services application-identification statistics on page 527
clear services application-identification statistics logical-system all on page 527

Output Fields

When you enter this command, you are provided no feedback on the status of your request.

Sample Output

clear services application-identification statistics

```
user@host> clear services application-identification statistics
appid statistics cleared
```

Sample Output

clear services application-identification statistics logical-system all

```
user@host> clear services application-identification statistics logical-system all
```

Copyright © 2018, Juniper Networks, Inc.

```
appid statistics cleared
```


Copyright © 2018, Juniper Networks, Inc.

clear services lrf collector statistics

Syntax

```
clear services lrf collector statistics
<collector-name>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Clear all the LRF statistics for the specified collector. If a collector is not specified, statistics are cleared for all collectors.

Options **none**—Clear LRF statistics for all collectors.

collector-name—(Optional) Clear LRF statistics for the specified collector.

Required Privilege Level clear

Related Documentation

- show services lrf collector statistics on page 607

Output Fields A message is displayed on successful execution of this command; otherwise an error message is displayed.

Sample Output

clear services lrf collector statistics

```
user@host> clear services lrf collector statistics coll1
Interface: ms-0/1/0, Status: LRF collector statistics successfully cleared
```

Copyright © 2018, Juniper Networks, Inc.

clear services lrf statistics

Syntax clear services lrf statistics

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Clear all the LRF statistics.

Required Privilege Level clear

Related Documentation
- show services lrf statistics on page 611

Output Fields A message is displayed on successful execution of this command; otherwise an error message is displayed.

Sample Output

clear services lrf statistics

```
user@host> clear services lrf statistics
Interface: ms-0/1/0, Status: LRF statistics successfully cleared
```


Copyright © 2018, Juniper Networks, Inc.

clear unified-edge tdf aaa radius client statistics

Syntax

```
clear unified-edge tdf aaa radius client statistics
<all>
<client name>
<fpc-slot fpc-slot>
<gateway gateway>
<pic-slot pic-slot>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Clear statistics for the accounting requests and responses transmitted and received by the RADIUS client for one or more TDF gateways. If a TDF gateway is not specified, then information for all TDF gateways is cleared.

Options

none—(Same as all) Clear statistics for all clients on all TDF gateways.

all—(Optional) Clear statistics for all the clients.

client *name*—(Optional) Clear statistics for the specified client.

fpc-slot *fpc-slot*—(Optional) Clear statistics for the specified Flexible PIC Concentrator (FPC).

gateway *gateway*—(Optional) Clear statistics for the specified TDF gateway.

pic-slot *pic-slot*—(Optional) Clear statistics for the specified PIC slot number. You must first specify an FPC slot number before specifying the PIC slot number.

Required Privilege Level clear, unified-edge

Related Documentation

- show unified-edge tdf aaa radius client statistics on page 620

List of Sample Output clear unified-edge tdf aaa radius client statistics all on page 531

Output Fields When you enter this command, you are provided feedback on the status of your request.

Sample Output

clear unified-edge tdf aaa radius client statistics all

```
user@host> clear unified-edge tdf aaa radius client statistics all

Cleared all RADIUS statistics
```

Copyright © 2018, Juniper Networks, Inc.

clear unified-edge tdf aaa radius network-element statistics

Syntax

```
clear unified-edge tdf aaa radius network-element statistics
<fpc-slot fpc-slot>
<gateway gateway>
<pic-slot pic-slot>
<name name>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Clear all the statistics for the specified network element.

Options

none—Clear statistics for all network elements for all TDF gateways.

fpc-slot *fpc-slot*—(Optional) Clear statistics for the specified Flexible PIC Concentrator (FPC).

gateway *gateway*—(Optional) Clear statistics for the specified TDF gateway.

pic-slot *pic-slot*—(Optional) Clear statistics for the specified PIC slot number. You must first specify an FPC slot number before specifying the PIC slot number.

name *name*—(Optional) Clear statistics for the specified network element.

Required Privilege Level clear, unified-edge

Related Documentation

- show unified-edge tdf aaa radius network-element statistics on page 628
- Understanding Network Elements on page 57

List of Sample Output clear unified-edge tdf aaa radius network-element statistics on page 532

Output Fields No message is displayed on successful execution of this command; otherwise, an error message is displayed.

Sample Output

clear unified-edge tdf aaa radius network-element statistics

```
user@host> clear unified-edge tdf aaa radius network-element statistics
```


Copyright © 2018, Juniper Networks, Inc.

clear unified-edge tdf aaa radius server statistics

Syntax

```
clear unified-edge tdf aaa radius server statistics
<fpc-slot fpc-slot>
<gateway gateway>
<pic-slot pic-slot>
<name name>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Clear all the statistics for the specified RADIUS server.

Options

none—Clear statistics for all RADIUS servers for all TDF gateways.

fpc-slot *fpc-slot*—(Optional) Clear statistics for the specified Flexible PIC Concentrator (FPC).

gateway *gateway*—(Optional) Clear statistics for the specified TDF gateway.

pic-slot *pic-slot*—(Optional) Clear statistics for the specified PIC slot number. You must first specify an FPC slot number before specifying the PIC slot number.

name *name*—(Optional) Clear statistics for the specified RADIUS server.

Required Privilege Level clear, unified-edge

Related Documentation

- show unified-edge tdf aaa radius server statistics on page 631
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

List of Sample Output clear unified-edge tdf aaa radius server statistics on page 533

Output Fields No message is displayed on successful execution of this command; otherwise, an error message is displayed.

Sample Output

clear unified-edge tdf aaa radius server statistics

```
user@host> clear unified-edge tdf aaa radius server statistics
```

Copyright © 2018, Juniper Networks, Inc.

clear unified-edge tdf aaa radius snoop-segment statistics

Syntax

```
clear unified-edge tdf aaa radius snoop-segment statistics
<fpc-slot fpc-slot>
<gateway gateway>
<pic-slot pic-slot>
<segment snoop-segment-name>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Clear all snoop segment statistics for FPCs, PICs, TDF gateways, or snoop segments that you specify.

Options

none—Clear all snoop-segment statistics for all TDF gateways.

fpc-slot *fpc-slot*—(Optional) Clear statistics for the specified Flexible PIC Concentrator (FPC).

gateway *gateway*—(Optional) Clear statistics for the specified TDF gateway.

pic-slot *pic-slot*—(Optional) Clear statistics for the specified PIC slot number. You must first specify an FPC slot number before specifying the PIC slot number.

segment *snoop-segment-name*—(Optional) Clear statistics for the specified snoop segment.

Required Privilege Level clear, unified-edge

Related Documentation

- show unified-edge tdf aaa radius snoop-segment statistics on page 638
- Snooping RADIUS Accounting Requests for IP-Based Subscribers Overview on page 94

List of Sample Output clear unified-edge tdf aaa radius snoop-segment statistics on page 534

Output Fields A message is displayed on successful execution of this command; otherwise an error message is displayed.

Sample Output

clear unified-edge tdf aaa radius snoop-segment statistics

```
user@host> clear unified-edge tdf aaa radius snoop-segment statistics
Cleared Radius snoop-segment Statistics
```


Copyright © 2018, Juniper Networks, Inc.

clear unified-edge tdf aaa statistics

Syntax

```
clear unified-edge tdf aaa statistics
<all>
<fpc-slot fpc-slot>
<gateway gateway>
<pic-slot pic-slot>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Clear global authentication, authorization, and accounting (AAA) statistics for one or more TDF gateways. If a TDF gateway is not specified, then information for all TDF gateways is cleared.

Options

none—(Same as all) Clear AAA statistics for all TDF gateways.

all—(Optional) Clear AAA statistics for all the TDF gateways.

fpc-slot *fpc-slot*—(Optional) Clear AAA statistics for the specified Flexible PIC Concentrator (FPC).

gateway *gateway*—(Optional) Clear AAA statistics for the specified TDF gateway.

pic-slot *pic-slot*—(Optional) Clear AAA statistics for the specified PIC slot number. You must first specify an FPC slot number before specifying the PIC slot number.

Required Privilege Level clear, unified-edge

Related Documentation

- show unified-edge tdf aaa statistics on page 642

List of Sample Output clear unified-edge tdf aaa statistics all on page 535

Output Fields When you enter this command, you are provided feedback on the status of your request.

Sample Output

clear unified-edge tdf aaa statistics all

```
user@host> clear unified-edge tdf aaa statistics all

Cleared all AAA statistics
```

Copyright © 2018, Juniper Networks, Inc.

clear unified-edge tdf address-assignment pool

Syntax

```
clear unified-edge tdf address-assignment pool name pool-name
<gateway gateway>
<routing-instance routing-instance>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Clear the sessions that have been assigned addresses from the specified mobile pool for one or more TDF gateways. If a TDF gateway is not specified, then the sessions for all TDF gateways are cleared.

Options

none—Clear the sessions for all TDF gateways associated with the specified mobile pool.

name *pool-name*—Clear the sessions for the specified mobile pool.

gateway *gateway*—(Optional) Clear the sessions on the specified TDF gateway.

routing-instance *routing-instance*—(Optional) Clear the sessions on the specified routing instance.

Required Privilege Level clear, unified-edge

Related Documentation

- show unified-edge tdf address-assignment pool on page 649

List of Sample Output clear unified-edge tdf address-assignment pool name on page 536

Output Fields When you enter this command, you are provided feedback on the status of your request.

Sample Output

clear unified-edge tdf address-assignment pool name

```
user@host> clear unified-edge tdf address-assignment pool name pool-1

Initiated clearing of sessions in the pool
```


Copyright © 2018, Juniper Networks, Inc.

clear unified-edge tdf address-assignment statistics

Syntax

```
clear unified-edge tdf address-assignment statistics
<fpc-slot fpc-slot>
<gateway gateway>
<pic-slot pic-slot>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Clear the global address assignment statistics for one or more TDF gateways. If a TDF gateway is not specified, then the statistics for all TDF gateways are cleared.

Options

none—Clear statistics for all TDF gateways.

fpc-slot *fpc-slot*—(Optional) Clear the statistics for the session PIC in the specified FPC slot.

gateway *gateway*—(Optional) Clear the statistics for the specified TDF gateway.

pic-slot *pic-slot*—(Optional) Clear information about the session PIC in this particular PIC slot. For routers, replace *pic-slot* with a value from 0 through 3.

Required Privilege Level clear, unified-edge

Related Documentation

- show unified-edge tdf address-assignment statistics on page 655

List of Sample Output clear unified-edge tdf address-assignment statistics on page 537

Output Fields When you enter this command, you are provided feedback on the status of your request.

Sample Output

clear unified-edge tdf address-assignment statistics

```
user@host> clear unified-edge tdf address-assignment statistics

Cleared address-assignment statistics
```

Copyright © 2018, Juniper Networks, Inc.

clear unified-edge tdf call-admission-control statistics

Syntax

```
clear unified-edge tdf call-admission-control statistics gateway gateway-name
<fpc-slot fpc-slot>
<pic-slot pic-slot>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Clear call admission control (CAC) statistics for the specified TDF gateway.

Options

fpc-slot *fpc-slot*—(Optional) Clear statistics for the session PIC in the specified FPC slot.

gateway *gateway-name*—Clear CAC statistics for the specified TDF gateway.

pic-slot *pic-slot*—(Optional) Clear statistics for the session PIC in the specified PIC slot.

Required Privilege Level clear, unified-edge

Related Documentation

- show unified-edge tdf call-admission-control statistics on page 657

List of Sample Output clear unified-edge tdf call-admission-control statistics gateway on page 538

Output Fields No message is displayed on successful execution of this command; otherwise an error message is displayed.

Sample Output

clear unified-edge tdf call-admission-control statistics gateway

```
user@host> clear unified-edge tdf call-admission-control statistics gateway TDF
```


Copyright © 2018, Juniper Networks, Inc.

clear unified-edge tdf diameter network-element statistics

Syntax

```
clear unified-edge tdf diameter network-element statistics
<fpc-slot fpc-slot>
<gateway gateway-name>
<network-element-name network-element-name>
<pic-slot pic-slot>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Clear the statistics for network elements for one or more TDF gateways. If a network element is not specified, then statistics for all network elements are cleared. If a TDF gateway is not specified, then statistics for all TDF gateways are cleared.

Options

none—Clear statistics for all network elements and TDF gateways.

fpc-slot *fpc-slot*—(Optional) Clear statistics for the specified Flexible PIC Concentrator (FPC).

gateway *gateway-name*—(Optional) Clear statistics for the specified TDF gateway.

network-element-name *network-element-name*—(Optional) Clear statistics for the specified network element.

pic-slot *pic-slot*—(Optional) Clear statistics for the specified PIC slot number. You must first specify an FPC slot number before specifying the PIC slot number.

Required Privilege Level clear, unified-edge

Related Documentation

- show unified-edge tdf diameter network-element statistics on page 662

List of Sample Output clear unified-edge tdf diameter network-element statistics on page 539

Output Fields No message is displayed on successful execution of this command; otherwise an error message is displayed.

Sample Output

clear unified-edge tdf diameter network-element statistics

```
user@host> clear unified-edge tdf diameter network-element statistics
```

Copyright © 2018, Juniper Networks, Inc.

clear unified-edge tdf diameter pcc-gx statistics

Syntax

```
clear unified-edge tdf diameter pcc-gx statistics
<fpc-slot fpc-slot>
<gateway gateway-name>
<pic-slot pic-slot>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Clear all statistics for the Gx application for one or more TDF gateways. If a TDF gateway is not specified, then statistics for all TDF gateways are cleared.

Options

none—Clear Gx application statistics for all TDF gateways.

fpc-slot *fpc-slot*—(Optional) Clear statistics for the specified Flexible PIC Concentrator (FPC).

gateway *gateway-name*—(Optional) Clear statistics for the specified TDF gateway.

pic-slot *pic-slot*—(Optional) Clear statistics for the specified PIC slot number. You must first specify an FPC slot number before specifying the PIC slot number.

Required Privilege Level clear, unified-edge

Related Documentation

- clear unified-edge tdf diameter pcc-gx statistics on page 540

List of Sample Output clear unified-edge tdf diameter pcc-gx statistics on page 540

Output Fields No message is displayed on successful execution of this command; otherwise an error message is displayed.

Sample Output

clear unified-edge tdf diameter pcc-gx statistics

```
user@host> clear unified-edge tdf diameter pcc-gx statistics
```


Copyright © 2018, Juniper Networks, Inc.

clear unified-edge tdf diameter peer statistics

Syntax

```
clear unified-edge tdf diameter peer statistics
<fpc-slot fpc-slot>
<gateway gateway-name>
<peer-name peer-name>
<pic-slot pic-slot>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Clear statistics for Diameter peers for one or more TDF gateways. If a peer is not specified, then statistics for all peers are cleared. If a TDF gateway is not specified, then statistics for all TDF gateways are cleared.

Options

none—Clear Diameter peer statistics for all TDF gateways.

fpc-slot *fpc-slot*—(Optional) Clear statistics for the specified Flexible PIC Concentrator (FPC).

gateway *gateway-name*—(Optional) Clear statistics for the specified TDF gateway.

peer-name *peer-name*—(Optional) Clear statistics for the specified peer.

pic-slot *pic-slot*—(Optional) Clear statistics for the specified PIC slot number. You must first specify an FPC slot number before specifying the PIC slot number.

Required Privilege Level clear, unified-edge

Related Documentation

- show unified-edge tdf diameter peer statistics on page 672

List of Sample Output clear unified-edge tdf diameter peer statistics on page 541

Output Fields No message is displayed on successful execution of this command; otherwise an error message is displayed.

Sample Output

clear unified-edge tdf diameter peer statistics

```
user@host> clear unified-edge tdf diameter peer statistics
```

Copyright © 2018, Juniper Networks, Inc.

clear unified-edge tdf statistics

Syntax

```
clear unified-edge tdf statistics
<data-plane>
<gateway gateway-name>
<domain domain-name
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Clear all the statistics for the specified TDF gateway, domain, or control plane.

Options

none—Clear statistics for all TDF control planes, domains, and gateways.

data-plane—(Optional) Clear statistics for the data plane.

domain *domain-name*—(Optional) Clear statistics for the specified TDF domain.

gateway *gateway-name*—(Optional) Clear statistics for the specified TDF gateway.

Required Privilege Level clear, unified-edge

Related Documentation

- show unified-edge tdf statistics on page 692

List of Sample Output clear unified-edge tdf statistics gateway on page 542

Output Fields No message is displayed on successful execution of this command; otherwise an error message is displayed.

Sample Output

clear unified-edge tdf statistics gateway

```
user@host> clear unified-edge tdf statistics gateway TDF
```


Copyright © 2018, Juniper Networks, Inc.

clear unified-edge tdf subscribers

Syntax clear unified-edge tdf subscribers [*option*]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Clear the subscribers identified by the option values. You must include at least one option. For IFL-based subscribers, use the **revert** option to re-create the cleared subscribers identified by the option values.

Options ***option***—One or more of the following options:

- **domain** ***domain-name***—Clear the subscribers for the specified TDF domain.
- **gateway** ***gateway-name***—Clear the subscribers for the specified TDF gateway.
- **interface** ***interface-name***—Clear the subscribers on the specified multiservices interface, aggregated multiservices interface, Packet Forwarding Engine interface, or aggregated Packet Forwarding Engine interface names.
- **peer** ***peer-name***—Clear the subscriber matching GPRS tunneling protocol (GTP) peer on the specified TDF gateway.
- **revert**—For an IFL-based subscriber, recreate an IFL-subscriber that was cleared.
- **routing-instance** ***routing-instance***—Clear the subscriber information for the specified routing instance.
- **subscriber-name** ***subscriber-name***—Clear the specified IFL-based subscriber.
- **v4-addr** ***v4-addr***—Clear the subscriber information for the specified IPv4 address of the IP-based subscriber's user equipment (UE).
- **v6-addr** ***v6-addr***—Clear the subscriber information for the specified IPv6 address of the IP-based subscriber's user equipment.

Required Privilege Level clear, unified-edge

Related Documentation

- clear unified-edge tdf statistics on page 542
- clear unified-edge tdf subscribers peer on page 545
- show unified-edge tdf subscribers on page 703
- IP-Based and IFL-Based TDF Subscribers Overview on page 88
- Understanding IFL-Based Subscriber Setup on page 95

List of Sample Output clear unified-edge tdf subscribers gateway tdf on page 544

Copyright © 2018, Juniper Networks, Inc.

Output Fields No message is displayed on successful execution of this command; otherwise an error message is displayed.

Sample Output

clear unified-edge tdf subscribers gateway tdf

```
user@host> clear unified-edge tdf subscribers gateway tdf
```


Copyright © 2018, Juniper Networks, Inc.

clear unified-edge tdf subscribers peer

Syntax

```
clear unified-edge tdf subscribers peer
<gateway gateway>
<remote-addr remote-addr>
<nas-id nas-id
<routing-instance routing-instance>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Clear the information for IP-based subscribers anchored on the specified RADIUS client, TDF gateway, or both, or for IP-based subscribers matching the specified routing instance.

Options

none—Clear information for all IP-based subscribers.

gateway *gateway*—(Optional) Clear IP-based subscriber information for the TDF gateway.

nas-id *nas-id*—(Optional) Clear IP-based subscriber information for the specified NAS identifier of the RADIUS client.

remote-addr *remote-addr*—(Optional) Clear IP-based subscriber information for the specified IPv4 address of the RADIUS client.

routing-instance *routing-instance*—(Optional) Clear IP-based subscriber information for the specified routing instance.

Required Privilege Level clear, unified-edge

Related Documentation

- clear unified-edge tdf subscribers on page 543
- show unified-edge tdf subscribers on page 703

List of Sample Output clear unified-edge tdf subscribers peer gateway remote-addr on page 545

Output Fields No message is displayed on successful execution of this command; otherwise an error message is displayed.

Sample Output

clear unified-edge tdf subscribers peer gateway remote-addr

```
user@host> clear unified-edge tdf subscribers peer gateway TDF remote-addr 198.0.2.2
```

Copyright © 2018, Juniper Networks, Inc.

request interface load-balancing revert (Aggregated Multiservices)

Syntax request interface load-balancing revert *interface-name*

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Revert the aggregated multiservices member interface (mams-) from the inactive state to the active or backup state based on the configuration and the operational state of the aggregated multiservices interface.

Options ***interface-name***—Name of the member interface. The member interface format is mams-*a*/*b*/0, where *a* is the FPC slot number and *b* is the PIC slot number.

Required Privilege Level view

Related Documentation
- request interface load-balancing switchover (Aggregated Multiservices) on page 547

List of Sample Output request interface load-balancing revert on page 546

Output Fields When you enter this command, you are provided feedback on the status of your request.

Sample Output

request interface load-balancing revert

```
user@host> request interface load-balancing revert mams-4/0/0
request succeeded
```


Copyright © 2018, Juniper Networks, Inc.

request interface load-balancing switchover (Aggregated Multiservices)

Syntax

```
request interface load-balancing switchover interface-name
<force>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Switch the active member interface to the backup state.

In the case of mobile control plane redundancy, the behavior depends on the replication state of the member interface:

- If the sync state is **in-sync**, then the active member is rebooted and the backup member becomes the new active member.
- If the sync-state is **in-progress**, then the **force** option must be used to force the switchover.

CAUTION: In this case, there is a risk of losing subscriber information because the synchronization has not yet been completed.

Options ***interface-name***—Name of the member interface. The member interface format is mams-*a*/*b*/0, where *a* is the FPC slot number and *b* is the PIC slot number.

force—(Optional) Force the switchover from the active member to the backup member.

Required Privilege Level view

Related Documentation

- request interface load-balancing revert (Aggregated Multiservices) on page 546

List of Sample Output request interface load-balancing switchover force on page 547

Output Fields When you enter this command, you are provided feedback on the status of your request.

Sample Output

request interface load-balancing switchover force

```
user@host> request interface load-balancing switchover force mams-4/0/0
Switchover Initiated
```

request services application-identification application

Syntax

```
request services application-identification application <disable | enable>
  predefined-application-name
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Disable or enable a predefined application signature.

Options ***predefined-application-name***—Application name; a maximum of up to 31 characters. Predefined applications have the prefix **junos-** to avoid conflict with user-defined ones. Do not name your custom application signature with the **junos** prefix; this prefix is reserved for predefined application signatures.

disable— (Optional) Disable a predefined application signature, initiate signature recompilation, and commit all pending uncompiled signatures to the configuration.

The following conditions apply:

- You cannot disable a predefined application signature that is referenced by an active security policy or custom application signature. First modify or deactivate the policy or custom application signature.
- If you disable an application signature, for example, junos:HTTP, that has nested applications, the nested applications are not recognized.

enable—(Optional) Enable a predefined application signature, initiate signature recompilation, and commit all pending uncompiled signatures to the configuration. Include the **no-commit** keyword to defer signature recompilation.

Required Privilege Level maintenance

Related Documentation

- show services application-identification application on page 574

List of Sample Output request services application-identification application disable on page 548

Output Fields When you enter this command, the system provides feedback on the status of your request.

Sample Output

request services application-identification application disable

```
user@host> request services application-identification application disable junos:163

Please wait while we are re-compiling signatures ..
Please wait while we are re-compiling signatures ..
```


Copyright © 2018, Juniper Networks, Inc.

```
Please wait while we are re-compiling signatures ..
Please wait while we are re-compiling signatures ..
Disable application junos:163 succeed.
```

Copyright © 2018, Juniper Networks, Inc.

request services application-identification download

Syntax

```
request services application-identification download <version version-number>;
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Manually download the application package for Junos OS application identification. The application package is extracted from the IDP signature database and contains signature definitions for known applications, such as DNS, Facebook, FTP, Skype, and SNMP.

Options **version *version-number***—(Optional) Download the specified version of the application package from the Juniper Networks website. If you do not enter a version, the most recent version is downloaded.

Required Privilege Level maintenance

Related Documentation

- request services application-identification install on page 554
- request services application-identification download status on page 551

List of Sample Output request services application-identification download on page 550

Output Fields When you enter this command, you are shown the command to use to check the status of your download.

Sample Output

request services application-identification download

```
user@host> request services application-identification download

Please use command "request services application-identification download status"
 to check status
```


Copyright © 2018, Juniper Networks, Inc.

request services application-identification download status

Syntax

```
request services application-identification download status
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Check the download status of the application signature package. The downloaded application package is saved under **/var/db/appid/sec-download/**.

Required Privilege Level maintenance

Related Documentation

- request services application-identification download on page 550

List of Sample Output request services application-identification download status on page 551

Output Fields When you enter this command, the system provides feedback on the status of your request.

Sample Output

request services application-identification download status

```
user@host> request services application-identifications download status
Application package 1608 is downloaded successfully.
```

Copyright © 2018, Juniper Networks, Inc.

request services application-identification group

Syntax

```
request services application-identification group (copy | disable | enable)
  predefined-application-group-name
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Copy, disable, or enable a predefined application signature group.

Options ***predefined-application-group-name***—Identifier for the application group. Maximum length is 32 characters.

copy—Copy the specified predefined application signature group from the database to the configuration and change the name (for example, my:FTP). The ID and order are generated automatically. You can copy the same predefined application signature group only once. You cannot copy duplicate custom signature groups.

NOTE: In configuration mode, if an uncommitted action is pending, the **request services application-identification group copy** command fails.

disable—Disable the specified predefined application signature group.

NOTE: You cannot disable a predefined application signature group that is referenced by an active security policy or custom application signature group. First modify or deactivate the policy or custom application signature group.

enable—Enable the specified predefined application signature group.

Required Privilege Level maintenance

Related Documentation

- show services application-identification group on page 587

List of Sample Output request services application-identification group copy on page 553

Output Fields When you enter this command, the system provides feedback on the status of your request.

Copyright © 2018, Juniper Networks, Inc.

Sample Output

request services application-identification group copy

```
user@host> request services application-identification group copy junos:SYBASE
group 1040 copied successfully.
```

Copyright © 2018, Juniper Networks, Inc.

request services application-identification install

Syntax

```
request services application-identification install
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Install the downloaded predefined application signature package.

The install operation fails if any custom application signatures or custom application signature groups have been manually inserted before any predefined application signatures or predefined application signature groups in the Junos OS configuration. Remove any insert-before signatures, then retry the install operation. This command does not display the installation status and only provides an informational message on the types of commands to use to verify the installation status of the application signature package and the protocol bundle.

Required Privilege Level

maintenance

Related Documentation

- request services application-identification download on page 550
- request services application-identification install status on page 555

List of Sample Output

request services application-identification install on page 554

Output Fields

When you enter this command, you are shown the command to use to check the status of your installation request.

Sample Output

request services application-identification install

```
user@host> request services application-identification install
```

```
Please use command "request services application-identification install status"
to check status and use command "request services application-identification
proto-bundle-status" to check protocol bundle status
```


Copyright © 2018, Juniper Networks, Inc.

request services application-identification install status

Syntax request services application-identification install status

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display the status of the install operation.

Required Privilege Level maintenance

Related Documentation
- request services application-identification install on page 554

List of Sample Output request services application-identification install status on page 555

Output Fields When you enter this command, the system provides feedback on whether your request succeeded or failed.

Sample Output

request services application-identification install status

```
user@host> request services application-identification install status
Install application package version (1776) succeed.
```

Copyright © 2018, Juniper Networks, Inc.

request services application-identification proto-bundle-status

Syntax request services application-identification proto-bundle-status

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display the status of the install operation of the protocol bundle. This command provides feedback on whether your request succeeded or failed.

Required Privilege Level maintenance

Related Documentation
- request services application-identification install on page 554

List of Sample Output request services application-identification proto-bundle-status on page 556

Output Fields When you enter this command, the system provides feedback on whether your request succeeded or failed.

Sample Output

request services application-identification proto-bundle-status

```
user@host> request services application-identification proto-bundle-status
Protocol Bundle Version (1.30.4-22.005 (build date Jan 17 2014)) and application
 secpack version (2345) is loaded and activated.
```


Copyright © 2018, Juniper Networks, Inc.

request services application-identification uninstall

Syntax request services application-identification uninstall

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Uninstall the predefined application package.

The uninstall operation fails if any active security policies, custom application signatures, or custom application signature groups reference predefined application signatures or predefined application signature groups in the Junos OS configuration. This command does not display the uninstallation status and only provides an informational message on the types of commands to use to verify the uninstallation status of the application signature package and the protocol bundle.

Required Privilege Level maintenance

Related Documentation

- request services application-identification install on page 554

List of Sample Output request services application-identification uninstall on page 557

Output Fields When you enter this command, you are shown the command to use to check the status of your uninstall request.

Sample Output

request services application-identification uninstall

```
user@host> request services application-identification uninstall

Please use command "request services application-identification uninstall status"
 to check status and use command "request services application-identification
proto-bundle-status" to check protocol bundle status
```

Copyright © 2018, Juniper Networks, Inc.

request services application-identification uninstall status

Syntax request services application-identification uninstall status

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display the status of the uninstall operation. This command provides information on whether the uninstall operation succeeded or failed.

Required Privilege Level maintenance

Related Documentation
- request services application-identification uninstall on page 557

List of Sample Output request services application-identification uninstall status on page 558

Output Fields When you enter this command, the system provides feedback on whether the request succeeded or failed..

Sample Output

request services application-identification uninstall status

```
user@host> request services application-identification uninstall status
Uninstall application package version (1776) succeed.
```


Copyright © 2018, Juniper Networks, Inc.

request unified-edge tdf call-trace clear

Syntax request unified-edge tdf call-trace clear

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Clear the completed or duplicate subscriber call traces on one or more TDF gateways.

Options This command has no options.

Required Privilege Level unified-edge

Related Documentation

- request unified-edge tdf call-trace show on page 560
- request unified-edge tdf call-trace start on page 563
- request unified-edge tdf call-trace stop on page 565

List of Sample Output request unified-edge tdf call-trace clear on page 559

Output Fields No message is displayed on successful execution of this command; otherwise an error message is displayed.

Sample Output

request unified-edge tdf call-trace clear

```
user@host> request unified-edge tdf call-trace clear
```

request unified-edge tdf call-trace show

Syntax

```
request unified-edge tdf call-trace show
<all | completed | current>
<brief | detail>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display the information related to subscriber call tracing on one or more TDF gateways.

Options

none—(Same as brief) Display information related to subscriber call tracing in brief.

all | completed | current—(Optional) Display call trace information for the following:

- **all**—All calls.
- **completed**—Completed calls only.
- **current**—Call traces that are currently active.

brief | detail—(Optional) Display the specified level of output.

Required Privilege Level unified-edge

Related Documentation

- request unified-edge tdf call-trace clear on page 559
- request unified-edge tdf call-trace start on page 563
- request unified-edge tdf call-trace stop on page 565

List of Sample Output

request unified-edge tdf call-trace show brief on page 561
request unified-edge tdf call-trace show detail on page 562

Output Fields Table 14 on page 560 lists the output fields for the **request unified-edge tdf call-trace show** command. Output fields are listed in the approximate order in which they appear.

Table 14: request unified-edge tdf call-trace show Output Fields

Field Name	Field Description	Level of Output
Identifier	Identifier for the call trace.	All levels
File name	Name of the call trace file.	none **brief**
Trace file	Name of the call trace file.	**detail**

Copyright © 2018, Juniper Networks, Inc.

Table 14: request unified-edge tdf call-trace show Output Fields (continued)

Field Name	Field Description	Level of Output
Status	Status of the call trace: • **done**—Call trace complete. • **not-done**—Call trace in progress. • **duplicate**—Another call trace record is present that has the same attributes.	All levels
SPIC Mask create	Internal mask of the services PIC where this call trace was enabled.	none **brief**
Create Mask	Internal mask of the services PIC where this call trace was enabled.	**detail**
SPIC Mask complete	Internal mask of the services PIC where this call trace was completed.	none **brief**
Complete Mask	Internal mask of the services PIC where this call trace was completed.	**detail**
IMSI	International Mobile Subscriber Identity (IMSI) of the subscriber's user equipment (UE).	**detail**
MSISDN	Mobile station ISDN of the subscriber's user equipment.	
Calls Traced	Number of calls traced.	**detail**
Next Call	Number of next calls to be traced. For example, a value of 10 indicates that the next 10 calls are traced.	**detail**
TDF domain	TDF domain pertaining to the subscriber's call.	**detail**
FPC	FPC slot on which the call trace was enabled. This field is displayed only if the call trace is enabled on the FPC slot.	**detail**
PIC	PIC slot on which the call trace was enabled. This field is displayed only if the call trace is enabled on the PIC slot.	**detail**

Sample Output

request unified-edge tdf call-trace show brief

```
user@host> request unified-edge tdf call-trace show brief
 Identifier           File name           Status       SPIC Mask   SPIC Mask
                                                        create      complete
call_trace_id_2 call_trace_id_2_02112012_060450        done 0x10   0x10
call_trace_id_3 call_trace_id_3_02112012_070614        done 0x10   0x10
call_trace_id_4 call_trace_id_4_02112012_071342   duplicate 0x0    0x0
call_trace_id_5 call_trace_id_5_02112012_201317   duplicate 0x0    0x0
call_trace_id_6 call_trace_id_6_02112012_201649   duplicate 0x0    0x0
```

Copyright © 2018, Juniper Networks, Inc.

```
call_trace_id_7 call_trace_id_7_02112012_202501        done 0x0    0x0
call_trace_id_8 call_trace_id_8_02112012_204718   duplicate 0x0    0x0
call_trace_id_9 call_trace_id_9_02112012_204759    not-done 0x10   0x0
```

request unified-edge tdf call-trace show detail

```
user@host> request unified-edge tdf call-trace show detail
Call trace information :

  Identifier : call_trace_id_13        Trace file :
call_trace_id_13_02292012_001343
  Status : not-done    Create Mask : 0x200      Complete Mask : 0x0
  IMSI : 29299
  Calls Traced : 0
  Identifier : call_trace_id_14        Trace file :
call_trace_id_14_02292012_001348
  Status : not-done    Create Mask : 0x200      Complete Mask : 0x0
                                                     MS-ISDN: 2929910000000000
  Calls Traced : 0
  Identifier : call_trace_id_15        Trace file :
call_trace_id_15_02292012_001408
  Status : not-done    Create Mask : 0x200      Complete Mask : 0x0
  Next Call : 1                        TDF domain : jnpr-sunnyvale

  Calls Traced : 0
  Identifier : call_trace_id_16        Trace file :
call_trace_id_16_02292012_001416
  Status : not-done    Create Mask : 0x200      Complete Mask : 0x0
  Calls Traced : 0                     FPC : 3   PIC : 1
  Identifier : call_trace_id_17        Trace file :
call_trace_id_17_02292012_001424
  Status : done        Create Mask : 0x200      Complete Mask : 0x200
  Next Call : 2
  Calls Traced : 2
```


Copyright © 2018, Juniper Networks, Inc.

request unified-edge tdf call-trace start

Syntax

```
request unified-edge tdf call-trace start
<imsi imsi>
<msisdn msisdn>
<next-call next-call>
<routing-instance routing-instance>
<subscriber-name string>
<user-name string>
<v4-addr v4-addr>
<v6-addr v6-addr>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Start TDF subscriber call tracing..

Options **none**—Start call tracing for all TDF subscribers.

imsi *imsi*—(Optional) Start the call tracing for subscribers with the specified International Mobile Subscriber Identity (IMSI) number.

msisdn *msisdn*—(Optional) Start call tracing for subscribers with the specified Mobile station ISDN (MSIDSN) number.

next-call *next-call*—(Optional) Start call tracing for the specified number of next call events (1 through 50). For example, if you specify 10, then the next 10 calls are traced.

NOTE: If you do not include the next-call keyword while tracing subscribers on a domain, the default value of 1 is used.

routing-instance *routing-instance*—(Optional) Start call tracing for subscribers for the specified routing instance.

subscriber-name *string*—(Optional) Start call tracing for the specified IFL-based subscriber.

user-name *string*—(Optional) Start call tracing for the specified IP-based subscriber.

v4-addr *v4-addr*—(Optional) Start call tracing for subscribers for the specified IPv4 address of the subscriber's user equipment (UE).

v6-addr *v6-addr*—(Optional) Start call tracing for subscribers for the specified IPv6 address of the subscriber's user equipment.

Required Privilege Level unified-edge

Copyright © 2018, Juniper Networks, Inc.

Related Documentation

- request unified-edge tdf call-trace clear on page 559
- request unified-edge tdf call-trace show on page 560
- request unified-edge tdf call-trace stop on page 565

List of Sample Output request unified-edge tdf call-trace start next-call on page 564

Output Fields Table 15 on page 564 lists the output fields for the **request unified-edge tdf call-trace start** command. Output fields are listed in the approximate order in which they appear.

Table 15: request unified-edge tdf call-trace start Output Fields

Field Name	Field Description
Session PIC	Identifier of the session PIC for which the call trace status is displayed.
Status	Status of the call trace: • **duplicate**—Another call trace record is present that has the same attributes. • **success**—Call trace started successfully. • **fail**—Call tracing cannot be started.

Sample Output

request unified-edge tdf call-trace start next-call

```
user@host> request unified-edge tdf call-trace start next-call 10

      Session PIC           Status
      ms-0/1/0            success
      ms-1/1/0            success
```


Copyright © 2018, Juniper Networks, Inc.

request unified-edge tdf call-trace stop

Syntax

```
request unified-edge tdf call-trace stop
<all>
<identifier call-trace-identifier>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Stop the previously configured subscriber call tracing on one or more TDF gateways.

Options

none—(Same as all) Stop all subscriber call tracing.

all—(Optional) Stop all subscriber call tracing.

identifier *call-trace-identifier*—(Optional) Stop call tracing for the specified call trace identifier.

Required Privilege Level unified-edge

Related Documentation

- request unified-edge tdf call-trace clear on page 559
- request unified-edge tdf call-trace show on page 560
- request unified-edge tdf call-trace start on page 563

List of Sample Output request unified-edge tdf call-trace stop on page 565

Output Fields Table 16 on page 565 lists the output fields for the **request unified-edge tdf call-trace stop** command. Output fields are listed in the approximate order in which they appear.

Table 16: request unified-edge tdf call-trace stop Output Fields

Field Name	Field Description
Session PIC	Identifier of session PIC for which the call trace status is displayed.
Status	Status of the call trace: • **success**—Call trace stopped successfully. • **fail**—Call tracing cannot be stopped.

Sample Output

request unified-edge tdf call-trace stop

```
user@host> request unified-edge tdf call-trace stop
```

Copyright © 2018, Juniper Networks, Inc.

```
    Session PIC           Status
    ms-0/1/0            success
    ms-1/1/0            success
```


Copyright © 2018, Juniper Networks, Inc.

show interfaces anchor-group (Aggregated Packet Forwarding Engine)

Syntax

```
show interfaces anchor-group
<brief | detail>
interface-name
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display interface information for the aggregated Packet Forwarding Engine group.

Options

none—(Same as brief) Display a summary of the aggregated Packet Forwarding Engine interface information.

brief | detail—(Optional) Display the specified level of output.

interface-name—Name of the interface within the anchor Packet Forwarding Engine group.

NOTE: The interface must be an aggregated Packet Forwarding Engine interface (apfe-).

Required Privilege Level view

Related Documentation

- show unified-edge tdf system interfaces on page 717

List of Sample Output

show interfaces anchor-group brief on page 569
show interfaces anchor-group detail on page 569

Output Fields Table 17 on page 567 lists the output fields for the **show interfaces anchor-group** command. Output fields are listed in the approximate order in which they appear.

Table 17: show interfaces anchor-group Output Fields

Field Name	Field Description	Level of Output
Active	Anchor Packet Forwarding Engine is operational.	All levels
Inactive	Anchor Packet Forwarding Engine is not operational.	All levels
PF	Primary Packet Forwarding Engine anchor has failed.	All levels
MS	Primary Packet Forwarding Engine is protected by a secondary Packet Forwarding Engine in manually switched mode for mastership change.	All levels

Copyright © 2018, Juniper Networks, Inc.

Table 17: show interfaces anchor-group Output Fields (continued)

Field Name	Field Description	Level of Output
HS	Primary Packet Forwarding Engine is protected by a secondary Packet Forwarding Engine in hot standby mode.	All levels
WS	Primary Packet Forwarding Engine is protected by a secondary Packet Forwarding Engine in warm standby mode.	All levels
Group	Name of the aggregated Packet Forwarding Engine group.	**brief** none
Mode	Redundancy mode in which the aggregated Packet Forwarding Engine group operates. Currently, only warm standby mode is supported.	**brief** none
Sub-group ID	Redundancy subgroups within the anchor Packet Forwarding Engine group configuration that has FPCs as members. This is derived out of the Packet Forwarding Engines on a given FPC. For example, if the first Packet Forwarding Engine is assigned the number 0, then all the other Packet Forwarding Engines with sub-group ID 0 form the N:1 redundancy group.	**brief** none
Interface	Anchor Packet Forwarding Engine interface (**pfe-**).	All levels
Configured State	State in which the anchor Packet Forwarding Engine was configured. • **Primary**—Anchor Packet Forwarding Engine is in the pool of primary members. • **Secondary**—Anchor Packet Forwarding Engine is a backup to all the primary members.	All levels
Operational State	Indication whether the anchor Packet Forwarding Engine is operational (**Active**) or not operational (**Inactive**).	All levels
Redundancy State	Redundancy state (primary or secondary) in which the anchor Packet Forwarding Engine was configured.	All levels
Group Name	Name of the aggregated Packet Forwarding Engine group.	**detail**
Group Mode	Redundancy mode in which the aggregated Packet Forwarding Engine group operates. Currently, only warm standby mode is supported.	**detail**
Group Id	Internal ID generated for the group.	**detail**
Switchover information	Switchover details, if any.	**detail**
Subgroup identifier	Number of redundancy subgroups within the anchor Packet Forwarding Engine group configuration that has FPCs as members. This is derived out of the Packet Forwarding Engines on a given FPC. For example, if the first Packet Forwarding Engine is assigned the number 0, then all the other Packet Forwarding Engines with subgroup ID 0 form the N:1 redundancy group.	**detail**

Copyright © 2018, Juniper Networks, Inc.

Sample Output

show interfaces anchor-group brief

```
user@host> show interfaces anchor-group brief
```

```
Redundancy Status Legend:

Active: Operational               Inactive: Non-operational
MS: Manually switched             PF: Primary failed
HS: Hot standby                   WS: Warm standby

Group     Mode  Sub-group  Interface  Configured  Operational    Redundancy
                   ID                    State       State          State

apfe0     WS       0       pfe-4/0/0  Primary     Active         Primary
                           pfe-5/0/0  Secondary   Active         Secondary
                   2       pfe-4/2/0  Primary     Active         Primary
                           pfe-5/2/0  Secondary   Active         Secondary
```

show interfaces anchor-group detail

```
user@host> show interfaces anchor-group detail
```

```
Active: Operational               Inactive: Non-operational
MS: Manually switched             PF: Primary failed
HS: Hot standby                   WS: Warm standby

Group Name: apfe0
  Group Mode: WS                       Group Id: 65
  Switchover information: None
  Interface pfe-4/2/0
    Configured state: Primary          Operational state: Active
    Redundancy state: Primary
    Subgroup identifier: 2
  Interface pfe-4/0/0
    Configured state: Primary          Operational state: Active
    Redundancy state: Primary
    Subgroup identifier: 0
  Interface pfe-5/0/0
    Configured state: Secondary        Operational state: Active
    Redundancy state: Secondary
    Subgroup identifier: 0
  Interface pfe-5/2/0
    Configured state: Secondary        Operational state: Active
    Redundancy state: Secondary
    Subgroup identifier: 2
```

Copyright © 2018, Juniper Networks, Inc.

show interfaces load-balancing (Aggregated Multiservices)

Syntax

```
show interfaces load-balancing
<detail>
<interface-name>
```

Release Information

Command introduced in Junos OS Release 11.4.
interface-name option added in Junos OS Release 16.1.

Description

Display information about the aggregated multiservices interface (AMS) as well as its individual member interfaces and the status of the replication state.

Options

none—Display standard information about status of all AMS interfaces.

detail—(Optional) Display detailed status of all AMS interfaces.

interface-name—(Optional) Name of the aggregated multiservices interface (**ams**). If this is omitted, then the information for all the aggregated multiservices interfaces, including those used in control plane redundancy and high availability (HA) for service applications, is displayed.

Required Privilege Level

view

Related Documentation

- *Understanding Aggregated Multiservices Interfaces*
- *Configuring Aggregated Multiservices Interfaces*
- *Example: Configuring an Aggregated Multiservices Interface (AMS)*

List of Sample Output

show interfaces load-balancing on page 573
show interfaces load-balancing detail on page 573
show interfaces load-balancing detail (Specific Interface) on page 573

Output Fields

Table 18 on page 570 lists the output fields for the **show interfaces load-balancing** (aggregated multiservices interfaces) command. Output fields are listed in the approximate order in which they appear.

Table 18: Aggregated Multiservices show interfaces load-balancing Output Fields

Field Name	Field Description	Level of Output
Interface	Name of the aggregated multiservices (AMS) interface.	**detail** none

Copyright © 2018, Juniper Networks, Inc.

Table 18: Aggregated Multiservices show interfaces load-balancing Output Fields (continued)

Field Name	Field Description	Level of Output
State	Status of AMS interfaces: • **Coming Up**—Interface is becoming operational. • **Members Seen**—Member interfaces (mams) are available. • **Up**—Interface is configured and operational. • **Wait for Members**—Member interfaces (mams) are not available. • **Wait Timer**—Interface is waiting for member interfaces (mams) to come online.	**detail** none
Last change	Time (in *hh:mm:ss* [*hours:minutes:seconds*] format) when the state last changed.	**detail** none
Members	Number of member interfaces (mams-).	none specified
Member count	Number of member PICs (mams) that are part of the aggregated interface.	**detail** none
HA Model	High availability (HA) model supported on the interface. • **Many-to-One**—The preferred backup Multiservices PIC, in hot standby mode, backs up one or more (N) active Multiservices PICs. • **One-to-One**—–The preferred backup Multiservices PIC, in hot standby mode, backs up only one active Multiservices PIC.	**detail** none

Members	Information about the member interfaces:
	• **Interface**—Name of the member interface.
	• **Weight**—Not applicable for the current release.
	• **State**—State of the member interface (mams-).
	  • **Active**—Member is an active member.
	  • **Backup**—Member is a backup.
	  • **Discard**—Member has not yet rejoined the ams interface after failure.
	  • **Down**—Member has not yet powered on.
	  • **Inactive**—Member has failed to rejoin the ams interface within the configured **rejoin-timeout**.
	  • **Invalid**—Multiservices PIC corresponding to the member interface has been configured but is not physically present in the chassis.
		detail

Copyright © 2018, Juniper Networks, Inc.

Table 18: Aggregated Multiservices show interfaces load-balancing Output Fields (continued)

Field Name	Field Description	Level of Output

Sync-state	Synchronization (sync) status of the control plane redundancy. The sync state is displayed only when the ams interface is **Up**.
	• **Interface**—Name of the member interface.
	• **Status**—Synchronization status of the member interfaces.
	  • **In progress**—The active member is currently synchronizing its state information with the backup member.
	  • **In sync**—The active member has finished synchronizing its state information with the backup and the backup is ready to take over if the active member fails.
	  • **NA (Not applicable)**—The backup member is not yet ready to synchronize with the active (primary) member. This condition may occur if the backup is still powered off or still booting.
	  • **Unknown**—The daemons are still initializing and the state information is unavailable.
		detail

Copyright © 2018, Juniper Networks, Inc.

Sample Output

show interfaces load-balancing

```
user@host> show interfaces load-balancing
```

```
Interface  State       Last change  Members  HA Model
ams0       Up          00:10:02     4        Many-to-One
```

show interfaces load-balancing detail

```
user@host> show interfaces load-balancing detail
```

```
Load-balancing interfaces detail
Interface        : ams0
  State          : Up
  Last change    : 00:10:23
  Member count   : 4
  HA Model       : Many-to-One
  Members        :
      Interface    Weight   State
      mams-4/0/0   10       Active
      mams-4/1/0   10       Active
      mams-5/0/0   10       Active
      mams-5/1/0   10       Backup
  Sync-state     :
      Interface    Status
      mams-4/0/0   Unknown
      mams-4/1/0   Unknown
      mams-5/0/0   Unknown
```

show interfaces load-balancing detail (Specific Interface)

```
user@host> show interfaces load-balancing ams0 detail
```

```
Load-balancing interfaces detail
Interface        : ams0
  State          : Up
  Last change    : 00:11:28
  Member count   : 4
  HA Model       : Many-to-One
  Members        :
      Interface    Weight   State
      mams-4/0/0   10       Active
      mams-4/1/0   10       Active
      mams-5/0/0   10       Active
      mams-5/1/0   10       Backup
  Sync-state     :
      Interface    Status
      mams-4/0/0   Unknown
      mams-4/1/0   Unknown
      mams-5/0/0   Unknown
```

Copyright © 2018, Juniper Networks, Inc.

show services application-identification application

Syntax

```
show services application-identification application
<detail <application-name> | summary >
```

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Display detailed information about a specified application signature, all application signatures, or a summary of the existing application signatures and nested application signatures. Both custom and predefined application signatures and nested application signatures can be displayed.

Options

none—(Same as summary) Display a summary of the application identification application information.

detail <*application-name*> | summary—(Optional) Display the specified level of output.

application-name—(Optional) Display detailed information for the specified application name; maximum 31 characters. Predefined applications have the prefix **junos-** to avoid conflict with user-defined ones.

Required Privilege Level

view

Related Documentation

- request services application-identification install on page 554
- request services application-identification application on page 548

List of Sample Output

show services application-identification application summary on page 576
show services application-identification application detail on page 576
show services application-identification application detail (Specific Application) on page 578
show services application-identification application detail (Specific Application) on page 579

Output Fields

Table 19 on page 574 lists the output fields for the **show services application-identification application** command. Output fields are listed in the approximate order in which they appear.

Table 19: show services application-identification application Output Fields

Field Name	Field Description	Level of Output
Application(s)	Number of applications present.	none **summary**

Copyright © 2018, Juniper Networks, Inc.

Table 19: show services application-identification application Output Fields (continued)

Field Name	Field Description	Level of Output
Application	Name of the predefined application.	none **summary**
Disabled	Status (**Yes** or **No**) of the application and whether the mapping method is currently used to identify this application.	none **summary**
Application ID	Unique ID number of an application. ID numbers 1 through 32,767 are automatically generated for predefined applications; these IDs do not change.	none **summary**
Order	Unique number used to specify priority when multiple applications match the traffic. The lowest order number takes the highest priority. The order attribute is applicable only for custom signatures.	none **summary**
Application Name	Name of the predefined application.	**detail**
Application type	Basic application type, such as HTTP.	**detail**
Description	Description of the predefined application.	**detail**
Number of Parent Group(s)	Number of parent groups associated with this application.	**detail**
Application Tags	Category specifying one or more following attributes of the application: **characteristic**: One or more characteristics of the application. **risk**: Level of risk of the application. **subcategory**: Subcategory of the application. **category**: Technology of the application.	**detail**
Layer-7 Protocol(s)	Layer 7 protocols associated with the application.	**detail**
Port Mapping Default port	Ports associated with the application.	**detail**
Signature	Signature mapping criteria for application identification: **Port range**, **Client-to-server**, and **Order**.	**detail**

Copyright © 2018, Juniper Networks, Inc.

Sample Output

show services application-identification application summary

```
user@host> show services application-identification application summary
```

```
Application(s): 2564
  Applications                                  Disabled         ID      Order
  junos:DOT-NET                                  No               10182   2564

  junos:ICMP-PHOTURIS-NEED-AUTHOR                No               11377   2563

  junos:MYSPACE-TAG-ME                           No               10683   2562

  junos:SLACKER                                  No               1179    2561

  junos:ICMP-TYPE-55                             No               11392   2560

  junos:FLIPDRIVE-SSL                            No               10939   2559

  junos:ICMP-MOBILE-HOST-REDIR                   No               11363   2558

  junos:TWITPIC                                  No               864     2557

  junos:ICMP-TYPE-245                            No               11582   2556
```

show services application-identification application detail

```
user@host> show services application-identification application detail
```

```
re0:
--------------------------------------------------------------------------------
Application Name: junos:dot-net
Application type: DOT-NET
Description: .Net Remoting
Application ID: 10182
Disabled: No
Number of Parent Group(s): 1
Application Groups:
    junos:infrastructure:rpc
Port Mapping:
    Default ports: N/A
Signature:
    Port range: N/A
    Client-to-server
    Order: 1
Application Name: junos:icmp-photuris-need-author
Application type: ICMP-PHOTURIS-NEED-AUTHOR
Description: ICMP Type 40 Code 5 - Photuris (Need Authorization)
Application ID: 11377
Disabled: No
Number of Parent Group(s): 1
Application Groups:
    junos:infrastructure:networking
Port Mapping:
    Default ports: N/A
Signature:
    Port range: N/A
    Client-to-server
    Order: 5
```


Copyright © 2018, Juniper Networks, Inc.

```
Application Name: junos:myspace-tag-me
Application type: MYSPACE-TAG-ME
Description: This signature detects Tag Me by BitRhymes on MySpace Apps.  Tag
             Me by BitRhymes on MySpace Apps is a Web-based entertainment
             application on the popular social network MySpace.
Application ID: 10683
Disabled: No
Number of Parent Group(s): 1
Application Groups:
    junos:web:social-networking
Port Mapping:
    Default ports: N/A
Signature:
    Port range: N/A
    Client-to-server
    Order: 4
Application Name: junos:slacker
Application type: SLACKER
Description: This protocol plug-in classifies the http traffic to the host
             .slacker.com.
Application ID: 1179
Disabled: No
Number of Parent Group(s): 2
Application Groups:
    junos:multimedia:divers
    junos:multimedia
Port Mapping:
    Default ports: N/A
Signature:
    Port range: N/A
    Client-to-server
    Order: 3
Application Name: junos:icmp-type-55
Application type: ICMP-TYPE-55
Description: ICMP Type 55 - Unassigned
Application ID: 11392
Disabled: No
Number of Parent Group(s): 1
Application Groups:
    junos:infrastructure:networking
Port Mapping:
    Default ports: N/A
Signature:
    Port range: N/A
    Client-to-server
    Order: 2
Application Name: junos:flipdrive-ssl
Application type: FLIPDRIVE-SSL
Description: This signature detects logins to FlipDrive, a cloud-based
             file-sharing and backup service.
Application ID: 10939
Disabled: No
Number of Parent Group(s): 1
Application Groups:
    junos:web:file-sharing
Port Mapping:
    Default ports: N/A
Signature:
    Port range: N/A
    Client-to-server
```

Copyright © 2018, Juniper Networks, Inc.

```
    Order: 1
Application Name: junos:icmp-mobile-host-redir
Application type: ICMP-MOBILE-HOST-REDIR
Description: ICMP Type 32 - Mobile Host Redirect
Application ID: 11363
Disabled: No
Number of Parent Group(s): 1
Application Groups:
    junos:infrastructure:networking
Port Mapping:
    Default ports: N/A
Signature:
    Port range: N/A
    Client-to-server
    Order: 5
Application Name: junos:twitpic
Application type: TWITPIC
Description: This signature detects Twitpic, a Web site that allows users to
             easily post pictures to the Twitter microblogging and social media
             service.
Application ID: 864
Disabled: No
Number of Parent Group(s): 1
Application Groups:
    junos:web:social-networking
Port Mapping:
    Default ports: N/A
Signature:
    Port range: N/A
    Client-to-server
    Order: 4
Application Name: junos:icmp-type-245
Application type: ICMP-TYPE-245
Description: ICMP Type 245 - Unassigned
Application ID: 11582
Disabled: No
Number of Parent Group(s): 1
Application Groups:
    junos:infrastructure:networking
Port Mapping:
    Default ports: N/A
Signature:
    Port range: N/A
    Client-to-server
    Order: 3

---(more)---
```

show services application-identification application detail (Specific Application)

```
user@host> show services application-identification application detail junos:SKYPE
```

```
Application Name: junos:SKYPE
Application type: SKYPE
Description: This signature detects Skype, which is a proprietary P2P VOIP
             network. It is a "complete black box" for both users and
             analyzers. It uses security through obscurity to make itself
             troublesome to analyze or reverse-engineer without a significant
             amount of work, or use of emulation. It uses AES block cipher, the
             RSA public key cryptosystem, the ISO 9796-2 signature padding
```


Copyright © 2018, Juniper Networks, Inc.

```
            scheme, the SHA-1 hash function, and the RC4 stream cipher through
            the communications between the client to client, client to
            supernodes and supernode to supernode.
Application ID: 183
Disabled: No
Number of Parent Group(s): 1
Application Groups:
    junos:web:infrastructure:voip
Application Tags:
    characteristic        : Supports File Transfer
    characteristic        : Evasive
    characteristic        : Bandwidth Consumer
    risk                  : 4
    subcategory           : VOIP
    category              : Infrastructure
Layer-7 Protocol(s): UDP         / 216
                     TCP         / 205
                     SSL         / 199
                     HTTPS       / 68
                     HTTP        / 67
Port Mapping:
    Default ports: N/A
Signature:
    Port range: N/A
    Client-to-server
    Order: 20
```

show services application-identification application detail (Specific Application)

```
user@host> show services application-identification detail junos:http
```

```
re0:
--------------------------------------------------------------------------
Application Name: junos:http
Application type: HTTP
Description: This signature detects HyperText Transfer Protocol (HTTP), which
             is a protocol used by the World Wide Web. It defines how messages
             are formatted and transmitted and what actions Web servers and
             browsers should take in response to various commands. HTTP usually
             runs on TCP port 80.
Application ID: 67
Disabled: No
Number of Parent Group(s): 1
Application Groups:
    junos:web
Port Mapping:
    Default ports: TCP/80,3128,8000,8080
Signature:
    Port range: N/A
    Client-to-server
    Order: 3
```

Copyright © 2018, Juniper Networks, Inc.

show services application-identification application-system-cache

Syntax

show services application-identification application-system-cache
<interface *interface-name*>

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Display the database of cached values stored by the application identification system.

NOTE: The **show services application-identification application-system-cache** command gives the information only when the application identifier (AI) is matched with the signature.

Options

none—Display the database of cached values for the all services interfaces.

interface *interface-name*—(Optional) Display the database of cached values for the specified services interface.

Required Privilege Level

view

Related Documentation

- request services application-identification application on page 548

List of Sample Output

show services application-identification application-system-cache on page 582
show services application-identification application-system-cache interface on page 582

Output Fields

Table 20 on page 580 lists the output fields for the **show services application-identification application-system-cache** command. Output fields are listed in the approximate order in which they appear.

Table 20: show services application-identification application-system-cache Output Fields

Field Name	Field Description
application-cache	Status (**on** or **off**) of the application cache.
cache-entry-timeout	Number of seconds the mapping information is saved.
pic	PIC number of the accumulated statistics.
IP address	IP address of the traffic flow for which application-identification is enabled.
Port	Port number of the traffic flow for which application-identification is enabled.

Copyright © 2018, Juniper Networks, Inc.

Table 20: show services application-identification application-system-cache Output Fields (continued)

Field Name	Field Description
Protocol	Protocol name of the flow for which application-identification is enabled.
Application	Application number, which is a unique identifier that denotes the application or service for which identification of traffic flows is enabled.
Classification Path	Protocols or nested applications that denote the paths traversed for classified packets.
PIC	PIC number of the accumulated statistics. For the interface on which deep packet inspection (DPI) application is not running, that detail is also displayed for the corresponding interface.
Unknown applications	Number of unknown applications.
Cache hits	Number of sessions that matched the application in the application identification cache.
Cache misses	Number of sessions that did not find the application in the application identification cache.
Client-to-server packets processed	Number of client-to-server packets processed.
Server-to-client packets processed	Number of server-to-client packets processed.
Client-to-server bytes processed	Number of client-to-server payload bytes processed.
Server-to-client layer bytes processed	Number of server-to-client payload bytes processed.
Client-to-server packets processed	Number of client-to-server packets processed.
Server-to-client packets processed	Number of server-to-client packets processed.
Client-to-server bytes processed	Number of client-to-server payload bytes processed.
Server-to-client layer bytes processed	Number of server-to-client payload bytes processed.
Sessions bypassed due to resource allocation failure	Number of sessions bypassed due to resource allocation failure.
Segment case 1 - New segment to left	Number of TCP segments contained before the previous segment.

Copyright © 2018, Juniper Networks, Inc.

Table 20: show services application-identification application-system-cache Output Fields (continued)

Field Name	Field Description
Segment case 2 - New segment overlap right	Number of TCP segments that start before the previous segment and are contained in it.
Segment case 3 - Old segment overlapped	Number of TCP segments that start before the previous segment and extend beyond it.
Segment case 4 - New segment overlapped	Number of TCP segments that start and end within the previous segment.
Segment case 5 - New segment overlap left	Number of TCP segments that start within the previous segments and extend beyond it.
Segment case 6 - New segment to right	Number of TCP segments that start after the previous segment. This is the normal case.

Sample Output

show services application-identification application-system-cache

```
user@host> show services application-identification application-system-cache
Application System Cache Configurations:
  application-cache: on
  cache-entry-timeout: 3600 seconds
pic: ams0
pic: ms-0/3/0
ms-0/3/0 is not running DPI engine
pic: ams1
pic: ms-0/0/0
IP address: 192.0.2.2                                Port: 80     Protocol: TCP
Application: HTTP:YOUTUBE
Classification Path: IP:TCP:HTTP:YOUTUBE
```

show services application-identification application-system-cache interface

```
user@host> show services application-identification application-system-cache interface ms-1/0/0
Application System Cache Configurations:
  application-cache: on
  cache-entry-timeout: 3600 seconds
pic: ms-0/0/0
IP address: 192.0.2.2                                Port: 80     Protocol: TCP
Application: HTTP:YOUTUBE
Classification Path: IP:TCP:HTTP:YOUTUBE
user@host> show services application-identification counter

pic: ams0
ms-0/3/0 is not running DPI engine
```


Copyright © 2018, Juniper Networks, Inc.

```
pic: ams1
  Counter type                                                  Value
Unknown applications                                             32682
Cache hits                                                       323504
Cache misses                                                     400
Client-to-server packets processed                               2034
Server-to-client packets processed                               1982
Client-to-server bytes processed                                 258786
Server-to-client bytes processed                                 1314722
Sessions bypassed due to resource allocation failure             0
Segment case 1 - New segment to left                             0
Segment case 2 - New segment overlap right                       0
Segment case 3 - Old segment overlapped                          0
Segment case 4 - New segment overlapped                          0
Segment case 5 - New segment overlap left                        0
Segment case 6 - New segment to right                            0
```

Copyright © 2018, Juniper Networks, Inc.

show services application-identification counter

Syntax

show services application-identification counter
<interface *interface-name*>

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Display application identification counter statistics.

Options

none—Display counter statistics for all services interfaces.

interface *interface-name*—(Optional) Display counter statistics for the specified services interface.

Required Privilege Level

view

Related Documentation

- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25

List of Sample Output

show services application-identification counter on page 585

Output Fields

Table 21 on page 584 lists the output fields for the **show services application-identification counter** command. Output fields are listed in an approximate order in which they appear.

Table 21: show services application-identification counter Output Fields

Field Name	Field Description
PIC	PIC number of the accumulated statistics.
Unknown applications	Number of unknown applications.
Cache hits	Number of sessions that matched the application in the application identification cache.
Cache misses	Number of sessions that did not find the application in the application identification cache.
Client-to-server packets processed	Number of client-to-server packets processed.
Server-to-client packets processed	Number of server-to-client packets processed.
Client-to-server bytes processed	Number of client-to-server payload bytes processed.
Server-to-client layer bytes processed	Number of server-to-client payload bytes processed.

Copyright © 2018, Juniper Networks, Inc.

Table 21: show services application-identification counter Output Fields (continued)

Field Name	Field Description
Sessions bypassed due to resource allocation failure	Number of sessions bypassed due to resource allocation failure.
Segment case 1 - New segment to left	Number of TCP segments contained before the previous segment.
Segment case 2 - New segment overlap right	Number of TCP segments that start before the previous segment and are contained in it.
Segment case 3 - Old segment overlapped	Number of TCP segments that start before the previous segment and extend beyond it.
Segment case 4 - New segment overlapped	Number of TCP segments that start and end within the previous segment.
Segment case 5 - New segment overlap left	Number of TCP segments that start within the previous segments and extend beyond it.
Segment case 6 - New segment to right	Number of TCP segments that start after the previous segment. This is the normal case.

Sample Output

show services application-identification counter

```
user@host> show services application-identification counter


pic: 5/0
  Counter type                                                  Value
 Unknown applications                                             0
 Cache hits                                                       0
 Cache misses                                                    36
 Client-to-server packets processed                              16
 Server-to-client packets processed                             101
 Client-to-server bytes processed                              3494
 Server-to-client bytes processed                            112493
 Sessions bypassed due to resource allocation failure             0
 Segment case 1 - New segment to left                            11
 Segment case 2 - New segment overlap right                       8
 Segment case 3 - Old segment overlapped                          0
 Segment case 4 - New segment overlapped                          0
 Segment case 5 - New segment overlap left                        0
 Segment case 6 - New segment to right                            7

pic: 5/1
  Counter type                                                  Value
 Unknown applications                                             0
 Cache hits                                                       0
 Cache misses                                                     0
 Client-to-server packets processed                               0
 Server-to-client packets processed                               0
```

Copyright © 2018, Juniper Networks, Inc.

```
Client-to-server bytes processed                                    0
Server-to-client bytes processed                                    0
Sessions bypassed due to resource allocation failure                0
Segment case 1 - New segment to left                                0
Segment case 2 - New segment overlap right                          0
Segment case 3 - Old segment overlapped                             0
Segment case 4 - New segment overlapped                             0
Segment case 5 - New segment overlap left                           0
Segment case 6 - New segment to right                               0
```


Copyright © 2018, Juniper Networks, Inc.

show services application-identification group

Syntax show services application-identification group [detail *application-group name* | summary]

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display detailed or summary information about a specified application signature group or all application signature groups. Both custom and predefined application signature groups can be displayed.

Options **none**—Display summary information for all application signature groups.

detail | summary—Display the specified level of output.

application-name—Application name; maximum 31 characters. Predefined applications have the prefix **junos-** to avoid conflict with user-defined ones.

Required Privilege Level view

Related Documentation

- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25
- request services application-identification group on page 552

List of Sample Output

show services application-identification group summary on page 588
show services application-identification group detail on page 589

Output Fields Table 22 on page 587 lists the output fields for the **show services application-identification group** command. Output fields are listed in the approximate order in which they appear.

Table 22: show services application-identification group Output Fields

Field Name	Field Description	Level of Output
Group ID	Unique ID number of an application signature group. ID numbers 1 through 32,767 are automatically generated for predefined application signatures and application signature groups; these IDs do not change. ID numbers for custom application signatures and application signature groups use ID numbers 32,768 through 65,534.	none **detail** **summary**
Disabled	Status of the application signature group and whether the signature method is currently used to identify this application. The default is No.	none **summary**

Copyright © 2018, Juniper Networks, Inc.

Table 22: show services application-identification group Output Fields (continued)

Field Name	Field Description	Level of Output
Application Group(s)	Number of application signature groups present.	none **summary**
Applications	Names of application signatures associated with this application signature group.	none **detail** **summary**
Group Name	Name of an application signature or application signature group.	**detail**
Description	Description of the specified application in the detailed display. If a description is not previously specified, **N/A** is displayed for this field.	**detail**
Number of Applications	Total number of applications contained in the group.	**detail**
Number of Sub-Groups	Total number of sub-groups associated with this application signature group.	**detail**
Number of Parent-Groups	Total number of parent groups in this application signature group or cluster.	**detail**
Sub-Group(s)	Application signature sub-groups present.	**detail**

Sample Output

show services application-identification group summary

```
user@host> show services application-identification group summary

Application Group(s): 66
Application Groups                                Disabled  ID
  junos:web:social-networking:facebook             No        68
  junos:web:reference                              No        67
  junos:infrastructure:legacy                      No        66
  junos:web:cdn                                    No        65
  junos:infrastructure:scada                       No        64
  junos:web:real-estate                            No        63
  junos:web:finance                                No        62
  junos:multimedia:audio-streaming                 No        61
  junos:web:remote-access                          No        60
  junos:web:p2p                                    No        59
  junos:remote-access:backdoors                    No        58
  junos:infrastructure:authentication              No        57
  junos:web:forums                                 No        56
  junos:remote-access:command                      No        55
  junos:infrastructure:scm                         No        54
  junos:web:portal                                 No        53
```


Copyright © 2018, Juniper Networks, Inc.

```
junos:web:shopping                                No        52
junos:infrastructure:rpc                          No        51
junos:messaging:mail                              No        50
junos:web:search                                  No        49
junos:infrastructure:encryption                   No        48
junos:gaming:divers                               No        47
junos:p2p:file-sharing                            No        46
junos:infrastructure:backup                       No        45
junos:multimedia:transport                        No        44
junos:gaming:protocols                            No        43
junos:web:advertisements                          No        42
junos:infrastructure:monitoring                   No        41
junos:infrastructure:mobile                       No        40
junos:infrastructure:file-servers                 No        39
junos:web:infrastructure                          No        38
junos:web:wiki                                    No        37
junos:web:image-sharing                           No        36
junos:infrastructure:directory                    No        35
junos:infrastructure:database                     No        34
junos:remote-access:tunneling                     No        33
junos:remote-access:interactive-desktop           No        32
junos:web:gaming                                  No        31
junos:web:anonymizer                              No        30
junos:web:blogging                                No        29
junos:remote-access:divers                        No        28
junos:remote-access                               No        27
junos:p2p:divers                                  No        26
junos:p2p                                         No        25
junos:web:news                                    No        24
junos:gaming:web-based                            No        23
junos:gaming                                      No        22
junos:web:messaging                               No        21
junos:multimedia:web-based                        No        20
junos:web:file-sharing                            No        19
junos:web:travel                                  No        18
junos:multimedia:video-streaming                  No        17
junos:messaging:instant-messaging                 No        16
junos:web:multimedia                              No        15
junos:infrastructure:voip                         No        14
junos:messaging:divers                            No        13
junos:messaging                                   No        12
junos:web:applications                            No        11
junos:multimedia:divers                           No        10
junos:multimedia                                  No        9
junos:web:divers                                  No        8
junos:web:social-networking                       No        7
junos:web                                         No        6
junos:infrastructure:networking                   No        5
junos:infrastructure:divers                       No        4
junos:infrastructure                              No        3
```

show services application-identification group detail

```
user@host> show services application-identification group detail junos:social-networking

Group Name: junos:web
Group ID: 15
Description: N/A
Disabled: No
Number of Applications: 1
```

```
Number of Sub-Groups: 21
Number of Parent-Groups: 1
Applications:
    junos:http
Sub Groups:
    junos:web:forums
    junos:web:travel
    junos:web:reference
    junos:web:portal
    junos:web:blogging
    junos:web:shopping
    junos:web:search
    junos:web:anonymizer
    junos:web:image-sharing
    junos:web:file-sharing
    junos:web:remote-access
    junos:web:real-estate
    junos:web:news
    junos:web:gaming
    junos:web:p2p
    junos:web:applications
    junos:web:multimedia
    junos:web:divers
    junos:web:messaging
    junos:web:social-networking
    junos:web:infrastructure
```


Copyright © 2018, Juniper Networks, Inc.

show services application-identification statistics application-groups

Syntax show services application-identification statistics application-groups

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display cumulative session and byte statistics per application group. Statistics are displayed in alphabetical order.

Options This command has no options.

Required Privilege Level view

Related Documentation
- clear services application-identification statistics on page 527

List of Sample Output show services application-identification statistics application-groups on page 591

Output Fields Table 23 on page 591 lists the output fields for the **show services application-identification statistics application-groups** command. Output fields are listed in the approximate order in which they appear.

Table 23: show services application-identification statistics application-groups Output Fields

Field Name	Field Description
Last Reset	Date, time, and how long ago the statistics for the sessions were cleared. The format None specified is *year-month-day hour:minute:second timezone*. If you did not clear the statistics previously at any point, **Never** is displayed.
Application Group	Name of the application group.
Sessions	Number of sessions for the application group.
Kilo Bytes	Size of the application group in kilobytes.

Sample Output

show services application-identification statistics application-groups

```
user@host> show services application-identification statistics application-groups

Last Reset: 2014-02-19 00:38:01 PST
                Application Group           Sessions         Kilo Bytes
             junos:infrastructure                  2                 18
  junos:infrastructure:monitoring                  2                 18
```

Copyright © 2018, Juniper Networks, Inc.

Copyright © 2018, Juniper Networks, Inc.

show services application-identification statistics applications

Syntax show services application-identification statistics applications

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display cumulative session and byte statistics per application. Statistics are displayed in alphabetical order.

Options This command has no options.

Required Privilege Level view

Related Documentation
- clear services application-identification statistics on page 527

List of Sample Output show services application-identification statistics applications on page 593

Output Fields Table 24 on page 593 lists the output fields for the **show services application-identification statistics applications** command. Output fields are listed in the approximate order in which they appear.

Table 24: show services application-identification statistics applications Output Fields

Field Name	Field Description
Last Reset	Date, time, and how long ago the statistics for the sessions were cleared in the format *year-month-day hour:minute:second timezone* . If you did not clear the statistics previously at any point, **Never** is displayed.
Application	Name of the application.
Sessions	Number of sessions for the application.
Bytes	Size of the application in bytes.

Sample Output

show services application-identification statistics applications

```
user@host> show services application-identification statistics applications
```

```
Last Reset: 2014-01-26 18:32:36 PST
         Application           Sessions             Bytes
          junos:http                  4             24009
          junos:https                 1            101823
```

```
        junos:hulu                  1              48329
    junos:linkedin                  1               2650
     junos:netflix                  2              32747
```


Copyright © 2018, Juniper Networks, Inc.

show services application-identification status

Syntax

show services application-identification status

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Display detailed information about application identification status.

Required Privilege Level

view

Related Documentation

- Application Identification Overview on page 23
- Configuring Custom Application Signatures on page 25
- request services application-identification application on page 548

List of Sample Output

show services application-identification status on page 596

Output Fields

Table 25 on page 595 lists the output fields for the **show services application-identification status** command. Output fields are listed in the approximate order in which they appear.

Table 25: show services application-identification status Output Fields

Field Name	Field Description
Application Identification	Details of the application-identification engine and the processing details of sessions.
Status	Status of application identification: **Enabled** or **Disabled**.
Sessions under app detection	Number of sessions undergoing application identification detection.
Engine Version	Application identification detector engine version.
Max TCP session packet memory	Maximum number of TCP sessions that application identification maintains.
Force packet plugin	Force packet plugin status: **Enabled** or **Disabled**.
Force stream plugin	Force stream plugin status: **Enabled** or **Disabled**.
Statistics collection interval	Frequency (in minutes) for collecting statistics.
Application System Cache	Details of entries in the application system cache.
Status	Status of application system cache: **Enabled** or **Disabled**.

Copyright © 2018, Juniper Networks, Inc.

Table 25: show services application-identification status Output Fields (continued)

Field Name	Field Description
Max Number of entries in cache	Maximum number of cache entries.
Cache timeout	Number of seconds after which the cache entries expires.
Protocol Bundle	Information regarding application package downloads.
Download Server CGI	URL of the server from where protocol bundle was downloaded.
Auto Update	Status of auto update to receive protocol bundle updates from the server: **Enabled** or **Disabled**.
Slot	Number of the slot pertaining to the packets for which application-identification is associated.
Status	Status of protocol bundle: **Active** or **Free**.
Version	Version of protocol bundle.
Session	Number of active sessions.

Sample Output

show services application-identification status

```
user@host> show services application-identification status
pic: 5/0

Application Identification
 Status                          Enabled
 Sessions under app detection    0
 Engine Version                  4.18.1-20 (build date Feb 15 2014)
 Max TCP session packet memory   30000
 Force packet plugin             Disabled
 Force stream plugin             Disabled
 Statistics collection interval  1 (in minutes)

Application System Cache
 Status                          Enabled
 Max Number of entries in cache  131072
 Cache timeout                   3600 (in seconds)

Protocol Bundle
 Download Server              https://services.netscreen.com/cgi-bin/index.cgi

 AutoUpdate                      Disabled
Slot 1:
 Status                          Active
 Version                         1.30.4-22.005 (build date Jan 17 2014)
 Sessions                        0
```


Copyright © 2018, Juniper Networks, Inc.

```
Slot 2
 Status                          Free
```

Copyright © 2018, Juniper Networks, Inc.

show services application-identification version

Syntax show services application-identification version

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display the Junos OS application package version.

Required Privilege Level view

Related Documentation
- request services application-identification download on page 550

List of Sample Output show services application-identification version on page 598

Sample Output

show services application-identification version

```
user@host> show services application-identification version
Application package version: 1608
```


Copyright © 2018, Juniper Networks, Inc.

show services ha detail

Syntax

```
show services ha detail
<interface interface-name>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display detailed information for stateful sync processing for a specified interface or for all interfaces.

Options

none—Display detailed information for stateful sync processing for all interfaces.

interface-name—(Optional) Name of a specific interface.

Required Privilege Level view

Related Documentation

- *Inter-Chassis Stateful Synchronization for Long Lived NAT and Stateful Firewall Flows (MS-MPC, MS-MIC) Overview (Release 16.1 and later)*

List of Sample Output show services ha detail on page 600

Output Fields Table 26 on page 599 lists the output fields for the **show services ha detail** command. Output fields are listed in the approximate order in which they appear.

Table 26: show services ha detail Output Fields

Field Name	Field Description
Interface	Name of the interface for which information is reported.
Inter-chassis	
Role	Role of the interface. • **active**—Active interface. • **backup**–Backup interface.
Connection	Status of the peer connection. • Up • Down
Synchronization	Synchronization state of peers. • Off–Peers are not currently engaged in synchronization.. • Cold–Peers are in a pre-synchronization state. • Hot—Peers are ready for synchronization.

Copyright © 2018, Juniper Networks, Inc.

Table 26: show services ha detail Output Fields (continued)

Field Name	Field Description
Peers	
Local	Local peer IP address.
Port	Local peer port number.
Remote	Remote peer IP address.
Port	Remote peer port number.

Sample Output

show services ha detail

```
user@host> show services ha detail
Interface:        ms-7/0/0
Inter-chassis:    Role: active, Connection: Up, Synchronization: Hot
Peers:            Local: 192.0.2.1 Port: 4001, Remote: 192.0.2.2 Port: 4001

Interface:        ms-7/1/0
Inter-chassis:    Role: active, Connection: Down, Synchronization: Off
Peers:           Local: 198.51.100.1 Port: 4001, Remote: 198.51.100.2 Port: 4001

Interface:        ms-8/0/0
Inter-chassis:    Role: active, Connection: Up, Synchronization: Cold
Peers:            Local: 203.0.113.1 Port: 4001, Remote: 203.0.113.2 Port: 4001

Interface:        ms-8/1/0
Inter-chassis:    Role: active, Connection: Up, Synchronization: Hot
Peers:            Local: 10.10.10.1 Port: 4001, Remote: 10.10.10.2 Port: 4001
```


Copyright © 2018, Juniper Networks, Inc.

show services hcm statistics

Syntax show services hcm statistics rule *rule-name*

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display the statistics collected for HTTP header enrichment for a specified tag rule.

NOTE: This command displays output only if the **count** statement is configured for the term in a tag rule at the **[edit services hcm tag-rule *rule-name* term *term-name* then]** hierarchy level.

If you change the configuration of tag rules during an existing subscriber data session and commit the change, the tag rule statistics are reset to 0 and stop incrementing for the existing TCP sessions.

Options **none**—Display detailed statistics about stateful sync processing for all interfaces.

rule *rule-name*—Display statistics for the specified tag rule.

Required Privilege Level view

Related Documentation

- count on page 259
- Configuring HTTP Header Enrichment Overview on page 33
- show services hcm pic-statistics on page 603

List of Sample Output show services hcm statistics rule on page 602

Output Fields Table 27 on page 601 lists the output fields for the **show services hcm statistics** command. Output fields are listed in the approximate order in which they appear.

Table 27: show services hcm statistics Output Fields

Field Name	Field Description
Interface	Name of the interface for which the statistics are displayed.
Term id	Identifier for the term (in the tag rule) for which the statistics are displayed.
Hits	Number of times that the term was matched. This field displays the aggregate number of occurrences in service sets that include the term.

Copyright © 2018, Juniper Networks, Inc.

Sample Output

show services hcm statistics rule

```
user@host> show services hcm statistics rule rule1

Interface: mams-3/1/0
Term id              Hits
1                   58
Interface: mams-4/1/0
Term id              Hits
1                   144
```


Copyright © 2018, Juniper Networks, Inc.

show services hcm pic-statistics

Syntax

```
show services hcm pic-statistics
<interface interface-name>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display the statistics collected (from the services PICs) for HTTP header enrichment.

Options

none—Display the statistics for all the services PICs.

interface *interface-name*—(Optional) Display the statistics for the specified services PIC.

Required Privilege Level view

Related Documentation

- show services hcm statistics on page 601

List of Sample Output show services hcm pic-statistics on page 606

Output Fields Table 28 on page 603 lists the output fields for the **show services hcm pic-statistics** command. Output fields are listed in the approximate order in which they appear.

Table 28: show services hcm pic-statistics Output Fields

Field Name	Field Description
Interface	Name of the services PIC interface for which statistics are displayed.
Session statistics—For each services PIC.	
Number of Session Interest events	Number of Session Interest events.
Number of Session Create events	Number of Session Create events.
Number of Session Close events	Number of Session Close events.
Number of Session Destroy events	Number of Session Destroy events.
Number of Session Data events	Number of Session Data events.
Number of Session Handle failures	Number of Session Handle failures.
Number of Session Extension allocations	Number of Session Extension allocations that were successful.
Number of Session Extension alloc failures	Number of Session Extension allocations that failed.

Copyright © 2018, Juniper Networks, Inc.

Table 28: show services hcm pic-statistics Output Fields (continued)

Field Name	Field Description
Number of Session Extension frees	Number of Session Extension frees (memory releases).
TCP Proxy statistics	
Number of missing stbuf	Number of missing stream buffers.
Number of stbuf initializations	Number of stream buffer initializations that were successful.
Number of stbuf initialization failures	Number of stream buffer initializations that failed.
Number of stbuf store failures	Number of stream buffer store failures.
Number of stbuf frees	Number of stream buffer frees (memory releases) that were successful.
Number of stbuf free failures	Number of stream buffer frees that failed.
Number of stbuf sends	Number of stream buffer sends that were successful.
Number of stbuf send failures	Number of stream buffer sends that failed.
Number of stbuf receives	Number of stream buffer receives that were successful.
Number of stbuf throttles	Number of stream buffer throttles. Throttles are done when the stream buffer queue is full.
Number of invalid stbuf	Number of invalid stream buffers.
THR statistics	
Number of THR creates	Number of successful TCP Header Rewriter (THR) Create Requests.
Number of missing THR handles	Number of missing THR handles.
Number of THR create failures	Number of THR Create Requests that failed.
Number of THR store failures	Number of THR store failures.
Number of THR short circuit failures	Number of THR short circuit (packet bypass) failures.
Number of THR update failures	Number of THR updates that failed.
Number of THR state updates	Number of THR state updates.
Number of THR destroy failures	Number of THR destroys that failed.
Number of THR destroys	Number of THR Cleanup Requests that were successful.

Copyright © 2018, Juniper Networks, Inc.

Table 28: show services hcm pic-statistics Output Fields (continued)

Field Name	Field Description
JCPP statistics	
Number of JCPP handle allocations	Number of Juniper Content and Protocol Parsers (JCPP) handle allocations that were successful.
Number of JCPP handle allocation failures	Number of JCPP handle allocations that failed.
Header Insertion statistics	
Number of HCM Header Insertions	Number of times that tags were successfully inserted into HTTP headers.
Number of HCM Header Insertion failures	Number of times that the insertion of tags into HTTP headers failed.
Number of HCM Header Renamed	Number of times that HTTP headers were successfully renamed.
Number of HCM Header Rename failures	Number of times that HTTP header rename attempts failed.
Number of HCM IPV4 Mask modifications	Number of times IPv4 address mask was inserted.
Number of HCM IPV6 Mask modifications	Number of times IPv6 address mask was inserted.
Number of HCM Tags too large	Number of tags that were not inserted into HTTP headers because the tag size was larger than the maximum allowed size.
Number of HCM Tag encryption failures	Number of times that the encryption of HTTP tags used for header insertion failed.
Number of HCM requests	Number of HTTP header enrichment requests.
Number of missing Subscribers in HCM	Number of times that tags were not inserted because subscriber was missing.
Number of HCM missing subscriber attributes	Number of times that tags were not inserted because subscriber attributes were missing.
Number of HCM missing IPV4 attributes	Number of times that tags were not inserted because subscriber IPv4 user address attributes were missing.
Number of HCM missing IPV6 attributes	Number of times that tags were not inserted because subscriber IPv6 user address attributes were missing.
Number of HCM IPV4 / IPV6 tag insertions	Number of times that an IPv4 or an IPv6 user address tag was successfully inserted into HTTP headers when the tag rule included both IPv4 and IPv6 user address tags.

Copyright © 2018, Juniper Networks, Inc.

Sample Output

show services hcm pic-statistics

```
user@host> show services hcm pic-statistics
Interface: mams-3/0/0
Session statistics
    Number of Session Interest events              :224590
    Number of Session Create events                :224590
    Number of Session Close events                 :224590
    Number of Session Destroy events               :224590
    Number of Session Data events                  :224589
    Number of Session Handle failures              :0
    Number of Session Extension allocations        :224590
    Number of Session Extension alloc failures     :0
    Number of Session Extension frees              :224590
TCP Proxy statistics
    Number of missing stbuf                        :0
    Number of stbuf initializations                :0
    Number of stbuf initialization failures        :0
    Number of stbuf store failures                 :0
    Number of stbuf frees                          :0
    Number of stbuf free failures                  :0
    Number of stbuf sends                          :0
    Number of stbuf send failures                  :0
    Number of stbuf receives                       :0
    Number of stbuf throttles                      :0
    Number of invalid stbuf                        :0
THR statistics
    Number of THR creates                          :224590
    Number of missing THR handles                  :0
    Number of THR create failures                  :0
    Number of THR store failures                   :0
    Number of THR short circuit failures           :0
    Number of THR update failures                  :0
    Number of THR state updates                    :449180
    Number of THR destroy failures                 :0
    Number of THR destroys                         :0
JCPP statistics
    Number of JCPP handle allocations              :0
    Number of JCPP handle allocation failures      :0
Header Insertion statistics
    Number of HCM Header Insertions                :224589
    Number of HCM Header Insertion failures        :0
    Number of HCM Header Renamed                   :0
    Number of HCM Header Rename failures           :0
    Number of HCM IPV4 Mask modifications          :0
    Number of HCM IPV6 Mask modifications          :0
    Number of HCM Tags too large                   :0
    Number of HCM Tag encryption failures          :0
    Number of HCM requests                         :224589
    Number of missing Subscribers in HCM           :0
    Number of HCM missing subscriber attributes    :0
    Number of HCM missing IPV4 attributes          :0
    Number of HCM missing IPV6 attributes          :0
    Number of HCM IPV4 / IPV6 tag insertions       :0
```


Copyright © 2018, Juniper Networks, Inc.

show services lrf collector statistics

Syntax

```
show services lrf collector statistics
<collector-name>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display LRF statistics for one or more collectors. If a collector is not specified, statistics are displayed for all collectors.

Options **none**—Display LRF statistics for all collectors.

collector-name—(Optional) Display LRF statistics for the specified collector.

Required Privilege Level view

Related Documentation

- Logging and Reporting Function for Subscribers on page 141

List of Sample Output show services lrf collector statistics on page 608

Output Fields Table 29 on page 607 lists the output fields for the **show services lrf collector statistics** command. Output fields are listed in the approximate order in which they appear.

Table 29: show services lrf collector statistics Output Fields

Field Name	Field Description
Interface	Name of the interface from which data records are sent to the collector.
Templates registered	Number of templates registered with the collector.
Template registration failures	Number of template registration failures.
Templates active	Number of active templates.
Sessions received	Number of data sessions received for logging of data.
Sessions ignored	Number of data sessions received for logging of data that were ignored.
Records logged	Number of logs sent to the collector.
Records exported	Number of data records exported to the collector.
Record export failures	Number of data record export attempts that failed.

Copyright © 2018, Juniper Networks, Inc.

Sample Output

show services lrf collector statistics

```
user@host> show services lrf collector statistics

LRF Collector Statistics
    Interface: ms-2/1/0
   Templates registered: 0, Template registration failures: 0, Templates active:
 1
    Sessions received: 0, Sessions ignored: 0, Records logged: 0
    Records exported: 0, Record export failures: 0
```


Copyright © 2018, Juniper Networks, Inc.

show services lrf rule statistics

Syntax

```
show services lrf rule statistics
<rule-name>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display LRF statistics for one or more LRF rules. If an LRF rule is not specified, statistics are displayed for all LRF rules.

Options **none**—Display LRF statistics for all LRF rules.

rule-name—(Optional) Display LRF statistics for the specified LRF rule.

Required Privilege Level view

Related Documentation

- Logging and Reporting Function for Subscribers on page 141

List of Sample Output show services lrf rule statistics on page 610

Output Fields Table 30 on page 609 lists the output fields for the **show services lrf rule statistics** command. Output fields are listed in the approximate order in which they appear.

Table 30: show services lrf rule statistics Output Fields

Field Name	Field Description
Interface	Name of the interface from which data records are sent to the collector.
Rule	Name of the LRF rule that caused data records to be exported to the collector.
Template	Name of the template that was used to export data records to the collector.
Templates registered	Number of templates registered with the collector.
Template registration failures	Number of template registration failures.
Collector	Name of the collector to which data records were sent.
Sessions received	Number of data sessions received for logging of data.
Sessions ignored	Number of data sessions received for logging of data that were ignored.
Sessions logged	Number of data sessions that had data records exported to the collector.
Records exported	Number of data records exported to the collector.

Copyright © 2018, Juniper Networks, Inc.

Table 30: show services lrf rule statistics Output Fields (continued)

Field Name	Field Description
Record export failures	Number of data record export attempts that failed.

Sample Output

show services lrf rule statistics

```
user@host> show services lrf rule statistics

LRF Rule Statistics
  Interface: ms-3/1/0
  Rule: r1
  Template: temp1
  Templates registered: 2, Template registration failures: 0
  Collector: coll1
  Sessions received: 115, Sessions ignored: 0, Sessions logged: 134
  Records exported: 134, Record export failures: 0
```


Copyright © 2018, Juniper Networks, Inc.

show services lrf statistics

Syntax show services lrf statistics

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display number of bytes, packets, and flows for carrying data records to the collector.

Required Privilege Level view

Related Documentation
- Logging and Reporting Function for Subscribers on page 141

List of Sample Output show services lrf statistics on page 611

Output Fields Table 31 on page 611 lists the output fields for the **show services lrf statistics** command. Output fields are listed in the approximate order in which they appear.

Table 31: show services lrf statistics Output Fields

Field Name	Field Description
Interface	Name of the interface from which data records are sent to the collector.
Flow packets	Number of packets carrying data records to the collector.
Flow bytes	Number of bytes carrying data records to the collector.
Active flows	Number of active flows carrying data records to the collector.
Total flows	Total number of flows for carrying data records to the collector.

Sample Output

show services lrf statistics

```
user@host> show services lrf statistics
LRF Statistics
    Interface: ms-3/1/0
    Flow packets: 31125, Flow bytes: 15335751
    Active flows: 0, Total flows: 1887

    Interface: ms-3/2/0
    Flow packets: 0, Flow bytes: 0
    Active flows: 0, Total flows: 0
```

Copyright © 2018, Juniper Networks, Inc.

show services lrf template

Syntax show services lrf template *option*

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display the fields for a template type. You must specify a template type.

Options ***option***—Specify one of the following template types:

- device-data—Display the fields for the Device Data template type.
- flow-id—Display the fields for the Flow ID template type.
- http—Display the fields for the HTTP template type.
- ifl-subscriber—Display the fields for the IFL Subscriber template type.
- ipflow—Display the fields for the IPFlow template type.
- ipflow-extended—Display the fields for the IPFlow Extended template type.
- ipflow-tcp—Displays the fields for the IPFlow TCP template type.
- ipflow-tcp-ts—Displays the fields for the IPFlow TCP Timestamp template type.
- ipflow-ts—Display the fields for the IPFlow Timestamp template type.
- ipv4—Display the fields for the IPv4 template type.
- ipv4-extended—Display the fields for the IPv4 Extended template type.
- ipv6—Display the fields for the IPv6 template type.
- ipv6-extended—Display the fields for the IPv6 Extended template type.
- l7-app—Display the fields for the L7 Application template type.
- mobile-subscriber—Display the fields for the Mobile Subscriber template type.
- pcc—Display the fields for the PCC template type.
- subscriber-data—Display the fields for the Subscriber Data template type.
- wireline-subscriber—Display the fields for the Wireline Subscriber template type.

Required Privilege Level view

Related Documentation
- Logging and Reporting Function for Subscribers on page 141

List of Sample Output
show services lrf template ipv4 on page 613
show services lrf template ipflow-extended on page 613

Copyright © 2018, Juniper Networks, Inc.

show services lrf template ipflow-tcp-ts on page 613
show services lrf template ipflow-tcp on page 613

Sample Output

show services lrf template ipv4

```
user@host> show services lrf template ipv4
LRF Template fields
    Ipv4 source address
    Ipv4 destination address
    TCP/UDP source port
    TCP/UDP destination port
```

show services lrf template ipflow-extended

```
user@host> show services lrf template ipflow-extended
Field                  Element Id       Length(bytes)      Vendor
Service set name       520              16                 Juniper
Routing-instance       521              16                 Juniper
```

show services lrf template ipflow-tcp-ts

```
user@host> show services lrf template ipflow-tcp-ts
Field                           Element Id    Length(bytes)  Vendor
Smooth RTT uplink               10000         4              Juniper
Smooth RTT downlink             10001         4              Juniper
Client setup Time               10002         4              Juniper
Server Setup time               10003         4              Juniper
Client first payload timestamp  10004         8              Juniper
Upload time                     10005         4              Juniper
Server first payload timestamp  10006         8              Juniper
Download time                   10007         4              Juniper
Acknowledged volumes uplink     10008         8              Juniper
Acknowledged volumes downlink   10009         8              Juniper
```

show services lrf template ipflow-tcp

```
user@host> show services lrf template ipflow-tcp
Field                            Element Id  Length(bytes)  Vendor
Retransmitted TCP packets uplink   115       4              Juniper
Retransmitted TCP packets downlink 116       4              Juniper
TCP flow creation timestamp        121       8              Juniper
```

Copyright © 2018, Juniper Networks, Inc.

show services traffic-detection-function hcm statistics

Syntax

```
show services traffic-detection-function hcm statistics
<ipv4-address v4-addr>
<ipv6-address v6-addr>
<routing-instance routing-instance>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display the statistics related to HTTP header enrichment for all the active HTTP sessions for the TDF subscriber.

Options

none—Display HTTP header enrichment statistics for all active HTTP sessions.

ipv4-address *v4-addr*—(Optional) Display HCM statistics for the specified IPv4 address of the subscriber's user equipment (UE).

ipv6-address *v6-addr*—(Optional) Display HCM statistics for the specified IPv6 address of the subscriber's user equipment.

routing-instance *routing-instance*—(Optional) Display HCM statistics for the specified routing instance of the subscriber's user equipment.

Required Privilege Level view

Related Documentation

- show services traffic-detection-function sessions on page 617

List of Sample Output

show services traffic-detection-function hcm statistics routing-instance on page 616
show services traffic-detection-function hcm statistics ipv4-address routing-instance on page 616

Output Fields Table 32 on page 614 lists the output fields for the **show services traffic-detection-function hcm statistics** command. Output fields are listed in the approximate order in which they appear.

Table 32: show services traffic-detection-function hcm statistics Output Fields

Field Name	Field Description
Interface Name	Name of the services PIC on which data sessions are being serviced. The HTTP header enrichment statistics sessions are displayed per services PIC.
Session id	Identifier for the session.

Copyright © 2018, Juniper Networks, Inc.

Table 32: show services traffic-detection-function hcm statistics Output Fields (continued)

Field Name	Field Description
Subscriber-type	Type of subscriber: • **ip**—IP-based subscriber. • **ifl**—Interface-based subscriber.
IMSI	International Mobile Subscriber Identity (IMSI) of the subscriber's user detail equipment (UE).
MSISDN	Mobile station ISDN of the subscriber's user equipment.
Header inserted	Number of times that tags were successfully inserted into HTTP headers for the data session.
Header insert failed	Number of times that the insertion of tags into HTTP headers failed for the data session.
Header renamed	Number of times an HTTP header was renamed.
Header rename fail	Number of times an attempt to rename an HTTP header failed.
IPV4 mask modification	Number of times IPv4 address mask was inserted.
IPV6 mask modification	Number of times IPv6 address mask was inserted.
Tag too large	Number of tags that cannot be inserted into HTTP headers because the tag size was larger than the maximum configured size for the data session.
Tag encryption failed	Number of times that the encryption of HTTP tags used for header insertion failed for the data session.
Total Get request	Total number of HTTP Get Requests received for the data session.
Subscriber info unavailable	Number of times that subscriber attributes were missing during attempted header insertions for the data session.
Subscriber attribute missing	Number of times that tags were not inserted because subscriber attributes were missing.
IPV4 attribute missing	Number of times that tags were not inserted because subscriber IPv4 user address attributes were missing.
IPV6 attribute missing	Number of times that tags were not inserted because subscriber IPv6 user address attributes were missing.
IPV4 / IPV6 attribute	Number of times that IPv4 and IPv6 user address tags were successfully inserted into HTTP headers.

Copyright © 2018, Juniper Networks, Inc.

Sample Output

show services traffic-detection-function hcm statistics routing-instance

```
user@host> show services traffic-detection-function hcm statistics routing-instance r1
```

```
Interface Name: mams-2/3/0 (ams1)
Session id: 134217730, Subscriber-type: ip
    Header inserted              : 6
    Header insert failed         : 0
    Header renamed               : 36
    Header rename fail           : 0
    IPV4 mask modification       : 3
    IPV6 mask modification       : 0
    Tag too large                : 0
    Tag encryption failed        : 0
    Total Get request            : 3
    Subscriber info unavailable  : 9
    Subscriber attribute missing : 9
    IPV4 attribute missing       : 0
    IPV6 attribute missing       : 3
    IPV4 / IPV6 attributes       : 0
```

Sample Output

show services traffic-detection-function hcm statistics ipv4-address routing-instance

```
user@host> show services traffic-detection-function hcm statistics ipv4-address 192.0.2.1
routing-instance default
```

```
Interface Name: mams-2/0/0 (ams1)
Session id: 67108865, Subscriber Type: IP, IMSI: 324234324, MSISDN: 0
    Header inserted              : 0
    Header insert failed         : 0
    Header renamed               : 0
    Header rename fail           : 0
    IPV4 mask modification       : 0
    IPV6 mask modification       : 0
    Tag too large                : 0
    Tag encryption failed        : 0
    Total Get request            : 0
    Subscriber info unavailable  : 0
    Subscriber attribute missing : 0
    IPV4 attribute missing       : 0
    IPV6 attribute missing       : 0
    IPV4 / IPV6 attributes       : 0
```


Copyright © 2018, Juniper Networks, Inc.

show services traffic-detection-function sessions

Syntax

```
show services traffic-detection-function sessions
<ipv4-address v4-addr>
<ipv6-address v6-addr>
<routing-instance routing-instance>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display the active data sessions (TCP or UDP flows) that are being serviced (passing through a services PIC) for a specified TDF subscriber.

Options

none—No output is displayed.

ipv4-address *v4-addr*—(Optional) Display subscriber sessions for the specified IPv4 address of the subscriber's user equipment (UE).

ipv6-address *v6-addr*—(Optional) Display subscriber sessions for the specified IPv6 address of the subscriber's user equipment.

routing-instance *routing-instance*—(Optional) Display subscriber sessions for the specified routing instance.

Required Privilege Level view

Related Documentation

- show unified-edge tdf subscribers on page 703

List of Sample Output

show services traffic-detection-function sessions routing-instance on page 618
show services traffic-detection-function sessions ipv4-address routing-instance on page 618

Output Fields Table 33 on page 617 lists the output fields for the **show services traffic-detection-function sessions** command. Output fields are listed in the approximate order in which they appear.

Table 33: show services traffic-detection-function sessions Output Fields

Field Name	Field Description
Interface Name	Name of the service PIC on which data sessions are being serviced. The data sessions are displayed per services PIC.
Service Set	Name of the service set on which the data session is being serviced.
Session	Identifier for the data session.

Copyright © 2018, Juniper Networks, Inc.

Table 33: show services traffic-detection-function sessions Output Fields (continued)

Field Name	Field Description
ALG	Identifier for the application-level gateway (ALG).
Subscriber-type	Type of subscriber: • **ip**—IP-based subscriber. • **ifl**—Interface-based subscriber.
IMSI	International Mobile Subscriber Identity (IMSI) of the subscriber's user detail equipment (UE).
MSISDN	Mobile station ISDN of the subscriber's user equipment.
For each session, the following information, pertaining to the flow, is displayed: • Flow protocol: **TCP**, **UDP**, or **ICMP** • Flow source IP address and source port address • Flow destination IP address and destination port address • Flow state: **Forward** or **Drop** • Flow direction: input (**I**) or output (**O**) • Number of packets transmitted	

Sample Output

show services traffic-detection-function sessions routing-instance

```
user@host> show services traffic-detection-function sessions routing-instance r1
Interface Name: mams-5/1/0 (ams1)
Service Set: set-hcm, Session: 67258263, ALG: none, Subscriber-type: ip
TCP         192.0.2.8:17751 ->     198.51.100.5:80    Forward  I              31
TCP         198.51.100.5:80    ->     192.0.2.8:17751 Forward  O              53
Service Set: set-hcm, Session: 67269654, ALG: none, Subscriber-type: ifl
TCP         192.0.2.8:18572 ->     198.51.100.5:80    Forward  I              31
TCP         198.51.100.5:80    ->     192.0.2.8:18572 Forward  O              54
Service Set: set-hcm, Session: 83939629, ALG: none, Subscriber-type: ifl
TCP         192.0.2.8:20826 ->     198.51.100.5:80    Forward  I              31
TCP         198.51.100.5:80    ->     192.0.2.8:20826 Forward  O              53
```

Sample Output

show services traffic-detection-function sessions ipv4-address routing-instance

```
user@host> show services traffic-detection-function sessions ipv4-address 203.0.113.1
routing-instance default
Interface Name: mams-2/0/0 (ams1)
Service Set: tdf-service-set, Session: 33554433, ALG: none, Subscriber Type: IP,
 IMSI: 324234324, MSISDN: 0
ICMP           203.0.113.1     ->    10.11.0.1     Forward  I              81
ICMP          10.11.0.1     ->    203.0.113.1     Forward  O               0
```


Copyright © 2018, Juniper Networks, Inc.

Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf aaa radius client statistics

Syntax

```
show unified-edge tdf aaa radius client statistics
<brief | detail>
<fpc-slot fpc-slot>
<gateway gateway>
<client name>
<pic-slot pic-slot>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display the statistics for the accounting packets transmitted and received from the RADIUS client for one or more TDF gateways. If a TDF gateway is not specified, then information for all TDF gateways is displayed.

Options

none—Display statistics for all TDF gateways.

brief | detail—(Optional) Display the specified level of output.

client *name*—(Optional) Display statistics for the specified RADIUS client.

fpc-slot *fpc-slot*—(Optional) Display statistics for the specified Flexible PIC Concentrator (FPC).

gateway *gateway*—(Optional) Display statistics for the specified TDF gateway.

pic-slot *pic-slot*—(Optional) Display statistics for the specified PIC slot number. You must first specify an FPC slot number before specifying the PIC slot number.

Required Privilege Level view

Related Documentation

- clear unified-edge tdf aaa radius client statistics on page 531
- show unified-edge tdf aaa statistics on page 642

List of Sample Output

show unified-edge tdf aaa radius client statistics brief on page 621
show unified-edge tdf aaa radius client statistics detail on page 622

Output Fields Table 34 on page 620 lists the output fields for the **show unified-edge tdf aaa radius client statistics** command. Output fields are listed in the approximate order in which they appear.

Table 34: show unified-edge tdf aaa radius client statistics Output Fields

Field Name	Field Description	Level of Output
Client	Name of the RADIUS client.	All levels

Copyright © 2018, Juniper Networks, Inc.

Table 34: show unified-edge tdf aaa radius client statistics Output Fields (continued)

Field Name	Field Description	Level of Output
Gateway Name	Name of the TDF gateway.	All levels
FPC/PIC	FPC and PIC slot numbers for which the statistics are displayed.	**detail**
Accounting Requests	Number of accounting requests sent to the RADIUS server from the FPC slot and PIC slot. The following information is displayed about each request type: • **Start**—Number of Accounting Start requests sent. • **Stop**—Number of Accounting Stop requests sent. • **Interim**—Number of Accounting Interim-Update requests sent. • **On**—Number of Accounting On requests sent. • **Off**—Number of Accounting Off requests sent.	All levels
Accounting Responses	Number of accounting responses sent to the RADIUS server from the FPC slot and PIC slot. The following information is displayed about each request type: • **Start**—Number of Accounting Start responses sent. • **Stop**—Number of Accounting Stop responses sent. • **Interim**—Number of Accounting Interim-Update responses sent. • **On**—Number of Accounting On responses sent. • **Off**—Number of Accounting Off responses sent.	All levels
Duplicate Requests	Number of duplicate accounting requests sent to the RADIUS server.	All levels
Malformed Requests	Number of malformed accounting requests sent to the RADIUS server.	All levels
Bad Authenticators	Number of responses received from the RADIUS server with bad authenticators.	All levels
Unknown Types	Number of unknown type responses (that the TDF gateway does not recognize) received from the RADIUS server.	All levels
Dropped Packets	Number of packets dropped.	All levels

Sample Output

show unified-edge tdf aaa radius client statistics brief

```
user@host> show unified-edge tdf aaa radius client statistics brief
Client: pgwclient
Gateway Name: TDF
    Accounting Requests: 8
        Start: 8
        Stop: 0
        Interim: 0
        On: 0
        Off: 0
    Accounting Responses: 8
```

Copyright © 2018, Juniper Networks, Inc.

```
        Start: 8
        Stop: 0
        Interim: 0
        On: 0
        Off: 0
    Duplicate Requests: 0
    Malformed Requests: 0
    Bad Authenticators: 0
    Unknown Types: 0
    Dropped Packets: 0

Client: pgwclient_jrad
Gateway Name: TDF
    Accounting Requests: 0
        Start: 0
        Stop: 0
        Interim: 0
        On: 0
        Off: 0
    Accounting Responses: 0
        Start: 0
        Stop: 0
        Interim: 0
        On: 0
        Off: 0
    Duplicate Requests: 0
    Malformed Requests: 0
    Bad Authenticators: 0
    Unknown Types: 0
    Dropped Packets: 0

Client: pgwclient_jrad1
Gateway Name: TDF
    Accounting Requests: 0
        Start: 0
        Stop: 0
        Interim: 0
        On: 0
        Off: 0
    Accounting Responses: 0
        Start: 0
        Stop: 0
        Interim: 0
        On: 0
        Off: 0
    Duplicate Requests: 0
    Malformed Requests: 0
    Bad Authenticators: 0
    Unknown Types: 0
    Dropped Packets: 0
```

show unified-edge tdf aaa radius client statistics detail

```
user@host> show unified-edge tdf aaa radius client statistics detail
```

```
Client: pgwclient
Gateway Name: TDF
FPC/PIC: 2/0
    Accounting Requests: 8
        Start: 8
```


Copyright © 2018, Juniper Networks, Inc.

```
        Stop: 0
        Interim: 0
        On: 0
        Off: 0
    Accounting Responses: 8
        Start: 8
        Stop: 0
        Interim: 0
        On: 0
        Off: 0
    Duplicate Requests: 0
    Malformed Requests: 0
    Bad Authenticators: 0
    Unknown Types: 0
    Dropped Packets: 0

Client: pgwclient
Gateway Name: TDF
FPC/PIC: 2/1
    Accounting Requests: 0
        Start: 0
        Stop: 0
        Interim: 0
        On: 0
        Off: 0
    Accounting Responses: 0
        Start: 0
        Stop: 0
        Interim: 0
        On: 0
        Off: 0
    Duplicate Requests: 0
    Malformed Requests: 0
    Bad Authenticators: 0
    Unknown Types: 0
    Dropped Packets: 0

Client: pgwclient_jrad
Gateway Name: TDF
FPC/PIC: 2/0
    Accounting Requests: 0
        Start: 0
        Stop: 0
        Interim: 0
        On: 0
        Off: 0
    Accounting Responses: 0
        Start: 0
        Stop: 0
        Interim: 0
        On: 0
        Off: 0
    Duplicate Requests: 0
    Malformed Requests: 0
    Bad Authenticators: 0
    Unknown Types: 0
    Dropped Packets: 0

Client: pgwclient_jrad
Gateway Name: TDF
```

Copyright © 2018, Juniper Networks, Inc.

```
FPC/PIC: 2/1
    Accounting Requests: 0
        Start: 0
        Stop: 0
        Interim: 0
        On: 0
        Off: 0
    Accounting Responses: 0
        Start: 0
        Stop: 0
        Interim: 0
        On: 0
        Off: 0
    Duplicate Requests: 0
    Malformed Requests: 0
    Bad Authenticators: 0
    Unknown Types: 0
    Dropped Packets: 0

Client: pgwclient_jrad1
Gateway Name: TDF
FPC/PIC: 2/0
    Accounting Requests: 0
        Start: 0
        Stop: 0
        Interim: 0
        On: 0
        Off: 0
    Accounting Responses: 0
        Start: 0
        Stop: 0
        Interim: 0
        On: 0
        Off: 0
    Duplicate Requests: 0
    Malformed Requests: 0
    Bad Authenticators: 0
    Unknown Types: 0
    Dropped Packets: 0

Client: pgwclient_jrad1
Gateway Name: TDF
FPC/PIC: 2/1
    Accounting Requests: 0
        Start: 0
        Stop: 0
        Interim: 0
        On: 0
        Off: 0
    Accounting Responses: 0
        Start: 0
        Stop: 0
        Interim: 0
        On: 0
        Off: 0
    Duplicate Requests: 0
    Malformed Requests: 0
    Bad Authenticators: 0
    Unknown Types: 0
    Dropped Packets: 0
```


Copyright © 2018, Juniper Networks, Inc.

Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf aaa radius client status

Syntax

```
show unified-edge tdf aaa radius client status
<fpc-slot fpc-slot>
<gateway gateway>
<client name>
<pic-slot pic-slot>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display the status of the RADIUS client for one or more TDF gateways. If a TDF gateway is not specified, then information for all TDF gateways is displayed.

Options

none—Display RADIUS client status for all TDF gateways.

client *name*—(Optional) Display the status for the specified RADIUS client.

fpc-slot *fpc-slot*—(Optional) Display the status for the specified Flexible PIC Concentrator (FPC).

gateway *gateway*—(Optional) Display the status for the specified TDF gateway.

pic-slot *pic-slot*—(Optional) Display the status for the specified PIC slot number. You must first specify an FPC slot number before specifying the PIC slot number.

Required Privilege Level view

Related Documentation

- clear unified-edge tdf aaa radius client statistics on page 531
- show unified-edge tdf aaa statistics on page 642

List of Sample Output show unified-edge tdf aaa radius client status on page 627

Output Fields Table 35 on page 626 lists the output fields for the **show unified-edge tdf aaa radius client status** command. Output fields are listed in the approximate order in which they appear.

Table 35: show unified-edge tdf aaa radius client status Output Fields

Field Name	Field Description
Client	Name of the RADIUS client.
FPC/PIC	FPC and PIC slot numbers for which the statistics are displayed.
Address	IP address of the RADIUS client.

Copyright © 2018, Juniper Networks, Inc.

Table 35: show unified-edge tdf aaa radius client status Output Fields (continued)

Field Name	Field Description
Last activity	Day of the week, month, date, time, and year when the last operation occurred on the RADIUS client. The term **No activity** is displayed if no communication occurred between the RADIUS client and the TDF gateway.

Sample Output

show unified-edge tdf aaa radius client status

```
user@host> show unified-edge tdf aaa radius statistics accounting brief
Client       FPC/PIC  Address              Last activity
-------------------------------------------------------------------
pgwclient    2/0      192.0.2.3           Mon Jul 21 11:00:16 2014
pgwclient_j  2/0      198.51.100.2            No activity
pgwclient_j  2/0      203.0.113.1           No activity
```

Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf aaa radius network-element statistics

Syntax

```
show unified-edge tdf aaa radius network-element statistics
<brief | detail>
<fpc-slot fpc-slot>
<gateway gateway>
<name name>
<pic-slot pic-slot>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display RADIUS network element statistics. If a TDF gateway is not specified, then statistics for all TDF gateways are displayed.

Options

none—Display statistics for all TDF gateways.

brief | detail—(Optional) Display the specified level of output.

The **brief** option is the default and displays the consolidated statistics for all TDF gateways, and the **detail** option displays the statistics for each Services PIC on the configured TDF gateways.

fpc-slot *fpc-slot*—(Optional) Display statistics for the specified Flexible PIC Concentrator (FPC).

gateway *gateway*—(Optional) Display statistics for the specified TDF gateway.

name *name*—(Optional) Display statistics for the specified network element.

pic-slot *pic-slot*—(Optional) Display statistics for the specified PIC slot number. You must first specify an FPC slot number before specifying the PIC slot number.

Required Privilege Level view

Related Documentation

- clear unified-edge tdf aaa radius network-element statistics on page 532
- Understanding Network Elements on page 57

List of Sample Output show unified-edge tdf aaa radius network-element statistics detail on page 629

Output Fields Table 36 on page 629 lists the output fields for the **show unified-edge tdf aaa radius network-element statistics** command. Output fields are listed in the approximate order in which they appear.

Copyright © 2018, Juniper Networks, Inc.

Table 36: show unified-edge tdf aaa radius network-element statistics Output Fields

Field Name	Field Description	Level of Output
Network-element	Name of the network element to which the statistics belong.	All levels
FPC/PIC	FPC and PIC slot numbers for which statistics are displayed.	**detail**
Requests Attempted	Number of access and accounting requests that were attempted.	All levels
Access Requests Sent	Number of access requests sent.	All levels
Accounting Requests Sent	Number of accounting requests sent.	All levels
Responses Received	Number of access and accounting response messages received.	All levels
Request Timeouts	Number of access and accounting requests to the RADIUS server that timed out.	All levels
Memory Failures	Number of internal memory allocation failures.	All levels
Invalid State Errors	Number of access requests and accounting requests that were attempted in non-operational state.	All levels
No Radius Server Found	Number of access requests and accounting requests that failed because no more RADIUS servers were available.	All levels
Source Port allocation Errors	Number of access and accounting requests that failed because of source port allocation failure for outgoing RADIUS messages.	All levels
Send Failures	Total number of failed attempts to send access requests and accounting requests.	All levels

Sample Output

show unified-edge tdf aaa radius network-element statistics detail

```
user@host> show unified-edge tdf aaa radius network-element statistics detail
Network-element: ne1
FPC/PIC:         5/2
  Requests Attempted:            0
  Access Requests Sent:          0
```

Copyright © 2018, Juniper Networks, Inc.

```
  Accounting Requests Sent:      0
  Responses Received:            0
  Request Timeouts:              0
  Memory Failures:               0
  Invalid State Errors:          0
  No Radius Server Found:        0
  Source Port allocation Errors: 0
  Send Failures:                 0

Network-element: ne2
FPC/PIC:         5/2
  Requests Attempted:            0
  Access Requests Sent:          0
  Accounting Requests Sent:      0
  Responses Received:            0
  Request Timeouts:              0
  Memory Failures:               0
  Invalid State Errors:          0
  No Radius Server Found:        0
  Source Port allocation Errors: 0
  Send Failures:                 0
```


Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf aaa radius server statistics

Syntax

```
show unified-edge tdf aaa radius server statistics
<brief | detail>
<fpc-slot fpc-slot>
<gateway gateway>
<name name>
<pic-slot pic-slot>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display RADIUS server statistics. If a TDF gateway is not specified, then statistics for all TDF gateways are displayed.

Options

none—Display the same output as the **brief** option.

brief | detail—(Optional) Display the specified level of output.

The **brief** option is the default and displays the consolidated statistics for all TDF gateways, and the **detail** option displays the statistics for each Services PIC on the configured TDF gateways.

fpc-slot *fpc-slot*—(Optional) Display statistics for the specified Flexible PIC Concentrator (FPC).

gateway *gateway*—(Optional) Display statistics for the specified TDF gateway.

name *name*—(Optional) Display statistics for the specified RADIUS server.

pic-slot *pic-slot*—(Optional) Display statistics for the specified PIC slot number. You must first specify an FPC slot number before specifying the PIC slot number.

Required Privilege Level view

Related Documentation

- clear unified-edge tdf aaa radius server statistics on page 533
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

List of Sample Output show unified-edge tdf aaa radius server statistics detail on page 633

Output Fields Table 37 on page 632 lists the output fields for the **show unified-edge tdf aaa radius server statistics** command. Output fields are listed in the approximate order in which they appear.

Copyright © 2018, Juniper Networks, Inc.

Table 37: show unified-edge tdf aaa radius server statistics Output Fields

Field Name	Field Description	Level of Output
RADIUS server	Name of the RADIUS server.	All levels
Address	IP address of the RADIUS server.	All levels
Routing-instance	Routing-instance of RADIUS server's source address.	**detail**
Authentication Statistics		
Port	RADIUS server port number to which access requests are sent.	All levels
FPC/PIC	FPC and PIC slot numbers for which the statistics are displayed.	**detail**
Access requests	Number of access requests sent to the RADIUS server.	All levels
Access req retransmissions	Number of access requests retransmitted to the RADIUS server.	All levels
Access accepts	Number of access accepts sent by the RADIUS server.	All levels
Access rejects	Number of access requests rejected by the RADIUS server.	All levels
Malformed responses	Number of malformed access responses received from the RADIUS server.	All levels
Bad authenticators	Number of bad authentication responses received for access-requests.	All levels
Timeouts	Number of access requests to the RADIUS server that timed out.	All levels
Unknown types	Number of unknown type responses received from the RADIUS server for access requests.	All levels
Packets dropped	Number of packets dropped for access requests and responses.	All levels
Accounting Statistics		
Port	RADIUS server port number to which accounting requests are sent.	All levels
Accounting requests	Number of accounting requests sent to the RADIUS server. The following information is displayed about each request type for the **detail** level: • **Start**—Number of accounting start requests sent. • **Stop**—Number of accounting stop requests sent. • **Interim**—Number of accounting interim-update requests sent. • **On**—Number of accounting on requests sent. • **Off**—Number of accounting off requests sent.	All levels
Accounting req retransmissions	Number of accounting requests retransmitted to the RADIUS server.	All levels

Copyright © 2018, Juniper Networks, Inc.

Table 37: show unified-edge tdf aaa radius server statistics Output Fields (continued)

Field Name	Field Description	Level of Output
Accounting responses	Number of accounting responses received from the RADIUS server.	All levels
Malformed responses	Number of malformed accounting responses received from the RADIUS server.	All levels
Bad authenticators	Number of bad accounting responses received for accounting requests.	All levels
Timeouts	Number of accounting requests to the RADIUS server that timed out.	All levels
Unknown types	Number of unknown type responses (that the TDF gateway does not recognize) received from the RADIUS server for accounting requests.	All levels
Packets dropped	Number of packets dropped for accounting requests and responses.	All levels
Dynamic Authorization Request Statistics		
CoA requests received	Number of change of authorization (CoA) requests received from the RADIUS server.	All levels
DM requests received	Number of Disconnect Message (DM) requests received from the RADIUS server.	All levels
CoA Acks sent	Number of CoA acknowledgements sent to the RADIUS server.	All levels
CoA Nacks sent	Number of CoA negative acknowledgements sent to the RADIUS server.	All levels
DM Acks sent	Number of DM acknowledgements sent to the RADIUS server.	All levels
DM Nacks sent	Number of DM negative acknowledgements sent to the RADIUS server.	All levels
Dropped	Number of dynamic authorization requests dropped.	All levels

Sample Output

show unified-edge tdf aaa radius server statistics detail

```
user@host> show unified-edge tdf aaa radius server statistics detail
RADIUS server: radius1 (FPC/PIC: 5/2)
Address: 192.0.2.2
Routing-instance: default
Authentication Statistics:
    Port: 1812
    Access requests: 0
    Access req retransmissions: 0
    Access accepts: 0
    Access rejects: 0
```

Copyright © 2018, Juniper Networks, Inc.

```
    Malformed responses: 0
    Bad authenticators: 0
    Timeouts: 0
    Unknown types: 0
    Packets dropped: 0
Accounting Statistics:
    Port: 1813
    Accounting requests: 0
      Start: 0      Stop: 0      Interim: 0      On: 0      Off: 0
    Accounting req retransmissions: 0
    Accounting responses: 0
    Malformed responses: 0
    Bad authenticators: 0
    Timeouts: 0
    Unknown types: 0
    Packets dropped: 0
Dynamic Authorization Request Statistics:
    CoA requests received: 0
    DM requests received: 0
    CoA Acks sent: 0
    CoA Nacks sent: 0
    DM Acks sent: 0
    DM Nacks sent: 0
    Dropped: 0
```


Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf aaa radius server status

Syntax

```
show unified-edge tdf aaa radius server status
<brief | detail>
<fpc-slot fpc-slot>
<gateway gateway>
<name name>
<pic-slot pic-slot>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display RADIUS server status. If a TDF gateway is not specified, then statistics for all TDF gateways are displayed.

Options

none—(Same as brief) Display consolidated statistics for all TDF gateways.

brief | detail—(Optional) Display the specified level of output.

The **brief** option is the default.

fpc-slot *fpc-slot*—(Optional) Display statistics for the specified Flexible PIC Concentrator (FPC).

gateway *gateway*—(Optional) Display statistics for the specified TDF gateway.

pic-slot *pic-slot*—(Optional) Display statistics for the specified PIC slot number. You must first specify an FPC slot number before specifying the PIC slot number.

Required Privilege Level view

Related Documentation

- show unified-edge tdf aaa radius server statistics on page 631
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53

List of Sample Output

show unified-edge tdf aaa radius server status brief on page 636
show unified-edge tdf aaa radius server status detail on page 637

Output Fields Table 38 on page 635 lists the output fields for the **show unified-edge tdf aaa radius server status** command. Output fields are listed in the approximate order in which they appear.

Table 38: show unified-edge tdf aaa radius server status Output Fields

Field Name	Field Description	Level of Output
Server	Name of the RADIUS server.	**brief**

Copyright © 2018, Juniper Networks, Inc.

Table 38: show unified-edge tdf aaa radius server status Output Fields (continued)

Field Name	Field Description	Level of Output
RADIUS Server	Name of the RADIUS server.	**detail**
FPC/PIC	FPC and PIC slot numbers for which the statistics are displayed.	All levels
Address	IP address of the RADIUS server.	All levels
State	State of the RADIUS server: **Active** or **Inactive** (dead).	All levels
Duration	Duration, in *weeks:days:MM:SS* format, for which the RADIUS server has been in the current state.	All levels
Previous duration	Duration, in *HH:MM:SS* format, for which the RADIUS server was in the previous state.	All levels
Flaps	Number of times that the RADIUS server transitioned from the active to inactive state.	All levels
Authentication Information		
Pending requests	Number of access requests waiting for responses from the RADIUS server.	**detail**
Round trip time (ms)	Time taken to receive the response from the RADIUS server for access requests. The minimum, maximum, and average round-trip times are also displayed.	**detail**
Accounting Information		
Pending requests	Number of accounting requests waiting for responses from the RADIUS server.	**detail**
Round trip time (ms)	Time taken to receive the response from the RADIUS server for accounting requests. The minimum, maximum, and average round-trip times are also displayed.	**detail**

Sample Output

show unified-edge tdf aaa radius server status brief

```
user@host> show unified-edge tdf aaa radius server status brief
                FPC/                                        Previous
Server          PIC     Address          State   Duration      Duration    Flaps
-------------------------------------------------------------------------------
radius1         5/2     192.0.2.2        Active  1w5d 23:12    00:00:00    0
radius2         5/2     198.51.100.100   Active  1w5d 23:12    00:00:00    0
radius3         5/2     203.0.113.100     Active  1w5d 23:12    00:00:00    0
radius4         5/2     203.0.113.100     Active  1w5d 23:12    00:00:00    0
```


Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf aaa radius server status detail

```
user@host> show unified-edge tdf aaa radius server status detail
RADIUS server: pgwcl (FPC/PIC: 4/0)
Address           : 198.51.100.100
State             : Active
Duration          : 1w6d 11:29
Previous Duration : 00:00:00
Flaps             : 0
Authentication Information:
    Pending requests     : 0
    Round trip time (ms) : 1 (Min: 1 Max: 1 Avg: 1)
Accounting Information:
    Pending requests     : 0
    Round trip time (ms) : 0 (Min: 0 Max: 0 Avg: 0)
```

show unified-edge tdf aaa radius snoop-segment statistics

Syntax

```
show unified-edge tdf aaa radius snoop-segment statistics
<brief | detail>
<fpc-slot fpc-slot>
<gateway gateway>
<pic-slot pic-slot>
<segment snoop-segment-name>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display statistics for snoop segments. If a snoop segment is not specified, then statistics for all snoop segments are displayed.

Options

none—(Same as brief) Display statistics for all snoop segments for all TDF gateways.

brief | detail—(Optional) Display the specified level of output.

The **brief** option displays the consolidated statistics for all TDF gateways, and the **detail** option displays the statistics for each Services PIC on the configured TDF gateways.

fpc-slot *fpc-slot*—(Optional) Display statistics for the specified Flexible PIC Concentrator (FPC).

gateway *gateway*—(Optional) Display statistics for the specified TDF gateway.

pic-slot *pic-slot*—(Optional) Display statistics for the specified PIC slot number. You must first specify an FPC slot number before specifying the PIC slot number.

segment *snoop-segment-name*—(Optional) Display statistics for the specified snoop segment.

Required Privilege Level view

Related Documentation

- clear unified-edge tdf aaa radius snoop-segment statistics on page 534
- Configuring Snooping of RADIUS Accounting Requests for IP-Based Subscribers on page 113
- Snooping RADIUS Accounting Requests for IP-Based Subscribers Overview on page 94

List of Sample Output

show unified-edge tdf aaa radius snoop-segment statistics brief on page 639
show unified-edge tdf aaa radius snoop-segment statistics detail on page 640

Copyright © 2018, Juniper Networks, Inc.

Output Fields Table 39 on page 639 lists the output fields for the **show unified-edge tdf aaa radius snoop-segment statistics** command. Output fields are listed in the approximate order in which they appear.

Table 39: show unified-edge tdf aaa radius snoop-segment statistics Output Fields

Field Name	Field Description	Level of Output
Snoop-segment	Name of the snoop-segment for which statistics are displayed.	All levels
Gateway Name	Name of the TDF gateway. If the statistics for all TDF gateways are displayed, then **All** is displayed.	All levels
FPC/PIC	FPC and PIC slot numbers for which the statistics are displayed.	**detail**
Accounting Requests	The following information is displayed for each category: • **Start**—Number of snooped Accounting Start requests. • **Interim**—Number of snooped Accounting Interim-Update requests. • **Stop**—Number of snooped Accounting Stop requests. • **On**—Number of snooped Accounting On requests. • **Off**—Number of snooped Accounting Off requests.	All levels
Duplicate Requests	Number of duplicate snooped accounting requests.	All levels
Malformed Requests	Number of snooped malformed accounting requests.	All levels
Bad Authenticators	Number of snooped acccounting requests with bad authenticators.	All levels
Unknown Types	Number of snooped accounting requests of unknown type.	All levels
Dropped Packets	Number of snooped packets dropped.	All levels

Sample Output

show unified-edge tdf aaa radius snoop-segment statistics brief

```
user@host> show unified-edge tdf aaa radius snoop-segment statistics brief

Snoop-segment: 123
Gateway Name: TDF
    Accounting Requests: 0
        Start: 0
        Stop: 0
        Interim: 0
        On: 0
        Off: 0
    Duplicate Requests: 0
    Malformed Requests: 0
    Bad Authenticators: 0
    Unknown Types: 0
    Dropped Packets: 0
```

Copyright © 2018, Juniper Networks, Inc.

```
Snoop-segment: dummy
Gateway Name: TDF
    Accounting Requests: 0
        Start: 0
        Stop: 0
        Interim: 0
        On: 0
        Off: 0
    Duplicate Requests: 0
    Malformed Requests: 0
    Bad Authenticators: 0
    Unknown Types: 0
    Dropped Packets: 0
```

show unified-edge tdf aaa radius snoop-segment statistics detail

```
user@host> show unified-edge tdf aaa radius snoop-segment statistics detail
Snoop-segment: 123
Gateway Name: TDF
FPC/PIC: 4/0
    Accounting Requests: 0
        Start: 0
        Stop: 0
        Interim: 0
        On: 0
        Off: 0
    Duplicate Requests: 0
    Malformed Requests: 0
    Bad Authenticators: 0
    Unknown Types: 0
    Dropped Packets: 0

Snoop-segment: 123
Gateway Name: TDF
FPC/PIC: 4/1
    Accounting Requests: 0
        Start: 0
        Stop: 0
        Interim: 0
        On: 0
        Off: 0
    Duplicate Requests: 0
    Malformed Requests: 0
    Bad Authenticators: 0
    Unknown Types: 0
    Dropped Packets: 0

Snoop-segment: dummy
Gateway Name: TDF
FPC/PIC: 4/0
    Accounting Requests: 0
        Start: 0
        Stop: 0
        Interim: 0
        On: 0
        Off: 0
    Duplicate Requests: 0
    Malformed Requests: 0
    Bad Authenticators: 0
```


Copyright © 2018, Juniper Networks, Inc.

```
    Unknown Types: 0
    Dropped Packets: 0

Snoop-segment: dummy
Gateway Name: TDF
FPC/PIC: 4/1
    Accounting Requests: 0
        Start: 0
        Stop: 0
        Interim: 0
        On: 0
        Off: 0
    Duplicate Requests: 0
    Malformed Requests: 0
    Bad Authenticators: 0
    Unknown Types: 0
    Dropped Packets: 0
```

Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf aaa statistics

Syntax

```
show unified-edge tdf aaa statistics
<brief | detail>
<fpc-slot fpc-slot>
<gateway gateway>
<pic-slot pic-slot>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display global statistics for accounting requests and responses for one or more TDF gateways. If a TDF gateway is not specified, then statistics for all TDF gateways are displayed.

Options

none—(Same as brief) Display statistics for all TDF gateways.

brief | detail—(Optional) Display the specified level of output.

The **brief** option displays the consolidated statistics for all TDF gateways, and the **detail** option displays the statistics for each Services PIC on the configured TDF gateways.

fpc-slot *fpc-slot*—(Optional) Display statistics for the specified Flexible PIC Concentrator (FPC).

gateway *gateway*—(Optional) Display statistics for the specified TDF gateway.

pic-slot *pic-slot*—(Optional) Display statistics for the specified PIC slot number. You must first specify an FPC slot number before specifying the PIC slot number.

Required Privilege Level view

Related Documentation

- clear unified-edge tdf aaa statistics on page 535
- show unified-edge tdf aaa radius client statistics on page 620
- show unified-edge tdf aaa radius server statistics on page 631
- Understanding How a RADIUS Server Controls Policy and Charging Control Rules on page 53
- IP-Based Subscriber Setup Overview on page 88
- Snooping RADIUS Accounting Requests for IP-Based Subscribers Overview on page 94

List of Sample Output

show unified-edge tdf aaa statistics brief on page 646
show unified-edge tdf aaa statistics detail on page 647

Copyright © 2018, Juniper Networks, Inc.

Output Fields Table 36 on page 629 lists the output fields for the **show unified-edge tdf aaa statistics** command. Output fields are listed in the approximate order in which they appear.

Table 40: show unified-edge tdf aaa statistics Output Fields

Field Name	Field Description	Level of Output
Gateway Name	Name of the TDF gateway. If the statistics for all TDF gateways are displayed, then **All** is displayed.	All levels
FPC/PIC	FPC and PIC slot numbers for which the statistics are displayed.	**detail**
Total Messages	Total number of all RADIUS requests and responses for the following categories: • **Received** • **Sent** • **Snooped**—Snooped by the MX Series router. • **Forwarded In**—Forwarded into the interface. • **Forwarded Out**—Forwarded out of the interface.	All levels **Forwarded In** and **Forwarded Out** are displayed only with the **detail** option.
Access Requests	Number of access requests for the following category: • **Sent**—Sent to the RADIUS server from the FPC slot and PIC slot.	All levels
Access Responses	Number of access responses for the following category: • **Received**—Received from the RADIUS server for the FPC slot and PIC slot. The following information is displayed: • **Accept**—Number of access accepts sent by the RADIUS server. • **Reject**—Number of access requests rejected by the RADIUS server.	All levels
Accounting Requests	Number of accounting requests for the following categories: • **Received** • **Sent** • **Snooped**—Snooped by the MX Series router. • **Forwarded In**—Forwarded into the interface. • **Forwarded Out**—Forwarded out of the interface. The following information is displayed for each category: • **Start**—Number of Accounting Start requests. • **Interim**—Number of Accounting Interim-Update requests. • **Stop**—Number of Accounting Stop requests. • **On**—Number of Accounting On requests. • **Off**—Number of Accounting Off requests.	All levels **Forwarded In** and **Forwarded Out** are displayed only with the **detail** option.

Copyright © 2018, Juniper Networks, Inc.

Table 40: show unified-edge tdf aaa statistics Output Fields (continued)

Field Name	Field Description	Level of Output
Accounting Responses	Number of accounting responses for the following categories: • **Received** • **Sent** • **Snooped**—Snooped by the MX Series router. • **Forwarded In**—Forwarded into the interface. • **Forwarded Out**—Forwarded out of the interface. The following information is displayed for each category: • **Start**—Number of Accounting Start responses. • **Interim**—Number of Accounting Interim-Update responses. • **Stop**—Number of Accounting Stop responses. • **On**—Number of Accounting On responses. • **Off**—Number of Accounting Off responses.	All levels **detail**—Number of responses that are forwarded into the interface and forwarded out of the interface is displayed only with the **detail** option.
Change of Auth Requests	Number of change of authorization (CoA) requests for the following categories: • **Received**—Received from the RADIUS server. • **Forwarded In**—Forwarded into the interface. • **Forwarded Out**—Forwarded out of the interface.	All levels **Forwarded In** and **Forwarded Out** are displayed only with the **detail** option.
Change of Auth Responses	Number of CoA responses for the following category: • **Sent**—Sent to the RADIUS server from the FPC slot and PIC slot. • **Forwarded In**—Forwarded into the interface. • **Forwarded Out**—Forwarded out of the interface. The following information is displayed: • **Ack**—Number of CoA acknowledgements sent to the RADIUS server. • **Nack**—Number of CoA negative acknowledgements sent to the RADIUS server.	All levels **Forwarded In** and **Forwarded Out** are displayed only with the **detail** option.
Disconnect Message Requests	Number of Disconnect Message requests for the following categories: • **Received**—Received from the RADIUS server. • **Forwarded In**—Forwarded into the interface. • **Forwarded Out**—Forwarded out of the interface.	All levels **Forwarded In** and **Forwarded Out** are displayed only with the **detail** option.

Copyright © 2018, Juniper Networks, Inc.

Table 40: show unified-edge tdf aaa statistics Output Fields (continued)

Field Name	Field Description	Level of Output
Disconnect Message Responses	Number of Disconnect Message responses for the following categories: • **Sent**—Sent to the RADIUS server. • **Forwarded In**—Forwarded into the interface. • **Forwarded Out**—Forwarded out of the interface. The following information is displayed: • **Ack**—Number of Disconnect Message acknowledgements sent to the RADIUS server. • **Nack**—Number of Disconnect Message negative acknowledgements sent to the RADIUS server.	All levels **Forwarded In** and **Forwarded Out** are displayed only with the **detail** option.
Duplicates	Number of duplicate requests received from RADIUS clients.	All levels
Request Processing errors	Number of errors that occurred during the processing of accounting requests.	All levels
Response Processing errors	Number of errors that occurred during the processing of access and accounting response packets from the RADIUS server.	All levels
Request Transmit errors	Number of errors that occurred during the transmission of access and accounting requests.	All levels
Response Transmit errors	Number of errors that occurred during the transmission of access and accounting responses to the RADIUS server.	All levels
Request Enqueue Errors	Number of errors that occurred while trying to place an access or accounting request packet in the queue.	All levels
Response Enqueue Errors	Number of errors that occurred while trying to place an access or accounting response packet in the queue.	All levels
Request Timeouts	Number of access and accounting requests to the RADIUS server that timed out.	All levels
Request Retransmissions	Number of access and accounting requests that were retransmitted to the RADIUS server because they did not receive a response.	All levels
Dropped Requests	Number of accounting requests that were dropped.	All levels
Dropped Responses	Number of access or accounting responses from the RADIUS server that were dropped.	All levels
Missing TDF Domain	Number of accounting requests from the GGSN, PGW, or BNG for which the TDF domain corresponding to the subscriber was not available.	All levels
Missing PCEF profile	Number of accounting requests from the GGSN, PGW, or BNG for which the PCEF profile corresponding to the subscriber was not available.	All levels

Copyright © 2018, Juniper Networks, Inc.

Table 40: show unified-edge tdf aaa statistics Output Fields (continued)

Field Name	Field Description	Level of Output
Server Initiated Request Processing Errors	Number of processing errors of CoA and Disconnect Message requests from the RADIUS server.	All levels
Dropped Server Initiated Requests	Number of CoA and Disconnect Message requests from the RADIUS server that were dropped.	All levels
Duplicate Server Initiated Requests	Number of duplicate requests received from RADIUS servers.	All levels
Cached Reply Sent	Number of RADIUS cached responses sent for RADIUS accounting request messages from the GGSN, PGW, or BNG. RADIUS replies are stored in the MX Series router response cache.	All levels

Sample Output

show unified-edge tdf aaa statistics brief

```
user@host> show unified-edge tdf aaa statistics brief


Gateway Name: TDF
Messages                      Received        Sent        Snooped
-------------------------------------------------------------------------
Total Messages                15              15          0
Access Requests               0               7           0
Access Responses              7               0           0
    Accept                    7               0           0
    Reject                    0               0           0
Accounting Requests           8               0           0
    Start                     8               0           0
    Interim                   0               0           0
    Stop                      0               0           0
    On                        0               0           0
    Off                       0               0           0
Accounting Responses          0               8           0
    Start                     0               8           0
    Interim                   0               0           0
    Stop                      0               0           0
    On                        0               0           0
    Off                       0               0           0
Change of Auth Requests       0               0           0
Change of Auth Responses      0               0           0
    Ack                       0               0           0
    Nak                       0               0           0
Disconnect Message Requests   0               0           0
Disconnect Message Responses  0               0           0
    Ack                       0               0           0
    Nak                       0               0           0

Duplicates:                                    0
Request Processing Errors:                     0
Response Processing Errors:                    0
Request Transmit Errors :                      0
```


Copyright © 2018, Juniper Networks, Inc.

```
Response Transmit Errors:                    0
Request Enqueue Errors:                      0
Response Enqueue Errors:                     0
Request Timeouts:                            0
Request Retransmissions:                     0
Missing TDF Domain:                          0
Missing PCEF profile:                        0
Dropped Requests:                            0
Dropped Responses:                           0
Server Initiated Request Processing Errors:  0
Dropped Server Initiated Requests:           0
Duplicate Server Initiated Requests:         0
Cached Reply Sent:                           0
```

show unified-edge tdf aaa statistics detail

user@host> **show unified-edge tdf aaa statistics detail**

```
Gateway Name: TDF
FPC/PIC: 2/0
Messages                  Received        Sent        Forwarded In     Forwarded Out   Snooped
-------------------------------------------------------------------------------------------

Total Messages               2              2          0                  0           0
Access Requests              0              0          0                  0           0
Access Responses             0              0          0                  0           0
    Accept                   0              0          0                  0           0
    Reject                   0              0          0                  0           0
Accounting Requests          2              0          0                  0           0
    Start                    2              0          0                  0           0
    Interim                  0              0          0                  0           0
    Stop                     0              0          0                  0           0
    On                       0              0          0                  0           0
    Off                      0              0          0                  0           0
Accounting Responses         0              2          0                  0           0
    Start                    0              2          0                  0           0
    Interim                  0              0          0                  0           0
    Stop                     0              0          0                  0           0
    On                       0              0          0                  0           0
    Off                      0              0          0                  0           0
Change of Auth Requests      0              0          0                  0           0
Change of Auth Responses     0              0          0                  0           0
    Ack                      0              0          0                  0           0
    Nak                      0              0          0                  0           0
Disconnect Message Requests  0              0          0                  0           0
Disconnect Message Responses 0              0          0                  0           0
    Ack                      0              0          0                  0           0
    Nak                      0              0          0                  0           0

Duplicates:                                  0
Request Processing Errors:                   0
Response Processing Errors:                  0
Request Transmit Errors :                    0
Response Transmit Errors:                    0
Request Enqueue Errors:                      0
Response Enqueue Errors:                     0
```

```
Request Timeouts:                           0
Request Retransmissions:                    0
Missing TDF Domain:                         0
Missing PCEF profile:                       0
Dropped Requests:                           0
Dropped Responses:                          0
Server Initiated Request Processing Errors:   0
Dropped Server Initiated Requests:          0
Duplicate Server Initiated Requests:        0
Cached Reply Sent:                          0

Gateway Name: TDF
FPC/PIC: 2/1
Messages                    Received        Sent        Forwarded In      Forwarded Out   Snooped
-------------------------------------------------------------------------------------------------
Total Messages                 0               0             0                  0             0
Access Requests                0               0             0                  0             0
Access Responses               0               0             0                  0             0
    Accept                     0               0             0                  0             0
    Reject                     0               0             0                  0             0
Accounting Requests            0               0             0                  0             0
    Start                      0               0             0                  0             0
    Interim                    0               0             0                  0             0
    Stop                       0               0             0                  0             0
    On                         0               0             0                  0             0
    Off                        0               0             0                  0             0
Accounting Responses           0               0             0                  0             0
    Start                      0               0             0                  0             0
    Interim                    0               0             0                  0             0
    Stop                       0               0             0                  0             0
    On                         0               0             0                  0             0
    Off                        0               0             0                  0             0
Change of Auth Requests        0               0             0                  0             0
Change of Auth Responses       0               0             0                  0             0
    Ack                        0               0             0                  0             0
    Nak                        0               0             0                  0             0
Disconnect Message Requests    0               0             0                  0             0
Disconnect Message Responses   0               0             0                  0             0
    Ack                        0               0             0                  0             0
    Nak                        0               0             0                  0             0

Duplicates:                                 0
Request Processing Errors:                  0
Response Processing Errors:                 0
Request Transmit Errors :                   0
Response Transmit Errors:                   0
Request Enqueue Errors:                     0
Response Enqueue Errors:                    0
Request Timeouts:                           0
Request Retransmissions:                    0
Missing TDF Domain:                         0
Missing PCEF profile:                       0
Number of Dropped Requests:                           0
Dropped Responses:                          0
Server Initiated Request Processing Errors: 0
Dropped Server Initiated Requests:          0
Duplicate Server Initiated Requests:        0
Cached Reply Sent:                          0
```


Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf address-assignment pool

Syntax

```
show unified-edge tdf address-assignment pool
<brief | detail | summary>
<fpc-slot fpc-slot>
<gateway gateway-name>
<name pool-name>
<pic-slot pic-slot>
<routing-instance routing-instance>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display information about the address pools for one or more TDF gateways. If a TDF gateway is not specified, then information for all TDF gateways is displayed.

Options

none—(Same as brief) Display address information about the address pools in brief for all TDF gateways.

brief | detail | summary—(Optional) Display the specified level of output.

fpc-slot *fpc-slot*—(Optional) Display address pool information for the session PIC in the specified FPC slot.

gateway *gateway-name*—(Optional) Display address pool information for the specified TDF gateway.

name *pool-name*—(Optional) Display information for the specified address pool.

pic-slot *pic-slot*—(Optional) Display address pool information for the session PIC in the specified PIC slot.

routing-instance *routing-instance*—(Optional) Display the address pool information for the specified routing instance.

Required Privilege Level view

Related Documentation

- clear unified-edge tdf address-assignment pool on page 536

List of Sample Output

show unified-edge tdf address-assignment pool brief on page 651
show unified-edge tdf address-assignment pool detail on page 651
show unified-edge tdf address-assignment pool summary on page 652

Output Fields Table 41 on page 650 lists the output fields for the **show unified-edge tdf address-assignment pool** command. Output fields are listed in the approximate order in which they appear.

Copyright © 2018, Juniper Networks, Inc.

Table 41: show unified-edge tdf address-assignment pool Output Fields

Field Name	Field Description	Level of Output
Pool or **Name**	Name of the address pool.	All levels
FPC/PIC	FPC and PIC slots of the session PIC for which the address pool information is displayed.	**detail**
Total addresses	Total number of addresses available in the address pool.	**brief** **detail**
Total	Total number of addresses available in the address pool.	**summary**
Addresses in use	Number of addresses that have been allocated.	**brief** **detail**
In-use	Number of addresses that have been allocated.	**summary**
Addresses skipped	Number of addresses that are excluded from allocation.	**brief** **detail**
Address usage (percent)	Percentage of the total addresses used.	**brief** **detail**
Util (%)	Percentage of the total addresses used.	**summary**
Addresses in aging period	Number of addresses that are currently being released and that cannot be allocated.	**brief** **detail**
Routing Instance	Name of the routing instance to which the address pool belongs.	All levels
Gateway	TDF gateway to which the session PIC belongs.	**detail**
Pool Maintenance Mode	Service mode of the address pool; for example, Operational or Maintenance.	**detail**
Address chunks	Number of chunks of IP addresses in the address pool (for the session PIC) that are currently being assigned	**detail**
Total address chunk size	Total number of addresses in the address chunk (for the session PIC).	**detail**
Total allocation failures	Total number of addresses that were not allocated.	**detail**

Copyright © 2018, Juniper Networks, Inc.

Sample Output

show unified-edge tdf address-assignment pool brief

```
user@host> show unified-edge tdf address-assignment pool brief


Pool: pool1
  Total addresses:           16777215
  Addresses in use:          1600
  Addresses skipped:         416
  Address usage (percent):   0
  Addresses in aging period: 1600
  Routing instance:          default


Pool: pool2
  Total addresses:           256
  Addresses in use:          254
  Addresses skipped:         2
  Address usage (percent):   99
  Addresses in aging period: 0
  Routing instance:          default

[...output truncated...]
```

show unified-edge tdf address-assignment pool detail

```
user@host> show unified-edge tdf address-assignment pool detail


Pool: pool1 (FPC/PIC: 4/0)
  Pool Maintenance Mode:     Operational
  Total addresses:           16777215
  Addresses in use:          822
  Addresses skipped:         208
  Address usage (percent):   0
  Addresses in aging period: 822
  Routing instance:          default
  Gateway:                   TDF
  Address chunks:            26
  Total address chunk size:  26416
  Total allocation failures: 0

Pool: pool1 (FPC/PIC: 4/1)
  Pool Maintenance Mode:     Operational
  Total addresses:           16777215
  Addresses in use:          778
  Addresses skipped:         208
  Address usage (percent):   0
  Addresses in aging period: 778
  Routing instance:          default
  Gateway:                   TDF
  Address chunks:            26
  Total address chunk size:  26416
  Total allocation failures: 0

Pool: pool2 (FPC/PIC: 4/0)
  Pool Maintenance Mode:     Operational
```

Copyright © 2018, Juniper Networks, Inc.

```
  Total addresses:           256
  Addresses in use:          0
  Addresses skipped:         0
  Address usage (percent):   0
  Addresses in aging period: 0
  Routing instance:          default
  Gateway:                   TDF
  Address chunks:            0
  Total address chunk size:  0
  Total allocation failures: 0

[...output truncated...]
```

show unified-edge tdf address-assignment pool summary

```
user@host> show unified-edge tdf address-assignment pool summary
```

```
                                                Util
Name                          Total       In-use    (%)  Routing instance
pool1                         16777215    1600      0    default
pool2                         256         254       99   default
pool3                         256         47        18   default
v4_pool                       16777216    0         0    default
v4_pool1                      16777215    0         0    default
v6_pool                       16777215    0         0    default
v6_pool1                      16777215    0         0    default
```


Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf address-assignment service-mode

Syntax

```
show unified-edge tdf address-assignment service-mode
<brief | detail>
<pool pool-name>
<routing-instance routing-instance-name>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display service mode information about address pools.

Options

none—(Same as brief) Display service mode information in brief.

brief | detail—(Optional) Display the specified level of output.

pool *pool-name*—(Optional) Display service mode information for the specified address pool.

routing-instance *routing-instance-name*—(Optional) Display service mode information about the address pools that are part of the specified routing instance.

Required Privilege Level view

Related Documentation

- Configuring Address Pools for Source-IP Filtering of IP-Based Subscribers on page 99

List of Sample Output

show unified-edge tdf address-assignment service-mode brief on page 654
show unified-edge tdf address-assignment service-mode detail on page 654

Output Fields Table 42 on page 653 lists the output fields for the **show unified-edge tdf address-assignment service-mode** command. Output fields are listed in the approximate order in which they appear.

Table 42: show unified-edge tdf address-assignment service-mode Output Fields

Field Name	Field Description	Level of Output
Maintenance Mode	Phases applicable when the address pool is in maintenance mode. • **MM - Active Phase**—All the attributes of the address pool can be modified. • **MM - In/Out Phase**—Only the non-maintenance mode attributes of the address pool can be modified.	None specified
Pool Name	Name of the address pool.	All levels
Routing Instance	Routing instance to which the address pool belongs.	All levels

Copyright © 2018, Juniper Networks, Inc.

Table 42: show unified-edge tdf address-assignment service-mode Output Fields (continued)

Field Name	Field Description	Level of Output
Service Mode	Service mode for the address pool: • **Operational**—Address pool is in operational mode. • **Maintenance**—Address pool is in maintenance mode. • **Maintenance - Active Phase**—All the attributes of the address pool can be modified. • **Maintenance - In/Out Phase**—Only the non-maintenance mode attributes of the address pool can be modified.	All levels

Sample Output

show unified-edge tdf address-assignment service-mode brief

```
user@host> show unified-edge tdf address-assignment service-mode brief
Maintenance Mode
    MM Active Phase - System is ready to accept configuration changes for all
                      attributes of this object and its sub-hierarchies.
    MM In/Out Phase - System is ready to accept configuration changes only for
                      non-maintenance mode attributes of this object and
                      its sub-hierarchies.

Routing-Instance               Pool Name                      Service Mode

default                        my_pool                        Operational
default                        v6_pool                        Operational
```

show unified-edge tdf address-assignment service-mode detail

```
user@host> show unified-edge tdf address-assignment service-mode detail
Routing Instance: default
Pool Name       : my_pool
Service Mode    : Operational

Routing Instance: default
Pool Name       : v6_pool
Service Mode    : Operational
```


Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf address-assignment statistics

Syntax

```
show unified-edge tdf address-assignment statistics
<brief | detail>
<fpc-slot fpc-slot>
<gateway gateway-name>
<pic-slot pic-slot>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display address assignment statistics for one or more TDF gateways. If a TDF gateway is not specified, then the consolidated statistics for all TDF gateways are displayed.

Options

none—(Same as brief) Display address assignment statistics in brief for all TDF gateways.

brief | detail—(Optional) Display the specified level of output.

fpc-slot *fpc-slot*—(Optional) Display statistics for the session PIC in the specified FPC slot.

gateway *gateway-name*—(Optional) Display consolidated statistics for the specified TDF gateway.

pic-slot *pic-slot*—(Optional) Display statistics for the session PIC in the specified PIC slot.

Required Privilege Level view

Related Documentation

- clear unified-edge tdf address-assignment statistics on page 537

Output Fields Table 43 on page 655 lists the output fields for the **show unified-edge tdf address-assignment statistics** command. Output fields are listed in the approximate order in which they appear.

Table 43: show unified-edge tdf address-assignment statistics Output Fields

Field Name	Field Description	Level of Output
FPC/PIC	FPC and PIC slots for which the statistics are displayed.	**detail**
Gateway	Name of the TDF gateway.	**detail**
Total address allocations	Total number of addresses allocated.	All levels
Total allocation failures	Total number of address allocations that failed.	All levels

Copyright © 2018, Juniper Networks, Inc.

Table 43: show unified-edge tdf address-assignment statistics Output Fields (continued)

Field Name	Field Description	Level of Output
Total address releases	Total number of addresses that were released.	All levels

Sample Output

show unified-edge tdf address-assignment statistics

```
user@host> show unified-edge tdf address-assignment statistics


Address assignment statistics
  Total address allocations: 1101
  Total allocation failures: 0
  Total address releases:    800
```

show unified-edge tdf address-assignment statistics detail

```
user@host> show unified-edge tdf address-assignment statistics detail


Address assignment statistics   (FPC/PIC: 4/0)
  Gateway:                  TDF
  Total address allocations: 416
  Total allocation failures: 0
  Total address releases:    416

Address assignment statistics   (FPC/PIC: 4/1)
  Gateway:                  TDF
  Total address allocations: 685
  Total allocation failures: 0
  Total address releases:    384
```


Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf call-admission-control statistics

Syntax

```
show unified-edge tdf call-admission-control statistics
<detail>
<fpc-slot fpc-slot>
<gateway gateway-name>
<pic-slot pic-slot>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display call admission control (CAC) statistics for one or more TDF gateways. If a TDF gateway is not specified, then statistics for all TDF gateways are displayed.

NOTE: CAC statistics are not stored on the Routing Engine. When this command is executed, the Routing Engine fetches the statistics from the active session PICs and displays the consolidated statistics for one or more TDF gateways.

Options **none**—Display CAC statistics for all TDF gateways.

detail—(Optional) Display detailed CAC statistics for the specified FPC and PIC slot numbers.

NOTE: The detail option is valid only when you specify an FPC and PIC slot number configured on the TDF gateway.

fpc-slot *fpc-slot* —(Optional) Display statistics for the session PIC in the specified FPC slot.

pic-slot *pic-slot*—(Optional) Display statistics for the session PIC in the specified PIC slot.

gateway *gateway-name*—(Optional) Display CAC statistics for the specified TDF gateway.

Required Privilege Level view

Related Documentation

- clear unified-edge tdf call-admission-control statistics on page 538

List of Sample Output show unified-edge tdf call-admission-control statistics on page 659

Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf call-admission-control statistics fpc-slot pic-slot detail on page 659

Output Fields Table 44 on page 658 lists the output fields for the **show unified-edge tdf call-admission-control statistics** command. Output fields are listed in the approximate order in which they appear.

Table 44: show unified-edge tdf call-admission-control statistics Output Fields

Field Name	Field Description	Level of Output
Gateway: TDF	Output is displayed for TDF gateways.	**detail** none
GW CAC Statistics	Statistical details are displayed at the TDF gateway level.	**detail** none
Memory High Rejects	Number of subscribers or PDP contexts that were rejected because the memory load or utilization (at the session PIC level) was high.	**detail** none
Memory High Redirects	Number of subscribers or PDP contexts that were redirected because the memory load or utilization (at the session PIC level) was high.	**detail** none
CPU High Rejects	Number of subscribers or PDP contexts that were rejected because the CPU load or utilization (at the session PIC level) was high.	**detail** none
CPU High Redirects	Number of subscribers or PDP contexts that were redirected because the CPU load or utilization (at the session PIC level) was high.	**detail** none
Session Reservation Rejects	Number of sessions that were rejected for reservation of TDF subscribers on a particular TDF gateway or domain.	**detail** none
Session Reservation Redirects	Number of sessions that were redirected to a different TDF gateway or domain for reservation of TDF subscribers.	**detail** none
Gateway Subscriber Count	Total number of subscribers that are connected to the TDF gateway.	**detail** none
TDF DOMAIN CAC Statistics	Statistical details are displayed at the TDF domain level.	**detail** none
Session Reservation Rejects	Number of sessions that were rejected for reservation of TDF subscribers on a particular TDF gateway or domain.	**detail** none

Copyright © 2018, Juniper Networks, Inc.

Table 44: show unified-edge tdf call-admission-control statistics Output Fields (continued)

Field Name	Field Description	Level of Output
Session Reservation Redirects	Number of sessions that were redirected to a different TDF gateway or domain for reservation of TDF subscribers.	**detail** none

Sample Output

show unified-edge tdf call-admission-control statistics

```
user@host> show unified-edge tdf call-admission-control statistics
Gateway: TDF

GW CAC Statistics:
  Memory High Rejects                     :   0
  Memory High Redirects                   :   0
  CPU High Rejects                        :   0
  CPU High Redirects                      :   0
  Session Reservation Rejects             :   0
  Session Reservation Redirects           :   0
  Gateway Subscriber Count                :   1

Domain CAC Statistics:
  Session Reservation Rejects             :   0
  Session Reservation Redirects           :   0
```

show unified-edge tdf call-admission-control statistics fpc-slot pic-slot detail

```
user@host> show unified-edge tdf call-admission-control statistics fpc-slot 3 pic-slot 1 detail

Gateway: TDF

GW CAC Statistics:
  Memory High Rejects                     :   0
  Memory High Redirects                   :   0
  CPU High Rejects                        :   0
  CPU High Redirects                      :   0
  Session Reservation Rejects             :   0
  Session Reservation Redirects           :   0
  Gateway Subscriber Count                :   1

Domain CAC Statistics:
  Session Reservation Rejects             :   0
  Session Reservation Redirects           :   0
```

Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf call-rate statistics

Syntax show unified-edge tdf call-rate statistics (domain *domain-name* | gateway *gateway-name*)

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display call-rate statistics for the specified TDF domain or specified TDF gateway.

Options **domain *domain-name***—Display call-rate statistics for the specified TDF domain.

gateway *gateway-name*—Display call-rate statistics for the specified TDF gateway.

Required Privilege Level view

Related Documentation
- Configuring Call-Rate Statistics Collection on page 200

List of Sample Output show unified-edge tdf call-rate statistics gateway on page 661

Output Fields Table 45 on page 660 lists the output fields for the **show unified-edge tdf call-rate statistics** command. Output fields are listed in the approximate order in which they appear.

Table 45: show unified-edge tdf call-rate statistics Output Fields

Field Name	Field Description
Gateway	Name of the TDF gateway.
TDF domain name	Name of the TDF domain. This is displayed only when the **domain** option is used.
Record *n*	Displays statistics for the most recent *n* number of intervals.
Number of Activations	Number of successful subscriber logins for this record.
Number of Deactivations	Number of subscriber logouts for this record.
Activations processing time (in ms)	Average subscriber login activation processing time.
Subscriber session duration (in mins)	Average subscriber session duration.
Statistics collection time	Time at which the statistics were collected.

Copyright © 2018, Juniper Networks, Inc.

Table 45: show unified-edge tdf call-rate statistics Output Fields (continued)

Field Name	Field Description
Control Plane Standard Deviation	Standard deviations for the following: • **Number of Activations**—Number of subscriber logins • **Number of Deactivations**—Number of subscriber logouts • **Activations processing time**—Length of time of subscriber login • **Subscriber session duration**—Length of time of subscriber logout

Sample Output

show unified-edge tdf call-rate statistics gateway

```
user@host> show unified-edge tdf call-rate statistics gateway TDF

Gateway: TDF
Record 1 (Call-rate statistics for the past 1 min):
Control Plane:
        Number of Activations:                  0
        Number of Deactivations:                0
        Activations processing time (in ms):    0
        Subscriber session duration (in mins):  0

Statistics collection time: 2014-03-04 11:45:44 UTC (00:03:06 ago)

Record 2 (Call-rate statistics for the past 2 min):
Control Plane:
        Number of Activations:                  0
        Number of Deactivations:                0
        Activations processing time (in ms):    0
        Subscriber session duration (in mins):  0

Control Plane Standard Deviation:
        Number of Activations:                  0
        Number of Deactivations:                0
        Activations processing time:            0
        Subscriber session duration:            0

Statistics collection time: 2014-03-04 11:44:44 UTC (00:04:06 ago)
```

Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf diameter network-element statistics

Syntax

```
show unified-edge tdf diameter network-element statistics
<brief | detail>
<fpc-slot fpc-slot>
<gateway gateway-name>
<network-element-name network-element-name>
<pic-slot pic-slot>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display statistics for network elements for one or more TDF gateways. If a network element is not specified, then statistics for all network elements are displayed. If a TDF gateway is not specified, then statistics for all TDF gateways are displayed.

Options

none—Display statistics for network elements for all TDF gateways.

brief | detail—(Optional) Display the specified level of output. The **brief** output is displayed by default.

fpc-slot *fpc-slot*—(Optional) Display statistics for the specified Flexible PIC Concentrator (FPC).

gateway *gateway-name*—(Optional) Display statistics for the specified TDF gateway.

network-element-name *network-element-name*—(Optional) Display statistics for the specified network element.

pic-slot *pic-slot*—(Optional) Display the statistics for the specified PIC slot number. You must first specify an FPC slot number before specifying the PIC slot number.

Required Privilege Level view

Related Documentation

- clear unified-edge tdf diameter network-element statistics on page 539
- show unified-edge tdf diameter network-element status on page 665

List of Sample Output

show unified-edge tdf diameter network-element statistics on page 663
show unified-edge tdf diameter network-element statistics detail on page 663

Output Fields Table 46 on page 663 lists the output fields for the **show unified-edge tdf diameter network-element statistics** command. Output fields are listed in the approximate order in which they appear.

Copyright © 2018, Juniper Networks, Inc.

Table 46: show unified-edge tdf diameter network-element statistics Output Fields

Field Name	Field Description	Level of Output
Name	Name of the network element.	All levels
FPC/PIC	FPC and PIC slot numbers through which the network element was reached.	**detail**
Packets Received	Number of incoming packets.	All levels
Packets Transmitted	Number of outgoing packets.	All levels
Request Timeouts	Number of request timeouts.	All levels
Credit Control Request Transmitted	Number of outgoing Credit-Control-Request messages.	All levels
Credit Control Answer Received	Number of incoming Credit-Control-Answer messages.	All levels

Sample Output

show unified-edge tdf diameter network-element statistics

```
user@host> show unified-edge tdf diameter network-element statistics

Name:   pcrf-dne
   Packets Received :                      0
   Packets Transmitted :                   0
   Request Timeouts :                      0
   Credit Control Request Transmitted :    0
   Credit Control Answer Received :        0

Name:   ocs-dne
   Packets Received :                      3
   Packets Transmitted :                   4
   Request Timeouts :                      1
   Credit Control Request Transmitted :    4
   Credit Control Answer Received :        3
```

show unified-edge tdf diameter network-element statistics detail

```
user@host> show unified-edge tdf diameter network-element statistics detail

Name :                              pcrf-dne
FPC/PIC :                           0/0
Packets Received :                  0
Packets Transmitted :               0
Request Timeouts :                  0
Credit Control Request Transmitted :  0
Credit Control Answer Received :    0

FPC/PIC :                           0/1
Packets Received :                  0
Packets Transmitted :               0
```

Copyright © 2018, Juniper Networks, Inc.

```
Request Timeouts :                    0
Credit Control Request Transmitted :  0
Credit Control Answer Received :      0

Name :                                ocs-dne
FPC/PIC :                             0/0
Packets Received :                    0
Packets Transmitted :                 0
Request Timeouts :                    0
Credit Control Request Transmitted :  0
Credit Control Answer Received :      0

FPC/PIC :                             0/1
Packets Received :                    3
Packets Transmitted :                 4
Request Timeouts :                    1
Credit Control Request Transmitted :  4
Credit Control Answer Received :      3
```


Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf diameter network-element status

Syntax

```
show unified-edge tdf diameter network-element status
<fpc-slot fpc-slot>
<gateway gateway-name>
<network-element-name network-element-name>
<pic-slot pic-slot>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display the status for one or more Diameter network elements. If a network element is not specified, then status for all network elements is displayed. If a TDF gateway is not specified, then status for all TDF gateways is displayed.

Options

none—Display status for all network elements for all TDF gateways.

fpc-slot *fpc-slot*—(Optional) Display the status for the specified Flexible PIC Concentrator (FPC).

gateway *gateway-name*—(Optional) Display the status for the specified TDF gateway.

network-element-name *network-element-name*—(Optional) Display the status for the specified network element.

pic-slot *pic-slot*—(Optional) Display the status for the specified PIC slot number. You must first specify an FPC slot number before specifying the PIC slot number.

Required Privilege Level view

Related Documentation

- show unified-edge tdf diameter network-element statistics on page 662

List of Sample Output show unified-edge tdf diameter network-element status on page 666

Output Fields Table 47 on page 665 lists the output fields for the **show unified-edge tdf diameter network-element status** command. Output fields are listed in the approximate order in which they appear.

Table 47: show unified-edge tdf diameter network-element status Output Fields

Field Name	Field Description
DNE	Name of the network element.
PEER	Name of the peer.
FPC/PIC	FPC and PIC slot numbers through which the network element was reached.

Copyright © 2018, Juniper Networks, Inc.

Table 47: show unified-edge tdf diameter network-element status Output Fields (continued)

Field Name	Field Description
PEER STATE	Current state of the peer. Possible states are: **Closed**, **Closing**, **I-Open**, **R-Open**, **Wait-Conn-Ack**, **Wait-Conn-Ack/Elect**, **Wait-I-CEA**, and **Wait-Returns**.
WATCHDOG STATE	Peer watchdog status. • **closed**—Connection between Diameter peers is terminated. • **initial**—Connection between Diameter peers is being initialized. • **okay**—Connection between Diameter peers is established and active.

Sample Output

show unified-edge tdf diameter network-element status

```
user@host> show unified-edge tdf diameter network-element status
DNE : pcrf-dne
    PEER : pcrf
       FPC/PIC          PEER STATE            WATCHDOG STATE
         0/0            Closed                initial
         0/1            Closed                initial
DNE : ocs-dne
    PEER : ocs
       FPC/PIC          PEER STATE            WATCHDOG STATE
         0/0            I-Open                okay
         0/1            I-Open                okay
```


Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf diameter pcc-gx statistics

Syntax

```
show unified-edge tdf diameter pcc-gx statistics
<brief | detail>
<fpc-slot fpc-slot>
<gateway gateway-name>
<pic-slot pic-slot>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display statistics for the Gx application for one or more TDF gateways. If a TDF gateway is not specified, then statistics for all TDF gateways are displayed.

Options

none—Display statistics for the Gx application for all TDF gateways.

brief | detail—(Optional) Display the specified level of output. The **brief** output is displayed by default.

fpc-slot *fpc-slot*—(Optional) Display statistics for the specified Flexible PIC Concentrator (FPC).

gateway *gateway-name*—(Optional) Display statistics for the specified TDF gateway.

pic-slot *pic-slot*—(Optional) Display statistics for the specified PIC slot number. You must first specify an FPC slot number before specifying the PIC slot number.

Required Privilege Level view

Related Documentation

- clear unified-edge tdf diameter pcc-gx statistics on page 540

List of Sample Output

show unified-edge tdf diameter pcc-gx statistics on page 669
show unified-edge tdf diameter pcc-gx statistics detail on page 670

Output Fields Table 48 on page 667 lists the output fields for the **show unified-edge tdf diameter pcc-gx statistics** command. Output fields are listed in the approximate order in which they appear.

Table 48: show unified-edge tdf diameter pcc-gx statistics Output Fields

Field Name	Field Description	Level of Output
Gateway	Name of the TDF gateway.	All levels
FPC/PIC	FPC and PIC slots for which the statistics are displayed.	**detail**
Total Sessions Established	Total number of active sessions.	All levels

Copyright © 2018, Juniper Networks, Inc.

Table 48: show unified-edge tdf diameter pcc-gx statistics Output Fields (continued)

Field Name	Field Description	Level of Output
Total Sessions Terminated	Total number of terminated sessions.	All levels
Internal Errors	Number of internal errors.	**detail**
Total	• **Requests**—Total number of request messages. • **Answers**—Total number of answer messages.	none **brief**
Credit Control Initial	• **Requests**—Number of initial transfer type Credit-Control-Request (CCR) messages. • **Answers**—Number of initial transfer type Credit-Control-Answer (CCA) messages.	none **brief**
Credit Control Update	• **Requests**—Number of update transfer type CCR messages. • **Answers**—Number of update transfer type CCA messages.	none **brief**
Credit Control Terminate	• **Requests**—Number of terminate transfer type CCR messages. • **Answers**—Number of terminate transfer type CCA messages.	none **brief**
Re-Auth	• **Requests**—Number of Re-Auth-Request (RAR) messages. • **Answers**—Number of Re-Auth-Answer (RAA) messages.	none **brief**
Dropped	• **Requests**—Number of dropped request messages. • **Answers**—Number of dropped answer messages.	none **brief**
Requests Transmitted	• **Initial**—Number of initial transfer type CCR messages sent. • **Update**—Number of update transfer type CCR messages sent. • **Terminate**—Number of terminate transfer type CCR messages sent. • **Total**—Number of CCR messages sent.	**detail**
Request Timeouts	• **Initial**—Number of initial transfer type CCR messages that timed out. • **Update**—Number of update transfer type CCR messages that timed out. • **Terminate**—Number of terminate transfer type CCR messages that timed out. • **Total**—Number of CCR messages that timed out.	**detail**
Request Tx Timeouts	• **Initial**—Number of initial transfer type CCR messages sent that timed out. • **Update**—Number of update transfer type CCR messages sent that timed out. • **Terminate**—Number of terminate transfer type CCR messages sent that timed out. • **Total**—Number of CCR messages sent that timed out.	**detail**

Copyright © 2018, Juniper Networks, Inc.

Table 48: show unified-edge tdf diameter pcc-gx statistics Output Fields (continued)

Field Name	Field Description	Level of Output
Request Discarded	• **Initial**—Number of initial transfer type CCR messages sent that were discarded. • **Update**—Number of update transfer type CCR messages sent that were discarded. • **Terminate**—Number of terminate transfer type CCR messages sent that were discarded. • **Total**—Number of CCR messages sent that were discarded.	**detail**
Answers Received	• **Initial**—Number of initial transfer type CCA messages received. • **Update**—Number of update transfer type CCA messages received. • **Terminate**—Number of terminate transfer type CCA messages received. • **Total**—Number of CCA messages received.	**detail**
Answers Dropped	• **Initial**—Number of initial transfer type CCA messages dropped. • **Update**—Number of update transfer type CCA messages dropped. • **Terminate**—Number of terminate transfer type CCA messages dropped. • **Total**—Number of CCA messages dropped.	**detail**
Answers Parse Errors	• **Initial**—Number of initial transfer type CCA messages with parse errors. • **Update**—Number of update transfer type CCA messages with parse errors. • **Terminate**—Number of terminate transfer type CCA messages with parse errors. • **Total**—Number of CCA messages with parse errors.	**detail**
Answers with Invalid AVP(s)	• **Initial**—Number of initial transfer type CCA messages with invalid AVPs. • **Update**—Number of update transfer type CCA messages with invalid AVPs. • **Terminate**—Number of terminate transfer type CCA messages with invalid AVPs. • **Total**—Number of CCA messages with invalid AVPs.	**detail**
Requests Received	Number of RAR messages received.	**detail**
Requests Dropped	Number of RAR messages dropped.	**detail**
Requests Parse Errors	Number of RAR messages with parse errors.	**detail**
Requests with Invalid AVP(s)	Number of RAR messages with invalid AVPs.	**detail**
Answers Transmitted	Number of RAA messages sent.	**detail**

Sample Output

show unified-edge tdf diameter pcc-gx statistics

```
user@host> show unified-edge tdf diameter pcc-gx statistics
```

Copyright © 2018, Juniper Networks, Inc.

```
Gateway: TDF
  Total Sessions Established:            0
  Total Sessions Terminated:     0
                              Requests            Answers
  ------------------------------------------------------
  Total                       0                   0
  Credit Control Initial      0                   0
  Credit Control Update       0                   0
  Credit Control Terminate    0                   0
  Re-Auth                     0                   0
  Dropped                     0                   0
```

show unified-edge tdf diameter pcc-gx statistics detail

```
user@host> show unified-edge tdf diameter pcc-gx statistics detail
```

```
Gateway: TDF
FPC/PIC: 0/0
  Total Sessions Established:            0
  Total Sessions Terminated:  0
  Internal Errors:            0

  Credit Control                 Initial     Update      Terminate       Total

  ------------------------------------------------------------------------------

  Requests Transmitted            0           0           0               0
  Request Timeouts                0           0           0               0
  Request Tx Timeouts             0           0           0               0
  Request Discarded               0           0           0               0
  Answers Received                0           0           0               0
  Answers Dropped                 0           0           0               0
  Answers Parse Errors            0           0           0               0
  Answers with Invalid AVP(s)     0           0           0               0

  Server Requests                 Re-Auth
  ------------------------------------
  Requests Received               0
  Requests Dropped                0
  Requests Parse Errors           0
  Requests with Invalid AVP(s)    0
  Answers Transmitted             0

Gateway: TDF
FPC/PIC: 0/1
  Total Sessions:             0
  Total Sessions Terminated:  0
  Internal Errors:            0

  Credit Control                 Initial     Update      Terminate       Total

  ------------------------------------------------------------------------------

  Requests Transmitted            0           0           0               0
  Request Timeouts                0           0           0               0
  Request Tx Timeouts             0           0           0               0
  Request Discarded               0           0           0               0
  Answers Received                0           0           0               0
  Answers Dropped                 0           0           0               0
  Answers Parse Errors            0           0           0               0
```


Copyright © 2018, Juniper Networks, Inc.

```
Answers with Invalid AVP(s)     0           0           0               0

Server Requests                 Re-Auth
---------------------------------------
Requests Received               0
Requests Dropped                0
Requests Parse Errors           0
Requests with Invalid AVP(s)    0
Answers Transmitted             0
```

show unified-edge tdf diameter peer statistics

Syntax

```
show unified-edge tdf diameter peer statistics
<brief | detail>
<fpc-slot fpc-slot>
<gateway gateway-name>
<peer-name peer-name>
<pic-slot pic-slot>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display statistics for Diameter peers for one or more TDF gateways. If a peer is not specified, then statistics for all Diameter peers are displayed. If a TDF gateway is not specified, then statistics for all TDF gateways are displayed.

Options

none—(Same as brief) Display statistics for Diameter peers for all TDF gateways in brief.

brief | detail—(Optional) Display the specified level of output. The **brief** output is displayed by default.

fpc-slot *fpc-slot*—(Optional) Display statistics for the specified Flexible PIC Concentrator (FPC).

gateway *gateway-name*—(Optional) Display statistics for the specified TDF gateway.

peer-name *peer-name*—(Optional) Display statistics for the specified peer.

pic-slot *pic-slot*—(Optional) Display statistics for the specified PIC slot number. You must first specify an FPC slot number before specifying the PIC slot number.

Required Privilege Level view

Related Documentation

- clear unified-edge tdf diameter peer statistics on page 541
- show unified-edge tdf diameter peer status on page 677

List of Sample Output

show unified-edge tdf diameter peer statistics on page 674
show unified-edge tdf diameter peer statistics detail on page 675

Output Fields Table 49 on page 673 lists the output fields for the **show unified-edge tdf diameter peer statistics** command. Output fields are listed in the approximate order in which they appear.

Copyright © 2018, Juniper Networks, Inc.

Table 49: show unified-edge tdf diameter peer statistics Output Fields

Field Name	Field Description	Level of Output
Peer	Name of the peer.	All levels
FPC/PIC	FPC and PIC slot numbers through which the peer was reached.	**detail**
Request Timeouts	Number of request timeouts.	All levels
Request Retransmissions	Number of request retransmissions.	All levels
Connect Failures	Number of connection failures.	**detail**
Duplicate Requests	Number of duplicate requests.	**detail**
Malformed Messages	Number of malformed requests.	**detail**
Dropped Responses	Number of dropped responses.	**detail**
Dropped Requests	Number of dropped requests.	**detail**
Last Disconnect Cause	Number of last disconnect cause messages.	**detail**
Transport Failures	Number of transport failures.	**detail**
Unknown Messages	Number of unknown type errors.	**detail**
High Watermark Hits	Number of times the high watermark is reached.	**detail**
Low Watermark Hits	Number of times the low watermark is reached.	**detail**
Device Watchdog Failured	Number of device watchdog failures.	**detail**
Capabilities Exchange Failures	Number of capabilities exchange failures.	**detail**
Total Messages	Total number of messages transmitted and received.	All levels
Credit Control Requests	Number of Credit-Control-Request messages transmitted and received.	All levels
Credit Control Answers	Number of Credit-Control-Answer messages transmitted and received.	All levels
Re-Auth Requests	Number of Re-Auth-Request messages transmitted and received.	All levels
Re-Auth Answers	Number of Re-Auth-Answer messages transmitted and received.	All levels
Abort Session Requests	Number of Abort-Session-Request messages transmitted and received.	All levels

Copyright © 2018, Juniper Networks, Inc.

Table 49: show unified-edge tdf diameter peer statistics Output Fields (continued)

Field Name	Field Description	Level of Output
Abort Session Answers	Number of Abort-Session-Answer messages transmitted and received.	All levels
Capability Exchange Requests	Number of Capabilities-Exchange-Request messages transmitted and received.	All levels
Capability Exchange Answers	Number of Capabilities-Exchange-Answer messages transmitted and received.	All levels
Device Watchdog Requests	Number of Device-Watchdog-Request messages transmitted and received.	All levels
Device Watchdog Answers	Number of Device-Watchdog-Answer messages transmitted and received.	All levels
Disconnect Peer Requests	Number of Disconnect-Peer-Request messages transmitted and received.	All levels
Disconnect Peer Answers	Number of Disconnect-Peer-Answer messages transmitted and received.	All levels
Permanent Failures	Number of permanent failure result codes transmitted and received.	**detail**
Protocol Errors	Number of protocol error result codes transmitted and received.	**detail**
Transient Failures	Number of transient failure result codes transmitted and received.	**detail**

Sample Output

show unified-edge tdf diameter peer statistics

```
user@host> show unified-edge tdf diameter peer statistics

Peer: ocs
    Request Timeouts:                  1
    Request Retransmissions:           0
    Messages                           Transmitted       Received
    ---------------------------------------------------------------
    Total Messages                     6                 5
    Credit Control Requests            4                 0
    Credit Control Answers             0                 3
    Re-Auth Requests                   0                 0
    Re-Auth Answers                    0                 0
    Abort Session Requests             0                 0
    Abort Session Answers              0                 0
    Capability Exchange Requests       2                 0
    Capability Exchange Answers        0                 2
    Device Watchdog Requests           0                 0
    Device Watchdog Answers            0                 0
```


Copyright © 2018, Juniper Networks, Inc.

```
    Disconnect Peer Requests            0                0
    Disconnect Peer Answers             0                0
```

show unified-edge tdf diameter peer statistics detail

```
user@host> show unified-edge tdf diameter peer statistics detail
```

```
Peer: ocs
    FPC/PIC: 0/0
    Request Timeouts:                   0
    Request Retransmissions:            0
    Connect Failures:                   0
    Duplicate Requests:                 0
    Malformed Messages:                 0
    Dropped Responses:                  0
    Dropped Requests:                   0
    Last Disconnect Cause:              0
    Transport Failures:                 0
    Unknown Messages:                   0
    High Watermark Hits:                0
    Low Watermark Hits:                 0
    Device Watchdog Failured:           0
    Capabilities Exchange Failures:     0

    Messages                            Transmitted       Received
    ---------------------------------------------------------------
    Total Messages                      1                 1
    Credit Control Requests             0                 0
    Credit Control Answers              0                 0
    Re-Auth Requests                    0                 0
    Re-Auth Answers                     0                 0
    Abort Session Requests              0                 0
    Abort Session Answers               0                 0
    Capability Exchange Requests        1                 0
    Capability Exchange Answers         0                 1
    Device Watchdog Requests            0                 0
    Device Watchdog Answers             0                 0
    Disconnect Peer Requests            0                 0
    Disconnect Peer Answers             0                 0

    Result-Code                         Transmitted       Received
    ---------------------------------------------------------------
    Permanent Failures                  0                 0
    Protocol Errors                     0                 0
    Transient Failures                  0                 0

    FPC/PIC: 0/1
    Request Timeouts:                   1
    Request Retransmissions:            0
    Connect Failures:                   0
    Duplicate Requests:                 0
    Malformed Messages:                 0
    Dropped Responses:                  0
    Dropped Requests:                   0
    Last Disconnect Cause:              0
    Transport Failures:                 0
    Unknown Messages:                   0
    High Watermark Hits:                0
    Low Watermark Hits:                 0
    Device Watchdog Failured:           0
```

```
Capabilities Exchange Failures:     0

Messages                            Transmitted       Received
-----------------------------------------------------------------
Total Messages                      5                 4
Credit Control Requests             4                 0
Credit Control Answers              0                 3
Re-Auth Requests                    0                 0
Re-Auth Answers                     0                 0
Abort Session Requests              0                 0
Abort Session Answers               0                 0
Capability Exchange Requests        1                 0
Capability Exchange Answers         0                 1
Device Watchdog Requests            0                 0
Device Watchdog Answers             0                 0
Disconnect Peer Requests            0                 0
Disconnect Peer Answers             0                 0

Result-Code                         Transmitted       Received
-----------------------------------------------------------------
Permanent Failures                  0                 0
Protocol Errors                     0                 0
Transient Failures                  0                 0
```


Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf diameter peer status

Syntax

```
show unified-edge tdf diameter peer status
<brief | detail>
<fpc-slot fpc-slot>
<gateway gateway-name>
<peer-name peer-name>
<pic-slot pic-slot>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display the status for one or more Diameter peers. If a peer is not specified, then status for all Diameter peers is displayed. If a TDF gateway is not specified, then status for all TDF gateways is displayed.

Options

none—(Same as brief) Display the status for Diameter peers for all TDF gateways in brief.

brief | detail—(Optional) Display the specified level of output. The **brief** output is displayed by default.

fpc-slot *fpc-slot*—(Optional) Display the status for the specified Flexible PIC Concentrator (FPC).

gateway *gateway-name*—(Optional) Display the status for the specified TDF gateway.

peer-name *peer-name*—(Optional) Display the status for the specified peer.

pic-slot *pic-slot*—(Optional) Display the status for the specified PIC slot number. You must first specify an FPC slot number before specifying the PIC slot number.

Required Privilege Level view

Related Documentation

- show unified-edge tdf diameter peer statistics on page 672

List of Sample Output

show unified-edge tdf diameter peer status on page 679
show unified-edge tdf diameter peer status detail on page 679

Output Fields Table 50 on page 677 lists the output fields for the **show unified-edge tdf diameter peer status** command. Output fields are listed in the approximate order in which they appear.

Table 50: show unified-edge tdf diameter peer status Output Fields

Field Name	Field Description	Level of Output
Name	Name of the peer. For the **brief** output, the name is truncated if it exceeds 11 characters.	All levels

Copyright © 2018, Juniper Networks, Inc.

Table 50: show unified-edge tdf diameter peer status Output Fields (continued)

Field Name	Field Description	Level of Output
FPC/PIC	FPC and PIC slot numbers through which the peer was reached.	All levels
Address	IP address of the Diameter peer.	**brief** none
Port	Port number of the Diameter peer.	**brief** none
State	Current state of the Diameter peer. Possible states are: **Closed**, **Closing**, **I-Open**, **R-Open**, **Wait-Conn-Ack**, **Wait-Conn-Ack/Elect**, **Wait-I-CEA**, and **Wait-Returns**. For the **brief** and none output, the state is truncated if it exceeds 11 characters.	All levels
Duration	Duration for which the Diameter peer has been in the current state in Coordinated Universal Time (UTC) format (HH:MM:SS).	none **brief**
State Duration	Duration for which the Diameter peer has been in the current state in Coordinated Universal Time (UTC) format (HH:MM:SS).	**detail**
Watchdog	Peer watchdog status. • **closed**—Connection between Diameter peers is terminated. • **initial**—Connection between Diameter peers is being initialized. • **okay**—Connection between Diameter peers is established and active.	none **brief**
Watchdog State	Peer watchdog status. • **closed**—Connection between Diameter peers is terminated. • **initial**—Connection between Diameter peers is being initialized. • **okay**—Connection between Diameter peers is established and active.	**detail**
Origin Host	Diameter Origin-Host.	**detail**
Origin Realm	Diameter Origin-Realm.	**detail**
Peer Address	IP address of the Diameter peer.	**detail**
Peer port	Port number of the Diameter peer.	**detail**
Source Address	Local source IP address used to connect to the peer.	**detail**
Source Port	Local source port number used to connect to the peer.	**detail**

Copyright © 2018, Juniper Networks, Inc.

Sample Output

show unified-edge tdf diameter peer status

```
user@host> show unified-edge tdf diameter peer status
```

```
Name          FPC/PIC  Address          Port    State        Duration  Watchdog
p_jpkt1       4/0      192.0.2.2        3868    Closed       00:00:00  initial
p_jpkt1       4/1      192.0.2.2        3868    Closed       00:00:00  initial
p_jpkt1       5/0      192.0.2.2        3868    Wait-Conn-A  00:00:00  initial
abcabcabcab   4/0      192.0.2.2        3868    Closed       00:00:00  initial
abcabcabcab   4/1      192.0.2.2        3868    Closed       00:00:00  initial
abcabcabcab   5/0      192.0.2.2        3868    Wait-Conn-A  00:00:00  initial
```

show unified-edge tdf diameter peer status detail

```
user@host> show unified-edge tdf diameter peer status detail
```

```
Diameter Peer Status
  Name : ocs
     FPC/PIC               :          0/0
     State                 :          I-Open
     State Duration        :          00:00:00
     Watchdog State        :          okay
     Origin Host           :          host5
     Origin Realm          :          example.com
     Peer Address          :          198.51.100.2
     Peer port             :          3868
     Source Address        :          203.0.113.1
     Source Port           :          30965
  Name : ocs
     FPC/PIC               :          0/1
     State                 :          I-Open
     State Duration        :          00:00:00
     Watchdog State        :          okay
     Origin Host           :          host5
     Origin Realm          :          example.com
     Peer Address          :          198.51.100.2
     Peer port             :          3868
     Source Address        :          203.0.113.1
     Source Port           :          30709
  Name : pcrf
     FPC/PIC               :          0/0
     State                 :          Closed
     State Duration        :          00:00:00
     Watchdog State        :          initial
     Peer Address          :          192.168.1.2
     Peer port             :          3868
     Source Address        :          203.0.113.1
     Source Port           :          0
  Name : pcrf
     FPC/PIC               :          0/1
     State                 :          Closed
     State Duration        :          00:00:00
     Watchdog State        :          initial
     Peer Address          :          192.168.1.2
     Peer port             :          3868
     Source Address        :          203.0.113.1
     Source Port           :          0
```

Copyright © 2018, Juniper Networks, Inc.

Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf domain service-mode

Syntax

```
show unified-edge tdf domain service-mode
<domain-name tdf-domain-name>
<brief | detail>
<gateway gateway>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display service mode information for a TDF domain for one or more TDF gateways. If a TDF domain is not specified, then the information for all domains for one or more TDF gateways is displayed.

Options

none—(Same as brief) Display the TDF domain service mode information in brief for all TDF gateways.

brief | detail—(Optional) Display the specified level of output.

domain-name *tdf-domain-name*—(Optional) Display service mode information for the specified TDF domain.

gateway *gateway*—(Optional) Display service mode information for the specified TDF gateway.

Required Privilege Level view

Related Documentation

- show unified-edge tdf service-mode on page 690

List of Sample Output

show unified-edge tdf domain service-mode brief on page 682
show unified-edge tdf domain service-mode detail on page 682

Output Fields Table 51 on page 681 lists the output fields for the **show unified-edge tdf domain service-mode** command. Output fields are listed in the approximate order in which they appear.

Table 51: show unified-edge tdf domain service-mode Output Fields

Field Name	Field Description	Level of Output
Maintenance Mode	Phases applicable when the address pool is in maintenance mode. • **MM - Active Phase**—All the attributes of the address pool can be modified. • **MM - In/Out Phase**—Only the non-maintenance mode attributes of the address pool can be modified.	None specified
Gateway Name	Name of the TDF gateway.	None specified

Copyright © 2018, Juniper Networks, Inc.

Table 51: show unified-edge tdf domain service-mode Output Fields (continued)

Field Name	Field Description	Level of Output
Gateway	Name of the TDF gateway.	**detail**
TDF domain Name	Name of the TDF domain.	All levels
Service Mode	Service mode for the TDF gateway: • **Operational**—Gateway is in operational mode. • **Maintenance**—Gateway is in maintenance mode.	All levels

Sample Output

show unified-edge tdf domain service-mode brief

```
user@host> show unified-edge tdf domain service-mode brief
Maintenance Mode
    MM Active Phase - System is ready to accept configuration changes for all
                      attributes of this object and its sub-hierarchies.
    MM In/Out Phase - System is ready to accept configuration changes only for
                      non-maintenance mode attributes of this object and
                      its sub-hierarchies.

TDF domain Name               Gateway Name                    Service Mode

jnpr-sunnyvale                  TDF                             Operational
jnpr-toxin                      TDF                             Operational
zoo                             TDF1                            Maintenance -
Active Phase
```

show unified-edge tdf domain service-mode detail

```
user@host> show unified-edge tdf domain service-mode detail
Gateway: TDF
TDF domain Name        : jnpr-sunnyvale
Service Mode    : Operational

TDF domain Name        : jnpr-toxin
Service Mode    : Operational
Gateway: TDF1

TDF domain Name        : zoo
Service Mode    : Maintenance - Active Phase
```


Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf domain statistics

Syntax

```
show unified-edge tdf domain statistics
<domain-name domain-name>
<gateway gateway>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display statistics for one or more domains in a TDF gateway. If a TDF gateway is not specified, then statistics for all TDF gateways are displayed.

Options

none—Display statistics for all domains for all TDF gateways.

domain-name *domain-name*—(Optional) Display the statistics for the specified TDF domain.

The output of the **show unified-edge tdf domain statistics** command is the same as the output of the **show unified-edge tdf statistics** command with the **tdf-domain** option.

gateway *gateway*—(Optional) Display the statistics for the specified TDF gateway.

Required Privilege Level view

Related Documentation

- clear unified-edge tdf statistics on page 542

List of Sample Output

show unified-edge tdf domain statistics gateway on page 685
show unified-edge tdf domain statistics domain-name on page 686

Output Fields Table 52 on page 683 lists the output fields for the **show unified-edge tdf domain statistics** command. Output fields are listed in the approximate order in which they appear.

Table 52: show unified-edge tdf domain statistics Output Fields

Field Name	Field Description
Gateway	Name of the TDF gateway.
Control Plane Statistics	
Subscriber attach attempts	Number of attempted session establishments and number of successful session establishments (**Success**).
TDF Time of day initiated update attempts	Number of attempted activations of rules based on time of day settings and number of successful activations (**Success**).

Copyright © 2018, Juniper Networks, Inc.

Table 52: show unified-edge tdf domain statistics Output Fields (continued)

Field Name	Field Description
TDF initiated subscriber detach attempts	Number of attempted subscriber session detachments initiated by the TDF.
PCRF initiated subscriber detach attempts	Number of attempted subscriber session detachments initiated by the PCRF.
Peer initiated subscriber detach attempts	Number of attempted subscriber session detachments initiated by the peer.
Subscriber attach failures by cause	Number of session establishments that failed: • **System failure** • **No resources** • **Policy denied** • **Service denied** • **Others**
Rejects due to early CAC	Number of subscriber sessions rejected due to early call admission control (CAC) for the TDF gateway.
Policy statistics	
Subscriber session activation attempts	Number of subscriber session activations attempted. In addition, the number of successful subscriber session establishments (**Success**) is displayed.
TDF initiated modification attempts	Number of session modifications initiated by TDF gateway. In addition, the number session modifications that were successful (**Success**) is displayed.
PCRF initiated modification attempts	Number of session modifications initiated by the policy and charging rules function (PCRF). In addition, the number of modifications that were successful (**Success**) is displayed.
TDF initiated session deactivations	Number of subscriber session deactivations initiated by the TDF gateway.
PCRF initiated session deactivations	Number of subscriber session deactivations initiated by the PCRF.

Copyright © 2018, Juniper Networks, Inc.

Table 52: show unified-edge tdf domain statistics Output Fields (continued)

Field Name	Field Description
Modification event reason	The number of Gx modifications for each event reason: • **Application Start** • **Application Stop**
Failure Statistics	• **Session terminations due to unreachable PCRF**—Number of sessions terminated because the PCRF was unreachable. • **Session terminations due to PCRF restart**—Number of sessions terminated because the PCRF was restarted. • **Rule Validation Failures**—Number of sessions terminated because the validation of rules failed.
PCC Rule Statistics	• **Dynamic rule activations**—Number of dynamic rule activations and deactivations (**Deactivations**). • **Static rule activations**—Number of static rule activations and deactivations (**Deactivations**). • **Dynamic rule modifications**—Number of dynamic rule modifications.
PCC Rule Failure Statistics	• **Rule update failure**—Number of rules that cannot be updated.
ePCC/ADC Rule Statistics	• **Dynamic rule activations**—Number of dynamic rule activations and deactivations (**Deactivations**). • **Static rule activations**—Number of static rule activations and deactivations (**Deactivations**). • **Dynamic rule modifications**—Number of dynamic rule modifications.
ePCC/ADC Rule Failure Statistics	• **Rule update failure**—Number of rules that cannot be updated.

Sample Output

show unified-edge tdf domain statistics gateway

```
user@host> show unified-edge tdf domain statistics gateway tdf
Gateway: TDF
Control Plane Statistics:
    Subscriber attach attempts:                0     Success: 0
    TDF Time of day initiated update attempts: 0     Success: 0
    TDF initiated subscriber detach attempts:  0
    PCRF initiated subscriber detach attempts: 0
    Peer initiated subscriber detach attempts: 0
    Subscriber attach failures by cause:
       System failure:      0
       No resources:        0
       Service denied:      0
       Policy denied:       0
       Others:              0
    Rejects due to early CAC: 0
Policy Statistics:
```

Copyright © 2018, Juniper Networks, Inc.

```
   Subscriber session activation attempts:     0     Success: 0
   TDF initiated modification attempts:        0     Success: 0
   PCRF initiated modification attempts:       0     Success: 0
   TDF initiated session deactivations:        0
   PCRF initiated session deactivations:       0
 Modification Event Reason:
      Application Start:   0
      Application Stop:    0
 Failure Statistics:
      Session terminations due to unreachable PCRF:  0
      Session terminations due to PCRF restart:      0
      Rule validation failures:                      0
 PCC Rule Statistics:
      Dynamic rule activations:     0      Deactivations:   0
      Static rules activations:     0      Deactivations:   0
      Dynamic rule modifications:   0
 PCC Rule Failure Statistics:
      Rule update failure:                 0
 ePCC/ADC Rule Statistics:
      Dynamic rule activations:     0      Deactivations:   0
      Static rules activations:     0      Deactivations:   0
      Dynamic rule modifications:   0
 ePCC/ADC Rule Failure Statistics:
      Rule update failure:                 0
```

show unified-edge tdf domain statistics domain-name

```
user@host> show unified-edge tdf domain statistics domain-name domain1
```

```
domain-name domain1
Gateway: TDF
Control Plane Statistics:
    Subscriber attach attempts:                 0     Success: 0
    TDF Time of day initiated update attempts:  0     Success: 0
    TDF initiated subscriber detach attempts:   0
    PCRF initiated subscriber detach attempts:  0
    Peer initiated subscriber detach attempts:  0
    Subscriber attach failures by cause:
       System failure:      0
       No resources:        0
       Service denied:      0
       Policy denied:       0
       Others:              0
Policy Statistics:
    Subscriber session activation attempts:     0     Success: 0
    TDF initiated modification attempts:        0     Success: 0
    PCRF initiated modification attempts:       0     Success: 0
    TDF initiated session deactivations:        0
    PCRF initiated session deactivations:       0
  Modification Event Reason:
       Application Start:   0
       Application Stop:    0
  Failure Statistics:
       Session terminations due to unreachable PCRF:  0
       Session terminations due to PCRF restart:      0
       Rule validation failures:                      0
  PCC Rule Statistics:
       Dynamic rule activations:     0      Deactivations:   0
       Static rules activations:     0      Deactivations:   0
```


Copyright © 2018, Juniper Networks, Inc.

```
     Dynamic rule modifications:   0
PCC Rule Failure Statistics:
     Rule update failure:                  0
ePCC/ADC Rule Statistics:
     Dynamic rule activations:     0      Deactivations:   0
     Static rules activations:     0      Deactivations:   0
     Dynamic rule modifications:   0
ePCC/ADC Rule Failure Statistics:
     Rule update failure:                  0
```

Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf resource-manager clients

Syntax

show unified-edge tdf resource-manager clients
<gateway *gateway*>

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Display information about the resource management clients (the session Dense Port Concentrators [DPCs] and interface DPCs and Modular Port Concentrators [MPCs]) on one or more TDF gateways. If a TDF gateway is not specified, then information for all TDF gateways is displayed.

Options

none—Display information for all TDF gateways.

gateway *gateway-name*—(Optional) Display information for the specified TDF gateway.

Required Privilege Level

view

Related Documentation

- show unified-edge tdf subscribers on page 703
- show unified-edge tdf system interfaces on page 717

List of Sample Output

show unified-edge tdf resource-manager clients on page 689
show unified-edge tdf resource-manager clients gateway on page 689

Output Fields

Table 53 on page 688 lists the output fields for the **show unified-edge gateways tdf resource-manager clients** command. Output fields are listed in the approximate order in which they appear.

Table 53: show unified-edge tdf resource-manager clients Output Fields

Field Name	Field Description
Client	Name of the resource manager client slot identified by the FPC and PIC slot numbers; for example, pfe-1/2/0 or ms-/7/0/0.
State	Resource manager client state. **In-Service** means that the client can handle session creation requests.
Role	Role of the resource manager client slot: • **Primary**—The resource manager client is a primary member. • **Secondary**—The resource manager client is a secondary or backup member.
Client type	Type of resource manager client: • **Session PIC**—Session PIC client used for the mobile control plane in the TDF gateway. • **Service PIC**—services PIC used for anchoring services-related subscriber sessions in the TDF gateway.

Copyright © 2018, Juniper Networks, Inc.

Table 53: show unified-edge tdf resource-manager clients Output Fields (continued)

Field Name	Field Description
Gateway	Name of the TDF gateway to which the resource manager client belongs.

Sample Output

show unified-edge tdf resource-manager clients

```
user@host> show unified-edge tdf resource-manager clients
Client      State          Redundancy role Client type Gateway
ms-2/0/0    In-Service     Primary         Service-PIC TDF
ms-2/1/0    In-Service     Secondary       Service-PIC TDF
ms-3/0/0    In-Service     Primary         Service-PIC TDF
ms-3/1/0    In-Service     Primary         Service-PIC TDF
ms-5/0/0    In-Service     Primary         Session-PIC TDF
ms-5/1/0    In-Service     Secondary       Session-PIC TDF
```

show unified-edge tdf resource-manager clients gateway

```
user@host> show unified-edge tdf resource-manager clients gateway TDF
Client      State          Redundancy role Client type Gateway
ms-3/0/0    In-Service     Secondary       Session-PIC TDF
ms-3/1/0    In-Service     Primary         Session-PIC TDF
ms-3/2/0    In-Service     Secondary       Service-PIC TDF
ms-3/3/0    In-Service     Primary         Service-PIC TDF
```

Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf service-mode

Syntax

```
show unified-edge tdf service-mode
<brief | detail>
<domain-name tdf-domain-name>
<gateway gateway-name>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display service mode information for one or more TDF gateways. If a TDF gateway is not specified, then service mode information for all the TDF gateways is displayed.

Options

none—(Same as brief) Display service mode information in brief for all TDF gateways.

brief | detail—(Optional) Display the specified level of output.

tdf-domain *domain-name*—(Optional) Display service mode information for the specified TDF domain.

The output of the **show unified-edge tdf service-mode** command with the **tdf-domain** option is the same as the output of the **show unified-edge tdf domain service-mode** command.

gateway *gateway-name*—(Optional) Display service mode information for the specified TDF gateway.

Required Privilege Level view

Related Documentation

- show unified-edge tdf domain service-mode on page 681

List of Sample Output

show unified-edge tdf service-mode brief on page 691
show unified-edge tdf service-mode detail on page 691

Output Fields Table 54 on page 690 lists the output fields for the **show unified-edge tdf service-mode** command. Output fields are listed in the approximate order in which they appear.

Table 54: show unified-edge tdf service-mode Output Fields

Field Name	Field Description	Level of Output
Maintenance Mode	Phases applicable when the TDF domain is in maintenance mode. • **MM - Active Phase**—All the attributes of the address pool can be modified. • **MM - In/Out Phase**—Only the non-maintenance mode attributes of the address pool can be modified.	none
Gateway Name	Name of the TDF gateway.	none

Copyright © 2018, Juniper Networks, Inc.

Table 54: show unified-edge tdf service-mode Output Fields (continued)

Field Name	Field Description	Level of Output
Service Mode	Service mode for the TDF gateway: • **Operational**—Gateway is in operational mode. • **Maintenance**—Gateway is in maintenance mode.	All levels

Sample Output

show unified-edge tdf service-mode brief

```
user@host> show unified-edge tdf service-mode brief
Maintenance Mode
    MM Active Phase - System is ready to accept configuration changes for all
                      attributes of this object and its sub-hierarchies.
    MM In/Out Phase - System is ready to accept configuration changes only for
                      non-maintenance mode attributes of this object and
                      its sub-hierarchies.

Gateway Name                    Service Mode

TDF                             Operational
TDF2                            Operational
```

show unified-edge tdf service-mode detail

```
user@host> show unified-edge tdf service-mode detail
Service Mode Status
Gateway Name    : PGW
Service Mode    : Operational
Service Mode Status
Gateway Name    : PGW2
Service Mode    : Operational
```

Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf statistics

Syntax

```
show unified-edge tdf statistics
<domain domain-name>
<gateway gateway>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display statistics for one or more TDF gateways. If a TDF gateway is not specified, then statistics for all TDF gateways are displayed.

Options

none—Display statistics for all TDF gateways.

domain *domain-name*—(Optional) Display statistics for the specified TDF domain.

> The output of the **show unified-edge tdf statistics** command with the **domain *domain-name*** option is the same as the output of the **show unified-edge tdf domain statistics** command.

gateway *gateway*—(Optional) Display statistics for the specified TDF gateway.

Required Privilege Level view

Related Documentation

- clear unified-edge tdf statistics on page 542
- show unified-edge tdf domain statistics on page 683
- IP-Based and IFL-Based TDF Subscribers Overview on page 88

List of Sample Output show unified-edge tdf statistics on page 696

Output Fields Table 55 on page 692 lists the output fields for the **show unified-edge tdf statistics** command. Output fields are listed in the approximate order in which they appear.

Table 55: show unified-edge tdf statistics Output Fields

Field Name	Field Description
Gateway	Name of the TDF gateway.
Control Plane Statistics	
Subscriber attach attempts	Number of attempted session establishments and number of successful session establishments for IP-based subscribers (**Success**).

Copyright © 2018, Juniper Networks, Inc.

Table 55: show unified-edge tdf statistics Output Fields (continued)

Field Name	Field Description
Peer initiated subscriber update attempts	Number of RADIUS client attempts to update the subscriber context of an IP-based subscriber.
TDF Time of day initiated update attempts	Number of attempted activations, deactivations, and revalidations of PCC rules and revalidations of the PCEF session for the time-of-day feature, and number of successful attempts (**Success**).
TDF initiated update attempts	Number of TDF gateway attempts to update an IFL-based subscriber context as a result of access interfaces going up or down, or as a result of access interfaces being added to or deleted from the subscriber configuration.
TDF initiated subscriber detach attempts	Number of attempted subscriber session detachments initiated by the TDF gateway.
Policy Server initiated subscriber detach attempts	Number of attempted subscriber session detachments initiated by the policy server.
Peer initiated subscriber detach attempts	Number of attempted IP-based subscriber session detachments initiated by the RADIUS client. For IFL-based subscribers, 0 is displayed.
Subscriber attach failures by cause	Number of session establishments that failed: • **System failure** • **No resources** • **Service denied** • **Policy denied** • **Service PIC NACK** • **Others**
Rejects due to early CAC	Number of rejects on the TDF gateway caused by early CAC.
Subscriber detach by cause	Number of subscriber detachments for the following cause: • **service PIC NACK**
Policy statistics	
Subscriber session activation attempts	Number of subscriber session activations attempted. In addition, the number of successful subscriber session establishments (**Success**) is displayed.
TDF initiated modification attempts	Number of session modifications initiated by TDF gateway. In addition, the number of session modifications that were successful (**Success**) is displayed.

Copyright © 2018, Juniper Networks, Inc.

Table 55: show unified-edge tdf statistics Output Fields (continued)

Field Name	Field Description
Policy Server initiated modification attempts	Number of session modifications initiated by the policy server. In addition, the number of modifications that were successful (**Success**) is displayed.
TDF initiated session deactivations	Number of subscriber session deactivations initiated by the TDF gateway.
Policy Server initiated session deactivations	Number of subscriber session deactivations initiated by the policy server.
Modification event reason	Number of Gx modifications for each event reason: • **Application Start** • **Application Stop** • **Revalidation**—PCEF re-requested PCC rules from the PCRF.
Failure Statistics	• **Session terminations due to unreachable policy server**—Number of sessions terminated because the policy server was unreachable. • **Session terminations due to PCRF restart**—Number of sessions terminated because the PCRF was restarted. • **Rule Validation Failures**—Number of sessions terminated because the validation of rules failed.
PCC Rule Statistics	• **Dynamic rule activations**—Number of dynamic rule activations and deactivations (**Deactivations**). • **Static rules activations**—Number of static rule activations and deactivations (**Deactivations**). • **Dynamic rule modifications**—Number of dynamic rule modifications.
PCC Rule Failure Statistics	• **Rule update failure**—Number of rules that cannot be updated.
ePCC/ADC Rule Statistics	• **Dynamic rule activations**—Number of dynamic rule activations and deactivations (**Deactivations**). • **Static rules activations**—Number of static rule activations and deactivations (**Deactivations**). • **Dynamic rule modifications**—Number of dynamic rule modifications.
ePCC/ADC Rule Failure Statistics	• **Rule update failure**—Number of rules that cannot be updated.
Usage Monitoring Statistics	
UMI AVP validation failures	Number of times that decoding fails for any of the grouped AVPs that belong to the Usage Monitoring Information, such as the Monitoring key, Monitoring Level, and Granted Service Unit AVPs.

Copyright © 2018, Juniper Networks, Inc.

Table 55: show unified-edge tdf statistics Output Fields (continued)

Field Name	Field Description
Session Level	The following information about usage monitoring at the session level is displayed: • **UM activations**—Number of session-level monitoring keys that the TDF gateway has activated. • **UM update quota attempts**—Number of times the PCRF has attempted to update the quota for a session-level monitoring key. The number of reports that the TDF gateway sent as a result of the update quota attempts is shown in **Stats report sent**. • **UM implicit deactivations**—Number of times that a session-level monitoring key has been implicitly deactivated by the TDF gateway. For example, this happens if a monitoring key does not receive additional quota after a threshold has been reached. • **UM explicit deactivations**—Number of session-level monitoring key deactivations that the TDF gateway has received from the PCRF. The number of reports that the TDF gateway sent as a result of the deactivations is shown in **Stats report sent**. • **Usage report request received**—Number of requests for session-level usage reports that the TDF gateway has received from the PCRF. The number of reports that the TDF gateway sent as a result of the requests is shown in **Stats report sent**. • **UM threshold hit**—Number of times that a threshold for a session-level monitoring key has been reached. The number of reports that the TDF gateway sent as a result of the threshold being reached is shown in **Stats report sent**.
Rule Level	The following information about usage monitoring at the rule level is displayed: • **UM activations**—Number of rule-level monitoring keys that the TDF gateway has activated. • **UM update quota attempts**—Number of times the PCRF has attempted to update the quota for a rule-level monitoring key. The number of reports that the TDF gateway sent as a result of the update quota attempts is shown in **Stats report sent**. • **UM implicit deactivations**—Number of times that a rule-level monitoring key has been implicitly deactivated by the TDF gateway. For example, this happens if a monitoring key does not receive additional quota after a threshold has been reached. • **UM explicit deactivations**—Number of rule-level monitoring key deactivations that the TDF gateway has received from the PCRF. The number of reports that the TDF gateway sent as a result of the deactivations is shown in **Stats report sent**. • **Usage report request received**—Number of requests for rule-level usage reports that the TDF gateway has received from the PCRF. The number of reports that the TDF gateway sent as a result of the requests is shown in **Stats report sent**. • **UM threshold hit**—Number of times that a threshold for a rule-level monitoring key has been reached. The number of reports that the TDF gateway sent as a result of the threshold being reached is shown in **Stats report sent**. • **UM with no rule reference**—Number of rule-level monitoring keys received by the TDF gateway that had no rule referring to it. These keys are not activated.
Service plane statistics	
Subscriber detach attempts (NACK) by cause	Number of service PIC messages to session PIC indicating that subscriber creation or modification failed for the following causes: • **Memory watermark high threshold hit** • **Memory watermark critical threshold hit** • **Memory alloc failure** • **Subscriber lookup failure** • **Others**

Copyright © 2018, Juniper Networks, Inc.

Table 55: show unified-edge tdf statistics Output Fields (continued)

Field Name	Field Description
Data plane statistics	
Subscriber Stats	The following information about packets processed by the data plane for subscribers connected to the TDF domains in the TDF gateway is displayed: • **Uplink**—Statistics for traffic in the uplink direction from the TDF gateway to the PDN (Internet). • **Downlink**—Statistics for traffic in the downlink direction from the PDN (Internet) to the TDF gateway. • **Packets**—Number of packets forwarded in the uplink direction and in the downlink direction. • **Bytes**—Number of bytes forwarded in the uplink direction and in the downlink direction. • **Dropped Packets**—Number of packets dropped in the uplink direction and in the downlink direction. • **Dropped Bytes**—Number of bytes dropped in the uplink direction and in the downlink direction.
Non Subscriber Stats	The following information about packets processed by the data plane for traffic that does not belong to subscribers connected to the TDF domains in the TDF gateway is displayed: • **Uplink**—Statistics for traffic in the uplink direction from the TDF gateway to the PDN (Internet). • **Downlink**—Statistics for traffic in the downlink direction from the PDN (Internet) to the TDF gateway. • **Packets**—Number of packets sent in the uplink direction and in the downlink direction. • **Bytes**—Number of bytes sent in the uplink direction and in the downlink direction. • **Dropped Packets**—Number of packets dropped in the uplink direction and in the downlink direction. • **Dropped Bytes**—Number of bytes dropped in the uplink direction and in the downlink direction.

Sample Output

show unified-edge tdf statistics

```
user@host> show unified-edge tdf statistics
Gateway: TDF
Control Plane Statistics:
    Subscriber attach attempts:                0     Success: 0
    Peer initiated subscriber update attempts:  0     Success: 0
    TDF Time of day initiated update attempts:  0     Success: 0
    TDF initiated update attempts:             0     Success: 0
    TDF initiated subscriber detach attempts:   0
    Policy Server initiated subscriber detach attempts:  0
    Peer initiated subscriber detach attempts:  0
    Subscriber attach failures by cause:
       System failure:      0
       No resources:        0
       Service denied:      0
       Policy denied:       0
       Service PIC NACK:    0
       Others:              0
    Rejects due to early CAC:   0
    Subscriber detach by cause:
       service PIC NACK: 0
  Policy Statistics:
    Subscriber session activation attempts:     0     Success: 0
    TDF initiated modification attempts:        0     Success: 0
    Policy Server initiated modification attempts:       0     Success: 0
```


Copyright © 2018, Juniper Networks, Inc.

```
    TDF initiated session deactivations:        0
    Policy Server initiated session deactivations:       0
  Modification Event Reason:
       Application Start:                0
       Application Stop:                 0
       Revalidation:                     0
  Failure Statistics:
       Session terminations due to unreachable policy server: 0
       Session terminations due to PCRF restart:              0
       Rule validation failures:                              0
  PCC Rule Statistics:
       Dynamic rule activations:     0      Deactivations:   0
       Static rules activations:     0      Deactivations:   0
       Dynamic rule modifications:   0
  PCC Rule Failure Statistics:
       Rule update failure:                  0
  ePCC/ADC Rule Statistics:
       Dynamic rule activations:     0      Deactivations:   0
       Static rules activations:     0      Deactivations:   0
       Dynamic rule modifications:   0
  ePCC/ADC Rule Failure Statistics:
       Rule update failure:                  0
  Usage Monitoring Statistics:
       UMI AVP validation failures:   0
    Session Level:
         UM activations:               0
         UM update quota attempts:     0      Stats report sent: 0
         UM implicit deactivations:    0
         UM explicit deactivations:    0      Stats report sent: 0
         Usage report request received: 0     Stats report sent: 0
         UM threshold hit:             0      Stats report sent: 0
    Rule Level:
         UM activations:               0
         UM update quota attempts:     0      Stats report sent: 0
         UM implicit deactivations:    0
         UM explicit deactivations:    0      Stats report sent: 0
         Usage report request received: 0     Stats report sent: 0
         UM threshold hit:             0      Stats report sent: 0
         UM with no rule reference: 0

Service plane statistics:
   Subscriber detach attempts (NACK) by cause:
     Memory watermark high threshold hit:      0
     Memory watermark critical threshold hit:  0
     Memory alloc failure:                     0
     Subscriber lookup failure:                0
     Others:                                   0

Data plane statistics:

Subscriber Stats:
                      Uplink               Downlink
-------------------------------------------------------------------
    Packets          :0                   :0
    Bytes            :0                   :0
    Dropped Packets  :0                   :0
    Dropped Bytes    :0                   :0

Non Subscriber Stats:
                      Uplink               Downlink
```

```
------------------------------------------------------------------
    Packets          :0                    :0
    Bytes            :0                    :0
    Dropped Packets  :0                    :0
    Dropped Bytes    :0                    :0
```


Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf status

Syntax

```
show unified-edge tdf status
<brief | detail | extensive>
<domain domain-name>
<fpc-slot fpc-slot>
<gateway gateway>
<pic-slot pic-slot>
<subscriber-state>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display status information, such as the number of subscribers, active sessions, and so on, for one or more TDF gateways. If a TDF gateway name is not specified, then the status information for all the TDF gateways is displayed.

Options

none—(Same as brief) Display the TDF gateway status information in brief for all TDF gateways.

brief | detail | extensive—(Optional) Display the specified level of output.

domain *domain-name*—(Optional) Display the status information for the specified TDF domain.

fpc-slot *fpc-slot*—(Optional) Display the status information for the specified FPC slot number.

gateway *gateway*—(Optional) Display the status information for the specified TDF gateway name.

pic-slot *pic-slot*—(Optional) Display the status information for the specified PIC slot number. You must first specify an FPC slot number before specifying the PIC slot number.

subscriber-state—(Optional) Display the status of the subscribers.

Required Privilege Level view

Related Documentation

- show unified-edge tdf aaa statistics on page 642
- IP-Based and IFL-Based TDF Subscribers Overview on page 88

List of Sample Output

show unified-edge tdf status brief on page 701
show unified-edge tdf status detail on page 701
show unified-edge tdf status subscriber-state on page 702

Copyright © 2018, Juniper Networks, Inc.

Output Fields Table 56 on page 700 lists the output fields for the **show unified-edge tdf status** command. Output fields are listed in the approximate order in which they appear.

Table 56: show unified-edge tdf status Output Fields

Field Name	Field Description	Level of Output
Gateway	Name of the TDF gateway.	All levels
Established	Number of established subscribers.	none with the **subscriber-state** option
Deleting	Number of subscribers that are being deleted.	none with the **subscriber-state** option

Control Plane	The following is displayed for the control plane:
	• **Active Subscribers**—Number of subscribers that are active in each of the following categories:
	  ◦ **IP Subscribers**
	  ◦ **IFL Subscribers**
		none
		brief

Service Plane	The following is displayed for the service plane:
	• **Active Subscribers**—Number of subscribers that are actively using services in each of the following categories:
	  ◦ **IP Subscribers**
	  ◦ **IFL Subscribers**
	• **Active Sessions**—Number of active subscriber sessions.
		none
		brief

CPU Load (%)	Percentage of the CPU load.	All levels
Memory Load (%)	Percentage of the memory load.	All levels
FPC SLOT	FPC slot number of the interface for which the status information is displayed.	**detail** **extensive**
PIC SLOT	PIC slot number of the FPC for which the status information is displayed.	**detail** **extensive**
Role	Role of the Packet Forwarding Engine, services PIC, or session PIC on the TDF gateway: • **Standalone** • **Primary**—Primary member. • **Secondary**—Secondary member.	**detail** **extensive**

Copyright © 2018, Juniper Networks, Inc.

Table 56: show unified-edge tdf status Output Fields (continued)

Field Name	Field Description	Level of Output
Type	Indicates whether the PIC is a Packet Forwarding Engine, a session PIC, or a services PIC.	**detail** **extensive**
Active Subscribers	Number of logged-in subscribers on the TDF gateway in each of the following categories: • **IP Subscribers** • **IFL Subscribers**	**brief** **detail** **extensive**
Delete Pending Subscribers	Number of pending subscribers that are being deleted on the TDF gateway in each of the following categories: • **IP Subscribers** • **IFL Subscribers**	**detail** **extensive**
Active Sessions	Number of logged-in sessions on the TDF gateway. NOTE: Active Sessions count may not match the output of the **show services session count** command. This is due to internal asynchronous message queues.	**detail** **extensive**

Sample Output

show unified-edge tdf status brief

```
user@host> show unified-edge tdf status brief
Gateway: TDF
    TDF gateway status:
    Control Plane:
        Active Subscribers                          :        0
            IP Subscribers                          :        0
            IFL Subscribers                         :        0
    Service Plane:
        Active Subscribers                          :        0
            IP Subscribers                          :        0
            IFL Subscribers                         :        0
        Active Sessions                             :        0
    CPU Load (%)                                    :        0
    Memory Load (%)                                 :        26
```

show unified-edge tdf status detail

```
user@host> show unified-edge tdf status detail
Gateway: TDF

    FPC SLOT: 0   PIC SLOT: 2
```

Copyright © 2018, Juniper Networks, Inc.

```
    Role                                        :       Primary
    Type                                        :       Session-PIC
    Active Subscribers                          :       0
        IP Subscribers                          :       0
        IFL Subscribers                         :       0
    CPU Load (%)                                :       0
    Memory Load (%)                             :       26

    FPC SLOT: 0   PIC SLOT: 3
    Role                                        :       Primary
    Type                                        :       Service-PIC
    Active Subscribers                          :       0
        IP Subscribers                          :       0
        IFL Subscribers                         :       0
    Delete Pending Subscribers                  :       0
        IP Subscribers                          :       0
        IFL Subscribers                         :       0
    Active Sessions                             :       0
    CPU Load (%)                                :       1
    Memory Load (%)                             :       12

    FPC SLOT: 1   PIC SLOT: 1
    Role                                        :       Secondary
    Type                                        :       Session-PIC
    Active Subscribers                          :       0
        IP Subscribers                          :       0
        IFL Subscribers                         :       0
    CPU Load (%)                                :       0
    Memory Load (%)                             :       26
```

show unified-edge tdf status subscriber-state

```
user@host> show unified-edge tdf status subscriber-state
```

```
show unified-edge tdf status subscriber-state
Gateway: TDF
    Established          :              1
    Deleting             :              0
```


Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf subscribers

Syntax

```
show unified-edge tdf subscribers
<brief | detail | extensive>
<business-subscribers>
<data-plane>
<domain domain-name>
<fpc-slot fpc-slot>
<gateway gateway>
<pdn-type (ipv4 | ipv4-v6 | ipv6)>
<pic-slot pic-slot>
<routing-instance routing-instance>
<stuck>
<subscriber-name subscriber-name>
<v4-addr v4-addr>
<v6-addr v6-addr>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display the subscriber information for one or more TDF gateways. If a TDF gateway is not specified, then subscriber information for all TDF gateways is displayed.

Options

none—(Same as brief) Display subscriber information in brief for all TDF gateways.

brief | detail | extensive—(Optional) Display the specified level of output.

business-subscribers—(Optional) Display subscriber information for only enterprise business subscribers (subscribers whose IPv4 prefix length is less than 32).

data-plane—(Optional) Display subscriber information for the data plane.

domain *domain-name*—(Optional) Display subscriber information for the specified TDF domain.

fpc-slot *fpc-slot*—(Optional) Display subscriber information for the specified FPC slot number.

gateway *gateway*—(Optional) Display subscriber information for the specified TDF gateway.

pdn-type (ipv4 | ipv4-v6 | ipv6)—(Optional) Display subscriber information according to the type of Packet Data Network (PDN): IPv4, IPv6, and both IPv4 and IPv6.

pic-slot *pic-slot*—(Optional) Display subscriber information for the specified PIC slot number. You must first specify an FPC slot number before specifying the PIC slot number.

routing-instance *routing-instance*—(Optional) Display subscriber information for the specified routing instance.

Copyright © 2018, Juniper Networks, Inc.

stuck—(Optional) Display subscribers for the TDF gateway that are not logged in successfully and are in a blocked state.

subscriber-name *subscriber-name*—(Optional) Display subscriber information for the specified IFL-based subscriber.

v4-addr *v4-addr*—(Optional) Display subscriber information for the specified IPv4 address of the subscriber's user equipment.

v6-addr *v6-addr*—(Optional) Display subscriber information for the specified IPv6 address of the subscriber's user equipment.

Required Privilege Level view

Related Documentation

- show unified-edge tdf statistics on page 692
- clear unified-edge tdf subscribers on page 543
- IP-Based and IFL-Based TDF Subscribers Overview on page 88

List of Sample Output

show unified-edge tdf subscribers (IP-Based Subscriber) on page 712
show unified-edge tdf subscribers (IFL-Based Subscriber) on page 712
show unified-edge tdf subscribers extensive on page 712
show unified-edge tdf subscribers detail on page 714
show unified-edge tdf subscribers data-plane on page 715

Output Fields Table 57 on page 704 lists the output fields for the **show unified-edge tdf subscribers** command. Output fields are listed in the approximate order in which they appear.

Table 57: show unified-edge tdf subscribers Output Fields

Field Name	Field Description	Level of Output
Gateway	Name of the TDF gateway.	All levels none
MSISDN/Name	MSISDN number of the IP-based subscriber's user equipment.	**brief** none
V4 Address	IPv4 address of the IP-based subscriber.	**brief** none
V6 Address	IPv6 address, if any, of the IP-based subscriber. Otherwise, **None** is displayed.	**brief** none
NAS-IP-Address	IP address to be used for the NAS IP address attribute of the IP-based subscriber when sending the requests to the RADIUS server.	**brief** none

Copyright © 2018, Juniper Networks, Inc.

Table 57: show unified-edge tdf subscribers Output Fields (continued)

Field Name	Field Description	Level of Output
Domain	TDF domain, on the TDF gateway, to which the subscriber is attached.	**brief** none
IFL-Subscriber-Name	Name of the IFL-based subscriber.	**brief** none
Subscriber Information		
Subscriber Type	Type of subscriber: • **IFL**—Interface-based subscriber. • **IP**—IP-based subscriber.	**detail** **extensive**
IMSI	IMSI of the IP-based subscriber's user equipment.	**detail** **extensive** none
IMEI	International Mobile Station Equipment Identity (IMEI) of the IP-based subscriber's user equipment.	**detail** **extensive**
MSISDN/Username	MSISDN number of the IP-based subscriber's user equipment.	**detail** **extensive**
Subscriber Name	Name of the IFL-based subscriber.	**detail** **extensive**
State	State of the subscriber session on the signaling plane.	**detail** **extensive**
Session Duration	Duration of the PDP session.	**detail** **extensive**
Domain	Name of the TDF domain that is used to establish the session on the TDF gateway for the subscriber.	**detail** **extensive**
Data VRF	Name of the data plane VRF.	**detail** **extensive**
TDF domain Name	Unique identifier that denotes the TDF domain to be used for the subscriber's session. This setting is applicable only when the domain specified in the Create Session Request message from the subscriber is virtual.	**detail** **extensive**

Copyright © 2018, Juniper Networks, Inc.

Table 57: show unified-edge tdf subscribers Output Fields (continued)

Field Name	Field Description	Level of Output
NAS-IP-Addr	IP address to be used for the NAS IP address attribute of the IP-based subscriber when sending the requests to the RADIUS server.	**detail** **extensive**
APN name	Name of the APN for the IP-based subscriber that is denoted by a unique identifier.	**detail** **extensive**
V4 Address	IPv4 address of the IP-based subscriber.	**detail** **extensive**
V4 Prefix Length	IPv4 prefix length of the IP-based subscriber's IPv4 address. This is displayed only if the length is less than 32.	**detail** **extensive** **data-plane**
V6 Address	IPv6 address of the IP-based subscriber, if any. Otherwise, **None** is displayed.	**detail** **extensive**
V6 Prefix Length	IPv6 prefix length of the IP-based subscriber's IPv6 address.	**detail**
Session PIC	FPC and PIC slots for the session PIC on which the subscriber control session is present.	**detail** **extensive**
Service PIC	FPC and PIC slots for the service PIC on which the subscriber control session is present.	**detail** **extensive**

Copyright © 2018, Juniper Networks, Inc.

Table 57: show unified-edge tdf subscribers Output Fields (continued)

Field Name	Field Description	Level of Output
PCRF Event Triggers	Policy and charging rules function (PCRF) event triggers, if any. If no trigger is configured, **None** is displayed. The notation used for the event triggers displayed in the output and the corresponding event triggers as per the 3GPP specifications are as follows: • **SGSN**—SGSN CHANGE (0) • **QoS**—QOS CHANGE (1) • **RAT**—RAT CHANGE (2) • **TFT**—TFT CHANGE (3) • **PLMN**—PLMN CHANGE (4) • **BL**—subscriber LOSS (5) • **BR**—subscriber RECOVERY (6) • **IPCAN**—IPCAN CHANGE (7) • **EAUTH**—EXCEEDING AUTH (11) • **RAI**—RAI CHANGE (12) • **ULI**—ULI CHANGE (13) • **NET**—NO EVENT TRIGGERS (14) • **OOC**—OUT OF CREDIT (15) • **ROC**—REALLOCATION OF CREDIT (16) • **REVALIDATION_TIMEOUT**—REVALIDATION TIMEOUT (17) • **IP ALLOC**—UE_IP_ADDRESS_ALLOCATE (18) • **IP RELEASE**—UE_IP_ADDRESS_RELEASE (19) • **DEFAULT QoS**—DEFAULT QoS (20) • **GW**—AN GW CHANGE (21) • **RA**—RESOURCE_ALLOCATION (22) • **RM**—RESOURCE_MODIFICATION (23) • **TRACE**—PGW TRACE CONTROL (24) • **TZ** —UE_TZ_CHANGE (25) • **TAI**—TAI CHANGE (26) • **ECGI**—ECGI CHANGE (27) • **CCE**—CHARGING CORRELATION EXCHANGE (28) • **AMBR**—AMBR CHANGE (29) • **UCIC**—USR CSG INFO CHANGE (30) • **QMF**—QoS MODIFICATION FAILURE (31) • **UR**—USAGE REPORT (33)	**detail** **extensive**
Revalidation due in	Time remaining in days, hours, minutes, and seconds until PCEF session revalidation takes place if the **REVALIDATION_TIMEOUT** event trigger is armed. Otherwise **N/A** is displayed.	**detail** **extensive**
Idle Timeout	Idle timeout for the session, in minutes.	**detail** **extensive**
Subscriber MBR	TDF subscriber maximum bit rate (MBR) for uplink and downlink traffic. Uplink traffic originates from the subscriber towards the public data network (PDN), and downlink traffic comes from the PDN and is destined for the subscriber.	**detail** **extensive**

Copyright © 2018, Juniper Networks, Inc.

Table 57: show unified-edge tdf subscribers Output Fields (continued)

Field Name	Field Description	Level of Output
Subscriber burst	TDF subscriber burst size configured for uplink and downlink traffic. Uplink traffic originates from the subscriber towards the PDN, and downlink traffic comes from the PDN and is destined for the subscriber.	**detail** **extensive**
Access IFL List	The following is displayed for each interface assigned to an IFL-based subscriber: • **Name**—Name of the interface. • **Index**—Index number of the interface. • **State**—Operational state of the interface: **Active** or **Inactive**.	
PCC Profile Name	Name of the PCEF profile that is assigned to the subscriber.	**detail** **extensive**

Usage Monitoring Information	The following is displayed for each monitoring key, which corresponds to a data set that is being monitored for the subscriber:
	• **Monitoring Key**—Identifier for the monitoring key.
	• **Level**—Indication of whether the monitoring key applies to particular PCC rules (Rule) or to the entire TDF subscriber session (Session).
	• **Status**—Indication of whether monitoring with the key is active or inactive.
	• **Total Available Quota**—Volume and time quota sent from the PCRF to indicate when a report should be sent to the PCRF. A value of zero indicates that the field is not applicable to the key.
	  ◦ **Input**—Uplink traffic volume quota.
	  ◦ **Output**—Downlink traffic volume quota.
	  ◦ **Total**—Uplink and downlink traffic volume quota.
	  ◦ **Time**—Time quota, in seconds.
		detail
		extensive

Copyright © 2018, Juniper Networks, Inc.

Table 57: show unified-edge tdf subscribers Output Fields (continued)

Field Name	Field Description	Level of Output
PCC Rule Information		**detail** **extensive**

Copyright © 2018, Juniper Networks, Inc.

Table 57: show unified-edge tdf subscribers Output Fields (continued)

Field Name	Field Description	Level of Output

	NOTE: Both ePCC rules and PCC rules appear under **PCC Rule Information**. Fields that apply only to ePCC rules are identified in the description.
	
	The following information for each PCC or ePCC rule is displayed per subscriber:
	
	• **Rule Name**—Name of the rule. In addition, the following is displayed:
	  • **Type**—Rrule type: **Static** or **Dynamic**.
	  • **Associated Rule Base**—Rule set with which the rule is associated, if any.
	  • **Precedence**—Rule precedence, which defines the order in which the policy is applied for incoming or outgoing packets; the lower the number, the higher its precedence.
	  • **Activation due in**—Day, time, or both at which the rule is scheduled for activation for the subscriber. If activation/deactivation settings have not been applied to the rule, then **N/A** appears.
	  • **Deactivation due in**—Day, time, or both at which the rule is scheduled for deactivation for the subscriber. If activation/deactivation settings have not been applied to the rule, then **N/A** appears.
	  • **Status**—Rule status: **Initialized**, **Active**, **Inactive**, or **Removal Pending**.
	  • **Application Id**—(ePCC rules only) Name of the application identification parameter associated with the rule.
	  • **Application Id Base**–(ePCC rules only) Name of the base application that serves as the primary application identification service if a group or cluster are configured.
	  • **Mute Notification**—(ePCC rules only) Whether the Mute-Notification AVP is included in the rule.
	• **QoS Parameters**—The following QoS attributes are displayed for each rule per subscriber:
	  • **MBR Uplink (kbps)**—Maximum bit rate (MBR) in the uplink direction, in kbps. Identifier.
	  • **MBR Downlink (kbps)**—MBR in the downlink direction, in kbps.
	  • **Burst size Uplink (bytes)**—TDF domain's default TDF subscriber burst size configured for uplink traffic, in bytes.
	  • **Burst size Downlink (bytes)**—TDF domain's default TDF subscriber burst size configured for downlink traffic, in bytes. Uplink traffic originates from the subscriber towards the public data network (PDN), and downlink traffic comes from the PDN and is destined for the subscriber.
	• **Charging Attributes**—The following charging attributes are displayed for each rule per subscriber:
	  • **Rating Group**—Rating group for the rule.
	  • **Service Id**—Service ID for the rule.
	  • **Gating Status**—Whether the flow is enabled or not. One of the following:
	  • **enable-uplink**
	  • **enable-downlink**
	  • **enable-both**
	  • **disable-both**
	  • **AF Charging Id**—Application function record information, which contains an octet string and the charging ID.
	  • **Charging Method**—Charging method for the rule (**none**, **offline**, **offline-online**, or **online**).
	  • **Metering Method**—Charging metering method for the rule:
	  • **Time**—Time based.	

Copyright © 2018, Juniper Networks, Inc.

Table 57: show unified-edge tdf subscribers Output Fields (continued)

Field Name	Field Description	Level of Output
	• **Volume**—Volume based. • **Volume-Time**—Both volume and time based. • **None**—No metering. • **Usage Monitoring Key**—Monitoring key that is associated with the rule. • **Services Attributes**—The following information about resource management and steering is displayed for the subscribers connected to the TDF gateway or the TDF domain: • **Steering IP**—IPv4 or IPv6 address for HTTP steering of the packets. • **Keep existing steering**—Whether existing steering is enabled or disabled. • **Service Chain VRF**—Routing instance for steering of packets. Use this to steer traffic to either a local service chain or external service chain. • **Forwarding Class**—Forwarding class that needs to be assigned to the packet. • **HCM ID**—Profile that identifies the HTTP header enrichment rules to apply. This action is restricted to PCC rules that are only matching HTTP-based applications. • **LRF ID**—Unique ID of the Location Retrieval Function • **Filter Attributes**—The following filter attributes are displayed per filter in each rule: • **Remote IP/Mask**—Remote IP address and subnet mask of the filter. • **Protocol**—Protocol configured for the filter. If all protocols are supported for the filter, **Any** is displayed. For the explanation of what the numbers represent, refer to the 3GPP specifications. • **Direction**—Direction in which the filter is applicable (**Downlink**, **Uplink**, or **Both**). • **Local Ports**—Local ports or port range for the filter. **Any** indicates that the filter does not restrict the local ports. • **Remote Ports**—Remote ports or port range for the filter. **Any** indicates that the filter does not restrict the remote ports. • **Application Name**—(ePCC rules only) Name of the predefined or custom application signature.	

Copyright © 2018, Juniper Networks, Inc.

Table 57: show unified-edge tdf subscribers Output Fields (continued)

Field Name	Field Description	Level of Output
Data Plane statistics	The following information about packets processed by the data plane for subscribers connected to the TDF domains in the TDF gateway: • **Subscriber-Name**—Name of the IFL-based subscriber. • **V4 Address**—IPv4 address of the IP-based subscriber. • **V6 Address**—IPv6 address of the IP-based subscriber. • **V6 Prefix Length**—IPv6 prefix length of the IP-based subscriber's IPv6 address. • **Vrf Id**—Name of the data plane VRF. • **Subscriber Stats**—Total statistics for the subscriber. • **Rule**—Statistics for traffic that was handled by the specified PCC rule. • **Uplink**—Statistics for traffic in the uplink direction from the TDF gateway to the PDN (Internet). • **Downlink**—Statistics for traffic in the downlink direction from the PDN (Internet) to the TDF gateway. • **Sessions**—Number of sessions in the uplink and downlink direction. • **Packets**—Number of packets forwarded in the uplink direction and in the downlink direction. • **Bytes**—Number of bytes forwarded in the uplink direction and in the downlink direction. • **Dropped Packets**—Number of packets dropped in the uplink direction and in the downlink direction. • **Dropped Bytes**—Number of bytes dropped in the uplink direction and in the downlink direction.	**data-plane** option

Sample Output

show unified-edge tdf subscribers (IP-Based Subscriber)

```
user@host> show unified-edge tdf subscribers

Gateway: TDF
   MSISDN/name       V4 Address      V6 Address          NAS-IP-Address  Domain
   att               192.0.2.11      None               198.51.100.123 domain1
```

show unified-edge tdf subscribers (IFL-Based Subscriber)

```
user@host> show unified-edge tdf subscribers

IFL-Subscriber-Name                                  Domain
   ifl-sub-radius-001                                domain-ifl-radius
   ifl-sub-static-001                                domain-ifl-static
```

show unified-edge tdf subscribers extensive

```
user@host> show unified-edge tdf subscribers extensive

Gateway: TDF

Subscriber Information:
     Subscriber Type : IFL
```


Copyright © 2018, Juniper Networks, Inc.

```
    Subscriber Name : IFL1
    State      : Established                    Session Duration: 000065 hrs
50 mins 15 secs
    Domain     : domain1
    Data VRF   : default
    Session PIC: 3 /0  (FPC/PIC)
    Service PIC: 3 /1  (FPC/PIC)
    PCRF Event Triggers : None
    Revalidation due in : N/A
    Subscriber MBR:   Uplink (kbps):  0            Downlink (kbps):  0
    Subscriber burst: Uplink (bytes): 0            Downlink (bytes): 0
    Access IFL List:          Name      (Index)      State
                        ge-1/1/8.0      (362  )      Active
                        ge-1/1/1.0      (361  )      Active
                        ge-1/0/9.0      (360  )      Active
   PCC Profile Name : pcef-prof-static
   PCC Rule Information:
   Rule Name: google-traffic
      Type      : Static             Associated Rule Base: None
      Precedence: 20                 Status: Active
      Activation due in  : N/A
      Deactivation due in: N/A
    QoS Parameters:
      MBR Uplink (kbps):         0           MBR Downlink (kbps):         0
      Burst size Uplink (bytes): 0           Burst size Downlink (bytes): 0
    Charging Attributes:
      Rating Group: 0          Service ID: 0               Gating Status:
enable-both
      AF Charging Id: None     Charging Method: None       Metering Method: None

      Usage Monitoring Key :  NULL
    Logging Rule Name :  r1
    Services Attributes:
      Forwarding Class: best-effort
    Filter Attributes:
      Remote IP/Mask: any/any            Protocol: any Direction: Both
      Local Ports:  any
      Remote Ports: any
      Application Name   : junos:google
      Application Name   : junos:udp
      Application Name   : junos:http
   Rule Name: http-traffic
      Type      : Static             Associated Rule Base: None
      Precedence: 30                 Status: Active
      Activation due in  : N/A
      Deactivation due in: N/A
    QoS Parameters:
      MBR Uplink (kbps):         0           MBR Downlink (kbps):         0
      Burst size Uplink (bytes): 0           Burst size Downlink (bytes): 0
    Charging Attributes:
      Rating Group: 0          Service ID: 0               Gating Status:
enable-both
      AF Charging Id: None     Charging Method: None       Metering Method: None

      Usage Monitoring Key :  NULL
    Logging Rule Name :  r1
    Services Attributes:
      Forwarding Class: best-effort
    Filter Attributes:
      Remote IP/Mask: any/any            Protocol: any Direction: Both
```

Copyright © 2018, Juniper Networks, Inc.

```
      Local Ports:  any
      Remote Ports: any
      Application Name   : junos:http
   Rule Name: all-traffic
      Type      : Static             Associated Rule Base: None
      Precedence: 40                 Status: Active
      Activation due in  : N/A
      Deactivation due in: N/A
    QoS Parameters:
      MBR Uplink (kbps):         0           MBR Downlink (kbps):         0
      Burst size Uplink (bytes): 0           Burst size Downlink (bytes): 0
    Charging Attributes:
      Rating Group: 0          Service ID: 0               Gating Status:
enable-both
      AF Charging Id: None     Charging Method: None       Metering Method: None

      Usage Monitoring Key :  NULL
    Logging Rule Name :  r1
    Services Attributes:
      Forwarding Class: best-effort
    Filter Attributes:
      Remote IP/Mask: any/any            Protocol: any Direction: Both
      Local Ports:  any
      Remote Ports: any
```

show unified-edge tdf subscribers detail

```
user@host> show unified-edge tdf subscribers detail
```

```
Gateway: TDF

Subscriber Information:
     Subscriber Type : IP

     IMSI       : 988888888888899               MSISDN/Username : 9741488201
     IMEI       : None
     State      : Established                    Session Duration: 000000 hrs
41 mins 04 secs
     Domain     : aaa
     Data VRF   : bng_vrf
     NAS-IP-Addr: 198.51.100.123
     NAS-ID     : dfssw
     APN name   : 3242
     V4 Address : 192.0.2.11
     V6 Address : 2001:db8::                       V6 Prefix Length: 64
     Session PIC: 3 /3  (FPC/PIC)
     Service PIC: 3 /0  (FPC/PIC)
     PCRF Event Triggers : UR
     Revalidation due in : N/A
     Idle Timeout: 0   min
     Subscriber MBR:   Uplink (kbps):  0            Downlink (kbps):  0

     Subscriber burst: Uplink (bytes): 0            Downlink (bytes): 0

    PCC Profile Name : pcef-jpkt-prof-dyn
    Usage Monitoring Information:
      Monitoring Key: 302
       Level: Session Status: Active
         Total Available Quota:
           Input: 0       Output: 0
```


Copyright © 2018, Juniper Networks, Inc.

```
          Total: 20000   Time  : 100
     Monitoring Key: 301
       Level: PCC-Rule Status: Active
         Total Available Quota:
           Input: 0       Output: 0
           Total: 20000   Time  : 0
   PCC Rule Information:
   Rule Name: Dyn_Rule_1
      Type : Dynamic Associated Rule Base: None
      Precedence: 1 Status: Active
      Activation due in : N/A
      Deactivation due in: N/A
    QoS Parameters:
      MBR Uplink (kbps): 2000 MBR Downlink (kbps): 3000
      Burst size Uplink (bytes): 0 Burst size Downlink (bytes): 0
    Charging Attributes:
      Rating Group: 0 Service ID: 0 Gating Status: enable-uplink
      AF Charging Id: None Charging Method: None Metering Method: None
      Usage Monitoring Key : 301
    Services Attributes:
      Steering VRF Uplink: changed_vrf     Downlink: new_vrf
      HCM ID: hcmtag1
    Filter Attributes:
      Remote IP/Mask: 203.0.113/32 Protocol: 1 Direction: Both
      Local Ports: any
      Remote Ports: any
      Application Id : None
      Application Id Base: None
```

show unified-edge tdf subscribers data-plane

```
user@host> show unified-edge tdf subscribers data-plane
```

```
Gateway: TDF
Data plane statistics :

V4 Address:192.0.2.11
V6 Address:2001:db8::                        V6 Prefix Length: 64
Subscriber-Type:IP
Vrf Id: 11
Subscriber Stats:
                      Uplink                 Downlink
-------------------------------------------------------------------
    Packets          :0                     :0
    Bytes            :0                     :0
    Dropped Packets  :0                     :0
    Dropped Bytes    :0                     :0


Rule: rule_zynga
                      Uplink                 Downlink
-------------------------------------------------------------------
    Sessions         :0                     :0
    Packets          :0                     :0
    Bytes            :0                     :0
    Dropped Packets  :0                     :0
    Dropped Bytes    :0                     :0
```

Copyright © 2018, Juniper Networks, Inc.

```
Rule: rule_youtube
                      Uplink                Downlink
-------------------------------------------------------------------
    Sessions         :0                    :0
    Packets          :0                    :0
    Bytes            :0                    :0
    Dropped Packets  :0                    :0
    Dropped Bytes    :0                    :0


Rule: rule_amazon
                      Uplink                Downlink
-------------------------------------------------------------------
    Sessions         :0                    :0
    Packets          :0                    :0
    Bytes            :0                    :0
    Dropped Packets  :0                    :0
    Dropped Bytes    :0                    :0


Rule: rule_monster
                      Uplink                Downlink
-------------------------------------------------------------------
    Sessions         :0                    :0
    Packets          :0                    :0
    Bytes            :0                    :0
    Dropped Packets  :0                    :0
    Dropped Bytes    :0                    :0


Rule: all-traffic-s
                      Uplink                Downlink
-------------------------------------------------------------------
    Sessions         :0                    :0
    Packets          :0                    :0
    Bytes            :0                    :0
    Dropped Packets  :0                    :0
    Dropped Bytes    :0                    :0
```


Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf system interfaces

Syntax

show unified-edge tdf system interfaces
<gateway *gateway-name*>

Release Information

Statement introduced in Junos OS Release 17.1 on MX Series.

Description

Display information about the aggregated Packet Forwarding Engine and the aggregated multiservices (AMS) interfaces and their states on one or more TDF gateways. If a TDF gateway is not specified, then information for all TDF gateways is displayed.

Options

none—Display information for all TDF gateways.

gateway *gateway-name*—(Optional) Display information for the specified TDF gateway.

Required Privilege Level

view

Related Documentation

- show interfaces anchor-group (Aggregated Packet Forwarding Engine) on page 567
- show interfaces load-balancing (Aggregated Multiservices) on page 570
- show unified-edge tdf resource-manager clients on page 688
- show unified-edge tdf system interfaces service-mode on page 719

List of Sample Output

show unified-edge tdf system interfaces on page 718

Output Fields

Table 58 on page 717 lists the output fields for the **show unified-edge tdf system interfaces** command. Output fields are listed in the approximate order in which they appear.

Table 58: show unified-edge tdf system interfaces Output Fields

Field Name	Field Description
Gateway	Name of the TDF gateway.
Interfaces	Name of the interface: • Aggregated multiservices; for example, ams0 • Aggregated Packet Forwarding Engine; for example, apfe1 • Member of aggregated multiservices; for example, mams-1/0/0 • Multiservices; for example, ms-1/0/0 • Packet Forwarding Engine; for example, pfe-0/1/0
Members	For ams and apfe interfaces, the member interfaces that are part of the aggregated interfaces are displayed.
Operational State	Whether the interface is operational (**Active**) or not (**Inactive**).

Copyright © 2018, Juniper Networks, Inc.

Table 58: show unified-edge tdf system interfaces Output Fields (continued)

Field Name	Field Description
Redundancy Role	Redundancy state in which the interface is configured: • **Primary**—Interface is a primary member. • **Secondary**—Interface is a backup to all the primary members. • **Standalone**—Interface has not been configured for redundancy.

Sample Output

show unified-edge tdf system interfaces

```
user@host> show unified-edge tdf system interfaces

Gateway: TDF
    Interfaces         Members        Operational    Redundancy
                                         State          Role
    ms-1/0/0                          Active         Standalone
    ms-1/1/0                          Active         Standalone
    ms-2/0/0                          Active         Standalone
    ms-2/1/0                          Active         Standalone
```


Copyright © 2018, Juniper Networks, Inc.

show unified-edge tdf system interfaces service-mode

Syntax

```
show unified-edge tdf system interfaces service-mode
<brief | detail>
<gateway gateway-name>
```

Release Information Statement introduced in Junos OS Release 17.1 on MX Series.

Description Display the service mode information for the interfaces on one or more TDF gateways. If a TDF gateway is not specified, then information for all TDF gateways is displayed.

Options

none—(Same as brief) Display service mode information for all TDF gateways.

brief | detail—(Optional) Display the specified level of output.

gateway-name *gateway-name*—(Optional) Display service mode information for the specified TDF gateway.

Required Privilege Level view

Related Documentation

- show unified-edge tdf system interfaces on page 717

List of Sample Output

show unified-edge tdf system interfaces service-mode brief on page 720
show unified-edge tdf system interfaces service-mode detail on page 720

Output Fields Table 59 on page 719 lists the output fields for the **show unified-edge tdf system interfaces service-mode** command. Output fields are listed in the approximate order in which they appear.

Table 59: show unified-edge tdf system interfaces service-mode Output Fields

Field Name	Field Description	Level of Output
Maintenance Mode	Phases applicable when the TDF interface is in maintenance mode. • **MM - Active Phase**—All the attributes of the address pool can be modified. • **MM - In/Out Phase**—Only the non-maintenance mode attributes of the address pool can be modified.	None **brief**
Interface Name	Name of the interface for which the service mode information is displayed: • Aggregated multiservices; for example, ams0 • Aggregated Packet Forwarding Engine; for example, apfe1 • Multiservices; for example, ms-1/0/0	All levels

Copyright © 2018, Juniper Networks, Inc.

Table 59: show unified-edge tdf system interfaces service-mode Output Fields (continued)

Field Name	Field Description	Level of Output
Gateway	Name of the TDF gateway.	None **brief**
Gateway Name	Name of the TDF gateway.	**detail**
Service Mode Status	Status of service mode for the TDF gateway.	**detail**
Service Mode	Service mode for the TDF gateway. The following service modes are possible: • **Operational**—Gateway is in operational mode. • **Maintenance**—Gateway is in maintenance mode.	All levels

Sample Output

show unified-edge tdf system interfaces service-mode brief

```
user@host> show unified-edge tdf system interfaces service-mode brief

Maintenance Mode
    MM Active Phase - System is ready to accept configuration changes for all
                      attributes of this object and its sub-hierarchies.
    MM In/Out Phase - System is ready to accept configuration changes only for
                      non-maintenance mode attributes of this object and
                      its sub-hierarchies.

Interface Name     Gateway                      Service Mode

ms-2/1/0          TDF                             Operational
ams1               TDF                             Operational
```

show unified-edge tdf system interfaces service-mode detail

```
user@host> show unified-edge tdf system interfaces service-mode detail

Service Mode Status
Interface Name  : ms-2/1/0
Gateway Name    : TDF
Service Mode    : Operational
Service Mode Status
Interface Name  : ams1
Gateway Name    : TDF
Service Mode    : Operational
```


Copyright © 2018, Juniper Networks, Inc.