

PART 1

Overview

- [Converged Networks Overview on page 3](#)

PART 3

Administration

- [Operational Commands on page 91](#)


```

FCF-MAC : 00:10:94:00:00:01      VLAN : v1an1
Configured FKA-ADV : 258          Running FKA-ADV : 222
  Enode Information
  Enode-MAC : 00:10:94:00:00:02 Interface: xe-0/0/1
  Configured FKA-ADV : 258
  Running FKA-ADV : 226
    Session Information
    VN-Port MAC : 0E:FC:00:00:00:05      FKA-ADV : 242
    VN-Port MAC : 0E:FC:00:00:00:01      FKA-ADV : 238
    
```


Number of VN_Port Claim Reply:	3
Number of FLOGI:	0
Number of FLOGI_ACC:	0
Number of FLOGI_RJT:	0
Number of FDISC:	0
Number of FDISC_ACC:	0
Number of FDISC_RJT:	0
Number of LOGO:	0
Number of LOGO_ACC:	0
Number of LOGO_RJT:	0

