

Chapter 3

Summary of Operational Response Tag Elements

This chapter lists the Extensible Markup Language (XML) tag elements in the JUNOS XML application programming interface (API) that contain operational information. The JUNOScript and NETCONF servers return them in response to requests from client applications. The tags are divided into the following sections and listed in alphabetical order within each section.

- `<output>` Tag Element on page 296
- Summary of Accounting Response Tags on page 297
- Summary of Adaptive Services Response Tags on page 321
- Summary of Alarm Response Tags on page 431
- Summary of APS Response Tags on page 434
- Summary of ARP Response Tags on page 437
- Summary of Authentication Response Tags on page 440
- Summary of Autoinstallation Response Tags on page 455
- Summary of BFD Response Tags on page 457
- Summary of Connectivity Fault Management Response Tags on page 464
- Summary of Chassis Response Tags on page 494
- Summary of Class-of-Service Response Tags on page 557
- “Summary of Database Replication Response Tags” on page 605
- Summary of Data Link Switching Response Tags on page 607
- Summary of DHCP Response Tags on page 619
- Summary of DHCP Relay Response Tags on page 629
- Summary of DHCP Server Response Tags on page 635

- Summary of Dialer Response Tags on page 641
- “Summary of Diameter Response Tags” on page 648
- Summary of Dynamic Configuration Response Tags on page 657
- Summary of Dynamic Flow Capture Response Tags on page 664
- Summary of Firewall Filter Response Tags on page 672
- Summary of Graceful Switchover Response Tags on page 675
- Summary of Interface Metadata Response Tags on page 678
- Summary of Interface Response Tags on page 680
- Summary of IPSec Response Tags on page 848
- Summary of IPv6 Neighbor Discovery Response Tags on page 884
- Summary of ISDN Response Tags on page 886
- Summary of J20 GGSN Response Tags on page 895
- Summary of Layer 2 Address Learning Response Tags on page 949
- Summary of Layer 2 Control Protocol Response Tags on page 973
- Summary of LACP Response Tags on page 946
- Summary of License Response Tags on page 1001
- Summary of Licensed Feature Metadata Response Tags on page 1008
- Summary of Link-Fault Management Response Tags on page 1010
- Summary of MIP Response Tags on page 1023
- Summary of MPLS OAM ResponseTags on page 1039
- Summary of Passive Monitoring Interfaces Response Tags on page 1046
- Summary of PGM Response Tags on page 1053
- Summary of Periodic Packet Management Response Tags on page 1061
- Summary of Periodic Packet Management Response Tags on page 1061
- Summary of PPP Response Tags on page 1066
- Summary of PPP over Ethernet Response Tags on page 1077
- Summary of Probe-Test Response Tags on page 1083
- Summary of Product Metadata Response Tags on page 1095

- Summary of Redundant Interfaces Response Tags on page 1098
- “Summary of Resource Cleanup Response Tags” on page 1099
- Summary of Routing and Forwarding Table Response Tags on page 1102
- Summary of Routing Protocols Response Tags on page 1108
- Summary of RPM Response Tags on page 1489
- Summary of SDX Response Tags on page 1506
- Summary of Services Accounting Response Tags on page 1508
- Summary of Services Flow Collector Response Tags on page 1522
- Summary of Shutdown Response Tags on page 1530
- Summary of SNMP Response Tags on page 1531
- “Summary of Subscribers Response Tags” on page 1560
- Summary of UDP Forwarding Helper Response Tags on page 1563
- Summary of Telephony Gateway Module Response Tags on page 1557
- Summary of UDP Forwarding Helper Response Tags on page 1563
- Summary of System Process Response Tags on page 1565
- Summary of Virtual Router Redundancy Protocol Response Tags on page 1579
- Summary of X.509 Certificate Response Tags on page 1591

For information about the notation used in this chapter, see Table 2 on page lxvii. To review the document type definitions (DTDs) for these tags, see “JUNOS XML Document Type Definitions” on page 1599.

<output> Tag Element

Usage <!-- when returned by the JUNOScript server -->

```
<rpc-reply xmlns:junos="URL">
```

```
  <output>response</output>
```

```
</rpc-reply>
```

<!-- when returned by the NETCONF server -->

```
<rpc-reply xmlns="URN">
```

```
  <output>response</output>
```

```
</rpc-reply>
```

```
]]>]]>
```

Description Contain a response to a client application request when the current version of the JUNOS XML API does not define a specific tag element for the response. The format of the contents is subject to change, so the client application must not rely on a particular format.

See Also <rpc-reply> in the *JUNOScript API Guide* or *NETCONF API Guide*

Summary of Accounting Response Tags

This section lists the JUNOS XML tags that contain operational information about accounting records. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-accounting>. To review the DTD for the tags, see “DTD for Accounting Response Tags” on page 1603.

<accounting-profile-columns>

- Usage** <accounting-profile-information>
 <accounting-profile-columns>
 <column-label>*column-label*</column-label>
 </accounting-profile-columns>
 </accounting-profile-information>
- Description** Name of each JUNOScript output tag that is included in records generated based on the profile.
- Contents** <column-label>—Name of an output tag that is included in records generated based on the profile.

<accounting-profile-filter>

- Usage** <accounting-profile-information>
 <accounting-profile-filter>
 <filter-name>*filter-name*</filter-name>
 <next-scheduled-collection>*next-scheduled-collection*
 </next-scheduled-collection>
 </accounting-profile-filter>
 </accounting-profile-information>
- Description** Name of each filter to which the profile is applied.
- Contents** <filter-name>—Name of the filter.
- <next-scheduled-collection>—Local time at which statistics collection will next begin, in the format YYYY-MM-DD-hh:mm:ss (year, month, day, hour in 24-hour format, minute, second).

<accounting-profile-header>

Usage <accounting-profile-information>
 <accounting-profile-header>
 <profile-name>*profile-name*</profile-name>
 <profile-type>*profile-type*</profile-type>
 <profile-interval>*profile-interval*</profile-interval>
 <profile-use-count>*profile-use-count*</profile-use-count>
 <filename>*filename*</filename>
 <filesize>*filesize*</filesize>
 <filenumber>*filenumber*</filenumber>
 <bytes-written>*bytes-written*</bytes-written>
 <transfer-interval>*transfer-interval*</transfer-interval>
 <next-transfer-time>*next-transfer-time*</next-transfer-time>
 </accounting-profile-header>
 </accounting-profile-information>

Description Information from the accounting profile header.

Contents <bytes-written>—Number of bytes of data written to the file between the start of the most recent collection interval and the time of the request for information about the profile.

<filename>—Name of the file in the /var/log directory to which records are written.

<filenumber>—Maximum number of rotating versions of the file in the /var/log directory (the active file plus compressed files containing earlier data).

<filesize>—Maximum number of bytes of data written to the active version of the file before the file is closed, and a new file opened. If the transfer interval expires first, the file might contain less data.

<next-transfer-time>—Date and time when the active file will next be closed and transferred to the configured archive site, in the format YYYY-MM-DD-hh:mm:ss (year, month, day, hour in 24-hour format, minute, second).

<profile-interval>—Frequency of statistics collection for each object sampled by the profile.

<profile-name>—Name of the accounting profile.

<profile-type>—Type of object to which the profile is applied.

<profile-use-count>—Number of objects to which this profile is applied (number of objects for which the statistics defined in this profile are collected).

<transfer-interval>—Frequency, in minutes, that the active file is closed and transferred to the configured archive site. The file is closed even if the maximum amount of data has not yet been written. As when the file is closed because the maximum size is reached, the contents of the active file are also compressed and copied to the first rotating file in the /var/log directory.

<accounting-profile-information>

Usage <rpc-reply>
 <accounting-profile-information>
 <accounting-profile-header>...</accounting-profile-header>
 <accounting-profile-columns>...</accounting-profile-columns>
 <accounting-profile-interfaces>...</accounting-profile-interfaces>
 <accounting-profile-mib>...</accounting-profile-mib>
 <accounting-profile-filter>...</accounting-profile-filter>
 </accounting-profile-information>
 </rpc-reply>

Description Information about an accounting profile.

Contents <accounting-profile-columns>—Name of each JUNOScript output tag that is included in records generated based on the profile.

<accounting-profile-filter>—Name of each filter to which the profile is applied.

<accounting-profile-header>—Information from the accounting profile header.

<accounting-profile-interfaces>—Name of each interface to which the profile is applied.

<accounting-profile-mib>—Name of each Management Information Base to which the profile is applied.

<accounting-profile-interfaces>

Usage <accounting-profile-information>
 <accounting-profile-interfaces>
 <interface-name>*interface-name*</interface-name>
 <next-scheduled-collection>*next-scheduled-collection*
 </next-scheduled-collection>
 </accounting-profile-interfaces>
 </accounting-profile-information>

Description Name of each interface to which the profile is applied.

Contents <interface-name>—Name of the interface.

<next-scheduled-collection>—Local time at which statistics collection will next begin, in the format YYYY-MM-DD-hh:mm:ss (year, month, day, hour in 24-hour format, minute, second).

<accounting-profile-mib>

- Usage** <accounting-profile-information>
 <accounting-profile-mib>
 <mib-name>*mib-name*</mib-name>
 <next-scheduled-collection>*next-scheduled-collection*
 </next-scheduled-collection>
 </accounting-profile-mib>
 </accounting-profile-information>
- Description** Name of each Management Information Base to which the profile is applied.
- Contents** <mib-name>—Name of a MIB.
- <next-scheduled-collection>—Local time at which statistics collection will next begin, in the format YYYY-MM-DD-hh:mm:ss (year, month, day, hour in 24-hour format, minute, second).

<accounting-record-information>

- Usage** <rpc-reply>
 <accounting-record-information>
 <interface-accounting-statistics>...</interface-accounting-statistics>
 <routing-engine-accounting-statistics>...
 </routing-engine-accounting-statistics>
 <filter-accounting-statistics>...</filter-accounting-statistics>
 <cu-accounting-statistics>...</cu-accounting-statistics>
 <mib-accounting-statistics>...</mib-accounting-statistics>
 <file-accounting-records>...</file-accounting-records>
 </accounting-record-information>
 </rpc-reply>
- Description** Information in a record that was generated based on an accounting profile.
- Contents** <cu-accounting-statistics>—Information from one or more records that were generated based on a destination class usage or source class usage profile.
- <file-accounting-records>—Records from an accounting file.
- <filter-accounting-statistics>—Information from one or more records that were generated based on a filter profile.
- <interface-accounting-statistics>—Information from one or more records that were generated based on an interface profile.
- <mib-accounting-statistics>—Information from one or more records that were generated based on a Management Information Base profile.
- <routing-engine-accounting-statistics>—Information from one or more records that were generated based on a Routing Engine profile.

<cu-accounting-record>

Usage <cu-accounting-statistics>
 <cu-accounting-record>
 <profile-layout>*profile-layout*</profile-layout>
 <epoch-timestamp>*epoch-timestamp*</epoch-timestamp>
 <utc-timestamp>*utc-timestamp*</utc-timestamp>
 <interface-name>*interface-name*</interface-name>
 <address-family>*address-family*</address-family>
 <destination-class-name>*destination-class-name*</destination-class-name>
 <source-class-name>*source-class-name*</source-class-name>
 <counter-name>*counter-name*</counter-name>
 <packet-count>*packet-count*</packet-count>
 <byte-count>*byte-count*</byte-count>
 </cu-accounting-record>
 </cu-accounting-statistics>

Description Information in a record that was generated based on a destination class usage or source class usage profile.

Contents <address-family>—Interface family configured on the interface.

<byte-count>—Number of bytes processed by the counter.

<counter-name>—Name of the counter.

<destination-class-name>—Name of the destination class.

<epoch-timestamp>—Time at which the record was written, expressed as local time.

<interface-name>—Name of the interface.

<packet-count>—Number of packets processed by the counter.

<profile-layout>—No documentation is available yet.

<source-class-name>—Name of the source class.

<utc-timestamp>—Time at which the record was written, expressed as Coordinated Universal Time.

<cu-accounting-statistics>

Usage <accounting-record-information>
 <cu-accounting-statistics>
 <cu-accounting-record>...</cu-accounting-record>
 </cu-accounting-statistics>
 </accounting-record-information>

Description Information from one or more records that were generated based on a destination class usage or source class usage profile.

Contents <cu-accounting-record>—Information in a record that was generated based on a destination class usage or source class usage profile.

<file-accounting-record>

Usage <file-accounting-records>
 <file-accounting-record>
 <profile-layout>*profile-layout*</profile-layout>
 <epoch-timestamp>*epoch-timestamp*</epoch-timestamp>
 </file-accounting-record>
 </file-accounting-records>

Description Record from an accounting file.

Contents <epoch-timestamp>—Time at which the record was written, expressed as local time.
 <profile-layout>—No documentation is available yet.

<file-accounting-records>

Usage <accounting-record-information>
 <file-accounting-records>
 <file-accounting-record>...</file-accounting-record>
 </file-accounting-records>
 </accounting-record-information>

Description Records from an accounting file.

Contents <file-accounting-record>—Record from an accounting file.

<filter-accounting-record>

Usage <filter-accounting-statistics>
 <filter-accounting-record>
 <profile-layout>*profile-layout*</profile-layout>
 <epoch-timestamp>*epoch-timestamp*</epoch-timestamp>
 <utc-timestamp>*utc-timestamp*</utc-timestamp>
 <interfaces>*interfaces*</interfaces>
 <filter-name>*filter-name*</filter-name>
 <counter-name>*counter-name*</counter-name>
 <packet-count>*packet-count*</packet-count>
 <byte-count>*byte-count*</byte-count>
 </filter-accounting-record>
 </filter-accounting-statistics>

Description Information in a record that was generated based on a filter profile.

Contents <byte-count>—Number of bytes processed by the counter.
 <counter-name>—Name of the counter.
 <epoch-timestamp>—Time at which the record was written, expressed as local time.
 <filter-name>—Name of the filter.
 <interfaces>—Name of one or more interfaces for which the record was collected.
 <packet-count>—Number of packets processed by the counter.
 <profile-layout>—No documentation is available yet.
 <utc-timestamp>—Time at which the record was written, expressed as Coordinated Universal Time.

<filter-accounting-statistics>

Usage <accounting-record-information>
 <filter-accounting-statistics>
 <filter-accounting-record>...</filter-accounting-record>
 </filter-accounting-statistics>
 </accounting-record-information>

Description Information from one or more records that were generated based on a filter profile.

Contents <filter-accounting-record>—Information in a record that was generated based on a filter profile.

<index>

Usage <snmp-object>
 <index>
 <index-name>*index-name*</index-name>
 <index-value>*index-value*</index-value>
 </index>
 </snmp-object>

Description No documentation is available yet.

Contents <index-name>—SNMP index name.
 <index-value>—SNMP index value.

<interface-accounting-record>

Usage <interface-accounting-statistics>
 <interface-accounting-record>
 <profile-layout>*profile-layout*</profile-layout>
 <epoch-timestamp>*epoch-timestamp*</epoch-timestamp>
 <utc-timestamp>*utc-timestamp*</utc-timestamp>
 <interface-name>*interface-name*</interface-name>
 <snmp-index>*snmp-index*</snmp-index>
 <input-bytes>*input-bytes*</input-bytes>
 <output-bytes>*output-bytes*</output-bytes>
 <input-packets>*input-packets*</input-packets>
 <output-packets>*output-packets*</output-packets>
 <input-unicast>*input-unicast*</input-unicast>
 <output-unicast>*output-unicast*</output-unicast>
 <input-multicast>*input-multicast*</input-multicast>
 <output-multicast>*output-multicast*</output-multicast>
 <input-errors>*input-errors*</input-errors>
 <output-errors>*output-errors*</output-errors>
 <no-proto>*no-proto*</no-proto>
 <rpf-check-bytes>*rpf-check-bytes*</rpf-check-bytes>
 <rpf-check-packets>*rpf-check-packets*</rpf-check-packets>
 <rpf-check6-bytes>*rpf-check6-bytes*</rpf-check6-bytes>
 <rpf-check6-packets>*rpf-check6-packets*</rpf-check6-packets>
 </interface-accounting-record>
 </interface-accounting-statistics>

Description Information in a record that was generated based on an interface profile.

Contents <epoch-timestamp>—Time at which the record was written, expressed as local time.

<input-bytes>—Number of bytes received at the interface during the collection interval.

<input-errors>—Number of packets received at the interface during the collection interval that had errors (for example, frame checksum sequence errors, or an invalid header length).

<input-multicast>—Number of multicast packets received at the interface during the collection interval.

<input-packets>—Number of packets received at the interface during the collection interval.

<input-unicast>—Number of unicast packets received at the interface during the collection interval.

<interface-name>—Name of the interface.

<no-proto>—Number of packets that used an unsupported protocol.

<output-bytes>—Number of bytes sent from the interface during the collection interval.

<output-errors>—Number of packets scheduled to be sent from the interface during

the collection interval that were not sent because of error conditions (for example, congestion or interface outages).

<output-multicast>—Number of multicast packets sent from the interface during the collection interval.

<output-packets>—Number of packets sent from the interface during the collection interval.

<output-unicast>—Number of unicast packets sent from the interface during the collection interval.

<profile-layout>—No documentation is available yet.

<rpf-check-bytes>—Number of bytes in reverse-path-forwarding check packets for IPv4.

<rpf-check-packets>—Number of reverse-path-forwarding check packets for IPv4.

<rpf-check6-bytes>—Number of bytes in reverse-path-forwarding check packets for IPv6.

<rpf-check6-packets>—Number of reverse-path-forwarding check packets for IPv6.

<snmp-index>—Simple Network Management Protocol index of the object described in the record.

<utc-timestamp>—Time at which the record was written, expressed as Coordinated Universal Time.

<interface-accounting-statistics>

Usage <accounting-record-information>
 <interface-accounting-statistics>
 <interface-accounting-record>...</interface-accounting-record>
 </interface-accounting-statistics>
 </accounting-record-information>

Description Information from one or more records that were generated based on an interface profile.

Contents <interface-accounting-record>—Information in a record that was generated based on an interface profile.

<mib-accounting-record>

- Usage** <mib-accounting-statistics>
 <mib-accounting-record>
 <profile>*profile*</profile>
 <epoch-timestamp>*epoch-timestamp*</epoch-timestamp>
 <utc-timestamp>*utc-timestamp*</utc-timestamp>
 <name>*name*</name>
 <object-value>*object-value*</object-value>
 </mib-accounting-record>
 </mib-accounting-statistics>
- Description** Information in a record that was generated based on a Management Information Base profile.
- Contents** <epoch-timestamp>—Time at which the record was written, expressed as local time.
- <name>—SNMP object name.
- <object-value>—SNMP object value.
- <profile>—Name of the MIB profile.
- <utc-timestamp>—Time at which the record was written, expressed as Coordinated Universal Time.

<mib-accounting-statistics>

- Usage** <accounting-record-information>
 <mib-accounting-statistics>
 <mib-accounting-record>...</mib-accounting-record>
 </mib-accounting-statistics>
 </accounting-record-information>
- Description** Information from one or more records that were generated based on a Management Information Base profile.
- Contents** <mib-accounting-record>—Information in a record that was generated based on a Management Information Base profile.

<pfe>

Usage <pfe-information>
 <pfe>
 <slot-index>*slot-index*</slot-index>
 <slot-type>*slot-type*</slot-type>
 <slot-state>*slot-state*</slot-state>
 <mgmt-state>*mgmt-state*</mgmt-state>
 <up-time>*up-time*</up-time>
 </pfe>
 </pfe-information>

Description No documentation is available yet.

Contents <mgmt-state>—Management state.

 <slot-index>—Slot index.

 <slot-state>—Slot state.

 <slot-type>—Packet Forwarding Engine component type.

 <up-time>—Time since the slot is up.

<pfe-bfd-statistics-detail>

Usage <pfe-statistics>
 <pfe-bfd-statistics-detail>
 <bfd-invalid-iif>*bfd-invalid-iif*</bfd-invalid-iif>
 <bfd-invalid-iff>*bfd-invalid-iff*</bfd-invalid-iff>
 <bfd-bad-checksum>*bfd-bad-checksum*</bfd-bad-checksum>
 <bfd-bad-options>*bfd-bad-options*</bfd-bad-options>
 <bfd-bad-length>*bfd-bad-length*</bfd-bad-length>
 <bfd-bad-udp-checksum>*bfd-bad-udp-checksum*</bfd-bad-udp-checksum>
 <bfd-bad-udp-length>*bfd-bad-udp-length*</bfd-bad-udp-length>
 <bfd-bad-udp-ports>*bfd-bad-udp-ports*</bfd-bad-udp-ports>
 <bfd-no-local-ifl>*bfd-no-local-ifl*</bfd-no-local-ifl>
 <bfd-bad-ifl-prefix-length>*bfd-bad-ifl-prefix-length*
 </bfd-bad-ifl-prefix-length>
 <bfd-rx-queue-overflow>*bfd-rx-queue-overflow*</bfd-rx-queue-overflow>
 <bfd-out-of-packets>*bfd-out-of-packets*</bfd-out-of-packets>
 <bfd-total-packets>*bfd-total-packets*</bfd-total-packets>
 <bfd-total-absorbed>*bfd-total-absorbed*</bfd-total-absorbed>
 <bfd-transmit-errors>*bfd-transmit-errors*</bfd-transmit-errors>
 </pfe-bfd-statistics-detail>
 </pfe-statistics>

Description No documentation is available yet.

Contents <bfd-bad-checksum>—Packets having incorrect checksum.

<bfd-bad-ifl-prefix-length>—Packets with logical interface prefix length mismatch.

<bfd-bad-length>—Packets having incorrect length.

<bfd-bad-options>—Packets having incorrect options.

<bfd-bad-udp-checksum>—Packets having incorrect udp checksum.

<bfd-bad-udp-length>—Packets having incorrect udp length.

<bfd-bad-udp-ports>—Packets with incorrect udp destination ports.

<bfd-invalid-iff>—Packets having an invalid address family .

<bfd-invalid-iif>—Packets with an invalid interface.

<bfd-no-local-ifl>—Packets with local logical interface lookup failures.

<bfd-out-of-packets>—Packet allocation failures.

<bfd-rx-queue-overflow>—Packet drops due to RX Queue overflow.

<bfd-total-absorbed>—Packets absorbed.

<bfd-total-packets>—Packets received.

<bfd-transmit-errors>—Packets failed to transmit.

<pfe-cfm-statistics-detail>

Usage <pfe-statistics>
 <pfe-cfm-statistics-detail>
 <cfm-packets-received>*cfm-packets-received*</cfm-packets-received>
 <cfm-packets-sent-to-re>*cfm-packets-sent-to-re*</cfm-packets-sent-to-re>
 <cfm-packets-absorbed>*cfm-packets-absorbed*</cfm-packets-absorbed>
 <cfm-packets-received-with-sequence-number>*cfm-pkts-recd-with-seq-num*
 </cfm-packets-received-with-sequence-number>
 <cfm-packets-received-invalid-length>*cfm-packets-recd-invalid-len*
 </cfm-packets-received-invalid-length>
 <cfm-packets-transmitted>*cfm-pkts-transm*</cfm-packets-transmitted>
 <cfm-packets-transmit-error>*cfm-packets-transmit-error*
 </cfm-packets-transmit-error>
 <cfm-packets-dropped>*cfm-packets-dropped*</cfm-packets-dropped>
 </pfe-cfm-statistics-detail>
 </pfe-statistics>

Description No documentation is available yet.

Contents <cfm-packets-absorbed>—Packets absorbed.

<cfm-packets-dropped>—Packets dropped on pfe.

<cfm-packets-received>—Total packets received on pfe.

<cfm-packets-received-invalid-length>—Packets received with invalid length.

<cfm-packets-received-with-sequence-number>—Packets received with sequence number.

<cfm-packets-sent-to-re>—Packets send to RE.

<cfm-packets-transmit-error>—Packets failed to transmit.

<cfm-packets-transmitted>—Total packets transmitted.

<pfe-chip-statistics>

Usage <pfe-statistics>
 <pfe-chip-statistics>
 <input-checksum>*input-checksum*</input-checksum>
 <output-mtu>*output-mtu*</output-mtu>
 </pfe-chip-statistics>
 </pfe-statistics>

Description No documentation is available yet.

Contents <input-checksum>—Packets having input checksum error.

<output-mtu>—Packets having output mtu error.

<pfe-hardware-discard-statistics>

Usage <pfe-statistics>
 <pfe-hardware-discard-statistics>
 <timeout-discard>*timeout-discard*</timeout-discard>
 <truncated-key-discard>*truncated-key-discard*</truncated-key-discard>
 <bits-to-test-discard>*bits-to-test-discard*</bits-to-test-discard>
 <data-error-discard>*data-error-discard*</data-error-discard>
 <stack-underflow-discard>*stack-underflow-discard*</stack-underflow-discard>
 <stack-overflow-discard>*stack-overflow-discard*</stack-overflow-discard>
 <bad-route-discard>*bad-route-discard*</bad-route-discard>
 <nexthop-discard>*nexthop-discard*</nexthop-discard>
 <invalid-iif-discard>*invalid-iif-discard*</invalid-iif-discard>
 <info-cell-discard>*info-cell-discard*</info-cell-discard>
 <fabric-discard>*fabric-discard*</fabric-discard>
 </pfe-hardware-discard-statistics>
 </pfe-statistics>

Description No documentation is available yet.

Contents <bad-route-discard>—Packets discarded because of bad route.

<bits-to-test-discard>—Packets failing bit-to test.

<data-error-discard>—Packets with data errors.

<fabric-discard>—Number of packets discarded by the fabric.

<info-cell-discard>—Number of discarded info-cells.

<invalid-iif-discard>—Packets coming in through an invalid interface.

<nexthop-discard>—Packets discarded because of an extended or illegal nexthop.

<stack-overflow-discard>—Packets discarded because of stack overflow.

<stack-underflow-discard>—Packets discarded because of stack underflow.

<timeout-discard>—Packets discarded because of a timeout.

<truncated-key-discard>—Truncated key packets.

<pfe-information>

Usage <rpc-reply>
 <pfe-information>
 <pfe>...</pfe>
 </pfe-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <pfe>—No documentation is available yet.

<pfe-lfm-statistics-detail>

Usage <pfe-statistics>
 <pfe-lfm-statistics-detail>
 <lfm-packets-received>*lfm-packets-received*</lfm-packets-received>
 <lfm-packets-sent-to-re>*lfm-packets-sent-to-re*</lfm-packets-sent-to-re>
 <lfm-packets-absorbed>*lfm-packets-absorbed*</lfm-packets-absorbed>
 <lfm-packets-transmitted>*lfm-packets-transmitted*</lfm-packets-transmitted>
 <lfm-packets-transmit-error>*lfm-packets-transmit-error*
 </lfm-packets-transmit-error>
 <lfm-packets-dropped>*lfm-packets-dropped*</lfm-packets-dropped>
 </pfe-lfm-statistics-detail>
 </pfe-statistics>

Description No documentation is available yet.

Contents <lfm-packets-absorbed>—Packets absorbed.

<lfm-packets-dropped>—Packets dropped on pfe.

<lfm-packets-received>—Total packets received on pfe.

<lfm-packets-sent-to-re>—Packets send to RE.

<lfm-packets-transmit-error>—Packets failed to transmit.

<lfm-packets-transmitted>—Total packets transmitted.

<pfe-local-protocol-statistics>

Usage <pfe-statistics>
 <pfe-local-protocol-statistics>
 <hdlc-keepalive-count>*hdlc-keepalive-count*</hdlc-keepalive-count>
 <atm-oam-count>*atm-oam-count*</atm-oam-count>
 <fr-lmi-count>*fr-lmi-count*</fr-lmi-count>
 <ppp-lcp-ncp-count>*ppp-lcp-ncp-count*</ppp-lcp-ncp-count>
 <ospf-hello-count>*ospf-hello-count*</ospf-hello-count>
 <ospf3-hello-count>*ospf3-hello-count*</ospf3-hello-count>
 <rsvp-hello-count>*rsvp-hello-count*</rsvp-hello-count>
 <ldp-hello-count>*ldp-hello-count*</ldp-hello-count>
 <bfd-count>*bfd-count*</bfd-count>
 <isis-iih-count>*isis-iih-count*</isis-iih-count>
 </pfe-local-protocol-statistics>
 </pfe-statistics>

Description No documentation is available yet.

Contents <atm-oam-count>—ATM OAM packet count.

<bfd-count>—BFD packets.

<fr-lmi-count>—Frame Relay LMI packet count.

<hdlc-keepalive-count>—HDLC keepalive packet count.

<isis-iih-count>—IS-IS IIH packets.

<ldp-hello-count>—LDP hello packets.

<ospf-hello-count>—OSPF hello packets.

<ospf3-hello-count>—OSPF3 hello packets.

<ppp-lcp-ncp-count>—PPP LCP/NCP packet count.

<rsvp-hello-count>—RSVP hello packets.

<pfe-local-traffic-statistics>

Usage <pfe-statistics>
 <pfe-local-traffic-statistics>
 <pfe-input-packets>*pfe-input-packets*</pfe-input-packets>
 <pfe-output-packets>*pfe-output-packets*</pfe-output-packets>
 <software-input-control-drops>*software-input-control-drops*
 </software-input-control-drops>
 <software-input-high-drops>*software-input-high-drops*
 </software-input-high-drops>
 <software-input-medium-drops>*software-input-medium-drops*
 </software-input-medium-drops>
 <software-input-low-drops>*software-input-low-drops*</software-input-low-drops>
 <software-output-low-drops>*software-output-low-drops*
 </software-output-low-drops>
 <hardware-input-drops>*hardware-input-drops*</hardware-input-drops>
 </pfe-local-traffic-statistics>
 </pfe-statistics>

Description No documentation is available yet.

Contents <hardware-input-drops>—Low-priority packets discarded by hardware.

<pfe-input-packets>—Packet Forwarding Engine input packets.

<pfe-output-packets>—Packet Forwarding Engine output packets.

<software-input-control-drops>—Drop count of control-priority packets received from host.

<software-input-high-drops>—Drop count of high-priority packets received from host.

<software-input-low-drops>—Drop count of low-priority packets received from host.

<software-input-medium-drops>—Drop count of medium-priority packets received from host.

<software-output-low-drops>—Drop count of low-priority packets sent to host.

<pfe-resource>

Usage <rpc-reply>
 <pfe-resource>
 <pfe-resource-usage>...</pfe-resource-usage>
 </pfe-resource>
 </rpc-reply>

Description No documentation is available yet.

Contents <pfe-resource-usage>—No documentation is available yet.

<pfe-resource-general-information>

Usage <pfe-resource-usage>
 <pfe-resource-general-information>
 <pfe-description>*pfe-description*</pfe-description>
 <pfe-instance>*pfe-instance*</pfe-instance>
 <pfe-forwarding-module-name>*pfe-forwarding-module-name*
 </pfe-forwarding-module-name>
 <pfe-forwarding-module-instance>*pfe-forwarding-module-instance*
 </pfe-forwarding-module-instance>
 <pfe-resource-usage-details>...</pfe-resource-usage-details>
 </pfe-resource-general-information>
 </pfe-resource-usage>

Description No documentation is available yet.

Contents <pfe-description>—Packet Forwarding Engine description.
 <pfe-forwarding-module-instance>—Packet Forwarding Engine module instance.
 <pfe-forwarding-module-name>—Packet Forwarding Engine module name.
 <pfe-instance>—Packet forwarding Engine instance.
 <pfe-resource-usage-details>—No documentation is available yet.

<pfe-resource-usage>

Usage <pfe-resource>
 <pfe-resource-usage>
 <pfe-fpc-instance>*pfe-fpc-instance*</pfe-fpc-instance>
 <pfe-resource-usage-legend>*pfe-resource-usage-legend*
 </pfe-resource-usage-legend>
 <pfe-resource-general-information>...</pfe-resource-general-information>
 </pfe-resource-usage>
 </pfe-resource>

Description No documentation is available yet.

Contents <pfe-fpc-instance>—Fpc slot of the PFE.
 <pfe-resource-general-information>—No documentation is available yet.
 <pfe-resource-usage-legend>—Legend for any markings/highlighting.

<pfe-resource-usage-details>

Usage <pfe-resource-general-information>
 <pfe-resource-usage-details>
 <pfe-resource-total>pfe-resource-total</pfe-resource-total>
 <pfe-resource-units>pfe-resource-units</pfe-resource-units>
 <pfe-resource-free>pfe-resource-free</pfe-resource-free>
 <pfe-resource-inuse>pfe-resource-inuse</pfe-resource-inuse>
 <pfe-resource-name>pfe-resource-name</pfe-resource-name>
 <pfe-resource-inuse-percent>pfe-resource-inuse-percent
 </pfe-resource-inuse-percent>
 <pfe-resource-highlight>pfe-resource-highlight</pfe-resource-highlight>
 </pfe-resource-usage-details>
 </pfe-resource-general-information>

Description No documentation is available yet.

Contents <pfe-resource-free>—Packet Forwarding Engine free number of resources.

<pfe-resource-highlight>—Packet Forwarding Engine resource highlight symbols.

<pfe-resource-inuse>—Packet Forwarding Engine resources used for a partition.

<pfe-resource-inuse-percent>—Packet Forwarding Engine resource percent utilization.

<pfe-resource-name>—Packet Forwarding Engine resource name.

<pfe-resource-total>—Packet Forwarding Engine total number of a resource.

<pfe-resource-units>—Packet Forwarding Engine units for the resource.

<pfe-statistics>

Usage <rpc-reply>
 <pfe-statistics>
 <pfe-traffic-statistics>...</pfe-traffic-statistics>
 <pfe-local-traffic-statistics>...</pfe-local-traffic-statistics>
 <pfe-local-protocol-statistics>...</pfe-local-protocol-statistics>
 <pfe-bfd-statistics-detail>...</pfe-bfd-statistics-detail>
 <pfe-cfm-statistics-detail>...</pfe-cfm-statistics-detail>
 <pfe-lfm-statistics-detail>...</pfe-lfm-statistics-detail>
 <pfe-hardware-discard-statistics>...</pfe-hardware-discard-statistics>
 <pfe-chip-statistics>...</pfe-chip-statistics>
 </pfe-statistics>
 </rpc-reply>

Description No documentation is available yet.

Contents <pfe-bfd-statistics-detail>—No documentation is available yet.

<pfe-cfm-statistics-detail>—No documentation is available yet.

<pfe-chip-statistics>—No documentation is available yet.

<pfe-hardware-discard-statistics>—No documentation is available yet.

<pfe-lfm-statistics-detail>—No documentation is available yet.

<pfe-local-protocol-statistics>—No documentation is available yet.

<pfe-local-traffic-statistics>—No documentation is available yet.

<pfe-traffic-statistics>—No documentation is available yet.

<pfe-traffic-statistics>

Usage <pfe-statistics>
 <pfe-traffic-statistics>
 <pfe-input-packets>*pfe-input-packets*</pfe-input-packets>
 <pfe-output-packets>*pfe-output-packets*</pfe-output-packets>
 <input-pps>*input-pps*</input-pps>
 <output-pps>*output-pps*</output-pps>
 </pfe-traffic-statistics>
 </pfe-statistics>

Description No documentation is available yet.

Contents <input-pps>—Input packets (per second).

<output-pps>—Output packets (per second).

<pfe-input-packets>—Packet Forwarding Engine input packets.

<pfe-output-packets>—Packet Forwarding Engine output packets.

<routing-engine-accounting-record>

Usage <routing-engine-accounting-statistics>
 <routing-engine-accounting-record>
 <profile-layout>*profile-layout*</profile-layout>
 <epoch-timestamp>*epoch-timestamp*</epoch-timestamp>
 <utc-timestamp>*utc-timestamp*</utc-timestamp>
 <hostname>*hostname*</hostname>
 <date-yyyyymmdd>*date-yyyyymmdd*</date-yyyyymmdd>
 <timeofday-hhmmss>*timeofday-hhmmss*</timeofday-hhmmss>
 <uptime>*uptime*</uptime>
 <cpu1min>*cpu1min*</cpu1min>
 <cpu5min>*cpu5min*</cpu5min>
 <cpu15min>*cpu15min*</cpu15min>
 <memory-usage>*memory-usage*</memory-usage>
 <total-cpu-usage>*total-cpu-usage*</total-cpu-usage>
 </routing-engine-accounting-record>
 </routing-engine-accounting-statistics>

Description Information in a record that was generated based on a Routing Engine profile.

Contents <cpu15min>—The load average for the 15 minutes before the record was written (a damped time-dependent average based on the number of active jobs and jobs in the CPU run queue).

<cpu1min>—The load average for the minute before the record was written (a damped time-dependent average based on the number of active jobs and jobs in the CPU run queue).

<cpu5min>—The load average for the five minutes before the record was written (a damped time-dependent average based on the number of active jobs and jobs in the CPU run queue).

<date-yyyyymmdd>—Current date on the Routing Engine, in the format YYYYMMDD (year, month, day).

<epoch-timestamp>—Time at which the record was written, expressed as local time.

<hostname>—Hostname of the Routing Engine.

<memory-usage>—Megabytes of RAM in use.

<profile-layout>—No documentation is available yet.

<timeofday-hhmmss>—Current time on the Routing Engine, in the format hhmmss (hour in 24-hour format, minute, second).

<total-cpu-usage>—Current CPU load, expressed as a percent.

<uptime>—Number of seconds since the Routing Engine last rebooted.

<utc-timestamp>—Time at which the record was written, expressed as Coordinated Universal Time.

<routing-engine-accounting-statistics>

- Usage** <accounting-record-information>
 <routing-engine-accounting-statistics>
 <routing-engine-accounting-record>...</routing-engine-accounting-record>
 </routing-engine-accounting-statistics>
 </accounting-record-information>
- Description** Information from one or more records that were generated based on a Routing Engine profile.
- Contents** <routing-engine-accounting-record>—Information in a record that was generated based on a Routing Engine profile.

<snmp-object>

- Usage** <snmp-object-information>
 <snmp-object>
 <name>name</name>
 <index>...</index>
 <oid>oid</oid>
 <object-value>object-value</object-value>
 <object-value-type>object-value-type</object-value-type>
 <error>error</error>
 </snmp-object>
 </snmp-object-information>
- Description** No documentation is available yet.
- Contents** <error>—SNMP object error.
- <index>—No documentation is available yet.
- <name>—SNMP object name.
- <object-value>—SNMP object value.
- <object-value-type>—No documentation is available yet.
- <oid>—SNMP object identifier.

<snmp-object-information>

Usage <rpc-reply>
 <snmp-object-information>
 <snmp-object>...</snmp-object>
 <snmp-request-error>...</snmp-request-error>
 </snmp-object-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <snmp-object>—No documentation is available yet.
 <snmp-request-error>—No documentation is available yet.

<snmp-request-error>

Usage <snmp-object-information>
 <snmp-request-error>
 <snmp-req-error-value>*snmp-req-error-value*</snmp-req-error-value>
 </snmp-request-error>
 </snmp-object-information>

Description No documentation is available yet.

Contents <snmp-req-error-value>—SNMP request error.

Summary of Adaptive Services Response Tags

This section lists JUNOS XML tags that contain operational information about adaptive services interfaces. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-adaptive-services>. To review the DTD for the tags, see “DTD for Adaptive Services Response Tags” on page 1611.

<alg-error-counters>

Usage <sfw-stats-service-set-entry>
<alg-error-counters>
 <alg-bootp-errors>alg-bootp-errors</alg-bootp-errors>
 <alg-dce-rpc-errors>alg-dce-rpc-errors</alg-dce-rpc-errors>
 <alg-dce-rpc-portmap-errors>alg-dce-rpc-portmap-errors
 </alg-dce-rpc-portmap-errors>
 <alg-dns-errors>alg-dns-errors</alg-dns-errors>
 <alg-exec-errors>alg-exec-errors</alg-exec-errors>
 <alg-ftp-errors>alg-ftp-errors</alg-ftp-errors>
 <alg-h323-errors>alg-h323-errors</alg-h323-errors>
 <alg-icmp-errors>alg-icmp-errors</alg-icmp-errors>
 <alg-iiop-errors>alg-iiop-errors</alg-iiop-errors>
 <alg-login-errors>alg-login-errors</alg-login-errors>
 <alg-netbios-errors>alg-netbios-errors</alg-netbios-errors>
 <alg-netshow-errors>alg-netshow-errors</alg-netshow-errors>
 <alg-realaudio-errors>alg-realaudio-errors</alg-realaudio-errors>
 <alg-rpc-errors>alg-rpc-errors</alg-rpc-errors>
 <alg-rpc-portmap-errors>alg-rpc-portmap-errors</alg-rpc-portmap-errors>
 <alg-rtsp-errors>alg-rtsp-errors</alg-rtsp-errors>
 <alg-shell-errors>alg-shell-errors</alg-shell-errors>
 <alg-sip-errors>alg-sip-errors</alg-sip-errors>
 <alg-snmp-errors>alg-snmp-errors</alg-snmp-errors>
 <alg-sqlnet-errors>alg-sqlnet-errors</alg-sqlnet-errors>
 <alg-tftp-errors>alg-tftp-errors</alg-tftp-errors>
 <alg-traceroute-errors>alg-traceroute-errors</alg-traceroute-errors>
</alg-error-counters>
 </sfw-stats-service-set-entry>

Description Extensive output of ALG processing errors.

Contents <alg-bootp-errors>—ALG BOOTP errors.
 <alg-dce-rpc-errors>—ALG DCE-RPC errors.
 <alg-dce-rpc-portmap-errors>—ALG DCE-RPC portmap errors.
 <alg-dns-errors>—ALG DNS errors.
 <alg-exec-errors>—ALG exec errors.
 <alg-ftp-errors>—ALG FTP errors.
 <alg-h323-errors>—ALG H323 errors.
 <alg-icmp-errors>—ALG ICMP errors.
 <alg-iiop-errors>—ALG IIOP errors.
 <alg-login-errors>—ALG login errors.
 <alg-netbios-errors>—ALG NetBIOS errors.
 <alg-netshow-errors>—ALG NetShow errors.

<alg-realaudio-errors>—ALG Real Audio errors.

<alg-rpc-errors>—ALG RPC errors.

<alg-rpc-portmap-errors>—ALG RPC portmap errors.

<alg-rtsp-errors>—ALG Real-Time Streaming Protocol errors.

<alg-shell-errors>—ALG shell errors.

<alg-sip-errors>—ALG Session Initiation Protocol errors.

<alg-snmp-errors>—ALG SNMP errors.

<alg-sqlnet-errors>—ALG SQLNet errors.

<alg-tftp-errors>—ALG TFTP errors.

<alg-traceroute-errors>—ALG traceroute errors.

<base-root-entry>

Usage <pgcpd-active-configuration | gateway-entry>
 <base-root-entry>

```
<normal-mg-execution-time>normal-mg-execution-time</normal-mg-execution-time>
  <mg-provisional-response-timer-value>mg-provisional-response-timer-value
    </mg-provisional-response-timer-value>
  <mg-originated-pending-limit>mg-originated-pending-limit
    </mg-originated-pending-limit>
  <normal-mgc-execution-time>normal-mgc-execution-time
    </normal-mgc-execution-time>
  <mgc-provisional-response-timer-value>mgc-provisional-response-timer-value
    </mgc-provisional-response-timer-value>
  <mgc-originated-pending-limit>mgc-originated-pending-limit
    </mgc-originated-pending-limit>
</base-root-entry>
```

</pgcpd-active-configuration | gateway-entry>

Description No documentation is available yet.

Contents <mg-originated-pending-limit>—No documentation is available yet.

<mg-provisional-response-timer-value>—No documentation is available yet.

<mgc-originated-pending-limit>—No documentation is available yet.

<mgc-provisional-response-timer-value>—No documentation is available yet.

<normal-mg-execution-time>—No documentation is available yet.

<normal-mgc-execution-time>—No documentation is available yet.

<controller-entry>

Usage	<p><pgcpd-active-configuration gateway-entry></p> <pre> <controller-entry> <controller-name>controller-name</controller-name> <remote-ip-address>remote-ip-address</remote-ip-address> <remote-port>remote-port</remote-port> </controller-entry> </pgcpd-active-configuration gateway-entry> </pre>
Description	No documentation is available yet.
Contents	<p><controller-name>—No documentation is available yet.</p> <p><remote-ip-address>—No documentation is available yet.</p> <p><remote-port>—No documentation is available yet.</p>

<cos-stats-service-set-dscp-entry>

Usage	<p><cos-stats-service-set-dscp-information></p> <pre> <cos-stats-service-set-dscp-entry> <received-dscp>received-dscp</received-dscp> <total-received-dscp-packets>total-received-dscp-packets </total-received-dscp-packets> <total-marked-dscp-packets>total-marked-dscp-packets </total-marked-dscp-packets> </cos-stats-service-set-dscp-entry> </cos-stats-service-set-dscp-information> </pre>
Description	Class-of-service service set statistics entry.
Contents	<p><received-dscp>—Received DiffServ Code Point.</p> <p><total-marked-dscp-packets>—Total packets marked per DSCP.</p> <p><total-received-dscp-packets>—Total packets received per DSCP.</p>

<cos-stats-service-set-dscp-information>

Usage	<p><service-cos-statistics-entry></p> <pre> <cos-stats-service-set-dscp-information> <cos-stats-service-set-dscp-entry>...</cos-stats-service-set-dscp-entry> </cos-stats-service-set-dscp-information> </service-cos-statistics-entry> </pre>
Description	No documentation is available yet.
Contents	<cos-stats-service-set-dscp-entry>—Class-of-service service set statistics entry.

<cos-stats-service-set-forwarding-class-entry>

- Usage** <cos-stats-service-set-forwarding-class-information>
 <cos-stats-service-set-forwarding-class-entry>
 <received-forwarding-class>*received-forwarding-class*
 </received-forwarding-class>
 <total-received-forwarding-class-packets>*total-received-forwarding-class-packets*
 </total-received-forwarding-class-packets>
 <total-assigned-forwarding-class-packets>*total-assigned-forwarding-class-packets*
 </total-assigned-forwarding-class-packets>
 </cos-stats-service-set-forwarding-class-entry>
 </cos-stats-service-set-forwarding-class-information>
- Description** Class-of-service service set statistics entry.
- Contents** <received-forwarding-class>—Received forwarding class.
- <total-assigned-forwarding-class-packets>—Total packets assigned per forwarding class.
- <total-received-forwarding-class-packets>—Total packets received per forwarding class.

<cos-stats-service-set-forwarding-class-information>

- Usage** <service-cos-statistics-entry>
 <cos-stats-service-set-forwarding-class-information>
 <cos-stats-service-set-forwarding-class-entry>...
 </cos-stats-service-set-forwarding-class-entry>
 </cos-stats-service-set-forwarding-class-information>
 </service-cos-statistics-entry>
- Description** No documentation is available yet.
- Contents** <cos-stats-service-set-forwarding-class-entry>—Class-of-service service set statistics entry.

<crtp-config-info-entry>

Usage <rpc-reply>
 <crtp-config-info-entry>
 <interface-name>*interface-name*</interface-name>
 <crtp-port-min>*crtp-port-min*</crtp-port-min>
 <crtp-port-max>*crtp-port-max*</crtp-port-max>
 <crtp-tcp-space>*crtp-tcp-space*</crtp-tcp-space>
 <crtp-udp-space>*crtp-udp-space*</crtp-udp-space>
 <crtp-max-period>*crtp-max-period*</crtp-max-period>
 <crtp-max-time>*crtp-max-time*</crtp-max-time>
 <crtp-rtp-queues>*crtp-rtp-queues*</crtp-rtp-queues>
 </crtp-config-info-entry>
 </rpc-reply>

Description Compressed Real-Time Protocol information.

Contents <crtp-max-period>—Number of CRTP packets after which a full header is generated.

<crtp-max-time>—Time after which a full header is generated (seconds).

<crtp-port-max>—RTP UDP maximum port number.

<crtp-port-min>—RTP UDP minimum port number.

<crtp-rtp-queues>—CRTP queues.

<crtp-tcp-space>—Maximum number of TCP compressed sessions negotiated.

<crtp-udp-space>—Maximum number of UDP compressed sessions negotiated.

<interface-name>—Name of the adaptive services interface.

<crtp-counter-table>

Usage <rpc-reply>
 <crtp-counter-table>
 <crtp-counter-name>*crtp-counter-name*</crtp-counter-name>
 <crtp-counter-received>*crtp-counter-received*</crtp-counter-received>
 <crtp-counter-transmit>*crtp-counter-transmit*</crtp-counter-transmit>
 </crtp-counter-table>
 </rpc-reply>

Description No documentation is available yet.

Contents <crtp-counter-name>—CRTP counter name.

<crtp-counter-received>—CRTP receive counter.

<crtp-counter-transmit>—CRTP transmit counter.

<crtp-flow-entry>

Usage	<pre> <service-crtp-flow-table> <crtp-flow-entry> <crtp-flow-context-id>crtp-flow-context-id</crtp-flow-context-id> <crtp-flow-rtp-id>crtp-flow-rtp-id</crtp-flow-rtp-id> <crtp-flow-source-info>crtp-flow-source-info</crtp-flow-source-info> <crtp-flow-destination-info>crtp-flow-destination-info </crtp-flow-destination-info> <crtp-flow-type>crtp-flow-type</crtp-flow-type> </crtp-flow-entry> </service-crtp-flow-table> </pre>
Description	C RTP flow information.
Contents	<p><crtp-flow-context-id>—Context identifier.</p> <p><crtp-flow-destination-info>—Flow destination information (IP address and UDP port).</p> <p><crtp-flow-rtp-id>—RTP SSRC identifier.</p> <p><crtp-flow-source-info>—Flow source information (IP address and UDP port).</p> <p><crtp-flow-type>—Flow type.</p>

<crtp-per-interface-flow-table>

Usage	<pre> <service-crtp-flow-table-information> <crtp-per-interface-flow-table> <interface-name>interface-name</interface-name> <service-crtp-flow-table>...</service-crtp-flow-table> </crtp-per-interface-flow-table> </service-crtp-flow-table-information> </pre>
Description	C RTP flows sorted by interface.
Contents	<p><interface-name>—Name of the adaptive services interface.</p> <p><service-crtp-flow-table>—C RTP flows.</p>

<crtp-stats-entry>

Usage <rpc-reply>
 <crtp-stats-entry>
 <crtp-compression-ratio>*crtp-compression-ratio*</crtp-compression-ratio>
 <crtp-decompression-ratio>*crtp-decompression-ratio*</crtp-decompression-ratio>
 <crtp-sessions-rx>*crtp-sessions-rx*</crtp-sessions-rx>
 <crtp-sessions-tx>*crtp-sessions-tx*</crtp-sessions-tx>
 <crtp-compressed-rx>*crtp-compressed-rx*</crtp-compressed-rx>
 <crtp-compressed-tx>*crtp-compressed-tx*</crtp-compressed-tx>
 <crtp-discards>*crtp-discards*</crtp-discards>
 </crtp-stats-entry>
 </rpc-reply>

Description CRTP statistics.

Contents <crtp-compressed-rx>—CRTP compressed packets received.

<crtp-compressed-tx>—CRTP compressed packets transmitted.

<crtp-compression-ratio>—CRTP compression ratio.

<crtp-decompression-ratio>—CRTP decompression ratio.

<crtp-discards>—CRTP discards.

<crtp-sessions-rx>—CRTP incoming sessions.

<crtp-sessions-tx>—CRTP outgoing sessions.

<drop_counters>

Usage <sfw-stats-service-set-entry>
 <drop_counters>
 <ip-option>*ip-option*</ip-option>
 <syn-defense>*syn-defense*</syn-defense>
 <nat-ports-exhausted>*nat-ports-exhausted*</nat-ports-exhausted>
 </drop_counters>
 </sfw-stats-service-set-entry>

Description Drop counters (rules or resource exhaustion).

Contents <ip-option>—IP option drops.

<nat-ports-exhausted>—NAT ports exhausted.

<syn-defense>—Incomplete TCP handshakes.

<encoding>

Usage	<pre> <h248-options-entry> <encoding> <no-dscp-bit-mirroring><i>no-dscp-bit-mirroring</i></no-dscp-bit-mirroring> </encoding> </h248-options-entry> </pre>
Description	No documentation is available yet.
Contents	<no-dscp-bit-mirroring>—No documentation is available yet.

<error-counters>

Usage	<pre> <sfw-stats-service-set-entry> <error-counters> <ip-errors><i>ip-errors</i></ip-errors> <tcp-errors><i>tcp-errors</i></tcp-errors> <udp-errors><i>udp-errors</i></udp-errors> <icmp-errors><i>icmp-errors</i></icmp-errors> <non-ip-packets><i>non-ip-packets</i></non-ip-packets> <alg-errors><i>alg-errors</i></alg-errors> </error-counters> </sfw-stats-service-set-entry> </pre>
Description	Summarized protocol processing errors.
Contents	<p><alg-errors>—ALG processing errors.</p> <p><icmp-errors>—ICMP processing errors.</p> <p><ip-errors>—IP processing errors.</p> <p><non-ip-packets>—Non-IP packets.</p> <p><tcp-errors>—TCP processing errors.</p> <p><udp-errors>—UDP processing errors.</p>

<existing-flow-counters>

Usage	<pre> <sfw-stats-service-set-entry> <existing-flow-counters> <existing-flow-accepts>existing-flow-accepts</existing-flow-accepts> <existing-flow-discards>existing-flow-discards</existing-flow-discards> <existing-flow-rejects>existing-flow-rejects</existing-flow-rejects> </existing-flow-counters> </sfw-stats-service-set-entry> </pre>
Description	Existing flow counters.
Contents	<p><existing-flow-accepts>—Packets accepted by existing flows.</p> <p><existing-flow-discards>—Packets discarded by existing flows.</p> <p><existing-flow-rejects>—Packets rejected by existing flows.</p>

<fast-update-filters-entry>

Usage	<pre> <pgcpd-active-configuration gateway-entry> <fast-update-filters-entry> <max-terms>max-terms</max-terms> <max-term-percentage>max-term-percentage</max-term-percentage> </fast-update-filters-entry> </pgcpd-active-configuration gateway-entry> </pre>
Description	Firewall filters limitation.
Contents	<p><max-term-percentage>—Maximum percentage of gates with filter terms.</p> <p><max-terms>—Maximum number of filter terms.</p>

<firewall-entry>

Usage	<pre> <pgcpd-active-configuration pgcpd-config> <firewall-entry> <connection-status>connection-status</connection-status> <number-of-terms>number-of-terms</number-of-terms> <number-of-filters>number-of-filters</number-of-filters> </firewall-entry> </pgcpd-active-configuration pgcpd-config> </pre>
Description	No documentation is available yet.
Contents	<p><connection-status>—No documentation is available yet.</p> <p><number-of-filters>—No documentation is available yet.</p> <p><number-of-terms>—No documentation is available yet.</p>

<flow-table-statistics>

Usage <flow-table-statistics-information>

<flow-table-statistics>

```

<interface-name>interface-name</interface-name>
<flow-tables>flow-tables</flow-tables>
<flow>flow</flow>
<flow-peak>flow-peak</flow-peak>
<flow-tcp>flow-tcp</flow-tcp>
<flow-tcp-peak>flow-tcp-peak</flow-tcp-peak>
<flow-udp>flow-udp</flow-udp>
<flow-udp-peak>flow-udp-peak</flow-udp-peak>
<flow-created>flow-created</flow-created>
<flow-freed>flow-freed</flow-freed>
<flow-freed-idle>flow-freed-idle</flow-freed-idle>
<flow-tcp-created>flow-tcp-created</flow-tcp-created>
<flow-tcp-freed>flow-tcp-freed</flow-tcp-freed>
<flow-tcp-freed-idle>flow-tcp-freed-idle</flow-tcp-freed-idle>
<flow-udp-created>flow-udp-created</flow-udp-created>
<flow-udp-freed>flow-udp-freed</flow-udp-freed>
<flow-udp-freed-idle>flow-udp-freed-idle</flow-udp-freed-idle>
<flow-packets-processed>flow-packets-processed</flow-packets-processed>
<flow-packets-errored>flow-packets-errored</flow-packets-errored>
<flow-bytes-processed>flow-bytes-processed</flow-bytes-processed>
<flow-byte-errored>flow-byte-errored</flow-byte-errored>
<flow-tcp-packets-processed>flow-tcp-packets-processed
</flow-tcp-packets-processed>
<flow-tcp-packets-errored>flow-tcp-packets-errored</flow-tcp-packets-errored>
<flow-tcp-packets-errored-bad-flow>flow-tcp-packets-errored-bad-flow
</flow-tcp-packets-errored-bad-flow>
<flow-tcp-bytes-processed>flow-tcp-bytes-processed</flow-tcp-bytes-processed>
<flow-tcp-bytes-errored>flow-tcp-bytes-errored</flow-tcp-bytes-errored>
<flow-udp-packets-processed>flow-udp-packets-processed
</flow-udp-packets-processed>
<flow-udp-packets-errored>flow-udp-packets-errored</flow-udp-packets-errored>
<flow-udp-packets-errored-bad-flow>flow-udp-packets-errored-bad-flow
</flow-udp-packets-errored-bad-flow>
<flow-udp-bytes-processed>flow-udp-bytes-processed</flow-udp-bytes-processed>
<flow-udp-bytes-errored>flow-udp-bytes-errored</flow-udp-bytes-errored>
<flow-icmp-packets-processed>flow-icmp-packets-processed
</flow-icmp-packets-processed>
<flow-icmp-packets-errored>flow-icmp-packets-errored
</flow-icmp-packets-errored>
<flow-icmp-packets-errored-bad-flow>flow-icmp-packets-errored-bad-flow
</flow-icmp-packets-errored-bad-flow>
<flow-icmp-bytes-processed>flow-icmp-bytes-processed
</flow-icmp-bytes-processed>
<flow-icmp-bytes-errored>flow-icmp-bytes-errored</flow-icmp-bytes-errored>
</flow-table-statistics>
</flow-table-statistics-information>

```

Description Statistics for one or more flow tables.

Contents <flow>—Total number of flows in the table.

<flow-byte-errored>—Total bytes for all packets errored by flow table processing.

<flow-bytes-processed>—Total bytes for all packets processed by flow table.

<flow-created>—Total flows created.

<flow-freed>—Total flows freed.

<flow-freed-idle>—Total flows freed by idle flow detection.

<flow-icmp-bytes-errored>—Total bytes for all ICMP packets errored in processing.

<flow-icmp-bytes-processed>—Total bytes for all processed ICMP packets.

<flow-icmp-packets-errored>—Total ICMP packets errored in processing.

<flow-icmp-packets-errored-bad-flow>—Total ICMP packets errored due to referencing an invalid flow.

<flow-icmp-packets-processed>—Total ICMP packets.

<flow-packets-errored>—Total packets errored by flow table processing.

<flow-packets-processed>—Total packets processed by flow table.

<flow-peak>—Sampled peak number of flows in the table.

<flow-tables>—Total number of flow tables being summarized.

<flow-tcp>—Total number of TCP flows in the table.

<flow-tcp-bytes-errored>—Total bytes for all TCP packets errored in processing.

<flow-tcp-bytes-processed>—Total bytes for all processed TCP packets.

<flow-tcp-created>—Total TCP flows created.

<flow-tcp-freed>—Total TCP flows freed.

<flow-tcp-freed-idle>—Total TCP flows freed by idle detection.

<flow-tcp-packets-errored>—Total TCP packets errored in processing.

<flow-tcp-packets-errored-bad-flow>—Total TCP packets errored due to referencing an invalid flow.

<flow-tcp-packets-processed>—Total TCP packets processed.

<flow-tcp-peak>—Sampled peak number of TCP flows in the table.

<flow-udp>—Total number of UDP flows in the table.

<flow-udp-bytes-errored>—Total bytes for all UDP packets errored in processing.

<flow-udp-bytes-processed>—Total bytes for all processed UDP packets.

`<flow-udp-created>`—Total UDP flows created.

`<flow-udp-freed>`—Total UDP flows freed.

`<flow-udp-freed-idle>`—Total UDP flows freed by idle detection.

`<flow-udp-packets-errored>`—Total UDP packets errored in processing.

`<flow-udp-packets-errored-bad-flow>`—Total UDP packets errored due to referencing an invalid flow.

`<flow-udp-packets-processed>`—Total UDP packets processed.

`<flow-udp-peak>`—Peak number of UDP flows in the table.

`<interface-name>`—Name of the adaptive services interface.

`<flow-table-statistics-information>`

Usage `<rpc-reply>`
 `<flow-table-statistics-information>`
 `<flow-table-statistics>...</flow-table-statistics>`
 `</flow-table-statistics-information>`
`</rpc-reply>`

Description No documentation is available yet.

Contents `<flow-table-statistics>`—Statistics for one or more flow tables.

`<fragmenter-entries>`

Usage `<lsqinfo-cpu-usage-information>`
 `<fragmenter-entries>`
 `<fragmenter-entry>...</fragmenter-entry>`
 `</fragmenter-entries>`
`</lsqinfo-cpu-usage-information>`

Description No documentation is available yet.

Contents `<fragmenter-entry>`—Fragmentation CPU usage information.

<fragmenter-entry>

Usage <fragmenter-entries>
 <fragmenter-entry>
 <cpu-name>*cpu-name*</cpu-name>
 <idle>*idle*</idle>
 <timer>*timer*</timer>
 <system>*system*</system>
 <freeback>*freeback*</freeback>
 <drop>*drop*</drop>
 <fragmentation>*fragmentation*</fragmentation>
 <reassembly>*reassembly*</reassembly>
 </fragmenter-entry>
 </fragmenter-entries>

Description Fragmentation CPU usage information.

Contents <cpu-name>— CPU name.

<drop>—Percentage of CPU time taken by Drop thread.

<fragmentation>—Percentage of CPU time taken by Fragmentation thread.

<freeback>—Percentage of CPU time taken by Freeback thread.

<idle>—Percentage of CPU time taken by Idle thread.

<reassembly>—Percentage of CPU time taken by reassembly thread.

<system>—Percentage of CPU time taken by System thread.

<timer>—Percentage of CPU time taken by Timer thread.

<gate-fuf-statistics-information>

Usage <service-pgcp-gate-entry-information>
 <gate-fuf-statistics-information>
 <gate-fuf-policer-drop-count>*gate-fuf-policer-drop-count*
 </gate-fuf-policer-drop-count>
 </gate-fuf-statistics-information>
 </service-pgcp-gate-entry-information>

Description FUF statistics.

Contents <gate-fuf-policer-drop-count>—Number of dropped policer packets.

<gate-rtcp-information>

- Usage** <service-pgcp-gate-entry-information>
 <gate-rtcp-information>
 <gate-rtcp-sender-information>...</gate-rtcp-sender-information>
 <gate-rtcp-receiver-information>...</gate-rtcp-receiver-information>
 </gate-rtcp-information>
 </service-pgcp-gate-entry-information>
- Description** No documentation is available yet.
- Contents** <gate-rtcp-receiver-information>—RTCP receiver reports.
 <gate-rtcp-sender-information>—RTCP statistics.

<gate-rtcp-receiver-entry>

- Usage** <gate-rtcp-receiver-information>
 <gate-rtcp-receiver-entry>
 <gate-rtcp-received-ssrc>*gate-rtcp-received-ssrc*</gate-rtcp-received-ssrc>
 <gate-rtcp-receiver-lost-pkts>*gate-rtcp-receiver-lost-pkts*
 </gate-rtcp-receiver-lost-pkts>
 <gate-rtcp-receiver-lost-pkt-fraction>*gate-rtcp-receiver-lost-pkt-fraction*
 </gate-rtcp-receiver-lost-pkt-fraction>
 <gate-rtcp-receiver-jitter>*gate-rtcp-receiver-jitter*
 </gate-rtcp-receiver-jitter>
 </gate-rtcp-receiver-entry>
 </gate-rtcp-receiver-information>
- Description** No documentation is available yet.
- Contents** <gate-rtcp-received-ssrc>—RTP Synchronization source.
 <gate-rtcp-receiver-jitter>—Jitter for received packets.
 <gate-rtcp-receiver-lost-pkt-fraction>—Fraction of packets lost.
 <gate-rtcp-receiver-lost-pkts>—Number of packets lost.

<gate-rtcp-receiver-information>

- Usage** <gate-rtcp-information>
 <gate-rtcp-receiver-information>
 <gate-rtcp-receiver-entry>...</gate-rtcp-receiver-entry>
 </gate-rtcp-receiver-information>
 </gate-rtcp-information>
- Description** RTCP receiver reports.
- Contents** <gate-rtcp-receiver-entry>—No documentation is available yet.

<gate-rtcp-sender-information>

Usage <gate-rtcp-information>
 <gate-rtcp-sender-information>
 <gate-rtcp-sender-ssrc>*gate-rtcp-sender-ssrc*</gate-rtcp-sender-ssrc>
 <gate-rtcp-sender-octets>*gate-rtcp-sender-octets*</gate-rtcp-sender-octets>
 <gate-rtcp-sender-pkts>*gate-rtcp-sender-pkts*</gate-rtcp-sender-pkts>
 <gate-rtcp-invalid-pkts>*gate-rtcp-invalid-pkts*</gate-rtcp-invalid-pkts>
 </gate-rtcp-sender-information>
 </gate-rtcp-information>

Description RTCP statistics.

Contents <gate-rtcp-invalid-pkts>—Invalid RTCP packets.

<gate-rtcp-sender-octets>—Number of bytes sent.

<gate-rtcp-sender-pkts>—Number of packets sent.

<gate-rtcp-sender-ssrc>—RTP Synchronization source.

<gateway-entry>

Usage <pgcpd-active-configuration | pgcpd-config | service-pgcp-statistics-gateway | service-pgcp-terminations | service-pgcp-gates>

```

<gateway-entry>
  <gateway-name>gateway-name</gateway-name>
  <local-ip-address>local-ip-address</local-ip-address>
  <local-port>local-port</local-port>
  <service-state>service-state</service-state>
  <active-controller>active-controller</active-controller>
  <replication-socket>replication-socket</replication-socket>
  <cleanup-timeout>cleanup-timeout</cleanup-timeout>
  <inactivity-timeout-delay>inactivity-timeout-delay</inactivity-timeout-delay>
  <inactivity-timeout-duration>inactivity-timeout-duration
    </inactivity-timeout-duration>
  <latch-deadlock-duration>latch-deadlock-duration</latch-deadlock-duration>
  <h248-timers-entry>...</h248-timers-entry>
  <base-root-entry>...</base-root-entry>
  <h248-options-entry>...</h248-options-entry>
  <h248-segmentation-properties-entry>...</h248-segmentation-properties-entry>
  <h248-diffserv-entry>...</h248-diffserv-entry>
  <h248-notification-behavior-entry>...</h248-notification-behavior-entry>
  <h248-application-data-inactivity-detection-entry>...
    </h248-application-data-inactivity-detection-entry>
  <h248-event-timestamp-notification-entry>...
    </h248-event-timestamp-notification-entry>
  <inactivity-timer-entry>...</inactivity-timer-entry>
  <fast-update-filters-entry>...</fast-update-filters-entry>
  <controller-entry>...</controller-entry>
  <overload-control-entry>...</overload-control-entry>
</gateway-entry>
</pgcpd-active-configuration | pgcpd-config | service-pgcp-statistics-gateway |
service-pgcp-terminations | service-pgcp-gates>

```

Description No documentation is available yet.

Contents

- <active-controller>—No documentation is available yet.
- <base-root-entry>—No documentation is available yet.
- <cleanup-timeout>—No documentation is available yet.
- <controller-entry>—No documentation is available yet.
- <fast-update-filters-entry>—Firewall filters limitation.
- <gateway-name>—No documentation is available yet.
- <h248-application-data-inactivity-detection-entry>—No documentation is available yet.
- <h248-diffserv-entry>—No documentation is available yet.
- <h248-event-timestamp-notification-entry>—No documentation is available yet.

<h248-notification-behavior-entry>—No documentation is available yet.

<h248-options-entry>—No documentation is available yet.

<h248-segmentation-properties-entry>—No documentation is available yet.

<h248-timers-entry>—No documentation is available yet.

<inactivity-timeout-delay>—No documentation is available yet.

<inactivity-timeout-duration>—No documentation is available yet.

<inactivity-timer-entry>—No documentation is available yet.

<latch-deadlock-duration>—No documentation is available yet.

<local-ip-address>—No documentation is available yet.

<local-port>—No documentation is available yet.

<overload-control-entry>—No documentation is available yet.

<replication-socket>—No documentation is available yet.

<service-state>—No documentation is available yet.

<h248-application-data-inactivity-detection-entry>

Usage <pgcpd-active-configuration | gateway-entry>
 <h248-application-data-inactivity-detection-entry>
 <ip-flow-stop-detection>*ip-flow-stop-detection*</ip-flow-stop-detection>
 </h248-application-data-inactivity-detection-entry>
 </pgcpd-active-configuration | gateway-entry>

Description No documentation is available yet.

Contents <ip-flow-stop-detection>—Notify behavior to media inactivity event.

<h248-diffserv-entry>

Usage <pgcpd-active-configuration | gateway-entry>
 <h248-diffserv-entry>
 <dscp>*dscp*</dscp>
 </h248-diffserv-entry>
 </pgcpd-active-configuration | gateway-entry>

Description No documentation is available yet.

Contents <dscp>—No documentation is available yet.

<h248-event-timestamp-notification-entry>

- Usage** <pgcpd-active-configuration | gateway-entry>
<h248-event-timestamp-notification-entry>
 <requested-timestamp>*requested-timestamp*</requested-timestamp>
</h248-event-timestamp-notification-entry>
 </pgcpd-active-configuration | gateway-entry>
- Description** No documentation is available yet.
- Contents** <requested-timestamp>—Notification timestamp.

<h248-notification-behavior-entry>

- Usage** <pgcpd-active-configuration | gateway-entry>
<h248-notification-behavior-entry>
 <notification-regulation>*notification-regulation*</notification-regulation>
</h248-notification-behavior-entry>
 </pgcpd-active-configuration | gateway-entry>
- Description** No documentation is available yet.
- Contents** <notification-regulation>—Notify regulation.

<h248-options-entry>

- Usage** <pgcpd-active-configuration | gateway-entry>
<h248-options-entry>
 <wildcard-response-service-change>*wildcard-response-service-change*
 </wildcard-response-service-change>
 <suppress-sc-forced-state-loss>*suppress-sc-forced-state-loss*
 </suppress-sc-forced-state-loss>
 <audit-observed-events-returns-history>*audit-observed-events-returns-history*
 </audit-observed-events-returns-history>
 <encoding>...</encoding>
</h248-options-entry>
 </pgcpd-active-configuration | gateway-entry>
- Description** No documentation is available yet.
- Contents** <audit-observed-events-returns-history>—Activation of event history.
- <encoding>—No documentation is available yet.
- <suppress-sc-forced-state-loss>—No documentation is available yet.
- <wildcard-response-service-change>—No documentation is available yet.

<h248-segmentation-properties-entry>

Usage <pgcpd-active-configuration | gateway-entry>
<h248-segmentation-properties-entry>
 <mg-segmentation-timer>*mg-segmentation-timer*</mg-segmentation-timer>
 <mg-maximum-pdu-size>*mg-maximum-pdu-size*</mg-maximum-pdu-size>
 <mgc-segmentation-timer>*mgc-segmentation-timer*</mgc-segmentation-timer>
 <mgc-maximum-pdu-size>*mgc-maximum-pdu-size*</mgc-maximum-pdu-size>
</h248-segmentation-properties-entry>
 </pgcpd-active-configuration | gateway-entry>

Description No documentation is available yet.

Contents <mg-maximum-pdu-size>—No documentation is available yet.
 <mg-segmentation-timer>—No documentation is available yet.
 <mgc-maximum-pdu-size>—No documentation is available yet.
 <mgc-segmentation-timer>—No documentation is available yet.

<h248-timers-entry>

Usage <pgcpd-active-configuration | gateway-entry>
<h248-timers-entry>
 <maximum-waiting-delay>*maximum-waiting-delay*</maximum-waiting-delay>
 <tmax-retransmission-delay>*tmax-retransmission-delay*
 </tmax-retransmission-delay>
 <initial-average-ack-delay>*initial-average-ack-delay*
 </initial-average-ack-delay>
 <maximum-net-propagation-delay>*maximum-net-propagation-delay*
 </maximum-net-propagation-delay>
</h248-timers-entry>
 </pgcpd-active-configuration | gateway-entry>

Description No documentation is available yet.

Contents <initial-average-ack-delay>—No documentation is available yet.
 <maximum-net-propagation-delay>—No documentation is available yet.
 <maximum-waiting-delay>—No documentation is available yet.
 <tmax-retransmission-delay>—No documentation is available yet.

<header-redirect-set-statistics>

Usage <header-redirect-set-statistics-information>
 <header-redirect-set-statistics>
 <header-redirect-set-name>*header-redirect-set-name*</header-redirect-set-name>
 <cause-roaming>*cause-roaming*</cause-roaming>
 <cause-time-of-day>*cause-time-of-day*</cause-time-of-day>
 <cause-quality-of-service>*cause-quality-of-service*</cause-quality-of-service>
 <cause-volume-expired>*cause-volume-expired*</cause-volume-expired>
 <cause-cost-warning>*cause-cost-warning*</cause-cost-warning>
 <cause-not-allowed>*cause-not-allowed*</cause-not-allowed>
 <cause-unsubscribed>*cause-unsubscribed*</cause-unsubscribed>
 <cause-credit-expiry>*cause-credit-expiry*</cause-credit-expiry>
 <cause-unknown>*cause-unknown*</cause-unknown>
 <cause-default>*cause-default*</cause-default>
 </header-redirect-set-statistics>
 </header-redirect-set-statistics-information>

Description Statistics for the header redirect sets.

Contents <cause-cost-warning>—Number of redirects due to cost warning limit.
 <cause-credit-expiry>—Number of redirects due to expiration of credit.
 <cause-default>—Number of redirects due to default reason match.
 <cause-not-allowed>—Number of redirects due to disallowed service class.
 <cause-quality-of-service>—Number of redirects due to QoS.
 <cause-roaming>—Number of redirects due to roaming.
 <cause-time-of-day>—Number of redirects due to time of day.
 <cause-unknown>—Number of redirects due to unknown reason.
 <cause-unsubscribed>—Number of redirects due to unsubscribed service class.
 <cause-volume-expired>—Number of redirects due to expiration of volume limit.
 <header-redirect-set-name>—Name of the header redirect set.

<header-redirect-set-statistics-information>

Usage <rpc-reply>
 <header-redirect-set-statistics-information>
 <interface-name>*interface-name*</interface-name>
 <interfaces>*interfaces*</interfaces>
 <header-redirect-set-statistics>...</header-redirect-set-statistics>
 </header-redirect-set-statistics-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <header-redirect-set-statistics>—Statistics for the header redirect sets.

<interface-name>—Name of the adaptive services interface.

<interfaces>—Total number of interfaces summarized.

<icmp-error-counters>

Usage <sfw-stats-service-set-entry>
 <icmp-error-counters>
 <icmp-length-error>*icmp-length-error*</icmp-length-error>
 <icmp-error-length-error>*icmp-error-length-error*</icmp-error-length-error>
 <ping-duplicate-sequence-number>*ping-duplicate-sequence-number*
 </ping-duplicate-sequence-number>
 <ping-mismatched-sequence-number>*ping-mismatched-sequence-number*
 </ping-mismatched-sequence-number>
 </icmp-error-counters>
 </sfw-stats-service-set-entry>

Description Extensive output of ICMP processing errors.

Contents <icmp-error-length-error>—ICMP error length inconsistencies.

<icmp-length-error>—IP data length less than minimum ICMP header length (8 bytes).

<ping-duplicate-sequence-number>—Duplicate ping sequence number.

<ping-mismatched-sequence-number>—Mismatched ping sequence number.

<ids-anomaly-entry>

Usage <ids-flow-entry>
 <ids-anomaly-entry>
 <ids-anomaly-description>*ids-anomaly-description*</ids-anomaly-description>
 <ids-anomaly-count>*ids-anomaly-count*</ids-anomaly-count>
 <ids-anomaly-rate>*ids-anomaly-rate*</ids-anomaly-rate>
 <ids-anomaly-elapsed>*ids-anomaly-elapsed*</ids-anomaly-elapsed>
 </ids-anomaly-entry>
 </ids-flow-entry>

Description IDS anomaly information.

Contents <ids-anomaly-count>—Number of anomalies for current type.

<ids-anomaly-description>—Anomaly description.

<ids-anomaly-elapsed>—Elapsed time from last event.

<ids-anomaly-rate>—Rate of anomalies (events per second).

<ids-flow-entry>

Usage <ids-flow-table>
 <ids-flow-entry>
 <ids-flow-source-ip>*ids-flow-source-ip*</ids-flow-source-ip>
 <ids-flow-destination-ip>*ids-flow-destination-ip*</ids-flow-destination-ip>
 <ids-flow-time>*ids-flow-time*</ids-flow-time>
 <ids-flow-flags>*ids-flow-flags*</ids-flow-flags>
 <ids-flow-long-flags>*ids-flow-long-flags*</ids-flow-long-flags>
 <ids-flow-count>*ids-flow-count*</ids-flow-count>
 <ids-flow-application>*ids-flow-application*</ids-flow-application>
 <ids-bytes-count>*ids-bytes-count*</ids-bytes-count>
 <ids-packets-count>*ids-packets-count*</ids-packets-count>
 <ids-flows-count>*ids-flows-count*</ids-flows-count>
 <ids-anomalies-count>*ids-anomalies-count*</ids-anomalies-count>
 <ids-anomaly-entry>...</ids-anomaly-entry>
 </ids-flow-entry>
 </ids-flow-table>

Description IDS terse information.

Contents <ids-anomalies-count>—Number of anomalies.

<ids-anomaly-entry>—IDS anomaly information.

<ids-bytes-count>—Number of bytes.

<ids-flow-application>—Application name.

<ids-flow-count>—Value depend from request (packet number, bytes, and so on).

<ids-flow-destination-ip>—Destination IP address.

<ids-flow-flags>—S - SYN cookie enabled, F - Forced entry.

<ids-flow-long-flags>—SYN cookie enabled, Forced entry.

<ids-flow-source-ip>—Source IP address.

<ids-flow-time>—Time from last event.

<ids-flows-count>—Number of flows.

<ids-packets-count>—Number of packets.

<ids-flow-table>

- Usage** <ids-per-service-set-flow-table>
 <ids-flow-table>
 <ids-flow-entry>...</ids-flow-entry>
 </ids-flow-table>
 </ids-per-service-set-flow-table>
- Description** IDS table sorted by service set.
- Contents** <ids-flow-entry>—IDS terse information.

<ids-per-service-set-flow-table>

- Usage** <service-ids-flow-table-information>
 <ids-per-service-set-flow-table>
 <service-set-name>service-set-name</service-set-name>
 <interface-name>interface-name</interface-name>
 <ids-sort-order>ids-sort-order</ids-sort-order>
 <ids-flow-table>...</ids-flow-table>
 </ids-per-service-set-flow-table>
 </service-ids-flow-table-information>
- Description** IDS table sorted by service set.
- Contents** <ids-flow-table>—IDS table sorted by service set.
- <ids-sort-order>—IDS table sorting order.
- <interface-name>—Name of the adaptive services interface.
- <service-set-name>—Name of the service set.

<ids-show-summary>

- Usage** <service-ids-flow-table-information>
 <ids-show-summary>
 <interface-name>interface-name</interface-name>
 <ids-total-entries>ids-total-entries</ids-total-entries>
 <ids-total-failed-insertions>ids-total-failed-insertions
 </ids-total-failed-insertions>
 <ids-total-events>ids-total-events</ids-total-events>
 </ids-show-summary>
 </service-ids-flow-table-information>
- Description** IDS table summary.
- Contents** <ids-total-entries>—Total number of filled entries in IDS table.
- <ids-total-events>—Total number of events (closed flows and anomalies).
- <ids-total-failed-insertions>—Total number of failed IDS table entry insertions.
- <interface-name>—Name of the adaptive services interface.

<inactivity-timer-entry>

Usage <pgcpd-active-configuration | gateway-entry>
 <inactivity-timer-entry>
 <detect>*detect*</detect>
 <maximum-inactivity-time>*maximum-inactivity-time*</maximum-inactivity-time>
 </inactivity-timer-entry>
</pgcpd-active-configuration | gateway-entry>

Description No documentation is available yet.

Contents <detect>—Detect inactivity timeout.
 <maximum-inactivity-time>—Default maximum inactivity timeout.

<ip-error-counters>

Usage	<pre> <sfw-stats-service-set-entry> <ip-error-counters> <ip-length-error>ip-length-error</ip-length-error> <ip-header-length-error>ip-header-length-error</ip-header-length-error> <long-packet>long-packet</long-packet> <illegal-source-address>illegal-source-address</illegal-source-address> <illegal-destination-address>illegal-destination-address </illegal-destination-address> <ttl-zero>ttl-zero</ttl-zero> <illegal-ip-protocol>illegal-ip-protocol</illegal-ip-protocol> <land-attack>land-attack</land-attack> <non-ipv4>non-ipv4</non-ipv4> <bad-checksum>bad-checksum</bad-checksum> <illegal-fragment-length>illegal-fragment-length</illegal-fragment-length> <fragment-overlap>fragment-overlap</fragment-overlap> <fragment-reassembly-timeout>fragment-reassembly-timeout </fragment-reassembly-timeout> <unknown>unknown</unknown> </ip-error-counters> </sfw-stats-service-set-entry> </pre>
Description	Extensive output of IP processing errors.
Contents	<p><bad-checksum>—Bad checksum.</p> <p><fragment-overlap>—IP fragment overlap.</p> <p><fragment-reassembly-timeout>—IP fragment reassembly timeout.</p> <p><illegal-destination-address>—Illegal destination address.</p> <p><illegal-fragment-length>—Illegal IP fragment length.</p> <p><illegal-ip-protocol>—Illegal IP protocol number (0 or 255).</p> <p><illegal-source-address>—Illegal source address.</p> <p><ip-header-length-error>—Minimum IP header length check failures.</p> <p><ip-length-error>—IP packet length inconsistencies.</p> <p><land-attack>—IP source address same as destination address.</p> <p><long-packet>—Reassembled packet exceeds maximum IP length (65,535 bytes).</p> <p><non-ipv4>—Non-IPv4 packets.</p> <p><ttl-zero>—IP packets received with a TTL value of 0.</p> <p><unknown>—Unknown errors.</p>

<l2tp-multilink-clear-entry>

Usage	<pre><service-l2tp-multilink-clear-information> <l2tp-multilink-clear-entry> <l2tp-multilink-bundle-id>l2tp-multilink-bundle-id</l2tp-multilink-bundle-id> </l2tp-multilink-clear-entry> </service-l2tp-multilink-clear-information></pre>
Description	Multilink information cleared by L2TP.
Contents	<l2tp-multilink-bundle-id>—Bundle ID.

<l2tp-multilink-entry>

Usage <services-l2tp-multilink-information>
<l2tp-multilink-entry>
 <l2tp-multilink-bundle-id>l2tp-multilink-bundle-id</l2tp-multilink-bundle-id>
 <l2tp-multilink-bundle-endpoint>l2tp-multilink-bundle-endpoint
 </l2tp-multilink-bundle-endpoint>
 <l2tp-multilink-bundle-num-links>l2tp-multilink-bundle-num-links
 </l2tp-multilink-bundle-num-links>
 <l2tp-multilink-bundle-mrru-input>l2tp-multilink-bundle-mrru-input
 </l2tp-multilink-bundle-mrru-input>
 <l2tp-multilink-bundle-mrru-output>l2tp-multilink-bundle-mrru-output
 </l2tp-multilink-bundle-mrru-output>
 <l2tp-statistics-since>l2tp-statistics-since</l2tp-statistics-since>
 <l2tp-control-tx-packets>l2tp-control-tx-packets</l2tp-control-tx-packets>
 <l2tp-control-rx-packets>l2tp-control-rx-packets</l2tp-control-rx-packets>
 <l2tp-data-tx-packets>l2tp-data-tx-packets</l2tp-data-tx-packets>
 <l2tp-data-rx-packets>l2tp-data-rx-packets</l2tp-data-rx-packets>
 <l2tp-control-tx-bytes>l2tp-control-tx-bytes</l2tp-control-tx-bytes>
 <l2tp-control-rx-bytes>l2tp-control-rx-bytes</l2tp-control-rx-bytes>
 <l2tp-data-tx-bytes>l2tp-data-tx-bytes</l2tp-data-tx-bytes>
 <l2tp-data-rx-bytes>l2tp-data-rx-bytes</l2tp-data-rx-bytes>
 <l2tp-error-tx-packets>l2tp-error-tx-packets</l2tp-error-tx-packets>
 <l2tp-error-rx-packets>l2tp-error-rx-packets</l2tp-error-rx-packets>
 <l2tp-multilink-links>...</l2tp-multilink-links>
</l2tp-multilink-entry>
 </services-l2tp-multilink-information>

Description L2TP multilink information.

Contents <l2tp-control-rx-bytes>—Control receive bytes.
 <l2tp-control-rx-packets>—Control receive packets.
 <l2tp-control-tx-bytes>—Control transmit bytes.
 <l2tp-control-tx-packets>—Control transmit packets.
 <l2tp-data-rx-bytes>—Data receive bytes.
 <l2tp-data-rx-packets>—Data receive packets.
 <l2tp-data-tx-bytes>—Data transmit bytes.
 <l2tp-data-tx-packets>—Data transmit packets.
 <l2tp-error-rx-packets>—Error receive packets.
 <l2tp-error-tx-packets>—Error transmit packets.
 <l2tp-multilink-bundle-endpoint>—Bundle endpoint.
 <l2tp-multilink-bundle-id>—Bundle ID.
 <l2tp-multilink-bundle-mrru-input>—Input MRRU.

`<l2tp-multilink-bundle-mrru-output>`—Output MRRU.

`<l2tp-multilink-bundle-num-links>`—Number of links in a bundle.

`<l2tp-multilink-links>`—L2TP multilink bundle links.

`<l2tp-statistics-since>`—Statistics since the displayed time.

`<l2tp-multilink-links>`

Usage `<l2tp-multilink-entry>`
 `<l2tp-multilink-links>`
 `<l2tp-session-entry>...</l2tp-session-entry>`
 `</l2tp-multilink-links>`
`</l2tp-multilink-entry>`

Description L2TP multilink bundle links.

Contents `<l2tp-session-entry>`—L2TP session information.

`<l2tp-per-tunnel-group-tunnel-table>`

Usage `<service-l2tp-tunnel-information>`
 `<l2tp-per-tunnel-group-tunnel-table>`
 `<tunnel-group-name>tunnel-group-name</tunnel-group-name>`
 `<interface-name>interface-name</interface-name>`
 `<l2tp-tunnel-table>...</l2tp-tunnel-table>`
 `</l2tp-per-tunnel-group-tunnel-table>`
`</service-l2tp-tunnel-information>`

Description Tunnel table sorted by tunnel group.

Contents `<interface-name>`—Name of the adaptive services interface.

`<l2tp-tunnel-table>`—L2TP tunnel table sorted by tunnel group.

`<tunnel-group-name>`—Name of the tunnel group.

<l2tp-per-tunnel-session-table>

Usage <service-l2tp-session-information>
 <l2tp-per-tunnel-session-table>
 <tunnel-group-name>*tunnel-group-name*</tunnel-group-name>
 <interface-name>*interface-name*</interface-name>
 <l2tp-tunnel-local-id>*l2tp-tunnel-local-id*</l2tp-tunnel-local-id>
 <l2tp-session-table>...</l2tp-session-table>
 </l2tp-per-tunnel-session-table>
 </service-l2tp-session-information>

Description Session table sorted by tunnel.

Contents <interface-name>—Name of the adaptive services interface.
 <l2tp-session-table>—L2TP session table sorted by tunnel ID.
 <l2tp-tunnel-local-id>—Local ID of tunnel.
 <tunnel-group-name>—Name of the tunnel group.

<l2tp-session-clear-entry>

Usage <service-l2tp-session-clear-information>
 <l2tp-session-clear-entry>
 <l2tp-session-local-id>*l2tp-session-local-id*</l2tp-session-local-id>
 </l2tp-session-clear-entry>
 </service-l2tp-session-clear-information>

Description L2TP cleared session information.

Contents <l2tp-session-local-id>—Local ID of session.

<l2tp-session-entry>**Usage** <l2tp-session-table | l2tp-multilink-links>**<l2tp-session-entry>**

```

<l2tp-session-local-id>l2tp-session-local-id</l2tp-session-local-id>
<l2tp-session-remote-id>l2tp-session-remote-id</l2tp-session-remote-id>
<l2tp-session-remote-ip>l2tp-session-remote-ip</l2tp-session-remote-ip>
<l2tp-session-local-ip>l2tp-session-local-ip</l2tp-session-local-ip>
<l2tp-session-state>l2tp-session-state</l2tp-session-state>
<l2tp-session-bundle-id>l2tp-session-bundle-id</l2tp-session-bundle-id>
<l2tp-session-user-name>l2tp-session-user-name</l2tp-session-user-name>
<l2tp-session-own-ip>l2tp-session-own-ip</l2tp-session-own-ip>
<l2tp-session-peer-ip>l2tp-session-peer-ip</l2tp-session-peer-ip>
<l2tp-session-local-name>l2tp-session-local-name</l2tp-session-local-name>
<l2tp-session-remote-name>l2tp-session-rem-name</l2tp-session-remote-name>
<l2tp-session-mode>l2tp-session-mode</l2tp-session-mode>
<l2tp-session-local-mru>l2tp-session-local-mru</l2tp-session-local-mru>
<l2tp-session-remote-mru>l2tp-session-remote-mru</l2tp-session-remote-mru>
<l2tp-session-tx-speed>l2tp-session-tx-speed</l2tp-session-tx-speed>
<l2tp-session-rx-speed>l2tp-session-rx-speed</l2tp-session-rx-speed>
<l2tp-session-bearer-type>l2tp-session-bearer-type</l2tp-session-bearer-type>
<l2tp-session-framing-type>l2tp-session-framing-type
    </l2tp-session-framing-type>
<l2tp-session-lcp-renegotiation>l2tp-session-lcp-renegotiation
    </l2tp-session-lcp-renegotiation>
<l2tp-session-authentication>l2tp-session-authentication
    </l2tp-session-authentication>
<l2tp-session-interface-id>l2tp-session-interface-id
    </l2tp-session-interface-id>
<l2tp-session-interface-unit>l2tp-session-interface-unit
    </l2tp-session-interface-unit>
<l2tp-session-call-serial-number>l2tp-session-call-serial-number
    </l2tp-session-call-serial-number>
<l2tp-session-policer-bandwidth>l2tp-session-policer-bandwidth
    </l2tp-session-policer-bandwidth>
<l2tp-session-policer-exclude-bandwidth>l2tp-session-policer-exclude-bandwidth
    </l2tp-session-policer-exclude-bandwidth>
<l2tp-session-policer-burstsize>l2tp-session-policer-burstsize
    </l2tp-session-policer-burstsize>
<l2tp-session-firewall-filter>l2tp-session-firewall-filter
    </l2tp-session-firewall-filter>
<l2tp-session-encapsulation-overhead>l2tp-session-encapsulation-overhead
    </l2tp-session-encapsulation-overhead>
<l2tp-session-cell-overhead>l2tp-session-cell-overhead
    </l2tp-session-cell-overhead>
<l2tp-session-create-time>l2tp-session-create-time</l2tp-session-create-time>
<l2tp-statistics-since>l2tp-statistics-since</l2tp-statistics-since>
<l2tp-control-tx-packets>l2tp-control-tx-packets</l2tp-control-tx-packets>
<l2tp-control-rx-packets>l2tp-control-rx-packets</l2tp-control-rx-packets>
<l2tp-data-tx-packets>l2tp-data-tx-packets</l2tp-data-tx-packets>
<l2tp-data-rx-packets>l2tp-data-rx-packets</l2tp-data-rx-packets>
<l2tp-control-tx-bytes>l2tp-control-tx-bytes</l2tp-control-tx-bytes>
<l2tp-control-rx-bytes>l2tp-control-rx-bytes</l2tp-control-rx-bytes>
<l2tp-data-tx-bytes>l2tp-data-tx-bytes</l2tp-data-tx-bytes>

```

```

<l2tp-data-rx-bytes>l2tp-data-rx-bytes</l2tp-data-rx-bytes>
<l2tp-error-tx-packets>l2tp-error-tx-packets</l2tp-error-tx-packets>
<l2tp-error-rx-packets>l2tp-error-rx-packets</l2tp-error-rx-packets>
<l2tp-create-time>l2tp-create-time</l2tp-create-time>
<l2tp-up-time>l2tp-up-time</l2tp-up-time>
<l2tp-idle-time>l2tp-idle-time</l2tp-idle-time>
</l2tp-session-entry>
</l2tp-session-table | l2tp-multilink-links>

```

Description L2TP session information.

Contents <l2tp-control-rx-bytes>—Control receive bytes.

<l2tp-control-rx-packets>—Control receive packets.

<l2tp-control-tx-bytes>—Control transmit bytes.

<l2tp-control-tx-packets>—Control transmit packets.

<l2tp-create-time>—Creation time.

<l2tp-data-rx-bytes>—Data receive bytes.

<l2tp-data-rx-packets>—Data receive packets.

<l2tp-data-tx-bytes>—Data transmit bytes.

<l2tp-data-tx-packets>—Data transmit packets.

<l2tp-error-rx-packets>—Error receive packets.

<l2tp-error-tx-packets>—Error transmit packets.

<l2tp-idle-time>—Idle time.

<l2tp-session-authentication>—Session authentication.

<l2tp-session-bearer-type>—Session bearer type.

<l2tp-session-bundle-id>—Session bundle ID.

<l2tp-session-call-serial-number>—Session call serial number.

<l2tp-session-cell-overhead>—Session cell overhead.

<l2tp-session-create-time>—Session create time.

<l2tp-session-encapsulation-overhead>—Session encapsulation overhead.

<l2tp-session-firewall-filter>—Session firewall filter name.

<l2tp-session-framing-type>—Session framing type.

<l2tp-session-interface-id>—Session interface ID.

<l2tp-session-interface-unit>—Session interface unit.

<l2tp-session-lcp-renegotiation>—Session LCP renegotiation.

<l2tp-session-local-id>—Local ID of session.

<l2tp-session-local-ip>—Local IP address of session.

<l2tp-session-local-mru>—Session local MRU.

<l2tp-session-local-name>—Name of session local end.

<l2tp-session-mode>—Session mode.

<l2tp-session-own-ip>—Local own IP address assigned to session.

<l2tp-session-peer-ip>—IP address assigned to peer for the session.

<l2tp-session-policer-bandwidth>—Session policer bandwidth.

<l2tp-session-policer-burstsize>—Session policer burst size.

<l2tp-session-policer-exclude-bandwidth>—Session policer exclude bandwidth.

<l2tp-session-remote-id>—Remote ID of session.

<l2tp-session-remote-ip>—Remote IP address of session.

<l2tp-session-remote-mru>—Session remote MRU.

<l2tp-session-remote-name>—Name of session remote end.

<l2tp-session-rx-speed>—Session receive speed.

<l2tp-session-state>—Session state.

<l2tp-session-tx-speed>—Session transmit speed.

<l2tp-session-user-name>—Session user name.

<l2tp-statistics-since>—Statistics since the displayed time.

<l2tp-up-time>—Up time.

<l2tp-session-table>

Usage	<pre> <l2tp-per-tunnel-session-table> <l2tp-session-table> <l2tp-session-entry>...</l2tp-session-entry> </l2tp-session-table> </l2tp-per-tunnel-session-table> </pre>
Description	L2TP session table sorted by tunnel ID.
Contents	<l2tp-session-entry>—L2TP session information.

<l2tp-summary-table>

Usage <service-l2tp-summary-information>
<l2tp-summary-table>
 <l2tp-tunnels>l2tp-tunnels</l2tp-tunnels>
 <l2tp-sessions>l2tp-sessions</l2tp-sessions>
 <l2tp-error-tx-packets>l2tp-error-tx-packets</l2tp-error-tx-packets>
 <l2tp-error-rx-packets>l2tp-error-rx-packets</l2tp-error-rx-packets>
 <l2tp-control-tx-packets>l2tp-control-tx-packets</l2tp-control-tx-packets>
 <l2tp-control-rx-packets>l2tp-control-rx-packets</l2tp-control-rx-packets>
 <l2tp-interface-error-tx-packets>l2tp-interface-error-tx-packets
 </l2tp-interface-error-tx-packets>
 <l2tp-interface-error-rx-packets>l2tp-interface-error-rx-packets
 </l2tp-interface-error-rx-packets>
 <l2tp-interface-control-tx-packets>l2tp-interface-control-tx-packets
 </l2tp-interface-control-tx-packets>
 <l2tp-interface-control-rx-packets>l2tp-interface-control-rx-packets
 </l2tp-interface-control-rx-packets>
 <l2tp-control-memory-bytes>l2tp-control-memory-bytes
 </l2tp-control-memory-bytes>
 <l2tp-data-tx-packets>l2tp-data-tx-packets</l2tp-data-tx-packets>
 <l2tp-data-rx-packets>l2tp-data-rx-packets</l2tp-data-rx-packets>
 <l2tp-interface-data-tx-packets>l2tp-interface-data-tx-packets
 </l2tp-interface-data-tx-packets>
 <l2tp-interface-data-rx-packets>l2tp-interface-data-rx-packets
 </l2tp-interface-data-rx-packets>
 <l2tp-data-memory-bytes>l2tp-data-memory-bytes</l2tp-data-memory-bytes>
 <l2tp-interface-name>l2tp-interface-name</l2tp-interface-name>
</l2tp-summary-table>
 </service-l2tp-summary-information>

Description L2TP summary.

Contents <l2tp-control-memory-bytes>—L2TP control memory (bytes).
 <l2tp-control-rx-packets>—Control receive packets.
 <l2tp-control-tx-packets>—Control transmit packets.
 <l2tp-data-memory-bytes>—L2TP data memory (bytes).
 <l2tp-data-rx-packets>—Data receive packets.
 <l2tp-data-tx-packets>—Data transmit packets.
 <l2tp-error-rx-packets>—Error receive packets.
 <l2tp-error-tx-packets>—Error transmit packets.
 <l2tp-interface-control-rx-packets>—Control receive packets sorted by interface.
 <l2tp-interface-control-tx-packets>—Control transmit packets sorted by interface.
 <l2tp-interface-data-rx-packets>—Data receive packets sorted by interface.

<l2tp-interface-data-tx-packets>—Data transmit packets sorted by interface.

<l2tp-interface-error-rx-packets>—Error receive packets sorted by interface.

<l2tp-interface-error-tx-packets>—Error transmit packets sorted by interface.

<l2tp-interface-name>—Name of interface to show summary information.

<l2tp-sessions>—Total number of L2TP sessions.

<l2tp-tunnels>—Total number of L2TP tunnels.

<l2tp-tunnel-clear-entry>

Usage <service-l2tp-tunnel-clear-information>
 <l2tp-tunnel-clear-entry>
 <l2tp-tunnel-local-id>l2tp-tunnel-local-id</l2tp-tunnel-local-id>
 </l2tp-tunnel-clear-entry>
 </service-l2tp-tunnel-clear-information>

Description L2TP cleared tunnel information.

Contents <l2tp-tunnel-local-id>—Local ID of tunnel.

<l2tp-tunnel-entry>

Usage <l2tp-tunnel-table>
 <l2tp-tunnel-entry>
 <l2tp-tunnel-local-id>l2tp-tunnel-local-id</l2tp-tunnel-local-id>
 <l2tp-tunnel-remote-id>l2tp-tunnel-remote-id</l2tp-tunnel-remote-id>
 <l2tp-tunnel-remote-ip>l2tp-tunnel-remote-ip</l2tp-tunnel-remote-ip>
 <l2tp-tunnel-state>l2tp-tunnel-state</l2tp-tunnel-state>
 <l2tp-tunnel-session-count>l2tp-tunnel-session-count
 </l2tp-tunnel-session-count>
 <l2tp-tunnel-local-ip>l2tp-tunnel-local-ip</l2tp-tunnel-local-ip>
 <l2tp-tunnel-remote-name>l2tp-tunnel-remote-name</l2tp-tunnel-remote-name>
 <l2tp-tunnel-local-name>l2tp-tunnel-local-name</l2tp-tunnel-local-name>
 <l2tp-tunnel-maximum-sessions>l2tp-tunnel-maximum-sessions
 </l2tp-tunnel-maximum-sessions>
 <l2tp-tunnel-window-size>l2tp-tunnel-window-size</l2tp-tunnel-window-size>
 <l2tp-tunnel-hello-interval>l2tp-tunnel-hello-interval
 </l2tp-tunnel-hello-interval>
 <l2tp-tunnel-tos-reflect>l2tp-tunnel-tos-reflect</l2tp-tunnel-tos-reflect>
 <l2tp-statistics-since>l2tp-statistics-since</l2tp-statistics-since>
 <l2tp-control-tx-packets>l2tp-control-tx-packets</l2tp-control-tx-packets>
 <l2tp-control-rx-packets>l2tp-control-rx-packets</l2tp-control-rx-packets>
 <l2tp-data-tx-packets>l2tp-data-tx-packets</l2tp-data-tx-packets>
 <l2tp-data-rx-packets>l2tp-data-rx-packets</l2tp-data-rx-packets>
 <l2tp-control-tx-bytes>l2tp-control-tx-bytes</l2tp-control-tx-bytes>
 <l2tp-control-rx-bytes>l2tp-control-rx-bytes</l2tp-control-rx-bytes>
 <l2tp-data-tx-bytes>l2tp-data-tx-bytes</l2tp-data-tx-bytes>
 <l2tp-data-rx-bytes>l2tp-data-rx-bytes</l2tp-data-rx-bytes>
 <l2tp-error-tx-packets>l2tp-error-tx-packets</l2tp-error-tx-packets>
 <l2tp-error-rx-packets>l2tp-error-rx-packets</l2tp-error-rx-packets>
 <l2tp-create-time>l2tp-create-time</l2tp-create-time>
 <l2tp-up-time>l2tp-up-time</l2tp-up-time>
 <l2tp-idle-time>l2tp-idle-time</l2tp-idle-time>
 </l2tp-tunnel-entry>
 </l2tp-tunnel-table>

Description L2TP tunnel information.

Contents <l2tp-control-rx-bytes>—Control receive bytes.
 <l2tp-control-rx-packets>—Control receive packets.
 <l2tp-control-tx-bytes>—Control transmit bytes.
 <l2tp-control-tx-packets>—Control transmit packets.
 <l2tp-create-time>—Creation time.
 <l2tp-data-rx-bytes>—Data receive bytes.
 <l2tp-data-rx-packets>—Data receive packets.
 <l2tp-data-tx-bytes>—Data transmit bytes.
 <l2tp-data-tx-packets>—Data transmit packets.

<l2tp-error-rx-packets>—Error receive packets.
 <l2tp-error-tx-packets>—Error transmit packets.
 <l2tp-idle-time>—Idle time.
 <l2tp-statistics-since>—Statistics since the displayed time.
 <l2tp-tunnel-hello-interval>—Tunnel hello interval.
 <l2tp-tunnel-local-id>—Local ID of tunnel.
 <l2tp-tunnel-local-ip>—Local IP address of session.
 <l2tp-tunnel-local-name>—Name of tunnel local end.
 <l2tp-tunnel-maximum-sessions>—Maximum number of sessions per tunnel.
 <l2tp-tunnel-remote-id>—Remote ID of tunnel.
 <l2tp-tunnel-remote-ip>—Remote IP address of tunnel.
 <l2tp-tunnel-remote-name>—Name of tunnel remote end.
 <l2tp-tunnel-session-count>—Tunnel session count.
 <l2tp-tunnel-state>—Tunnel state.
 <l2tp-tunnel-tos-reflect>—Tunnel ToS Reflect.
 <l2tp-tunnel-window-size>—Tunnel window size.
 <l2tp-up-time>—Up time.

<l2tp-tunnel-table>

Usage	<l2tp-per-tunnel-group-tunnel-table> <l2tp-tunnel-table> <l2tp-tunnel-entry>...</l2tp-tunnel-entry> </l2tp-tunnel-table> </l2tp-per-tunnel-group-tunnel-table>
Description	L2TP tunnel table sorted by tunnel group.
Contents	<l2tp-tunnel-entry>—L2TP tunnel information.

<load-balancer-entries>

- Usage** <lsqinfo-cpu-usage-information>
 <load-balancer-entries>
 <load-balancer-entry>...</load-balancer-entry>
 </load-balancer-entries>
 </lsqinfo-cpu-usage-information>
- Description** No documentation is available yet.
- Contents** <load-balancer-entry>—Load Balancer CPU usage information.

<load-balancer-entry>

- Usage** <load-balancer-entries>
 <load-balancer-entry>
 <cpu-name>cpu-name</cpu-name>
 <idle>idle</idle>
 <system>system</system>
 <output>output</output>
 <freeback>freeback</freeback>
 <input-1>input-1</input-1>
 <input-2>input-2</input-2>
 </load-balancer-entry>
 </load-balancer-entries>
- Description** Load Balancer CPU usage information.
- Contents** <cpu-name>— CPU name.
- <freeback>—Percentage of CPU time taken by Freeback thread.
- <idle>—Percentage of CPU time taken by Idle thread.
- <input-1>—Percentage of CPU time taken by Input 1 thread.
- <input-2>—Percentage of CPU time taken by Input 2 thread.
- <output>—Percentage of CPU time taken by Output thread.
- <system>—Percentage of CPU time taken by System thread.

<lsqinfo-cpu-usage-information>

Usage <rpc-reply>
 <lsqinfo-cpu-usage-information>
 <cpu-role-name>*cpu-role-name*</cpu-role-name>
 <one-second-usage>*one-second-usage*</one-second-usage>
 <five-second-usage>*five-second-usage*</five-second-usage>
 <fragmenter-entries>...</fragmenter-entries>
 <quality-of-service-entries>...</quality-of-service-entries>
 <sequencer-entries>...</sequencer-entries>
 <load-balancer-entries>...</load-balancer-entries>
 </lsqinfo-cpu-usage-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <cpu-role-name>—CPU family name.

<five-second-usage>—CPU usage. 5 second average.

<fragmenter-entries>—No documentation is available yet.

<load-balancer-entries>—No documentation is available yet.

<one-second-usage>—CPU usage. 1 second average.

<quality-of-service-entries>—No documentation is available yet.

<sequencer-entries>—No documentation is available yet.

<media-service-entry>

Usage <pgcpd-config>
 <media-service-entry>
 <media-service-name>*media-service-name*</media-service-name>
 <media-service-nat-pool>*media-service-nat-pool*</media-service-nat-pool>
 </media-service-entry>
 </pgcpd-config>

Description No documentation is available yet.

Contents <media-service-name>—No documentation is available yet.

<media-service-nat-pool>—No documentation is available yet.

<media-service-ref-entry>

- Usage** <virtual-interface-entry | rule-entry>
 <media-service-ref-entry>
 <media-service-ref-name>*media-service-ref-name*</media-service-ref-name>
 </media-service-ref-entry>
 </virtual-interface-entry | rule-entry>
- Description** No documentation is available yet.
- Contents** <media-service-ref-name>—No documentation is available yet.

<message-counters>

Usage <sip-alg-counters>
<message-counters>
 <register-new>*register-new*</register-new>
 <invite-new>*invite-new*</invite-new>
 <reinvites>*reinvites*</reinvites>
 <invite-retransmits>*invite-retransmits*</invite-retransmits>
 <response-provisional>*response-provisional*</response-provisional>
 <response-invite-ok>*response-invite-ok*</response-invite-ok>
 <response-non-invite-ok>*response-non-invite-ok*</response-non-invite-ok>
 <response-redir>*response-redir*</response-redir>
 <response-request-failure>*response-request-failure*</response-request-failure>
 <response-server-failure>*response-server-failure*</response-server-failure>
 <response-global-failure>*response-global-failure*</response-global-failure>
 <response-invalid>*response-invalid*</response-invalid>
 <response-retransmits>*response-retransmits*</response-retransmits>
 <ack-valid>*ack-valid*</ack-valid>
 <ack-invalid>*ack-invalid*</ack-invalid>
 <ack-retransmits>*ack-retransmits*</ack-retransmits>
 <bye-valid>*bye-valid*</bye-valid>
 <bye-invalid>*bye-invalid*</bye-invalid>
 <cancel-valid>*cancel-valid*</cancel-valid>
 <cancel-invalid>*cancel-invalid*</cancel-invalid>
 <subscribe-valid>*subscribe-valid*</subscribe-valid>
 <subscribe-invalid>*subscribe-invalid*</subscribe-invalid>
 <notify-valid>*notify-valid*</notify-valid>
 <notify-invalid>*notify-invalid*</notify-invalid>
 <options-valid>*options-valid*</options-valid>
 <options-invalid>*options-invalid*</options-invalid>
 <info-valid>*info-valid*</info-valid>
 <info-invalid>*info-invalid*</info-invalid>
 <update-valid>*update-valid*</update-valid>
 <update-invalid>*update-invalid*</update-invalid>
 <refer-valid>*refer-valid*</refer-valid>
 <refer-invalid>*refer-invalid*</refer-invalid>
</message-counters>
 </sip-alg-counters>

Description SIP message counters.

Contents <ack-invalid>—Number of invalid ACK messages.

<ack-retransmits>—Number of ACK message retransmissions.

<ack-valid>—Number of valid ACK messages.

<bye-invalid>—Number of invalid BYE messages.

<bye-valid>—Number of valid BYE messages.

<cancel-invalid>—Number of invalid CANCEL messages.

<cancel-valid>—Number of valid CANCEL messages.

<info-invalid>—Number of invalid INFO messages.

<info-valid>—Number of valid INFO messages.

<invite-new>—Number of new INVITE messages.

<invite-retransmits>—Number of INVITE message retransmissions.

<notify-invalid>—Number of invalid NOTIFY messages.

<notify-valid>—Number of valid NOTIFY messages.

<options-invalid>—Number of invalid OPTIONS messages.

<options-valid>—Number of valid OPTIONS messages.

<refer-invalid>—Number of invalid REFER messages.

<refer-valid>—Number of valid REFER messages.

<register-new>—Number of REGISTER messages.

<reinvites>—Number of ReINVITE messages.

<response-global-failure>—Number of global failure (6xx) responses.

<response-invalid>—Number of invalid responses.

<response-invite-ok>—Number of 'OK' responses to INVITE messages.

<response-non-invite-ok>—Number of 'OK' responses to messages other than INVITE.

<response-provisional>—Number of provisional responses.

<response-redir>—Number of redirection (3xx) responses.

<response-request-failure>—Number of request failure (4xx) responses.

<response-retransmits>—Number of response retransmissions.

<response-server-failure>—Number of server failure (5xx) responses.

<subscribe-invalid>—Number of invalid SUBSCRIBE messages.

<subscribe-valid>—Number of valid SUBSCRIBE messages.

<update-invalid>—Number of invalid UPDATE messages.

<update-valid>—Number of valid UPDATE messages.

<new-flow-counters>

Usage	<pre> <sfw-stats-service-set-entry> <new-flow-counters> <new-flow-accepts>new-flow-accepts</new-flow-accepts> <new-flow-discards>new-flow-discards</new-flow-discards> <new-flow-rejects>new-flow-rejects</new-flow-rejects> </new-flow-counters> </sfw-stats-service-set-entry> </pre>
Description	New flow counters.
Contents	<p><new-flow-accepts>—Packets accepted by new flows.</p> <p><new-flow-discards>—Packets discarded by new flows.</p> <p><new-flow-rejects>—Packets rejected by new flows.</p>

<overload-control-entry>

Usage	<pre> <pgcpd-active-configuration gateway-entry> <overload-control-entry> <queue-limit-percentage>queue-limit-percentage</queue-limit-percentage> </overload-control-entry> </pgcpd-active-configuration gateway-entry> </pre>
Description	No documentation is available yet.
Contents	<queue-limit-percentage>—No documentation is available yet.

<parser-counters>

Usage	<pre> <sip-alg-counters> <parser-counters> <syntax-errors>syntax-errors</syntax-errors> <content-errors>content-errors</content-errors> <unknown-methods>unknown-methods</unknown-methods> </parser-counters> </sip-alg-counters> </pre>
Description	Parser statistics.
Contents	<p><content-errors>—SIP message content errors.</p> <p><syntax-errors>—SIP syntax errors.</p> <p><unknown-methods>—SIP unknown methods.</p>

<pgcp-conversation>

Usage <pgcp-per-service-set-conversation>
 <pgcp-conversation>
 <pgcp-flow-table-conv-initiator>*pgcp-flow-table-conv-initiator*
 </pgcp-flow-table-conv-initiator>
 <pgcp-flow-table-conv-responder>*pgcp-flow-table-conv-responder*
 </pgcp-flow-table-conv-responder>
 <service-pgcp-flow-table>...</service-pgcp-flow-table>
 </pgcp-conversation>
 </pgcp-per-service-set-conversation>

Description Stateful firewall conversations.

Contents <pgcp-flow-table-conv-initiator>—Number of initiator flows.
 <pgcp-flow-table-conv-responder>—Number of responder flows.
 <service-pgcp-flow-table>—Stateful firewall flows.

<pgcp-flow-entry>

Usage <service-pgcp-flow-table>
<pgcp-flow-entry>
 <pgcp-flow-protocol>*pgcp-flow-protocol*</pgcp-flow-protocol>
 <pgcp-flow-source-ip>*pgcp-flow-source-ip*</pgcp-flow-source-ip>
 <pgcp-flow-source-port>*pgcp-flow-source-port*</pgcp-flow-source-port>
 <pgcp-flow-destination-ip>*pgcp-flow-destination-ip*</pgcp-flow-destination-ip>
 <pgcp-flow-destination-port>*pgcp-flow-destination-port*
 </pgcp-flow-destination-port>
 <pgcp-flow-state>*pgcp-flow-state*</pgcp-flow-state>
 <pgcp-flow-direction>*pgcp-flow-direction*</pgcp-flow-direction>
 <pgcp-flow-frame-counter>*pgcp-flow-frame-counter*</pgcp-flow-frame-counter>
 <pgcp-flow-gate-id>*pgcp-flow-gate-id*</pgcp-flow-gate-id>
 <pgcp-flow-nat>...</pgcp-flow-nat>
 <pgcp-flow-table-byte-count>*pgcp-flow-table-byte-count*
 </pgcp-flow-table-byte-count>
 <source-routing-instance>*source-routing-instance*</source-routing-instance>
 <destination-routing-instance>*destination-routing-instance*
 </destination-routing-instance>
 <pgcp-flow-table-tcp-window-size>*pgcp-flow-table-tcp-window-size*
 </pgcp-flow-table-tcp-window-size>
 <pgcp-flow-table-tcp-acknowledge>*pgcp-flow-table-tcp-acknowledge*
 </pgcp-flow-table-tcp-acknowledge>
 <pgcp-flow-table-tcp-tickle>*pgcp-flow-table-tcp-tickle*
 </pgcp-flow-table-tcp-tickle>
 <pgcp-flow-table-role>*pgcp-flow-table-role*</pgcp-flow-table-role>
 <pgcp-flow-table-timeout>*pgcp-flow-table-timeout*</pgcp-flow-table-timeout>
 <pgcp-flow-table-protocol-detail>*pgcp-flow-table-protocol-detail*
 </pgcp-flow-table-protocol-detail>
 <flow-gate-tman-policing>*flow-gate-tman-policing*</flow-gate-tman-policing>
 <flow-gate-sdr>*flow-gate-sdr*</flow-gate-sdr>
 <flow-gate-sdr-mbs>*flow-gate-sdr-mbs*</flow-gate-sdr-mbs>
 <flow-gate-pdr>*flow-gate-pdr*</flow-gate-pdr>
 <flow-gate-pdr-mbs>*flow-gate-pdr-mbs*</flow-gate-pdr-mbs>
</pgcp-flow-entry>
 </service-pgcp-flow-table>

Description Flow brief information.

Contents <destination-routing-instance>—Destination routing-instance.

<flow-gate-pdr>—Peak data rate threshold for a gate.

<flow-gate-pdr-mbs>—Maximum pdr burst size limit for a gate.

<flow-gate-sdr>—Sustainable data rate threshold for a gate.

<flow-gate-sdr-mbs>—Maximum sdr burst size limit for a gate.

<flow-gate-tman-policing>—Install/uninstall a traffic management policing for this gate.

<pgcp-flow-destination-ip>—Flow destination IP address.

<pgcp-flow-destination-port>—PGCP Flow destination port.

<pgcp-flow-direction>—PGCP Flow direction.

<pgcp-flow-frame-counter>—Number of frames transmitted.

<pgcp-flow-gate-id>—PGCP gate-id.

<pgcp-flow-nat>—NAT translation.

<pgcp-flow-protocol>—PGCP Flow protocol description.

<pgcp-flow-source-ip>—PGCP Source IP address.

<pgcp-flow-source-port>—PGCP Source port address.

<pgcp-flow-state>—Flow state.

<pgcp-flow-table-byte-count>—PGCP Flow byte count.

<pgcp-flow-table-protocol-detail>—PGCP Flow protocol detail information.

<pgcp-flow-table-role>—Role of flow in conversation.

<pgcp-flow-table-tcp-acknowledge>—PGCP TCP protocol acknowledge.

<pgcp-flow-table-tcp-tickle>—PGCP Time between TCP tickles (seconds).

<pgcp-flow-table-tcp-window-size>—PGCP TCP protocol window size.

<pgcp-flow-table-timeout>—Timeout value of PGCP flow (seconds).

<source-routing-instance>—Source routing-instance.

<pgcp-flow-nat>

Usage <pgcp-flow-entry>
 <pgcp-flow-nat>
 <pgcp-flow-nat-ip>*pgcp-flow-nat-ip*</pgcp-flow-nat-ip>
 <pgcp-flow-nat-port>*pgcp-flow-nat-port*</pgcp-flow-nat-port>
 <pgcp-flow-translated-ip>*pgcp-flow-translated-ip*</pgcp-flow-translated-ip>
 <pgcp-flow-translated-port>*pgcp-flow-translated-port*
 </pgcp-flow-translated-port>
 </pgcp-flow-nat>
 </pgcp-flow-entry>

Description NAT translation.

Contents <pgcp-flow-nat-ip>—PGCP NAT IP address.

<pgcp-flow-nat-port>—PGCP NAT port.

<pgcp-flow-translated-ip>—Translated PGCP IP address.

<pgcp-flow-translated-port>—Translated PGCP port.

<pgcp-per-service-set-conversation>

- Usage** <service-pgcp-conversation-information>
 <pgcp-per-service-set-conversation>
 <service-set-name>*service-set-name*</service-set-name>
 <interface-name>*interface-name*</interface-name>
 <pgcp-conversation>...</pgcp-conversation>
 </pgcp-per-service-set-conversation>
 </service-pgcp-conversation-information>
- Description** Show conversations.
- Contents** <interface-name>—Name of the adaptive services interface.
 <pgcp-conversation>—Stateful firewall conversations.
 <service-set-name>—Name of the service set.

<pgcp-per-service-set-flow-table>

- Usage** <service-pgcp-flow-table-information>
 <pgcp-per-service-set-flow-table>
 <service-set-name>*service-set-name*</service-set-name>
 <interface-name>*interface-name*</interface-name>
 <service-pgcp-flow-table>...</service-pgcp-flow-table>
 </pgcp-per-service-set-flow-table>
 </service-pgcp-flow-table-information>
- Description** Flows sorted by service set.
- Contents** <interface-name>—Name of the adaptive services interface.
 <service-pgcp-flow-table>—Stateful firewall flows.
 <service-set-name>—Name of the service set.

<pgcpd-active-configuration>

Usage <rpc-reply>
 <pgcpd-active-configuration>
 <virtual-interface-entry>...</virtual-interface-entry>
 <controller-entry>...</controller-entry>
 <h248-timers-entry>...</h248-timers-entry>
 <h248-options-entry>...</h248-options-entry>
 <base-root-entry>...</base-root-entry>
 <h248-segmentation-properties-entry>...</h248-segmentation-properties-entry>
 <h248-diffserv-entry>...</h248-diffserv-entry>
 <h248-notification-behavior-entry>...</h248-notification-behavior-entry>
 <h248-application-data-inactivity-detection-entry>...
 </h248-application-data-inactivity-detection-entry>
 <h248-event-timestamp-notification-entry>...
 </h248-event-timestamp-notification-entry>
 <inactivity-timer-entry>...</inactivity-timer-entry>
 <fast-update-filters-entry>...</fast-update-filters-entry>
 <overload-control-entry>...</overload-control-entry>
 <gateway-entry>...</gateway-entry>
 <rule-ref-entry>...</rule-ref-entry>
 <rule-entry>...</rule-entry>
 <service-pic-entry>...</service-pic-entry>
 <service-set-entry>...</service-set-entry>
 <firewall-entry>...</firewall-entry>
 <pgcpd-config>...</pgcpd-config>
 </pgcpd-active-configuration>
 </rpc-reply>

Description No documentation is available yet.

Contents <base-root-entry>—No documentation is available yet.
 <controller-entry>—No documentation is available yet.
 <fast-update-filters-entry>—Firewall filters limitation.
 <firewall-entry>—No documentation is available yet.
 <gateway-entry>—No documentation is available yet.
 <h248-application-data-inactivity-detection-entry>—No documentation is available yet.
 <h248-diffserv-entry>—No documentation is available yet.
 <h248-event-timestamp-notification-entry>—No documentation is available yet.
 <h248-notification-behavior-entry>—No documentation is available yet.
 <h248-options-entry>—No documentation is available yet.
 <h248-segmentation-properties-entry>—No documentation is available yet.
 <h248-timers-entry>—No documentation is available yet.

<inactivity-timer-entry>—No documentation is available yet.

<overload-control-entry>—No documentation is available yet.

<pgcpd-config>—No documentation is available yet.

<rule-entry>—No documentation is available yet.

<rule-ref-entry>—No documentation is available yet.

<service-pic-entry>—No documentation is available yet.

<service-set-entry>—No documentation is available yet.

<virtual-interface-entry>—No documentation is available yet.

<pgcpd-config>

Usage <pgcpd-active-configuration>
 <pgcpd-config>
 <media-service-entry>...</media-service-entry>
 <virtual-interface-entry>...</virtual-interface-entry>
 <gateway-entry>...</gateway-entry>
 <rule-entry>...</rule-entry>
 <service-set-entry>...</service-set-entry>
 <service-pic-entry>...</service-pic-entry>
 <firewall-entry>...</firewall-entry>
 </pgcpd-config>
 </pgcpd-active-configuration>

Description No documentation is available yet.

Contents <firewall-entry>—No documentation is available yet.

<gateway-entry>—No documentation is available yet.

<media-service-entry>—No documentation is available yet.

<rule-entry>—No documentation is available yet.

<service-pic-entry>—No documentation is available yet.

<service-set-entry>—No documentation is available yet.

<virtual-interface-entry>—No documentation is available yet.

<quality-of-service-entries>

- Usage** <lsqinfo-cpu-usage-information>
 <quality-of-service-entries>
 <quality-of-service-entry>...</quality-of-service-entry>
 </quality-of-service-entries>
 </lsqinfo-cpu-usage-information>
- Description** No documentation is available yet.
- Contents** <quality-of-service-entry>—QoS CPU usage information.

<quality-of-service-entry>

- Usage** <quality-of-service-entries>
 <quality-of-service-entry>
 <cpu-name>cpu-name</cpu-name>
 <idle>idle</idle>
 <timer>timer</timer>
 <system>system</system>
 <output>output</output>
 <input>input</input>
 <fragment-output>fragment-output</fragment-output>
 <bypass-output>bypass-output</bypass-output>
 <free-frame>free-frame</free-frame>
 </quality-of-service-entry>
 </quality-of-service-entries>
- Description** QoS CPU usage information.
- Contents** <bypass-output>—Percentage of CPU time taken by Bypass Output thread.
- <cpu-name>— CPU name.
- <fragment-output>—Percentage of CPU time taken by Fragment Output thread.
- <free-frame>—Percentage of CPU time taken by Free Frame thread.
- <idle>—Percentage of CPU time taken by Idle thread.
- <input>—Percentage of CPU time taken by Input thread.
- <output>—Percentage of CPU time taken by Output thread.
- <system>—Percentage of CPU time taken by System thread.
- <timer>—Percentage of CPU time taken by Timer thread.

<radius-accounting-server-information-entry>

Usage <services-l2tp-radius-accounting-servers-information |
 services-l2tp-radius-authentication-accounting-servers-information>
<radius-accounting-server-information-entry>
 <radius-server-ip-address>*radius-server-ip-address*</radius-server-ip-address>
 <radius-server-state>*radius-server-state*</radius-server-state>
 <radius-server-udp-port>*radius-server-udp-port*</radius-server-udp-port>
 <radius-server-retry-count>*radius-server-retry-count*
 </radius-server-retry-count>
 <radius-server-timeout>*radius-server-timeout*</radius-server-timeout>
 <radius-server-pending-requests>*radius-server-pending-requests*
 </radius-server-pending-requests>
 <radius-server-maximum-sessions>*radius-server-maximum-sessions*
 </radius-server-maximum-sessions>
 <radius-server-dead-time>*radius-server-dead-time*</radius-server-dead-time>
 <radius-server-secret-type>*radius-server-secret-type*
 </radius-server-secret-type>
</radius-accounting-server-information-entry>
 </services-l2tp-radius-accounting-servers-information |
 services-l2tp-radius-authentication-accounting-servers-information>

Description RADIUS accounting server information entry sorted by IP address.

Contents <radius-server-dead-time>—Server dead time value in seconds.

<radius-server-ip-address>—Server IP address.

<radius-server-maximum-sessions>—Server maximum allowed sessions.

<radius-server-pending-requests>—Server number of requests pending.

<radius-server-retry-count>—Server retry count.

<radius-server-secret-type>—Server secret type.

<radius-server-state>—Server state.

<radius-server-timeout>—Server timeout value in seconds.

<radius-server-udp-port>—Server UDP port.

<radius-accounting-statistic-information-entry>

Usage <services-l2tp-radius-accounting-statistics-information |
 services-l2tp-radius-authentication-accounting-statistics-information>
<radius-accounting-statistic-information-entry>
 <radius-server-ip-address>*radius-server-ip-address*</radius-server-ip-address>
 <radius-server-udp-port>*radius-server-udp-port*</radius-server-udp-port>
 <radius-statistic-requests>*radius-statistic-requests*
 </radius-statistic-requests>
 <radius-statistic-start-requests>*rad-stat-strt-reqs*
 </radius-statistic-start-requests>
 <radius-statistic-interim-requests>*rad-stat-interim-reqs*
 </radius-statistic-interim-requests>
 <radius-statistic-stop-requests>*radius-statistic-stop-requests*
 </radius-statistic-stop-requests>
 <radius-statistic-rollover-requests>*radius-statistic-rollover-reqs*
 </radius-statistic-rollover-requests>
 <radius-statistic-retransmissions>*rad-stat-retransmsns*
 </radius-statistic-retransmissions>
 <radius-statistic-responses>*radius-statistic-responses*
 </radius-statistic-responses>
 <radius-statistic-start-responses>*rad-stat-start-resp*
 </radius-statistic-start-responses>
 <radius-statistic-interim-responses>*radius-stat-interim-resps*
 </radius-statistic-interim-responses>
 <radius-statistic-stop-responses>*radius-statistic-stop-resps*
 </radius-statistic-stop-responses>
 <radius-statistic-malformed-responses>*radius-stat-malformed-resps*
 </radius-statistic-malformed-responses>
 <radius-statistic-bad-authenticators>*radius-statistic-bad-authrs*
 </radius-statistic-bad-authenticators>
 <radius-statistic-requests-pending>*radius-statistic-reqs-pending*
 </radius-statistic-requests-pending>
 <radius-statistic-request-timeouts>*radius-statistic-reqs-timeouts*
 </radius-statistic-request-timeouts>
 <radius-statistic-unknown-responses>*radius-statistic-unknown-resps*
 </radius-statistic-unknown-responses>
 <radius-statistic-packets-dropped>*radius-statistic-packets-dropped*
 </radius-statistic-packets-dropped>
</radius-accounting-statistic-information-entry>
 </services-l2tp-radius-accounting-statistics-information |
 services-l2tp-radius-authentication-accounting-statistics-information>

Description RADIUS accounting statistic entry sorted by IP address.

Contents <radius-server-ip-address>—Server IP address.
 <radius-server-udp-port>—Server UDP port.
 <radius-statistic-bad-authenticators>—Bad authenticators count.
 <radius-statistic-interim-requests>—Interim requests count.
 <radius-statistic-interim-responses>—Interim responses count.

<radius-statistic-malformed-responses>—Malformed responses count.

<radius-statistic-packets-dropped>—Packets dropped count.

<radius-statistic-request-timeouts>—Request timeouts count.

<radius-statistic-requests>—Requests count.

<radius-statistic-requests-pending>—Requests pending count.

<radius-statistic-responses>—Responses count.

<radius-statistic-retransmissions>—Retransmissions count.

<radius-statistic-rollover-requests>—Rollover requests count.

<radius-statistic-start-requests>—Start requests count.

<radius-statistic-start-responses>—Start responses count.

<radius-statistic-stop-requests>—Stop requests count.

<radius-statistic-stop-responses>—Stop responses count.

<radius-statistic-unknown-responses>—Unknown responses count.

<radius-authentication-server-information-entry>

Usage <services-l2tp-radius-authentication-servers-information |
 services-l2tp-radius-authentication-accounting-servers-information>
<radius-authentication-server-information-entry>
 <radius-server-ip-address>*radius-server-ip-addr*</radius-server-ip-address>
 <radius-server-state>*radius-server-state*</radius-server-state>
 <radius-server-udp-port>*radius-server-udp-port*</radius-server-udp-port>
 <radius-server-retry-count>*radius-server-retry-count*
 </radius-server-retry-count>
 <radius-server-timeout>*radius-srvr-tmout*</radius-server-timeout>
 <radius-server-pending-requests>*radius-server-pending-requests*
 </radius-server-pending-requests>
 <radius-server-maximum-sessions>*radius-srvr-max-sessions*
 </radius-server-maximum-sessions>
 <radius-server-dead-time>*radius-srvr-dead-time*</radius-server-dead-time>
 <radius-server-secret-type>*radius-srvr-secret-type*
 </radius-server-secret-type>
</radius-authentication-server-information-entry>
 </services-l2tp-radius-authentication-servers-information |
 services-l2tp-radius-authentication-accounting-servers-information>

Description RADIUS authentication server information entry sorted by IP address.

Contents <radius-server-dead-time>—Server dead time value in seconds.

<radius-server-ip-address>—Server IP address.

<radius-server-maximum-sessions>—Server maximum allowed sessions.

<radius-server-pending-requests>—Server number of requests pending.

<radius-server-retry-count>—Server retry count.

<radius-server-secret-type>—Server secret type.

<radius-server-state>—Server state.

<radius-server-timeout>—Server timeout value in seconds.

<radius-server-udp-port>—Server UDP port.

<radius-authentication-statistic-information-entry>

Usage <services-l2tp-radius-authentication-statistics-information |
 services-l2tp-radius-authentication-accounting-statistics-information>
<radius-authentication-statistic-information-entry>
 <radius-server-ip-address>*radius-server-ip-address*</radius-server-ip-address>
 <radius-server-udp-port>*radius-server-udp-port*</radius-server-udp-port>
 <radius-statistic-access-requests>*radius-statistic-access-requests*
 </radius-statistic-access-requests>
 <radius-statistic-rollover-requests>*radius-statistic-rollover-requests*
 </radius-statistic-rollover-requests>
 <radius-statistic-retransmissions>*radius-statistic-retransmissions*
 </radius-statistic-retransmissions>
 <radius-statistic-access-accepts>*radius-statistic-access-accepts*
 </radius-statistic-access-accepts>
 <radius-statistic-access-rejects>*radius-statistic-access-rejects*
 </radius-statistic-access-rejects>
 <radius-statistic-access-challenges>*radius-statistic-access-challenges*
 </radius-statistic-access-challenges>
 <radius-statistic-malformed-responses>*radius-statistic-malformed-responses*
 </radius-statistic-malformed-responses>
 <radius-statistic-bad-authenticators>*radius-statistic-bad-authenticators*
 </radius-statistic-bad-authenticators>
 <radius-statistic-requests-pending>*radius-statistic-requests-pending*
 </radius-statistic-requests-pending>
 <radius-statistic-request-timeouts>*radius-statistic-request-timeouts*
 </radius-statistic-request-timeouts>
 <radius-statistic-unknown-responses>*radius-statistic-unknown-responses*
 </radius-statistic-unknown-responses>
 <radius-statistic-packets-dropped>*radius-statistic-packets-dropped*
 </radius-statistic-packets-dropped>
</radius-authentication-statistic-information-entry>
 </services-l2tp-radius-authentication-statistics-information |
 services-l2tp-radius-authentication-accounting-statistics-information>

Description RADIUS authentication statistic entry sorted by IP address.

Contents <radius-server-ip-address>—Server IP address.

<radius-server-udp-port>—Server UDP port.

<radius-statistic-access-accepts>—Access accepts count.

<radius-statistic-access-challenges>—Access challenges count.

<radius-statistic-access-rejects>—Access rejects count.

<radius-statistic-access-requests>—Access requests count.

<radius-statistic-bad-authenticators>—Bad authenticators count.

<radius-statistic-malformed-responses>—Malformed responses count.

<radius-statistic-packets-dropped>—Packets dropped count.

<radius-statistic-request-timeouts>—Request timeouts count.

<radius-statistic-requests-pending>—Requests pending count.

<radius-statistic-retransmissions>—Retransmissions count.

<radius-statistic-rollover-requests>—Rollover requests count.

<radius-statistic-unknown-responses>—Unknown responses count.

<radius-profile-access-test-detail-result>

Usage <rpc-reply>
<radius-profile-access-test-detail-result>
 <radius-profile-name>*radius-profile-name*</radius-profile-name>
 <radius-client-user-name>*radius-client-user-name*</radius-client-user-name>
 <radius-client-password>*radius-client-password*</radius-client-password>
 <radius-profile-num-servers>*radius-profile-num-servers*
 </radius-profile-num-servers>
 <radius-server-ip-address>*radius-server-ip-address*</radius-server-ip-address>
 <radius-server-udp-port>*radius-server-udp-port*</radius-server-udp-port>
 <radius-server-source-address>*radius-server-source-address*
 </radius-server-source-address>
 <radius-server-timeout>*radius-server-timeout*</radius-server-timeout>
 <radius-server-retry-count>*radius-server-retry-count*
 </radius-server-retry-count>
 <radius-server-secret>*radius-server-secret*</radius-server-secret>
 <radius-server-status>*radius-server-status*</radius-server-status>
 <radius-server-attempts>*radius-server-attempts*</radius-server-attempts>
 <radius-server-attribute-name>*radius-server-attribute-name*
 </radius-server-attribute-name>
 <radius-server-attribute-len>*radius-server-attribute-len*
 </radius-server-attribute-len>
 <radius-server-attribute-value>*radius-server-attribute-value*
 </radius-server-attribute-value>
</radius-profile-access-test-detail-result>
 </rpc-reply>

Description RADIUS server access test detail.

Contents <radius-client-password>—Session password.
 <radius-client-user-name>—Session user name.
 <radius-profile-name>—Access profile name.
 <radius-profile-num-servers>—Access profile num servers.
 <radius-server-attempts>—Access profile connection attempts.
 <radius-server-attribute-len>—Access radius attribute length.
 <radius-server-attribute-name>—Access radius attribute name.
 <radius-server-attribute-value>—Access radius attribute value.
 <radius-server-ip-address>—Server IP address.
 <radius-server-retry-count>—Server retry count.
 <radius-server-secret>—Radius shared secret.
 <radius-server-source-address>—Source IP address.
 <radius-server-status>—Server status.

<radius-server-timeout>—Server timeout value in seconds.

<radius-server-udp-port>—Server UDP port.

<radius-profile-access-test-result>

Usage <rpc-reply>
<radius-profile-access-test-result>
 <radius-profile-name>*radius-profile-name*</radius-profile-name>
 <radius-client-user-name>*radius-client-user-name*</radius-client-user-name>
 <radius-client-password>*radius-client-password*</radius-client-password>
 <radius-profile-num-servers>*radius-profile-num-servers*
 </radius-profile-num-servers>
 <radius-server-ip-address>*radius-server-ip-address*</radius-server-ip-address>
 <radius-server-udp-port>*radius-server-udp-port*</radius-server-udp-port>
 <radius-server-source-address>*radius-server-source-address*
 </radius-server-source-address>
 <radius-server-timeout>*radius-server-timeout*</radius-server-timeout>
 <radius-server-retry-count>*radius-server-retry-count*
 </radius-server-retry-count>
 <radius-server-secret>*radius-server-secret*</radius-server-secret>
 <radius-server-status>*radius-server-status*</radius-server-status>
 <radius-server-attempts>*radius-server-attempts*</radius-server-attempts>
</radius-profile-access-test-result>
 </rpc-reply>

Description RADIUS server access test.

Contents <radius-client-password>—Session password.

<radius-client-user-name>—Session user name.

<radius-profile-name>—Access profile name.

<radius-profile-num-servers>—Access profile num servers.

<radius-server-attempts>—Access profile connection attempts.

<radius-server-ip-address>—Server IP address.

<radius-server-retry-count>—Server retry count.

<radius-server-secret>—Radius shared secret.

<radius-server-source-address>—Source IP address.

<radius-server-status>—Server status.

<radius-server-timeout>—Server timeout value in seconds.

<radius-server-udp-port>—Server UDP port.

<radius-server-access-test-result>

Usage <rpc-reply>
<radius-server-access-test-result>
 <radius-server-ip-address>*radius-server-ip-address*</radius-server-ip-address>
 <radius-server-udp-port>*radius-server-udp-port*</radius-server-udp-port>
 <radius-server-source-address>*radius-server-source-address*
 </radius-server-source-address>
 <radius-server-timeout>*radius-server-timeout*</radius-server-timeout>
 <radius-server-retry-count>*radius-server-retry-count*
 </radius-server-retry-count>
 <radius-server-secret>*radius-server-secret*</radius-server-secret>
 <radius-client-user-name>*radius-client-user-name*</radius-client-user-name>
 <radius-client-password>*radius-client-password*</radius-client-password>
 <radius-server-status>*radius-server-status*</radius-server-status>
</radius-server-access-test-result>
 </rpc-reply>

Description RADIUS server access test.

Contents <radius-client-password>—Session password.
 <radius-client-user-name>—Session user name.
 <radius-server-ip-address>—Server IP address.
 <radius-server-retry-count>—Server retry count.
 <radius-server-secret>—Radius shared secret.
 <radius-server-source-address>—Source IP address.
 <radius-server-status>—Server status.
 <radius-server-timeout>—Server timeout value in seconds.
 <radius-server-udp-port>—Server UDP port.

<rule-entry>

Usage <pgcpd-active-configuration | pgcpd-config>
<rule-entry>
 <rule-name>*rule-name*</rule-name>
 <rule-gateway-name>*rule-gateway-name*</rule-gateway-name>
 <media-service-ref-entry>...</media-service-ref-entry>
</rule-entry>
 </pgcpd-active-configuration | pgcpd-config>

Description No documentation is available yet.

Contents <media-service-ref-entry>—No documentation is available yet.
 <rule-gateway-name>—No documentation is available yet.
 <rule-name>—No documentation is available yet.

<rule-ref-entry>

Usage	<pgcpd-active-configuration service-set-entry> <rule-ref-entry> <rule-ref-name> <i>rule-ref-name</i> </rule-ref-name> </rule-ref-entry> </pgcpd-active-configuration service-set-entry>
Description	No documentation is available yet.
Contents	<rule-ref-name>—No documentation is available yet.

<sequencer-entries>

Usage	<lsqinfo-cpu-usage-information> <sequencer-entries> <sequencer-entry>...</sequencer-entry> </sequencer-entries> </lsqinfo-cpu-usage-information>
Description	No documentation is available yet.
Contents	<sequencer-entry>—Sequencer CPU usage information.

<sequencer-entry>

Usage	<sequencer-entries> <sequencer-entry> <cpu-name> <i>cpu-name</i> </cpu-name> <idle> <i>idle</i> </idle> <system> <i>system</i> </system> <input-lfi> <i>input-lfi</i> </input-lfi> <input-fragments> <i>input-fragments</i> </input-fragments> <output-fragments> <i>output-fragments</i> </output-fragments> <output-retry> <i>output-retry</i> </output-retry> </sequencer-entry> </sequencer-entries>
Description	Sequencer CPU usage information.
Contents	<cpu-name>— CPU name. <idle>—Percentage of CPU time taken by Idle thread. <input-fragments>—Percentage of CPU time taken by Input Fragments thread. <input-lfi>—Percentage of CPU time taken by Input LFI thread. <output-fragments>—Percentage of CPU time taken by Output Fragments thread. <output-retry>—Percentage of CPU time taken by Output Retry thread. <system>—Percentage of CPU time taken by System thread.

<service-cos-statistics-entry>

Usage <service-cos-statistics-information>
 <service-cos-statistics-entry>
 <interface-name>*interface-name*</interface-name>
 <service-set-name>*service-set-name*</service-set-name>
 <cos-stats-service-set-dscp-information>...
 </cos-stats-service-set-dscp-information>
 <cos-stats-service-set-forwarding-class-information>...
 </cos-stats-service-set-forwarding-class-information>
 </service-cos-statistics-entry>
 </service-cos-statistics-information>

Description Class of service statistics entry.

Contents <cos-stats-service-set-dscp-information>—No documentation is available yet.

<cos-stats-service-set-forwarding-class-information>—No documentation is available yet.

<interface-name>—Name of the adaptive services interface.

<service-set-name>—Name of the service set.

<service-cos-statistics-information>

Usage <rpc-reply>
 <service-cos-statistics-information>
 <service-cos-statistics-entry>...</service-cos-statistics-entry>
 </service-cos-statistics-information>
 </rpc-reply>

Description Class of service statistics information.

Contents <service-cos-statistics-entry>—Class of service statistics entry.

<service-crtf-flow-table>

Usage <crtf-per-interface-flow-table>
 <service-crtf-flow-table>
 <crtf-flow-entry>...</crtf-flow-entry>
 </service-crtf-flow-table>
 </crtf-per-interface-flow-table>

Description CRTF flows.

Contents <crtf-flow-entry>—CRTF flow information.

<service-crtf-flow-table-information>

- Usage** <rpc-reply>
 <service-crtf-flow-table-information>
 <crtf-per-interface-flow-table>...</crtf-per-interface-flow-table>
 </service-crtf-flow-table-information>
 </rpc-reply>
- Description** CRTF flows sorted by interface name.
- Contents** <crtf-per-interface-flow-table>—CRTF flows sorted by interface.

<service-identification-statistics>

Usage <service-identification-statistics-information>

```

<service-identification-statistics>
  <interface-name>interface-name</interface-name>
  <interfaces>interfaces</interfaces>
  <packets>packets</packets>
  <bytes>bytes</bytes>
  <errored-packets>errored-packets</errored-packets>
  <errored-bytes>errored-bytes</errored-bytes>
  <packet-processing-error>packet-processing-error</packet-processing-error>
  <errored-packets-tcp-malformed>errored-packets-tcp-malformed
    </errored-packets-tcp-malformed>
  <errored-packets-wap-invalid-transaction>errored-packets-wap-invalid-transaction
    </errored-packets-wap-invalid-transaction>
  <errored-packets-wap-transaction-in-error>errored-packets-wap-transaction-in-error
    </errored-packets-wap-transaction-in-error>
  <errored-packets-http-transaction-in-error>errored-packets-http-transaction-in-error
    </errored-packets-http-transaction-in-error>
  <header-examination-packets>hdr-exam-pkts
    </header-examination-packets>
  <header-examination-bytes>hdr-exam-bytes
    </header-examination-bytes>
  <header-examination-flow>header-examination-flow
    </header-examination-flow>
  <header-examination-flow-matched>header-examination-flow-matched
    </header-examination-flow-matched>
  <header-examination-protocol-required>hdr-exm-protcl-reqd
    </header-examination-protocol-required>
  <header-examination-http-protocol-required>hdr-exam-http-protocol-reqd
    </header-examination-http-protocol-required>
  <header-examination-wap-protocol-required>hdr-exam-wap-protocol-req
    </header-examination-wap-protocol-required>
  <protocol-inspected-flow>protocol-inspected-flow</protocol-inspected-flow>
  <protocol-inspection-flow>protocol-inspection-flow
    </protocol-inspection-flow>
  <protocol-inspection-packets>protocol-inspection-packets
    </protocol-inspection-packets>
  <protocol-inspection-bytes>prtl-inspn-bytes
    </protocol-inspection-bytes>
  <protocol-inspection-flow-protocol-identified>pr-in-fl-pr-id
    </protocol-inspection-flow-protocol-identified>
  <protocol-inspection-http-uri>protocol-inspection-http-uri
    </protocol-inspection-http-uri>
  <protocol-inspection-http-uri-matched>protocol-inspection-http-uri-matched
    </protocol-inspection-http-uri-matched>
  <protocol-inspection-wap-uri>protocol-inspection-wap-uri
    </protocol-inspection-wap-uri>
  <protocol-inspection-wap-uri-matched>protocol-inspection-wap-uri-matched
    </protocol-inspection-wap-uri-matched>
  <wap-transaction-created>wp-tr-cr</wap-transaction-created>
  <wap-transaction-maximum>wap-transtn-max
    </wap-transaction-maximum>
  <wap-transaction-freed>wap-transn-freed</wap-transaction-freed>

```

```

<wap-transaction-idle-freed>wap-transaction-idle-freed
  </wap-transaction-idle-freed>
<http-transaction-created>http-transaction-created
  </http-transaction-created>
<http-transaction-maximum>http-transaction-maximum
  </http-transaction-maximum>
<http-transaction-freed>http-transaction-freed
  </http-transaction-freed>
<http-transaction-idle-freed>http-transaction-idle-freed
  </http-transaction-idle-freed>
<uri-processing-error>uri-processing-error</uri-processing-error>
<uri-error-failed-to-process>uri-error-failed-to-process
  </uri-error-failed-to-process>
<uri-error-too-long>uri-error-too-long
  </uri-error-too-long>
<transaction-error-failed-to-parse>transaction-error-failed-to-parse
  </transaction-error-failed-to-parse>
<uri-error-no-system-resources>uri-error-no-system-resources
  </uri-error-no-system-resources>
<header-examination-failed-configuration>hdr-examn-failed-config
  </header-examination-failed-configuration>
<uri-examination-failed-configuration>uri-examination-failed-configuration
  </uri-examination-failed-configuration>
</service-identification-statistics>
</service-identification-statistics-information>

```

Description Statistics for the service-identification service.

Contents <bytes>—Total bytes for all packets processed by the service-identification service.

<errored-bytes>—Total bytes for all packets errored by the service-identification service.

<errored-packets>—Packets errored by the service-identification service in processing.

<errored-packets-http-transaction-in-error>—HTTP packets errored because the transaction is in error.

<errored-packets-tcp-malformed>—TCP packets errored because they were malformed.

<errored-packets-wap-invalid-transaction>—WAP packets errored for referencing an invalid transaction.

<errored-packets-wap-transaction-in-error>—WAP packets errored because the transaction is in error.

<header-examination-bytes>—Total bytes for all packets processed by header examination.

<header-examination-failed-configuration>—Number of header examinations failing due to configuration error.

<header-examination-flow>—Total flows examined by header examination.

<header-examination-flow-matched>—Total flows that matched a header examination rule.

<header-examination-http-protocol-required>—Flows identified as possible HTTP flows by header examination rules.

<header-examination-packets>—Packets processed by header examination.

<header-examination-protocol-required>—Flows identified as requiring protocol inspection.

<header-examination-wap-protocol-required>—Flows identified as possible WAP flows by header examination rules.

<http-transaction-created>—HTTP transaction sessions created.

<http-transaction-freed>—HTTP transaction sessions freed.

<http-transaction-idle-freed>—HTTP transaction sessions freed by idle clean-up.

<http-transaction-maximum>—Peak HTTP transaction sessions.

<interface-name>—Name of the adaptive services interface.

<interfaces>—Total number of interfaces summarized.

<packet-processing-error>—Total for all packet-processing errors.

<packets>—Total packets processed by service.

<protocol-inspected-flow>—Total flows that have been protocol inspected.

<protocol-inspection-bytes>—Total bytes for all packets processed by protocol inspection.

<protocol-inspection-flow>—Total flows currently undergoing protocol inspection.

<protocol-inspection-flow-protocol-identified>—Total flows that have been protocol-identified by protocol inspection.

<protocol-inspection-http-uri>—HTTP URI by protocol inspection.

<protocol-inspection-http-uri-matched>—HTTP URI that matched a URI rule.

<protocol-inspection-packets>—Packets processed by protocol inspection.

<protocol-inspection-wap-uri>—WAP URI by protocol inspection.

<protocol-inspection-wap-uri-matched>—WAP URI that matched a URI rule.

<transaction-error-failed-to-parse>—Failures to parse a transaction.

<uri-error-failed-to-process>—Failures to process a URI due to internal error.

<uri-error-no-system-resources>—Failures to process a transaction or URI due to lack of resources.

<uri-error-too-long>—Failures to process a URI due to maximum length exceeded.

<uri-examination-failed-configuration>—Number of URI examinations failing due to configuration error.

<uri-processing-error>—Total for all URI processing errors.

<wap-transaction-created>—WAP transaction sessions created.

<wap-transaction-freed>—WAP transaction sessions freed.

<wap-transaction-idle-freed>—WAP transaction sessions freed by idle clean-up.

<wap-transaction-maximum>—Peak WAP transaction sessions.

<service-identification-statistics-information>

Usage <rpc-reply>
 <service-identification-statistics-information>
 <service-identification-statistics>...</service-identification-statistics>
 </service-identification-statistics-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <service-identification-statistics>—Statistics for the service-identification service.

<service-ids-flow-table-information>

Usage <rpc-reply>
 <service-ids-flow-table-information>
 <ids-show-summary>...</ids-show-summary>
 <ids-per-service-set-flow-table>...</ids-per-service-set-flow-table>
 </service-ids-flow-table-information>
 </rpc-reply>

Description IDS table.

Contents <ids-per-service-set-flow-table>—IDS table sorted by service set.

 <ids-show-summary>—IDS table summary.

<service-l2tp-multilink-clear-information>

- Usage** <rpc-reply>
 <service-l2tp-multilink-clear-information>
 <l2tp-multilink-clear-entry>...</l2tp-multilink-clear-entry>
 </service-l2tp-multilink-clear-information>
 </rpc-reply>
- Description** Multilink information cleared by L2TP.
- Contents** <l2tp-multilink-clear-entry>—Multilink information cleared by L2TP.

<service-l2tp-session-clear-information>

- Usage** <rpc-reply>
 <service-l2tp-session-clear-information>
 <l2tp-session-clear-entry>...</l2tp-session-clear-entry>
 </service-l2tp-session-clear-information>
 </rpc-reply>
- Description** L2TP cleared session information.
- Contents** <l2tp-session-clear-entry>—L2TP cleared session information.

<service-l2tp-session-information>

- Usage** <rpc-reply>
 <service-l2tp-session-information>
 <l2tp-per-tunnel-session-table>...</l2tp-per-tunnel-session-table>
 </service-l2tp-session-information>
 </rpc-reply>
- Description** L2TP session information.
- Contents** <l2tp-per-tunnel-session-table>—Session table sorted by tunnel.

<service-l2tp-summary-information>

- Usage** <rpc-reply>
 <service-l2tp-summary-information>
 <l2tp-summary-table>...</l2tp-summary-table>
 </service-l2tp-summary-information>
 </rpc-reply>
- Description** L2TP summary information.
- Contents** <l2tp-summary-table>—L2TP summary.

<service-l2tp-tunnel-clear-information>

```
Usage <rpc-reply>
    <service-l2tp-tunnel-clear-information>
        <l2tp-tunnel-clear-entry>...</l2tp-tunnel-clear-entry>
    </service-l2tp-tunnel-clear-information>
</rpc-reply>
```

Description	L2TP cleared tunnel information.
--------------------	----------------------------------

Contents <l2tp-tunnel-clear-entry>—L2TP cleared tunnel information.

<service-l2tp-tunnel-information>

```
Usage <rpc-reply>
  <service-l2tp-tunnel-information>
    <l2tp-per-tunnel-group-tunnel-table>...</l2tp-per-tunnel-group-tunnel-table>
  </service-l2tp-tunnel-information>
</rpc-reply>
```

Description	L2TP tunnel information.
--------------------	--------------------------

Contents <|2tp-per-tunnel-group-tunnel-table>—Tunnel table sorted by tunnel group.

<service-l2tp-user-information>

```
Usage  <rpc-reply>
      <service-l2tp-user-information>
        <l2tp-per-tunnel-user-table>l2tp-per-tunnel-user-table
        </l2tp-per-tunnel-user-table>
      </service-l2tp-user-information>
    </rpc-reply>
```

Description L2TP user information.

Contents <|2tp-per-tunnel-user-table>—No documentation is available yet.

<service-nat-ipv6-multicast-interfaces>

Usage <service-nat-ipv6-multicast-interfaces-information>
 <service-nat-ipv6-multicast-interfaces>
 <v6-multicast-interface-name>*v6-multicast-interface-name*
 </v6-multicast-interface-name>
 <v6-multicast-configured-status>*v6-multicast-configured-status*
 </v6-multicast-configured-status>
 <v6-multicast-operation-status>*v6-multicast-operation-status*
 </v6-multicast-operation-status>
 <v6-multicast-by-all>*v6-multicast-by-all*</v6-multicast-by-all>
 </service-nat-ipv6-multicast-interfaces>
 </service-nat-ipv6-multicast-interfaces-information>

Description IPv6 multicast interfaces.

Contents <v6-multicast-by-all>—IPv6 multicast configured by all keyword.
 <v6-multicast-configured-status>—IPv6 multicast configuration.
 <v6-multicast-interface-name>—Name of interface for IPv6 multicast.
 <v6-multicast-operation-status>—IPv6 multicast status.

<service-nat-ipv6-multicast-interfaces-information>

Usage <rpc-reply>
 <service-nat-ipv6-multicast-interfaces-information>
 <service-nat-ipv6-multicast-interfaces>...
 </service-nat-ipv6-multicast-interfaces>
 </service-nat-ipv6-multicast-interfaces-information>
 </rpc-reply>

Description IPv6 multicast interfaces information.

Contents <service-nat-ipv6-multicast-interfaces>—IPv6 multicast interfaces.

<service-nat-pool>

Usage <sfw-per-service-set-nat-pool>
 <service-nat-pool>
 <pool-name>*pool-name*</pool-name>
 <translation-type>*translation-type*</translation-type>
 <pool-address-start>*pool-address-start*</pool-address-start>
 <pool-address-end>*pool-address-end*</pool-address-end>
 <pool-address-range>*pool-address-range*</pool-address-range>
 <pool-address-range-list>*pool-address-range-list*</pool-address-range-list>
 <pool-port-low>*pool-port-low*</pool-port-low>
 <pool-port-high>*pool-port-high*</pool-port-high>
 <pool-port-range>*pool-port-range*</pool-port-range>
 <pool-ports-in-use>*pool-ports-in-use*</pool-ports-in-use>
 <pool-out-of-port-errors>*pool-out-of-port-errors*</pool-out-of-port-errors>
 <pool-out-of-address-errors>*pool-out-of-address-errors*
 </pool-out-of-address-errors>
 <pool-max-ports-in-use>*pool-max-ports-in-use*</pool-max-ports-in-use>
 <pool-addresses-in-use>*pool-addresses-in-use*</pool-addresses-in-use>
 </service-nat-pool>
 </sfw-per-service-set-nat-pool>

Description NAT pool information.

Contents <pool-address-end>—End of address range.

<pool-address-range>—Range of port addresses.

<pool-address-range-list>—List of address ranges.

<pool-address-start>—Start of address range.

<pool-addresses-in-use>—Number of Addresses in use.

<pool-max-ports-in-use>—Maximum number of ports ever used in this pool so far.

<pool-name>—Name of the NAT pool.

<pool-out-of-address-errors>—Number of address allocation failures.

<pool-out-of-port-errors>—Number of port allocation failures.

<pool-port-high>—End of port range.

<pool-port-low>—Start of port range.

<pool-port-range>—Range of port numbers.

<pool-ports-in-use>—Number of ports in use.

<translation-type>—Type of Network Address Translation.

<service-nat-pool-information>

- Usage** <rpc-reply>
 <service-nat-pool-information>
 <sfw-per-service-set-nat-pool>...</sfw-per-service-set-nat-pool>
 </service-nat-pool-information>
 </rpc-reply>
- Description** Show information about NAT pools.
- Contents** <sfw-per-service-set-nat-pool>—NAT pool information for one service set.

<service-pgcp-conversation-information>

- Usage** <rpc-reply>
 <service-pgcp-conversation-information>
 <pgcp-per-service-set-conversation>...</pgcp-per-service-set-conversation>
 </service-pgcp-conversation-information>
 </rpc-reply>
- Description** Show conversations.
- Contents** <pgcp-per-service-set-conversation>—Show conversations.

<service-pgcp-debug-mem-mgmt-location>

- Usage** <rpc-reply>
 <service-pgcp-debug-mem-mgmt-location>
 <debug-mem-mgmt-location-information>*debug-mem-mgmt-location-information*
 </debug-mem-mgmt-location-information>
 </service-pgcp-debug-mem-mgmt-location>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <debug-mem-mgmt-location-information>—A list of all memory allocations sorted by type and function.

<service-pgcp-debug-mem-mgmt-memory-usage>

- Usage** <rpc-reply>
 <service-pgcp-debug-mem-mgmt-memory-usage>
 <debug-mem-mgmt-memory-usage-information>*debug-mem-mgmt-memory-usage-information*
 </debug-mem-mgmt-memory-usage-information>
 </service-pgcp-debug-mem-mgmt-memory-usage>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <debug-mem-mgmt-memory-usage-information>—A brief information of the memory usage.

<service-pgcp-debug-mem-mgmt-type>

Usage <rpc-reply>
 <service-pgcp-debug-mem-mgmt-type>
 <debug-mem-mgmt-type-information>*debug-mem-mgmt-type-information*
 </debug-mem-mgmt-type-information>
 </service-pgcp-debug-mem-mgmt-type>
 </rpc-reply>

Description No documentation is available yet.

Contents <debug-mem-mgmt-type-information>—A list of all memory allocations sorted by type.

<service-pgcp-debug-roundtrip>

Usage <rpc-reply>
 <service-pgcp-debug-roundtrip>
 <debug-roundtrip-information>*debug-roundtrip-information*
 </debug-roundtrip-information>
 </service-pgcp-debug-roundtrip>
 </rpc-reply>

Description No documentation is available yet.

Contents <debug-roundtrip-information>—Gate requests roundtrip delay (daemon <--> pic).

<service-pgcp-flow-count>

Usage <service-pgcp-flow-count-information>
 <service-pgcp-flow-count>
 <interface-name>*interface-name*</interface-name>
 <service-set-name>*service-set-name*</service-set-name>
 <flow-count>*flow-count*</flow-count>
 </service-pgcp-flow-count>
 </service-pgcp-flow-count-information>

Description Stateful firewall flow count.

Contents <flow-count>—Number of flows in the service set.

<interface-name>—Name of the adaptive services interface.

<service-set-name>—Name of the service set.

<service-pgcp-flow-count-information>

- Usage** <rpc-reply>
 <service-pgcp-flow-count-information>
 <service-pgcp-flow-count>...</service-pgcp-flow-count>
 </service-pgcp-flow-count-information>
 </rpc-reply>
- Description** Count of matching flow entries.
- Contents** <service-pgcp-flow-count>—Stateful firewall flow count.

<service-pgcp-flow-table>

- Usage** <pgcp-per-service-set-flow-table | pgcp-conversation>
 <service-pgcp-flow-table>
 <pgcp-flow-entry>...</pgcp-flow-entry>
 </service-pgcp-flow-table>
 </pgcp-per-service-set-flow-table | pgcp-conversation>
- Description** Stateful firewall flows.
- Contents** <pgcp-flow-entry>—Flow brief information.

<service-pgcp-flow-table-information>

- Usage** <rpc-reply>
 <service-pgcp-flow-table-information>
 <pgcp-per-service-set-flow-table>...</pgcp-per-service-set-flow-table>
 </service-pgcp-flow-table-information>
 </rpc-reply>
- Description** Conversations sorted by service set.
- Contents** <pgcp-per-service-set-flow-table>—Flows sorted by service set.

<service-pgcp-gate-entry-information>**Usage** <service-pgcp-gates>**<service-pgcp-gate-entry-information>**

```

<gate-id>gate-id</gate-id>
<gate-state>gate-state</gate-state>
<gate-direction>gate-direction</gate-direction>
<gate-action>gate-action</gate-action>
<source-routing-instance>source-routing-instance
  </source-routing-instance>
<destination-routing-instance>destination-routing-instance
  </destination-routing-instance>
<gate-service-set-id>gate-service-set-id</gate-service-set-id>
<media-card-name>media-card-name</media-card-name>
<media-handler-name>media-handler-name</media-handler-name>
<termination-id-string>termination-id-string</termination-id-string>
<gate-remote-source-address>gate-remote-source-address
  </gate-remote-source-address>
<gate-remote-source-port>gate-remote-source-port
  </gate-remote-source-port>
<gate-remote-destination-address>gate-remote-destination-address
  </gate-remote-destination-address>
<gate-remote-destination-port>gate-remote-destination-port
  </gate-remote-destination-port>
<gate-local-source-address>gate-local-source-address
  </gate-local-source-address>
<gate-local-source-port>gate-local-source-port
  </gate-local-source-port>
<gate-local-destination-address>gate-local-destination-address
  </gate-local-destination-address>
<gate-local-destination-port>gate-local-destination-port
  </gate-local-destination-port>
<gate-transport>gate-transport</gate-transport>
<gate-rtcp-shadow>gate-rtcp-shadow</gate-rtcp-shadow>
<gate-latch>gate-latch</gate-latch>
<gate-dscp>gate-dscp</gate-dscp>
<gate-tman-policing>gate-tman-policing</gate-tman-policing>
<gate-sdr>gate-sdr</gate-sdr>
<gate-pdr>gate-pdr</gate-pdr>
<gate-mbs>gate-mbs</gate-mbs>
<rtcp-sdr>rtcp-sdr</rtcp-sdr>
<rtcp-pdr>rtcp-pdr</rtcp-pdr>
<rtcp-mbs>rtcp-mbs</rtcp-mbs>
<gate-fuf-policing>gate-fuf-policing</gate-fuf-policing>
<gate-green-action>gate-green-action</gate-green-action>
<gate-yellow-action>gate-yellow-action</gate-yellow-action>
<gate-red-action>gate-red-action</gate-red-action>
<gate-output-packets>gate-output-packets</gate-output-packets>
<gate-input-packets>gate-input-packets</gate-input-packets>
<gate-dropped-packets>gate-dropped-packets</gate-dropped-packets>
<gate-lost-rtp-packets>gate-lost-rtp-packets</gate-lost-rtp-packets>
<gate-rtcp-information>...</gate-rtcp-information>
<gate-measured-rate>gate-measured-rate</gate-measured-rate>
<service-rate-limit-information>...</service-rate-limit-information>

```

```

    <gate-fuf-statistics-information>...</gate-fuf-statistics-information>
    <gate-mirroring-state>gate-mirroring-state</gate-mirroring-state>
    <gate-mirroring-correlation-number>gate-mirroring-correlation-number
        </gate-mirroring-correlation-number>
    <gate-mirroring-target-id>gate-mirroring-target-id</gate-mirroring-target-id>
    <gate-mirroring-direction>gate-mirroring-direction</gate-mirroring-direction>
  </service-pgcp-gate-entry-information>
</service-pgcp-gates>

```

Description No documentation is available yet.

Contents

- <destination-routing-instance>—Destination routing-instance.
- <gate-action>—Gate action (forward/drop).
- <gate-direction>—Gate direction (A-> B/B-> A).
- <gate-dropped-packets>—Packet-dropped by gate statistics.
- <gate-dscp>—DSCP for outgoing packets on this gate.
- <gate-fuf-policing>—Install/uninstall a fuf policer for this gate.
- <gate-fuf-statistics-information>—FUF statistics.
- <gate-green-action>—Action to be application over green packets.
- <gate-id>—Gate id.
- <gate-input-packets>—Packet-received by gate statistics.
- <gate-latch>—Install/uninstall a latch for this gate.
- <gate-local-destination-address>—Gate local destination address.
- <gate-local-destination-port>—Gate local destination port.
- <gate-local-source-address>—Gate local source address.
- <gate-local-source-port>—Gate local source port.
- <gate-lost-rtp-packets>—Number of lost RTP packets lost.
- <gate-mbs>—Maximum pdr burst size limit for a gate.
- <gate-measured-rate>—Measured rate of traffic for gate in bytes/second.
- <gate-mirroring-correlation-number>—Session mirroring correlation number.
- <gate-mirroring-direction>—Whether session mirroring is done before or after NAT.
- <gate-mirroring-state>—Whether session mirroring is active for this gate.
- <gate-mirroring-target-id>—List of session mirroring destinations.
- <gate-output-packets>—Packet-sent by gate statistics.

<gate-pdr>—Peak data rate threshold for a gate.

<gate-red-action>—Action to be application over red packets.

<gate-remote-destination-address>—Gate remote destination address.

<gate-remote-destination-port>—Gate remote destination port.

<gate-remote-source-address>—Gate remote source address.

<gate-remote-source-port>—Gate remote source port.

<gate-rtcp-information>—No documentation is available yet.

<gate-rtcp-shadow>—Is there a shadowed RTCP gate associated.

<gate-sdr>—Sustainable data rate threshold for a gate.

<gate-service-set-id>—Service set id.

<gate-state>—Gate state (active/disabled).

<gate-tman-policing>—Install/uninstall a traffic management policing for this gate.

<gate-transport>—Gate transport protocols.

<gate-yellow-action>—Action to be application over yellow packets.

<media-card-name>—Media card name.

<media-handler-name>—Media handler name.

<rtcp-mbs>—Maximum burst size limit of the RTCP stream.

<rtcp-pdr>—Peak data rate threshold of the RTCP stream.

<rtcp-sdr>—SDR Sustainable data rate threshold of the RTCP stream.

<service-rate-limit-information>—Rate limiting statistics.

<source-routing-instance>—Source routing-instance.

<termination-id-string>—Termination id as string.

<service-pgcp-gates>

Usage <rpc-reply>
 <service-pgcp-gates>
 <gateway-entry>...</gateway-entry>
 <service-pgcp-gate-entry-information>...</service-pgcp-gate-entry-information>
 <service-pgcp-gates-count>...</service-pgcp-gates-count>
 </service-pgcp-gates>
 </rpc-reply>

Description No documentation is available yet.

Contents <gateway-entry>—No documentation is available yet.
 <service-pgcp-gate-entry-information>—No documentation is available yet.
 <service-pgcp-gates-count>—Count of gate entries per gateway.

<service-pgcp-gates-count>

Usage <service-pgcp-gates>
 <service-pgcp-gates-count>
 <gate-count>*gate-count*</gate-count>
 <gateway-name>*gateway-name*</gateway-name>
 </service-pgcp-gates-count>
 </service-pgcp-gates>

Description Count of gate entries per gateway.

Contents <gate-count>—Number of gates in the gateway.
 <gateway-name>—No documentation is available yet.

<service-pgcp-gates-drain-information>

Usage <rpc-reply>
 <service-pgcp-gates-drain-information>
 <gateway-collections-number>*gateway-collections-number*
 </gateway-collections-number>
 </service-pgcp-gates-drain-information>
 </rpc-reply>

Description Gates information cleared by pgcpd.

Contents <gateway-collections-number>—No documentation is available yet.

<service-pgcp-stat-h248-extensive>

Usage <service-pgcp-statistics-gateway>
 <service-pgcp-stat-h248-extensive>
 <ex-command-flavor>ex-command-flavor</ex-command-flavor>
 <ex-commands-sent>ex-commands-sent</ex-commands-sent>
 <ex-commands-sent-wc>ex-commands-sent-wc</ex-commands-sent-wc>
 <ex-response-received>ex-response-received</ex-response-received>
 <ex-response-received-err>ex-response-received-err</ex-response-received-err>
 </service-pgcp-stat-h248-extensive>
 </service-pgcp-statistics-gateway>

Description No documentation is available yet.

Contents <ex-command-flavor>—H.248 command requests.

<ex-commands-sent>—Number of H.248 commands sent.

<ex-commands-sent-wc>—Number of H.248 wildcards commands sent.

<ex-response-received>—Number of H.248 received command responses.

<ex-response-received-err>—Number of H.248 received error command responses.

<service-pgcp-stat-h248-extensive-header>

Usage <service-pgcp-statistics-gateway>
 <service-pgcp-stat-h248-extensive-header>
 <ex-header-name>ex-header-name</ex-header-name>
 </service-pgcp-stat-h248-extensive-header>
 </service-pgcp-statistics-gateway>

Description No documentation is available yet.

Contents <ex-header-name>—Extensive statistics header.

<service-pgcp-stat-h248-per-command-rq>

Usage <service-pgcp-statistics-gateway>
 <service-pgcp-stat-h248-per-command-rq>
 <command-name>*command-name*</command-name>
 <commands-sent>*commands-sent*</commands-sent>
 <commands-sent-wc>*commands-sent-wc*</commands-sent-wc>
 <commands-received>*commands-received*</commands-received>
 <commands-received-wc>*commands-received-wc*
 </commands-received-wc>
 </service-pgcp-stat-h248-per-command-rq>
 </service-pgcp-statistics-gateway>

Description No documentation is available yet.

Contents <command-name>—H.248 command requests.

<commands-received>—Number of H.248 commands received.

<commands-received-wc>—Number of H.248 wildcards commands received.

<commands-sent>—Number of H.248 commands sent.

<commands-sent-wc>—Number of H.248 wildcards commands sent.

<service-pgcp-stat-h248-per-command-rsp>

Usage <service-pgcp-statistics-gateway>
 <service-pgcp-stat-h248-per-command-rsp>
 <response-name>*response-name*</response-name>
 <response-received>*response-received*</response-received>
 <response-received-err>*response-received-err*</response-received-err>
 <response-sent>*response-sent*</response-sent>
 <response-sent-err>*response-sent-err*</response-sent-err>
 </service-pgcp-stat-h248-per-command-rsp>
 </service-pgcp-statistics-gateway>

Description No documentation is available yet.

Contents <response-name>—H.248 command response.

<response-received>—Number of H.248 received command responses.

<response-received-err>—Number of H.248 received error command responses.

<response-sent>—Number of H.248 commands response sent.

<response-sent-err>—Number of H.248 error response sent.

<service-pgcp-statistics-gateway>

Usage <rpc-reply>
 <service-pgcp-statistics-gateway>
 <gateway-entry>...</gateway-entry>
 <service-pgcp-statistics-h248>...</service-pgcp-statistics-h248>
 <service-pgcp-stat-h248-per-command-rq>...
 </service-pgcp-stat-h248-per-command-rq>
 <service-pgcp-stat-h248-per-command-rsp>...
 </service-pgcp-stat-h248-per-command-rsp>
 <service-pgcp-stat-h248-extensive-header>...
 </service-pgcp-stat-h248-extensive-header>
 <service-pgcp-stat-h248-extensive>...</service-pgcp-stat-h248-extensive>
 </service-pgcp-statistics-gateway>
 </rpc-reply>

Description No documentation is available yet.

Contents <gateway-entry>—No documentation is available yet.

<service-pgcp-stat-h248-extensive>—No documentation is available yet.

<service-pgcp-stat-h248-extensive-header>—No documentation is available yet.

<service-pgcp-stat-h248-per-command-rq>—No documentation is available yet.

<service-pgcp-stat-h248-per-command-rsp>—No documentation is available yet.

<service-pgcp-statistics-h248>—No documentation is available yet.

<service-pgcp-statistics-h248>

Usage <service-pgcp-statistics-gateway>
 <service-pgcp-statistics-h248>
 <messages-received>*messages-received*</messages-received>
 <octets-received>*octets-received*</octets-received>
 <messages-sent>*messages-sent*</messages-sent>
 <octets-sent>*octets-sent*</octets-sent>
 <protocol-errors>*protocol-errors*</protocol-errors>
 <transport-losses>*transport-losses*</transport-losses>
 <last-detected-event>*last-detected-event*</last-detected-event>
 <last-detected-event-time>*last-detected-event-time*
 </last-detected-event-time>
 <last-reset-time>*last-reset-time*</last-reset-time>
 </service-pgcp-statistics-h248>
 </service-pgcp-statistics-gateway>

Description No documentation is available yet.

Contents <last-detected-event>—Last detected H.248 event.

<last-detected-event-time>—Last detected H.248 event time.

<last-reset-time>—Last H.248 reset time.

<messages-received>—Number of H.248 messages received.

<messages-sent>—Number of H.248 messages sent.

<octets-received>—Number of H.248 octets received.

<octets-sent>—Number of H.248 octet sent.

<protocol-errors>—Number of H.248 protocol erros.

<transport-losses>—Number of H.248 transport losses.

<service-pgcp-termination-entry-information>

Usage <service-pgcp-terminations>
 <service-pgcp-termination-entry-information>
 <termination-id-string>*termination-id-string*</termination-id-string>
 <termination-state>*termination-state*</termination-state>
 <termination-duration>*termination-duration*</termination-duration>
 <termination-h248-dump>*termination-h248-dump*</termination-h248-dump>
 </service-pgcp-termination-entry-information>
 </service-pgcp-terminations>

Description No documentation is available yet.

Contents <termination-duration>—Termination duration (in milliseconds).
 <termination-h248-dump>—Termination information.
 <termination-id-string>—Termination id as string.
 <termination-state>—Termination state (in/out of service).

<service-pgcp-termination-gates-information>

Usage <service-pgcp-terminations>
 <service-pgcp-termination-gates-information>
 <gate-id>*gate-id*</gate-id>
 <gate-direction>*gate-direction*</gate-direction>
 <gate-state>*gate-state*</gate-state>
 <gate-action>*gate-action*</gate-action>
 </service-pgcp-termination-gates-information>
 </service-pgcp-terminations>

Description No documentation is available yet.

Contents <gate-action>—Gate action (forward/drop).
 <gate-direction>—Gate direction (A- > B/B- > A).
 <gate-id>—Gate id.
 <gate-state>—Gate state (active/disabled).

<service-pgcp-terminations>

Usage <rpc-reply>
 <service-pgcp-terminations>
 <gateway-entry>...</gateway-entry>
 <service-pgcp-termination-entry-information>...
 </service-pgcp-termination-entry-information>
 <service-pgcp-termination-gates-information>...
 </service-pgcp-termination-gates-information>
 <service-pgcp-terminations-count>...</service-pgcp-terminations-count>
 </service-pgcp-terminations>
 </rpc-reply>

Description No documentation is available yet.

Contents <gateway-entry>—No documentation is available yet.

<service-pgcp-termination-entry-information>—No documentation is available yet.

<service-pgcp-termination-gates-information>—No documentation is available yet.

<service-pgcp-terminations-count>—Count of termination entries per gateway.

<service-pgcp-terminations-count>

Usage <service-pgcp-terminations>
 <service-pgcp-terminations-count>
 <termination-count>*termination-count*</termination-count>
 <gateway-name>*gateway-name*</gateway-name>
 </service-pgcp-terminations-count>
 </service-pgcp-terminations>

Description Count of termination entries per gateway.

Contents <gateway-name>—No documentation is available yet.

<termination-count>—Number of terminations in the gateway.

<service-pic-entry>

Usage <pgcpd-active-configuration | pgcpd-config>
 <service-pic-entry>
 <pic-name>*pic-name*</pic-name>
 <pic-status>*pic-status*</pic-status>
 </service-pic-entry>
 </pgcpd-active-configuration | pgcpd-config>

Description No documentation is available yet.

Contents <pic-name>—No documentation is available yet.

<pic-status>—No documentation is available yet.

<service-rate-limit-entry>

Usage	<pre> <service-rate-limit-information> <service-rate-limit-entry> <service-rate-limit-mark-color>service-rate-limit-mark-color </service-rate-limit-mark-color> <service-rate-limit-packet-count>service-rate-limit-packet-count </service-rate-limit-packet-count> <service-rate-limit-byte-count>service-rate-limit-byte-count </service-rate-limit-byte-count> </service-rate-limit-entry> </service-rate-limit-information> </pre>
Description	No documentation is available yet.
Contents	<p><service-rate-limit-byte-count>—Number of bytes marked.</p> <p><service-rate-limit-mark-color>—Mark color.</p> <p><service-rate-limit-packet-count>—Number of packets marked.</p>

<service-rate-limit-information>

Usage	<pre> <service-pgcp-gate-entry-information> <service-rate-limit-information> <service-rate-limit-entry>...</service-rate-limit-entry> </service-rate-limit-information> </service-pgcp-gate-entry-information> </pre>
Description	Rate limiting statistics.
Contents	<service-rate-limit-entry>—No documentation is available yet.

<service-set-cpu-statistics>

Usage	<pre> <service-set-cpu-statistics-information> <service-set-cpu-statistics> <service-set-name>service-set-name</service-set-name> <interface-name>interface-name</interface-name> <cpu-utilization-percent>cpu-utilization-percent</cpu-utilization-percent> </service-set-cpu-statistics> </service-set-cpu-statistics-information> </pre>
Description	CPU usage statistics.
Contents	<p><cpu-utilization-percent>—CPU utilization (percent).</p> <p><interface-name>—Name of the adaptive services interface.</p> <p><service-set-name>—Name of the service set.</p>

<service-set-cpu-statistics-information>

Usage	<pre><rpc-reply> <service-set-cpu-statistics-information> <service-set-cpu-statistics>...</service-set-cpu-statistics> </service-set-cpu-statistics-information> </rpc-reply></pre>
Description	No documentation is available yet.
Contents	<service-set-cpu-statistics>—CPU usage statistics.

<service-set-entry>

Usage	<pre><pgcpd-active-configuration pgcpd-config> <service-set-entry> <service-set-name>service-set-name</service-set-name> <id>id</id> <rule-ref-entry>...</rule-ref-entry> </service-set-entry> </pgcpd-active-configuration pgcpd-config></pre>
Description	No documentation is available yet.
Contents	<p><id>—No documentation is available yet.</p> <p><rule-ref-entry>—No documentation is available yet.</p> <p><service-set-name>—Name of the service set.</p>

<service-set-memory-statistics>

Usage	<pre><service-set-memory-statistics-information> <service-set-memory-statistics> <service-set-name>service-set-name</service-set-name> <interface-name>interface-name</interface-name> <bytes-used>bytes-used</bytes-used> </service-set-memory-statistics> </service-set-memory-statistics-information></pre>
Description	Memory usage statistics.
Contents	<p><bytes-used>—Memory used (bytes).</p> <p><interface-name>—Name of the adaptive services interface.</p> <p><service-set-name>—Name of the service set.</p>

<service-set-memory-statistics-information>

- Usage** <rpc-reply>
 <service-set-memory-statistics-information>
 <service-set-memory-statistics>...</service-set-memory-statistics>
 </service-set-memory-statistics-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <service-set-memory-statistics>—Memory usage statistics.

<service-set-packet-drop-statistics>

- Usage** <rpc-reply>
 <service-set-packet-drop-statistics>
 <service-set-packet-drops>...</service-set-packet-drops>
 </service-set-packet-drop-statistics>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <service-set-packet-drops>—Packet-drop statistics.

<service-set-packet-drops>

- Usage** <service-set-packet-drop-statistics>
 <service-set-packet-drops>
 <service-set-name>service-set-name</service-set-name>
 <interface-name>interface-name</interface-name>
 <cpulimit-drops>cpulimit-drops</cpulimit-drops>
 <memlimit-drops>memlimit-drops</memlimit-drops>
 <flowlimit-drops>flowlimit-drops</flowlimit-drops>
 </service-set-packet-drops>
 </service-set-packet-drop-statistics>
- Description** Packet-drop statistics.
- Contents** <cpulimit-drops>—Drops because CPU usage limit is reached.
- <flowlimit-drops>—Drops because Flow limit is reached.
- <interface-name>—Name of the adaptive services interface.
- <memlimit-drops>—Drops because Memory usage limit is reached.
- <service-set-name>—Name of the service set.

<service-set-service-type-entry>

Usage	<pre> <service-set-summary-information-entry> <service-set-service-type-entry> <service-type>service-type</service-type> <service-sets-configured>srvc-sets-configured </service-sets-configured> <service-set-bytes-used>srvc-set-bytes-used</service-set-bytes-used> <service-set-percent-bytes-used>service-set-percent-bytes-used </service-set-percent-bytes-used> <service-set-cpu-utilization>srvc-set-cpu-util </service-set-cpu-utilization> <service-set-policy-bytes-used>servc-set-policy-bytes-used </service-set-policy-bytes-used> <service-set-percent-policy-bytes-used>srvc-set-percnt-policy-bytes-used </service-set-percent-policy-bytes-used> </service-set-service-type-entry> </service-set-summary-information-entry> </pre>
Description	Service set service type entry.
Contents	<pre> <service-set-bytes-used>—Memory used (bytes). <service-set-cpu-utilization>—CPU utilization (percent). <service-set-percent-bytes-used>—Memory used (percent). <service-set-percent-policy-bytes-used>—Policy memory used (percent). <service-set-policy-bytes-used>—Policy memory used (bytes). <service-sets-configured>—Number of service sets configured. <service-type>—Service type. </pre>

<service-set-summary-information>

Usage	<pre> <rpc-reply> <service-set-summary-information> <service-set-summary-information-entry>... </service-set-summary-information-entry> </service-set-summary-information> </rpc-reply> </pre>
Description	Service set summary information.
Contents	<pre> <service-set-summary-information-entry>—Service set summary information entry. </pre>

<service-set-summary-information-entry>

- Usage** <service-set-summary-information>
 <service-set-summary-information-entry>
 <interface-name>*interface-name*</interface-name>
 <service-set-service-type-entry>...</service-set-service-type-entry>
 </service-set-summary-information-entry>
 </service-set-summary-information>
- Description** Service set summary information entry.
- Contents** <interface-name>—Name of the adaptive services interface.
 <service-set-service-type-entry>—Service set service type entry.

<service-sfw-conversation-information>

- Usage** <rpc-reply>
 <service-sfw-conversation-information>
 <sfw-per-service-set-conversation>...</sfw-per-service-set-conversation>
 </service-sfw-conversation-information>
 </rpc-reply>
- Description** Show conversations.
- Contents** <sfw-per-service-set-conversation>—Show conversations.

<service-sfw-flow-count>

- Usage** <service-sfw-flow-count-information>
 <service-sfw-flow-count>
 <interface-name>*interface-name*</interface-name>
 <service-set-name>*service-set-name*</service-set-name>
 <flow-count>*flow-count*</flow-count>
 </service-sfw-flow-count>
 </service-sfw-flow-count-information>
- Description** Stateful firewall flow count.
- Contents** <flow-count>—Number of flows in the service set.
 <interface-name>—Name of the adaptive services interface.
 <service-set-name>—Name of the service set.

<service-sfw-flow-count-information>

Usage <rpc-reply>
 <service-sfw-flow-count-information>
 <service-sfw-flow-count>...</service-sfw-flow-count>
 </service-sfw-flow-count-information>
 </rpc-reply>

Description Count of matching flow entries.

Contents <service-sfw-flow-count>—Stateful firewall flow count.

<service-sfw-flow-drain>

Usage <service-sfw-flow-drain-information>
 <service-sfw-flow-drain>
 <interface-name>*interface-name*</interface-name>
 <service-set-name>*service-set-name*</service-set-name>
 <conversations-removed>*conversations-removed*</conversations-removed>
 </service-sfw-flow-drain>
 </service-sfw-flow-drain-information>

Description Stateful firewall flow removed.

Contents <conversations-removed>—Number of conversations removed in the service set.

 <interface-name>—Name of the adaptive services interface.

 <service-set-name>—Name of the service set.

<service-sfw-flow-drain-information>

Usage <rpc-reply>
 <service-sfw-flow-drain-information>
 <service-sfw-flow-drain>...</service-sfw-flow-drain>
 </service-sfw-flow-drain-information>
 </rpc-reply>

Description Remove established flows from the flow table.

Contents <service-sfw-flow-drain>—Stateful firewall flow removed.

<service-sfw-flow-table>

Usage <sfw-per-service-set-flow-table | sfw-conversation>
 <service-sfw-flow-table>
 <sfw-flow-entry>...</sfw-flow-entry>
 </service-sfw-flow-table>
 </sfw-per-service-set-flow-table | sfw-conversation>

Description Stateful firewall flows.

Contents <sfw-flow-entry>—Flow brief information.

<service-sfw-flow-table-information>

- Usage** <rpc-reply>
 <service-sfw-flow-table-information>
 <sfw-per-service-set-flow-table>...</sfw-per-service-set-flow-table>
 </service-sfw-flow-table-information>
 </rpc-reply>
- Description** Conversations sorted by service set.
- Contents** <sfw-per-service-set-flow-table>—Flows sorted by service set.

<service-sfw-sip-call-count>

- Usage** <service-sfw-sip-call-count-information>
 <service-sfw-sip-call-count>
 <interface-name>*interface-name*</interface-name>
 <service-set-name>*service-set-name*</service-set-name>
 <sip-call-count>*sip-call-count*</sip-call-count>
 </service-sfw-sip-call-count>
 </service-sfw-sip-call-count-information>
- Description** SIP call count.
- Contents** <interface-name>—Name of the adaptive services interface.
 <service-set-name>—Name of the service set.
 <sip-call-count>—Number of SIP calls in the service set.

<service-sfw-sip-call-count-information>

- Usage** <rpc-reply>
 <service-sfw-sip-call-count-information>
 <service-sfw-sip-call-count>...</service-sfw-sip-call-count>
 </service-sfw-sip-call-count-information>
 </rpc-reply>
- Description** Display a count of the matching SIP calls.
- Contents** <service-sfw-sip-call-count>—SIP call count.

<service-sfw-sip-call-drain>

- Usage** <service-sfw-sip-call-drain-information>
 <service-sfw-sip-call-drain>
 <interface-name>*interface-name*</interface-name>
 <service-set-name>*service-set-name*</service-set-name>
 <sip-calls-removed>*sip-calls-removed*</sip-calls-removed>
 </service-sfw-sip-call-drain>
 </service-sfw-sip-call-drain-information>
- Description** SIP calls removed.
- Contents** <interface-name>—Name of the adaptive services interface.
 <service-set-name>—Name of the service set.
 <sip-calls-removed>—SIP calls removed from the service set.

<service-sfw-sip-call-drain-information>

- Usage** <rpc-reply>
 <service-sfw-sip-call-drain-information>
 <service-sfw-sip-call-drain>...</service-sfw-sip-call-drain>
 </service-sfw-sip-call-drain-information>
 </rpc-reply>
- Description** Remove established SIP calls from the flow table.
- Contents** <service-sfw-sip-call-drain>—SIP calls removed.

<service-sfw-sip-call-information>

- Usage** <rpc-reply>
 <service-sfw-sip-call-information>
 <sfw-per-service-set-sip-calls>...</sfw-per-service-set-sip-calls>
 </service-sfw-sip-call-information>
 </rpc-reply>
- Description** SIP call information.
- Contents** <sfw-per-service-set-sip-calls>—Stateful firewall SIP calls sorted by service set.

<service-sfw-sip-registration-count>

- Usage** <service-sfw-sip-registration-count-information>
 <service-sfw-sip-registration-count>
 <interface-name>*interface-name*</interface-name>
 <service-set-name>*service-set-name*</service-set-name>
 <sip-registration-count>*sip-registration-count*
 </sip-registration-count>
 </service-sfw-sip-registration-count>
 </service-sfw-sip-registration-count-information>
- Description** SIP registration count.
- Contents** <interface-name>—Name of the adaptive services interface.
 <service-set-name>—Name of the service set.
 <sip-registration-count>—Number of SIP registration in the service set.

<service-sfw-sip-registration-count-information>

- Usage** <rpc-reply>
 <service-sfw-sip-registration-count-information>
 <service-sfw-sip-registration-count>...</service-sfw-sip-registration-count>
 </service-sfw-sip-registration-count-information>
 </rpc-reply>
- Description** Display a count of the matching SIP registrations.
- Contents** <service-sfw-sip-registration-count>—SIP registration count.

<service-sfw-sip-registration-drain>

- Usage** <service-sfw-sip-registration-drain-information>
 <service-sfw-sip-registration-drain>
 <interface-name>*interface-name*</interface-name>
 <service-set-name>*service-set-name*</service-set-name>
 <sip-registration-removed>*sip-registration-removed*
 </sip-registration-removed>
 </service-sfw-sip-registration-drain>
 </service-sfw-sip-registration-drain-information>
- Description** SIP registration removed.
- Contents** <interface-name>—Name of the adaptive services interface.
 <service-set-name>—Name of the service set.
 <sip-registration-removed>—SIP registration removed from the service set.

<service-sfw-sip-registration-drain-information>

- Usage** <rpc-reply>
 <service-sfw-sip-registration-drain-information>
 <service-sfw-sip-registration-drain>...</service-sfw-sip-registration-drain>
 </service-sfw-sip-registration-drain-information>
 </rpc-reply>
- Description** Remove established SIP registrations from the flow table.
- Contents** <service-sfw-sip-registration-drain>—SIP registration removed.

<service-sfw-sip-registration-information>

- Usage** <rpc-reply>
 <service-sfw-sip-registration-information>
 <sfw-per-service-set-sip-registrations>...
 </sfw-per-service-set-sip-registrations>
 </service-sfw-sip-registration-information>
 </rpc-reply>
- Description** SIP registration information.
- Contents** <sfw-per-service-set-sip-registrations>—Stateful firewall SIP registrations sorted by service set.

<service-sfw-statistics-entry>

- Usage** <service-sfw-statistics-information>
 <service-sfw-statistics-entry>
 <interface-name>*interface-name*</interface-name>
 <sfw-stats-service-set-entry>...</sfw-stats-service-set-entry>
 </service-sfw-statistics-entry>
 </service-sfw-statistics-information>
- Description** Stateful firewall statistics entry.
- Contents** <interface-name>—Name of the adaptive services interface.
 <sfw-stats-service-set-entry>—Stateful firewall service set statistics entry.

<service-sfw-statistics-information>

- Usage** <rpc-reply>
 <service-sfw-statistics-information>
 <service-sfw-statistics-entry>...</service-sfw-statistics-entry>
 </service-sfw-statistics-information>
 </rpc-reply>
- Description** Stateful firewall statistics information.
- Contents** <service-sfw-statistics-entry>—Stateful firewall statistics entry.

<services-l2tp-multilink-information>

- Usage** <rpc-reply>
 <services-l2tp-multilink-information>
 <l2tp-multilink-entry>...</l2tp-multilink-entry>
 </services-l2tp-multilink-information>
 </rpc-reply>
- Description** L2TP multilink information.
- Contents** <l2tp-multilink-entry>—L2TP multilink information.

<services-l2tp-radius-accounting-servers-information>

- Usage** <rpc-reply>
 <services-l2tp-radius-accounting-servers-information>
 <radius-accounting-server-information-entry>...
 </radius-accounting-server-information-entry>
 </services-l2tp-radius-accounting-servers-information>
 </rpc-reply>
- Description** RADIUS accounting servers information table.
- Contents** <radius-accounting-server-information-entry>—RADIUS accounting server information entry sorted by IP address.

<services-l2tp-radius-accounting-statistics-information>

- Usage** <rpc-reply>
 <services-l2tp-radius-accounting-statistics-information>
 <radius-accounting-statistic-information-entry>...
 </radius-accounting-statistic-information-entry>
 </services-l2tp-radius-accounting-statistics-information>
 </rpc-reply>
- Description** RADIUS accounting statistics information table.
- Contents** <radius-accounting-statistic-information-entry>—RADIUS accounting statistic entry sorted by IP address.

<services-l2tp-radius-authentication-accounting-servers-information>

- Usage** <rpc-reply>
 <services-l2tp-radius-authentication-accounting-servers-information>
 <radius-authentication-server-information-entry>...
 </radius-authentication-server-information-entry>
 <radius-accounting-server-information-entry>...
 </radius-accounting-server-information-entry>
 </services-l2tp-radius-authentication-accounting-servers-information>
 </rpc-reply>
- Description** RADIUS authentication and accounting servers information.
- Contents** <radius-accounting-server-information-entry>—RADIUS accounting server information entry sorted by IP address.
- <radius-authentication-server-information-entry>—RADIUS authentication server information entry sorted by IP address.

<services-l2tp-radius-authentication-accounting-statistics-information>

- Usage** <rpc-reply>
 <services-l2tp-radius-authentication-accounting-statistics-information>
 <radius-authentication-statistic-information-entry>...
 </radius-authentication-statistic-information-entry>
 <radius-accounting-statistic-information-entry>...
 </radius-accounting-statistic-information-entry>
 </services-l2tp-radius-authentication-accounting-statistics-information>
 </rpc-reply>
- Description** RADIUS authentication and accounting statistics information.
- Contents** <radius-accounting-statistic-information-entry>—RADIUS accounting statistic entry sorted by IP address.
- <radius-authentication-statistic-information-entry>—RADIUS authentication statistic entry sorted by IP address.

<services-l2tp-radius-authentication-servers-information>

- Usage** <rpc-reply>
 <services-l2tp-radius-authentication-servers-information>
 <radius-authentication-server-information-entry>...
 </radius-authentication-server-information-entry>
 </services-l2tp-radius-authentication-servers-information>
 </rpc-reply>
- Description** RADIUS authentication servers information.
- Contents** <radius-authentication-server-information-entry>—RADIUS authentication server information entry sorted by IP address.

<services-l2tp-radius-authentication-statistics-information>

- Usage** <rpc-reply>
 <services-l2tp-radius-authentication-statistics-information>
 <radius-authentication-statistic-information-entry>...
 </radius-authentication-statistic-information-entry>
 </services-l2tp-radius-authentication-statistics-information>
 </rpc-reply>
- Description** RADIUS authentication statistics information.
- Contents** <radius-authentication-statistic-information-entry>—RADIUS authentication statistic entry sorted by IP address.

<services-pgcpd-root-termination>

- Usage** <rpc-reply>
 <services-pgcpd-root-termination>
 <root-termination-information>*root-termination-information*
 </root-termination-information>
 </services-pgcpd-root-termination>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <root-termination-information>—H248 root termination information.

<sfw-conversation>

- Usage** <sfw-per-service-set-conversation>
 <sfw-conversation>
 <sfw-flow-table-conv-arg>*sfw-flow-table-conv-arg*</sfw-flow-table-conv-arg>
 <sfw-flow-table-conv-initiator>*sfw-flow-table-conv-initiator*
 </sfw-flow-table-conv-initiator>
 <sfw-flow-table-conv-responder>*sfw-flow-table-conv-responder*
 </sfw-flow-table-conv-responder>
 <service-sfw-flow-table>...</service-sfw-flow-table>
 </sfw-conversation>
 </sfw-per-service-set-conversation>
- Description** Stateful firewall conversations.
- Contents** <service-sfw-flow-table>—Stateful firewall flows.
- <sfw-flow-table-conv-arg>—Application Protocol Gateway protocol.
- <sfw-flow-table-conv-initiator>—Number of initiator flows.
- <sfw-flow-table-conv-responder>—Number of responder flows.

<sfw-flow-entry>

Usage <service-sfw-flow-table>
<sfw-flow-entry>
 <sfw-flow-protocol>sfw-flow-protocol</sfw-flow-protocol>
 <sfw-flow-source-ip>sfw-flow-source-ip</sfw-flow-source-ip>
 <sfw-flow-source-port>sfw-flow-source-port</sfw-flow-source-port>
 <sfw-flow-destination-ip>sfw-flow-destination-ip</sfw-flow-destination-ip>
 <sfw-flow-destination-port>sfw-flow-destination-port
 </sfw-flow-destination-port>
 <sfw-flow-state>sfw-flow-state</sfw-flow-state>
 <sfw-flow-direction>sfw-flow-direction</sfw-flow-direction>
 <sfw-flow-frame-counter>sfw-flow-frame-counter</sfw-flow-frame-counter>
 <sfw-flow-gate-id>sfw-flow-gate-id</sfw-flow-gate-id>
 <sfw-flow-nat>...</sfw-flow-nat>
 <sfw-flow-table-byte-count>sfw-flow-table-byte-count
 </sfw-flow-table-byte-count>
 <sfw-flow-table-tcp-window-size>sfw-flow-table-tcp-window-size
 </sfw-flow-table-tcp-window-size>
 <sfw-flow-table-tcp-acknowledge>sfw-flow-table-tcp-acknowledge
 </sfw-flow-table-tcp-acknowledge>
 <sfw-flow-table-tcp-tickle>sfw-flow-table-tcp-tickle
 </sfw-flow-table-tcp-tickle>
 <sfw-flow-table-role>sfw-flow-table-role</sfw-flow-table-role>
 <sfw-flow-table-timeout>sfw-flow-table-timeout</sfw-flow-table-timeout>
 <sfw-flow-table-protocol-detail>sfw-flow-table-protocol-detail
 </sfw-flow-table-protocol-detail>
</sfw-flow-entry>
 </service-sfw-flow-table>

Description Flow brief information.

Contents <sfw-flow-destination-ip>—Flow destination IP address.
 <sfw-flow-destination-port>—Flow destination port.
 <sfw-flow-direction>—Flow direction.
 <sfw-flow-frame-counter>—Number of frames transmitted.
 <sfw-flow-gate-id>—PGCP gate-id.
 <sfw-flow-nat>—NAT translation.
 <sfw-flow-protocol>—Flow protocol description.
 <sfw-flow-source-ip>—Source IP address.
 <sfw-flow-source-port>—Source port address.
 <sfw-flow-state>—Flow state.
 <sfw-flow-table-byte-count>—Flow byte count.
 <sfw-flow-table-protocol-detail>—Flow protocol detail information.

<sfw-flow-table-role>—Role of flow in conversation.

<sfw-flow-table-tcp-acknowledge>—TCP protocol acknowledge.

<sfw-flow-table-tcp-tickle>—Time between TCP tickles (seconds).

<sfw-flow-table-tcp-window-size>—TCP protocol window size.

<sfw-flow-table-timeout>—Timeout value of flow (seconds).

<sfw-flow-nat>

Usage <sfw-flow-entry>
 <sfw-flow-nat>
 <sfw-flow-nat-ip>sfw-flow-nat-ip</sfw-flow-nat-ip>
 <sfw-flow-nat-port>sfw-flow-nat-port</sfw-flow-nat-port>
 <sfw-flow-translated-ip>sfw-flow-translated-ip</sfw-flow-translated-ip>
 <sfw-flow-translated-port>sfw-flow-translated-port</sfw-flow-translated-port>
 </sfw-flow-nat>
 </sfw-flow-entry>

Description NAT translation.

Contents <sfw-flow-nat-ip>—Original IP address.

<sfw-flow-nat-port>—Original port.

<sfw-flow-translated-ip>—Translated IP address.

<sfw-flow-translated-port>—Translated port.

<sfw-per-service-set-conversation>

Usage <service-sfw-conversation-information>
 <sfw-per-service-set-conversation>
 <service-set-name>service-set-name</service-set-name>
 <interface-name>interface-name</interface-name>
 <sfw-conversation>...</sfw-conversation>
 </sfw-per-service-set-conversation>
 </service-sfw-conversation-information>

Description Show conversations.

Contents <interface-name>—Name of the adaptive services interface.

<service-set-name>—Name of the service set.

<sfw-conversation>—Stateful firewall conversations.

<sfw-per-service-set-flow-table>

- Usage** <service-sfw-flow-table-information>
 <sfw-per-service-set-flow-table>
 <service-set-name>*service-set-name*</service-set-name>
 <interface-name>*interface-name*</interface-name>
 <service-sfw-flow-table>...</service-sfw-flow-table>
 </sfw-per-service-set-flow-table>
 </service-sfw-flow-table-information>
- Description** Flows sorted by service set.
- Contents** <interface-name>—Name of the adaptive services interface.
 <service-set-name>—Name of the service set.
 <service-sfw-flow-table>—Stateful firewall flows.

<sfw-per-service-set-nat-pool>

- Usage** <service-nat-pool-information>
 <sfw-per-service-set-nat-pool>
 <service-set-name>*service-set-name*</service-set-name>
 <interface-name>*interface-name*</interface-name>
 <service-nat-pool>...</service-nat-pool>
 </sfw-per-service-set-nat-pool>
 </service-nat-pool-information>
- Description** NAT pool information for one service set.
- Contents** <interface-name>—Name of the adaptive services interface.
 <service-nat-pool>—NAT pool information.
 <service-set-name>—Name of the service set.

<sfw-per-service-set-sip-calls>

- Usage** <service-sfw-sip-call-information>
 <sfw-per-service-set-sip-calls>
 <interface-name>*interface-name*</interface-name>
 <service-set-name>*service-set-name*</service-set-name>
 <sfw-sip-calls>...</sfw-sip-calls>
 </sfw-per-service-set-sip-calls>
 </service-sfw-sip-call-information>
- Description** Stateful firewall SIP calls sorted by service set.
- Contents** <interface-name>—Name of the adaptive services interface.
 <service-set-name>—Name of the service set.
 <sfw-sip-calls>—No documentation is available yet.

<sfw-per-service-set-sip-registrations>

- Usage** <service-sfw-sip-registration-information>
 <sfw-per-service-set-sip-registrations>
 <interface-name>*interface-name*</interface-name>
 <service-set-name>*service-set-name*</service-set-name>
 <sfw-sip-registers>...</sfw-sip-registers>
 </sfw-per-service-set-sip-registrations>
 </service-sfw-sip-registration-information>
- Description** Stateful firewall SIP registrations sorted by service set.
- Contents** <interface-name>—Name of the adaptive services interface.
 <service-set-name>—Name of the service set.
 <sfw-sip-registers>—No documentation is available yet.

<sfw-sip-call-entry>

Usage <sfw-sip-calls>
<sfw-sip-call-entry>
 <sfw-sip-from>sfw-sip-from</sfw-sip-from>
 <sfw-sip-to>sfw-sip-to</sfw-sip-to>
 <sfw-sip-callid>sfw-sip-callid</sfw-sip-callid>
 <sfw-sip-number-control-iflows>sfw-sip-number-control-iflows
 </sfw-sip-number-control-iflows>
 <sfw-sip-number-control-rflows>sfw-sip-number-control-rflows
 </sfw-sip-number-control-rflows>
 <sfw-sip-control-iflow-table>sfw-sip-control-iflow-table
 </sfw-sip-control-iflow-table>
 <sfw-sip-control-rflow-table>sfw-sip-control-rflow-table
 </sfw-sip-control-rflow-table>
 <sfw-sip-number-contact-iflows>sfw-sip-number-contact-iflows
 </sfw-sip-number-contact-iflows>
 <sfw-sip-number-contact-rflows>sfw-sip-number-contact-rflows
 </sfw-sip-number-contact-rflows>
 <sfw-sip-contact-iflow-table>sfw-sip-contact-iflow-table
 </sfw-sip-contact-iflow-table>
 <sfw-sip-contact-rflow-table>sfw-sip-contact-rflow-table
 </sfw-sip-contact-rflow-table>
 <sfw-sip-number-media-iflows>sfw-sip-number-media-iflows
 </sfw-sip-number-media-iflows>
 <sfw-sip-number-media-rflows>sfw-sip-number-media-rflows
 </sfw-sip-number-media-rflows>
 <sfw-sip-media-iflow-table>sfw-sip-media-iflow-table
 </sfw-sip-media-iflow-table>
 <sfw-sip-media-rflow-table>sfw-sip-media-rflow-table
 </sfw-sip-media-rflow-table>
</sfw-sip-call-entry>
 </sfw-sip-calls>

Description Session Initiation Protocol call.

Contents <sfw-sip-callid>—SIP call ID.

<sfw-sip-contact-iflow-table>—No documentation is available yet.

<sfw-sip-contact-rflow-table>—No documentation is available yet.

<sfw-sip-control-iflow-table>—No documentation is available yet.

<sfw-sip-control-rflow-table>—No documentation is available yet.

<sfw-sip-from>—SIP invite from.

<sfw-sip-media-iflow-table>—No documentation is available yet.

<sfw-sip-media-rflow-table>—No documentation is available yet.

<sfw-sip-number-contact-iflows>—Number of SIP contact initiator flows.

<sfw-sip-number-contact-rflows>—Number of SIP contact responder flows.

<sfw-sip-number-control-iflows>—Number of SIP Control initiator flows.

<sfw-sip-number-control-rflows>—Number of SIP control responder flows.

<sfw-sip-number-media-iflows>—Number of SIP media initiator flows.

<sfw-sip-number-media-rflows>—Number of SIP media responder flows.

<sfw-sip-to>—SIP invite to.

<sfw-sip-calls>

Usage <sfw-per-service-set-sip-calls>
 <sfw-sip-calls>
 <sfw-sip-call-entry>...</sfw-sip-call-entry>
 </sfw-sip-calls>
 </sfw-per-service-set-sip-calls>

Description No documentation is available yet.

Contents <sfw-sip-call-entry>—Session Initiation Protocol call.

<sfw-sip-register-entry>

Usage <sfw-sip-registers>
 <sfw-sip-register-entry>
 <sfw-sip-register-protocol>sfw-sip-register-protocol
 </sfw-sip-register-protocol>
 <sfw-sip-register-address>sfw-sip-register-address</sfw-sip-register-address>
 <sfw-sip-register-port>sfw-sip-register-port</sfw-sip-register-port>
 <sfw-sip-register-acked/>
 <sfw-sip-register-expiration>sfw-sip-register-expiration
 </sfw-sip-register-expiration>
 <sfw-sip-register-remaining>sfw-sip-register-remaining
 </sfw-sip-register-remaining>
 <sfw-sip-from>sfw-sip-from</sfw-sip-from>
 <sfw-sip-to>sfw-sip-to</sfw-sip-to>
 <sfw-sip-callid>sfw-sip-callid</sfw-sip-callid>
 </sfw-sip-register-entry>
 </sfw-sip-registers>

Description Display a SIP register.

Contents <sfw-sip-callid>—SIP call ID.

<sfw-sip-from>—SIP invite from.

<sfw-sip-register-acked>—SIP register is acked by registrar.

<sfw-sip-register-address>—SIP registered IP address.

<sfw-sip-register-expiration>—SIP register expiration timeout.

<sfw-sip-register-port>—SIP registered port.

<sfw-sip-register-protocol>—SIP registration protocol description.

<sfw-sip-register-remaining>—SIP register valid tile expiration.

<sfw-sip-to>—SIP invite to.

<sfw-sip-registers>

Usage <sfw-per-service-set-sip-registrations>
 <sfw-sip-registers>
 <sfw-sip-register-entry>...</sfw-sip-register-entry>
 </sfw-sip-registers>
 </sfw-per-service-set-sip-registrations>

Description No documentation is available yet.

Contents <sfw-sip-register-entry>—Display a SIP register.

<sfw-stats-service-set-entry>

Usage <service-sfw-statistics-entry>
 <sfw-stats-service-set-entry>
 <service-set-name>service-set-name</service-set-name>
 <total-flow-accepts>total-flow-accepts</total-flow-accepts>
 <total-flow-discards>total-flow-discards</total-flow-discards>
 <total-flow-rejects>total-flow-rejects</total-flow-rejects>
 <total-drops>total-drops</total-drops>
 <new-flow-counters>...</new-flow-counters>
 <existing-flow-counters>...</existing-flow-counters>
 <drop_counters>...</drop_counters>
 <error-counters>...</error-counters>
 <ip-error-counters>...</ip-error-counters>
 <tcp-error-counters>...</tcp-error-counters>
 <udp-error-counters>...</udp-error-counters>
 <icmp-error-counters>...</icmp-error-counters>
 <alg-error-counters>...</alg-error-counters>
 <alg-name>alg-name</alg-name>
 <sip-active-call-count>sip-active-call-count</sip-active-call-count>
 <sip-active-reg-count>sip-active-reg-count</sip-active-reg-count>
 <sip-alg-counters>...</sip-alg-counters>
 </sfw-stats-service-set-entry>
 </service-sfw-statistics-entry>

Description Stateful firewall service set statistics entry.

Contents <alg-error-counters>—Extensive output of ALG processing errors.

<alg-name>—Name of the ALG.

<drop_counters>—Drop counters (rules or resource exhaustion).

<error-counters>—Summarized protocol processing errors.

<existing-flow-counters>—Existing flow counters.

<icmp-error-counters>—Extensive output of ICMP processing errors.

<ip-error-counters>—Extensive output of IP processing errors.

<new-flow-counters>—New flow counters.

<service-set-name>—Name of the service set.

<sip-active-call-count>—Number of active SIP calls in the service set.

<sip-active-reg-count>—Number of active SIP registrations in the service set.

<sip-alg-counters>—SIP statistics.

<tcp-error-counters>—Extensive output of TCP processing errors.

<total-drops>—Total packets dropped by protocol processing.

<total-flow-accepts>—Total packets accepted by new and existing flows.

<total-flow-discards>—Total packets discarded by new and existing flows.

<total-flow-rejects>—Total packets rejected by new and existing flows.

<udp-error-counters>—Extensive output of UDP processing errors.

<sip-alg-counters>

Usage <sfw-stats-service-set-entry>
 <sip-alg-counters>
 <total-counters>...</total-counters>
 <parser-counters>...</parser-counters>
 <message-counters>...</message-counters>
 </sip-alg-counters>
 </sfw-stats-service-set-entry>

Description SIP statistics.

Contents <message-counters>—SIP message counters.

<parser-counters>—Parser statistics.

<total-counters>—Total statistics.

<tcp-error-counters>

Usage <sfw-stats-service-set-entry>
<tcp-error-counters>
 <tcp-header-length-error>*tcp-header-length-error*</tcp-header-length-error>
 <tcp-zero-port>*tcp-zero-port*</tcp-zero-port>
 <illegal-sequence-number-flags>*illegal-sequence-number-flags*
 </illegal-sequence-number-flags>
 <syn-attack>*syn-attack*</syn-attack>
 <non-syn-first-packet>*non-syn-first-packet*</non-syn-first-packet>
 <tcp-port-scan>*tcp-port-scan*</tcp-port-scan>
 <bad-syn-cookie-response>*bad-syn-cookie-response*</bad-syn-cookie-response>
 <tcp-recon-sequence-number-error>*tcp-recon-sequence-number-error*
 </tcp-recon-sequence-number-error>
 <tcp-recon-retransmits>*tcp-recon-retransmits*</tcp-recon-retransmits>
</tcp-error-counters>
 </sfw-stats-service-set-entry>

Description Extensive output of TCP processing errors.

Contents <bad-syn-cookie-response>—Bad SYN cookie response.
 <illegal-sequence-number-flags>—Illegal sequence number and flags combinations.
 <non-syn-first-packet>—First packet not a SYN message.
 <syn-attack>—SYN attack.
 <tcp-header-length-error>—TCP header length inconsistencies.
 <tcp-port-scan>—TCP port scan.
 <tcp-recon-retransmits>—TCP reconstructor retransmissions.
 <tcp-recon-sequence-number-error>—TCP reconstructor sequence number error.
 <tcp-zero-port>—Source or destination port number is zero.

<total-counters>

Usage <sip-alg-counters>
<total-counters>
 <total-messages>*total-messages*</total-messages>
 <call-segments>*call-segments*</call-segments>
</total-counters>
 </sip-alg-counters>

Description Total statistics.

Contents <call-segments>—SIP call segments.
 <total-messages>—Total SIP messages.

<udp-error-counters>

Usage <sfw-stats-service-set-entry>
 <udp-error-counters>
 <udp-header-length-error>*udp-header-length-error*</udp-header-length-error>
 <udp-zero-port>*udp-zero-port*</udp-zero-port>
 <udp-port-scan>*udp-port-scan*</udp-port-scan>
 </udp-error-counters>
 </sfw-stats-service-set-entry>

Description Extensive output of UDP processing errors.

Contents <udp-header-length-error>—IP data length is less than minimum UDP header length (8 bytes).

<udp-port-scan>—UDP port scan (ICMP error seen for UDP flow).

<udp-zero-port>—Source or destination port number is zero.

<uri-redirect-set-statistics>

Usage <uri-redirect-set-statistics-information>
 <uri-redirect-set-statistics>
 <uri-redirect-set-name>*uri-redirect-set-name*</uri-redirect-set-name>
 <cause-roaming>*cause-roaming*</cause-roaming>
 <cause-time-of-day>*cause-time-of-day*</cause-time-of-day>
 <cause-quality-of-service>*cause-quality-of-service*</cause-quality-of-service>
 <cause-volume-expired>*cause-volume-expired*</cause-volume-expired>
 <cause-cost-warning>*cause-cost-warning*</cause-cost-warning>
 <cause-not-allowed>*cause-not-allowed*</cause-not-allowed>
 <cause-unsubscribed>*cause-unsubscribed*</cause-unsubscribed>
 <cause-credit-expiry>*cause-credit-expiry*</cause-credit-expiry>
 <cause-unknown>*cause-unknown*</cause-unknown>
 <cause-default>*cause-default*</cause-default>
 </uri-redirect-set-statistics>
 </uri-redirect-set-statistics-information>

Description Statistics for the URI redirect sets.

Contents <cause-cost-warning>—Number of redirects due to cost warning limit.
 <cause-credit-expiry>—Number of redirects due to expiration of credit.
 <cause-default>—Number of redirects due to default reason match.
 <cause-not-allowed>—Number of redirects due to disallowed service class.
 <cause-quality-of-service>—Number of redirects due to QoS.
 <cause-roaming>—Number of redirects due to roaming.
 <cause-time-of-day>—Number of redirects due to time of day.
 <cause-unknown>—Number of redirects due to unknown reason.
 <cause-unsubscribed>—Number of redirects due to unsubscribed service class.
 <cause-volume-expired>—Number of redirects due to expiration of volume limit.
 <uri-redirect-set-name>—Name of header redirect set.

<uri-redirect-set-statistics-information>

Usage <rpc-reply>
 <uri-redirect-set-statistics-information>
 <interface-name>*interface-name*</interface-name>
 <interfaces>*interfaces*</interfaces>
 <uri-redirect-set-statistics>...</uri-redirect-set-statistics>
 </uri-redirect-set-statistics-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <interface-name>—Name of the adaptive services interface.
 <interfaces>—Total number of interfaces summarized.
 <uri-redirect-set-statistics>—Statistics for the URI redirect sets.

<virtual-interface-entry>

Usage <pgcpd-active-configuration | pgcpd-config>
 <virtual-interface-entry>
 <virtual-interface-name>*virtual-interface-name*</virtual-interface-name>
 <routing-instance>*routing-instance*</routing-instance>
 <interface-name>*interface-name*</interface-name>
 <vif-service-state>*vif-service-state*</vif-service-state>
 <media-service-ref-entry>...</media-service-ref-entry>
 </virtual-interface-entry>
 </pgcpd-active-configuration | pgcpd-config>

Description No documentation is available yet.

Contents <interface-name>—Name of the adaptive services interface.
 <media-service-ref-entry>—No documentation is available yet.
 <routing-instance>—No documentation is available yet.
 <vif-service-state>—No documentation is available yet.
 <virtual-interface-name>—No documentation is available yet.

Summary of Alarm Response Tags

This section lists JUNOS XML tags that contain operational information about alarms. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-alarm>. To review the DTD for the tags, see “DTD for Alarm Response Tags” on page 1647.

<alarm-detail>

- Usage** <alarm-information>
 <alarm-detail>
 <alarm-time>*alarm-time*</alarm-time>
 <alarm-class>*alarm-class*</alarm-class>
 <alarm-description>*alarm-description*</alarm-description>
 <alarm-short-description>*alarm-short-description*</alarm-short-description>
 <alarm-type>*alarm-type*</alarm-type>
 </alarm-detail>
 </alarm-information>
- Description** Detailed information about an active alarm.
- Contents** <alarm-class>—Class of the alarm.
- <alarm-description>—Description of the alarm.
- <alarm-short-description>—Short description of the alarm.
- <alarm-time>—Time of the alarm.
- <alarm-type>—Type (class) of the alarm.

<alarm-id-information>

- Usage** <rpc-reply>
 <alarm-id-information>
 <alarm-id>*alarm-id*</alarm-id>
 </alarm-id-information>
 </rpc-reply>
- Description** Alarm identification information.
- Contents** <alarm-id>—Alarm identification number.

<alarm-information>

- Usage** <multi-routing-engine-item>
 <alarm-information>
 <alarm-summary>...</alarm-summary>
 <alarm-detail>...</alarm-detail>
 </alarm-information>
 </multi-routing-engine-item>
- Description** Information about all active alarms.
- Contents** <alarm-detail>—Detailed information about an active alarm.
 <alarm-summary>—Number of alarms currently active.

<alarm-summary>

- Usage** <alarm-information>
 <alarm-summary>
 <active-alarm-count>active-alarm-count</active-alarm-count>
 <no-active-alarms/>
 </alarm-summary>
 </alarm-information>
- Description** Number of alarms currently active.
- Contents** <active-alarm-count>—Number of active alarms.
 <no-active-alarms>—No active alarms.

<multi-routing-engine-item>

- Usage** <multi-routing-engine-results>
 <multi-routing-engine-item>
 <re-name>re-name</re-name>
 <alarm-information>...</alarm-information>
 </multi-routing-engine-item>
 </multi-routing-engine-results>
- Description** Information about the active alarms on one Routing Engine on a platform with multiple Routing Engines.
- Contents** <alarm-information>—Information about all active alarms.
 <re-name>—Hostname of the Routing Engine.

<multi-routing-engine-results>

Usage <rpc-reply>
 <multi-routing-engine-results>
 <multi-routing-engine-item>...</multi-routing-engine-item>
 </multi-routing-engine-results>
 </rpc-reply>

Description Information about alarms on one or more Routing Engines on a platform with multiple Routing Engines.

Contents <multi-routing-engine-item>—Information about the active alarms on one Routing Engine on a platform with multiple Routing Engines.

Summary of APS Response Tags

This section lists JUNOS XML tags that contain operational information about Automatic Protection Switching (APS). The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-aps>. To review the DTD for the tags, see “DTD for APS Response Tags” on page 1649.

<aps-interface>

Usage <aps-interface-information>

```

<aps-interface>
  <aps-interface-name>aps-interface-name</aps-interface-name>
  <aps-interface-group>aps-interface-group</aps-interface-group>
  <aps-interface-circuit-type>aps-interface-circuit-type
    </aps-interface-circuit-type>
  <aps-interface-circuit-state>aps-interface-circuit-state
    </aps-interface-circuit-state>
  <aps-interface-state>aps-interface-state</aps-interface-state>
  <aps-neighbor>aps-neighbor</aps-neighbor>
  <aps-adjacent-state>aps-adjacent-state</aps-adjacent-state>
  <aps-neighbor-select-state>aps-neighbor-select-state
    </aps-neighbor-select-state>
  <aps-time-remaining>aps-time-remaining
    </aps-time-remaining>
  <aps-channel-state>aps-channel-state
    </aps-channel-state>
  <aps-config-state>aps-config-state</aps-config-state>
  <aps-config-state-circuit>aps-config-state-circuit
    </aps-config-state-circuit>
  <aps-loop-circuit-type>aps-loop-circuit-type
    </aps-loop-circuit-type>
  <aps-loop-circuit-name>aps-loop-circuit-name
    </aps-loop-circuit-name>
  <aps-pair-interface-name>aps-pair-interface-name
    </aps-pair-interface-name>
  <aps-pair-group-name>aps-pair-group-name
    </aps-pair-group-name>
  <aps-local-mode>aps-local-mode</aps-local-mode>
  <aps-neighbor-mode>aps-neighbor-mode</aps-neighbor-mode>
  <aps-request-k1>aps-request-k1</aps-request-k1>
  <aps-receive-k1>aps-receive-k1</aps-receive-k1>
  <aps-transmit-k1>aps-transmit-k1</aps-transmit-k1>
  <aps-neighbor-k1>aps-neighbor-k1</aps-neighbor-k1>
  <aps-neighbor-paired-request>aps-neighbor-paired-request
    </aps-neighbor-paired-request>
  <aps-revert-time>aps-revert-time</aps-revert-time>
  <aps-neighbor-revert-time>aps-neighbor-revert-time
    </aps-neighbor-revert-time>
  <aps-remaining-revert-time>aps-remaining-revert-time
    </aps-remaining-revert-time>
  <aps-remaining-forced-revert-time>aps-remaining-forced-revert-time
    </aps-remaining-forced-revert-time>
  <aps-remaining-hello-timer>aps-remaining-hello-timer
    </aps-remaining-hello-timer>

```

```

    <aps-remaining-update-timer>aps-remaining-update-timer
    </aps-remaining-update-timer>
    <aps-remaining-holddown-timer>aps-remaining-holddown-timer
    </aps-remaining-holddown-timer>
  </aps-interface>
</aps-interface-information>

```

Description Information about an Automatic Protection Switching interface.

Contents

- <aps-adjacent-state>—Adjacent state.
- <aps-channel-state>—State of the channel.
- <aps-config-state>—State of config.
- <aps-config-state-circuit>—State of circuit config.
- <aps-interface-circuit-state>—State of the circuit.
- <aps-interface-circuit-type>—Type of the circuit.
- <aps-interface-group>—Name of the interface group.
- <aps-interface-name>—Name of the interface.
- <aps-interface-state>—State of the interface.
- <aps-local-mode>—APS local mode.
- <aps-loop-circuit-name>—Loop circuit name.
- <aps-loop-circuit-type>—Loop circuit type.
- <aps-neighbor>—Neighbor address.
- <aps-neighbor-k1>—Neighbor K1 value.
- <aps-neighbor-mode>—APS neighbor mode.
- <aps-neighbor-paired-request>—Neighbor paired switch request.
- <aps-neighbor-revert-time>—Neighbor revert time.
- <aps-neighbor-select-state>—Neighbor interface state.
- <aps-pair-group-name>—Paired group name.
- <aps-pair-interface-name>—Paired interface name.
- <aps-receive-k1>—Receive K1 value.
- <aps-remaining-forced-revert-time>—Remaining forced revert time.
- <aps-remaining-hello-timer>—Remaining hello timer.
- <aps-remaining-holddown-timer>—Remaining holddown timer.

<aps-remaining-revert-time>—Remaining revert time.

<aps-remaining-update-timer>—Remaining update timer.

<aps-request-k1>—Request K1 value.

<aps-revert-time>—APS revert time.

<aps-time-remaining>—Remaining time.

<aps-transmit-k1>—Transmit K1 value.

<aps-interface-information>

Usage <rpc-reply>
 <aps-interface-information>
 <aps-interface>...</aps-interface>
 </aps-interface-information>
 </rpc-reply>

Description Information about one or more Automatic Protection Switching interfaces.

Contents <aps-interface>—Information about an Automatic Protection Switching interface.

Summary of ARP Response Tags

This section lists JUNOS XML tags that contain operational information about the Address Resolution Protocol (ARP). The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-arp>. To review the DTD for the tags, see “DTD for ARP Response Tags” on page 1651.

<arp-table-entry>

Usage <arp-table-information>
 <arp-table-entry>
 <mac-address>*mac-address*</mac-address>
 <ip-address>*ip-address*</ip-address>
 <hostname>*hostname*</hostname>
 <interface-name>*interface-name*</interface-name>
 <arp-table-entry-flags>...</arp-table-entry-flags>
 <time-to-expire>*time-to-expire*</time-to-expire>
 </arp-table-entry>
 </arp-table-information>

Description Information about an entry in the ARP table.

Contents <arp-table-entry-flags>—One or more status flags for the ARP entry.
 <hostname>—Resolved hostname of the ARP entry.
 <interface-name>—Name of the interface associated with the ARP entry.
 <ip-address>—IP address of the ARP entry.
 <mac-address>—Hardware MAC address associated with the ARP entry.
 <time-to-expire>—Seconds remaining until the entry expires.

<arp-table-entry-flags>

Usage <arp-table-entry>
 <arp-table-entry-flags>
 <none/>
 <permanent/>
 <published/>
 <dead/>
 <free/>
 </arp-table-entry-flags>
 </arp-table-entry>

Description One or more status flags for the ARP entry.

Contents <dead>—ARP entry is dead.
 <free>—ARP entry is free.
 <none>—ARP entry has no flags.
 <permanent>—ARP entry is permanent.
 <published>—ARP entry is published.

<arp-table-information>

Usage <rpc-reply>
 <arp-table-information>
 <arp-table-entry>...</arp-table-entry>
 <arp-entry-count>*arp-entry-count*</arp-entry-count>
 </arp-table-information>
 </rpc-reply>

Description Information about one or more entries in the ARP table.

Contents <arp-entry-count>—Total number of ARP table entries.
 <arp-table-entry>—Information about an entry in the ARP table.

<clear-arp-table-result>

Usage <clear-arp-table-results>
 <clear-arp-table-result>
 <ip-address>*ip-address*</ip-address>
 <clear-success/>
 </clear-arp-table-result>
 </clear-arp-table-results>

Description Results of a clear ARP command.

Contents <clear-success>—Clear ARP was successful.
 <ip-address>—IP address of the ARP entry.

<clear-arp-table-results>

Usage <rpc-reply>
 <clear-arp-table-results>
 <clear-arp-table-result>...</clear-arp-table-result>
 </clear-arp-table-results>
 </rpc-reply>

Description Clear ARP table entry results.

Contents <clear-arp-table-result>—Results of a clear ARP command.

Summary of Authentication Response Tags

This section lists JUNOS XML tags that contain operational information about authentication. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-auth>. To review the DTD for the tags, see “DTD for Authentication Response Tags” on page 1653.

<aaa-module-accounting-statistics>

Usage <aaa-module-statistics>
 <aaa-module-accounting-statistics>
 <requests>requests</requests>
 <accounting-response-failures>accounting-response-failures
 </accounting-response-failures>
 <accounting-response-success>accounting-response-success
 </accounting-response-success>
 <timeouts>timeouts</timeouts>
 </aaa-module-accounting-statistics>
 </aaa-module-statistics>

Description No documentation is available yet.

Contents <accounting-response-failures>—Number of accounting response failures.
 <accounting-response-success>—Number of successful accounting responses.
 <requests>—Number of requests received.
 <timeouts>—Number of requests timedout.

<aaa-module-authentication-statistics>

Usage <aaa-module-statistics>
 <aaa-module-authentication-statistics>
 <requests>requests</requests>
 <accepts>accepts</accepts>
 <rejects>rejects</rejects>
 <challenges>challenges</challenges>
 <timeouts>timeouts</timeouts>
 </aaa-module-authentication-statistics>
 </aaa-module-statistics>

Description No documentation is available yet.

Contents <accepts>—Number of authentication accepts.
 <challenges>—Number of authentication challenges.
 <rejects>—Number of authentication rejects.
 <requests>—Number of requests received.
 <timeouts>—Number of requests timedout.

<aaa-module-dynamic-requests-statistics>

Usage <aaa-module-statistics>
 <aaa-module-dynamic-requests-statistics>
 <requests>*requests*</requests>
 <processed-ok>*processed-ok*</processed-ok>
 <processing-error>*processing-error*</processing-error>
 <silent-drops>*silent-drops*</silent-drops>
 </aaa-module-dynamic-requests-statistics>
 </aaa-module-statistics>

Description No documentation is available yet.

Contents <processed-ok>—Number of requests successfully processed.
 <processing-error>—Number of requests unsuccessfully processed.
 <requests>—Number of requests received.
 <silent-drops>—Number of requests silently dropped.

<aaa-module-statistics>

Usage <rpc-reply>
<aaa-module-statistics>
 <requests>*requests*</requests>
 <accepts>*accepts*</accepts>
 <rejects>*rejects*</rejects>
 <accounting-response-failures>*accounting-response-failures*
 </accounting-response-failures>
 <accounting-response-success>*accounting-response-success*
 </accounting-response-success>
 <timeouts>*timeouts*</timeouts>
 <challenges>*challenges*</challenges>
 <processed-ok>*processed-ok*</processed-ok>
 <processing-error>*processing-error*</processing-error>
 <silent-drops>*silent-drops*</silent-drops>
 <aaa-module-authentication-statistics>...
 </aaa-module-authentication-statistics>
 <aaa-module-accounting-statistics>...
 </aaa-module-accounting-statistics>
 <aaa-module-dynamic-requests-statistics>...
 </aaa-module-dynamic-requests-statistics>
</aaa-module-statistics>
 </rpc-reply>

Description Statistics for the authentication authorization and accounting (AAA) modules.

Contents <aaa-module-accounting-statistics>—No documentation is available yet.
 <aaa-module-authentication-statistics>—No documentation is available yet.
 <aaa-module-dynamic-requests-statistics>—No documentation is available yet.
 <accepts>—Number of authentication accepts.
 <accounting-response-failures>—Number of accounting response failures.
 <accounting-response-success>—Number of successful accounting responses.
 <challenges>—Number of authentication challenges.
 <processed-ok>—Number of requests successfully processed.
 <processing-error>—Number of requests unsuccessfully processed.
 <rejects>—Number of authentication rejects.
 <requests>—Number of requests received.
 <silent-drops>—Number of requests silently dropped.
 <timeouts>—Number of requests timedout.

<aaa-subscriber-accounting-statistics>

Usage <aaa-subscriber-statistics>
<aaa-subscriber-accounting-statistics>
 <accounting-start-sent-successfully>accounting-start-sent-successfully
 </accounting-start-sent-successfully>
 <accounting-start-send-failed>accounting-start-send-failed
 </accounting-start-send-failed>
 <accounting-start-responses>accounting-start-responses
 </accounting-start-responses>
 <accounting-interim-sent-successfully>accounting-interim-sent-successfully
 </accounting-interim-sent-successfully>
 <accounting-interim-send-failed>accounting-interim-send-failed
 </accounting-interim-send-failed>
 <accounting-interim-responses>acc-int-res</acctng-interim-responses>
 <accounting-stop-on-failure-sent-successfully>acc-stp-on-failr-sent-successfly
 </accounting-stop-on-failure-sent-successfully>
 <accounting-stop-on-failure-send-failed>acctng-stop-on-failure-send-failed
 </accounting-stop-on-failure-send-failed>
 <accounting-stop-on-failure-responses>accounting-stop-on-failure-responses
 </accounting-stop-on-failure-responses>
 <accounting-stop-sent-successfully>accounting-stop-sent-successfully
 </accounting-stop-sent-successfully>
 <accounting-stop-send-failed>accounting-stop-send-failed
 </accounting-stop-send-failed>
 <accounting-stop-responses>accounting-stop-responses
 </accounting-stop-responses>
</aaa-subscriber-accounting-statistics>
 </aaa-subscriber-statistics>

Description No documentation is available yet.

Contents <accounting-interim-responses>—Number of INTERIM ack received.
 <accounting-interim-send-failed>—Number of INTERIM send failures.
 <accounting-interim-sent-successfully>—Number of INTERIM messages sent successfully.
 <accounting-start-responses>—Number of START ack received.
 <accounting-start-send-failed>—Number of START send failures.
 <accounting-start-sent-successfully>—Number of START messages sent successfully.
 <accounting-stop-on-failure-responses>—Number of STOP-on-failure ack received.
 <accounting-stop-on-failure-send-failed>—Number of STOP-on-failure send failures.
 <accounting-stop-on-failure-sent-successfully>—Number of STOP-on-failure messages sent successfully.

<accounting-stop-responses>—Number of STOP ack received.

<accounting-stop-send-failed>—Number of STOP send failures.

<accounting-stop-sent-successfully>—Number of STOP messages sent successfully.

<aaa-subscriber-auth-statistics>

Usage <aaa-subscriber-statistics>
 <aaa-subscriber-auth-statistics>
 <authentication-challenge-requests>*authentication-challenge-requests*
 </authentication-challenge-requests>
 <authentication-challenge-responses>*authentication-challenge-responses*
 </authentication-challenge-responses>
 </aaa-subscriber-auth-statistics>
 </aaa-subscriber-statistics>

Description No documentation is available yet.

Contents <authentication-challenge-requests>—Number of authentication challenge requests.
 <authentication-challenge-responses>—Number of authentication challenge responses.

<aaa-subscriber-service-statistics>

Usage <aaa-subscriber-statistics>
 <aaa-subscriber-service-statistics>
 <service-creates>*service-creates*</service-creates>
 <service-deletes>*service-deletes*</service-deletes>
 <service-timeouts>*service-timeouts*</service-timeouts>
 </aaa-subscriber-service-statistics>
 </aaa-subscriber-statistics>

Description No documentation is available yet.

Contents <service-creates>—Number of services creations received.
 <service-deletes>—Number of service deletions received .
 <service-timeouts>—Number of service timeouts.

<aaa-subscriber-statistics>

Usage <aaa-subscriber-table-details>
<aaa-subscriber-statistics>
 <authentication-challenge-requests>*au-ch-re*</authentication-challenge-requests>
 <authentication-challenge-responses>*authentication-challenge-responses*
 </authentication-challenge-responses>
 <accounting-start-sent-successfully>*a-s-s-s*
 </accounting-start-sent-successfully>
 <accounting-start-send-failed>*ac-st-se-fa*
 </accounting-start-send-failed>
 <accounting-start-responses>*ac-st-resp*
 </accounting-start-responses>
 <accounting-interim-sent-successfully>*accounting-interim-sent-successfully*
 </accounting-interim-sent-successfully>
 <accounting-interim-send-failed>*ac-int-sn-fail*
 </accounting-interim-send-failed>
 <accounting-interim-responses>*ac-int-res*
 </accounting-interim-responses>
 <accounting-stop-on-failure-sent-successfully>*a-s-o-f-s-s*
 </accounting-stop-on-failure-sent-successfully>
 <accounting-stop-on-failure-send-failed>*accounting-stop-on-failure-send-failed*
 </accounting-stop-on-failure-send-failed>
 <accounting-stop-on-failure-responses>*accounting-stop-on-failure-responses*
 </accounting-stop-on-failure-responses>
 <accounting-stop-sent-successfully>*accounting-stop-sent-successfully*
 </accounting-stop-sent-successfully>
 <accounting-stop-send-failed>*accounting-stop-send-failed*
 </accounting-stop-send-failed>
 <accounting-stop-responses>*accounting-stop-responses*
 </accounting-stop-responses>
 <service-creates>*service-creates*</service-creates>
 <service-deletes>*service-deletes*</service-deletes>
 <service-timeouts>*service-timeouts*</service-timeouts>
 <aaa-subscriber-auth-statistics>...</aaa-subscriber-auth-statistics>
 <aaa-subscriber-accounting-statistics>...
 </aaa-subscriber-accounting-statistics>
 <aaa-subscriber-service-statistics>...</aaa-subscriber-service-statistics>
</aaa-subscriber-statistics>
 </aaa-subscriber-table-details>

Description No documentation is available yet.

Contents <aaa-subscriber-accounting-statistics>—No documentation is available yet.

<aaa-subscriber-auth-statistics>—No documentation is available yet.

<aaa-subscriber-service-statistics>—No documentation is available yet.

<accounting-interim-responses>—Number of INTERIM ack received.

<accounting-interim-send-failed>—Number of INTERIM send failures.

<accounting-interim-sent-successfully>—Number of INTERIM messages sent successfully.

<accounting-start-responses>—Number of START ack received.

<accounting-start-send-failed>—Number of START send failures.

<accounting-start-sent-successfully>—Number of START messages sent successfully.

<accounting-stop-on-failure-responses>—Number of STOP-on-failure ack received.

<accounting-stop-on-failure-send-failed>—Number of STOP-on-failure send failures.

<accounting-stop-on-failure-sent-successfully>—Number of STOP-on-failure messages sent successfully.

<accounting-stop-responses>—Number of STOP ack received.

<accounting-stop-send-failed>—Number of STOP send failures.

<accounting-stop-sent-successfully>—Number of STOP messages sent successfully.

<authentication-challenge-requests>—Number of authentication challenge requests.

<authentication-challenge-responses>—Number of authentication challenge responses.

<service-creates>—Number of services creations received.

<service-deletes>—Number of service deletions received .

<service-timeouts>—Number of service timeouts.

<aaa-subscriber-table>

Usage <aaa-subscriber-table-details>
 <aaa-subscriber-table>
 <aaa-subscriber-table-entry>...</aaa-subscriber-table-entry>
 <aaa-subscriber-table-entry-details>...</aaa-subscriber-table-entry-details>
 <aaa-subscriber-table-logical-system-routing-instance-entries>...
 </aaa-subscriber-table-logical-system-routing-instance-entries>
 <aaa-subscriber-table-entry-service-details>...
 </aaa-subscriber-table-entry-service-details>
 </aaa-subscriber-table>
 </aaa-subscriber-table-details>

Description No documentation is available yet.

Contents <aaa-subscriber-table-entry>—No documentation is available yet.

<aaa-subscriber-table-entry-details>—No documentation is available yet.

<aaa-subscriber-table-entry-service-details>—No documentation is available yet.

<aaa-subscriber-table-logical-system-routing-instance-entries>—No documentation is available yet.

<aaa-subscriber-table-details>

- Usage** <rpc-reply>
 <aaa-subscriber-table-details>
 <aaa-subscriber-table>...</aaa-subscriber-table>
 <aaa-subscriber-statistics>...</aaa-subscriber-statistics>
 </aaa-subscriber-table-details>
 </rpc-reply>
- Description** Information about authentication, authorization and accounting (AAA) subscriber table.
- Contents** <aaa-subscriber-statistics>—No documentation is available yet.
 <aaa-subscriber-table>—No documentation is available yet.

<aaa-subscriber-table-entry>

- Usage** <aaa-subscriber-table>
 <aaa-subscriber-table-entry>
 <user-name>*user-name*</user-name>
 <logical-system-routing-instance>*logical-system-routing-instance*
 </logical-system-routing-instance>
 <client-type>*client-type*</client-type>
 </aaa-subscriber-table-entry>
 </aaa-subscriber-table>
- Description** No documentation is available yet.
- Contents** <client-type>—Subscriber type.
 <logical-system-routing-instance>—Logical system/Routing instance this subscriber session is part of.
 <user-name>—Username for the user being authenticated.

<aaa-subscriber-table-entry-details>

Usage <aaa-subscriber-table>
 <aaa-subscriber-table-entry-details>
 <logical-system-routing-instance>*logical-system-routing-instance*
 </logical-system-routing-instance>
 <client-type>*client-type*</client-type>
 <session-uptime>*session-uptime*</session-uptime>
 <accounting-status>*accounting-status*</accounting-status>
 </aaa-subscriber-table-entry-details>
 </aaa-subscriber-table>

Description No documentation is available yet.

Contents <accounting-status>—Subscriber session's accounting configuration details.

<client-type>—Subscriber type.

<logical-system-routing-instance>—Logical system/Routing instance this subscriber session is part of.

<session-uptime>—Duration since this subscriber session has been authenticated and active.

<aaa-subscriber-table-entry-service-details>

Usage <aaa-subscriber-table>
 <aaa-subscriber-table-entry-service-details>
 <service-name>*service-name*</service-name>
 <service-type>*service-type*</service-type>
 <service-quota>*service-quota*</service-quota>
 <accounting-status>*accounting-status*</accounting-status>
 </aaa-subscriber-table-entry-service-details>
 </aaa-subscriber-table>

Description No documentation is available yet.

Contents <accounting-status>—Subscriber session's accounting configuration details.

<service-name>—Service associated with the subscriber's session.

<service-quota>—Quota for this service type.

<service-type>—Service type (volume/time based) associated with the subscriber's session.

<aaa-subscriber-table-logical-system-routing-instance-entries>

- Usage** <aaa-subscriber-table>
 <aaa-subscriber-table-logical-system-routing-instance-entries>
 <user-name>*user-name*</user-name>
 <client-type>*client-type*</client-type>
 <logical-system-routing-instance>*logical-system-routing-instance*
 </logical-system-routing-instance>
 </aaa-subscriber-table-logical-system-routing-instance-entries>
 </aaa-subscriber-table>
- Description** No documentation is available yet.
- Contents** <client-type>—Subscriber type.
- <logical-system-routing-instance>—Logical system/Routing instance this subscriber session is part of.
- <user-name>—Username for the user being authenticated.

<address-assignment-pool-entry>

- Usage** <address-assignment-pool-table>
 <address-assignment-pool-entry>
 <ip-address>*ip-address*</ip-address>
 <hardware-address>*hardware-address*</hardware-address>
 <subscriber-type>*subscriber-type*</subscriber-type>
 </address-assignment-pool-entry>
 </address-assignment-pool-table>
- Description** No documentation is available yet.
- Contents** <hardware-address>—Hardware address of the client.
- <ip-address>—IPv4 address assigned to the client.
- <subscriber-type>—Subscriber type.

<address-assignment-pool-table>

- Usage** <address-assignment-pool-table-details>
 <address-assignment-pool-table>
 <address-assignment-pool-entry>...</address-assignment-pool-entry>
 </address-assignment-pool-table>
 </address-assignment-pool-table-details>
- Description** No documentation is available yet.
- Contents** <address-assignment-pool-entry>—No documentation is available yet.

<address-assignment-pool-table-details>

Usage <rpc-reply>
 <address-assignment-pool-table-details>
 <address-assignment-pool-table>...</address-assignment-pool-table>
 </address-assignment-pool-table-details>
 </rpc-reply>

Description Information about address-assignment pool.

Contents <address-assignment-pool-table>—No documentation is available yet.

<auth-pending-entry>

Usage <auth-pending-table>
 <auth-pending-entry>
 <index>*index*</index>
 <auth-status>*auth-status*</auth-status>
 <profile-name>*profile-name*</profile-name>
 <user-name>*user-name*</user-name>
 </auth-pending-entry>
 </auth-pending-table>

Description No documentation is available yet.

Contents <auth-status>—Current authentication status for the request entry.
 <index>—Index of the authentication request entry.
 <profile-name>—Profile-name using which the user is being authenticated.
 <user-name>—Username for the user being authenticated.

<auth-pending-table>

Usage <auth-pending-table-details>
 <auth-pending-table>
 <auth-pending-entry>...</auth-pending-entry>
 </auth-pending-table>
 </auth-pending-table-details>

Description No documentation is available yet.

Contents <auth-pending-entry>—No documentation is available yet.

<auth-pending-table-details>

- Usage** <rpc-reply>
 <auth-pending-table-details>
 <auth-pending-table-info>...</auth-pending-table-info>
 <auth-pending-table>...</auth-pending-table>
 </auth-pending-table-details>
 </rpc-reply>
- Description** Information about pending authentication requests.
- Contents** <auth-pending-table>—No documentation is available yet.
 <auth-pending-table-info>—No documentation is available yet.

<auth-pending-table-info>

- Usage** <auth-pending-table-details>
 <auth-pending-table-info>
 <auth-pending-total-entries>*auth-pending-total-entries*
 </auth-pending-total-entries>
 </auth-pending-table-info>
 </auth-pending-table-details>
- Description** No documentation is available yet.
- Contents** <auth-pending-total-entries>—No documentation is available yet.

<auth-statistics>

- Usage** <rpc-reply>
 <auth-statistics>
 <total-statistics>...</total-statistics>
 <radius-auth-statistics>...</radius-auth-statistics>
 <ldap-auth-statistics>...</ldap-auth-statistics>
 <securig-auth-statistics>...</securig-auth-statistics>
 <local-auth-statistics>...</local-auth-statistics>
 </auth-statistics>
 </rpc-reply>
- Description** Authentication statistics.
- Contents** <ldap-auth-statistics>—No documentation is available yet.
 <local-auth-statistics>—No documentation is available yet.
 <radius-auth-statistics>—No documentation is available yet.
 <securig-auth-statistics>—No documentation is available yet.
 <total-statistics>—No documentation is available yet.

<ldap-auth-statistics>

Usage <auth-statistics>
 <ldap-auth-statistics>
 <total-requests>*total-requests*</total-requests>
 <success-responses>*success-responses*</success-responses>
 <failure-responses>*failure-responses*</failure-responses>
 </ldap-auth-statistics>
 </auth-statistics>

Description No documentation is available yet.

Contents <failure-responses>—Number of failed authentication requests.
 <success-responses>—Number of succeeded authentication requests.
 <total-requests>—Number of authentication requests received.

<local-auth-statistics>

Usage <auth-statistics>
 <local-auth-statistics>
 <total-requests>*total-requests*</total-requests>
 <success-responses>*success-responses*</success-responses>
 <failure-responses>*failure-responses*</failure-responses>
 </local-auth-statistics>
 </auth-statistics>

Description No documentation is available yet.

Contents <failure-responses>—Number of failed authentication requests.
 <success-responses>—Number of succeeded authentication requests.
 <total-requests>—Number of authentication requests received.

<node-secret-file-table>

Usage <rpc-reply>
 <node-secret-file-table>
 <node-secret-file-table-entry>...</node-secret-file-table-entry>
 </node-secret-file-table>
 </rpc-reply>

Description Information about SecurID authentication node secret files.

Contents <node-secret-file-table-entry>—No documentation is available yet.

<node-secret-file-table-entry>

- Usage** <node-secret-file-table>
 <node-secret-file-table-entry>
 <server-name>*server-name*</server-name>
 <node-secret-file>*node-secret-file*</node-secret-file>
 </node-secret-file-table-entry>
 </node-secret-file-table>
- Description** No documentation is available yet.
- Contents** <node-secret-file>—Path of the node secret file.
 <server-name>—Name of the SecurID server associated with this node secret file.

<radius-auth-statistics>

- Usage** <auth-statistics>
 <radius-auth-statistics>
 <total-requests>*total-requests*</total-requests>
 <success-responses>*success-responses*</success-responses>
 <failure-responses>*failure-responses*</failure-responses>
 </radius-auth-statistics>
 </auth-statistics>
- Description** No documentation is available yet.
- Contents** <failure-responses>—Number of failed authentication requests.
 <success-responses>—Number of succeeded authentication requests.
 <total-requests>—Number of authentication requests received.

<securid-auth-statistics>

- Usage** <auth-statistics>
 <securid-auth-statistics>
 <total-requests>*total-requests*</total-requests>
 <success-responses>*success-responses*</success-responses>
 <failure-responses>*failure-responses*</failure-responses>
 </securid-auth-statistics>
 </auth-statistics>
- Description** No documentation is available yet.
- Contents** <failure-responses>—Number of failed authentication requests.
 <success-responses>—Number of succeeded authentication requests.
 <total-requests>—Number of authentication requests received.

<total-statistics>

Usage <auth-statistics>
 <total-statistics>
 <total-requests>*total-requests*</total-requests>
 <total-responses>*total-responses*</total-responses>
 </total-statistics>
 </auth-statistics>

Description No documentation is available yet.

Contents <total-requests>—Number of authentication requests received.
 <total-responses>—Number of authentication requests replied to.

Summary of Autoinstallation Response Tags

This section lists JUNOS XML tags that contain operational information about autoinstallation on J-series platforms. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-autoinstallation>. To review the DTD for the tags, see “DTD for Autoinstallation Response Tags” on page 1657.

<autoinstallation-status-information>

Usage	<pre><rpc-reply> <autoinstallation-status-information> <master-state>master-state</master-state> <last-configuration-filename>last-configuration-filename </last-configuration-filename> <last-configuration-server>last-configuration-server </last-configuration-server> <autoinstallation-status-interface-information>... </autoinstallation-status-interface-information> </autoinstallation-status-information> </rpc-reply></pre>
Description	Autoinstallation status.
Contents	<p><autoinstallation-status-interface-information>—Autoinstallation status for a particular interface.</p> <p><last-configuration-filename>—Name of last configuration file committed.</p> <p><last-configuration-server>—IP address of last configuration server.</p> <p><master-state>—State of master state machine.</p>

<autoinstallation-status-interface-address-information>

Usage	<pre><autoinstallation-status-interface-information> <autoinstallation-status-interface-address-information> <protocol-name>protocol-name</protocol-name> <protocol-address>protocol-address</protocol-address> </autoinstallation-status-interface-address-information> </autoinstallation-status-interface-information></pre>
Description	Autoinstallation status for address acquisition protocols on a particular interface.
Contents	<p><protocol-address>—Address acquired on this interface using this address acquisition protocol.</p> <p><protocol-name>—Address acquisition protocol on this interface.</p>

<autoinstallation-status-interface-information>

Usage <autoinstallation-status-information>
<autoinstallation-status-interface-information>
 <interface-name>*int-name*</interface-name>
 <interface-state>*int-state*</interface-state>
 <interface-acquired-address>*int-acq-add*
 </interface-acquired-address>
 <interface-acquired-hostname>*int-acq-hostn*
 </interface-acquired-hostname>
 <interface-acquired-hostname-source>*i-a-h-s*
 </interface-acquired-hostname-source>
 <interface-acquired-configuration-filename>*int-ac-config-filenm*
 </interface-acquired-configuration-filename>
 <interface-acquired-configuration-server>*interface-acquired-configuration-server*
 </interface-acquired-configuration-server>
 <autoinstallation-status-interface-address-information>...
 </autoinstallation-status-interface-address-information>
</autoinstallation-status-interface-information>
 </autoinstallation-status-information>

Description Autoinstallation status for a particular interface.

Contents <autoinstallation-status-interface-address-information>—Autoinstallation status for address acquisition protocols on a particular interface.

<interface-acquired-address>—IP address acquired on this interface.

<interface-acquired-configuration-filename>—Name of configuration file acquired on this interface.

<interface-acquired-configuration-server>—IP address of configuration server acquired on this interface.

<interface-acquired-hostname>—Hostname acquired on this interface.

<interface-acquired-hostname-source>—Source of hostname acquired on this interface.

<interface-name>—Interface name.

<interface-state>—State of interface state machine.

Summary of BFD Response Tags

This section lists the JUNOS XML tags that contain operational information about the Bidirectional Forwarding Detection (BFD) Protocol. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-bfd>. To review the DTD for the tags, see “DTD for BFD Response Tags” on page 1659.

<bfd-client>

Usage <bfd-session>
 <bfd-client>
 <client-name>*client-name*</client-name>
 <client-transmission-interval>*client-transmission-interval*
 </client-transmission-interval>
 <client-reception-interval>*client-reception-interval*
 </client-reception-interval>
 <client-multiplier>*client-multiplier*</client-multiplier>
 <client-holddown-interval>*client-holddown-interval*</client-holddown-interval>
 <client-state>*client-state*</client-state>
 </bfd-client>
 </bfd-session>

Description Information about the clients.

Contents <client-holddown-interval>—Hold interval for which BFD does not send a session UP notification to the client (seconds).

<client-multiplier>—Multiplier that the client has requested to determine the liveness of the BFD session.

<client-name>—Protocol for which the BFD session is active (for example: OSPF, ISIS, Static, and so on) .

<client-reception-interval>—Base frequency that the client has proposed for peer to send BFD control packets (seconds).

<client-state>—Tells whether client is in holddown or not.

<client-transmission-interval>—Base frequency that the client proposes for sending BFD control packets (seconds).

<bfd-replication>

Usage <rpc-reply>
 <bfd-replication>
 <bfd-replication-session-entry>...</bfd-replication-session-entry>
 </bfd-replication>
 </rpc-reply>

Description Information about bidirectional forwarding detection replication state.

Contents <bfd-replication-session-entry>—No documentation is available yet.

<bfd-replication-session-entry>

Usage <bfd-replication>
 <bfd-replication-session-entry>
 <session-neighbor>*session-neighbor*</session-neighbor>
 <session-interface>*session-interface*</session-interface>
 <local-discriminator>*local-discriminator*</local-discriminator>
 <replication-state>*replication-state*</replication-state>
 </bfd-replication-session-entry>
 </bfd-replication>

Description No documentation is available yet.

Contents <local-discriminator>—Authentication code used by the local system to identify the BFD session.

<replication-state>—Replication state.

<session-interface>—Name of the interface on which the BFD session is active.

<session-neighbor>—IP address of the neighbor for the BFD session.

<bfd-session>**Usage** <bfd-session-information>**<bfd-session>**

```

<session-state>session-state</session-state>
<session-interface>session-interface</session-interface>
<session-neighbor>session-neighbor</session-neighbor>
<session-detection-time>session-detection-time</session-detection-time>
<session-transmission-interval>session-transmission-interval
    </session-transmission-interval>
<session-adaptive-multiplier>session-adaptive-multiplier
    </session-adaptive-multiplier>
<bfd-client>...</bfd-client>
<session-up-time>session-up-time</session-up-time>
<previous-up-time>previous-up-time</previous-up-time>
<session-down-time>session-down-time</session-down-time>
<previous-down-time>previous-down-time</previous-down-time>
<local-diagnostic>local-diagnostic</local-diagnostic>
<remote-diagnostic>remote-diagnostic</remote-diagnostic>
<remote-state>remote-state</remote-state>
<v0-remote-state>v0-remote-state</v0-remote-state>
<remote-listen>remote-listen</remote-listen>
<session-version>session-version</session-version>
<logical-system-id>logical-system-id</logical-system-id>
<route-table-index>route-table-index</route-table-index>
<minimum-asynchronous-interval>m-a-i
    </minimum-asynchronous-interval>
<minimum-slow-interval>mini-sl-int
    </minimum-slow-interval>
<adaptive-asynchronous-transmission-interval>adaptive-asyn-trans-int
    </adaptive-asynchronous-transmission-interval>
<adaptive-reception-interval>adaptive-reception-interval
    </adaptive-reception-interval>
<minimum-transmission-interval>minimum-transmission-interval
    </minimum-transmission-interval>
<threshold-transmission-interval>threshold-transmission-interval
    </threshold-transmission-interval>
<minimum-reception-interval>minimum-reception-interval
    </minimum-reception-interval>
<detection-multiplier>detection-multiplier</detection-multiplier>
<threshold-detection-time>threshold-detection-time</threshold-detection-time>
<neighbor-minimum-transmission-interval>neighbor-minimum-transmission-interval
    </neighbor-minimum-transmission-interval>
<neighbor-minimum-reception-interval>neighbor-minimum-reception-interval
    </neighbor-minimum-reception-interval>
<neighbor-session-multiplier>neighbor-session-multiplier
    </neighbor-session-multiplier>
<issu-state>issu-state</issu-state>
<original-transmission-interval>original-transmission-interval
    </original-transmission-interval>
<original-reception-interval>original-reception-interval
    </original-reception-interval>
<local-discriminator>local-discriminator</local-discriminator>
<remote-discriminator>remote-discriminator</remote-discriminator>

```

```

<echo-mode-desired>echo-mode-desired</echo-mode-desired>
<echo-mode-state>echo-mode-state</echo-mode-state>
<no-absorb>no-absorb</no-absorb>
<no-refresh>no-refresh</no-refresh>
<update-adjacency>update-adjacency</update-adjacency>
<update-transmit>update-transmit</update-transmit>
<neighbor-fate>neighbor-fate</neighbor-fate>
<replicated>replicated</replicated>
<holddown-timer>holddown-timer</holddown-timer>
<adaptation-disabled>adaptation-disabled</adaptation-disabled>
<tunnel-name>tunnel-name</tunnel-name>
<tunnel-path>tunnel-path</tunnel-path>
<tunnel-prefix>tunnel-prefix</tunnel-prefix>
<tunnel-prefix-length>tunnel-prefix-length</tunnel-prefix-length>
<tunnel-type>tunnel-type</tunnel-type>
<tunnel-destination>tunnel-destination</tunnel-destination>
<multihop-time-to-live>multihop-time-to-live</multihop-time-to-live>
<multihop-routing-table-index>multihop-routing-table-index
</multihop-routing-table-index>
<multihop-local-address>multihop-local-address</multihop-local-address>
</bfd-session>
</bfd-session-information>

```

Description Information about bidirectional forwarding detection session.

Contents

- <adaptation-disabled>—Indicates whether adaptation has been disabled.
- <adaptive-asynchronous-transmission-interval>—Minimum asynchronous interval used when there is route flapping.
- <adaptive-reception-interval>—Adjusted value of minimum reception interval.
- <bfd-client>—Information about the clients.
- <detection-multiplier>—Desired detect time multiplier for BFD control packets. It is multiplied by the negotiated control packet reception interval to determine the session detection time (time to detect whether the session is alive).
- <echo-mode-desired>—Indicates whether the local system proposes that echo transmissions be enabled for the BFD session.
- <echo-mode-state>—Indicates whether echo transmissions are enabled for the BFD session.
- <holddown-timer>—Status of version negotiation.
- <issu-state>—ISSU state of the session.
- <local-diagnostic>—Information provided by the local host about BFD session that have failed (for example if the node is administratively down or a control timer has expired).
- <local-discriminator>—Authentication code used by the local system to identify the BFD session.

- <logical-system-id>—Logical system on which the session is established.
- <minimum-asynchronous-interval>—Minimum amount of time that the local system proposes for the delay between transmission of asynchronous control packets across the BFD session (seconds).
- <minimum-reception-interval>—Minimum amount of time that the local system waits between checks for newly received control packets (seconds).
- <minimum-slow-interval>—Either one second or the minimum asynchronous interval, whichever is greater.
- <minimum-transmission-interval>—Minimum amount of time that the local system proposes for the delay between transmission of control packets across the BFD session (seconds). It is either the minimum slow interval or the adaptive asynchronous transmission interval.
- <multihop-local-address>—Multihop local address.
- <multihop-routing-table-index>—Multihop session index in the routing table.
- <multihop-time-to-live>—Time-to-live for multihop session.
- <neighbor-fate>—Indicates whether the remote system is control-plane independent.
- <neighbor-minimum-reception-interval>—Minimum amount of time that the remote system waits between checks for newly received control packets (seconds).
- <neighbor-minimum-transmission-interval>—Minimum amount of time that the remote system proposes for the delay between transmission of control packets across the BFD session (seconds).
- <neighbor-session-multiplier>—Neighbor's detection multiplier.
- <no-absorb>—Incoming packets are not absorbed.
- <no-refresh>—The adjacency is not refreshed.
- <original-reception-interval>—Original pre-ISSU reception interval.
- <original-transmission-interval>—Original pre-ISSU transmission interval.
- <previous-down-time>—Amount of time the previous session was down (hours:minutes:seconds).
- <previous-up-time>—Duration of the previous session (hours:minutes:seconds).
- <remote-diagnostic>—Information provided by the remote host about BFD sessions that have failed (for example if the node is administratively down or a control timer has expired).
- <remote-discriminator>—Authentication code used by the remote system to identify the BFD session.

- `<remote-listen>`—(BFD version 0 only.) Indicates whether the remote system is receiving control packets transmitted by the local system.
- `<remote-state>`—(BFD version 1 only.) Indicates the remote session state.
- `<replicated>`—Indicates whether the session is replicated between master and standby RE.
- `<route-table-index>`—Routing table index for the current logical system.
- `<session-adaptive-multiplier>`—The adjusted value of detect multiplier.
- `<session-detection-time>`—Time period within which the host must receive BFD control packets to continue considering the session active (seconds).
- `<session-down-time>`—Time for which the current session was down (hours:minutes:seconds).
- `<session-interface>`—Name of the interface on which the BFD session is active.
- `<session-neighbor>`—IP address of the neighbor for the BFD session.
- `<session-state>`—BFD session state.
- `<session-transmission-interval>`—Frequency at which the host system sends BFD control packets (seconds).
- `<session-up-time>`—Time since the current session began (hours:minutes:seconds).
- `<session-version>`—Version of the BFD protocol being used for the session.
- `<threshold-detection-time>`—The maximum duration (in seconds) for the detection time before an SNMP trap is generated.
- `<threshold-transmission-interval>`—The maximum duration (in seconds) for the transmission interval before an SNMP trap is generated.
- `<tunnel-destination>`—Destination for the Label Distribution Protocol tunnel.
- `<tunnel-name>`—Name of the BFD tunnel.
- `<tunnel-path>`—Path of the BFD tunnel.
- `<tunnel-prefix>`—Prefix for the Label Distribution Protocol tunnel.
- `<tunnel-prefix-length>`—Length of prefix for the Label Distribution Protocol tunnel.
- `<tunnel-type>`—Type of tunnel.
- `<update-adjacency>`—Indicates whether the adjacency needs to be updated.
- `<update-transmit>`—Indicates whether a transmission needs to be updated.
- `<v0-remote-state>`—(BFD version 0 only.) Indicates whether the local system is receiving BFD control packets from the remote system.

<bfd-session-information>

Usage <rpc-reply>
 <bfd-session-information>
 <bfd-session>...</bfd-session>
 <sessions>sessions</sessions>
 <clients>clients</clients>
 <cumulative-transmission-rate>cumulative-transmission-rate
 </cumulative-transmission-rate>
 <cumulative-reception-rate>cumulative-reception-rate
 </cumulative-reception-rate>
 <error-value>error-value</error-value>
 </bfd-session-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <bfd-session>—Information about bidirectional forwarding detection session.

<clients>—Total number of clients that are hosting BFD sessions.

<cumulative-reception-rate>—Number of BFD control packets received per second in all active sessions.

<cumulative-transmission-rate>—Number of BFD control packets transmitted per second in all active sessions.

<error-value>—Error code that is returned when a 'clear' operation (such as the 'clear bfd session' command) fails.

<sessions>—Total number of active BFD sessions.

Summary of Connectivity Fault Management Response Tags

This section lists the JUNOS XML tags that contain operational information about connectivity fault management process. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-cfm>. To review the DTD for the tags, see “DTD for Connectivity Fault Management Response Tags” on page 1663.

<cfm-counters-route-socket-operations>

- Usage** <rpc-reply>
 <cfm-counters-route-socket-operations>
 <cfm-route-socket-message-counters>...</cfm-route-socket-message-counters>
 </cfm-counters-route-socket-operations>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <cfm-route-socket-message-counters>—No documentation is available yet.

<cfm-counters-route-socket-received>

- Usage** <rpc-reply>
 <cfm-counters-route-socket-received>
 <cfm-route-socket-message-counters>...</cfm-route-socket-message-counters>
 </cfm-counters-route-socket-received>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <cfm-route-socket-message-counters>—No documentation is available yet.

<cfm-cross-connect-session>

Usage <cfm-cross-connect-sessions>
 <cfm-cross-connect-session>
 <cfm-session-defect-type>*cfm-session-defect-type*</cfm-session-defect-type>
 <cfm-session-defect-description>*cfm-session-defect-description*
 </cfm-session-defect-description>
 <cfm-level>*cfm-level*</cfm-level>
 <cfm-maintenance-domain-name>*cfm-maintenance-domain-name*
 </cfm-maintenance-domain-name>
 <cfm-maintenance-domain-name-format>*cfm-maintenance-domain-name-format*
 </cfm-maintenance-domain-name-format>
 <cfm-maintenance-association-name>*cfm-maint-asc-name*
 </cfm-maintenance-association-name>
 <cfm-maintenance-association-name-format>*cfm-maint-assc-nm-frmt*
 </cfm-maintenance-association-name-format>
 <cfm-mep-identifier>*cfm-mep-identifier*</cfm-mep-identifier>
 <cfm-continuity-check-interval>*cfm-continuity-check-interval*
 </cfm-continuity-check-interval>
 </cfm-cross-connect-session>
 </cfm-cross-connect-sessions>

Description No documentation is available yet.

Contents <cfm-continuity-check-interval>—Continuity-check message interval.

<cfm-level>—Maintenance-domain level.

<cfm-maintenance-association-name>—Name of maintenance association.

<cfm-maintenance-association-name-format>—Format of maintenance association name.

<cfm-maintenance-domain-name>—Name of maintenance domain.

<cfm-maintenance-domain-name-format>—Format of maintenance domain name.

<cfm-mep-identifier>—Identifier of MEP.

<cfm-session-defect-description>—CCM session defect description.

<cfm-session-defect-type>—CCM session defect type.

<cfm-cross-connect-sessions>

Usage <cfm-entry>
 <cfm-cross-connect-sessions>
 <cfm-cross-connect-session-count>*cfm-cross-connect-session-count*
 </cfm-cross-connect-session-count>
 <cfm-cross-connect-session>...</cfm-cross-connect-session>
 </cfm-cross-connect-sessions>
 </cfm-entry>

Description No documentation is available yet.

Contents <cfm-cross-connect-session>—No documentation is available yet.
 <cfm-cross-connect-session-count>—Number of cross connect CCM sessions.

<cfm-entry>

Usage <cfm-interface | cfm-mep-database>
<cfm-entry>
 <cfm-interface-entry>...</cfm-interface-entry>
 <cfm-interface-sessions>...</cfm-interface-sessions>
 <cfm-mep-database-session>...</cfm-mep-database-session>
 <cfm-mep-database-continuity-check>...</cfm-mep-database-continuity-check>
 <cfm-mep-database-interface>...</cfm-mep-database-interface>
 <cfm-local-mep>...</cfm-local-mep>
 <cfm-local-mep-defects>...</cfm-local-mep-defects>
 <cfm-local-mep-statistics>...</cfm-local-mep-statistics>
 <cfm-remote-meps>...</cfm-remote-meps>
 <cfm-cross-connect-sessions>...</cfm-cross-connect-sessions>
 <cfm-error-sessions>...</cfm-error-sessions>
</cfm-entry>
 </cfm-interface | cfm-mep-database>

Description No documentation is available yet.

Contents <cfm-cross-connect-sessions>—No documentation is available yet.

<cfm-error-sessions>—No documentation is available yet.

<cfm-interface-entry>—No documentation is available yet.

<cfm-interface-sessions>—No documentation is available yet.

<cfm-local-mep>—No documentation is available yet.

<cfm-local-mep-defects>—No documentation is available yet.

<cfm-local-mep-statistics>—No documentation is available yet.

<cfm-mep-database-continuity-check>—No documentation is available yet.

<cfm-mep-database-interface>—No documentation is available yet.

<cfm-mep-database-session>—No documentation is available yet.

<cfm-remote-meps>—No documentation is available yet.

<cfm-error-session>

Usage <cfm-error-sessions>
 <cfm-error-session>
 <cfm-session-defect-type>*cfm-session-defect-type*</cfm-session-defect-type>
 <cfm-session-defect-description>*cfm-session-defect-description*
 </cfm-session-defect-description>
 <cfm-level>*cfm-level*</cfm-level>
 <cfm-maintenance-domain-name>*cfm-maintenance-domain-name*
 </cfm-maintenance-domain-name>
 <cfm-maintenance-domain-name-format>*cfm-maintenance-domain-name-format*
 </cfm-maintenance-domain-name-format>
 <cfm-maintenance-association-name>*cfm-maintenance-association-name*
 </cfm-maintenance-association-name>
 <cfm-maintenance-association-name-format>*cfm-ma-as-name-format*
 </cfm-maintenance-association-name-format>
 <cfm-continuity-check-interval>*cfm-continuity-check-interval*
 </cfm-continuity-check-interval>
 <cfm-mep-identifier>*cfm-mep-identifier*</cfm-mep-identifier>
 </cfm-error-session>
 </cfm-error-sessions>

Description No documentation is available yet.

Contents <cfm-continuity-check-interval>—Continuity-check message interval.

<cfm-level>—Maintenance-domain level.

<cfm-maintenance-association-name>—Name of maintenance association.

<cfm-maintenance-association-name-format>—Format of maintenance association name.

<cfm-maintenance-domain-name>—Name of maintenance domain.

<cfm-maintenance-domain-name-format>—Format of maintenance domain name.

<cfm-mep-identifier>—Identifier of MEP.

<cfm-session-defect-description>—CCM session defect description.

<cfm-session-defect-type>—CCM session defect type.

<cfm-error-sessions>

- Usage** `<cfm-entry>`
 <cfm-error-sessions>
 `<cfm-error-session-count>cfm-error-session-count</cfm-error-session-count>`
 `<cfm-error-session>...</cfm-error-session>`
 </cfm-error-sessions>
`</cfm-entry>`
- Description** No documentation is available yet.
- Contents** `<cfm-error-session>`—No documentation is available yet.
`<cfm-error-session-count>`—Number of error CCM sessions.

<cfm-filter>

- Usage** `<cfm-firewall-filter-instance-information | cfm-firewall-filter-interface-information>`
 <cfm-filter>
 `<cfm-filter-name>cfm-filter-name</cfm-filter-name>`
 `<cfm-filter-state>cfm-filter-state</cfm-filter-state>`
 `<cfm-filter-term-count>cfm-filter-term-count</cfm-filter-term-count>`
 `<cfm-filter-term-attachment>cfm-filter-term-attachment`
 `</cfm-filter-term-attachment>`
 </cfm-filter>
`</cfm-firewall-filter-instance-information | cfm-firewall-filter-interface-information>`
- Description** No documentation is available yet.
- Contents** `<cfm-filter-name>`—No documentation is available yet.
`<cfm-filter-state>`—No documentation is available yet.
`<cfm-filter-term-attachment>`—No documentation is available yet.
`<cfm-filter-term-count>`—No documentation is available yet.

<cfm-filter-term>

Usage	<pre> <cfm-firewall-filter-instance-information cfm-firewall-filter-interface-information> <cfm-filter-term> <cfm-filter-term-name>cfm-filter-term-name</cfm-filter-term-name> <cfm-filter-term-id>cfm-filter-term-id</cfm-filter-term-id> <cfm-filter-term-state>cfm-filter-term-state</cfm-filter-term-state> <cfm-filter-term-key>cfm-filter-term-key</cfm-filter-term-key> <cfm-filter-term-action>cfm-filter-term-action</cfm-filter-term-action> <cfm-filter-term-action-details>cfm-filter-term-action-details </cfm-filter-term-action-details> <cfm-flood-nexthop-components>...</cfm-flood-nexthop-components> </cfm-filter-term> </cfm-firewall-filter-instance-information cfm-firewall-filter-interface-information> </pre>
Description	No documentation is available yet.
Contents	<pre> <cfm-filter-term-action>—No documentation is available yet. <cfm-filter-term-action-details>—No documentation is available yet. <cfm-filter-term-id>—No documentation is available yet. <cfm-filter-term-key>—No documentation is available yet. <cfm-filter-term-name>—No documentation is available yet. <cfm-filter-term-state>—No documentation is available yet. <cfm-flood-nexthop-components>—No documentation is available yet. </pre>

<cfm-firewall-filter-instance-information>

Usage	<pre> <rpc-reply> <cfm-firewall-filter-instance-information> <cfm-instance-name>cfm-instance-name</cfm-instance-name> <cfm-filter>...</cfm-filter> <cfm-filter-term>...</cfm-filter-term> </cfm-firewall-filter-instance-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<pre> <cfm-filter>—No documentation is available yet. <cfm-filter-term>—No documentation is available yet. <cfm-instance-name>—Forwarding instance. </pre>

<cfm-firewall-filter-interface-information>

Usage <rpc-reply>
 <cfm-firewall-filter-interface-information>
 <cfm-interface-name>*cfm-interface-name*</cfm-interface-name>
 <cfm-instance-name>*cfm-instance-name*</cfm-instance-name>
 <cfm-filter>...</cfm-filter>
 <cfm-filter-term>...</cfm-filter-term>
 </cfm-firewall-filter-interface-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <cfm-filter>—No documentation is available yet.
 <cfm-filter-term>—No documentation is available yet.
 <cfm-instance-name>—Forwarding instance.
 <cfm-interface-name>—Name of interface.

<cfm-flood-instance-information>

Usage <rpc-reply>
 <cfm-flood-instance-information>
 <cfm-instance-name>*cfm-instance-name*</cfm-instance-name>
 <cfm-num-active-customer-endpoint-iffs>*cfm-num-active-customer-endpoint-iffs*
 </cfm-num-active-customer-endpoint-iffs>
 <cfm-num-active-vpn-endpoint-iffs>*cfm-num-active-vpn-endpoint-iffs*
 </cfm-num-active-vpn-endpoint-iffs>
 <cfm-flood-maintenance-domain-level>...</cfm-flood-maintenance-domain-level>
 </cfm-flood-instance-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <cfm-flood-maintenance-domain-level>—No documentation is available yet.
 <cfm-instance-name>—Forwarding instance.
 <cfm-num-active-customer-endpoint-iffs>—Number of customer endpoints (or customer-facing) ports.
 <cfm-num-active-vpn-endpoint-iffs>—Number of VPN endpoints (or pseudowire/core-facing) ports.

<cfm-flood-interface-information>

Usage <rpc-reply>
 <cfm-flood-interface-information>
 <cfm-interface-name>*cfm-interface-name*</cfm-interface-name>
 <cfm-instance-name>*cfm-instance-name*</cfm-instance-name>
 <cfm-flood-maintenance-domain-level>...</cfm-flood-maintenance-domain-level>
 </cfm-flood-interface-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <cfm-flood-maintenance-domain-level>—No documentation is available yet.

<cfm-instance-name>—Forwarding instance.

<cfm-interface-name>—Name of interface.

<cfm-flood-maintenance-domain-level>

Usage <cfm-flood-instance-information | cfm-flood-interface-information>
 <cfm-flood-maintenance-domain-level>
 <cfm-level>*cfm-level*</cfm-level>
 <cfm-local-mep-direction>*cfm-local-mep-direction*</cfm-local-mep-direction>
 <cfm-filter-action>*cfm-filter-action*</cfm-filter-action>
 <cfm-nexthop-type>*cfm-nexthop-type*</cfm-nexthop-type>
 <cfm-nexthop-index>*cfm-nexthop-index*</cfm-nexthop-index>
 <cfm-flood-nexthop-components>...</cfm-flood-nexthop-components>
 </cfm-flood-maintenance-domain-level>
 </cfm-flood-instance-information | cfm-flood-interface-information>

Description No documentation is available yet.

Contents <cfm-filter-action>—Action taken on receiving a CFM protocol packet.

<cfm-flood-nexthop-components>—No documentation is available yet.

<cfm-level>—Maintenance-domain level.

<cfm-local-mep-direction>—Direction in which continuity-check messages are sent.

<cfm-nexthop-index>—No documentation is available yet.

<cfm-nexthop-type>—No documentation is available yet.

<cfm-flood-nexthop-components>

Usage <cfm-flood-maintenance-domain-level | cfm-route-maintenance-domain-level | cfm-filter-term | cfm-nexthop-information | cfm-route-information>
<cfm-flood-nexthop-components>
 <cfm-interface-name>*cfm-interface-name*</cfm-interface-name>
 <cfm-interface-type>*cfm-interface-type*</cfm-interface-type>
 <cfm-interface-nexthop-type>*cfm-interface-nexthop-type*
 </cfm-interface-nexthop-type>
 <cfm-interface-nexthop-index>*cfm-interface-nexthop-index*
 </cfm-interface-nexthop-index>
</cfm-flood-nexthop-components>
 </cfm-flood-maintenance-domain-level | cfm-route-maintenance-domain-level | cfm-filter-term | cfm-nexthop-information | cfm-route-information>

Description No documentation is available yet.

Contents <cfm-interface-name>—Name of interface.
 <cfm-interface-nexthop-index>—No documentation is available yet.
 <cfm-interface-nexthop-type>—No documentation is available yet.
 <cfm-interface-type>—No documentation is available yet.

<cfm-interface>

Usage <rpc-reply>
<cfm-interface>
 <cfm-interface-snapshot>...</cfm-interface-snapshot>
 <cfm-entry>...</cfm-entry>
</cfm-interface>
 </rpc-reply>

Description Information about connectivity fault management for one or more interfaces.

Contents <cfm-entry>—No documentation is available yet.
 <cfm-interface-snapshot>—No documentation is available yet.

<cfm-interface-continuity-check>

Usage <cfm-interface-session>
 <cfm-interface-continuity-check>
 <cfm-continuity-check-status>*cfm-continuity-check-status*
 </cfm-continuity-check-status>
 <cfm-continuity-check-interval>*cfm-continuity-check-interval*
 </cfm-continuity-check-interval>
 <cfm-continuity-check-loss-threshold>*cfm-continuity-check-loss-threshold*
 </cfm-continuity-check-loss-threshold>
 </cfm-interface-continuity-check>
 </cfm-interface-session>

Description No documentation is available yet.

Contents <cfm-continuity-check-interval>—Continuity-check message interval.

<cfm-continuity-check-loss-threshold>—Maximum number of continuity-check messages that the endpoint can fail to acknowledge before it is marked as inoperative.

<cfm-continuity-check-status>—Continuity-check protocol status.

<cfm-interface-entry>

Usage <cfm-entry>
 <cfm-interface-entry>
 <cfm-interface-name>*cfm-interface-name*</cfm-interface-name>
 <cfm-interface-status>*cfm-interface-status*</cfm-interface-status>
 <cfm-interface-link-status>*cfm-interface-link-status*
 </cfm-interface-link-status>
 </cfm-interface-entry>
 </cfm-entry>

Description No documentation is available yet.

Contents <cfm-interface-link-status>—Operational status of this interface.

<cfm-interface-name>—Name of interface.

<cfm-interface-status>—Status of 802.1ag on the interface.

<cfm-interface-local-mep-defects>

Usage	<pre> <cfm-interface-session> cfm-interface-local-mep-defects <cfm-defect-remote-mep-no-ccm>cfm-defect-remote-mep-no-ccm </cfm-defect-remote-mep-no-ccm> <cfm-defect-error-ccm>cfm-defect-error-ccm</cfm-defect-error-ccm> <cfm-defect-cross-connect-ccm>cfm-defect-cross-connect-ccm </cfm-defect-cross-connect-ccm> <cfm-defect-rdi-in-some-mep>cfm-defect-rdi-in-some-mep </cfm-defect-rdi-in-some-mep> </cfm-interface-local-mep-defects </cfm-interface-session> </pre>
Description	No documentation is available yet.
Contents	<p><cfm-defect-cross-connect-ccm>—Indicates whether cross-connect continuity-check messages (CCMs) were received.</p> <p><cfm-defect-error-ccm>—Indicates whether erroneous continuity-check messages (CCMs) were received.</p> <p><cfm-defect-rdi-in-some-mep>—Indicates whether any remote MEPs are sending continuity-check messages (CCMs) with the RDI bit set.</p> <p><cfm-defect-remote-mep-no-ccm>—Indicates whether remote MEPs are receiving continuity-check messages (CCMs).</p>

<cfm-interface-local-mep-info>

Usage	<pre> <cfm-interface-session> cfm-interface-local-mep-info <cfm-local-mep-identifier>cfm-local-mep-identifier</cfm-local-mep-identifier> <cfm-local-mep-direction>cfm-local-mep-direction</cfm-local-mep-direction> <cfm-local-mep-mac-address>cfm-local-mep-mac-address </cfm-local-mep-mac-address> <cfm-local-mep-status>cfm-local-mep-status</cfm-local-mep-status> </cfm-interface-local-mep-info </cfm-interface-session> </pre>
Description	No documentation is available yet.
Contents	<p><cfm-local-mep-direction>—Direction in which continuity-check messages are sent.</p> <p><cfm-local-mep-identifier>—Identifier of local MEP.</p> <p><cfm-local-mep-mac-address>—MAC address of local MEP.</p> <p><cfm-local-mep-status>—Status of maintenance association endpoint.</p>

<cfm-interface-local-mep-statistics>

Usage <cfm-interface-session>
<cfm-interface-local-mep-statistics>
 <cfm-total-ccm-sent>*cfm-total-ccm-sent*</cfm-total-ccm-sent>
 <cfm-out-of-sequence-ccm-received>*cfm-out-of-sequence-ccm-received*
 </cfm-out-of-sequence-ccm-received>
 <cfm-lbm-sent>*cfm-lbm-sent*</cfm-lbm-sent>
 <cfm-lbr-sent>*cfm-lbr-sent*</cfm-lbr-sent>
 <cfm-lbr-received>*cfm-lbr-received*</cfm-lbr-received>
 <cfm-lbr-received-out-of-order>*cfm-lbr-received-out-of-order*
 </cfm-lbr-received-out-of-order>
 <cfm-lbr-bad-msdu>*cfm-lbr-bad-msdu*</cfm-lbr-bad-msdu>
 <cfm-total-ltm-sent>*cfm-total-ltm-sent*</cfm-total-ltm-sent>
 <cfm-total-ltm-received>*cfm-total-ltm-received*</cfm-total-ltm-received>
 <cfm-total-ltr-sent>*cfm-total-ltr-sent*</cfm-total-ltr-sent>
 <cfm-total-ltr-received>*cfm-total-ltr-received*</cfm-total-ltr-received>
 <cfm-next-ltm-sequence-number>*cfm-next-ltm-sequence-number*
 </cfm-next-ltm-sequence-number>
</cfm-interface-local-mep-statistics>
 </cfm-interface-session>

Description No documentation is available yet.

Contents <cfm-lbm-sent>—Number of loopback messages sent.

<cfm-lbr-bad-msdu>—Number of loopback responses received with corrupted data.

<cfm-lbr-received>—Number of valid in-order loopback responses received.

<cfm-lbr-received-out-of-order>—Number of valid out-of-order loopback responses received.

<cfm-lbr-sent>—Number of loopback responses sent.

<cfm-next-ltm-sequence-number>—Sequence Number of the next LTM request.

<cfm-out-of-sequence-ccm-received>—Number of continuity-check messages received out of sequence.

<cfm-total-ccm-sent>—Number of continuity-check messages sent.

<cfm-total-ltm-received>—Number of linktrace-request messages received.

<cfm-total-ltm-sent>—Number of linktrace-request messages sent.

<cfm-total-ltr-received>—Number of linktrace-response messages received.

<cfm-total-ltr-sent>—Number of linktrace-response messages sent.

<cfm-interface-remote-meps>

- Usage** <cfm-interface-session>
 <cfm-interface-remote-meps>
 <cfm-remote-mep-count>cfm-remote-mep-count</cfm-remote-mep-count>
 <cfm-remote-mep>...</cfm-remote-mep>
 </cfm-interface-remote-meps>
 </cfm-interface-session>
- Description** No documentation is available yet.
- Contents** <cfm-remote-mep>—No documentation is available yet.
 <cfm-remote-mep-count>—Number of remote MEP configured or learnt.

<cfm-interface-session>

- Usage** <cfm-interface-sessions>
 <cfm-interface-session>
 <cfm-interface-session-identifier>...</cfm-interface-session-identifier>
 <cfm-interface-continuity-check>...</cfm-interface-continuity-check>
 <cfm-interface-local-mep-info>...</cfm-interface-local-mep-info>
 <cfm-interface-local-mep-defects>...</cfm-interface-local-mep-defects>
 <cfm-interface-local-mep-statistics>...</cfm-interface-local-mep-statistics>
 <cfm-interface-remote-meps>...</cfm-interface-remote-meps>
 </cfm-interface-session>
 </cfm-interface-sessions>
- Description** No documentation is available yet.
- Contents** <cfm-interface-continuity-check>—No documentation is available yet.
 <cfm-interface-local-mep-defects>—No documentation is available yet.
 <cfm-interface-local-mep-info>—No documentation is available yet.
 <cfm-interface-local-mep-statistics>—No documentation is available yet.
 <cfm-interface-remote-meps>—No documentation is available yet.
 <cfm-interface-session-identifier>—No documentation is available yet.

<cfm-interface-session-identifier>

Usage <cfm-interface-session>
 <cfm-interface-session-identifier>
 <cfm-level>*cfm-level*</cfm-level>
 <cfm-maintenance-domain-name>*cfm-maintenance-domain-name*
 </cfm-maintenance-domain-name>
 <cfm-maintenance-domain-name-format>*cfm-maintenance-domain-name-format*
 </cfm-maintenance-domain-name-format>
 <cfm-maintenance-association-name>*cfm-maintenance-association-name*
 </cfm-maintenance-association-name>
 <cfm-maintenance-association-name-format>*cfm-maint-as-name-format*
 </cfm-maintenance-association-name-format>
 </cfm-interface-session-identifier>
 </cfm-interface-session>

Description No documentation is available yet.

Contents <cfm-level>—Maintenance-domain level.

<cfm-maintenance-association-name>—Name of maintenance association.

<cfm-maintenance-association-name-format>—Format of maintenance association name.

<cfm-maintenance-domain-name>—Name of maintenance domain.

<cfm-maintenance-domain-name-format>—Format of maintenance domain name.

<cfm-interface-session-snapshot>

Usage <cfm-interface-snapshot>
 <cfm-interface-session-snapshot>
 <cfm-level>*cfm-level*</cfm-level>
 <cfm-mep-identifier>*cfm-mep-identifier*</cfm-mep-identifier>
 <cfm-remote-mep-count>*cfm-remote-mep-count*</cfm-remote-mep-count>
 </cfm-interface-session-snapshot>
 </cfm-interface-snapshot>

Description No documentation is available yet.

Contents <cfm-level>—Maintenance-domain level.

<cfm-mep-identifier>—Identifier of MEP.

<cfm-remote-mep-count>—Number of remote MEP configured or learnt.

<cfm-interface-sessions>

- Usage** <cfm-entry>
 <cfm-interface-sessions>
 <cfm-interface-session>...</cfm-interface-session>
 </cfm-interface-sessions>
 </cfm-entry>
- Description** No documentation is available yet.
- Contents** <cfm-interface-session>—No documentation is available yet.

<cfm-interface-snapshot>

- Usage** <cfm-interface>
 <cfm-interface-snapshot>
 <cfm-interface-name>*cfm-interface-name*</cfm-interface-name>
 <cfm-interface-link-status>*cfm-interface-link-status*
 </cfm-interface-link-status>
 <cfm-interface-status>*cfm-interface-status*</cfm-interface-status>
 <cfm-interface-session-snapshot>...</cfm-interface-session-snapshot>
 </cfm-interface-snapshot>
 </cfm-interface>
- Description** No documentation is available yet.
- Contents** <cfm-interface-link-status>—Operational status of this interface.
- <cfm-interface-name>—Name of interface.
- <cfm-interface-session-snapshot>—No documentation is available yet.
- <cfm-interface-status>—Status of 802.1ag on the interface.

<cfm-linktrace-path-database>

- Usage** <rpc-reply>
 <cfm-linktrace-path-database>
 <cfm-ltm-request-snapshot>...</cfm-ltm-request-snapshot>
 <cfm-ltr-reply-entry>...</cfm-ltr-reply-entry>
 </cfm-linktrace-path-database>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <cfm-ltm-request-snapshot>—No documentation is available yet.
- <cfm-ltr-reply-entry>—No documentation is available yet.

<cfm-local-mep>

Usage <cfm-entry>
 <cfm-local-mep>
 <cfm-local-mep-identifier>*cfm-local-mep-identifier*</cfm-local-mep-identifier>
 <cfm-local-mep-direction>*cfm-local-mep-direction*</cfm-local-mep-direction>
 <cfm-local-mep-mac-address>*cfm-local-mep-mac-address*
 </cfm-local-mep-mac-address>
 <cfm-local-mep-auto-discovery>*cfm-local-mep-auto-discovery*
 </cfm-local-mep-auto-discovery>
 <cfm-local-mep-priority>*cfm-local-mep-priority*</cfm-local-mep-priority>
 <cfm-local-mep-status>*cfm-local-mep-status*</cfm-local-mep-status>
 </cfm-local-mep>
 </cfm-entry>

Description No documentation is available yet.

Contents <cfm-local-mep-auto-discovery>—Indicates whether auto-discovery of remote MEPS are enabled.

<cfm-local-mep-direction>—Direction in which continuity-check messages are sent.

<cfm-local-mep-identifier>—Identifier of local MEP.

<cfm-local-mep-mac-address>—MAC address of local MEP.

<cfm-local-mep-priority>—VLAN priority used in the continuity-check and link-trace messages.

<cfm-local-mep-status>—Status of maintenance association endpoint.

<cfm-local-mep-defects>

Usage <cfm-entry>
 <cfm-local-mep-defects>
 <cfm-defect-remote-mep-no-ccm>*cfm-defect-remote-mep-no-ccm*
 </cfm-defect-remote-mep-no-ccm>
 <cfm-defect-error-ccm>*cfm-defect-error-ccm*</cfm-defect-error-ccm>
 <cfm-defect-cross-connect-ccm>*cfm-defect-cross-connect-ccm*
 </cfm-defect-cross-connect-ccm>
 <cfm-defect-rdi-in-some-mep>*cfm-defect-rdi-in-some-mep*
 </cfm-defect-rdi-in-some-mep>
 </cfm-local-mep-defects>
 </cfm-entry>

Description No documentation is available yet.

Contents <cfm-defect-cross-connect-ccm>—Indicates whether cross-connect continuity-check messages (CCMs) were received.

<cfm-defect-error-ccm>—Indicates whether erroneous continuity-check messages (CCMs) were received.

<cfm-defect-rdi-in-some-mep>—Indicates whether any remote MEPs are sending continuity-check messages (CCMs) with the RDI bit set.

<cfm-defect-remote-mep-no-ccm>—Indicates whether remote MEPs are receiving continuity-check messages (CCMs).

<cfm-local-mep-statistics>

Usage <cfm-entry>
<cfm-local-mep-statistics>
 <cfm-total-ccm-sent>*cfm-total-ccm-sent*</cfm-total-ccm-sent>
 <cfm-out-of-sequence-ccm-received>*cfm-out-of-sequence-ccm-received*
 </cfm-out-of-sequence-ccm-received>
 <cfm-lbm-sent>*cfm-lbm-sent*</cfm-lbm-sent>
 <cfm-lbr-sent>*cfm-lbr-sent*</cfm-lbr-sent>
 <cfm-lbr-received>*cfm-lbr-received*</cfm-lbr-received>
 <cfm-lbr-received-out-of-order>*cfm-lbr-received-out-of-order*
 </cfm-lbr-received-out-of-order>
 <cfm-lbr-bad-msdu>*cfm-lbr-bad-msdu*</cfm-lbr-bad-msdu>
 <cfm-total-ltm-sent>*cfm-total-ltm-sent*</cfm-total-ltm-sent>
 <cfm-total-ltm-received>*cfm-total-ltm-received*</cfm-total-ltm-received>
 <cfm-total-ltr-sent>*cfm-total-ltr-sent*</cfm-total-ltr-sent>
 <cfm-total-ltr-received>*cfm-total-ltr-received*</cfm-total-ltr-received>
 <cfm-next-ltm-sequence-number>*cfm-next-ltm-sequence-number*
 </cfm-next-ltm-sequence-number>
</cfm-local-mep-statistics>
 </cfm-entry>

Description No documentation is available yet.

Contents <cfm-lbm-sent>—Number of loopback messages sent.

<cfm-lbr-bad-msdu>—Number of loopback responses received with corrupted data.

<cfm-lbr-received>—Number of valid in-order loopback responses received.

<cfm-lbr-received-out-of-order>—Number of valid out-of-order loopback responses received.

<cfm-lbr-sent>—Number of loopback responses sent.

<cfm-next-ltm-sequence-number>—Sequence Number of the next LTM request.

<cfm-out-of-sequence-ccm-received>—Number of continuity-check messages received out of sequence.

<cfm-total-ccm-sent>—Number of continuity-check messages sent.

<cfm-total-ltm-received>—Number of linktrace-request messages received.

<cfm-total-ltm-sent>—Number of linktrace-request messages sent.

<cfm-total-ltr-received>—Number of linktrace-response messages received.

<cfm-total-ltr-sent>—Number of linktrace-response messages sent.

<cfm-ltm-request-snapshot>

Usage <cfm-linktrace-path-database>
 <cfm-ltm-request-snapshot>
 <cfm-interface-name>*cfm-interface-name*</cfm-interface-name>
 <cfm-level>*cfm-level*</cfm-level>
 <cfm-maintenance-domain-name>*cfm-maintenance-domain-name*
 </cfm-maintenance-domain-name>
 <cfm-maintenance-association-name>*cfm-maintenance-association-name*
 </cfm-maintenance-association-name>
 <cfm-local-mep-identifier>*cfm-local-mep-identifier*</cfm-local-mep-identifier>
 <cfm-ltm-target-mac-address>*cfm-ltm-target-mac-address*
 </cfm-ltm-target-mac-address>
 </cfm-ltm-request-snapshot>
 </cfm-linktrace-path-database>

Description No documentation is available yet.

Contents <cfm-interface-name>—Name of interface.

<cfm-level>—Maintenance-domain level.

<cfm-local-mep-identifier>—Identifier of local MEP.

<cfm-ltm-target-mac-address>—MAC address of the target host in linktrace request.

<cfm-maintenance-association-name>—Name of maintenance association.

<cfm-maintenance-domain-name>—Name of maintenance domain.

<cfm-ltr-reply-entry>

Usage <cfm-linktrace-path-database>
 <cfm-ltr-reply-entry>
 <cfm-ltm-transaction-identifier>*cfm-ltm-transaction-identifier*
 </cfm-ltm-transaction-identifier>
 <cfm-ltr-request-hop-identifier>*cfm-ltr-request-hop-identifier*
 </cfm-ltr-request-hop-identifier>
 <cfm-ltr-reply-ttl>*cfm-ltr-reply-ttl*</cfm-ltr-reply-ttl>
 <cfm-ltr-mep-mip-mac-address>*cfm-ltr-mep-mip-mac-address*
 </cfm-ltr-mep-mip-mac-address>
 <cfm-ltr-next-hop-mac-address>*cfm-ltr-next-hop-mac-address*
 </cfm-ltr-next-hop-mac-address>
 </cfm-ltr-reply-entry>
 </cfm-linktrace-path-database>

Description No documentation is available yet.

Contents <cfm-ltm-transaction-identifier>—Identifier which uniquely identifies a linktrace request.

<cfm-ltr-mep-mip-mac-address>—MAC address of the of the host sending the linktrace reply.

<cfm-ltr-next-hop-mac-address>—MAC address of the next-hop to which the linktrace request is forwarded.

<cfm-ltr-reply-ttl>—Time-to-live value received in linktrace reply.

<cfm-ltr-request-hop-identifier>—Identifier showing the order in which linktrace replies are received.

<cfm-mep-database>

Usage <rpc-reply>
 <cfm-mep-database>
 <cfm-entry>...</cfm-entry>
 </cfm-mep-database>
 </rpc-reply>

Description Information about MEP database for one or more CFM sessions.

Contents <cfm-entry>—No documentation is available yet.

<cfm-mep-database-continuity-check>

Usage <cfm-entry>
 <cfm-mep-database-continuity-check>
 <cfm-continuity-check-status>*cfm-continuity-check-status*
 </cfm-continuity-check-status>
 <cfm-continuity-check-interval>*cfm-continuity-check-interval*
 </cfm-continuity-check-interval>
 <cfm-continuity-check-loss-threshold>*cfm-continuity-check-loss-threshold*
 </cfm-continuity-check-loss-threshold>
 </cfm-mep-database-continuity-check>
 </cfm-entry>

Description No documentation is available yet.

Contents <cfm-continuity-check-interval>—Continuity-check message interval.

<cfm-continuity-check-loss-threshold>—Maximum number of continuity-check messages that the endpoint can fail to acknowledge before it is marked as inoperative.

<cfm-continuity-check-status>—Continuity-check protocol status.

<cfm-mep-database-interface>

Usage <cfm-entry>
 <cfm-mep-database-interface>
 <cfm-interface-name>*cfm-interface-name*</cfm-interface-name>
 <cfm-interface-status>*cfm-interface-status*</cfm-interface-status>
 <cfm-interface-link-status>*cfm-interface-link-status*
 </cfm-interface-link-status>
 </cfm-mep-database-interface>
 </cfm-entry>

Description No documentation is available yet.

Contents <cfm-interface-link-status>—Operational status of this interface.

<cfm-interface-name>—Name of interface.

<cfm-interface-status>—Status of 802.1ag on the interface.

<cfm-mep-database-session>

Usage <cfm-entry>
 <cfm-mep-database-session>
 <cfm-maintenance-domain-name>*cfm-maintenance-domain-name*
 </cfm-maintenance-domain-name>
 <cfm-maintenance-domain-name-format>*cfm-maintenance-domain-name-format*
 </cfm-maintenance-domain-name-format>
 <cfm-level>*cfm-level*</cfm-level>
 <cfm-maintenance-association-name>*cfm-maintenance-association-name*
 </cfm-maintenance-association-name>
 <cfm-maintenance-association-name-format>*cfm-maint-asc-name-format*
 </cfm-maintenance-association-name-format>
 </cfm-mep-database-session>
 </cfm-entry>

Description No documentation is available yet.

Contents <cfm-level>—Maintenance-domain level.

 <cfm-maintenance-association-name>—Name of maintenance association.

 <cfm-maintenance-association-name-format>—Format of maintenance association name.

 <cfm-maintenance-domain-name>—Name of maintenance domain.

 <cfm-maintenance-domain-name-format>—Format of maintenance domain name.

<cfm-nexthop-information>

Usage <rpc-reply>
<cfm-nexthop-information>
 <cfm-nexthop-index>*cfm-nexthop-index*</cfm-nexthop-index>
 <cfm-nexthop-type>*cfm-nexthop-type*</cfm-nexthop-type>
 <cfm-nexthop-last-operation>*cfm-nexthop-last-operation*
 </cfm-nexthop-last-operation>
 <cfm-nexthop-last-error>*cfm-nexthop-last-error*</cfm-nexthop-last-error>
 <cfm-nexthop-statistics>*cfm-nexthop-statistics*</cfm-nexthop-statistics>
 <cfm-nexthop-reference-count>*cfm-nexthop-reference-count*
 </cfm-nexthop-reference-count>
 <cfm-nexthop-owner>*cfm-nexthop-owner*</cfm-nexthop-owner>
 <cfm-level>*cfm-level*</cfm-level>
 <cfm-flood-nexthop-components>...</cfm-flood-nexthop-components>
</cfm-nexthop-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <cfm-flood-nexthop-components>—No documentation is available yet.

<cfm-level>—Maintenance-domain level.

<cfm-nexthop-index>—No documentation is available yet.

<cfm-nexthop-last-error>—No documentation is available yet.

<cfm-nexthop-last-operation>—No documentation is available yet.

<cfm-nexthop-owner>—No documentation is available yet.

<cfm-nexthop-reference-count>—No documentation is available yet.

<cfm-nexthop-statistics>—No documentation is available yet.

<cfm-nexthop-type>—No documentation is available yet.

<cfm-remote-mep>

Usage <cfm-interface-remote-meps | cfm-remote-meps>

```

<cfm-remote-mep>
  <cfm-remote-mep-identifier>cfm-remote-mep-identifier
  </cfm-remote-mep-identifier>
  <cfm-remote-mep-state>cfm-remote-mep-state</cfm-remote-mep-state>
  <cfm-remote-mep-mac-address>cfm-remote-mep-mac-address
  </cfm-remote-mep-mac-address>
  <cfm-remote-mep-interface>cfm-remote-mep-interface</cfm-remote-mep-interface>
  <cfm-remote-mep-type>cfm-remote-mep-type</cfm-remote-mep-type>
  <cfm-remote-mep-rdi>cfm-remote-mep-rdi</cfm-remote-mep-rdi>
  <cfm-remote-mep-last-flapped>cfm-remote-mep-last-flapped
  </cfm-remote-mep-last-flapped>
  <cfm-remote-mep-port-status-tlv>cfm-remote-mep-port-status-tlv
  </cfm-remote-mep-port-status-tlv>
  <cfm-remote-mep-interface-status-tlv>cfm-remote-mep-interface-status-tlv
  </cfm-remote-mep-interface-status-tlv>
</cfm-remote-mep>
</cfm-interface-remote-meps | cfm-remote-meps>

```

Description No documentation is available yet.

Contents <cfm-remote-mep-identifier>—Identifier of remote MEP.

<cfm-remote-mep-interface>—Interface on which this remote MEP has been discovered.

<cfm-remote-mep-interface-status-tlv>—Interface status TLV information in the received CCM from remote MEP.

<cfm-remote-mep-last-flapped>—Last time when remote MEP flapped.

<cfm-remote-mep-mac-address>—MAC address of remote MEP.

<cfm-remote-mep-port-status-tlv>—Port status TLV information in the received CCM from remote MEP.

<cfm-remote-mep-rdi>—Remote defect indication status of the remote MEP.

<cfm-remote-mep-state>—State of the remote MEP.

<cfm-remote-mep-type>—Type of the remote MEP.

<cfm-remote-meps>

- Usage** `<cfm-entry>`
 <cfm-remote-meps>
 `<cfm-remote-mep-count>cfm-remote-mep-count</cfm-remote-mep-count>`
 `<cfm-remote-mep>...</cfm-remote-mep>`
 </cfm-remote-meps>
`</cfm-entry>`
- Description** No documentation is available yet.
- Contents** `<cfm-remote-mep>`—No documentation is available yet.
 `<cfm-remote-mep-count>`—Number of remote MEP configured or learnt.

<cfm-route-information>

- Usage** `<rpc-reply>`
 <cfm-route-information>
 `<cfm-route-prefix>cfm-route-prefix</cfm-route-prefix>`
 `<cfm-nexthop-index>cfm-nexthop-index</cfm-nexthop-index>`
 `<cfm-route-last-operation>cfm-route-last-operation</cfm-route-last-operation>`
 `<cfm-route-last-error>cfm-route-last-error</cfm-route-last-error>`
 `<cfm-route-statistics>cfm-route-statistics</cfm-route-statistics>`
 `<cfm-level>cfm-level</cfm-level>`
 `<cfm-route-table-index>cfm-route-table-index</cfm-route-table-index>`
 `<cfm-route-owner>cfm-route-owner</cfm-route-owner>`
 `<cfm-flood-nexthop-components>...</cfm-flood-nexthop-components>`
 </cfm-route-information>
`</rpc-reply>`
- Description** No documentation is available yet.
- Contents** `<cfm-flood-nexthop-components>`—No documentation is available yet.
 `<cfm-level>`—Maintenance-domain level.
 `<cfm-nexthop-index>`—No documentation is available yet.
 `<cfm-route-last-error>`—No documentation is available yet.
 `<cfm-route-last-operation>`—No documentation is available yet.
 `<cfm-route-owner>`—No documentation is available yet.
 `<cfm-route-prefix>`—No documentation is available yet.
 `<cfm-route-statistics>`—No documentation is available yet.
 `<cfm-route-table-index>`—No documentation is available yet.

<cfm-route-maintenance-domain-level>

Usage	<pre> <cfm-transmit-interface-information> cfm-route-maintenance-domain-level <cfm-level>cfm-level</cfm-level> <cfm-local-mep-direction>cfm-local-mep-direction</cfm-local-mep-direction> <cfm-transmit-route-prefix>cfm-transmit-route-prefix </cfm-transmit-route-prefix> <cfm-nexthop-index>cfm-nexthop-index</cfm-nexthop-index> <cfm-flood-nexthop-components>...</cfm-flood-nexthop-components> </cfm-route-maintenance-domain-level> </cfm-transmit-interface-information> </pre>
Description	No documentation is available yet.
Contents	<p><cfm-flood-nexthop-components>—No documentation is available yet.</p> <p><cfm-level>—Maintenance-domain level.</p> <p><cfm-local-mep-direction>—Direction in which continuity-check messages are sent.</p> <p><cfm-nexthop-index>—No documentation is available yet.</p> <p><cfm-transmit-route-prefix>—Route prefix looked up for forwarding locally generated packets.</p>

<cfm-route-socket-message-counters>

Usage	<pre> <cfm-counters-route-socket-operations cfm-counters-route-socket-received> cfm-route-socket-message-counters <cfm-route-socket-message-type>cfm-route-socket-message-type </cfm-route-socket-message-type> <cfm-route-socket-message-add>cfm-route-socket-message-add </cfm-route-socket-message-add> <cfm-route-socket-message-change>cfm-route-socket-message-change </cfm-route-socket-message-change> <cfm-route-socket-message-delete>cfm-route-socket-message-delete </cfm-route-socket-message-delete> </cfm-route-socket-message-counters> </cfm-counters-route-socket-operations cfm-counters-route-socket-received> </pre>
Description	No documentation is available yet.
Contents	<p><cfm-route-socket-message-add>—No documentation is available yet.</p> <p><cfm-route-socket-message-change>—No documentation is available yet.</p> <p><cfm-route-socket-message-delete>—No documentation is available yet.</p> <p><cfm-route-socket-message-type>—No documentation is available yet.</p>

<cfm-transmit-interface-information>

Usage <rpc-reply>
 <cfm-transmit-interface-information>
 <cfm-interface-name>*cfm-interface-name*</cfm-interface-name>
 <cfm-instance-name>*cfm-instance-name*</cfm-instance-name>
 <cfm-route-maintenance-domain-level>...</cfm-route-maintenance-domain-level>
 </cfm-transmit-interface-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <cfm-instance-name>—Forwarding instance.
 <cfm-interface-name>—Name of interface.
 <cfm-route-maintenance-domain-level>—No documentation is available yet.

<cfmd-internal-state>

Usage <rpc-reply>
<cfmd-internal-state>
 <cfm-session-count>*cfm-session-count*</cfm-session-count>
 <cfm-session-created-count>*cfm-session-created-count*
 </cfm-session-created-count>
 <cfm-session-deleted-count>*cfm-session-deleted-count*
 </cfm-session-deleted-count>
 <cfm-session-freed-count>*cfm-session-freed-count*</cfm-session-freed-count>
 <cfm-vpls>*cfm-vpls*</cfm-vpls>
 <cfm-token-based-forwarding>*cfm-token-based-forwarding*
 </cfm-token-based-forwarding>
 <cfm-forwarding-table-filtering-simulation>*cfm-forwarding-table-filtering-simulation*
 </cfm-forwarding-table-filtering-simulation>
 <cfm-hardware-assist-flooding>*cfm-hardware-assist-flooding*
 </cfm-hardware-assist-flooding>
 <cfm-gres-flood-resynchronization>*cfm-gres-flood-resynchronization*
 </cfm-gres-flood-resynchronization>
 <cfm-shared-interface-filters>*cfm-shared-interface-filters*
 </cfm-shared-interface-filters>
 <cfm-ppmd-connection-state>*cfm-ppmd-connection-state*
 </cfm-ppmd-connection-state>
 <cfm-ppmd-flow-state>*cfm-ppmd-flow-state*</cfm-ppmd-flow-state>
 <cfm-ppmd-job-state>*cfm-ppmd-job-state*</cfm-ppmd-job-state>
 <cfm-ppmd-blocked-count>*cfm-ppmd-blocked-count*</cfm-ppmd-blocked-count>
 <cfm-dfwd-connection-state>*cfm-dfwd-connection-state*
 </cfm-dfwd-connection-state>
 <cfm-dfwd-requests>*cfm-dfwd-requests*</cfm-dfwd-requests>
</cfmd-internal-state>
 </rpc-reply>

Description No documentation is available yet.

Contents <cfm-dfwd-connection-state>—No documentation is available yet.
 <cfm-dfwd-requests>—No documentation is available yet.
 <cfm-forwarding-table-filtering-simulation>—No documentation is available yet.
 <cfm-gres-flood-resynchronization>—No documentation is available yet.
 <cfm-hardware-assist-flooding>—No documentation is available yet.
 <cfm-ppmd-blocked-count>—No documentation is available yet.
 <cfm-ppmd-connection-state>—No documentation is available yet.
 <cfm-ppmd-flow-state>—No documentation is available yet.
 <cfm-ppmd-job-state>—No documentation is available yet.
 <cfm-session-count>—No documentation is available yet.
 <cfm-session-created-count>—No documentation is available yet.

<cfm-session-deleted-count>—No documentation is available yet.

<cfm-session-freed-count>—No documentation is available yet.

<cfm-shared-interface-filters>—No documentation is available yet.

<cfm-token-based-forwarding>—No documentation is available yet.

<cfm-vpls>—No documentation is available yet.

Summary of Chassis Response Tags

This section lists JUNOS XML tags that contain operational information about the routing platform chassis. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-chassis>. To review the DTD for the tags, see “DTD for Chassis Response Tags” on page 1671.

<alarm-indicators>

Usage <front-panel>
 <alarm-indicators>
 <red-led/>
 <yellow-led/>
 <major-alarm-relay/>
 <minor-alarm-relay/>
 </alarm-indicators>
 </front-panel>

Description Information about alarms from the craft interface.

Contents <major-alarm-relay>—Major (red) alarm relay is active.
 <minor-alarm-relay>—Minor (yellow) alarm relay is active.
 <red-led>—Red LED is lit.
 <yellow-led>—Yellow LED is lit.

<cb>

Usage <cb-panel>
 <cb>
 <slot>slot</slot>
 <amber-led/>
 <green-led/>
 <blue-led/>
 </cb>
 </cb-panel>

Description State of status LEDs on a Control Board.

Contents <amber-led>—Amber LED is lit.
 <blue-led>—Blue LED is lit.
 <green-led>—Green LED is lit.
 <slot>—No documentation is available yet.

<cb-panel>

- Usage** <craft-information>
 <cb-panel>
 <cb>...</cb>
 </cb-panel>
 </craft-information>
- Description** State of status LEDs on one or more Control Boards.
- Contents** <cb>—State of status LEDs on a Control Board.

<chassis>

- Usage** <chassis-inventory | firmware-information>
 <chassis>
 <hardware-incomplete/>
 <name>*name*</name>
 <version>*version*</version>
 <part-number>*part-number*</part-number>
 <serial-number>*serial-number*</serial-number>
 <model-number>*model-number*</model-number>
 <clei-code>*clei-code*</clei-code>
 <description>*description*</description>
 <i2c-information>...</i2c-information>
 <chassis-module>...</chassis-module>
 </chassis>
 </chassis-inventory | firmware-information>
- Description** Hardware inventory of this chassis.
- Contents** <chassis-module>—No documentation is available yet.
- <clei-code>—Common Language Equipment Identifier code of this component.
- <description>—Description of this component.
- <hardware-incomplete>—No documentation is available yet.
- <i2c-information>—No documentation is available yet.
- <model-number>—Model number of this component.
- <name>—Name of this component.
- <part-number>—Part number of this component.
- <serial-number>—Serial number of this component.
- <version>—Version of this component.

<chassis-inventory>

- Usage** <multi-routing-engine-item>
 <chassis-inventory>
 <chassis>...</chassis>
 </chassis-inventory>
 </multi-routing-engine-item>
- Description** No documentation is available yet.
- Contents** <chassis>—Hardware inventory of this chassis.

<chassis-location>

- Usage** <rpc-reply>
 <chassis-location>
 <chassis-location-information>...</chassis-location-information>
 </chassis-location>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <chassis-location-information>—No documentation is available yet.

<chassis-location-fpc>

- Usage** <rpc-reply>
 <chassis-location-fpc>
 <chassis-location-fpc-information>...</chassis-location-fpc-information>
 </chassis-location-fpc>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <chassis-location-fpc-information>—No documentation is available yet.

<chassis-location-fpc-information>

- Usage** <chassis-location-fpc>
 <chassis-location-fpc-information>
 <global-fpc-number>*global-fpc-number*</global-fpc-number>
 <lcc-number>*lcc-number*</lcc-number>
 <local-fpc-number>*local-fpc-number*</local-fpc-number>
 </chassis-location-fpc-information>
 </chassis-location-fpc>
- Description** No documentation is available yet.
- Contents** <global-fpc-number>—Global FPC number.
- <lcc-number>—LCC number.
- <local-fpc-number>—Local FPC number.

<chassis-location-information>

Usage	<chassis-location multi-routing-engine-item> <chassis-location-information> <country-code> <i>country-code</i> </country-code> <postal-code> <i>postal-code</i> </postal-code> <npa-nxx> <i>npa-nxx</i> </npa-nxx> <latitude> <i>latitude</i> </latitude> <longitude> <i>longitude</i> </longitude> <altitude> <i>altitude</i> </altitude> <lata> <i>lata</i> </lata> <vcoord> <i>vcoord</i> </vcoord> <hcoord> <i>hcoord</i> </hcoord> <building> <i>building</i> </building> <floor> <i>floor</i> </floor> <rack> <i>rack</i> </rack> </chassis-location-information> </chassis-location multi-routing-engine-item>
Description	No documentation is available yet.
Contents	<altitude>—Feet above (or below) sea level. <building>—Building information. <country-code>—Country code. <floor>—Floor in building. <hcoord>—Bellcore horizontal coordinate. <lata>—Long distance service area. <latitude>—Latitude. <longitude>—Longitude. <npa-nxx>—Six digits of the phone number. <postal-code>—Postal code. <rack>—Rack. <vcoord>—Bellcore vertical coordinate.

<chassis-module>

Usage <chassis>
 <chassis-module>
 <name>*name*</name>
 <version>*version*</version>
 <part-number>*part-number*</part-number>
 <serial-number>*serial-number*</serial-number>
 <model-number>*model-number*</model-number>
 <clei-code>*clei-code*</clei-code>
 <description>*description*</description>
 <i2c-information>...</i2c-information>
 <firmware>...</firmware>
 <chassis-sub-module>...</chassis-sub-module>
 <chassis-re-disk-module>...</chassis-re-disk-module>
 <chassis-re-usb-module>...</chassis-re-usb-module>
 </chassis-module>
 </chassis>

Description No documentation is available yet.

Contents <chassis-re-disk-module>—No documentation is available yet.

<chassis-re-usb-module>—No documentation is available yet.

<chassis-sub-module>—No documentation is available yet.

<clei-code>—Common Language Equipment Identifier code of this component.

<description>—Description of this component.

<firmware>—No documentation is available yet.

<i2c-information>—No documentation is available yet.

<model-number>—Model number of this component.

<name>—Name of this component.

<part-number>—Part number of this component.

<serial-number>—Serial number of this component.

<version>—Version of this component.

<chassis-re-disk-module>

Usage <chassis-module>
 <chassis-re-disk-module>
 <name>*name*</name>
 <model>*model*</model>
 <serial-number>*serial-number*</serial-number>
 <disk-size>*disk-size*</disk-size>
 <description>*description*</description>
 </chassis-re-disk-module>
 </chassis-module>

Description No documentation is available yet.

Contents <description>—Description of this component.
 <disk-size>—Disk size (megabytes).
 <model>—No documentation is available yet.
 <name>—Name of this component.
 <serial-number>—Serial number of this component.

<chassis-re-usb-module>

Usage <chassis-module>
 <chassis-re-usb-module>
 <name>*name*</name>
 <product>*product*</product>
 <product-number>*product-number*</product-number>
 <vendor>*vendor*</vendor>
 <description>*description*</description>
 </chassis-re-usb-module>
 </chassis-module>

Description No documentation is available yet.

Contents <description>—Description of this component.
 <name>—Name of this component.
 <product>—No documentation is available yet.
 <product-number>—No documentation is available yet.
 <vendor>—No documentation is available yet.

<chassis-sub-module>

Usage <chassis-module>
 <chassis-sub-module>
 <name>*name*</name>
 <version>*version*</version>
 <part-number>*part-number*</part-number>
 <serial-number>*serial-number*</serial-number>
 <model-number>*model-number*</model-number>
 <clei-code>*clei-code*</clei-code>
 <description>*description*</description>
 <i2c-information>...</i2c-information>
 <firmware>...</firmware>
 <chassis-sub-sub-module>...</chassis-sub-sub-module>
 </chassis-sub-module>
 </chassis-module>

Description No documentation is available yet.

Contents <chassis-sub-sub-module>—No documentation is available yet.

<clei-code>—Common Language Equipment Identifier code of this component.

<description>—Description of this component.

<firmware>—No documentation is available yet.

<i2c-information>—No documentation is available yet.

<model-number>—Model number of this component.

<name>—Name of this component.

<part-number>—Part number of this component.

<serial-number>—Serial number of this component.

<version>—Version of this component.

<chassis-sub-sub-module>

Usage <chassis-sub-module>
 <chassis-sub-sub-module>
 <name>*name*</name>
 <version>*version*</version>
 <part-number>*part-number*</part-number>
 <serial-number>*serial-number*</serial-number>
 <model-number>*model-number*</model-number>
 <clei-code>*clei-code*</clei-code>
 <description>*description*</description>
 </chassis-sub-sub-module>
 </chassis-sub-module>

Description No documentation is available yet.

Contents <clei-code>—Common Language Equipment Identifier code of this component.

<description>—Description of this component.

<model-number>—Model number of this component.

<name>—Name of this component.

<part-number>—Part number of this component.

<serial-number>—Serial number of this component.

<version>—Version of this component.

<chassisd-database-memory-usage>

Usage <multi-routing-engine-item>
 <chassisd-database-memory-usage>
 <database-memory-usage>...</database-memory-usage>
 </chassisd-database-memory-usage>
 </multi-routing-engine-item>

Description No documentation is available yet.

Contents <database-memory-usage>—No documentation is available yet.

<clock-synchronization>

Usage <clock-synchronization-information>
 <clock-synchronization>
 <clock-fru>*clock-fru*</clock-fru>
 <mastership-state>*mastership-state*</mastership-state>
 <signal-type>*signal-type*</signal-type>
 <switching-mode>*switching-mode*</switching-mode>
 <line-termination>*line-termination*</line-termination>
 <transmit>*transmit*</transmit>
 <validation-interval>*validation-interval*</validation-interval>
 <automatic-switching>*automatic-switching*</automatic-switching>
 <marked-as-failed-source-list>...</marked-as-failed-source-list>
 <synchronization-source-list>...</synchronization-source-list>
 </clock-synchronization>
 </clock-synchronization-information>

Description No documentation is available yet.

Contents <automatic-switching>—Clock synchronization source switching: manual or automatic.

<clock-fru>—FRU on which clock module is present.

<line-termination>—How external signal is wired to redundant CBs.

<marked-as-failed-source-list>—No documentation is available yet.

<mastership-state>—Current state of mastership on this Routing Engine.

<signal-type>—Frequency for provided reference clocks.

<switching-mode>—Should system revert to higher priority valid source.

<synchronization-source-list>—No documentation is available yet.

<transmit>—Control whether diagnostic timing signal is transmitted.

<validation-interval>—Time between successive frequency measurements.

<clock-synchronization-information>

Usage <rpc-reply>
 <clock-synchronization-information>
 <clock-synchronization>...</clock-synchronization>
 </clock-synchronization-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <clock-synchronization>—No documentation is available yet.

<configured-source>

Usage <configured-source-list>
 <configured-source>
 <source-priority>*source-priority*</source-priority>
 <source-name>*source-name*</source-name>
 <deviation>*deviation*</deviation>
 <last-deviation>*last-deviation*</last-deviation>
 <status>*status*</status>
 </configured-source>
 </configured-source-list>

Description No documentation is available yet.

Contents <deviation>—Frequency deviation of clock synchronization source.
 <last-deviation>—Frequency deviation measured last.
 <source-name>—Name of clock synchronization source.
 <source-priority>—Priority of clock synchronization source.
 <status>—Status of clock synchronization source.

<configured-source-list>

Usage <synchronization-source-list>
 <configured-source-list>
 <configured-source>...</configured-source>
 </configured-source-list>
 </synchronization-source-list>

Description No documentation is available yet.

Contents <configured-source>—No documentation is available yet.

<craft-information>

Usage <rpc-reply>
 <craft-information>
 <front-panel>...</front-panel>
 <mcs-panel>...</mcs-panel>
 <sfm-panel>...</sfm-panel>
 <pcg-panel>...</pcg-panel>
 <cb-panel>...</cb-panel>
 <sib-panel>...</sib-panel>
 <scg-panel>...</scg-panel>
 <feb-panel>...</feb-panel>
 <power-supply-panel>...</power-supply-panel>
 <fan-tray-panel>...</fan-tray-panel>
 <output>output</output>
 </craft-information>
 </rpc-reply>

Description Information from the craft interface and, if applicable, the state of the status LEDs on the front panels of other components installed in the chassis.

Contents <cb-panel>—State of status LEDs on one or more Control Boards.

<fan-tray-panel>—State of status LEDs on the craft interface for Fan Trays.

<feb-panel>—State of the status LEDs on the faceplate of one or more Forwarding Engine Boards.

<front-panel>—Information from the craft interface.

<mcs-panel>—State of the status LEDs on the faceplate of one or more Miscellaneous Control Subsystems.

<output>—Formatted ASCII output displayed by the CLI.

<pcg-panel>—State of the status LEDs on the faceplate of one or more Packet Forwarding Engine Clock Generators.

<power-supply-panel>—State of the status LEDs on the faceplate of one or more power supplies.

<scg-panel>—State of the status LEDs on the faceplate of one or more SONET Clock Generators.

<sfm-panel>—State of the status LEDs on the faceplate of one or more Switching and Forwarding Modules.

<sib-panel>—State of the status LEDs on the faceplate of one or more Switch Interface Boards. Some of the LEDs also appear on the craft interface.

<current-source>

Usage	<pre> <synchronization-source-list> <current-source> <clock-state>clock-state</clock-state> <up-time>up-time</up-time> <active-time>active-time</active-time> <deviation>deviation</deviation> <last-deviation>last-deviation</last-deviation> </current-source> </synchronization-source-list> </pre>
Description	No documentation is available yet.
Contents	<p><active-time>—Time since clock synchronization source is in use.</p> <p><clock-state>—State of the clock synchronization source.</p> <p><deviation>—Frequency deviation of clock synchronization source.</p> <p><last-deviation>—Frequency deviation measured last.</p> <p><up-time>—Length of time this component has been operational.</p>

<database-memory-usage>

Usage	<pre> <chassisd-database-memory-usage> <database-memory-usage> <database-size>database-size</database-size> <database-allocated-size>database-allocated-size</database-allocated-size> <database-free-size>database-free-size</database-free-size> </database-memory-usage> </chassisd-database-memory-usage> </pre>
Description	No documentation is available yet.
Contents	<p><database-allocated-size>—Number of bytes used by the database.</p> <p><database-free-size>—Number of bytes free within the database.</p> <p><database-size>—Database size.</p>

<dc-detail>

Usage	<pre> <dc-information> <dc-detail> <dc-device><i>dc-device</i></dc-device> <dc-voltage><i>dc-voltage</i></dc-voltage> <dc-current><i>dc-current</i></dc-current> <dc-power><i>dc-power</i></dc-power> <dc-load><i>dc-load</i></dc-load> </dc-detail> </dc-information> </pre>
Description	Detailed DC information.
Contents	<p><dc-current>—No documentation is available yet.</p> <p><dc-device>—No documentation is available yet.</p> <p><dc-load>—No documentation is available yet.</p> <p><dc-power>—No documentation is available yet.</p> <p><dc-voltage>—No documentation is available yet.</p>

<dc-information>

Usage	<pre> <environment-component-item> <dc-information> <dc-input><i>dc-input</i></dc-input> <dc-output><i>dc-output</i></dc-output> <dc-detail>...</dc-detail> </dc-information> </environment-component-item> </pre>
Description	No documentation is available yet.
Contents	<p><dc-detail>—Detailed DC information.</p> <p><dc-input>—DC input state.</p> <p><dc-output>—DC output state.</p>

<display-panel>

Usage	<pre> <front-panel> <display-panel> <display-line><i>display-line</i></display-line> </display-panel> </front-panel> </pre>
Description	Text currently appearing on the craft interface display.
Contents	<display-line>—Single line of text currently appearing on the craft interface display.

<environment-component-information>

Usage <rpc-reply>
 <environment-component-information>
 <environment-component-item>...</environment-component-item>
 </environment-component-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <environment-component-item>—Chassis environment component.

<environment-component-item>

Usage <environment-component-information>
 <environment-component-item>
 <name>*name*</name>
 <state>*state*</state>
 <temperature-reading>...</temperature-reading>
 <bus-revision>*bus-revision*</bus-revision>
 <cmb-revision>*cmb-revision*</cmb-revision>
 <fpga-revision>*fpga-revision*</fpga-revision>
 <fpga-revision-detail>...</fpga-revision-detail>
 <slave-revision>*slave-revision*</slave-revision>
 <reason>*reason*</reason>
 <revision>...</revision>
 <slave-registers-information>...</slave-registers-information>
 <fpga-registers>...</fpga-registers>
 <power-information>...</power-information>
 <frequency>*frequency*</frequency>
 <pcg-frequency>...</pcg-frequency>
 <dc-information>...</dc-information>
 <load>*load*</load>
 <ac-input>*ac-input*</ac-input>
 </environment-component-item>
 </environment-component-information>

Description Chassis environment component.

Contents <ac-input>—AC input state.

<bus-revision>—Bus revision.

<cmb-revision>—CMB revision.

<dc-information>—No documentation is available yet.

<fpga-registers>—FPGA register values.

<fpga-revision>—FPGA revision.

<fpga-revision-detail>—FPGA revision in detail.

<frequency>—Frequency.

<load>—Load.

<name>—Name of this component.

<pcg-frequency>—PCG Frequency.

<power-information>—No documentation is available yet.

<reason>—Reason.

<revision>—No documentation is available yet.

<slave-registers-information>—No documentation is available yet.

<slave-revision>—Slave revision.

<state>—Status of the component.

<temperature-reading>—No documentation is available yet.

<environment-information>

Usage <multi-routing-engine-item>
 <environment-information>
 <environment-item>...</environment-item>
 </environment-information>
 </multi-routing-engine-item>

Description No documentation is available yet.

Contents <environment-item>—No documentation is available yet.

<environment-item>

Usage <environment-information>
 <environment-item>
 <class>*class*</class>
 <name>*name*</name>
 <status>*status*</status>
 <temperature>*temperature*</temperature>
 <comment>*comment*</comment>
 </environment-item>
 </environment-information>

Description No documentation is available yet.

Contents <class>—No documentation is available yet.

<comment>—No documentation is available yet.

<name>—Name of this component.

<status>—Status of clock synchronization source.

<temperature>—Temperature of the item.

<fan-information>

Usage <rpc-reply>
 <fan-information>
 <name>*name*</name>
 <status>*status*</status>
 <rpm>*rpm*</rpm>
 <comment>*comment*</comment>
 <fan-information-item>*fan-information-item*</fan-information-item>
 </fan-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <comment>—No documentation is available yet.

<fan-information-item>—No documentation is available yet.

<name>—Name of this component.

<rpm>—Fan speed in RPM.

<status>—Status of clock synchronization source.

<fan-tray>

Usage <fan-tray-panel>
 <fan-tray>
 <slot>*slot*</slot>
 <red-led/>
 <green-led/>
 </fan-tray>
 </fan-tray-panel>

Description State of the status LEDs on the craft interface for a fan tray.

Contents <green-led>—Green LED is lit.

<red-led>—Red LED is lit.

<slot>—No documentation is available yet.

<fan-tray-panel>

Usage <craft-information>
 <fan-tray-panel>
 <fan-tray>...</fan-tray>
 </fan-tray-panel>
 </craft-information>

Description State of status LEDs on the craft interface for Fan Trays.

Contents <fan-tray>—State of the status LEDs on the craft interface for a fan tray.

<feb>

Usage <feb-panel>
 <feb>
 <slot>slot</slot>
 <ok-led/>
 <fail-led/>
 <active-led/>
 </feb>
 </feb-panel>

Description State of the status LEDs on the faceplate of a Forwarding Engine Board.

Contents <active-led>—Active LED is lit.

<fail-led>—Fail LED is lit.

<ok-led>—OK LED is lit.

<slot>—No documentation is available yet.

<feb-led>

Usage <feb-led-information>
 <feb-led>
 <feb-slot>*feb-slot*</feb-slot>
 <feb-state>*feb-state*</feb-state>
 <feb-ok-led>*feb-ok-led*</feb-ok-led>
 <feb-fail-led>*feb-fail-led*</feb-fail-led>
 <feb-active-led>*feb-active-led*</feb-active-led>
 <connectivity-led0>*connectivity-led0*</connectivity-led0>
 <connectivity-led1>*connectivity-led1*</connectivity-led1>
 <connectivity-led2>*connectivity-led2*</connectivity-led2>
 <connectivity-led3>*connectivity-led3*</connectivity-led3>
 <connectivity-led4>*connectivity-led4*</connectivity-led4>
 <connectivity-led5>*connectivity-led5*</connectivity-led5>
 </feb-led>
 </feb-led-information>

Description No documentation is available yet.

Contents <connectivity-led0>—State of connectivity LED on FEB for FPC 0.
 <connectivity-led1>—State of connectivity LED on FEB for FPC 1.
 <connectivity-led2>—State of connectivity LED on FEB for FPC 2.
 <connectivity-led3>—State of connectivity LED on FEB for FPC 3.
 <connectivity-led4>—State of connectivity LED on FEB for FPC 4.
 <connectivity-led5>—State of connectivity LED on FEB for FPC 5.
 <feb-active-led>—State of 'ACTIVE' LED on FEB.
 <feb-fail-led>—State of 'FAIL' LED on FEB.
 <feb-ok-led>—State of 'OK' LED on FEB.
 <feb-slot>—FEB slot.
 <feb-state>—FEB state.

<feb-led-information>

Usage <rpc-reply>
 <feb-led-information>
 <feb-led>...</feb-led>
 </feb-led-information>
 </rpc-reply>

Description Information about the LEDs on the Forwarding Engine Board.

Contents <feb-led>—No documentation is available yet.

<feb-panel>

Usage <craft-information>
 <feb-panel>
 <feb>...</feb>
 </feb-panel>
 </craft-information>

Description State of the status LEDs on the faceplate of one or more Forwarding Engine Boards.

Contents <feb>—State of the status LEDs on the faceplate of a Forwarding Engine Board.

<feb-redundancy-error-information>

Usage <rpc-reply>
 <feb-redundancy-error-information>
 <feb-redundancy-group-errors>...</feb-redundancy-group-errors>
 </feb-redundancy-error-information>
 </rpc-reply>

Description FEB redundancy error information.

Contents <feb-redundancy-group-errors>—FEB redundancy error information for a FEB group.

<feb-redundancy-group-errors>

Usage <feb-redundancy-error-information>
 <feb-redundancy-group-errors>
 <feb-redundancy-group-name>*feb-redundancy-group-name*
 </feb-redundancy-group-name>
 <feb-redundancy-group-description>*feb-redundancy-group-description*
 </feb-redundancy-group-description>
 <feb-redundancy-group-feb-errors>...</feb-redundancy-group-feb-errors>
 </feb-redundancy-group-errors>
 </feb-redundancy-error-information>

Description FEB redundancy error information for a FEB group.

Contents <feb-redundancy-group-description>—FEB redundancy group description.

<feb-redundancy-group-feb-errors>—FEB redundancy error information for a FEB.

<feb-redundancy-group-name>—FEB redundancy group name.

<feb-redundancy-group-feb-errors>

Usage <feb-redundancy-group-errors>
 <feb-redundancy-group-feb-errors>
 <feb-slot>*feb-slot*</feb-slot>
 <feb-state>*feb-state*</feb-state>
 <feb-harderror-state>*feb-harderror-state*</feb-harderror-state>
 <feb-redundancy-group-feb-fpc-errors>...</feb-redundancy-group-feb-fpc-errors>
 <feb-redundancy-group-feb-fabric-plane-errors>...
 </feb-redundancy-group-feb-fabric-plane-errors>
 </feb-redundancy-group-feb-errors>
 </feb-redundancy-group-errors>

Description FEB redundancy error information for a FEB.

Contents <feb-harderror-state>—FEB hard error state.

<feb-redundancy-group-feb-fabric-plane-errors>—FEB redundancy error information for a fabric plane.

<feb-redundancy-group-feb-fpc-errors>—FEB redundancy error information for an FPC.

<feb-slot>—FEB slot.

<feb-state>—FEB state.

<feb-redundancy-group-feb-fabric-plane-errors>

Usage <feb-redundancy-group-feb-errors>
 <feb-redundancy-group-feb-fabric-plane-errors>
 <fabric-plane-number>*fabric-plane-number*</fabric-plane-number>
 <fabric-plane-status>*fabric-plane-status*</fabric-plane-status>
 </feb-redundancy-group-feb-fabric-plane-errors>
 </feb-redundancy-group-feb-errors>

Description FEB redundancy error information for a fabric plane.

Contents <fabric-plane-number>—Fabric plane number.

<fabric-plane-status>—Fabric plane status.

<feb-redundancy-group-feb-fpc-errors>

- Usage** <feb-redundancy-group-feb-errors>
 <feb-redundancy-group-feb-fpc-errors>
 <fpc-slot>*fpc-slot*</fpc-slot>
 <fpc-link-status>*fpc-link-status*</fpc-link-status>
 </feb-redundancy-group-feb-fpc-errors>
 </feb-redundancy-group-feb-errors>
- Description** FEB redundancy error information for an FPC.
- Contents** <fpc-link-status>—FPC link status.
 <fpc-slot>—FPC slot.

<feb-redundancy-group-information>

- Usage** <feb-redundancy-information>
 <feb-redundancy-group-information>
 <feb-redundancy-group-name>*feb-redundancy-group-name*
 </feb-redundancy-group-name>
 <feb-redundancy-group-description>*feb-redundancy-group-description*
 </feb-redundancy-group-description>
 <feb-redundancy-group-information-item>...
 </feb-redundancy-group-information-item>
 <feb-redundancy-autofailover>*feb-redundancy-autofailover*
 </feb-redundancy-autofailover>
 <feb-redundancy-switch-reason>*feb-redundancy-switch-reason*
 </feb-redundancy-switch-reason>
 </feb-redundancy-group-information>
 </feb-redundancy-information>
- Description** FEB redundancy information for a redundancy group.
- Contents** <feb-redundancy-autofailover>—FEB redundancy autofailover information.
 <feb-redundancy-group-description>—FEB redundancy group description.
 <feb-redundancy-group-information-item>—FEB redundancy information for a FEB.
 <feb-redundancy-group-name>—FEB redundancy group name.
 <feb-redundancy-switch-reason>—FEB redundancy reason for switchover.

<feb-redundancy-group-information-item>

Usage <feb-redundancy-group-information>
 <feb-redundancy-group-information-item>
 <feb-slot>*feb-slot*</feb-slot>
 <feb-state>*feb-state*</feb-state>
 <redundancy-priority>*redundancy-priority*</redundancy-priority>
 <connected-fpcs>*connected-fpcs*</connected-fpcs>
 <redundancy-state>*redundancy-state*</redundancy-state>
 <redundancy-state-description>*redundancy-state-description*
 </redundancy-state-description>
 </feb-redundancy-group-information-item>
 </feb-redundancy-group-information>

Description FEB redundancy information for a FEB.

Contents <connected-fpcs>—List of FPCs connected to the FEB in printable form.

<feb-slot>—FEB slot.

<feb-state>—FEB state.

<redundancy-priority>—FEB redundancy priority.

<redundancy-state>—Redundancy state.

<redundancy-state-description>—Description of redundancy state.

<feb-redundancy-information>

Usage <rpc-reply>
 <feb-redundancy-information>
 <feb-redundancy-group-information>...</feb-redundancy-group-information>
 </feb-redundancy-information>
 </rpc-reply>

Description FEB redundancy information.

Contents <feb-redundancy-group-information>—FEB redundancy information for a redundancy group.

<firmware>

- Usage** <chassis-module | chassis-sub-module>
 <firmware>
 <type>type</type>
 <firmware-version>firmware-version</firmware-version>
 </firmware>
 </chassis-module | chassis-sub-module>
- Description** No documentation is available yet.
- Contents** <firmware-version>—Firmware version string for this component.
 <type>—Type of this component.

<firmware-information>

- Usage** <multi-routing-engine-item>
 <firmware-information>
 <chassis>...</chassis>
 </firmware-information>
 </multi-routing-engine-item>
- Description** Information about component firmware versions.
- Contents** <chassis>—Hardware inventory of this chassis.

<firmware-version-mismatch>

- Usage** <system-firmware-compatibility-information>
 <firmware-version-mismatch>
 <routing-engine-software-version>routing-engine-software-version
 </routing-engine-software-version>
 <jfirmware-version>jfirmware-version</jfirmware-version>
 </firmware-version-mismatch>
 </system-firmware-compatibility-information>
- Description** Firmware version mismatch warning.
- Contents** <jfirmware-version>—JFirmware version.
 <routing-engine-software-version>—Version of software running on Routing engine.

<fm-fpc-ln>

Usage	<pre> <fm-fpc-state-information> <fm-fpc-ln> <slot>slot</slot> <fm-pfe-ln>...</fm-pfe-ln> </fm-fpc-ln> </fm-fpc-state-information> </pre>
Description	No documentation is available yet.
Contents	<p><fm-pfe-ln>—No documentation is available yet.</p> <p><slot>—No documentation is available yet.</p>

<fm-fpc-state-information>

Usage	<pre> <multi-routing-engine-item> <fm-fpc-state-information> <fm-fpc-ln>...</fm-fpc-ln> </fm-fpc-state-information> </multi-routing-engine-item> </pre>
Description	No documentation is available yet.
Contents	<fm-fpc-ln>—No documentation is available yet.

<fm-pfe-ln>

Usage	<pre> <fm-fpc-ln> <fm-pfe-ln> <pfe-slot>pfe-slot</pfe-slot> <fm-sib-ln>...</fm-sib-ln> </fm-pfe-ln> </fm-fpc-ln> </pre>
Description	No documentation is available yet.
Contents	<p><fm-sib-ln>—No documentation is available yet.</p> <p><pfe-slot>—No documentation is available yet.</p>

<fm-sib-ln>

Usage	<pre> <fm-pfe-ln> <fm-sib-ln> <sib-slot>sib-slot</sib-slot> <sib-fm-state>sib-fm-state</sib-fm-state> </fm-sib-ln> </fm-pfe-ln> </pre>
Description	No documentation is available yet.
Contents	<p><sib-fm-state>—No documentation is available yet.</p> <p><sib-slot>—No documentation is available yet.</p>

<fm-sib-state-information>

Usage	<pre> <multi-routing-engine-item> <fm-sib-state-information> <fms-sib-ln>...</fms-sib-ln> </fm-sib-state-information> </multi-routing-engine-item> </pre>
Description	No documentation is available yet.
Contents	<fms-sib-ln>—No documentation is available yet.

<fms-fpc-ln>

Usage	<pre> <fms-sib-ln> <fms-fpc-ln> <slot>slot</slot> <fms-pfe-ln>...</fms-pfe-ln> </fms-fpc-ln> </fms-sib-ln> </pre>
Description	No documentation is available yet.
Contents	<p><fms-pfe-ln>—No documentation is available yet.</p> <p><slot>—No documentation is available yet.</p>

<fms-lcc-ln>

Usage	<pre> <fms-sib-ln> fms-lcc-ln <lcc-slot>lcc-slot</lcc-slot> <fms-lcc-link-state>fms-lcc-link-state</fms-lcc-link-state> </fms-lcc-ln> </fms-sib-ln> </pre>
Description	No documentation is available yet.
Contents	<p><fms-lcc-link-state>—No documentation is available yet.</p> <p><lcc-slot>—No documentation is available yet.</p>

<fms-pfe-ln>

Usage	<pre> <fms-fpc-ln> fms-pfe-ln <pfe-slot>pfe-slot</pfe-slot> <fms-pfe-link-state>fms-pfe-link-state</fms-pfe-link-state> </fms-pfe-ln> </fms-fpc-ln> </pre>
Description	No documentation is available yet.
Contents	<p><fms-pfe-link-state>—No documentation is available yet.</p> <p><pfe-slot>—No documentation is available yet.</p>

<fms-scc-ln>

Usage	<pre> <fms-sib-ln> fms-scc-ln <fms-scc-link-state>fms-scc-link-state</fms-scc-link-state> </fms-scc-ln> </fms-sib-ln> </pre>
Description	No documentation is available yet.
Contents	<fms-scc-link-state>—No documentation is available yet.

<fms-sib-ln>

Usage	<pre> <fm-sib-state-information> fms-sib-ln <sib-slot>sib-slot</sib-slot> <sib-fm-state>sib-fm-state</sib-fm-state> <fms-fpc-ln>...</fms-fpc-ln> <fms-lcc-ln>...</fms-lcc-ln> <fms-scc-ln>...</fms-scc-ln> </fms-sib-ln> </fm-sib-state-information> </pre>
Description	No documentation is available yet.
Contents	<p><fms-fpc-ln>—No documentation is available yet.</p> <p><fms-lcc-ln>—No documentation is available yet.</p> <p><fms-scc-ln>—No documentation is available yet.</p> <p><sib-fm-state>—No documentation is available yet.</p> <p><sib-slot>—No documentation is available yet.</p>

<fpc>

Usage <fpc-information | fpc-panel>

```

<fpc>
  <slot>slot</slot>
  <logical-slot>logical-slot</logical-slot>
  <state>state</state>
  <description>description</description>
  <error-code>error-code</error-code>
  <temperature>temperature</temperature>
  <cpu-total>cpu-total</cpu-total>
  <cpu-interrupt>cpu-interrupt</cpu-interrupt>
  <cpu-less-info-str>cpu-less-info-str</cpu-less-info-str>
  <memory-dram-size>memory-dram-size</memory-dram-size>
  <memory-sram-size>memory-sram-size</memory-sram-size>
  <memory-sdram-size>memory-sdram-size</memory-sdram-size>
  <memory-rldram-size>memory-rldram-size</memory-rldram-size>
  <memory-ddr-dram-size>memory-ddr-dram-size</memory-ddr-dram-size>
  <memory-notification-sdram-size>memory-notification-sdram-size
    </memory-notification-sdram-size>
  <memory-heap-utilization>memory-heap-utilization</memory-heap-utilization>
  <memory-buffer-utilization>memory-buffer-utilization
    </memory-buffer-utilization>
  <asic-information>asic-information</asic-information>
  <start-time>start-time</start-time>
  <up-time>up-time</up-time>
  <comment>comment</comment>
  <pic>...</pic>
  <pic-detail>...</pic-detail>
  <red-led/>
  <green-led/>
</fpc>
</fpc-information | fpc-panel>

```

Description No documentation is available yet.

Contents <asic-information>—No documentation is available yet.

<comment>—No documentation is available yet.

<cpu-interrupt>—Percentage of CPU utilized by interrupt processing.

<cpu-less-info-str>—Flexible PIC Concentrator (FPC) without CPU.

<cpu-total>—Percentage of CPU utilized.

<description>—Description of this component.

<error-code>—Code resulting from major or minor error.

<green-led>—Green LED is lit.

<logical-slot>—No documentation is available yet.

<memory-buffer-utilization>—Percentage of buffer memory utilized.

<memory-ddr-dram-size>—DDR DRAM.

<memory-dram-size>—DRAM.

<memory-heap-utilization>—Percentage of heap memory utilized.

<memory-notification-sdram-size>—Notification SDRAM.

<memory-rldram-size>—RLDRAM.

<memory-sdram-size>—SDRAM.

<memory-sram-size>—SRAM.

<pic>—No documentation is available yet.

<pic-detail>—No documentation is available yet.

<red-led>—Red LED is lit.

<slot>—No documentation is available yet.

<start-time>—Time this component was started.

<state>—Status of the component.

<temperature>—Temperature of the item.

<up-time>—Length of time this component has been operational.

<fpc-feb-connectivity>

Usage <rpc-reply>
 <fpc-feb-connectivity>
 <fpc-feb-connectivity-item>...</fpc-feb-connectivity-item>
 </fpc-feb-connectivity>
 </rpc-reply>

Description Information about connectivity between FPCs and FEBs.

Contents <fpc-feb-connectivity-item>—FEB connectivity information for an FPC.

<fpc-feb-connectivity-item>

Usage <fpc-feb-connectivity>
 <fpc-feb-connectivity-item>
 <fpc-slot>*fpc-slot*</fpc-slot>
 <fpc-type>*fpc-type*</fpc-type>
 <fpc-state>*fpc-state*</fpc-state>
 <feb-slot>*feb-slot*</feb-slot>
 <no-feb-slot/>
 <feb-state>*feb-state*</feb-state>
 <fpc-link-status>*fpc-link-status*</fpc-link-status>
 </fpc-feb-connectivity-item>
 </fpc-feb-connectivity>

Description FEB connectivity information for an FPC.

Contents <feb-slot>—FEB slot.
 <feb-state>—FEB state.
 <fpc-link-status>—FPC link status.
 <fpc-slot>—FPC slot.
 <fpc-state>—FPC state.
 <fpc-type>—FPC type.
 <no-feb-slot>—No documentation is available yet.

<fpc-information>

Usage <multi-routing-engine-item>
 <fpc-information>
 <fpc>...</fpc>
 </fpc-information>
 </multi-routing-engine-item>

Description No documentation is available yet.

Contents <fpc>—No documentation is available yet.

<fpc-panel>

Usage <front-panel>
 <fpc-panel>
 <fpc>...</fpc>
 </fpc-panel>
 </front-panel>

Description State of status LEDs on the craft interface for Flexible PIC Concentrators.

Contents <fpc>—No documentation is available yet.

<fpga-registers>

- Usage** <environment-component-item>
 <fpga-registers>
 <fpga-registers-name>*fpga-registers-name*</fpga-registers-name>
 <fpga-registers-value>*fpga-registers-value*</fpga-registers-value>
 </fpga-registers>
 </environment-component-item>
- Description** FPGA register values.
- Contents** <fpga-registers-name>—No documentation is available yet.
 <fpga-registers-value>—No documentation is available yet.

<fpga-revision-detail>

- Usage** <environment-component-item>
 <fpga-revision-detail>
 <fpga-revision-name>*fpga-revision-name*</fpga-revision-name>
 <fpga-revision-value>*fpga-revision-value*</fpga-revision-value>
 </fpga-revision-detail>
 </environment-component-item>
- Description** FPGA revision in detail.
- Contents** <fpga-revision-name>—No documentation is available yet.
 <fpga-revision-value>—No documentation is available yet.

<front-panel>

- Usage** <craft-information>
 <front-panel>
 <display-panel>...</display-panel>
 <re-panel>...</re-panel>
 <alarm-indicators>...</alarm-indicators>
 <fpc-panel>...</fpc-panel>
 </front-panel>
 </craft-information>
- Description** Information from the craft interface.
- Contents** <alarm-indicators>—Information about alarms from the craft interface.
 <display-panel>—Text currently appearing on the craft interface display.
 <fpc-panel>—State of status LEDs on the craft interface for Flexible PIC Concentrators.
 <re-panel>—State of status LEDs on the craft interface for one or more Routing Engines. The front panel of each Routing Engine has the same LEDs.

<fru>

Usage <fru-information>
 <fru>
 <slot>slot</slot>
 <state>state</state>
 <up-time>up-time</up-time>
 <comment>comment</comment>
 </fru>
 </fru-information>

Description No documentation is available yet.

Contents <comment>—No documentation is available yet.

<slot>—No documentation is available yet.

<state>—Status of the component.

<up-time>—Length of time this component has been operational.

<fru-information>

Usage <rpc-reply>
 <fru-information>
 <fru>...</fru>
 </fru-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <fru>—No documentation is available yet.

<i2c-information>

Usage	<pre> <chassis chassis-module chassis-sub-module> <i2c-information> <jedec-code>jedec-code</jedec-code> <eeprom-version>eeprom-version</eeprom-version> <part-number>part-number</part-number> <serial-number>serial-number</serial-number> <model-number>model-number</model-number> <clei-code>clei-code</clei-code> <assembly-identifier>assembly-identifier</assembly-identifier> <assembly-version>assembly-version</assembly-version> <manufacture-date>manufacture-date</manufacture-date> <assembly-flags>assembly-flags</assembly-flags> <i2c-version>i2c-version</i2c-version> <i2c-identifier>i2c-identifier</i2c-identifier> <i2c-data>i2c-data</i2c-data> <board-information-record>board-information-record</board-information-record> </i2c-information> </chassis chassis-module chassis-sub-module> </pre>
Description	No documentation is available yet.
Contents	<p><assembly-flags>—No documentation is available yet.</p> <p><assembly-identifier>—No documentation is available yet.</p> <p><assembly-version>—No documentation is available yet.</p> <p><board-information-record>—Hex dump of board information record.</p> <p><clei-code>—Common Language Equipment Identifier code of this component.</p> <p><eeprom-version>—No documentation is available yet.</p> <p><i2c-data>—Hex dump of I2C data.</p> <p><i2c-identifier>—No documentation is available yet.</p> <p><i2c-version>—No documentation is available yet.</p> <p><jedec-code>—No documentation is available yet.</p> <p><manufacture-date>—Date this component was manufactured.</p> <p><model-number>—Model number of this component.</p> <p><part-number>—Part number of this component.</p> <p><serial-number>—Serial number of this component.</p>

<in-service-upgrade-fru-status>

Usage	<pre> <in-service-upgrade-status> <in-service-upgrade-fru-status> <fru-name>fru-name</fru-name> <fru-status>fru-status</fru-status> <fru-reason>fru-reason</fru-reason> <in-service-upgrade-pic-status>...</in-service-upgrade-pic-status> </in-service-upgrade-fru-status> </in-service-upgrade-status> </pre>
Description	In-Service Software Upgrade status for chassis.
Contents	<p><fru-name>—No documentation is available yet.</p> <p><fru-reason>—No documentation is available yet.</p> <p><fru-status>—No documentation is available yet.</p> <p><in-service-upgrade-pic-status>—No documentation is available yet.</p>

<in-service-upgrade-pic-status>

Usage	<pre> <in-service-upgrade-fru-status> <in-service-upgrade-pic-status> <fru-name>fru-name</fru-name> <fru-status>fru-status</fru-status> <fru-reason>fru-reason</fru-reason> </in-service-upgrade-pic-status> </in-service-upgrade-fru-status> </pre>
Description	No documentation is available yet.
Contents	<p><fru-name>—No documentation is available yet.</p> <p><fru-reason>—No documentation is available yet.</p> <p><fru-status>—No documentation is available yet.</p>

<in-service-upgrade-status>

Usage	<pre> <rpc-reply> <in-service-upgrade-status> <in-service-upgrade-fru-status>...</in-service-upgrade-fru-status> </in-service-upgrade-status> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<in-service-upgrade-fru-status>—In-Service Software Upgrade status for chassis.

<ioc-npc-connectivity>

Usage <rpc-reply>
 <ioc-npc-connectivity>
 <ioc-npc-connectivity-item>...</ioc-npc-connectivity-item>
 </ioc-npc-connectivity>
 </rpc-reply>

Description Information about connectivity between IOCs and NPCs.

Contents <ioc-npc-connectivity-item>—NPC connectivity information for an IOC.

<ioc-npc-connectivity-item>

Usage <ioc-npc-connectivity>
 <ioc-npc-connectivity-item>
 <ioc-slot>*ioc-slot*</ioc-slot>
 <ioc-type>*ioc-type*</ioc-type>
 <ioc-state>*ioc-state*</ioc-state>
 <npc-slot>*npc-slot*</npc-slot>
 <no-npc-slot/>
 <npc-state>*npc-state*</npc-state>
 <fpc-link-status>*fpc-link-status*</fpc-link-status>
 </ioc-npc-connectivity-item>
 </ioc-npc-connectivity>

Description NPC connectivity information for an IOC.

Contents <fpc-link-status>—FPC link status.

<ioc-slot>—No documentation is available yet.

<ioc-state>—IOC state.

<ioc-type>—IOC type.

<no-npc-slot>—No documentation is available yet.

<npc-slot>—No documentation is available yet.

<npc-state>—No documentation is available yet.

<lcc>

Usage	<pre> <lcc-information> <lcc> <slot>slot</slot> <state>state</state> <up-time>up-time</up-time> <comment>comment</comment> </lcc> </lcc-information> </pre>
Description	No documentation is available yet.
Contents	<p><comment>—No documentation is available yet.</p> <p><slot>—No documentation is available yet.</p> <p><state>—Status of the component.</p> <p><up-time>—Length of time this component has been operational.</p>

<lcc-information>

Usage	<pre> <rpc-reply> <lcc-information> <lcc>...</lcc> </lcc-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<lcc>—No documentation is available yet.

<marked-as-failed-source>

Usage	<pre> <marked-as-failed-source-list> <marked-as-failed-source> <source-name>source-name</source-name> </marked-as-failed-source> </marked-as-failed-source-list> </pre>
Description	No documentation is available yet.
Contents	<source-name>—Name of clock synchronization source.

<marked-as-failed-source-list>

- Usage** <clock-synchronization>
 <marked-as-failed-source-list>
 <marked-as-failed-source>...</marked-as-failed-source>
 </marked-as-failed-source-list>
 </clock-synchronization>
- Description** No documentation is available yet.
- Contents** <marked-as-failed-source>—No documentation is available yet.

<mcs>

- Usage** <mcs-panel>
 <mcs>
 <slot>slot</slot>
 <amber-led/>
 <green-led/>
 <blue-led/>
 </mcs>
 </mcs-panel>
- Description** State of the status LEDs on the faceplate of a Miscellaneous Control Subsystem.
- Contents** <amber-led>—Amber LED is lit.
- <blue-led>—Blue LED is lit.
- <green-led>—Green LED is lit.
- <slot>—No documentation is available yet.

<mcs-panel>

- Usage** <craft-information>
 <mcs-panel>
 <mcs>...</mcs>
 </mcs-panel>
 </craft-information>
- Description** State of the status LEDs on the faceplate of one or more Miscellaneous Control Subsystems.
- Contents** <mcs>—State of the status LEDs on the faceplate of a Miscellaneous Control Subsystem.

<multi-routing-engine-item>

Usage <multi-routing-engine-results>
 <multi-routing-engine-item>
 <re-name>*re-name*</re-name>
 <chassis-location-information>...</chassis-location-information>
 <chassisd-database-memory-usage>...</chassisd-database-memory-usage>
 <chassis-inventory>...</chassis-inventory>
 <environment-information>...</environment-information>
 <fpc-information>...</fpc-information>
 <spmb-information>...</spmb-information>
 <sib-information>...</sib-information>
 <fm-fpc-state-information>...</fm-fpc-state-information>
 <fm-sib-state-information>...</fm-sib-state-information>
 <scb-information>...</scb-information>
 <route-engine-information>...</route-engine-information>
 <firmware-information>...</firmware-information>
 <system-firmware-information>...</system-firmware-information>
 <system-firmware-compatibility-information>...
 </system-firmware-compatibility-information>
 </multi-routing-engine-item>
 </multi-routing-engine-results>

Description No documentation is available yet.

Contents <chassis-inventory>—No documentation is available yet.

<chassis-location-information>—No documentation is available yet.

<chassisd-database-memory-usage>—No documentation is available yet.

<environment-information>—No documentation is available yet.

<firmware-information>—Information about component firmware versions.

<fm-fpc-state-information>—No documentation is available yet.

<fm-sib-state-information>—No documentation is available yet.

<fpc-information>—No documentation is available yet.

<re-name>—No documentation is available yet.

<route-engine-information>—No documentation is available yet.

<scb-information>—No documentation is available yet.

<sib-information>—No documentation is available yet.

<spmb-information>—No documentation is available yet.

<system-firmware-compatibility-information>—Compatibility information about installed firmware version & JFirmware.

<system-firmware-information>—Information about component firmware versions.

<multi-routing-engine-results>

- Usage** <rpc-reply>
 <multi-routing-engine-results>
 <multi-routing-engine-item>...</multi-routing-engine-item>
 </multi-routing-engine-results>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <multi-routing-engine-item>—No documentation is available yet.

<pcg>

- Usage** <pcg-panel>
 <pcg>
 <slot>slot</slot>
 <amber-led/>
 <green-led/>
 <blue-led/>
 </pcg>
 </pcg-panel>
- Description** State of the status LEDs on the faceplate of a Packet Forwarding Engine Clock Generator.
- Contents** <amber-led>—Amber LED is lit.
 <blue-led>—Blue LED is lit.
 <green-led>—Green LED is lit.
 <slot>—No documentation is available yet.

<pcg-frequency>

- Usage** <environment-component-item>
 <pcg-frequency>
 <pcg-frequency-setting>pcg-frequency-setting</pcg-frequency-setting>
 <pcg-frequency-measurement>pcg-frequency-measurement
 </pcg-frequency-measurement>
 </pcg-frequency>
 </environment-component-item>
- Description** PCG Frequency.
- Contents** <pcg-frequency-measurement>—No documentation is available yet.
 <pcg-frequency-setting>—No documentation is available yet.

<pcg-panel>

Usage	<pre> <craft-information> <pcg-panel> <pcg>...</pcg> </pcg-panel> </craft-information> </pre>
Description	State of the status LEDs on the faceplate of one or more Packet Forwarding Engine Clock Generators.
Contents	<pcg>—State of the status LEDs on the faceplate of a Packet Forwarding Engine Clock Generator.

<pic>

Usage	<pre> <fpc> <pic> <pic-slot>pic-slot</pic-slot> <pic-type>pic-type</pic-type> <pic-state>pic-state</pic-state> <comment>comment</comment> </pic> </fpc> </pre>
Description	No documentation is available yet.
Contents	<p><comment>—No documentation is available yet.</p> <p><pic-slot>—No documentation is available yet.</p> <p><pic-state>—No documentation is available yet.</p> <p><pic-type>—No documentation is available yet.</p>

<pic-detail>

Usage <fpc>
 <pic-detail>
 <slot>slot</slot>
 <pic-slot>pic-slot</pic-slot>
 <pic-type>pic-type</pic-type>
 <asic-type>asic-type</asic-type>
 <comment>comment</comment>
 <pic-version>pic-version</pic-version>
 <state>state</state>
 <cpu-total>cpu-total</cpu-total>
 <cpu-interrupt>cpu-interrupt</cpu-interrupt>
 <memory-buffer-utilization>memory-buffer-utilization
 </memory-buffer-utilization>
 <memory-heap-utilization>memory-heap-utilization</memory-heap-utilization>
 <memory-dram-size>memory-dram-size</memory-dram-size>
 <cpu-sw-version>cpu-sw-version</cpu-sw-version>
 <cpu-rom-version>cpu-rom-version</cpu-rom-version>
 <up-time>up-time</up-time>
 <pic-package>pic-package</pic-package>
 <pic-clock-sync>pic-clock-sync</pic-clock-sync>
 <port-information>...</port-information>
 </pic-detail>
 </fpc>

Description No documentation is available yet.

Contents <asic-type>—Type of ASIC on the PIC.

<comment>—No documentation is available yet.

<cpu-interrupt>—Percentage of CPU utilized by interrupt processing.

<cpu-rom-version>—PIC ROM version.

<cpu-sw-version>—Version of operating system running on the PIC.

<cpu-total>—Percentage of CPU utilized.

<memory-buffer-utilization>—Percentage of buffer memory utilized.

<memory-dram-size>—DRAM.

<memory-heap-utilization>—Percentage of heap memory utilized.

<pic-clock-sync>—PIC Clock Synchronization.

<pic-package>—No documentation is available yet.

<pic-slot>—No documentation is available yet.

<pic-type>—No documentation is available yet.

<pic-version>—PIC hardware version.

<port-information>—No documentation is available yet.

<slot>—No documentation is available yet.

<state>—Status of the component.

<up-time>—Length of time this component has been operational.

<port>

Usage <port-information>
 <port>
 <port-number>*port-number*</port-number>
 <cabl-e-type>*cabl-e-type*</cabl-e-type>
 <fiber-mode>*fiber-mode*</fiber-mode>
 <sfp-vendor-name>*sfp-vendor-name*</sfp-vendor-name>
 <sfp-vendor-pno>*sfp-vendor-pno*</sfp-vendor-pno>
 <wavelength>*wavelength*</wavelength>
 </port>
 </port-information>

Description No documentation is available yet.

Contents <cabl-e-type>—Port cabl-e type.
 <fiber-mode>—Single or multi-mode.
 <port-number>—Port number on the PIC.
 <sfp-vendor-name>—SFP vendor name.
 <sfp-vendor-pno>—SFP vendor part number.
 <wavelength>—Wavelength of the optical transceiver.

<port-information>

Usage <pic-detail>
 <port-information>
 <port>...</port>
 </port-information>
 </pic-detail>

Description No documentation is available yet.

Contents <port>—No documentation is available yet.

<power-information>

- Usage** <environment-component-item>
 <power-information>
 <power-title>...</power-title>
 <voltage-title>voltage-title</voltage-title>
 <voltage>...</voltage>
 </power-information>
 </environment-component-item>
- Description** No documentation is available yet.
- Contents** <power-title>—No documentation is available yet.
 <voltage>—No documentation is available yet.
 <voltage-title>—Title for the display of voltage.

<power-management>

- Usage** <power-management-information>
 <power-management>
 <power-mgmt-device>power-mgmt-device</power-mgmt-device>
 <power-mgmt-low-power>power-mgmt-low-power</power-mgmt-low-power>
 <power-mgmt-high-power>power-mgmt-high-power</power-mgmt-high-power>
 <power-mgmt-heat>power-mgmt-heat</power-mgmt-heat>
 <power-mgmt-state>power-mgmt-state</power-mgmt-state>
 </power-management>
 </power-management-information>
- Description** Information about JSeries Power Management.
- Contents** <power-mgmt-device>—Type of device.
 <power-mgmt-heat>—Heat Rating tokens.
 <power-mgmt-high-power>—High power Rating tokens.
 <power-mgmt-low-power>—Low power Rating tokens.
 <power-mgmt-state>—Ratings exceed Chassis limits or not.

<power-management-information>

- Usage** <rpc-reply>
 <power-management-information>
 <power-management>...</power-management>
 </power-management-information>
 </rpc-reply>
- Description** All information about JSeries Power Management.
- Contents** <power-management>—Information about JSeries Power Management.

<power-supply>

Usage	<pre> <power-supply-panel> <power-supply> <slot>slot</slot> <amber-led/> <green-led/> <blue-led/> </power-supply> </power-supply-panel> </pre>
Description	State of the status LEDs on the faceplate of a power supply.
Contents	<p><amber-led>—Amber LED is lit.</p> <p><blue-led>—Blue LED is lit.</p> <p><green-led>—Green LED is lit.</p> <p><slot>—No documentation is available yet.</p>

<power-supply-panel>

Usage	<pre> <craft-information> <power-supply-panel> <power-supply>...</power-supply> </power-supply-panel> </craft-information> </pre>
Description	State of the status LEDs on the faceplate of one or more power supplies.
Contents	<power-supply>—State of the status LEDs on the faceplate of a power supply.

<power-title>

Usage	<pre> <power-information> <power-title> <power-type>power-type</power-type> <power-state>power-state</power-state> </power-title> </power-information> </pre>
Description	No documentation is available yet.
Contents	<p><power-state>—State of power.</p> <p><power-type>—Title for the display of power.</p>

<psd>

Usage	<pre> <psd-information> <psd> <slot>slot</slot> <description>description</description> <state>state</state> <up-time>up-time</up-time> <comment>comment</comment> </psd> </psd-information> </pre>
Description	No documentation is available yet.
Contents	<p><comment>—No documentation is available yet.</p> <p><description>—Description of this component.</p> <p><slot>—No documentation is available yet.</p> <p><state>—Status of the component.</p> <p><up-time>—Length of time this component has been operational.</p>

<psd-information>

Usage	<pre> <rpc-reply> <psd-information> <psd>...</psd> </psd-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<psd>—No documentation is available yet.

<re>

Usage <re-panel>
 <re>
 <slot>slot</slot>
 <ok-led/>
 <fail-led/>
 <master-led/>
 </re>
 </re-panel>

Description State of status LEDs on the craft interface for a Routing Engine. The front panel of the Routing Engine has the same LEDs.

Contents <fail-led>—Fail LED is lit.
 <master-led>—Master LED is lit.
 <ok-led>—OK LED is lit.
 <slot>—No documentation is available yet.

<re-panel>

Usage <front-panel>
 <re-panel>
 <re>...</re>
 </re-panel>
 </front-panel>

Description State of status LEDs on the craft interface for one or more Routing Engines. The front panel of each Routing Engine has the same LEDs.

Contents <re>—State of status LEDs on the craft interface for a Routing Engine. The front panel of the Routing Engine has the same LEDs.

<read-register>

Usage	<pre> <rpc-reply> <read-register> <cb-slot>cb-slot</cb-slot> <fchip-id>fchip-id</fchip-id> <address>address</address> <data>data</data> </read-register> </rpc-reply> </pre>
Description	Read switch fabric register.
Contents	<p><address>—No documentation is available yet.</p> <p><cb-slot>—No documentation is available yet.</p> <p><data>—No documentation is available yet.</p> <p><fchip-id>—F-chip id.</p>

<revision>

Usage	<pre> <environment-component-item> <revision> <revision-name>revision-name</revision-name> <revision-number>revision-number</revision-number> </revision> </environment-component-item> </pre>
Description	No documentation is available yet.
Contents	<p><revision-name>—Revision Name.</p> <p><revision-number>—Revision Number.</p>

<route-engine>

Usage <route-engine-information>
<route-engine>
 <description>*description*</description>
 <slot>*slot*</slot>
 <physical-slot>*physical-slot*</physical-slot>
 <mastership-state>*mastership-state*</mastership-state>
 <mastership-priority>*mastership-priority*</mastership-priority>
 <status>*status*</status>
 <model>*model*</model>
 <temperature>*temperature*</temperature>
 <cpu-temperature>*cpu-temperature*</cpu-temperature>
 <memory-dram-size>*memory-dram-size*</memory-dram-size>
 <memory-buffer-utilization>*memory-buffer-utilization*
 </memory-buffer-utilization>
 <cpu-user>*cpu-user*</cpu-user>
 <cpu-real-time>*cpu-real-time*</cpu-real-time>
 <cpu-background>*cpu-background*</cpu-background>
 <cpu-system>*cpu-system*</cpu-system>
 <cpu-interrupt>*cpu-interrupt*</cpu-interrupt>
 <cpu-idle>*cpu-idle*</cpu-idle>
 <serial-number>*serial-number*</serial-number>
 <start-time>*start-time*</start-time>
 <up-time>*up-time*</up-time>
 <last-reboot-reason>*last-reboot-reason*</last-reboot-reason>
 <load-average-one>*load-average-one*</load-average-one>
 <load-average-five>*load-average-five*</load-average-five>
 <load-average-fifteen>*load-average-fifteen*</load-average-fifteen>
 <bios-version>*bios-version*</bios-version>
 <bios-date>*bios-date*</bios-date>
 <bios-id>*bios-id*</bios-id>
</route-engine>
 </route-engine-information>

Description No documentation is available yet.

Contents <bios-date>—Routing engine BIOS date.

<bios-id>—Routing engine BIOS ID.

<bios-version>—Routing engine BIOS version.

<cpu-background>—Percentage of CPU utilized by background processes.

<cpu-idle>—Percentage of CPU idle time.

<cpu-interrupt>—Percentage of CPU utilized by interrupt processing.

<cpu-real-time>—Percentage of CPU utilized by real-time threads.

<cpu-system>—Percentage of CPU utilized by the kernel.

<cpu-temperature>—No documentation is available yet.

<cpu-user>—Percentage of CPU utilized by user processes.

<description>—Description of this component.

<last-reboot-reason>—Last reboot reason of routing engine.

<load-average-fifteen>—No documentation is available yet.

<load-average-five>—No documentation is available yet.

<load-average-one>—No documentation is available yet.

<mastership-priority>—Configured priority for mastership on this Routing Engine.

<mastership-state>—Current state of mastership on this Routing Engine.

<memory-buffer-utilization>—Percentage of buffer memory utilized.

<memory-dram-size>—DRAM.

<model>—No documentation is available yet.

<physical-slot>—No documentation is available yet.

<serial-number>—Serial number of this component.

<slot>—No documentation is available yet.

<start-time>—Time this component was started.

<status>—Status of clock synchronization source.

<temperature>—Temperature of the item.

<up-time>—Length of time this component has been operational.

<route-engine-information>

Usage	<pre> <multi-routing-engine-item> <route-engine-information> <route-engine>...</route-engine> </route-engine-information> </multi-routing-engine-item> </pre>
Description	No documentation is available yet.
Contents	<route-engine>—No documentation is available yet.

<scb>

Usage <scb-information>

```

  <scb>
    <slot>slot</slot>
    <state>state</state>
    <failover-count>failover-count</failover-count>
    <reset-count>reset-count</reset-count>
    <activate-count>activate-count</activate-count>
    <temperature>temperature</temperature>
    <intake-temperature>intake-temperature</intake-temperature>
    <exhaust-temperature>exhaust-temperature</exhaust-temperature>
    <exhaust-a-temperature>exhaust-a-temperature</exhaust-a-temperature>
    <exhaust-b-temperature>exhaust-b-temperature</exhaust-b-temperature>
    <spp-temperature>spp-temperature</spp-temperature>
    <spr-temperature>spr-temperature</spr-temperature>
    <cpu-total>cpu-total</cpu-total>
    <cpu-total-ukern>cpu-total-ukern</cpu-total-ukern>
    <cpu-total-rt>cpu-total-rt</cpu-total-rt>
    <cpu-interrupt>cpu-interrupt</cpu-interrupt>
    <memory-dram-size>memory-dram-size</memory-dram-size>
    <memory-sram-size>memory-sram-size</memory-sram-size>
    <memory-rldram-size>memory-rldram-size</memory-rldram-size>
    <memory-ddr-dram-size>memory-ddr-dram-size</memory-ddr-dram-size>
    <memory-heap-utilization>memory-heap-utilization</memory-heap-utilization>
    <memory-buffer-utilization>memory-buffer-utilization
      </memory-buffer-utilization>
    <asic-name>asic-name</asic-name>
    <asic-information>asic-information</asic-information>
    <start-time>start-time</start-time>
    <up-time>up-time</up-time>
    <comment>comment</comment>
  </scb>
</scb-information>

```

Description No documentation is available yet.

Contents <activate-count>—No documentation is available yet.

<asic-information>—No documentation is available yet.

<asic-name>—No documentation is available yet.

<comment>—No documentation is available yet.

<cpu-interrupt>—Percentage of CPU utilized by interrupt processing.

<cpu-total>—Percentage of CPU utilized.

<cpu-total-rt>—No documentation is available yet.

<cpu-total-ukern>—No documentation is available yet.

<exhaust-a-temperature>—Exhaust A temperature.

<exhaust-b-temperature>—Exhaust B temperature.

<exhaust-temperature>—No documentation is available yet.

<failover-count>—No documentation is available yet.

<intake-temperature>—No documentation is available yet.

<memory-buffer-utilization>—Percentage of buffer memory utilized.

<memory-ddr-dram-size>—DDR DRAM.

<memory-dram-size>—DRAM.

<memory-heap-utilization>—Percentage of heap memory utilized.

<memory-rldram-size>—RLDRAM.

<memory-sram-size>—SRAM.

<reset-count>—No documentation is available yet.

<slot>—No documentation is available yet.

<spp-temperature>—No documentation is available yet.

<spr-temperature>—No documentation is available yet.

<start-time>—Time this component was started.

<state>—Status of the component.

<temperature>—Temperature of the item.

<up-time>—Length of time this component has been operational.

<scb-information>

Usage	<pre> <multi-routing-engine-item> <scb-information> <scb-type>scb-type</scb-type> <scb>...</scb> </scb-information> </multi-routing-engine-item> </pre>
Description	No documentation is available yet.
Contents	<p><scb>—No documentation is available yet.</p> <p><scb-type>—No documentation is available yet.</p>

<scg>

Usage <scg-panel>
 <scg>
 <slot>slot</slot>
 <amber-led/>
 <green-led/>
 <blue-led/>
 </scg>
 </scg-panel>

Description State of the status LEDs on the faceplate of a SONET Clock Generator.

Contents <amber-led>—Amber LED is lit.
 <blue-led>—Blue LED is lit.
 <green-led>—Green LED is lit.
 <slot>—No documentation is available yet.

<scg-panel/>

Usage <craft-information>
 <scg-panel>
 <scg>...</scg>
 </scg-panel>
 </craft-information>

Description State of the status LEDs on the faceplate of one or more SONET ClockGenerators.

Contents <scg>—State of the status LEDs on the faceplate of a SONET Clock Generator.

<sfm>

Usage <sfm-panel>
 <sfm>
 <slot>slot</slot>
 <amber-led/>
 <green-led/>
 <blue-led/>
 </sfm>
 </sfm-panel>

Description State of the status LEDs on the faceplate of a Switching andForwarding Module.

Contents <amber-led>—Amber LED is lit.
 <blue-led>—Blue LED is lit.
 <green-led>—Green LED is lit.
 <slot>—No documentation is available yet.

<sfm-panel>

Usage	<pre> <craft-information> <sfm-panel> <sfm>...</sfm> </sfm-panel> </craft-information> </pre>
Description	State of the status LEDs on the faceplate of one or more Switching and Forwarding Modules.
Contents	<sfm>—State of the status LEDs on the faceplate of a Switching and Forwarding Module.

<sib>

Usage	<pre> <sib-information sib-panel> <sib> <slot>slot</slot> <state>state</state> <up-time>up-time</up-time> <comment>comment</comment> <ok-led/> <fail-led/> <active-led/> </sib> </sib-information sib-panel> </pre>
Description	No documentation is available yet.
Contents	<p><active-led>—Active LED is lit.</p> <p><comment>—No documentation is available yet.</p> <p><fail-led>—Fail LED is lit.</p> <p><ok-led>—OK LED is lit.</p> <p><slot>—No documentation is available yet.</p> <p><state>—Status of the component.</p> <p><up-time>—Length of time this component has been operational.</p>

<sib-information>

- Usage** <multi-routing-engine-item>
 <sib-information>
 <sib>...</sib>
 </sib-information>
 </multi-routing-engine-item>
- Description** No documentation is available yet.
- Contents** <sib>—No documentation is available yet.

<sib-panel>

- Usage** <craft-information>
 <sib-panel>
 <sib>...</sib>
 </sib-panel>
 </craft-information>
- Description** State of the status LEDs on the faceplate of one or more Switch Interface Boards. Some of the LEDs also appear on the craft interface.
- Contents** <sib>—No documentation is available yet.

<slave-registers>

- Usage** <slave-registers-information>
 <slave-registers>
 <slave-registers-name>slave-registers-name</slave-registers-name>
 <slave-registers-value>slave-registers-value</slave-registers-value>
 </slave-registers>
 </slave-registers-information>
- Description** Slave register values.
- Contents** <slave-registers-name>—No documentation is available yet.
 <slave-registers-value>—No documentation is available yet.

<slave-registers-information>

- Usage** <environment-component-item>
 <slave-registers-information>
 <slave-registers-title>slave-registers-title</slave-registers-title>
 <slave-registers>...</slave-registers>
 </slave-registers-information>
 </environment-component-item>
- Description** No documentation is available yet.
- Contents** <slave-registers>—Slave register values.
 <slave-registers-title>—Title for the dump of slave registers.

<spmb>

Usage <spmb-information>
 <spmb>
 <slot>slot</slot>
 <state>state</state>
 <cpu-total>cpu-total</cpu-total>
 <cpu-interrupt>cpu-interrupt</cpu-interrupt>
 <memory-heap-utilization>memory-heap-utilization</memory-heap-utilization>
 <memory-buffer-utilization>memory-buffer-utilization
 </memory-buffer-utilization>
 <start-time>start-time</start-time>
 <up-time>up-time</up-time>
 </spmb>
 </spmb-information>

Description No documentation is available yet.

Contents <cpu-interrupt>—Percentage of CPU utilized by interrupt processing.
 <cpu-total>—Percentage of CPU utilized.
 <memory-buffer-utilization>—Percentage of buffer memory utilized.
 <memory-heap-utilization>—Percentage of heap memory utilized.
 <slot>—No documentation is available yet.
 <start-time>—Time this component was started.
 <state>—Status of the component.
 <up-time>—Length of time this component has been operational.

<spmb-information>

Usage <multi-routing-engine-item>
 <spmb-information>
 <spmb>...</spmb>
 </spmb-information>
 </multi-routing-engine-item>

Description No documentation is available yet.

Contents <spmb>—No documentation is available yet.

<synchronization-source-list>

- Usage** <clock-synchronization>
 <synchronization-source-list>
 <current-source>...</current-source>
 <configured-source-list>...</configured-source-list>
 </synchronization-source-list>
 </clock-synchronization>
- Description** No documentation is available yet.
- Contents** <configured-source-list>—No documentation is available yet.
 <current-source>—No documentation is available yet.

<system-firmware>

- Usage** <system-firmware-information>
 <system-firmware>
 <firmware-name>*firmware-name*</firmware-name>
 <firmware-type>*firmware-type*</firmware-type>
 <firmware-tag>*firmware-tag*</firmware-tag>
 <firmware-revision>*firmware-revision*</firmware-revision>
 <firmware-revision-available>*firmware-revision-available*
 </firmware-revision-available>
 <firmware-status>*firmware-status*</firmware-status>
 <system-sub-module-firmware-list>...</system-sub-module-firmware-list>
 </system-firmware>
 </system-firmware-information>
- Description** No documentation is available yet.
- Contents** <firmware-name>—Name of this component.
 <firmware-revision>—Firmware version for this component.
 <firmware-revision-available>—Firmware version available on disk for this component.
 <firmware-status>—Firmware status for this component.
 <firmware-tag>—Multiple firmware per FRU delimiter.
 <firmware-type>—Type of this component.
 <system-sub-module-firmware-list>—No documentation is available yet.

<system-firmware-compatibility>

Usage <system-firmware-compatibility-information>
 <system-firmware-compatibility>
 <firmware-name>*firmware-name*</firmware-name>
 <firmware-type>*firmware-type*</firmware-type>
 <firmware-tag>*firmware-tag*</firmware-tag>
 <firmware-revision>*firmware-revision*</firmware-revision>
 <firmware-revision-available>*firmware-revision-available*
 </firmware-revision-available>
 <firmware-status>*firmware-status*</firmware-status>
 <firmware-action>*firmware-action*</firmware-action>
 <system-sub-module-firmware-compatibility-list>...
 </system-sub-module-firmware-compatibility-list>
 </system-firmware-compatibility>
 </system-firmware-compatibility-information>

Description Firmware compatibility information with installed JFirmware.

Contents <firmware-action>—Firmware action required for this component.

<firmware-name>—Name of this component.

<firmware-revision>—Firmware version for this component.

<firmware-revision-available>—Firmware version available on disk for this component.

<firmware-status>—Firmware status for this component.

<firmware-tag>—Multiple firmware per FRU delimiter.

<firmware-type>—Type of this component.

<system-sub-module-firmware-compatibility-list>—No documentation is available yet.

<system-firmware-compatibility-information>

Usage <multi-routing-engine-item>
 <system-firmware-compatibility-information>
 <firmware-version-mismatch>...</firmware-version-mismatch>
 <system-firmware-compatibility>...</system-firmware-compatibility>
 </system-firmware-compatibility-information>
 </multi-routing-engine-item>

Description Compatibility information about installed firmware version & JFirmware.

Contents <firmware-version-mismatch>—Firmware version mismatch warning.

<system-firmware-compatibility>—Firmware compatibility information with installed JFirmware.

<system-firmware-information>

- Usage** <multi-routing-engine-item>
 <system-firmware-information>
 <system-firmware>...</system-firmware>
 </system-firmware-information>
 </multi-routing-engine-item>
- Description** Information about component firmware versions.
- Contents** <system-firmware>—No documentation is available yet.

<system-sub-module-firmware>

- Usage** <system-sub-module-firmware-list>
 <system-sub-module-firmware>
 <firmware-name>*firmware-name*</firmware-name>
 <firmware-type>*firmware-type*</firmware-type>
 <firmware-tag>*firmware-tag*</firmware-tag>
 <firmware-revision>*firmware-revision*</firmware-revision>
 <firmware-revision-available>*firmware-revision-available*
 </firmware-revision-available>
 <firmware-status>*firmware-status*</firmware-status>
 </system-sub-module-firmware>
 </system-sub-module-firmware-list>
- Description** Firmware sub module.
- Contents** <firmware-name>—Name of this component.
- <firmware-revision>—Firmware version for this component.
- <firmware-revision-available>—Firmware version available on disk for this component.
- <firmware-status>—Firmware status for this component.
- <firmware-tag>—Multiple firmware per FRU delimiter.
- <firmware-type>—Type of this component.

<system-sub-module-firmware-compatibility>

Usage <system-sub-module-firmware-compatibility-list>
 <system-sub-module-firmware-compatibility>
 <firmware-name>firmware-name</firmware-name>
 <firmware-type>firmware-type</firmware-type>
 <firmware-tag>firmware-tag</firmware-tag>
 <firmware-revision>firmware-revision</firmware-revision>
 <firmware-revision-available>firmware-revision-available
 </firmware-revision-available>
 <firmware-status>firmware-status</firmware-status>
 <firmware-action>firmware-action</firmware-action>
 </system-sub-module-firmware-compatibility>
 </system-sub-module-firmware-compatibility-list>

Description Firmware sub module.

Contents <firmware-action>—Firmware action required for this component.

<firmware-name>—Name of this component.

<firmware-revision>—Firmware version for this component.

<firmware-revision-available>—Firmware version available on disk for this component.

<firmware-status>—Firmware status for this component.

<firmware-tag>—Multiple firmware per FRU delimiter.

<firmware-type>—Type of this component.

<system-sub-module-firmware-compatibility-list>

Usage <system-firmware-compatibility>
 <system-sub-module-firmware-compatibility-list>
 <system-sub-module-firmware-compatibility>...
 </system-sub-module-firmware-compatibility>
 </system-sub-module-firmware-compatibility-list>
 </system-firmware-compatibility>

Description No documentation is available yet.

Contents <system-sub-module-firmware-compatibility>—Firmware sub module.

<system-sub-module-firmware-list>

Usage <system-firmware>
 <system-sub-module-firmware-list>
 <system-sub-module-firmware>...</system-sub-module-firmware>
 </system-sub-module-firmware-list>
 </system-firmware>

Description No documentation is available yet.

Contents <system-sub-module-firmware>—Firmware sub module.

<temperature-reading>

Usage <environment-component-item>
 <temperature-reading>
 <temperature-name>temperature-name</temperature-name>
 <temperature>temperature</temperature>
 </temperature-reading>
 </environment-component-item>

Description No documentation is available yet.

Contents <temperature>—Temperature of the item.

<temperature-name>—No documentation is available yet.

<temperature-threshold>

Usage <temperature-threshold-information>
 <temperature-threshold>
 <name>*name*</name>
 <fan-normal-speed>*fan-normal-speed*</fan-normal-speed>
 <fan-high-speed>*fan-high-speed*</fan-high-speed>
 <yellow-alarm>*yellow-alarm*</yellow-alarm>
 <bad-fan-yellow-alarm>*bad-fan-yellow-alarm*</bad-fan-yellow-alarm>
 <red-alarm>*red-alarm*</red-alarm>
 <bad-fan-red-alarm>*bad-fan-red-alarm*</bad-fan-red-alarm>
 <temperature-threshold-information-item>*temperature-threshold-information-item*
 </temperature-threshold-information-item>
 </temperature-threshold>
 </temperature-threshold-information>

Description Temperature threshold information for a component on the routing platform.

Contents <bad-fan-red-alarm>—Temperature above which red alarm is raised if one or more fans are bad.

<bad-fan-yellow-alarm>—Temperature above which yellow alarm is raised if one or more fans are bad.

<fan-high-speed>—Temperature above which fans are set to high speed.

<fan-normal-speed>—Temperature above which fans are set to normal speed.

<name>—Name of this component.

<red-alarm>—Temperature above which red alarm is raised.

<temperature-threshold-information-item>—No documentation is available yet.

<yellow-alarm>—Temperature above which yellow alarm is raised.

<temperature-threshold-information>

Usage <rpc-reply>
 <temperature-threshold-information>
 <temperature-threshold>...</temperature-threshold>
 </temperature-threshold-information>
 </rpc-reply>

Description Information about the temperature threshold settings for components in the routing platform.

Contents <temperature-threshold>—Temperature threshold information for a component on the routing platform.

<voltage>

Usage <power-information>
 <voltage>
 <reference-voltage>*reference-voltage*</reference-voltage>
 <actual-voltage>*actual-voltage*</actual-voltage>
 </voltage>
 </power-information>

Description No documentation is available yet.

Contents <actual-voltage>—Voltage of the item in mVlots.
 <reference-voltage>—Voltage of the item in Volts.

<write-register>

Usage <rpc-reply>
 <write-register>
 <cb-slot>*cb-slot*</cb-slot>
 <fchip-id>*fchip-id*</fchip-id>
 <address>*address*</address>
 <data>*data*</data>
 </write-register>
 </rpc-reply>

Description Write switch fabric register.

Contents <address>—No documentation is available yet.
 <cb-slot>—No documentation is available yet.
 <data>—No documentation is available yet.
 <fchip-id>—F-chip id.

Summary of Class-of-Service Response Tags

This section lists JUNOS XML tags that contain operational information about class of service. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-cos>. To review the DTD for the tags, see “DTD for Class-of-Service Response Tags” on page 1687.

<adaptive-shaper>

Usage	<pre><cos-adaptive-shaper-information> <adaptive-shaper> <adaptive-shaper-name>adaptive-shaper-name</adaptive-shaper-name> <table-index>table-index</table-index> <trigger-item>...</trigger-item> </adaptive-shaper> </cos-adaptive-shaper-information></pre>
Description	Class-of-service adaptive shaper.
Contents	<p><adaptive-shaper-name>—Class-of-service adaptive shaper name.</p> <p><table-index>—Table index.</p> <p><trigger-item>—No documentation is available yet.</p>

<alias-map>

Usage	<pre><code-point-map> <alias-map> <alias-map-item>...</alias-map-item> </alias-map> </code-point-map></pre>
Description	No documentation is available yet.
Contents	<alias-map-item>—No documentation is available yet.

<alias-map-item>

Usage	<pre><alias-map> <alias-map-item> <code-point-bits>code-point-bits</code-point-bits> <code-point-alias>code-point-alias</code-point-alias> </alias-map-item> </alias-map></pre>
Description	No documentation is available yet.
Contents	<p><code-point-alias>—Class-of-service code point alias name.</p> <p><code-point-bits>—Class-of-service code point bit sequence.</p>

<channel>

Usage	<pre> <virtual-channel-group> <channel> <virtual-channel-name><i>virtual-channel-name</i></virtual-channel-name> <scheduler-map-name><i>scheduler-map-name</i></scheduler-map-name> <channel-shaping-rate><i>channel-shaping-rate</i></channel-shaping-rate> </channel> </virtual-channel-group> </pre>
Description	No documentation is available yet.
Contents	<p><channel-shaping-rate>—Class-of-service channel shaping rate.</p> <p><scheduler-map-name>—Class-of-service scheduler map name.</p> <p><virtual-channel-name>—Class-of-service virtual channel name.</p>

<classifier>

Usage	<pre> <cos-classifier-information> <classifier> <classifier-name><i>classifier-name</i></classifier-name> <code-point-type><i>code-point-type</i></code-point-type> <table-index><i>table-index</i></table-index> <classifier-map>...</classifier-map> </classifier> </cos-classifier-information> </pre>
Description	Class-of-service code point classifier.
Contents	<p><classifier-map>—No documentation is available yet.</p> <p><classifier-name>—Class-of-service classifier name.</p> <p><code-point-type>—Class-of-service code point type.</p> <p><table-index>—Table index.</p>

<classifier-map>

Usage	<pre> <classifier> <classifier-map> <classifier-map-item>...</classifier-map-item> </classifier-map> </classifier> </pre>
Description	No documentation is available yet.
Contents	<classifier-map-item>—No documentation is available yet.

<classifier-map-item>

- Usage** <classifier-map>
 <classifier-map-item>
 <code-point>*code-point*</code-point>
 <fc-name>*fc-name*</fc-name>
 <loss-priority>*loss-priority*</loss-priority>
 </classifier-map-item>
 </classifier-map>
- Description** No documentation is available yet.
- Contents** <code-point>—Class-of-service code point alias name or bits.
 <fc-name>—Class-of-service forwarding class name.
 <loss-priority>—Class-of-service loss priority.

<classifier-table>

- Usage** <cos-classifier-table-information>
 <classifier-table>
 <table-index>*table-index*</table-index>
 <number-of-entries>*number-of-entries*</number-of-entries>
 <table-type>*table-type*</table-type>
 <classifier-table-entry>...</classifier-table-entry>
 </classifier-table>
 </cos-classifier-table-information>
- Description** No documentation is available yet.
- Contents** <classifier-table-entry>—No documentation is available yet.
 <number-of-entries>—Number of entries in an output list.
 <table-index>—Table index.
 <table-type>—Table type.

<classifier-table-entry>

Usage <classifier-table>
 <classifier-table-entry>
 <table-index>*table-index*</table-index>
 <code-point>*code-point*</code-point>
 <fc-queue-number>*fc-queue-number*</fc-queue-number>
 <loss-priority>*loss-priority*</loss-priority>
 </classifier-table-entry>
 </classifier-table>

Description No documentation is available yet.

Contents <code-point>—Class-of-service code point alias name or bits.
 <fc-queue-number>—Class-of-service forwarding class queue number.
 <loss-priority>—Class-of-service loss priority.
 <table-index>—Table index.

<classifier-table-map>

Usage <cos-classifier-table-map-information>
 <classifier-table-map>
 <table-index>*table-index*</table-index>
 <table-type>*table-type*</table-type>
 <logical-interface>*logical-interface*</logical-interface>
 <logical-interface-index>*logical-interface-index*</logical-interface-index>
 </classifier-table-map>
 </cos-classifier-table-map-information>

Description No documentation is available yet.

Contents <logical-interface>—Logical interface name.
 <logical-interface-index>—Logical interface index.
 <table-index>—Table index.
 <table-type>—Table type.

<code-point-map>

- Usage** <cos-code-point-map-information>
 <code-point-map>
 <code-point-type>*code-point-type*</code-point-type>
 <alias-map>...</alias-map>
 </code-point-map>
 </cos-code-point-map-information>
- Description** Class-of-service code point alias map.
- Contents** <alias-map>—No documentation is available yet.
 <code-point-type>—Class-of-service code point type.

<cos-adaptive-shaper-information>

- Usage** <rpc-reply>
 <cos-adaptive-shaper-information>
 <adaptive-shaper>...</adaptive-shaper>
 </cos-adaptive-shaper-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <adaptive-shaper>—Class-of-service adaptive shaper.

<cos-classifier-information>

- Usage** <cos-information>
 <cos-classifier-information>
 <classifier>...</classifier>
 </cos-classifier-information>
 </cos-information>
- Description** No documentation is available yet.
- Contents** <classifier>—Class-of-service code point classifier.

<cos-classifier-table-information>

- Usage** <cos-table-information>
 <cos-classifier-table-information>
 <classifier-table>...</classifier-table>
 </cos-classifier-table-information>
 </cos-table-information>
- Description** No documentation is available yet.
- Contents** <classifier-table>—No documentation is available yet.

<cos-classifier-table-map-information>

Usage <cos-table-information>
 <cos-classifier-table-map-information>
 <classifier-table-map>...</classifier-table-map>
 </cos-classifier-table-map-information>
 </cos-table-information>

Description No documentation is available yet.

Contents <classifier-table-map>—No documentation is available yet.

<cos-code-point-map-information>

Usage <cos-information>
 <cos-code-point-map-information>
 <code-point-map>...</code-point-map>
 </cos-code-point-map-information>
 </cos-information>

Description No documentation is available yet.

Contents <code-point-map>—Class-of-service code point alias map.

<cos-drop-profile-information>

Usage <cos-information>
 <cos-drop-profile-information>
 <drop-profile>...</drop-profile>
 </cos-drop-profile-information>
 </cos-information>

Description No documentation is available yet.

Contents <drop-profile>—Class-of-service drop profile.

<cos-fabric-scheduler-map-information>

Usage <rpc-reply>
 <cos-fabric-scheduler-map-information>
 <fabric-scheduler-map>...</fabric-scheduler-map>
 </cos-fabric-scheduler-map-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <fabric-scheduler-map>—No documentation is available yet.

<cos-fabric-scheduler-map-table-information>

- Usage** <rpc-reply>
 <cos-fabric-scheduler-map-table-information>
 <fabric-scheduler-map-table>...</fabric-scheduler-map-table>
 </cos-fabric-scheduler-map-table-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <fabric-scheduler-map-table>—No documentation is available yet.

<cos-forwarding-class-information>

- Usage** <cos-information>
 <cos-forwarding-class-information>
 <fc-map>...</fc-map>
 </cos-forwarding-class-information>
 </cos-information>
- Description** No documentation is available yet.
- Contents** <fc-map>—Class-of-service forwarding class to queue mapping.

<cos-fragmentation-map-information>

- Usage** <cos-information>
 <cos-fragmentation-map-information>
 <fragmentation-map>...</fragmentation-map>
 </cos-fragmentation-map-information>
 </cos-information>
- Description** No documentation is available yet.
- Contents** <fragmentation-map>—Class-of-service fragmentation map.

<cos-information>

Usage <rpc-reply>
 <cos-information>
 <cos-forwarding-class-information>...</cos-forwarding-class-information>
 <cos-classifier-information>...</cos-classifier-information>
 <cos-loss-priority-map-information>...</cos-loss-priority-map-information>
 <cos-drop-profile-information>...</cos-drop-profile-information>
 <cos-rewrite-information>...</cos-rewrite-information>
 <cos-code-point-map-information>...</cos-code-point-map-information>
 <cos-fragmentation-map-information>...</cos-fragmentation-map-information>
 <cos-translation-table-map-information>...
 </cos-translation-table-map-information>
 </cos-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <cos-classifier-information>—No documentation is available yet.
 <cos-code-point-map-information>—No documentation is available yet.
 <cos-drop-profile-information>—No documentation is available yet.
 <cos-forwarding-class-information>—No documentation is available yet.
 <cos-fragmentation-map-information>—No documentation is available yet.
 <cos-loss-priority-map-information>—No documentation is available yet.
 <cos-rewrite-information>—No documentation is available yet.
 <cos-translation-table-map-information>—No documentation is available yet.

<cos-interface-information>

Usage <rpc-reply>
 <cos-interface-information>
 <interface-map>...</interface-map>
 </cos-interface-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <interface-map>—Class-of-service interface mappings.

<cos-interface-set-information>

- Usage** <rpc-reply>
 <cos-interface-set-information>
 <interface-set-map>...</interface-set-map>
 </cos-interface-set-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <interface-set-map>—No documentation is available yet.

<cos-l2tp-session-information>

- Usage** <rpc-reply>
 <cos-l2tp-session-information>
 <l2tp-session-map>...</l2tp-session-map>
 </cos-l2tp-session-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <l2tp-session-map>—Class-of-service L2TP session mappings.

<cos-loss-priority-map-information>

- Usage** <cos-information>
 <cos-loss-priority-map-information>
 <loss-priority-map>...</loss-priority-map>
 </cos-loss-priority-map-information>
 </cos-information>
- Description** No documentation is available yet.
- Contents** <loss-priority-map>—Class-of-service code point loss priority map.

<cos-loss-priority-map-table-binding-information>

- Usage** <cos-table-information>
 <cos-loss-priority-map-table-binding-information>
 <loss-priority-map-table-binding>...</loss-priority-map-table-binding>
 </cos-loss-priority-map-table-binding-information>
 </cos-table-information>
- Description** No documentation is available yet.
- Contents** <loss-priority-map-table-binding>—No documentation is available yet.

<cos-loss-priority-map-table-information>

- Usage** <cos-table-information>
 <cos-loss-priority-map-table-information>
 <loss-priority-map-table>...</loss-priority-map-table>
 </cos-loss-priority-map-table-information>
 </cos-table-information>
- Description** No documentation is available yet.
- Contents** <loss-priority-map-table>—No documentation is available yet.

<cos-policer-table-map-information>

- Usage** <cos-table-information>
 <cos-policer-table-map-information>
 <policer-table-map>...</policer-table-map>
 </cos-policer-table-map-information>
 </cos-table-information>
- Description** No documentation is available yet.
- Contents** <policer-table-map>—No documentation is available yet.

<cos-red-information>

- Usage** <cos-table-information>
 <cos-red-information>
 <red>...</red>
 </cos-red-information>
 </cos-table-information>
- Description** No documentation is available yet.
- Contents** <red>—No documentation is available yet.

<cos-rewrite-information>

- Usage** <cos-information>
 <cos-rewrite-information>
 <rewrite>...</rewrite>
 </cos-rewrite-information>
 </cos-information>
- Description** No documentation is available yet.
- Contents** <rewrite>—Class-of-service drop profile.

<cos-rewrite-table-information>

- Usage** <cos-table-information>
 <cos-rewrite-table-information>
 <rewrite-table>...</rewrite-table>
 </cos-rewrite-table-information>
 </cos-table-information>
- Description** No documentation is available yet.
- Contents** <rewrite-table>—No documentation is available yet.

<cos-rewrite-table-map-information>

- Usage** <cos-table-information>
 <cos-rewrite-table-map-information>
 <rewrite-table-map>...</rewrite-table-map>
 </cos-rewrite-table-map-information>
 </cos-table-information>
- Description** No documentation is available yet.
- Contents** <rewrite-table-map>—No documentation is available yet.

<cos-routing-instance-information>

- Usage** <rpc-reply>
 <cos-routing-instance-information>
 <routing-instance-map>...</routing-instance-map>
 </cos-routing-instance-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <routing-instance-map>—Mapping between class-of-service objects and routing instances.

<cos-scheduler-map-information>

- Usage** <rpc-reply>
 <cos-scheduler-map-information>
 <scheduler-map>...</scheduler-map>
 </cos-scheduler-map-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <scheduler-map>—Class-of-service scheduler map.

<cos-scheduler-map-table-information>

- Usage** <cos-table-information>
 <cos-scheduler-map-table-information>
 <policy>...</policy>
 </cos-scheduler-map-table-information>
</cos-table-information>
- Description** No documentation is available yet.
- Contents** <policy>—No documentation is available yet.

<cos-shaper-table-map-information>

- Usage** <cos-table-information>
 <cos-shaper-table-map-information>
 <shaper-table-map>...</shaper-table-map>
 </cos-shaper-table-map-information>
</cos-table-information>
- Description** No documentation is available yet.
- Contents** <shaper-table-map>—No documentation is available yet.

<cos-table-information>

Usage <rpc-reply>
 <cos-table-information>
 <cos-classifier-table-information>...</cos-classifier-table-information>
 <cos-classifier-table-map-information>...
 </cos-classifier-table-map-information>
 <cos-loss-priority-map-table-information>...
 </cos-loss-priority-map-table-information>
 <cos-loss-priority-map-table-binding-information>...
 </cos-loss-priority-map-table-binding-information>
 <cos-scheduler-map-table-information>...</cos-scheduler-map-table-information>
 <cos-red-information>...</cos-red-information>
 <cos-rewrite-table-information>...</cos-rewrite-table-information>
 <cos-rewrite-table-map-information>...</cos-rewrite-table-map-information>
 <cos-policer-table-map-information>...</cos-policer-table-map-information>
 <cos-shaper-table-map-information>...</cos-shaper-table-map-information>
 </cos-table-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <cos-classifier-table-information>—No documentation is available yet.
 <cos-classifier-table-map-information>—No documentation is available yet.
 <cos-loss-priority-map-table-binding-information>—No documentation is available yet.
 <cos-loss-priority-map-table-information>—No documentation is available yet.
 <cos-policer-table-map-information>—No documentation is available yet.
 <cos-red-information>—No documentation is available yet.
 <cos-rewrite-table-information>—No documentation is available yet.
 <cos-rewrite-table-map-information>—No documentation is available yet.
 <cos-scheduler-map-table-information>—No documentation is available yet.
 <cos-shaper-table-map-information>—No documentation is available yet.

<cos-traffic-control-profile-information>

Usage <rpc-reply>
 <cos-traffic-control-profile-information>
 <traffic-control-profile>...</traffic-control-profile>
 </cos-traffic-control-profile-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <traffic-control-profile>—Information about one or more traffic control profiles.

<cos-translation-table-information>

- Usage** <rpc-reply>
 <cos-translation-table-information>
 <translation-table>...</translation-table>
 </cos-translation-table-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <translation-table>—Class-of-service code point translation table.

<cos-translation-table-map-information>

- Usage** <cos-information>
 <cos-translation-table-map-information>
 <translation-table>...</translation-table>
 </cos-translation-table-map-information>
 </cos-information>
- Description** No documentation is available yet.
- Contents** <translation-table>—Class-of-service code point translation table.

<cos-translation-table-mapping-information>

- Usage** <rpc-reply>
 <cos-translation-table-mapping-information>
 <translation-table-mapping>...</translation-table-mapping>
 </cos-translation-table-mapping-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <translation-table-mapping>—No documentation is available yet.

<cos-virtual-channel-group-information>

- Usage** <rpc-reply>
 <cos-virtual-channel-group-information>
 <virtual-channel-group>...</virtual-channel-group>
 </cos-virtual-channel-group-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <virtual-channel-group>—Class-of-service virtual channel group.

<cos-virtual-channel-information>

- Usage** <rpc-reply>
 <cos-virtual-channel-information>
 <virtual-channel>...</virtual-channel>
 </cos-virtual-channel-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <virtual-channel>—Class-of-service virtual channel.

<drop-profile>

- Usage** <cos-drop-profile-information>
 <drop-profile>
 <profile-name>*profile-name*</profile-name>
 <profile-type>*profile-type*</profile-type>
 <table-index>*table-index*</table-index>
 <profile-map>...</profile-map>
 </drop-profile>
 </cos-drop-profile-information>
- Description** Class-of-service drop profile.
- Contents** <profile-map>—No documentation is available yet.
- <profile-name>—Class-of-service drop profile name.
- <profile-type>—Class-of-service drop profile type.
- <table-index>—Table index.

<drop-statistics>

Usage <fpc-queue-information>
 <drop-statistics>
 <drop-pkts-high>*drop-pkts-high*</drop-pkts-high>
 <drop-pkts-low>*drop-pkts-low*</drop-pkts-low>
 <drop-bytes-high>*drop-bytes-high*</drop-bytes-high>
 <drop-bytes-low>*drop-bytes-low*</drop-bytes-low>
 <drop-pps-high>*drop-pps-high*</drop-pps-high>
 <drop-pps-low>*drop-pps-low*</drop-pps-low>
 <drop-bps-high>*drop-bps-high*</drop-bps-high>
 <drop-bps-low>*drop-bps-low*</drop-bps-low>
 </drop-statistics>
 </fpc-queue-information>

Description Drop statistics.

Contents <drop-bps-high>—Dropped bytes per second count for high-priority queue.
 <drop-bps-low>—Dropped bytes per second count for low-priority queue.
 <drop-bytes-high>—Dropped byte count for high-priority queue.
 <drop-bytes-low>—Dropped byte count for low-priority queue.
 <drop-pkts-high>—Dropped packet count for high-priority queue.
 <drop-pkts-low>—Dropped packet count for low-priority queue.
 <drop-pps-high>—Dropped packets per second count for high-priority queue.
 <drop-pps-low>—Dropped packets per second count for low-priority queue.

<fabric-queue-information>

Usage <rpc-reply>
 <fabric-queue-information>
 <fpc-queue-information>...</fpc-queue-information>
 </fabric-queue-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <fpc-queue-information>—Show fabric queuing information for an FPC.

<fabric-scheduler>

Usage <fabric-scheduler-map>
<fabric-scheduler>
 <fabric-scheduler-name>*fabric-scheduler-name*</fabric-scheduler-name>
 <fabric-scheduler-index>*fabric-scheduler-index*</fabric-scheduler-index>
 <fabric-scheduler-drop-profile-ln-index>*fabric-scheduler-drop-profile-ln-index*
 </fabric-scheduler-drop-profile-ln-index>
 <fabric-scheduler-drop-profile-ln>*fabric-scheduler-drop-profile-ln*
 </fabric-scheduler-drop-profile-ln>
 <fabric-scheduler-drop-profile-lt-index>*fabric-scheduler-drop-profile-lt-index*
 </fabric-scheduler-drop-profile-lt-index>
 <fabric-scheduler-drop-profile-lt>*fabric-scheduler-drop-profile-lt*
 </fabric-scheduler-drop-profile-lt>
 <fabric-scheduler-drop-profile-hn-index>*fabric-scheduler-drop-profile-hn-index*
 </fabric-scheduler-drop-profile-hn-index>
 <fabric-scheduler-drop-profile-hn>*fabric-scheduler-drop-profile-hn*
 </fabric-scheduler-drop-profile-hn>
 <fabric-scheduler-drop-profile-ht-index>*fabric-scheduler-drop-profile-ht-index*
 </fabric-scheduler-drop-profile-ht-index>
 <fabric-scheduler-drop-profile-ht>*fabric-scheduler-drop-profile-ht*
 </fabric-scheduler-drop-profile-ht>
</fabric-scheduler>
 </fabric-scheduler-map>

Description No documentation is available yet.

Contents <fabric-scheduler-drop-profile-hn>—Class-of-service scheduler drop profile high, non-TCP.

<fabric-scheduler-drop-profile-hn-index>—Class-of-service scheduler drop profile index high, non-TCP.

<fabric-scheduler-drop-profile-ht>—Class-of-service scheduler drop profile high, TCP.

<fabric-scheduler-drop-profile-ht-index>—Class-of-service scheduler drop profile index high, TCP.

<fabric-scheduler-drop-profile-ln>—Class-of-service scheduler drop profile low, non-TCP.

<fabric-scheduler-drop-profile-ln-index>—Class-of-service scheduler drop profile index low, non-TCP.

<fabric-scheduler-drop-profile-lt>—Class-of-service scheduler drop profile low, TCP.

<fabric-scheduler-drop-profile-lt-index>—Class-of-service scheduler drop profile index low, TCP.

<fabric-scheduler-index>—Class of service scheduler index.

<fabric-scheduler-name>—Class-of-service scheduler name.

<fabric-scheduler-map>

- Usage** <cos-fabric-scheduler-map-information>
 <fabric-scheduler-map>
 <fabric-scheduler-priority>*fabric-scheduler-priority*
 </fabric-scheduler-priority>
 <fabric-scheduler>...</fabric-scheduler>
 </fabric-scheduler-map>
 </cos-fabric-scheduler-map-information>
- Description** No documentation is available yet.
- Contents** <fabric-scheduler>—No documentation is available yet.
 <fabric-scheduler-priority>—No documentation is available yet.

<fabric-scheduler-map-table>

- Usage** <cos-fabric-scheduler-map-table-information>
 <fabric-scheduler-map-table>
 <fabric-scheduler-priority>*fabric-scheduler-priority*
 </fabric-scheduler-priority>
 <fabric-scheduler-queues>*fabric-scheduler-queues*</fabric-scheduler-queues>
 <fabric-scheduler-table>...</fabric-scheduler-table>
 </fabric-scheduler-map-table>
 </cos-fabric-scheduler-map-table-information>
- Description** No documentation is available yet.
- Contents** <fabric-scheduler-priority>—No documentation is available yet.
 <fabric-scheduler-queues>—No documentation is available yet.
 <fabric-scheduler-table>—No documentation is available yet.

<fabric-scheduler-table>

Usage	<pre> <fabric-scheduler-map-table> <fabric-scheduler-table> <fabric-scheduler-index>fabric-scheduler-index</fabric-scheduler-index> <fabric-scheduler-drop-profile-hn-index>fabric-scheduler-drop-profile-hn-index </fabric-scheduler-drop-profile-hn-index> <fabric-scheduler-drop-profile-ln-index>fabric-scheduler-drop-profile-ln-index </fabric-scheduler-drop-profile-ln-index> <fabric-scheduler-drop-profile-ht-index>fabric-scheduler-drop-profile-ht-index </fabric-scheduler-drop-profile-ht-index> <fabric-scheduler-drop-profile-lt-index>fabric-scheduler-drop-profile-lt-index </fabric-scheduler-drop-profile-lt-index> </fabric-scheduler-table> </fabric-scheduler-map-table> </pre>
Description	No documentation is available yet.
Contents	<p><fabric-scheduler-drop-profile-hn-index>—Class-of-service scheduler drop profile index high, non-TCP.</p> <p><fabric-scheduler-drop-profile-ht-index>—Class-of-service scheduler drop profile index high, TCP.</p> <p><fabric-scheduler-drop-profile-ln-index>—Class-of-service scheduler drop profile index low, non-TCP.</p> <p><fabric-scheduler-drop-profile-lt-index>—Class-of-service scheduler drop profile index low, TCP.</p> <p><fabric-scheduler-index>—Class of service scheduler index.</p>

<fc-map>

Usage	<pre> <cos-forwarding-class-information> <fc-map> <fc-map-item>...</fc-map-item> </fc-map> </cos-forwarding-class-information> </pre>
Description	Class-of-service forwarding class to queue mapping.
Contents	<fc-map-item>—No documentation is available yet.

<fc-map-item>

Usage <fc-map>
 <fc-map-item>
 <fc-name>*fc-name*</fc-name>
 <fc-number>*fc-number*</fc-number>
 <fc-queue-number>*fc-queue-number*</fc-queue-number>
 <fc-rqueue-number>*fc-rqueue-number*</fc-rqueue-number>
 <fc-priority>*fc-priority*</fc-priority>
 <fc-policing-priority>*fc-policing-priority*</fc-policing-priority>
 </fc-map-item>
 </fc-map>

Description No documentation is available yet.

Contents <fc-name>—Class-of-service forwarding class name.

<fc-number>—Identifier for Class-of-service forwarding class.

<fc-policing-priority>—Class-of-service forwarding class policing priority.

<fc-priority>—Class-of-service forwarding class queue priority.

<fc-queue-number>—Class-of-service forwarding class queue number.

<fc-rqueue-number>—Class-of-service forwarding class restricted queue number.

<fpc-queue-information>

Usage <fabric-queue-information>
 <fpc-queue-information>
 <dest-fpc-index>*dest-fpc-index*</dest-fpc-index>
 <src-fpc-index>*src-fpc-index*</src-fpc-index>
 <total-statistics>...</total-statistics>
 <tx-statistics>...</tx-statistics>
 <drop-statistics>...</drop-statistics>
 </fpc-queue-information>
 </fabric-queue-information>

Description Show fabric queuing information for an FPC.

Contents <dest-fpc-index>—Destination FPC index.

<drop-statistics>—Drop statistics.

<src-fpc-index>—Source FPC index.

<total-statistics>—Total statistics.

<tx-statistics>—Tx statistics.

<fragment-map>

Usage	<pre> <fragmentation-map> <fragment-map> <fc-name>fc-name</fc-name> <fragment-threshold>fragment-threshold</fragment-threshold> <no-fragmentation/> <fragment-multilink-class>fragment-multilink-class</fragment-multilink-class> </fragment-map> </fragmentation-map> </pre>
Description	No documentation is available yet.
Contents	<p><fc-name>—Class-of-service forwarding class name.</p> <p><fragment-multilink-class>—Identifier for multilink class.</p> <p><fragment-threshold>—Fragmentation threshold.</p> <p><no-fragmentation>—Do not fragment packets of this class.</p>

<fragmentation-map>

Usage	<pre> <cos-fragmentation-map-information> <fragmentation-map> <fragmentation-map-name>fragmentation-map-name</fragmentation-map-name> <fragmentation-map-index>fragmentation-map-index</fragmentation-map-index> <fragment-map>...</fragment-map> </fragmentation-map> </cos-fragmentation-map-information> </pre>
Description	Class-of-service fragmentation map.
Contents	<p><fragment-map>—No documentation is available yet.</p> <p><fragmentation-map-index>—Index number for Class-of-service fragmentation map.</p> <p><fragmentation-map-name>—Class-of-service fragmentation map name.</p>

<i-logical-map>

Usage <interface-map | routing-instance-map>
<i-logical-map>
 <i-logical-name>*i-logical-name*</i-logical-name>
 <i-logical-index>*i-logical-index*</i-logical-index>
 <i-logical-objects>...</i-logical-objects>
 <policer-bandwidth>*policer-bandwidth*</policer-bandwidth>
 <policer-burst>*policer-burst*</policer-burst>
 <shaper-bandwidth>*shaper-bandwidth*</shaper-bandwidth>
 <shaper-burst>*shaper-burst*</shaper-burst>
 <shaping-rate>*shaping-rate*</shaping-rate>
 <burst-size>*burst-size*</burst-size>
 <input-shaping-rate>*input-shaping-rate*</input-shaping-rate>
 <input-burst-size>*input-burst-size*</input-burst-size>
</i-logical-map>
 </interface-map | routing-instance-map>

Description No documentation is available yet.

Contents <burst-size>—Class-of-service logical interface shaping burst.
 <i-logical-index>—Class-of-service logical interface index.
 <i-logical-name>—Class-of-service logical interface name.
 <i-logical-objects>—Class-of-service logical interface mappings.
 <input-burst-size>—Class-of-service logical interface input shaping burst.
 <input-shaping-rate>—Class-of-service input shaping rate.
 <policer-bandwidth>—Class-of-service logical interface policer bandwidth.
 <policer-burst>—Class-of-service logical interface policer burst.
 <shaper-bandwidth>—Class-of-service logical interface shaper bandwidth.
 <shaper-burst>—Class-of-service logical interface shaper burst.
 <shaping-rate>—Class-of-service shaping rate.

<i-logical-objects>

Usage <i-logical-map>
 <i-logical-objects>
 <i-logical-object-type>*i-logical-object-type*</i-logical-object-type>
 <i-logical-object-name>*i-logical-object-name*</i-logical-object-name>
 <i-logical-object-subtype>*i-logical-object-subtype*</i-logical-object-subtype>
 <i-logical-object-index>*i-logical-object-index*</i-logical-object-index>
 </i-logical-objects>
 </i-logical-map>

Description Class-of-service logical interface mappings.

Contents <i-logical-object-index>—Class-of-service logical interface object index.
 <i-logical-object-name>—Class-of-service logical interface object name.
 <i-logical-object-subtype>—Class-of-service logical interface object subtype.
 <i-logical-object-type>—Class-of-service logical interface object type.

<interface-map>

Usage <cos-interface-information>

```

<interface-map>
  <interface-name>interface-name</interface-name>
  <interface-index>interface-index</interface-index>
  <interface-queues-supported>interface-queues-supported
    </interface-queues-supported>
  <interface-queues-in-use>interface-queues-in-use</interface-queues-in-use>
  <interface-shaping-rate>interface-shaping-rate</interface-shaping-rate>
  <scheduler-map-name>scheduler-map-name</scheduler-map-name>
  <scheduler-map-index>scheduler-map-index</scheduler-map-index>
  <interface-input-shaping-rate>interface-input-shaping-rate
    </interface-input-shaping-rate>
  <input-scheduler-map-name>inp-sch-map-name</input-scheduler-map-name>
  <input-scheduler-map-index>input-scheduler-map-index
    </input-scheduler-map-index>
  <chassis-scheduler-map-name>chassis-scheduler-map-name
    </chassis-scheduler-map-name>
  <chassis-scheduler-map-index>chassis-scheduler-map-index
    </chassis-scheduler-map-index>
  <input-traffic-control-profile-name>input-traffic-control-profile-name
    </input-traffic-control-profile-name>
  <input-traffic-control-profile-index>input-traffic-control-profile-index
    </input-traffic-control-profile-index>
  <output-traffic-control-profile-name>output-traffic-control-profile-name
    </output-traffic-control-profile-name>
  <output-traffic-control-profile-index>output-traffic-control-profile-index
    </output-traffic-control-profile-index>
  <i-logical-map>...</i-logical-map>
</interface-map>
</cos-interface-information>

```

Description Class-of-service interface mappings.

Contents <chassis-scheduler-map-index>—Index number for Class-of-service chassis scheduler map.

<chassis-scheduler-map-name>—Class-of-service chassis scheduler map name.

<i-logical-map>—No documentation is available yet.

<input-scheduler-map-index>—Index number for Class-of-service input scheduler map.

<input-scheduler-map-name>—Class-of-service input scheduler map name.

<input-traffic-control-profile-index>—Index number for Class-of-service input traffic control profile.

<input-traffic-control-profile-name>—Class-of-service input traffic control profile name.

<interface-index>—Class-of-service interface index.

<interface-input-shaping-rate>—Class-of-service interface input shaping rate.

<interface-name>—Class-of-service interface name.

<interface-queues-in-use>—Number of queues in use on this interface.

<interface-queues-supported>—Number of queues supported on this interface.

<interface-shaping-rate>—Class-of-service interface shaping rate.

<output-traffic-control-profile-index>—Index number for Class-of-service output traffic control profile.

<output-traffic-control-profile-name>—Class-of-service output traffic control profile name.

<scheduler-map-index>—Class-of-service scheduler map index.

<scheduler-map-name>—Class-of-service scheduler map name.

<interface-set-map>

Usage <cos-interface-set-information>
 <interface-set-map>
 <interface-set-name>*interface-set-name*</interface-set-name>
 <interface-set-index>*interface-set-index*</interface-set-index>
 <interface-name>*interface-name*</interface-name>
 <interface-index>*interface-index*</interface-index>
 <interface-queues-supported>*interface-queues-supported*
 </interface-queues-supported>
 <interface-queues-in-use>*interface-queues-in-use*</interface-queues-in-use>
 <output-traffic-control-profile-name>*output-traffic-control-profile-name*
 </output-traffic-control-profile-name>
 <output-traffic-control-profile-index>*output-traffic-control-profile-index*
 </output-traffic-control-profile-index>
 <input-traffic-control-profile-name>*input-traffic-control-profile-name*
 </input-traffic-control-profile-name>
 <input-traffic-control-profile-index>*input-traffic-control-profile-index*
 </input-traffic-control-profile-index>
 </interface-set-map>
 </cos-interface-set-information>

Description No documentation is available yet.

Contents <input-traffic-control-profile-index>—Index number for Class-of-service input traffic control profile.

<input-traffic-control-profile-name>—Class-of-service input traffic control profile name.

<interface-index>—Class-of-service interface index.

<interface-name>—Class-of-service interface name.

<interface-queues-in-use>—Number of queues in use on this interface.

<interface-queues-supported>—Number of queues supported on this interface.

<interface-set-index>—Class-of-service logical interface index.

<interface-set-name>—Class-of-service interface-set name.

<output-traffic-control-profile-index>—Index number for Class-of-service output traffic control profile.

<output-traffic-control-profile-name>—Class-of-service output traffic control profile name.

<l2tp-session-map>

Usage <cos-l2tp-session-information>
<l2tp-session-map>
 <interface-name>*interface-name*</interface-name>
 <interface-index>*interface-index*</interface-index>
 <interface-queues-supported>*interface-queues-supported*
 </interface-queues-supported>
 <interface-queues-in-use>*interface-queues-in-use*</interface-queues-in-use>
 <l2tp-session-username>*l2tp-session-username*</l2tp-session-username>
 <l2tp-session-index>*l2tp-session-index*</l2tp-session-index>
 <traffic-control-profile-name>*traffic-control-profile-name*
 </traffic-control-profile-name>
 <traffic-control-profile-index>*traffic-control-profile-index*
 </traffic-control-profile-index>
 <scheduler-map-name>*scheduler-map-name*</scheduler-map-name>
 <scheduler-map-index>*scheduler-map-index*</scheduler-map-index>
 <shaping-rate>*shaping-rate*</shaping-rate>
 <guaranteed-rate>*guaranteed-rate*</guaranteed-rate>
 <delay-buffer-rate>*delay-buffer-rate*</delay-buffer-rate>
 <encapsulation-overhead>*encapsulation-overhead*</encapsulation-overhead>
 <cell-overhead>*cell-overhead*</cell-overhead>
</l2tp-session-map>
 </cos-l2tp-session-information>

Description Class-of-service L2TP session mappings.

Contents <cell-overhead>—Class-of-service Cell Overhead.
 <delay-buffer-rate>—Class-of-service delay buffer rate.
 <encapsulation-overhead>—Class-of-service Encapsulation Overhead.
 <guaranteed-rate>—Class-of-service guaranteed rate.
 <interface-index>—Class-of-service interface index.
 <interface-name>—Class-of-service interface name.
 <interface-queues-in-use>—Number of queues in use on this interface.
 <interface-queues-supported>—Number of queues supported on this interface.
 <l2tp-session-index>—Class-of-service session index.
 <l2tp-session-username>—Class-of-service session username.
 <scheduler-map-index>—Class-of-service scheduler map index.
 <scheduler-map-name>—Class-of-service scheduler map name.
 <shaping-rate>—Class-of-service shaping rate.
 <traffic-control-profile-index>—Index number for Class-of-service traffic control profile.

<traffic-control-profile-name>—Class-of-service traffic control profile name.

<loss-priority-map>

Usage <cos-loss-priority-map-information>
 <loss-priority-map>
 <loss-priority-map-name>*loss-priority-map-name*</loss-priority-map-name>
 <code-point-type>*code-point-type*</code-point-type>
 <table-index>*table-index*</table-index>
 <loss-priority-map-table>...</loss-priority-map-table>
 </loss-priority-map>
 </cos-loss-priority-map-information>

Description Class-of-service code point loss priority map.

Contents <code-point-type>—Class-of-service code point type.

<loss-priority-map-name>—Name of class-of-service loss priority map.

<loss-priority-map-table>—No documentation is available yet.

<table-index>—Table index.

<loss-priority-map-item>

Usage <loss-priority-map-table>
 <loss-priority-map-item>
 <code-point>*code-point*</code-point>
 <loss-priority>*loss-priority*</loss-priority>
 </loss-priority-map-item>
 </loss-priority-map-table>

Description No documentation is available yet.

Contents <code-point>—Class-of-service code point alias name or bits.

<loss-priority>—Class-of-service loss priority.

<loss-priority-map-table>

- Usage** <loss-priority-map | cos-loss-priority-map-table-information>
<loss-priority-map-table>
 <loss-priority-map-item>...</loss-priority-map-item>
 <table-index>*table-index*</table-index>
 <number-of-entries>*number-of-entries*</number-of-entries>
 <table-type>*table-type*</table-type>
 <loss-priority-map-table-entry>...</loss-priority-map-table-entry>
</loss-priority-map-table>
 </loss-priority-map | cos-loss-priority-map-table-information>
- Description** No documentation is available yet.
- Contents** <loss-priority-map-item>—No documentation is available yet.
- <loss-priority-map-table-entry>—No documentation is available yet.
- <number-of-entries>—Number of entries in an output list.
- <table-index>—Table index.
- <table-type>—Table type.

<loss-priority-map-table-binding>

- Usage** <cos-loss-priority-map-table-binding-information>
<loss-priority-map-table-binding>
 <table-index>*table-index*</table-index>
 <table-type>*table-type*</table-type>
 <logical-interface>*logical-interface*</logical-interface>
 <logical-interface-index>*logical-interface-index*</logical-interface-index>
</loss-priority-map-table-binding>
 </cos-loss-priority-map-table-binding-information>
- Description** No documentation is available yet.
- Contents** <logical-interface>—Logical interface name.
- <logical-interface-index>—Logical interface index.
- <table-index>—Table index.
- <table-type>—Table type.

<loss-priority-map-table-entry>

Usage <loss-priority-map-table>
 <loss-priority-map-table-entry>
 <table-index>*table-index*</table-index>
 <code-point>*code-point*</code-point>
 <loss-priority>*loss-priority*</loss-priority>
 </loss-priority-map-table-entry>
 </loss-priority-map-table>

Description No documentation is available yet.

Contents <code-point>—Class-of-service code point alias name or bits.
 <loss-priority>—Class-of-service loss priority.
 <table-index>—Table index.

<policer-table-map>

Usage <cos-policer-table-map-information>
 <policer-table-map>
 <p-interface>*p-interface*</p-interface>
 <p-interface-index>*p-interface-index*</p-interface-index>
 <policer-bandwidth>*policer-bandwidth*</policer-bandwidth>
 <policer-burst>*policer-burst*</policer-burst>
 </policer-table-map>
 </cos-policer-table-map-information>

Description No documentation is available yet.

Contents <p-interface>—No documentation is available yet.
 <p-interface-index>—No documentation is available yet.
 <policer-bandwidth>—Class-of-service logical interface policer bandwidth.
 <policer-burst>—Class-of-service logical interface policer burst.

<policy>

Usage <cos-scheduler-map-table-information>
 <policy>
 <interface>*interface*</interface>
 <interface-index>*interface-index*</interface-index>
 <policy-index>*policy-index*</policy-index>
 <policy-type>*policy-type*</policy-type>
 <policy-number-of-queues>*policy-number-of-queues*</policy-number-of-queues>
 <traffic-control-profile-name>*traffic-control-profile-name*
 </traffic-control-profile-name>
 <traffic-control-profile-index>*traffic-control-profile-index*
 </traffic-control-profile-index>
 <policy-entry>...</policy-entry>
 </policy>
 </cos-scheduler-map-table-information>

Description No documentation is available yet.

Contents <interface>—No documentation is available yet.

<interface-index>—Class-of-service interface index.

<policy-entry>—No documentation is available yet.

<policy-index>—No documentation is available yet.

<policy-number-of-queues>—Number of queues in this policy.

<policy-type>—No documentation is available yet.

<traffic-control-profile-index>—Index number for Class-of-service traffic control profile.

<traffic-control-profile-name>—Class-of-service traffic control profile name.

<policy-entry>

Usage <policy>
 <policy-entry>
 <table-index>*table-index*</table-index>
 <policy-entry-identifier>*policy-entry-identifier*</policy-entry-identifier>
 <fc-number>*fc-number*</fc-number>
 <fc-queue-number>*fc-queue-number*</fc-queue-number>
 <policy-transmit-rate>*policy-transmit-rate*</policy-transmit-rate>
 <policy-transmit-rate-percentage>*policy-transmit-rate-percentage*
 </policy-transmit-rate-percentage>
 <policy-transmit-rate-remainder>*policy-transmit-rate-remainder*
 </policy-transmit-rate-remainder>
 <policy-buffer-size-temporal>*policy-buffer-size-temporal*
 </policy-buffer-size-temporal>
 <policy-buffer-size-percentage>*policy-buffer-size-percentage*
 </policy-buffer-size-percentage>
 <policy-buffer-size-remainder>*policy-buffer-size-remainder*
 </policy-buffer-size-remainder>
 <policy-scheduling-priority>*policy-scheduling-priority*
 </policy-scheduling-priority>
 <policy-excess-priority>*policy-excess-priority*</policy-excess-priority>
 <policy-excess-rate-proportional>*policy-excess-rate-proportional*
 </policy-excess-rate-proportional>
 <policy-excess-rate-percentage>*policy-excess-rate-percentage*
 </policy-excess-rate-percentage>
 <policy-shaping-rate>*policy-shaping-rate*</policy-shaping-rate>
 <policy-shaping-rate-percentage>*policy-shaping-rate-percentage*
 </policy-shaping-rate-percentage>
 <policy-packet-loss-profile>...</policy-packet-loss-profile>
 <policy-exact>*policy-exact*</policy-exact>
 </policy-entry>
 </policy>

Description No documentation is available yet.

Contents <fc-number>—Identifier for Class-of-service forwarding class.
 <fc-queue-number>—Class-of-service forwarding class queue number.
 <policy-buffer-size-percentage>—Buffer size percentage.
 <policy-buffer-size-remainder>—Buffer size is remainder.
 <policy-buffer-size-temporal>—Buffer size in units of time.
 <policy-entry-identifier>—Policy entry ID number.
 <policy-exact>—Policy is exact Boolean.
 <policy-excess-priority>—Excess priority.
 <policy-excess-rate-percentage>—Excess rate as percentage.
 <policy-excess-rate-proportional>—Excess rate as proportion.

<policy-packet-loss-profile>—No documentation is available yet.

<policy-scheduling-priority>—Scheduling priority.

<policy-shaping-rate>—Shaping rate.

<policy-shaping-rate-percentage>—Shaping rate as percentage.

<policy-transmit-rate>—Transmit rate.

<policy-transmit-rate-percentage>—Transmit rate percentage.

<policy-transmit-rate-remainder>—Transmit rate is remainder.

<table-index>—Table index.

<policy-packet-loss-profile>

Usage <policy-entry>

<policy-packet-loss-profile>

<high-drop-profile-identifier>*high-drop-profile-identifier*

</high-drop-profile-identifier>

<medium-drop-profile-identifier>*medium-drop-profile-identifier*

</medium-drop-profile-identifier>

<low-drop-profile-identifier>*low-drop-profile-identifier*

</low-drop-profile-identifier>

<medium-high-drop-profile-identifier>*medium-high-drop-profile-identifier*

</medium-high-drop-profile-identifier>

<medium-low-drop-profile-identifier>*medium-low-drop-profile-identifier*

</medium-low-drop-profile-identifier>

<tcp-high-drop-profile-identifier>*tcp-high-drop-profile-identifier*

</tcp-high-drop-profile-identifier>

<tcp-low-drop-profile-identifier>*tcp-low-drop-profile-identifier*

</tcp-low-drop-profile-identifier>

</policy-packet-loss-profile>

</policy-entry>

Description No documentation is available yet.

Contents <high-drop-profile-identifier>—PLP high drop profile ID.

<low-drop-profile-identifier>—PLP low drop profile ID.

<medium-drop-profile-identifier>—PLP medium drop profile ID.

<medium-high-drop-profile-identifier>—PLP medium-high drop profile ID.

<medium-low-drop-profile-identifier>—PLP medium-low drop profile ID.

<tcp-high-drop-profile-identifier>—TCP PLP high drop profile ID.

<tcp-low-drop-profile-identifier>—TCP PLP low drop profile ID.

<profile-map>

Usage	<pre> <drop-profile> <profile-map> <profile-map-item>...</profile-map-item> </profile-map> </drop-profile> </pre>
Description	No documentation is available yet.
Contents	<profile-map-item>—No documentation is available yet.

<profile-map-item>

Usage	<pre> <profile-map> <profile-map-item> <fill-level>fill-level</fill-level> <probability>probability</probability> </profile-map-item> </profile-map> </pre>
Description	No documentation is available yet.
Contents	<fill-level>—Class-of-service drop profile fill level value. <probability>—Class-of-service drop profile probability value.

<red>

Usage	<pre> <cos-red-information> <red> <red-drop-profile-identifier>red-drop-profile-identifier </red-drop-profile-identifier> <number-of-entries>number-of-entries</number-of-entries> <red-entry>...</red-entry> </red> </cos-red-information> </pre>
Description	No documentation is available yet.
Contents	<number-of-entries>—Number of entries in an output list. <red-drop-profile-identifier>—No documentation is available yet. <red-entry>—No documentation is available yet.

<red-entry>

Usage	<pre> <red> <red-entry> <red-entry-index>red-entry-index</red-entry-index> <red-fullness>red-fullness</red-fullness> <red-drop-probability>red-drop-probability</red-drop-probability> </red-entry> </red> </pre>
Description	No documentation is available yet.
Contents	<p><red-drop-probability>—No documentation is available yet.</p> <p><red-entry-index>—No documentation is available yet.</p> <p><red-fullness>—No documentation is available yet.</p>

<rewrite>

Usage	<pre> <cos-rewrite-information> <rewrite> <rewrite-name>rewrite-name</rewrite-name> <code-point-type>code-point-type</code-point-type> <table-index>table-index</table-index> <rewrite-map>...</rewrite-map> </rewrite> </cos-rewrite-information> </pre>
Description	Class-of-service drop profile.
Contents	<p><code-point-type>—Class-of-service code point type.</p> <p><rewrite-map>—No documentation is available yet.</p> <p><rewrite-name>—Class-of-service rewrite rule name.</p> <p><table-index>—Table index.</p>

<rewrite-map>

Usage	<pre> <rewrite> <rewrite-map> <rewrite-map-item>...</rewrite-map-item> </rewrite-map> </rewrite> </pre>
Description	No documentation is available yet.
Contents	<rewrite-map-item>—No documentation is available yet.

<rewrite-map-item>

Usage	<pre> <rewrite-map> <rewrite-map-item> <code-point>code-point</code-point> <fc-name>fc-name</fc-name> <loss-priority>loss-priority</loss-priority> </rewrite-map-item> </rewrite-map> </pre>
Description	No documentation is available yet.
Contents	<p><code-point>—Class-of-service code point alias name or bits.</p> <p><fc-name>—Class-of-service forwarding class name.</p> <p><loss-priority>—Class-of-service loss priority.</p>

<rewrite-table>

Usage	<pre> <cos-rewrite-table-information> <rewrite-table> <table-index>table-index</table-index> <number-of-entries>number-of-entries</number-of-entries> <table-type>table-type</table-type> <rewrite-table-entry>...</rewrite-table-entry> </rewrite-table> </cos-rewrite-table-information> </pre>
Description	No documentation is available yet.
Contents	<p><number-of-entries>—Number of entries in an output list.</p> <p><rewrite-table-entry>—No documentation is available yet.</p> <p><table-index>—Table index.</p> <p><table-type>—Table type.</p>

<rewrite-table-entry>

Usage <rewrite-table>
 <rewrite-table-entry>
 <fc-queue-number>*fc-queue-number*</fc-queue-number>
 <rewrite-low-codepoint>*rewrite-low-codepoint*</rewrite-low-codepoint>
 <rewrite-low-enable-state>*rewrite-low-enable-state*</rewrite-low-enable-state>
 <rewrite-high-codepoint>*rewrite-high-codepoint*</rewrite-high-codepoint>
 <rewrite-high-enable-state>*rewrite-high-enable-state*
 </rewrite-high-enable-state>
 <rewrite-medium-codepoint>*rw-medium-codepoint*</rewrite-medium-codepoint>
 <rewrite-medium-enable-state>*rewrite-medium-enable-state*
 </rewrite-medium-enable-state>
 <rewrite-medium-low-codepoint>*rewrite-medium-low-codepoint*
 </rewrite-medium-low-codepoint>
 <rewrite-medium-low-enable-state>*rewrite-medium-low-enable-state*
 </rewrite-medium-low-enable-state>
 <rewrite-medium-high-codepoint>*rewrite-medium-high-codepoint*
 </rewrite-medium-high-codepoint>
 <rewrite-medium-high-enable-state>*rewrite-medium-high-enable-state*
 </rewrite-medium-high-enable-state>
 </rewrite-table-entry>
 </rewrite-table>

Description No documentation is available yet.

Contents <fc-queue-number>—Class-of-service forwarding class queue number.

<rewrite-high-codepoint>—High loss-priority code point.

<rewrite-high-enable-state>—Rewrite state for loss-priority high.

<rewrite-low-codepoint>—Low loss-priority code point.

<rewrite-low-enable-state>—Rewrite state for loss-priority low.

<rewrite-medium-codepoint>—Medium loss-priority code point.

<rewrite-medium-enable-state>—Rewrite state for loss-priority medium.

<rewrite-medium-high-codepoint>—Medium-high loss-priority code point.

<rewrite-medium-high-enable-state>—Rewrite state for loss-priority medium-high.

<rewrite-medium-low-codepoint>—Medium-low loss-priority code point.

<rewrite-medium-low-enable-state>—Rewrite state for loss-priority medium-low.

<rewrite-table-map>

Usage <cos-rewrite-table-map-information>
 <rewrite-table-map>
 <table-index>*table-index*</table-index>
 <table-type>*table-type*</table-type>
 <logical-interface>*logical-interface*</logical-interface>
 <logical-interface-index>*logical-interface-index*</logical-interface-index>
 </rewrite-table-map>
 </cos-rewrite-table-map-information>

Description No documentation is available yet.

Contents <logical-interface>—Logical interface name.
 <logical-interface-index>—Logical interface index.
 <table-index>—Table index.
 <table-type>—Table type.

<routing-instance-map>

Usage <cos-routing-instance-information>
 <routing-instance-map>
 <routing-instance-name>*routing-instance-name*</routing-instance-name>
 <i-logical-map>...</i-logical-map>
 </routing-instance-map>
 </cos-routing-instance-information>

Description Mapping between class-of-service objects and routing instances.

Contents <i-logical-map>—No documentation is available yet.
 <routing-instance-name>—Name of class-of-service routing instance.

<scheduler>

```

Usage <scheduler-map>
      <scheduler>
        <fc-name>fc-name</fc-name>
        <scheduler-name>scheduler-name</scheduler-name>
        <scheduler-index>scheduler-index</scheduler-index>
        <scheduler-tx-rate>scheduler-tx-rate</scheduler-tx-rate>
        <scheduler-tx-limit>scheduler-tx-limit</scheduler-tx-limit>
        <scheduler-buffer-size>scheduler-buffer-size</scheduler-buffer-size>
        <scheduler-priority>scheduler-priority</scheduler-priority>
        <scheduler-excess-priority>scheduler-excess-priority
          </scheduler-excess-priority>
        <scheduler-shaping-rate>scheduler-shaping-rate</scheduler-shaping-rate>
        <scheduler-excess-rate>scheduler-excess-rate</scheduler-excess-rate>
        <scheduler-drop-profile-ln-index>scheduler-drop-profile-ln-index
          </scheduler-drop-profile-ln-index>
        <scheduler-drop-profile-ln>scheduler-drop-profile-ln
          </scheduler-drop-profile-ln>
        <scheduler-drop-profile-lt-index>scheduler-drop-profile-lt-index
          </scheduler-drop-profile-lt-index>
        <scheduler-drop-profile-lt>scheduler-drop-profile-lt
          </scheduler-drop-profile-lt>
        <scheduler-drop-profile-hn-index>scheduler-drop-profile-hn-index
          </scheduler-drop-profile-hn-index>
        <scheduler-drop-profile-hn>scheduler-drop-profile-hn
          </scheduler-drop-profile-hn>
        <scheduler-drop-profile-ht-index>scheduler-drop-profile-ht-index
          </scheduler-drop-profile-ht-index>
        <scheduler-drop-profile-ht>scheduler-drop-profile-ht
          </scheduler-drop-profile-ht>
        <scheduler-drop-profile-la-index>scheduler-drop-profile-la-index
          </scheduler-drop-profile-la-index>
        <scheduler-drop-profile-la>scheduler-drop-profile-la
          </scheduler-drop-profile-la>
        <scheduler-drop-profile-mla-index>scheduler-drop-profile-mla-index
          </scheduler-drop-profile-mla-index>
        <scheduler-drop-profile-mla>scheduler-drop-profile-mla
          </scheduler-drop-profile-mla>
        <scheduler-drop-profile-mha-index>scheduler-drop-profile-mha-index
          </scheduler-drop-profile-mha-index>
        <scheduler-drop-profile-mha>scheduler-drop-profile-mha
          </scheduler-drop-profile-mha>
        <scheduler-drop-profile-ma-index>scheduler-drop-profile-ma-index
          </scheduler-drop-profile-ma-index>
        <scheduler-drop-profile-ma>scheduler-drop-profile-ma
          </scheduler-drop-profile-ma>
        <scheduler-drop-profile-ha-index>scheduler-drop-profile-ha-index
          </scheduler-drop-profile-ha-index>
        <scheduler-drop-profile-ha>scheduler-drop-profile-ha
          </scheduler-drop-profile-ha>
      </scheduler>
    </scheduler-map>

```

Description No documentation is available yet.

Contents

- <fc-name>—Class-of-service forwarding class name.
- <scheduler-buffer-size>—Class-of-service scheduler buffer size.
- <scheduler-drop-profile-ha>—Class-of-service scheduler drop profile high.
- <scheduler-drop-profile-ha-index>—Class-of-service scheduler drop profile index high.
- <scheduler-drop-profile-hn>—Class-of-service scheduler drop profile high, non-TCP.
- <scheduler-drop-profile-hn-index>—Class-of-service scheduler drop profile index high, non-TCP.
- <scheduler-drop-profile-ht>—Class-of-service scheduler drop profile high, TCP.
- <scheduler-drop-profile-ht-index>—Class-of-service scheduler drop profile index high, TCP.
- <scheduler-drop-profile-la>—Class-of-service scheduler drop profile low.
- <scheduler-drop-profile-la-index>—Class-of-service scheduler drop profile index low.
- <scheduler-drop-profile-ln>—Class-of-service scheduler drop profile low, non-TCP.
- <scheduler-drop-profile-ln-index>—Class-of-service scheduler drop profile index low, non-TCP.
- <scheduler-drop-profile-lt>—Class-of-service scheduler drop profile low, TCP.
- <scheduler-drop-profile-lt-index>—Class-of-service scheduler drop profile index low, TCP.
- <scheduler-drop-profile-ma>—Class-of-service scheduler drop profile medium.
- <scheduler-drop-profile-ma-index>—Class-of-service scheduler drop profile index medium.
- <scheduler-drop-profile-mha>—Class-of-service scheduler drop profile medium-high.
- <scheduler-drop-profile-mha-index>—Class-of-service scheduler drop profile index medium-high.
- <scheduler-drop-profile-mla>—Class-of-service scheduler drop profile medium-low.
- <scheduler-drop-profile-mla-index>—Class-of-service scheduler drop profile index medium-low.
- <scheduler-excess-priority>—Class-of-service scheduler excess priority.
- <scheduler-excess-rate>—Class-of-service scheduler excess rate.
- <scheduler-index>—Class of service scheduler index.
- <scheduler-name>—Class-of-service scheduler name.

<scheduler-priority>—Class-of-service scheduler priority.

<scheduler-shaping-rate>—Class-of-service scheduler shaping rate.

<scheduler-tx-limit>—Class-of-service scheduler transmit limit.

<scheduler-tx-rate>—Class-of-service scheduler transmit rate.

<scheduler-map>

Usage <cos-scheduler-map-information>
 <scheduler-map>
 <scheduler-map-name>*scheduler-map-name*</scheduler-map-name>
 <scheduler-map-index>*scheduler-map-index*</scheduler-map-index>
 <scheduler>...</scheduler>
 </scheduler-map>
 </cos-scheduler-map-information>

Description Class-of-service scheduler map.

Contents <scheduler>—No documentation is available yet.
 <scheduler-map-index>—Class-of-service scheduler map index.
 <scheduler-map-name>—Class-of-service scheduler map name.

<shaper-table-map>

Usage <cos-shaper-table-map-information>
 <shaper-table-map>
 <s-interface>*s-interface*</s-interface>
 <s-interface-index>*s-interface-index*</s-interface-index>
 <shaper-bandwidth>*shaper-bandwidth*</shaper-bandwidth>
 <shaper-burst>*shaper-burst*</shaper-burst>
 </shaper-table-map>
 </cos-shaper-table-map-information>

Description No documentation is available yet.

Contents <s-interface>—No documentation is available yet.
 <s-interface-index>—No documentation is available yet.
 <shaper-bandwidth>—Class-of-service logical interface shaper bandwidth.
 <shaper-burst>—Class-of-service logical interface shaper burst.

<total-statistics>

Usage <fpc-queue-information>
 <total-statistics>
 <total-pkts-high>*total-pkts-high*</total-pkts-high>
 <total-pkts-low>*total-pkts-low*</total-pkts-low>
 <total-bytes-high>*total-bytes-high*</total-bytes-high>
 <total-bytes-low>*total-bytes-low*</total-bytes-low>
 <total-pps-high>*total-pps-high*</total-pps-high>
 <total-pps-low>*total-pps-low*</total-pps-low>
 <total-bps-high>*total-bps-high*</total-bps-high>
 <total-bps-low>*total-bps-low*</total-bps-low>
 </total-statistics>
 </fpc-queue-information>

Description Total statistics.

Contents <total-bps-high>—Total bytes per second count for high-priority queue.
 <total-bps-low>—Total bytes per second count for low-priority queue.
 <total-bytes-high>—Total byte count for high-priority queue.
 <total-bytes-low>—Total byte count for low-priority queue.
 <total-pkts-high>—Total packet count for high-priority queue.
 <total-pkts-low>—Total packet count for low-priority queue.
 <total-pps-high>—Total packets per second count for high-priority queue.
 <total-pps-low>—Total packets per second count for low-priority queue.

<traffic-control-profile>

Usage <cos-traffic-control-profile-information>
 <traffic-control-profile>
 <traffic-control-profile-name>*traffic-control-profile-name*
 </traffic-control-profile-name>
 <scheduler-map-name>*scheduler-map-name*</scheduler-map-name>
 <shaping-rate>*shaping-rate*</shaping-rate>
 <traffic-control-profile-index>*traffic-control-profile-index*
 </traffic-control-profile-index>
 <traffic-control-profile-instance>...</traffic-control-profile-instance>
 <guaranteed-rate>*guaranteed-rate*</guaranteed-rate>
 <delay-buffer-rate>*delay-buffer-rate*</delay-buffer-rate>
 <excess-rate>*excess-rate*</excess-rate>
 </traffic-control-profile>
 </cos-traffic-control-profile-information>

Description Information about one or more traffic control profiles.

Contents <delay-buffer-rate>—Class-of-service delay buffer rate.

<excess-rate>—Class-of-service excess rate.

<guaranteed-rate>—Class-of-service guaranteed rate.

<scheduler-map-name>—Class-of-service scheduler map name.

<shaping-rate>—Class-of-service shaping rate.

<traffic-control-profile-index>—Index number for Class-of-service traffic control profile.

<traffic-control-profile-instance>—Class-of-service traffic control profile instance.

<traffic-control-profile-name>—Class-of-service traffic control profile name.

<traffic-control-profile-instance>

Usage <traffic-control-profile>
 <traffic-control-profile-instance>
 <traffic-control-profile-instance-name>*traffic-control-profile-instance-name*
 </traffic-control-profile-instance-name>
 <traffic-control-profile-instance-index>*traffic-control-profile-instance-index*
 </traffic-control-profile-instance-index>
 <instance-reference-count>*instance-reference-count*</instance-reference-count>
 </traffic-control-profile-instance>
 </traffic-control-profile>

Description Class-of-service traffic control profile instance.

Contents <instance-reference-count>—Instance reference count.

<traffic-control-profile-instance-index>—Index number for Class-of-service traffic control profile instance.

<traffic-control-profile-instance-name>—Class-of-service traffic control profile instance.

<translation-table>

Usage <cos-translation-table-map-information | cos-translation-table-information>
 <translation-table>
 <translation-table-name>*translation-table-name*</translation-table-name>
 <translation-table-type>*translation-table-type*</translation-table-type>
 <table-index>*table-index*</table-index>
 <translation-table-map>...</translation-table-map>
 <number-of-entries>*number-of-entries*</number-of-entries>
 <translation-table-entry>...</translation-table-entry>
 </translation-table>
 </cos-translation-table-map-information | cos-translation-table-information>

Description Class-of-service code point translation table.

Contents <number-of-entries>—Number of entries in an output list.

<table-index>—Table index.

<translation-table-entry>—No documentation is available yet.

<translation-table-map>—No documentation is available yet.

<translation-table-name>—Class-of-service translation table name.

<translation-table-type>—Class-of-service translation table type.

<translation-table-entry>

- Usage** <translation-table>
 <translation-table-entry>
 <table-index>*table-index*</table-index>
 <from-code-point>*from-code-point*</from-code-point>
 <to-code-point>*to-code-point*</to-code-point>
 </translation-table-entry>
 </translation-table>
- Description** No documentation is available yet.
- Contents** <from-code-point>—Class-of-service code point alias name or bits.
 <table-index>—Table index.
 <to-code-point>—Class-of-service code point alias name or bits.

<translation-table-map>

- Usage** <translation-table>
 <translation-table-map>
 <translation-table-map-item>...</translation-table-map-item>
 </translation-table-map>
 </translation-table>
- Description** No documentation is available yet.
- Contents** <translation-table-map-item>—No documentation is available yet.

<translation-table-map-item>

- Usage** <translation-table-map>
 <translation-table-map-item>
 <from-code-point>*from-code-point*</from-code-point>
 <to-code-point>*to-code-point*</to-code-point>
 </translation-table-map-item>
 </translation-table-map>
- Description** No documentation is available yet.
- Contents** <from-code-point>—Class-of-service code point alias name or bits.
 <to-code-point>—Class-of-service code point alias name or bits.

<translation-table-mapping>

Usage <cos-translation-table-mapping-information>
 <translation-table-mapping>
 <table-index>*table-index*</table-index>
 <translation-table-type>*translation-table-type*</translation-table-type>
 <logical-interface>*logical-interface*</logical-interface>
 <logical-interface-index>*logical-interface-index*</logical-interface-index>
 </translation-table-mapping>
 </cos-translation-table-mapping-information>

Description No documentation is available yet.

Contents <logical-interface>—Logical interface name.
 <logical-interface-index>—Logical interface index.
 <table-index>—Table index.
 <translation-table-type>—Class-of-service translation table type.

<trigger-item>

Usage <adaptive-shaper>
 <trigger-item>
 <trigger-type>*trigger-type*</trigger-type>
 <adaptive-shaping-rate>*adaptive-shaping-rate*</adaptive-shaping-rate>
 </trigger-item>
 </adaptive-shaper>

Description No documentation is available yet.

Contents <adaptive-shaping-rate>—Class-of-service adaptive shaping rate.
 <trigger-type>—Class-of-service adaptive shaper trigger type.

<tx-statistics>

Usage <fpc-queue-information>
 <tx-statistics>
 <tx-pkts-high>*tx-pkts-high*</tx-pkts-high>
 <tx-pkts-low>*tx-pkts-low*</tx-pkts-low>
 <tx-bytes-high>*tx-bytes-high*</tx-bytes-high>
 <tx-bytes-low>*tx-bytes-low*</tx-bytes-low>
 <tx-pps-high>*tx-pps-high*</tx-pps-high>
 <tx-pps-low>*tx-pps-low*</tx-pps-low>
 <tx-bps-high>*tx-bps-high*</tx-bps-high>
 <tx-bps-low>*tx-bps-low*</tx-bps-low>
 </tx-statistics>
 </fpc-queue-information>

Description Tx statistics.

Contents <tx-bps-high>—Transmitted bytes per second count for high-priority queue.
 <tx-bps-low>—Transmitted bytes per second count for low-priority queue.
 <tx-bytes-high>—Transmitted byte count for high-priority queue.
 <tx-bytes-low>—Transmitted byte count for low-priority queue.
 <tx-pkts-high>—Transmitted packet count for high-priority queue.
 <tx-pkts-low>—Transmitted packet count for low-priority queue.
 <tx-pps-high>—Transmitted packets per second count for high-priority queue.
 <tx-pps-low>—Transmitted packets per second count for low-priority queue.

<virtual-channel>

Usage <cos-virtual-channel-information>
 <virtual-channel>
 <virtual-channel-name>*virtual-channel-name*</virtual-channel-name>
 <table-index>*table-index*</table-index>
 </virtual-channel>
 </cos-virtual-channel-information>

Description Class-of-service virtual channel.

Contents <table-index>—Table index.
 <virtual-channel-name>—Class-of-service virtual channel name.

<virtual-channel-group>

Usage <cos-virtual-channel-group-information>
 <virtual-channel-group>
 <virtual-channel-group-name>*virtual-channel-group-name*
 </virtual-channel-group-name>
 <table-index>*table-index*</table-index>
 <channel>...</channel>
 </virtual-channel-group>
 </cos-virtual-channel-group-information>

Description Class-of-service virtual channel group.

Contents <channel>—No documentation is available yet.

 <table-index>—Table index.

 <virtual-channel-group-name>—Class-of-service virtual channel group name.

Summary of Database Replication Response Tags

This section lists JUNOS XML tags that contain operational information about data replication. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-database-replication>. To review the DTD for the tags, see “DTD for Database Replication Response Tags” on page 1701.

<database-replication-statistics-information>

Usage <rpc-reply>
 <database-replication-statistics-information>
 <dropped-connections-total>*dropped-connections-total*
 </dropped-connections-total>
 <max-buffer-count>*max-buffer-count*</max-buffer-count>
 <msg-received-bytes>*msg-received-bytes*</msg-received-bytes>
 <msgs-received-total>*msgs-received-total*</msgs-received-total>
 <msg-sent-bytes>*msg-sent-bytes*</msg-sent-bytes>
 <msgs-sent-total>*msgs-sent-total*</msgs-sent-total>
 <queue-full-total>*queue-full-total*</queue-full-total>
 <queue-max-size>*queue-max-size*</queue-max-size>
 </database-replication-statistics-information>
 </rpc-reply>

Description Statistics from the database replication.

Contents <dropped-connections-total>—Total number times connection was restarted.

 <max-buffer-count>—Maximum number of outstanding buffers.

 <msg-received-bytes>—Total number bytes received.

 <msg-sent-bytes>—Total number bytes sent.

 <msgs-received-total>—Total number messages received.

 <msgs-sent-total>—Total number messages sent.

 <queue-full-total>—Total number times queue was full.

 <queue-max-size>—Maximum size queue reached.

<database-replication-summary-information>

Usage <rpc-reply>
 <database-replication-summary-information>
 <replication-graceful-restart-type>*replication-graceful-restart-type*
 </replication-graceful-restart-type>
 <replication-mastership-type>*replication-mastership-type*
 </replication-mastership-type>
 <replication-connection-type>*replication-connection-type*
 </replication-connection-type>
 <replication-database-type>*replication-database-type*
 </replication-database-type>
 <replication-queue-type>*replication-queue-type*</replication-queue-type>
 </database-replication-summary-information>
 </rpc-reply>

Description General state information about the database replication status.

Contents <replication-connection-type>—Connection status of the database replication.
 <replication-database-type>—Synchronizing status of the database replication.
 <replication-graceful-restart-type>—Mode of the chassis graceful restart.
 <replication-mastership-type>—Mode of the database replication.
 <replication-queue-type>—Queue status of the database replication.

Summary of Data Link Switching Response Tags

This section lists JUNOS XML tags that contain operational information about data link switching (DLSw). The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-dlswd>. To review the DTD for the tags, see “DTD for Data Link Switching Response Tags” on page 1703.

<dlsw-capabilities>

Usage <dlsw-capabilities-list>
 <dlsw-capabilities>
 <peer-address>peer-address</peer-address>
 <vendor-id>vendor-id</vendor-id>
 <version-number>version-number</version-number>
 <initial-pacing-window-size>initial-pacing-window-size
 </initial-pacing-window-size>
 <version-string>version-string</version-string>
 <dlsw-capability-strings>dlsw-capability-strings</dlsw-capability-strings>
 <version-string-multi>version-string-multi</version-string-multi>
 </dlsw-capabilities>
 </dlsw-capabilities-list>

Description No documentation is available yet.

Contents <dlsw-capability-strings>—No documentation is available yet.
 <initial-pacing-window-size>—Initial pacing window size.
 <peer-address>—Peer address.
 <vendor-id>—Vendor ID.
 <version-number>—Version number.
 <version-string>—Version string.
 <version-string-multi>—No documentation is available yet.

<dlsw-capabilities-list>

Usage <rpc-reply>
 <dlsw-capabilities-list>
 <dlsw-capabilities>...</dlsw-capabilities>
 </dlsw-capabilities-list>
 </rpc-reply>

Description No documentation is available yet.

Contents <dlsw-capabilities>—No documentation is available yet.

<dlsw-circuit>

Usage <dlsw-circuit-list>
 <dlsw-circuit>
 <local-address>*local-address*</local-address>
 <lsap>*lsap*</lsap>
 <remote-address>*remote-address*</remote-address>
 <dsap>*dsap*</dsap>
 <circuit-state>*circuit-state*</circuit-state>
 <peer-address>*peer-address*</peer-address>
 <circuit-id>*circuit-id*</circuit-id>
 <circuit-uptime>*circuit-uptime*</circuit-uptime>
 <current-state-time>*current-state-time*</current-state-time>
 <max-btu-size>*max-btu-size*</max-btu-size>
 <circuit-priority>*circuit-priority*</circuit-priority>
 <dlsw-circuit-statistics>...</dlsw-circuit-statistics>
 </dlsw-circuit>
 </dlsw-circuit-list>

Description No documentation is available yet.

Contents <circuit-id>—Circuit id.
 <circuit-priority>—Circuit priority.
 <circuit-state>—Circuit state.
 <circuit-uptime>—Uptime for the circuit.
 <current-state-time>—Time since current state.
 <dlsw-circuit-statistics>—DLSw circuit statistics.
 <dsap>—DSAP.
 <local-address>—Local address.
 <lsap>—LSAP.
 <max-btu-size>—Max BTU size.
 <peer-address>—Peer address.
 <remote-address>—Remote address.

<dlsw-circuit-list>

- Usage** <rpc-reply>
 <dlsw-circuit-list>
 <dlsw-circuit>...</dlsw-circuit>
 </dlsw-circuit-list>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <dlsw-circuit>—No documentation is available yet.

<dlsw-circuit-statistics>

Usage <dlsw-circuit>
 <dlsw-circuit-statistics>
 <iframes-received>*iframes-received*</iframes-received>
 <iframes-sent>*iframes-sent*</iframes-sent>
 <ibytes-received>*ibytes-received*</ibytes-received>
 <ibytes-sent>*ibytes-sent*</ibytes-sent>
 <iframes-rejected>*iframes-rejected*</iframes-rejected>
 <ibytes-rejected>*ibytes-rejected*</ibytes-rejected>
 <iframes-retransmitted>*iframes-retransmitted*</iframes-retransmitted>
 <ibytes-retransmitted>*ibytes-retransmitted*</ibytes-retransmitted>
 <reject-sent>*reject-sent*</reject-sent>
 <reject-received>*reject-received*</reject-received>
 <xid-sent>*xid-sent*</xid-sent>
 <xid-received>*xid-received*</xid-received>
 </dlsw-circuit-statistics>
 </dlsw-circuit>

Description DLSw circuit statistics.

Contents <ibytes-received>—Number of bytes received in I-frames.
 <ibytes-rejected>—Number of bytes in the rejected I-frames.
 <ibytes-retransmitted>—Number of bytes in retransmitted I-frames.
 <ibytes-sent>—Number of bytes sent in I-frames.
 <iframes-received>—I-frames received.
 <iframes-rejected>—I-frames rejected.
 <iframes-retransmitted>—I-frames retransmitted.
 <iframes-sent>—I-frames sent.
 <reject-received>—Reject frames received.
 <reject-sent>—Reject frames sent.
 <xid-received>—XID frames received.
 <xid-sent>—XID frames sent.

<dlsw-peer>

Usage <dlsw-peer-list>
 <dlsw-peer>
 <peer-address>*peer-address*</peer-address>
 <peer-state>*peer-state*</peer-state>
 <peer-circuits>*peer-circuits*</peer-circuits>
 <local-address>*local-address*</local-address>
 <peer-uptime>*peer-uptime*</peer-uptime>
 <initial-receive-pacing>*initial-receive-pacing*</initial-receive-pacing>
 <connection-idle-timeout>*connection-idle-timeout*</connection-idle-timeout>
 <dlsw-peer-statistics>...</dlsw-peer-statistics>
 <tos-value>*tos-value*</tos-value>
 <destination-sna-interface>*destination-sna-interface*
 </destination-sna-interface>
 <peer-cost>*peer-cost*</peer-cost>
 <peer-circuit-weight>*peer-circuit-weight*</peer-circuit-weight>
 <load-balance>*load-balance*</load-balance>
 </dlsw-peer>
 </dlsw-peer-list>

Description No documentation is available yet.

Contents <connection-idle-timeout>—No circuits timeout.

<destination-sna-interface>—Name of destination interface for SNA packets.

<dlsw-peer-statistics>—DLSw Peer Statistics.

<initial-receive-pacing>—Size of initial receive pacing window.

<load-balance>—Load balance.

<local-address>—Local address.

<peer-address>—Peer address.

<peer-circuit-weight>—Peer circuit weight.

<peer-circuits>—Number of peer circuits.

<peer-cost>—Peer cost.

<peer-state>—Peer state.

<peer-uptime>—Uptime for peer connection.

<tos-value>—IP Type-of-service value.

<dlsw-peer-list>

Usage <rpc-reply>
 <dlsw-peer-list>
 <dlsw-peer>...</dlsw-peer>
 </dlsw-peer-list>
 </rpc-reply>

Description No documentation is available yet.

Contents <dlsw-peer>—No documentation is available yet.

<dlsw-peer-statistics>

Usage <dlsw-peer>
 <dlsw-peer-statistics>
 <packets-received>*packets-received*</packets-received>
 <packets-sent>*packets-sent*</packets-sent>
 <bytes-received>*bytes-received*</bytes-received>
 <bytes-sent>*bytes-sent*</bytes-sent>
 <control-packets-received>*control-packets-received*</control-packets-received>
 <control-packets-sent>*control-packets-sent*</control-packets-sent>
 <canureach-ex-received>*canureach-ex-received*</canureach-ex-received>
 <canureach-ex-sent>*canureach-ex-sent*</canureach-ex-sent>
 <icanreach-ex-received>*icanreach-ex-received*</icanreach-ex-received>
 <icanreach-ex-sent>*icanreach-ex-sent*</icanreach-ex-sent>
 </dlsw-peer-statistics>
 </dlsw-peer>

Description DLSw Peer Statistics.

Contents <bytes-received>—Bytes received.

<bytes-sent>—Bytes sent.

<canureach-ex-received>—CANUREACH_ex received.

<canureach-ex-sent>—CANUREACH_ex sent.

<control-packets-received>—Control packets received.

<control-packets-sent>—Control packets sent.

<icanreach-ex-received>—ICANREACH_ex received.

<icanreach-ex-sent>—ICANREACH_ex sent.

<packets-received>—Packets received.

<packets-sent>—Packets sent.

<dlsw-reachability>

Usage <dlsw-reachability-list>
 <dlsw-reachability>
 <mac-index>*mac-index*</mac-index>
 <mac-address>*mac-address*</mac-address>
 <mac-location>*mac-location*</mac-location>
 <remote-dlsw-address>*remote-dlsw-address*</remote-dlsw-address>
 <dlsw-peer-interface>*dlsw-peer-interface*</dlsw-peer-interface>
 </dlsw-reachability>
 </dlsw-reachability-list>

Description No documentation is available yet.

Contents <dlsw-peer-interface>—DLSw peer or interface.
 <mac-address>—MAC address.
 <mac-index>—MAC index.
 <mac-location>—MAC location.
 <remote-dlsw-address>—Remote DLSw address.

<dlsw-reachability-list>

Usage <rpc-reply>
 <dlsw-reachability-list>
 <dlsw-reachability>...</dlsw-reachability>
 </dlsw-reachability-list>
 </rpc-reply>

Description No documentation is available yet.

Contents <dlsw-reachability>—No documentation is available yet.

<llc2>

Usage <llc2-redundancy-track-interface | llc2-redundancy-track-dlsw-peer | llc2-redundancy-track-dlsw-destination | llc2-redundancy-mac-translation | llc2-redundancy | llc2-redundancy-interface-statistics>

```

<llc2>
  <interface>interface</interface>
  <track-peer>track-peer</track-peer>
  <track-destination>track-destination</track-destination>
  <track-interface>track-interface</track-interface>
  <unit>unit</unit>
  <group>group</group>
  <interface-state>interface-state</interface-state>
  <state>state</state>
  <track-interface-state>track-interface-state</track-interface-state>
  <track-interface-cost>track-interface-cost</track-interface-cost>
  <track-peer-state>track-peer-state</track-peer-state>
  <track-peer-cost>track-peer-cost</track-peer-cost>
  <track-destination-state>track-destination-state</track-destination-state>
  <track-destination-cost>track-destination-cost</track-destination-cost>
  <group-configured-priority>group-configured-priority
    </group-configured-priority>
  <group-run-priority>group-run-priority</group-run-priority>
  <local-mac>local-mac</local-mac>
  <remote-mac>remote-mac</remote-mac>
  <ifl-index>ifl-index</ifl-index>
  <advertise-interval>advertise-interval</advertise-interval>
  <advertise-timer>advertise-timer</advertise-timer>
  <preempt>preempt</preempt>
  <master-router-uptime>master-router-uptime</master-router-uptime>
  <tracking>tracking</tracking>
  <interface-ads-sent>interface-ads-sent</interface-ads-sent>
  <interface-ads-received>interface-ads-received</interface-ads-received>
  <interface-bad-ttl-value-received>interface-bad-ttl-value-received
    </interface-bad-ttl-value-received>
  <interface-bad-version-received>interface-bad-version-received
    </interface-bad-version-received>
  <interface-bad-pdu-type-received>interface-bad-pdu-type-received
    </interface-bad-pdu-type-received>
  <interface-bad-checksum-received>interface-bad-checksum-received
    </interface-bad-checksum-received>
</llc2>
</llc2-redundancy-track-interface | llc2-redundancy-track-dlsw-peer |
llc2-redundancy-track-dlsw-destination | llc2-redundancy-mac-translation |
llc2-redundancy | llc2-redundancy-interface-statistics>

```

Description No documentation is available yet.

Contents <advertise-interval>—Advertisement interval for LLC2 redundancy group.

<advertise-timer>—Advertisement timer for LLC2 redundancy group.

<group>—LLC2 redundancy group number.

<group-configured-priority>—Configured priority of LLC2 redundancy group.

<group-run-priority>—Run priority of LLC2 redundancy group.

<ifl-index>—LLC2 logical interface index number.

<interface>—Name of LLC2 Interface.

<interface-ads-received>—Number of LLC2 redundancy interface advertisements received.

<interface-ads-sent>—Number of LLC2 redundancy interface advertisements sent.

<interface-bad-checksum-received>—Number of bad checksum received for LLC2 redundancy interface.

<interface-bad-pdu-type-received>—Number of bad PDU types received for LLC2 redundancy.

<interface-bad-ttl-value-received>—Number of bad time-to-live values received for LLC2 redundancy interface.

<interface-bad-version-received>—Number of bad version numbers received for LLC2 redundancy interface.

<interface-state>—LLC2 interface state.

<local-mac>—Local MAC address entry for LLC2 redundancy group.

<master-router-uptime>—Time that LLC2 redundancy group router has been the master.

<preempt>—Preemption enablement status for LLC2 redundancy group.

<remote-mac>—Remote MAC address entry for LLC2 redundancy group.

<state>—LLC2 router state.

<track-destination>—LLC2 track dest.

<track-destination-cost>—Cost of tracking LLC2 destination.

<track-destination-state>—State of tracked LLC2 destination.

<track-interface>—Name of LLC2 interface being tracked.

<track-interface-cost>—Cost of tracking LLC2 interface.

<track-interface-state>—State of tracked LLC2 interface.

<track-peer>—LLC2 track peer.

<track-peer-cost>—Cost of tracking LLC2 peer.

<track-peer-state>—State of tracked LLC2 remote peer.

<tracking>—Tracking status of LLC2 redundancy group.

<unit>—LLC2 unit number.

<llc2-redundancy>

Usage <llc2-redundancy-list>
 <llc2-redundancy>
 <llc2>...</llc2>
 </llc2-redundancy>
 </llc2-redundancy-list>

Description No documentation is available yet.

Contents <llc2>—No documentation is available yet.

<llc2-redundancy-interface-statistics>

Usage <llc2-redundancy-interface-statistics-list>
 <llc2-redundancy-interface-statistics>
 <llc2>...</llc2>
 </llc2-redundancy-interface-statistics>
 </llc2-redundancy-interface-statistics-list>

Description No documentation is available yet.

Contents <llc2>—No documentation is available yet.

<llc2-redundancy-interface-statistics-list>

Usage <rpc-reply>
 <llc2-redundancy-interface-statistics-list>
 <llc2-redundancy-interface-statistics>...
 </llc2-redundancy-interface-statistics>
 </llc2-redundancy-interface-statistics-list>
 </rpc-reply>

Description No documentation is available yet.

Contents <llc2-redundancy-interface-statistics>—No documentation is available yet.

<llc2-redundancy-list>

Usage <rpc-reply>
 <llc2-redundancy-list>
 <llc2-redundancy>...</llc2-redundancy>
 </llc2-redundancy-list>
 </rpc-reply>

Description No documentation is available yet.

Contents <llc2-redundancy>—No documentation is available yet.

<llc2-redundancy-mac-translation>

Usage <llc2-redundancy-mac-translation-list>
 <llc2-redundancy-mac-translation>
 <llc2>...</llc2>
 </llc2-redundancy-mac-translation>
 </llc2-redundancy-mac-translation-list>

Description No documentation is available yet.

Contents <llc2>—No documentation is available yet.

<llc2-redundancy-mac-translation-list>

```
Usage  <rpc-reply>
      <llc2-redundancy-mac-translation-list>
        <llc2-redundancy-mac-translation>...</llc2-redundancy-mac-translation>
      </llc2-redundancy-mac-translation-list>
</rpc-reply>
```

Description No documentation is available yet.

Contents <llc2-redundancy-mac-translation>—No documentation is available yet.

<llc2-redundancy-track-dlsw-destination>

```
Usage <llc2-redundancy-track-dlsw-destination-list>
      <llc2-redundancy-track-dlsw-destination>
      <llc2>...</llc2>
      </llc2-redundancy-track-dlsw-destination>
</llc2-redundancy-track-dlsw-destination-list>
```

Description No documentation is available yet.

Contents <llc2>—No documentation is available yet.

<llc2-redundancy-track-dlsw-destination-list>

```
Usage <rpc-reply>
  <llc2-redundancy-track-dlsw-destination-list>
    <llc2-redundancy-track-dlsw-destination>...
    </llc2-redundancy-track-dlsw-destination>
  </llc2-redundancy-track-dlsw-destination-list>
</rpc-reply>
```

Description No documentation is available yet.

Contents <llc2-redundancy-track-dlsw-destination>—No documentation is available yet.

<llc2-redundancy-track-dlsw-peer>

Usage <llc2-redundancy-track-dlsw-peer-list>
 <llc2-redundancy-track-dlsw-peer>
 <llc2>...</llc2>
 </llc2-redundancy-track-dlsw-peer>
 </llc2-redundancy-track-dlsw-peer-list>

Description No documentation is available yet.

Contents <llc2>—No documentation is available yet.

<llc2-redundancy-track-dlsw-peer-list>

Usage <rpc-reply>
 <llc2-redundancy-track-dlsw-peer-list>
 <llc2-redundancy-track-dlsw-peer>...</llc2-redundancy-track-dlsw-peer>
 </llc2-redundancy-track-dlsw-peer-list>
 </rpc-reply>

Description No documentation is available yet.

Contents <llc2-redundancy-track-dlsw-peer>—No documentation is available yet.

<llc2-redundancy-track-interface>

Usage <llc2-redundancy-track-interface-list>
 <llc2-redundancy-track-interface>
 <llc2>...</llc2>
 </llc2-redundancy-track-interface>
 </llc2-redundancy-track-interface-list>

Description No documentation is available yet.

Contents <llc2>—No documentation is available yet.

<llc2-redundancy-track-interface-list>

Usage <rpc-reply>
 <llc2-redundancy-track-interface-list>
 <llc2-redundancy-track-interface>...</llc2-redundancy-track-interface>
 </llc2-redundancy-track-interface-list>
 </rpc-reply>

Description No documentation is available yet.

Contents <llc2-redundancy-track-interface>—No documentation is available yet.

Summary of DHCP Response Tags

This section lists JUNOS XML tags that contain operational information about the Dynamic Host Configuration Protocol (DHCP). The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-dhcp>. To review the DTD for the tags, see “DTD for DHCP Response Tags” on page 1709.

<client-identifier>

Usage	<pre> <dhcp-binding> <client-identifier> <hex-data><i>hex-data</i></hex-data> <hex-data-line><i>hex-data-line</i></hex-data-line> <printable-data-line><i>printable-data-line</i></printable-data-line> </client-identifier> </dhcp-binding> </pre>
Description	Identifier that the DHCP client provided for itself when it requested an address assignment.
Contents	<p><hex-data>—Data in hexadecimal format.</p> <p><hex-data-line>—Line of data in hexadecimal format.</p> <p><printable-data-line>—Line of data in printable format.</p>

<dhcp-binding>

Usage <dhcp-binding-information>
 <dhcp-binding>
 <allocated-address>*allocated-address*</allocated-address>
 <mac-address>*mac-address*</mac-address>
 <dhcp-lease-binding-type>*dhcp-lease-binding-type*</dhcp-lease-binding-type>
 <lease-end-time>*lease-end-time*</lease-end-time>
 <lease-state>*lease-state*</lease-state>
 <dhcp-option-table>...</dhcp-option-table>
 <address-pool-name>*address-pool-name*</address-pool-name>
 <interface-name>*interface-name*</interface-name>
 <bootp-relay-address>*bootp-relay-address*</bootp-relay-address>
 <dhcp-lease-information>...</dhcp-lease-information>
 <client-identifier>...</client-identifier>
 </dhcp-binding>
 </dhcp-binding-information>

Description Information about the address assigned to a Dynamic Host Configuration Protocol client.

Contents <address-pool-name>—Name of the address pool.

<allocated-address>—IPv4 address assigned to the DHCP client.

<bootp-relay-address>—IP address of the bootstrap protocol server that relayed the address assigned by the DHCP server.

<client-identifier>—Identifier that the DHCP client provided for itself when it requested an address assignment.

<dhcp-lease-binding-type>—Type of the address assignment.

<dhcp-lease-information>—Information about an address assignment.

<dhcp-option-table>—Information about one or more Dynamic Host Configuration Protocol options that are associated with the address assignment.

<interface-name>—Name of the interface via which the DHCP relay process transmitted the address assignment.

<lease-end-time>—Time when the address assignment will expire, in the format YYYY-MM-DD hh:mm:ss TZ (year, month, date, hour in 24-hour format, minute, second, time zone). The value 'never' indicates that the lease does not expire.

<lease-state>—Status of the address assignment.

<mac-address>—Media access control (hardware) address of the DHCP client.

<dhcp-binding-information>

- Usage** <rpc-reply>
 <dhcp-binding-information>
 <dhcp-binding>...</dhcp-binding>
 </dhcp-binding-information>
 </rpc-reply>
- Description** Information about the address assigned to each of one or more Dynamic Host Configuration Protocol clients.
- Contents** <dhcp-binding>—Information about the address assigned to a Dynamic Host Configuration Protocol client.

<dhcp-conflict>

- Usage** <dhcp-conflict-information>
 <dhcp-conflict>
 <detec-tion-time>detec-tion-time</detec-tion-time>
 <detec-tion-method>detec-tion-method</detec-tion-method>
 <conflict-address>conflict-address</conflict-address>
 </dhcp-conflict>
 </dhcp-conflict-information>
- Description** Information about a Dynamic Host Configuration Protocol conflict. A conflict arises when an address assigned to DHCP client is already assigned to another entity (computer or interface, for example).
- Contents** <conflict-address>—IPv4 address that is already in use by another host.
- <detec-tion-method>—Method used to detect the conflict.
- <detec-tion-time>—Time when the conflict was detected, in the format YYYY-MM-DD hh:mm:ss TZ (year, month, date, hour in 24-hour format, minute, second, time zone).

<dhcp-conflict-information>

- Usage** <rpc-reply>
 <dhcp-conflict-information>
 <dhcp-conflict>...</dhcp-conflict>
 </dhcp-conflict-information>
 </rpc-reply>
- Description** Information about one or more Dynamic Host Configuration Protocol conflicts.
- Contents** <dhcp-conflict>—Information about a Dynamic Host Configuration Protocol conflict. A conflict arises when an address assigned to DHCP client is already assigned to another entity (computer or interface, for example).

<dhcp-global-information>

Usage <rpc-reply>
 <dhcp-global-information>
 <dhcp-lease-time-information>...</dhcp-lease-time-information>
 <dhcp-option-table>...</dhcp-option-table>
 <bootp-lease-length>*bootp-lease-length*</bootp-lease-length>
 </dhcp-global-information>
 </rpc-reply>

Description Information about Dynamic Host Configuration Protocol settings that are configured for the global scope.

Contents <bootp-lease-length>—Duration of address assignments to bootstrap protocol (BOOTP) clients.

<dhcp-lease-time-information>—Information about configured default, maximum, and minimum duration for address assignments.

<dhcp-option-table>—Information about one or more Dynamic Host Configuration Protocol options that are associated with the address assignment.

<dhcp-lease-information>

Usage <dhcp-binding>
 <dhcp-lease-information>
 <dhcp-lease-type>*dhcp-lease-type*</dhcp-lease-type>
 <lease-start-time>*lease-start-time*</lease-start-time>
 <lease-end-time>*lease-end-time*</lease-end-time>
 <lease-state>*lease-state*</lease-state>
 </dhcp-lease-information>
 </dhcp-binding>

Description Information about an address assignment.

Contents <dhcp-lease-type>—Lease type.

<lease-end-time>—Time when the address assignment will expire, in the format YYYY-MM-DD hh:mm:ss TZ (year, month, date, hour in 24-hour format, minute, second, time zone). The value 'never' indicates that the lease does not expire.

<lease-start-time>—Time when the client obtained the address assignment, in the format YYYY-MM-DD hh:mm:ss TZ (year, month, date, hour in 24-hour format, minute, second, time zone).

<lease-state>—Status of the address assignment.

<dhcp-lease-time-information>

- Usage** <dhcp-pool | dhcp-global-information>
<dhcp-lease-time-information>
 <default-lease-time>*default-lease-time*</default-lease-time>
 <minimum-lease-time>*minimum-lease-time*</minimum-lease-time>
 <maximum-lease-time>*maximum-lease-time*</maximum-lease-time>
</dhcp-lease-time-information>
 </dhcp-pool | dhcp-global-information>
- Description** Information about configured default, maximum, and minimum duration for address assignments.
- Contents** <default-lease-time>—Duration of an address assignment when the DHCP client does not specify a duration in its request.
- <maximum-lease-time>—Maximum possible duration of an address assignment.
- <minimum-lease-time>—Minimum possible duration of an address assignment.

<dhcp-option>

- Usage** <dhcp-option-table>
<dhcp-option>
 <dhcp-option-code>*dhcp-option-code*</dhcp-option-code>
 <dhcp-option-name>*dhcp-option-name*</dhcp-option-name>
 <dhcp-option-type>*dhcp-option-type*</dhcp-option-type>
 <dhcp-option-value>*dhcp-option-value*</dhcp-option-value>
</dhcp-option>
 </dhcp-option-table>
- Description** Information about a Dynamic Host Configuration Protocol option that is associated with the address assignment.
- Contents** <dhcp-option-code>—Numeric code assigned to the DHCP option.
- <dhcp-option-name>—Name of the DHCP option.
- <dhcp-option-type>—Type of value for the DHCP option (for example, string [word], integer, IP address).
- <dhcp-option-value>—Value of the DHCP option.

<dhcp-option-table>

- Usage** <dhcp-binding | dhcp-pool | dhcp-global-information>
 <dhcp-option-table>
 <dhcp-option>...</dhcp-option>
 </dhcp-option-table>
</dhcp-binding | dhcp-pool | dhcp-global-information>
- Description** Information about one or more Dynamic Host Configuration Protocol options that are associated with the address assignment.
- Contents** <dhcp-option>—Information about a Dynamic Host Configuration Protocol option that is associated with the address assignment.

<dhcp-pool>

Usage <dhcp-pool-information>
 <dhcp-pool>
 <address-pool-name>*address-pool-name*</address-pool-name>
 <address-pool-low-address>*address-pool-low-address*</address-pool-low-address>
 <address-pool-high-address>*address-pool-high-address*
 </address-pool-high-address>
 <address-pool-excluded-address>*address-pool-excluded-address*
 </address-pool-excluded-address>
 <dhcp-lease-time-information>...</dhcp-lease-time-information>
 <dhcp-option-table>...</dhcp-option-table>
 <address-count>*address-count*</address-count>
 <assigned-lease-count>*assigned-lease-count*</assigned-lease-count>
 <active-lease-count>*active-lease-count*</active-lease-count>
 <offered-lease-count>*offered-lease-count*</offered-lease-count>
 <expired-lease-count>*expired-lease-count*</expired-lease-count>
 <conflict-count>*conflict-count*</conflict-count>
 <exclusion-count>*exclusion-count*</exclusion-count>
 </dhcp-pool>
 </dhcp-pool-information>

Description Information about a Dynamic Host Configuration Protocol address pool.

Contents <active-lease-count>—Number of active address assignments.

<address-count>—Number of addresses in the pool.

<address-pool-excluded-address>—IP address that the DHCP relay process does not assign even though the address is in the configured range of addresses in the address pool.

<address-pool-high-address>—Highest IP address that can be assigned from the pool.

<address-pool-low-address>—Lowest IP address that can be assigned from the pool.

<address-pool-name>—Name of the address pool.

<assigned-lease-count>—Number of addresses currently assigned.

<conflict-count>—Number of addresses in conflict.

<dhcp-lease-time-information>—Information about configured default, maximum, and minimum duration for address assignments.

<dhcp-option-table>—Information about one or more Dynamic Host Configuration Protocol options that are associated with the address assignment.

<exclusion-count>—Number of addresses excluded from the address pool.

<expired-lease-count>—Number of expired address assignments.

<offered-lease-count>—Number of address assignments offered.

<dhcp-pool-information>

Usage <rpc-reply>
 <dhcp-pool-information>
 <dhcp-pool>...</dhcp-pool>
 </dhcp-pool-information>
 </rpc-reply>

Description Information about one or more Dynamic Host Configuration Protocol address pools.

Contents <dhcp-pool>—Information about a Dynamic Host Configuration Protocol address pool.

<dhcp-statistics-information>

Usage <rpc-reply>
<dhcp-statistics-information>
 <dropped-packet-total>*dropped-packet-total*</dropped-packet-total>
 <dropped-packet-bad-hardware>*dropped-packet-bad-hardware*
 </dropped-packet-bad-hardware>
 <dropped-packet-bad-opcode>*dropped-packet-bad-opcode*
 </dropped-packet-bad-opcode>
 <dropped-packet-bad-options>*dropped-packet-bad-options*
 </dropped-packet-bad-options>
 <dropped-packet-invalid-server-address>*dropped-packet-invalid-server-address*
 </dropped-packet-invalid-server-address>
 <dropped-packet-no-addresses>*dropped-packet-no-addresses*
 </dropped-packet-no-addresses>
 <dropped-packet-no-interface>*dropped-packet-no-interface*
 </dropped-packet-no-interface>
 <dropped-packet-no-routing-instance>*dropped-packet-no-routing-instance*
 </dropped-packet-no-routing-instance>
 <dropped-packet-no-local-address>*dropped-packet-no-local-address*
 </dropped-packet-no-local-address>
 <dropped-packet-too-short>*dropped-packet-too-short*</dropped-packet-too-short>
 <dropped-packet-read-error>*dropped-packet-read-error*
 </dropped-packet-read-error>
 <dropped-packet-send-error>*dropped-packet-send-error*
 </dropped-packet-send-error>
 <message-table>...</message-table>
</dhcp-statistics-information>
 </rpc-reply>

Description Statistics from the Dynamic Host Configuration Protocol relay process.

Contents <dropped-packet-bad-hardware>—Number of packets discarded by the DHCP relay process because they specified an invalid hardware address.

<dropped-packet-bad-opcode>—Number of packets discarded by the DHCP relay process because they specified an invalid operation code.

<dropped-packet-bad-options>—Number of packets discarded by the DHCP relay process because they specified invalid options.

<dropped-packet-invalid-server-address>—Number of packets discarded by the DHCP relay process because they specified an invalid server address.

<dropped-packet-no-addresses>—Number of packets discarded by the DHCP relay process because there were no addresses available for it to assign.

<dropped-packet-no-interface>—Number of packets discarded by the DHCP relay process because of an interface mismatch.

<dropped-packet-no-local-address>—Number of packets discarded by the DHCP relay process because there was no valid local address.

<dropped-packet-no-routing-instance>—Number of packets discarded by the DHCP relay process because of a routing-instance mismatch.

- <dropped-packet-read-error>**—Number of packets discarded by the DHCP relay process because of a read error.
- <dropped-packet-send-error>**—Number of packets that the DHCP relay process could not send.
- <dropped-packet-too-short>**—Number of packets discarded by the DHCP relay process because they were too short.
- <dropped-packet-total>**—Total number of packets discarded by the DHCP relay process because of errors.
- <message-table>**—Information about one or more DHCP or bootstrap protocol (BOOTP) messages sent or received by the DHCP relay process.

<message>

- Usage** `<message-table>
 <message>
 <message-name>message-name</message-name>
 <message-count>message-count</message-count>
 </message>
</message-table>`
- Description** Information about a DHCP or BOOTP message.
- Contents** `<message-count>`—Number of times the DHCP relay process received or sent the message.
- `<message-name>`—Name of the message.

<message-table>

- Usage** `<dhcp-statistics-information>
 <message-table>
 <message-direction>message-direction</message-direction>
 <message>...</message>
 </message-table>
</dhcp-statistics-information>`
- Description** Information about one or more DHCP or bootstrap protocol (BOOTP) messages sent or received by the DHCP relay process.
- Contents** `<message>`—Information about a DHCP or BOOTP message.
- `<message-direction>`—Indicator of whether the DHCP relay process sent or received the messages.

Summary of DHCP Relay Response Tags

This section lists JUNOS XML tags that contain operational information about Dynamic Host Configuration Protocol (DHCP) Relay. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-dhcp-relay>. To review the DTD for the tags, see “DTD for DHCP Relay Response Tags” on page 1713.

<binding-summary>

Usage	<pre> <dhcp-relay-binding-information> <binding-summary> <binding-count>binding-count</binding-count> <bound-count>bound-count</bound-count> <selecting-count>selecting-count</selecting-count> <renewing-count>renewing-count</renewing-count> <rebinding-count>rebinding-count</rebinding-count> <restore-count>restore-count</restore-count> </binding-summary> </dhcp-relay-binding-information> </pre>
Description	No documentation is available yet.
Contents	<p><binding-count>—Number of bindings in this routing instance.</p> <p><bound-count>—No documentation is available yet.</p> <p><rebinding-count>—No documentation is available yet.</p> <p><renewing-count>—No documentation is available yet.</p> <p><restore-count>—Number of clients waiting to be restored.</p> <p><selecting-count>—No documentation is available yet.</p>

<client-identifier>

Usage	<pre> <dhcp-binding> <client-identifier> <hex-data>hex-data</hex-data> <hex-data-line>hex-data-line</hex-data-line> <printable-data-line>printable-data-line</printable-data-line> </client-identifier> </dhcp-binding> </pre>
Description	Identifier that the DHCP client provided for itself when it requested an address assignment.
Contents	<p><hex-data>—Data in hexadecimal format.</p> <p><hex-data-line>—Line of data in hexadecimal format.</p> <p><printable-data-line>—Line of data in printable format.</p>

<dhcp-binding>

Usage <dhcp-relay-binding-information>
 <dhcp-binding>
 <allocated-address>*allocated-address*</allocated-address>
 <mac-address>*mac-address*</mac-address>
 <dhcp-lease-binding-type>*dhcp-lease-binding-type*</dhcp-lease-binding-type>
 <lease-end-time>*lease-end-time*</lease-end-time>
 <lease-state>*lease-state*</lease-state>
 <interface-name>*interface-name*</interface-name>
 <bootp-relay-address>*bootp-relay-address*</bootp-relay-address>
 <dhcp-lease-information>...</dhcp-lease-information>
 <client-identifier>...</client-identifier>
 </dhcp-binding>
 </dhcp-relay-binding-information>

Description Information about the address assigned to a Dynamic Host Configuration Protocol client.

Contents <allocated-address>—IPv4 address assigned to the DHCP client.

<bootp-relay-address>—IP address of the bootstrap protocol server that relayed the address assigned by the DHCP server.

<client-identifier>—Identifier that the DHCP client provided for itself when it requested an address assignment.

<dhcp-lease-binding-type>—Type of the address assignment.

<dhcp-lease-information>—Information about an address assignment.

<interface-name>—Name of the interface via which the DHCP server transmitted the address assignment.

<lease-end-time>—Time when the address assignment will expire, in the format YYYY-MM-DD hh:mm:ss TZ (year, month, date, hour in 24-hour format, minute, second, time zone). The value 'never' indicates that the lease does not expire.

<lease-state>—Status of the address assignment.

<mac-address>—Media access control (hardware) address of the DHCP client.

<dhcp-lease-information>

Usage	<pre> <dhcp-binding> <dhcp-lease-information> <dhcp-lease-type>dhcp-lease-type</dhcp-lease-type> <lease-start-time>lease-start-time</lease-start-time> <lease-end-time>lease-end-time</lease-end-time> <lease-state>lease-state</lease-state> </dhcp-lease-information> </dhcp-binding> </pre>
Description	Information about an address assignment.
Contents	<p><dhcp-lease-type>—Lease type.</p> <p><lease-end-time>—Time when the address assignment will expire, in the format YYYY-MM-DD hh:mm:ss TZ (year, month, date, hour in 24-hour format, minute, second, time zone). The value 'never' indicates that the lease does not expire.</p> <p><lease-start-time>—Time when the client obtained the address assignment, in the format YYYY-MM-DD hh:mm:ss TZ (year, month, date, hour in 24-hour format, minute, second, time zone).</p> <p><lease-state>—Status of the address assignment.</p>

<dhcp-relay-binding-information>

Usage	<pre> <rpc-reply> <dhcp-relay-binding-information> <binding-summary>...</binding-summary> <dhcp-binding>...</dhcp-binding> </dhcp-relay-binding-information> </rpc-reply> </pre>
Description	Information about the address assigned to each of one or more Dynamic Host Configuration Protocol clients.
Contents	<p><binding-summary>—No documentation is available yet.</p> <p><dhcp-binding>—Information about the address assigned to a Dynamic Host Configuration Protocol client.</p>

<dhcp-relay-statistics-information>**Usage** <rpc-reply>**<dhcp-relay-statistics-information>**

```

<dropped-packet-total>dropped-packet-total</dropped-packet-total>
<dropped-packet-bad-hardware>dropped-packet-bad-hardware
  </dropped-packet-bad-hardware>
<dropped-packet-bad-opcode>dropped-packet-bad-opcode
  </dropped-packet-bad-opcode>
<dropped-packet-bad-options>dropped-packet-bad-options
  </dropped-packet-bad-options>
<dropped-packet-invalid-server-address>dropped-packet-invalid-server-address
  </dropped-packet-invalid-server-address>
<dropped-packet-no-addresses>dropped-packet-no-addresses
  </dropped-packet-no-addresses>
<dropped-packet-no-interface>dropped-packet-no-interface
  </dropped-packet-no-interface>
<dropped-packet-no-routing-instance>dropped-packet-no-routing-instance
  </dropped-packet-no-routing-instance>
<dropped-packet-no-local-address>dropped-packet-no-local-address
  </dropped-packet-no-local-address>
<dropped-packet-too-short>dropped-packet-too-short</dropped-packet-too-short>
<dropped-packet-read-error>dropped-packet-read-error
  </dropped-packet-read-error>
<dropped-packet-send-error>dropped-packet-send-error
  </dropped-packet-send-error>
<dropped-packet-option-60>dropped-packet-option-60</dropped-packet-option-60>
<dropped-packet-option-82>dropped-packet-option-82</dropped-packet-option-82>
<dropped-packet-authentication>dropped-packet-authentication
  </dropped-packet-authentication>
<dropped-packet-dynamic-profile>dropped-packet-dynamic-profile
  </dropped-packet-dynamic-profile>
<dropped-packet-license>dropped-packet-license</dropped-packet-license>
<message-table>...</message-table>

```

</dhcp-relay-statistics-information>

</rpc-reply>

Description Statistics from the Dynamic Host Configuration Protocol Relay.**Contents** <dropped-packet-authentication>—Number of packets discarded because authentication failed.

<dropped-packet-bad-hardware>—Number of packets discarded by the DHCP relay because they specified an invalid hardware address.

<dropped-packet-bad-opcode>—Number of packets discarded by the DHCP relay because they specified an invalid operation code.

<dropped-packet-bad-options>—Number of packets discarded by the DHCP relay because they specified invalid options.

<dropped-packet-dynamic-profile>—Number of packets discarded because a dynamic profile failed.

<dropped-packet-invalid-server-address>—Number of packets discarded by the DHCP relay because they specified an invalid server address.

<dropped-packet-license>—Number of packets discarded because of a license failure.

<dropped-packet-no-addresses>—Number of packets discarded by the DHCP relay because there were no addresses available for it to assign.

<dropped-packet-no-interface>—Number of packets discarded by the DHCP relay because of an interface mismatch.

<dropped-packet-no-local-address>—Number of packets discarded by the DHCP relay because there was no valid local address.

<dropped-packet-no-routing-instance>—Number of packets discarded by the DHCP relay because of a routing-instance mismatch.

<dropped-packet-option-60>—Number of packets discarded with no matching option-60.

<dropped-packet-option-82>—Number of packets discarded because option-82 could not be added.

<dropped-packet-read-error>—Number of packets discarded by the DHCP relay because of a read error.

<dropped-packet-send-error>—Number of packets that the DHCP relay could not send.

<dropped-packet-too-short>—Number of packets discarded by the DHCP relay because they were too short.

<dropped-packet-total>—Total number of packets discarded by the DHCP relay because of errors.

<message-table>—Information about one or more DHCP or bootstrap protocol (BOOTP) messages sent or received by the DHCP relay.

<message>

Usage **<message-table>**
 <message>
 <message-name>*message-name*</message-name>
 <message-count>*message-count*</message-count>
 </message>
</message-table>

Description Information about a DHCP or BOOTP message.

Contents **<message-count>**—Number of times the DHCP relay received or sent the message.

<message-name>—Name of the message.

<message-table>

Usage	<pre><dhcp-relay-statistics-information> <message-table> <message-direction>message-direction</message-direction> <message>...</message> </message-table> </dhcp-relay-statistics-information></pre>
Description	Information about one or more DHCP or bootstrap protocol (BOOTP) messages sent or received by the DHCP relay.
Contents	<p><message>—Information about a DHCP or BOOTP message.</p> <p><message-direction>—Indicator of whether the DHCP relay sent or received the messages.</p>

Summary of DHCP Server Response Tags

This section lists JUNOS XML tags that contain operational information about the Dynamic Host Configuration Protocol (DHCP) Server. The associated XML namespace is `http://xml.juniper.net/junos/9.3R1/junos-dhcp-server`. To review the DTD for the tags, see “DTD for DHCP Server Response Tags” on page 1717.

<binding-summary>

Usage	<pre><dhcp-server-binding-information> <binding-summary> <binding-count>binding-count</binding-count> <bound-count>bound-count</bound-count> <selecting-count>selecting-count</selecting-count> <renewing-count>renewing-count</renewing-count> <rebinding-count>rebinding-count</rebinding-count> <restore-count>restore-count</restore-count> </binding-summary> </dhcp-server-binding-information></pre>
Description	No documentation is available yet.
Contents	<p><binding-count>—Number of bindings in this routing instance.</p> <p><bound-count>—No documentation is available yet.</p> <p><rebinding-count>—No documentation is available yet.</p> <p><renewing-count>—No documentation is available yet.</p> <p><restore-count>—Number of clients waiting to be restored.</p> <p><selecting-count>—No documentation is available yet.</p>

<client-identifier>

Usage	<pre><dhcp-binding> <client-identifier> <hex-data>hex-data</hex-data> <hex-data-line>hex-data-line</hex-data-line> <printable-data-line>printable-data-line</printable-data-line> </client-identifier> </dhcp-binding></pre>
Description	Identifier that the DHCP client provided for itself when it requested an address assignment.
Contents	<p><hex-data>—Data in hexadecimal format.</p> <p><hex-data-line>—Line of data in hexadecimal format.</p> <p><printable-data-line>—Line of data in printable format.</p>

<dhcp-binding>

Usage <dhcp-server-binding-information>
 <dhcp-binding>
 <allocated-address>*allocated-address*</allocated-address>
 <mac-address>*mac-address*</mac-address>
 <dhcp-lease-binding-type>*dhcp-lease-binding-type*</dhcp-lease-binding-type>
 <lease-start-time>*lease-start-time*</lease-start-time>
 <lease-end-time>*lease-end-time*</lease-end-time>
 <lease-state>*lease-state*</lease-state>
 <dhcp-lease-type>*dhcp-lease-type*</dhcp-lease-type>
 <interface-name>*interface-name*</interface-name>
 <bootp-relay-address>*bootp-relay-address*</bootp-relay-address>
 <client-identifier>...</client-identifier>
 </dhcp-binding>
 </dhcp-server-binding-information>

Description Information about the address assigned to a Dynamic Host Configuration Protocol client.

Contents <allocated-address>—IPv4 address assigned to the DHCP client.

<bootp-relay-address>—IP address of the bootstrap protocol server that relayed the address assigned by the DHCP server.

<client-identifier>—Identifier that the DHCP client provided for itself when it requested an address assignment.

<dhcp-lease-binding-type>—Type of the address assignment.

<dhcp-lease-type>—Lease type.

<interface-name>—Name of the interface via which the DHCP server transmitted the address assignment.

<lease-end-time>—Time when the address assignment will expire, in the format YYYY-MM-DD hh:mm:ss TZ (year, month, date, hour in 24-hour format, minute, second, time zone). The value 'never' indicates that the lease does not expire.

<lease-start-time>—Time when the client obtained the address assignment, in the format YYYY-MM-DD hh:mm:ss TZ (year, month, date, hour in 24-hour format, minute, second, time zone).

<lease-state>—Status of the address assignment.

<mac-address>—Media access control (hardware) address of the DHCP client.

<dhcp-server-binding-information>

Usage <rpc-reply>
 <dhcp-server-binding-information>
 <binding-summary>...</binding-summary>
 <dhcp-binding>...</dhcp-binding>
 </dhcp-server-binding-information>
 </rpc-reply>

Description Information about the address assigned to each of one or more Dynamic Host Configuration Protocol clients.

Contents <binding-summary>—No documentation is available yet.
 <dhcp-binding>—Information about the address assigned to a Dynamic Host Configuration Protocol client.

<dhcp-server-statistics-information>

Usage <rpc-reply>

```

<dhcp-server-statistics-information>
  <dropped-packet-total>dropped-packet-total</dropped-packet-total>
  <dropped-packet-bad-hardware>dropped-packet-bad-hardware
    </dropped-packet-bad-hardware>
  <dropped-packet-bad-opcode>dropped-packet-bad-opcode
    </dropped-packet-bad-opcode>
  <dropped-packet-bad-options>dropped-packet-bad-options
    </dropped-packet-bad-options>
  <dropped-packet-invalid-server-address>dropped-packet-invalid-server-address
    </dropped-packet-invalid-server-address>
  <dropped-packet-no-addresses>dropped-packet-no-addresses
    </dropped-packet-no-addresses>
  <dropped-packet-no-interface>dropped-packet-no-interface
    </dropped-packet-no-interface>
  <dropped-packet-no-routing-instance>dropped-packet-no-routing-instance
    </dropped-packet-no-routing-instance>
  <dropped-packet-no-local-address>dropped-packet-no-local-address
    </dropped-packet-no-local-address>
  <dropped-packet-too-short>dropped-packet-too-short</dropped-packet-too-short>
  <dropped-packet-read-error>dropped-packet-read-error
    </dropped-packet-read-error>
  <dropped-packet-send-error>dropped-packet-send-error
    </dropped-packet-send-error>
  <dropped-packet-authentication>dropped-packet-authentication
    </dropped-packet-authentication>
  <dropped-packet-dynamic-profile>dropped-packet-dynamic-profile
    </dropped-packet-dynamic-profile>
  <dropped-packet-license>dropped-packet-license</dropped-packet-license>
  <message-table>...</message-table>
</dhcp-server-statistics-information>
</rpc-reply>

```

Description Statistics from the Dynamic Host Configuration Protocol Server.

Contents <dropped-packet-authentication>—Number of packets discarded because authentication failed.

<dropped-packet-bad-hardware>—Number of packets discarded by the DHCP server because they specified an invalid hardware address.

<dropped-packet-bad-opcode>—Number of packets discarded by the DHCP server because they specified an invalid operation code.

<dropped-packet-bad-options>—Number of packets discarded by the DHCP server because they specified invalid options.

<dropped-packet-dynamic-profile>—Number of packets discarded because a dynamic profile failed.

<dropped-packet-invalid-server-address>—Number of packets discarded by the DHCP server because they specified an invalid server address.

<dropped-packet-license>—Number of packets discarded because of a license failure.

<dropped-packet-no-addresses>—Number of packets discarded by the DHCP server because there were no addresses available for it to assign.

<dropped-packet-no-interface>—Number of packets discarded by the DHCP server because of an interface mismatch.

<dropped-packet-no-local-address>—Number of packets discarded by the DHCP server because there was no valid local address.

<dropped-packet-no-routing-instance>—Number of packets discarded by the DHCP server because of a routing-instance mismatch.

<dropped-packet-read-error>—Number of packets discarded by the DHCP server because of a read error.

<dropped-packet-send-error>—Number of packets that the DHCP server could not send.

<dropped-packet-too-short>—Number of packets discarded by the DHCP server because they were too short.

<dropped-packet-total>—Total number of packets discarded by the DHCP server because of errors.

<message-table>—Information about one or more DHCP or bootstrap protocol (BOOTP) messages sent or received by the DHCP server.

<message>

Usage **<message-table>**
<message>
 <message-name>*message-name*</message-name>
 <message-count>*message-count*</message-count>
</message>
</message-table>

Description Information about a DHCP or BOOTP message.

Contents <message-count>—Number of times the DHCP server received or sent the message.
 <message-name>—Name of the message.

<message-table>

Usage	<pre><dhcp-server-statistics-information> <message-table> <message-direction>message-direction</message-direction> <message>...</message> </message-table> </dhcp-server-statistics-information></pre>
Description	Information about one or more DHCP or bootstrap protocol (BOOTP) messages sent or received by the DHCP server.
Contents	<p><message>—Information about a DHCP or BOOTP message.</p> <p><message-direction>—Indicator of whether the DHCP server sent or received the messages.</p>

Summary of Dialer Response Tags

This section lists JUNOS XML tags that contain operational information about the Integrated Services Digital Network (ISDN) dialer. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-dood>. To review the DTD for the tags, see “DTD for Dialer Response Tags” on page 1721.

<dial-string-list>

Usage	<pre> <dialer-interface> <dial-string-list> <dial-string>dial-string</dial-string> </dial-string-list> </dialer-interface> </pre>
Description	No documentation is available yet.
Contents	<dial-string>—Dial string.

<dialer-defaults-information>

Usage <rpc-reply>
 <dialer-defaults-information>
 <default-idle-timeout>default-idle-timeout</default-idle-timeout>
 <default-activation-delay>default-activation-delay</default-activation-delay>
 <default-deactivation-delay>default-deactivation-delay
 </default-deactivation-delay>
 <default-initial-route-check>default-initial-route-check
 </default-initial-route-check>
 <default-pool-priority>default-pool-priority</default-pool-priority>
 <default-load-threshold>default-load-threshold</default-load-threshold>
 <default-load-interval>default-load-interval</default-load-interval>
 <default-redial-delay>default-redial-delay</default-redial-delay>
 <default-callback-wait-period>default-callback-wait-period
 </default-callback-wait-period>
 </dialer-defaults-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <default-activation-delay>—Default value of dialer activation delay.

 <default-callback-wait-period>—Default value of dialer callback wait period which determines how long to wait before dialer attempts a callback.

 <default-deactivation-delay>—Default value of dialer deactivation delay.

 <default-idle-timeout>—Default value of dialer idle timeout.

 <default-initial-route-check>—Default value of dialer watch initial route check time.

 <default-load-interval>—Default value of dialer load interval.

 <default-load-threshold>—Default value of dialer load threshold.

 <default-pool-priority>—Default value of dialer pool priority.

 <default-redial-delay>—Default value for dialer redial delay which determines how long to wait before dialer attempts to redial.

<dialer-info>

Usage <pool-member-list>
 <dialer-info>
 <dialer-interface-name>*dialer-interface-name*</dialer-interface-name>
 <dialer-interface-state>*dialer-interface-state*</dialer-interface-state>
 <dialer-interface-flags>...</dialer-interface-flags>
 </dialer-info>
 </pool-member-list>

Description No documentation is available yet.

Contents <dialer-interface-flags>—Flags indicating interface configuration.
 <dialer-interface-name>—Interface name.
 <dialer-interface-state>—Dialer interface state.

<dialer-interface>

Usage <dialer-interface-information>
<dialer-interface>
 <dialer-interface-name>*dialer-interface-name*</dialer-interface-name>
 <dialer-interface-state>*dialer-interface-state*</dialer-interface-state>
 <dialer-interface-flags>...</dialer-interface-flags>
 <pool-id>*pool-id*</pool-id>
 <primary-interface>*primary-interface*</primary-interface>
 <dial-string-list>...</dial-string-list>
 <sub-interface-list>...</sub-interface-list>
 <watch-list>...</watch-list>
 <activation-delay>*activation-delay*</activation-delay>
 <deactivation-delay>*deactivation-delay*</deactivation-delay>
 <activation-delay-elapsed>*activation-delay-elapsed*</activation-delay-elapsed>
 <deactivation-delay-elapsed>*deactivation-delay-elapsed*
 </deactivation-delay-elapsed>
 <call-idle-timeout>*call-idle-timeout*</call-idle-timeout>
 <initial-route-check>*initial-route-check*</initial-route-check>
 <redial-delay>*redial-delay*</redial-delay>
 <callback-wait-period>*callback-wait-period*</callback-wait-period>
 <callback-wait-period-elapsed>*callback-wait-period-elapsed*
 </callback-wait-period-elapsed>
 <load-threshold>*load-threshold*</load-threshold>
 <load-interval>*load-interval*</load-interval>
</dialer-interface>
 </dialer-interface-information>

Description No documentation is available yet.

Contents <activation-delay>—Activation delay.

<activation-delay-elapsed>—Activation delay elapsed.

<call-idle-timeout>—Call idle timeout.

<callback-wait-period>—Delay before dialer attempts callback (seconds).

<callback-wait-period-elapsed>—Number of seconds in callback wait period that have elapsed.

<deactivation-delay>—Deactivation delay.

<deactivation-delay-elapsed>—Deactivation delay elapsed.

<dial-string-list>—No documentation is available yet.

<dialer-interface-flags>—Flags indicating interface configuration.

<dialer-interface-name>—Interface name.

<dialer-interface-state>—Dialer interface state.

<initial-route-check>—Initial route check delay.

<load-interval>—Interval over which average load is calculated.

<load-threshold>—Load threshold that determines when interfaces are added to bundle.

<pool-id>—Pool identifier.

<primary-interface>—Primary interface.

<redial-delay>—Delay before dialer dials out again (seconds).

<sub-interface-list>—No documentation is available yet.

<watch-list>—No documentation is available yet.

<dialer-interface-flags>

Usage <dialer-interface | dialer-info>
<dialer-interface-flags>
 <backup/>
 <multilink/>
 <watchlist/>
 <interesting-detected/>
</dialer-interface-flags>
 </dialer-interface | dialer-info>

Description Flags indicating interface configuration.

Contents <backup>—Dialer backup.
 <interesting-detected>—Interesting packet detected.
 <multilink>—Dialer multilink.
 <watchlist>—Dialer watchlist.

<dialer-interface-information>

Usage <rpc-reply>
<dialer-interface-information>
 <dialer-interface>...</dialer-interface>
</dialer-interface-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <dialer-interface>—No documentation is available yet.

<dialer-pool>

Usage	<pre> <dialer-pool-information> <dialer-pool> <pool-id>pool-id</pool-id> <pool-member-list>...</pool-member-list> </dialer-pool> </dialer-pool-information> </pre>
Description	No documentation is available yet.
Contents	<p><pool-id>—Pool identifier.</p> <p><pool-member-list>—No documentation is available yet.</p>

<dialer-pool-information>

Usage	<pre> <rpc-reply> <dialer-pool-information> <dialer-pool>...</dialer-pool> </dialer-pool-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<dialer-pool>—No documentation is available yet.

<pool-member-list>

Usage	<pre> <dialer-pool> <pool-member-list> <dialer-info>...</dialer-info> <sub-info>...</sub-info> </pool-member-list> </dialer-pool> </pre>
Description	No documentation is available yet.
Contents	<p><dialer-info>—No documentation is available yet.</p> <p><sub-info>—No documentation is available yet.</p>

<sub-info>

Usage	<pre> <pool-member-list> <sub-info> <sub-interface-name>sub-interface-name</sub-interface-name> <sub-interface-flags>sub-interface-flags</sub-interface-flags> <pool-priority>pool-priority</pool-priority> </sub-info> </pool-member-list> </pre>
Description	No documentation is available yet.
Contents	<p><pool-priority>—Pool priority.</p> <p><sub-interface-flags>—Flags indicating subordinate interface status.</p> <p><sub-interface-name>—Subordinate interface name.</p>

<sub-interface-list>

Usage	<pre> <dialer-interface> <sub-interface-list> <sub-interface-name>sub-interface-name</sub-interface-name> </sub-interface-list> </dialer-interface> </pre>
Description	No documentation is available yet.
Contents	<sub-interface-name>—Subordinate interface name.

<watch-list>

Usage	<pre> <dialer-interface> <watch-list> <watch-route>watch-route</watch-route> </watch-list> </dialer-interface> </pre>
Description	No documentation is available yet.
Contents	<watch-route>—Watch route.

Summary of Diameter Response Tags

This section lists JUNOS XML tags that contain operational information about Diameter peers and nodes. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-diameter>. To review the DTD for the tags, see “DTD for Diameter Response Tags” on page 1725.

<diameter-all-peer-connection-tags>

Usage <show-diameter-results>
 <diameter-all-peer-connection-tags>
 <diameter-peer-address>*diameter-peer-address*</diameter-peer-address>
 <diameter-peer-port>*diameter-peer-port*</diameter-peer-port>
 <diameter-node-address>*diameter-node-address*</diameter-node-address>
 <diameter-node-port>*diameter-node-port*</diameter-node-port>
 <diameter-current-connection-start-time>*diameter-current-connection-start-time*
 </diameter-current-connection-start-time>
 <diameter-message-sent>*diameter-message-sent*</diameter-message-sent>
 <diameter-message-received>*diameter-message-received*
 </diameter-message-received>
 <diameter-bad-message-received>*diameter-bad-message-received*
 </diameter-bad-message-received>
 <diameter-last-message-received-time>*diameter-last-message-received-time*
 </diameter-last-message-received-time>
 <diameter-last-message-sent-time>*diameter-last-message-sent-time*
 </diameter-last-message-sent-time>
 </diameter-all-peer-connection-tags>
 </show-diameter-results>

Description No documentation is available yet.

Contents <diameter-bad-message-received>—Total number of bad Diameter message received.

<diameter-current-connection-start-time>—Start time of current connection.

<diameter-last-message-received-time>—Time of last message received.

<diameter-last-message-sent-time>—Time of last message received.

<diameter-message-received>—Total number of Diameter message received.

<diameter-message-sent>—Total number of Diameter message sent.

<diameter-node-address>—IP address of a Diameter node (host).

<diameter-node-port>—Port of a Diameter node (host).

<diameter-peer-address>—IP address of a peer.

<diameter-peer-port>—Port of a Diameter peer.

<diameter-all-peer-summary-tags>

Usage <show-diameter-results>
 <diameter-all-peer-summary-tags>
 <diameter-peer-mandatory-name>*diameter-peer-mandatory-name*
 </diameter-peer-mandatory-name>
 <diameter-peer-mandatory-ipaddr>*diameter-peer-mandatory-ipaddr*
 </diameter-peer-mandatory-ipaddr>
 <diameter-application-id>*diameter-application-id*</diameter-application-id>
 <diameter-application-name>*diameter-application-name*
 </diameter-application-name>
 <diameter-connection-status>*diameter-connection-status*
 </diameter-connection-status>
 </diameter-all-peer-summary-tags>
 </show-diameter-results>

Description No documentation is available yet.

Contents <diameter-application-id>—Applications Id supported by peer.
 <diameter-application-name>—Application name.
 <diameter-connection-status>—Connection status of the peer.
 <diameter-peer-mandatory-ipaddr>—Address of a peer.
 <diameter-peer-mandatory-name>—Name of a peer.

<diameter-message-statistics-tags>

Usage <diameter-statistics-tags | diameter-peer-statistics-tags>

<diameter-message-statistics-tags>

```

<diameter-asr-message-sent>diameter-asr-message-sent
  </diameter-asr-message-sent>
<diameter-asa-message-received>diameter-asa-message-received
  </diameter-asa-message-received>
<diameter-asr-message-received>diameter-asr-message-received
  </diameter-asr-message-received>
<diameter-asa-message-sent>diameter-asa-message-sent
  </diameter-asa-message-sent>
<diameter-acr-message-sent>diameter-acr-message-sent
  </diameter-acr-message-sent>
<diameter-aca-message-received>diameter-aca-message-received
  </diameter-aca-message-received>
<diameter-acr-message-received>diameter-acr-message-received
  </diameter-acr-message-received>
<diameter-aca-message-sent>diameter-aca-message-sent
  </diameter-aca-message-sent>
<diameter-cer-message-sent>diameter-cer-message-sent
  </diameter-cer-message-sent>
<diameter-cea-message-received>diameter-cea-message-received
  </diameter-cea-message-received>
<diameter-cer-message-received>diameter-cer-message-received
  </diameter-cer-message-received>
<diameter-cea-message-sent>diameter-cea-message-sent
  </diameter-cea-message-sent>
<diameter-dwr-message-sent>diameter-dwr-message-sent
  </diameter-dwr-message-sent>
<diameter-dwa-message-received>diameter-dwa-message-received
  </diameter-dwa-message-received>
<diameter-dwr-message-received>diameter-dwr-message-received
  </diameter-dwr-message-received>
<diameter-dwa-message-sent>diameter-dwa-message-sent
  </diameter-dwa-message-sent>
<diameter-dpr-message-sent>diameter-dpr-message-sent
  </diameter-dpr-message-sent>
<diameter-dpa-message-received>diameter-dpa-message-received
  </diameter-dpa-message-received>
<diameter-dpr-message-received>diameter-dpr-message-received
  </diameter-dpr-message-received>
<diameter-dpa-message-sent>diameter-dpa-message-sent
  </diameter-dpa-message-sent>
<diameter-rar-message-sent>diameter-rar-message-sent
  </diameter-rar-message-sent>
<diameter-raa-message-received>diameter-raa-message-received
  </diameter-raa-message-received>
<diameter-rar-message-received>diameter-rar-message-received
  </diameter-rar-message-received>
<diameter-raa-message-sent>diameter-raa-message-sent
  </diameter-raa-message-sent>
<diameter-str-message-sent>diameter-str-message-sent
  </diameter-str-message-sent>

```

```

<diameter-sta-message-received>diameter-sta-message-received
</diameter-sta-message-received>
<diameter-str-message-received>diameter-str-message-received
</diameter-str-message-received>
<diameter-sta-message-sent>diameter-sta-message-sent
</diameter-sta-message-sent>
</diameter-message-statistics-tags>
</diameter-statistics-tags | diameter-peer-statistics-tags>

```

Description No documentation is available yet.

Contents

<diameter-aca-message-received>—Total number of Accounting-Answer message received from the peer.

<diameter-aca-message-sent>—Total number of Accounting-Answer message sent to the peer.

<diameter-acr-message-received>—Total number of Accounting-Request message received from the peer.

<diameter-acr-message-sent>—Total number of Accounting-Request message sent to the peer.

<diameter-asa-message-received>—Total number of Abort-Session-Answer received.

<diameter-asa-message-sent>—Total number of Abort-Session-Answer sent to the peer.

<diameter-asr-message-received>—Total number of Abort-Session-Request received from the peer.

<diameter-asr-message-sent>—Total number of Abort-Session-Request message sent.

<diameter-cea-message-received>—Total number of Capabilities-Exchange-Answer message received from the peer.

<diameter-cea-message-sent>—Total number of Capabilities-Exchange-Answer message sent to the peer.

<diameter-cer-message-received>—Total number of Capabilities-Exchange-Request message received from the peer.

<diameter-cer-message-sent>—Total number of Capabilities-Exchange-Request message sent to the peer.

<diameter-dpa-message-received>—Total number of Disconnect-Peer-Answer message received from the peer.

<diameter-dpa-message-sent>—Total number of Disconnect-Peer-Answer message sent to the peer.

<diameter-dpr-message-received>—Total number of Disconnect-Peer-Request message received from the peer.

<diameter-dpr-message-sent>—Total number of Disconnect-Peer-Request message sent to the peer.

<diameter-dwa-message-received>—Total number of Device-Watchdog-Answer message received from the peer.

<diameter-dwa-message-sent>—Total number of Device-Watchdog-Answer message sent to the peer.

<diameter-dwr-message-received>—Total number of Device-Watchdog-Request message received from the peer.

<diameter-dwr-message-sent>—Total number of Device-Watchdog-Request message sent to the peer.

<diameter-raa-message-received>—Total number of Re-Auth-Answer message received from the peer.

<diameter-raa-message-sent>—Total number of Re-Auth-Answer message sent to the peer.

<diameter-rar-message-received>—Total number of Re-Auth-Request message received from the peer.

<diameter-rar-message-sent>—Total number of Re-Auth-Request message sent to the peer.

<diameter-sta-message-received>—Total number of Session-Termination-Answer message received from the peer.

<diameter-sta-message-sent>—Total number of Session-Termination-Answer message sent to the peer.

<diameter-str-message-received>—Total number of Session-Termination-Request message received from the peer.

<diameter-str-message-sent>—Total number of Session-Termination-Request message sent to the peer.

<diameter-peer-session-tags>

Usage `<show-diameter-peer-results>`
 <diameter-peer-session-tags>
 <diameter-session-id>*diameter-session-id*</diameter-session-id>
 <diameter-session-tba>*diameter-session-tba*</diameter-session-tba>
 </diameter-peer-session-tags>
`</show-diameter-peer-results>`

Description No documentation is available yet.

Contents `<diameter-session-id>`—Session Id.
 `<diameter-session-tba>`—Session TBA.

<diameter-peer-statistics-tags>

- Usage** <show-diameter-peer-results>
 <diameter-peer-statistics-tags>
 <diameter-message-statistics-tags>...</diameter-message-statistics-tags>
 </diameter-peer-statistics-tags>
 </show-diameter-peer-results>
- Description** No documentation is available yet.
- Contents** <diameter-message-statistics-tags>—No documentation is available yet.

<diameter-peer-summary-tags>

Usage <show-diameter-peer-results>

```

<diameter-peer-summary-tags>
  <diameter-peer-mandatory-name>diameter-peer-mandatory-name
  </diameter-peer-mandatory-name>
  <diameter-peer-mandatory-ipaddr>diameter-peer-mandatory-ipaddr
  </diameter-peer-mandatory-ipaddr>
  <diameter-connection-status>diameter-connection-status
  </diameter-connection-status>
  <diameter-connection-type>diameter-connection-type</diameter-connection-type>
  <diameter-peer-port>diameter-peer-port</diameter-peer-port>
  <diameter-security>diameter-security</diameter-security>
  <diameter-application-supported>diameter-application-supported
  </diameter-application-supported>
  <diameter-message-sent>diameter-message-sent</diameter-message-sent>
  <diameter-message-received>diameter-message-received
  </diameter-message-received>
  <diameter-bad-message-received>diameter-bad-message-received
  </diameter-bad-message-received>
  <diameter-opened-session>diameter-opened-session</diameter-opened-session>
  <diameter-closed-session>diameter-closed-session</diameter-closed-session>
  <diameter-active-session>diameter-active-session</diameter-active-session>
  <diameter-list-session-id>diameter-list-session-id</diameter-list-session-id>
  <diameter-last-connection-start-time>diameter-last-connection-start-time
  </diameter-last-connection-start-time>
  <diameter-last-connection-closed-time>diameter-last-connection-closed-time
  </diameter-last-connection-closed-time>
  <diameter-current-connection-start-time>diameter-current-connection-start-time
  </diameter-current-connection-start-time>
</diameter-peer-summary-tags>
</show-diameter-peer-results>

```

Description No documentation is available yet.

Contents

- <diameter-active-session>—Total number of active sessions.
- <diameter-application-supported>—List of names application supported.
- <diameter-bad-message-received>—Total number of bad Diameter message received.
- <diameter-closed-session>—Total number of sessions closed.
- <diameter-connection-status>—Connection status of the peer.
- <diameter-connection-type>—Connection type of the peer.
- <diameter-current-connection-start-time>—Start time of current connection.
- <diameter-last-connection-closed-time>—Time of last connection closed.
- <diameter-last-connection-start-time>—Time of last message received.
- <diameter-list-session-id>—List of session Id.

<diameter-message-received>—Total number of Diameter message received.

<diameter-message-sent>—Total number of Diameter message sent.

<diameter-opened-session>—Total number of sessions opened.

<diameter-peer-mandatory-ipaddr>—Address of a peer.

<diameter-peer-mandatory-name>—Name of a peer.

<diameter-peer-port>—Port of a Diameter peer.

<diameter-security>—Security used.

<diameter-process-summary-tags>

Usage <show-diameter-results>
 <diameter-process-summary-tags>
 <diameter-pid>*diameter-pid*</diameter-pid>
 <diameter-up-time>*diameter-up-time*</diameter-up-time>
 <diameter-peer-connected>*diameter-peer-connected*</diameter-peer-connected>
 <diameter-peer-closed>*diameter-peer-closed*</diameter-peer-closed>
 <diameter-peer-active>*diameter-peer-active*</diameter-peer-active>
 </diameter-process-summary-tags>
 </show-diameter-results>

Description Diameter process summary.

Contents <diameter-peer-active>—Number of Diameter peers currently active.
 <diameter-peer-closed>—Number of Diameter peers closed.
 <diameter-peer-connected>—Number of Diameter peers connected to the router.
 <diameter-pid>—Diameter process Id.
 <diameter-up-time>—Diameter process up time.

<diameter-statistics-tags>

Usage <show-diameter-results>
 <diameter-statistics-tags>
 <diameter-message-statistics-tags>...</diameter-message-statistics-tags>
 </diameter-statistics-tags>
 </show-diameter-results>

Description No documentation is available yet.

Contents <diameter-message-statistics-tags>—No documentation is available yet.

<show-diameter-peer-results>

Usage <rpc-reply>
 <show-diameter-peer-results>
 <diameter-peer-summary-tags>...</diameter-peer-summary-tags>
 <diameter-peer-session-tags>...</diameter-peer-session-tags>
 <diameter-peer-statistics-tags>...</diameter-peer-statistics-tags>
 </show-diameter-peer-results>
 </rpc-reply>

Description Show diameter peer information for a specific peer.

Contents <diameter-peer-session-tags>—No documentation is available yet.
 <diameter-peer-statistics-tags>—No documentation is available yet.
 <diameter-peer-summary-tags>—No documentation is available yet.

<show-diameter-results>

Usage <rpc-reply>
 <show-diameter-results>
 <diameter-process-summary-tags>...</diameter-process-summary-tags>
 <diameter-all-peer-summary-tags>...</diameter-all-peer-summary-tags>
 <diameter-all-peer-connection-tags>...</diameter-all-peer-connection-tags>
 <diameter-statistics-tags>...</diameter-statistics-tags>
 </show-diameter-results>
 </rpc-reply>

Description Show diameter information.

Contents <diameter-all-peer-connection-tags>—No documentation is available yet.
 <diameter-all-peer-summary-tags>—No documentation is available yet.
 <diameter-process-summary-tags>—Diameter process summary.
 <diameter-statistics-tags>—No documentation is available yet.

Summary of Dynamic Configuration Response Tags

This section lists JUNOS XML tags that contain operational information about dynamic configuration. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-dynamic-configuration>. To review the DTD for the tags, see “DTD for Dynamic Configuration Response Tags” on page 1729.

<client-session-info>

Usage <dynamic-configuration-information>
<client-session-info>
 <accounting-session-id>*accounting-session-id*</accounting-session-id>
 <address-pool>*address-pool*</address-pool>
 <interface>*interface*</interface>
 <ip-address>*ip-address*</ip-address>
 <ip-address-mask>*ip-address-mask*</ip-address-mask>
 <ipv6-address>*ipv6-address*</ipv6-address>
 <ipv6-address-mask>*ipv6-address-mask*</ipv6-address-mask>
 <logical-system>*logical-system*</logical-system>
 <profile>*profile*</profile>
 <mac-address>*mac-address*</mac-address>
 <nas-port-type>*nas-port-type*</nas-port-type>
 <routing-instance>*routing-instance*</routing-instance>
 <session-id>*session-id*</session-id>
 <client-session-type>*client-session-type*</client-session-type>
 <user-name>*user-name*</user-name>
 <dhcp-gi-address>*dhcp-gi-address*</dhcp-gi-address>
 <ifl-type>*ifl-type*</ifl-type>
 <service-bundle>*service-bundle*</service-bundle>
 <state>*state*</state>
 <dynamic-configuration-info>...</dynamic-configuration-info>
 <session-ids>...</session-ids>
</client-session-info>
 </dynamic-configuration-information>

Description Client session information.

Contents <accounting-session-id>—Radius accounting session ID.

<address-pool>—Address pool name.

<client-session-type>—Session type.

<dhcp-gi-address>—DHCP relay agent IP address.

<dynamic-configuration-info>—Dynamic configuration.

<ifl-type>—IFL type.

<interface>—Interface name.

<ip-address>—IP address.

<ip-address-mask>—IP netmask.

<ipv6-address>—IPv6 address.

<ipv6-address-mask>—IPv6 netmask.

<logical-system>—Logical system name.

<mac-address>—MAC address.

<nas-port-type>—NAS port type.

<profile>—Profile name.

<routing-instance>—Routing instance name.

<service-bundle>—Service bundle.

<session-id>—Session ID.

<session-ids>—Session IDs.

<state>—State.

<user-name>—User name.

<dynamic-configuration-attribute>

Usage <dynamic-configuration-info>
 <dynamic-configuration-attribute>
 <attribute-name>*attribute-name*</attribute-name>
 <attribute-value>*attribute-value*</attribute-value>
 </dynamic-configuration-attribute>
 </dynamic-configuration-info>

Description Dynamic configuration attribute.

Contents <attribute-name>—Dynamic configuration attribute name.

<attribute-value>—Dynamic configuration attribute value.

<dynamic-configuration-info>

Usage <client-session-info | service-session-info>
 <dynamic-configuration-info>
 <dynamic-configuration-attribute>...</dynamic-configuration-attribute>
 </dynamic-configuration-info>
 </client-session-info | service-session-info>

Description Dynamic configuration.

Contents <dynamic-configuration-attribute>—Dynamic configuration attribute.

<dynamic-configuration-information>

Usage <rpc-reply>
 <dynamic-configuration-information>
 <session-ids>...</session-ids>
 <client-session-info>...</client-session-info>
 <service-session-info>...</service-session-info>
 <results>...</results>
 <profile-results>...</profile-results>
 </dynamic-configuration-information>
 </rpc-reply>

Description Dynamic configuration command information.

Contents <client-session-info>—Client session information.

<profile-results>—No documentation is available yet.

<results>—Result for dynamic configuration operation command.

<service-session-info>—Service session information.

<session-ids>—Session IDs.

<profile-results>

Usage <dynamic-configuration-information>
 <profile-results>
 <profile-name>*profile-name*</profile-name>
 <profile-action>*profile-action*</profile-action>
 <session-id>*session-id*</session-id>
 <session-type>*session-type*</session-type>
 <request-result>*request-result*</request-result>
 <failure-reason>*failure-reason*</failure-reason>
 </profile-results>
 </dynamic-configuration-information>

Description No documentation is available yet.

Contents <failure-reason>—Problem collecting shm-ipc data.

<profile-action>—No documentation is available yet.

<profile-name>—No documentation is available yet.

<request-result>—No documentation is available yet.

<session-id>—Session ID.

<session-type>—Session type if provide in command request.

<results>

Usage	<pre> <dynamic-configuration-information> <results> <action>action</action> <session-type>session-type</session-type> <session-id>session-id</session-id> <success/> <failure>failure</failure> </results> </dynamic-configuration-information> </pre>
Description	Result for dynamic configuration operation command.
Contents	<p><action>—Dynamic configuration action.</p> <p><failure>—Dynamic configuration operation failed.</p> <p><session-id>—Session ID.</p> <p><session-type>—Session type if provide in command request.</p> <p><success>—Dynamic configuration operation succeed.</p>

<service-session-info>

Usage	<pre> <dynamic-configuration-information> <service-session-info> <session-id>session-id</session-id> <start-time>start-time</start-time> <service-name>service-name</service-name> <agg-type>agg-type</agg-type> <state>state</state> <dynamic-configuration-info>...</dynamic-configuration-info> </service-session-info> </dynamic-configuration-information> </pre>
Description	Service session information.
Contents	<p><agg-type>—Multi-client IFL.</p> <p><dynamic-configuration-info>—Dynamic configuration.</p> <p><service-name>—Service name.</p> <p><session-id>—Session ID.</p> <p><start-time>—Time when the client logged in, in the format YY-MM-DD hh:mm:ss.</p> <p><state>—State.</p>

<session-ids>

Usage	<pre><dynamic-configuration-information client-session-info> <session-ids> <session-id>session-id</session-id> </session-ids> </dynamic-configuration-information client-session-info></pre>
Description	Session IDs.
Contents	<session-id>—Session ID.

<shm-ipc-statistics>

Usage <rpc-reply>
 <shm-ipc-statistics>
 <producer-name>*producer-name*</producer-name>
 <producer-number>*producer-number*</producer-number>
 <consumer-name>*consumer-name*</consumer-name>
 <backpressure>*backpressure*</backpressure>
 <telluser>*telluser*</telluser>
 <telluser_failed>*telluser_failed*</telluser_failed>
 <malformed-msgs>*malformed-msgs*</malformed-msgs>
 <failure-reason>*failure-reason*</failure-reason>
 <blank-err-str-name>*blank-err-str-name*</blank-err-str-name>
 <blank-err-string>*blank-err-string*</blank-err-string>
 <blank-err-int-name>*blank-err-int-name*</blank-err-int-name>
 <blank-err-int>*blank-err-int*</blank-err-int>
 </shm-ipc-statistics>
 </rpc-reply>

Description No documentation is available yet.

Contents <backpressure>—Backpressure.

<blank-err-int>—Reusable integer field.

<blank-err-int-name>—Reusable integer field title.

<blank-err-str-name>—Reusable string field title.

<blank-err-string>—Reusable string field.

<consumer-name>—Consumer Name.

<failure-reason>—Problem collecting shm-ipc data.

<malformed-msgs>—Malformed msgs.

<producer-name>—Producer Name.

<producer-number>—Producer ID.

<telluser>—User told.

<telluser_failed>—User told failed.

Summary of Dynamic Flow Capture Response Tags

This section lists JUNOS XML tags that contain operational information about dynamic flow capture (DFC). The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-dfc>. To review the DTD for the tags, see “DTD for Dynamic Flow Capture Response Tags” on page 1733.

<content-destination-information>

Usage <dfc-information>
 <content-destination-information>
 <capture-group-id>*capture-group-id*</capture-group-id>
 <content-destination-id>*content-destination-id*</content-destination-id>
 <criteria>*criteria*</criteria>
 <bandwidth>*bandwidth*</bandwidth>
 <average-bandwidth>*average-bandwidth*</average-bandwidth>
 <matched-packets>*matched-packets*</matched-packets>
 <matched-bytes>*matched-bytes*</matched-bytes>
 <dropped-packets>*dropped-packets*</dropped-packets>
 <congestion-notifications>*congestion-notifications*</congestion-notifications>
 </content-destination-information>
 </dfc-information>

Description No documentation is available yet.

Contents <average-bandwidth>—Average bandwidth.
 <bandwidth>—Total bandwidth.
 <capture-group-id>—No documentation is available yet.
 <congestion-notifications>—Number of congestion notifications.
 <content-destination-id>—No documentation is available yet.
 <criteria>—Number of criteria.
 <dropped-packets>—Number of dropped packets.
 <matched-bytes>—Matched bytes processed.
 <matched-packets>—Matched packets processed.

<control-source-information>**Usage** <dfc-information>**<control-source-information>**

```

<capture-group-id>capture-group-id</capture-group-id>
<control-source-id>control-source-id</control-source-id>
<criteria-added>criteria-added</criteria-added>
<criteria-add-failed>criteria-add-failed</criteria-add-failed>
<active-criteria>active-criteria</active-criteria>
<active-criteria-static>active-criteria-static</active-criteria-static>
<active-criteria-dynamic>active-criteria-dynamic</active-criteria-dynamic>
<control-protocol-requests>control-protocol-requests
    </control-protocol-requests>
<control-protocol-requests-add>control-protocol-requests-add
    </control-protocol-requests-add>
<control-protocol-requests-delete>control-protocol-requests-delete
    </control-protocol-requests-delete>
<control-protocol-requests-list>control-protocol-requests-list
    </control-protocol-requests-list>
<control-protocol-requests-refresh>control-protocol-requests-refresh
    </control-protocol-requests-refresh>
<control-protocol-requests-noop>control-protocol-requests-noop
    </control-protocol-requests-noop>
<control-protocol-requests-add-failed>control-protocol-requests-add-failed
    </control-protocol-requests-add-failed>
<control-protocol-requests-delete-failed>control-protocol-requests-delete-failed
    </control-protocol-requests-delete-failed>
<control-protocol-requests-list-failed>control-protocol-requests-list-failed
    </control-protocol-requests-list-failed>
<control-protocol-requests-refresh-failed>control-protocol-requests-refresh-failed
    </control-protocol-requests-refresh-failed>
<control-protocol-requests-noop-failed>control-protocol-requests-noop-failed
    </control-protocol-requests-noop-failed>
<add-request-rate>add-request-rate</add-request-rate>
<add-request-peak-rate>add-request-peak-rate</add-request-peak-rate>
<bandwidth-all>bandwidth-all</bandwidth-all>
<notifications>notifications</notifications>
<notifications-restart>notifications-restart</notifications-restart>
<notifications-rollover>notifications-rollover</notifications-rollover>
<notifications-noop>notifications-noop</notifications-noop>
<notifications-timeout>notifications-timeout</notifications-timeout>
<notifications-congestion>notifications-congestion</notifications-congestion>
<notifications-congestion-delete>notifications-congestion-delete
    </notifications-congestion-delete>
<notifications-dups-dropped>notifications-dups-dropped
    </notifications-dups-dropped>
<criteria-deleted>criteria-deleted</criteria-deleted>
<criteria-deleted-timeout-idle>criteria-deleted-timeout-idle
    </criteria-deleted-timeout-idle>
<criteria-deleted-timeout-total>criteria-deleted-timeout-total
    </criteria-deleted-timeout-total>
<criteria-deleted-packets>criteria-deleted-packets</criteria-deleted-packets>
<criteria-deleted-bytes>criteria-deleted-bytes</criteria-deleted-bytes>
<sequence-number>sequence-number</sequence-number>

```

```

    </control-source-information>
  </dfc-information>

```

Description No documentation is available yet.

Contents

- <active-criteria>—Total number of active criteria.
- <active-criteria-dynamic>—Number of dynamic criteria.
- <active-criteria-static>—Number of static criteria.
- <add-request-peak-rate>—Peak process rate of add requests.
- <add-request-rate>—Process rate of add requests.
- <bandwidth-all>—Total bandwidth across all criteria.
- <capture-group-id>—No documentation is available yet.
- <control-protocol-requests>—Total number of protocol requests.
- <control-protocol-requests-add>—Number of add requests.
- <control-protocol-requests-add-failed>—Number of failed add requests.
- <control-protocol-requests-delete>—Number of delete requests.
- <control-protocol-requests-delete-failed>—Number of failed delete requests.
- <control-protocol-requests-list>—Number of list requests.
- <control-protocol-requests-list-failed>—Number of failed list requests.
- <control-protocol-requests-noop>—Number of no-op requests.
- <control-protocol-requests-noop-failed>—Number of failed no-op requests.
- <control-protocol-requests-refresh>—Number of refresh requests.
- <control-protocol-requests-refresh-failed>—Number of failed refresh requests.
- <control-source-id>—No documentation is available yet.
- <criteria-add-failed>—Number of failures to add criteria.
- <criteria-added>—Number of criteria added.
- <criteria-deleted>—Number of criteria deleted.
- <criteria-deleted-bytes>—Number of criteria deleted by bytes.
- <criteria-deleted-packets>—Number of criteria deleted by packets.
- <criteria-deleted-timeout-idle>—Number of criteria deleted by timeout idle.
- <criteria-deleted-timeout-total>—Number of criteria deleted by timeout total.

<notifications>—Total number of notifications.

<notifications-congestion>—Number of congestion notifications.

<notifications-congestion-delete>—Number of congestion delete notifications.

<notifications-dups-dropped>—Number notifications that duplicate packets were dropped.

<notifications-noop>—Number of no-op notifications.

<notifications-restart>—Number of restart notifications.

<notifications-rollover>—Number of rollover notifications.

<notifications-timeout>—Number of timeout notifications.

<sequence-number>—Protocol sequence number.

<dfc-information>

Usage <rpc-reply>
 <dfc-information>
 <control-source-information>...</control-source-information>
 <content-destination-information>...</content-destination-information>
 <dfc-statistics-information>...</dfc-statistics-information>
 </dfc-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <content-destination-information>—No documentation is available yet.
 <control-source-information>—No documentation is available yet.
 <dfc-statistics-information>—No documentation is available yet.

<dfc-statistics-information>**Usage** <dfc-information>**<dfc-statistics-information>**

```

<capture-group-id>capture-group-id</capture-group-id>
<input-packets-control-protocol>input-packets-control-protocol
</input-packets-control-protocol>
<input-packets-cap-data>input-packets-cap-data</input-packets-cap-data>
<input-packets-control-iri>input-packets-control-iri
</input-packets-control-iri>
<input-packets-control-protocol-not-ip>input-packets-control-protocol-not-ip
</input-packets-control-protocol-not-ip>
<input-packets-control-protocol-not-udp>inp-pac-con-pro-not-udp
</input-packets-control-protocol-not-udp>
<input-packets-control-protocol-invalid-dest-ip>inp-pac-con-pro-invalid-dest-ip
</input-packets-control-protocol-invalid-dest-ip>
<input-packets-control-protocol-drop-other>input-packets-control-protocol-drop-other
</input-packets-control-protocol-drop-other>
<input-packets-control-protocol-drop-no-memory>inp-pac-con-pro-drop-no-memory
</input-packets-control-protocol-drop-no-memory>
<input-packets-control-protocol-drop-unauthorized>inp-pac-con-pro-drp-unauth
</input-packets-control-protocol-drop-unauthorized>
<input-packets-control-protocol-drop-bad-req>in-pa-co-pr-drp-bad-req
</input-packets-control-protocol-drop-bad-req>
<input-packets-control-protocol-drop-unknown-control-source>i-p-c-p-d-u-c-sr
</input-packets-control-protocol-drop-unknown-control-source>
<input-packets-control-protocol-drop-not-dtcp>in-packets-control-protocol-drop-not-dtcp
</input-packets-control-protocol-drop-not-dtcp>
<input-packets-control-protocol-drop-bad-cmdline>in-pa-cn-pr-drp-bad-cmdline
</input-packets-control-protocol-drop-bad-cmdline>
<input-packets-control-protocol-drop-bandwidth-exceeded>in-pac-con-pro-drop-bw-ex
</input-packets-control-protocol-drop-bandwidth-exceeded>
<input-packets-control-protocol-drop-rate-bandwidth-exceeded>i-p-c-p-d-r-b-ex
</input-packets-control-protocol-drop-rate-bandwidth-exceeded>
<input-packets-drop-unknown>input-packets-drop-uk
</input-packets-drop-unknown>
<input-packets-drop-cap-data-not-ipv4>input-packets-drop-cap-data-not-ipv4
</input-packets-drop-cap-data-not-ipv4>
<input-packets-drop-cap-data-too-small>input-packets-drop-cap-data-too-small
</input-packets-drop-cap-data-too-small>
<input-packets-drop-cap-data-drop>input-packets-drop-cap-data-drop
</input-packets-drop-cap-data-drop>
<input-packets-drop-cap-data-nomatch>input-packets-drop-cap-data-nomatch
</input-packets-drop-cap-data-nomatch>
<input-packets-drop-bandwidth-exceeded>input-packets-drop-bandwidth-exceeded
</input-packets-drop-bandwidth-exceeded>
<input-packets-drop-rate-bandwidth-exceeded>i-p-d-r-bw-ex
</input-packets-drop-rate-bandwidth-exceeded>
<output-packets-control-protocol>output-packets-control-protocol
</output-packets-control-protocol>
<output-packets-cap-data>output-packets-cap-data</output-packets-cap-data>
<output-packets-drop-control-protocol>output-packets-drop-control-protocol
</output-packets-drop-control-protocol>
<output-packets-drop-cap-data>ou-pa-dr-ca-da

```



```

        </output-packets-drop-cap-data>
    <flowstats-active-cache-entries-count>flowstats-active-cache-entries-count
        </flowstats-active-cache-entries-count>
    <flowstats-active-cache-usage-percentage>flowstats-active-cache-usage-percentage
        </flowstats-active-cache-usage-percentage>
    <flowstats-cache-entries-allocated>flowstats-cache-entries-allocated
        </flowstats-cache-entries-allocated>
    <flowstats-control-source-count>flowstats-control-source-count
        </flowstats-control-source-count>
    <flowstats-content-destination-count>flowstats-content-destination-count
        </flowstats-content-destination-count>
    <flowstats-criteria-count>flowstats-criteria-count</flowstats-criteria-count>
    <flowstats-maximum-criteria-matching-flow>fl-ma-cr-ma-fl
        </flowstats-maximum-criteria-matching-flow>
    <flowstats-purged-flows>fl-pu-fl</flowstats-purged-flows>
    <flowstats-maximum-filter-matching-packet>flowstats-max-filter-mg-pkt
        </flowstats-maximum-filter-matching-packet>
    </dfc-statistics-information>
</dfc-information>

```

Description No documentation is available yet.

Contents <capture-group-id>—No documentation is available yet.

<flowstats-active-cache-entries-count>—Number of active flow cache entries.

<flowstats-active-cache-usage-percentage>—Usage percentage of the current active flow cache.

<flowstats-cache-entries-allocated>—Total number of flow cache entries allocated.

<flowstats-content-destination-count>—Number of content destinations in the capture group.

<flowstats-control-source-count>—Number of control sources in the capture group.

<flowstats-criteria-count>—Number of criterias for the capture group.

<flowstats-maximum-criteria-matching-flow>—Maximum criteria matching one flow.

<flowstats-maximum-filter-matching-packet>—Maximum number of filters matched for one packet.

<flowstats-purged-flows>—Cached flows purged for memory.

<input-packets-cap-data>—Number of input captured data packets.

<input-packets-control-iri>—Number of input control IRI packets.

<input-packets-control-protocol>—Number of input control protocol packets.

<input-packets-control-protocol-drop-bad-cmdline>—Control protocol packets dropped with bad command line.

<input-packets-control-protocol-drop-bad-req>—Control protocol packets dropped due to bad request.

<input-packets-control-protocol-drop-bandwidth-exceeded>—Control protocol packets dropped due to exceeded bandwidth.

<input-packets-control-protocol-drop-no-memory>—Control protocol packets dropped due to no memory.

<input-packets-control-protocol-drop-not-dtcp>—Control protocol packets dropped since they are not DTCP.

<input-packets-control-protocol-drop-other>—Control protocol packets dropped with other reasons.

<input-packets-control-protocol-drop-rate-bandwidth-exceeded>—Control protocol packets drop rate due to exceeded bandwidth.

<input-packets-control-protocol-drop-unauthorized>—Control protocol packets dropped since they are unauthorized.

<input-packets-control-protocol-drop-unknown-control-source>—Control protocol packets dropped with unknown control source.

<input-packets-control-protocol-invalid-dest-ip>—Control protocol packets dropped since they have invalid destination IP address.

<input-packets-control-protocol-not-ip>—Control protocol packets dropped since they are not IP packets.

<input-packets-control-protocol-not-udp>—Control protocol packets dropped since they are not UDP packets.

<input-packets-drop-bandwidth-exceeded>—Input packets dropped due to exceeded bandwidth.

<input-packets-drop-cap-data-drop>—Input packets dropped due to captured data dropped.

<input-packets-drop-cap-data-nomatch>—Input packets dropped due to captured data not matched.

<input-packets-drop-cap-data-not-ipv4>—Input packets dropped since they are not IPv4 packets.

<input-packets-drop-cap-data-too-small>—Input packets dropped since they are too small.

<input-packets-drop-rate-bandwidth-exceeded>—Input packets drop rate due to exceeded bandwidth.

<input-packets-drop-unknown>—Input packets dropped since they are unknown packets.

<output-packets-cap-data>—Output captured data packets.

<output-packets-control-protocol>—Output control protocol packets.

<output-packets-drop-cap-data>—Output captured data packets dropped.

<output-packets-drop-control-protocol>—Output control protocol packets dropped.

Summary of Firewall Filter Response Tags

This section lists JUNOS XML tags that contain operational information about firewall filters. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-filter>. To review the DTD for the tags, see “DTD for Firewall Filter Response Tags” on page 1739.

<counter>

Usage	<pre> <filter-information firewall-prefix-action-information> <counter> <counter-name>counter-name</counter-name> <byte-count>byte-count</byte-count> <packet-count>packet-count</packet-count> </counter> </filter-information firewall-prefix-action-information> </pre>
Description	Counter information.
Contents	<pre> <byte-count>—Bytes counted. <counter-name>—Counter name. <packet-count>—Packets counted. </pre>

<filter-information>

Usage	<pre> <firewall-information> <filter-information> <filter-name>filter-name</filter-name> <counter>...</counter> <policer>...</policer> </filter-information> </firewall-information> </pre>
Description	Details of a firewall filter.
Contents	<pre> <counter>—Counter information. <filter-name>—Name of filter. <policer>—Policer information. </pre>

<firewall-information>

- Usage** <rpc-reply>
 <firewall-information>
 <filter-information>...</filter-information>
 </firewall-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <filter-information>—Details of a firewall filter.

<firewall-log-information>

- Usage** <rpc-reply>
 <firewall-log-information>
 <log-information>...</log-information>
 </firewall-log-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <log-information>—Details of a single firewall log entry.

<firewall-prefix-action-information>

- Usage** <rpc-reply>
 <firewall-prefix-action-information>
 <filter-name>*filter-name*</filter-name>
 <counter>...</counter>
 <policer>...</policer>
 </firewall-prefix-action-information>
 </rpc-reply>
- Description** Display prefix specific counter and policer statistics for a filter.
- Contents** <counter>—Counter information.
- <filter-name>—Name of filter.
- <policer>—Policer information.

<log-information>

Usage	<pre> <firewall-log-information> <log-information> <time>time</time> <filter-name>filter-name</filter-name> <action-name>action-name</action-name> <interface-name>interface-name</interface-name> <protocol-name>protocol-name</protocol-name> <source-address>source-address</source-address> <destination-address>destination-address</destination-address> <packet-length>packet-length</packet-length> <icmp-type>icmp-type</icmp-type> <icmp-code>icmp-code</icmp-code> </log-information> </firewall-log-information> </pre>
Description	Details of a single firewall log entry.
Contents	<p><action-name>—Filter action.</p> <p><destination-address>—Destination address.</p> <p><filter-name>—Name of filter.</p> <p><icmp-code>—ICMP code.</p> <p><icmp-type>—ICMP type.</p> <p><interface-name>—Name of interface.</p> <p><packet-length>—Packet length.</p> <p><protocol-name>—Name of protocol.</p> <p><source-address>—Source address.</p> <p><time>—Time of log.</p>

<policer>

Usage	<pre> <filter-information firewall-prefix-action-information> <policer> <policer-name>policer-name</policer-name> <packet-count>packet-count</packet-count> </policer> </filter-information firewall-prefix-action-information> </pre>
Description	Policer information.
Contents	<p><packet-count>—Packets counted.</p> <p><policer-name>—Name of this policer.</p>

Summary of Graceful Switchover Response Tags

This section lists JUNOS XML tags that contain operational information about graceful Routing Engine switchover. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-switchover>. To review the DTD for the tags, see “DTD for Graceful Switchover Response Tags” on page 1741.

<configuration-state>

- Usage** <switchover-information>
 <configuration-state>
 <configuration-ready/>
 <configuration-synchronizing/>
 <configuration-synchronize-error/>
 </configuration-state>
 </switchover-information>
- Description** No documentation is available yet.
- Contents** <configuration-ready>—Configuration database is synchronized with master.
 <configuration-synchronize-error>—Failure during configuration database synchronize.
 <configuration-synchronizing>—Synchronizing configuration database with master.

<multi-routing-engine-item>

- Usage** <multi-routing-engine-results>
 <multi-routing-engine-item>
 <re-name>re-name</re-name>
 <switchover-information>...</switchover-information>
 </multi-routing-engine-item>
 </multi-routing-engine-results>
- Description** No documentation is available yet.
- Contents** <re-name>—No documentation is available yet.
 <switchover-information>—No documentation is available yet.

<multi-routing-engine-results>

- Usage** <rpc-reply>
 <multi-routing-engine-results>
 <multi-routing-engine-item>...</multi-routing-engine-item>
 </multi-routing-engine-results>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <multi-routing-engine-item>—No documentation is available yet.

<peer-transition-state>

- Usage** <switchover-information>
 <peer-transition-state>
 <peer-connected/>
 <peer-in-steady-state/>
 </peer-transition-state>
 </switchover-information>
- Description** No documentation is available yet.
- Contents** <peer-connected>—Peer in switchover transition.
 <peer-in-steady-state>—Peer completed switchover transition.

<replication-state>

- Usage** <switchover-information>
 <replication-state>
 <replication-ready/>
 <replication-synchronizing/>
 <replication-error/>
 <replication-version-mismatch/>
 <replication-connection-error/>
 <replication-reconnect-error/>
 <replication-init-error/>
 </replication-state>
 </switchover-information>
- Description** No documentation is available yet.
- Contents** <replication-connection-error>—Master connection error.
 <replication-error>—Replicated and master kernels do not have identical state.
 <replication-init-error>—Error during initialization.
 <replication-ready>—Replicated kernel state is synchronized with master.
 <replication-reconnect-error>—Reconnect to master failed.
 <replication-synchronizing>—Replicated kernel is receiving state updates from master.
 <replication-version-mismatch>—Replicated and master kernels running incompatible versions.

<switchover-information>

- Usage** <multi-routing-engine-item>
 <switchover-information>
 <switchover-state>switchover-state</switchover-state>
 <switchover-mode>...</switchover-mode>
 <configuration-state>...</configuration-state>
 <replication-state>...</replication-state>
 <peer-transition-state>...</peer-transition-state>
 </switchover-information>
 </multi-routing-engine-item>
- Description** No documentation is available yet.
- Contents** <configuration-state>—No documentation is available yet.
 <peer-transition-state>—No documentation is available yet.
 <replication-state>—No documentation is available yet.
 <switchover-mode>—No documentation is available yet.
 <switchover-state>—No documentation is available yet.

<switchover-mode>

- Usage** <switchover-information>
 <switchover-mode>
 <multichassis-mode/>
 <gres-mode/>
 <unknown-mode/>
 </switchover-mode>
 </switchover-information>
- Description** No documentation is available yet.
- Contents** <gres-mode>—Kernel replication for graceful switchover.
 <multichassis-mode>—Kernel replication for multichassis.
 <unknown-mode>—Kernel replication for unknown mode.

Summary of Interface Metadata Response Tags

This section lists JUNOS XML tags that contain operational information about the interface metadata. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-interface-metadata>. To review the DTD for the tags, see “DTD for Interface Metadata Reponse Tags” on page 1801.

<channels>

Usage	<pre><interface> <channels> <subunit>subunit</subunit> </channels> </interface></pre>
Description	Channelized interface information.
Contents	<subunit>—Number of subunits for channelized interface.

<interface>

Usage	<pre><interface-metadata-information> <interface> <name>name</name> <long>long</long> <pics-per-slot>pics-per-slot</pics-per-slot> <ports-per-slot>ports-per-slot</ports-per-slot> <max-mtu>max-mtu</max-mtu> <flag>flag</flag> <channels>...</channels> <max-channelization>max-channelization</max-channelization> <product>product</product> </interface> </interface-metadata-information></pre>
Description	Information about an interface.
Contents	<p><channels>—Channelized interface information.</p> <p><flag>—Flags for this interface type.</p> <p><long>—Product number.</p> <p><max-channelization>—Maximum level of channelization.</p> <p><max-mtu>—Maximum mtu.</p> <p><name>—Product model number.</p> <p><pics-per-slot>—Number of pics allowed per nic.</p> <p><ports-per-slot>—Number of ports per pic.</p> <p><product>—Product(s) this interface is supported on.</p>

<interface-metadata-information>

Usage	<code><rpc-reply></code> <interface-metadata-information> <interface>...</interface> </interface-metadata-information> <code></rpc-reply></code>
Description	Information on one or more interfaces.
Contents	<interface>—Information about an interface.

Summary of Interface Response Tags

This section lists JUNOS XML tags that contain operational information about routing platform interfaces. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-interface>. To review the DTD for the tags, see “DTD for Interface Response Tags” on page 1743.

<active-alarms>

- Usage** <physical-interface | link-entry>
 <active-alarms>
 <type>type</type>
 <interface-alarms>...</interface-alarms>
 </active-alarms>
 </physical-interface | link-entry>
- Description** Media-specific defects that can render the interface unable to pass packets. When a defect persists for a certain amount of time, it is promoted to an alarm. Based on the router configuration, an alarm can ring the red or yellow alarm bell on the router, or the red or yellow alarm LED on the craft interface.
- Contents** <interface-alarms>—Container tag for interface alarms.
 <type>—Media type for associated interface alarms.

<active-defects>

- Usage** <physical-interface | link-entry>
 <active-defects>
 <type>type</type>
 <interface-alarms>...</interface-alarms>
 </active-defects>
 </physical-interface | link-entry>
- Description** Media-specific defects that can render the interface unable to pass packets. When a defect persists for a certain amount of time, it is promoted to an alarm. Based on the router configuration, an alarm can ring the red or yellow alarm bell on the router, or the red or yellow alarm LED on the craft interface.
- Contents** <interface-alarms>—Container tag for interface alarms.
 <type>—Media type for associated interface alarms.

<address-family>

Usage <logical-interface>
<address-family>

```

<compression-device-name>compression-device-name</compression-device-name>
  <address-family-name>address-family-name</address-family-name>
  <multilink-bundle-name>multilink-bundle-name</multilink-bundle-name>
  <as-bundle-name>as-bundle-name</as-bundle-name>
  <ae-bundle-name>ae-bundle-name</ae-bundle-name>
  <es-sa-name>es-sa-name</es-sa-name>
  <es-sa-fail-count>es-sa-fail-count</es-sa-fail-count>
  <es-sa-xmt-seq-num>es-sa-xmt-seq-num</es-sa-xmt-seq-num>
  <es-sa-recv-seq-num>es-sa-recv-seq-num</es-sa-recv-seq-num>
  <mtu>mtu</mtu>
  <address-family-flags>...</address-family-flags>
  <address-family-unnumbered>...</address-family-unnumbered>
  <arp-respond-any-local-address>arp-respond-any-local-address
    </arp-respond-any-local-address>
  <generation>generation</generation>
  <route-table>route-table</route-table>
  <filter-information>...</filter-information>
  <policer-information>...</policer-information>
  <interface-address>...</interface-address>
  <mac-validate-statistics>...</mac-validate-statistics>
  <route-rpf-statistics>...</route-rpf-statistics>
  <destination-class-statistics>...</destination-class-statistics>
  <source-class-statistics>...</source-class-statistics>
</address-family>
</logical-interface>

```

Description No documentation is available yet.

Contents <address-family-flags>—No documentation is available yet.

<address-family-name>—No documentation is available yet.

<address-family-unnumbered>—Information about an unnumbered address family.

<ae-bundle-name>—Name of the aggregated Ethernet bundle.

<arp-respond-any-local-address>—Respond to ARP requests for any local address.

<as-bundle-name>—Name of the aggregated SONET bundle for this address family.

<compression-device-name>—Name of the link service device.

<destination-class-statistics>—Destination class usage (DCU) statistics.

<es-sa-fail-count>—Number of failures for IPSec security association for this family.

<es-sa-name>—Name of the IPSec security association for this address family.

<es-sa-recv-seq-num>—Receive sequence number of IPSec security association family.

<es-sa-xmt-seq-num>—Transmit sequence number of IPSec security association family.

<filter-information>—No documentation is available yet.

<generation>—Generation number used to distinguish between successive instances of this interface.

<interface-address>—No documentation is available yet.

<mac-validate-statistics>—SRC MAC validate statistics.

<mtu>—MTU size on this interface.

<multilink-bundle-name>—Name of the multilink bundle for this address family.

<policer-information>—Interface policer information.

<route-rpf-statistics>—Unicast reverse-path forwarding (RPF) statistics.

<route-table>—No documentation is available yet.

<source-class-statistics>—Source class usage (SCU) statistics.

<address-family-flags>

Usage <address-family>
 <address-family-flags>
 <iff-none/>
 <iff-primary/>
 <iff-redirects/>
 <iff-no-redirects/>
 <iff-hard-down/>
 <iff-down/>
 <iff-up/>
 <iff-func1/>
 <iff-func2/>
 <iff-is-primary/>
 <iff-recv-options/>
 <iff-recv-ttl-exceeded/>
 <iff-dst-class-usage/>
 <iff-src-class-input/>
 <iff-src-class-output/>
 <iff-mtu-user-conf/>
 <iff-mac-validate-strict/>
 <iff-mac-validate-loose/>
 <iff-rpf-check/>
 <iff-rpf-loose-mode/>
 <iff-sample-input/>
 <iff-sample-output/>
 <iff-no-async-notification/>
 <iff-negotiate-address/>
 <iff-port-mode-trunk/>
 <iff-mtu-protocol-adj/>
 <iff-unnumbered/>
 <iff-tcc-mpls/>
 <iff-tcc-inet/>
 <iff-tcc-inet6/>
 <iff-tcc-iso/>
 <generic-value>generic-value</generic-value>
 </address-family-flags>
 </address-family>

Description No documentation is available yet.

Contents <generic-value>—Hexadecimal value of unknown flag bits.

<iff-down>—Protocol is inactive.

<iff-dst-class-usage>—Interface family is configured for DCU.

<iff-func1>—No documentation is available yet.

<iff-func2>—No documentation is available yet.

<iff-hard-down>—Protocol failed to negotiate correctly.

<iff-is-primary>—Interface is the primary one for the protocol.

<iff-mac-validate-loose>—Interface family is configured for loose mac-validate.

<iff-mac-validate-strict>—Interface family is configured for strict mac-validate.

<iff-mtu-protocol-adj>—MTU is adjusted by protocol.

<iff-mtu-user-conf>—Protocol MTU has been changed by configuration.

<iff-negotiate-address>—Get local address using IPCP address negotiation.

<iff-no-asynch-notification>—Do not send asynchronous notification upon link failure.

<iff-no-redirects>—Protocol redirects are disabled.

<iff-none>—No documentation is available yet.

<iff-port-mode-trunk>—Port mode is trunk.

<iff-primary>—Interface can be considered for selection as the primary family address.

<iff-recv-options>—Receive nonlocal options packets.

<iff-recv-ttl-exceeded>—Receive nonlocal TTL-exceeded packets.

<iff-redirects>—No documentation is available yet.

<iff-rpf-check>—Interface family is configured for unicast RPF.

<iff-rpf-loose-mode>—Interface family is configured for uRPF loose mode.

<iff-sample-input>—Interface family is configured to sample input packets.

<iff-sample-output>—Interface family is configured to sample output packets.

<iff-src-class-input>—Interface family is configured for SCU input.

<iff-src-class-output>—Interface family is configured for SCU output.

<iff-tcc-inet>—IP version 4 over translational cross-connect.

<iff-tcc-inet6>—IP version 6 over translational cross-connect.

<iff-tcc-iso>—International Organization for Standardization over translational cross-connect.

<iff-tcc-mpls>—Multiprotocol Label Switching over translational cross-connect.

<iff-unnumbered>—Unnumbered.

<iff-up>—Protocol is configured and operational.

<address-family-unnumbered>

Usage <address-family>
 <address-family-unnumbered>
 <unnumbered-family-donor-interface-name>*unnumbered-family-donor-interface-name*
 </unnumbered-family-donor-interface-name>
 <unnumbered-family-donor-interface-index>*unnumbered-family-donor-interface-index*
 </unnumbered-family-donor-interface-index>
 <unnumbered-family-preferred-source-address>*unnumbered-family-preferred-source-address*
 </unnumbered-family-preferred-source-address>
 </address-family-unnumbered>
 </address-family>

Description Information about an unnumbered address family.

Contents <unnumbered-family-donor-interface-index>—Donor interface index.
 <unnumbered-family-donor-interface-name>—Donor interface name.
 <unnumbered-family-preferred-source-address>—Unnumbered interface preferred
 source address.

<atm-cos-information>

Usage <virtual-circuit-information>
 <atm-cos-information>
 <vc-cos-mode>*vc-cos-mode*</vc-cos-mode>
 <atm-cos-queue>...</atm-cos-queue>
 </atm-cos-information>
 </virtual-circuit-information>

Description No documentation is available yet.

Contents <atm-cos-queue>—No documentation is available yet.
 <vc-cos-mode>—Virtual circuit CoS scheduling mode.

<atm-cos-plp-statistics>

Usage <atm-cos-queue>
 <atm-cos-plp-statistics>
 <atm-plp0-output-bytes>atm-plp0-output-bytes</atm-plp0-output-bytes>
 <atm-plp1-output-bytes>atm-plp1-output-bytes</atm-plp1-output-bytes>
 <atm-plp0-output-packets>atm-plp0-output-packets</atm-plp0-output-packets>
 <atm-plp1-output-packets>atm-plp1-output-packets</atm-plp1-output-packets>
 <atm-plp0-byte-drops>atm-plp0-byte-drops</atm-plp0-byte-drops>
 <atm-plp1-byte-drops>atm-plp1-byte-drops</atm-plp1-byte-drops>
 <atm-plp0-packet-drops>atm-plp0-packet-drops</atm-plp0-packet-drops>
 <atm-plp1-packet-drops>atm-plp1-packet-drops</atm-plp1-packet-drops>
 </atm-cos-plp-statistics>
 </atm-cos-queue>

Description No documentation is available yet.

Contents <atm-plp0-byte-drops>—No documentation is available yet.
 <atm-plp0-output-bytes>—No documentation is available yet.
 <atm-plp0-output-packets>—No documentation is available yet.
 <atm-plp0-packet-drops>—No documentation is available yet.
 <atm-plp1-byte-drops>—No documentation is available yet.
 <atm-plp1-output-bytes>—No documentation is available yet.
 <atm-plp1-output-packets>—No documentation is available yet.
 <atm-plp1-packet-drops>—No documentation is available yet.

<atm-cos-queue>

Usage <atm-cos-information>
 <atm-cos-queue>
 <atm-cos-queue-parameters>...</atm-cos-queue-parameters>
 <atm-cos-queue-statistics>...</atm-cos-queue-statistics>
 <atm-cos-plp-statistics>...</atm-cos-plp-statistics>
 </atm-cos-queue>
 </atm-cos-information>

Description No documentation is available yet.

Contents <atm-cos-plp-statistics>—No documentation is available yet.
 <atm-cos-queue-parameters>—No documentation is available yet.
 <atm-cos-queue-statistics>—No documentation is available yet.

<atm-cos-queue-parameters>

Usage <atm-cos-queue>
 <atm-cos-queue-parameters>
 <cos-forwarding-class-name>*cos-forwarding-class-name*
 </cos-forwarding-class-name>
 <cos-queue-number>*cos-queue-number*</cos-queue-number>
 <scheduling-priority>*scheduling-priority*</scheduling-priority>
 <transmit-weight-cells>*transmit-weight-cells*</transmit-weight-cells>
 <transmit-weight-percent>*transmit-weight-percent*</transmit-weight-percent>
 <epd-threshold>*epd-threshold*</epd-threshold>
 <epd-threshold-plp0>*epd-threshold-plp0*</epd-threshold-plp0>
 <epd-threshold-plp1>*epd-threshold-plp1*</epd-threshold-plp1>
 <linear-red-drop-profile>...</linear-red-drop-profile>
 </atm-cos-queue-parameters>
 </atm-cos-queue>

Description No documentation is available yet.

Contents <cos-forwarding-class-name>—Forwarding class name associated with queue.

<cos-queue-number>—Queue number.

<epd-threshold>—Early packet drop threshold.

<epd-threshold-plp0>—Early packet drop threshold for PLP 0.

<epd-threshold-plp1>—Early packet drop threshold for PLP 1.

<linear-red-drop-profile>—No documentation is available yet.

<scheduling-priority>—Scheduling priority.

<transmit-weight-cells>—Weight to apply to scheduling as number of cells.

<transmit-weight-percent>—Weight to apply to scheduling as fill percentage.

<atm-cos-queue-statistics>

Usage <atm-cos-queue>
 <atm-cos-queue-statistics>
 <atm-output-bytes>*atm-output-bytes*</atm-output-bytes>
 <atm-output-packets>*atm-output-packets*</atm-output-packets>
 <atm-packet-drops>*atm-packet-drops*</atm-packet-drops>
 </atm-cos-queue-statistics>
 </atm-cos-queue>

Description No documentation is available yet.

Contents <atm-output-bytes>—No documentation is available yet.

<atm-output-packets>—No documentation is available yet.

<atm-packet-drops>—No documentation is available yet.

<atm-defects>

Usage <atm-information>
 <atm-defects>
 <media-alarm>...</media-alarm>
 </atm-defects>
 </atm-information>

Description No documentation is available yet.

Contents <media-alarm>—No documentation is available yet.

<atm-information>

Usage <physical-interface>
 <atm-information>
 <plcp-defects>...</plcp-defects>
 <atm-defects>...</atm-defects>
 <plcp-statistics>...</plcp-statistics>
 <atm-hcs-state>*atm-hcs-state*</atm-hcs-state>
 <atm-loss-of-cell>*atm-loss-of-cell*</atm-loss-of-cell>
 <atm-statistics>...</atm-statistics>
 </atm-information>
 </physical-interface>

Description Operational information and statistics for ATM interfaces.

Contents <atm-defects>—No documentation is available yet.

<atm-hcs-state>—No documentation is available yet.

<atm-loss-of-cell>—No documentation is available yet.

<atm-statistics>—No documentation is available yet.

<plcp-defects>—No documentation is available yet.

<plcp-statistics>—No documentation is available yet.

<atm-statistics>

Usage <atm-information | virtual-circuit-information>
<atm-statistics>
 <uncorrectable-hcs-errors>*uncorrectable-hcs-errors*</uncorrectable-hcs-errors>
 <correctable-hcs-errors>*correctable-hcs-errors*</correctable-hcs-errors>
 <tx-cell-fifo-overruns>*tx-cell-fifo-overruns*</tx-cell-fifo-overruns>
 <rx-cell-fifo-overruns>*rx-cell-fifo-overruns*</rx-cell-fifo-overruns>
 <rx-cell-fifo-underruns>*rx-cell-fifo-underruns*</rx-cell-fifo-underruns>
 <rx-cell-count>*rx-cell-count*</rx-cell-count>
 <tx-cell-count>*tx-cell-count*</tx-cell-count>
 <tx-idle-cell-count>*tx-idle-cell-count*</tx-idle-cell-count>
 <vc-queue-drops>*vc-queue-drops*</vc-queue-drops>
 <no-buffers>*no-buffers*</no-buffers>
 <length-errors>*length-errors*</length-errors>
 <timeouts>*timeouts*</timeouts>
 <bundle-timeouts>*bundle-timeouts*</bundle-timeouts>
 <rx-invalid-vcs>*rx-invalid-vcs*</rx-invalid-vcs>
 <bad-crcs>*bad-crcs*</bad-crcs>
 <oam-cell-no-buffers>*oam-cell-no-buffers*</oam-cell-no-buffers>
</atm-statistics>
 </atm-information | virtual-circuit-information>

Description No documentation is available yet.

Contents <bad-crcs>—No documentation is available yet.
 <bundle-timeouts>—No documentation is available yet.
 <correctable-hcs-errors>—No documentation is available yet.
 <length-errors>—No documentation is available yet.
 <no-buffers>—No documentation is available yet.
 <oam-cell-no-buffers>—No documentation is available yet.
 <rx-cell-count>—No documentation is available yet.
 <rx-cell-fifo-overruns>—No documentation is available yet.
 <rx-cell-fifo-underruns>—No documentation is available yet.
 <rx-invalid-vcs>—No documentation is available yet.
 <timeouts>—No documentation is available yet.
 <tx-cell-count>—No documentation is available yet.
 <tx-cell-fifo-overruns>—No documentation is available yet.
 <tx-idle-cell-count>—No documentation is available yet.
 <uncorrectable-hcs-errors>—No documentation is available yet.

<vc-queue-drops>—No documentation is available yet.

<ber-threshold>

Usage	<pre> <physical-interface> <ber-threshold> <ber-sd>ber-sd</ber-sd> <ber-sf>ber-sf</ber-sf> </ber-threshold> </physical-interface> </pre>
Description	Bit error rate (BER) threshold for SONET interface.
Contents	<p><ber-sd>—BER-SD threshold.</p> <p><ber-sf>—BER-SF threshold.</p>

<bundle>

Usage	<pre> <multilink-traffic-statistics mlfr-uni-nni-traffic-statistics> <bundle> <multilink-frames>...</multilink-frames> <network-frames>...</network-frames> </bundle> </multilink-traffic-statistics mlfr-uni-nni-traffic-statistics> </pre>
Description	No documentation is available yet.
Contents	<p><multilink-frames>—Link-pic bound frame statistics for multilink bundles and classes.</p> <p><network-frames>—Internet/RE bound frame statistics for multilink bundles and classes.</p>

<bundle-detail>

Usage	<pre> <multilink-detail-statistics> <bundle-detail> <fragments>...</fragments> <non-fragments>...</non-fragments> <lfi>...</lfi> </bundle-detail> </multilink-detail-statistics> </pre>
Description	No documentation is available yet.
Contents	<p><fragments>—Fragment statistics for multilink bundles and classes.</p> <p><lfi>—LFI frame statistics for multilink bundles and classes.</p> <p><non-fragments>—Non-fragment statistics for multilink bundles and classes.</p>

<cds1-information>

- Usage** <physical-interface>
 <cds1-information>
 <interface-tx-queue>...</interface-tx-queue>
 </cds1-information>
 </physical-interface>
- Description** No documentation is available yet.
- Contents** <interface-tx-queue>—No documentation is available yet.

<cesopsn-information>

- Usage** <physical-interface>
 <cesopsn-information>
 <ce-packetization-latency>*ce-packetization-latency*</ce-packetization-latency>
 <ce-idle-pattern>*ce-idle-pattern*</ce-idle-pattern>
 <ce-jitter-buffer-packets>*ce-jitter-buffer-packets*</ce-jitter-buffer-packets>
 <ce-jitter-buffer-latency>*ce-jitter-buffer-latency*</ce-jitter-buffer-latency>
 <ce-jitter-buffer-auto-adjust>*ce-jitter-buffer-auto-adjust*
 </ce-jitter-buffer-auto-adjust>

 <ce-excessive-packet-loss-rate-sample-period>*ce-excessive-packet-loss-rate-sample-period*
 </ce-excessive-packet-loss-rate-sample-period>
 <ce-excessive-packet-loss-rate-threshold>*ce-excessive-packet-loss-rate-threshold*
 </ce-excessive-packet-loss-rate-threshold>
 </cesopsn-information>
 </physical-interface>
- Description** No documentation is available yet.
- Contents** <ce-excessive-packet-loss-rate-sample-period>—No documentation is available yet.
- <ce-excessive-packet-loss-rate-threshold>—No documentation is available yet.
- <ce-idle-pattern>—No documentation is available yet.
- <ce-jitter-buffer-auto-adjust>—No documentation is available yet.
- <ce-jitter-buffer-latency>—No documentation is available yet.
- <ce-jitter-buffer-packets>—No documentation is available yet.
- <ce-packetization-latency>—No documentation is available yet.

<chassis-queue-counters>

- Usage** <physical-interface>
 <chassis-queue-counters>
 <interface-chassis-cos-summary>...</interface-chassis-cos-summary>
 <queue>...</queue>
 </chassis-queue-counters>
 </physical-interface>
- Description** Chassis queue counter statistics.
- Contents** <interface-chassis-cos-summary>—Packet Forwarding Engine chassis forwarding class and queue information for an interface.
- <queue>—Counters for a single queue.

<class>

- Usage** <multilink-traffic-statistics>
 <class>
 <class-info>...</class-info>
 <multilink-frames>...</multilink-frames>
 <network-frames>...</network-frames>
 </class>
 </multilink-traffic-statistics>
- Description** Multilink class traffic statistics.
- Contents** <class-info>—Multilink class information.
- <multilink-frames>—Link-pic bound frame statistics for multilink bundles and classes.
- <network-frames>—Internet/RE bound frame statistics for multilink bundles and classes.

<class-detail>

- Usage** <multilink-detail-statistics>
 <class-detail>
 <class-info>...</class-info>
 <fragments>...</fragments>
 <non-fragments>...</non-fragments>
 </class-detail>
 </multilink-detail-statistics>
- Description** No documentation is available yet.
- Contents** <class-info>—Multilink class information.
- <fragments>—Fragment statistics for multilink bundles and classes.
- <non-fragments>—Non-fragment statistics for multilink bundles and classes.

<class-info>

Usage	<pre><class class-detail> <class-info> <multilink-class-id><i>multilink-class-id</i></multilink-class-id> </class-info> </class class-detail></pre>
Description	Multilink class information.
Contents	<multilink-class-id>—Multilink class ID.

<clocking-mode>

Usage	<pre><serial-information> <clocking-mode> <clock-mode><i>clock-mode</i></clock-mode> </clocking-mode> </serial-information></pre>
Description	No documentation is available yet.
Contents	<clock-mode>—No documentation is available yet.

<clocking-rate>

Usage	<pre><serial-information> <clocking-rate> <clock-rate><i>clock-rate</i></clock-rate> </clocking-rate> </serial-information></pre>
Description	No documentation is available yet.
Contents	<clock-rate>—Interface clock rate.

<controller>

Usage	<pre><interface-information> <controller> <name><i>name</i></name> <admin-status><i>admin-status</i></admin-status> <oper-status><i>oper-status</i></oper-status> </controller> </interface-information></pre>
Description	No documentation is available yet.
Contents	<p><admin-status>—Desired state of the interface.</p> <p><name>—Name of this item.</p> <p><oper-status>—Current operational state of the interface.</p>

<cos-information>

Usage <physical-interface>
 <cos-information>
 <cos-stream-information>...</cos-stream-information>
 </cos-information>
 </physical-interface>

Description Information about class-of-service configuration.

Contents <cos-stream-information>—Information about the traffic stream.

<cos-queue-configuration>

Usage	<pre> <cos-stream-information> <cos-queue-configuration> <cos-queue-number>cos-queue-number</cos-queue-number> <cos-queue-forwarding-class>cos-queue-forwarding-class </cos-queue-forwarding-class> <cos-queue-bandwidth>cos-queue-bandwidth</cos-queue-bandwidth> <cos-queue-bandwidth-remainder>cos-queue-bandwidth-remainder </cos-queue-bandwidth-remainder> <cos-queue-bandwidth-bps>cos-queue-bandwidth-bps</cos-queue-bandwidth-bps> <cos-queue-bandwidth-bps-remainder>cos-queue-bandwidth-bps-remainder </cos-queue-bandwidth-bps-remainder> <cos-queue-buffer>cos-queue-buffer</cos-queue-buffer> <cos-queue-buffer-remainder>cos-queue-buffer-remainder </cos-queue-buffer-remainder> <cos-queue-buffer-bytes>cos-queue-buffer-bytes</cos-queue-buffer-bytes> <cos-queue-priority>cos-queue-priority</cos-queue-priority> <cos-queue-limit>cos-queue-limit</cos-queue-limit> </cos-queue-configuration> </cos-stream-information> </pre>
Description	No documentation is available yet.
Contents	<p><cos-queue-bandwidth>—No documentation is available yet.</p> <p><cos-queue-bandwidth-bps>—No documentation is available yet.</p> <p><cos-queue-bandwidth-bps-remainder>—No documentation is available yet.</p> <p><cos-queue-bandwidth-remainder>—No documentation is available yet.</p> <p><cos-queue-buffer>—No documentation is available yet.</p> <p><cos-queue-buffer-bytes>—No documentation is available yet.</p> <p><cos-queue-buffer-remainder>—No documentation is available yet.</p> <p><cos-queue-forwarding-class>—No documentation is available yet.</p> <p><cos-queue-limit>—No documentation is available yet.</p> <p><cos-queue-number>—Queue number.</p> <p><cos-queue-priority>—No documentation is available yet.</p>

<cos-stream-information>

- Usage** <cos-information>
 <cos-stream-information>
 <cos-direction>*cos-direction*</cos-direction>
 <cos-queue-configuration>...</cos-queue-configuration>
 </cos-stream-information>
 </cos-information>
- Description** Information about the traffic stream.
- Contents** <cos-direction>—Direction of the traffic stream.
 <cos-queue-configuration>—No documentation is available yet.

<crtp>

- Usage** <multilink-traffic-statistics>
 <crtp>
 <crtp-sessions>...</crtp-sessions>
 <crtp-statistics>...</crtp-statistics>
 </crtp>
 </multilink-traffic-statistics>
- Description** No documentation is available yet.
- Contents** <crtp-sessions>—No documentation is available yet.
 <crtp-statistics>—No documentation is available yet.

<crtp-sessions>

- Usage** <crtp>
 <crtp-sessions>
 <input-frames>*input-frames*</input-frames>
 <output-frames>*output-frames*</output-frames>
 </crtp-sessions>
 </crtp>
- Description** No documentation is available yet.
- Contents** <input-frames>—No documentation is available yet.
 <output-frames>—No documentation is available yet.

<crtp-statistics>

Usage <crtp>
 <crtp-statistics>
 <name>*name*</name>
 <input-frames>*input-frames*</input-frames>
 <input-fps>*input-fps*</input-fps>
 <input-bytes>*input-bytes*</input-bytes>
 <input-bps>*input-bps*</input-bps>
 <output-frames>*output-frames*</output-frames>
 <output-fps>*output-fps*</output-fps>
 <output-bytes>*output-bytes*</output-bytes>
 <output-bps>*output-bps*</output-bps>
 </crtp-statistics>
 </crtp>

Description No documentation is available yet.

Contents <input-bps>—No documentation is available yet.
 <input-bytes>—No documentation is available yet.
 <input-fps>—No documentation is available yet.
 <input-frames>—No documentation is available yet.
 <name>—Name of this item.
 <output-bps>—No documentation is available yet.
 <output-bytes>—No documentation is available yet.
 <output-fps>—No documentation is available yet.
 <output-frames>—No documentation is available yet.

<ct3-information>

Usage <physical-interface>
 <ct3-information>
 <interface-tx-queue>...</interface-tx-queue>
 </ct3-information>
 </physical-interface>

Description No documentation is available yet.

Contents <interface-tx-queue>—No documentation is available yet.

<data-signal>

- Usage** <serial-information>
 <data-signal>
 <rx-clock>*rx-clock*</rx-clock>
 </data-signal>
</serial-information>
- Description** No documentation is available yet.
- Contents** <rx-clock>—No documentation is available yet.

<demux-information>

- Usage** <logical-interface>
 <demux-information>
 <demux-interface>...</demux-interface>
 </demux-information>
</logical-interface>
- Description** Demux information.
- Contents** <demux-interface>—No documentation is available yet.

<demux-interface>

Usage <logical-interface | demux-information>
<demux-interface>
 <demux-underlying-interface-name>*demux-underlying-interface-name*
 </demux-underlying-interface-name>
 <demux-underlying-interface-index>*demux-underlying-interface-index*
 </demux-underlying-interface-index>
 <demux-inet-prefix-type>*demux-inet-prefix-type*</demux-inet-prefix-type>
 <demux-inet-prefix-count>*demux-inet-prefix-count*</demux-inet-prefix-count>
 <demux-inet-prefix>*demux-inet-prefix*</demux-inet-prefix>
 <demux-inet6-prefix-type>*demux-inet6-prefix-type*</demux-inet6-prefix-type>
 <demux-inet6-prefix-count>*demux-inet6-prefix-count*</demux-inet6-prefix-count>
 <demux-inet6-prefix>*demux-inet6-prefix*</demux-inet6-prefix>
</demux-interface>
 </logical-interface | demux-information>

Description No documentation is available yet.

Contents <demux-inet-prefix>—IPv4 Prefix.
 <demux-inet-prefix-count>—IPv4 Prefix count.
 <demux-inet-prefix-type>—Prefix type.
 <demux-inet6-prefix>—IPv6 Prefix.
 <demux-inet6-prefix-count>—IPv6 Prefix count.
 <demux-inet6-prefix-type>—Prefix type.
 <demux-underlying-interface-index>—Underlying interface index.
 <demux-underlying-interface-name>—Underlying interface name.

<destination-class>

Usage <destination-class-statistics>
 <destination-class>
 <dcu-class-name>*dcu-class-name*</dcu-class-name>
 <dcu-class-packets>*dcu-class-packets*</dcu-class-packets>
 <dcu-class-bytes>*dcu-class-bytes*</dcu-class-bytes>
 <dcu-class-pps>*dcu-class-pps*</dcu-class-pps>
 <dcu-class-bps>*dcu-class-bps*</dcu-class-bps>
 </destination-class>
 </destination-class-statistics>

Description DCU statistics for a single class.

Contents <dcu-class-bps>—Bit-per-seconds counted by DCU for this class.
 <dcu-class-bytes>—Number of bytes counted by DCU for this class.
 <dcu-class-name>—Name of DCU class.
 <dcu-class-packets>—Number of packets counted by DCU for this class.
 <dcu-class-pps>—Packet-per-seconds counted by DCU for this class.

<destination-class-statistics>

Usage <address-family>
 <destination-class-statistics>
 <destination-class>...</destination-class>
 </destination-class-statistics>
 </address-family>

Description Destination class usage (DCU) statistics.

Contents <destination-class>—DCU statistics for a single class.

<dial-string-list>

Usage <dialer-interface>
 <dial-string-list>
 <dial-string>*dial-string*</dial-string>
 </dial-string-list>
 </dialer-interface>

Description No documentation is available yet.

Contents <dial-string>—Dial string.

<dialer-information>

Usage	<pre> <logical-interface> <dialer-information> <dialer-interface>...</dialer-interface> <dialer-time-to-disconnect><i>dialer-time-to-disconnect</i> </dialer-time-to-disconnect> </dialer-information> </logical-interface> </pre>
Description	Dialer information.
Contents	<p><dialer-interface>—No documentation is available yet.</p> <p><dialer-time-to-disconnect>—Time for dialer to disconnect due to idle timeout.</p>

<dialer-interface>

Usage <dialer-interface-information | dialer-information>

```

<dialer-interface>
  <dialer-interface-name>dialer-interface-name</dialer-interface-name>
  <dialer-interface-state>dialer-interface-state</dialer-interface-state>
  <dialer-interface-flags>...</dialer-interface-flags>
  <pool-id>pool-id</pool-id>
  <primary-interface>primary-interface</primary-interface>
  <dial-string-list>...</dial-string-list>
  <sub-interface-list>...</sub-interface-list>
  <watch-list>...</watch-list>
  <activation-delay>activation-delay</activation-delay>
  <deactivation-delay>deactivation-delay</deactivation-delay>
  <activation-delay-elapsed>activation-delay-elapsed</activation-delay-elapsed>
  <deactivation-delay-elapsed>deactivation-delay-elapsed
    </deactivation-delay-elapsed>
  <call-idle-timeout>call-idle-timeout</call-idle-timeout>
  <initial-route-check>initial-route-check</initial-route-check>
  <redial-delay>redial-delay</redial-delay>
  <callback-wait-period>callback-wait-period</callback-wait-period>
  <callback-wait-period-elapsed>callback-wait-period-elapsed
    </callback-wait-period-elapsed>
  <load-threshold>load-threshold</load-threshold>
  <load-interval>load-interval</load-interval>
</dialer-interface>
</dialer-interface-information | dialer-information>

```

Description No documentation is available yet.

Contents

- <activation-delay>—Activation delay.
- <activation-delay-elapsed>—Activation delay elapsed.
- <call-idle-timeout>—Call idle timeout.
- <callback-wait-period>—Delay before dialer attempts callback (seconds).
- <callback-wait-period-elapsed>—Number of seconds in callback wait period that have elapsed.
- <deactivation-delay>—Deactivation delay.
- <deactivation-delay-elapsed>—Deactivation delay elapsed.
- <dial-string-list>—No documentation is available yet.
- <dialer-interface-flags>—Flags indicating interface configuration.
- <dialer-interface-name>—Interface name.
- <dialer-interface-state>—Dialer interface state.
- <initial-route-check>—Initial route check delay.

<load-interval>—Interval over which average load is calculated.

<load-threshold>—Load threshold that determines when interfaces are added to bundle.

<pool-id>—Pool identifier.

<primary-interface>—Primary interface.

<redial-delay>—Delay before dialer dials out again (seconds).

<sub-interface-list>—No documentation is available yet.

<watch-list>—No documentation is available yet.

<dialer-interface-flags>

Usage <dialer-interface>
 <dialer-interface-flags>
 <backup/>
 <multilink/>
 <watchlist/>
 <interesting-detected/>
 </dialer-interface-flags>
 </dialer-interface>

Description Flags indicating interface configuration.

Contents <backup>—Dialer backup.
 <interesting-detected>—Interesting packet detected.
 <multilink>—Dialer multilink.
 <watchlist>—Dialer watchlist.

<dialer-interface-information>

Usage <rpc-reply>
 <dialer-interface-information>
 <dialer-interface>...</dialer-interface>
 </dialer-interface-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <dialer-interface>—No documentation is available yet.

<dlci-statistics>

Usage <virtual-circuit-information>
 <dlci-statistics>
 <dlci-active>*dlci-active*</dlci-active>
 <dlci-inactive>*dlci-inactive*</dlci-inactive>
 </dlci-statistics>
</virtual-circuit-information>

Description DLCI statistics for an interface.

Contents <dlci-active>—Number of DLCIs in active state.
 <dlci-inactive>—Number of DLCIs in inactive state.

<ds0-bert-information>

Usage <physical-interface>
<ds0-bert-information>
 <ds0-bert-period>*ds0-bert-period*</ds0-bert-period>
 <ds0-bert-elapsed>*ds0-bert-elapsed*</ds0-bert-elapsed>
 <ds0-bert-status>*ds0-bert-status*</ds0-bert-status>
 <ds0-bert-algorithm>*ds0-bert-algorithm*</ds0-bert-algorithm>
 <ds0-bert-error-rate>*ds0-bert-error-rate*</ds0-bert-error-rate>
 <ds0-bert-induced-error-rate>*ds0-bert-induced-error-rate*
 </ds0-bert-induced-error-rate>
 <ds0-bert-bit-count>*ds0-bert-bit-count*</ds0-bert-bit-count>
 <ds0-bert-error-bit-count>*ds0-bert-error-bit-count*</ds0-bert-error-bit-count>
 <ds0-bert-los-status>*ds0-bert-los-status*</ds0-bert-los-status>
 <ds0-bert-los-count>*ds0-bert-los-count*</ds0-bert-los-count>
 <ds0-bert-los-seconds>*ds0-bert-los-seconds*</ds0-bert-los-seconds>
</ds0-bert-information>
 </physical-interface>

Description DS0 BERT configuration and statistics.

Contents <ds0-bert-algorithm>—No documentation is available yet.
 <ds0-bert-bit-count>—No documentation is available yet.
 <ds0-bert-elapsed>—No documentation is available yet.
 <ds0-bert-error-bit-count>—No documentation is available yet.
 <ds0-bert-error-rate>—No documentation is available yet.
 <ds0-bert-induced-error-rate>—No documentation is available yet.
 <ds0-bert-los-count>—No documentation is available yet.
 <ds0-bert-los-seconds>—No documentation is available yet.
 <ds0-bert-los-status>—No documentation is available yet.
 <ds0-bert-period>—No documentation is available yet.
 <ds0-bert-status>—No documentation is available yet.

<ds1-bert-information>

Usage <physical-interface>
 <ds1-bert-information>
 <ds1-bert-period>*ds1-bert-period*</ds1-bert-period>
 <ds1-bert-elapsed>*ds1-bert-elapsed*</ds1-bert-elapsed>
 <ds1-bert-status>*ds1-bert-status*</ds1-bert-status>
 <ds1-bert-algorithm>*ds1-bert-algorithm*</ds1-bert-algorithm>
 <ds1-bert-error-rate>*ds1-bert-error-rate*</ds1-bert-error-rate>
 <ds1-bert-induced-error-rate>*ds1-bert-induced-error-rate*
 </ds1-bert-induced-error-rate>
 <ds1-bert-bit-count>*ds1-bert-bit-count*</ds1-bert-bit-count>
 <ds1-bert-error-bit-count>*ds1-bert-error-bit-count*</ds1-bert-error-bit-count>
 <ds1-bert-los-status>*ds1-bert-los-status*</ds1-bert-los-status>
 <ds1-bert-los-count>*ds1-bert-los-count*</ds1-bert-los-count>
 <ds1-bert-los-seconds>*ds1-bert-los-seconds*</ds1-bert-los-seconds>
 </ds1-bert-information>
 </physical-interface>

Description DS1 BERT configuration and statistics.

Contents <ds1-bert-algorithm>—No documentation is available yet.
 <ds1-bert-bit-count>—No documentation is available yet.
 <ds1-bert-elapsed>—No documentation is available yet.
 <ds1-bert-error-bit-count>—No documentation is available yet.
 <ds1-bert-error-rate>—No documentation is available yet.
 <ds1-bert-induced-error-rate>—No documentation is available yet.
 <ds1-bert-los-count>—No documentation is available yet.
 <ds1-bert-los-seconds>—No documentation is available yet.
 <ds1-bert-los-status>—No documentation is available yet.
 <ds1-bert-period>—No documentation is available yet.
 <ds1-bert-status>—No documentation is available yet.

<ds1-crc-alarm-threshold>

Usage <physical-interface>
 <ds1-crc-alarm-threshold>
 <ds1-crc-alarm-threshold-major>*ds1-crc-alarm-threshold-major*
 </ds1-crc-alarm-threshold-major>
 <ds1-crc-alarm-threshold-minor>*ds1-crc-alarm-threshold-minor*
 </ds1-crc-alarm-threshold-minor>
 </ds1-crc-alarm-threshold>
 </physical-interface>

Description DS1 CRC alarm thresholds.

Contents <ds1-crc-alarm-threshold-major>—Threshold for CRC Major alarm.
 <ds1-crc-alarm-threshold-minor>—Threshold for CRC Minor alarm.

<ds3-bert-information>

Usage <physical-interface>
 <ds3-bert-information>
 <ds3-bert-period>ds3-bert-period</ds3-bert-period>
 <ds3-bert-elapsed>ds3-bert-elapsed</ds3-bert-elapsed>
 <ds3-bert-status>ds3-bert-status</ds3-bert-status>
 <ds3-bert-algorithm>ds3-bert-algorithm</ds3-bert-algorithm>
 <ds3-bert-error-rate>ds3-bert-error-rate</ds3-bert-error-rate>
 <ds3-bert-induced-error-rate>ds3-bert-induced-error-rate
 </ds3-bert-induced-error-rate>
 <ds3-bert-bit-count>ds3-bert-bit-count</ds3-bert-bit-count>
 <ds3-bert-bit-count-overflow>ds3-bert-bit-count-overflow
 </ds3-bert-bit-count-overflow>
 <ds3-bert-error-bit-count>ds3-bert-error-bit-count</ds3-bert-error-bit-count>
 <ds3-bert-error-bit-count-overflow>ds3-bert-error-bit-count-overflow
 </ds3-bert-error-bit-count-overflow>
 <ds3-bert-los-status>ds3-bert-los-status</ds3-bert-los-status>
 <ds3-bert-los-count>ds3-bert-los-count</ds3-bert-los-count>
 <ds3-bert-los-seconds>ds3-bert-los-seconds</ds3-bert-los-seconds>
 </ds3-bert-information>
 </physical-interface>

Description DS3 BERT configuration and statistics.

Contents <ds3-bert-algorithm>—No documentation is available yet.

<ds3-bert-bit-count>—No documentation is available yet.

<ds3-bert-bit-count-overflow>—No documentation is available yet.

<ds3-bert-elapsed>—No documentation is available yet.

<ds3-bert-error-bit-count>—No documentation is available yet.

<ds3-bert-error-bit-count-overflow>—No documentation is available yet.

<ds3-bert-error-rate>—No documentation is available yet.

<ds3-bert-induced-error-rate>—No documentation is available yet.

<ds3-bert-los-count>—No documentation is available yet.

<ds3-bert-los-seconds>—No documentation is available yet.

<ds3-bert-los-status>—No documentation is available yet.

<ds3-bert-period>—No documentation is available yet.

<ds3-bert-status>—No documentation is available yet.

<dsl-chipset-information>

Usage <dsl-information>
 <dsl-chipset-information>
 <atu-r-vendor-id>atu-r-vendor-id</atu-r-vendor-id>
 <atu-c-vendor-id>atu-c-vendor-id</atu-c-vendor-id>
 <atu-r-vendor-specific>atu-r-vendor-specific</atu-r-vendor-specific>
 <atu-c-vendor-specific>atu-c-vendor-specific</atu-c-vendor-specific>
 <atu-r-country-code>atu-r-country-code</atu-r-country-code>
 <atu-c-country-code>atu-c-country-code</atu-c-country-code>
 </dsl-chipset-information>
 </dsl-information>

Description No documentation is available yet.

Contents <atu-c-country-code>—Country code for ATU-C chipset vendor.
 <atu-c-vendor-id>—ATU-C ITU chipset vendor ID.
 <atu-c-vendor-specific>—ATU-C vendor-specific data.
 <atu-r-country-code>—Country code for ATU-R chipset vendor.
 <atu-r-vendor-id>—ATU-R ITU chipset vendor ID.
 <atu-r-vendor-specific>—ATU-R vendor-specific data.

<dsl-information>

Usage <physical-interface>
 <dsl-information>
 <dsl-line-status>*dsl-line-status*</dsl-line-status>
 <dsl-line-operating-mode>*dsl-line-operating-mode*</dsl-line-operating-mode>
 <dsl-line-type>*dsl-line-type*</dsl-line-type>
 <adsl-annex-type>*adsl-annex-type*</adsl-annex-type>
 <adsl-last-fail-code>*adsl-last-fail-code*</adsl-last-fail-code>
 <adsl-subfunction>*adsl-subfunction*</adsl-subfunction>
 <adsl-seconds-in-showtime>*adsl-seconds-in-showtime*</adsl-seconds-in-showtime>
 <dsl-chipset-information>...</dsl-chipset-information>
 <dsl-statistics>...</dsl-statistics>
 </dsl-information>
 </physical-interface>

Description Operational information and statistics for ADSL interfaces.

Contents <adsl-annex-type>—Type of ADSL annex.

<adsl-last-fail-code>—Reason for the last line-open failure.

<adsl-seconds-in-showtime>—Number of seconds the ADSL connection is in showtime state.

<adsl-subfunction>—Specified analog front-end chip and discrete front end.

<dsl-chipset-information>—No documentation is available yet.

<dsl-line-operating-mode>—Line type of digital subscriber line.

<dsl-line-status>—Status of modem.

<dsl-line-type>—Line type of digital subscriber line.

<dsl-statistics>—No documentation is available yet.

<dsl-statistics>

Usage <dsl-information>
<dsl-statistics>
 <near-end-attainable-bitrate>*near-end-attainable-bitrate*
 </near-end-attainable-bitrate>
 <far-end-attainable-bitrate>*far-end-attainable-bitrate*
 </far-end-attainable-bitrate>
 <near-end-attenuation>*near-end-attenuation*</near-end-attenuation>
 <far-end-attenuation>*far-end-attenuation*</far-end-attenuation>
 <near-end-capacity-used>*near-end-capacity-used*</near-end-capacity-used>
 <far-end-capacity-used>*far-end-capacity-used*</far-end-capacity-used>
 <near-end-noise-margin>*near-end-noise-margin*</near-end-noise-margin>
 <far-end-noise-margin>*far-end-noise-margin*</far-end-noise-margin>
 <near-end-output-power>*near-end-output-power*</near-end-output-power>
 <far-end-output-power>*far-end-output-power*</far-end-output-power>
 <interleaved-rx-cells>*interleaved-rx-cells*</interleaved-rx-cells>
 <fast-rx-cells>*fast-rx-cells*</fast-rx-cells>
 <interleaved-tx-cells>*interleaved-tx-cells*</interleaved-tx-cells>
 <fast-tx-cells>*fast-tx-cells*</fast-tx-cells>
 <near-end-interleaved-bitrate>*near-end-interleaved-bitrate*
 </near-end-interleaved-bitrate>
 <near-end-fast-bitrate>*near-end-fast-bitrate*</near-end-fast-bitrate>
 <far-end-interleaved-bitrate>*far-end-interleaved-bitrate*
 </far-end-interleaved-bitrate>
 <far-end-fast-bitrate>*far-end-fast-bitrate*</far-end-fast-bitrate>
 <near-end-interleaved-crc>*near-end-interleaved-crc*</near-end-interleaved-crc>
 <near-end-fast-crc>*near-end-fast-crc*</near-end-fast-crc>
 <far-end-interleaved-crc>*far-end-interleaved-crc*</far-end-interleaved-crc>
 <far-end-fast-crc>*far-end-fast-crc*</far-end-fast-crc>
 <near-end-interleaved-hec>*near-end-interleaved-hec*</near-end-interleaved-hec>
 <near-end-fast-hec>*near-end-fast-hec*</near-end-fast-hec>
 <far-end-interleaved-hec>*far-end-interleaved-hec*</far-end-interleaved-hec>
 <far-end-fast-hec>*far-end-fast-hec*</far-end-fast-hec>
 <near-end-interleaved-fec>*near-end-interleaved-fec*</near-end-interleaved-fec>
 <near-end-fast-fec>*near-end-fast-fec*</near-end-fast-fec>
 <far-end-interleaved-fec>*far-end-interleaved-fec*</far-end-interleaved-fec>
 <far-end-fast-fec>*far-end-fast-fec*</far-end-fast-fec>
 <near-end-interleaved-rx-cells>*near-end-interleaved-rx-cells*
 </near-end-interleaved-rx-cells>
 <near-end-fast-rx-cells>*near-end-fast-rx-cells*</near-end-fast-rx-cells>
 <near-end-interleaved-tx-cells>*near-end-interleaved-tx-cells*
 </near-end-interleaved-tx-cells>
 <near-end-fast-tx-cells>*near-end-fast-tx-cells*</near-end-fast-tx-cells>
</dsl-statistics>
 </dsl-information>

Description No documentation is available yet.

Contents <far-end-attainable-bitrate>—Far-end attainable bit rate.

<far-end-attenuation>—Far-end attenuation.

<far-end-capacity-used>—Far-end capacity used.

<far-end-fast-bitrate>—Far-end fast bit rate.

<far-end-fast-crc>—Far-end fast cyclic redundancy check.

<far-end-fast-fec>—Far-end fast footer error correction.

<far-end-fast-hec>—Far-end fast header error correction.

<far-end-interleaved-bitrate>—Far-end interleaved bit rate.

<far-end-interleaved-crc>—Far-end interleaved cyclic redundancy check correction.

<far-end-interleaved-fec>—Far-end interleaved footer error correction.

<far-end-interleaved-hec>—Far-end interleaved header error correction.

<far-end-noise-margin>—Far-end noise margin.

<far-end-output-power>—Far-end output power.

<fast-rx-cells>—Fast receiver cells.

<fast-tx-cells>—Fast transmitter cells.

<interleaved-rx-cells>—Interleaved receiver cells.

<interleaved-tx-cells>—Interleaved transmitter cells.

<near-end-attainable-bitrate>—Near-end attainable bit rate.

<near-end-attenuation>—Near-end attenuation.

<near-end-capacity-used>—Near-end capacity used.

<near-end-fast-bitrate>—Near-end fast bit rate.

<near-end-fast-crc>—Near-end fast cyclic redundancy check correction.

<near-end-fast-fec>—Near-end fast footer error correction.

<near-end-fast-hec>—Near-end fast header error correction.

<near-end-fast-rx-cells>—Near-end fast receiver cells.

<near-end-fast-tx-cells>—Near-end fast transmitter cells.

<near-end-interleaved-bitrate>—Near-end interleaved bit rate.

<near-end-interleaved-crc>—Near-end interleaved cyclic redundancy check correction.

<near-end-interleaved-fec>—Near-end interleaved footer error correction.

<near-end-interleaved-hec>—Near-end interleaved header error correction.

<near-end-interleaved-rx-cells>—Near-end interleaved receiver cells.

<near-end-interleaved-tx-cells>—Near-end interleaved transmitter cells.

<near-end-noise-margin>—Near-end noise margin.

<near-end-output-power>—Near-end output power.

<dsu-information>

Usage <physical-interface>
 <dsu-information>
 <dsu-compatibility-mode>*dsu-compatibility-mode*</dsu-compatibility-mode>
 <dsu-scrambler>*dsu-scrambler*</dsu-scrambler>
 <dsu-subrate>*dsu-subrate*</dsu-subrate>
 <feac-loopback>*feac-loopback*</feac-loopback>
 <feac-response>*feac-response*</feac-response>
 <feac-count>*feac-count*</feac-count>
 </dsu-information>
 </physical-interface>

Description DSU configuration and statistics.

Contents <dsu-compatibility-mode>—No documentation is available yet.
 <dsu-scrambler>—No documentation is available yet.
 <dsu-subrate>—No documentation is available yet.
 <feac-count>—No documentation is available yet.
 <feac-loopback>—No documentation is available yet.
 <feac-response>—No documentation is available yet.

<dtr-circuit>

Usage <serial-information>
 <dtr-circuit>
 <dtr-circuit-mode>*dtr-circuit-mode*</dtr-circuit-mode>
 </dtr-circuit>
 </serial-information>

Description No documentation is available yet.

Contents <dtr-circuit-mode>—No documentation is available yet.

<e3-bert-information>

Usage <physical-interface>
<e3-bert-information>
 <e3-bert-period>e3-bert-period</e3-bert-period>
 <e3-bert-elapsed>e3-bert-elapsed</e3-bert-elapsed>
 <e3-bert-status>e3-bert-status</e3-bert-status>
 <e3-bert-algorithm>e3-bert-algorithm</e3-bert-algorithm>
 <e3-bert-error-rate>e3-bert-error-rate</e3-bert-error-rate>
 <e3-bert-induced-error-rate>e3-bert-induced-error-rate
 </e3-bert-induced-error-rate>
 <e3-bert-bit-count>e3-bert-bit-count</e3-bert-bit-count>
 <e3-bert-bit-count-overflow>e3-bert-bit-count-overflow
 </e3-bert-bit-count-overflow>
 <e3-bert-error-bit-count>e3-bert-error-bit-count</e3-bert-error-bit-count>
 <e3-bert-error-bit-count-overflow>e3-bert-error-bit-count-overflow
 </e3-bert-error-bit-count-overflow>
 <e3-bert-los-status>e3-bert-los-status</e3-bert-los-status>
 <e3-bert-los-count>e3-bert-los-count</e3-bert-los-count>
 <e3-bert-los-seconds>e3-bert-los-seconds</e3-bert-los-seconds>
</e3-bert-information>
 </physical-interface>

Description E3 BERT configuration and statistics.

Contents <e3-bert-algorithm>—No documentation is available yet.
 <e3-bert-bit-count>—No documentation is available yet.
 <e3-bert-bit-count-overflow>—No documentation is available yet.
 <e3-bert-elapsed>—No documentation is available yet.
 <e3-bert-error-bit-count>—No documentation is available yet.
 <e3-bert-error-bit-count-overflow>—No documentation is available yet.
 <e3-bert-error-rate>—No documentation is available yet.
 <e3-bert-induced-error-rate>—No documentation is available yet.
 <e3-bert-los-count>—No documentation is available yet.
 <e3-bert-los-seconds>—No documentation is available yet.
 <e3-bert-los-status>—No documentation is available yet.
 <e3-bert-period>—No documentation is available yet.
 <e3-bert-status>—No documentation is available yet.

<eia530-control-signal>

Usage <serial-information>
 <eia530-control-signal>
 <mode>*mode*</mode>
 <to-dce>...</to-dce>
 <from-dce>...</from-dce>
 <to-dte>...</to-dte>
 <from-dte>...</from-dte>
 </eia530-control-signal>
 </serial-information>

Description No documentation is available yet.

Contents <from-dce>—No documentation is available yet.
 <from-dte>—No documentation is available yet.
 <mode>—No documentation is available yet.
 <to-dce>—No documentation is available yet.
 <to-dte>—No documentation is available yet.

<eia530-signal-polarity>

Usage <serial-information>
 <eia530-signal-polarity>
 <dtr-polarity>*dtr-polarity*</dtr-polarity>
 <rts-polarity>*rts-polarity*</rts-polarity>
 <dcd-polarity>*dcd-polarity*</dcd-polarity>
 <dsr-polarity>*dsr-polarity*</dsr-polarity>
 <cts-polarity>*cts-polarity*</cts-polarity>
 <tm-polarity>*tm-polarity*</tm-polarity>
 </eia530-signal-polarity>
 </serial-information>

Description No documentation is available yet.

Contents <cts-polarity>—No documentation is available yet.
 <dcd-polarity>—No documentation is available yet.
 <dsr-polarity>—No documentation is available yet.
 <dtr-polarity>—No documentation is available yet.
 <rts-polarity>—No documentation is available yet.
 <tm-polarity>—No documentation is available yet.

<es-ifd-stats>

Usage	<pre> <physical-interface> <es-ifd-stats> <total-anti-replay-count>total-anti-replay-count</total-anti-replay-count> <total-authentication-failure-count>total-authentication-failure-count </total-authentication-failure-count> </es-ifd-stats> </physical-interface> </pre>
Description	ES PIC statistics.
Contents	<p><total-anti-replay-count>—Number of antireplay failures.</p> <p><total-authentication-failure-count>—Number of authentication failures.</p>

<ether-policer-list>

Usage	<pre> <mac-policer-information> <ether-policer-list> <ether-policer-record>...</ether-policer-record> </ether-policer-list> </mac-policer-information> </pre>
Description	No documentation is available yet.
Contents	<ether-policer-record>—No documentation is available yet.

<ether-policer-record>

Usage	<pre> <ether-policer-list> <ether-policer-record> <policer-type>policer-type</policer-type> <out-of-spec-bytes>out-of-spec-bytes</out-of-spec-bytes> <out-of-spec-frames>out-of-spec-frames</out-of-spec-frames> </ether-policer-record> </ether-policer-list> </pre>
Description	No documentation is available yet.
Contents	<p><out-of-spec-bytes>—No documentation is available yet.</p> <p><out-of-spec-frames>—No documentation is available yet.</p> <p><policer-type>—No documentation is available yet.</p>

<ethernet-autonegotiation>

Usage <jswitch-port | physical-interface>
<ethernet-autonegotiation>
 <autonegotiation-status>*autonegotiation-status*</autonegotiation-status>
 <link-partner-status>*link-partner-status*</link-partner-status>
 <link-partner-reason>*link-partner-reason*</link-partner-reason>
 <link-partner-duplexity>*link-partner-duplexity*</link-partner-duplexity>
 <link-partner-speed>*link-partner-speed*</link-partner-speed>
 <flow-control>*flow-control*</flow-control>
 <local-info>...</local-info>
</ethernet-autonegotiation>
 </jswitch-port | physical-interface>

Description Ethernet autonegotiation information.

Contents <autonegotiation-status>—No documentation is available yet.

<flow-control>—No documentation is available yet.

<link-partner-duplexity>—No documentation is available yet.

<link-partner-reason>—Reason link partner is down.

<link-partner-speed>—Link partner speed.

<link-partner-status>—Auto-negotiation status of link partner.

<local-info>—Auto-negotiation status of local partner.

<ethernet-filter-statistics>

Usage <physical-interface>
<ethernet-filter-statistics>
 <input-packets>*input-packets*</input-packets>
 <input-reject-count>*input-reject-count*</input-reject-count>
 <input-reject-destination-address-count>*input-reject-destination-address-count*
 </input-reject-destination-address-count>
 <input-reject-source-address-count>*input-reject-source-address-count*
 </input-reject-source-address-count>
 <output-packets>*output-packets*</output-packets>
 <output-packet-pad-count>*output-packet-pad-count*</output-packet-pad-count>
 <output-packet-error-count>*output-packet-error-count*
 </output-packet-error-count>
 <cam-destination-filter-count>*cam-destination-filter-count*
 </cam-destination-filter-count>
 <cam-source-filter-count>*cam-source-filter-count*</cam-source-filter-count>
</ethernet-filter-statistics>
 </physical-interface>

Description Ethernet filter statistics.

Contents <cam-destination-filter-count>—No documentation is available yet.
 <cam-source-filter-count>—No documentation is available yet.
 <input-packets>—No documentation is available yet.
 <input-reject-count>—No documentation is available yet.
 <input-reject-destination-address-count>—No documentation is available yet.
 <input-reject-source-address-count>—No documentation is available yet.
 <output-packet-error-count>—No documentation is available yet.
 <output-packet-pad-count>—No documentation is available yet.
 <output-packets>—No documentation is available yet.

<ethernet-mac-statistics>

Usage <jswitch-port | physical-interface>

```

<ethernet-mac-statistics>
  <input-bytes>input-bytes</input-bytes>
  <input-packets>input-packets</input-packets>
  <input-unicasts>input-unicasts</input-unicasts>
  <input-broadcasts>input-broadcasts</input-broadcasts>
  <input-multicasts>input-multicasts</input-multicasts>
  <input-crc-errors>input-crc-errors</input-crc-errors>
  <input-fifo-errors>input-fifo-errors</input-fifo-errors>
  <input-mac-control-frames>input-mac-control-frames</input-mac-control-frames>
  <input-mac-pause-frames>input-mac-pause-frames</input-mac-pause-frames>
  <input-oversized-frames>input-oversized-frames</input-oversized-frames>
  <input-undersized-frames>input-undersized-frames</input-undersized-frames>
  <input-jabber-frames>input-jabber-frames</input-jabber-frames>
  <input-fragment-frames>input-fragment-frames</input-fragment-frames>
  <input-vlan-tagged-frames>input-vlan-tagged-frames</input-vlan-tagged-frames>
  <input-code-violations>input-code-violations</input-code-violations>
  <input-policer-frame-drops>input-policer-frame-drops
    </input-policer-frame-drops>
  <input-policer-byte-drops>input-policer-byte-drops</input-policer-byte-drops>
  <output-bytes>output-bytes</output-bytes>
  <output-packets>output-packets</output-packets>
  <output-unicasts>output-unicasts</output-unicasts>
  <output-broadcasts>output-broadcasts</output-broadcasts>
  <output-multicasts>output-multicasts</output-multicasts>
  <output-crc-errors>output-crc-errors</output-crc-errors>
  <output-fifo-errors>output-fifo-errors</output-fifo-errors>
  <output-mac-control-frames>output-mac-control-frames
    </output-mac-control-frames>
  <output-mac-pause-frames>output-mac-pause-frames</output-mac-pause-frames>
</ethernet-mac-statistics>
</jswitch-port | physical-interface>

```

Description Ethernet MAC statistics.

Contents <input-broadcasts>—No documentation is available yet.

<input-bytes>—No documentation is available yet.

<input-code-violations>—No documentation is available yet.

<input-crc-errors>—No documentation is available yet.

<input-fifo-errors>—Number of FIFO errors in the receive direction as reported by the ASIC on the PIC. If this value is nonzero, the PIC is probably broken.

<input-fragment-frames>—No documentation is available yet.

<input-jabber-frames>—No documentation is available yet.

<input-mac-control-frames>—No documentation is available yet.

<input-mac-pause-frames>—No documentation is available yet.

<input-multicasts>—No documentation is available yet.

<input-oversized-frames>—No documentation is available yet.

<input-packets>—No documentation is available yet.

<input-policer-byte-drops>—No documentation is available yet.

<input-policer-frame-drops>—No documentation is available yet.

<input-undersized-frames>—No documentation is available yet.

<input-unicasts>—No documentation is available yet.

<input-vlan-tagged-frames>—No documentation is available yet.

<output-broadcasts>—No documentation is available yet.

<output-bytes>—No documentation is available yet.

<output-crc-errors>—No documentation is available yet.

<output-fifo-errors>—No documentation is available yet.

<output-mac-control-frames>—No documentation is available yet.

<output-mac-pause-frames>—No documentation is available yet.

<output-multicasts>—No documentation is available yet.

<output-packets>—No documentation is available yet.

<output-unicasts>—No documentation is available yet.

<ethernet-pcs-statistics>

Usage <physical-interface>
 <ethernet-pcs-statistics>
 <bit-error-seconds>*bit-error-seconds*</bit-error-seconds>
 <errored-blocks-seconds>*errored-blocks-seconds*</errored-blocks-seconds>
 </ethernet-pcs-statistics>
 </physical-interface>

Description Ethernet PCS statistics.

Contents <bit-error-seconds>—Bit error duration.

<errored-blocks-seconds>—Errored blocks duration.

<filter-information>

Usage	<pre> <logical-interface address-family> <filter-information> <filter-family>filter-family</filter-family> <filter-input>filter-input</filter-input> <filter-input-precedence>filter-input-precedence</filter-input-precedence> <filter-output>filter-output</filter-output> <filter-output-precedence>filter-output-precedence</filter-output-precedence> </filter-information> </logical-interface address-family> </pre>
Description	No documentation is available yet.
Contents	<p><filter-family>—Protocol family of the filter.</p> <p><filter-input>—Name of the input filter.</p> <p><filter-input-precedence>—Precedence of the input filter.</p> <p><filter-output>—Name of the output filter.</p> <p><filter-output-precedence>—Precedence of the output filter.</p>

<fragments>

Usage <bundle-detail | class-detail>
<fragments>
 <input-frames>*input-frames*</input-frames>
 <input-fps>*input-fps*</input-fps>
 <input-bytes>*input-bytes*</input-bytes>
 <input-bps>*input-bps*</input-bps>
 <output-frames>*output-frames*</output-frames>
 <output-fps>*output-fps*</output-fps>
 <output-bytes>*output-bytes*</output-bytes>
 <output-bps>*output-bps*</output-bps>
</fragments>
 </bundle-detail | class-detail>

Description Fragment statistics for multilink bundles and classes.

Contents <input-bps>—No documentation is available yet.
 <input-bytes>—No documentation is available yet.
 <input-fps>—No documentation is available yet.
 <input-frames>—No documentation is available yet.
 <output-bps>—No documentation is available yet.
 <output-bytes>—No documentation is available yet.
 <output-fps>—No documentation is available yet.
 <output-frames>—No documentation is available yet.

<from-dce>

Usage	<pre> <eia530-control-signal> <from-dce> <dtr>dtr</dtr> <rts>rts</rts> <cts>cts</cts> <dcd>dcd</dcd> <dsr>dsr</dsr> <tm>tm</tm> </from-dce> </eia530-control-signal> </pre>
Description	No documentation is available yet.
Contents	<p><cts>—No documentation is available yet.</p> <p><dcd>—No documentation is available yet.</p> <p><dsr>—No documentation is available yet.</p> <p><dtr>—No documentation is available yet.</p> <p><rts>—No documentation is available yet.</p> <p><tm>—No documentation is available yet.</p>

<from-dte>

Usage	<pre> <eia530-control-signal> <from-dte> <dtr>dtr</dtr> <rts>rts</rts> <cts>cts</cts> <dcd>dcd</dcd> <dsr>dsr</dsr> <tm>tm</tm> </from-dte> </eia530-control-signal> </pre>
Description	No documentation is available yet.
Contents	<p><cts>—No documentation is available yet.</p> <p><dcd>—No documentation is available yet.</p> <p><dsr>—No documentation is available yet.</p> <p><dtr>—No documentation is available yet.</p> <p><rts>—No documentation is available yet.</p> <p><tm>—No documentation is available yet.</p>

<hdlc-information>

Usage <physical-interface>
 <hdlc-information>
 <hdlc-rx-bucket-state>*hdlc-rx-bucket-state*</hdlc-rx-bucket-state>
 <hdlc-rx-bit-rate>*hdlc-rx-bit-rate*</hdlc-rx-bit-rate>
 <hdlc-rx-threshold>*hdlc-rx-threshold*</hdlc-rx-threshold>
 <hdlc-tx-bit-rate>*hdlc-tx-bit-rate*</hdlc-tx-bit-rate>
 <hdlc-tx-bucket-state>*hdlc-tx-bucket-state*</hdlc-tx-bucket-state>
 <hdlc-tx-threshold>*hdlc-tx-threshold*</hdlc-tx-threshold>
 <hdlc-giant-threshold>*hdlc-giant-threshold*</hdlc-giant-threshold>
 <hdlc-runt-threshold>*hdlc-runt-threshold*</hdlc-runt-threshold>
 </hdlc-information>
 </physical-interface>

Description No documentation is available yet.

Contents <hdlc-giant-threshold>—No documentation is available yet.

<hdlc-runt-threshold>—No documentation is available yet.

<hdlc-rx-bit-rate>—No documentation is available yet.

<hdlc-rx-bucket-state>—No documentation is available yet.

<hdlc-rx-threshold>—No documentation is available yet.

<hdlc-tx-bit-rate>—No documentation is available yet.

<hdlc-tx-bucket-state>—No documentation is available yet.

<hdlc-tx-threshold>—No documentation is available yet.

<if-config-flags>

Usage <physical-interface | logical-interface>

```

<if-config-flags>
  <iff-none/>
  <iff-hardware-down/>
  <iff-down/>
  <iff-up/>
  <iff-admin-down/>
  <iff-admin-up/>
  <iff-link-down/>
  <iff-device-down/>
  <iff-point-to-point/>
  <iff-point-to-multipoint/>
  <plp-to-clp/>
  <iff-multiaccess/>
  <iff-change/>
  <iff-inverse-arp/>
  <iff-no-multicast/>
  <iff-multicast/>
  <iff-promiscuous/>
  <iff-all-multicast/>
  <iff-snmp-traps/>
  <iff-rx-passive/>
  <iff-tx-passive/>
  <iff-ccc-down/>
  <iff-clear-df/>
  <iff-tunnel-reassembly/>
  <iff-acfc/>
  <iff-pfc/>
  <iff-rdd/>
  <iff-looped/>
  <internal-flags>internal-flags</internal-flags>
</if-config-flags>
</physical-interface | logical-interface>

```

Description No documentation is available yet.

Contents <iff-acfc>—PPP Address/Control field compression is enabled.

<iff-admin-down>—Interface is in test mode, which means that some sanity checking, such as loop detection, is disabled.

<iff-admin-up>—No documentation is available yet.

<iff-all-multicast>—No multicast filtering (multicast promiscuous).

<iff-ccc-down>—CCC/TCC endpoint is down.

<iff-change>—No documentation is available yet.

<iff-clear-df>—Clear Don't-Fragment bit.

<iff-device-down>—No documentation is available yet.

<iff-down>—No documentation is available yet.

<iff-hardware-down>—Interface is nonfunctional or incorrectly connected.

<iff-inverse-arp>—No documentation is available yet.

<iff-link-down>—Interface keepalives have indicated that the link is incomplete.

<iff-looped>—Logical interface is looped.

<iff-multiaccess>—No documentation is available yet.

<iff-multicast>—No documentation is available yet.

<iff-no-multicast>—Interface does not support multicast traffic.

<iff-none>—No documentation is available yet.

<iff-pfc>—PPP Protocol field compression is enabled.

<iff-point-to-multipoint>—No documentation is available yet.

<iff-point-to-point>—Interface is point-to-point.

<iff-promiscuous>—Interface is in promiscuous mode and will see frames addressed to all physical addresses.

<iff-rdd>—Redundancy device.

<iff-rx-passive>—Receive is disabled.

<iff-snmp-traps>—SNMP traps are enabled.

<iff-tunnel-reassembly>—Perform reassembly.

<iff-tx-passive>—Transmit is disabled.

<iff-up>—Interface is enabled and operational.

<internal-flags>—Hexadecimal value of internal flag bits.

<plp-to-clp>—No documentation is available yet.

<if-device-flags>

Usage	<pre> <physical-interface> <if-device-flags> <ifdf-none/> <ifdf-present/> <ifdf-running/> <ifdf-duplex/> <ifdf-down/> <ifdf-no-carrier/> <ifdf-error1/> <ifdf-error2/> <ifdf-no-multicast/> <ifdf-loopback/> <ifdf-quench/> <ifdf-recv-all-multicasts/> <ifdf-promiscuous/> <ifdf-link-layer-down/> <ifdf-loop-detected/> <ifdf-pfe-gone/> <generic-value>generic-value</generic-value> </if-device-flags> </physical-interface> </pre>
Description	No documentation is available yet.
Contents	<p><generic-value>—Hexadecimal value of unknown flag bits.</p> <p><ifdf-down>—Device has been administratively disabled.</p> <p><ifdf-duplex>—Device will hear its own transmissions.</p> <p><ifdf-error1>—No documentation is available yet.</p> <p><ifdf-error2>—No documentation is available yet.</p> <p><ifdf-link-layer-down>—Link-layer protocol failed to connect successfully with the remote end point.</p> <p><ifdf-loop-detected>—Link layer has received frames that it sent and suspects a physical loopback.</p> <p><ifdf-loopback>—Device is in physical loopback.</p> <p><ifdf-no-carrier>—Where the media supports carrier recognition, this indicates that no carrier is currently seen.</p> <p><ifdf-no-multicast>—Device does not support multicast traffic.</p> <p><ifdf-none>—No documentation is available yet.</p> <p><ifdf-pfe-gone>—No documentation is available yet.</p> <p><ifdf-present>—Device is physically present and recognized.</p>

<ifdf-promiscuous>—Device is in promiscuous mode and will see frames addressed to all physical addresses on the media.

<ifdf-quench>—Device is quenched because it overran its output buffer.

<ifdf-recv-all-multicasts>—No multicast filtering (multicast promiscuous).

<ifdf-running>—Device is active and enabled.

<if-media-flags>

Usage	<pre> <physical-interface> <if-media-flags> <ifmf-none/> <ifmf-autoselect/> <ifmf-scheduler/> <ifmf-shared-scheduler/> <ifmf-keepalives/> <ifmf-no-keepalives/> <ifmf-give-up/> <ifmf-loose-lcp/> <ifmf-loose-ncp/> <ifmf-ppp-acfc/> <ifmf-ppp-pfc/> <ifmf-loose-lmi/> <ifmf-dce/> <ifmf-dte/> <generic-value>generic-value</generic-value> </if-media-flags> </physical-interface> </pre>
Description	No documentation is available yet.
Contents	<p><generic-value>—Hexadecimal value of unknown flag bits.</p> <p><ifmf-autoselect>—No documentation is available yet.</p> <p><ifmf-dce>—No documentation is available yet.</p> <p><ifmf-dte>—No documentation is available yet.</p> <p><ifmf-give-up>—Link protocol will not continue to retry to connect after repeated failures.</p> <p><ifmf-keepalives>—Link protocol keepalives are enabled.</p> <p><ifmf-loose-lcp>—PPP will not use LCP to indicate whether the link protocol is up.</p> <p><ifmf-loose-lmi>—Frame Relay will not use LMI to indicate whether the link protocol is up.</p> <p><ifmf-loose-ncp>—PPP will not use NCP to indicate whether the device is up.</p> <p><ifmf-no-keepalives>—Link protocol keepalives are disabled.</p> <p><ifmf-none>—No documentation is available yet.</p> <p><ifmf-ppp-acfc>—PPP negotiates Address/Control field compression.</p> <p><ifmf-ppp-pfc>—PPP negotiates Protocol field compression.</p> <p><ifmf-scheduler>—No documentation is available yet.</p> <p><ifmf-shared-scheduler>—No documentation is available yet.</p>

<ifa-flags>

Usage <interface-address>
 <ifa-flags>
 <ifaf-none/>
 <ifaf-primary/>
 <ifaf-preferred/>
 <ifaf-master-only/>
 <ifaf-down/>
 <ifaf-kernel/>
 <ifaf-current-default/>
 <ifaf-current-preferred/>
 <ifaf-current-primary/>
 <ifaf-duplicate/>
 <ifaf-webauth-http/>
 <generic-value>*generic-value*</generic-value>
 </ifa-flags>
 </interface-address>

Description No documentation is available yet.

Contents <generic-value>—Hexadecimal value of unknown flag bits.

<ifaf-current-default>—SNMP, ping, traceroute, and other network utilities source this address (it is the router's default address).

<ifaf-current-preferred>—Packets sourced by the local router to destinations on the subnet use this address as the default local address.

<ifaf-current-primary>—Broadcast and multicast packets sourced locally and sent out the interface use this address by default as the local address.

<ifaf-down>—Software noticed that the link was down and changed the interface routes to be nonforwarding.

<ifaf-duplicate>—This address appears on another node attached to this interface.

<ifaf-kernel>—The kernel created this address after negotiating the address using IPCP.

<ifaf-master-only>—Address to use as the active management-only interface of the master Routing Engine.

<ifaf-none>—No documentation is available yet.

<ifaf-preferred>—This address is a candidate to become the preferred address.

<ifaf-primary>—This address is a candidate to become the primary address.

<ifaf-webauth-http>—Web-based firewall user authentication via HTTP is enabled for this address.

<ifvc-flags>

Usage	<pre> <virtual-circuit-information> <ifvc-flags> <ifvc-down/> <ifvc-none/> <ifvc-active/> <ifvc-closed/> <ifvc-inverse-arp/> <ifvc-ilmi/> <ifvc-oam/> <ifvc-shaping/> <ifvc-passiveoam/> <ifvc-multicast/> <ifvc-ccc-down/> <ifvc-configured/> <ifvc-unconfigured/> <generic-value>generic-value</generic-value> </ifvc-flags> </virtual-circuit-information> </pre>
Description	No documentation is available yet.
Contents	<p><generic-value>—Hexadecimal value of unknown flag bits.</p> <p><ifvc-active>—No documentation is available yet.</p> <p><ifvc-ccc-down>—No documentation is available yet.</p> <p><ifvc-closed>—No documentation is available yet.</p> <p><ifvc-configured>—DCE-end is configured.</p> <p><ifvc-down>—No documentation is available yet.</p> <p><ifvc-ilmi>—No documentation is available yet.</p> <p><ifvc-inverse-arp>—No documentation is available yet.</p> <p><ifvc-multicast>—No documentation is available yet.</p> <p><ifvc-none>—No documentation is available yet.</p> <p><ifvc-oam>—No documentation is available yet.</p> <p><ifvc-passiveoam>—No documentation is available yet.</p> <p><ifvc-shaping>—No documentation is available yet.</p> <p><ifvc-unconfigured>—DCE-end is unconfigured.</p>

<ifvc-multipoint-destination>

Usage <virtual-circuit-information>
 <ifvc-multipoint-destination>
 <multipoint-address>*multipoint-address*</multipoint-address>
 </ifvc-multipoint-destination>
 </virtual-circuit-information>

Description No documentation is available yet.

Contents <multipoint-address>—Protocol address of the remote side of this connection.

<ifvp-flags>

Usage <virtual-path-information>
 <ifvp-flags>
 <ifvp-down/>
 <ifvp-none/>
 <ifvp-active/>
 <ifvp-closed/>
 <ifvp-oam/>
 <ifvp-shaping/>
 <ifvp-passiveoam/>
 <ifvp-tunnel/>
 <generic-value>*generic-value*</generic-value>
 </ifvp-flags>
 </virtual-path-information>

Description No documentation is available yet.

Contents <generic-value>—Hexadecimal value of unknown flag bits.

<ifvp-active>—No documentation is available yet.

<ifvp-closed>—No documentation is available yet.

<ifvp-down>—No documentation is available yet.

<ifvp-none>—No documentation is available yet.

<ifvp-oam>—No documentation is available yet.

<ifvp-passiveoam>—No documentation is available yet.

<ifvp-shaping>—No documentation is available yet.

<ifvp-tunnel>—No documentation is available yet.

<in-arp-statistics>

Usage <virtual-circuit-information | logical-interface>
<in-arp-statistics>
 <received-count>*received-count*</received-count>
 <transmitted-count>*transmitted-count*</transmitted-count>
 <denied-count>*denied-count*</denied-count>
 <operation-not-supported-count>*operation-not-supported-count*
 </operation-not-supported-count>
 <bad-packet-length-count>*bad-packet-length-count*</bad-packet-length-count>
 <bad-protocol-count>*bad-protocol-count*</bad-protocol-count>
 <bad-protocol-length-count>*bad-protocol-length-count*
 </bad-protocol-length-count>
 <bad-hardware-length-count>*bad-hardware-length-count*
 </bad-hardware-length-count>
 <dropped-count>*dropped-count*</dropped-count>
 <last-received>*last-received*</last-received>
 <last-transmitted>*last-transmitted*</last-transmitted>
</in-arp-statistics>
 </virtual-circuit-information | logical-interface>

Description Container tag for ARP statistics.

Contents <bad-hardware-length-count>—Number of ARPs with bad hardware length.
 <bad-packet-length-count>—Number of ARPs with bad packet length.
 <bad-protocol-count>—Number of ARPs with bad protocol.
 <bad-protocol-length-count>—Number of ARPs with bad protocol length.
 <denied-count>—Number of ARPs denied.
 <dropped-count>—Number of ARPs dropped.
 <last-received>—Time an ARP was last received.
 <last-transmitted>—Time an ARP was last sent.
 <operation-not-supported-count>—Number of ARPs with operation not supported.
 <received-count>—Number of ARPs received.
 <transmitted-count>—Number of ARPs sent.

<in6-addr-flags>

Usage <interface-address>
 <in6-addr-flags>
 <in6-anycast/>
 <in6-tentative/>
 <in6-duplicate/>
 <in6-detached/>
 <in6-deprecated/>
 <in6-nodad/>
 <in6-temporary/>
 <in6-autoconf/>
 <in6-nopfxmgt/>
 </in6-addr-flags>
 </interface-address>

Description No documentation is available yet.

Contents <in6-anycast>—No documentation is available yet.
 <in6-autoconf>—No documentation is available yet.
 <in6-deprecated>—No documentation is available yet.
 <in6-detached>—No documentation is available yet.
 <in6-duplicate>—No documentation is available yet.
 <in6-nodad>—No documentation is available yet.
 <in6-nopfxmgt>—No documentation is available yet.
 <in6-temporary>—No documentation is available yet.
 <in6-tentative>—No documentation is available yet.

<ingress-queue-counters>

Usage <logical-interface | physical-interface | interface-set-queue-information>
<ingress-queue-counters>
 <interface-chassis-cos-summary>...</interface-chassis-cos-summary>
 <queue>...</queue>
 <interface-cos-summary>...</interface-cos-summary>
 <interface-cos-short-summary>...</interface-cos-short-summary>
</ingress-queue-counters>
 </logical-interface | physical-interface | interface-set-queue-information>

Description Ingress queue counter statistics.

Contents <interface-chassis-cos-summary>—Packet Forwarding Engine chassis forwarding class and queue information for an interface.

<interface-cos-short-summary>—Summary of queue information on an interface.

<interface-cos-summary>—Summary of forwarding class and queue information on an interface.

<queue>—Counters for a single queue.

<ingress-traffic-statistics>

Usage <physical-interface | logical-interface>
<ingress-traffic-statistics>
 <input-bytes>*input-bytes*</input-bytes>
 <input-bps>*input-bps*</input-bps>
 <input-packets>*input-packets*</input-packets>
 <input-pps>*input-pps*</input-pps>
 <input-drop-bytes>*input-drop-bytes*</input-drop-bytes>
 <input-drop-packets>*input-drop-packets*</input-drop-packets>
 <input-drop-bps>*input-drop-bps*</input-drop-bps>
 <input-drop-pps>*input-drop-pps*</input-drop-pps>
</ingress-traffic-statistics>
 </physical-interface | logical-interface>

Description Number and rate of bytes and packets received in the ingress side at Packet Forwarding Engine.

Contents <input-bps>—No documentation is available yet.

<input-bytes>—No documentation is available yet.

<input-drop-bps>—Drop rate at ingress in bits per second .

<input-drop-bytes>—Drop statistics at ingress in bytes.

<input-drop-packets>—Drop statistics at ingress in packets.

<input-drop-pps>—Drop rate at ingress in packets per second .

<input-packets>—No documentation is available yet.

<input-pps>—No documentation is available yet.

<input-error-list>

Usage <physical-interface>
 <input-error-list>
 <input-errors>*input-errors*</input-errors>
 <input-drops>*input-drops*</input-drops>
 <invalid-vcs>*invalid-vcs*</invalid-vcs>
 <framing-errors>*framing-errors*</framing-errors>
 <input-runts>*input-runts*</input-runts>
 <input-giants>*input-giants*</input-giants>
 <input-bucket-drops>*input-bucket-drops*</input-bucket-drops>
 <input-discards>*input-discards*</input-discards>
 <input-l3-incompletes>*input-l3-incompletes*</input-l3-incompletes>
 <input-l2-channel-errors>*input-l2-channel-errors*</input-l2-channel-errors>
 <input-l2-mismatch-timeouts>*input-l2-mismatch-timeouts*
 </input-l2-mismatch-timeouts>
 <input-fifo-errors>*input-fifo-errors*</input-fifo-errors>
 <hs-link-crc-errors>*hs-link-crc-errors*</hs-link-crc-errors>
 <hs-link-fifo-overflows>*hs-link-fifo-overflows*</hs-link-fifo-overflows>
 <sram-errors>*sram-errors*</sram-errors>
 <input-resource-errors>*input-resource-errors*</input-resource-errors>
 </input-error-list>
 </physical-interface>

Description Input errors on this interface.

Contents <framing-errors>—No documentation is available yet.

<hs-link-crc-errors>—Count of errors on the high-speed links between the ASICs responsible for handling the router interfaces.

<hs-link-fifo-overflows>—Count of errors on the high-speed links between the ASICs responsible for handling the router interfaces.

<input-bucket-drops>—No documentation is available yet.

<input-discards>—Frames that the incoming packet match code discarded because they were not recognized or of interest. Usually, this field reports protocols that the JUNOS software does not handle, such as CDP.

<input-drops>—No documentation is available yet.

<input-errors>—Sum of the incoming frame aborts and FCS errors.

<input-fifo-errors>—Number of FIFO errors in the receive direction as reported by the ASIC on the PIC. If this value is nonzero, the PIC is probably broken.

<input-giants>—No documentation is available yet.

<input-l2-channel-errors>—This counter increments when the software cannot find a valid logical interface (for example, s0-6/0/3.0) for an incoming frame.

<input-l2-mismatch-timeouts>—Count of malformed or short packets that cause the incoming packet handler to discard the frame as unreadable.

<input-l3-incompletes>—This counter is incremented when the incoming packet fails Layer 3 (usually IPv4) sanity checks of the header. For example, a frame with less than 20 bytes of available IP header would be discarded and this counter would be incremented.

<input-resource-errors>—Sum of B chip Rx drops and IXP Rx net receive drops.

<input-runs>—No documentation is available yet.

<invalid-vcs>—No documentation is available yet.

<sram-errors>—No documentation is available yet.

<interface-address>

Usage `<address-family>`
<interface-address>
`<ifa-flags>...</ifa-flags>`
`<generation>generation</generation>`
`<ifa-destination>ifa-destination</ifa-destination>`
`<ifa-local>ifa-local</ifa-local>`
`<in6-addr-flags>...</in6-addr-flags>`
`<ifa-broadcast>ifa-broadcast</ifa-broadcast>`
`<ifa-primary-dns>ifa-primary-dns</ifa-primary-dns>`
`<ifa-primary-nbns>ifa-primary-nbns</ifa-primary-nbns>`
`<ifa-secondary-dns>ifa-secondary-dns</ifa-secondary-dns>`
`<ifa-secondary-nbns>ifa-secondary-nbns</ifa-secondary-nbns>`
`<ifa-address-pool>ifa-address-pool</ifa-address-pool>`
</interface-address>
`</address-family>`

Description No documentation is available yet.

Contents `<generation>`—Generation number used to distinguish between successive instances of this interface.

`<ifa-address-pool>`—Address pool name.

`<ifa-broadcast>`—Network broadcast address.

`<ifa-destination>`—Protocol address of the remote side of this connection.

`<ifa-flags>`—No documentation is available yet.

`<ifa-local>`—Protocol address on this interface.

`<ifa-primary-dns>`—Primary DNS server address.

`<ifa-primary-nbns>`—Primary Netbios Name server address.

`<ifa-secondary-dns>`—Secondary DNS server address.

`<ifa-secondary-nbns>`—Secondary Netbios Name server address.

`<in6-addr-flags>`—No documentation is available yet.

<interface-alarms>**Usage** <active-alarms | active-defects>**<interface-alarms>**

<alarm-not-present/>
 <sonet-alarm-lol/>
 <sonet-alarm-pll/>
 <sonet-alarm-lof/>
 <sonet-alarm-los/>
 <sonet-alarm-sef/>
 <sonet-alarm-lais/>
 <sonet-alarm-pais/>
 <sonet-alarm-lop/>
 <sonet-alarm-berr-sd/>
 <sonet-alarm-berr-sf/>
 <sonet-alarm-lrdi/>
 <sonet-alarm-prdi/>
 <sonet-alarm-rei/>
 <sonet-alarm-uneq/>
 <sonet-alarm-pmis/>
 <sonet-alarm-loc/>
 <sonet-alarm-vais/>
 <sonet-alarm-vlop/>
 <sonet-alarm-vrdi/>
 <sonet-alarm-vuneq/>
 <sonet-alarm-vmis/>
 <sonet-alarm-vloc/>
 <sdh-alarm-lol/>
 <sdh-alarm-pll/>
 <sdh-alarm-lof/>
 <sdh-alarm-los/>
 <sdh-alarm-oof/>
 <sdh-alarm-msais/>
 <sdh-alarm-hpais/>
 <sdh-alarm-lop/>
 <sdh-alarm-berr-sd/>
 <sdh-alarm-berr-sf/>
 <sdh-alarm-msferf/>
 <sdh-alarm-hpferf/>
 <sdh-alarm-hpfebe/>
 <sdh-alarm-hpuneq/>
 <sdh-alarm-hpplm/>
 <sdh-alarm-loc/>
 <sdh-alarm-tuais/>
 <sdh-alarm-tulop/>
 <sdh-alarm-turdi/>
 <sdh-alarm-tuuneq/>
 <sdh-alarm-tumis/>
 <sdh-alarm-tuloc/>
 <ds3-alarm-pll/>
 <ds3-alarm-ais/>
 <ds3-alarm-lof/>
 <ds3-alarm-los/>
 <ds3-alarm-lcv/>

```

<ds3-alarm-exz/>
<ds3-alarm-ferf/>
<ds3-alarm-ylw/>
<ds3-alarm-idle/>
<ds1-alarm-ais/>
<ds1-alarm-lof/>
<ds1-alarm-los/>
<ds1-alarm-ylw/>
<ds1-alarm-crc-major/>
<ds1-alarm-crc-minor/>
<dsl-alarm-lof/>
<dsl-alarm-los/>
<dsl-alarm-lom/>
<dsl-alarm-locdi/>
<dsl-alarm-locdni/>
<dsl-alarm-lop/>
<dsl-alarm-far-lof/>
<dsl-alarm-far-los/>
<dsl-alarm-far-locdi/>
<dsl-alarm-far-locdni/>
<ethernet-alarm-link-down/>
<ethernet-alarm-lcdp/>
<isdn-alarm-los/>
<isdn-alarm-lof/>
<shdsl-alarm-losd/>
<shdsl-alarm-losw/>
<shdsl-alarm-line1-losd/>
<shdsl-alarm-line1-losw/>
<shdsl-alarm-line2-losd/>
<shdsl-alarm-line2-losw/>
<generic-value>generic-value</generic-value>
</interface-alarms>
</active-alarms | active-defects>

```

Description Container tag for interface alarms.

Contents <alarm-not-present>—No alarm indicated.

<ds1-alarm-ais>—AIS alarm.

<ds1-alarm-crc-major>—CRC errors crossed major threshold.

<ds1-alarm-crc-minor>—CRC errors crossed minor threshold.

<ds1-alarm-lof>—Loss of frame alarm.

<ds1-alarm-los>—Loss of signal alarm.

<ds1-alarm-ylw>—Yellow alarm.

<ds3-alarm-ais>—AIS alarm.

<ds3-alarm-exz>—Excessive zeros alarm.

<ds3-alarm-ferf>—Far-end receive failure alarm.

<ds3-alarm-idle>—Idle alarm.

<ds3-alarm-lcv>—Line code violation alarm.

<ds3-alarm-lof>—Loss of frame alarm.

<ds3-alarm-los>—Loss of signal alarm.

<ds3-alarm-pll>—PLL lock alarm.

<ds3-alarm-ylw>—Yellow alarm.

<dsl-alarm-far-locdi>—Far-end loss-of-cell-delineation alarm for interleaved channel.

<dsl-alarm-far-locdni>—Far-end loss-of-cell-delineation alarm for non-interleaved channel.

<dsl-alarm-far-lof>—Far-end loss-of-frame alarm.

<dsl-alarm-far-los>—Far-end loss-of-signal alarm.

<dsl-alarm-locdi>—Loss of cell delineation alarm for interleaved channel.

<dsl-alarm-locdni>—Loss of cell delineation alarm for non-interleaved channel.

<dsl-alarm-lof>—Loss of frame alarm.

<dsl-alarm-lom>—Loss of multiframe alarm.

<dsl-alarm-lop>—Loss of power alarm.

<dsl-alarm-los>—Loss of signal alarm.

<ethernet-alarm-lcdp>—Loss of code-group delineation.

<ethernet-alarm-link-down>—Link alive failure.

<generic-value>—Hexadecimal value of unknown flag bits.

<isdn-alarm-lof>—Loss of frame alarm.

<isdn-alarm-los>—Loss of signal alarm.

<sdh-alarm-berr-sd>—Bit error rate alarm, defect.

<sdh-alarm-berr-sf>—Bit error rate alarm, fault.

<sdh-alarm-hpais>—High order path AIS alarm.

<sdh-alarm-hpfebe>—High order path far-end block error alarm.

<sdh-alarm-hpferf>—High order path far-end remote failure alarm.

<sdh-alarm-hpplm>—High order path payload level mismatch alarm.

<sdh-alarm-hpuneq>—High order path unequipped alarm.

<sdh-alarm-loc>—Loss of cell delineation alarm.

<sdh-alarm-lof>—Loss of frame alarm.

<sdh-alarm-lol>—Loss of light alarm.

<sdh-alarm-lop>—Loss of pointer alarm.

<sdh-alarm-los>—Loss of signal alarm.

<sdh-alarm-msais>—Multiplex section AIS alarm.

<sdh-alarm-msferf>—Multiplex section far-end remote failure alarm.

<sdh-alarm-oof>—Out of frame alarm.

<sdh-alarm-pll>—PLL lock alarm.

<sdh-alarm-tuais>—TU AIS alarm.

<sdh-alarm-tuloc>—TU loss of cell delineation alarm.

<sdh-alarm-tulop>—TU loss of pointer alarm.

<sdh-alarm-tumis>—TU label mismatch error.

<sdh-alarm-turdi>—TU remote defect indicator alarm.

<sdh-alarm-tuuneq>—TU unequipped alarm.

<shdsl-alarm-line1-losd>—Loss of signal (line 1) alarm.

<shdsl-alarm-line1-losw>—Loss of sync word (line 1) alarm.

<shdsl-alarm-line2-losd>—Loss of signal (line 2) alarm.

<shdsl-alarm-line2-losw>—Loss of sync word (line 2) alarm.

<shdsl-alarm-losd>—Loss of signal alarm.

<shdsl-alarm-losw>—Loss of sync word alarm.

<sonet-alarm-berr-sd>—Bit error rate alarm, defect.

<sonet-alarm-berr-sf>—Bit error rate alarm, fault.

<sonet-alarm-lais>—Line AIS alarm.

<sonet-alarm-loc>—Loss of cell delineation alarm.

<sonet-alarm-lof>—Loss of frame alarm.

<sonet-alarm-lol>—Loss of light alarm.

<sonet-alarm-lop>—Loss of pointer alarm.

<sonet-alarm-los>—Loss of signal alarm.

<sonet-alarm-lrldi>—Line remote defect indicator alarm.

<sonet-alarm-pais>—Path AIS alarm.

<sonet-alarm-pll>—PLL lock alarm.

<sonet-alarm-pmis>—Path payload level mismatch alarm.

<sonet-alarm-prdi>—Path remote defect indicator alarm.

<sonet-alarm-rei>—Path remote error indicator alarm.

<sonet-alarm-sef>—Severely errored frame alarm.

<sonet-alarm-uneq>—Unequipped alarm.

<sonet-alarm-vais>—VT AIS alarm.

<sonet-alarm-vloc>—VT loss of cell delineation alarm.

<sonet-alarm-vlop>—VT loss of pointer alarm.

<sonet-alarm-vmis>—VT label mismatch alarm.

<sonet-alarm-vrldi>—VT remote defect indicator alarm.

<sonet-alarm-vuneq>—VT unequipped alarm.

<interface-chassis-cos-summary>

Usage <ingress-queue-counters | chassis-queue-counters>
 <interface-chassis-cos-summary>
 <intf-cos-chassis-num-queues-supported>intf-cos-chassis-num-queues-supported
 </intf-cos-chassis-num-queues-supported>
 <intf-cos-chassis-num-queues-in-use>intf-cos-chassis-num-queues-in-use
 </intf-cos-chassis-num-queues-in-use>
 </interface-chassis-cos-summary>
 </ingress-queue-counters | chassis-queue-counters>

Description Packet Forwarding Engine chassis forwarding class and queue information for an interface.

Contents <intf-cos-chassis-num-queues-in-use>—Number of Packet Forwarding Engine chassis queues in use on the interface.

<intf-cos-chassis-num-queues-supported>—Number of Packet Forwarding Engine chassis queues the interface supports.

<interface-cos-short-summary>

Usage <queue-counters | ingress-queue-counters>
<interface-cos-short-summary>
 <intf-cos-queue-type>*intf-cos-queue-type*</intf-cos-queue-type>
 <intf-cos-num-queues-supported>*intf-cos-num-queues-supported*
 </intf-cos-num-queues-supported>
 <intf-cos-num-queues-in-use>*intf-cos-num-queues-in-use*
 </intf-cos-num-queues-in-use>
</interface-cos-short-summary>
 </queue-counters | ingress-queue-counters>

Description Summary of queue information on an interface.

Contents <intf-cos-num-queues-in-use>—Number of queues currently in use on this interface.
 <intf-cos-num-queues-supported>—Number of queues supported on this interface.
 <intf-cos-queue-type>—Interface queue type.

<interface-cos-summary>

Usage <queue-counters | ingress-queue-counters>
<interface-cos-summary>
 <intf-cos-forwarding-classes-supported>*intf-cos-forwarding-classes-supported*
 </intf-cos-forwarding-classes-supported>
 <intf-cos-forwarding-classes-in-use>*intf-cos-forwarding-classes-in-use*
 </intf-cos-forwarding-classes-in-use>
 <intf-cos-queue-type>*intf-cos-queue-type*</intf-cos-queue-type>
 <intf-cos-num-queues-supported>*intf-cos-num-queues-supported*
 </intf-cos-num-queues-supported>
 <intf-cos-num-queues-in-use>*intf-cos-num-queues-in-use*
 </intf-cos-num-queues-in-use>
 <intf-cos-burst-size-for-ifl>*intf-cos-burst-size-for-ifl*
 </intf-cos-burst-size-for-ifl>
</interface-cos-summary>
 </queue-counters | ingress-queue-counters>

Description Summary of forwarding class and queue information on an interface.

Contents <intf-cos-burst-size-for-ifl>—Burst size for the logical interface.
 <intf-cos-forwarding-classes-in-use>—Number of forwarding classes currently in use on this interface.
 <intf-cos-forwarding-classes-supported>—Number of forwarding classes supported on this interface.
 <intf-cos-num-queues-in-use>—Number of queues currently in use on this interface.
 <intf-cos-num-queues-supported>—Number of queues supported on this interface.
 <intf-cos-queue-type>—Interface queue type.

<interface-filter-information>

- Usage** <rpc-reply>
 <interface-filter-information>
 <physical-interface>...</physical-interface>
 <logical-interface>...</logical-interface>
 </interface-filter-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <logical-interface>—Information about a single logical interface.
 <physical-interface>—Information about a single physical interface.

<interface-information>

- Usage** <rpc-reply>
 <interface-information>
 <physical-interface>...</physical-interface>
 <logical-interface>...</logical-interface>
 <controller>...</controller>
 <interface-set>...</interface-set>
 </interface-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <controller>—No documentation is available yet.
 <interface-set>—No documentation is available yet.
 <logical-interface>—Information about a single logical interface.
 <physical-interface>—Information about a single physical interface.

<interface-location-name-information>

- Usage** <rpc-reply>
 <interface-location-name-information>
 <location-name-information>...</location-name-information>
 </interface-location-name-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <location-name-information>—No documentation is available yet.

<interface-location-slot-information>

- Usage** <rpc-reply>
 <interface-location-slot-information>
 <location-slot-information>...</location-slot-information>
 </interface-location-slot-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <location-slot-information>—No documentation is available yet.

<interface-policer-information>

- Usage** <rpc-reply>
 <interface-policer-information>
 <physical-interface>...</physical-interface>
 <logical-interface>...</logical-interface>
 </interface-policer-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <logical-interface>—Information about a single logical interface.
 <physical-interface>—Information about a single physical interface.

<interface-set>

- Usage** <interface-information>
 <interface-set>
 <name>*name*</name>
 <interface-set-index>*interface-set-index*</interface-set-index>
 <interface-set-member-list>...</interface-set-member-list>
 <traffic-statistics>...</traffic-statistics>
 <interface-set-queue-information>...</interface-set-queue-information>
 </interface-set>
 </interface-information>
- Description** No documentation is available yet.
- Contents** <interface-set-index>—No documentation is available yet.
 <interface-set-member-list>—No documentation is available yet.
 <interface-set-queue-information>—No documentation is available yet.
 <name>—Name of this item.
 <traffic-statistics>—Number and rate of bytes and packets received and transmitted on the physical interface.

<interface-set-member-list>

- Usage** <interface-set>
 <interface-set-member-list>
 <interface-set-member>*interface-set-member*</interface-set-member>
 </interface-set-member-list>
 </interface-set>
- Description** No documentation is available yet.
- Contents** <interface-set-member>—No documentation is available yet.

<interface-set-queue-information>

- Usage** <interface-set>
 <interface-set-queue-information>
 <queue-counters>...</queue-counters>
 <ingress-queue-counters>...</ingress-queue-counters>
 </interface-set-queue-information>
 </interface-set>
- Description** No documentation is available yet.
- Contents** <ingress-queue-counters>—Ingress queue counter statistics.
 <queue-counters>—Queue counter statistics.

<interface-tx-queue>

Usage <ct3-information | cds1-information | nxds0-information>
<interface-tx-queue>
 <name>*name*</name>
 <bandwidth>*bandwidth*</bandwidth>
 <wrr>*wrr*</wrr>
 <output-packets>*output-packets*</output-packets>
 <output-bytes>*output-bytes*</output-bytes>
 <output-drops>*output-drops*</output-drops>
 <output-drops-bytes>*output-drops-bytes*</output-drops-bytes>
 <output-errors>*output-errors*</output-errors>
</interface-tx-queue>
 </ct3-information | cds1-information | nxds0-information>

Description No documentation is available yet.

Contents <bandwidth>—No documentation is available yet.

<name>—Name of this item.

<output-bytes>—No documentation is available yet.

<output-drops>—Number of packets dropped by the output queue of the I/O Manager ASIC. If the interface is saturated, this number increments once for every packet that is dropped by the ASIC's RED mechanism.

<output-drops-bytes>—No documentation is available yet.

<output-errors>—Sum of the outgoing frame aborts and FCS errors.

<output-packets>—No documentation is available yet.

<wrr>—No documentation is available yet.

<interval>

Usage <interval-information>
<interval>
 <range>*range*</range>
 <media-alarm>...</media-alarm>
</interval>
 </interval-information>

Description Statistics for a single interval.

Contents <media-alarm>—No documentation is available yet.

<range>—Time range for this interval.

<interval-information>

- Usage** <physical-interface>
 <interval-information>
 <interval>...</interval>
 </interval-information>
 </physical-interface>
- Description** No documentation is available yet.
- Contents** <interval>—Statistics for a single interval.

<ipv6-transit-statistics>

- Usage** <traffic-statistics | transit-traffic-statistics>
 <ipv6-transit-statistics>
 <input-bytes>*input-bytes*</input-bytes>
 <output-bytes>*output-bytes*</output-bytes>
 <input-packets>*input-packets*</input-packets>
 <output-packets>*output-packets*</output-packets>
 </ipv6-transit-statistics>
 </traffic-statistics | transit-traffic-statistics>
- Description** No documentation is available yet.
- Contents** <input-bytes>—No documentation is available yet.
- <input-packets>—No documentation is available yet.
- <output-bytes>—No documentation is available yet.
- <output-packets>—No documentation is available yet.

<irb-domain>

- Usage** <logical-interface>
 <irb-domain>
 <irb-routing-instance>*irb-routing-instance*</irb-routing-instance>
 <irb-bridge>*irb-bridge*</irb-bridge>
 </irb-domain>
 </logical-interface>
- Description** No documentation is available yet.
- Contents** <irb-bridge>—Name of the Bridging Domain.
- <irb-routing-instance>—Name of the Routing Instance.

<jswitch-port>

Usage <jswitch-port-information>
 <jswitch-port>
 <physical-interface-name>*physical-interface-name*</physical-interface-name>
 <port>*port*</port>
 <admin-state>*admin-state*</admin-state>
 <physical-link>*physical-link*</physical-link>
 <link-speed>*link-speed*</link-speed>
 <auto-negotiation>*auto-negotiation*</auto-negotiation>
 <link-duplexity>*link-duplexity*</link-duplexity>
 <port-mtu>*port-mtu*</port-mtu>
 <ethernet-mac-statistics>...</ethernet-mac-statistics>
 <ethernet-autonegotiation>...</ethernet-autonegotiation>
 <vlan-id>*vlan-id*</vlan-id>
 <default-vlan-id>*default-vlan-id*</default-vlan-id>
 <cascade-port>*cascade-port*</cascade-port>
 </jswitch-port>
 </jswitch-port-information>

Description No documentation is available yet.

Contents <admin-state>—No documentation is available yet.

<auto-negotiation>—No documentation is available yet.

<cascade-port>—No documentation is available yet.

<default-vlan-id>—No documentation is available yet.

<ethernet-autonegotiation>—Ethernet autonegotiation information.

<ethernet-mac-statistics>—Ethernet MAC statistics.

<link-duplexity>—No documentation is available yet.

<link-speed>—No documentation is available yet.

<physical-interface-name>—No documentation is available yet.

<physical-link>—No documentation is available yet.

<port>—No documentation is available yet.

<port-mtu>—No documentation is available yet.

<vlan-id>—No documentation is available yet.

<jswitch-port-information>

- Usage** <rpc-reply>
 <jswitch-port-information>
 <jswitch-port>...</jswitch-port>
 </jswitch-port-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <jswitch-port>—No documentation is available yet.

<keepalive-config>

- Usage** <physical-interface | logical-interface>
 <keepalive-config>
 <keepalive-interval>*keepalive-interval*</keepalive-interval>
 <keepalive-up-count>*keepalive-up-count*</keepalive-up-count>
 <keepalive-down-count>*keepalive-down-count*</keepalive-down-count>
 </keepalive-config>
 </physical-interface | logical-interface>
- Description** Configured keepalive settings on this interface.
- Contents** <keepalive-down-count>—No documentation is available yet.
- <keepalive-interval>—No documentation is available yet.
- <keepalive-up-count>—No documentation is available yet.

<keepalive-statistics>

- Usage** <physical-interface | logical-interface>
 <keepalive-statistics>
 <keepalive-lmi-descriptor>*keepalive-lmi-descriptor*</keepalive-lmi-descriptor>
 <keepalive-input-count>*keepalive-input-count*</keepalive-input-count>
 <keepalive-input-time>*keepalive-input-time*</keepalive-input-time>
 <keepalive-output-count>*keepalive-output-count*</keepalive-output-count>
 <keepalive-output-time>*keepalive-output-time*</keepalive-output-time>
 </keepalive-statistics>
 </physical-interface | logical-interface>
- Description** Keepalive statistics for this interface.
- Contents** <keepalive-input-count>—No documentation is available yet.
- <keepalive-input-time>—No documentation is available yet.
- <keepalive-lmi-descriptor>—No documentation is available yet.
- <keepalive-output-count>—No documentation is available yet.
- <keepalive-output-time>—No documentation is available yet.

<l2circuit-info>

Usage <logical-interface>
 <l2circuit-info>
 <cell-bundle-size>*cell-bundle-size*</cell-bundle-size>
 <cell-bundle-timeout>*cell-bundle-timeout*</cell-bundle-timeout>
 <cell-timeout-count>*cell-timeout-count*</cell-timeout-count>
 <out-of-sequence>*out-of-sequence*</out-of-sequence>
 </l2circuit-info>
 </logical-interface>

Description No documentation is available yet.

Contents <cell-bundle-size>—No documentation is available yet.
 <cell-bundle-timeout>—No documentation is available yet.
 <cell-timeout-count>—No documentation is available yet.
 <out-of-sequence>—No documentation is available yet.

<lag-bundle>

Usage <lag-traffic-statistics>
 <lag-bundle>
 <input-packets>*input-packets*</input-packets>
 <input-pps>*input-pps*</input-pps>
 <input-bytes>*input-bytes*</input-bytes>
 <input-bps>*input-bps*</input-bps>
 <output-packets>*output-packets*</output-packets>
 <output-pps>*output-pps*</output-pps>
 <output-bytes>*output-bytes*</output-bytes>
 <output-bps>*output-bps*</output-bps>
 </lag-bundle>
 </lag-traffic-statistics>

Description No documentation is available yet.

Contents <input-bps>—No documentation is available yet.
 <input-bytes>—No documentation is available yet.
 <input-packets>—No documentation is available yet.
 <input-pps>—No documentation is available yet.
 <output-bps>—No documentation is available yet.
 <output-bytes>—No documentation is available yet.
 <output-packets>—No documentation is available yet.
 <output-pps>—No documentation is available yet.

<lag-lacp-info>

Usage	<pre> <lag-traffic-statistics> <lag-lacp-info> <name>name</name> <lacp-role>lacp-role</lacp-role> <lacp-sys-priority>lacp-sys-priority</lacp-sys-priority> <lacp-system-id>lacp-system-id</lacp-system-id> <lacp-port-priority>lacp-port-priority</lacp-port-priority> <lacp-port-number>lacp-port-number</lacp-port-number> <lacp-port-key>lacp-port-key</lacp-port-key> </lag-lacp-info> </lag-traffic-statistics> </pre>
Description	LACP information.
Contents	<p><lacp-port-key>—Operational key of the port.</p> <p><lacp-port-number>—Port number.</p> <p><lacp-port-priority>—Priority of the port.</p> <p><lacp-role>—Whether it is an actor or partner.</p> <p><lacp-sys-priority>—System priority.</p> <p><lacp-system-id>—LACP system identifier.</p> <p><name>—Name of this item.</p>

<lag-lacp-protocol>

Usage	<pre> <lag-traffic-statistics> <lag-lacp-protocol> <name>name</name> <lacp-receive-state>lacp-receive-state</lacp-receive-state> <lacp-transmit-state>lacp-transmit-state</lacp-transmit-state> <lacp-mux-state>lacp-mux-state</lacp-mux-state> </lag-lacp-protocol> </lag-traffic-statistics> </pre>
Description	LACP protocol information.
Contents	<p><lacp-mux-state>—State of the mux lacp machine.</p> <p><lacp-receive-state>—State of the receive lacp machine.</p> <p><lacp-transmit-state>—State of the transmit lacp machine.</p> <p><name>—Name of this item.</p>

<lag-lacp-state>

Usage <lag-traffic-statistics>
 <lag-lacp-state>
 <name>*name*</name>
 <lacp-role>*lacp-role*</lacp-role>
 <lacp-expired>*lacp-expired*</lacp-expired>
 <lacp-defaulted>*lacp-defaulted*</lacp-defaulted>
 <lacp-distributing>*lacp-distributing*</lacp-distributing>
 <lacp-collecting>*lacp-collecting*</lacp-collecting>
 <lacp-synchronization>*lacp-synchronization*</lacp-synchronization>
 <lacp-aggregation>*lacp-aggregation*</lacp-aggregation>
 <lacp-timeout>*lacp-timeout*</lacp-timeout>
 <lacp-activity>*lacp-activity*</lacp-activity>
 </lag-lacp-state>
 </lag-traffic-statistics>

Description LACP protocol state information.

Contents <lacp-activity>—Configured as either active or passive.

<lacp-aggregation>—Actor view of partner information is in sync.

<lacp-collecting>—State of the mux lacp machine is COLLECTING?.

<lacp-defaulted>—State of the receive lacp machine is DEFAULTED?.

<lacp-distributing>—State of the mux lacp machine is DISTRIBUTING?.

<lacp-expired>—State of the receive lacp machine is EXPIRED?.

<lacp-role>—Whether it is an actor or partner.

<lacp-synchronization>—Actor view of partner information is in sync.

<lacp-timeout>—Configured as either fast or slow periodic.

<name>—Name of this item.

<lag-lacp-statistics>

Usage <lag-traffic-statistics>
 <lag-lacp-statistics>
 <name>*name*</name>
 <lacp-rx-packets>*lacp-rx-packets*</lacp-rx-packets>
 <lacp-tx-packets>*lacp-tx-packets*</lacp-tx-packets>
 <unknown-rx-packets>*unknown-rx-packets*</unknown-rx-packets>
 <illegal-rx-packets>*illegal-rx-packets*</illegal-rx-packets>
 </lag-lacp-statistics>
 </lag-traffic-statistics>

Description No documentation is available yet.

Contents <illegal-rx-packets>—Number of ill formed packets received.

<lacp-rx-packets>—Number of lacp packets received.

<lacp-tx-packets>—Number of lacp packets transmitted.

<name>—Name of this item.

<unknown-rx-packets>—Number of unknown type packets received.

<lag-link>

Usage <lag-traffic-statistics>
 <lag-link>
 <name>*name*</name>
 <down/>
 <input-packets>*input-packets*</input-packets>
 <input-pps>*input-pps*</input-pps>
 <input-bytes>*input-bytes*</input-bytes>
 <input-bps>*input-bps*</input-bps>
 <output-packets>*output-packets*</output-packets>
 <output-pps>*output-pps*</output-pps>
 <output-bytes>*output-bytes*</output-bytes>
 <output-bps>*output-bps*</output-bps>
 </lag-link>
 </lag-traffic-statistics>

Description No documentation is available yet.

Contents <down>—Link is down.

<input-bps>—No documentation is available yet.

<input-bytes>—No documentation is available yet.

<input-packets>—No documentation is available yet.

<input-pps>—No documentation is available yet.

<name>—Name of this item.

<output-bps>—No documentation is available yet.

<output-bytes>—No documentation is available yet.

<output-packets>—No documentation is available yet.

<output-pps>—No documentation is available yet.

<lag-marker>

Usage	<pre> <lag-traffic-statistics> <lag-marker> <name>name</name> <marker-rx-packets>marker-rx-packets</marker-rx-packets> <marker-response-tx-packets>marker-response-tx-packets </marker-response-tx-packets> <unknown-rx-packets>unknown-rx-packets</unknown-rx-packets> <illegal-rx-packets>illegal-rx-packets</illegal-rx-packets> </lag-marker> </lag-traffic-statistics> </pre>
Description	No documentation is available yet.
Contents	<p><illegal-rx-packets>—Number of ill formed packets received.</p> <p><marker-response-tx-packets>—No documentation is available yet.</p> <p><marker-rx-packets>—No documentation is available yet.</p> <p><name>—Name of this item.</p> <p><unknown-rx-packets>—Number of unknown type packets received.</p>

<lag-traffic-statistics>

Usage	<pre> <logical-interface> <lag-traffic-statistics> <lag-bundle>...</lag-bundle> <lag-link>...</lag-link> <lag-marker>...</lag-marker> <lag-lacp-statistics>...</lag-lacp-statistics> <lag-lacp-info>...</lag-lacp-info> <lag-lacp-state>...</lag-lacp-state> <lag-lacp-protocol>...</lag-lacp-protocol> </lag-traffic-statistics> </logical-interface> </pre>
Description	No documentation is available yet.
Contents	<p><lag-bundle>—No documentation is available yet.</p> <p><lag-lacp-info>—LACP information.</p> <p><lag-lacp-protocol>—LACP protocol information.</p> <p><lag-lacp-state>—LACP protocol state information.</p> <p><lag-lacp-statistics>—No documentation is available yet.</p> <p><lag-link>—No documentation is available yet.</p> <p><lag-marker>—No documentation is available yet.</p>

<layer2-input-policer-information>

- Usage** <logical-interface>
 <layer2-input-policer-information>
 <layer2-input-policer>*layer2-input-policer*</layer2-input-policer>
 </layer2-input-policer-information>
 </logical-interface>
- Description** Information about Layer 2 input policer for interface.
- Contents** <layer2-input-policer>—Name of the Layer 2 input policer.

<layer2-input-policer-statistics>

- Usage** <logical-interface>
 <layer2-input-policer-statistics>
 <policer-low-frames>*policer-low-frames*</policer-low-frames>
 <policer-medium-low-frames>*policer-medium-low-frames*
 </policer-medium-low-frames>
 <policer-medium-high-frames>*policer-medium-high-frames*
 </policer-medium-high-frames>
 <policer-high-frames>*policer-high-frames*</policer-high-frames>
 <policer-dropped-frames>*policer-dropped-frames*</policer-dropped-frames>
 </layer2-input-policer-statistics>
 </logical-interface>
- Description** Layer 2 input policer statistics for interface.
- Contents** <policer-dropped-frames>—Number of dropped frames.
- <policer-high-frames>—Number of high-loss frames.
- <policer-low-frames>—Number of low-loss frames.
- <policer-medium-high-frames>—Number of medium-high-loss frames.
- <policer-medium-low-frames>—Number of medium-low-loss frames.

<layer2-output-policer-information>

- Usage** <logical-interface>
 <layer2-output-policer-information>
 <layer2-output-policer>*layer2-output-policer*</layer2-output-policer>
 </layer2-output-policer-information>
 </logical-interface>
- Description** Information about Layer 2 output policer for interface.
- Contents** <layer2-output-policer>—Name of the Layer 2 output policer.

<layer2-output-policer-statistics>

Usage <logical-interface>
 <layer2-output-policer-statistics>
 <policer-low-frames>*policer-low-frames*</policer-low-frames>
 <policer-medium-low-frames>*policer-medium-low-frames*
 </policer-medium-low-frames>
 <policer-medium-high-frames>*policer-medium-high-frames*
 </policer-medium-high-frames>
 <policer-high-frames>*policer-high-frames*</policer-high-frames>
 <policer-dropped-frames>*policer-dropped-frames*</policer-dropped-frames>
 </layer2-output-policer-statistics>
 </logical-interface>

Description Layer 2 output policer statistics for interface.

Contents <policer-dropped-frames>—Number of dropped frames.

<policer-high-frames>—Number of high-loss frames.

<policer-low-frames>—Number of low-loss frames.

<policer-medium-high-frames>—Number of medium-high-loss frames.

<policer-medium-low-frames>—Number of medium-low-loss frames.

<lfi>

Usage <bundle-detail>
 <lfi>
 <input-frames>*input-frames*</input-frames>
 <input-fps>*input-fps*</input-fps>
 <input-bytes>*input-bytes*</input-bytes>
 <input-bps>*input-bps*</input-bps>
 <output-frames>*output-frames*</output-frames>
 <output-fps>*output-fps*</output-fps>
 <output-bytes>*output-bytes*</output-bytes>
 <output-bps>*output-bps*</output-bps>
 </lfi>
 </bundle-detail>

Description LFI frame statistics for multilink bundles and classes.

Contents <input-bps>—No documentation is available yet.
 <input-bytes>—No documentation is available yet.
 <input-fps>—No documentation is available yet.
 <input-frames>—No documentation is available yet.
 <output-bps>—No documentation is available yet.
 <output-bytes>—No documentation is available yet.
 <output-fps>—No documentation is available yet.
 <output-frames>—No documentation is available yet.

<line-protocol>

Usage <serial-information>
 <line-protocol>
 <line-protocol-mode>*line-protocol-mode*</line-protocol-mode>
 </line-protocol>
 </serial-information>

Description No documentation is available yet.

Contents <line-protocol-mode>—No documentation is available yet.

<linear-red-drop-profile>

Usage <atm-cos-queue-parameters>
 <linear-red-drop-profile>
 <queue-depth>*queue-depth*</queue-depth>
 <low-red>*low-red*</low-red>
 <high-red>*high-red*</high-red>
 <max-low-red>*max-low-red*</max-low-red>
 <max-high-red>*max-high-red*</max-high-red>
 </linear-red-drop-profile>
 </atm-cos-queue-parameters>

Description No documentation is available yet.

Contents <high-red>—Fill level percentage when linear RED is applied for high PLP.
 <low-red>—Fill level percentage when linear RED is applied for low PLP.
 <max-high-red>—Fill level percentage with 100 % packet drop for high PLP.
 <max-low-red>—Fill level percentage with 100 % packet drop for low PLP.
 <queue-depth>—Maximum queue depth.

<link>

Usage <multilink-traffic-statistics>
 <link>
 <name>*name*</name>
 <down/>
 <link-uptime>*link-uptime*</link-uptime>
 <input-frames>*input-frames*</input-frames>
 <input-fps>*input-fps*</input-fps>
 <input-bytes>*input-bytes*</input-bytes>
 <input-bps>*input-bps*</input-bps>
 <output-frames>*output-frames*</output-frames>
 <output-fps>*output-fps*</output-fps>
 <output-bytes>*output-bytes*</output-bytes>
 <output-bps>*output-bps*</output-bps>
 </link>
 </multilink-traffic-statistics>

Description No documentation is available yet.

Contents <down>—Link is down.

<input-bps>—No documentation is available yet.

<input-bytes>—No documentation is available yet.

<input-fps>—No documentation is available yet.

<input-frames>—No documentation is available yet.

<link-uptime>—Total uptime for the member link.

<name>—Name of this item.

<output-bps>—No documentation is available yet.

<output-bytes>—No documentation is available yet.

<output-fps>—No documentation is available yet.

<output-frames>—No documentation is available yet.

<link-entry>

Usage <links>
 <link-entry>
 <link-id>*link-id*</link-id>
 <active-alarms>...</active-alarms>
 <active-defects>...</active-defects>
 <sonet-errors>...</sonet-errors>
 <sonet-physical-information>...</sonet-physical-information>
 <sonet-section-information>...</sonet-section-information>
 <sonet-line-information>...</sonet-line-information>
 <sonet-path-information>...</sonet-path-information>
 <sonet-payload-pointer-information>...</sonet-payload-pointer-information>
 <sonet-payload-pointer-curptr>*sonet-payload-pointer-curptr*
 </sonet-payload-pointer-curptr>
 <sonet-payload-pointer-ptrinc-count>*sonet-payload-pointer-ptrinc-count*
 </sonet-payload-pointer-ptrinc-count>
 <sonet-payload-pointer-ptrdec-count>*sonet-payload-pointer-ptrdec-count*
 </sonet-payload-pointer-ptrdec-count>
 <sonet-payload-pointer-newptr-ndf-count>*sonet-payload-pointer-newptr-ndf-count*
 </sonet-payload-pointer-newptr-ndf-count>
 <sonet-vt-information>...</sonet-vt-information>
 <sonet-rx-overhead>*sonet-rx-overhead*</sonet-rx-overhead>
 <sonet-tx-overhead>*sonet-tx-overhead*</sonet-tx-overhead>
 <sonet-rx-path-trace>*sonet-rx-path-trace*</sonet-rx-path-trace>
 <sonet-tx-path-trace>*sonet-tx-path-trace*</sonet-tx-path-trace>
 <optics-diagnostics>...</optics-diagnostics>
 </link-entry>
 </links>

Description SONET/SDH link information.

Contents <active-alarms>—Media-specific defects that can render the interface unable to pass packets. When a defect persists for a certain amount of time, it is promoted to an alarm. Based on the router configuration, an alarm can ring the red or yellow alarm bell on the router, or the red or yellow alarm LED on the craft interface.

<active-defects>—Media-specific defects that can render the interface unable to pass packets. When a defect persists for a certain amount of time, it is promoted to an alarm. Based on the router configuration, an alarm can ring the red or yellow alarm bell on the router, or the red or yellow alarm LED on the craft interface.

<link-id>—Link id for aggregated SONET/SDH interface.

<optics-diagnostics>—Optics diagnostics.

<sonet-errors>—No documentation is available yet.

<sonet-line-information>—No documentation is available yet.

<sonet-path-information>—No documentation is available yet.

<sonet-payload-pointer-curptr>—Value of the SONET/SDH payload pointer, derived

from the H1 and H2 overhead bytes.

`<sonet-payload-pointer-information>`—No documentation is available yet.

`<sonet-payload-pointer-newptr-ndf-count>`—Number of times a new payload pointer was created with the New Data Found flag set.

`<sonet-payload-pointer-ptrdec-count>`—Number of times the value of the SONET/SDH payload pointer had negative justification.

`<sonet-payload-pointer-ptrinc-count>`—Number of times the value of the SONET/SDH payload pointer had positive justification.

`<sonet-physical-information>`—No documentation is available yet.

`<sonet-rx-overhead>`—No documentation is available yet.

`<sonet-rx-path-trace>`—Received SONET path trace.

`<sonet-section-information>`—No documentation is available yet.

`<sonet-tx-overhead>`—No documentation is available yet.

`<sonet-tx-path-trace>`—Transmitted SONET path trace.

`<sonet-vt-information>`—No documentation is available yet.

`<links>`

Usage `<physical-interface>`
 `<links>`
 `<link-entry>...</link-entry>`
 `</links>`
`</physical-interface>`

Description Aggregated SONET/SDH link information.

Contents `<link-entry>`—SONET/SDH link information.

<Imi-dce-config>

- Usage** <physical-interface>
 <Imi-dce-config>
 <Imi-type>Imi-type</Imi-type>
 <Imi-n392dce>Imi-n392dce</Imi-n392dce>
 <Imi-n393dce>Imi-n393dce</Imi-n393dce>
 <Imi-t392dce>Imi-t392dce</Imi-t392dce>
 </Imi-dce-config>
 </physical-interface>
- Description** Configured LMI DCE setting on this interface.
- Contents** <Imi-n392dce>—No documentation is available yet.
 <Imi-n393dce>—No documentation is available yet.
 <Imi-t392dce>—No documentation is available yet.
 <Imi-type>—No documentation is available yet.

<Imi-dte-config>

- Usage** <physical-interface>
 <Imi-dte-config>
 <Imi-type>Imi-type</Imi-type>
 <Imi-n391dte>Imi-n391dte</Imi-n391dte>
 <Imi-n392dte>Imi-n392dte</Imi-n392dte>
 <Imi-n393dte>Imi-n393dte</Imi-n393dte>
 <Imi-t391dte>Imi-t391dte</Imi-t391dte>
 </Imi-dte-config>
 </physical-interface>
- Description** Configured LMI DTE setting on this interface.
- Contents** <Imi-n391dte>—No documentation is available yet.
 <Imi-n392dte>—No documentation is available yet.
 <Imi-n393dte>—No documentation is available yet.
 <Imi-t391dte>—No documentation is available yet.
 <Imi-type>—No documentation is available yet.

<Imi-statistics>

Usage <physical-interface>
<Imi-statistics>
 <Imi-statistics-dte-descriptor>*Imi-statistics-dte-descriptor*
 </Imi-statistics-dte-descriptor>
 <Imi-enquiries-sent>*Imi-enquiries-sent*</Imi-enquiries-sent>
 <Imi-full-enquiries-sent>*Imi-full-enquiries-sent*</Imi-full-enquiries-sent>
 <Imi-enquiry-responses-received>*Imi-enquiry-responses-received*
 </Imi-enquiry-responses-received>
 <Imi-full-enquiry-responses-received>*Imi-full-enquiry-responses-received*
 </Imi-full-enquiry-responses-received>
 <Imi-statistics-dce-descriptor>*Imi-statistics-dce-descriptor*
 </Imi-statistics-dce-descriptor>
 <Imi-enquiries-received>*Imi-enquiries-received*</Imi-enquiries-received>
 <Imi-full-enquiries-received>*Imi-full-enquiries-received*
 </Imi-full-enquiries-received>
 <Imi-enquiry-responses-sent>*Imi-enquiry-responses-sent*
 </Imi-enquiry-responses-sent>
 <Imi-full-enquiry-responses-sent>*Imi-full-enquiry-responses-sent*
 </Imi-full-enquiry-responses-sent>
 <Imi-statistics-common-descriptor>*Imi-statistics-common-descriptor*
 </Imi-statistics-common-descriptor>
 <Imi-unknown-messages-received>*Imi-unknown-messages-received*
 </Imi-unknown-messages-received>
 <Imi-asynchronous-updates-received>*Imi-asynchronous-updates-received*
 </Imi-asynchronous-updates-received>
 <Imi-out-of-sequence>*Imi-out-of-sequence*</Imi-out-of-sequence>
 <Imi-keepalive-responses-timeout>*Imi-keepalive-responses-timeout*
 </Imi-keepalive-responses-timeout>
</Imi-statistics>
 </physical-interface>

Description LMI statistics for an interface.

Contents <Imi-asynchronous-updates-received>—Number of ifstate change updates received.
 <Imi-enquiries-received>—Number of enquiry packets received.
 <Imi-enquiries-sent>—Number of enquiry packets sent.
 <Imi-enquiry-responses-received>—Number of enquiry response packets received.
 <Imi-enquiry-responses-sent>—Number of enquiry response packets sent.
 <Imi-full-enquiries-received>—Number of full enquiry packets received.
 <Imi-full-enquiries-sent>—Number of full enquiry packets sent.
 <Imi-full-enquiry-responses-received>—Number of full enquiry packets received.
 <Imi-full-enquiry-responses-sent>—Number of full enquiry response packets sent.
 <Imi-keepalive-responses-timeout>—Number of times, the timer for keepalive packets expired.

<Imi-out-of-sequence>—Number of packets received in unexpected sequence.

<Imi-statistics-common-descriptor>—Statistics common to DTE and DCE.

<Imi-statistics-dce-descriptor>—DCE interface statistics.

<Imi-statistics-dte-descriptor>—DTE interface statistics.

<Imi-unknown-messages-received>—Number of packets received that do not contain valid messages.

<local-info>

Usage <ethernet-autonegotiation | physical-interface>
 <local-info>
 <local-flow-control>*local-flow-control*</local-flow-control>
 <local-remote-fault>*local-remote-fault*</local-remote-fault>
 </local-info>
 </ethernet-autonegotiation | physical-interface>

Description Auto-negotiation status of local partner.

Contents <local-flow-control>—Local interface flow control type.

<local-remote-fault>—Local interface remote fault type.

<local-traffic-statistics>

Usage <logical-interface>
 <local-traffic-statistics>
 <input-bytes>*input-bytes*</input-bytes>
 <output-bytes>*output-bytes*</output-bytes>
 <input-bps>*input-bps*</input-bps>
 <output-bps>*output-bps*</output-bps>
 <input-packets>*input-packets*</input-packets>
 <output-packets>*output-packets*</output-packets>
 <input-pps>*input-pps*</input-pps>
 <output-pps>*output-pps*</output-pps>
 </local-traffic-statistics>
 </logical-interface>

Description Statistics for traffic received from and transmitted to the Routing Engine. When a burst of traffic is received, the value in the output packet rate field might briefly exceed the peak cell rate. It takes a while (generally less than 1 second) for this counter to stabilize.

Contents <input-bps>—No documentation is available yet.

<input-bytes>—No documentation is available yet.

<input-packets>—No documentation is available yet.

<input-pps>—No documentation is available yet.

<output-bps>—No documentation is available yet.

<output-bytes>—No documentation is available yet.

<output-packets>—No documentation is available yet.

<output-pps>—No documentation is available yet.

<location-name-information>

Usage <interface-location-name-information>
 <location-name-information>
 <interface-name>*interface-name*</interface-name>
 <fpc-number>*fpc-number*</fpc-number>
 <lcc-number>*lcc-number*</lcc-number>
 </location-name-information>
 </interface-location-name-information>

Description No documentation is available yet.

Contents <fpc-number>—FPC number.

<interface-name>—Interface name.

<lcc-number>—LCC Chassis number.

<location-slot-information>

- Usage** <interface-location-slot-information>
 <location-slot-information>
 <global-fpc-number>*global-fpc-number*</global-fpc-number>
 </location-slot-information>
</interface-location-slot-information>
- Description** No documentation is available yet.
- Contents** <global-fpc-number>—Global FPC number.

<logical-interface>

Usage <physical-interface | interface-information | interface-filter-information | interface-policer-information>

<logical-interface>

```

<name>name</name>
<admin-status>admin-status</admin-status>
<oper-status>oper-status</oper-status>
<vrfname>vrfname</vrfname>
<local-index>local-index</local-index>
<hardware-token>hardware-token</hardware-token>
<snmp-index>snmp-index</snmp-index>
<generation>generation</generation>
<description>description</description>
<if-config-flags>...</if-config-flags>
<multilink-flapped>multilink-flapped</multilink-flapped>
<link-address>link-address</link-address>
<encapsulation>encapsulation</encapsulation>
<demux-table-type>demux-table-type</demux-table-type>
<copy-tos-to-outer-ip-header>copy-tos-to-outer-ip-header
  </copy-tos-to-outer-ip-header>
<redundant-logical-interface-name>redundant-logical-interface-name
  </redundant-logical-interface-name>
<layer2-input-policer-information>...</layer2-input-policer-information>
<layer2-output-policer-information>...</layer2-output-policer-information>
<pppoe-information>...</pppoe-information>
<demux-interface>...</demux-interface>
<demux-information>...</demux-information>
<dialer-time-to-disconnect>dialer-time-to-disconnect
  </dialer-time-to-disconnect>
<dialer-information>...</dialer-information>
<shared-uplink-information>...</shared-uplink-information>
<logical-interface-mac>logical-interface-mac</logical-interface-mac>
<mac-database>...</mac-database>
<logical-interface-bandwidth>logical-interface-bandwidth
  </logical-interface-bandwidth>
<queue-counters>...</queue-counters>
<ingress-queue-counters>...</ingress-queue-counters>
<multilink-bundle-link-information>...</multilink-bundle-link-information>
<multilink-bundle-options>...</multilink-bundle-options>
<multilink-bundle-errors>...</multilink-bundle-errors>
<multilink-traffic-statistics>...</multilink-traffic-statistics>
<traffic-statistics>...</traffic-statistics>
<ingress-traffic-statistics>...</ingress-traffic-statistics>
<local-traffic-statistics>...</local-traffic-statistics>
<transit-traffic-statistics>...</transit-traffic-statistics>
<keepalive-config>...</keepalive-config>
<keepalive-statistics>...</keepalive-statistics>
<ppp-flags>...</ppp-flags>
<lcp-state>lcp-state</lcp-state>
<ncp-information>...</ncp-information>
<chap-state>chap-state</chap-state>
<pap-state>pap-state</pap-state>
<virtual-circuit-information>...</virtual-circuit-information>

```

```

<filter-information>...</filter-information>
<policer-information>...</policer-information>
<address-family>...</address-family>
<in-arp-statistics>...</in-arp-statistics>
<l2circuit-info>...</l2circuit-info>
<irb-domain>...</irb-domain>
<media-information>...</media-information>
<multilink-bundle-status>...</multilink-bundle-status>
<multilink-bundle-class>...</multilink-bundle-class>
<lag-traffic-statistics>...</lag-traffic-statistics>
<layer2-input-policer-statistics>...</layer2-input-policer-statistics>
<layer2-output-policer-statistics>...</layer2-output-policer-statistics>
<mac-policer-information>...</mac-policer-information>
<ppp-parameters>...</ppp-parameters>
</logical-interface>
</physical-interface | interface-information | interface-filter-information |
interface-policer-information>

```

Description Information about a single logical interface.

Contents <address-family>—No documentation is available yet.

<admin-status>—Desired state of the interface.

<chap-state>—State of the Challenge Handshake Authentication Protocol.

<copy-tos-to-outer-ip-header>—Flag that enables copying of the value in the ToS field of the IP packet's payload header to the delivery header in the generic routing encapsulation packet.

<demux-information>—Demux information.

<demux-interface>—No documentation is available yet.

<demux-table-type>—Demux table enabled on the logical interface.

<description>—Description of this interface.

<dialer-information>—Dialer information.

<dialer-time-to-disconnect>—Time for dialer to disconnect due to idle timeout.

<encapsulation>—Encapsulation on the logical interface.

<filter-information>—No documentation is available yet.

<generation>—Generation number used to distinguish between successive instances of this interface.

<hardware-token>—Hardware token for layer 3 ifl.

<if-config-flags>—No documentation is available yet.

<in-arp-statistics>—Container tag for ARP statistics.

<ingress-queue-counters>—Ingress queue counter statistics.

<ingress-traffic-statistics>—Number and rate of bytes and packets received in the ingress side at Packet Forwarding Engine.

<irb-domain>—No documentation is available yet.

<keepalive-config>—Configured keepalive settings on this interface.

<keepalive-statistics>—Keepalive statistics for this interface.

<l2circuit-info>—No documentation is available yet.

<lag-traffic-statistics>—No documentation is available yet.

<layer2-input-policer-information>—Information about Layer 2 input policer for interface.

<layer2-input-policer-statistics>—Layer 2 input policer statistics for interface.

<layer2-output-policer-information>—Information about Layer 2 output policer for interface.

<layer2-output-policer-statistics>—Layer 2 output policer statistics for interface.

<lcp-state>—State of the Line Control Protocol.

<link-address>—Link address on this logical interface.

<local-index>—Local kernel index for this interface.

<local-traffic-statistics>—Statistics for traffic received from and transmitted to the Routing Engine. When a burst of traffic is received, the value in the output packet rate field might briefly exceed the peak cell rate. It takes a while (generally less than 1 second) for this counter to stabilize.

<logical-interface-bandwidth>—Bandwidth of this logical interface.

<logical-interface-mac>—MAC on the logical interface.

<mac-database>—No documentation is available yet.

<mac-policer-information>—No documentation is available yet.

<media-information>—Information about media alarms.

<multilink-bundle-class>—Multilink class status.

<multilink-bundle-errors>—Multilink bundle errors.

<multilink-bundle-link-information>—No documentation is available yet.

<multilink-bundle-options>—No documentation is available yet.

<multilink-bundle-status>—Multilink bundle status.

<multilink-flapped>—Time when the interface last flapped.

<multilink-traffic-statistics>—No documentation is available yet.

<name>—Name of this item.

<ncp-information>—Network Control Protocol information.

<oper-status>—Current operational state of the interface.

<pap-state>—State of the Password Authentication Protocol.

<policer-information>—Interface policer information.

<ppp-flags>—Additional flags applicable to PPP encapsulation.

<ppp-parameters>—PPP parameters.

<pppoe-information>—PPPoE information.

<queue-counters>—Queue counter statistics.

<redundant-logical-interface-name>—Name of the redundant logical interface.

<shared-uplink-information>—Shared uplink information.

<snmp-index>—SNMP ifIndex for this interface.

<traffic-statistics>—Number and rate of bytes and packets received and transmitted on the physical interface.

<transit-traffic-statistics>—Statistics for traffic passing through the router. When a burst of traffic is received, the value in the output packet rate field might briefly exceed the peak cell rate. The counter usually stabilizes in 1 second or less.

<virtual-circuit-information>—Operational information and statistics for a virtual circuit.

<vrfname>—Routing instance name.

<lsi-traffic-statistics>

Usage <physical-interface>
 <lsi-traffic-statistics>
 <input-bytes>*input-bytes*</input-bytes>
 <input-bps>*input-bps*</input-bps>
 <input-packets>*input-packets*</input-packets>
 <input-pps>*input-pps*</input-pps>
 </lsi-traffic-statistics>
 </physical-interface>

Description Information about label-switched bytes and packets received on the physical interface.

Contents <input-bps>—No documentation is available yet.
 <input-bytes>—No documentation is available yet.
 <input-packets>—No documentation is available yet.
 <input-pps>—No documentation is available yet.

<mac-database>

Usage <physical-interface | logical-interface>
 <mac-database>
 <mac-record>...</mac-record>
 <number-of-mac-record>*number-of-mac-record*</number-of-mac-record>
 </mac-database>
 </physical-interface | logical-interface>

Description No documentation is available yet.

Contents <mac-record>—No documentation is available yet.
 <number-of-mac-record>—No documentation is available yet.

<mac-policer-information>

Usage <logical-interface>
 <mac-policer-information>
 <mac-address>*mac-address*</mac-address>
 <mac-entry-type>*mac-entry-type*</mac-entry-type>
 <receive-bytes>*receive-bytes*</receive-bytes>
 <transmit-bytes>*transmit-bytes*</transmit-bytes>
 <receive-frames>*receive-frames*</receive-frames>
 <transmit-frames>*transmit-frames*</transmit-frames>
 <ether-policer-list>...</ether-policer-list>
 </mac-policer-information>
 </logical-interface>

Description No documentation is available yet.

Contents <ether-policer-list>—No documentation is available yet.

<mac-address>—No documentation is available yet.

<mac-entry-type>—No documentation is available yet.

<receive-bytes>—No documentation is available yet.

<receive-frames>—No documentation is available yet.

<transmit-bytes>—No documentation is available yet.

<transmit-frames>—No documentation is available yet.

<mac-record>

Usage <mac-database>
 <mac-record>
 <mac-address>*mac-address*</mac-address>
 <receive-frames>*receive-frames*</receive-frames>
 <receive-bytes>*receive-bytes*</receive-bytes>
 <transmit-frames>*transmit-frames*</transmit-frames>
 <transmit-bytes>*transmit-bytes*</transmit-bytes>
 </mac-record>
 </mac-database>

Description No documentation is available yet.

Contents <mac-address>—No documentation is available yet.

<receive-bytes>—No documentation is available yet.

<receive-frames>—No documentation is available yet.

<transmit-bytes>—No documentation is available yet.

<transmit-frames>—No documentation is available yet.

<mac-validate-statistics>

Usage	<pre> <address-family> <mac-validate-statistics> <mac-validate-packets><i>mac-validate-packets</i></mac-validate-packets> <mac-validate-bytes><i>mac-validate-bytes</i></mac-validate-bytes> </mac-validate-statistics> </address-family> </pre>
Description	SRC MAC validate statistics.
Contents	<p><mac-validate-bytes>—Number of bytes that have failed the mac-validate check.</p> <p><mac-validate-packets>—Number of packets that have failed the mac-validate check.</p>

<media-alarm>

Usage	<pre> <sonet-errors sonet-physical-information sonet-section-information sonet-line-information sonet-path-information sonet-vt-information otn-errors media-information plcp-defects atm-defects otn-oc-information otn-otu-information otn-odu-information interval> <media-alarm> <media-alarm-name><i>media-alarm-name</i></media-alarm-name> <media-alarm-seconds><i>media-alarm-seconds</i></media-alarm-seconds> <media-alarm-count><i>media-alarm-count</i></media-alarm-count> <media-alarm-state><i>media-alarm-state</i></media-alarm-state> <ce-counter-name><i>ce-counter-name</i></ce-counter-name> <ce-counter-packets><i>ce-counter-packets</i></ce-counter-packets> <ce-counter-bytes><i>ce-counter-bytes</i></ce-counter-bytes> <ce-counter-count><i>ce-counter-count</i></ce-counter-count> </media-alarm> </sonet-errors sonet-physical-information sonet-section-information sonet-line-information sonet-path-information sonet-vt-information otn-errors media-information plcp-defects atm-defects otn-oc-information otn-otu-information otn-odu-information interval> </pre>
Description	No documentation is available yet.
Contents	<p><ce-counter-bytes>—Circuit Emulation number of bytes.</p> <p><ce-counter-count>—Circuit Emulation number of event occurrences.</p> <p><ce-counter-name>—Circuit Emulation counter information.</p> <p><ce-counter-packets>—Circuit Emulation number of packets.</p> <p><media-alarm-count>—No documentation is available yet.</p> <p><media-alarm-name>—No documentation is available yet.</p> <p><media-alarm-seconds>—No documentation is available yet.</p> <p><media-alarm-state>—No documentation is available yet.</p>

<media-information>

Usage <physical-interface | logical-interface>
<media-information>
 <media-alarm>...</media-alarm>
 <ds1-timeslots>*ds1-timeslots*</ds1-timeslots>
 <ds1-line-encoding>*ds1-line-encoding*</ds1-line-encoding>
 <ds1-byte-encoding>*ds1-byte-encoding*</ds1-byte-encoding>
 <ds1-data-inversion>*ds1-data-inversion*</ds1-data-inversion>
 <ds1-buildout>*ds1-buildout*</ds1-buildout>
 <ds0-byte-encoding>*ds0-byte-encoding*</ds0-byte-encoding>
 <ds0-data-inversion>*ds0-data-inversion*</ds0-data-inversion>
 <idle-cycle-flag>*idle-cycle-flag*</idle-cycle-flag>
 <start-end-flag>*start-end-flag*</start-end-flag>
 <e3-data-inversion>*e3-data-inversion*</e3-data-inversion>
 <media-type>*media-type*</media-type>
</media-information>
 </physical-interface | logical-interface>

Description Information about media alarms.

Contents <ds0-byte-encoding>—No documentation is available yet.
 <ds0-data-inversion>—No documentation is available yet.
 <ds1-buildout>—Number of feet.
 <ds1-byte-encoding>—No documentation is available yet.
 <ds1-data-inversion>—No documentation is available yet.
 <ds1-line-encoding>—No documentation is available yet.
 <ds1-timeslots>—No documentation is available yet.
 <e3-data-inversion>—No documentation is available yet.
 <idle-cycle-flag>—No documentation is available yet.
 <media-alarm>—No documentation is available yet.
 <media-type>—Type of media this information is for.
 <start-end-flag>—No documentation is available yet.

<mlfr-uni-nni-bundle-options>

Usage <physical-interface>

```

<mlfr-uni-nni-bundle-options>
  <mlfr-uni-nni-device-type>mlfr-uni-nni-device-type</mlfr-uni-nni-device-type>
  <mlfr-uni-nni-mrru>mlfr-uni-nni-mrru</mlfr-uni-nni-mrru>
  <red-differential-delay>red-differential-delay</red-differential-delay>
  <red-differential-delay-action>red-differential-delay-action
    </red-differential-delay-action>
  <yellow-differential-delay>yellow-differential-delay
    </yellow-differential-delay>
  <lip-hello-timer>lip-hello-timer</lip-hello-timer>
  <lip-ack-timer>lip-ack-timer</lip-ack-timer>
  <lip-ack-retries>lip-ack-retries</lip-ack-retries>
  <bundle-class>bundle-class</bundle-class>
  <mlfr-uni-nni-drop-timeout>mlfr-uni-nni-drop-timeout
    </mlfr-uni-nni-drop-timeout>
  <mlfr-uni-nni-link-layer-overhead>mlfr-uni-nni-link-layer-overhead
    </mlfr-uni-nni-link-layer-overhead>
  <mlfr-uni-nni-lmi-type>mlfr-uni-nni-lmi-type</mlfr-uni-nni-lmi-type>
  <mlfr-uni-nni-fragment-threshold>mlfr-uni-nni-fragment-threshold
    </mlfr-uni-nni-fragment-threshold>
  <mlfr-uni-nni-minimum-links>mlfr-uni-nni-minimum-links
    </mlfr-uni-nni-minimum-links>
  <t391>t391</t391>
  <t392>t392</t392>
  <n391>n391</n391>
  <n392>n392</n392>
  <n393>n393</n393>
</mlfr-uni-nni-bundle-options>
</physical-interface>

```

Description No documentation is available yet.

Contents <bundle-class>—Type of bundle class: A, B or C.

<lip-ack-retries>—Maximum number of retransmissions for HELLO and LINK_ADD.

<lip-ack-timer>—How long to wait for a HELLO_ACK, ADD_LINK_ACK, or REMOVE_LINK_ACK.

<lip-hello-timer>—Timer for sending periodic hello messages to the remote endpoint.

<mlfr-uni-nni-device-type>—LMI device type of this multilink Frame Relay UNI NNI bundle instance.

<mlfr-uni-nni-drop-timeout>—How long to wait for all fragments of a complete packet to arrive.

<mlfr-uni-nni-fragment-threshold>—Fragment size of this multilink Frame Relay UNI NNI bundle instance.

<mlfr-uni-nni-link-layer-overhead>—Multilink Frame Relay UNI NNI bundle link layer overhead.

<mlfr-uni-nni-lmi-type>—LMI type (ANSI or Q.933A) of this multilink Frame Relay UNI NNI bundle instance.

<mlfr-uni-nni-minimum-links>—Minimum number of links to sustain this multilink Frame Relay UNI NNI bundle instance.

<mlfr-uni-nni-mrru>—Maximum RRU size of this multilink Frame Relay UNI NNI bundle instance.

<n391>—Multilink Frame Relay UNI NNI full status polling counter.

<n392>—Multilink Frame Relay UNI NNI LMI error threshold.

<n393>—Multilink Frame Relay UNI NNI LMI monitored event count.

<red-differential-delay>—Maximum allowable differential delay of this multilink Frame Relay UNI NNI bundle instance.

<red-differential-delay-action>—Action to perform (remove link from bundle or disable transmit) when exceeding red limit.

<t391>—Multilink Frame Relay UNI NNI link integrity verify polling timer.

<t392>—Multilink Frame Relay UNI NNI polling verification timer.

<yellow-differential-delay>—Maximum allowable differential delay of this multilink Frame Relay UNI NNI bundle instance.

<mlfr-uni-nni-link>

Usage <mlfr-uni-nni-traffic-statistics>

```

<mlfr-uni-nni-link>
  <name>name</name>
  <down/>
  <link-uptime>link-uptime</link-uptime>
  <input-frames>input-frames</input-frames>
  <input-fps>input-fps</input-fps>
  <input-bytes>input-bytes</input-bytes>
  <input-bps>input-bps</input-bps>
  <output-frames>output-frames</output-frames>
  <output-fps>output-fps</output-fps>
  <output-bytes>output-bytes</output-bytes>
  <output-bps>output-bps</output-bps>
  <lip-header-string>lip-header-string</lip-header-string>
  <current-differential-delay>current-differential-delay
    </current-differential-delay>
  <recent-high-differential-delay>recent-high-differential-delay
    </recent-high-differential-delay>
  <over-red-differential>over-red-differential</over-red-differential>
  <over-yellow-differential>over-yellow-differential</over-yellow-differential>
  <rcv-lip-addlink>rcv-lip-addlink</rcv-lip-addlink>
  <rcv-lip-link-ack>rcv-lip-link-ack</rcv-lip-link-ack>
  <rcv-lip-link-rej>rcv-lip-link-rej</rcv-lip-link-rej>
  <rcv-lip-hello>rcv-lip-hello</rcv-lip-hello>
  <rcv-lip-hello-ack>rcv-lip-hello-ack</rcv-lip-hello-ack>
  <rcv-lip-link-rem>rcv-lip-link-rem</rcv-lip-link-rem>
  <rcv-lip-rem-ack>rcv-lip-rem-ack</rcv-lip-rem-ack>
  <xmt-lip-addlink>xmt-lip-addlink</xmt-lip-addlink>
  <xmt-lip-link-ack>xmt-lip-link-ack</xmt-lip-link-ack>
  <xmt-lip-link-rej>xmt-lip-link-rej</xmt-lip-link-rej>
  <xmt-lip-hello>xmt-lip-hello</xmt-lip-hello>
  <xmt-lip-hello-ack>xmt-lip-hello-ack</xmt-lip-hello-ack>
  <xmt-lip-link-rem>xmt-lip-link-rem</xmt-lip-link-rem>
  <xmt-lip-rem-ack>xmt-lip-rem-ack</xmt-lip-rem-ack>
</mlfr-uni-nni-link>
</mlfr-uni-nni-traffic-statistics>

```

Description No documentation is available yet.

Contents <current-differential-delay>—Current differential delay of this bundle link.

<down>—Link is down.

<input-bps>—No documentation is available yet.

<input-bytes>—No documentation is available yet.

<input-fps>—No documentation is available yet.

<input-frames>—No documentation is available yet.

<link-uptime>—Total uptime for the member link.

<lip-header-string>—Header string of the LIP display.

<name>—Name of this item.

<output-bps>—No documentation is available yet.

<output-bytes>—No documentation is available yet.

<output-fps>—No documentation is available yet.

<output-frames>—No documentation is available yet.

<over-red-differential>—Number of times over red differential delay.

<over-yellow-differential>—Number of times over yellow differential delay.

<rcv-lip-addlink>—Number of LIP ADD_LINKs received.

<rcv-lip-hello>—Number of LIP HELLOs received.

<rcv-lip-hello-ack>—Number of LIP HELLO_ACKs received.

<rcv-lip-link-ack>—Number of LIP ADD_LINK_ACKs received.

<rcv-lip-link-rej>—Number of LIP ADD_LINK_REJs received.

<rcv-lip-link-rem>—Number of LIP LINK_REMOVEs received.

<rcv-lip-rem-ack>—Number of LIP LINK_REMOVE_ACKs received.

<recent-high-differential-delay>—Recent highest differential delay of this bundle link (in every 256 measurements).

<xmt-lip-addlink>—Number of LIP ADD_LINKs transmitted.

<xmt-lip-hello>—Number of LIP HELLOs transmitted.

<xmt-lip-hello-ack>—Number of LIP HELLO_ACKs transmitted.

<xmt-lip-link-ack>—Number of LIP LINK_ACKs transmitted.

<xmt-lip-link-rej>—Number of LIP LINK_REJs transmitted.

<xmt-lip-link-rem>—Number of LIP LINK_REMOVEs transmitted.

<xmt-lip-rem-ack>—Number of LIP LINK_REMOVE_ACKs transmitted.

<mlfr-uni-nni-link-information>

Usage <mlfr-uni-nni-traffic-statistics>
 <mlfr-uni-nni-link-information>
 <active-bundle-links>*active-bundle-links*</active-bundle-links>
 <removed-bundle-links>*removed-bundle-links*</removed-bundle-links>
 <disabled-bundle-links>*disabled-bundle-links*</disabled-bundle-links>
 </mlfr-uni-nni-link-information>
 </mlfr-uni-nni-traffic-statistics>

Description No documentation is available yet.

Contents <active-bundle-links>—Number of active bundle links in this multilink Frame Relay UNI NNI bundle instance.

<disabled-bundle-links>—Number of bundle links that are not allowed to transmit in this multilink Frame Relay UNI NNI bundle instance.

<removed-bundle-links>—Number of bundle links that are removed from service in this multilink Frame Relay UNI NNI bundle instance.

<mlfr-uni-nni-traffic-statistics>

Usage <physical-interface>
 <mlfr-uni-nni-traffic-statistics>
 <bundle>...</bundle>
 <mlfr-uni-nni-link-information>...</mlfr-uni-nni-link-information>
 <mlfr-uni-nni-link>...</mlfr-uni-nni-link>
 </mlfr-uni-nni-traffic-statistics>
 </physical-interface>

Description No documentation is available yet.

Contents <bundle>—No documentation is available yet.

<mlfr-uni-nni-link>—No documentation is available yet.

<mlfr-uni-nni-link-information>—No documentation is available yet.

<modem-information>

Usage <physical-interface>
 <modem-information>
 <modem-type>*modem-type*</modem-type>
 <init-command-str>*init-command-str*</init-command-str>
 <init-status>*init-status*</init-status>
 <baud-rate>*baud-rate*</baud-rate>
 <call-status>*call-status*</call-status>
 <error-code>*error-code*</error-code>
 <call-duration>*call-duration*</call-duration>
 <call-direction>*call-direction*</call-direction>
 </modem-information>
 </physical-interface>

Description Operational information for MODEM interfaces.

Contents <baud-rate>—Modem baud rate.

<call-direction>—Direction of call (incoming or outgoing).

<call-duration>—Duration for which call has been on.

<call-status>—Current status of call.

<error-code>—Error string as returned by modem.

<init-command-str>—Modem initialization command string.

<init-status>—Modem initialization status.

<modem-type>—Modem type information.

<multilink-bundle-class>

Usage <logical-interface>
 <multilink-bundle-class>
 <multilink-class-id>*multilink-class-id*</multilink-class-id>
 <rx-sequence-number>*rx-sequence-number*</rx-sequence-number>
 <tx-sequence-number>*tx-sequence-number*</tx-sequence-number>
 <packet-drops>*packet-drops*</packet-drops>
 <packet-drop-bytes>*packet-drop-bytes*</packet-drop-bytes>
 <fragment-drops>*fragment-drops*</fragment-drops>
 <fragment-drop-bytes>*fragment-drop-bytes*</fragment-drop-bytes>
 <mrru-exceeded>*mrru-exceeded*</mrru-exceeded>
 <processing-errors>*processing-errors*</processing-errors>
 <fragment-timeout>*fragment-timeout*</fragment-timeout>
 <sequence-number-missing>*seq-number-missing*</sequence-number-missing>
 <out-of-order-sequence-number>*out-of-order-sequence-number*
 </out-of-order-sequence-number>
 <out-of-range-sequence-number>*out-of-range-sequence-number*
 </out-of-range-sequence-number>
 <packet-buffer-overflow>*packet-buffer-overflow*</packet-buffer-overflow>
 <fragment-buffer-overflow>*fragment-buffer-overflow*</fragment-buffer-overflow>
 <multilink-class-drop-timeout>*multilink-class-drop-timeout*
 </multilink-class-drop-timeout>
 </multilink-bundle-class>
 </logical-interface>

Description Multilink class status.

Contents <fragment-buffer-overflow>—Number of times the fragment data buffer overflowed.

<fragment-drop-bytes>—Number of bytes in dropped fragments.

<fragment-drops>—Number of fragments dropped.

<fragment-timeout>—Fragments timed out during assembly.

<mrru-exceeded>—Number of assembled packets that exceeded MRRU.

<multilink-class-drop-timeout>—Drop timeout for multilink class (milliseconds).

<multilink-class-id>—Multilink class ID.

<out-of-order-sequence-number>—Fragments with an out-of-order sequence number.

<out-of-range-sequence-number>—Fragments with an out-of-range sequence number.

<packet-buffer-overflow>—Number of times the packet data buffer overflowed.

<packet-drop-bytes>—Number of bytes in dropped packets.

<packet-drops>—Number of packets dropped.

<processing-errors>—Number of errors encountered in assembling packets.

<rx-sequence-number>—Received sequence number.

<sequence-number-missing>—Gap detected in sequence numbers.

<tx-sequence-number>—Transmitted sequence number.

<multilink-bundle-errors>

Usage <physical-interface | logical-interface>
<multilink-bundle-errors>
 <packet-drops>*packet-drops*</packet-drops>
 <packet-drop-bytes>*packet-drop-bytes*</packet-drop-bytes>
 <fragment-drops>*fragment-drops*</fragment-drops>
 <fragment-drop-bytes>*fragment-drop-bytes*</fragment-drop-bytes>
 <mrru-exceeded>*mrru-exceeded*</mrru-exceeded>
 <processing-errors>*processing-errors*</processing-errors>
</multilink-bundle-errors>
 </physical-interface | logical-interface>

Description Multilink bundle errors.

Contents <fragment-drop-bytes>—Number of bytes in dropped fragments.
 <fragment-drops>—Number of fragments dropped.
 <mrru-exceeded>—Number of assembled packets that exceeded MRRU.
 <packet-drop-bytes>—Number of bytes in dropped packets.
 <packet-drops>—Number of packets dropped.
 <processing-errors>—Number of errors encountered in assembling packets.

<multilink-bundle-link-information>

Usage <logical-interface>
 <multilink-bundle-link-information>
 <multilink-active-bundle-links>*multilink-active-bundle-links*
 </multilink-active-bundle-links>
 <multilink-removed-bundle-links>*multilink-removed-bundle-links*
 </multilink-removed-bundle-links>
 <multilink-disabled-bundle-links>*multilink-disabled-bundle-links*
 </multilink-disabled-bundle-links>
 </multilink-bundle-link-information>
 </logical-interface>

Description No documentation is available yet.

Contents <multilink-active-bundle-links>—Number of active bundle links in this multilink bundle instance.

<multilink-disabled-bundle-links>—Number of bundle links that are not allowed to transmit in this multilink bundle instance.

<multilink-removed-bundle-links>—Number of bundle links that are removed from service in this multilink bundle instance.

<multilink-bundle-options>

Usage <logical-interface>
 <multilink-bundle-options>
 <mrru>*mrru*</mrru>
 <remote-mrru>*remote-mrru*</remote-mrru>
 <drop-timeout>*drop-timeout*</drop-timeout>
 <mlppp-inner-ppp-pfc>*mlppp-inner-ppp-pfc*</mlppp-inner-ppp-pfc>
 <sequence-number-format>*sequence-number-format*</sequence-number-format>
 <fragment-threshold>*fragment-threshold*</fragment-threshold>
 <minimum-links>*minimum-links*</minimum-links>
 <interleave-fragments>*interleave-fragments*</interleave-fragments>
 <multilink-classes>*multilink-classes*</multilink-classes>
 <link-layer-overhead>*link-layer-overhead*</link-layer-overhead>
 </multilink-bundle-options>
 </logical-interface>

Description No documentation is available yet.

Contents <drop-timeout>—No documentation is available yet.

<fragment-threshold>—No documentation is available yet.

<interleave-fragments>—No documentation is available yet.

<link-layer-overhead>—Link layer overhead.

<minimum-links>—No documentation is available yet.

<mlppp-inner-ppp-pfc>—MLPPP inner PPP protocol field compression.

<mrru>—No documentation is available yet.

<multilink-classes>—Number of multilink classes.

<remote-mrru>—Remote max received reconstructed unit.

<sequence-number-format>—No documentation is available yet.

<multilink-bundle-status>

Usage <logical-interface>
<multilink-bundle-status>
 <rx-sequence-number>*rx-sequence-number*</rx-sequence-number>
 <tx-sequence-number>*tx-sequence-number*</tx-sequence-number>
 <packet-drops>*packet-drops*</packet-drops>
 <packet-drop-bytes>*packet-drop-bytes*</packet-drop-bytes>
 <fragment-drops>*fragment-drops*</fragment-drops>
 <fragment-drop-bytes>*fragment-drop-bytes*</fragment-drop-bytes>
 <mrru-exceeded>*mrru-exceeded*</mrru-exceeded>
 <processing-errors>*processing-errors*</processing-errors>
 <fragment-timeout>*fragment-timeout*</fragment-timeout>
 <sequence-number-missing>*seq-number-missing*</sequence-number-missing>
 <out-of-order-sequence-number>*out-of-order-sequence-number*
 </out-of-order-sequence-number>
 <out-of-range-sequence-number>*out-of-range-sequence-number*
 </out-of-range-sequence-number>
 <packet-buffer-overflow>*packet-buffer-overflow*</packet-buffer-overflow>
 <fragment-buffer-overflow>*fragment-buffer-overflow*</fragment-buffer-overflow>
</multilink-bundle-status>
 </logical-interface>

Description Multilink bundle status.

Contents <fragment-buffer-overflow>—Number of times the fragment data buffer overflowed.

<fragment-drop-bytes>—Number of bytes in dropped fragments.

<fragment-drops>—Number of fragments dropped.

<fragment-timeout>—Fragments timed out during assembly.

<mrru-exceeded>—Number of assembled packets that exceeded MRRU.

<out-of-order-sequence-number>—Fragments with an out-of-order sequence number.

<out-of-range-sequence-number>—Fragments with an out-of-range sequence number.

<packet-buffer-overflow>—Number of times the packet data buffer overflowed.

<packet-drop-bytes>—Number of bytes in dropped packets.

<packet-drops>—Number of packets dropped.

<processing-errors>—Number of errors encountered in assembling packets.

<rx-sequence-number>—Received sequence number.

<sequence-number-missing>—Gap detected in sequence numbers.

<tx-sequence-number>—Transmitted sequence number.

<multilink-detail-statistics>

- Usage** `<multilink-traffic-statistics>`
 <multilink-detail-statistics>
 `<bundle-detail>...</bundle-detail>`
 `<class-detail>...</class-detail>`
 </multilink-detail-statistics>
 `</multilink-traffic-statistics>`
- Description** No documentation is available yet.
- Contents** `<bundle-detail>`—No documentation is available yet.
 `<class-detail>`—No documentation is available yet.

<multilink-frames>

- Usage** `<bundle | class>`
 <multilink-frames>
 `<input-frames>input-frames</input-frames>`
 `<input-fps>input-fps</input-fps>`
 `<input-bytes>input-bytes</input-bytes>`
 `<input-bps>input-bps</input-bps>`
 `<output-frames>output-frames</output-frames>`
 `<output-fps>output-fps</output-fps>`
 `<output-bytes>output-bytes</output-bytes>`
 `<output-bps>output-bps</output-bps>`
 </multilink-frames>
 `</bundle | class>`
- Description** Link-pic bound frame statistics for multilink bundles and classes.
- Contents** `<input-bps>`—No documentation is available yet.
 `<input-bytes>`—No documentation is available yet.
 `<input-fps>`—No documentation is available yet.
 `<input-frames>`—No documentation is available yet.
 `<output-bps>`—No documentation is available yet.
 `<output-bytes>`—No documentation is available yet.
 `<output-fps>`—No documentation is available yet.
 `<output-frames>`—No documentation is available yet.

<multilink-interface-errors>

Usage <physical-interface>
 <multilink-interface-errors>
 <oversized-frames>*oversized-frames*</oversized-frames>
 <input-error-frames>*input-error-frames*</input-error-frames>
 <input-disabled-bundle>*input-disabled-bundle*</input-disabled-bundle>
 <output-disabled-bundle>*output-disabled-bundle*</output-disabled-bundle>
 <queuing-drops>*queuing-drops*</queuing-drops>
 <packet-buffer-overflow>*packet-buffer-overflow*</packet-buffer-overflow>
 <fragment-buffer-overflow>*fragment-buffer-overflow*</fragment-buffer-overflow>
 <fragment-timeout>*fragment-timeout*</fragment-timeout>
 <sequence-number-missing>*seq-number-missing*</sequence-number-missing>
 <out-of-order-sequence-number>*out-of-order-sequence-number*
 </out-of-order-sequence-number>
 <out-of-range-sequence-number>*out-of-range-sequence-number*
 </out-of-range-sequence-number>
 <data-memory-error>*data-memory-error*</data-memory-error>
 <control-memory-error>*control-memory-error*</control-memory-error>
 </multilink-interface-errors>
 </physical-interface>

Description No documentation is available yet.

Contents <control-memory-error>—Errors detected in control memory.

<data-memory-error>—Errors detected in data memory.

<fragment-buffer-overflow>—Number of times the fragment data buffer overflowed.

<fragment-timeout>—Fragments timed out during assembly.

<input-disabled-bundle>—Count of packets received on a disabled link or bundle.

<input-error-frames>—Number of frames for which an error occurred on input.

<out-of-order-sequence-number>—Fragments with an out-of-order sequence number.

<out-of-range-sequence-number>—Fragments with an out-of-range sequence number.

<output-disabled-bundle>—Count of packets transmitted on a disabled link or bundle.

<oversized-frames>—Number of oversized frames detected.

<packet-buffer-overflow>—Number of times the packet data buffer overflowed.

<queuing-drops>—Count of packets dropped by the output queue of the I/O Manager ASIC.

<sequence-number-missing>—Gap detected in sequence numbers.

<multilink-traffic-statistics>

Usage	<pre> <logical-interface> <multilink-traffic-statistics> <bundle>...</bundle> <class>...</class> <link>...</link> <multilink-detail-statistics>...</multilink-detail-statistics> <crtp>...</crtp> </multilink-traffic-statistics> </logical-interface> </pre>
Description	No documentation is available yet.
Contents	<p><bundle>—No documentation is available yet.</p> <p><class>—Multilink class traffic statistics.</p> <p><crtp>—No documentation is available yet.</p> <p><link>—No documentation is available yet.</p> <p><multilink-detail-statistics>—No documentation is available yet.</p>

<ncp-information>

Usage	<pre> <physical-interface logical-interface> <ncp-information> <ncp-protocol><i>ncp-protocol</i></ncp-protocol> <ncp-state><i>ncp-state</i></ncp-state> </ncp-information> </physical-interface logical-interface> </pre>
Description	Network Control Protocol information.
Contents	<p><ncp-protocol>—Network protocol for this NCP instance.</p> <p><ncp-state>—State of this NCP instance.</p>

<network-frames>

Usage <bundle | class>
<network-frames>
 <input-frames>*input-frames*</input-frames>
 <input-fps>*input-fps*</input-fps>
 <input-bytes>*input-bytes*</input-bytes>
 <input-bps>*input-bps*</input-bps>
 <output-frames>*output-frames*</output-frames>
 <output-fps>*output-fps*</output-fps>
 <output-bytes>*output-bytes*</output-bytes>
 <output-bps>*output-bps*</output-bps>
</network-frames>
 </bundle | class>

Description Internet/RE bound frame statistics for multilink bundles and classes.

Contents <input-bps>—No documentation is available yet.

<input-bytes>—No documentation is available yet.

<input-fps>—No documentation is available yet.

<input-frames>—No documentation is available yet.

<output-bps>—No documentation is available yet.

<output-bytes>—No documentation is available yet.

<output-fps>—No documentation is available yet.

<output-frames>—No documentation is available yet.

<non-fragments>

Usage <bundle-detail | class-detail>
<non-fragments>
 <input-frames>*input-frames*</input-frames>
 <input-fps>*input-fps*</input-fps>
 <input-bytes>*input-bytes*</input-bytes>
 <input-bps>*input-bps*</input-bps>
 <output-frames>*output-frames*</output-frames>
 <output-fps>*output-fps*</output-fps>
 <output-bytes>*output-bytes*</output-bytes>
 <output-bps>*output-bps*</output-bps>
</non-fragments>
 </bundle-detail | class-detail>

Description Non-fragment statistics for multilink bundles and classes.

Contents <input-bps>—No documentation is available yet.
 <input-bytes>—No documentation is available yet.
 <input-fps>—No documentation is available yet.
 <input-frames>—No documentation is available yet.
 <output-bps>—No documentation is available yet.
 <output-bytes>—No documentation is available yet.
 <output-fps>—No documentation is available yet.
 <output-frames>—No documentation is available yet.

<nxd0-information>

Usage <physical-interface>
<nxd0-information>
 <interface-tx-queue>...</interface-tx-queue>
</nxd0-information>
 </physical-interface>

Description No documentation is available yet.

Contents <interface-tx-queue>—No documentation is available yet.

<oam-parameters>

Usage	<virtual-path-information virtual-circuit-information> <oam-parameters> <period> <i>period</i> </period> <up-count> <i>up-count</i> </up-count> <down-count> <i>down-count</i> </down-count> </oam-parameters> </virtual-path-information virtual-circuit-information>
Description	No documentation is available yet.
Contents	<down-count>—No documentation is available yet. <period>—No documentation is available yet. <up-count>—No documentation is available yet.

<oam-statistics>

Usage <virtual-path-information | virtual-circuit-information>

```

<oam-statistics>
  <oam-loopback-received-count>oam-loopback-received-count
  </oam-loopback-received-count>
  <oam-loopback-received-last>oam-loopback-received-last
  </oam-loopback-received-last>
  <oam-loopback-transmitted-count>oam-loopback-transmitted-count
  </oam-loopback-transmitted-count>
  <oam-loopback-transmitted-last>oam-loopback-transmitted-last
  </oam-loopback-transmitted-last>
  <oam-rdi-received-count>oam-rdi-received-count</oam-rdi-received-count>
  <oam-rdi-received-last>oam-rdi-received-last</oam-rdi-received-last>
  <oam-rdi-transmitted-count>oam-rdi-transmitted-count
  </oam-rdi-transmitted-count>
  <oam-rdi-transmitted-last>oam-rdi-transmitted-last</oam-rdi-transmitted-last>
  <oam-ais-received-count>oam-ais-received-count</oam-ais-received-count>
  <oam-ais-received-last>oam-ais-received-last</oam-ais-received-last>
  <oam-ais-transmitted-count>oam-ais-transmitted-count
  </oam-ais-transmitted-count>
  <oam-ais-transmitted-last>oam-ais-transmitted-last</oam-ais-transmitted-last>
  <oam-total-transmitted-count>oam-total-transmitted-count
  </oam-total-transmitted-count>
  <oam-total-received-count>oam-total-received-count</oam-total-received-count>
  <oam-total-transmitted-count-4>oam-total-transmitted-count-4
  </oam-total-transmitted-count-4>
  <oam-total-received-count-4>oam-total-received-count-4
  </oam-total-received-count-4>
</oam-statistics>
</virtual-path-information | virtual-circuit-information>

```

Description Container tag for OAM statistics.

Contents

- <oam-ais-received-count>—No documentation is available yet.
- <oam-ais-received-last>—No documentation is available yet.
- <oam-ais-transmitted-count>—No documentation is available yet.
- <oam-ais-transmitted-last>—No documentation is available yet.
- <oam-loopback-received-count>—No documentation is available yet.
- <oam-loopback-received-last>—No documentation is available yet.
- <oam-loopback-transmitted-count>—No documentation is available yet.
- <oam-loopback-transmitted-last>—No documentation is available yet.
- <oam-rdi-received-count>—No documentation is available yet.
- <oam-rdi-received-last>—No documentation is available yet.
- <oam-rdi-transmitted-count>—No documentation is available yet.

<oam-rdi-transmitted-last>—No documentation is available yet.

<oam-total-received-count>—No documentation is available yet.

<oam-total-received-count-4>—No documentation is available yet.

<oam-total-transmitted-count>—No documentation is available yet.

<oam-total-transmitted-count-4>—No documentation is available yet.

<optics-diagnostics>**Usage** <link-entry>**<optics-diagnostics>**

```

<optic-diagnostics-not-available>optic-diagnostics-not-available
</optic-diagnostics-not-available>
<laser-bias-current-not-available>laser-bias-current-not-available
</laser-bias-current-not-available>
<laser-tx-power-not-available>laser-tx-power-not-available
</laser-tx-power-not-available>
<module-temperature-not-available>module-temperature-not-available
</module-temperature-not-available>
<laser-rx-power-not-available>laser-rx-power-not-available
</laser-rx-power-not-available>
<laser-bias-current>laser-bias-current</laser-bias-current>
<laser-output-power>laser-output-power</laser-output-power>
<laser-output-power-dbm>laser-output-power-dbm</laser-output-power-dbm>
<module-temperature>module-temperature</module-temperature>
<module-voltage>module-voltage</module-voltage>
<rx-signal-avg-optical-power>rx-signal-avg-optical-power
</rx-signal-avg-optical-power>
<rx-signal-avg-optical-power-dbm>rx-signal-avg-optical-power-dbm
</rx-signal-avg-optical-power-dbm>
<laser-rx-optical-power>laser-rx-optical-power</laser-rx-optical-power>
<laser-rx-optical-power-dbm>laser-rx-optical-power-dbm
</laser-rx-optical-power-dbm>
<laser-bias-current-high-alarm>laser-bias-current-high-alarm
</laser-bias-current-high-alarm>
<laser-bias-current-low-alarm>laser-bias-current-low-alarm
</laser-bias-current-low-alarm>
<laser-bias-current-high-warn>laser-bias-current-high-warn
</laser-bias-current-high-warn>
<laser-bias-current-low-warn>laser-bias-current-low-warn
</laser-bias-current-low-warn>
<module-voltage-high-alarm>module-voltage-high-alarm
</module-voltage-high-alarm>
<module-voltage-low-alarm>module-voltage-low-alarm</module-voltage-low-alarm>
<module-voltage-high-warn>module-voltage-high-warn</module-voltage-high-warn>
<module-voltage-low-warn>module-voltage-low-warn</module-voltage-low-warn>
<laser-tx-power-high-alarm>laser-tx-power-high-alarm
</laser-tx-power-high-alarm>
<laser-tx-power-low-alarm>laser-tx-power-low-alarm</laser-tx-power-low-alarm>
<laser-tx-power-high-warn>laser-tx-power-high-warn</laser-tx-power-high-warn>
<laser-tx-power-low-warn>laser-tx-power-low-warn</laser-tx-power-low-warn>
<module-temperature-high-alarm>module-temperature-high-alarm
</module-temperature-high-alarm>
<module-temperature-low-alarm>module-temperature-low-alarm
</module-temperature-low-alarm>
<module-temperature-high-warn>module-temperature-high-warn
</module-temperature-high-warn>
<module-temperature-low-warn>module-temperature-low-warn
</module-temperature-low-warn>
<laser-rx-power-high-alarm>laser-rx-power-high-alarm
</laser-rx-power-high-alarm>

```

```

<laser-rx-power-low-alarm>laser-rx-power-low-alarm</laser-rx-power-low-alarm>
<laser-rx-power-high-warn>laser-rx-power-high-warn</laser-rx-power-high-warn>
<laser-rx-power-low-warn>laser-rx-power-low-warn</laser-rx-power-low-warn>
<laser-end-of-life-alarm>laser-end-of-life-alarm</laser-end-of-life-alarm>
<laser-wavelength-alarm>laser-wavelength-alarm</laser-wavelength-alarm>
<laser-bias-current-alarm>la-bi-cu-alm</laser-bias-current-alarm>
<module-temperature-alarm>mod-temp-alarm</module-temperature-alarm>
<laser-power-alarm>laser-power-alarm</laser-power-alarm>
<modulator-temperature-alarm>modulator-temperature-alarm
  </modulator-temperature-alarm>
<modulator-bias-alarm>modulator-bias-alarm</modulator-bias-alarm>
<module-not-ready-alarm>module-not-ready-alarm</module-not-ready-alarm>
<module-power-down-alarm>mod-power-down-alarm</module-power-down-alarm>
<apd-supply-fault-alarm>apd-supply-fault-alarm</apd-supply-fault-alarm>
<tec-fault-alarm>tec-fault-alarm</tec-fault-alarm>
<wavelength-unlocked-alarm>wavelength-unlocked-alarm
  </wavelength-unlocked-alarm>
<tx-mux-fifo-error-alarm>tx-mux-fifo-error-alarm</tx-mux-fifo-error-alarm>
<tx-loss-of-pll-alarm>tx-loss-of-pll-alarm</tx-loss-of-pll-alarm>
<tx-data-not-ready-alarm>tx-data-not-ready-alarm</tx-data-not-ready-alarm>
<tx-not-ready-alarm>tx-not-ready-alarm</tx-not-ready-alarm>
<tx-laser-fault-alarm>tx-laser-fault-alarm</tx-laser-fault-alarm>
<tx-cdr-loss-of-lock-alarm>tx-cdr-loss-of-lock-alarm
  </tx-cdr-loss-of-lock-alarm>
<rx-loss-avg-opt-power-alarm>rx-loss-avg-opt-power-alarm
  </rx-loss-avg-opt-power-alarm>
<rx-loss-ac-power-alarm>rx-loss-ac-power-alarm</rx-loss-ac-power-alarm>
<rx-loss-of-pll-alarm>rx-loss-of-pll-alarm</rx-loss-of-pll-alarm>
<rx-not-ready-alarm>rx-not-ready-alarm</rx-not-ready-alarm>
<rx-loss-of-signal-alarm>rx-loss-of-signal-alarm</rx-loss-of-signal-alarm>
<rx-cdr-loss-of-lock-alarm>rx-cdr-loss-of-lock-alarm
  </rx-cdr-loss-of-lock-alarm>
<module-voltage-high-alarm-threshold>module-voltage-high-alarm-threshold
  </module-voltage-high-alarm-threshold>
<module-voltage-low-alarm-threshold>module-voltage-low-alarm-threshold
  </module-voltage-low-alarm-threshold>
<module-voltage-high-warn-threshold>module-voltage-high-warn-threshold
  </module-voltage-high-warn-threshold>
<module-voltage-low-warn-threshold>module-voltage-low-warn-threshold
  </module-voltage-low-warn-threshold>
<laser-bias-current-high-alarm-threshold>laser-bias-current-high-alarm-threshold
  </laser-bias-current-high-alarm-threshold>
<laser-bias-current-low-alarm-threshold>laser-bias-current-low-alarm-threshold
  </laser-bias-current-low-alarm-threshold>
<laser-bias-current-high-warn-threshold>laser-bias-current-high-warn-threshold
  </laser-bias-current-high-warn-threshold>
<laser-bias-current-low-warn-threshold>laser-bias-current-low-warn-threshold
  </laser-bias-current-low-warn-threshold>
<laser-tx-power-high-alarm-threshold>laser-tx-power-high-alarm-threshold
  </laser-tx-power-high-alarm-threshold>
<laser-tx-power-low-alarm-threshold>laser-tx-power-low-alarm-threshold
  </laser-tx-power-low-alarm-threshold>
<laser-tx-power-high-warn-threshold>laser-tx-power-high-warn-threshold
  </laser-tx-power-high-warn-threshold>

```

```

<laser-tx-power-low-warn-threshold>laser-tx-power-low-warn-threshold
</laser-tx-power-low-warn-threshold>
<laser-tx-power-high-alarm-threshold-dbm>laser-tx-power-high-alarm-threshold-dbm
</laser-tx-power-high-alarm-threshold-dbm>
<laser-tx-power-low-alarm-threshold-dbm>laser-tx-power-low-alarm-threshold-dbm
</laser-tx-power-low-alarm-threshold-dbm>
<laser-tx-power-high-warn-threshold-dbm>laser-tx-power-high-warn-threshold-dbm
</laser-tx-power-high-warn-threshold-dbm>
<laser-tx-power-low-warn-threshold-dbm>laser-tx-power-low-warn-threshold-dbm
</laser-tx-power-low-warn-threshold-dbm>
<module-temperature-high-alarm-threshold>mod-temp-high-alarm-threshold
</module-temperature-high-alarm-threshold>
<module-temperature-low-alarm-threshold>module-temperature-low-alarm-threshold
</module-temperature-low-alarm-threshold>
<module-temperature-high-warn-threshold>module-temperature-high-warn-threshold
</module-temperature-high-warn-threshold>
<module-temperature-low-warn-threshold>module-temperature-low-warn-threshold
</module-temperature-low-warn-threshold>
<laser-rx-power-high-alarm-threshold>laser-rx-power-high-alarm-threshold
</laser-rx-power-high-alarm-threshold>
<laser-rx-power-low-alarm-threshold>laser-rx-power-low-alarm-threshold
</laser-rx-power-low-alarm-threshold>
<laser-rx-power-high-warn-threshold>laser-rx-power-high-warn-threshold
</laser-rx-power-high-warn-threshold>
<laser-rx-power-low-warn-threshold>laser-rx-power-low-warn-threshold
</laser-rx-power-low-warn-threshold>
<laser-rx-power-high-alarm-threshold-dbm>laser-rx-power-high-alarm-threshold-dbm
</laser-rx-power-high-alarm-threshold-dbm>
<laser-rx-power-low-alarm-threshold-dbm>laser-rx-power-low-alarm-threshold-dbm
</laser-rx-power-low-alarm-threshold-dbm>
<laser-rx-power-high-warn-threshold-dbm>laser-rx-power-high-warn-threshold-dbm
</laser-rx-power-high-warn-threshold-dbm>
<laser-rx-power-low-warn-threshold-dbm>laser-rx-power-low-warn-threshold-dbm
</laser-rx-power-low-warn-threshold-dbm>
<optics-diagnostics-lane-values>...</optics-diagnostics-lane-values>
</optics-diagnostics>
</link-entry>

```

Description Optics diagnostics.

Contents <apd-supply-fault-alarm>—APD supply fault alarm.

<laser-bias-current>—Laser bias current (milliamperes).

<laser-bias-current-alarm>—Laser bias current alarm.

<laser-bias-current-high-alarm>—Laser bias current high alarm.

<laser-bias-current-high-alarm-threshold>—Laser bias current high alarm threshold (milliamperes).

<laser-bias-current-high-warn>—Laser bias current high warning.

<laser-bias-current-high-warn-threshold>—Laser bias current high warning threshold (milliamperes).

<laser-bias-current-low-alarm>—Laser bias current low alarm.

<laser-bias-current-low-alarm-threshold>—Laser bias current low alarm threshold (milliamperes).

<laser-bias-current-low-warn>—Laser bias current low warning.

<laser-bias-current-low-warn-threshold>—Laser bias current low warning threshold (milliamperes).

<laser-bias-current-not-available>—Laser bias current measurement not available.

<laser-end-of-life-alarm>—Laser end-of-life alarm.

<laser-output-power>—Laser output power (milliwatts).

<laser-output-power-dbm>—Laser output power (dBm).

<laser-power-alarm>—Laser power alarm.

<laser-rx-optical-power>—Laser receiver optical power (milliwatts).

<laser-rx-optical-power-dbm>—Laser receiver optical power (dBm).

<laser-rx-power-high-alarm>—Laser receiver optical power high alarm.

<laser-rx-power-high-alarm-threshold>—Laser receiver power high alarm (milliwatts).

<laser-rx-power-high-alarm-threshold-dbm>—Laser receiver power high alarm (dBm).

<laser-rx-power-high-warn>—Laser receiver optical power high warning.

<laser-rx-power-high-warn-threshold>—Laser receiver power high warning (milliwatts).

<laser-rx-power-high-warn-threshold-dbm>—Laser receiver power high warning (dBm).

<laser-rx-power-low-alarm>—Laser receiver optical power low alarm.

<laser-rx-power-low-alarm-threshold>—Laser receiver power low alarm (milliwatts).

<laser-rx-power-low-alarm-threshold-dbm>—Laser receiver power low alarm (dBm).

<laser-rx-power-low-warn>—Laser receiver optical power low warning.

<laser-rx-power-low-warn-threshold>—Laser receiver power low warning (milliwatts).

<laser-rx-power-low-warn-threshold-dbm>—Laser receiver power low warning (dBm).

<laser-rx-power-not-available>—Laser receiver optical power measurement not available.

<laser-tx-power-high-alarm>—Laser transmitter optical power high alarm.

<laser-tx-power-high-alarm-threshold>—Laser transmitter power high alarm threshold (milliwatts).

<laser-tx-power-high-alarm-threshold-dbm>—Laser transmitter power high alarm threshold (dBm).

<laser-tx-power-high-warn>—Laser transmitter optical power high warning.

<laser-tx-power-high-warn-threshold>—Laser transmitter power high warning threshold (milliwatts).

<laser-tx-power-high-warn-threshold-dbm>—Laser transmitter power high warning threshold (dBm).

<laser-tx-power-low-alarm>—Laser transmitter optical power low alarm.

<laser-tx-power-low-alarm-threshold>—Laser transmitter power low alarm threshold (milliwatts).

<laser-tx-power-low-alarm-threshold-dbm>—Laser transmitter power low alarm threshold (dBm).

<laser-tx-power-low-warn>—Laser transmitter optical power low warning.

<laser-tx-power-low-warn-threshold>—Laser transmitter power low warning threshold (milliwatts).

<laser-tx-power-low-warn-threshold-dbm>—Laser transmitter power low warning threshold (dBm).

<laser-tx-power-not-available>—Laser output power measurement not available.

<laser-wavelength-alarm>—Laser wavelength alarm.

<modulator-bias-alarm>—Modulator bias alarm.

<modulator-temperature-alarm>—Modulator temperature alarm.

<module-not-ready-alarm>—Module not ready alarm.

<module-power-down-alarm>—Module power down alarm.

<module-temperature>—Module temperature.

<module-temperature-alarm>—Module temperature alarm.

<module-temperature-high-alarm>—Module temperature high alarm.

<module-temperature-high-alarm-threshold>—Module temperature high alarm threshold.

<module-temperature-high-warn>—Module temperature high warning.

<module-temperature-high-warn-threshold>—Module temperature high warning threshold.

<module-temperature-low-alarm>—Module temperature low alarm.

<module-temperature-low-alarm-threshold>—Module temperature low alarm threshold.

<module-temperature-low-warn>—Module temperature low warning.

<module-temperature-low-warn-threshold>—Module temperature low warning threshold.

<module-temperature-not-available>—Module temperature measurement not available.

<module-voltage>—Module voltage.

<module-voltage-high-alarm>—Module voltage high alarm.

<module-voltage-high-alarm-threshold>—Module voltage high alarm threshold (volts).

<module-voltage-high-warn>—Module voltage high warning.

<module-voltage-high-warn-threshold>—Module voltage high warning threshold (volts).

<module-voltage-low-alarm>—Module voltage low alarm.

<module-voltage-low-alarm-threshold>—Module voltage low alarm threshold (volts).

<module-voltage-low-warn>—Module voltage low warning.

<module-voltage-low-warn-threshold>—Module voltage low warning threshold (volts).

<optic-diagnostics-not-available>—Optical diagnostics not supported by this transceiver.

<optics-diagnostics-lane-values>—No documentation is available yet.

<rx-cdr-loss-of-lock-alarm>—Receiver CDR loss of lock alarm.

<rx-loss-ac-power-alarm>—Receiver loss of AC power alarm.

<rx-loss-avg-opt-power-alarm>—Receiver loss of average optical power alarm.

<rx-loss-of-pll-alarm>—Receiver loss of PLL alarm.

<rx-loss-of-signal-alarm>—Receiver loss of signal alarm.

<rx-not-ready-alarm>—Receiver not ready alarm.

<rx-signal-avg-optical-power>—Receiver signal average power (milliwatts).

<rx-signal-avg-optical-power-dbm>—Receiver signal average power (dBm).

<tec-fault-alarm>—TEC fault alarm.

<tx-cdr-loss-of-lock-alarm>—Tx CDR loss of lock alarm.

<tx-data-not-ready-alarm>—Tx data not ready alarm.

<tx-laser-fault-alarm>—Tx laser fault alarm.

<tx-loss-of-pll-alarm>—Tx loss of PLL alarm.

<tx-mux-fifo-error-alarm>—Tx multiplexer fifo error alarm.

<tx-not-ready-alarm>—Tx not ready alarm.

<wavelength-unlocked-alarm>—Wavelength unlocked alarm.

<optics-diagnostics-lane-values>

Usage <optics-diagnostics>
 <optics-diagnostics-lane-values>
 <lane-index>*lane-index*</lane-index>
 <laser-bias-current>*laser-bias-current*</laser-bias-current>
 <laser-output-power>*laser-output-power*</laser-output-power>
 <laser-output-power-dbm>*laser-output-power-dbm*</laser-output-power-dbm>
 <module-temperature>*module-temperature*</module-temperature>
 <laser-rx-optical-power>*laser-rx-optical-power*</laser-rx-optical-power>
 <laser-rx-optical-power-dbm>*laser-rx-optical-power-dbm*
 </laser-rx-optical-power-dbm>
 <laser-bias-current-high-alarm>*laser-bias-current-high-alarm*
 </laser-bias-current-high-alarm>
 <laser-bias-current-low-alarm>*laser-bias-current-low-alarm*
 </laser-bias-current-low-alarm>
 <laser-bias-current-high-warn>*laser-bias-current-high-warn*
 </laser-bias-current-high-warn>
 <laser-bias-current-low-warn>*laser-bias-current-low-warn*
 </laser-bias-current-low-warn>
 </optics-diagnostics-lane-values>
 </optics-diagnostics>

Description No documentation is available yet.

Contents <lane-index>—No documentation is available yet.

<laser-bias-current>—Laser bias current (milliamperes).

<laser-bias-current-high-alarm>—Laser bias current high alarm.

<laser-bias-current-high-warn>—Laser bias current high warning.

<laser-bias-current-low-alarm>—Laser bias current low alarm.

<laser-bias-current-low-warn>—Laser bias current low warning.

<laser-output-power>—Laser output power (milliwatts).

<laser-output-power-dbm>—Laser output power (dBm).

<laser-rx-optical-power>—Laser receiver optical power (milliwatts).

<laser-rx-optical-power-dbm>—Laser receiver optical power (dBm).

<module-temperature>—Module temperature.

<optics-properties>

Usage	<pre> <physical-interface> <optics-properties> <wavelength>wavelength</wavelength> <frequency>frequency</frequency> </optics-properties> </physical-interface> </pre>
Description	Optics properties.
Contents	<p><frequency>—Frequency of optics in terahertz.</p> <p><wavelength>—Wavelength of optics in nanometers.</p>

<otn-errors>

Usage	<pre> <physical-interface> <otn-errors> <media-alarm>...</media-alarm> </otn-errors> </physical-interface> </pre>
Description	No documentation is available yet.
Contents	<media-alarm>—No documentation is available yet.

<otn-fec-statistics>

Usage	<pre> <physical-interface> <otn-fec-statistics> <fec-corrected-errors>fec-corrected-errors</fec-corrected-errors> <fec-corrected-error-ratio>fec-corrected-error-ratio </fec-corrected-error-ratio> </otn-fec-statistics> </physical-interface> </pre>
Description	No documentation is available yet.
Contents	<p><fec-corrected-error-ratio>—No documentation is available yet.</p> <p><fec-corrected-errors>—No documentation is available yet.</p>

<otn-oc-information>

Usage	<pre> <physical-interface> <otn-oc-information> <media-alarm>...</media-alarm> </otn-oc-information> </physical-interface> </pre>
Description	No documentation is available yet.
Contents	<media-alarm>—No documentation is available yet.

<otn-odu-information>

Usage <physical-interface>
 <otn-odu-information>
 <media-alarm>...</media-alarm>
 </otn-odu-information>
</physical-interface>

Description No documentation is available yet.

Contents <media-alarm>—No documentation is available yet.

<otn-otu-information>

Usage <physical-interface>
 <otn-otu-information>
 <media-alarm>...</media-alarm>
 </otn-otu-information>
</physical-interface>

Description No documentation is available yet.

Contents <media-alarm>—No documentation is available yet.

<output-error-list>

Usage	<pre> <physical-interface> <output-error-list> <carrier-transitions>carrier-transitions</carrier-transitions> <output-errors>output-errors</output-errors> <output-drops>output-drops</output-drops> <output-collisions>output-collisions</output-collisions> <output-hs-link-fifo-overflows>output-hs-link-fifo-overflows </output-hs-link-fifo-overflows> <aged-packets>aged-packets</aged-packets> <output-fifo-errors>output-fifo-errors</output-fifo-errors> <hs-link-fifo-underflows>hs-link-fifo-underflows</hs-link-fifo-underflows> <hs-link-crc-errors>hs-link-crc-errors</hs-link-crc-errors> <mtu-errors>mtu-errors</mtu-errors> <output-resource-errors>output-resource-errors</output-resource-errors> </output-error-list> </physical-interface> </pre>
Description	Output errors on this interface.
Contents	<p><aged-packets>—Number of packets that remained in shared packet SDRAM for so long that the system automatically purged them. The value in this field should never increment. If it does, it is most likely a software bug or possible broken hardware.</p> <p><carrier-transitions>—Number of times the interface has gone from down to up. This number should not increment quickly, increasing, for example, only when the cable is unplugged or the far-end system is powered down and up. If it does increment quickly (perhaps 1 every 10 seconds), then something is broken: the cable, the far-end system, or the PIC.</p> <p><hs-link-crc-errors>—Count of errors on the high-speed links between the ASICs responsible for handling the router interfaces.</p> <p><hs-link-fifo-underflows>—Numbers of errors on the high-speed links between the ASICs responsible for handling the router interfaces. The value in this field should always be 0. If it increments, either the FPC or the PIC is broken.</p> <p><mtu-errors>—Number of packets whose size exceeded MTU of interface.</p> <p><output-collisions>—Number of Ethernet collisions. The Gigabit Ethernet PIC and Fast Ethernet PIC support only full-duplex operation, so this number should always remain 0. If it is nonzero, there is a software bug.</p> <p><output-drops>—Number of packets dropped by the output queue of the I/O Manager ASIC. If the interface is saturated, this number increments once for every packet that is dropped by the ASIC's RED mechanism.</p> <p><output-errors>—Sum of the outgoing frame aborts and FCS errors.</p> <p><output-fifo-errors>—No documentation is available yet.</p> <p><output-hs-link-fifo-overflows>—No documentation is available yet.</p>

<output-resource-errors>—Sum of B chip Tx drops and IXP Tx net transmit drops.

<peer-configuration-status>

Usage <physical-interface>
 <peer-configuration-status>
 <peer-nonmatching-dlci>*peer-nonmatching-dlci*</peer-nonmatching-dlci>
 </peer-configuration-status>
 </physical-interface>

Description Nonmatching DCE end DLCIs.

Contents <peer-nonmatching-dlci>—DCE end DLCIs that does not match the DTE.

<pfe-information>

Usage <physical-interface>
 <pfe-information>
 <destination-slot>*destination-slot*</destination-slot>
 <destination-mask>*destination-mask*</destination-mask>
 <stream-number>*stream-number*</stream-number>
 <stream-mask>*stream-mask*</stream-mask>
 <plp-byte>*plp-byte*</plp-byte>
 <plp-byte-count>*plp-byte-count*</plp-byte-count>
 <pop-all-label>*pop-all-label*</pop-all-label>
 </pfe-information>
 </physical-interface>

Description Information about Packet Forwarding Engine configuration.

Contents <destination-mask>—No documentation is available yet.
 <destination-slot>—No documentation is available yet.
 <plp-byte>—No documentation is available yet.
 <plp-byte-count>—No documentation is available yet.
 <pop-all-label>—No documentation is available yet.
 <stream-mask>—No documentation is available yet.
 <stream-number>—No documentation is available yet.

<physical-interface>**Usage** <interface-information | interface-filter-information | interface-policer-information>**<physical-interface>**

```

<name>name</name>
<admin-status>admin-status</admin-status>
<oper-status>oper-status</oper-status>
<local-index>local-index</local-index>
<snmp-index>snmp-index</snmp-index>
<generation>generation</generation>
<description>description</description>
<if-type>if-type</if-type>
<link-level-type>link-level-type</link-level-type>
<mtu>mtu</mtu>
<link-mode>link-mode</link-mode>
<speed>speed</speed>
<max-speed>max-speed</max-speed>
<duplex>duplex</duplex>
<clocking>clocking</clocking>
<sonet-mode>sonet-mode</sonet-mode>
<physical-mode>physical-mode</physical-mode>
<l2circuit-mode>l2circuit-mode</l2circuit-mode>
<ifd-cell-bundle-size>ifd-cell-bundle-size</ifd-cell-bundle-size>
<ifd-cell-bundle-timeout>ifd-cell-bundle-timeout</ifd-cell-bundle-timeout>
<loopback>loopback</loopback>
<ih-parent>ih-parent</ih-parent>
<atm-line-build-out>atm-line-build-out</atm-line-build-out>
<atm-encapsulation>atm-encapsulation</atm-encapsulation>
<atm-e3-framing>atm-e3-framing</atm-e3-framing>
<sonet-loopback>sonet-loopback</sonet-loopback>
<crc>crc</crc>
<payload-scrambler>payload-scrambler</payload-scrambler>
<ingress-rate-limit>ingress-rate-limit</ingress-rate-limit>
<source-filtering>source-filtering</source-filtering>
<if-flow-control>if-flow-control</if-flow-control>
<bpdu-error>bpdu-error</bpdu-error>
<l2pt-error>l2pt-error</l2pt-error>
<if-unidirectional>if-unidirectional</if-unidirectional>
<if-auto-negotiation>if-auto-negotiation</if-auto-negotiation>
<if-remote-fault>if-remote-fault</if-remote-fault>
<minimum-links-in-aggregate>minimum-links-in-aggregate
</minimum-links-in-aggregate>
<minimum-bandwidth-in-aggregate>minimum-bandwidth-in-aggregate
</minimum-bandwidth-in-aggregate>
<if-device-flags>...</if-device-flags>
<if-config-flags>...</if-config-flags>
<shared-uplink-physical-interface>...</shared-uplink-physical-interface>
<link-type>link-type</link-type>
<if-media-flags>...</if-media-flags>
<optics-properties>...</optics-properties>
<keepalive-config>...</keepalive-config>
<lmi-dce-config>...</lmi-dce-config>
<lmi-dte-config>...</lmi-dte-config>
<queue-counters>...</queue-counters>

```

```

<keepalive-statistics>...</keepalive-statistics>
<ppp-flags>...</ppp-flags>
<lcp-state>lcp-state</lcp-state>
<ncp-information>...</ncp-information>
<chap-state>chap-state</chap-state>
<pap-state>pap-state</pap-state>
<physical-information>physical-information</physical-information>
<es-ifd-stats>...</es-ifd-stats>
<up-hold-time>up-hold-time</up-hold-time>
<down-hold-time>down-hold-time</down-hold-time>
<current-physical-address>current-physical-address</current-physical-address>
<hardware-physical-address>hardware-physical-address
    </hardware-physical-address>
<alternate-physical-address>alternate-physical-address
    </alternate-physical-address>
<interface-flapped>interface-flapped</interface-flapped>
<statistics-cleared>statistics-cleared</statistics-cleared>
<preserve-interface>preserve-interface</preserve-interface>
<preserve-interface-statistics>...</preserve-interface-statistics>
<traffic-statistics>...</traffic-statistics>
<ingress-traffic-statistics>...</ingress-traffic-statistics>
<multilink-interface-errors>...</multilink-interface-errors>
<mlfr-uni-nni-bundle-options>...</mlfr-uni-nni-bundle-options>
<multilink-bundle-errors>...</multilink-bundle-errors>
<input-error-list>...</input-error-list>
<input-error-count>input-error-count</input-error-count>
<output-error-list>...</output-error-list>
<output-error-count>output-error-count</output-error-count>
<ber-threshold>...</ber-threshold>
<ds1-crc-alarm-threshold>...</ds1-crc-alarm-threshold>
<active-alarms>...</active-alarms>
<active-defects>...</active-defects>
<sonet-errors>...</sonet-errors>
<sonet-physical-information>...</sonet-physical-information>
<sonet-section-information>...</sonet-section-information>
<sonet-line-information>...</sonet-line-information>
<sonet-path-information>...</sonet-path-information>
<sonet-payload-pointer-information>...</sonet-payload-pointer-information>
<sonet-payload-pointer-curptr>sonet-payload-pointer-curptr
    </sonet-payload-pointer-curptr>
<sonet-payload-pointer-ptrinc-count>sonet-payload-pointer-ptrinc-count
    </sonet-payload-pointer-ptrinc-count>
<sonet-payload-pointer-ptrdec-count>sonet-payload-pointer-ptrdec-count
    </sonet-payload-pointer-ptrdec-count>
<sonet-payload-pointer-newptr-ndf-count>sonet-payload-pointer-newptr-ndf-count
    </sonet-payload-pointer-newptr-ndf-count>
<sonet-vt-information>...</sonet-vt-information>
<sonet-rx-overhead>sonet-rx-overhead</sonet-rx-overhead>
<sonet-tx-overhead>sonet-tx-overhead</sonet-tx-overhead>
<sonet-rx-path-trace>sonet-rx-path-trace</sonet-rx-path-trace>
<sonet-tx-path-trace>sonet-tx-path-trace</sonet-tx-path-trace>
<otn-errors>...</otn-errors>
<otn-rx-overhead>otn-rx-overhead</otn-rx-overhead>
<otn-tx-overhead>otn-tx-overhead</otn-tx-overhead>

```

```

<otn-fec-statistics>...</otn-fec-statistics>
<media-information>...</media-information>
<ethernet-pcs-statistics>...</ethernet-pcs-statistics>
<ethernet-mac-statistics>...</ethernet-mac-statistics>
<ethernet-filter-statistics>...</ethernet-filter-statistics>
<ethernet-autonegotiation>...</ethernet-autonegotiation>
<link-partner-status>link-partner-status</link-partner-status>
<local-info>...</local-info>
<mac-database>...</mac-database>
<dsl-information>...</dsl-information>
<shdsl-information>...</shdsl-information>
<atm-information>...</atm-information>
<modem-information>...</modem-information>
<serial-information>...</serial-information>
<virtual-path-information>...</virtual-path-information>
<ct3-information>...</ct3-information>
<cds1-information>...</cds1-information>
<nxds0-information>...</nxds0-information>
<ds3-mode>ds3-mode</ds3-mode>
<ds3-long-buildout>ds3-long-buildout</ds3-long-buildout>
<e3-framing>e3-framing</e3-framing>
<ds1-framing>ds1-framing</ds1-framing>
<dsu-information>...</dsu-information>
<ds3-bert-information>...</ds3-bert-information>
<e3-bert-information>...</e3-bert-information>
<ds1-bert-information>...</ds1-bert-information>
<ds0-bert-information>...</ds0-bert-information>
<hdlc-information>...</hdlc-information>
<pfe-information>...</pfe-information>
<logical-interface>...</logical-interface>
<links>...</links>
<peer-configuration-status>...</peer-configuration-status>
<lmi-statistics>...</lmi-statistics>
<lsi-traffic-statistics>...</lsi-traffic-statistics>
<stp-traffic-statistics>...</stp-traffic-statistics>
<chassis-queue-counters>...</chassis-queue-counters>
<ingress-queue-counters>...</ingress-queue-counters>
<otn-oc-information>...</otn-oc-information>
<otn-otu-information>...</otn-otu-information>
<otn-odu-information>...</otn-odu-information>
<satop-information>...</satop-information>
<cesopsn-information>...</cesopsn-information>
<cos-information>...</cos-information>
<physical-interface-cos-information>...</physical-interface-cos-information>
<mlfr-uni-nni-traffic-statistics>...</mlfr-uni-nni-traffic-statistics>
<interval-information>...</interval-information>
</physical-interface>
</interface-information | interface-filter-information | interface-policer-information>

```

Description Information about a single physical interface.

Contents	<p><active-alarms>—Media-specific defects that can render the interface unable to pass packets. When a defect persists for a certain amount of time, it is promoted to an alarm. Based on the router configuration, an alarm can ring the red or yellow alarm bell on the router, or the red or yellow alarm LED on the craft interface.</p> <p><active-defects>—Media-specific defects that can render the interface unable to pass packets. When a defect persists for a certain amount of time, it is promoted to an alarm. Based on the router configuration, an alarm can ring the red or yellow alarm bell on the router, or the red or yellow alarm LED on the craft interface.</p> <p><admin-status>—Desired state of the interface.</p> <p><alternate-physical-address>—Alternate physical address for this interface.</p> <p><atm-e3-framing>—Type of framing.</p> <p><atm-encapsulation>—Type of ATM encapsulation.</p> <p><atm-information>—Operational information and statistics for ATM interfaces.</p> <p><atm-line-build-out>—Line buildout.</p> <p><ber-threshold>—Bit error rate (BER) threshold for SONET interface.</p> <p><bpdu-error>—No documentation is available yet.</p> <p><cds1-information>—No documentation is available yet.</p> <p><cesopsn-information>—No documentation is available yet.</p> <p><chap-state>—State of the Challenge Handshake Authentication Protocol.</p> <p><chassis-queue-counters>—Chassis queue counter statistics.</p> <p><clocking>—Reference clock source.</p> <p><cos-information>—Information about class-of-service configuration.</p> <p><crc>—Frame checksum on the interface (either 16 or 32).</p> <p><ct3-information>—No documentation is available yet.</p> <p><current-physical-address>—Configured physical address for this interface.</p> <p><description>—Description of this interface.</p> <p><down-hold-time>—Down hold-time for this interface (milliseconds).</p> <p><ds0-bert-information>—DS0 BERT configuration and statistics.</p> <p><ds1-bert-information>—DS1 BERT configuration and statistics.</p> <p><ds1-crc-alarm-threshold>—DS1 CRC alarm thresholds.</p>
-----------------	--

<ds1-framing>—No documentation is available yet.

<ds3-bert-information>—DS3 BERT configuration and statistics.

<ds3-long-buildout>—No documentation is available yet.

<ds3-mode>—No documentation is available yet.

<dsl-information>—Operational information and statistics for ADSL interfaces.

<dsu-information>—DSU configuration and statistics.

<duplex>—Duplex at which the interface is running.

<e3-bert-information>—E3 BERT configuration and statistics.

<e3-framing>—No documentation is available yet.

<es-ifd-stats>—ES PIC statistics.

<ethernet-autonegotiation>—Ethernet autonegotiation information.

<ethernet-filter-statistics>—Ethernet filter statistics.

<ethernet-mac-statistics>—Ethernet MAC statistics.

<ethernet-pcs-statistics>—Ethernet PCS statistics.

<generation>—Generation number used to distinguish between successive instances of this interface.

<hardware-physical-address>—Hardware physical address for this interface.

<hdlc-information>—No documentation is available yet.

<if-auto-negotiation>—Status of auto-negotiation.

<if-config-flags>—No documentation is available yet.

<if-device-flags>—No documentation is available yet.

<if-flow-control>—No documentation is available yet.

<if-media-flags>—No documentation is available yet.

<if-remote-fault>—Status of remote fault.

<if-type>—No documentation is available yet.

<if-unidirectional>—No documentation is available yet.

<ifd-cell-bundle-size>—Cell bundle size for physical interface.

<ifd-cell-bundle-timeout>—Cell bundle timeout for physical interface.

<ih-parent>—Controller parent.

<ingress-queue-counters>—Ingress queue counter statistics.

<ingress-rate-limit>—Layer 2 rate limit on ingress traffic for the port.

<ingress-traffic-statistics>—Number and rate of bytes and packets received in the ingress side at Packet Forwarding Engine.

<input-error-count>—Sum of all input errors on this interface.

<input-error-list>—Input errors on this interface.

<interface-flapped>—Time when the interface last flapped.

<interval-information>—No documentation is available yet.

<keepalive-config>—Configured keepalive settings on this interface.

<keepalive-statistics>—Keepalive statistics for this interface.

<l2circuit-mode>—Indicates if the interface is in L2 circuit AAL5 or Cell mode.

<l2pt-error>—No documentation is available yet.

<lcp-state>—State of the Line Control Protocol.

<link-level-type>—Encapsulation being used on the physical interface.

<link-mode>—Link mode of the interface.

<link-partner-status>—Auto-negotiation status of link partner.

<link-type>—No documentation is available yet.

<links>—Aggregated SONET/SDH link information.

<lmi-dce-config>—Configured LMI DCE setting on this interface.

<lmi-dte-config>—Configured LMI DTE setting on this interface.

<lmi-statistics>—LMI statistics for an interface.

<local-index>—Local kernel index for this interface.

<local-info>—Auto-negotiation status of local partner.

<logical-interface>—Information about a single logical interface.

<loopback>—Whether loopback is enabled and the type of loopback.

<lsi-traffic-statistics>—Information about label-switched bytes and packets received on the physical interface.

<mac-database>—No documentation is available yet.

<max-speed>—Maximum speed at which interface can run.

<media-information>—Information about media alarms.

<minimum-bandwidth-in-aggregate>—Minimum bandwidth needed for the bundle to be up.

<minimum-links-in-aggregate>—Minimum number of links needed for the bundle to be up.

<mlfr-uni-nni-bundle-options>—No documentation is available yet.

<mlfr-uni-nni-traffic-statistics>—No documentation is available yet.

<modem-information>—Operational information for MODEM interfaces.

<mtu>—MTU size on this interface.

<multilink-bundle-errors>—Multilink bundle errors.

<multilink-interface-errors>—No documentation is available yet.

<name>—Name of this item.

<ncp-information>—Network Control Protocol information.

<nxd0-information>—No documentation is available yet.

<oper-status>—Current operational state of the interface.

<optics-properties>—Optics properties.

<otn-errors>—No documentation is available yet.

<otn-fec-statistics>—No documentation is available yet.

<otn-oc-information>—No documentation is available yet.

<otn-odu-information>—No documentation is available yet.

<otn-otu-information>—No documentation is available yet.

<otn-rx-overhead>—No documentation is available yet.

<otn-tx-overhead>—No documentation is available yet.

<output-error-count>—Sum of all output errors on this interface.

<output-error-list>—Output errors on this interface.

<pap-state>—State of the Password Authentication Protocol.

<payload-scrambler>—Whether payload scrambling is enabled.

<peer-configuration-status>—Nonmatching DCE end DLCIs.

<pfe-information>—Information about Packet Forwarding Engine configuration.

<physical-information>—No documentation is available yet.

<physical-interface-cos-information>—Physical interface class-of-service parameters.

<physical-mode>—Physical mode.

<ppp-flags>—Additional flags applicable to PPP encapsulation.

<preserve-interface>—Whether interface preservation is enabled or disabled.

<preserve-interface-statistics>—Interface switchover statistics.

<queue-counters>—Queue counter statistics.

<satop-information>—No documentation is available yet.

<serial-information>—Serial interfaces information and statistics.

<shared-uplink-physical-interface>—Shared uplink physical interface.

<shdsl-information>—Operational information and statistics for SHDSL interfaces.

<snmp-index>—SNMP ifIndex for this interface.

<sonet-errors>—No documentation is available yet.

<sonet-line-information>—No documentation is available yet.

<sonet-loopback>—SONET loopback setting on channelized OC12 interface.

<sonet-mode>—Whether the interface is in SDH or SONET mode.

<sonet-path-information>—No documentation is available yet.

<sonet-payload-pointer-curptr>—Value of the SONET/SDH payload pointer, derived from the H1 and H2 overhead bytes.

<sonet-payload-pointer-information>—No documentation is available yet.

<sonet-payload-pointer-newptr-ndf-count>—Number of times a new payload pointer was created with the New Data Found flag set.

<sonet-payload-pointer-ptrdec-count>—Number of times the value of the SONET/SDH payload pointer had negative justification.

<sonet-payload-pointer-ptrinc-count>—Number of times the value of the SONET/SDH payload pointer had positive justification.

<sonet-physical-information>—No documentation is available yet.

<sonet-rx-overhead>—No documentation is available yet.

<sonet-rx-path-trace>—Received SONET path trace.

<sonet-section-information>—No documentation is available yet.

<sonet-tx-overhead>—No documentation is available yet.

<sonet-tx-path-trace>—Transmitted SONET path trace.

<sonet-vt-information>—No documentation is available yet.

<source-filtering>—Whether source filtering is enabled or disabled.

<speed>—Speed at which the interface is running.

<statistics-cleared>—Time when statistics were last cleared.

<stp-traffic-statistics>—Information about dropped bytes and packets due to STP state.

<traffic-statistics>—Number and rate of bytes and packets received and transmitted on the physical interface.

<up-hold-time>—Up hold-time for this interface (milliseconds).

<virtual-path-information>—Operational information and statistics for a virtual path.

<physical-interface-cos-information>

Usage <physical-interface>
 <physical-interface-cos-information>
 <physical-interface-cos-hw-max-queues>*physical-interface-cos-hw-max-queues*
 </physical-interface-cos-hw-max-queues>
 <physical-interface-cos-use-max-queues>*physical-interface-cos-use-max-queues*
 </physical-interface-cos-use-max-queues>
 <physical-interface-schedulers>*physical-interface-schedulers*
 </physical-interface-schedulers>
 <physical-interface-red-buffer-occupancy>...
 </physical-interface-red-buffer-occupancy>
 </physical-interface-cos-information>
 </physical-interface>

Description Physical interface class-of-service parameters.

Contents <physical-interface-cos-hw-max-queues>—Maximum number of class-of-service queues supported by the hardware.

<physical-interface-cos-use-max-queues>—Maximum number of usable class-of-service queues.

<physical-interface-red-buffer-occupancy>—Type of buffer occupancy information used for performing random early drop on the interface.

<physical-interface-schedulers>—Schedulers allocated to this interface.

<physical-interface-red-buffer-occupancy>

- Usage** <physical-interface-cos-information>
 <physical-interface-red-buffer-occupancy>
 <instant-usage-weight-exponent>*instant-usage-weight-exponent*
 </instant-usage-weight-exponent>
 </physical-interface-red-buffer-occupancy>
 </physical-interface-cos-information>
- Description** Type of buffer occupancy information used for performing random early drop on the interface.
- Contents** <instant-usage-weight-exponent>—Weight used for instant buffer usage information for computing buffer occupancy expressed as a negative exponent of 2.

<plcp-defects>

- Usage** <atm-information>
 <plcp-defects>
 <media-alarm>...</media-alarm>
 </plcp-defects>
 </atm-information>
- Description** No documentation is available yet.
- Contents** <media-alarm>—No documentation is available yet.

<plcp-statistics>

- Usage** <atm-information>
 <plcp-statistics>
 <ferr-count>*ferr-count*</ferr-count>
 <ferr-seconds>*ferr-seconds*</ferr-seconds>
 <bipe-count>*bipe-count*</bipe-count>
 <bipe-seconds>*bipe-seconds*</bipe-seconds>
 <febe-count>*febe-count*</febe-count>
 <febe-seconds>*febe-seconds*</febe-seconds>
 </plcp-statistics>
 </atm-information>
- Description** No documentation is available yet.
- Contents** <bipe-count>—No documentation is available yet.
 <bipe-seconds>—No documentation is available yet.
 <febe-count>—No documentation is available yet.
 <febe-seconds>—No documentation is available yet.
 <ferr-count>—No documentation is available yet.
 <ferr-seconds>—No documentation is available yet.

<policer-information>

- Usage** <logical-interface | address-family>
<policer-information>
 <policer-family>*policer-family*</policer-family>
 <policer-input>*policer-input*</policer-input>
 <policer-output>*policer-output*</policer-output>
</policer-information>
 </logical-interface | address-family>
- Description** Interface policer information.
- Contents** <policer-family>—Protocol family of the policer.
 <policer-input>—Name of the input policer.
 <policer-output>—Name of the output policer.

<ppp-flags>

- Usage** <physical-interface | logical-interface>
<ppp-flags>
 <iff-ppp-flags-acfc/>
 <iff-ppp-flags-pfc/>
</ppp-flags>
 </physical-interface | logical-interface>
- Description** Additional flags applicable to PPP encapsulation.
- Contents** <iff-ppp-flags-acfc>—PPP Address/Control field compression is enabled.
 <iff-ppp-flags-pfc>—PPP Protocol field compression is enabled.

<ppp-parameters>

- Usage** <logical-interface>
<ppp-parameters>
 <lcp-restart-timer>*lcp-restart-timer*</lcp-restart-timer>
 <ncp-restart-timer>*ncp-restart-timer*</ncp-restart-timer>
 <termination-requests>*termination-requests*</termination-requests>
 <loopback-clear-timer>*loopback-clear-timer*</loopback-clear-timer>
</ppp-parameters>
 </logical-interface>
- Description** PPP parameters.
- Contents** <lcp-restart-timer>—LCP restart timer (milliseconds).
 <loopback-clear-timer>—PPP loopback clear timer (seconds).
 <ncp-restart-timer>—NCP restart timer (milliseconds).
 <termination-requests>—Whether PPP termination requests are sent.

<pppoe-information>

Usage	<logical-interface> <pppoe-information> <pppoe-interface>...</pppoe-interface> </pppoe-information> </logical-interface>
Description	PPPoE information.
Contents	<pppoe-interface>—No documentation is available yet.

<pppoe-interface>

Usage <pppoe-information>
 <pppoe-interface>
 <interface-name>*interface-name*</interface-name>
 <interface-index>*interface-index*</interface-index>
 <underlying-interface-name>*underlying-interface-name*
 </underlying-interface-name>
 <underlying-interface-index>*underlying-interface-index*
 </underlying-interface-index>
 <state>*state*</state>
 <session-id>*session-id*</session-id>
 <ac-name-config>*ac-name-config*</ac-name-config>
 <ac-name-session>*ac-name-session*</ac-name-session>
 <service-name>*service-name*</service-name>
 <ac-mac>*ac-mac*</ac-mac>
 <auto-reconnect>*auto-reconnect*</auto-reconnect>
 <idle-timeout>*idle-timeout*</idle-timeout>
 <session-uptime>*session-uptime*</session-uptime>
 </pppoe-interface>
 </pppoe-information>

Description No documentation is available yet.

Contents <ac-mac>—AC MAC address.

<ac-name-config>—Configured AC name.

<ac-name-session>—Session AC name.

<auto-reconnect>—Autoreconnect timeout.

<idle-timeout>—Idle timeout.

<interface-index>—Index.

<interface-name>—Interface name.

<service-name>—Service name.

<session-id>—Session ID.

<session-uptime>—Duration for which the session has been up.

<state>—State.

<underlying-interface-index>—Underlying interface index.

<underlying-interface-name>—Underlying interface name.

<preserve-interface-statistics>

Usage <physical-interface>
 <preserve-interface-statistics>
 <if-switchover-total>*if-switchover-total*</if-switchover-total>
 <if-switchover-last-attempt>*if-switchover-last-attempt*
 </if-switchover-last-attempt>
 <if-switchover-last-time>*if-switchover-last-time*</if-switchover-last-time>
 <if-switchover-min-max-avg-time>*if-switchover-min-max-avg-time*
 </if-switchover-min-max-avg-time>
 </preserve-interface-statistics>
 </physical-interface>

Description Interface switchover statistics.

Contents <if-switchover-last-attempt>—Interface on which the last switchover was attempted.

<if-switchover-last-time>—Time at which last interface switchover was attempted.

<if-switchover-min-max-avg-time>—Minimum, maximum and average interface switchover time.

<if-switchover-total>—Total number of interface switchovers.

<queue>**Usage** <queue-counters | ingress-queue-counters | chassis-queue-counters>**<queue>**

```

<queue-number>queue-number</queue-number>
<forwarding-class-name>forwarding-class-name</forwarding-class-name>
<queue-counters-queued-packets>queue-counters-queued-packets
  </queue-counters-queued-packets>
<queue-counters-queued-packets-na>queue-counters-queued-packets-na
  </queue-counters-queued-packets-na>
<queue-counters-queued-bytes-na>queue-counters-queued-bytes-na
  </queue-counters-queued-bytes-na>
<queue-counters-queued-bytes>queue-counters-queued-bytes
  </queue-counters-queued-bytes>
<queue-counters-queued-packets-rate>queue-counters-queued-packets-rate
  </queue-counters-queued-packets-rate>
<queue-counters-queued-bytes-rate>queue-counters-queued-bytes-rate
  </queue-counters-queued-bytes-rate>
<queue-counters-trans-packets>queue-counters-trans-packets
  </queue-counters-trans-packets>
<queue-counters-trans-bytes>queue-counters-trans-bytes
  </queue-counters-trans-bytes>
<queue-counters-trans-packets-rate>queue-counters-trans-packets-rate
  </queue-counters-trans-packets-rate>
<queue-counters-trans-bytes-rate>queue-counters-trans-bytes-rate
  </queue-counters-trans-bytes-rate>
<queue-counters-tail-drop-packets>queue-counters-tail-drop-packets
  </queue-counters-tail-drop-packets>
<queue-counters-tail-drop-packets-rate>queue-counters-tail-drop-packets-rate
  </queue-counters-tail-drop-packets-rate>
<queue-counters-tail-drop-packets-na>queue-counters-tail-drop-packets-na
  </queue-counters-tail-drop-packets-na>
<queue-counters-rate-limit-drop-packets>queue-counters-rate-limit-drop-packets
  </queue-counters-rate-limit-drop-packets>
<queue-counters-rate-limit-drop-packets-rate>queue-counters-rate-limit-drop-packets-rate
  </queue-counters-rate-limit-drop-packets-rate>
<queue-counters-rate-limit-drop-packets-na>queue-counters-rate-limit-drop-packets-na
  </queue-counters-rate-limit-drop-packets-na>
<queue-counters-rate-limit-drop-bytes>queue-counters-rate-limit-drop-bytes
  </queue-counters-rate-limit-drop-bytes>
<queue-counters-rate-limit-drop-bytes-rate>queue-counters-rate-limit-drop-bytes-rate
  </queue-counters-rate-limit-drop-bytes-rate>
<queue-counters-rate-limit-drop-bytes-na>queue-counters-rate-limit-drop-bytes-na
  </queue-counters-rate-limit-drop-bytes-na>
<queue-counters-red-packets-na>queue-counters-red-packets-na
  </queue-counters-red-packets-na>
<queue-counters-red-packets>queue-counters-red-packets
  </queue-counters-red-packets>
<queue-counters-red-bytes-na>queue-counters-red-bytes-na
  </queue-counters-red-bytes-na>
<queue-counters-red-bytes>queue-counters-red-bytes</queue-counters-red-bytes>
<queue-counters-red-packets-rate>queue-counters-red-packets-rate
  </queue-counters-red-packets-rate>
<queue-counters-red-bytes-rate>queue-counters-red-bytes-rate

```

```

        </queue-counters-red-bytes-rate>
    <queue-counters-red-packets-ln>queue-counters-red-packets-ln
        </queue-counters-red-packets-ln>
    <queue-counters-red-bytes-ln>queue-counters-red-bytes-ln
        </queue-counters-red-bytes-ln>
    <queue-counters-red-packets-rate-ln>queue-counters-red-packets-rate-ln
        </queue-counters-red-packets-rate-ln>
    <queue-counters-red-bytes-rate-ln>queue-counters-red-bytes-rate-ln
        </queue-counters-red-bytes-rate-ln>
    <queue-counters-red-packets-lt>queue-counters-red-packets-lt
        </queue-counters-red-packets-lt>
    <queue-counters-red-bytes-lt>queue-counters-red-bytes-lt
        </queue-counters-red-bytes-lt>
    <queue-counters-red-packets-rate-lt>queue-counters-red-packets-rate-lt
        </queue-counters-red-packets-rate-lt>
    <queue-counters-red-bytes-rate-lt>queue-counters-red-bytes-rate-lt
        </queue-counters-red-bytes-rate-lt>
    <queue-counters-red-packets-ht>queue-counters-red-packets-ht
        </queue-counters-red-packets-ht>
    <queue-counters-red-bytes-ht>queue-counters-red-bytes-ht
        </queue-counters-red-bytes-ht>
    <queue-counters-red-packets-rate-ht>queue-counters-red-packets-rate-ht
        </queue-counters-red-packets-rate-ht>
    <queue-counters-red-bytes-rate-ht>queue-counters-red-bytes-rate-ht
        </queue-counters-red-bytes-rate-ht>
    <queue-counters-red-packets-hn>queue-counters-red-packets-hn
        </queue-counters-red-packets-hn>
    <queue-counters-red-bytes-hn>queue-counters-red-bytes-hn
        </queue-counters-red-bytes-hn>
    <queue-counters-red-packets-rate-hn>queue-counters-red-packets-rate-hn
        </queue-counters-red-packets-rate-hn>
    <queue-counters-red-bytes-rate-hn>queue-counters-red-bytes-rate-hn
        </queue-counters-red-bytes-rate-hn>
    <queue-counters-red-packets-low>queue-counters-red-packets-low
        </queue-counters-red-packets-low>
    <queue-counters-red-bytes-low>queue-counters-red-bytes-low
        </queue-counters-red-bytes-low>
    <queue-counters-red-packets-rate-low>queue-counters-red-packets-rate-low
        </queue-counters-red-packets-rate-low>
    <queue-counters-red-bytes-rate-low>queue-counters-red-bytes-rate-low
        </queue-counters-red-bytes-rate-low>
    <queue-counters-red-packets-medium-low>queue-counters-red-packets-medium-low
        </queue-counters-red-packets-medium-low>
    <queue-counters-red-bytes-medium-low>queue-counters-red-bytes-medium-low
        </queue-counters-red-bytes-medium-low>
    <queue-counters-red-packets-rate-medium-low>qu-co-red-packets-rate-medium-low
        </queue-counters-red-packets-rate-medium-low>
    <queue-counters-red-bytes-rate-medium-low>qu-counters-red-bytes-rate-medium-low
        </queue-counters-red-bytes-rate-medium-low>
    <queue-counters-red-packets-medium-high>qu-counters-red-packets-medium-high
        </queue-counters-red-packets-medium-high>
    <queue-counters-red-bytes-medium-high>qu-co-red-bytes-medium-high
        </queue-counters-red-bytes-medium-high>
    <queue-counters-red-packets-rate-medium-high>que-co-red-pkts-rate-med-high

```

```

        </queue-counters-red-packets-rate-medium-high>
    <queue-counters-red-bytes-rate-medium-high>queue-co-red-bytes-rate-medium-high
        </queue-counters-red-bytes-rate-medium-high>
    <queue-counters-red-packets-medium>queue-counters-red-packets-medium
        </queue-counters-red-packets-medium>
    <queue-counters-red-bytes-medium>queue-counters-red-bytes-medium
        </queue-counters-red-bytes-medium>
    <queue-counters-red-packets-rate-medium>que-counters-red-packets-rate-medium
        </queue-counters-red-packets-rate-medium>
    <queue-counters-red-bytes-rate-medium>queue-counters-red-bytes-rate-medium
        </queue-counters-red-bytes-rate-medium>
    <queue-counters-red-packets-high>queue-counters-red-packets-high
        </queue-counters-red-packets-high>
    <queue-counters-red-bytes-high>queue-counters-red-bytes-high
        </queue-counters-red-bytes-high>
    <queue-counters-red-packets-rate-high>queue-counters-red-packets-rate-high
        </queue-counters-red-packets-rate-high>
    <queue-counters-red-bytes-rate-high>queue-counters-red-bytes-rate-high
        </queue-counters-red-bytes-rate-high>
    </queue>
</queue-counters | ingress-queue-counters | chassis-queue-counters>

```

Description Counters for a single queue.

Contents <forwarding-class-name>—Forwarding class name associated with queue.

<queue-counters-queued-bytes>—Queued bytes count.

<queue-counters-queued-bytes-na>—Queued bytes not available.

<queue-counters-queued-bytes-rate>—Rate at which bytes are queued.

<queue-counters-queued-packets>—Queued packet count.

<queue-counters-queued-packets-na>—Queued packets not available.

<queue-counters-queued-packets-rate>—Rate at which packets are queued.

<queue-counters-rate-limit-drop-bytes>—Number of bytes dropped at the tail of the queue.

<queue-counters-rate-limit-drop-bytes-na>—Number of bytes dropped due to tail drop not available.

<queue-counters-rate-limit-drop-bytes-rate>—Rate at which bytes are dropped at the tail of the queue.

<queue-counters-rate-limit-drop-packets>—Number of packets dropped by rate-limit for the queue.

<queue-counters-rate-limit-drop-packets-na>—Number of packets dropped due to rate-limit drop not available.

<queue-counters-rate-limit-drop-packets-rate>—Rate at which packets are dropped by rate-limit for the queue.

<queue-counters-red-bytes>—Number of bytes dropped due to RED.

<queue-counters-red-bytes-high>—Number of RED dropped high-loss bytes.

<queue-counters-red-bytes-hn>—Number of RED dropped high-loss, non-TCP bytes.

<queue-counters-red-bytes-ht>—Number of RED dropped high-loss, TCP bytes.

<queue-counters-red-bytes-ln>—Number of RED dropped low-loss, non-TCP bytes.

<queue-counters-red-bytes-low>—Number of RED dropped low-loss bytes.

<queue-counters-red-bytes-lt>—Number of RED dropped low-loss, TCP bytes.

<queue-counters-red-bytes-medium>—Number of RED dropped medium-loss bytes.

<queue-counters-red-bytes-medium-high>—Number of RED dropped medium-high-loss bytes.

<queue-counters-red-bytes-medium-low>—Number of RED dropped medium-low-loss bytes.

<queue-counters-red-bytes-na>—Number of bytes dropped due to RED not available.

<queue-counters-red-bytes-rate>—Rate at which bytes are dropped due to RED.

<queue-counters-red-bytes-rate-high>—RED drop rate for high-loss bytes.

<queue-counters-red-bytes-rate-hn>—RED drop rate for high-loss, non-TCP bytes.

<queue-counters-red-bytes-rate-ht>—RED drop rate for high-loss, TCP bytes.

<queue-counters-red-bytes-rate-ln>—RED drop rate for low-loss, non-TCP bytes.

<queue-counters-red-bytes-rate-low>—RED drop rate for low-loss bytes.

<queue-counters-red-bytes-rate-lt>—RED drop rate for low-loss, TCP bytes.

<queue-counters-red-bytes-rate-medium>—RED drop rate for medium-loss bytes.

<queue-counters-red-bytes-rate-medium-high>—RED drop rate for medium-high-loss bytes.

<queue-counters-red-bytes-rate-medium-low>—RED drop rate for medium-low-loss bytes.

<queue-counters-red-packets>—Number of packets dropped due to RED.

<queue-counters-red-packets-high>—Number of RED dropped high-loss packets.

<queue-counters-red-packets-hn>—Number of RED dropped high-loss, non-TCP packets.

<queue-counters-red-packets-ht>—Number of RED dropped high-loss, TCP packets.

<queue-counters-red-packets-ln>—Number of RED dropped low-loss, non-TCP packets.

<queue-counters-red-packets-low>—Number of RED dropped low-loss packets.

<queue-counters-red-packets-lt>—Number of RED dropped of low-loss, TCP packets.

<queue-counters-red-packets-medium>—Number of RED dropped medium-loss packets.

<queue-counters-red-packets-medium-high>—Number of RED dropped medium-high-loss packets.

<queue-counters-red-packets-medium-low>—Number of RED dropped medium-low-loss packets.

<queue-counters-red-packets-na>—Number of packets dropped due to RED not available.

<queue-counters-red-packets-rate>—Rate at which packets are dropped due to RED.

<queue-counters-red-packets-rate-high>—RED drop rate for high-loss packets.

<queue-counters-red-packets-rate-hn>—RED drop rate for high-loss, non-TCP packets.

<queue-counters-red-packets-rate-ht>—RED drop rate for high-loss, TCP packets.

<queue-counters-red-packets-rate-ln>—RED drop rate for low-loss, non-TCP packets.

<queue-counters-red-packets-rate-low>—RED drop rate for low-loss packets.

<queue-counters-red-packets-rate-lt>—RED drop rate for low-loss, TCP packets.

<queue-counters-red-packets-rate-medium>—RED drop rate for medium-loss packets.

<queue-counters-red-packets-rate-medium-high>—RED drop rate for medium-high-loss packets.

<queue-counters-red-packets-rate-medium-low>—RED drop rate for medium-low-loss packets.

<queue-counters-tail-drop-packets>—Number of packets dropped at the tail of the queue.

<queue-counters-tail-drop-packets-na>—Number of packets dropped due to tail drop not available.

<queue-counters-tail-drop-packets-rate>—Rate at which packets are dropped at tail of queue.

<queue-counters-trans-bytes>—Total number of transmitted bytes.

<queue-counters-trans-bytes-rate>—Rate at which bytes are transmitted.

`<queue-counters-trans-packets>`—Total number of transmitted packets.

`<queue-counters-trans-packets-rate>`—Rate at which packets are transmitted.

`<queue-number>`—Queue number.

`<queue-counters>`

Usage `<physical-interface | logical-interface | interface-set-queue-information>`
`<queue-counters>`
 `<queue-counters-error-message>`*queue-counters-error-message*
 `</queue-counters-error-message>`
 `<queue>`...`</queue>`
 `<interface-cos-short-summary>`...`</interface-cos-short-summary>`
 `<interface-cos-summary>`...`</interface-cos-summary>`
`</queue-counters>`
`</physical-interface | logical-interface | interface-set-queue-information>`

Description Queue counter statistics.

Contents `<interface-cos-short-summary>`—Summary of queue information on an interface.
`<interface-cos-summary>`—Summary of forwarding class and queue information on an interface.
`<queue>`—Counters for a single queue.
`<queue-counters-error-message>`—Queue statistics not available for this interface.

`<resync-history>`

Usage `<serial-information>`
`<resync-history>`
 `<resync-counter>`*resync-counter*`</resync-counter>`
 `<resync-timestamp>`*resync-timestamp*`</resync-timestamp>`
`</resync-history>`
`</serial-information>`

Description No documentation is available yet.

Contents `<resync-counter>`—No documentation is available yet.
`<resync-timestamp>`—No documentation is available yet.

<route-rpf-statistics>

Usage <address-family>
 <route-rpf-statistics>
 <route-rpf-packets>*route-rpf-packets*</route-rpf-packets>
 <route-rpf-bytes>*route-rpf-bytes*</route-rpf-bytes>
 </route-rpf-statistics>
 </address-family>

Description Unicast reverse-path forwarding (RPF) statistics.

Contents <route-rpf-bytes>—Number of bytes that have failed the RPF check.
 <route-rpf-packets>—Number of packets that have failed the RPF check.

<satop-information>

Usage <physical-interface>
 <satop-information>
 <ce-payload-size>*ce-payload-size*</ce-payload-size>
 <ce-idle-pattern>*ce-idle-pattern*</ce-idle-pattern>
 <ce-octet-aligned>*ce-octet-aligned*</ce-octet-aligned>
 <ce-jitter-buffer-packets>*ce-jitter-buffer-packets*</ce-jitter-buffer-packets>
 <ce-jitter-buffer-latency>*ce-jitter-buffer-latency*</ce-jitter-buffer-latency>
 <ce-jitter-buffer-auto-adjust>*ce-jitter-buffer-auto-adjust*
 </ce-jitter-buffer-auto-adjust>
 <ce-excessive-packet-loss-rate-sample-period>*ce-exc-packet-loss-rate-sample-period*
 </ce-excessive-packet-loss-rate-sample-period>
 <ce-excessive-packet-loss-rate-threshold>*ce-excessive-packet-loss-rate-threshold*
 </ce-excessive-packet-loss-rate-threshold>
 </satop-information>
 </physical-interface>

Description No documentation is available yet.

Contents <ce-excessive-packet-loss-rate-sample-period>—No documentation is available yet.
 <ce-excessive-packet-loss-rate-threshold>—No documentation is available yet.
 <ce-idle-pattern>—No documentation is available yet.
 <ce-jitter-buffer-auto-adjust>—No documentation is available yet.
 <ce-jitter-buffer-latency>—No documentation is available yet.
 <ce-jitter-buffer-packets>—No documentation is available yet.
 <ce-octet-aligned>—No documentation is available yet.
 <ce-payload-size>—No documentation is available yet.

<serial-encoding>

Usage <serial-information>
 <serial-encoding>
 <serial-encoding-conf>*serial-encoding-conf*</serial-encoding-conf>
 </serial-encoding>
 </serial-information>

Description No documentation is available yet.

Contents <serial-encoding-conf>—No documentation is available yet.

<serial-information>

Usage <physical-interface>
 <serial-information>
 <line-protocol>...</line-protocol>
 <resync-history>...</resync-history>
 <clocking-mode>...</clocking-mode>
 <clocking-rate>...</clocking-rate>
 <serial-encoding>...</serial-encoding>
 <dtr-circuit>...</dtr-circuit>
 <eia530-signal-polarity>...</eia530-signal-polarity>
 <x21-signal-polarity>...</x21-signal-polarity>
 <serial-loopback>...</serial-loopback>
 <tx-clock>...</tx-clock>
 <data-signal>...</data-signal>
 <eia530-control-signal>...</eia530-control-signal>
 <x21-control-signal>...</x21-control-signal>
 <dce-loopback-override>dce-loopback-override</dce-loopback-override>
 </serial-information>
 </physical-interface>

Description Serial interfaces information and statistics.

Contents <clocking-mode>—No documentation is available yet.
 <clocking-rate>—No documentation is available yet.
 <data-signal>—No documentation is available yet.
 <dce-loopback-override>—No documentation is available yet.
 <dtr-circuit>—No documentation is available yet.
 <eia530-control-signal>—No documentation is available yet.
 <eia530-signal-polarity>—No documentation is available yet.
 <line-protocol>—No documentation is available yet.
 <resync-history>—No documentation is available yet.
 <serial-encoding>—No documentation is available yet.
 <serial-loopback>—No documentation is available yet.
 <tx-clock>—No documentation is available yet.
 <x21-control-signal>—No documentation is available yet.
 <x21-signal-polarity>—No documentation is available yet.

<serial-loopback>

- Usage** <serial-information>
 <serial-loopback>
 <serial-loopback-mode>*serial-loopback-mode*</serial-loopback-mode>
 </serial-loopback>
 </serial-information>
- Description** No documentation is available yet.
- Contents** <serial-loopback-mode>—No documentation is available yet.

<shared-uplink-information>

- Usage** <logical-interface>
 <shared-uplink-information>
 <shared-uplink-logical-interface>...</shared-uplink-logical-interface>
 </shared-uplink-information>
 </logical-interface>
- Description** Shared uplink information.
- Contents** <shared-uplink-logical-interface>—Shared uplink logical interface.

<shared-uplink-logical-interface>

- Usage** <shared-uplink-information>
 <shared-uplink-logical-interface>
 <peer-interface-name>*peer-interface-name*</peer-interface-name>
 <uplink-shared-with>*uplink-shared-with*</uplink-shared-with>
 <rx-fe>*rx-fe*</rx-fe>
 <rx-nhid>*rx-nhid*</rx-nhid>
 <tx-fe>*tx-fe*</tx-fe>
 <tx-nhid>*tx-nhid*</tx-nhid>
 </shared-uplink-logical-interface>
 </shared-uplink-information>
- Description** Shared uplink logical interface.
- Contents** <peer-interface-name>—Peer interface name.
- <rx-fe>—Rx tunnel token forwarding element.
- <rx-nhid>—Rx tunnel token next hop index.
- <tx-fe>—Tx tunnel token forwarding element.
- <tx-nhid>—Tx tunnel token next hop index.
- <uplink-shared-with>—Logical interface owner.

<shared-uplink-physical-interface>

Usage <physical-interface>
 <shared-uplink-physical-interface>
 <ownership>ownership</ownership>
 </shared-uplink-physical-interface>
 </physical-interface>

Description Shared uplink physical interface.

Contents <ownership>—Shared uplink physical interface ownership.

<shdsl-information>

Usage <physical-interface>
<shdsl-information>
 <shdsl-line-termination>*shdsl-line-termination*</shdsl-line-termination>
 <shdsl-annex>*shdsl-annex*</shdsl-annex>
 <shdsl-line-mode>*shdsl-line-mode*</shdsl-line-mode>
 <shdsl-modem-status>*shdsl-modem-status*</shdsl-modem-status>
 <shdsl-bit-rate>*shdsl-bit-rate*</shdsl-bit-rate>
 <shdsl-last-fail-reason>*shdsl-last-fail-reason*</shdsl-last-fail-reason>
 <shdsl-last-fail-code>*shdsl-last-fail-code*</shdsl-last-fail-code>
 <shdsl-framer-mode>*shdsl-framer-mode*</shdsl-framer-mode>
 <shdsl-dying-gasp>*shdsl-dying-gasp*</shdsl-dying-gasp>
 <shdsl-framer-sync-status>*shdsl-framer-sync-status*</shdsl-framer-sync-status>
 <shdsl-chipset-version>*shdsl-chipset-version*</shdsl-chipset-version>
 <shdsl-firmware-version>*shdsl-firmware-version*</shdsl-firmware-version>
 <shdsl-statistics>...</shdsl-statistics>
</shdsl-information>
 </physical-interface>

Description Operational information and statistics for SHDSL interfaces.

Contents <shdsl-annex>—Type of SHDSL annex.

<shdsl-bit-rate>—Actual line rate.

<shdsl-chipset-version>—Version number for the DSP/framer chip.

<shdsl-dying-gasp>—Dying gasp is enabled or disabled.

<shdsl-firmware-version>—Transceiver firmware release number.

<shdsl-framer-mode>—Framer mode used.

<shdsl-framer-sync-status>—Framer synchronization status.

<shdsl-last-fail-code>—Last line-open failure code.

<shdsl-last-fail-reason>—Reason for last line-open failure.

<shdsl-line-mode>—Two or four wire mode.

<shdsl-line-termination>—Line termination remote or central.

<shdsl-modem-status>—Status of the SHDSL modem.

<shdsl-statistics>—No documentation is available yet.

<shdsl-statistics>

Usage	<pre> <shdsl-information> <shdsl-statistics> <shdsl-loop-attenuation>shdsl-loop-attenuation</shdsl-loop-attenuation> <shdsl-transmit-power>shdsl-transmit-power</shdsl-transmit-power> <shdsl-receiver-gain>shdsl-receiver-gain</shdsl-receiver-gain> <shdsl-snr-sampling>shdsl-snr-sampling</shdsl-snr-sampling> <shdsl-rx-cells>shdsl-rx-cells</shdsl-rx-cells> <shdsl-tx-cells>shdsl-tx-cells</shdsl-tx-cells> <shdsl-crc>shdsl-crc</shdsl-crc> <shdsl-sega>shdsl-sega</shdsl-sega> <shdsl-losw>shdsl-losw</shdsl-losw> <shdsl-hec>shdsl-hec</shdsl-hec> <shdsl-cell-drop>shdsl-cell-drop</shdsl-cell-drop> </shdsl-statistics> </shdsl-information> </pre>
Description	No documentation is available yet.
Contents	<p><shdsl-cell-drop>—Cells dropped because of errors.</p> <p><shdsl-crc>—Number of CRC errors.</p> <p><shdsl-hec>—Header error check errors.</p> <p><shdsl-loop-attenuation>—An estimate of the loop attenuation.</p> <p><shdsl-losw>—Number of LOSW errors.</p> <p><shdsl-receiver-gain>—Total receiver gain.</p> <p><shdsl-rx-cells>—Total ATM cells received.</p> <p><shdsl-sega>—Number of SEGA errors.</p> <p><shdsl-snr-sampling>—Received signal to noise ratio.</p> <p><shdsl-transmit-power>—Nominal transmit power.</p> <p><shdsl-tx-cells>—Total ATM cells transmitted.</p>

<sonet-errors>

Usage	<pre> <physical-interface link-entry> <sonet-errors> <media-alarm>...</media-alarm> </sonet-errors> </physical-interface link-entry> </pre>
Description	No documentation is available yet.
Contents	<media-alarm>—No documentation is available yet.

<sonet-line-information>

- Usage** <physical-interface | link-entry>
 <sonet-line-information>
 <media-alarm>...</media-alarm>
 </sonet-line-information>
 </physical-interface | link-entry>
- Description** No documentation is available yet.
- Contents** <media-alarm>—No documentation is available yet.

<sonet-path-information>

- Usage** <physical-interface | link-entry>
 <sonet-path-information>
 <media-alarm>...</media-alarm>
 </sonet-path-information>
 </physical-interface | link-entry>
- Description** No documentation is available yet.
- Contents** <media-alarm>—No documentation is available yet.

<sonet-payload-pointer-information>

- Usage** <physical-interface | link-entry>
 <sonet-payload-pointer-information>
 <sonet-payload-pointer-curptr>*sonet-payload-pointer-curptr*
 </sonet-payload-pointer-curptr>
 <sonet-payload-pointer-ptrinc-count>*sonet-payload-pointer-ptrinc-count*
 </sonet-payload-pointer-ptrinc-count>
 <sonet-payload-pointer-ptrdec-count>*sonet-payload-pointer-ptrdec-count*
 </sonet-payload-pointer-ptrdec-count>
 <sonet-payload-pointer-newptr-ndf-count>*sonet-payload-pointer-newptr-ndf-count*
 </sonet-payload-pointer-newptr-ndf-count>
 </sonet-payload-pointer-information>
 </physical-interface | link-entry>
- Description** No documentation is available yet.
- Contents** <sonet-payload-pointer-curptr>—Value of the SONET/SDH payload pointer, derived from the H1 and H2 overhead bytes.
- <sonet-payload-pointer-newptr-ndf-count>—Number of times a new payload pointer was created with the New Data Found flag set.
- <sonet-payload-pointer-ptrdec-count>—Number of times the value of the SONET/SDH payload pointer had negative justification.
- <sonet-payload-pointer-ptrinc-count>—Number of times the value of the SONET/SDH payload pointer had positive justification.

<sonet-physical-information>

- Usage** <physical-interface | link-entry>
 <sonet-physical-information>
 <media-alarm>...</media-alarm>
 </sonet-physical-information>
 </physical-interface | link-entry>
- Description** No documentation is available yet.
- Contents** <media-alarm>—No documentation is available yet.

<sonet-section-information>

- Usage** <physical-interface | link-entry>
 <sonet-section-information>
 <media-alarm>...</media-alarm>
 </sonet-section-information>
 </physical-interface | link-entry>
- Description** No documentation is available yet.
- Contents** <media-alarm>—No documentation is available yet.

<sonet-vt-information>

- Usage** <physical-interface | link-entry>
 <sonet-vt-information>
 <media-alarm>...</media-alarm>
 </sonet-vt-information>
 </physical-interface | link-entry>
- Description** No documentation is available yet.
- Contents** <media-alarm>—No documentation is available yet.

<source-class>

Usage <source-class-statistics>
 <source-class>
 <scu-class-name>*scu-class-name*</scu-class-name>
 <scu-class-packets>*scu-class-packets*</scu-class-packets>
 <scu-class-bytes>*scu-class-bytes*</scu-class-bytes>
 <scu-class-pps>*scu-class-pps*</scu-class-pps>
 <scu-class-bps>*scu-class-bps*</scu-class-bps>
 </source-class>
 </source-class-statistics>

Description SCU statistics for a single class.

Contents <scu-class-bps>—Bit-per-seconds counted by SCU for this class.
 <scu-class-bytes>—Number of bytes counted by SCU for this class.
 <scu-class-name>—Name of SCU class.
 <scu-class-packets>—Number of packets counted by SCU for this class.
 <scu-class-pps>—Packet-per-seconds counted by SCU for this class.

<source-class-statistics>

Usage <address-family>
 <source-class-statistics>
 <source-class>...</source-class>
 </source-class-statistics>
 </address-family>

Description Source class usage (SCU) statistics.

Contents <source-class>—SCU statistics for a single class.

<stp-traffic-statistics>

Usage <physical-interface>
 <stp-traffic-statistics>
 <stp-input-bytes-dropped>*stp-input-bytes-dropped*</stp-input-bytes-dropped>
 <stp-output-bytes-dropped>*stp-output-bytes-dropped*</stp-output-bytes-dropped>
 <stp-input-packets-dropped>*stp-input-packets-dropped*
 </stp-input-packets-dropped>
 <stp-output-packets-dropped>*stp-output-packets-dropped*
 </stp-output-packets-dropped>
 </stp-traffic-statistics>
 </physical-interface>

Description Information about dropped bytes and packets due to STP state.

Contents <stp-input-bytes-dropped>—Drop statistics due to stp state at ingress in bytes.
 <stp-input-packets-dropped>—Drop statistics due to stp state at ingress in packets.
 <stp-output-bytes-dropped>—Drop statistics due to stp state at egress in bytes.
 <stp-output-packets-dropped>—Drop statistics due to stp state at egress in packets.

<sub-interface-list>

Usage <dialer-interface>
 <sub-interface-list>
 <sub-interface-name>*sub-interface-name*</sub-interface-name>
 </sub-interface-list>
 </dialer-interface>

Description No documentation is available yet.

Contents <sub-interface-name>—Subordinate interface name.

<to-dce>

Usage <eia530-control-signal>
 <to-dce>
 <dtr>dtr</dtr>
 <rts>rts</rts>
 <cts>cts</cts>
 <dcd>dcd</dcd>
 <dsr>dsr</dsr>
 </to-dce>
 </eia530-control-signal>

Description No documentation is available yet.

Contents <cts>—No documentation is available yet.
 <dcd>—No documentation is available yet.
 <dsr>—No documentation is available yet.
 <dtr>—No documentation is available yet.
 <rts>—No documentation is available yet.

<to-dte>

Usage <eia530-control-signal>
 <to-dte>
 <dtr>dtr</dtr>
 <rts>rts</rts>
 <cts>cts</cts>
 <dcd>dcd</dcd>
 <dsr>dsr</dsr>
 </to-dte>
 </eia530-control-signal>

Description No documentation is available yet.

Contents <cts>—No documentation is available yet.
 <dcd>—No documentation is available yet.
 <dsr>—No documentation is available yet.
 <dtr>—No documentation is available yet.
 <rts>—No documentation is available yet.

<traffic-statistics>

Usage	<p><physical-interface virtual-path-information logical-interface virtual-circuit-information interface-set></p> <p><traffic-statistics></p> <p><input-bytes><i>input-bytes</i></input-bytes></p> <p><output-bytes><i>output-bytes</i></output-bytes></p> <p><input-bps><i>input-bps</i></input-bps></p> <p><output-bps><i>output-bps</i></output-bps></p> <p><input-packets><i>input-packets</i></input-packets></p> <p><output-packets><i>output-packets</i></output-packets></p> <p><input-pps><i>input-pps</i></input-pps></p> <p><output-pps><i>output-pps</i></output-pps></p> <p><ipv6-transit-statistics>...</ipv6-transit-statistics></p> <p></traffic-statistics></p> <p></physical-interface virtual-path-information logical-interface virtual-circuit-information interface-set></p>
Description	Number and rate of bytes and packets received and transmitted on the physical interface.
Contents	<p><input-bps>—No documentation is available yet.</p> <p><input-bytes>—No documentation is available yet.</p> <p><input-packets>—No documentation is available yet.</p> <p><input-pps>—No documentation is available yet.</p> <p><ipv6-transit-statistics>—No documentation is available yet.</p> <p><output-bps>—No documentation is available yet.</p> <p><output-bytes>—No documentation is available yet.</p> <p><output-packets>—No documentation is available yet.</p> <p><output-pps>—No documentation is available yet.</p>

<transit-traffic-statistics>

Usage	<pre> <logical-interface> <transit-traffic-statistics> <input-bytes>input-bytes</input-bytes> <output-bytes>output-bytes</output-bytes> <input-bps>input-bps</input-bps> <output-bps>output-bps</output-bps> <input-packets>input-packets</input-packets> <output-packets>output-packets</output-packets> <input-pps>input-pps</input-pps> <output-pps>output-pps</output-pps> <ipv6-transit-statistics>...</ipv6-transit-statistics> </transit-traffic-statistics> </logical-interface> </pre>
Description	Statistics for traffic passing through the router. When a burst of traffic is received, the value in the output packet rate field might briefly exceed the peak cell rate. The counter usually stabilizes in 1 second or less.
Contents	<p><input-bps>—No documentation is available yet.</p> <p><input-bytes>—No documentation is available yet.</p> <p><input-packets>—No documentation is available yet.</p> <p><input-pps>—No documentation is available yet.</p> <p><ipv6-transit-statistics>—No documentation is available yet.</p> <p><output-bps>—No documentation is available yet.</p> <p><output-bytes>—No documentation is available yet.</p> <p><output-packets>—No documentation is available yet.</p> <p><output-pps>—No documentation is available yet.</p>

<tx-clock>

Usage	<pre> <serial-information> <tx-clock> <tx-clock-mode>tx-clock-mode</tx-clock-mode> </tx-clock> </serial-information> </pre>
Description	No documentation is available yet.
Contents	<tx-clock-mode>—No documentation is available yet.

<vci-range>

Usage	<pre> <virtual-circuit-information> vci-range <vpi>vpi</vpi> <start-vci>start-vci</start-vci> <end-vci>end-vci</end-vci> </virtual-circuit-information> </pre>
Description	ATM VCI range.
Contents	<p><end-vci>—ATM VCI range's end value.</p> <p><start-vci>—ATM VCI range's start value.</p> <p><vpi>—Virtual path identifier.</p>

<virtual-circuit-information>

Usage <logical-interface>
<virtual-circuit-information>
 <dlci-statistics>...</dlci-statistics>
 <vpi>*vpi*</vpi>
 <vci>*vci*</vci>
 <vci-range>...</vci-range>
 <trunk>*trunk*</trunk>
 <trunk-bandwidth>*trunk-bandwidth*</trunk-bandwidth>
 <dlci>*dlci*</dlci>
 <ifvc-flags>...</ifvc-flags>
 <ifvc-multipoint-destination>...</ifvc-multipoint-destination>
 <atm-tm-cbr/>
 <atm-tm-vbr/>
 <atm-tm-rtvbr/>
 <peak>*peak*</peak>
 <sustained>*sustained*</sustained>
 <burst>*burst*</burst>
 <queue-limit>*queue-limit*</queue-limit>
 <down-time>*down-time*</down-time>
 <last-down-time>*last-down-time*</last-down-time>
 <ifvc-epd>*ifvc-epd*</ifvc-epd>
 <ifvc-epd-plp0>*ifvc-epd-plp0*</ifvc-epd-plp0>
 <ifvc-epd-plp1>*ifvc-epd-plp1*</ifvc-epd-plp1>
 <ifvc-weight>*ifvc-weight*</ifvc-weight>
 <oam-parameters>...</oam-parameters>
 <oam-statistics>...</oam-statistics>
 <traffic-statistics>...</traffic-statistics>
 <atm-statistics>...</atm-statistics>
 <atm-cos-information>...</atm-cos-information>
 <in-arp-statistics>...</in-arp-statistics>
</virtual-circuit-information>
 </logical-interface>

Description Operational information and statistics for a virtual circuit.

Contents <atm-cos-information>—No documentation is available yet.

<atm-statistics>—No documentation is available yet.

<atm-tm-cbr>—Constant bit rate.

<atm-tm-rtvbr>—Real-time variable bit rate.

<atm-tm-vbr>—Variable bit rate.

<burst>—No documentation is available yet.

<dlci>—No documentation is available yet.

<dlci-statistics>—DLCI statistics for an interface.

<down-time>—Total down time for this circuit.

<ifvc-epd>—Early packet discard threshold.

<ifvc-epd-plp0>—Early packet discard threshold for PLP 0.

<ifvc-epd-plp1>—Early packet discard threshold for PLP 1.

<ifvc-flags>—No documentation is available yet.

<ifvc-multipoint-destination>—No documentation is available yet.

<ifvc-weight>—Transmit weight.

<in-arp-statistics>—Container tag for ARP statistics.

<last-down-time>—Time elapsed since circuit last went down.

<oam-parameters>—No documentation is available yet.

<oam-statistics>—Container tag for OAM statistics.

<peak>—No documentation is available yet.

<queue-limit>—No documentation is available yet.

<sustained>—No documentation is available yet.

<traffic-statistics>—Number and rate of bytes and packets received and transmitted on the physical interface.

<trunk>—ATM trunk identifier.

<trunk-bandwidth>—ATM trunk bandwidth.

<vci>—Virtual circuit identifier.

<vci-range>—ATM VCI range.

<vpi>—Virtual path identifier.

<virtual-path-information>

Usage <physical-interface>
 <virtual-path-information>
 <vpi>*vpi*</vpi>
 <ifvp-flags>...</ifvp-flags>
 <atm-tm-cbr/>
 <atm-tm-vbr/>
 <atm-tm-rtvbr/>
 <peak>*peak*</peak>
 <sustained>*sustained*</sustained>
 <burst>*burst*</burst>
 <queue-limit>*queue-limit*</queue-limit>
 <down-time>*down-time*</down-time>
 <last-down-time>*last-down-time*</last-down-time>
 <oam-parameters>...</oam-parameters>
 <oam-statistics>...</oam-statistics>
 <traffic-statistics>...</traffic-statistics>
 </virtual-path-information>
 </physical-interface>

Description Operational information and statistics for a virtual path.

Contents <atm-tm-cbr>—Constant bit rate.

<atm-tm-rtvbr>—Real-time variable bit rate.

<atm-tm-vbr>—Variable bit rate.

<burst>—No documentation is available yet.

<down-time>—Total down time for this circuit.

<ifvp-flags>—No documentation is available yet.

<last-down-time>—Time elapsed since circuit last went down.

<oam-parameters>—No documentation is available yet.

<oam-statistics>—Container tag for OAM statistics.

<peak>—No documentation is available yet.

<queue-limit>—No documentation is available yet.

<sustained>—No documentation is available yet.

<traffic-statistics>—Number and rate of bytes and packets received and transmitted on the physical interface.

<vpi>—Virtual path identifier.

<watch-list>

- Usage** <dialer-interface>
 <watch-list>
 <watch-route>*watch-route*</watch-route>
 </watch-list>
 </dialer-interface>
- Description** No documentation is available yet.
- Contents** <watch-route>—Watch route.

<x21-control-signal>

- Usage** <serial-information>
 <x21-control-signal>
 <rts>*rts*</rts>
 <cts>*cts*</cts>
 </x21-control-signal>
 </serial-information>
- Description** No documentation is available yet.
- Contents** <cts>—No documentation is available yet.
 <rts>—No documentation is available yet.

<x21-signal-polarity>

- Usage** <serial-information>
 <x21-signal-polarity>
 <rts-polarity>*rts-polarity*</rts-polarity>
 <cts-polarity>*cts-polarity*</cts-polarity>
 </x21-signal-polarity>
 </serial-information>
- Description** No documentation is available yet.
- Contents** <cts-polarity>—No documentation is available yet.
 <rts-polarity>—No documentation is available yet.

Summary of IPSec Response Tags

This section lists JUNOS XML tags that contain operational information about IP Security (IPSec). The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-ipsec>. To review the DTD for the tags, see “DTD for IPSec Response Tags” on page 1803.

<ah-statistics>

Usage <ipsec-statistics>
 <ah-statistics>
 <ah-input-bytes>*ah-input-bytes*</ah-input-bytes>
 <ah-output-bytes>*ah-output-bytes*</ah-output-bytes>
 <ah-input-packets>*ah-input-packets*</ah-input-packets>
 <ah-output-packets>*ah-output-packets*</ah-output-packets>
 </ah-statistics>
 </ipsec-statistics>

Description No documentation is available yet.

Contents <ah-input-bytes>—AH input bytes information.
 <ah-input-packets>—AH input packets information.
 <ah-output-bytes>—AH output bytes information.
 <ah-output-packets>—AH output packets information.

<alternate-subject-list>

Usage <x509-certificate-info | x509-certificate-cache-info>
 <alternate-subject-list>
 <alternate-subject>*alternate-subject*</alternate-subject>
 </alternate-subject-list>
 </x509-certificate-info | x509-certificate-cache-info>

Description No documentation is available yet.

Contents <alternate-subject>—Series of alternate subject in X.509 certificate.

<auto-re-enrollment>

- Usage** <x509-certificate-info>
 <auto-re-enrollment>
 <auto-re-enrollment-status>*auto-re-enrollment-status*
 </auto-re-enrollment-status>
 <auto-re-enrollment-next-trigger-time>*auto-re-enrollment-next-trigger-time*
 </auto-re-enrollment-next-trigger-time>
 </auto-re-enrollment>
 </x509-certificate-info>
- Description** No documentation is available yet.
- Contents** <auto-re-enrollment-next-trigger-time>—Auto-re-enrollment next trigger time.
 <auto-re-enrollment-status>—Auto-re-enrollment information.

<ca-certificate-enroll>

- Usage** <ca-certificate-enroll-list>
 <ca-certificate-enroll>
 <ca-subject>*ca-subject*</ca-subject>
 <fingerprint>...</fingerprint>
 </ca-certificate-enroll>
 </ca-certificate-enroll-list>
- Description** Dump the subject and fingerprint of received CA certificate.
- Contents** <ca-subject>—Certificate authority subject.
 <fingerprint>—Fingerprint.

<ca-certificate-enroll-list>

- Usage** <rpc-reply>
 <ca-certificate-enroll-list>
 <ca-certificate-enroll-msg>*ca-certificate-enroll-msg*
 </ca-certificate-enroll-msg>
 <ca-certificate-enroll>...</ca-certificate-enroll>
 </ca-certificate-enroll-list>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <ca-certificate-enroll>—Dump the subject and fingerprint of received CA certificate.
 <ca-certificate-enroll-msg>—Certificate authority enrollment message.

<cert-ca-load-status>

- Usage** <rpc-reply>
 <cert-ca-load-status>
 <cert-ca-profile>cert-ca-profile</cert-ca-profile>
 </cert-ca-load-status>
 </rpc-reply>
- Description** Certificate Authority certificate load status.
- Contents** <cert-ca-profile>—Certificate Authority profile.

<cert-ca-manual-load>

- Usage** <rpc-reply>
 <cert-ca-manual-load>
 <fingerprint>...</fingerprint>
 </cert-ca-manual-load>
 </rpc-reply>
- Description** CA certificate manual-load prompt.
- Contents** <fingerprint>—Fingerprint.

<cert-flag-info>

- Usage** <x509-certificate-cache-info>
 <cert-flag-info>
 <cert-flag-trust>cert-flag-trust</cert-flag-trust>
 <cert-flag-root>cert-flag-root</cert-flag-root>
 </cert-flag-info>
 </x509-certificate-cache-info>
- Description** Information about state of certificates present in the cache.
- Contents** <cert-flag-root>—Information to indicate whether it is a root certificate or not.
 <cert-flag-trust>—Information to indicate whether the certificate is trusted or not.

<cert-key-pair>

- Usage** <rpc-reply>
 <cert-key-pair>
 <cert-key-pair-name>cert-key-pair-name</cert-key-pair-name>
 <cert-key-pair-size>cert-key-pair-size</cert-key-pair-size>
 </cert-key-pair>
 </rpc-reply>
- Description** Generate key pair status.
- Contents** <cert-key-pair-name>—Key pair name.
 <cert-key-pair-size>—Key pair size.

<cert-load-status>

Usage	<pre> <rpc-reply> <cert-load-status> <cert-certificate-id>cert-certificate-id</cert-certificate-id> </cert-load-status> </rpc-reply> </pre>
Description	Local certificate load status.
Contents	<cert-certificate-id>—Certificate identifier.

<cert-request-dump>

Usage	<pre> <rpc-reply> <cert-request-dump> <cert-request-dump-msg>cert-request-dump-msg</cert-request-dump-msg> <cert-request-dump-file>...</cert-request-dump-file> <fingerprint>...</fingerprint> </cert-request-dump> </rpc-reply> </pre>
Description	Dump the generated certificate request.
Contents	<p><cert-request-dump-file>—File contents.</p> <p><cert-request-dump-msg>—Certificate request generated message.</p> <p><fingerprint>—Fingerprint.</p>

<cert-request-dump-file>

Usage	<pre> <cert-request-dump> <cert-request-dump-file> <cert-request-dump-file-content>cert-request-dump-file-content </cert-request-dump-file> </cert-request-dump> </pre>
Description	File contents.
Contents	<cert-request-dump-file-content>—File contents.

<certificate-information>

Usage <rpc-reply>
 <certificate-information>
 <certificates>...</certificates>
 <total-entries>*total-entries*</total-entries>
 <active-entries>*active-entries*</active-entries>
 <locked-entries>*locked-entries*</locked-entries>
 <db-stats>*db-stats*</db-stats>
 </certificate-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <active-entries>—Number of active entries in database.
 <certificates>—Information about a single certificate.
 <db-stats>—No documentation is available yet.
 <locked-entries>—Number of locked entries in database.
 <total-entries>—Number of entries in database.

<certificates>

Usage <certificate-information>
 <certificates>
 <cert-subject>*cert-subject*</cert-subject>
 <cert-serial>*cert-serial*</cert-serial>
 <cert-id>*cert-id*</cert-id>
 <cert-references>*cert-references*</cert-references>
 <cert-issuer>*cert-issuer*</cert-issuer>
 <cert-trust>*cert-trust*</cert-trust>
 <cert-root>*cert-root*</cert-root>
 <cert-crl>*cert-crl*</cert-crl>
 <cert-before>*cert-before*</cert-before>
 <cert-after>*cert-after*</cert-after>
 <x509>...</x509>
 </certificates>
 </certificate-information>

Description Information about a single certificate.

Contents <cert-after>—No documentation is available yet.
 <cert-before>—No documentation is available yet.
 <cert-crl>—No documentation is available yet.
 <cert-id>—No documentation is available yet.
 <cert-issuer>—No documentation is available yet.
 <cert-references>—No documentation is available yet.
 <cert-root>—No documentation is available yet.
 <cert-serial>—No documentation is available yet.
 <cert-subject>—No documentation is available yet.
 <cert-trust>—No documentation is available yet.
 <x509>—Information about a single x509 record.

<crl>

Usage	<pre> <crl-information> <crl> <cert-issuer>cert-issuer</cert-issuer> <cert-id>cert-id</cert-id> <cert-references>cert-references</cert-references> <crl-list>...</crl-list> </crl> </crl-information> </pre>
Description	No documentation is available yet.
Contents	<p><cert-id>—No documentation is available yet.</p> <p><cert-issuer>—No documentation is available yet.</p> <p><cert-references>—No documentation is available yet.</p> <p><crl-list>—Information about a single CRL entry.</p>

<crl-information>

Usage	<pre> <rpc-reply> <crl-information> <crl>...</crl> </crl-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<crl>—No documentation is available yet.

<crl-issuer-alternate-subject-list>

Usage	<pre> <x509-crl-information> <crl-issuer-alternate-subject-list> <crl-issuer-alternate-subject>crl-issuer-alternate-subject </crl-issuer-alternate-subject> </crl-issuer-alternate-subject-list> </x509-crl-information> </pre>
Description	No documentation is available yet.
Contents	<crl-issuer-alternate-subject>—One or more alternate subject names for CRL issuer.

<crl-issuer-detail>

- Usage** <x509-crl-information>
 <crl-issuer-detail>
 <distinguished-name>...</distinguished-name>
 </crl-issuer-detail>
 </x509-crl-information>
- Description** Distinguished name of CRL issuer.
- Contents** <distinguished-name>—No documentation is available yet.

<crl-list>

- Usage** <crl>
 <crl-list>
 <serial>*serial*</serial>
 <revocation-date>*revocation-date*</revocation-date>
 </crl-list>
 </crl>
- Description** Information about a single CRL entry.
- Contents** <revocation-date>—No documentation is available yet.
 <serial>—No documentation is available yet.

<crl-load-status>

- Usage** <rpc-reply>
 <crl-load-status>
 <ca-profile-name>*ca-profile-name*</ca-profile-name>
 </crl-load-status>
 </rpc-reply>
- Description** Status of manual load of certificate revocation list.
- Contents** <ca-profile-name>—Certificate authority profile name.

<crl-revocation-list>

- Usage** <x509-crl-information>
 <crl-revocation-list>
 <revoked-cert-serial-number>*revoked-cert-serial-number*
 </revoked-cert-serial-number>
 <crl-revocation-date>*crl-revocation-date*</crl-revocation-date>
 </crl-revocation-list>
 </x509-crl-information>
- Description** No documentation is available yet.
- Contents** <crl-revocation-date>—Revocation date.
 <revoked-cert-serial-number>—Serial number of revoked certificate.

<crl-validity>

Usage	<pre> <x509-crl-information> <crl-validity> <effective-date>effective-date</effective-date> <next-update>next-update</next-update> </crl-validity> </x509-crl-information> </pre>
Description	Information about validity period for X.509 certificate revocation list.
Contents	<p><effective-date>—Effective date of CRL.</p> <p><next-update>—Next update of CRL.</p>

<distinguished-name>

Usage	<pre> <issuer subject crl-issuer-detail> <distinguished-name> <organization-name>organization-name</organization-name> <organizational-unit-name>organizational-unit-name</organizational-unit-name> <country-name>country-name</country-name> <state-or-province-name>state-or-province-name</state-or-province-name> <locality-name>locality-name</locality-name> <common-name>common-name</common-name> <email-address>email-address</email-address> <domain-component>domain-component</domain-component> </distinguished-name> </issuer subject crl-issuer-detail> </pre>
Description	No documentation is available yet.
Contents	<p><common-name>—Common name.</p> <p><country-name>—Country name.</p> <p><domain-component>—Domain component.</p> <p><email-address>—E-mail address.</p> <p><locality-name>—Locality.</p> <p><organization-name>—Organization.</p> <p><organizational-unit-name>—Organization unit.</p> <p><state-or-province-name>—State.</p>

<distribution-crl-list>

- Usage** <x509-certificate-info | x509-certificate-cache-info>
<distribution-crl-list>
 <distribution-crl>*distribution-crl*</distribution-crl>
</distribution-crl-list>
 </x509-certificate-info | x509-certificate-cache-info>
- Description** Information about one or more distribution certificate revocation lists.
- Contents** <distribution-crl>—Information about a distribution CRL.

<error-statistics>

- Usage** <ipsec-statistics>
<error-statistics>
 <ah-authentication-failures>*ah-authentication-failures*
 </ah-authentication-failures>
 <replay-errors>*replay-errors*</replay-errors>
 <esp-authentication-failures>*esp-authentication-failures*
 </esp-authentication-failures>
 <esp-decryption-failures>*esp-decryption-failures*</esp-decryption-failures>
 <bad-headers>*bad-headers*</bad-headers>
 <bad-trailers>*bad-trailers*</bad-trailers>
</error-statistics>
 </ipsec-statistics>
- Description** No documentation is available yet.
- Contents** <ah-authentication-failures>—AH authentication failures information.
- <bad-headers>—Bad header information.
- <bad-trailers>—Bad trailer information.
- <esp-authentication-failures>—ESP authentication failures information.
- <esp-decryption-failures>—ESP decryption failures information.
- <replay-errors>—Replay error information.

<esp-statistics>

Usage	<pre> <ipsec-statistics> <esp-statistics> <esp-encrypted-bytes>esp-encrypted-bytes</esp-encrypted-bytes> <esp-decrypted-bytes>esp-decrypted-bytes</esp-decrypted-bytes> <esp-encrypted-packets>esp-encrypted-packets</esp-encrypted-packets> <esp-decrypted-packets>esp-decrypted-packets</esp-decrypted-packets> </esp-statistics> </ipsec-statistics> </pre>
Description	No documentation is available yet.
Contents	<p><esp-decrypted-bytes>—ESP decrypted bytes information.</p> <p><esp-decrypted-packets>—ESP decrypted packets information.</p> <p><esp-encrypted-bytes>—ESP encrypted bytes information.</p> <p><esp-encrypted-packets>—ESP encrypted packets information.</p>

<fingerprint>

Usage	<pre> <x509-certificate-info cert-ca-manual-load cert-request-dump ca-certificate-enroll x509-certificate-cache-info> <fingerprint> <fingerprint-hash-algorithm>fingerprint-hash-algorithm </fingerprint-hash-algorithm> <fingerprint-content>fingerprint-content</fingerprint-content> </fingerprint> </x509-certificate-info cert-ca-manual-load cert-request-dump ca-certificate-enroll x509-certificate-cache-info> </pre>
Description	Fingerprint.
Contents	<p><fingerprint-content>—No documentation is available yet.</p> <p><fingerprint-hash-algorithm>—No documentation is available yet.</p>

<fips-pic-status>

Usage	<pre> <fips-pic-status-information> fips-pic-status <fpc-slot>fpc-slot</fpc-slot> <pic-slot>pic-slot</pic-slot> <serial-number>serial-number</serial-number> <authorization-status>authorization-status</authorization-status> </fips-pic-status> </fips-pic-status-information> </pre>
Description	No documentation is available yet.
Contents	<p><authorization-status>—PIC authorization status.</p> <p><fpc-slot>—FPC slot.</p> <p><pic-slot>—PIC slot.</p> <p><serial-number>—PIC serial number.</p>

<fips-pic-status-information>

Usage	<pre> <rpc-reply> fips-pic-status-information <fips-pic-status>...</fips-pic-status> </fips-pic-status-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<fips-pic-status>—No documentation is available yet.

<ike-sa-algorithms>

Usage	<pre> <ike-security-associations> ike-sa-algorithms <ike-sa-authentication-algorithm>ike-sa-authentication-algorithm </ike-sa-authentication-algorithm> <ike-sa-encryption-algorithm>ike-sa-encryption-algorithm </ike-sa-encryption-algorithm> <ike-sa-prf-algorithm>ike-sa-prf-algorithm</ike-sa-prf-algorithm> </ike-sa-algorithms> </ike-security-associations> </pre>
Description	Algorithms used with the SA information.
Contents	<p><ike-sa-authentication-algorithm>—Authentication algorithm.</p> <p><ike-sa-encryption-algorithm>—Encryption algorithm.</p> <p><ike-sa-prf-algorithm>—PRF algorithm.</p>

<ike-sa-misc>

Usage <ike-security-associations>
 <ike-sa-misc>
 <ike-sa-flags>*ike-sa-flags*</ike-sa-flags>
 <ike-sa-num-ipsec-sas-created>*ike-sa-num-ipsec-sas-created*
 </ike-sa-num-ipsec-sas-created>
 <ike-sa-num-ipsec-sas-deleted>*ike-sa-num-ipsec-sas-deleted*
 </ike-sa-num-ipsec-sas-deleted>
 <ike-sa-num-phase2-negotiations>*ike-sa-num-phase2-negotiations*
 </ike-sa-num-phase2-negotiations>
 </ike-sa-misc>
 </ike-security-associations>

Description Miscellaneous IKE SA information.

Contents <ike-sa-flags>—IKE SA flags.

<ike-sa-num-ipsec-sas-created>—Number of IPSec SAs created using this SA.

<ike-sa-num-ipsec-sas-deleted>—Number of IPSec SAs deleted using this SA.

<ike-sa-num-phase2-negotiations>—Number of negotiations in progress on this SA.

<ike-sa-phase2-information>

Usage <ike-security-associations | ike-security-associations-information>
<ike-sa-phase2-information>
 <ike-sa-phase2-type>*ike-sa-phase2-type*</ike-sa-phase2-type>
 <ike-sa-role>*ike-sa-role*</ike-sa-role>
 <ike-sa-msg-id>*ike-sa-msg-id*</ike-sa-msg-id>
 <ike-sa-local-address>*ike-sa-local-address*</ike-sa-local-address>
 <ike-sa-local-port>*ike-sa-local-port*</ike-sa-local-port>
 <ike-sa-remote-address>*ike-sa-remote-address*</ike-sa-remote-address>
 <ike-sa-remote-port>*ike-sa-remote-port*</ike-sa-remote-port>
 <ike-sa-local-id>*ike-sa-local-id*</ike-sa-local-id>
 <ike-sa-remote-id>*ike-sa-remote-id*</ike-sa-remote-id>
 <ike-sa-flags>*ike-sa-flags*</ike-sa-flags>
</ike-sa-phase2-information>
 </ike-security-associations | ike-security-associations-information>

Description Information about phase 2 negotiation.

Contents <ike-sa-flags>—IKE SA flags.

<ike-sa-local-address>—Local address.

<ike-sa-local-id>—Local end identity in phase 2.

<ike-sa-local-port>—Local port.

<ike-sa-msg-id>—Message ID of the quick mode negotiation.

<ike-sa-phase2-type>—Type of phase 2 negotiation.

<ike-sa-remote-address>—Remote address.

<ike-sa-remote-id>—Remote end identity in phase 2.

<ike-sa-remote-port>—Remote port.

<ike-sa-role>—Role of our end.

<ike-sa-traffic-statistics>

Usage <ike-security-associations>
 <ike-sa-traffic-statistics>
 <ike-sa-input-packets>*ike-sa-input-packets*</ike-sa-input-packets>
 <ike-sa-output-packets>*ike-sa-output-packets*</ike-sa-output-packets>
 <ike-sa-input-bytes>*ike-sa-input-bytes*</ike-sa-input-bytes>
 <ike-sa-output-bytes>*ike-sa-output-bytes*</ike-sa-output-bytes>
 </ike-sa-traffic-statistics>
 </ike-security-associations>

Description Number of packets and bytes received and transmitted on the SA.

Contents <ike-sa-input-bytes>—Input bytes, including retransmissions.
 <ike-sa-input-packets>—Input packets, including retransmissions.
 <ike-sa-output-bytes>—Output bytes, including retransmissions.
 <ike-sa-output-packets>—Output packets, including retransmissions.

<ike-security-associations>

Usage <ike-security-associations-information | ike-security-associations-block>
<ike-security-associations>
 <ike-sa-role>ike-sa-role</ike-sa-role>
 <ike-sa-state>ike-sa-state</ike-sa-state>
 <ike-sa-initiator-cookie>ike-sa-initiator-cookie</ike-sa-initiator-cookie>
 <ike-sa-responder-cookie>ike-sa-responder-cookie</ike-sa-responder-cookie>
 <ike-sa-exchange-type>ike-sa-exchange-type</ike-sa-exchange-type>
 <ike-sa-authentication-method>ike-sa-authentication-method
 </ike-sa-authentication-method>
 <ike-sa-local-address>ike-sa-local-address</ike-sa-local-address>
 <ike-sa-local-port>ike-sa-local-port</ike-sa-local-port>
 <ike-sa-remote-address>ike-sa-remote-address</ike-sa-remote-address>
 <ike-sa-remote-port>ike-sa-remote-port</ike-sa-remote-port>
 <ike-sa-lifetime>ike-sa-lifetime</ike-sa-lifetime>
 <ike-sa-algorithms>...</ike-sa-algorithms>
 <ike-sa-traffic-statistics>...</ike-sa-traffic-statistics>
 <ike-sa-misc>...</ike-sa-misc>
 <ike-sa-phase2-information>...</ike-sa-phase2-information>
</ike-security-associations>
 </ike-security-associations-information | ike-security-associations-block>

Description Information about a single security association.

Contents <ike-sa-algorithms>—Algorithms used with the SA information.

<ike-sa-authentication-method>—No documentation is available yet.

<ike-sa-exchange-type>—Exchange type.

<ike-sa-initiator-cookie>—IKE SA initiator cookie.

<ike-sa-lifetime>—Remaining lifetime before expiration, in seconds or kilobytes.

<ike-sa-local-address>—Local address.

<ike-sa-local-port>—Local port.

<ike-sa-misc>—Miscellaneous IKE SA information.

<ike-sa-phase2-information>—Information about phase 2 negotiation.

<ike-sa-remote-address>—Remote address.

<ike-sa-remote-port>—Remote port.

<ike-sa-responder-cookie>—IKE SA responder cookie.

<ike-sa-role>—Role of our end.

<ike-sa-state>—Status of the SA.

<ike-sa-traffic-statistics>—Number of packets and bytes received and transmitted on the SA.

<ike-security-associations-block>

- Usage** <ike-security-associations-information>
 <ike-security-associations-block>
 <ike-sa-remote-address>*ike-sa-remote-address*</ike-sa-remote-address>
 <ike-security-associations>...</ike-security-associations>
 </ike-security-associations-block>
 </ike-security-associations-information>
- Description** Information about a single security association block.
- Contents** <ike-sa-remote-address>—Remote address.
 <ike-security-associations>—Information about a single security association.

<ike-security-associations-information>

- Usage** <rpc-reply>
 <ike-security-associations-information>
 <ike-security-associations>...</ike-security-associations>
 <ike-sa-phase2-information>...</ike-sa-phase2-information>
 <ike-security-associations-block>...</ike-security-associations-block>
 </ike-security-associations-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <ike-sa-phase2-information>—Information about phase 2 negotiation.
 <ike-security-associations>—Information about a single security association.
 <ike-security-associations-block>—Information about a single security association block.

<ipsec-pic-redundancy>

Usage <ipsec-pic-redundancy-information>
 <ipsec-pic-redundancy>
 <ipsec-redundancy-counter>*ipsec-redundancy-counter*</ipsec-redundancy-counter>
 <ipsec-redundancy-pic-no-information/>
 <ipsec-pic-redundancy-primary-interface>*ipsec-pic-redundancy-primary-interface*
 </ipsec-pic-redundancy-primary-interface>
 <ipsec-pic-redundancy-backup-interface>*ipsec-pic-redundancy-backup-interface*
 </ipsec-pic-redundancy-backup-interface>
 <ipsec-redundancy-primary-state>*ipsec-redundancy-primary-state*
 </ipsec-redundancy-primary-state>
 <ipsec-redundancy-backup-state>*ipsec-redundancy-backup-state*
 </ipsec-redundancy-backup-state>
 </ipsec-pic-redundancy>
 </ipsec-pic-redundancy-information>

Description Information about ipsec pic redundancy.

Contents <ipsec-pic-redundancy-backup-interface>—Backup ES interface.
 <ipsec-pic-redundancy-primary-interface>—Primary ES interface.
 <ipsec-redundancy-backup-state>—State of backup remote gateway.
 <ipsec-redundancy-counter>—Failover counter.
 <ipsec-redundancy-pic-no-information>—Output string when there are no pic redundancy present.
 <ipsec-redundancy-primary-state>—State of primary remote gateway.

<ipsec-pic-redundancy-information>

Usage <rpc-reply>
 <ipsec-pic-redundancy-information>
 <ipsec-pic-redundancy>...</ipsec-pic-redundancy>
 </ipsec-pic-redundancy-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <ipsec-pic-redundancy>—Information about ipsec pic redundancy.

<ipsec-service-set-statistics>

- Usage** <ipsec-total-statistics | ipsec-total-statistics-information>
<ipsec-service-set-statistics>
 <pic-name>*pic-name*</pic-name>
 <service-set-name>*service-set-name*</service-set-name>
 <ipsec-statistics>...</ipsec-statistics>
</ipsec-service-set-statistics>
 </ipsec-total-statistics | ipsec-total-statistics-information>
- Description** No documentation is available yet.
- Contents** <ipsec-statistics>—No documentation is available yet.
 <pic-name>—PIC name.
 <service-set-name>—Service set name.

<ipsec-statistics>

- Usage** <ipsec-service-set-statistics>
<ipsec-statistics>
 <local-gateway>*local-gateway*</local-gateway>
 <remote-gateway>*remote-gateway*</remote-gateway>
 <tunnel-index>*tunnel-index*</tunnel-index>
 <esp-statistics>...</esp-statistics>
 <ah-statistics>...</ah-statistics>
 <error-statistics>...</error-statistics>
 <statistics-no-information/>
</ipsec-statistics>
 </ipsec-service-set-statistics>
- Description** No documentation is available yet.
- Contents** <ah-statistics>—No documentation is available yet.
 <error-statistics>—No documentation is available yet.
 <esp-statistics>—No documentation is available yet.
 <local-gateway>—Local gateway address.
 <remote-gateway>—Remote gateway address.
 <statistics-no-information>—Output string when there are no statistics to report.
 <tunnel-index>—Tunnel index.

<ipsec-total-statistics>

Usage <rpc-reply>
 <ipsec-total-statistics>
 <ipsec-service-set-statistics>...</ipsec-service-set-statistics>
 </ipsec-total-statistics>
 </rpc-reply>

Description No documentation is available yet.

Contents <ipsec-service-set-statistics>—No documentation is available yet.

<ipsec-total-statistics-information>

Usage <rpc-reply>
 <ipsec-total-statistics-information>
 <ipsec-service-set-statistics>...</ipsec-service-set-statistics>
 </ipsec-total-statistics-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <ipsec-service-set-statistics>—No documentation is available yet.

<ipsec-tunnel-redundancy>

Usage <ipsec-tunnel-redundancy-information>
<ipsec-tunnel-redundancy>
 <sa-name>*sa-name*</sa-name>
 <ipsec-redundancy-counter>*ipsec-redundancy-counter*</ipsec-redundancy-counter>
 <ipsec-redundancy-tunnel-no-information/>
 <ipsec-tunnel-redundancy-local-address>*ipsec-tunnel-red-local-add*
 </ipsec-tunnel-redundancy-local-address>
 <ipsec-tunnel-redundancy-primary-remote-address>*ipsec-tunnel-red-prim-rem-add*
 </ipsec-tunnel-redundancy-primary-remote-address>
 <ipsec-tunnel-redundancy-backup-remote-address>*ipsec-tunnel-red-backup-rem-add*
 </ipsec-tunnel-redundancy-backup-remote-address>
 <ipsec-redundancy-primary-state>*ipsec-redundancy-primary-state*
 </ipsec-redundancy-primary-state>
 <ipsec-redundancy-backup-state>*ipsec-redundancy-backup-state*
 </ipsec-redundancy-backup-state>
</ipsec-tunnel-redundancy>
 </ipsec-tunnel-redundancy-information>

Description Information about ipsec tunnel redundancy.

Contents <ipsec-redundancy-backup-state>—State of backup remote gateway.
 <ipsec-redundancy-counter>—Failover counter.
 <ipsec-redundancy-primary-state>—State of primary remote gateway.
 <ipsec-redundancy-tunnel-no-information>—Output string when tunnel redundancy is not configured.
 <ipsec-tunnel-redundancy-backup-remote-address>—Address of backup remote gateway.
 <ipsec-tunnel-redundancy-local-address>—Address of local gateway.
 <ipsec-tunnel-redundancy-primary-remote-address>—Address of primary remote gateway.
 <sa-name>—Name of the security association.

<ipsec-tunnel-redundancy-information>

Usage <rpc-reply>
<ipsec-tunnel-redundancy-information>
 <ipsec-tunnel-redundancy>...</ipsec-tunnel-redundancy>
</ipsec-tunnel-redundancy-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <ipsec-tunnel-redundancy>—Information about ipsec tunnel redundancy.

<issue-info>

Usage	<x509-certificate-info x509-certificate-cache-info> <issue-info> <recipient> <i>recipient</i> </recipient> <issued-by> <i>issued-by</i> </issued-by> </issue-info> </x509-certificate-info x509-certificate-cache-info>
Description	No documentation is available yet.
Contents	<issued-by>—No documentation is available yet. <recipient>—No documentation is available yet.

<issuer>

Usage	<x509-certificate-info> <issuer> <distinguished-name>...</distinguished-name> </issuer> </x509-certificate-info>
Description	Identifies the CA that issued certificate.
Contents	<distinguished-name>—No documentation is available yet.

<key-usage-list>

Usage	<x509-certificate-info x509-certificate-cache-info> <key-usage-list> <key-usage> <i>key-usage</i> </key-usage> </key-usage-list> </x509-certificate-info x509-certificate-cache-info>
Description	No documentation is available yet.
Contents	<key-usage>—Purpose for which X.509 key is used.

<kmd-memory-usage>

Usage	<kmd-memory-usage-information> <kmd-memory-usage> <memory-block-type> <i>memory-block-type</i> </memory-block-type> <memory-in-use> <i>memory-in-use</i> </memory-in-use> </kmd-memory-usage> </kmd-memory-usage-information>
Description	Information about key management daemon memory usage.
Contents	<memory-block-type>—Memory block type. <memory-in-use>—Memory in use.

<kmd-memory-usage-information>

Usage	<pre> <rpc-reply> <kmd-memory-usage-information> <kmd-memory-usage>...</kmd-memory-usage> </kmd-memory-usage-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<kmd-memory-usage>—Information about key management daemon memory usage.

<pki-scep>

Usage	<pre> <rpc-reply> <pki-scep> <url>url</url> <ca-name>ca-name</ca-name> <ca-file>ca-file</ca-file> <key>key</key> <certificate-subject>certificate-subject</certificate-subject> <certificate-dns>certificate-dns</certificate-dns> <certificate-alternate-subject>certificate-alternate-subject </certificate-alternate-subject> <encoding>encoding</encoding> <message>message</message> </pki-scep> </rpc-reply> </pre>
Description	Simple Certificate Enrollment Protocol.
Contents	<p><ca-file>—Filename containing CA certificate.</p> <p><ca-name>—Name of certificate authority.</p> <p><certificate-alternate-subject>—Alternate subject.</p> <p><certificate-dns>—Domain name.</p> <p><certificate-subject>—Subject.</p> <p><encoding>—Encoding.</p> <p><key>—Key pair.</p> <p><message>—Message displayed when SCEP initializes.</p> <p><url>—Enrollment request URL.</p>

<public-key>

- Usage** <x509-certificate-info | x509-certificate-cache-info>
 <public-key>
 <public-key-algorithm>*public-key-algorithm*</public-key-algorithm>
 <public-key-length>*public-key-length*</public-key-length>
 <public-key-verification-status>*public-key-verification-status*
 </public-key-verification-status>
 </public-key>
 </x509-certificate-info | x509-certificate-cache-info>
- Description** Information about an X.509 public key.
- Contents** <public-key-algorithm>—Algorithm used for creating the subject public key.
 <public-key-length>—Length of X.509 public.
 <public-key-verification-status>—Verification status of X.509 public key.

<public-key-contents-list>

- Usage** <x509-certificate-info | x509-certificate-cache-info>
 <public-key-contents-list>
 <key-contents>*key-contents*</key-contents>
 </public-key-contents-list>
 </x509-certificate-info | x509-certificate-cache-info>
- Description** No documentation is available yet.
- Contents** <key-contents>—Contents of an X.509 public key.

<sa-tunnel-information>

Usage <security-associations-block | security-associations-information |
services-security-associations-block | services-security-associations-information>

<sa-tunnel-information>

```
<sa-rule-name>sa-rule-name</sa-rule-name>
<sa-term-name>sa-term-name</sa-term-name>
<sa-tunnel-index>sa-tunnel-index</sa-tunnel-index>
<sa-local-gateway>sa-local-gateway</sa-local-gateway>
<sa-remote-gateway>sa-remote-gateway</sa-remote-gateway>
<sa-local-identity>sa-local-identity</sa-local-identity>
<sa-remote-identity>sa-remote-identity</sa-remote-identity>
<sa-inside-interface>sa-inside-interface</sa-inside-interface>
<sa-tunnel-mtu>sa-tunnel-mtu</sa-tunnel-mtu>
<sa-no-information/>
```

</sa-tunnel-information>

```
</security-associations-block | security-associations-information |
services-security-associations-block | services-security-associations-information>
```

Description No documentation is available yet.

Contents <sa-inside-interface>—Name of IPSec interface to internal network.

<sa-local-gateway>—Local gateway address.

<sa-local-identity>—Local identity information.

<sa-no-information>—Output string when there are no security associations present.

<sa-remote-gateway>—Remote gateway address.

<sa-remote-identity>—Remote identity information.

<sa-rule-name>—Name of the rule.

<sa-term-name>—Name of the term.

<sa-tunnel-index>—Tunnel index.

<sa-tunnel-mtu>—MTU of the IPSec Tunnel.

<security-associations>

Usage	<security-associations-block security-associations-information services-security-associations-block services-security-associations-information> <security-associations> <sa-direction>sa-direction</sa-direction> <sa-spi>sa-spi</sa-spi> <sa-aux-spi>sa-aux-spi</sa-aux-spi> <sa-state>sa-state</sa-state> <sa-mode>sa-mode</sa-mode> <sa-type>sa-type</sa-type> <sa-protocol>sa-protocol</sa-protocol> <sa-authentication-algorithm>sa-authentication-algorithm </sa-authentication-algorithm> <sa-encryption-algorithm>sa-encryption-algorithm</sa-encryption-algorithm> <sa-soft-lifetime>sa-soft-lifetime</sa-soft-lifetime> <sa-hard-lifetime>sa-hard-lifetime</sa-hard-lifetime> <sa-anti-replay-service>sa-anti-replay-service</sa-anti-replay-service> <sa-replay-window-size>sa-replay-window-size</sa-replay-window-size> </security-associations> </security-associations-block security-associations-information services-security-associations-block services-security-associations-information>
Description	Information about a single security association.
Contents	<sa-anti-replay-service>—Anti-replay service. <sa-authentication-algorithm>—Authentication algorithm. <sa-aux-spi>—Auxiliary Security Parameter Index. <sa-direction>—Direction of the security association. <sa-encryption-algorithm>—Encryption algorithm. <sa-hard-lifetime>—Remaining lifetime, in seconds or kilobytes, before hard lifetime expires. <sa-mode>—Mode of the security association. <sa-protocol>—IPSec security protocol. <sa-replay-window-size>—Replay window size. <sa-soft-lifetime>—Remaining lifetime, in seconds or kilobytes, before soft lifetime expires. <sa-spi>—Security Parameter Index. <sa-state>—Status of the SA. <sa-type>—No documentation is available yet.

<security-associations-block>

- Usage** <security-associations-information>
 <security-associations-block>
 <sa-name>*sa-name*</sa-name>
 <sa-block-state>*sa-block-state*</sa-block-state>
 <sa-tunnel-information>...</sa-tunnel-information>
 <security-associations>...</security-associations>
 </security-associations-block>
 </security-associations-information>
- Description** Information about a single security association block.
- Contents** <sa-block-state>—Status of the SA configuration block.
- <sa-name>—Name of the security association.
- <sa-tunnel-information>—No documentation is available yet.
- <security-associations>—Information about a single security association.

<security-associations-information>

- Usage** <rpc-reply>
 <security-associations-information>
 <security-associations-block>...</security-associations-block>
 <sa-tunnel-information>...</sa-tunnel-information>
 <security-associations>...</security-associations>
 </security-associations-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <sa-tunnel-information>—No documentation is available yet.
- <security-associations>—Information about a single security association.
- <security-associations-block>—Information about a single security association block.

<serial-number-list>

- Usage** <x509-certificate-info | x509-certificate-cache-info>
 <serial-number-list>
 <serial-number-x509>*serial-number-x509*</serial-number-x509>
 </serial-number-list>
 </x509-certificate-info | x509-certificate-cache-info>
- Description** Serial numbers of one or more X.509 certificate.
- Contents** <serial-number-x509>—Serial number of an X.509 certificate.

<service-set-info>

- Usage** <x509-certificate-cache-info>
 <service-set-info>
 <service-set-name>service-set-name</service-set-name>
 <total-cert-entries>total-cert-entries</total-cert-entries>
 </service-set-info>
 </x509-certificate-cache-info>
- Description** Information about service set and certificate cache statistics.
- Contents** <service-set-name>—Service set name.
 <total-cert-entries>—Information about certificate entries present in the cache.

<services-security-associations-block>

- Usage** <services-security-associations-information>
 <services-security-associations-block>
 <svc-set-name>svc-set-name</svc-set-name>
 <outside-service-interface-routing-instance>outside-service-interface-routing-instance
 </outside-service-interface-routing-instance>
 <sa-tunnel-information>...</sa-tunnel-information>
 <security-associations>...</security-associations>
 <tunnel-redundancy-extensive>...</tunnel-redundancy-extensive>
 </services-security-associations-block>
 </services-security-associations-information>
- Description** Information about a single services security associations block.
- Contents** <outside-service-interface-routing-instance>—Name of routing instance that hosts outside service interface.
 <sa-tunnel-information>—No documentation is available yet.
 <security-associations>—Information about a single security association.
 <svc-set-name>—Name of the service set.
 <tunnel-redundancy-extensive>—Information about IPSec tunnel redundancy.

<services-security-associations-information>

Usage <rpc-reply>
 <services-security-associations-information>
 <services-security-associations-block>...
 </services-security-associations-block>
 <sa-tunnel-information>...</sa-tunnel-information>
 <security-associations>...</security-associations>
 <tunnel-redundancy-extensive>...</tunnel-redundancy-extensive>
 </services-security-associations-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <sa-tunnel-information>—No documentation is available yet.

<security-associations>—Information about a single security association.

<services-security-associations-block>—Information about a single services security associations block.

<tunnel-redundancy-extensive>—Information about IPSec tunnel redundancy.

<subject>

Usage <x509-certificate-info>
 <subject>
 <distinguished-name>...</distinguished-name>
 </subject>
 </x509-certificate-info>

Description Information about certificate owner.

Contents <distinguished-name>—No documentation is available yet.

<tunnel-redundancy-extensive>

Usage	<pre> <services-security-associations-block services-security-associations-information> <tunnel-redundancy-extensive> <ipsec-redundancy-counter>ipsec-redundancy-counter</ipsec-redundancy-counter> <ipsec-redundancy-tunnel-no-information/> <ipsec-tunnel-redundancy-primary-remote-address>ipsec-tunnel-red-prim-rem-add </ipsec-tunnel-redundancy-primary-remote-address> <ipsec-tunnel-redundancy-backup-remote-address>ipsec-tunnel-red-bkup-rem-addr </ipsec-tunnel-redundancy-backup-remote-address> <ipsec-redundancy-primary-state>ipsec-redundancy-primary-state </ipsec-redundancy-primary-state> <ipsec-redundancy-backup-state>ipsec-redundancy-backup-state </ipsec-redundancy-backup-state> </tunnel-redundancy-extensive> </services-security-associations-block services-security-associations-information> </pre>
Description	Information about IPSec tunnel redundancy.
Contents	<pre> <ipsec-redundancy-backup-state>—State of backup remote gateway. <ipsec-redundancy-counter>—Failover counter. <ipsec-redundancy-primary-state>—State of primary remote gateway. <ipsec-redundancy-tunnel-no-information>—Output string when tunnel redundancy is not configured. <ipsec-tunnel-redundancy-backup-remote-address>—Address of backup remote gateway. <ipsec-tunnel-redundancy-primary-remote-address>—Address of primary remote gateway. </pre>

<validity>

Usage	<pre> <x509-certificate-info x509-certificate-cache-info> <validity> <not-before>not-before</not-before> <not-after>not-after</not-after> </validity> </x509-certificate-info x509-certificate-cache-info> </pre>
Description	Information about validity period for X.509 certificate.
Contents	<pre> <not-after>—End date of validity period. <not-before>—Start date of validity period. </pre>

<x509>

Usage <certificates>
 <x509>
 <x509-ip>x509-ip</x509-ip>
 <x509-dns>x509-dns</x509-dns>
 <x509-uri>x509-uri</x509-uri>
 <x509-email>x509-email</x509-email>
 </x509>
 </certificates>

Description Information about a single x509 record.

Contents <x509-dns>—No documentation is available yet.

 <x509-email>—No documentation is available yet.

 <x509-ip>—No documentation is available yet.

 <x509-uri>—No documentation is available yet.

<x509-certificate-cache-info>

Usage <x509-certificate-cache-info-list>
<x509-certificate-cache-info>
 <service-set-info>...</service-set-info>
 <cert-flag-info>...</cert-flag-info>
 <issue-info>...</issue-info>
 <serial-number-list>...</serial-number-list>
 <public-key>...</public-key>
 <fingerprint>...</fingerprint>
 <public-key-contents-list>...</public-key-contents-list>
 <alternate-subject-list>...</alternate-subject-list>
 <key-usage-list>...</key-usage-list>
 <distribution-crl-list>...</distribution-crl-list>
 <signature-algorithm>*signature-algorithm*</signature-algorithm>
 <identifier>*identifier*</identifier>
 <validity>...</validity>
 <version>*version*</version>
 <certificate-cache-entry>*certificate-cache-entry*</certificate-cache-entry>
</x509-certificate-cache-info>
 </x509-certificate-cache-info-list>

Description Information about an X.509 certificate present in the cache.

Contents <alternate-subject-list>—No documentation is available yet.

<cert-flag-info>—Information about state of certificates present in the cache.

<certificate-cache-entry>—Identifier for the certificate entry present in the cache.

<distribution-crl-list>—Information about one or more distribution certificate revocation lists.

<fingerprint>—Fingerprint.

<identifier>—Certificate identifier.

<issue-info>—No documentation is available yet.

<key-usage-list>—No documentation is available yet.

<public-key>—Information about an X.509 public key.

<public-key-contents-list>—No documentation is available yet.

<serial-number-list>—Serial numbers of one or more X.509 certificate.

<service-set-info>—Information about service set and certificate cache statistics.

<signature-algorithm>—Algorithm used by the CA to sign the certificate.

<validity>—Information about validity period for X.509 certificate.

<version>—Certificate version.

<x509-certificate-cache-info-list>

Usage <rpc-reply>
 <x509-certificate-cache-info-list>
 <x509-certificate-cache-info>...</x509-certificate-cache-info>
 </x509-certificate-cache-info-list>
 </rpc-reply>

Description Details of X.509 certificates present in the cache.

Contents <x509-certificate-cache-info>—Information about an X.509 certificate present in the cache.

<x509-certificate-info>

Usage <x509-pki-certificate-info-list>
 <x509-certificate-info>
 <issue-info>...</issue-info>
 <serial-number-list>...</serial-number-list>
 <public-key>...</public-key>
 <fingerprint>...</fingerprint>
 <public-key-contents-list>...</public-key-contents-list>
 <alternate-subject-list>...</alternate-subject-list>
 <key-usage-list>...</key-usage-list>
 <distribution-crl-list>...</distribution-crl-list>
 <signature-algorithm>*signature-algorithm*</signature-algorithm>
 <identifier>*identifier*</identifier>
 <validity>...</validity>
 <version>*version*</version>
 <auto-re-enrollment>...</auto-re-enrollment>
 <certificate-type>*certificate-type*</certificate-type>
 <status>*status*</status>
 <issuer>...</issuer>
 <subject>...</subject>
 </x509-certificate-info>
 </x509-pki-certificate-info-list>

Description Detailed information about an X.509 certificate.

Contents <alternate-subject-list>—No documentation is available yet.

<auto-re-enrollment>—No documentation is available yet.

<certificate-type>—X.509 certificate type.

<distribution-crl-list>—Information about one or more distribution certificate revocation lists.

<fingerprint>—Fingerprint.

<identifier>—Certificate identifier.

<issue-info>—No documentation is available yet.

<issuer>—Identifies the CA that issued certificate.

<key-usage-list>—No documentation is available yet.

<public-key>—Information about an X.509 public key.

<public-key-contents-list>—No documentation is available yet.

<serial-number-list>—Serial numbers of one or more X.509 certificate.

<signature-algorithm>—Algorithm used by the CA to sign the certificate.

<status>—No documentation is available yet.

<subject>—Information about certificate owner.

<validity>—Information about validity period for X.509 certificate.

<version>—Certificate version.

<x509-crl-information>

Usage <x509-pki-crl-information-list>
 <x509-crl-information>
 <crl-number>*crl-number*</crl-number>
 <crl-revocation-list>...</crl-revocation-list>
 <crl-validity>...</crl-validity>
 <crl-version>*crl-version*</crl-version>
 <crl-issuer>*crl-issuer*</crl-issuer>
 <identifier>*identifier*</identifier>
 <crl-issuer-alternate-subject-list>...</crl-issuer-alternate-subject-list>
 <crl-issuer-detail>...</crl-issuer-detail>
 </x509-crl-information>
 </x509-pki-crl-information-list>

Description Detailed information about X.509 certificate revocation list.

Contents <crl-issuer>—CRL issuer name.

<crl-issuer-alternate-subject-list>—No documentation is available yet.

<crl-issuer-detail>—Distinguished name of CRL issuer.

<crl-number>—CRL sequence number.

<crl-revocation-list>—No documentation is available yet.

<crl-validity>—Information about validity period for X.509 certificate revocation list.

<crl-version>—CRL version.

<identifier>—Certificate identifier.

<x509-pki-certificate-info-list>

Usage <rpc-reply>
 <x509-pki-certificate-info-list>
 <x509-certificate-info>...</x509-certificate-info>
 </x509-pki-certificate-info-list>
 </rpc-reply>

Description X.509 certificate details.

Contents <x509-certificate-info>—Detailed information about an X.509 certificate.

<x509-pki-crl-information-list>

Usage <rpc-reply>
 <x509-pki-crl-information-list>
 <x509-crl-information>...</x509-crl-information>
 </x509-pki-crl-information-list>
 </rpc-reply>

Description Detailed information about X.509 certificate revocation list.

Contents <x509-crl-information>—Detailed information about X.509 certificate revocation list.

Summary of IPv6 Neighbor Discovery Response Tags

This section lists JUNOS XML tags that contain operational information about IP version 6 (IPv6) neighbor discovery. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-ipv6-nd>. To review the DTD for the tags, see “DTD for IPv6 Neighbor Discovery Response Tags” on page 1813.

<ipv6-modify-nd>

Usage	<pre><rpc-reply> <ipv6-modify-nd> <ipv6-modify-nd-entry>...</ipv6-modify-nd-entry> </ipv6-modify-nd> </rpc-reply></pre>
Description	No documentation is available yet.
Contents	<ipv6-modify-nd-entry>—No documentation is available yet.

<ipv6-modify-nd-entry>

Usage	<pre><ipv6-modify-nd> <ipv6-modify-nd-entry> <ipv6-nd-neighbor-address>ipv6-nd-neighbor-address</ipv6-nd-neighbor-address> <ipv6-nd-neighbor-l2-address>ipv6-nd-neighbor-l2-address </ipv6-nd-neighbor-l2-address> <ipv6-nd-change>ipv6-nd-change</ipv6-nd-change> </ipv6-modify-nd-entry> </ipv6-modify-nd></pre>
Description	No documentation is available yet.
Contents	<p><ipv6-nd-change>—No documentation is available yet.</p> <p><ipv6-nd-neighbor-address>—Address of the neighbor.</p> <p><ipv6-nd-neighbor-l2-address>—Layer 2 address of the neighbor.</p>

<ipv6-nd-entry>

Usage <ipv6-nd-information>
 <ipv6-nd-entry>
 <ipv6-nd-neighbor-address>ipv6-nd-neighbor-address</ipv6-nd-neighbor-address>
 <ipv6-nd-neighbor-l2-address>ipv6-nd-neighbor-l2-address
 </ipv6-nd-neighbor-l2-address>
 <ipv6-nd-total>ipv6-nd-total</ipv6-nd-total>
 <ipv6-nd-state>ipv6-nd-state</ipv6-nd-state>
 <ipv6-nd-expire>ipv6-nd-expire</ipv6-nd-expire>
 <ipv6-nd-isrouter>ipv6-nd-isrouter</ipv6-nd-isrouter>
 <ipv6-nd-issecure>ipv6-nd-issecure</ipv6-nd-issecure>
 <ipv6-nd-interface-name>ipv6-nd-interface-name</ipv6-nd-interface-name>
 </ipv6-nd-entry>
 </ipv6-nd-information>

Description No documentation is available yet.

Contents <ipv6-nd-expire>—No documentation is available yet.

<ipv6-nd-interface-name>—Name of the interface.

<ipv6-nd-isrouter>—No documentation is available yet.

<ipv6-nd-issecure>—No documentation is available yet.

<ipv6-nd-neighbor-address>—Address of the neighbor.

<ipv6-nd-neighbor-l2-address>—Layer 2 address of the neighbor.

<ipv6-nd-state>—No documentation is available yet.

<ipv6-nd-total>—Total number of cache entries.

<ipv6-nd-information>

Usage <rpc-reply>
 <ipv6-nd-information>
 <ipv6-nd-entry>...</ipv6-nd-entry>
 </ipv6-nd-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <ipv6-nd-entry>—No documentation is available yet.

Summary of ISDN Response Tags

This section lists JUNOS XML tags that contain operational information about ISDN. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-isdnd>. To review the DTD for the tags, see “DTD for ISDN Response Tags” on page 1815.

<ces-status>

Usage	<pre><q921-status> <ces-status> <ces-num>ces-num</ces-num> <layer2-status>layer2-status</layer2-status> <tei-status>tei-status</tei-status> <tei-assigned>tei-assigned</tei-assigned> </ces-status> </q921-status></pre>
Description	Connection Endpoint Suffix status.
Contents	<p><ces-num>—Connection Endpoint Suffix number.</p> <p><layer2-status>—Layer 2 status.</p> <p><tei-assigned>—Terminal Equipment Identifier (TEI) assigned value.</p> <p><tei-status>—Terminal Equipment Identifier (TEI) assigned status.</p>

<endpoint>

Usage	<pre><endpoint-status> <endpoint> <ces-num>ces-num</ces-num> <isdn-sp-id>isdn-sp-id</isdn-sp-id> <endpoint-state>endpoint-state</endpoint-state> <usid>usid</usid> <tid>tid</tid> </endpoint> </endpoint-status></pre>
Description	Detailed output for one endpoint.
Contents	<p><ces-num>—Connection Endpoint Suffix number.</p> <p><endpoint-state>—State of the endpoint.</p> <p><isdn-sp-id>—Configured ISDN SPID.</p> <p><tid>—Terminal identifier.</p> <p><usid>—User service identifier.</p>

<endpoint-status>

- Usage** <isdn-config-options>
 <endpoint-status>
 <endpoint>...</endpoint>
 </endpoint-status>
 </isdn-config-options>
- Description** ISDN endpoint status.
- Contents** <endpoint>—Detailed output for one endpoint.

<isdn-call>

- Usage** <isdn-calls | isdn-call-history>
 <isdn-call>
 <bc-interface-name>*bc-interface-name*</bc-interface-name>
 <call-status>*call-status*</call-status>
 <error-code>*error-code*</error-code>
 <call-duration>*call-duration*</call-duration>
 <call-direction>*call-direction*</call-direction>
 <called-number>*called-number*</called-number>
 <calling-number>*calling-number*</calling-number>
 </isdn-call>
 </isdn-calls | isdn-call-history>
- Description** No documentation is available yet.
- Contents** <bc-interface-name>—Interface name.
- <call-direction>—Direction of call (incoming or outgoing).
- <call-duration>—Duration for which call has been on.
- <call-status>—Current status of call.
- <called-number>—Number to which call was made.
- <calling-number>—Number from which call was made.
- <error-code>—Error code as returned by ISDN stack.

<isdn-call-history>

- Usage** <rpc-reply>
 <isdn-call-history>
 <isdn-call>...</isdn-call>
 </isdn-call-history>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <isdn-call>—No documentation is available yet.

<isdn-calls>

Usage <rpc-reply>
 <isdn-calls>
 <isdn-call>...</isdn-call>
 </isdn-calls>
 </rpc-reply>

Description No documentation is available yet.

Contents <isdn-call>—No documentation is available yet.

<isdn-config-options>

Usage <rpc-reply>
 <isdn-config-options>
 <isdn-switch-type>*isdn-switch-type*</isdn-switch-type>
 <isdn-interface-type>*isdn-interface-type*</isdn-interface-type>
 <isdn-calling-number>*isdn-calling-number*</isdn-calling-number>
 <isdn-timer-t306>*isdn-timer-t306*</isdn-timer-t306>
 <isdn-timer-t310>*isdn-timer-t310*</isdn-timer-t310>
 <isdn-tei-option>*isdn-tei-option*</isdn-tei-option>
 <endpoint-status>...</endpoint-status>
 </isdn-config-options>
 </rpc-reply>

Description No documentation is available yet.

Contents <endpoint-status>—ISDN endpoint status.

<isdn-calling-number>—ISDN calling number configured.

<isdn-interface-type>—ISDN interface type configured.

<isdn-switch-type>—ISDN switch type configured.

<isdn-tei-option>—ISDN tei negotiation.

<isdn-timer-t306>—ISDN timer t306 value.

<isdn-timer-t310>—ISDN timer t310 value.

<isdn-status>

Usage <rpc-reply>
 <isdn-status>
 <isdn-interface-name>*isdn-interface-name*</isdn-interface-name>
 <layer1-status>*layer1-status*</layer1-status>
 <q921-status>...</q921-status>
 <q931-status>...</q931-status>
 </isdn-status>
 </rpc-reply>

Description Isdn stack status.

Contents <isdn-interface-name>—Interface name.

<layer1-status>—Layer 1 status.

<q921-status>—Q921 status.

<q931-status>—Q931 layer 3 status.

<q921-statistics>

Usage <rpc-reply>
<q921-statistics>
 <info-frame-sent>info-frame-sent</info-frame-sent>
 <rr-frame-sent>rr-frame-sent</rr-frame-sent>
 <rn timer-frame-sent>rn timer-frame-sent</rn timer-frame-sent>
 <rej-frame-sent>rej-frame-sent</rej-frame-sent>
 <sabme-frame-sent>sabme-frame-sent</sabme-frame-sent>
 <disc-frame-sent>disc-frame-sent</disc-frame-sent>
 <ua-frame-sent>ua-frame-sent</ua-frame-sent>
 <dm-frame-sent>dm-frame-sent</dm-frame-sent>
 <frmr-frame-sent>frmr-frame-sent</frmr-frame-sent>
 <xid-frame-sent>xid-frame-sent</xid-frame-sent>
 <ui-frame-sent>ui-frame-sent</ui-frame-sent>
 <info-frame-recv>info-frame-recv</info-frame-recv>
 <rr-frame-recv>rr-frame-recv</rr-frame-recv>
 <rn timer-frame-recv>rn timer-frame-recv</rn timer-frame-recv>
 <rej-frame-recv>rej-frame-recv</rej-frame-recv>
 <sabme-frame-recv>sabme-frame-recv</sabme-frame-recv>
 <disc-frame-recv>disc-frame-recv</disc-frame-recv>
 <ua-frame-recv>ua-frame-recv</ua-frame-recv>
 <dm-frame-recv>dm-frame-recv</dm-frame-recv>
 <frmr-frame-recv>frmr-frame-recv</frmr-frame-recv>
 <xid-frame-recv>xid-frame-recv</xid-frame-recv>
 <ui-frame-recv>ui-frame-recv</ui-frame-recv>
</q921-statistics>
 </rpc-reply>

Description No documentation is available yet.

Contents <disc-frame-recv>—Number of Disconnect (DISC) frames received.
 <disc-frame-sent>—Number of Disconnect (DISC) frames sent.
 <dm-frame-recv>—Number of Disconnect Mode (DM) frames received.
 <dm-frame-sent>—Number of Disconnect Mode (DM) frames sent.
 <frmr-frame-recv>—Number of Frame Reject (FRMR) frames received.
 <frmr-frame-sent>—Number of Frame Reject (FRMR) frames sent.
 <info-frame-recv>—Number of Information (INFO) frames received.
 <info-frame-sent>—Number of Information (INFO) frames sent.
 <rej-frame-recv>—Number of Reject (REJ) frames received.
 <rej-frame-sent>—Number of Reject (REJ) frames sent.
 <rn timer-frame-recv>—Number of Receive Not Ready (RNR) frames received.
 <rn timer-frame-sent>—Number of Receive Not Ready (RNR) frames sent.

<rr-frame-recv>—Number of Receive Ready (RR) frames received.

<rr-frame-sent>—Number of Receive Ready (RR) frames sent.

<sabme-frame-recv>—Number of Set Asynchronous Balanced Mode Extended (SABME) frames received.

<sabme-frame-sent>—Number of Set Asynchronous Balanced Mode Extended (SABME) frames sent.

<ua-frame-recv>—Number of Unnumbered Acknowledgment (UA) frames received.

<ua-frame-sent>—Number of Unnumbered Acknowledgment (UA) frames sent.

<ui-frame-recv>—Number of Unnumbered Information (UI) frames received.

<ui-frame-sent>—Number of Unnumbered Information (UI) frames sent.

<xid-frame-recv>—Number of Xid (XID) frames received.

<xid-frame-sent>—Number of Xid (XID) frames sent.

<q921-status>

Usage <isdn-status>
 <q921-status>
 <ces-status>...</ces-status>
 </q921-status>
 </isdn-status>

Description Q921 status.

Contents <ces-status>—Connection Endpoint Suffix status.

<q931-statistics>

Usage <rpc-reply>
<q931-statistics>
 <alerting-sent>*alerting-sent*</alerting-sent>
 <call-proceed-sent>*call-proceed-sent*</call-proceed-sent>
 <conn-sent>*conn-sent*</conn-sent>
 <conn-ack-sent>*conn-ack-sent*</conn-ack-sent>
 <progress-sent>*progress-sent*</progress-sent>
 <setup-sent>*setup-sent*</setup-sent>
 <setup-ack-sent>*setup-ack-sent*</setup-ack-sent>
 <disc-sent>*disc-sent*</disc-sent>
 <rel-sent>*rel-sent*</rel-sent>
 <rel-cmplt-sent>*rel-cmplt-sent*</rel-cmplt-sent>
 <rst-sent>*rst-sent*</rst-sent>
 <rst-ack-sent>*rst-ack-sent*</rst-ack-sent>
 <info-sent>*info-sent*</info-sent>
 <notify-sent>*notify-sent*</notify-sent>
 <stat-sent>*stat-sent*</stat-sent>
 <stat-enq-sent>*stat-enq-sent*</stat-enq-sent>
 <alerting-recv>*alerting-recv*</alerting-recv>
 <call-proceed-recv>*call-proceed-recv*</call-proceed-recv>
 <conn-recv>*conn-recv*</conn-recv>
 <conn-ack-recv>*conn-ack-recv*</conn-ack-recv>
 <progress-recv>*progress-recv*</progress-recv>
 <setup-recv>*setup-recv*</setup-recv>
 <setup-ack-recv>*setup-ack-recv*</setup-ack-recv>
 <disc-recv>*disc-recv*</disc-recv>
 <rel-recv>*rel-recv*</rel-recv>
 <rel-cmplt-recv>*rel-cmplt-recv*</rel-cmplt-recv>
 <rst-recv>*rst-recv*</rst-recv>
 <rst-ack-recv>*rst-ack-recv*</rst-ack-recv>
 <info-recv>*info-recv*</info-recv>
 <notify-recv>*notify-recv*</notify-recv>
 <stat-recv>*stat-recv*</stat-recv>
 <stat-enq-recv>*stat-enq-recv*</stat-enq-recv>
</q931-statistics>
 </rpc-reply>

Description No documentation is available yet.

Contents <alerting-recv>—Number of ALERTING messages received.

<alerting-sent>—Number of ALERTING messages sent.

<call-proceed-recv>—Number of CALL PROCEED messages received.

<call-proceed-sent>—Number of CALL PROCEED messages sent.

<conn-ack-recv>—Number of CONNECT ACK messages received.

<conn-ack-sent>—Number of CONNECT ACK messages sent.

<conn-recv>—Number of CONNECT messages received.

<conn-sent>—Number of CONNECT messages sent.
 <disc-recv>—Number of DISCONNECT messages received.
 <disc-sent>—Number of DISCONNECT messages sent.
 <info-recv>—Number of INFORMATION messages received.
 <info-sent>—Number of INFORMATION messages sent.
 <notify-recv>—Number of NOTIFICATION messages received.
 <notify-sent>—Number of NOTIFICATION messages sent.
 <progress-recv>—Number of PROGRESS messages received.
 <progress-sent>—Number of PROGRESS messages sent.
 <rel-cmplt-recv>—Number of RELEASE COMPLETION messages received.
 <rel-cmplt-sent>—Number of RELEASE COMPLETION messages sent.
 <rel-recv>—Number of RELEASE messages received.
 <rel-sent>—Number of RELEASE messages sent.
 <rst-ack-recv>—Number of RESTART ACK messages received.
 <rst-ack-sent>—Number of RESTART ACK messages sent.
 <rst-recv>—Number of RESTART messages received.
 <rst-sent>—Number of RESTART messages sent.
 <setup-ack-recv>—Number of SETUP ACK messages received.
 <setup-ack-sent>—Number of SETUP ACK messages sent.
 <setup-recv>—Number of SETUP messages received.
 <setup-sent>—Number of SETUP messages sent.
 <stat-enq-recv>—Number of STATUS ENQUIRY messages received.
 <stat-enq-sent>—Number of STATUS ENQUIRY messages sent.
 <stat-recv>—Number of STATUS messages received.
 <stat-sent>—Number of STATUS messages sent.

<q931-status>

Usage <isdn-status>
 <q931-status>
 <active-num-calls>*active-num-calls*</active-num-calls>
 </q931-status>
 </isdn-status>

Description Q931 layer 3 status.

Contents <active-num-calls>—Number of active calls.

Summary of J20 GGSN Response Tags

This section lists JUNOS XML tags that contain operational information about the J20 gateway GPRS support node (GGSN). The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-ggsn>. To review the DTD for the tags, see “DTD for J20 GGSN Response Tags” on page 1819.

<apn-pdp-context-deletion-results>

Usage <rpc-reply>
 <apn-pdp-context-deletion-results>
 <apn-name>apn-name</apn-name>
 <user-category>user-category</user-category>
 <interface-pdp-context-deletion-information>...
 </interface-pdp-context-deletion-information>
 </apn-pdp-context-deletion-results>
 </rpc-reply>

Description Results for an APN-wide PDP context deletion command.

Contents <apn-name>—APN for this context.

 <interface-pdp-context-deletion-information>—Information about PDP context deletion on a per-interface basis.

 <user-category>—User category.

<apn-statistics>

Usage <apn-statistics-information>

```

<apn-statistics>
  <name>name</name>
  <pdp-context-statistics>...</pdp-context-statistics>
  <gtp-error-statistics>...</gtp-error-statistics>
  <uplink>...</uplink>
  <downlink>...</downlink>
  <ggsn-pdp-per-user-category>...</ggsn-pdp-per-user-category>
  <radius-statistics-information>...</radius-statistics-information>
  <rulespace-based-charging-statistics>...</rulespace-based-charging-statistics>
  <signalling>...</signalling>
  <tft-filter-count>tft-filter-count</tft-filter-count>
  <neighbor-solicitation-req-received>neighbor-solicitation-req-received
    </neighbor-solicitation-req-received>
  <neighbor-solicitation-req-responded>neighbor-solicitation-req-responded
    </neighbor-solicitation-req-responded>
  <router-solicitation-req-received>router-solicitation-req-received
    </router-solicitation-req-received>
  <router-solicitation-req-responded>router-solicitation-req-responded
    </router-solicitation-req-responded>
</apn-statistics>
</apn-statistics-information>

```

Description Statistics for a single APN.

Contents <downlink>—Link traffic in the downlink direction.

<ggsn-pdp-per-user-category>—Active PDP per user category.

<gtp-error-statistics>—GTP error statistics.

<name>—No documentation is available yet.

<neighbor-solicitation-req-received>—Number of IPv6 ND neighbor solicitation requests received by U.

<neighbor-solicitation-req-responded>—Number of IPv6 ND neighbor solicitation responses sent by U.

<pdp-context-statistics>—Information about PDP context events.

<radius-statistics-information>—Radius statistics.

<router-solicitation-req-received>—Number of IPv6 ND router solicitation requests received by U.

<router-solicitation-req-responded>—Number of IPv6 ND router solicitation responses sent by U.

<rulespace-based-charging-statistics>—Information about rule spaces.

<signalling>—Signaling traffic.

<tft-filter-count>—Number of traffic flow template filters in use.

<uplink>—Link traffic in the uplink direction.

<apn-statistics-information>

Usage <rpc-reply>
 <apn-statistics-information>
 <apn-statistics>...</apn-statistics>
 <sbcc-statistics-information>...</sbcc-statistics-information>
 <service-based-charging-for-gx>...</service-based-charging-for-gx>
 </apn-statistics-information>
 </rpc-reply>

Description APN statistics for the GGSN.

Contents <apn-statistics>—Statistics for a single APN.
 <sbcc-statistics-information>—Service-based charging statistics.
 <service-based-charging-for-gx>—Service-base charging statistics for the gx interface.

<authorization-discard-information>

Usage <sbcc-statistics-information>
 <authorization-discard-information>
 <authorization-discard-statistics>...</authorization-discard-statistics>
 </authorization-discard-information>
 </sbcc-statistics-information>

Description No documentation is available yet.

Contents <authorization-discard-statistics>—Statistics for authorization-based packet discards.

<authorization-discard-statistics>

Usage <authorization-discard-information>
 <authorization-discard-statistics>
 <service-class-source>service-class-source</service-class-source>
 <packets>packets</packets>
 <bytes>bytes</bytes>
 </authorization-discard-statistics>
 </authorization-discard-information>

Description Statistics for authorization-based packet discards.

Contents <bytes>—Count of bytes.
 <packets>—Count of packets.
 <service-class-source>—Service class list source.

<billing-gateway>

Usage	<pre> <gtp-prime-statistics-information> <billing-gateway> <address>address</address> <time-connected>time-connected</time-connected> </billing-gateway> </gtp-prime-statistics-information> </pre>
Description	Active billing gateway information.
Contents	<p><address>—No documentation is available yet.</p> <p><time-connected>—Time at which a connection was made to a server.</p>

<call-trace>

Usage	<pre> <call-trace-information> <call-trace> <imsi>imsi</imsi> <msisdn>msisdn</msisdn> <time-started>time-started</time-started> <nsapi-information>...</nsapi-information> </call-trace> </call-trace-information> </pre>
Description	Information about a GGSN node call trace.
Contents	<p><imsi>—International Mobile Subscriber Identity for user.</p> <p><msisdn>—Mobile Station Integrated Services Digital Network number for user.</p> <p><nsapi-information>—List of NSAPIs associated with user.</p> <p><time-started>—Time at which the service started.</p>

<call-trace-information>

Usage	<pre> <rpc-reply> <call-trace-information> <number-enabled>number-enabled</number-enabled> <number-active>number-active</number-active> <call-trace>...</call-trace> </call-trace-information> </rpc-reply> </pre>
Description	Information about call traces enabled for the GGSN node.
Contents	<p><call-trace>—Information about a GGSN node call trace.</p> <p><number-active>—Number of call traces that are active.</p> <p><number-enabled>—Number of call traces that are set up.</p>

<ccas-information>

Usage	<sbcc-statistics-information> <ccas-information> <ccas-statistics>...</ccas-statistics> </ccas-information> </sbcc-statistics-information>
Description	Information about credit control application systems.
Contents	<ccas-statistics>—Statistics for a credit control application system.

<ccas-statistics>

Usage <ccas-information>
 <ccas-statistics>
 <ccas-identifier>*ccas-identifier*</ccas-identifier>
 <ccas-start-request>*ccas-start-request*</ccas-start-request>
 <ccas-start-request-failed>*ccas-start-request-failed*
 </ccas-start-request-failed>
 <ccas-update-request>*ccas-update-request*</ccas-update-request>
 <ccas-update-request-failed>*ccas-update-request-failed*
 </ccas-update-request-failed>
 <ccas-stop-request>*ccas-stop-request*</ccas-stop-request>
 <ccas-stop-request-failed>*ccas-stop-request-failed*</ccas-stop-request-failed>
 <ccas-user-service-denied>*ccas-user-service-denied*</ccas-user-service-denied>
 <ccas-user-unknown>*ccas-user-unknown*</ccas-user-unknown>
 <ccas-authorization-failure>*ccas-authorization-failure*
 </ccas-authorization-failure>
 <ccas-cc-not-applicable>*ccas-cc-not-applicable*</ccas-cc-not-applicable>
 </ccas-statistics>
 </ccas-information>

Description Statistics for a credit control application system.

Contents <ccas-authorization-failure>—Failed CC-AS requests due to result code Authorization Rejected.

<ccas-cc-not-applicable>—Credit control not applicable.

<ccas-identifier>—Credit control application system identifier.

<ccas-start-request>—CC-AS start requests.

<ccas-start-request-failed>—CC-AS start requests failed.

<ccas-stop-request>—CC-AS stop requests.

<ccas-stop-request-failed>—CC-AS stop requests failed.

<ccas-update-request>—CC-AS update requests.

<ccas-update-request-failed>—CC-AS update requests failed.

<ccas-user-service-denied>—CC-AS requests failed with user service denied.

<ccas-user-unknown>—CC-AS requests failed with user unknown.

<ccr-statistics>

Usage	<pre> <service-based-charging-for-gx> <ccr-statistics> <ccr-identifier>ccr-identifier</ccr-identifier> <authorization-failure>authorization-failure</authorization-failure> <authentication-failure>authentication-failure</authentication-failure> <session-failure>session-failure</session-failure> </ccr-statistics> </service-based-charging-for-gx> </pre>
Description	Statistics for a credit control application system.
Contents	<p><authentication-failure>—Failed CC requests due to result code Authentication Rejected.</p> <p><authorization-failure>—Failed CC requests due to result code Authorization Rejected.</p> <p><ccr-identifier>—Credit control application system identifier.</p> <p><session-failure>—Failed CC requests due to result code Unknown Session ID.</p>

<charging-statistics-information>

Usage	<pre> <ggsn-statistics> <charging-statistics-information> <encoded-cdrs>encoded-cdrs</encoded-cdrs> <failed-encoded-cdrs>failed-encoded-cdrs</failed-encoded-cdrs> <generated-ftp-cdrs>generated-ftp-cdrs</generated-ftp-cdrs> <generated-gtp-cdrs>generated-gtp-cdrs</generated-gtp-cdrs> <gtp-log-cdrs>gtp-log-cdrs</gtp-log-cdrs> <gtp-send-attempted-cdrs>gtp-send-attempted-cdrs</gtp-send-attempted-cdrs> <gtp-send-failed-cdrs>gtp-send-failed-cdrs</gtp-send-failed-cdrs> </charging-statistics-information> </ggsn-statistics> </pre>
Description	Charging statistics.
Contents	<p><encoded-cdrs>—Number of encoded CDRs.</p> <p><failed-encoded-cdrs>—Number of CDRs that failed encoding.</p> <p><generated-ftp-cdrs>—Number of CDRs generated for FTP.</p> <p><generated-gtp-cdrs>—Number of CDRs generated for GTP prime.</p> <p><gtp-log-cdrs>—Number of GTP prime CDRs stored in the charging log.</p> <p><gtp-send-attempted-cdrs>—Number of CDRs attempted to be sent for GTP prime.</p> <p><gtp-send-failed-cdrs>—Number of CDRs failed to be sent for GTP prime.</p>

<cpu-info>

Usage	<pre> <resources> <cpu-info> <cpu-id>cpu-id</cpu-id> <cpu-load>cpu-load</cpu-load> </cpu-info> </resources> </pre>
Description	CPU usage.
Contents	<p><cpu-id>—CPU ID.</p> <p><cpu-load>—CPU usage (percentage).</p>

<das-information>

Usage	<pre> <sbcc-statistics-information> <das-information> <das-statistics>...</das-statistics> </das-information> </sbcc-statistics-information> </pre>
Description	Information about diameter application systems.
Contents	<das-statistics>—Statistics for a diameter application system.

<das-statistics>

Usage	<pre> <das-information> <das-statistics> <das-identifier>das-identifier</das-identifier> <request>request</request> </das-statistics> </das-information> </pre>
Description	Statistics for a diameter application system.
Contents	<p><das-identifier>—Diameter application system identifier.</p> <p><request>—Requests.</p>

<data-record-transfer-statistics>

Usage <gtp-prime-statistics>
<data-record-transfer-statistics>
 <request-transmitted>*request-transmitted*</request-transmitted>
 <response-received>*response-received*</response-received>
 <request-accepted>*request-accepted*</request-accepted>
 <error-no-resources>*error-no-resources*</error-no-resources>
 <error-service-unsupported>*error-service-unsupported*
 </error-service-unsupported>
 <error-system-failure>*error-system-failure*</error-system-failure>
 <error-invalid-request-format>*error-invalid-request-format*
 </error-invalid-request-format>
 <error-version-unsupported>*error-version-unsupported*
 </error-version-unsupported>
 <error-request-unfulfilled>*error-request-unfulfilled*
 </error-request-unfulfilled>
 <error-decoding-error>*error-decoding-error*</error-decoding-error>
 <error-already-fulfilled>*error-already-fulfilled*</error-already-fulfilled>
 <error-duplicate-packet-fulfilled>*error-duplicate-packet-fulfilled*
 </error-duplicate-packet-fulfilled>
 <send-data-record-packet>*send-data-record-packet*</send-data-record-packet>
</data-record-transfer-statistics>
 </gtp-prime-statistics>

Description GTP Prime data record transfer statistics.

Contents <error-already-fulfilled>—Failed with error: already fulfilled.
 <error-decoding-error>—Failed with error: decoding error.
 <error-duplicate-packet-fulfilled>—Failed with error: duplicate packet fulfilled.
 <error-invalid-request-format>—Failed with error: invalid message format.
 <error-no-resources>—Failed with error: no resources.
 <error-request-unfulfilled>—Failed with error: request unfulfilled.
 <error-service-unsupported>—Failed with error: service unsupported.
 <error-system-failure>—Failed with error: system failure.
 <error-version-unsupported>—Failed with error: version unsupported.
 <request-accepted>—Requests that were accepted.
 <request-transmitted>—Requests sent.
 <response-received>—Responses received.
 <send-data-record-packet>—Number of data transfer request send data record packets sent.

<downlink>

Usage <ggsn-statistics | apn-statistics | sgsn-statistics>
<downlink>
 <packets>*packets*</packets>
 <packets-ipv6>*packets-ipv6*</packets-ipv6>
 <bytes>*bytes*</bytes>
 <bytes-ipv6>*bytes-ipv6*</bytes-ipv6>
 <dropped-packets>*dropped-packets*</dropped-packets>
 <dropped-packets-ipv6>*dropped-packets-ipv6*</dropped-packets-ipv6>
 <dropped-bytes>*dropped-bytes*</dropped-bytes>
 <dropped-bytes-ipv6>*dropped-bytes-ipv6*</dropped-bytes-ipv6>
</downlink>
 </ggsn-statistics | apn-statistics | sgsn-statistics>

Description Link traffic in the downlink direction.

Contents <bytes>—Count of bytes.

<bytes-ipv6>—Count of bytes for IPv6.

<dropped-bytes>—Count of packet dropped bytes.

<dropped-bytes-ipv6>—Count of packet dropped bytes for IPv6.

<dropped-packets>—Count of packet drops.

<dropped-packets-ipv6>—Count of packet drops for IPv6.

<packets>—Count of packets.

<packets-ipv6>—Count of packets for IPv6.

<echo-request-statistics>

Usage <gtp-statistics | gtp-prime-statistics>
<echo-request-statistics>
 <request-received>*request-received*</request-received>
 <request-transmitted>*request-transmitted*</request-transmitted>
 <response-received>*response-received*</response-received>
 <response-transmitted>*response-transmitted*</response-transmitted>
</echo-request-statistics>
 </gtp-statistics | gtp-prime-statistics>

Description Echo request information.

Contents <request-received>—Requests received.

<request-transmitted>—Requests sent.

<response-received>—Responses received.

<response-transmitted>—Responses sent.

<ggsn-interface>

Usage <ggsn-interface-information>
 <ggsn-interface>
 <service-interface>*service-interface*</service-interface>
 <weighted-pdp-context-load-in-payload>*weighted-pdp-context-load-in-payload*
 </weighted-pdp-context-load-in-payload>
 <weighted-pdp-context-load-in-control>*weighted-pdp-context-load-in-control*
 </weighted-pdp-context-load-in-control>
 <external-address>*external-address*</external-address>
 <internal-address>*internal-address*</internal-address>
 <operating-function>*operating-function*</operating-function>
 <hardware-version>*hardware-version*</hardware-version>
 <software-version>*software-version*</software-version>
 <pdp>...</pdp>
 <resources>...</resources>
 <tft-statistics>...</tft-statistics>
 <time-started>*time-started*</time-started>
 <sbcc-statistics-information>...</sbcc-statistics-information>
 </ggsn-interface>
 </ggsn-interface-information>

Description Information about GGSN-C and GGSN-U service interfaces.

Contents <external-address>—External address for the PIC.
 <hardware-version>—PIC hardware version.
 <internal-address>—Internal address for the PIC.
 <operating-function>—Current cluster function for the PIC.
 <pdp>—PDP context information.
 <resources>—CPU and memory information for a PIC.
 <sbcc-statistics-information>—Service-based charging statistics.
 <service-interface>—Service interface for the information.
 <software-version>—GGSN service software version.
 <tft-statistics>—No documentation is available yet.
 <time-started>—Time at which the service started.
 <weighted-pdp-context-load-in-control>—No documentation is available yet.
 <weighted-pdp-context-load-in-payload>—No documentation is available yet.

<ggsn-interface-information>

Usage <rpc-reply>
 <ggsn-interface-information>
 <ggsn-interface>...</ggsn-interface>
 </ggsn-interface-information>
 </rpc-reply>

Description GGSN PIC information.

Contents <ggsn-interface>—Information about GGSN-C and GGSN-U service interfaces.

<ggsn-pdp-per-user-category>

Usage <apn-statistics>
 <ggsn-pdp-per-user-category>
 <user-category-line>...</user-category-line>
 </ggsn-pdp-per-user-category>
 </apn-statistics>

Description Active PDP per user category.

Contents <user-category-line>—No documentation is available yet.

<ggsn-statistics>

Usage <rpc-reply>
<ggsn-statistics>
 <time-started>*time-started*</time-started>
 <pdp-context-statistics>...</pdp-context-statistics>
 <interface-pdp-context-statistics-information>...
 </interface-pdp-context-statistics-information>
 <subscriber-count>*subscriber-count*</subscriber-count>
 <uplink>...</uplink>
 <downlink>...</downlink>
 <tft-filter-count>*tft-filter-count*</tft-filter-count>
 <wlan-pdp-context-activation-procedures>*wlan-pdp-context-activation-procedures*
 </wlan-pdp-context-activation-procedures>
 <wlan-processed-uplink-bytes>*wlan-processed-uplink-bytes*
 </wlan-processed-uplink-bytes>
 <wlan-dropped-uplink-packets>*wlan-dropped-uplink-packets*
 </wlan-dropped-uplink-packets>
 <wlan-processed-uplink-packets>*wlan-processed-uplink-packets*
 </wlan-processed-uplink-packets>
 <wlan-completed-pdp-context-activations>*wlan-completed-pdp-context-activations*
 </wlan-completed-pdp-context-activations>
 <wlan-active-pdp-contexts>*wlan-active-pdp-contexts*</wlan-active-pdp-contexts>
 <wlan-processed-downlink-bytes>*wlan-processed-downlink-bytes*
 </wlan-processed-downlink-bytes>
 <wlan-dropped-downlink-packets>*wlan-dropped-downlink-packets*
 </wlan-dropped-downlink-packets>
 <wlan-processed-downlink-packets>*wlan-processed-downlink-packets*
 </wlan-processed-downlink-packets>
 <weighted-pdp-context-load>...</weighted-pdp-context-load>
 <sbcc-statistics-information>...</sbcc-statistics-information>
 <charging-statistics-information>...</charging-statistics-information>
 <radius-statistics-information>...</radius-statistics-information>
</ggsn-statistics>
 </rpc-reply>

Description Global statistics for the GGSN node.

Contents <charging-statistics-information>—Charging statistics.

<downlink>—Link traffic in the downlink direction.

<interface-pdp-context-statistics-information>—No documentation is available yet.

<pdp-context-statistics>—Information about PDP context events.

<radius-statistics-information>—Radius statistics.

<sbcc-statistics-information>—Service-based charging statistics.

<subscriber-count>—Number of subscribers currently serviced by this GGSN.

<tft-filter-count>—Number of traffic flow template filters in use.

<time-started>—Time at which the service started.

<uplink>—Link traffic in the uplink direction.

<weighted-pdp-context-load>—No documentation is available yet.

<wlan-active-pdp-contexts>—Number of active WLAN PDP contexts.

<wlan-completed-pdp-context-activations>—Number of completed WLAN PDP context activations.

<wlan-dropped-downlink-packets>—Total WLAN downlink packets dropped by this GGSN.

<wlan-dropped-uplink-packets>—Number of dropped WLAN packets in uplink direction.

<wlan-pdp-context-activation-procedures>—Number of WLAN PDP context activation procedures initiated by MS.

<wlan-processed-downlink-bytes>—Total WLAN downlink bytes processed by this GGSN.

<wlan-processed-downlink-packets>—Total WLAN downlink packets processed by this GGSN.

<wlan-processed-uplink-bytes>—Total bytes for all processed uplink WLAN packets via this GGSN.

<wlan-processed-uplink-packets>—Total WLAN uplink packets processed by this GGSN.

<gtp-error-statistics>

Usage <gtp-statistics | apn-statistics | sgsn-statistics>

<gtp-error-statistics>

```

<request-accepted>request-accepted</request-accepted>
<error-indication-received>error-indication-received
  </error-indication-received>
<error-indication-transmitted>error-indication-transmitted
  </error-indication-transmitted>
<error-version-unsupported>error-version-unsupported
  </error-version-unsupported>
<error-invalid-request-format>error-invalid-request-format
  </error-invalid-request-format>
<error-invalid-request-format-when-update>error-invalid-request-format-when-update
  </error-invalid-request-format-when-update>
<error-invalid-request-format-when-delete>error-invalid-request-format-when-delete
  </error-invalid-request-format-when-delete>
<error-no-resources>error-no-resources</error-no-resources>
<error-no-dynamic-address-available>error-no-dynamic-address-available
  </error-no-dynamic-address-available>
<error-no-memory>error-no-memory</error-no-memory>
<error-unknown-apn>error-unknown-apn</error-unknown-apn>
<error-unknown-pdp-address-or-type>error-unknown-pdp-address-or-type
  </error-unknown-pdp-address-or-type>
<error-authentication-failed>error-authentication-failed
  </error-authentication-failed>
<error-system-failure>error-system-failure</error-system-failure>
<error-system-failure-when-update>error-system-failure-when-update
  </error-system-failure-when-update>
<error-tft-error-semantic>error-tft-error-semantic</error-tft-error-semantic>
<error-tft-error-semantic-when-update>error-tft-error-semantic-when-update
  </error-tft-error-semantic-when-update>
<error-tft-error-syntax>error-tft-error-syntax</error-tft-error-syntax>
<error-tft-error-syntax-when-update>error-tft-error-syntax-when-update
  </error-tft-error-syntax-when-update>
<error-packet-filter-semantic>error-packet-filter-semantic
  </error-packet-filter-semantic>
<error-packet-filter-semantic-when-update>error-packet-filter-semantic-when-update
  </error-packet-filter-semantic-when-update>
<error-packet-filter-syntax>error-packet-filter-syntax
  </error-packet-filter-syntax>
<error-packet-filter-syntax-when-update>error-packet-filter-syntax-when-update
  </error-packet-filter-syntax-when-update>
<error-mandatory-ie-missing>error-mandatory-ie-missing
  </error-mandatory-ie-missing>
<error-mandatory-ie-missing-when-update>error-mandatory-ie-missing-when-update
  </error-mandatory-ie-missing-when-update>
<error-mandatory-ie-missing-when-delete>error-mandatory-ie-missing-when-delete
  </error-mandatory-ie-missing-when-delete>
<error-mandatory-ie-invalid>error-mandatory-ie-invalid
  </error-mandatory-ie-invalid>
<error-mandatory-ie-invalid-when-update>error-mandatory-ie-invalid-when-update
  </error-mandatory-ie-invalid-when-update>
<error-mandatory-ie-invalid-when-delete>error-mandatory-ie-invalid-when-delete

```

```

        </error-mandatory-ie-invalid-when-delete>
    <error-optional-ie-invalid>error-optional-ie-invalid
    </error-optional-ie-invalid>
    <error-optional-ie-invalid-when-update>error-optional-ie-invalid-when-update
    </error-optional-ie-invalid-when-update>
    <error-optional-ie-invalid-when-delete>error-optional-ie-invalid-when-delete
    </error-optional-ie-invalid-when-delete>
    <error-reference-invalid>error-reference-invalid</error-reference-invalid>
    <error-reference-invalid-when-update>error-reference-invalid-when-update
    </error-reference-invalid-when-update>
    <error-reference-invalid-when-delete>error-reference-invalid-when-delete
    </error-reference-invalid-when-delete>
    <error-service-unsupported>error-service-unsupported
    </error-service-unsupported>
    <error-already-activated>error-already-activated</error-already-activated>
    <error-access-denied>error-access-denied</error-access-denied>
</gtp-error-statistics>
</gtp-statistics | apn-statistics | sgsn-statistics>

```

Description GTP error statistics.

Contents

- <error-access-denied>—PDP context create failed with error: Access denied.
- <error-already-activated>—PDP context create failed with error: already activated.
- <error-authentication-failed>—Failed with error: authentication failed.
- <error-indication-received>—Error indications received.
- <error-indication-transmitted>—Error indications sent.
- <error-invalid-request-format>—Failed with error: invalid message format.
- <error-invalid-request-format-when-delete>—PDP context delete failed with error: invalid message format.
- <error-invalid-request-format-when-update>—PDP context update failed with error: invalid message format.
- <error-mandatory-ie-invalid>—Failed with error: mandatory information element invalid.
- <error-mandatory-ie-invalid-when-delete>—PDP context update failed with error: mandatory information element invalid.
- <error-mandatory-ie-invalid-when-update>—PDP context update failed with error: mandatory information element invalid.
- <error-mandatory-ie-missing>—Failed with error: mandatory information element missing.
- <error-mandatory-ie-missing-when-delete>—PDP context delete failed with error: mandatory information element missing.
- <error-mandatory-ie-missing-when-update>—PDP context update failed with error:

mandatory information element missing.

<error-no-dynamic-address-available>—Failed with error: no dynamic address available.

<error-no-memory>—Failed with error: no memory.

<error-no-resources>—Failed with error: no resources.

<error-optional-ie-invalid>—Failed with error: optional information element invalid.

<error-optional-ie-invalid-when-delete>—PDP context delete failed with error: optional information element invalid.

<error-optional-ie-invalid-when-update>—PDP context update failed with error: optional information element invalid.

<error-packet-filter-semantic>—Failed with error: packet filtering semantic error.

<error-packet-filter-semantic-when-update>—PDP context update failed with error: packet filtering semantic error.

<error-packet-filter-syntax>—Failed with error: packet filtering syntax error.

<error-packet-filter-syntax-when-update>—PDP context update failed with error: packet filtering syntax error.

<error-reference-invalid>—Failed with error: invalid reference.

<error-reference-invalid-when-delete>—PDP context delete failed with error: invalid reference.

<error-reference-invalid-when-update>—PDP context update failed with error: invalid reference.

<error-service-unsupported>—Failed with error: service unsupported.

<error-system-failure>—Failed with error: system failure.

<error-system-failure-when-update>—PDP context update failed with error: system failure.

<error-tft-error-semantic>—Failed with error: TFT semantic error.

<error-tft-error-semantic-when-update>—PDP context update failed with error: TFT semantic error.

<error-tft-error-syntax>—Failed with error: TFT syntax error.

<error-tft-error-syntax-when-update>—PDP context failed with error: TFT syntax error.

<error-unknown-apn>—Failed with error: unknown APN.

`<error-unknown-pdp-address-or-type>`—Failed with error: unknown PDP address or type.

`<error-version-unsupported>`—Failed with error: version unsupported.

`<request-accepted>`—Requests that were accepted.

`<gtp-prime-error-statistics>`

Usage `<gtp-prime-statistics>`
 `<gtp-prime-error-statistics>`
 `<error-mandatory-ie-missing>`*error-mandatory-ie-missing*
 `</error-mandatory-ie-missing>`
 `<error-mandatory-ie-invalid>`*error-mandatory-ie-invalid*
 `</error-mandatory-ie-invalid>`
 `<error-optional-ie-invalid>`*error-optional-ie-invalid*
 `</error-optional-ie-invalid>`
 `<error-reference-invalid>`*error-reference-invalid*`</error-reference-invalid>`
 `</gtp-prime-error-statistics>`
`</gtp-prime-statistics>`

Description GTP Prime error statistics.

Contents `<error-mandatory-ie-invalid>`—Failed with error: mandatory information element invalid.

`<error-mandatory-ie-missing>`—Failed with error: mandatory information element missing.

`<error-optional-ie-invalid>`—Failed with error: optional information element invalid.

`<error-reference-invalid>`—Failed with error: invalid reference.

<gtp-prime-statistics>

Usage <gtp-prime-statistics-information>
 <gtp-prime-statistics>
 <service-interface>service-interface</service-interface>
 <echo-request-statistics>...</echo-request-statistics>
 <version-unsupported-statistics>...</version-unsupported-statistics>
 <node-alive-request-statistics>...</node-alive-request-statistics>
 <redirection-request-statistics>...</redirection-request-statistics>
 <data-record-transfer-statistics>...</data-record-transfer-statistics>
 <gtp-prime-error-statistics>...</gtp-prime-error-statistics>
 </gtp-prime-statistics>
 </gtp-prime-statistics-information>

Description GTP Prime statistics information.

Contents <data-record-transfer-statistics>—GTP Prime data record transfer statistics.

<echo-request-statistics>—Echo request information.

<gtp-prime-error-statistics>—GTP Prime error statistics.

<node-alive-request-statistics>—GTP Prime node alive request statistics.

<redirection-request-statistics>—GTP Prime redirection request statistics.

<service-interface>—Service interface for the information.

<version-unsupported-statistics>—Version unsupported message information.

<gtp-prime-statistics-information>

Usage <rpc-reply>
 <gtp-prime-statistics-information>
 <billing-gateway>...</billing-gateway>
 <gtp-prime-statistics>...</gtp-prime-statistics>
 </gtp-prime-statistics-information>
 </rpc-reply>

Description GTP Prime statistics information.

Contents <billing-gateway>—Active billing gateway information.

<gtp-prime-statistics>—GTP Prime statistics information.

<gtp-statistics>

Usage <gtp-statistics-information>
 <gtp-statistics>
 <service-interface>*service-interface*</service-interface>
 <uplink-packets>*uplink-packets*</uplink-packets>
 <uplink-bytes>*uplink-bytes*</uplink-bytes>
 <downlink-packets>*downlink-packets*</downlink-packets>
 <downlink-bytes>*downlink-bytes*</downlink-bytes>
 <dropped-packets>*dropped-packets*</dropped-packets>
 <active-tunnels>*active-tunnels*</active-tunnels>
 <created-tunnels>*created-tunnels*</created-tunnels>
 <echo-request-statistics>...</echo-request-statistics>
 <version-unsupported-statistics>...</version-unsupported-statistics>
 <pdp-request-statistics>...</pdp-request-statistics>
 <gtp-error-statistics>...</gtp-error-statistics>
 </gtp-statistics>
 </gtp-statistics-information>

Description GTP statistics information.

Contents <active-tunnels>—Number of currently active tunnels.

<created-tunnels>—Total number of created tunnels since last node controller restart.

<downlink-bytes>—Bytes in the downlink direction.

<downlink-packets>—Packets in the downlink direction.

<dropped-packets>—Count of packet drops.

<echo-request-statistics>—Echo request information.

<gtp-error-statistics>—GTP error statistics.

<pdp-request-statistics>—PDP context request statistics.

<service-interface>—Service interface for the information.

<uplink-bytes>—Bytes in the uplink direction.

<uplink-packets>—Packets in the uplink direction.

<version-unsupported-statistics>—Version unsupported message information.

<gtp-statistics-information>

- Usage** <rpc-reply>
 <gtp-statistics-information>
 <gtp-statistics>...</gtp-statistics>
 </gtp-statistics-information>
 </rpc-reply>
- Description** GTP statistics information.
- Contents** <gtp-statistics>—GTP statistics information.

<incoming>

- Usage** <signalling>
 <incoming>
 <packets>*packets*</packets>
 <bytes>*bytes*</bytes>
 </incoming>
 </signalling>
- Description** No documentation is available yet.
- Contents** <bytes>—Count of bytes.
 <packets>—Count of packets.

<inspection-information>

- Usage** <rpc-reply>
 <inspection-information>
 <packet-inspection>*packet-inspection*</packet-inspection>
 </inspection-information>
 </rpc-reply>
- Description** Packet inspection related information.
- Contents** <packet-inspection>—Packet inspection details.

<interface-action-results>

- Usage** <rpc-reply>
 <interface-action-results>
 <interface-action>*interface-action*</interface-action>
 <service-interface>*service-interface*</service-interface>
 <daemon-name>*daemon-name*</daemon-name>
 </interface-action-results>
 </rpc-reply>
- Description** Results of an interface action.
- Contents** <daemon-name>—Daemon being restarted.
- <interface-action>—Actions performed on service interfaces.
- <service-interface>—Service interface for the information.

<interface-pdp-context-deletion>

- Usage** <interface-pdp-context-deletion-information>
 <interface-pdp-context-deletion>
 <pdp-deleted>*pdp-deleted*</pdp-deleted>
 <service-interface>*service-interface*</service-interface>
 </interface-pdp-context-deletion>
 </interface-pdp-context-deletion-information>
- Description** No documentation is available yet.
- Contents** <pdp-deleted>—Total number of PDP contexts deleted.
- <service-interface>—Service interface for the information.

<interface-pdp-context-deletion-information>

- Usage** <apn-pdp-context-deletion-results>
 <interface-pdp-context-deletion-information>
 <interface-pdp-context-deletion>...</interface-pdp-context-deletion>
 </interface-pdp-context-deletion-information>
 </apn-pdp-context-deletion-results>
- Description** Information about PDP context deletion on a per-interface basis.
- Contents** <interface-pdp-context-deletion>—No documentation is available yet.

<interface-pdp-context-statistics>

- Usage** <interface-pdp-context-statistics-information>
 <interface-pdp-context-statistics>
 <service-interface>*service-interface*</service-interface>
 <pdp-context-statistics>...</pdp-context-statistics>
 </interface-pdp-context-statistics>
 </interface-pdp-context-statistics-information>
- Description** Interface-level PDP context statistics.
- Contents** <pdp-context-statistics>—Information about PDP context events.
 <service-interface>—Service interface for the information.

<interface-pdp-context-statistics-information>

- Usage** <ggsn-statistics>
 <interface-pdp-context-statistics-information>
 <interface-pdp-context-statistics>...</interface-pdp-context-statistics>
 </interface-pdp-context-statistics-information>
 </ggsn-statistics>
- Description** No documentation is available yet.
- Contents** <interface-pdp-context-statistics>—Interface-level PDP context statistics.

<l2tp-tunnel-packet-statistics>

Usage <l2tp-tunnel-statistics>
<l2tp-tunnel-packet-statistics>
 <control-tx-packets>*control-tx-packets*</control-tx-packets>
 <control-rx-packets>*control-rx-packets*</control-rx-packets>
 <data-tx-packets>*data-tx-packets*</data-tx-packets>
 <data-rx-packets>*data-rx-packets*</data-rx-packets>
 <discard-tx-packets>*discard-tx-packets*</discard-tx-packets>
 <discard-rx-packets>*discard-rx-packets*</discard-rx-packets>
</l2tp-tunnel-packet-statistics>
 </l2tp-tunnel-statistics>

Description L2TP tunnel statistics.

Contents <control-rx-packets>—Number of control packets received for this tunnel.

<control-tx-packets>—Number of control packets transmitted for this tunnel.

<data-rx-packets>—Number of data packets received for this tunnel.

<data-tx-packets>—Number of data packets transmitted for this tunnel.

<discard-rx-packets>—Number of received packets that were discarded by this tunnel.

<discard-tx-packets>—Number of (attempted) transmitted packets that were discarded by this tunnel.

<l2tp-tunnel-statistics>

Usage <l2tp-tunnel-statistics-information>
<l2tp-tunnel-statistics>
 <local-tid>*local-tid*</local-tid>
 <remote-tid>*remote-tid*</remote-tid>
 <local-ip>*local-ip*</local-ip>
 <remote-ip>*remote-ip*</remote-ip>
 <active-sessions>*active-sessions*</active-sessions>
 <l2tp-tunnel-packet-statistics>...</l2tp-tunnel-packet-statistics>
</l2tp-tunnel-statistics>
 </l2tp-tunnel-statistics-information>

Description L2TP tunnel-statistics for a single tunnel.

Contents <active-sessions>—Number of sessions that are currently active for this tunnel.

<l2tp-tunnel-packet-statistics>—L2TP tunnel statistics.

<local-ip>—Local IP this tunnel is bound to.

<local-tid>—Local tunnel identifier.

<remote-ip>—Remote IP this tunnel is bound to.

<remote-tid>—Remote tunnel identifier.

<l2tp-tunnel-statistics-information>

- Usage** <rpc-reply>
 <l2tp-tunnel-statistics-information>
 <l2tp-tunnel-statistics>...</l2tp-tunnel-statistics>
 </l2tp-tunnel-statistics-information>
 </rpc-reply>
- Description** L2TP tunnel-statistics for the GGSN.
- Contents** <l2tp-tunnel-statistics>—L2TP tunnel-statistics for a single tunnel.

<logical-apn-statistics>

- Usage** <logical-apn-statistics-information>
 <logical-apn-statistics>
 <name>*name*</name>
 <pdp-attempted-activation>*pdp-attempted-activation*</pdp-attempted-activation>
 <pdp-blocked>*pdp-blocked*</pdp-blocked>
 <default-apn-selected>*default-apn-selected*</default-apn-selected>
 <default-apn-invalid>*default-apn-invalid*</default-apn-invalid>
 <username-based-apn-selected>*username-based-apn-selected*
 </username-based-apn-selected>
 <username-based-apn-invalid>*username-based-apn-invalid*
 </username-based-apn-invalid>
 </logical-apn-statistics>
 </logical-apn-statistics-information>
- Description** Statistics for a single logical APN.
- Contents** <default-apn-invalid>—Count of create requests that attempted to use a nonexistent default APN.
- <default-apn-selected>—Count of create requests that used the default APN.
- <name>—No documentation is available yet.
- <pdp-attempted-activation>—Number of attempted PDP activations.
- <pdp-blocked>—Number of PDP context creates denied due to administrative block.
- <username-based-apn-invalid>—Count of create requests using username-based APN selection that had a nonselectable APN name.
- <username-based-apn-selected>—Count of create requests that used username-based APN selection.

<logical-apn-statistics-information>

Usage	<pre> <rpc-reply> <logical-apn-statistics-information> <logical-apn-statistics>...</logical-apn-statistics> </logical-apn-statistics-information> </rpc-reply> </pre>
Description	Logical APN statistics for the GGSN.
Contents	<logical-apn-statistics>—Statistics for a single logical APN.

<mobile-user>

Usage	<pre> <mobile-user-information pdp-context-deletion-results> <mobile-user> <imsi>imsi</imsi> <msisdn>msisdn</msisdn> <pdp-context-information>...</pdp-context-information> </mobile-user> </mobile-user-information pdp-context-deletion-results> </pre>
Description	Information about a mobile user.
Contents	<p><imsi>—International Mobile Subscriber Identity for user.</p> <p><msisdn>—Mobile Station Integrated Services Digital Network number for user.</p> <p><pdp-context-information>—List of PDP contexts associated with the user.</p>

<mobile-user-information>

Usage	<pre> <rpc-reply> <mobile-user-information> <mobile-user>...</mobile-user> </mobile-user-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<mobile-user>—Information about a mobile user.

<node-action-results>

Usage	<pre> <rpc-reply> <node-action-results> <node-action>node-action</node-action> </node-action-results> </rpc-reply> </pre>
Description	Results of a GGSN node action command.
Contents	<node-action>—Actions performed on the GGSN node.

<node-alive-request-statistics>

Usage	<pre> <gtp-prime-statistics> <node-alive-request-statistics> <request-received>request-received</request-received> <request-transmitted>request-transmitted</request-transmitted> <response-received>response-received</response-received> <response-transmitted>response-transmitted</response-transmitted> </node-alive-request-statistics> </gtp-prime-statistics> </pre>
Description	GTP Prime node alive request statistics.
Contents	<pre> <request-received>—Requests received. <request-transmitted>—Requests sent. <response-received>—Responses received. <response-transmitted>—Responses sent. </pre>

<nsapi-information>

Usage	<pre> <call-trace> <nsapi-information> <nsapi>nsapi</nsapi> </nsapi-information> </call-trace> </pre>
Description	List of NSAPIs associated with user.
Contents	<pre> <nsapi>—Network Service Access Point Identifier for user. </pre>

<outgoing>

Usage	<pre> <signalling> <outgoing> <packets>packets</packets> <bytes>bytes</bytes> </outgoing> </signalling> </pre>
Description	No documentation is available yet.
Contents	<pre> <bytes>—Count of bytes. <packets>—Count of packets. </pre>

<packet-filter>

Usage <packet-filter-information>
 <packet-filter>
 <evaluation-precedence>*evaluation-precedence*</evaluation-precedence>
 <source-address>*source-address*</source-address>
 <source-mask>*source-mask*</source-mask>
 <source-port-range>*source-port-range*</source-port-range>
 <destination-port-range>*destination-port-range*
 </destination-port-range>
 <diffserv-code-point>*diffserv-code-point*</diffserv-code-point>
 <flow-label>*flow-label*</flow-label>
 <spi>*spi*</spi>
 <protocol>*protocol*</protocol>
 </packet-filter>
 </packet-filter-information>

Description No documentation is available yet.

Contents <destination-port-range>—Destination port range.

<diffserv-code-point>—No documentation is available yet.

<evaluation-precedence>—Evaluation precedence for PDP context packets.

<flow-label>—No documentation is available yet.

<protocol>—Protocol for this filter.

<source-address>—No documentation is available yet.

<source-mask>—No documentation is available yet.

<source-port-range>—Source port range.

<spi>—IPSec security parameters index.

<packet-filter-information>

Usage <traffic-flow-template>
 <packet-filter-information>
 <packet-filter>...</packet-filter>
 </packet-filter-information>
 </traffic-flow-template>

Description Filters for this TFT.

Contents <packet-filter>—No documentation is available yet.

<pdp>

Usage	<pre> <ggsn-interface> <pdp> <pdp-state>pdp-state</pdp-state> <pdp-assigned>pdp-assigned</pdp-assigned> <pdp-capacity>pdp-capacity</pdp-capacity> </pdp> </ggsn-interface> </pre>
Description	PDP context information.
Contents	<p><pdp-assigned>—PDP contexts assigned to a PIC.</p> <p><pdp-capacity>—Maximum number of active PDP contexts that a PIC can service.</p> <p><pdp-state>—PDP service state for the PIC.</p>

<pdp-context>

Usage	<pre> <pdp-context-information> <pdp-context> <nsapi>nsapi</nsapi> <nsapi-linked>nsapi-linked</nsapi-linked> <apn-name>apn-name</apn-name> <sgsn-address>sgsn-address</sgsn-address> <address>address</address> <charging-identifier>charging-identifier</charging-identifier> <quality-of-service>...</quality-of-service> <traffic-flow-template-information>...</traffic-flow-template-information> </pdp-context> </pdp-context-information> </pre>
Description	Information relating to an MT/MS PDP context.
Contents	<p><address>—No documentation is available yet.</p> <p><apn-name>—APN for this context.</p> <p><charging-identifier>—Charging identifier associated with the user.</p> <p><nsapi>—Network Service Access Point Identifier for user.</p> <p><nsapi-linked>—NSAPI of associated primary context.</p> <p><quality-of-service>—PDP context quality-of-service information.</p> <p><sgsn-address>—SGSN for this context.</p> <p><traffic-flow-template-information>—Traffic flow templates (TFTs).</p>

<pdp-context-deletion-results>

Usage <rpc-reply>
 <pdp-context-deletion-results>
 <mobile-user>...</mobile-user>
 </pdp-context-deletion-results>
 </rpc-reply>

Description Results for a single PDP context deletion command.

Contents <mobile-user>—Information about a mobile user.

<pdp-context-information>

Usage <mobile-user>
 <pdp-context-information>
 <pdp-context>...</pdp-context>
 </pdp-context-information>
 </mobile-user>

Description List of PDP contexts associated with the user.

Contents <pdp-context>—Information relating to an MT/MS PDP context.

<pdp-context-statistics>

Usage <ggsn-statistics | interface-pdp-context-statistics | apn-statistics | sgsn-statistics>

<pdp-context-statistics>

- <pdp-active>*pdp-active*</pdp-active>
- <pdp-active-conversational>*pdp-active-conversational*
</pdp-active-conversational>
- <pdp-active-streaming>*pdp-active-streaming*</pdp-active-streaming>
- <pdp-active-interactive>*pdp-active-interactive*</pdp-active-interactive>
- <pdp-active-background>*pdp-active-background*</pdp-active-background>
- <pdp-active-ipv6>*pdp-active-ipv6*</pdp-active-ipv6>
- <pdp-active-imsi>*pdp-active-imsi*</pdp-active-imsi>
- <pdp-active-msisdn>*pdp-active-msisdn*</pdp-active-msisdn>
- <pdp-blocked>*pdp-blocked*</pdp-blocked>
- <pdp-apn-by-logical-apn-selection>*pdp-apn-by-logical-apn-selection*
</pdp-apn-by-logical-apn-selection>
- <pdp-apn-by-logical-apn-default>*pdp-apn-by-logical-apn-default*
</pdp-apn-by-logical-apn-default>
- <pdp-assigned-msisdn>*pdp-assigned-msisdn*</pdp-assigned-msisdn>
- <pdp-assigned-shared-msisdn>*pdp-assigned-shared-msisdn*
</pdp-assigned-shared-msisdn>
- <pdp-attempted-activation>*pdp-attempted-activation*</pdp-attempted-activation>
- <pdp-attempted-activation-ipv6>*pdp-attempted-activation-ipv6*
</pdp-attempted-activation-ipv6>
- <pdp-completed-activation>*pdp-completed-activation*</pdp-completed-activation>
- <pdp-completed-activation-ipv6>*pdp-completed-activation-ipv6*
</pdp-completed-activation-ipv6>
- <pdp-attempted-activation-dhcp>*pdp-attempted-activation-dhcp*
</pdp-attempted-activation-dhcp>
- <pdp-completed-activation-dhcp>*pdp-completed-activation-dhcp*
</pdp-completed-activation-dhcp>
- <pdp-attempted-activation-radius>*pdp-attempted-activation-radius*
</pdp-attempted-activation-radius>
- <pdp-completed-activation-radius>*pdp-completed-activation-radius*
</pdp-completed-activation-radius>
- <pdp-attempted-activation-local-pool>*pdp-attempted-activation-local-pool*
</pdp-attempted-activation-local-pool>
- <pdp-completed-activation-local-pool>*pdp-completed-activation-local-pool*
</pdp-completed-activation-local-pool>
- <pdp-attempted-activation-dynamic>*pdp-attempted-activation-dynamic*
</pdp-attempted-activation-dynamic>
- <pdp-completed-activation-dynamic>*pdp-completed-activation-dynamic*
</pdp-completed-activation-dynamic>
- <pdp-attempted-mobile-activation>*pdp-attempted-mobile-activation*
</pdp-attempted-mobile-activation>
- <pdp-completed-mobile-activation>*pdp-completed-mobile-activation*
</pdp-completed-mobile-activation>
- <pdp-attempted-deactivation>*pdp-attempted-deactivation*
</pdp-attempted-deactivation>
- <pdp-completed-deactivation>*pdp-completed-deactivation*
</pdp-completed-deactivation>
- <pdp-attempted-node-deactivation>*pdp-attempted-node-deactivation*
</pdp-attempted-node-deactivation>
- <pdp-completed-node-deactivation>*pdp-completed-node-deactivation*

```

        </pdp-completed-node-deactivation>
    <pdp-completed-idle-deactivation>pdp-completed-idle-deactivation
        </pdp-completed-idle-deactivation>
    <pdp-completed-session-deactivation>pdp-completed-session-deactivation
        </pdp-completed-session-deactivation>
    <pdp-attempted-mobile-deactivation>pdp-attempted-mobile-deactivation
        </pdp-attempted-mobile-deactivation>
    <pdp-completed-mobile-deactivation>pdp-completed-mobile-deactivation
        </pdp-completed-mobile-deactivation>
    <pdp-attempted-authentication-activation>pdp-attempted-authentication-activation
        </pdp-attempted-authentication-activation>
    <pdp-completed-authentication-activation>pdp-completed-authentication-activation
        </pdp-completed-authentication-activation>
    <pdp-attempted-mobile-sgsn-update>pdp-attempted-mobile-sgsn-update
        </pdp-attempted-mobile-sgsn-update>
    <pdp-completed-mobile-sgsn-update>pdp-completed-mobile-sgsn-update
        </pdp-completed-mobile-sgsn-update>
    <pdp-created>pdp-created</pdp-created>
    <pdp-created-ipv6>pdp-created-ipv6</pdp-created-ipv6>
    <pdp-create-failed>pdp-create-failed</pdp-create-failed>
    <pdp-create-failed-ipv6>pdp-create-failed-ipv6</pdp-create-failed-ipv6>
    <pdp-secondary-created>pdp-secondary-created</pdp-secondary-created>
    <pdp-secondary-created-ipv6>pdp-secondary-created-ipv6
        </pdp-secondary-created-ipv6>
    <pdp-secondary-create-failed>pdp-secondary-create-failed
        </pdp-secondary-create-failed>
    <pdp-secondary-attempted-ipv6>pdp-secondary-attempted-ipv6
        </pdp-secondary-attempted-ipv6>
    <pdp-secondary-completed-ipv6>pdp-secondary-completed-ipv6
        </pdp-secondary-completed-ipv6>
    <pdp-last-create>pdp-last-create</pdp-last-create>
    <pdp-secondary-create-failed-ipv6>pdp-secondary-create-failed-ipv6
        </pdp-secondary-create-failed-ipv6>
    <pdp-updates>pdp-updates</pdp-updates>
    <pdp-update-failed>pdp-update-failed</pdp-update-failed>
    <pdp-deleted>pdp-deleted</pdp-deleted>
    <pdp-deleted-by-idle-supervision>pdp-deleted-by-idle-supervision
        </pdp-deleted-by-idle-supervision>
    <pdp-deleted-by-session-supervision>pdp-deleted-by-session-supervision
        </pdp-deleted-by-session-supervision>
    <pdp-deleted-by-command>pdp-deleted-by-command</pdp-deleted-by-command>
    <pdp-deleted-by-failure>pdp-deleted-by-failure</pdp-deleted-by-failure>
    <pdp-delete-failed>pdp-delete-failed</pdp-delete-failed>
    <pdp-last-delete>pdp-last-delete</pdp-last-delete>
    <pdp-successful-deactivations>pdp-successful-deactivations
        </pdp-successful-deactivations>
    <pdp-failed-deactivations>pdp-failed-deactivations</pdp-failed-deactivations>
    <pdp-maximum>pdp-maximum</pdp-maximum>
    <pdp-minimum>pdp-minimum</pdp-minimum>
    <pdp-mean>pdp-mean</pdp-mean>
    <pdp-active-l2tp-tunnels>pdp-active-l2tp-tunnels</pdp-active-l2tp-tunnels>
    <pdp-active-l2tp-sessions>pdp-active-l2tp-sessions</pdp-active-l2tp-sessions>
    <pdp-maximum-active-l2tp-tunnels>pdp-maximum-active-l2tp-tunnels
        </pdp-maximum-active-l2tp-tunnels>

```

```

<pdp-maximum-active-l2tp-sessions>pdp-maximum-active-l2tp-sessions
</pdp-maximum-active-l2tp-sessions>
<ims-dedicated-completed-activation>ims-dedicated-completed-activation
</ims-dedicated-completed-activation>
<ims-dedicated-failed-activation>ims-dedicated-failed-activation
</ims-dedicated-failed-activation>
<ims-general-completed-activation>ims-general-completed-activation
</ims-general-completed-activation>
<ims-general-failed-activation>ims-general-failed-activation
</ims-general-failed-activation>
<ims-general-active-failed-activation>ims-general-active-failed-activation
</ims-general-active-failed-activation>
<ims-signalling-packets-drops>ims-signalling-packets-drops
</ims-signalling-packets-drops>
</pdp-context-statistics>
</ggsn-statistics | interface-pdp-context-statistics | apn-statistics | sgsn-statistics>

```

Description Information about PDP context events.

Contents <ims-dedicated-completed-activation>—Successful dedicated signaling PDP ctx activations.

<ims-dedicated-failed-activation>—Failed dedicated signaling PDP ctx activations, APN OFF.

<ims-general-active-failed-activation>—Failed general purpose PDP ctx, normal ctx is created.

<ims-general-completed-activation>—Successful general purpose PDP ctx activations.

<ims-general-failed-activation>—Failed general purpose PDP ctx activations, APN OFF.

<ims-signalling-packets-drops>—Dropped unauthorized IMS signaling packets.

<pdp-active>—Number of active PDP contexts.

<pdp-active-background>—Active contexts, traffic class background.

<pdp-active-conversational>—Active contexts, traffic class conversational.

<pdp-active-imsi>—Number of active IMSIs.

<pdp-active-interactive>—Active contexts, traffic class interactive.

<pdp-active-ipv6>—Number of active IPv6 PDP contexts.

<pdp-active-l2tp-sessions>—Number of active L2TP sessions.

<pdp-active-l2tp-tunnels>—Number of active L2TP tunnels.

<pdp-active-msisdns>—Number of active MSISDNs.

<pdp-active-streaming>—Active contexts, traffic class streaming.

<pdp-apn-by-logical-apn-default>—Number of times this APN was the result of a logical APN default selection.

<pdp-apn-by-logical-apn-selection>—Number of times this APN was the result of a logical APN user selection.

<pdp-assigned-msisdn>—Number of assigned MSISDNs.

<pdp-assigned-shared-msisdn>—Number of assigned shared MSISDNs.

<pdp-attempted-activation>—Number of attempted PDP activations.

<pdp-attempted-activation-dhcp>—Number of attempted PDP activations with DHCP address.

<pdp-attempted-activation-dynamic>—Number of attempted PDP activations with dynamic address.

<pdp-attempted-activation-ipv6>—Number of attempted IPv6 PDP activations.

<pdp-attempted-activation-local-pool>—Number of attempted PDP activations with local pool address.

<pdp-attempted-activation-radius>—Number of attempted PDP activations with RADIUS address.

<pdp-attempted-authentication-activation>—Number of PDP context activations attempted with user authentication required.

<pdp-attempted-deactivation>—Number of attempted PDP context deactivations.

<pdp-attempted-mobile-activation>—Number of mobile-station-initiated PDP context activations attempted.

<pdp-attempted-mobile-deactivation>—Number of mobile-station-initiated PDP context deactivations attempted.

<pdp-attempted-mobile-sgsn-update>—Number of mobile station or SGSN initiated PDP context updates attempted.

<pdp-attempted-node-deactivation>—Number of GGSN-initiated PDP context deactivations attempted.

<pdp-blocked>—Number of PDP context creates denied due to administrative block.

<pdp-completed-activation>—Number of successfully completed PDP activations.

<pdp-completed-activation-dhcp>—Number of completed PDP activations with DHCP address.

<pdp-completed-activation-dynamic>—Number of completed PDP activations with dynamic address.

- <pdp-completed-activation-ipv6>—Number of successfully completed IPv6 PDP activations.
- <pdp-completed-activation-local-pool>—Number of completed PDP activations with local pool address.
- <pdp-completed-activation-radius>—Number of completed PDP activations with RADIUS address.
- <pdp-completed-authentication-activation>—Number of PDP context activations completed with user authentication required.
- <pdp-completed-deactivation>—Number of completed PDP context deactivations.
- <pdp-completed-idle-deactivation>—Number of PDP context deactivations completed due to idle timeout.
- <pdp-completed-mobile-activation>—Number of mobile-station-initiated PDP context activations completed.
- <pdp-completed-mobile-deactivation>—Number of mobile-station-initiated PDP context deactivations completed.
- <pdp-completed-mobile-sgsn-update>—Number of mobile station or SGSN initiated PDP context updates completed.
- <pdp-completed-node-deactivation>—Number of GGSN-initiated PDP context deactivations completed.
- <pdp-completed-session-deactivation>—Number of PDP context deactivations completed due to session timeout.
- <pdp-create-failed>—Total number of PDP context creation failures.
- <pdp-create-failed-ipv6>—Total number of IPv6 PDP context creation failures.
- <pdp-created>—Total number of PDP contexts successfully created.
- <pdp-created-ipv6>—Total number of IPv6 PDP contexts successfully created.
- <pdp-delete-failed>—Total number of failed requests for deletion of a PDP context.
- <pdp-deleted>—Total number of PDP contexts deleted.
- <pdp-deleted-by-command>—PDP delete requests initiated by a node administrator.
- <pdp-deleted-by-failure>—PDP deletions due to system or path failure.
- <pdp-deleted-by-idle-supervision>—PDP delete requests initiated by the idle supervision function.
- <pdp-deleted-by-session-supervision>—PDP delete requests initiated by the session supervision function.
- <pdp-failed-deactivations>—Count of failed PDP context deactivations.

<pdp-last-create>—Time when the last PDP context was created.

<pdp-last-delete>—Time when the last PDP context was deleted.

<pdp-maximum>—Maximum PDP contexts for measured period.

<pdp-maximum-active-l2tp-sessions>—Maximum number of active L2TP sessions since restart.

<pdp-maximum-active-l2tp-tunnels>—Maximum number of active L2TP tunnels since restart.

<pdp-mean>—Average number of PDP contexts for measured period.

<pdp-minimum>—Minimum PDP contexts for measured period.

<pdp-secondary-attempted-ipv6>—Total number of attempted IPv6 secondary PDP context activations.

<pdp-secondary-completed-ipv6>—Total number of successful IPv6 secondary PDP context activations.

<pdp-secondary-create-failed>—Total number of secondary PDP context creation failures.

<pdp-secondary-create-failed-ipv6>—Total number of IPv6 secondary PDP context creation failures.

<pdp-secondary-created>—Total number of secondary PDP contexts successfully created.

<pdp-secondary-created-ipv6>—Total number of IPv6 secondary PDP contexts successfully created.

<pdp-successful-deactivations>—Count of successfully deactivated PDP contexts.

<pdp-update-failed>—Total number of failed PDP context updates.

<pdp-updates>—Total number of successful PDP context updates.

<pdp-diagnostics-per-apn>

Usage <rpc-reply>
 <pdp-diagnostics-per-apn>
 <pdp-id>*pdp-id*</pdp-id>
 </pdp-diagnostics-per-apn>
 </rpc-reply>

Description No documentation is available yet.

Contents <pdp-id>—PDP id.

<pdp-request-statistics>

Usage <gtp-statistics>
 <pdp-request-statistics>
 <create-request-received>*create-request-received*</create-request-received>
 <create-response-transmitted>*create-response-transmitted*
 </create-response-transmitted>
 <update-request-received>*update-request-received*</update-request-received>
 <update-request-transmitted>*update-request-transmitted*
 </update-request-transmitted>
 <update-response-received>*update-resp-received*</update-response-received>
 <update-response-transmitted>*update-response-transmitted*
 </update-response-transmitted>
 <delete-request-received>*delete-request-received*</delete-request-received>
 <delete-request-transmitted>*delete-request-transmitted*
 </delete-request-transmitted>
 <delete-response-received>*delete-response-received*</delete-response-received>
 <delete-response-transmitted>*delete-response-transmitted*
 </delete-response-transmitted>
 </pdp-request-statistics>
 </gtp-statistics>

Description PDP context request statistics.

Contents <create-request-received>—GTP PDP create requests received.
 <create-response-transmitted>—GTP PDP create responses sent.
 <delete-request-received>—GTP PDP delete requests received.
 <delete-request-transmitted>—GTP PDP delete requests sent.
 <delete-response-received>—GTP PDP delete responses received.
 <delete-response-transmitted>—GTP PDP delete responses sent.
 <update-request-received>—GTP PDP update requests received.
 <update-request-transmitted>—GTP PDP update requests sent.
 <update-response-received>—GTP PDP update responses received.
 <update-response-transmitted>—GTP PDP update responses sent.

<pras-information>

Usage <sbcc-statistics-information>
 <pras-information>
 <pras-statistics>...</pras-statistics>
 </pras-information>
 </sbcc-statistics-information>

Description Information about policy rating application systems.

Contents <pras-statistics>—Statistics for a policy rating application system.

<pras-statistics>

Usage <pras-information>
 <pras-statistics>
 <pras-identifier>*pras-identifier*</pras-identifier>
 <pras-start-request>*pras-start-request*</pras-start-request>
 <pras-start-request-failed>*pras-start-request-failed*
 </pras-start-request-failed>
 <pras-update-request>*pras-update-request*</pras-update-request>
 <pras-update-request-failed>*pras-update-request-failed*
 </pras-update-request-failed>
 <pras-stop-request>*pras-stop-request*</pras-stop-request>
 <pras-stop-request-failed>*pras-stop-request-failed*</pras-stop-request-failed>
 <pras-user-service-denied>*pras-user-service-denied*</pras-user-service-denied>
 <pras-user-unknown>*pras-user-unknown*</pras-user-unknown>
 </pras-statistics>
 </pras-information>

Description Statistics for a policy rating application system.

Contents <pras-identifier>—Policy rating application system identifier.

<pras-start-request>—PR-AS start requests.

<pras-start-request-failed>—PR-AS start requests failed.

<pras-stop-request>—PR-AS stop requests.

<pras-stop-request-failed>—PR-AS stop requests failed.

<pras-update-request>—PR-AS update requests.

<pras-update-request-failed>—PR-AS update requests failed.

<pras-user-service-denied>—PR-AS requests failed with user service denied.

<pras-user-unknown>—PR-AS requests failed with user unknown.

<quality-of-service>

Usage <pdp-context>
 <quality-of-service>
 <gi-diffserv-code-point>*gi-diffserv-code-point*</gi-diffserv-code-point>
 <gn-diffserv-code-point>*gn-diffserv-code-point*</gn-diffserv-code-point>
 <downlink-bitrate>*downlink-bitrate*</downlink-bitrate>
 </quality-of-service>
 </pdp-context>

Description PDP context quality-of-service information.

Contents <downlink-bitrate>—Downlink bit rate.

<gi-diffserv-code-point>—Gi DiffServ class.

<gn-diffserv-code-point>—Gn DiffServ class.

<radius-statistics-information>

Usage	<ggsn-statistics apn-statistics> <radius-statistics-information> <radius-authentication-failure> <i>radius-authentication-failure</i> </radius-authentication-failure> <accounting-failure> <i>accounting-failure</i> </accounting-failure> </radius-statistics-information> </ggsn-statistics apn-statistics>
Description	Radius statistics.
Contents	<accounting-failure>—Number of failed RADIUS Accounting procedures. <radius-authentication-failure>—Number of failed RADIUS Authentication procedures.

<rate-group-information>

Usage	<sbcc-statistics-information> <rate-group-information> <rate-group-statistics>...</rate-group-statistics> </rate-group-information> </sbcc-statistics-information>
Description	Information about a rate group.
Contents	<rate-group-statistics>—Statistics for a rate group.

<rate-group-statistics>

Usage	<rate-group-information> <rate-group-statistics> <rate-group-identifier> <i>rate-group-identifier</i> </rate-group-identifier> <transactions-start> <i>transactions-start</i> </transactions-start> <transactions-success> <i>transactions-success</i> </transactions-success> </rate-group-statistics> </rate-group-information>
Description	Statistics for a rate group.
Contents	<rate-group-identifier>—Rate group identifier. <transactions-start>—Start transaction events. <transactions-success>—Successful transaction events.

<redirection-request-statistics>

Usage <gtp-prime-statistics>
 <redirection-request-statistics>
 <request-received>*request-received*</request-received>
 <request-transmitted>*request-transmitted*</request-transmitted>
 <response-received>*response-received*</response-received>
 <response-transmitted>*response-transmitted*</response-transmitted>
 </redirection-request-statistics>
 </gtp-prime-statistics>

Description GTP Prime redirection request statistics.

Contents <request-received>—Requests received.
 <request-transmitted>—Requests sent.
 <response-received>—Responses received.
 <response-transmitted>—Responses sent.

<resources>

Usage <ggsn-interface>
 <resources>
 <cpu-info>...</cpu-info>
 <memory-total>*memory-total*</memory-total>
 <memory-used>*memory-used*</memory-used>
 </resources>
 </ggsn-interface>

Description CPU and memory information for a PIC.

Contents <cpu-info>—CPU usage.
 <memory-total>—DRAM size (megabytes).
 <memory-used>—DRAM used (megabytes).

<rs-statistics>

Usage	<pre> <rulespace-based-charging-statistics> <rs-statistics> <rs-identifier>rs-identifier</rs-identifier> <uplink-statistics>uplink-statistics</uplink-statistics> <downlink-statistics>downlink-statistics</downlink-statistics> <service-instances>service-instances</service-instances> <discarded-uplink>discarded-uplink</discarded-uplink> <discarded-downlink>discarded-downlink</discarded-downlink> <gate-discarded-uplink>gate-discarded-uplink</gate-discarded-uplink> <gate-discarded-downlink>gate-discarded-downlink</gate-discarded-downlink> </rs-statistics> </rulespace-based-charging-statistics> </pre>
Description	Statistics for a rule space.
Contents	<p><discarded-downlink>—Discarded downlink packets due to authorization based on policy and credit control.</p> <p><discarded-uplink>—Discarded uplink packets due to authorization based on policy and credit control.</p> <p><downlink-statistics>—Downlink bytes identified per APN and rule space.</p> <p><gate-discarded-downlink>—Discarded downlink packets due to closed gate.</p> <p><gate-discarded-uplink>—Discarded uplink packets due to closed gate.</p> <p><rs-identifier>—Rule space identifier.</p> <p><service-instances>—Service instances identified per APN and rule space.</p> <p><uplink-statistics>—Uplink bytes identified per APN and rule space.</p>

<rulespace-based-charging-statistics>

Usage	<pre> <apn-statistics> <rulespace-based-charging-statistics> <rs-statistics>...</rs-statistics> </rulespace-based-charging-statistics> </apn-statistics> </pre>
Description	Information about rule spaces.
Contents	<rs-statistics>—Statistics for a rule space.

<sbcc-statistics-information>

Usage <ggsn-interface | ggsn-statistics | apn-statistics-information>

<sbcc-statistics-information>

```

<prepaid-request>prepaid-request</prepaid-request>
<rating-request>rating-request</rating-request>
<prepaid-user>prepaid-user</prepaid-user>
<prepaid-context>prepaid-context</prepaid-context>
<prepaid-pdp-creates-attempted>prepaid-pdp-creates-attempted
  </prepaid-pdp-creates-attempted>
<prepaid-pdp-creates-failed>prepaid-pdp-creates-failed
  </prepaid-pdp-creates-failed>
<pdp-initiated-deactivation>pdp-initiated-deactivation
  </pdp-initiated-deactivation>
<credit-start-request-attempted>credit-start-request-attempted
  </credit-start-request-attempted>
<credit-start-request-failed>credit-start-request-failed
  </credit-start-request-failed>
<rating-initial-request-attempted>rating-initial-request-attempted
  </rating-initial-request-attempted>
<rating-initial-request-failed>rating-initial-request-failed
  </rating-initial-request-failed>
<rating-update-request-attempted>rating-update-request-attempted
  </rating-update-request-attempted>
<rating-update-request-failed>rating-update-request-failed
  </rating-update-request-failed>
<credit-update-request-attempted>credit-update-request-attempted
  </credit-update-request-attempted>
<credit-update-request-failed>credit-update-request-failed
  </credit-update-request-failed>
<credit-stop-request-attempted>credit-stop-request-attempted
  </credit-stop-request-attempted>
<credit-stop-request-failed>credit-stop-request-failed
  </credit-stop-request-failed>
<external-prs-update>external-prs-update</external-prs-update>
<external-prs-update-no-match>external-prs-update-no-match
  </external-prs-update-no-match>
<external-credit-update>external-credit-update</external-credit-update>
<external-credit-update-no-match>external-credit-update-no-match
  </external-credit-update-no-match>
<external-update-failed>external-update-failed</external-update-failed>
<duration-time>duration-time</duration-time>
<activation-bearer-ctrl-accept>activation-bearer-ctrl-accept
  </activation-bearer-ctrl-accept>
<activation-bearer-ctrl-reject>activation-bearer-ctrl-reject
  </activation-bearer-ctrl-reject>
<activation-bearer-ctrl-upgrade>activation-bearer-ctrl-upgrade
  </activation-bearer-ctrl-upgrade>
<activation-bearer-ctrl-downgrade>activation-bearer-ctrl-downgrade
  </activation-bearer-ctrl-downgrade>
<modification-bearer-ctrl-accept>modification-bearer-ctrl-accept
  </modification-bearer-ctrl-accept>
<modification-bearer-ctrl-deactivate>modification-bearer-ctrl-deactivate
  </modification-bearer-ctrl-deactivate>

```

```

<modification-bearer-ctrl-upgrade>modification-bearer-ctrl-upgrade
  </modification-bearer-ctrl-upgrade>
<modification-bearer-ctrl-downgrade>modification-bearer-ctrl-downgrade
  </modification-bearer-ctrl-downgrade>
<activation-no-bearer-ctrl-accept>activation-no-bearer-ctrl-accept
  </activation-no-bearer-ctrl-accept>
<activation-no-bearer-ctrl-reject>activation-no-bearer-ctrl-reject
  </activation-no-bearer-ctrl-reject>
<activation-no-bearer-ctrl-downgrade>activation-no-bearer-ctrl-downgrade
  </activation-no-bearer-ctrl-downgrade>
<modification-no-bearer-ctrl-accept>modification-no-bearer-ctrl-accept
  </modification-no-bearer-ctrl-accept>
<modification-no-bearer-ctrl-deactivate>modification-no-bearer-ctrl-deactivate
  </modification-no-bearer-ctrl-deactivate>
<modification-no-bearer-ctrl-downgrade>modification-no-bearer-ctrl-downgrade
  </modification-no-bearer-ctrl-downgrade>
<das-information>...</das-information>
<pras-information>...</pras-information>
<ccas-information>...</ccas-information>
<service-class-information>...</service-class-information>
<service-identifier-information>service-identifier-information
  </service-identifier-information>
<rate-group-information>...</rate-group-information>
<authorization-discard-information>...</authorization-discard-information>
</sbcc-statistics-information>
</ggsn-interface | ggsn-statistics | apn-statistics-information>

```

Description Service-based charging statistics.

Contents

- <activation-bearer-ctrl-accept>—QoS accepts at activation, SGSN bearer ctrl.
- <activation-bearer-ctrl-downgrade>—QoS downgrades at activation, SGSN bearer ctrl.
- <activation-bearer-ctrl-reject>—PDP context rejects at activation, SGSN bearer ctrl.
- <activation-bearer-ctrl-upgrade>—QoS upgrades at activation, SGSN bearer ctrl.
- <activation-no-bearer-ctrl-accept>—QoS accepts at activation, no SGSN bearer ctrl.
- <activation-no-bearer-ctrl-downgrade>—QoS downgrades at activation, no SGSN bearer ctrl.
- <activation-no-bearer-ctrl-reject>—PDP context rejects at activation, no SGSN bearer ctrl.
- <authorization-discard-information>—No documentation is available yet.
- <ccas-information>—Information about credit control application systems.
- <credit-start-request-attempted>—Number of credit start requests attempted.
- <credit-start-request-failed>—Number of credit start requests failed.
- <credit-stop-request-attempted>—Number of credit stop requests attempted.

<credit-stop-request-failed>—Number of credit start requests failed.

<credit-update-request-attempted>—Number of credit update requests attempted.

<credit-update-request-failed>—Number of credit update requests failed.

<das-information>—Information about diameter application systems.

<duration-time>—Seconds measured for duration time.

<external-credit-update>—Number of externally initiated credit updates for users with prepaid service.

<external-credit-update-no-match>—Number of external credit updates for non-existing users or users not using prepaid service.

<external-prs-update>—Number of externally initiated URT updates for users using PRS.

<external-prs-update-no-match>—Number of external URT updates for non-existing users or users not using PRS.

<external-update-failed>—Number of failed external URT/credit updates.

<modification-bearer-ctrl-accept>—QoS accepts at modification, SGSN bearer ctrl.

<modification-bearer-ctrl-deactivate>—PDP ctx deactivates at modification, SGSN bearer ctrl.

<modification-bearer-ctrl-downgrade>—QoS downgrades at modification, SGSN bearer ctrl.

<modification-bearer-ctrl-upgrade>—QoS upgrades at modification, SGSN bearer ctrl.

<modification-no-bearer-ctrl-accept>—QoS accepts at modification, no SGSN bearer ctrl.

<modification-no-bearer-ctrl-deactivate>—PDP ctx deactivates at modification, no SGSN bearer ctrl.

<modification-no-bearer-ctrl-downgrade>—QoS downgrades at modification, no SGSN bearer ctrl.

<pdp-initiated-deactivation>—Number of PDP context deactivations initiated by service-based-charging.

<pras-information>—Information about policy rating application systems.

<prepaid-context>—Number of prepaid contexts.

<prepaid-pdp-creates-attempted>—Number of prepaid PDP context creates attempted.

<prepaid-pdp-creates-failed>—Number of prepaid PDP context create attempts that failed.

<prepaid-request>—Number of application transaction towards prepaid server.

<prepaid-user>—Number of prepaid users.

<rate-group-information>—Information about a rate group.

<rating-initial-request-attempted>—Number of initial rating requests attempted.

<rating-initial-request-failed>—Number of initial rating requests failed.

<rating-request>—Number of application transaction towards policy/rate server.

<rating-update-request-attempted>—Number of attempted rating update requests.

<rating-update-request-failed>—Number of failed rating update requests.

<service-class-information>—Information about a service class.

<service-identifier-information>—No documentation is available yet.

<service-based-charging-for-gx>

Usage <apn-statistics-information>
 <service-based-charging-for-gx>
 <ccr-statistics>...</ccr-statistics>
 <dynamic-charging-rules>*dynamic-charging-rules*</dynamic-charging-rules>
 <active-predifened-charging-rules>*active-predifened-charging-rules*
 </active-predifened-charging-rules>
 <active-predifened-charging-rulbases>*active-predifened-charging-rulbases*
 </active-predifened-charging-rulbases>
 </service-based-charging-for-gx>
 </apn-statistics-information>

Description Service-base charging statistics for the gx interface.

Contents <active-predifened-charging-rulbases>—Active predefined charging rule bases per APN.

<active-predifened-charging-rules>—Active predefined charging rules per APN.

<ccr-statistics>—Statistics for a credit control application system.

<dynamic-charging-rules>—Simultaneously installed dynamic charging rules.

<service-class-information>

- Usage** `<sbcc-statistics-information>
 <service-class-information>
 <service-class-statistics>...</service-class-statistics>
 </service-class-information>
</sbcc-statistics-information>`
- Description** Information about a service class.
- Contents** `<service-class-statistics>`—Statistics for a service class.

<service-class-statistics>

- Usage** `<service-class-information>
 <service-class-statistics>
 <service-class-identifier>service-class-identifier</service-class-identifier>
 <uplink-bytes>uplink-bytes</uplink-bytes>
 <downlink-bytes>downlink-bytes</downlink-bytes>
 <active-time>active-time</active-time>
 </service-class-statistics>
</service-class-information>`
- Description** Statistics for a service class.
- Contents** `<active-time>`—Seconds measured for active time for service class.
- `<downlink-bytes>`—Bytes in the downlink direction.
- `<service-class-identifier>`—Service class identifier.
- `<uplink-bytes>`—Bytes in the uplink direction.

<service-id-information>

- Usage** `<rpc-reply>
 <service-id-information>
 <service-id-statistics>...</service-id-statistics>
 </service-id-information>
</rpc-reply>`
- Description** Information about a service ID.
- Contents** `<service-id-statistics>`—Statistics for a service ID.

<service-id-statistics>

Usage <service-id-information>
 <service-id-statistics>
 <service-id-identifier>service-id-identifier</service-id-identifier>
 <uplink-bytes>uplink-bytes</uplink-bytes>
 <downlink-bytes>downlink-bytes</downlink-bytes>
 <transactions-charged>transactions-charged</transactions-charged>
 <transactions-failed>transactions-failed</transactions-failed>
 <transactions-start>transactions-start</transactions-start>
 <transactions-success>transactions-success</transactions-success>
 </service-id-statistics>
 </service-id-information>

Description Statistics for a service ID.

Contents <downlink-bytes>—Bytes in the downlink direction.

<service-id-identifier>—Service ID.

<transactions-charged>—Transactions for which event charging applies.

<transactions-failed>—Failed transactions.

<transactions-start>—Start transaction events.

<transactions-success>—Successful transaction events.

<uplink-bytes>—Bytes in the uplink direction.

<sgsn-statistics>

Usage <sgsn-statistics-information>
 <sgsn-statistics>
 <address>address</address>
 <pdp-context-statistics>...</pdp-context-statistics>
 <uplink>...</uplink>
 <downlink>...</downlink>
 <gtp-error-statistics>...</gtp-error-statistics>
 </sgsn-statistics>
 </sgsn-statistics-information>

Description Statistics information for an SGSN.

Contents <address>—No documentation is available yet.

<downlink>—Link traffic in the downlink direction.

<gtp-error-statistics>—GTP error statistics.

<pdp-context-statistics>—Information about PDP context events.

<uplink>—Link traffic in the uplink direction.

<sgsn-statistics-information>

Usage	<pre> <rpc-reply> <sgsn-statistics-information> <sgsn-statistics>...</sgsn-statistics> </sgsn-statistics-information> </rpc-reply> </pre>
Description	SGSN-level statistics for the GGSN service.
Contents	<sgsn-statistics>—Statistics information for an SGSN.

<signalling>

Usage	<pre> <apn-statistics> <signalling> <incoming>...</incoming> <outgoing>...</outgoing> </signalling> </apn-statistics> </pre>
Description	Signaling traffic.
Contents	<incoming>—No documentation is available yet. <outgoing>—No documentation is available yet.

<software-action-results>

Usage	<pre> <rpc-reply> <software-action-results> <software-action-message>software-action-message</software-action-message> </software-action-results> </rpc-reply> </pre>
Description	Results of a GGSN software software command.
Contents	<software-action-message>—Software action message.

<tft-statistics>

Usage	<pre> <ggsn-interface> <tft-statistics> <maximum-tft-filter-depth>maximum-tft-filter-depth</maximum-tft-filter-depth> <mean-tft-filter-depth>mean-tft-filter-depth</mean-tft-filter-depth> </tft-statistics> </ggsn-interface> </pre>
Description	No documentation is available yet.
Contents	<maximum-tft-filter-depth>—Maximum TFT filter depth per user in the last period. <mean-tft-filter-depth>—Mean TFT filter depth per user in the last period.

<traffic-flow-template>

- Usage** <traffic-flow-template-information>
 <traffic-flow-template>
 <packet-filter-information>...</packet-filter-information>
 </traffic-flow-template>
 </traffic-flow-template-information>
- Description** TFT information.
- Contents** <packet-filter-information>—Filters for this TFT.

<traffic-flow-template-information>

- Usage** <pdp-context>
 <traffic-flow-template-information>
 <traffic-flow-template>...</traffic-flow-template>
 </traffic-flow-template-information>
 </pdp-context>
- Description** Traffic flow templates (TFTs).
- Contents** <traffic-flow-template>—TFT information.

<uplink>

Usage <ggsn-statistics | apn-statistics | sgsn-statistics>
<uplink>
 <packets>packets</packets>
 <packets-ipv6>packets-ipv6</packets-ipv6>
 <bytes>bytes</bytes>
 <bytes-ipv6>bytes-ipv6</bytes-ipv6>
 <dropped-packets>dropped-packets</dropped-packets>
 <dropped-packets-ipv6>dropped-packets-ipv6</dropped-packets-ipv6>
 <dropped-bytes>dropped-bytes</dropped-bytes>
 <dropped-bytes-ipv6>dropped-bytes-ipv6</dropped-bytes-ipv6>
</uplink>
 </ggsn-statistics | apn-statistics | sgsn-statistics>

Description Link traffic in the uplink direction.

Contents <bytes>—Count of bytes.

<bytes-ipv6>—Count of bytes for IPv6.

<dropped-bytes>—Count of packet dropped bytes.

<dropped-bytes-ipv6>—Count of packet dropped bytes for IPv6.

<dropped-packets>—Count of packet drops.

<dropped-packets-ipv6>—Count of packet drops for IPv6.

<packets>—Count of packets.

<packets-ipv6>—Count of packets for IPv6.

<user-category-line>

Usage <ggsn-pdp-per-user-category>
<user-category-line>
 <user-category>user-category</user-category>
 <pdp-active>pdp-active</pdp-active>
</user-category-line>
 </ggsn-pdp-per-user-category>

Description No documentation is available yet.

Contents <pdp-active>—Number of active PDP contexts.

<user-category>—User category.

<version-unsupported-statistics>

- Usage** <gtp-statistics | gtp-prime-statistics>
<version-unsupported-statistics>
 <version-unsupported-received>*version-unsupported-received*
 </version-unsupported-received>
 <version-unsupported-transmitted>*version-unsupported-transmitted*
 </version-unsupported-transmitted>
</version-unsupported-statistics>
 </gtp-statistics | gtp-prime-statistics>
- Description** Version unsupported message information.
- Contents** <version-unsupported-received>—Unsupported version messages received.
 <version-unsupported-transmitted>—Unsupported version messages sent.

<weighted-pdp-context-load>

- Usage** <ggsn-statistics>
<weighted-pdp-context-load>
 <weighted-pdp-context-load-in-control>*weighted-pdp-context-load-in-control*
 </weighted-pdp-context-load-in-control>
 <weighted-pdp-context-load-in-payload>*weighted-pdp-context-load-in-payload*
 </weighted-pdp-context-load-in-payload>
</weighted-pdp-context-load>
 </ggsn-statistics>
- Description** No documentation is available yet.
- Contents** <weighted-pdp-context-load-in-control>—No documentation is available yet.
 <weighted-pdp-context-load-in-payload>—No documentation is available yet.

Summary of LACP Response Tags

This section lists JUNOS XML tags that contain operational information about the Link Aggregation Control Protocol (LACP). The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-lacpd>. To review the DTD for the tags, see “DTD for LACP Response Tags” on page 1837.

<lacp-interface-information>

Usage	<pre> <lacp-interface-information-list> <lag-lacp-header>...</lag-lacp-header> <lag-lacp-info>...</lag-lacp-info> <lag-lacp-state>...</lag-lacp-state> <lag-lacp-protocol>...</lag-lacp-protocol> </lacp-interface-information-list> </pre>
Description	Information about an aggregated interface.
Contents	<p><lag-lacp-header>—LACP header.</p> <p><lag-lacp-info>—LACP information.</p> <p><lag-lacp-protocol>—LACP protocol information.</p> <p><lag-lacp-state>—LACP protocol state information.</p>

<lacp-interface-information-list>

Usage	<pre> <rpc-reply> <lacp-interface-information-list> <lacp-interface-information>...</lacp-interface-information> </lacp-interface-information-list> </rpc-reply> </pre>
Description	Information about one or more aggregated interfaces.
Contents	<lacp-interface-information>—Information about an aggregated interface.

<lag-lacp-header>

Usage	<pre> <lacp-interface-information> <lag-lacp-header> <aggregate-name>aggregate-name</aggregate-name> </lag-lacp-header> </lacp-interface-information> </pre>
Description	LACP header.
Contents	<aggregate-name>—Aggregated Interface name.

<lag-lacp-info>

Usage	<pre> <lacp-interface-information> <lag-lacp-info> <name>name</name> <lacp-role>lacp-role</lacp-role> <lacp-sys-priority>lacp-sys-priority</lacp-sys-priority> <lacp-system-id>lacp-system-id</lacp-system-id> <lacp-port-priority>lacp-port-priority</lacp-port-priority> <lacp-port-number>lacp-port-number</lacp-port-number> <lacp-port-key>lacp-port-key</lacp-port-key> </lag-lacp-info> </lacp-interface-information> </pre>
Description	LACP information.
Contents	<p><lacp-port-key>—Operational key of the port.</p> <p><lacp-port-number>—Port number.</p> <p><lacp-port-priority>—Priority of the port.</p> <p><lacp-role>—Whether it is an actor or partner.</p> <p><lacp-sys-priority>—System priority.</p> <p><lacp-system-id>—LACP system identifier.</p> <p><name>—Interface name.</p>

<lag-lacp-protocol>

Usage	<pre> <lacp-interface-information> <lag-lacp-protocol> <name>name</name> <lacp-receive-state>lacp-receive-state</lacp-receive-state> <lacp-transmit-state>lacp-transmit-state</lacp-transmit-state> <lacp-mux-state>lacp-mux-state</lacp-mux-state> </lag-lacp-protocol> </lacp-interface-information> </pre>
Description	LACP protocol information.
Contents	<p><lacp-mux-state>—State of the mux lacp machine.</p> <p><lacp-receive-state>—State of the receive lacp machine.</p> <p><lacp-transmit-state>—State of the transmit lacp machine.</p> <p><name>—Interface name.</p>

<lag-lacp-state>

Usage <lacp-interface-information>
 <lag-lacp-state>
 <name>*name*</name>
 <lacp-role>*lacp-role*</lacp-role>
 <lacp-expired>*lacp-expired*</lacp-expired>
 <lacp-defaulted>*lacp-defaulted*</lacp-defaulted>
 <lacp-distributing>*lacp-distributing*</lacp-distributing>
 <lacp-collecting>*lacp-collecting*</lacp-collecting>
 <lacp-synchronization>*lacp-synchronization*</lacp-synchronization>
 <lacp-aggregation>*lacp-aggregation*</lacp-aggregation>
 <lacp-timeout>*lacp-timeout*</lacp-timeout>
 <lacp-activity>*lacp-activity*</lacp-activity>
 </lag-lacp-state>
 </lacp-interface-information>

Description LACP protocol state information.

Contents <lacp-activity>—Configured as either active or passive.

<lacp-aggregation>—Actor view of partner information is in sync.

<lacp-collecting>—State of the mux lacp machine is COLLECTING?.

<lacp-defaulted>—State of the receive lacp machine is DEFAULTED?.

<lacp-distributing>—State of the mux lacp machine is DISTRIBUTING?.

<lacp-expired>—State of the receive lacp machine is EXPIRED?.

<lacp-role>—Whether it is an actor or partner.

<lacp-synchronization>—Actor view of partner information is in sync.

<lacp-timeout>—Configured as either fast or slow periodic.

<name>—Interface name.

Summary of Layer 2 Address Learning Response Tags

This section lists JUNOS XML tags that contain operational information about Layer 2 address learning. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-l2al>. To review the DTD for the tags, see “DTD for Layer 2 Address Learning Response Tags” on page 1839.

<bridge-statistics-information>

Usage	<pre><rpc-reply> <bridge-statistics-information> <l2ald-rtb-entry>...</l2ald-rtb-entry> <interface-statistics>...</interface-statistics> </bridge-statistics-information> </rpc-reply></pre>
Description	No documentation is available yet.
Contents	<p><interface-statistics>—No documentation is available yet.</p> <p><l2ald-rtb-entry>—No documentation is available yet.</p>

<flood-nh-components>

Usage	<pre><flood-route flood-nh-group> <flood-nh-components> <interface-name>interface-name</interface-name> <interface-type>interface-type</interface-type> <nhtype>nhtype</nhtype> <nhindex>nhindex</nhindex> </flood-nh-components> </flood-route flood-nh-group></pre>
Description	No documentation is available yet.
Contents	<p><interface-name>—Bridging media access control address interface.</p> <p><interface-type>—No documentation is available yet.</p> <p><nhindex>—No documentation is available yet.</p> <p><nhtype>—No documentation is available yet.</p>

<flood-nh-group>

Usage <flood-route>
 <flood-nh-group>
 <flood-nh-group-name>*flood-nh-group-name*</flood-nh-group-name>
 <flood-nh-group-type>*flood-nh-group-type*</flood-nh-group-type>
 <nhtype>*nhtype*</nhtype>
 <nhindex>*nhindex*</nhindex>
 <flood-group-composite-function>*flood-group-composite-function*
 </flood-group-composite-function>
 <flood-nh-components>...</flood-nh-components>
 <flood-nh-p2mp-components>...</flood-nh-p2mp-components>
 </flood-nh-group>
 </flood-route>

Description No documentation is available yet.

Contents <flood-group-composite-function>—No documentation is available yet.

<flood-nh-components>—No documentation is available yet.

<flood-nh-group-name>—No documentation is available yet.

<flood-nh-group-type>—No documentation is available yet.

<flood-nh-p2mp-components>—No documentation is available yet.

<nhindex>—No documentation is available yet.

<nhtype>—No documentation is available yet.

<flood-nh-p2mp-components>

Usage <flood-route | flood-nh-group>
 <flood-nh-p2mp-components>
 <component-nhindex>*component-nhindex*</component-nhindex>
 </flood-nh-p2mp-components>
 </flood-route | flood-nh-group>

Description No documentation is available yet.

Contents <component-nhindex>—No documentation is available yet.

<flood-route>

Usage	<l2ald-vpls-flood-instance-information l2ald-vpls-flood-route-information l2ald-bridge-domain-flood-instance-information l2ald-bridge-domain-flood-route-information> <flood-route> <route-prefix>route-prefix</route-prefix> <route-type>route-type</route-type> <owner>owner</owner> <route-flood-group-name>route-flood-group-name</route-flood-group-name> <route-flood-group-index>route-flood-group-index</route-flood-group-index> <nhtype>nhtype</nhtype> <nhindex>nhindex</nhindex> <flood-nh-p2mp-components>...</flood-nh-p2mp-components> <flood-nh-components>...</flood-nh-components> <flood-nh-group>...</flood-nh-group> </flood-route> </l2ald-vpls-flood-instance-information l2ald-vpls-flood-route-information l2ald-bridge-domain-flood-instance-information l2ald-bridge-domain-flood-route-information>
Description	No documentation is available yet.
Contents	<flood-nh-components>—No documentation is available yet. <flood-nh-group>—No documentation is available yet. <flood-nh-p2mp-components>—No documentation is available yet. <nhindex>—No documentation is available yet. <nhtype>—No documentation is available yet. <owner>—No documentation is available yet. <route-flood-group-index>—No documentation is available yet. <route-flood-group-name>—No documentation is available yet. <route-prefix>—No documentation is available yet. <route-type>—No documentation is available yet.

<interface>

Usage <interface-statistics>
 <interface>
 <interface-name>*interface-name*</interface-name>
 <interface-id>*interface-id*</interface-id>
 <interface-description>*interface-description*</interface-description>
 <local-interface-index>*local-interface-index*</local-interface-index>
 <interface-flags>*interface-flags*</interface-flags>
 <interface-flags-description>*interface-flags-description*
 </interface-flags-description>
 </interface>
 </interface-statistics>

Description No documentation is available yet.

Contents <interface-description>—No documentation is available yet.
 <interface-flags>—No documentation is available yet.
 <interface-flags-description>—No documentation is available yet.
 <interface-id>—No documentation is available yet.
 <interface-name>—Bridging media access control address interface.
 <local-interface-index>—No documentation is available yet.

<interface-statistics>

Usage <bridge-statistics-information>
 <interface-statistics>
 <interface>...</interface>
 <remote-pe>*remote-pe*</remote-pe>
 <broadcast-packets>*broadcast-packets*</broadcast-packets>
 <broadcast-bytes>*broadcast-bytes*</broadcast-bytes>
 <multicast-packets>*multicast-packets*</multicast-packets>
 <multicast-bytes>*multicast-bytes*</multicast-bytes>
 <flooded-packets>*flooded-packets*</flooded-packets>
 <flooded-bytes>*flooded-bytes*</flooded-bytes>
 <unicast-packets>*unicast-packets*</unicast-packets>
 <unicast-bytes>*unicast-bytes*</unicast-bytes>
 <mac-limit>*mac-limit*</mac-limit>
 <num-mac-count>*num-mac-count*</num-mac-count>
 </interface-statistics>
 </bridge-statistics-information>

Description No documentation is available yet.

Contents <broadcast-bytes>—Broadcast bytes.
 <broadcast-packets>—Broadcast packets.
 <flooded-bytes>—Flooded bytes.
 <flooded-packets>—Flooded packets.
 <interface>—No documentation is available yet.
 <mac-limit>—Limit of number of addresses learned on interface.
 <multicast-bytes>—Multicast bytes.
 <multicast-packets>—Multicast packets.
 <num-mac-count>—Number of addresses learned on the interface.
 <remote-pe>—No documentation is available yet.
 <unicast-bytes>—Unicast bytes.
 <unicast-packets>—Unicast packets.

<l2ald-bridge-domain-flood-event-info>

Usage <l2ald-bridge-domain-flood-next-event | l2ald-bridge-domain-flood-event-list>
<l2ald-bridge-domain-flood-event-info>
 <event-name>event-name</event-name>
 <event-type>event-type</event-type>
 <event-owner>event-owner</event-owner>
 <event-op>event-op</event-op>
 <event-error>event-error</event-error>
</l2ald-bridge-domain-flood-event-info>
 </l2ald-bridge-domain-flood-next-event | l2ald-bridge-domain-flood-event-list>

Description No documentation is available yet.

Contents <event-error>—No documentation is available yet.
 <event-name>—No documentation is available yet.
 <event-op>—No documentation is available yet.
 <event-owner>—No documentation is available yet.
 <event-type>—No documentation is available yet.

<l2ald-bridge-domain-flood-event-list>

Usage <l2ald-bridge-domain-flood-event-queue>
<l2ald-bridge-domain-flood-event-list>
 <l2ald-bridge-domain-flood-event-info>...
 </l2ald-bridge-domain-flood-event-info>
</l2ald-bridge-domain-flood-event-list>
 </l2ald-bridge-domain-flood-event-queue>

Description No documentation is available yet.

Contents <l2ald-bridge-domain-flood-event-info>—No documentation is available yet.

<l2ald-bridge-domain-flood-event-queue>

Usage <rpc-reply>
<l2ald-bridge-domain-flood-event-queue>
 <l2ald-bridge-domain-flood-next-event>...
 </l2ald-bridge-domain-flood-next-event>
 <l2ald-bridge-domain-flood-event-list>...
 </l2ald-bridge-domain-flood-event-list>
</l2ald-bridge-domain-flood-event-queue>
 </rpc-reply>

Description No documentation is available yet.

Contents <l2ald-bridge-domain-flood-event-list>—No documentation is available yet.
 <l2ald-bridge-domain-flood-next-event>—No documentation is available yet.

<l2ald-bridge-domain-flood-instance>

- Usage** <rpc-reply>
 <l2ald-bridge-domain-flood-instance>
 <l2ald-bridge-domain-lr-information>...</l2ald-bridge-domain-lr-information>
 </l2ald-bridge-domain-flood-instance>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <l2ald-bridge-domain-lr-information>—No documentation is available yet.

<l2ald-bridge-domain-flood-instance-information>

- Usage** <l2ald-bridge-domain-lr-information>
 <l2ald-bridge-domain-flood-instance-information>
 <instance-name>*instance-name*</instance-name>
 <num-active-ce-iffs>*num-active-ce-iffs*</num-active-ce-iffs>
 <num-active-ve-iffs>*num-active-ve-iffs*</num-active-ve-iffs>
 <flood-route>...</flood-route>
 </l2ald-bridge-domain-flood-instance-information>
 </l2ald-bridge-domain-lr-information>
- Description** No documentation is available yet.
- Contents** <flood-route>—No documentation is available yet.
- <instance-name>—No documentation is available yet.
- <num-active-ce-iffs>—No documentation is available yet.
- <num-active-ve-iffs>—No documentation is available yet.

<l2ald-bridge-domain-flood-next-event>

- Usage** <l2ald-bridge-domain-flood-event-queue>
 <l2ald-bridge-domain-flood-next-event>
 <l2ald-bridge-domain-flood-event-info>...
 </l2ald-bridge-domain-flood-event-info>
 </l2ald-bridge-domain-flood-next-event>
 </l2ald-bridge-domain-flood-event-queue>
- Description** No documentation is available yet.
- Contents** <l2ald-bridge-domain-flood-event-info>—No documentation is available yet.

<l2ald-bridge-domain-flood-route-information>

Usage <rpc-reply>
 <l2ald-bridge-domain-flood-route-information>
 <flood-route>...</flood-route>
 </l2ald-bridge-domain-flood-route-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <flood-route>—No documentation is available yet.

<l2ald-bridge-domain-lr-information>

Usage <l2ald-bridge-domain-flood-instance>
 <l2ald-bridge-domain-lr-information>
 <logical-system-info>...</logical-system-info>
 <l2ald-bridge-domain-flood-instance-information>...
 </l2ald-bridge-domain-flood-instance-information>
 </l2ald-bridge-domain-lr-information>
 </l2ald-bridge-domain-flood-instance>

Description No documentation is available yet.

Contents <l2ald-bridge-domain-flood-instance-information>—No documentation is available yet.
 <logical-system-info>—No documentation is available yet.

<l2ald-bridge-instance-group>

Usage <l2ald-bridge-instance-information>
<l2ald-bridge-instance-group>
 <l2rtb-name>l2rtb-name</l2rtb-name>
 <l2rtb-bridging-domain>l2rtb-bridging-domain</l2rtb-bridging-domain>
 <l2rtb-instance-description>l2rtb-instance-description
 </l2rtb-instance-description>
 <l2rtb-instance-type>l2rtb-instance-type</l2rtb-instance-type>
 <l2rtb-instance-state>l2rtb-instance-state</l2rtb-instance-state>
 <l2rtb-instance-restart-state>l2rtb-instance-restart-state
 </l2rtb-instance-restart-state>
 <l2rtb-instance-pathse1-timeout>l2rtb-instance-pathse1-timeout
 </l2rtb-instance-pathse1-timeout>
 <l2rtb-interface-name>l2rtb-interface-name</l2rtb-interface-name>
 <l2rtb-table-name>l2rtb-table-name</l2rtb-table-name>
 <l2rtb-table-mac-count>l2rtb-table-mac-count</l2rtb-table-mac-count>
 <l2rtb-table-active-mac-count>l2rtb-table-active-mac-count
 </l2rtb-table-active-mac-count>
</l2ald-bridge-instance-group>
 </l2ald-bridge-instance-information>

Description No documentation is available yet.

Contents <l2rtb-bridging-domain>—Name of the bridging domain.
 <l2rtb-instance-description>—No documentation is available yet.
 <l2rtb-instance-pathse1-timeout>—No documentation is available yet.
 <l2rtb-instance-restart-state>—No documentation is available yet.
 <l2rtb-instance-state>—No documentation is available yet.
 <l2rtb-instance-type>—Type of instance (routing instance/bridge domain).
 <l2rtb-interface-name>—No documentation is available yet.
 <l2rtb-name>—Name of the routing instance.
 <l2rtb-table-active-mac-count>—No documentation is available yet.
 <l2rtb-table-mac-count>—No documentation is available yet.
 <l2rtb-table-name>—No documentation is available yet.

<l2ald-bridge-instance-information>

Usage <rpc-reply>
 <l2ald-bridge-instance-information>
 <l2ald-bridge-instance-group>...</l2ald-bridge-instance-group>
 </l2ald-bridge-instance-information>
 </rpc-reply>

Description Operational bridge instances that can be passed to netapp commands.

Contents <l2ald-bridge-instance-group>—No documentation is available yet.

<l2ald-global-configuration>

Usage <l2ald-process-information>
<l2ald-global-configuration>
 <l2ald-mac-aging-time>l2ald-mac-aging-time</l2ald-mac-aging-time>
 <l2ald-config-flag>l2ald-config-flag</l2ald-config-flag>
 <l2ald-mac-learning-status>l2ald-mac-learning-status
 </l2ald-mac-learning-status>
 <l2ald-hardware-mac-learning-status>l2ald-hardware-mac-learning-status
 </l2ald-hardware-mac-learning-status>
 <l2ald-software-mac-learning-status>l2ald-software-mac-learning-status
 </l2ald-software-mac-learning-status>
 <l2ald-statistics-status>l2ald-statistics-status</l2ald-statistics-status>
 <l2ald-sequence-number>l2ald-sequence-number</l2ald-sequence-number>
 <l2ald-mac-learn-toggle-count>l2ald-mac-learn-toggle-count
 </l2ald-mac-learn-toggle-count>
 <l2ald-hardware-mac-learn-toggle-count>l2ald-hardware-mac-learn-toggle-count
 </l2ald-hardware-mac-learn-toggle-count>
 <l2ald-software-mac-learn-toggle-count>l2ald-software-mac-learn-toggle-count
 </l2ald-software-mac-learn-toggle-count>
 <l2ald-statistics-toggle-count>l2ald-statistics-toggle-count
 </l2ald-statistics-toggle-count>
 <l2ald-global-mac-limit-count>l2ald-global-mac-limit-count
 </l2ald-global-mac-limit-count>
 <l2ald-global-mac-limit>l2ald-global-mac-limit</l2ald-global-mac-limit>
 <l2ald-global-packet-action-drop>l2ald-global-packet-action-drop
 </l2ald-global-packet-action-drop>
 <l2ald-interface-mac-limit-wm>l2ald-interface-mac-limit-wm
 </l2ald-interface-mac-limit-wm>
 <l2ald-rtb-mac-limit-wm>l2ald-rtb-mac-limit-wm</l2ald-rtb-mac-limit-wm>
 <l2ald-mac-limit-wm>l2ald-mac-limit-wm</l2ald-mac-limit-wm>
 <l2ald-interface-mac-limit-timeout>l2ald-interface-mac-limit-timeout
 </l2ald-interface-mac-limit-timeout>
 <l2ald-rtb-mac-limit-timeout>l2ald-rtb-mac-limit-timeout
 </l2ald-rtb-mac-limit-timeout>
 <l2ald-mac-limit-timeout>l2ald-mac-limit-timeout</l2ald-mac-limit-timeout>
 <l2ald-config-smac-count>l2ald-config-smac-count</l2ald-config-smac-count>
 <l2ald-non-config-smac-count>l2ald-non-config-smac-count
 </l2ald-non-config-smac-count>
</l2ald-global-configuration>
 </l2ald-process-information>

Description Global configuration values for the the media access control address learning process.

Contents <l2ald-config-flag>—Show the global configuration flag value.

<l2ald-config-smac-count>—Number of configured static MACs that are learned globally.

<l2ald-global-mac-limit>—Status of global mac limit (whether reached or not).

<l2ald-global-mac-limit-count>—Count of number of MACs allowed globally in the system.

- <l2ald-global-packet-action-drop>—Status of packet action drop (enabled or disabled).
- <l2ald-hardware-mac-learn-toggle-count>—Count of status changes for media access control address learning in hardware (between enabled and disabled).
- <l2ald-hardware-mac-learning-status>—Status of media access control address learning in hardware (enabled or disabled).
- <l2ald-interface-mac-limit-timeout>—Timeout value on Interface MAC limit in seconds.
- <l2ald-interface-mac-limit-wm>—Watermark of Interface MAC limit in percentage.
- <l2ald-mac-aging-time>—Configured aging interval for media access control entries.
- <l2ald-mac-learn-toggle-count>—Count of status changes for media access control address learning (between enabled and disabled).
- <l2ald-mac-learning-status>—Status of media access control address learning (enabled or disabled).
- <l2ald-mac-limit-timeout>—Timeout value on Global MAC limit in seconds.
- <l2ald-mac-limit-wm>—Watermark of Global MAC limit in percentage.
- <l2ald-non-config-smac-count>—Number of non configured static MACs that are learned globally.
- <l2ald-rtb-mac-limit-timeout>—Timeout value on Routing instance MAC limit in seconds.
- <l2ald-rtb-mac-limit-wm>—Watermark of Routing MAC limit in percentage.
- <l2ald-sequence-number>—Count of global sequence number.
- <l2ald-software-mac-learn-toggle-count>—Count of status changes for media access control address learning in software (between enabled and disabled).
- <l2ald-software-mac-learning-status>—Status of media access control address learning in software (enabled or disabled).
- <l2ald-statistics-status>—Status of statistics collection for media access control entries (enabled or disabled).
- <l2ald-statistics-toggle-count>—Count of status changes for statistics collection on media access control entries (between enabled and disabled).

<l2ald-global-macdb>

- Usage** <rpc-reply>
 <l2ald-global-macdb>
 <l2ald-mac-entry>...</l2ald-mac-entry>
 </l2ald-global-macdb>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <l2ald-mac-entry>—No documentation is available yet.

<l2ald-global-macdb-count>

- Usage** <rpc-reply>
 <l2ald-global-macdb-count>
 <mac-count>*mac-count*</mac-count>
 </l2ald-global-macdb-count>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <mac-count>—Number of media access control addresses.

<l2ald-if-mac-count-entry>

- Usage** <l2ald-interface-mac-count>
 <l2ald-if-mac-count-entry>
 <interface-name>*interface-name*</interface-name>
 <mac-count>*mac-count*</mac-count>
 </l2ald-if-mac-count-entry>
 </l2ald-interface-mac-count>
- Description** MAC Address count for interface.
- Contents** <interface-name>—Bridging media access control address interface.
 <mac-count>—Number of media access control addresses.

<l2ald-interface-mac-count>

- Usage** <rpc-reply>
 <l2ald-interface-mac-count>
 <l2ald-total-intf-mac-count>*l2ald-total-intf-mac-count*
 </l2ald-total-intf-mac-count>
 <l2ald-if-mac-count-entry>...</l2ald-if-mac-count-entry>
 </l2ald-interface-mac-count>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <l2ald-if-mac-count-entry>—MAC Address count for interface.
 <l2ald-total-intf-mac-count>—Total MAC address count for all interfaces.

<l2ald-interface-macdb>

Usage <rpc-reply>
 <l2ald-interface-macdb>
 <l2ald-macdb-if-name>l2ald-macdb-if-name</l2ald-macdb-if-name>
 <l2ald-mac-entry>...</l2ald-mac-entry>
 </l2ald-interface-macdb>
 </rpc-reply>

Description No documentation is available yet.

Contents <l2ald-mac-entry>—No documentation is available yet.
 <l2ald-macdb-if-name>—Bridging MAC database for an interface.

<l2ald-mac-destination-address-statistics>

Usage <l2ald-mac-entry>
 <l2ald-mac-destination-address-statistics>
 <packet-count>packet-count</packet-count>
 <byte-count>byte-count</byte-count>
 </l2ald-mac-destination-address-statistics>
 </l2ald-mac-entry>

Description MAC destination address statistics.

Contents <byte-count>—Byte count.
 <packet-count>—Packet count.

<l2ald-mac-entry>

Usage <l2ald-global-macdb | l2ald-interface-macdb | l2ald-rtb-macdb>
<l2ald-mac-entry>
 <l2-mac-address>l2-mac-address</l2-mac-address>
 <l2-mac-interface-device>l2-mac-interface-device</l2-mac-interface-device>
 <l2-mac-logical-interface>l2-mac-logical-interface</l2-mac-logical-interface>
 <l2-mac-routing-instance>l2-mac-routing-instance</l2-mac-routing-instance>
 <l2-mac-bridging-domain>l2-mac-bridging-domain</l2-mac-bridging-domain>
 <l2-mac-logical-system>l2-mac-logical-system</l2-mac-logical-system>
 <l2-mac-vlan>l2-mac-vlan</l2-mac-vlan>
 <l2-mac-stp-index>l2-mac-stp-index</l2-mac-stp-index>
 <l2-mac-epoch>l2-mac-epoch</l2-mac-epoch>
 <l2-mac-ifl-generation>l2-mac-ifl-generation</l2-mac-ifl-generation>
 <l2-mac-sequence-number>l2-mac-sequence-number</l2-mac-sequence-number>
 <l2-mac-learn-mask>l2-mac-learn-mask</l2-mac-learn-mask>
 <l2-mac-entry-flags>l2-mac-entry-flags</l2-mac-entry-flags>
 <l2-mac-flags>l2-mac-flags</l2-mac-flags>
 <l2-bridge-vlan>l2-bridge-vlan</l2-bridge-vlan>
 <l2ald-mac-source-address-statistics>...</l2ald-mac-source-address-statistics>
 <l2ald-mac-destination-address-statistics>...
 </l2ald-mac-destination-address-statistics>
</l2ald-mac-entry>
 </l2ald-global-macdb | l2ald-interface-macdb | l2ald-rtb-macdb>

Description No documentation is available yet.

Contents <l2-bridge-vlan>—Vlan for the bridging domain.

<l2-mac-address>—Media access control address learned from another source.

<l2-mac-bridging-domain>—Bridging domain in which the MAC address was learned.

<l2-mac-entry-flags>—Forwarding entry flags associated with these MAC addresses.

<l2-mac-epoch>—Spanning Tree Protocol (STP) epoch number when MAC address was learned.

<l2-mac-flags>—Forwarding entry flags associated with MACs displayed in short form.

<l2-mac-ifl-generation>—Creation time of the logical interface when this MAC address was learned.

<l2-mac-interface-device>—Name of interface device on which MAC address was learned.

<l2-mac-learn-mask>—Mask of Packet Forwarding Engines where this MAC address was learned.

<l2-mac-logical-interface>—Name of logical interface on which MAC address was learned.

<l2-mac-logical-system>—Name of logical system in which this MAC address was learned.

`<l2-mac-routing-instance>`—Routing instance in which the MAC address was learned.

`<l2-mac-sequence-number>`—Sequence number assigned to this MAC address.

`<l2-mac-stp-index>`—Spanning Tree Protocol (STP) index of the logical interface in which the MAC address was learned.

`<l2-mac-vlan>`—VLAN ID of the routing instance in which the MAC address was learned.

`<l2ald-mac-destination-address-statistics>`—MAC destination address statistics.

`<l2ald-mac-source-address-statistics>`—MAC source address statistics.

`<l2ald-mac-source-address-statistics>`

Usage `<l2ald-mac-entry>`
 `<l2ald-mac-source-address-statistics>`
 `<packet-count>`*packet-count*`</packet-count>`
 `<byte-count>`*byte-count*`</byte-count>`
 `</l2ald-mac-source-address-statistics>`
`</l2ald-mac-entry>`

Description MAC source address statistics.

Contents `<byte-count>`—Byte count.
 `<packet-count>`—Packet count.

<l2ald-perf-counters>

Usage <rpc-reply>
<l2ald-perf-counters>
 <ipc-mac-add>ipc-mac-add</ipc-mac-add>
 <ipc-start-time-sec>ipc-start-time-sec</ipc-start-time-sec>
 <ipc-start-time-usec>ipc-start-time-usec</ipc-start-time-usec>
 <ipc-end-time-sec>ipc-end-time-sec</ipc-end-time-sec>
 <ipc-end-time-usec>ipc-end-time-usec</ipc-end-time-usec>
 <ipc-diff-time-sec>ipc-diff-time-sec</ipc-diff-time-sec>
 <ipc-diff-time-usec>ipc-diff-time-usec</ipc-diff-time-usec>
 <kernel-mac-add>kernel-mac-add</kernel-mac-add>
 <kernel-start-time-sec>kernel-start-time-sec</kernel-start-time-sec>
 <kernel-start-time-usec>kernel-start-time-usec</kernel-start-time-usec>
 <kernel-end-time-sec>kernel-end-time-sec</kernel-end-time-sec>
 <kernel-end-time-usec>kernel-end-time-usec</kernel-end-time-usec>
 <kernel-diff-time-sec>kernel-diff-time-sec</kernel-diff-time-sec>
 <kernel-diff-time-usec>kernel-diff-time-usec</kernel-diff-time-usec>
</l2ald-perf-counters>
 </rpc-reply>

Description Show L2 address learning performance information.

Contents <ipc-diff-time-sec>—IPC time difference (seconds hand).
 <ipc-diff-time-usec>—IPC time difference (microseconds hand).
 <ipc-end-time-sec>—IPC end time in seconds from Jan 1, 1970.
 <ipc-end-time-usec>—IPC end time in MicroSeconds from Jan 1, 1970.
 <ipc-mac-add>—Number of MACs seen in IPC.
 <ipc-start-time-sec>—IPC start time in seconds from Jan 1, 1970.
 <ipc-start-time-usec>—IPC start time in MicroSeconds from Jan 1, 1970.
 <kernel-diff-time-sec>—Kernel time difference (seconds hand).
 <kernel-diff-time-usec>—Kernel time difference (microseconds hand).
 <kernel-end-time-sec>—Kernel end time in seconds from Jan 1, 1970.
 <kernel-end-time-usec>—Kernel end time in MicroSeconds from Jan 1, 1970.
 <kernel-mac-add>—Number of unique MACs sent to kernel.
 <kernel-start-time-sec>—Kernel start time in seconds from Jan 1, 1970.
 <kernel-start-time-usec>—Kernel start time in MicroSeconds from Jan 1, 1970.

<l2ald-rtb-entry>

Usage <l2ald-routing-table-information | bridge-statistics-information>
<l2ald-rtb-entry>
 <l2rtb-name>l2rtb-name</l2rtb-name>
 <l2rtb-bridging-domain>l2rtb-bridging-domain</l2rtb-bridging-domain>
 <l2rtb-id>l2rtb-id</l2rtb-id>
 <l2rtb-l2irb-ifl-index>l2rtb-l2irb-ifl-index</l2rtb-l2irb-ifl-index>
 <l2bd-id>l2bd-id</l2bd-id>
 <l2bd-vlan-id>l2bd-vlan-id</l2bd-vlan-id>
 <l2rtb-logical-system>l2rtb-logical-system</l2rtb-logical-system>
 <l2rtb-sequence-number>l2rtb-sequence-number</l2rtb-sequence-number>
 <l2rtb-mac-limit>l2rtb-mac-limit</l2rtb-mac-limit>
 <l2rtb-macs-learned>l2rtb-macs-learned</l2rtb-macs-learned>
 <l2rtb-config-smacs-learned>l2rtb-config-smacs-learned
 </l2rtb-config-smacs-learned>
 <l2rtb-non-config-smacs-learned>l2rtb-non-config-smacs-learned
 </l2rtb-non-config-smacs-learned>
 <l2rtb-flags>l2rtb-flags</l2rtb-flags>
 <l2rtb-irb-interface>l2rtb-irb-interface</l2rtb-irb-interface>
 <l2rtb-irb-interface-index>l2rtb-irb-interface-index
 </l2rtb-irb-interface-index>
 <l2rtb-handle>l2rtb-handle</l2rtb-handle>
 <l2rtb-config-bd-vlan>l2rtb-config-bd-vlan</l2rtb-config-bd-vlan>
 <l2rtb-config-operation>l2rtb-config-operation</l2rtb-config-operation>
 <l2rtb-config-flags>l2rtb-config-flags</l2rtb-config-flags>
 <l2rtb-config-params>l2rtb-config-params</l2rtb-config-params>
 <l2rtb-instance-type>l2rtb-instance-type</l2rtb-instance-type>
 <l2rtb-config-smac-count>l2rtb-config-smac-count</l2rtb-config-smac-count>
 <l2rtb-rtsock-write-errors>l2rtb-rtsock-write-errors
 </l2rtb-rtsock-write-errors>
</l2ald-rtb-entry>
 </l2ald-routing-table-information | bridge-statistics-information>

Description No documentation is available yet.

Contents <l2bd-id>—Bridge domain identifier.

<l2bd-vlan-id>—Bridge domain VLAN.

<l2rtb-bridging-domain>—Name of the bridging domain.

<l2rtb-config-bd-vlan>—Vlan configured for the given bridge domain on routing instance.

<l2rtb-config-flags>—Configured flags associated with this routing instance/bridge domain.

<l2rtb-config-operation>—Configuration notify operation on bridge domain/routing instance.

<l2rtb-config-params>—Configured attributes associated with this routing instance/bridge domain.

<l2rtb-config-smac-count>—Configured Static MAC on the BD.

<l2rtb-config-smacs-learned>—Number of configured static MACs that are learned on this routing instance.

<l2rtb-flags>—Attributes associated with this routing instance.

<l2rtb-handle>—Handle associated with this routing instance.

<l2rtb-id>—Routing instance identifier.

<l2rtb-instance-type>—Type of instance (routing instance/bridge domain).

<l2rtb-irb-interface>—Name of the IRB interface associated with this routing instance.

<l2rtb-irb-interface-index>—IRB interface index associated with this routing instance.

<l2rtb-l2irb-ifl-index>—No documentation is available yet.

<l2rtb-logical-system>—Logical system name.

<l2rtb-mac-limit>—Maximum number of MAC addresses that can be learned on this routing instance.

<l2rtb-macs-learned>—Number of configured static and dynamic MACs that are learned on this routing instance.

<l2rtb-name>—Name of the routing instance.

<l2rtb-non-config-smacs-learned>—Number of non configured static MACs that are learned on this routing instance.

<l2rtb-rtsock-write-errors>—Number of times kernel write has failed.

<l2rtb-sequence-number>—Current routing instance sequence number.

<l2ald-rtb-if-mac-count>

Usage	<pre> <l2ald-rtb-mac-count-entry> <l2ald-rtb-if-mac-count> <l2ald-rtb-if-mac-count-entry>...</l2ald-rtb-if-mac-count-entry> </l2ald-rtb-if-mac-count> </l2ald-rtb-mac-count-entry> </pre>
Description	MAC address count for all the interfaces in the routing instance.
Contents	<l2ald-rtb-if-mac-count-entry>—No documentation is available yet.

<l2ald-rtb-if-mac-count-entry>

Usage <l2ald-rtb-if-mac-count>
 <l2ald-rtb-if-mac-count-entry>
 <interface-name>*interface-name*</interface-name>
 <mac-count>*mac-count*</mac-count>
 </l2ald-rtb-if-mac-count-entry>
 </l2ald-rtb-if-mac-count>

Description No documentation is available yet.

Contents <interface-name>—Bridging media access control address interface.
 <mac-count>—Number of media access control addresses.

<l2ald-rtb-learn-vlan-mac-count>

Usage <l2ald-rtb-mac-count-entry>
 <l2ald-rtb-learn-vlan-mac-count>
 <l2ald-rtb-learn-vlan-mac-count-entry>...
 </l2ald-rtb-learn-vlan-mac-count-entry>
 </l2ald-rtb-learn-vlan-mac-count>
 </l2ald-rtb-mac-count-entry>

Description MAC address count for all the learn vlans within the routing instance.

Contents <l2ald-rtb-learn-vlan-mac-count-entry>—No documentation is available yet.

<l2ald-rtb-learn-vlan-mac-count-entry>

Usage <l2ald-rtb-learn-vlan-mac-count>
 <l2ald-rtb-learn-vlan-mac-count-entry>
 <learn-vlan>*learn-vlan*</learn-vlan>
 <mac-count>*mac-count*</mac-count>
 </l2ald-rtb-learn-vlan-mac-count-entry>
 </l2ald-rtb-learn-vlan-mac-count>

Description No documentation is available yet.

Contents <learn-vlan>—VLAN ID of the routing instance in which the MAC address was learned.
 <mac-count>—Number of media access control addresses.

<l2ald-rtb-mac-count>

Usage <rpc-reply>
 <l2ald-rtb-mac-count>
 <l2ald-rtb-mac-count-entry>...</l2ald-rtb-mac-count-entry>
 </l2ald-rtb-mac-count>
 </rpc-reply>

Description No documentation is available yet.

Contents <l2ald-rtb-mac-count-entry>—No documentation is available yet.

<l2ald-rtb-mac-count-entry>

Usage <l2ald-rtb-mac-count>
 <l2ald-rtb-mac-count-entry>
 <rtb-name>*rtb-name*</rtb-name>
 <bd-name>*bd-name*</bd-name>
 <rtb-mac-count>*rtb-mac-count*</rtb-mac-count>
 <l2ald-rtb-if-mac-count>...</l2ald-rtb-if-mac-count>
 <l2ald-rtb-learn-vlan-mac-count>...</l2ald-rtb-learn-vlan-mac-count>
 </l2ald-rtb-mac-count-entry>
 </l2ald-rtb-mac-count>

Description No documentation is available yet.

Contents <bd-name>—Bridging media access control address count for bridge-domain.

<l2ald-rtb-if-mac-count>—MAC address count for all the interfaces in the routing instance.

<l2ald-rtb-learn-vlan-mac-count>—MAC address count for all the learn vlans within the routing instance.

<rtb-mac-count>—Media access control addresses count.

<rtb-name>—Bridging media access control address count for routing-instance.

<l2ald-rtb-mac-learn-count>

Usage <rpc-reply>
 <l2ald-rtb-mac-learn-count>
 <l2ald-rtb-mac-learn-address>*l2ald-rtb-mac-learn-address*
 </l2ald-rtb-mac-learn-address>
 <l2ald-rtb-mac-learn-num-times>*l2ald-rtb-mac-learn-num-times*
 </l2ald-rtb-mac-learn-num-times>
 </l2ald-rtb-mac-learn-count>
 </rpc-reply>

Description No documentation is available yet.

Contents <l2ald-rtb-mac-learn-address>—Bridging media access control address.

<l2ald-rtb-mac-learn-num-times>—Number of times an entry has been learned.

<l2ald-rtb-macdb>

Usage <rpc-reply>
 <l2ald-rtb-macdb>
 <l2ald-macdb-rtb-name>l2ald-macdb-rtb-name</l2ald-macdb-rtb-name>
 <l2ald-mac-entry>...</l2ald-mac-entry>
 </l2ald-rtb-macdb>
 </rpc-reply>

Description No documentation is available yet.

Contents <l2ald-mac-entry>—No documentation is available yet.
 <l2ald-macdb-rtb-name>—Bridging MAC database for a routing instance.

<l2ald-vpls-flood-event-info>

Usage <l2ald-vpls-flood-next-event | l2ald-vpls-flood-event-list>
 <l2ald-vpls-flood-event-info>
 <event-name>event-name</event-name>
 <event-type>event-type</event-type>
 <event-owner>event-owner</event-owner>
 <event-op>event-op</event-op>
 <event-error>event-error</event-error>
 </l2ald-vpls-flood-event-info>
 </l2ald-vpls-flood-next-event | l2ald-vpls-flood-event-list>

Description No documentation is available yet.

Contents <event-error>—No documentation is available yet.
 <event-name>—No documentation is available yet.
 <event-op>—No documentation is available yet.
 <event-owner>—No documentation is available yet.
 <event-type>—No documentation is available yet.

<l2ald-vpls-flood-event-list>

Usage <l2ald-vpls-flood-event-queue>
 <l2ald-vpls-flood-event-list>
 <l2ald-vpls-flood-event-info>...</l2ald-vpls-flood-event-info>
 </l2ald-vpls-flood-event-list>
 </l2ald-vpls-flood-event-queue>

Description No documentation is available yet.

Contents <l2ald-vpls-flood-event-info>—No documentation is available yet.

<l2ald-vpls-flood-event-queue>

Usage <rpc-reply>
 <l2ald-vpls-flood-event-queue>
 <l2ald-vpls-flood-next-event>...</l2ald-vpls-flood-next-event>
 <l2ald-vpls-flood-event-list>...</l2ald-vpls-flood-event-list>
 </l2ald-vpls-flood-event-queue>
 </rpc-reply>

Description No documentation is available yet.

Contents <l2ald-vpls-flood-event-list>—No documentation is available yet.
 <l2ald-vpls-flood-next-event>—No documentation is available yet.

<l2ald-vpls-flood-instance>

Usage <rpc-reply>
 <l2ald-vpls-flood-instance>
 <l2ald-vpls-lr-information>...</l2ald-vpls-lr-information>
 </l2ald-vpls-flood-instance>
 </rpc-reply>

Description No documentation is available yet.

Contents <l2ald-vpls-lr-information>—No documentation is available yet.

<l2ald-vpls-flood-instance-information>

Usage <l2ald-vpls-lr-information>
 <l2ald-vpls-flood-instance-information>
 <instance-name>*instance-name*</instance-name>
 <num-active-ce-iffs>*num-active-ce-iffs*</num-active-ce-iffs>
 <num-active-ve-iffs>*num-active-ve-iffs*</num-active-ve-iffs>
 <flood-route>...</flood-route>
 </l2ald-vpls-flood-instance-information>
 </l2ald-vpls-lr-information>

Description No documentation is available yet.

Contents <flood-route>—No documentation is available yet.
 <instance-name>—No documentation is available yet.
 <num-active-ce-iffs>—No documentation is available yet.
 <num-active-ve-iffs>—No documentation is available yet.

<l2ald-vpls-flood-next-event>

Usage <l2ald-vpls-flood-event-queue>
 <l2ald-vpls-flood-next-event>
 <l2ald-vpls-flood-event-info>...</l2ald-vpls-flood-event-info>
 </l2ald-vpls-flood-next-event>
 </l2ald-vpls-flood-event-queue>

Description No documentation is available yet.

Contents <l2ald-vpls-flood-event-info>—No documentation is available yet.

<l2ald-vpls-flood-route-information>

Usage <rpc-reply>
 <l2ald-vpls-flood-route-information>
 <flood-route>...</flood-route>
 </l2ald-vpls-flood-route-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <flood-route>—No documentation is available yet.

<l2ald-vpls-lr-information>

Usage <l2ald-vpls-flood-instance>
 <l2ald-vpls-lr-information>
 <logical-system-info>...</logical-system-info>
 <l2ald-vpls-flood-instance-information>...
 </l2ald-vpls-flood-instance-information>
 </l2ald-vpls-lr-information>
 </l2ald-vpls-flood-instance>

Description No documentation is available yet.

Contents <l2ald-vpls-flood-instance-information>—No documentation is available yet.

<logical-system-info>—No documentation is available yet.

<logical-system-info>

Usage <l2ald-vpls-lr-information | l2ald-bridge-domain-lr-information>
 <logical-system-info>
 <logical-system-name>logical-system-name</logical-system-name>
 </logical-system-info>
 </l2ald-vpls-lr-information | l2ald-bridge-domain-lr-information>

Description No documentation is available yet.

Contents <logical-system-name>—No documentation is available yet.

Summary of Layer 2 Control Protocol Response Tags

This section lists JUNOS XML tags that contain operational information about the Layer 2 Control Protocol (L2CP). The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-l2cp>. To review the DTD for the tags, see “DTD for Layer 2 Control Protocol Response Tags” on page 1847.

<cist-bridge-parameters>

Usage <stp-bridge>
 <cist-bridge-parameters>
 <cist-id>*cist-id*</cist-id>
 <root-bridge>...</root-bridge>
 <root-port>*root-port*</root-port>
 <root-cost>*root-cost*</root-cost>
 <regional-root-bridge>...</regional-root-bridge>
 <internal-root-cost>*internal-root-cost*</internal-root-cost>
 <hello-time-learned>*hello-time-learned*</hello-time-learned>
 <max-age-learned>*max-age-learned*</max-age-learned>
 <forward-delay-learned>*forward-delay-learned*</forward-delay-learned>
 <msg-age>*msg-age*</msg-age>
 <hop-count>*hop-count*</hop-count>
 <time-since-last-tc>*time-since-last-tc*</time-since-last-tc>
 <topology-change-count>*topology-change-count*</topology-change-count>
 <extended-system-id>*extended-system-id*</extended-system-id>
 <this-bridge>...</this-bridge>
 <hello-time-configured>*hello-time-configured*</hello-time-configured>
 <max-age-configured>*max-age-configured*</max-age-configured>
 <forward-delay-configured>*forward-delay-configured*</forward-delay-configured>
 <max-hop-count-configured>*max-hop-count-configured*</max-hop-count-configured>
 <path-cost-method>*path-cost-method*</path-cost-method>
 </cist-bridge-parameters>
 </stp-bridge>

Description STP bridge parameters for Common and Internal Spanning Tree.

Contents <cist-id>—CIST identifier.

<extended-system-id>—Extended system identifier.

<forward-delay-configured>—Forward delay configured on this bridge.

<forward-delay-learned>—Forward delay.

<hello-time-configured>—Hello time configured on this bridge.

<hello-time-learned>—Hello time.

<hop-count>—Hop count received from the root bridge.

<internal-root-cost>—CIST internal root cost.

<max-age-configured>—Maximum age configured on this bridge.

<max-age-learned>—Maximum age for received BPDUs.

<max-hop-count-configured>—Maximum hop count configured on this bridge.

<msg-age>—Age of the received BPDU.

<path-cost-method>—Type of path cost method currently in use.

<regional-root-bridge>—CIST regional root bridge identifier.

<root-bridge>—Root bridge identifier.

<root-cost>—Root cost.

<root-port>—Root port.

<this-bridge>—ID of bridge.

<time-since-last-tc>—Time since last topology change.

<topology-change-count>—Number of topology changes.

<dot1x-authentication-failed-users>

Usage <dot1x-interface-information>
 <dot1x-authentication-failed-users>
 <authentication-failed-interface>*authentication-failed-interface*
 </authentication-failed-interface>
 <authentication-failed-mac-addr>*authentication-failed-mac-addr*
 </authentication-failed-mac-addr>
 <authentication-failed-user>*authentication-failed-user*
 </authentication-failed-user>
 </dot1x-authentication-failed-users>
 </dot1x-interface-information>

Description List of users who failed authentication.

Contents <authentication-failed-interface>—Interface used in failed authentication.
 <authentication-failed-mac-addr>—MAC address used by user who failed authentication.
 <authentication-failed-user>—Users who failed authentication.

<dot1x-interface-information>

Usage <rpc-reply>
 <dot1x-interface-information>
 <interface>...</interface>
 <dot1x-static-mac-address>...</dot1x-static-mac-address>
 <dot1x-authentication-failed-users>...</dot1x-authentication-failed-users>
 </dot1x-interface-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <dot1x-authentication-failed-users>—List of users who failed authentication.
 <dot1x-static-mac-address>—Information about configured static MAC addresses.
 <interface>—No documentation is available yet.

<dot1x-static-mac-address>

Usage <dot1x-interface-information>
 <dot1x-static-mac-address>
 <static-mac-address>*static-mac-address*</static-mac-address>
 <static-mac-vlan-assignment>*static-mac-vlan-assignment*
 </static-mac-vlan-assignment>
 <static-mac-interface>*static-mac-interface*</static-mac-interface>
 </dot1x-static-mac-address>
 </dot1x-interface-information>

Description Information about configured static MAC addresses.

Contents <static-mac-address>—MAC address configured for bypass.
 <static-mac-interface>—Interface on which client MAC was learned.
 <static-mac-vlan-assignment>—VLAN assigned to the client with this MAC address.

<interface>

Usage <dot1x-interface-information>
<interface>
 <user-name>*user-name*</user-name>
 <user-mac-address>*user-mac-address*</user-mac-address>
 <role>*role*</role>
 <state>*state*</state>
 <administrative-state>*administrative-state*</administrative-state>
 <administrative-mode>*administrative-mode*</administrative-mode>
 <number-of-retries>*number-of-retries*</number-of-retries>
 <quiet-period>*quiet-period*</quiet-period>
 <transmit-period>*transmit-period*</transmit-period>
 <reauthentication>*reauthentication*</reauthentication>
 <reauthentication-interval>*reauthentication-interval*
 </reauthentication-interval>
 <supplicant-timeout>*supplicant-timeout*</supplicant-timeout>
 <server-timeout>*server-timeout*</server-timeout>
 <max-eapol-request>*max-eapol-request*</max-eapol-request>
 <frame-control>*frame-control*</frame-control>
 <guest-vlan>*guest-vlan*</guest-vlan>
 <number-of-authentication-bypassed-clients>*num-auth-bypassed-clients*
 </number-of-authentication-bypassed-clients>
 <static-mac-bypass>*static-mac-bypass*</static-mac-bypass>
 <number-of-connected-supplicants>*number-of-connected-supplicants*
 </number-of-connected-supplicants>
 <reauthentication-due>*reauthentication-due*</reauthentication-due>
</interface>
 </dot1x-interface-information>

Description No documentation is available yet.

Contents <administrative-mode>—Supplicant authorization mode.
 <administrative-state>—Administrative state of port.
 <frame-control>—Block only ingress traffic before authentication.
 <guest-vlan>—VLAN members for unauthenticated or non-responsive hosts.
 <max-eapol-request>—Maximum number of EAPOL request IDs to client.
 <number-of-authentication-bypassed-clients>—Number of clients bypassed because of authentication.
 <number-of-connected-supplicants>—Number of connected supplicants.
 <number-of-retries>—Number of retries after which port is placed into wait state.
 <quiet-period>—Time to wait after authentication failure.
 <reauthentication>—Reauthentication status.
 <reauthentication-due>—How long before reauthenticating supplicant.

<reauthentication-interval>—Reauthentication interval.

<role>—Role of interface.

<server-timeout>—Time to wait before invoking server-fail action.

<state>—Current state of interface.

<static-mac-bypass>—MAC address of bypassed client.

<supplicant-timeout>—Time to wait for response from supplicant before resending request.

<transmit-period>—Interval before retransmitting initial EAPOL PDUs.

<user-mac-address>—MAC address of client.

<user-name>—User name as sent by client for authentication.

<l2pt-interface-entry>

Usage <l2pt-interface-list>
 <l2pt-interface-entry>
 <protocols>*protocols*</protocols>
 </l2pt-interface-entry>
 </l2pt-interface-list>

Description No documentation is available yet.

Contents <protocols>—Protocols for which tunnelling is enabled.

<l2pt-interface-list>

Usage <rpc-reply>
 <l2pt-interface-list>
 <l2pt-interface-entry>...</l2pt-interface-entry>
 </l2pt-interface-list>
 </rpc-reply>

Description L2PT interface information.

Contents <l2pt-interface-entry>—No documentation is available yet.

<msti-bridge-parameters>

Usage <stp-bridge>
 <msti-bridge-parameters>
 <msti-id>*msti-id*</msti-id>
 <msti-regional-root-bridge>...</msti-regional-root-bridge>
 <root-port>*root-port*</root-port>
 <root-cost>*root-cost*</root-cost>
 <hello-time-learned>*hello-time-learned*</hello-time-learned>
 <max-age-learned>*max-age-learned*</max-age-learned>
 <forward-delay-learned>*forward-delay-learned*</forward-delay-learned>
 <max-hop-count-configured>*max-hop-count-configured*</max-hop-count-configured>
 <hop-count>*hop-count*</hop-count>
 <time-since-last-tc>*time-since-last-tc*</time-since-last-tc>
 <topology-change-count>*topology-change-count*</topology-change-count>
 <extended-system-id>*extended-system-id*</extended-system-id>
 <this-bridge>...</this-bridge>
 <hello-time-configured>*hello-time-configured*</hello-time-configured>
 <max-age-configured>*max-age-configured*</max-age-configured>
 <forward-delay-configured>*forward-delay-configured*</forward-delay-configured>
 <path-cost-method>*path-cost-method*</path-cost-method>
 </msti-bridge-parameters>
 </stp-bridge>

Description STP bridge parameters for Multiple Spanning Tree instances.

Contents <extended-system-id>—Extended system identifier.

<forward-delay-configured>—Forward delay configured on this bridge.

<forward-delay-learned>—Forward delay.

<hello-time-configured>—Hello time configured on this bridge.

<hello-time-learned>—Hello time.

<hop-count>—Hop count received from the root bridge.

<max-age-configured>—Maximum age configured on this bridge.

<max-age-learned>—Maximum age for received BPDUs.

<max-hop-count-configured>—Maximum hop count configured on this bridge.

<msti-id>—MSTI ID.

<msti-regional-root-bridge>—MSTI regional root identifier.

<path-cost-method>—Type of path cost method currently in use.

<root-cost>—Root cost.

<root-port>—Root port.

<this-bridge>—ID of bridge.

`<time-since-last-tc>`—Time since last topology change.

`<topology-change-count>`—Number of topology changes.

`<msti-regional-root-bridge>`

Usage `<msti-bridge-parameters>`
 `<msti-regional-root-bridge>`
 `<bridge-priority>`*bridge-priority*`</bridge-priority>`
 `<bridge-mac>`*bridge-mac*`</bridge-mac>`
 `</msti-regional-root-bridge>`
`</msti-bridge-parameters>`

Description MSTI regional root identifier.

Contents `<bridge-mac>`—Media access control address of bridge.

`<bridge-priority>`—Bridge priority.

`<mstp-configuration>`

Usage `<rpc-reply>`
 `<mstp-configuration>`
 `<mstp-name>`*mstp-name*`</mstp-name>`
 `<mstp-revision>`*mstp-revision*`</mstp-revision>`
 `<mstp-configuration-digest>`*mstp-configuration-digest*
 `</mstp-configuration-digest>`
 `<vlan-map>`...`</vlan-map>`
 `</mstp-configuration>`
`</rpc-reply>`

Description Information about Multiple Spanning Tree protocol configuration.

Contents `<mstp-configuration-digest>`—MSTP configuration digest.

`<mstp-name>`—MSTP region name.

`<mstp-revision>`—MSTP revision.

`<vlan-map>`—No documentation is available yet.

<regional-root-bridge>

- Usage** <cist-bridge-parameters>
 <regional-root-bridge>
 <bridge-priority>*bridge-priority*</bridge-priority>
 <bridge-mac>*bridge-mac*</bridge-mac>
 </regional-root-bridge>
 </cist-bridge-parameters>
- Description** CIST regional root bridge identifier.
- Contents** <bridge-mac>—Media access control address of bridge.
 <bridge-priority>—Bridge priority.

<root-bridge>

- Usage** <cist-bridge-parameters | vst-bridge-parameters>
 <root-bridge>
 <bridge-priority>*bridge-priority*</bridge-priority>
 <bridge-mac>*bridge-mac*</bridge-mac>
 </root-bridge>
 </cist-bridge-parameters | vst-bridge-parameters>
- Description** Root bridge identifier.
- Contents** <bridge-mac>—Media access control address of bridge.
 <bridge-priority>—Bridge priority.

<stp-bridge>

Usage <rpc-reply>
 <stp-bridge>
 <routing-instance-name>*routing-instance-name*</routing-instance-name>
 <bpd-destination-mac-address>*bpd-destination-mac-address*
 </bpd-destination-mac-address>
 <protocol>*protocol*</protocol>
 <cist-bridge-parameters>...</cist-bridge-parameters>
 <msti-bridge-parameters>...</msti-bridge-parameters>
 <vst-bridge-parameters>...</vst-bridge-parameters>
 </stp-bridge>
 </rpc-reply>

Description Information about STP bridge parameters.

Contents <bpd-destination-mac-address>—Destination MAC address in the spanning tree BPDUs.

<cist-bridge-parameters>—STP bridge parameters for Common and Internal Spanning Tree.

<msti-bridge-parameters>—STP bridge parameters for Multiple Spanning Tree instances.

<protocol>—Enabled protocol.

<routing-instance-name>—Routing instance name.

<vst-bridge-parameters>—STP bridge parameters for VLAN Spanning Tree.

<stp-context-statistics-information>

Usage <rpc-reply>
 <stp-context-statistics-information>
 <message-type>message-type</message-type>
 <total-bpdus-sent>total-bpdus-sent</total-bpdus-sent>
 <total-bpdus-received>total-bpdus-received</total-bpdus-received>
 <bpdus-sent-5seconds>bpdus-sent-5seconds</bpdus-sent-5seconds>
 <bpdus-received-5seconds>bpdus-received-5seconds</bpdus-received-5seconds>
 <vstp-statistics>...</vstp-statistics>
 </stp-context-statistics-information>
 </rpc-reply>

Description Spanning Tree Protocol statistics at routing instance level.

Contents <bpdus-received-5seconds>—Total number of BPDUs received on this routing instance in last 5 secs.

<bpdus-sent-5seconds>—Total number of BPDUs sent out for this routing instance in last 5 secs.

<message-type>—Spanning Tree message type.

<total-bpdus-received>—Total number of BPDUs received.

<total-bpdus-sent>—Total number of BPDUs sent out.

<vstp-statistics>—VLAN Spanning Tree Protocol statistics.

<stp-instance>

Usage <stp-interface-information>
 <stp-instance>
 <stp-interfaces>...</stp-interfaces>
 </stp-instance>
 </stp-interface-information>

Description No documentation is available yet.

Contents <stp-interfaces>—Information about one or more Spanning Tree Protocol interfaces.

<stp-interface-entry>

Usage <stp-interfaces>
 <stp-interface-entry>
 <port-priority>*port-priority*</port-priority>
 <designated-port-priority>*designated-port-priority*</designated-port-priority>
 <designated-port-number>*designated-port-number*</designated-port-number>
 <port-cost>*port-cost*</port-cost>
 <port-state>*port-state*</port-state>
 <designated-bridge-priority>*designated-bridge-priority*
 </designated-bridge-priority>
 <designated-bridge-mac>*designated-bridge-mac*</designated-bridge-mac>
 <port-role>*port-role*</port-role>
 <link-type>*link-type*</link-type>
 <port-migrated-protocol>*port-migrated-protocol*</port-migrated-protocol>
 <boundary-port>*boundary-port*</boundary-port>
 </stp-interface-entry>
 </stp-interfaces>

Description Information about Spanning Tree Protocol interface.

Contents <boundary-port>—STP boundary port.

<designated-bridge-mac>—Media access control address of bridge.

<designated-bridge-priority>—Bridge priority.

<designated-port-number>—Designated port number.

<designated-port-priority>—Designated port priority.

<link-type>—Type of link.

<port-cost>—Port cost.

<port-migrated-protocol>—Migrated protocol for port.

<port-priority>—Port priority.

<port-role>—Role of port.

<port-state>—Port state.

<stp-interface-information>

Usage <rpc-reply>
 <stp-interface-information>
 <stp-instance>...</stp-instance>
 </stp-interface-information>
 </rpc-reply>

Description Information about one or more Spanning Tree Protocol interfaces for one or more Spanning Tree Protocol instances.

Contents <stp-instance>—No documentation is available yet.

<stp-interface-statistics>

- Usage** <rpc-reply>
 <stp-interface-statistics>
 <stp-interface-statistics-entry>...</stp-interface-statistics-entry>
 <vstp-interface-statistics>...</vstp-interface-statistics>
 </stp-interface-statistics>
 </rpc-reply>
- Description** Statistics information about one or more STP interfaces.
- Contents** <stp-interface-statistics-entry>—Spanning Tree Protocol interface statistics.
 <vstp-interface-statistics>—Statistics information about one or more VLAN STP interfaces.

<stp-interface-statistics-entry>

- Usage** <stp-interface-statistics | vstp-interface-statistics>
 <stp-interface-statistics-entry>
 <total-bpdu-sent>*total-bpdu-sent*</total-bpdu-sent>
 <total-bpdu-received>*total-bpdu-received*</total-bpdu-received>
 <next-bpdu-time>*next-bpdu-time*</next-bpdu-time>
 </stp-interface-statistics-entry>
 </stp-interface-statistics | vstp-interface-statistics>
- Description** Spanning Tree Protocol interface statistics.
- Contents** <next-bpdu-time>—Next bpdu send time in the steady state in seconds.
 <total-bpdu-received>—Total number of BPDUs received.
 <total-bpdu-sent>—Total number of BPDUs sent out.

<stp-interfaces>

- Usage** <stp-instance>
 <stp-interfaces>
 <stp-interface-entry>...</stp-interface-entry>
 </stp-interfaces>
 </stp-instance>
- Description** Information about one or more Spanning Tree Protocol interfaces.
- Contents** <stp-interface-entry>—Information about Spanning Tree Protocol interface.

<stp-kernel-table>

Usage <rpc-reply>
 <stp-kernel-table>
 <stp-kernel-table-entry>...</stp-kernel-table-entry>
 </stp-kernel-table>
 </rpc-reply>

Description Information about Spanning Tree Protocol kernel table.

Contents <stp-kernel-table-entry>—No documentation is available yet.

<stp-kernel-table-entry>

Usage <stp-kernel-table>
 <stp-kernel-table-entry>
 <stp-index>stp-index</stp-index>
 <kernel-if-name>kernel-if-name</kernel-if-name>
 <kernel-stp-instance>kernel-stp-instance</kernel-stp-instance>
 <kernel-state>kernel-state</kernel-state>
 <kernel-action>kernel-action</kernel-action>
 <epoch>epoch</epoch>
 <hardware-learning>hardware-learning</hardware-learning>
 </stp-kernel-table-entry>
 </stp-kernel-table>

Description No documentation is available yet.

Contents <epoch>—No documentation is available yet.

<hardware-learning>—No documentation is available yet.

<kernel-action>—No documentation is available yet.

<kernel-if-name>—No documentation is available yet.

<kernel-state>—No documentation is available yet.

<kernel-stp-instance>—No documentation is available yet.

<stp-index>—No documentation is available yet.

<task>

Usage	<task-information task-timer-information> <task> <task-name> <i>task-name</i> </task-name> <task-no-information/> <task-timer>...</task-timer> </task> </task-information task-timer-information>
Description	No documentation is available yet.
Contents	<task-name>—Name of this task. <task-no-information>—No information is available for this task. <task-timer>—No documentation is available yet.

<task-block>

Usage <task-block-list>
 <task-block>
 <tb-name>*tb-name*</tb-name>
 <tb-size>*tb-size*</tb-size>
 <tb-alloc-size>*tb-alloc-size*</tb-alloc-size>
 <tb-terse-transient/>
 <tb-terse-fullpage/>
 <tb-terse-debug/>
 <tb-alloc-blocks>*tb-alloc-blocks*</tb-alloc-blocks>
 <tb-alloc-bytes>*tb-alloc-bytes*</tb-alloc-bytes>
 <tb-max-alloc-blocks>*tb-max-alloc-blocks*</tb-max-alloc-blocks>
 <tb-max-alloc-bytes>*tb-max-alloc-bytes*</tb-max-alloc-bytes>
 </task-block>
 </task-block-list>

Description No documentation is available yet.

Contents <tb-alloc-blocks>—Number of allocated structures.

<tb-alloc-bytes>—Number of allocated bytes.

<tb-alloc-size>—Allocated size for this block.

<tb-max-alloc-blocks>—Maximum number of structures ever allocated.

<tb-max-alloc-bytes>—Maximum number of bytes ever allocated.

<tb-name>—Name for this block.

<tb-size>—Actual size of this block.

<tb-terse-debug>—No documentation is available yet.

<tb-terse-fullpage>—No documentation is available yet.

<tb-terse-transient>—No documentation is available yet.

<task-block-list>

Usage <task-memory-allocator-report>
 <task-block-list>
 <task-block>...</task-block>
 </task-block-list>
 </task-memory-allocator-report>

Description No documentation is available yet.

Contents <task-block>—No documentation is available yet.

<task-information>

Usage	<pre> <rpc-reply> <task-information> <task>...</task> </task-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<task>—No documentation is available yet.

<task-lite-page>

Usage	<pre> <task-lite-page-list> <task-lite-page> <tlp-name>tlp-name</tlp-name> <tlp-alloc-pages>tlp-alloc-pages</tlp-alloc-pages> <tlp-alloc-bytes>tlp-alloc-bytes</tlp-alloc-bytes> <tlp-max-alloc-pages>tlp-max-alloc-pages</tlp-max-alloc-pages> <tlp-max-alloc-bytes>tlp-max-alloc-bytes</tlp-max-alloc-bytes> </task-lite-page> </task-lite-page-list> </pre>
Description	No documentation is available yet.
Contents	<p><tlp-alloc-bytes>—Number of bytes allocated.</p> <p><tlp-alloc-pages>—Number of pages allocated.</p> <p><tlp-max-alloc-bytes>—Maximum bytes ever allocated.</p> <p><tlp-max-alloc-pages>—Maximum pages ever allocated.</p> <p><tlp-name>—Name of this pool.</p>

<task-lite-page-list>

Usage	<pre> <task-memory-allocator-report> <task-lite-page-list> <task-lite-page>...</task-lite-page> </task-lite-page-list> </task-memory-allocator-report> </pre>
Description	No documentation is available yet.
Contents	<task-lite-page>—No documentation is available yet.

<task-malloc>

Usage <task-malloc-list>
 <task-malloc>
 <tm-name>*tm-name*</tm-name>
 <tm-allocs>*tm-allocs*</tm-allocs>
 <tm-alloc-bytes>*tm-alloc-bytes*</tm-alloc-bytes>
 <tm-max-allocs>*tm-max-allocs*</tm-max-allocs>
 <tm-max-alloc-bytes>*tm-max-alloc-bytes*</tm-max-alloc-bytes>
 <tm-function-calls>*tm-function-calls*</tm-function-calls>
 </task-malloc>
 </task-malloc-list>

Description No documentation is available yet.

Contents <tm-alloc-bytes>—Number of bytes allocated.
 <tm-allocs>—Number of allocations out.
 <tm-function-calls>—Number of function calls.
 <tm-max-alloc-bytes>—Maximum bytes allocated.
 <tm-max-allocs>—Maximum allocations ever out.
 <tm-name>—No documentation is available yet.

<task-malloc-list>

Usage <task-memory-malloc-usage-report>
 <task-malloc-list>
 <task-malloc>...</task-malloc>
 </task-malloc-list>
 </task-memory-malloc-usage-report>

Description No documentation is available yet.

Contents <task-malloc>—No documentation is available yet.

<task-memory-allocator-report>

Usage <task-memory-information>
 <task-memory-allocator-report>
 <task-block-list>...</task-block-list>
 <task-lite-page-list>...</task-lite-page-list>
 <task-memory-total-bytes>*task-memory-total-bytes*</task-memory-total-bytes>
 <task-memory-total-max-bytes>*task-memory-total-max-bytes*
 </task-memory-total-max-bytes>
 </task-memory-allocator-report>
 </task-memory-information>

Description No documentation is available yet.

Contents <task-block-list>—No documentation is available yet.
 <task-lite-page-list>—No documentation is available yet.
 <task-memory-total-bytes>—No documentation is available yet.
 <task-memory-total-max-bytes>—No documentation is available yet.

<task-memory-information>

Usage <rpc-reply>
<task-memory-information>
 <task-memory-in-use-size>task-memory-in-use-size</task-memory-in-use-size>
 <task-memory-in-use-avail>task-memory-in-use-avail</task-memory-in-use-avail>
 <task-memory-max-size>task-memory-max-size</task-memory-max-size>
 <task-memory-max-avail>task-memory-max-avail</task-memory-max-avail>
 <task-memory-max-when>task-memory-max-when</task-memory-max-when>
 <task-memory-free-size>task-memory-free-size</task-memory-free-size>
 <task-memory-overall-report>...</task-memory-overall-report>
 <task-memory-allocator-report>...</task-memory-allocator-report>
 <task-memory-malloc-usage-report>...</task-memory-malloc-usage-report>
 <task-memory-dynamic-allocs>task-memory-dynamic-allocs
 </task-memory-dynamic-allocs>
 <task-memory-max-dynamic-allocs>task-memory-max-dynamic-allocs
 </task-memory-max-dynamic-allocs>
 <task-memory-bss-bytes>task-memory-bss-bytes</task-memory-bss-bytes>
 <task-memory-max-bss-bytes>task-memory-max-bss-bytes
 </task-memory-max-bss-bytes>
 <task-memory-page-data-bytes>task-memory-page-data-bytes
 </task-memory-page-data-bytes>
 <task-memory-max-page-data-bytes>task-memory-max-page-data-bytes
 </task-memory-max-page-data-bytes>
 <task-memory-dir-bytes>task-memory-dir-bytes</task-memory-dir-bytes>
 <task-memory-max-dir-bytes>task-memory-max-dir-bytes
 </task-memory-max-dir-bytes>
 <task-memory-total-bytes-in-use>task-memory-total-bytes-in-use
 </task-memory-total-bytes-in-use>
 <task-memory-total-bytes-percent>task-memory-total-bytes-percent
 </task-memory-total-bytes-percent>
</task-memory-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <task-memory-allocator-report>—No documentation is available yet.
 <task-memory-bss-bytes>—No documentation is available yet.
 <task-memory-dir-bytes>—No documentation is available yet.
 <task-memory-dynamic-allocs>—No documentation is available yet.
 <task-memory-free-size>—No documentation is available yet.
 <task-memory-in-use-avail>—No documentation is available yet.
 <task-memory-in-use-size>—No documentation is available yet.
 <task-memory-malloc-usage-report>—No documentation is available yet.
 <task-memory-max-avail>—No documentation is available yet.
 <task-memory-max-bss-bytes>—No documentation is available yet.

<task-memory-max-dir-bytes>—No documentation is available yet.

<task-memory-max-dynamic-allocs>—No documentation is available yet.

<task-memory-max-page-data-bytes>—No documentation is available yet.

<task-memory-max-size>—No documentation is available yet.

<task-memory-max-when>—No documentation is available yet.

<task-memory-overall-report>—No documentation is available yet.

<task-memory-page-data-bytes>—No documentation is available yet.

<task-memory-total-bytes-in-use>—No documentation is available yet.

<task-memory-total-bytes-percent>—No documentation is available yet.

<task-memory-malloc-usage-report>

Usage <task-memory-information>
 <task-memory-malloc-usage-report>
 <task-malloc-list>...</task-malloc-list>
 <task-memory-total-bytes>*task-memory-total-bytes*</task-memory-total-bytes>
 <task-memory-total-max-bytes>*task-memory-total-max-bytes*
 </task-memory-total-max-bytes>
 </task-memory-malloc-usage-report>
 </task-memory-information>

Description No documentation is available yet.

Contents <task-malloc-list>—No documentation is available yet.
 <task-memory-total-bytes>—No documentation is available yet.
 <task-memory-total-max-bytes>—No documentation is available yet.

<task-memory-overall-report>

Usage <task-memory-information>
 <task-memory-overall-report>
 <task-size-block-list>...</task-size-block-list>
 <task-memory-stats-list>...</task-memory-stats-list>
 <task-memory-total-bytes>*task-mem-total-bytes*</task-memory-total-bytes>
 <task-memory-total-max-bytes>*task-memory-total-max-bytes*
 </task-memory-total-max-bytes>
 <task-memory-total-free-bytes>*task-memory-total-free-bytes*
 </task-memory-total-free-bytes>
 </task-memory-overall-report>
 </task-memory-information>

Description No documentation is available yet.

Contents <task-memory-stats-list>—No documentation is available yet.

<task-memory-total-bytes>—No documentation is available yet.

<task-memory-total-free-bytes>—No documentation is available yet.

<task-memory-total-max-bytes>—No documentation is available yet.

<task-size-block-list>—No documentation is available yet.

<task-memory-stats>

Usage <task-memory-stats-list>
 <task-memory-stats>
 <tms-name>*tms-name*</tms-name>
 <tms-allocs>*tms-allocs*</tms-allocs>
 <tms-mallocs>*tms-mallocs*</tms-mallocs>
 <tms-alloc-bytes>*tms-alloc-bytes*</tms-alloc-bytes>
 <tms-max-allocs>*tms-max-allocs*</tms-max-allocs>
 <tms-max-bytes>*tms-max-bytes*</tms-max-bytes>
 <tms-free-bytes>*tms-free-bytes*</tms-free-bytes>
 </task-memory-stats>
 </task-memory-stats-list>

Description No documentation is available yet.

Contents <tms-alloc-bytes>—Number of bytes now allocated.

<tms-allocs>—Number of items allocated.

<tms-free-bytes>—No documentation is available yet.

<tms-mallocs>—Number of items allocated using malloc.

<tms-max-allocs>—Maximum items ever allocated.

<tms-max-bytes>—Maximum bytes ever allocated.

<tms-name>—No documentation is available yet.

<task-memory-stats-list>

- Usage** <task-memory-overall-report>
 <task-memory-stats-list>
 <task-memory-stats>...</task-memory-stats>
 </task-memory-stats-list>
 </task-memory-overall-report>
- Description** No documentation is available yet.
- Contents** <task-memory-stats>—No documentation is available yet.

<task-replication-state>

- Usage** <rpc-reply>
 <task-replication-state>
 <task-gres-state>*task-gres-state*</task-gres-state>
 <task-re-mode>*task-re-mode*</task-re-mode>
 <task-protocol-replication-state>*task-protocol-replication-state*
 </task-protocol-replication-state>
 <task-protocol-replication-name>*task-protocol-replication-name*
 </task-protocol-replication-name>
 </task-replication-state>
 </rpc-reply>
- Description** Current state of task replication.
- Contents** <task-gres-state>—Current state of graceful Routing Engine Switchover.
- <task-protocol-replication-name>—No documentation is available yet.
- <task-protocol-replication-state>—No documentation is available yet.
- <task-re-mode>—Current mastership state of Routing Engine.

<task-size-block>

Usage <task-size-block-list>
 <task-size-block>
 <tsb-size>*tsb-size*</tsb-size>
 <tsb-terse-transient/>
 <tsb-terse-fullpage/>
 <tsb-allocs>*tsb-allocs*</tsb-allocs>
 <tsb-mallocs>*tsb-mallocs*</tsb-mallocs>
 <tsb-alloc-bytes>*tsb-alloc-bytes*</tsb-alloc-bytes>
 <tsb-max-allocs>*tsb-max-allocs*</tsb-max-allocs>
 <tsb-max-bytes>*tsb-max-bytes*</tsb-max-bytes>
 <tsb-free-bytes>*tsb-free-bytes*</tsb-free-bytes>
 </task-size-block>
 </task-size-block-list>

Description No documentation is available yet.

Contents <tsb-alloc-bytes>—Number of items allocated in bytes.
 <tsb-allocs>—Number of items allocated now not using malloc.
 <tsb-free-bytes>—Number of free bytes.
 <tsb-mallocs>—Number of items allocated using malloc.
 <tsb-max-allocs>—Maximum items ever allocated.
 <tsb-max-bytes>—Maximum items ever allocated in bytes.
 <tsb-size>—Size of this block.
 <tsb-terse-fullpage>—No documentation is available yet.
 <tsb-terse-transient>—No documentation is available yet.

<task-size-block-list>

Usage <task-memory-overall-report>
 <task-size-block-list>
 <task-size-block>...</task-size-block>
 </task-size-block-list>
 </task-memory-overall-report>

Description No documentation is available yet.

Contents <task-size-block>—No documentation is available yet.

<task-timer>

Usage	<pre> <task> <task-timer> <timer-name>timer-name</timer-name> <timer-late/> <timer-expires>timer-expires</timer-expires> <timer-jitter>timer-jitter</timer-jitter> <timer-interval>timer-interval</timer-interval> <timer-flags>timer-flags</timer-flags> </task-timer> </task> </pre>
Description	No documentation is available yet.
Contents	<p><timer-expires>—Time after which timer expires.</p> <p><timer-flags>—No documentation is available yet.</p> <p><timer-interval>—Time to sleep between timer jobs.</p> <p><timer-jitter>—Jitter, in percent.</p> <p><timer-late>—Timer is expired but is still running.</p> <p><timer-name>—Timer name.</p>

<task-timer-information>

Usage	<pre> <rpc-reply> <task-timer-information> <task>...</task> </task-timer-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<task>—No documentation is available yet.

<this-bridge>

Usage	<pre> <cist-bridge-parameters msti-bridge-parameters vst-bridge-parameters> <this-bridge> <bridge-priority>bridge-priority</bridge-priority> <bridge-mac>bridge-mac</bridge-mac> </this-bridge> </cist-bridge-parameters msti-bridge-parameters vst-bridge-parameters> </pre>
Description	ID of bridge.
Contents	<p><bridge-mac>—Media access control address of bridge.</p> <p><bridge-priority>—Bridge priority.</p>

<vlan-map>

- Usage** <mstp-configuration>
 <vlan-map>
 <vlan-map-entry>...</vlan-map-entry>
 </vlan-map>
 </mstp-configuration>
- Description** No documentation is available yet.
- Contents** <vlan-map-entry>—No documentation is available yet.

<vlan-map-entry>

- Usage** <vlan-map>
 <vlan-map-entry>
 <msti-id>*msti-id*</msti-id>
 <vlan-string>*vlan-string*</vlan-string>
 </vlan-map-entry>
 </vlan-map>
- Description** No documentation is available yet.
- Contents** <msti-id>—MSTI ID.
 <vlan-string>—Member VLANs in MSTI.

<vst-bridge-parameters>

Usage <stp-bridge>
 <vst-bridge-parameters>
 <root-bridge>...</root-bridge>
 <root-port>root-port</root-port>
 <root-cost>root-cost</root-cost>
 <hello-time-learned>hello-time-learned</hello-time-learned>
 <max-age-learned>max-age-learned</max-age-learned>
 <forward-delay-learned>forward-delay-learned</forward-delay-learned>
 <msg-age>msg-age</msg-age>
 <time-since-last-tc>time-since-last-tc</time-since-last-tc>
 <topology-change-count>topology-change-count</topology-change-count>
 <extended-system-id>extended-system-id</extended-system-id>
 <this-bridge>...</this-bridge>
 <hello-time-configured>hello-time-configured</hello-time-configured>
 <max-age-configured>max-age-configured</max-age-configured>
 <forward-delay-configured>forward-delay-configured</forward-delay-configured>
 <path-cost-method>path-cost-method</path-cost-method>
 </vst-bridge-parameters>
 </stp-bridge>

Description STP bridge parameters for VLAN Spanning Tree.

Contents <extended-system-id>—Extended system identifier.

<forward-delay-configured>—Forward delay configured on this bridge.

<forward-delay-learned>—Forward delay.

<hello-time-configured>—Hello time configured on this bridge.

<hello-time-learned>—Hello time.

<max-age-configured>—Maximum age configured on this bridge.

<max-age-learned>—Maximum age for received BPDUs.

<msg-age>—Age of the received BPDU.

<path-cost-method>—Type of path cost method currently in use.

<root-bridge>—Root bridge identifier.

<root-cost>—Root cost.

<root-port>—Root port.

<this-bridge>—ID of bridge.

<time-since-last-tc>—Time since last topology change.

<topology-change-count>—Number of topology changes.

<vstp-interface-statistics>

- Usage** `<stp-interface-statistics>`
 <vstp-interface-statistics>
 `<stp-interface-statistics-entry>...</stp-interface-statistics-entry>`
 </vstp-interface-statistics>
 `</stp-interface-statistics>`
- Description** Statistics information about one or more VLAN STP interfaces.
- Contents** `<stp-interface-statistics-entry>`—Spanning Tree Protocol interface statistics.

<vstp-statistics>

- Usage** `<stp-context-statistics-information>`
 <vstp-statistics>
 `<message-type>message-type</message-type>`
 `<total-bpdus-sent>total-bpdus-sent</total-bpdus-sent>`
 `<total-bpdus-received>total-bpdus-received</total-bpdus-received>`
 `<bpdus-sent-5seconds>bpdus-sent-5seconds</bpdus-sent-5seconds>`
 `<bpdus-received-5seconds>bpdus-recd-5secs</bpdus-received-5seconds>`
 </vstp-statistics>
 `</stp-context-statistics-information>`
- Description** VLAN Spanning Tree Protocol statistics.
- Contents** `<bpdus-received-5seconds>`—Total number of BPDUs received on this routing instance in last 5 secs.
- `<bpdus-sent-5seconds>`—Total number of BPDUs sent out for this routing instance in last 5 secs.
- `<message-type>`—Spanning Tree message type.
- `<total-bpdus-received>`—Total number of BPDUs received.
- `<total-bpdus-sent>`—Total number of BPDUs sent out.

Summary of License Response Tags

This section lists JUNOS XML tags that contain operational information about licenses on J-series platforms. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-license>. To review the DTD for the tags, see “DTD for License Response Tags” on page 1863.

<add-individual-result>

Usage	<pre> <add-license-results> <add-individual-result> <operation-status>operation-status</operation-status> <filename>filename</filename> <line-number>line-number</line-number> <name>name</name> <message>message</message> </add-individual-result> </add-license-results> </pre>
Description	Report status of individual license add operation.
Contents	<p><filename>—File name in which error exist.</p> <p><line-number>—Line number where error exist.</p> <p><message>—Text to explain the status of an operation.</p> <p><name>—Identifier for this object.</p> <p><operation-status>—Defines that status of a license operation.</p>

<add-license-results>

Usage	<pre> <rpc-reply> <add-license-results> <add-individual-result>...</add-individual-result> <add-error-count>add-error-count</add-error-count> <add-success/> </add-license-results> </rpc-reply> </pre>
Description	Results of license add operation.
Contents	<p><add-error-count>—Number of errors during add license operation.</p> <p><add-individual-result>—Report status of individual license add operation.</p> <p><add-success>—Add completed with no errors.</p>

<feature>

Usage	<pre><feature-block> <feature> <name>name</name> <description>description</description> <validity-information>...</validity-information> </feature> </feature-block></pre>
Description	A single feature instance.
Contents	<p><description>—Description of feature.</p> <p><name>—Identifier for this object.</p> <p><validity-information>—No documentation is available yet.</p>

<feature-block>

Usage	<pre><license> <feature-block> <feature>...</feature> </feature-block> </license></pre>
Description	No documentation is available yet.
Contents	<feature>—A single feature instance.

<feature-summary>

Usage <license-usage-summary>
 <feature-summary>
 <name>*name*</name>
 <description>*description*</description>
 <licensed>*licensed*</licensed>
 <used-licensed>*used-licensed*</used-licensed>
 <used-given>*used-given*</used-given>
 <needed>*needed*</needed>
 <validity-type>*validity-type*</validity-type>
 <remaining-time>...</remaining-time>
 <end-date>*end-date*</end-date>
 </feature-summary>
 </license-usage-summary>

Description No documentation is available yet.

Contents <description>—Description of feature.

<end-date>—No documentation is available yet.

<licensed>—Number available in valid licenses.

<name>—Identifier for this object.

<needed>—Number used that require a license above licensed count.

<remaining-time>—No documentation is available yet.

<used-given>—Number used that do not require a license.

<used-licensed>—Number used that require a license.

<validity-type>—Type of validity of the license.

<license>

Usage <license-information>
 <license>
 <name>*name*</name>
 <license-state>*license-state*</license-state>
 <license-version>*license-version*</license-version>
 <license-type>*license-type*</license-type>
 <device-reference>*device-reference*</device-reference>
 <group-reference>*group-reference*</group-reference>
 <group-define>*group-define*</group-define>
 <unsupported-attribute>*unsupported-attribute*</unsupported-attribute>
 <feature-block>...</feature-block>
 </license>
 </license-information>

Description No documentation is available yet.

Contents <device-reference>—License is tied to this device.

<feature-block>—No documentation is available yet.

<group-define>—License defines device to be part of this license group.

<group-reference>—License is tied to this group.

<license-state>—License state.

<license-type>—Type of license.

<license-version>—Version of license.

<name>—Identifier for this object.

<unsupported-attribute>—An attribute that is not recognized by this implementation.

<license-information>

Usage <license-summary-information>
 <license-information>
 <no-licenses-installed/>
 <licenses-installed/>
 <license>...</license>
 </license-information>
 </license-summary-information>

Description Information about feature licenses installed on device.

Contents <license>—No documentation is available yet.

<licenses-installed>—Feature licenses are installed.

<no-licenses-installed>—No feature licenses are installed.

<license-key>

Usage	<pre> <license-key-information> <license-key> <name>name</name> <key-data>key-data</key-data> </license-key> </license-key-information> </pre>
Description	No documentation is available yet.
Contents	<p><key-data>—Textual license key.</p> <p><name>—Identifier for this object.</p>

<license-key-information>

Usage	<pre> <rpc-reply> <license-key-information> <license-key>...</license-key> </license-key-information> </rpc-reply> </pre>
Description	Textual license keys.
Contents	<license-key>—No documentation is available yet.

<license-summary-information>

Usage	<pre> <rpc-reply> <license-summary-information> <license-usage-summary>...</license-usage-summary> <license-information>...</license-information> </license-summary-information> </rpc-reply> </pre>
Description	Feature license information.
Contents	<p><license-information>—Information about feature licenses installed on device.</p> <p><license-usage-summary>—Information about features licensed on this device.</p>

<license-usage-summary>

Usage	<pre> <license-summary-information> <license-usage-summary> <features-used/> <no-feature-used/> <feature-summary>...</feature-summary> </license-usage-summary> </license-summary-information> </pre>
Description	Information about features licensed on this device.
Contents	<p><feature-summary>—No documentation is available yet.</p> <p><features-used>—Licensed features are being used.</p> <p><no-feature-used>—No licensed feature is being used.</p>

<original-validity>

Usage	<pre> <validity-information> <original-validity> <original-validity-value>original-validity-value</original-validity-value> <original-validity-time-unit>original-validity-time-unit </original-validity-time-unit> </original-validity> </validity-information> </pre>
Description	No documentation is available yet.
Contents	<p><original-validity-time-unit>—Unit of time measurement.</p> <p><original-validity-value>—Integer value.</p>

<remaining-time>

Usage	<pre> <validity-information feature-summary> <remaining-time> <remaining-validity-value>remaining-validity-value</remaining-validity-value> <remaining-validity-time-unit>remaining-validity-time-unit </remaining-validity-time-unit> </remaining-time> </validity-information feature-summary> </pre>
Description	No documentation is available yet.
Contents	<p><remaining-validity-time-unit>—Unit of time measurement.</p> <p><remaining-validity-value>—Integer value.</p>

<validity-information>

Usage <feature>
 <validity-information>
 <validity-type>*validity-type*</validity-type>
 <original-validity>...</original-validity>
 <remaining-time>...</remaining-time>
 <start-date>*start-date*</start-date>
 <end-date>*end-date*</end-date>
 <license-state>*license-state*</license-state>
 </validity-information>
 </feature>

Description No documentation is available yet.

Contents <end-date>—No documentation is available yet.

<license-state>—License state.

<original-validity>—No documentation is available yet.

<remaining-time>—No documentation is available yet.

<start-date>—No documentation is available yet.

<validity-type>—Type of validity of the license.

Summary of Licensed Feature Metadata Response Tags

This section lists JUNOS XML tags that contain operational information about the licensed feature metadata. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-licensed-feature-metadata>. To review the DTD for the tags, see “DTD for Licensed Feature Metadata Response Tags” on page 1867

<alias>

Usage	<pre> <licensed-feature> <alias> <base-feature>base-feature</base-feature> <cummulative-value>cummulative-value</cummulative-value> </alias> </licensed-feature> </pre>
Description	No documentation is available yet.
Contents	<p><base-feature>—Alias for the base feature.</p> <p><cummulative-value>—The number of features being aliased.</p>

<licensed-feature>

Usage	<pre> <licensed-feature-metadata-information> <licensed-feature> <id>id</id> <name>name</name> <description>description</description> <flag>flag</flag> <alias>...</alias> </licensed-feature> </licensed-feature-metadata-information> </pre>
Description	Information on a licensed feature.
Contents	<p><alias>—No documentation is available yet.</p> <p><description>—Feature description.</p> <p><flag>—Feature flags.</p> <p><id>—Feature ID.</p> <p><name>—Feature display name.</p>

<licensed-feature-metadata-information>

- Usage** <rpc-reply>
 <licensed-feature-metadata-information>
 <licensed-feature>...</licensed-feature>
 </licensed-feature-metadata-information>
</rpc-reply>
- Description** Information on one or more licensed features.
- Contents** <licensed-feature>—Information on a licensed feature.

Summary of Link-Fault Management Response Tags

This section lists JUNOS XML tags that contain operational information about link-fault management (802.3ah Operation, Administration, and Management). The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-lfm>. To review the DTD for the tags, see “DTD for Link-Fault Management Response Tags” on page 1857

<lfmd-action-profile-information>

```

Usage    <lfmd-information>
            <lfmd-action-profile-information>
              <lfmd-action-profile-name>lfmd-action-profile-name</lfmd-action-profile-name>
              <lfmd-action-profile-invoke-count>lfmd-action-profile-invoke-count
                </lfmd-action-profile-invoke-count>
              <lfmd-action-profile-execution-count>lfmd-action-profile-execution-count
                </lfmd-action-profile-execution-count>
            </lfmd-action-profile-information>
          </lfmd-information>

```

Description Link-fault action profile information.

Contents <lfmd-action-profile-execution-count>—Number of times the action profile has been executed.

<Ifmd-action-profile-invoke-count>—Number of times the action profile has been invoked.

<lfmd-action-profile-name>—Name of action profile.

<lfmd-discovery-flags>

Usage <lfmd-interface-information>
 <lfmd-discovery-flags>
 <lfmd-flag-remote-stable/>
 <lfmd-flag-remote-evaluating/>
 <lfmd-flag-remote-state-valid/>
 <lfmd-flag-local-satisfied/>
 <lfmd-flag-local-stable/>
 <lfmd-pdu-flags>*lfmd-pdu-flags*</lfmd-pdu-flags>
 </lfmd-discovery-flags>
 </lfmd-interface-information>

Description No documentation is available yet.

Contents <lfmd-flag-local-satisfied>—No documentation is available yet.
 <lfmd-flag-local-stable>—No documentation is available yet.
 <lfmd-flag-remote-evaluating>—No documentation is available yet.
 <lfmd-flag-remote-stable>—No documentation is available yet.
 <lfmd-flag-remote-state-valid>—No documentation is available yet.
 <lfmd-pdu-flags>—No documentation is available yet.

<lfmd-event-received-frame-error>

Usage <lfmd-events-received>
 <lfmd-event-received-frame-error>
 <lfmd-event-received-frame-error-window>*lfmd-event-received-frame-error-window*
 </lfmd-event-received-frame-error-window>

 <lfmd-event-received-frame-error-threshold>*lfmd-event-received-frame-error-threshold*
 </lfmd-event-received-frame-error-threshold>
 <lfmd-event-received-frame-error-count>*lfmd-event-received-frame-error-count*
 </lfmd-event-received-frame-error-count>

 <lfmd-event-received-frame-error-total-count>*lfmd-event-received-frame-error-total-count*
 </lfmd-event-received-frame-error-total-count>
 <lfmd-event-received-frame-count>*lfmd-event-received-frame-count*
 </lfmd-event-received-frame-count>
 </lfmd-event-received-frame-error>
 </lfmd-events-received>

Description Errored frame event information.

Contents <lfmd-event-received-frame-count>—Errored frame event count.

 <lfmd-event-received-frame-error-count>—Errored frame count.

 <lfmd-event-received-frame-error-threshold>—Errored frame event threshold.

 <lfmd-event-received-frame-error-total-count>—Errored frame event total count.

 <lfmd-event-received-frame-error-window>—Errored frame event window.

<lfmd-event-received-frame-period-error>

Usage <lfmd-events-received>
 <lfmd-event-received-frame-period-error>
 <lfmd-event-received-frame-period-error-window>*lfmd-evnt-recd-frame-per-err-window*
 </lfmd-event-received-frame-period-error-window>
 <lfmd-event-received-frame-period-error-threshold>*lfmd-evnt-recd-frame-perd-err-thr*
 </lfmd-event-received-frame-period-error-threshold>
 <lfmd-event-received-frame-period-error-count>*lfmd-evnt-re-fr-per-err-cnt*
 </lfmd-event-received-frame-period-error-count>
 <lfmd-event-received-frame-period-error-total-count>*lfmd-evnt-recd-frm-per-err-tot-cnt*
 </lfmd-event-received-frame-period-error-total-count>
 <lfmd-event-received-frame-period-count>*lfmd-event-received-frame-period-count*
 </lfmd-event-received-frame-period-count>
 </lfmd-event-received-frame-period-error>
 </lfmd-events-received>

Description Errored frame period event information.

Contents <lfmd-event-received-frame-period-count>—Errored frame period event count.

<lfmd-event-received-frame-period-error-count>—Errored frame period count.

<lfmd-event-received-frame-period-error-threshold>—Errored frame period event threshold.

<lfmd-event-received-frame-period-error-total-count>—Errored frame period event total count.

<lfmd-event-received-frame-period-error-window>—Errored frame period event window.

<lfmd-event-received-frame-seconds-error>

Usage <lfmd-events-received>
 <lfmd-event-received-frame-seconds-error>
 <lfmd-event-received-frame-seconds-error-window>*lfm-evnt-recd-frame-secs-error-window*
 </lfmd-event-received-frame-seconds-error-window>
 <lfmd-event-received-frame-seconds-error-threshold>*lfmd-e-re-frame-secs-err-thresh*
 </lfmd-event-received-frame-seconds-error-threshold>
 <lfmd-event-received-frame-seconds-error-count>*lfmd-evt-recd-frame-secs-err-count*
 </lfmd-event-received-frame-seconds-error-count>
 <lfmd-event-received-frame-seconds-error-total-count>*lfmd-ev-rec-frm-sec-err-tot-cnt*
 </lfmd-event-received-frame-seconds-error-total-count>
 <lfmd-event-received-frame-seconds-count>*lfmd-evt-recd-frame-secs-cnt*
 </lfmd-event-received-frame-seconds-count>
 </lfmd-event-received-frame-seconds-error>
 </lfmd-events-received>

Description Errored frame seconds event information.

Contents <lfmd-event-received-frame-seconds-count>—Errored frame seconds event count.

<lfmd-event-received-frame-seconds-error-count>—Errored frame seconds count.

<lfmd-event-received-frame-seconds-error-threshold>—Errored frame seconds event threshold.

<lfmd-event-received-frame-seconds-error-total-count>—Errored frame seconds event total count.

<lfmd-event-received-frame-seconds-error-window>—Errored frame seconds event window.

<lfmd-event-received-symbol-error>

Usage <lfmd-events-received>
 <lfmd-event-received-symbol-error>
 <lfmd-event-received-symbol-error-window>*lfmd-ev-rec-sy-er-win*
 </lfmd-event-received-symbol-error-window>
 <lfmd-event-received-symbol-error-threshold>*lfmd-evt-recd-symbol-err-thresh*
 </lfmd-event-received-symbol-error-threshold>
 <lfmd-event-received-symbol-error-count>*lfmd-event-received-symbol-error-count*
 </lfmd-event-received-symbol-error-count>
 <lfmd-event-received-symbol-error-total-count>*lfmd-evt-recd-symbol-err-tot-cnt*
 </lfmd-event-received-symbol-error-total-count>
 <lfmd-event-received-symbol-count>*lfmd-event-received-symbol-count*
 </lfmd-event-received-symbol-count>
 </lfmd-event-received-symbol-error>
 </lfmd-events-received>

Description Errored symbol period event information.

Contents <lfmd-event-received-symbol-count>—Errored symbol period event count.

<lfmd-event-received-symbol-error-count>—Errored symbol count.

<lfmd-event-received-symbol-error-threshold>—Errored symbol period event threshold.

<lfmd-event-received-symbol-error-total-count>—Errored symbol period event total count.

<lfmd-event-received-symbol-error-window>—Errored symbol period event window.

<lfmd-event-transmitted-frame-error>

Usage <lfmd-events-transmitted>
 <lfmd-event-transmitted-frame-error>
 <lfmd-event-transmitted-frame-error-window>*lfmd-event-transmitted-frame-error-window*
 </lfmd-event-transmitted-frame-error-window>
 <lfmd-event-transmitted-frame-error-threshold>*lfmd-evt-transd-frame-err-threshold*
 </lfmd-event-transmitted-frame-error-threshold>
 <lfmd-event-transmitted-frame-error-count>*lfmd-evt-transd-frame-err-count*
 </lfmd-event-transmitted-frame-error-count>
 <lfmd-event-transmitted-frame-error-total-count>*lfmd-evt-transd-frame-err-total-count*
 </lfmd-event-transmitted-frame-error-total-count>
 <lfmd-event-transmitted-frame-count>*lfmd-event-transmitted-frame-count*
 </lfmd-event-transmitted-frame-count>
 </lfmd-event-transmitted-frame-error>
 </lfmd-events-transmitted>

Description Errored frame event information.

Contents <lfmd-event-transmitted-frame-count>—Errored frame event count.

<lfmd-event-transmitted-frame-error-count>—Errored frame count.

<lfmd-event-transmitted-frame-error-threshold>—Errored frame event threshold.

<lfmd-event-transmitted-frame-error-total-count>—Errored frame event total count.

<lfmd-event-transmitted-frame-error-window>—Errored frame event window.

<lfmd-event-transmitted-symbol-error>

Usage <lfmd-events-transmitted>
 <lfmd-event-transmitted-symbol-error>
 <lfmd-event-transmitted-symbol-error-window>*lfmd-evt-tr-sy-er-win*
 </lfmd-event-transmitted-symbol-error-window>
 <lfmd-event-transmitted-symbol-error-threshold>*lfmd-evt-tr-syl-err-threshold*
 </lfmd-event-transmitted-symbol-error-threshold>
 <lfmd-event-transmitted-symbol-error-count>*lfmd-evt-tr-sy-err-cnt*
 </lfmd-event-transmitted-symbol-error-count>
 <lfmd-event-transmitted-symbol-error-total-count>*lfmd-evt-tr-sym-err-tot-cnt*
 </lfmd-event-transmitted-symbol-error-total-count>
 <lfmd-event-transmitted-symbol-count>*lfmd-ev-tr-sy-co*
 </lfmd-event-transmitted-symbol-count>
 </lfmd-event-transmitted-symbol-error>
 </lfmd-events-transmitted>

Description Errored symbol period event information.

Contents <lfmd-event-transmitted-symbol-count>—Errored symbol period event count.

<lfmd-event-transmitted-symbol-error-count>—Errored symbol period event count.

<lfmd-event-transmitted-symbol-error-threshold>—Errored symbol period event threshold.

<lfmd-event-transmitted-symbol-error-total-count>—Errored symbol period event total count.

<lfmd-event-transmitted-symbol-error-window>—Errored symbol period event window.

<lfmd-events>

Usage <lfmd-interface-information>
 <lfmd-events>
 <lfmd-events-received>...</lfmd-events-received>
 <lfmd-events-transmitted>...</lfmd-events-transmitted>
 </lfmd-events>
 </lfmd-interface-information>

Description Event information.

Contents <lfmd-events-received>—Received link events.

<lfmd-events-transmitted>—Transmitted link events.

<lfmd-events-received>

Usage <lfmd-events>
 <lfmd-events-received>
 <lfmd-event-received-symbol-error>...</lfmd-event-received-symbol-error>
 <lfmd-event-received-frame-error>...</lfmd-event-received-frame-error>
 <lfmd-event-received-frame-period-error>...
 </lfmd-event-received-frame-period-error>
 <lfmd-event-received-frame-seconds-error>...
 </lfmd-event-received-frame-seconds-error>
 </lfmd-events-received>
 </lfmd-events>

Description Received link events.

Contents <lfmd-event-received-frame-error>—Errored frame event information.

<lfmd-event-received-frame-period-error>—Errored frame period event information.

<lfmd-event-received-frame-seconds-error>—Errored frame seconds event information.

<lfmd-event-received-symbol-error>—Errored symbol period event information.

<lfmd-events-transmitted>

Usage <lfmd-events>
 <lfmd-events-transmitted>
 <lfmd-event-transmitted-symbol-error>...</lfmd-event-transmitted-symbol-error>
 <lfmd-event-transmitted-frame-error>...</lfmd-event-transmitted-frame-error>
 </lfmd-events-transmitted>
 </lfmd-events>

Description Transmitted link events.

Contents <lfmd-event-transmitted-frame-error>—Errored frame event information.

<lfmd-event-transmitted-symbol-error>—Errored symbol period event information.

<lfmd-information>

Usage <rpc-reply>
 <lfmd-information>
 <lfmd-interface-information>...</lfmd-interface-information>
 <lfmd-action-profile-information>...</lfmd-action-profile-information>
 </lfmd-information>
 </rpc-reply>

Description Information about the Link-Fault Management protocol.

Contents <lfmd-action-profile-information>—Link-fault action profile information.

<lfmd-interface-information>—Link-fault management information for one or more interfaces.

<lfmd-interface-information>

Usage <lfmd-information>
 <lfmd-interface-information>
 <lfmd-interface-name>*lfmd-interface-name*</lfmd-interface-name>
 <lfmd-status>*lfmd-status*</lfmd-status>
 <lfmd-discovery-state>*lfmd-discovery-state*</lfmd-discovery-state>
 <lfmd-discovery-flags>...</lfmd-discovery-flags>
 <lfmd-peer-address>*lfmd-peer-address*</lfmd-peer-address>
 <lfmd-peer-mux-action>*lfmd-peer-mux-action*</lfmd-peer-mux-action>
 <lfmd-peer-parser-action>*lfmd-peer-parser-action*</lfmd-peer-parser-action>
 <lfmd-peer-config-mode>*lfmd-peer-config-mode*</lfmd-peer-config-mode>
 <lfmd-peer-config-unidirectional>*lfmd-peer-config-unidirectional*
 </lfmd-peer-config-unidirectional>
 <lfmd-peer-config-loopback>*lfmd-peer-config-loopback*
 </lfmd-peer-config-loopback>
 <lfmd-peer-config-link-events>*lfmd-peer-config-link-events*
 </lfmd-peer-config-link-events>
 <lfmd-peer-config-variable-request>*lfmd-peer-config-variable-request*
 </lfmd-peer-config-variable-request>
 <lfmd-loopback-local-enabled/>
 <lfmd-loopback-remote-enabled/>
 <lfmd-statistics>...</lfmd-statistics>
 <lfmd-events>...</lfmd-events>
 </lfmd-interface-information>
 </lfmd-information>

Description Link-fault management information for one or more interfaces.

Contents <lfmd-discovery-flags>—No documentation is available yet.

<lfmd-discovery-state>—No documentation is available yet.

<lfmd-events>—Event information.

<lfmd-interface-name>—Name of interface.

<lfmd-loopback-local-enabled>—No documentation is available yet.

<lfmd-loopback-remote-enabled>—No documentation is available yet.

<lfmd-peer-address>—No documentation is available yet.

<lfmd-peer-config-link-events>—Support for remote peer link events.

<lfmd-peer-config-loopback>—Support for remote peer loopback mode.

<lfmd-peer-config-mode>—Remote peer discovery configuration.

<lfmd-peer-config-unidirectional>—Support for remote peer unidirectional mode.

<lfmd-peer-config-variable-request>—Support for remote peer variable requests.

<lfmd-peer-mux-action>—Remote multiplexor action.

<lfmd-peer-parser-action>—Remote parser action.

<lfmd-statistics>—Interface statistics.

<lfmd-status>—Status of 802.3ah on the interface.

<lfmd-statistics>

Usage <lfmd-interface-information>
 <lfmd-statistics>
 <lfmd-statistics-received>...</lfmd-statistics-received>
 <lfmd-statistics-transmitted>...</lfmd-statistics-transmitted>
 </lfmd-statistics>
</lfmd-interface-information>

Description Interface statistics.

Contents <lfmd-statistics-received>—OAM receive statistics.

<lfmd-statistics-transmitted>—OAM transmit statistics.

<lfmd-statistics-received>

Usage <lfmd-statistics>
<lfmd-statistics-received>
 <lfmd-information-pdus-received>*lfmd-information-pdus-received*
 </lfmd-information-pdus-received>
 <lfmd-event-pdus-received>*lfmd-event-pdus-received*</lfmd-event-pdus-received>
 <lfmd-variable-request-pdus-received>*lfmd-variable-request-pdus-received*
 </lfmd-variable-request-pdus-received>
 <lfmd-variable-response-pdus-received>*lfmd-variable-response-pdus-received*
 </lfmd-variable-response-pdus-received>
 <lfmd-loopback-control-pdus-received>*lfmd-loopback-control-pdus-received*
 </lfmd-loopback-control-pdus-received>
 <lfmd-organization-pdus-received>*lfmd-organization-pdus-received*
 </lfmd-organization-pdus-received>
 <lfmd-unknown-pdus-received>*lfmd-unknown-pdus-received*
 </lfmd-unknown-pdus-received>
 <lfmd-critical-event-received>*lfmd-critical-event-received*
 </lfmd-critical-event-received>
 <lfmd-dying-gasp-received>*lfmd-dying-gasp-received*</lfmd-dying-gasp-received>
 <lfmd-link-fault-received>*lfmd-link-fault-received*</lfmd-link-fault-received>
</lfmd-statistics-received>
 </lfmd-statistics>

Description OAM receive statistics.

Contents <lfmd-critical-event-received>—Number of PDUs received with Critical event flag bit set.

<lfmd-dying-gasp-received>—Number of PDUs received with Dying gasp flag bit set.

<lfmd-event-pdus-received>—Number of event PDUs received.

<lfmd-information-pdus-received>—Number of information PDUs received.

<lfmd-link-fault-received>—Number of PDUs received with Link fault flag bit set.

<lfmd-loopback-control-pdus-received>—Number of loopback-control PDUs received.

<lfmd-organization-pdus-received>—Number of organization-specific PDUs received.

<lfmd-unknown-pdus-received>—Number of unknown PDUs received.

<lfmd-variable-request-pdus-received>—Number of variable-request PDUs received.

<lfmd-variable-response-pdus-received>—Number of variable-response PDUs received.

<lfmd-statistics-transmitted>

Usage <lfmd-statistics>
<lfmd-statistics-transmitted>
 <lfmd-information-pdus-transmitted>*lfmd-information-pdus-transmitted*
 </lfmd-information-pdus-transmitted>
 <lfmd-event-pdus-transmitted>*lfmd-event-pdus-transmitted*
 </lfmd-event-pdus-transmitted>
 <lfmd-variable-request-pdus-transmitted>*lfmd-variable-request-pdus-transmitted*
 </lfmd-variable-request-pdus-transmitted>
 <lfmd-variable-response-pdus-transmitted>*lfmd-variable-response-pdus-transmitted*
 </lfmd-variable-response-pdus-transmitted>
 <lfmd-loopback-control-pdus-transmitted>*lfmd-loopback-control-pdus-transmitted*
 </lfmd-loopback-control-pdus-transmitted>
 <lfmd-organization-pdus-transmitted>*lfmd-organization-pdus-transmitted*
 </lfmd-organization-pdus-transmitted>
 <lfmd-unknown-pdus-transmitted>*lfmd-unknown-pdus-transmitted*
 </lfmd-unknown-pdus-transmitted>
</lfmd-statistics-transmitted>
 </lfmd-statistics>

Description OAM transmit statistics.

Contents <lfmd-event-pdus-transmitted>—Number of event PDUs transmitted.

<lfmd-information-pdus-transmitted>—Number of information PDUs transmitted.

<lfmd-loopback-control-pdus-transmitted>—Number of loopback-control PDUs transmitted.

<lfmd-organization-pdus-transmitted>—Number of organization-specific PDUs transmitted.

<lfmd-unknown-pdus-transmitted>—Number of unknown PDUs transmitted.

<lfmd-variable-request-pdus-transmitted>—Number of variable-request PDUs transmitted.

<lfmd-variable-response-pdus-transmitted>—Number of variable-response PDUs transmitted.

Summary of MIP Response Tags

This section lists JUNOS XML tags that contain operational information about MIP. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-mip>. To review the DTD for the tags, see “DTD for MIP Response Tags” on page 1873.

<addr-pool>

Usage	<pre><mip-home-agent-virtual-network mip-home-agent-interface-network> <addr-pool> <start-addr>start-addr</start-addr> <end-addr>end-addr</end-addr> </addr-pool> </mip-home-agent-virtual-network mip-home-agent-interface-network></pre>
Description	Mobile IP ha address pool.
Contents	<p><end-addr>—Ending address for the pool.</p> <p><start-addr>—Starting address for the pool.</p>

<address-list>

Usage	<pre><mip-home-agent-overview> <address-list> <address>address</address> </address-list> </mip-home-agent-overview></pre>
Description	Mobile IP HA address list.
Contents	<address>—Home agent address.

<mip-binding>

Usage <mip-binding-information>
 <mip-binding>
 <mip-home-address>*mip-home-address*</mip-home-address>
 <mip-nai>*mip-nai*</mip-nai>
 <mip-home-agent>*mip-home-agent*</mip-home-agent>
 <mip-care-of-address>*mip-care-of-address*</mip-care-of-address>
 <lifetime-granted>*lifetime-granted*</lifetime-granted>
 <lifetime-remaining>*lifetime-remaining*</lifetime-remaining>
 <tunnel-type>*tunnel-type*</tunnel-type>
 <tunnel-id>*tunnel-id*</tunnel-id>
 <tunnel-source>*tunnel-source*</tunnel-source>
 <tunnel-destination>*tunnel-destination*</tunnel-destination>
 <identification>*identification*</identification>
 <revocation-support>*revocation-support*</revocation-support>
 <revocation-inform>*revocation-inform*</revocation-inform>
 <count>*count*</count>
 </mip-binding>
 </mip-binding-information>

Description No documentation is available yet.

Contents <count>—Mobile IP Binding Count.

<identification>—Mobile IP identification.

<lifetime-granted>—Mobile IP Registration Lifetime Granted by HA.

<lifetime-remaining>—Mobile IP Lifetime remaining for mobile node to re-register.

<mip-care-of-address>—Mobile IP care-of-address.

<mip-home-address>—Mobile node's home address.

<mip-home-agent>—Mobile node's home agent address.

<mip-nai>—Mobile IP network access identifier.

<revocation-inform>—Mobile IP revocation inform to MN.

<revocation-support>—Mobile IP revocation support.

<tunnel-destination>—Mobile IP tunnel destination.

<tunnel-id>—Mobile IP tunnel ID.

<tunnel-source>—Mobile IP tunnel source.

<tunnel-type>—Mobile IP tunnel type.

<mip-binding-information>

- Usage** <rpc-reply>
 <mip-binding-information>
 <mip-binding>...</mip-binding>
 </mip-binding-information>
 </rpc-reply>
- Description** Mobile IP Binding information.
- Contents** <mip-binding>—No documentation is available yet.

<mip-error>

- Usage** <rpc-reply>
 <mip-error>
 <mip-error-message>*mip-error-message*</mip-error-message>
 </mip-error>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <mip-error-message>—MIP error message.

<mip-fa>

Usage <mip-fa-information>
 <mip-fa>
 <mip-fa-status>*mip-fa-status*</mip-fa-status>
 <mip-fa-max-pending-request>*mip-fa-max-pending-request*
 </mip-fa-max-pending-request>
 <mip-fa-request-timeout>*mip-fa-request-timeout*</mip-fa-request-timeout>
 <mip-fa-registration-required>*mip-fa-registration-required*
 </mip-fa-registration-required>
 <mip-fa-registration-lifetime>*mip-fa-registration-lifetime*
 </mip-fa-registration-lifetime>
 <mip-fa-coa>*mip-fa-coa*</mip-fa-coa>
 <mip-fa-serice-enabled>*mip-fa-serice-enabled*</mip-fa-serice-enabled>
 <mip-fa-reverse-tunnel>*mip-fa-reverse-tunnel*</mip-fa-reverse-tunnel>
 </mip-fa>
 </mip-fa-information>

Description Mobile IP foreign agent information.

Contents <mip-fa-coa>—Mobile IP foreign agent care-of-address's used.

<mip-fa-max-pending-request>—Mobile IP foreign agent maximum pending request.

<mip-fa-registration-lifetime>—Mobile IP foreign agent registration lifetime.

<mip-fa-registration-required>—Mobile foreign agent registration required flag.

<mip-fa-request-timeout>—Mobile IP foreign agent request timeout.

<mip-fa-reverse-tunnel>—Mobile IP foreign agent reverse tunnel.

<mip-fa-serice-enabled>—Mobile IP foreign agent enabled on.

<mip-fa-status>—Mobile IP foreign agent status.

<mip-fa-information>

Usage <rpc-reply>
 <mip-fa-information>
 <mip-fa>...</mip-fa>
 </mip-fa-information>
 </rpc-reply>

Description Mobile IP foreign agent information.

Contents <mip-fa>—Mobile IP foreign agent information.

<mip-home-agent-interface-network>

Usage <mip-home-agent-interface-network-information>
 <mip-home-agent-interface-network>
 <interface>*interface*</interface>
 <mip-home-agent>*mip-home-agent*</mip-home-agent>
 <registration-lifetime>*registration-lifetime*</registration-lifetime>
 <time-tolerance>*time-tolerance*</time-tolerance>
 <addr-pool>...</addr-pool>
 <number-of-mn>*number-of-mn*</number-of-mn>
 <mip-home-address>*mip-home-address*</mip-home-address>
 <range>*range*</range>
 <mip-nai>*mip-nai*</mip-nai>
 <mip-care-of-address>*mip-care-of-address*</mip-care-of-address>
 <lifetime-granted>*lifetime-granted*</lifetime-granted>
 <lifetime-remaining>*lifetime-remaining*</lifetime-remaining>
 </mip-home-agent-interface-network>
 </mip-home-agent-interface-network-information>

Description Mobile IP interface-network information.

Contents <addr-pool>—Mobile IP ha address pool.

<interface>—Mobile IP Home agent interface.

<lifetime-granted>—Mobile IP Registration Lifetime Granted by HA.

<lifetime-remaining>—Mobile IP Lifetime remaining for mobile node to re-register.

<mip-care-of-address>—Mobile IP care-of-address.

<mip-home-address>—Mobile node's home address.

<mip-home-agent>—Mobile node's home agent address.

<mip-nai>—Mobile IP network access identifier.

<number-of-mn>—Mobile IP number of MNs.

<range>—Mobile IP ha valid address range .

<registration-lifetime>—Mobile IP Registration lifetime.

<time-tolerance>—Mobile IP time tolerance.

<mip-home-agent-interface-network-information>

- Usage** <rpc-reply>
 <mip-home-agent-interface-network-information>
 <mip-home-agent-interface-network>...</mip-home-agent-interface-network>
 </mip-home-agent-interface-network-information>
 </rpc-reply>
- Description** Mobile IP home-agent interface-network information.
- Contents** <mip-home-agent-interface-network>—Mobile IP interface-network information.

<mip-home-agent-overview>

- Usage** <mip-home-agent-overview-information>
 <mip-home-agent-overview>
 <status>status</status>
 <service-enabled-on>...</service-enabled-on>
 <address-list>...</address-list>
 <authentication>authentication</authentication>
 </mip-home-agent-overview>
 </mip-home-agent-overview-information>
- Description** No documentation is available yet.
- Contents** <address-list>—Mobile IP HA address list.
- <authentication>—Mobile IP Authentication.
- <service-enabled-on>—Mobile IP HA enabled interfaces.
- <status>—Mobile IP HA status.

<mip-home-agent-overview-information>

- Usage** <rpc-reply>
 <mip-home-agent-overview-information>
 <mip-home-agent-overview>...</mip-home-agent-overview>
 </mip-home-agent-overview-information>
 </rpc-reply>
- Description** Mobile IP home-agent overview.
- Contents** <mip-home-agent-overview>—No documentation is available yet.

<mip-home-agent-traffic>

Usage <mip-home-agent-traffic-information>
 <mip-home-agent-traffic>
 <request-received>*request-received*</request-received>
 <request-forwarded>*request-forwarded*</request-forwarded>
 <request-denied>*request-denied*</request-denied>
 <replies-forwarded>*replies-forwarded*</replies-forwarded>
 <unspecified>*unspecified*</unspecified>
 <administrative-prohibited>*administrative-prohibited*
 </administrative-prohibited>
 <no-resource>*no-resource*</no-resource>
 <bad-request>*bad-request*</bad-request>
 <too-many-bindings>*too-many-bindings*</too-many-bindings>
 <unknown-ha>*unknown-ha*</unknown-ha>
 <id-mismatch>*id-mismatch*</id-mismatch>
 <unavailable-reverse-tunnel>*unavailable-reverse-tunnel*
 </unavailable-reverse-tunnel>
 <unavailable-encapsulation>*unavailable-encapsulation*
 </unavailable-encapsulation>
 <failed-mn>*failed-mn*</failed-mn>
 <failed-fa>*failed-fa*</failed-fa>
 </mip-home-agent-traffic>
 </mip-home-agent-traffic-information>

Description Mobile IP violation information in specific.

Contents <administrative-prohibited>—Administrative prohibited.

<bad-request>—Bad request form.

<failed-fa>—FA authentication failed.

<failed-mn>—Authentication failed mobile node.

<id-mismatch>—ID mismatch.

<no-resource>—No resource.

<replies-forwarded>—Registration replies forwarded.

<request-denied>—Registration request denied.

<request-forwarded>—Registration request forwarded.

<request-received>—Registration request received.

<too-many-bindings>—Too many Binding.

<unavailable-encapsulation>—Unavailable encapsulation.

<unavailable-reverse-tunnel>—Unavailable reverse tunnel.

<unknown-ha>—Unknown HA.

<unspecified>—Unspecified.

<mip-home-agent-traffic-information>

Usage <rpc-reply>
 <mip-home-agent-traffic-information>
 <mip-home-agent-traffic>...</mip-home-agent-traffic>
 </mip-home-agent-traffic-information>
 </rpc-reply>

Description Mobile IP HA traffic information.

Contents <mip-home-agent-traffic>—Mobile IP violation information in specific.

<mip-home-agent-virtual-network>

Usage <mip-home-agent-virtual-network-information>
 <mip-home-agent-virtual-network>
 <mip-home-agent>*mip-home-agent*</mip-home-agent>
 <registration-lifetime>*registration-lifetime*</registration-lifetime>
 <time-tolerance>*time-tolerance*</time-tolerance>
 <addr-pool>...</addr-pool>
 <number-of-mn>*number-of-mn*</number-of-mn>
 <mip-home-address>*mip-home-address*</mip-home-address>
 <mip-nai>*mip-nai*</mip-nai>
 <mip-care-of-address>*mip-care-of-address*</mip-care-of-address>
 <lifetime-granted>*lifetime-granted*</lifetime-granted>
 <lifetime-remaining>*lifetime-remaining*</lifetime-remaining>
 </mip-home-agent-virtual-network>
 </mip-home-agent-virtual-network-information>

Description Mobile IP virtual-network information.

Contents <addr-pool>—Mobile IP ha address pool.

<lifetime-granted>—Mobile IP Registration Lifetime Granted by HA.

<lifetime-remaining>—Mobile IP Lifetime remaining for mobile node to re-register.

<mip-care-of-address>—Mobile IP care-of-address.

<mip-home-address>—Mobile node's home address.

<mip-home-agent>—Mobile node's home agent address.

<mip-nai>—Mobile IP network access identifier.

<number-of-mn>—Mobile IP number of MNs.

<registration-lifetime>—Mobile IP Registration lifetime.

<time-tolerance>—Mobile IP time tolerance.

<mip-home-agent-virtual-network-information>

- Usage** <rpc-reply>
 <mip-home-agent-virtual-network-information>
 <mip-home-agent-virtual-network>...</mip-home-agent-virtual-network>
 </mip-home-agent-virtual-network-information>
 </rpc-reply>
- Description** Mobile IP home-agent virtual-network information.
- Contents** <mip-home-agent-virtual-network>—Mobile IP virtual-network information.

<mip-security>

- Usage** <mip-security-information>
 <mip-security>
 <mip-nai>*mip-nai*</mip-nai>
 <mip-home-address>*mip-home-address*</mip-home-address>
 <mip-security-spi>*mip-security-spi*</mip-security-spi>
 <mip-security-algorithm>*mip-security-algorithm*</mip-security-algorithm>
 <mip-security-key>*mip-security-key*</mip-security-key>
 <mip-security-replay>*mip-security-replay*</mip-security-replay>
 <mip-security-replay-type>*mip-security-replay-type*</mip-security-replay-type>
 <mip-security-time-tolerance>*mip-security-time-tolerance*
 </mip-security-time-tolerance>
 <mip-security-count>*mip-security-count*</mip-security-count>
 </mip-security>
 </mip-security-information>
- Description** Mobile IP security association information.
- Contents** <mip-home-address>—Mobile node's home address.
- <mip-nai>—Mobile IP network access identifier.
- <mip-security-algorithm>—Mobile IP security association algorithm.
- <mip-security-count>—Mobile IP security association count.
- <mip-security-key>—Mobile IP security association key.
- <mip-security-replay>—Mobile IP security association replay.
- <mip-security-replay-type>—Mobile IP security association replay type.
- <mip-security-spi>—Mobile IP security association SPI value.
- <mip-security-time-tolerance>—Mobile IP security association replay time tolerance.

<mip-security-information>

Usage <rpc-reply>
 <mip-security-information>
 <mip-security>...</mip-security>
 </mip-security-information>
 </rpc-reply>

Description Mobile IP security association information.

Contents <mip-security>—Mobile IP security association information.

<mip-statistics-information>

Usage <rpc-reply>
 <mip-statistics-information>
 <registration-request-received>*registration-request-received*
 </registration-request-received>
 <registration-request-accepted>*registration-request-accepted*
 </registration-request-accepted>
 <registration-request-rejected>*registration-request-rejected*
 </registration-request-rejected>
 </mip-statistics-information>
 </rpc-reply>

Description Statistics from Mobile IP.

Contents <registration-request-accepted>—Registration request accepted.

<registration-request-received>—Registration request received.

<registration-request-rejected>—Registration request rejected.

<mip-traffic>

Usage <mip-traffic-information>
 <mip-traffic>
 <request-received>*request-received*</request-received>
 <request-forwarded>*request-forwarded*</request-forwarded>
 <request-denied>*request-denied*</request-denied>
 <replies-received>*replies-received*</replies-received>
 <replies-forwarded>*replies-forwarded*</replies-forwarded>
 <replies-denied>*replies-denied*</replies-denied>
 <unspecified>*unspecified*</unspecified>
 <ha-unreachable>*ha-unreachable*</ha-unreachable>
 <administrative-prohibited>*administrative-prohibited*
 </administrative-prohibited>
 <no-resource>*no-resource*</no-resource>
 <bad-lifetime>*bad-lifetime*</bad-lifetime>
 <bad-request>*bad-request*</bad-request>
 <unavailable-encapsulation>*unavailable-encapsulation*
 </unavailable-encapsulation>
 <unavailable-reverse-tunnel>*unavailable-reverse-tunnel*
 </unavailable-reverse-tunnel>
 <failed-mn>*failed-mn*</failed-mn>
 <failed-ha>*failed-ha*</failed-ha>
 <unknown-challenge>*unknown-challenge*</unknown-challenge>
 <missing-challenge>*missing-challenge*</missing-challenge>
 <stale-challenge>*stale-challenge*</stale-challenge>
 </mip-traffic>
 </mip-traffic-information>

Description Mobile IP violation information in specific.

Contents <administrative-prohibited>—Administrative prohibited.

<bad-lifetime>—Bad lifetime.

<bad-request>—Bad request form.

<failed-ha>—Authentication failed HA.

<failed-mn>—Authentication failed mobile node.

<ha-unreachable>—HA unreachable.

<missing-challenge>—Missing challenge.

<no-resource>—No resource.

<replies-denied>—Registration replies denied.

<replies-forwarded>—Registration replies forwarded.

<replies-received>—Registration replies received.

<request-denied>—Registration request denied.

<request-forwarded>—Registration request forwarded.

<request-received>—Registration request received.

<stale-challenge>—Stale challenge.

<unavailable-encapsulation>—Unavailable encapsulation.

<unavailable-reverse-tunnel>—Unavailable reverse tunnel.

<unknown-challenge>—Unknown challenge.

<unspecified>—Unspecified.

<mip-traffic-information>

Usage <rpc-reply>
 <mip-traffic-information>
 <mip-traffic>...</mip-traffic>
 </mip-traffic-information>
 </rpc-reply>

Description Mobile IP traffic information.

Contents <mip-traffic>—Mobile IP violation information in specific.

<mip-tunnel>

Usage <mip-tunnel-information>
 <mip-tunnel>
 <mip-tunnel-source>*mip-tunnel-source*</mip-tunnel-source>
 <mip-tunnel-destination>*mip-tunnel-destination*</mip-tunnel-destination>
 <mip-tunnel-type>*mip-tunnel-type*</mip-tunnel-type>
 </mip-tunnel>
 </mip-tunnel-information>

Description Mobile IP tunnel information in specific.

Contents <mip-tunnel-destination>—Tunnel destination address.

<mip-tunnel-source>—Tunnel source address.

<mip-tunnel-type>—Tunnel type.

<mip-tunnel-information>

- Usage** <rpc-reply>
 <mip-tunnel-information>
 <mip-tunnel>...</mip-tunnel>
 </mip-tunnel-information>
 </rpc-reply>
- Description** Mobile IP tunnel information.
- Contents** <mip-tunnel>—Mobile IP tunnel information in specific.

<mip-violation>

- Usage** <mip-violation-information>
 <mip-violation>
 <mip-nai>*mip-nai*</mip-nai>
 <mip-home-address>*mip-home-address*</mip-home-address>
 <mip-violation-code>*mip-violation-code*</mip-violation-code>
 <mip-violation-time>*mip-violation-time*</mip-violation-time>
 <mip-violation-spi>*mip-violation-spi*</mip-violation-spi>
 <mip-violation-error-code>*mip-violation-error-code*</mip-violation-error-code>
 <mip-violation-reason>*mip-violation-reason*</mip-violation-reason>
 <mip-violation-count-per-peer>*mip-violation-count-per-peer*
 </mip-violation-count-per-peer>
 <mip-violation-totol-count>*mip-violation-totol-count*
 </mip-violation-totol-count>
 </mip-violation>
 </mip-violation-information>
- Description** Mobile IP violation information.
- Contents** <mip-home-address>—Mobile node's home address.
- <mip-nai>—Mobile IP network access identifier.
- <mip-violation-code>—Mobile IP violation code.
- <mip-violation-count-per-peer>—Count of violation done by a peer.
- <mip-violation-error-code>—Mobile IP violation error code.
- <mip-violation-reason>—Violation code reason.
- <mip-violation-spi>—SPI value.
- <mip-violation-time>—Time of last violation done.
- <mip-violation-totol-count>—Total violation count.

<mip-violation-information>

Usage	<pre> <rpc-reply> <mip-violation-information> <mip-violation>...</mip-violation> </mip-violation-information> </rpc-reply> </pre>
Description	Mobile IP violation information.
Contents	<mip-violation>—Mobile IP violation information.

<mip-visitor>

Usage	<pre> <mip-visitor-information> <mip-visitor> <mip-nai>mip-nai</mip-nai> <mip-home-address>mip-home-address</mip-home-address> <mip-home-agent>mip-home-agent</mip-home-agent> <mip-care-of-address>mip-care-of-address</mip-care-of-address> <mip-visitor-time-requested>mip-visitor-time-requested </mip-visitor-time-requested> <mip-visitor-time-alloted>mip-visitor-time-alloted</mip-visitor-time-alloted> <mip-visitor-time-remaining>mip-visitor-time-remaining </mip-visitor-time-remaining> <mip-visitor-count>mip-visitor-count</mip-visitor-count> <mip-visitor-pending-count>mip-visitor-pending-count </mip-visitor-pending-count> </mip-visitor> </mip-visitor-information> </pre>
Description	Mobile IP visitor information.
Contents	<p><mip-care-of-address>—Mobile IP care-of-address.</p> <p><mip-home-address>—Mobile node's home address.</p> <p><mip-home-agent>—Mobile node's home agent address.</p> <p><mip-nai>—Mobile IP network access identifier.</p> <p><mip-visitor-count>—Mobile IP visitor count.</p> <p><mip-visitor-pending-count>—Mobile IP pending visitor count.</p> <p><mip-visitor-time-alloted>—Mobile IP registration lifetime allotted.</p> <p><mip-visitor-time-remaining>—Mobile IP registration lifetime remaining.</p> <p><mip-visitor-time-requested>—Mobile IP registration lifetime requested.</p>

<mip-visitor-information>

- Usage** <rpc-reply>
 <mip-visitor-information>
 <mip-visitor>...</mip-visitor>
 </mip-visitor-information>
 </rpc-reply>
- Description** Mobile IP visitor information.
- Contents** <mip-visitor>—Mobile IP visitor information.

<service-enabled-on>

- Usage** <mip-home-agent-overview>
 <service-enabled-on>
 <interface-name>*interface-name*</interface-name>
 </service-enabled-on>
 </mip-home-agent-overview>
- Description** Mobile IP HA enabled interfaces.
- Contents** <interface-name>—Home agent address.

Summary of MSP Response Tags

This section lists JUNOS XML tags that contain operational information about MSP. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-mspinfo>. To review the DTD for the tags, see “DTD for MSP Response Tags” on page 1879.

<mspinfo-raw-output>

Usage <rpc-reply>
 <mspinfo-raw-output>
 <interface-name>*interface-name*</interface-name>
 <raw-output>*raw-output*</raw-output>
 </mspinfo-raw-output>
 </rpc-reply>

Description No documentation is available yet.

Contents <interface-name>—Name of the adaptive services interface.

 <raw-output>—Raw Output Field.

Summary of MPLS OAM ResponseTags

This section lists JUNOS XML tags that contain information about the MPLS OAM response. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-mpls-oam>. To review the DTD for the tags, see “DTD for MPLS OAM Response Tags” on page 1869.

<fec>

Usage <rpc-reply>
 <fec>
 <fec-prefix>*fec-prefix*</fec-prefix>
 </fec>
 </rpc-reply>

Description No documentation is available yet.

Contents <fec-prefix>—No documentation is available yet.

<instance>

Usage <rpc-reply>
 <instance>
 <count>*count*</count>
 </instance>
 </rpc-reply>

Description No documentation is available yet.

Contents <count>—No documentation is available yet.

<last-trace-time>

Usage <rpc-reply>
 <last-trace-time>
 <date-time>*date-time*</date-time>
 </last-trace-time>
 </rpc-reply>

Description No documentation is available yet.

Contents <date-time>—No documentation is available yet.

<multipath-information>

Usage <rpc-reply>
 <multipath-information>
 <multipath-type>*multipath-type*</multipath-type>
 <address-range-index>*address-range-index*</address-range-index>
 <low-address>*low-address*</low-address>
 <high-address>*high-address*</high-address>
 </multipath-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <address-range-index>—No documentation is available yet.
 <high-address>—No documentation is available yet.
 <low-address>—No documentation is available yet.
 <multipath-type>—No documentation is available yet.

<next-scheduled-trace>

Usage <rpc-reply>
 <next-scheduled-trace>
 <timer-expiry>*timer-expiry*</timer-expiry>
 </next-scheduled-trace>
 </rpc-reply>

Description No documentation is available yet.

Contents <timer-expiry>—No documentation is available yet.

<options>

Usage <rpc-reply>
 <options>
 <probe-ttl>*probe-ttl*</probe-ttl>
 <probe-retries>*probe-retries*</probe-retries>
 <probe-wait>*probe-wait*</probe-wait>
 <probe-paths>*probe-paths*</probe-paths>
 <probe-source>*probe-source*</probe-source>
 <probe-destination>*probe-destination*</probe-destination>
 <probe-exp>*probe-exp*</probe-exp>
 <probe-fanout>*probe-fanout*</probe-fanout>
 </options>
 </rpc-reply>

Description No documentation is available yet.

Contents <probe-destination>—No documentation is available yet.

<probe-exp>—No documentation is available yet.

<probe-fanout>—No documentation is available yet.

<probe-paths>—No documentation is available yet.

<probe-retries>—No documentation is available yet.

<probe-source>—No documentation is available yet.

<probe-ttl>—No documentation is available yet.

<probe-wait>—No documentation is available yet.

<probe-options>

Usage <rpc-reply>
 <probe-options>
 <probe-ttl>*probe-ttl*</probe-ttl>
 <probe-retries>*probe-retries*</probe-retries>
 <probe-wait>*probe-wait*</probe-wait>
 <probe-paths>*probe-paths*</probe-paths>
 <probe-source>*probe-source*</probe-source>
 <probe-destination>*probe-destination*</probe-destination>
 <probe-exp>*probe-exp*</probe-exp>
 <probe-fanout>*probe-fanout*</probe-fanout>
 </probe-options>
 </rpc-reply>

Description No documentation is available yet.

Contents <probe-destination>—No documentation is available yet.

<probe-exp>—No documentation is available yet.

<probe-fanout>—No documentation is available yet.

<probe-paths>—No documentation is available yet.

<probe-retries>—No documentation is available yet.

<probe-source>—No documentation is available yet.

<probe-ttl>—No documentation is available yet.

<probe-wait>—No documentation is available yet.

<scan-status>

Usage <rpc-reply>
 <scan-status>
 <status>*status*</status>
 </scan-status>
 </rpc-reply>

Description No documentation is available yet.

Contents <status>—No documentation is available yet.

<tracelsp-label>

Usage	<pre> <rpc-reply> <tracelsp-label> <label-value>label-value</label-value> <label-depth>label-depth</label-depth> <label-protocol>label-protocol</label-protocol> </tracelsp-label> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<p><label-depth>—No documentation is available yet.</p> <p><label-protocol>—No documentation is available yet.</p> <p><label-value>—No documentation is available yet.</p>

<tracelsp-node>

Usage <rpc-reply>
 <tracelsp-node>
 <depth>*depth*</depth>
 <label-value>*label-value*</label-value>
 <label-protocol>*label-protocol*</label-protocol>
 <address>*address*</address>
 <parent>*parent*</parent>
 <response-time>*response-time*</response-time>
 <return-code>*return-code*</return-code>
 <multipath-type>*multipath-type*</multipath-type>
 <sender-timestamp>*sender-timestamp*</sender-timestamp>
 <receiver-timestamp>*receiver-timestamp*</receiver-timestamp>
 <status>*status*</status>
 <path-index>*path-index*</path-index>
 <path-status>*path-status*</path-status>
 <probe-destination>*probe-destination*</probe-destination>
 <mtu>*mtu*</mtu>
 <interface>*interface*</interface>
 </tracelsp-node>
 </rpc-reply>

Description No documentation is available yet.

Contents <address>—No documentation is available yet.
 <depth>—No documentation is available yet.
 <interface>—No documentation is available yet.
 <label-protocol>—No documentation is available yet.
 <label-value>—No documentation is available yet.
 <mtu>—No documentation is available yet.
 <multipath-type>—No documentation is available yet.
 <parent>—No documentation is available yet.
 <path-index>—No documentation is available yet.
 <path-status>—No documentation is available yet.
 <probe-destination>—No documentation is available yet.
 <receiver-timestamp>—No documentation is available yet.

<response-time>—No documentation is available yet.

<return-code>—No documentation is available yet.

<sender-timestamp>—No documentation is available yet.

<status>—No documentation is available yet.

Summary of Passive Monitoring Interfaces Response Tags

This section lists JUNOS XML tags that contain operational information about passive monitoring interfaces. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-passive-monitoring>. To review the DTD for the tags, see “DTD for Passive Monitoring Interfaces Response Tags” on page 1881.

<error-information>

Usage	<pre> <passive-monitoring-information> <error-information> <error-packets-dropped-no-memory>error-packets-dropped-no-memory </error-packets-dropped-no-memory> <error-packets-dropped-not-ip>error-packets-dropped-not-ip </error-packets-dropped-not-ip> <error-packets-dropped-not-ipv4>error-packets-dropped-not-ipv4 </error-packets-dropped-not-ipv4> <error-packets-too-small>error-packets-too-small</error-packets-too-small> <error-allocation-failures>error-allocation-failures </error-allocation-failures> <error-free-failures>error-free-failures</error-free-failures> <error-free-list-failures>error-free-list-failures</error-free-list-failures> <error-memory-warning>error-memory-warning</error-memory-warning> <error-memory-overload>error-memory-overload</error-memory-overload> <error-packets-per-second-overload>error-packets-per-second-overload </error-packets-per-second-overload> <error-bytes-per-second-overload>error-bytes-per-second-overload </error-bytes-per-second-overload> </error-information> </passive-monitoring-information> </pre>
Description	Passive monitoring error information.
Contents	<p><error-allocation-failures>—Number of failed attempts to allocate memory.</p> <p><error-bytes-per-second-overload>—Whether the number of incoming bytes exceeds the designed per-second limit.</p> <p><error-free-failures>—Number of failed attempts to free memory.</p> <p><error-free-list-failures>—Number of operations that failed because free list memory is exhausted.</p> <p><error-memory-overload>—Whether memory is exhausted.</p> <p><error-memory-warning>—Reached low memory condition.</p> <p><error-packets-dropped-no-memory>—Number of packets dropped because memory is exhausted.</p> <p><error-packets-dropped-not-ip>—Number of packets dropped because they are not IP.</p> <p><error-packets-dropped-not-ipv4>—Number of packets dropped because they are not IPv4.</p> <p><error-packets-per-second-overload>—Whether the number of incoming packets exceeds the designed per-second limit.</p> <p><error-packets-too-small>—Number of packets dropped because their header is too small.</p>

<flow-information>

Usage <passive-monitoring-information>
 <flow-information>
 <flow-packets>*flow-packets*</flow-packets>
 <flow-bytes>*flow-bytes*</flow-bytes>
 <flow-packets-ten-second-rate>*flow-packets-ten-second-rate*
 </flow-packets-ten-second-rate>
 <flow-bytes-ten-second-rate>*flow-bytes-ten-second-rate*
 </flow-bytes-ten-second-rate>
 <active-flows>*active-flows*</active-flows>
 <flows>*flows*</flows>
 <flows-exported>*flows-exported*</flows-exported>
 <flow-packets-exported>*flow-packets-exported*</flow-packets-exported>
 <flows-expired>*flows-expired*</flows-expired>
 <flows-aged>*flows-aged*</flows-aged>
 </flow-information>
 </passive-monitoring-information>

Description Passive monitoring flow information.

Contents <active-flows>—Active flows.

<flow-bytes>—Flow bytes.

<flow-bytes-ten-second-rate>—Flow bytes 10-second rate.

<flow-packets>—Flow packets.

<flow-packets-exported>—Flows packets exported.

<flow-packets-ten-second-rate>—Flow packets 10-second rate.

<flows>—Flows.

<flows-aged>—Flows active timed out.

<flows-expired>—Flows inactive timed out.

<flows-exported>—Flows exported.

<memory-information>

Usage <passive-monitoring-information>
 <memory-information>
 <allocation-count>*allocation-count*</allocation-count>
 <free-count>*free-count*</free-count>
 <maximum-allocated>*maximum-allocated*</maximum-allocated>
 <allocations-per-second>*allocations-per-second*</allocations-per-second>
 <frees-per-second>*frees-per-second*</frees-per-second>
 <memory-used>*memory-used*</memory-used>
 <memory-free>*memory-free*</memory-free>
 </memory-information>
 </passive-monitoring-information>

Description Passive monitoring memory utilization.

Contents <allocation-count>—Flow record allocations.

<allocations-per-second>—Flow record allocations per second.

<free-count>—Flow record frees.

<frees-per-second>—Flow record frees per second.

<maximum-allocated>—Maximum flow records allocated.

<memory-free>—Total memory free.

<memory-used>—Total memory used.

<passive-monitoring-information>

Usage <rpc-reply>
 <passive-monitoring-information>
 <interface-name>*interface-name*</interface-name>
 <local-index>*local-index*</local-index>
 <pic-status>*pic-status*</pic-status>
 <usage-information>...</usage-information>
 <memory-information>...</memory-information>
 <flow-information>...</flow-information>
 <error-information>...</error-information>
 <status-information>...</status-information>
 </passive-monitoring-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <error-information>—Passive monitoring error information.

<flow-information>—Passive monitoring flow information.

<interface-name>—Physical interface name.

<local-index>—Local physical interface index.

<memory-information>—Passive monitoring memory utilization.

<pic-status>—Current interface state.

<status-information>—Passive monitoring status information.

<usage-information>—Passive monitoring CPU utilization.

<status-information>

Usage <passive-monitoring-information>
<status-information>
 <status-group-index>status-group-index</status-group-index>
 <status-export-interval>status-export-interval</status-export-interval>
 <status-export-format>status-export-format</status-export-format>
 <status-proto>status-proto</status-proto>
 <status-engine-type>status-engine-type</status-engine-type>
 <status-engine-id>status-engine-id</status-engine-id>
 <status-route-record-count>status-route-record-count
 </status-route-record-count>
 <status-ifl-snmp-map-count>status-ifl-snmp-map-count
 </status-ifl-snmp-map-count>
 <status-as-count>status-as-count</status-as-count>
 <status-monitor-time-set>status-monitor-time-set</status-monitor-time-set>
 <status-monitor-config-set>status-monitor-config-set
 </status-monitor-config-set>
 <status-monitor-route-record-set>status-monitor-route-record-set
 </status-monitor-route-record-set>
 <status-monitor-ifl-snmp-set>status-monitor-ifl-snmp-set
 </status-monitor-ifl-snmp-set>
</status-information>
 </passive-monitoring-information>

Description Passive monitoring status information.

Contents <status-as-count>—Autonomous system number count.
 <status-engine-id>—Engine ID.
 <status-engine-type>—Engine type.
 <status-export-format>—Export format.
 <status-export-interval>—Export interval, in seconds.
 <status-group-index>—Group index.
 <status-ifl-snmp-map-count>—Local index to SNMP index count.
 <status-monitor-config-set>—Configuration set on PIC.
 <status-monitor-ifl-snmp-set>—Local index to SNMP index map set on PIC.
 <status-monitor-route-record-set>—Route records set on PIC.
 <status-monitor-time-set>—Time set on PIC.
 <status-proto>—Protocol.
 <status-route-record-count>—Route record count.

<usage-information>

Usage <passive-monitoring-information>
 <usage-information>
 <uptime>*uptime*</uptime>
 <inttime>*inttime*</inttime>
 <five-second-load>*five-second-load*</five-second-load>
 <one-minute-load>*one-minute-load*</one-minute-load>
 </usage-information>
</passive-monitoring-information>

Description Passive monitoring CPU utilization.

Contents <five-second-load>—5-second load.

<inttime>—CPU interrupt time, in microseconds.

<one-minute-load>—1-minute load.

<uptime>—CPU uptime, in milliseconds.

Summary of PGM Response Tags

This section lists JUNOS XML tags that contain operational information about the Pragmatic General Multicast (PGM) protocol. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-pgm>. To review the DTD for the tags, see “DTD for PGM Response Tags” on page 1885.

<errors>

Usage <packet-counters>
<errors>
 <short-pgm-header>*short-pgm-header*</short-pgm-header>
 <bad-checksum>*bad-checksum*</bad-checksum>
 <zero-checksum>*zero-checksum*</zero-checksum>
 <bad-tsdu-length>*bad-tsdu-length*</bad-tsdu-length>
 <bad-spm-length>*bad-spm-length*</bad-spm-length>
 <bad-spm-family>*bad-spm-family*</bad-spm-family>
 <bad-nak-length>*bad-nak-length*</bad-nak-length>
 <bad-nak-family>*bad-nak-family*</bad-nak-family>
 <nak-unknown-tsi>*nak-unknown-tsi*</nak-unknown-tsi>
 <nak-throttled>*nak-throttled*</nak-throttled>
 <bad-ncf-length>*bad-ncf-length*</bad-ncf-length>
 <bad-ncf-family>*bad-ncf-family*</bad-ncf-family>
 <ncf-unknown-tsi>*ncf-unknown-tsi*</ncf-unknown-tsi>
 <bad-rdata-length>*bad-rdata-length*</bad-rdata-length>
 <rdata-unknown-tsi>*rdata-unknown-tsi*</rdata-unknown-tsi>
 <odata-with-ra>*odata-with-ra*</odata-with-ra>
</errors>
 </packet-counters>

Description No documentation is available yet.

Contents <bad-checksum>—No documentation is available yet.
 <bad-nak-family>—No documentation is available yet.
 <bad-nak-length>—No documentation is available yet.
 <bad-ncf-family>—No documentation is available yet.
 <bad-ncf-length>—No documentation is available yet.
 <bad-rdata-length>—No documentation is available yet.
 <bad-spm-family>—No documentation is available yet.
 <bad-spm-length>—No documentation is available yet.
 <bad-tsdu-length>—No documentation is available yet.
 <nak-throttled>—No documentation is available yet.
 <nak-unknown-tsi>—No documentation is available yet.
 <ncf-unknown-tsi>—No documentation is available yet.
 <odata-with-ra>—No documentation is available yet.

<rdata-unknown-tsi>—No documentation is available yet.

<short-pgm-header>—No documentation is available yet.

<zero-checksum>—No documentation is available yet.

<nak>

Usage <packet-counters>
 <nak>
 <received>received</received>
 <sent>sent</sent>
 </nak>
 </packet-counters>

Description No documentation is available yet.

Contents <received>—No documentation is available yet.
 <sent>—No documentation is available yet.

<ncf>

Usage <packet-counters>
 <ncf>
 <received>received</received>
 <sent>sent</sent>
 </ncf>
 </packet-counters>

Description No documentation is available yet.

Contents <received>—No documentation is available yet.
 <sent>—No documentation is available yet.

<nullnak>

Usage <packet-counters>
 <nullnak>
 <received>received</received>
 <sent>sent</sent>
 </nullnak>
 </packet-counters>

Description No documentation is available yet.

Contents <received>—No documentation is available yet.
 <sent>—No documentation is available yet.

<other>

Usage	<pre> <packet-counters> <other> <received>received</received> <sent>sent</sent> </other> </packet-counters> </pre>
Description	No documentation is available yet.
Contents	<p><received>—No documentation is available yet.</p> <p><sent>—No documentation is available yet.</p>

<packet-counters>

Usage	<pre> <pgm-statistics-information> <packet-counters> <spm>...</spm> <poll>...</poll> <polr>...</polr> <rdata>...</rdata> <nak>...</nak> <nullnak>...</nullnak> <ncf>...</ncf> <spmr>...</spmr> <other>...</other> <errors>...</errors> </packet-counters> </pgm-statistics-information> </pre>
Description	No documentation is available yet.
Contents	<p><errors>—No documentation is available yet.</p> <p><nak>—No documentation is available yet.</p> <p><ncf>—No documentation is available yet.</p> <p><nullnak>—No documentation is available yet.</p> <p><other>—No documentation is available yet.</p> <p><poll>—No documentation is available yet.</p> <p><polr>—No documentation is available yet.</p> <p><rdata>—No documentation is available yet.</p> <p><spm>—No documentation is available yet.</p> <p><spmr>—No documentation is available yet.</p>

<pgm-nak-interface>

- Usage** <pgm-spm-nak>
 <pgm-nak-interface>
 <pgm-nak-interface-name>*pgm-nak-int-name*
 </pgm-nak-interface-name>
 <pgm-nak-interface-sender>*pgm-nak-int-sen*
 </pgm-nak-interface-sender>
 </pgm-nak-interface>
 </pgm-spm-nak>
- Description** No documentation is available yet.
- Contents** <pgm-nak-interface-name>—No documentation is available yet.
 <pgm-nak-interface-sender>—No documentation is available yet.

<pgm-spm-information>

- Usage** <rpc-reply>
 <pgm-spm-information>
 <pgm-spm-tsi>...</pgm-spm-tsi>
 </pgm-spm-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <pgm-spm-tsi>—No documentation is available yet.

<pgm-spm-nak>

- Usage** <pgm-spm-tsi>
 <pgm-spm-nak>
 <pgm-nak-sequence>*pgm-nak-sequence*</pgm-nak-sequence>
 <pgm-nak-source>*pgm-nak-source*</pgm-nak-source>
 <pgm-nak-group>*pgm-nak-group*</pgm-nak-group>
 <pgm-nak-interface>...</pgm-nak-interface>
 </pgm-spm-nak>
 </pgm-spm-tsi>
- Description** No documentation is available yet.
- Contents** <pgm-nak-group>—No documentation is available yet.
 <pgm-nak-interface>—No documentation is available yet.
 <pgm-nak-sequence>—No documentation is available yet.
 <pgm-nak-source>—No documentation is available yet.

<pgm-spm-tsi>

Usage <pgm-spm-information>
 <pgm-spm-tsi>
 <pgm-spm-gsid>*pgm-spm-gsid*</pgm-spm-gsid>
 <pgm-spm-sport>*pgm-spm-sport*</pgm-spm-sport>
 <pgm-spm-seq>*pgm-spm-seq*</pgm-spm-seq>
 <pgm-spm-trail>*pgm-spm-trail*</pgm-spm-trail>
 <pgm-spm-lead>*pgm-spm-lead*</pgm-spm-lead>
 <pgm-spm-nla>*pgm-spm-nla*</pgm-spm-nla>
 <pgm-spm-nak>...</pgm-spm-nak>
 </pgm-spm-tsi>
 </pgm-spm-information>

Description No documentation is available yet.

Contents <pgm-spm-gsid>—No documentation is available yet.
 <pgm-spm-lead>—No documentation is available yet.
 <pgm-spm-nak>—No documentation is available yet.
 <pgm-spm-nla>—No documentation is available yet.
 <pgm-spm-seq>—No documentation is available yet.
 <pgm-spm-sport>—No documentation is available yet.
 <pgm-spm-trail>—No documentation is available yet.

<pgm-statistics-information>

Usage <rpc-reply>
 <pgm-statistics-information>
 <packet-counters>...</packet-counters>
 </pgm-statistics-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <packet-counters>—No documentation is available yet.

<poll>

Usage	<pre> <packet-counters> <poll> <received>received</received> <sent>sent</sent> </poll> </packet-counters> </pre>
Description	No documentation is available yet.
Contents	<p><received>—No documentation is available yet.</p> <p><sent>—No documentation is available yet.</p>

<polr>

Usage	<pre> <packet-counters> <polr> <received>received</received> <sent>sent</sent> </polr> </packet-counters> </pre>
Description	No documentation is available yet.
Contents	<p><received>—No documentation is available yet.</p> <p><sent>—No documentation is available yet.</p>

<rdata>

Usage	<pre> <packet-counters> <rdata> <received>received</received> <sent>sent</sent> </rdata> </packet-counters> </pre>
Description	No documentation is available yet.
Contents	<p><received>—No documentation is available yet.</p> <p><sent>—No documentation is available yet.</p>

<spm>

Usage	<pre><packet-counters> <spm> <received>received</received> <sent>sent</sent> </spm> </packet-counters></pre>
Description	No documentation is available yet.
Contents	<pre><received>—No documentation is available yet. <sent>—No documentation is available yet.</pre>

<spmr>

Usage	<pre><packet-counters> <spmr> <received>received</received> <sent>sent</sent> </spmr> </packet-counters></pre>
Description	No documentation is available yet.
Contents	<pre><received>—No documentation is available yet. <sent>—No documentation is available yet.</pre>

Summary of Periodic Packet Management Response Tags

This section lists JUNOS XML tags that contain information about periodic packet management process. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-ppm>. To review the DTD for the tags, see “DTD for Periodic Packet Management Response Tag Elements” on page 1889.

<adjacency-data>

Usage <ppm-adjacencies>
 <adjacency-data>
 <protocol>*protocol*</protocol>
 <adjacency-holdtime>*adjacency-holdtime*</adjacency-holdtime>
 <adjacency-interface-index>*adjacency-interface-index*
 </adjacency-interface-index>
 <adjacency-no-absorb/>
 <adjacency-no-refresh/>
 <adjacency-do-not-age/>
 <adjacency-hello-dropped/>
 <adjacency-distributed/>
 <adjacency-ospf-src-key>*adjacency-ospf-src-key*</adjacency-ospf-src-key>
 <adjacency-ospf-area-id>*adjacency-ospf-area-id*</adjacency-ospf-area-id>
 <adjacency-ospf-transit-area-id>*adjacency-ospf-transit-area-id*
 </adjacency-ospf-transit-area-id>
 <adjacency-ospf-routing-table-index>*adjacency-ospf-routing-table-index*
 </adjacency-ospf-routing-table-index>
 <adjacency-isis-level>*adjacency-isis-level*</adjacency-isis-level>
 <adjacency-isis-sysid>*adjacency-isis-sysid*</adjacency-isis-sysid>
 <adjacency-esis-type>*adjacency-esis-type*</adjacency-esis-type>
 <adjacency-bfd-discriminator>*adjacency-bfd-discriminator*
 </adjacency-bfd-discriminator>
 <adjacency-bfd-routing-table-index>*adjacency-bfd-routing-table-index*
 </adjacency-bfd-routing-table-index>
 <adjacency-ldp-source>*adjacency-ldp-source*</adjacency-ldp-source>
 <adjacency-ldp-routing-table-index>*adjacency-ldp-routing-table-index*
 </adjacency-ldp-routing-table-index>
 <adjacency-stp-source-key>*adjacency-stp-source-key*</adjacency-stp-source-key>
 <adjacency-pfe-handle>*adjacency-pfe-handle*</adjacency-pfe-handle>
 <adjacency-pfe-addr>*adjacency-pfe-addr*</adjacency-pfe-addr>
 </adjacency-data>
 </ppm-adjacencies>

Description Information about an adjacency of the PPM process.

Contents <adjacency-bfd-discriminator>—BFD discriminator.
 <adjacency-bfd-routing-table-index>—BFD routing table index.
 <adjacency-distributed>—Distributed flag.
 <adjacency-do-not-age>—Do-not-age flag.
 <adjacency-esis-type>—ES-IS type.
 <adjacency-hello-dropped>—Dropped-hellos flag.
 <adjacency-holdtime>—Delay after the last keepalive message received after which an adjacency is considered down.
 <adjacency-interface-index>—Logical interface index.
 <adjacency-isis-level>—IS-IS level.

<adjacency-isis-sysid>—IS-IS system ID.

<adjacency-ldp-routing-table-index>—LDP routing table index.

<adjacency-ldp-source>—LDP source.

<adjacency-no-absorb>—No-absorb flag.

<adjacency-no-refresh>—No-refresh flag.

<adjacency-ospf-area-id>—OSPF area ID.

<adjacency-ospf-routing-table-index>—OSPF routing table index.

<adjacency-ospf-src-key>—OSPF source key.

<adjacency-ospf-transit-area-id>—OSPF transit area ID.

<adjacency-pfe-addr>—Distribution address.

<adjacency-pfe-handle>—Distribution handle.

<adjacency-stp-source-key>— STP source key.

<protocol>—Protocol that connected to the PPM process.

<connection-data>

Usage <ppm-connections>
 <connection-data>
 <protocol>*protocol*</protocol>
 <logical-system-id>*logical-system-id*</logical-system-id>
 <number-adjacencies>*number-adjacencies*</number-adjacencies>
 <number-transmissions>*number-transmissions*</number-transmissions>
 </connection-data>
 </ppm-connections>

Description Information about a connection to the PPM process.

Contents <logical-system-id>—Logical system ID.

<number-adjacencies>—Number of adjacencies.

<number-transmissions>—Number of transmission entries.

<protocol>—Protocol that connected to the PPM process.

<ppm-adjacencies>

Usage	<pre> <rpc-reply> <ppm-adjacencies> <adjacency-data>...</adjacency-data> <total-adjacencies>total-adjacencies</total-adjacencies> <remote-adjacencies>remote-adjacencies</remote-adjacencies> </ppm-adjacencies> </rpc-reply> </pre>
Description	Information about one or more adjacencies of the periodic packet management process.
Contents	<p><adjacency-data>—Information about an adjacency of the PPM process.</p> <p><remote-adjacencies>—Number of remote adjacencies.</p> <p><total-adjacencies>—Number of adjacencies.</p>

<ppm-connections>

Usage	<pre> <rpc-reply> <ppm-connections> <connection-data>...</connection-data> <total-connections>total-connections</total-connections> <remote-connections>remote-connections</remote-connections> </ppm-connections> </rpc-reply> </pre>
Description	Information about one or more connections to the periodic packet management process.
Contents	<p><connection-data>—Information about a connection to the PPM process.</p> <p><remote-connections>—Number of remote connections.</p> <p><total-connections>—Number of connections.</p>

<ppm-transmissions>

- Usage** <rpc-reply>
 <ppm-transmissions>
 <transmission-data>...</transmission-data>
 <total-transmissions>*total-transmissions*</total-transmissions>
 <remote-transmissions>*remote-transmissions*</remote-transmissions>
 </ppm-transmissions>
 </rpc-reply>
- Description** Information about one or more transmissions of the periodic packet management process.
- Contents** <remote-transmissions>—Number of remote transmissions.
- <total-transmissions>—Number of transmissions.
- <transmission-data>—Information about a transmission of the PPM process.

<transmission-data>

- Usage** <ppm-transmissions>
 <transmission-data>
 <transmission-destination>*transmission-destination*</transmission-destination>
 <protocol>*protocol*</protocol>
 <transmission-interval>*transmission-interval*</transmission-interval>
 <transmission-distributed/>
 <transmission-pfe-handle>*transmission-pfe-handle*</transmission-pfe-handle>
 <transmission-pfe-addr>*transmission-pfe-addr*</transmission-pfe-addr>
 </transmission-data>
 </ppm-transmissions>
- Description** Information about a transmission of the PPM process.
- Contents** <protocol>—Protocol that connected to the PPM process.
- <transmission-destination>—Destination.
- <transmission-distributed>—Distributed flag.
- <transmission-interval>—Interval between transmissions.
- <transmission-pfe-addr>—Distribution address.
- <transmission-pfe-handle>—Distribution handle.

Summary of PPP Response Tags

This section lists JUNOS XML tags that contain information about the Point-to-Point Protocol (PPP). The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-ppp>. To review the DTD for the tags, see “DTD for PPP Response Tag Elements” on page 1893.

<assigned-address-list>

Usage	<pre><ppp-address-pool-information> <assigned-address-list> <pool-address-assignment>...</pool-address-assignment> </assigned-address-list> </ppp-address-pool-information></pre>
Description	List of addresses assigned in pool.
Contents	<pool-address-assignment>—Assignment information for one address in the pool.

<ipcp-address>

Usage	<pre><ppp-negotiated-options> <ipcp-address> <local-address>local-address</local-address> <remote-address>remote-address</remote-address> </ipcp-address> </ppp-negotiated-options></pre>
Description	Negotiated IP address Internet Protocol Control Protocol option.
Contents	<local-address>—Local interface address negotiated with remote peer. <remote-address>—Destination address negotiated with remote peer.

<ipv6cp-interface-identifier>

Usage	<pre><ppp-negotiated-options> <ipv6cp-interface-identifier> <local-interface-identifier>local-interface-identifier </local-interface-identifier> <remote-interface-identifier>remote-interface-identifier </remote-interface-identifier> </ipv6cp-interface-identifier> </ppp-negotiated-options></pre>
Description	Negotiated Internet Protocol Version 6 Control Protocol interface identifier option.
Contents	<local-interface-identifier>—Local interface identifier negotiated with remote peer. <remote-interface-identifier>—Remote interface identifier negotiated with remote peer.

<lcp-authentication-protocol>

- Usage** <ppp-negotiated-options>
 <lcp-authentication-protocol>
 <authentication-protocol-name>*authentication-protocol-name*
 </authentication-protocol-name>
 <authentication-algorithm>*authentication-algorithm*</authentication-algorithm>
 </lcp-authentication-protocol>
 </ppp-negotiated-options>
- Description** Link Control Protocol authentication protocol option.
- Contents** <authentication-algorithm>—Authentication algorithm identifier.
 <authentication-protocol-name>—Name of authentication protocol.

<lcp-endpoint-discriminator>

- Usage** <ppp-negotiated-options>
 <lcp-endpoint-discriminator>
 <endpoint-discriminator-class>*endpoint-discriminator-class*
 </endpoint-discriminator-class>
 <endpoint-discriminator-identifier>*endpoint-discriminator-identifier*
 </endpoint-discriminator-identifier>
 </lcp-endpoint-discriminator>
 </ppp-negotiated-options>
- Description** Link Control Protocol endpoint discriminator option.
- Contents** <endpoint-discriminator-class>—Endpoint discriminator class.
 <endpoint-discriminator-identifier>—Endpoint discriminator identifier.

<lcp-multilink-header>

- Usage** <ppp-negotiated-options>
 <lcp-multilink-header>
 <multilink-header-code>*multilink-header-code*</multilink-header-code>
 <multilink-header-suspendable-classes>*multilink-header-suspendable-classes*
 </multilink-header-suspendable-classes>
 </lcp-multilink-header>
 </ppp-negotiated-options>
- Description** Link Control Protocol multilink header format option.
- Contents** <multilink-header-code>—Multilink header format code.
 <multilink-header-suspendable-classes>—Number of suspendable classes.

<pool-address-assignment>

- Usage** <assigned-address-list>
 <pool-address-assignment>
 <pool-address>*pool-address*</pool-address>
 <session-name>*session-name*</session-name>
 <pool-address-blocked/>
 </pool-address-assignment>
 </assigned-address-list>
- Description** Assignment information for one address in the pool.
- Contents** <pool-address>—Address in pool.
 <pool-address-blocked>—Address is already in use by a local interface.
 <session-name>—PPP session name.

<pool-address-list>

- Usage** <ppp-address-pool-information>
 <pool-address-list>
 <pool-address>*pool-address*</pool-address>
 </pool-address-list>
 </ppp-address-pool-information>
- Description** List of addresses in pool.
- Contents** <pool-address>—Address in pool.

<pool-range>

- Usage** <ppp-address-pool-information>
 <pool-range>
 <low-address>*low-address*</low-address>
 <high-address>*high-address*</high-address>
 </pool-range>
 </ppp-address-pool-information>
- Description** Range of addresses in pool.
- Contents** <high-address>—High range of address pool.
 <low-address>—Low range of address pool.

<ppp-address-pool-information>

Usage <rpc-reply>
 <ppp-address-pool-information>
 <pool-name>*pool-name*</pool-name>
 <assigned-addresses>*assigned-addresses*</assigned-addresses>
 <configured-addresses>*configured-addresses*</configured-addresses>
 <pool-range>...</pool-range>
 <pool-address-list>...</pool-address-list>
 <assigned-address-list>...</assigned-address-list>
 </ppp-address-pool-information>
 </rpc-reply>

Description PPP address pool information.

Contents <assigned-address-list>—List of addresses assigned in pool.

<assigned-addresses>—Number of assigned addresses.

<configured-addresses>—Number of configured addresses.

<pool-address-list>—List of addresses in pool.

<pool-name>—Name of pool from which addresses are assigned.

<pool-range>—Range of addresses in pool.

<ppp-auth-protocol-information>

Usage <ppp-session>
 <ppp-auth-protocol-information>
 <ppp-state>*ppp-state*</ppp-state>
 <ppp-last-started>*ppp-last-started*</ppp-last-started>
 <ppp-last-completed>*ppp-last-completed*</ppp-last-completed>
 <ppp-auth-proto>*ppp-auth-proto*</ppp-auth-proto>
 </ppp-auth-protocol-information>
 </ppp-session>

Description Authentication protocol information for PPP session.

Contents <ppp-auth-proto>—No documentation is available yet.

<ppp-last-completed>—Time when negotiation of the protocol last completed successfully, in the format YYYY-MM-DD hh:mm:ss TZ (year, month, date, hour in 24-hour format, minute second, timezone).

<ppp-last-started>—Time when negotiation of the protocol last started, in the format YYYY-MM-DD hh:mm:ss TZ (year, month, date, hour in 24-hour format, minute second, time zone).

<ppp-state>—Protocol state.

<ppp-destination-profile>

Usage <ppp-session-protocol-information>
 <ppp-destination-profile>
 <pool-name>*pool-name*</pool-name>
 </ppp-destination-profile>
 </ppp-session-protocol-information>

Description Destination profile information.

Contents <pool-name>—Name of pool from which addresses are assigned.

<ppp-interface-information>

Usage <rpc-reply>
 <ppp-interface-information>
 <interface-name>*interface-name*</interface-name>
 <ppp-session>...</ppp-session>
 </ppp-interface-information>
 </rpc-reply>

Description PPP interface information.

Contents <interface-name>—Interface name.

<ppp-session>—PPP session.

<ppp-memory-statistics>

Usage <ppp-statistics-information>
 <ppp-memory-statistics>
 <ppp-memory-tag>...</ppp-memory-tag>
 </ppp-memory-statistics>
 </ppp-statistics-information>

Description PPP process memory statistics.

Contents <ppp-memory-tag>—Tag associated with memory blocks.

<ppp-memory-tag>

Usage <ppp-memory-statistics>
 <ppp-memory-tag>
 <ppp-memory-tag-name>*ppp-memory-tag-name*</ppp-memory-tag-name>
 <ppp-memory-tag-size>*ppp-memory-tag-size*</ppp-memory-tag-size>
 <ppp-memory-tag-active>*ppp-memory-tag-active*</ppp-memory-tag-active>
 <ppp-memory-tag-free>*ppp-memory-tag-free*</ppp-memory-tag-free>
 <ppp-memory-tag-maximum-free>*ppp-memory-tag-maximum-free*
 </ppp-memory-tag-maximum-free>
 <ppp-memory-tag-requests>*ppp-memory-tag-requests*</ppp-memory-tag-requests>
 <ppp-memory-tag-failures>*ppp-memory-tag-failures*</ppp-memory-tag-failures>
 <ppp-memory-tag-total>*ppp-memory-tag-total*</ppp-memory-tag-total>
 </ppp-memory-tag>
 </ppp-memory-statistics>

Description Tag associated with memory blocks.

Contents <ppp-memory-tag-active>—Number of active memory blocks.

<ppp-memory-tag-failures>—Number of failed memory allocation requests.

<ppp-memory-tag-free>—Number of memory blocks on the free list.

<ppp-memory-tag-maximum-free>—Maximum number of memory blocks allowed on the free list.

<ppp-memory-tag-name>—Name of memory tag.

<ppp-memory-tag-requests>—Number of successful memory allocation requests.

<ppp-memory-tag-size>—Number of bytes of tagged memory allocated.

<ppp-memory-tag-total>—Total number of bytes of memory allocated by the memory tag.

<ppp-negotiated-options>

Usage <ppp-session-protocol-information>
 <ppp-negotiated-options>
 <ipcp-address>...</ipcp-address>
 <ipcp-compression-protocol/>
 <ipcp-primary-dns>*ipcp-primary-dns*</ipcp-primary-dns>
 <ipcp-primary-wins>*ipcp-primary-wins*</ipcp-primary-wins>
 <ipcp-secondary-dns>*ipcp-secondary-dns*</ipcp-secondary-dns>
 <ipcp-secondary-wins>*ipcp-secondary-wins*</ipcp-secondary-wins>
 <ipv6cp-interface-identifier>...</ipv6cp-interface-identifier>
 <lcp-address-compression-field-compression/>
 <lcp-async-map/>
 <lcp-authentication-protocol>...</lcp-authentication-protocol>
 <lcp-endpoint-discriminator>...</lcp-endpoint-discriminator>
 <lcp-magic-number>*lcp-magic-number*</lcp-magic-number>
 <lcp-mrru>*lcp-mrru*</lcp-mrru>
 <lcp-mru>*lcp-mru*</lcp-mru>
 <lcp-multilink-header>...</lcp-multilink-header>
 <lcp-protocol-field-compression/>
 <lcp-short-sequence/>
 </ppp-negotiated-options>
 </ppp-session-protocol-information>

Description PPP options negotiated with the remote peer.

Contents <ipcp-address>—Negotiated IP address Internet Protocol Control Protocol option.

<ipcp-compression-protocol>—Compression protocol Internet Protocol Control Protocol option.

<ipcp-primary-dns>—Internet Protocol Control Protocol primary domain name server option.

<ipcp-primary-wins>—Internet Protocol Control Protocol primary WINS option.

<ipcp-secondary-dns>—Internet Protocol Control Protocol secondary domain name server option.

<ipcp-secondary-wins>—Internet Protocol Control Protocol secondary WINS option.

<ipv6cp-interface-identifier>—Negotiated Internet Protocol Version 6 Control Protocol interface identifier option.

<lcp-address-compression-field-compression>—Link Control Protocol address compression/field compression option.

<lcp-async-map>—Link Control Protocol asynchronous map option.

<lcp-authentication-protocol>—Link Control Protocol authentication protocol option.

<lcp-endpoint-discriminator>—Link Control Protocol endpoint discriminator option.

<lcp-magic-number>—Link Control Protocol magic number option.

<lcp-mrru>—Link Control Protocol maximum reconstructed receive unit option.

<lcp-mru>—Link Control Protocol maximum receive unit option.

<lcp-multilink-header>—Link Control Protocol multilink header format option.

<lcp-protocol-field-compression>—Link Control Protocol protocol/field compression option.

<lcp-short-sequence>—Link Control Protocol short sequence option.

<ppp-session>

Usage <ppp-interface-information | ppp-summary-information>
<ppp-session>
 <session-name>session-name</session-name>
 <session-type>session-type</session-type>
 <session-phase>session-phase</session-phase>
 <session-flags>...</session-flags>
 <ppp-last-started>ppp-last-started</ppp-last-started>
 <ppp-last-completed>ppp-last-completed</ppp-last-completed>
 <ppp-auth-protocol-information>...</ppp-auth-protocol-information>
 <ppp-session-protocol-information>...</ppp-session-protocol-information>
</ppp-session>
 </ppp-interface-information | ppp-summary-information>

Description PPP session.

Contents <ppp-auth-protocol-information>—Authentication protocol information for PPP session.

<ppp-last-completed>—Time when negotiation of the protocol last completed successfully, in the format YYYY-MM-DD hh:mm:ss TZ (year, month, date, hour in 24-hour format, minute second, timezone).

<ppp-last-started>—Time when negotiation of the protocol last started, in the format YYYY-MM-DD hh:mm:ss TZ (year, month, date, hour in 24-hour format, minute second, time zone).

<ppp-session-protocol-information>—LCP/NCP protocol information for PPP session.

<session-flags>—PPP session flags.

<session-name>—PPP session name.

<session-phase>—PPP session phase.

<session-type>—PPP session type.

<ppp-session-protocol-information>

Usage <ppp-session>
 <ppp-session-protocol-information>
 <ppp-state>*ppp-state*</ppp-state>
 <ppp-last-started>*ppp-last-started*</ppp-last-started>
 <ppp-last-completed>*ppp-last-completed*</ppp-last-completed>
 <ppp-protocol>*ppp-protocol*</ppp-protocol>
 <ppp-destination-profile>...</ppp-destination-profile>
 <ppp-negotiated-options>...</ppp-negotiated-options>
 </ppp-session-protocol-information>
 </ppp-session>

Description LCP/NCP protocol information for PPP session.

Contents <ppp-destination-profile>—Destination profile information.

<ppp-last-completed>—Time when negotiation of the protocol last completed successfully, in the format YYYY-MM-DD hh:mm:ss TZ (year, month, date, hour in 24-hour format, minute second, timezone).

<ppp-last-started>—Time when negotiation of the protocol last started, in the format YYYY-MM-DD hh:mm:ss TZ (year, month, date, hour in 24-hour format, minute second, time zone).

<ppp-negotiated-options>—PPP options negotiated with the remote peer.

<ppp-protocol>—Protocol value.

<ppp-state>—Protocol state.

<ppp-session-statistics>

- Usage** <ppp-statistics-information>
 <ppp-session-statistics>
 <sessions-total>sessions-total</sessions-total>
 <sessions-disabled>sessions-disabled</sessions-disabled>
 <sessions-establish>sessions-establish</sessions-establish>
 <sessions-authenticate>sessions-authenticate</sessions-authenticate>
 <sessions-network>sessions-network</sessions-network>
 <bundles-pending>bundles-pending</bundles-pending>
 </ppp-session-statistics>
 </ppp-statistics-information>
- Description** PPP session statistics.
- Contents** <bundles-pending>—Number of multilink bundles with links waiting.
 <sessions-authenticate>—Number of session in authenticate phase.
 <sessions-disabled>—Number of sessions in disabled phase.
 <sessions-establish>—Number of sessions in establishment phase.
 <sessions-network>—Number of session in network phase.
 <sessions-total>—Total number of sessions.

<ppp-statistics-information>

- Usage** <rpc-reply>
 <ppp-statistics-information>
 <ppp-session-statistics>...</ppp-session-statistics>
 <ppp-memory-statistics>...</ppp-memory-statistics>
 </ppp-statistics-information>
 </rpc-reply>
- Description** PPP statistics.
- Contents** <ppp-memory-statistics>—PPP process memory statistics.
 <ppp-session-statistics>—PPP session statistics.

<ppp-summary-information>

- Usage** <rpc-reply>
 <ppp-summary-information>
 <ppp-session>...</ppp-session>
 </ppp-summary-information>
 </rpc-reply>
- Description** PPP summary information.
- Contents** <ppp-session>—PPP session.

<session-flags>

Usage <ppp-session>
 <session-flags>
 <session-bundled/>
 <session-ncp-only/>
 <session-always-up/>
 <session-tcc/>
 <session-looped/>
 <session-monitored/>
 </session-flags>
 </ppp-session>

Description PPP session flags.

Contents <session-always-up>—Session is always up.

<session-bundled>—Session is part of a multilink bundle.

<session-looped>—Session has detected a loop.

<session-monitored>—Session packet exchange is being monitored.

<session-ncp-only>—Session only negotiates Network Control Protocol.

<session-tcc>—Session is a translational cross-connect.

Summary of PPP over Ethernet Response Tags

This section lists JUNOS XML tags that contain information about the Point-to-Point Protocol (PPP) over Ethernet. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-pppoed>. To review the DTD for the tags, see “DTD for PPP over Ethernet Response Tags” on page 1897.

<pppoe-counters>

Usage <pppoe-statistics>
 <pppoe-counters>
 <padi-sent>*padi-sent*</padi-sent>
 <padi-received>*padi-received*</padi-received>
 <pado-sent>*pado-sent*</pado-sent>
 <pado-received>*pado-received*</pado-received>
 <padr-sent>*padr-sent*</padr-sent>
 <padr-received>*padr-received*</padr-received>
 <pads-sent>*pads-sent*</pads-sent>
 <pads-received>*pads-received*</pads-received>
 <padt-sent>*padt-sent*</padt-sent>
 <padt-received>*padt-received*</padt-received>
 <servname-err-sent>*servname-err-sent*</servname-err-sent>
 <servname-err-received>*servname-err-received*</servname-err-received>
 <acsystem-err-sent>*acsystem-err-sent*</acsystem-err-sent>
 <acsystem-err-received>*acsystem-err-received*</acsystem-err-received>
 <generic-err-sent>*generic-err-sent*</generic-err-sent>
 <generic-err-received>*generic-err-received*</generic-err-received>
 <malformed-pkt-received>*malformed-pkt-received*</malformed-pkt-received>
 <unknown-pkt-received>*unknown-pkt-received*</unknown-pkt-received>
 <padi-tmo>*padi-tmo*</padi-tmo>
 <pado-tmo>*pado-tmo*</pado-tmo>
 <padr-tmo>*padr-tmo*</padr-tmo>
 </pppoe-counters>
 </pppoe-statistics>

Description No documentation is available yet.

Contents <acsystem-err-received>—AC system error received counter.

<acsystem-err-sent>—AC system error sent counter.

<generic-err-received>—Generic error received counter.

<generic-err-sent>—Generic error sent counter.

<malformed-pkt-received>—Generic error received counter.

<padi-received>—PADI received counter.

<padi-sent>—PADI sent counter.

<padi-tmo>—PADI timeout counter.

<pado-received>—PADO received counter.

<pado-sent>—PADO sent counter.

<pado-tmo>—PADO timeout counter.

<padr-received>—PADR received counter.

<padr-sent>—PADR sent counter.

<padr-tmo>—PADR timeout counter.

<pads-received>—PADS received counter.

<pads-sent>—PADS sent counter.

<padt-received>—PADT received counter.

<padt-sent>—PADT sent counter.

<servname-err-received>—Service name error received counter.

<servname-err-sent>—Service name error sent counter.

<unknown-pkt-received>—Unknown packet received counter.

<pppoe-interface>

Usage <pppoe-interface-information>
<pppoe-interface>
 <interface-name>*interface-name*</interface-name>
 <interface-index>*interface-index*</interface-index>
 <underlying-interface-name>*underlying-interface-name*
 </underlying-interface-name>
 <underlying-interface-index>*underlying-interface-index*
 </underlying-interface-index>
 <state>*state*</state>
 <session-id>*session-id*</session-id>
 <ac-name-config>*ac-name-config*</ac-name-config>
 <ac-name-session>*ac-name-session*</ac-name-session>
 <service-name>*service-name*</service-name>
 <ac-mac>*ac-mac*</ac-mac>
 <auto-reconnect>*auto-reconnect*</auto-reconnect>
 <idle-timeout>*idle-timeout*</idle-timeout>
 <session-uptime>*session-uptime*</session-uptime>
</pppoe-interface>
 </pppoe-interface-information>

Description No documentation is available yet.

Contents <ac-mac>—AC MAC address.

<ac-name-config>—Configured AC name.

<ac-name-session>—Session AC name.

<auto-reconnect>—Autoreconnect timeout.

<idle-timeout>—Idle timeout.

<interface-index>—Index.

<interface-name>—Interface name.

<service-name>—Service name.

<session-id>—Session ID.

<session-uptime>—Duration for which the session has been up.

<state>—State.

<underlying-interface-index>—Underlying interface index.

<underlying-interface-name>—Underlying interface name.

<pppoe-interface-information>

- Usage** <rpc-reply>
 <pppoe-interface-information>
 <pppoe-interface>...</pppoe-interface>
 </pppoe-interface-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <pppoe-interface>—No documentation is available yet.

<pppoe-statistics>

- Usage** <pppoe-statistics-information>
 <pppoe-statistics>
 <active-sessions>active-sessions</active-sessions>
 <pppoe-counters>...</pppoe-counters>
 </pppoe-statistics>
 </pppoe-statistics-information>
- Description** No documentation is available yet.
- Contents** <active-sessions>—Number of active PPPoE sessions.
 <pppoe-counters>—No documentation is available yet.

<pppoe-statistics-information>

- Usage** <rpc-reply>
 <pppoe-statistics-information>
 <pppoe-statistics>...</pppoe-statistics>
 </pppoe-statistics-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <pppoe-statistics>—No documentation is available yet.

<pppoe-version>

Usage <rpc-reply>
 <pppoe-version>
 <max-sessions>*max-sessions*</max-sessions>
 <padi-resend-tmo>*padi-resend-tmo*</padi-resend-tmo>
 <padr-resend-tmo>*padr-resend-tmo*</padr-resend-tmo>
 <max-resend-tmo>*max-resend-tmo*</max-resend-tmo>
 <max-ac-tmo>*max-ac-tmo*</max-ac-tmo>
 </pppoe-version>
 </rpc-reply>

Description No documentation is available yet.

Contents <max-ac-tmo>—Maximum configured AC timeout.

<max-resend-tmo>—Maximum resend timeout.

<max-sessions>—Maximum number of PPPoE sessions.

<padi-resend-tmo>—PADI resend timeout.

<padr-resend-tmo>—PADR resend timeout.

Summary of Probe-Test Response Tags

This section lists JUNOS XML tags that contain information about probe tests related to real-time performance monitoring. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-probe-tests>. To review the DTD for the tags, see “DTD for Probe-Test Response Tags” on page 1901.

<hop>

Usage <traceroute-results>
 <hop>
 <ttl-value>*ttl-value*</ttl-value>
 <percent-loss>*percent-loss*</percent-loss>
 <icmp-extension>*icmp-extension*</icmp-extension>
 <probe-result>...</probe-result>
 </hop>
 </traceroute-results>

Description Traceroute results for a single hop (TTL value).

Contents <icmp-extension>—String representation of data in ICMP packet extension.
 <percent-loss>—Probe packet loss (no response at all) as percentage.
 <probe-result>—Result of one probe.
 <ttl-value>—Current TTL value being sent in probes.

<icmp-code>

Usage <probe-result>
 <icmp-code>
 <icmp-code-none/>
 <icmp-unreach-net/>
 <icmp-unreach-host/>
 <icmp-unreach-protocol/>
 <icmp-unreach-port/>
 <icmp-unreach-needfrag/>
 <icmp-unreach-srcfail/>
 <icmp-unreach-net-unknown/>
 <icmp-unreach-host-unknown/>
 <icmp-unreach-isolated/>
 <icmp-unreach-net-prohib/>
 <icmp-unreach-host-prohib/>
 <icmp-unreach-tosnet/>
 <icmp-unreach-toshost/>
 <icmp-unreach-filter-prohib/>
 <icmp-unreach-host-precedence/>
 <icmp-unreach-precedence-cutoff/>
 <icmp-redirect-net/>
 <icmp-redirect-host/>
 <icmp-redirect-tosnet/>
 <icmp-redirect-toshost/>
 <icmp-timxceed-intrans/>
 <icmp-timxceed-reass/>
 <icmp-paramprob-optabsent/>
 <icmp6-unreach-noroute/>
 <icmp6-unreach-admin/>
 <icmp6-unreach-beyond-scope/>
 <icmp6-unreach-address/>
 <icmp6-unreach-port/>
 <icmp6-time-exceed-transit/>
 <icmp6-time-exceed-reassembly/>
 <icmp6-parameter-problem-header/>
 <icmp6-parameter-problem-nextheader/>
 <icmp6-parameter-problem-option/>
 <icmp6-ni-subject-ipv6/>
 <icmp6-ni-subject-fqdn/>
 <icmp6-ni-subject-ipv4/>
 <icmp6-ni-success/>
 <icmp6-ni-refused/>
 <icmp6-ni-unknown/>
 </icmp-code>
 </probe-result>

Description Type of ICMP message type sub code.

Contents <icmp-code-none>—No documentation is available yet.

<icmp-paramprob-optabsent>—No documentation is available yet.

<icmp-redirect-host>—No documentation is available yet.

<icmp-redirect-net>—No documentation is available yet.

<icmp-redirect-toshost>—No documentation is available yet.

<icmp-redirect-tosnet>—No documentation is available yet.

<icmp-timxceed-intrans>—No documentation is available yet.

<icmp-timxceed-reass>—No documentation is available yet.

<icmp-unreach-filter-prohib>—No documentation is available yet.

<icmp-unreach-host>—No documentation is available yet.

<icmp-unreach-host-precedence>—No documentation is available yet.

<icmp-unreach-host-prohib>—No documentation is available yet.

<icmp-unreach-host-unknown>—No documentation is available yet.

<icmp-unreach-isolated>—No documentation is available yet.

<icmp-unreach-needfrag>—No documentation is available yet.

<icmp-unreach-net>—No documentation is available yet.

<icmp-unreach-net-prohib>—No documentation is available yet.

<icmp-unreach-net-unknown>—No documentation is available yet.

<icmp-unreach-port>—No documentation is available yet.

<icmp-unreach-precedence-cutoff>—No documentation is available yet.

<icmp-unreach-protocol>—No documentation is available yet.

<icmp-unreach-srcfail>—No documentation is available yet.

<icmp-unreach-toshost>—No documentation is available yet.

<icmp-unreach-tosnet>—No documentation is available yet.

<icmp6-ni-refused>—No documentation is available yet.

<icmp6-ni-subject-fqdn>—No documentation is available yet.

<icmp6-ni-subject-ipv4>—No documentation is available yet.

<icmp6-ni-subject-ipv6>—No documentation is available yet.

<icmp6-ni-success>—No documentation is available yet.

<icmp6-ni-unknown>—No documentation is available yet.

<icmp6-parameter-problem-header>—No documentation is available yet.

<icmp6-parameter-problem-nexthead>—No documentation is available yet.

<icmp6-parameter-problem-option>—No documentation is available yet.

<icmp6-time-exceed-reassembly>—No documentation is available yet.

<icmp6-time-exceed-transit>—No documentation is available yet.

<icmp6-unreach-address>—No documentation is available yet.

<icmp6-unreach-admin>—No documentation is available yet.

<icmp6-unreach-beyond-scope>—No documentation is available yet.

<icmp6-unreach-noroute>—No documentation is available yet.

<icmp6-unreach-port>—No documentation is available yet.

<icmp-type>

Usage <probe-result>
 <icmp-type>
 <icmp-type-none/>
 <icmp-echoreply/>
 <icmp-unreach/>
 <icmp-sourcequench/>
 <icmp-redirect/>
 <icmp-echo/>
 <icmp-routeradvert/>
 <icmp-routersolicit/>
 <icmp-timxceed/>
 <icmp-paramprob/>
 <icmp-tstamp/>
 <icmp-tstampreply/>
 <icmp-ireq/>
 <icmp-ireqreply/>
 <icmp-maskreq/>
 <icmp-maskreply/>
 <icmp6-unreach/>
 <icmp6-packet-too-big/>
 <icmp6-time-exceeded/>
 <icmp6-parameter-problem/>
 <icmp6-echo-request/>
 <icmp6-echo-reply/>
 <icmp6-membership-query/>
 <icmp6-membership-report/>
 <icmp6-membership-reduction/>
 <icmp6-router-solicit/>
 <icmp6-router-advert/>
 <icmp6-neighbor-solicit/>
 <icmp6-neighbor-advert/>
 <icmp6-redirect/>
 <icmp6-router-renumbering/>
 <icmp6-ni-query/>
 <icmp6-ni-reply/>
 </icmp-type>
 </probe-result>

Description Type of ICMP message.

Contents <icmp-echo>—No documentation is available yet.
 <icmp-echoreply>—No documentation is available yet.
 <icmp-ireq>—No documentation is available yet.
 <icmp-ireqreply>—No documentation is available yet.
 <icmp-maskreply>—No documentation is available yet.
 <icmp-maskreq>—No documentation is available yet.
 <icmp-paramprob>—No documentation is available yet.

<icmp-redirect>—No documentation is available yet.

<icmp-routeradvert>—No documentation is available yet.

<icmp-routersolicit>—No documentation is available yet.

<icmp-sourcequench>—No documentation is available yet.

<icmp-timxceed>—No documentation is available yet.

<icmp-tstamp>—No documentation is available yet.

<icmp-tstampreply>—No documentation is available yet.

<icmp-type-none>—No documentation is available yet.

<icmp-unreach>—No documentation is available yet.

<icmp6-echo-reply>—No documentation is available yet.

<icmp6-echo-request>—No documentation is available yet.

<icmp6-membership-query>—No documentation is available yet.

<icmp6-membership-reduction>—No documentation is available yet.

<icmp6-membership-report>—No documentation is available yet.

<icmp6-neighbor-advert>—No documentation is available yet.

<icmp6-neighbor-solicit>—No documentation is available yet.

<icmp6-ni-query>—No documentation is available yet.

<icmp6-ni-reply>—No documentation is available yet.

<icmp6-packet-too-big>—No documentation is available yet.

<icmp6-parameter-problem>—No documentation is available yet.

<icmp6-redirect>—No documentation is available yet.

<icmp6-router-advert>—No documentation is available yet.

<icmp6-router-renumbering>—No documentation is available yet.

<icmp6-router-solicit>—No documentation is available yet.

<icmp6-time-exceeded>—No documentation is available yet.

<icmp6-unreach>—No documentation is available yet.

<ip-options>

Usage	<pre> <probe-result> <ip-options> <record-route>...</record-route> <loose-source-route>...</loose-source-route> <strict-source-route>...</strict-source-route> </ip-options> </probe-result> </pre>
Description	IP options contained in the response.
Contents	<pre> <loose-source-route>—Loose source route (LSRR) IP option. <record-route>—Record route (RR) IP option. <strict-source-route>—Strict source route (SSRR) IP option. </pre>

<loose-source-route>

Usage	<pre> <ip-options> <loose-source-route> <record-route-host>...</record-route-host> </loose-source-route> </ip-options> </pre>
Description	Loose source route (LSRR) IP option.
Contents	<pre> <record-route-host>—Host entry in the record route. </pre>

<ping-results>

Usage <rpc-reply>
 <ping-results>
 <target-host>*target-host*</target-host>
 <source>*source*</source>
 <target-ip>*target-ip*</target-ip>
 <packet-size>*packet-size*</packet-size>
 <probe-result>...</probe-result>
 <probe-results-summary>...</probe-results-summary>
 <ping-success/>
 <ping-failure>*ping-failure*</ping-failure>
 </ping-results>
 </rpc-reply>

Description No documentation is available yet.

Contents <packet-size>—Packet size of probes (bytes).
 <ping-failure>—Ping failed.
 <ping-success>—Destination was reached.
 <probe-result>—Result of one probe.
 <probe-results-summary>—Summary of probe results.
 <source>—Specified source address or hostname.
 <target-host>—Specified target address or hostname.
 <target-ip>—Resolved target IP address.

<probe-result>

Usage <ping-results | hop>
<probe-result>
 <date-determined>*date-determined*</date-determined>
 <probe-index>*probe-index*</probe-index>
 <sequence-number>*sequence-number*</sequence-number>
 <time-to-live>*time-to-live*</time-to-live>
 <response-size>*response-size*</response-size>
 <rtt>*rtt*</rtt>
 <ingress-interface>*ingress-interface*</ingress-interface>
 <icmp-type>...</icmp-type>
 <icmp-code>...</icmp-code>
 <ip-address>*ip-address*</ip-address>
 <host-name>*host-name*</host-name>
 <ip-options>...</ip-options>
 <probe-success/>
 <probe-duplicate/>
 <probe-reached/>
 <probe-failure>*probe-failure*</probe-failure>
</probe-result>
 </ping-results | hop>

Description Result of one probe.

Contents <date-determined>—UTC time when the result was determined, as number of seconds since 1 January 1970.

<host-name>—Hostname of interface that received probe.

<icmp-code>—Type of ICMP message type sub code.

<icmp-type>—Type of ICMP message.

<ingress-interface>—Interface that received the response.

<ip-address>—IP address of interface that received probe.

<ip-options>—IP options contained in the response.

<probe-duplicate>—A duplicate response was received.

<probe-failure>—No valid response received.

<probe-index>—Sequence number of probe.

<probe-reached>—Probe reached destination host.

<probe-success>—A valid response was received.

<response-size>—Size of response (bytes).

<rtt>—Route trip time for probe (microseconds).

`<sequence-number>`—Sequence number in response packet.

`<time-to-live>`—Time-to-live (TTL) value in response packet.

`<probe-results-summary>`

Usage `<ping-results>`
`<probe-results-summary>`
`<probes-sent>`*probes-sent*`</probes-sent>`
`<responses-received>`*responses-received*`</responses-received>`
`<packet-loss>`*packet-loss*`</packet-loss>`
`<response-duplicates>`*response-duplicates*`</response-duplicates>`
`<response-unexpected-sequence>`*response-unexpected-sequence*
`</response-unexpected-sequence>`
`<rtt-minimum>`*rtt-minimum*`</rtt-minimum>`
`<rtt-average>`*rtt-average*`</rtt-average>`
`<rtt-maximum>`*rtt-maximum*`</rtt-maximum>`
`<rtt-stddev>`*rtt-stddev*`</rtt-stddev>`
`</probe-results-summary>`
`</ping-results>`

Description Summary of probe results.

Contents `<packet-loss>`—Percentage of probes that resulted in no response.

`<probes-sent>`—Number of probes sent to target host.

`<response-duplicates>`—Number of duplicate responses received for one or more probes.

`<response-unexpected-sequence>`—Number of responses received with unexpected sequence number.

`<responses-received>`—Number of responses to probes received from target host.

`<rtt-average>`—Average round trip time (microseconds).

`<rtt-maximum>`—Maximum round trip time (microseconds).

`<rtt-minimum>`—Minimum round trip time (microseconds).

`<rtt-stddev>`—Standard Deviation of round trip time (microseconds).

`<record-route>`

Usage `<ip-options>`
`<record-route>`
`<record-route-host>`...`</record-route-host>`
`</record-route>`
`</ip-options>`

Description Record route (RR) IP option.

Contents `<record-route-host>`—Host entry in the record route.

<record-route-host>

Usage <record-route | loose-source-route | strict-source-route>
 <record-route-host>
 <ip-address>*ip-address*</ip-address>
 <host-name>*host-name*</host-name>
 </record-route-host>
 </record-route | loose-source-route | strict-source-route>

Description Host entry in the record route.

Contents <host-name>—Hostname of interface that received probe.
 <ip-address>—IP address of interface that received probe.

<strict-source-route>

Usage <ip-options>
 <strict-source-route>
 <record-route-host>...</record-route-host>
 </strict-source-route>
 </ip-options>

Description Strict source route (SSRR) IP option.

Contents <record-route-host>—Host entry in the record route.

<traceroute-results>

Usage <rpc-reply>
 <traceroute-results>
 <target-host>*target-host*</target-host>
 <source>*source*</source>
 <target-ip>*target-ip*</target-ip>
 <packet-size>*packet-size*</packet-size>
 <max-hop-index>*max-hop-index*</max-hop-index>
 <hop>...</hop>
 <traceroute-success/>
 <traceroute-failure>*traceroute-failure*</traceroute-failure>
 </traceroute-results>
 </rpc-reply>

Description No documentation is available yet.

Contents <hop>—Traceroute results for a single hop (TTL value).
 <max-hop-index>—Maximum number of hops (maximum TTL value).
 <packet-size>—Packet size of probes (bytes).
 <source>—Specified source address or hostname.
 <target-host>—Specified target address or hostname.
 <target-ip>—Resolved target IP address.
 <traceroute-failure>—Traceroute failed.
 <traceroute-success>—Destination was reached.

Summary of Product Metadata Response Tags

This section lists JUNOS XML tags that contain information about the product metadata. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-productmetadata>. To review the DTD for the tags, see DTD for Product Metadata Response Tag Elements on page 1907

<product>

Usage <product-metadata-information>

```

  <product>
    <model>model</model>
    <product-number>product-number</product-number>
    <series>series</series>
    <product-line>product-line</product-line>
    <name>name</name>
    <description>description</description>
    <flag>flag</flag>
    <max-fpc-per-router>max-fpc-per-router</max-fpc-per-router>
    <max-fpc-per-chassis>max-fpc-per-chassis</max-fpc-per-chassis>
    <max-pics-per-slot>max-pics-per-slot</max-pics-per-slot>
    <max-sfm>max-sfm</max-sfm>
    <max-pfe-per-slot>max-pfe-per-slot</max-pfe-per-slot>
    <max-re>max-re</max-re>
    <max-chassis>max-chassis</max-chassis>
    <max-spm-per-chassis>max-spm-per-chassis</max-spm-per-chassis>
    <max-sib-per-chassis>max-sib-per-chassis</max-sib-per-chassis>
    <max-pem-per-chassis>max-pem-per-chassis</max-pem-per-chassis>
    <max-fwd-classes>max-fwd-classes</max-fwd-classes>
    <defaults>defaults</defaults>
    <factory>factory</factory>
  </product>
</product-metadata-information>

```

Description Information about a product.

Contents <defaults>—Defaults configuration file.

<description>—Descriptive name of the product.

<factory>—Factory configuration file.

<flag>—Flags for the product model.

<max-chassis>—Maximum number of chassis.

<max-fpc-per-chassis>—Maximum number of FPCs in a single chassis.

<max-fpc-per-router>—Maximum number of FPCs in the router.

<max-fwd-classes>—Maximum number of forwarding classes.

<max-pem-per-chassis>—Maximum number of Power Entry Modules per chassis.

<max-pfe-per-slot>—Maximum number of Packet Forwarding Engines per slot.

<max-pics-per-slot>—Maximum number of pics per slot.

<max-re>—Maximum number of Routing Engines.

<max-sfm>—Maximum number of Switching and Forwarding Modules.

<max-sib-per-chassis>—Maximum number of Switch Interface Boards per chassis.

<max-symb-per-chassis>—Maximum number of Switch Processor Mezzanine Boards per chassis.

<model>—Product model number.

<name>—Official name of the product.

<product-line>—Product-line of the product.

<product-number>—Product number.

<series>—Product version.

<product-metadata-information>

Usage <rpc-reply>
 <product-metadata-information>
 <product>...</product>
 </product-metadata-information>
 </rpc-reply>

Description Information on one or more products.

Contents <product>—Information about a product.

Summary of Redundant Interfaces Response Tags

This section lists JUNOS XML tags that contain operational information about redundant services interfaces. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-rdd>. To review the DTD for the tags, see “DTD for Redundant Interfaces Response Tags” on page 1909.

<interface-redundancy>

Usage <interface-redundancy-information>
 <interface-redundancy>
 <interface-name>*interface-name*</interface-name>
 <state>*state*</state>
 <last-change>*last-change*</last-change>
 <primary>*primary*</primary>
 <secondary>*secondary*</secondary>
 <current-status>*current-status*</current-status>
 </interface-redundancy>
 </interface-redundancy-information>

Description No documentation is available yet.

Contents <current-status>—Status of primary or secondary interface, or both.
 <interface-name>—Name of the interface.
 <last-change>—Time since last state change ([weeks][days] hours:minutes[:seconds]).
 <primary>—Primary interface.
 <secondary>—Secondary interface.
 <state>—Interface state.

<interface-redundancy-information>

Usage <rpc-reply>
 <interface-redundancy-information>
 <interface-redundancy>...</interface-redundancy>
 </interface-redundancy-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <interface-redundancy>—No documentation is available yet.

Summary of Resource Cleanup Response Tags

This section lists JUNOS XML tags that contain operational information about resource cleanup. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-res-cleanup>. To review the DTD for the tags, see “DTD for Resource Cleanup Response Tags” on page 1911.

<cleanup-resources>

Usage <process-resource-cleanup>
 <cleanup-resources>
 <resource>...</resource>
 </cleanup-resources>
 </process-resource-cleanup>

Description Resources that can be cleaned up.

Contents <resource>—Resource information.

<process-resource-cleanup>

Usage <system-resource-cleanup-processes-information>
 <process-resource-cleanup>
 <pid>*pid*</pid>
 <process-name>*process-name*</process-name>
 <cleanup-resources>...</cleanup-resources>
 </process-resource-cleanup>
 </system-resource-cleanup-processes-information>

Description Resource clean up information for a process.

Contents <cleanup-resources>—Resources that can be cleaned up.

 <pid>—Process identifier.

 <process-name>—Process name.

<resource>

Usage	<pre> <cleanup-resources> <resource> <type>type</type> <major-number>major-number</major-number> <minor-number>minor-number</minor-number> <id>id</id> <key>key</key> </resource> </cleanup-resources> </pre>
Description	Resource information.
Contents	<p><id>—Resource ID.</p> <p><key>—Resource key value.</p> <p><major-number>—GENCFG blob major number.</p> <p><minor-number>—GENCFG blob minor number.</p> <p><type>—Resource type name.</p>

<resource-type>

Usage	<pre> <system-resource-cleanup-resources-information> <resource-type> <type>type</type> </resource-type> </system-resource-cleanup-resources-information> </pre>
Description	Type of resource.
Contents	<type>—Resource type name.

<system-resource-cleanup-processes-information>

Usage	<pre> <rpc-reply> <system-resource-cleanup-processes-information> <process-resource-cleanup>...</process-resource-cleanup> </system-resource-cleanup-processes-information> </rpc-reply> </pre>
Description	Resource clean up information for one or more processes.
Contents	<process-resource-cleanup>—Resource clean up information for a process.

<system-resource-cleanup-resources-information>

Usage <rpc-reply>
 <system-resource-cleanup-resources-information>
 <resource-type>...</resource-type>
 </system-resource-cleanup-resources-information>
 </rpc-reply>

Description Resources types that can be cleaned up.

Contents <resource-type>—Type of resource.

Summary of Routing and Forwarding Table Response Tags

This section lists JUNOS XML tags that contain operational information about routing and forwarding tables. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-rtinfo>. To review the DTD for the tags, see “DTD for Routing and Forwarding Table Response Tags” on page 2019.

<bridge-mac-destination-address-statistics>

Usage	<pre><rt-entry> <bridge-mac-destination-address-statistics> <packet-count>packet-count</packet-count> <byte-count>byte-count</byte-count> </bridge-mac-destination-address-statistics> </rt-entry></pre>
Description	MAC destination address statistics.
Contents	<pre><byte-count>—Byte count. <packet-count>—Packet count.</pre>

<bridge-mac-source-address-statistics>

Usage	<pre><rt-entry> <bridge-mac-source-address-statistics> <packet-count>packet-count</packet-count> <byte-count>byte-count</byte-count> </bridge-mac-source-address-statistics> </rt-entry></pre>
Description	MAC source address statistics.
Contents	<pre><byte-count>—Byte count. <packet-count>—Packet count.</pre>

<forwarding-table-information>

Usage	<pre><rpc-reply> <forwarding-table-information> <route-table>...</route-table> </forwarding-table-information> </rpc-reply></pre>
Description	Information about forwarding-table routing entries.
Contents	<pre><route-table>—Denotes a routing table.</pre>

<nh>

Usage <rt-entry>
 <nh>
 <to>*to*</to>
 <nh-type>*nh-type*</nh-type>
 <nh-index>*nh-index*</nh-index>
 <nh-reference-count>*nh-reference-count*</nh-reference-count>
 <via>*via*</via>
 <nh-weight>*nh-weight*</nh-weight>
 <nh-balance>*nh-balance*</nh-balance>
 <nh-composite-num-nhs>*nh-composite-num-nhs*</nh-composite-num-nhs>
 <nh-composite-nh-index>*nh-composite-nh-index*</nh-composite-nh-index>
 <nh-composite-function>*nh-composite-function*</nh-composite-function>
 <nh-composite-num-derived-nhs>*nh-composite-num-derived-nhs*
 </nh-composite-num-derived-nhs>
 <nh-composite-derived-nh-index>*nh-composite-derived-nh-index*
 </nh-composite-derived-nh-index>
 </nh>
 </rt-entry>

Description Next hop for this routing table entry.

Contents <nh-balance>—Next-hop balance.

<nh-composite-derived-nh-index>—Index of derived next hops in a composite next hop.

<nh-composite-function>—Composition function for next hops in a composite next hop.

<nh-composite-nh-index>—Index of next hops in a composite next hop.

<nh-composite-num-derived-nhs>—Number of derived next hops for a composite next hop.

<nh-composite-num-nhs>—Number of next hops in a composite next hop.

<nh-index>—Index in next-hop table.

<nh-reference-count>—Next-hop reference count.

<nh-type>—Next-hop type.

<nh-weight>—Next-hop weight.

<to>—Next-hop address for this entry.

<via>—Network interface name.

<route-table>

Usage <forwarding-table-information>
 <route-table>
 <logical-system-name>*logical-system-name*</logical-system-name>
 <table-name>*table-name*</table-name>
 <bd-name>*bd-name*</bd-name>
 <route-table-deleted/>
 <bridge-table-deleted/>
 <address-family>*address-family*</address-family>
 <address-family-number>*address-family-number*</address-family-number>
 <rt-entry>...</rt-entry>
 <route-table-summary>...</route-table-summary>
 </route-table>
 </forwarding-table-information>

Description Denotes a routing table.

Contents <address-family>—Address family for this routing table.

<address-family-number>—If the address family name is unknown, print the number.

<bd-name>—Name of this bridging domain.

<bridge-table-deleted>—Whether this bridge table has been deleted.

<logical-system-name>—Name of this logical system.

<route-table-deleted>—Whether this routing table has been deleted.

<route-table-summary>—Routing table summary.

<rt-entry>—Routing table entry for a destination.

<table-name>—Name of this routing table.

<route-table-summary>

Usage <route-table>
 <route-table-summary>
 <route-table-type>*route-table-type*</route-table-type>
 <route-count>*route-count*</route-count>
 </route-table-summary>
 </route-table>

Description Routing table summary.

Contents <route-count>—Number of routes in this routing table.

<route-table-type>—Type for this routing table.

<rpf-information>

Usage <rt-entry>
 <rpf-information>
 <via>via</via>
 </rpf-information>
 </rt-entry>

Description Reverse-path forwarding check for this route.

Contents <via>—Network interface name.

<rt-entry>

Usage <route-table>
 <rt-entry>
 <rt-destination>*rt-destination*</rt-destination>
 <learn-vlan>*learn-vlan*</learn-vlan>
 <destination-type>*destination-type*</destination-type>
 <route-reference-count>*route-reference-count*</route-reference-count>
 <route-interface-index>*route-interface-index*</route-interface-index>
 <ifl-generation>*ifl-generation*</ifl-generation>
 <epoch>*epoch*</epoch>
 <mac-sequence-number>*mac-sequence-number*</mac-sequence-number>
 <learn-mask>*learn-mask*</learn-mask>
 <l2al-rtflags>*l2al-rtflags*</l2al-rtflags>
 <route-flags>*route-flags*</route-flags>
 <nh>...</nh>
 <rpf-information>...</rpf-information>
 <vpls-mac-source-address-statistics>...</vpls-mac-source-address-statistics>
 <vpls-mac-destination-address-statistics>...
 </vpls-mac-destination-address-statistics>
 <bridge-mac-source-address-statistics>...
 </bridge-mac-source-address-statistics>
 <bridge-mac-destination-address-statistics>...
 </bridge-mac-destination-address-statistics>
 </rt-entry>
 </route-table>

Description Routing table entry for a destination.

Contents <bridge-mac-destination-address-statistics>—MAC destination address statistics.
 <bridge-mac-source-address-statistics>—MAC source address statistics.
 <destination-type>—Destination type for this entry.
 <epoch>—Time when this MAC was learned.
 <ifl-generation>—Creation time of the IFL when this MAC was learned.
 <l2al-rtflags>—Route flags associated with MAC routes.
 <learn-mask>—Mask of PFEs where this MAC was learned.
 <learn-vlan>—VLAN ID in the routing instance in which the MAC address was learned.
 <mac-sequence-number>—Sequence number assigned to this MAC.
 <nh>—Next hop for this routing table entry.
 <route-flags>—Flags associated with this route entry.
 <route-interface-index>—Interface referenced by this route.
 <route-reference-count>—Reference count for this destination entry.

<rpf-information>—Reverse-path forwarding check for this route.

<rt-destination>—Destination address.

<vpls-mac-destination-address-statistics>—MAC destination address statistics.

<vpls-mac-source-address-statistics>—MAC source address statistics.

<vpls-mac-destination-address-statistics>

Usage <rt-entry>
 <vpls-mac-destination-address-statistics>
 <packet-count>*packet-count*</packet-count>
 <byte-count>*byte-count*</byte-count>
 </vpls-mac-destination-address-statistics>
 </rt-entry>

Description MAC destination address statistics.

Contents <byte-count>—Byte count.
 <packet-count>—Packet count.

<vpls-mac-source-address-statistics>

Usage <rt-entry>
 <vpls-mac-source-address-statistics>
 <packet-count>*packet-count*</packet-count>
 <byte-count>*byte-count*</byte-count>
 </vpls-mac-source-address-statistics>
 </rt-entry>

Description MAC source address statistics.

Contents <byte-count>—Byte count.
 <packet-count>—Packet count.

Summary of Routing Protocols Response Tags

This section lists JUNOS XML tags that contain operational information about routing protocols. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-routing>. To review the DTD for the tags, see “DTD for Routing Protocols Response Tags” on page 1913.

<accepted-prefix-limit>

Usage <bgp-option-information>
 <accepted-prefix-limit>
 <nlri-type>*nlri-type*</nlri-type>
 <prefix-count>*prefix-count*</prefix-count>
 <limit-action>*limit-action*</limit-action>
 <warning-percentage>*warning-percentage*</warning-percentage>
 </accepted-prefix-limit>
 </bgp-option-information>

Description Limit number of prefixes accepted by policy.

Contents <limit-action>—Action taken upon reaching limit.
 <nlri-type>—Type of NLRI being limited.
 <prefix-count>—Number of prefixes accepted before action is taken.
 <warning-percentage>—Percentage of limit at which to log a warning.

<admin-groups>

Usage <isis-reachability-subtlv | mpls-lsp | mpls-lsp-path | ted-link>
 <admin-groups>
 <color>*color*</color>
 <no-group-flag/>
 <admin-group-name>*admin-group-name*</admin-group-name>
 <admin-group-number>*admin-group-number*</admin-group-number>
 </admin-groups>
 </isis-reachability-subtlv | mpls-lsp | mpls-lsp-path | ted-link>

Description No documentation is available yet.

Contents <admin-group-name>—Name of the admin group.
 <admin-group-number>—Number of the admin group.
 <color>—No documentation is available yet.
 <no-group-flag>—No documentation is available yet.

<aggregate>

Usage	<pre> <rt-entry> <aggregate> <aggregate-flags>aggregate-flags</aggregate-flags> <aggregate-depth>aggregate-depth</aggregate-depth> <aggregate-active/> <aggregate-as-path>...</aggregate-as-path> <contributing-route-count>contributing-route-count</contributing-route-count> <aggregated-route>...</aggregated-route> </aggregate> </rt-entry> </pre>
Description	No documentation is available yet.
Contents	<p><aggregate-active>—Present if this aggregate is active.</p> <p><aggregate-as-path>—No documentation is available yet.</p> <p><aggregate-depth>—Depth of this aggregate.</p> <p><aggregate-flags>—Flags on this aggregate route entry.</p> <p><aggregated-route>—No documentation is available yet.</p> <p><contributing-route-count>—Number of contributing routes in this aggregate.</p>

<aggregate-as-path>

Usage	<pre> <aggregate> <aggregate-as-path> <as-path>as-path</as-path> <reference-count>reference-count</reference-count> </aggregate-as-path> </aggregate> </pre>
Description	No documentation is available yet.
Contents	<p><as-path>—AS path of this route.</p> <p><reference-count>—No documentation is available yet.</p>

<aggregated-route>

Usage	<pre> <aggregate> <aggregated-route> <destination-prefix>destination-prefix</destination-prefix> <protocol-name>protocol-name</protocol-name> </aggregated-route> </aggregate> </pre>
Description	No documentation is available yet.
Contents	<p><destination-prefix>—Destination prefix and mask.</p> <p><protocol-name>—No documentation is available yet.</p>

<area-address-tlv>

Usage	<pre> <isis-tlv> <area-address-tlv> <address>address</address> <tlv-length>tlv-length</tlv-length> </area-address-tlv> </isis-tlv> </pre>
Description	No documentation is available yet.
Contents	<p><address>—No documentation is available yet.</p> <p><tlv-length>—No documentation is available yet.</p>

<aspath-bucket>

Usage	<pre> <aspath-table> <aspath-bucket> <aspath-entry>...</aspath-entry> <bucket>bucket</bucket> <count>count</count> </aspath-bucket> </aspath-table> </pre>
Description	No documentation is available yet.
Contents	<p><aspath-entry>—No documentation is available yet.</p> <p><bucket>—Hash bucket.</p> <p><count>—Number of entries.</p>

<aspath-domain>

Usage	<pre> <juniper-routing-aspath> <aspath-domain> <identifier>identifier</identifier> <domain-flags>domain-flags</domain-flags> <primary>primary</primary> <references>references</references> <path-count>path-count</path-count> <local-asn>...</local-asn> </aspath-domain> </juniper-routing-aspath> </pre>
Description	No documentation is available yet.
Contents	<p><domain-flags>—No documentation is available yet.</p> <p><identifier>—Domain identifier.</p> <p><local-asn>—No documentation is available yet.</p> <p><path-count>—Number of AS paths.</p> <p><primary>—Primary autonomous system.</p> <p><references>—Instance references.</p>

<aspath-entry>

Usage <aspath-bucket>
 <aspath-entry>
 <as-path>*as-path*</as-path>
 <domain>*domain*</domain>
 <path-references>*path-references*</path-references>
 <length>*length*</length>
 <segments>*segments*</segments>
 <overhead>*overhead*</overhead>
 <compare-length>*compare-length*</compare-length>
 <neighbor-as>*neighbor-as*</neighbor-as>
 <entry-state>*entry-state*</entry-state>
 </aspath-entry>
 </aspath-bucket>

Description No documentation is available yet.

Contents <as-path>—AS path of this route.

<compare-length>—Comparison length.

<domain>—Domain identifier.

<entry-state>—No documentation is available yet.

<length>—Number of ASs in path.

<neighbor-as>—Neighbor autonomous system.

<overhead>—Memory allocation overhead.

<path-references>—Reference count.

<segments>—Number of AS path segments.

<aspath-table>

Usage <juniper-routing-aspath>
 <aspath-table>
 <path-count>*path-count*</path-count>
 <bucket-count>*bucket-count*</bucket-count>
 <bucket-max-entries>*bucket-max-entries*</bucket-max-entries>
 <bucket-min-entries>*bucket-min-entries*</bucket-min-entries>
 <bucket-avg-entries>*bucket-avg-entries*</bucket-avg-entries>
 <bucket-std-deviation>*bucket-std-deviation*</bucket-std-deviation>
 <aspath-bucket>...</aspath-bucket>
 </aspath-table>
 </juniper-routing-aspath>

Description No documentation is available yet.

Contents <aspath-bucket>—No documentation is available yet.

<bucket-avg-entries>—Average number of entries per bucket.

<bucket-count>—Number of hash buckets in use.

<bucket-max-entries>—Maximum number of entries per bucket.

<bucket-min-entries>—Minimum number of entries per bucket.

<bucket-std-deviation>—Standard deviation of entries per bucket.

<path-count>—Number of AS paths.

<attrset>

Usage <rt-entry>
 <attrset>
 <attrset-as>*attrset-as*</attrset-as>
 <med>*med*</med>
 <local-preference>*local-preference*</local-preference>
 <as-path>*as-path*</as-path>
 <communities>...</communities>
 <cluster-id>*cluster-id*</cluster-id>
 <pmsi>*pmsi*</pmsi>
 <originator>*originator*</originator>
 </attrset>
 </rt-entry>

Description No documentation is available yet.

Contents <as-path>—AS path of this route.
 <attrset-as>—Originator AS.
 <cluster-id>—No documentation is available yet.
 <communities>—No documentation is available yet.
 <local-preference>—No documentation is available yet.
 <med>—Multiple exit discriminator.
 <originator>—No documentation is available yet.
 <pmsi>—P-multicast service interface.

<authentication-tlv>

Usage <isis-tlv>
 <authentication-tlv>
 <tlv-length>*tlv-length*</tlv-length>
 </authentication-tlv>
 </isis-tlv>

Description No documentation is available yet.

Contents <tlv-length>—No documentation is available yet.

<automatic-site-timers>

- Usage** <reference-site>
 <automatic-site-timers>
 <automatic-site-startup-wait-time>*automatic-site-startup-wait-time*
 </automatic-site-startup-wait-time>
 <automatic-site-new-site-wait-time>*automatic-site-new-site-wait-time*
 </automatic-site-new-site-wait-time>
 <automatic-site-collision-detect-time>*automatic-site-collision-detect-time*
 </automatic-site-collision-detect-time>
 <automatic-site-reclaim-wait-time>*automatic-site-reclaim-wait-time*
 </automatic-site-reclaim-wait-time>
 </automatic-site-timers>
 </reference-site>
- Description** No documentation is available yet.
- Contents** <automatic-site-collision-detect-time>—No documentation is available yet.
 <automatic-site-new-site-wait-time>—No documentation is available yet.
 <automatic-site-reclaim-wait-time>—No documentation is available yet.
 <automatic-site-startup-wait-time>—No documentation is available yet.

<backup-pes>

- Usage** <multicast-backup-pe-group>
 <backup-pes>
 <multicast-backup-pe-address>*multicast-backup-pe-address*
 </multicast-backup-pe-address>
 </backup-pes>
 </multicast-backup-pe-group>
- Description** Backup PE addresses.
- Contents** <multicast-backup-pe-address>—Backup PE address.

<bgp-bfd>

- Usage** <bgp-peer>
 <bgp-bfd>
 <bfd-configuration-state>*bfd-configuration-state*</bfd-configuration-state>
 <bfd-operational-state>*bfd-operational-state*</bfd-operational-state>
 </bgp-bfd>
 </bgp-peer>
- Description** No documentation is available yet.
- Contents** <bfd-configuration-state>—BFD configuration state for the BGP session.
 <bfd-operational-state>—BFD operational state for the BGP session.

<bgp-error>

Usage <bgp-peer>
 <bgp-error>
 <name>*name*</name>
 <send-count>*send-count*</send-count>
 <receive-count>*receive-count*</receive-count>
 </bgp-error>
</bgp-peer>

Description No documentation is available yet.

Contents <name>—No documentation is available yet.

<receive-count>—No documentation is available yet.

<send-count>—No documentation is available yet.

<bgp-group>

Usage <bgp-group-information>
 <bgp-group>
 <type>type</type>
 <peer-as>peer-as</peer-as>
 <local-as>local-as</local-as>
 <group-index>group-index</group-index>
 <group-state>group-state</group-state>
 <name>name</name>
 <bgp-options>bgp-options</bgp-options>
 <bgp-options2>bgp-options2</bgp-options2>
 <group-flags>group-flags</group-flags>
 <peer-count>peer-count</peer-count>
 <established-count>established-count</established-count>
 <peer-address>peer-address</peer-address>
 <flap-count>flap-count</flap-count>
 <unconfigured-peers>...</unconfigured-peers>
 <igp-protocol>igp-protocol</igp-protocol>
 <route-queue>...</route-queue>
 <bgp-peer>...</bgp-peer>
 <bgp-option-information>...</bgp-option-information>
 <tracing-information>...</tracing-information>
 <bgp-rib>...</bgp-rib>
 </bgp-group>
 </bgp-group-information>

Description Operational and configuration information for a BGP group.

Contents <bgp-option-information>—Configured BGP options.

<bgp-options>—No documentation is available yet.

<bgp-options2>—No documentation is available yet.

<bgp-peer>—Operational and configuration information for a BGP peer.

<bgp-rib>—No documentation is available yet.

<established-count>—Number of peers within the group that are in the established state.

<flap-count>—Number of times the BGP session has gone down.

<group-flags>—Internal BGP group flags.

<group-index>—No documentation is available yet.

<group-state>—No documentation is available yet.

<igp-protocol>—No documentation is available yet.

<local-as>—Local AS number.

<name>—No documentation is available yet.

`<peer-address>`—Address of the BGP peer, followed by its port number.

`<peer-as>`—Peer AS number.

`<peer-count>`—Total number of peers.

`<route-queue>`—No documentation is available yet.

`<tracing-information>`—No documentation is available yet.

`<type>`—No documentation is available yet.

`<unconfigured-peers>`—Set of address prefixes from which this group allows peering.

`<bgp-group-information>`

Usage `<rpc-reply>`
 `<bgp-group-information>`
 `<bgp-group>...</bgp-group>`
 `<bgp-information>...</bgp-information>`
 `</bgp-group-information>`
`</rpc-reply>`

Description Operational and configuration information for BGP groups.

Contents `<bgp-group>`—Operational and configuration information for a BGP group.

`<bgp-information>`—Operational and configuration information for BGP.

<bgp-information>

Usage <bgp-group-information>
 <bgp-information>
 <group-count>*group-count*</group-count>
 <peer-count>*peer-count*</peer-count>
 <external-peer-count>*external-peer-count*</external-peer-count>
 <internal-peer-count>*internal-peer-count*</internal-peer-count>
 <down-peer-count>*down-peer-count*</down-peer-count>
 <unconfigured-peer-count>*unconfigured-peer-count*</unconfigured-peer-count>
 <half-open-peer-count>*half-open-peer-count*</half-open-peer-count>
 <igp-converging/>
 <flap-count>*flap-count*</flap-count>
 <bgp-rib>...</bgp-rib>
 <bgp-peer>...</bgp-peer>
 </bgp-information>
 </bgp-group-information>

Description Operational and configuration information for BGP.

Contents <bgp-peer>—Operational and configuration information for a BGP peer.

<bgp-rib>—No documentation is available yet.

<down-peer-count>—No documentation is available yet.

<external-peer-count>—No documentation is available yet.

<flap-count>—Number of times the BGP session has gone down.

<group-count>—No documentation is available yet.

<half-open-peer-count>—No documentation is available yet.

<igp-converging>—This tag is present if BGP is quenched because the IGP is still converging.

<internal-peer-count>—No documentation is available yet.

<peer-count>—Total number of peers.

<unconfigured-peer-count>—No documentation is available yet.

<bgp-option-information>

Usage <bgp-peer | bgp-group>
<bgp-option-information>
 <export-policy>*export-policy*</export-policy>
 <import-policy>*import-policy*</import-policy>
 <bgp-options>*bgp-options*</bgp-options>
 <bgp-options2>*bgp-options2*</bgp-options2>
 <authentication-key>*authentication-key*</authentication-key>
 <authentication-key-chain>*authentication-key-chain*</authentication-key-chain>
 <authentication-algorithm>*authentication-algorithm*</authentication-algorithm>
 <authentication-configured/>
 <address-families>*address-families*</address-families>
 <local-address>*local-address*</local-address>
 <holdtime>*holdtime*</holdtime>
 <metric-out>*metric-out*</metric-out>
 <preference>*preference*</preference>
 <local-preference>*local-preference*</local-preference>
 <prefix-limit>...</prefix-limit>
 <accepted-prefix-limit>...</accepted-prefix-limit>
 <nlri-information>...</nlri-information>
 <local-as>*local-as*</local-as>
 <local-as-private/>
 <local-system-as>*local-system-as*</local-system-as>
 <receive-buffer-size>*receive-buffer-size*</receive-buffer-size>
 <send-buffer-size>*send-buffer-size*</send-buffer-size>
 <outbound-timer>*outbound-timer*</outbound-timer>
 <med-action>*med-action*</med-action>
 <ipsec-sa>*ipsec-sa*</ipsec-sa>
</bgp-option-information>
 </bgp-peer | bgp-group>

Description Configured BGP options.

Contents <accepted-prefix-limit>—Limit number of prefixes accepted by policy.

<address-families>—No documentation is available yet.

<authentication-algorithm>—Name of authentication algorithm.

<authentication-configured>—No documentation is available yet.

<authentication-key>—No documentation is available yet.

<authentication-key-chain>—Name of authentication key chain.

<bgp-options>—No documentation is available yet.

<bgp-options2>—No documentation is available yet.

<export-policy>—No documentation is available yet.

<holdtime>—Hold time configured with the hold-time statement. The default hold time is 90 seconds. The hold time is three times the interval at which keepalive messages are sent.

<import-policy>—No documentation is available yet.

<ipsec-sa>—No documentation is available yet.

<local-address>—No documentation is available yet.

<local-as>—Local AS number.

<local-as-private>—No documentation is available yet.

<local-preference>—No documentation is available yet.

<local-system-as>—No documentation is available yet.

<med-action>—No documentation is available yet.

<metric-out>—No documentation is available yet.

<nlrri-information>—No documentation is available yet.

<outbound-timer>—No documentation is available yet.

<preference>—Preference value configured with the preference statement. The default preference value is 170.

<prefix-limit>—No documentation is available yet.

<receive-buffer-size>—No documentation is available yet.

<send-buffer-size>—No documentation is available yet.

<bgp-orf>

Usage <bgp-orf-information>
 <bgp-orf>
 <peer-address>peer-address</peer-address>
 <peer-type>peer-type</peer-type>
 <group-name>group-name</group-name>
 <bgp-orf-nlrri-info>...</bgp-orf-nlrri-info>
 </bgp-orf>
 </bgp-orf-information>

Description No documentation is available yet.

Contents <bgp-orf-nlrri-info>—No documentation is available yet.
 <group-name>—No documentation is available yet.
 <peer-address>—Address of the BGP peer, followed by its port number.
 <peer-type>—No documentation is available yet.

<bgp-orf-extcomm-filter>

Usage	<pre> <bgp-orf-filter-info> <bgp-orf-extcomm-filter> <extended-community>extended-community</extended-community> </bgp-orf-extcomm-filter> </bgp-orf-filter-info> </pre>
Description	No documentation is available yet.
Contents	<extended-community>—Extended community.

<bgp-orf-filter-info>

Usage	<pre> <bgp-orf-filter-information> <bgp-orf-filter-info> <bgp-orf-extcomm-filter>...</bgp-orf-extcomm-filter> <bgp-orf-prefix-filter>...</bgp-orf-prefix-filter> </bgp-orf-filter-info> </bgp-orf-filter-information> </pre>
Description	No documentation is available yet.
Contents	<bgp-orf-extcomm-filter>—No documentation is available yet. <bgp-orf-prefix-filter>—No documentation is available yet.

<bgp-orf-filter-information>

Usage	<pre> <bgp-orf-nlri-info> <bgp-orf-filter-information> <filter-type>filter-type</filter-type> <filter-mode>filter-mode</filter-mode> <filter-in-updates>filter-in-updates</filter-in-updates> <filter-out-updates>filter-out-updates</filter-out-updates> <filter-qcount>filter-qcount</filter-qcount> <bgp-orf-filter-info>...</bgp-orf-filter-info> </bgp-orf-filter-information> </bgp-orf-nlri-info> </pre>
Description	No documentation is available yet.
Contents	<bgp-orf-filter-info>—No documentation is available yet. <filter-in-updates>—No documentation is available yet. <filter-mode>—No documentation is available yet. <filter-out-updates>—No documentation is available yet. <filter-qcount>—No documentation is available yet. <filter-type>—No documentation is available yet.

<bgp-orf-information>

- Usage** <rpc-reply>
 <bfgp-orf-information>
 <bgp-orf>...</bgp-orf>
 </bfgp-orf-information>
 </rpc-reply>
- Description** Operational information on BGP Outbound Route filtering.
- Contents** <bgp-orf>—No documentation is available yet.

<bgp-orf-nlri-info>

- Usage** <bgp-orf>
 <bfgp-orf-nlri-info>
 <nlri-name>nlri-name</nlri-name>
 <filter-in-updates>filter-in-updates</filter-in-updates>
 <filter-out-updates>filter-out-updates</filter-out-updates>
 <filter-qcount>filter-qcount</filter-qcount>
 <immediate-count>immediate-count</immediate-count>
 <bgp-orf-filter-information>...</bgp-orf-filter-information>
 </bfgp-orf-nlri-info>
 </bgp-orf>
- Description** No documentation is available yet.
- Contents** <bgp-orf-filter-information>—No documentation is available yet.
- <filter-in-updates>—No documentation is available yet.
- <filter-out-updates>—No documentation is available yet.
- <filter-qcount>—No documentation is available yet.
- <immediate-count>—No documentation is available yet.
- <nlri-name>—No documentation is available yet.

<bgp-orf-prefix-filter>

- Usage** <bgp-orf-filter-info>
 <bfgp-orf-prefix-filter>
 <prefix-orf>prefix-orf</prefix-orf>
 </bfgp-orf-prefix-filter>
 </bgp-orf-filter-info>
- Description** No documentation is available yet.
- Contents** <prefix-orf>—Prefix-based outbound route filter.

<bgp-output-queue>

Usage <bgp-peer>
 <bgp-output-queue>
 <number>*number*</number>
 <count>*count*</count>
 </bgp-output-queue>
 </bgp-peer>

Description Number of BGP packets that are queued to be transmitted to a particular neighbor for a particular routing table.

Contents <count>—Number of entries.
 <number>—No documentation is available yet.

<bgp-peer>

Usage <bgp-information | bgp-group>

<bgp-peer>

```

<peer-address>peer-address</peer-address>
<peer-as>peer-as</peer-as>
<local-address>local-address</local-address>
<local-as>local-as</local-as>
<description>description</description>
<peer-type>peer-type</peer-type>
<route-reflector-client/>
<peer-state>peer-state</peer-state>
<peer-flags>peer-flags</peer-flags>
<last-state>last-state</last-state>
<last-event>last-event</last-event>
<last-error>last-error</last-error>
<bgp-option-information>...</bgp-option-information>
<flap-count>flap-count</flap-count>
<last-flap-event>last-flap-event</last-flap-event>
<peer-id>peer-id</peer-id>
<local-id>local-id</local-id>
<active-holdtime>active-holdtime</active-holdtime>
<keepalive-interval>keepalive-interval</keepalive-interval>
<peer-index>peer-index</peer-index>
<bgp-bfd>...</bgp-bfd>
<local-interface-name>local-interface-name</local-interface-name>
<local-interface-index>local-interface-index</local-interface-index>
<nlri-type-peer>nlri-type-peer</nlri-type-peer>
<nlri-type-session>nlri-type-session</nlri-type-session>
<peer-no-refresh/>
<peer-refresh-capability>peer-refresh-capability</peer-refresh-capability>
<peer-4byte-as-capability-not-supported/>
<peer-4byte-as-capability-advertised>peer-4byte-as-capability-advertised
  </peer-4byte-as-capability-advertised>
<peer-restart-nlri-configured>peer-restart-nlri-configured
  </peer-restart-nlri-configured>
<peer-restart-time-configured>peer-restart-time-configured
  </peer-restart-time-configured>
<peer-stale-route-time-configured>peer-stale-route-time-configured
  </peer-stale-route-time-configured>
<peer-restart-time-received>peer-restart-time-received
  </peer-restart-time-received>
<peer-restart-flags-received>peer-restart-flags-received
  </peer-restart-flags-received>
<peer-restart-nlri-received>peer-restart-nlri-received
  </peer-restart-nlri-received>
<peer-restart-nlri-can-save-state>peer-restart-nlri-can-save-state
  </peer-restart-nlri-can-save-state>
<peer-restart-nlri-state-saved>peer-restart-nlri-state-saved
  </peer-restart-nlri-state-saved>
<peer-no-restart/>
<peer-restart-nlri-negotiated>peer-restart-nlri-negotiated
  </peer-restart-nlri-negotiated>
<peer-end-of-rib-received>peer-end-of-rib-received</peer-end-of-rib-received>

```

```

<peer-end-of-rib-sent>peer-end-of-rib-sent</peer-end-of-rib-sent>
<peer-end-of-rib-scheduled>peer-end-of-rib-scheduled
    </peer-end-of-rib-scheduled>
<last-received>last-received</last-received>
<last-sent>last-sent</last-sent>
<last-checked>last-checked</last-checked>
<input-messages>input-messages</input-messages>
<input-updates>input-updates</input-updates>
<input-refreshes>input-refreshes</input-refreshes>
<input-octets>input-octets</input-octets>
<output-messages>output-messages</output-messages>
<output-updates>output-updates</output-updates>
<output-refreshes>output-refreshes</output-refreshes>
<output-octets>output-octets</output-octets>
<buffered-octets-rx>buffered-octets-rx</buffered-octets-rx>
<buffered-octets-tx>buffered-octets-tx</buffered-octets-tx>
<bgp-output-queue>...</bgp-output-queue>
<route-queue-count>route-queue-count</route-queue-count>
<bgp-rib>...</bgp-rib>
<elapsed-time>elapsed-time</elapsed-time>
<extended-information>extended-information</extended-information>
<bgp-error>...</bgp-error>
<route-queue>...</route-queue>
<tracing-information>...</tracing-information>
</bgp-peer>
</bgp-information | bgp-group>

```

Description Operational and configuration information for a BGP peer.

Contents

- <active-holdtime>—Hold time the local router negotiated with the peer.
- <bgp-bfd>—No documentation is available yet.
- <bgp-error>—No documentation is available yet.
- <bgp-option-information>—Configured BGP options.
- <bgp-output-queue>—Number of BGP packets that are queued to be transmitted to a particular neighbor for a particular routing table.
- <bgp-rib>—No documentation is available yet.
- <buffered-octets-rx>—Number of octets that have been received and are still buffered.
- <buffered-octets-tx>—Number of octets in the transmit buffer.
- <description>—No documentation is available yet.
- <elapsed-time>—Time this adjacency or session has been up or down.
- <extended-information>—No documentation is available yet.
- <flap-count>—Number of times the BGP session has gone down.

<input-messages>—Total number of messages received from the receive socket buffer.

<input-octets>—Number of octets received from the receive socket buffer.

<input-refreshes>—Number of refresh messages received from the receive socket buffer.

<input-updates>—Number of update messages received from the receive socket buffer.

<keepalive-interval>—No documentation is available yet.

<last-checked>—No documentation is available yet.

<last-error>—Last error that occurred in the BGP session.

<last-event>—Last activity that occurred in the BGP session.

<last-flap-event>—Event that caused the last BGP session flap.

<last-received>—No documentation is available yet.

<last-sent>—No documentation is available yet.

<last-state>—Previous state of the BGP session.

<local-address>—No documentation is available yet.

<local-as>—Local AS number.

<local-id>—Router identifier of the local router.

<local-interface-index>—SNMP ifIndex of local interface.

<local-interface-name>—Logical interface name.

<nlr-type-peer>—Types of NLRIs supported by the peer: unicast or multicast.

<nlr-type-session>—Types of NLRIs being used for this session.

<output-messages>—Total number of messages written to the receive socket buffer.

<output-octets>—Number of octets written to the receive socket buffer.

<output-refreshes>—Number of refresh messages written to the receive socket buffer.

<output-updates>—Number of update messages written to the receive socket buffer.

<peer-4byte-as-capability-advertised>—4 byte Autonomous System capability advertised by this peer.

<peer-4byte-as-capability-not-supported>—This peer does not support 4 byte AS extension.

<peer-address>—Address of the BGP peer, followed by its port number.

<peer-as>—Peer AS number.

<peer-end-of-rib-received>—Types of NLRIs for which peer received an end-of-rib marker.

<peer-end-of-rib-scheduled>—Types of NLRIs for which peer scheduled an end-of-rib marker.

<peer-end-of-rib-sent>—Types of NLRIs for which peer sent an end-of-rib marker.

<peer-flags>—Internal BGP flags.

<peer-id>—Router identifier of the peer.

<peer-index>—Index of this peer in its group.

<peer-no-refresh>—Present if this peer does not support refresh.

<peer-no-restart>—Present if this peer does not support graceful restart.

<peer-refresh-capability>—Version of refresh capability supported by this peer.

<peer-restart-flags-received>—Flags received from this peer in its restart capability.

<peer-restart-nlri-can-save-state>—Types of NLRIs for which peer can save forwarding state.

<peer-restart-nlri-configured>—Types of NLRIs for which restart is locally configured.

<peer-restart-nlri-negotiated>—Types of NLRIs for which restart negotiated with peer.

<peer-restart-nlri-received>—Types of NLRIs for which restart was advertised by peer.

<peer-restart-nlri-state-saved>—Types of NLRIs for which peer saved all forwarding state.

<peer-restart-time-configured>—Restart time configured locally for this peer.

<peer-restart-time-received>—Restart time requested by peer in its restart capability.

<peer-stale-route-time-configured>—Maximum time for which stale routes from peer are kept.

<peer-state>—Current state of the BGP session.

<peer-type>—No documentation is available yet.

<route-queue>—No documentation is available yet.

<route-queue-count>—Total number of routes queued for output to this peer.

<route-reflector-client>—No documentation is available yet.

<tracing-information>—No documentation is available yet.

<bgp-rib>

Usage <bgp-information | bgp-peer | bgp-group>

```

<bgp-rib>
  <name>name</name>
  <rib-bit>rib-bit</rib-bit>
  <bgp-rib-state>bgp-rib-state</bgp-rib-state>
  <vpn-rib-state>vpn-rib-state</vpn-rib-state>
  <send-state>send-state</send-state>
  <total-external-prefix-count>total-external-prefix-count
    </total-external-prefix-count>
  <active-external-prefix-count>active-external-prefix-count
    </active-external-prefix-count>
  <accepted-external-prefix-count>accepted-external-prefix-count
    </accepted-external-prefix-count>
  <suppressed-external-prefix-count>suppressed-external-prefix-count
    </suppressed-external-prefix-count>
  <total-internal-prefix-count>total-internal-prefix-count
    </total-internal-prefix-count>
  <active-internal-prefix-count>active-internal-prefix-count
    </active-internal-prefix-count>
  <accepted-internal-prefix-count>accepted-internal-prefix-count
    </accepted-internal-prefix-count>
  <suppressed-internal-prefix-count>suppressed-internal-prefix-count
    </suppressed-internal-prefix-count>
  <total-prefix-count>total-prefix-count</total-prefix-count>
  <active-prefix-count>active-prefix-count</active-prefix-count>
  <received-prefix-count>received-prefix-count</received-prefix-count>
  <accepted-prefix-count>accepted-prefix-count</accepted-prefix-count>
  <damped-prefix-count>damped-prefix-count</damped-prefix-count>
  <suppressed-prefix-count>suppressed-prefix-count</suppressed-prefix-count>
  <history-prefix-count>history-prefix-count</history-prefix-count>
  <pending-prefix-count>pending-prefix-count</pending-prefix-count>
  <advertised-prefix-count>advertised-prefix-count</advertised-prefix-count>
</bgp-rib>
</bgp-information | bgp-peer | bgp-group>

```

Description No documentation is available yet.

Contents <accepted-external-prefix-count>—Number of accepted prefixes received from external peers.

<accepted-internal-prefix-count>—Number of accepted prefixes received from internal peers.

<accepted-prefix-count>—For a peer RIB, number of prefixes from this peer accepted by policy.

<active-external-prefix-count>—Number of active prefixes received from external peers.

<active-internal-prefix-count>—Number of active prefixes received from internal peers.

<active-prefix-count>—Number of active prefixes.

<advertised-prefix-count>—Number of prefixes present in the RIB-OUT.

<bgp-rib-state>—State of the RIB. Indicates if a BGP graceful restart is in progress.

<damped-prefix-count>—Number of prefixes in any damped state.

<history-prefix-count>—Number of prefixes with damping history maintained.

<name>—No documentation is available yet.

<pending-prefix-count>—Number of prefixes with pending changes.

<received-prefix-count>—For a peer RIB, number of prefixes received from this peer.

<rib-bit>—Number that represents the entry in the routing table for this peer.

<send-state>—State of the BGP group: in sync, not in sync, or not advertising.

<suppressed-external-prefix-count>—Number of external prefixes suppressed due to damping.

<suppressed-internal-prefix-count>—Number of internal prefixes suppressed due to damping.

<suppressed-prefix-count>—Number of prefixes suppressed due to damping.

<total-external-prefix-count>—Total number of prefixes received from external peers.

<total-internal-prefix-count>—Total number of prefixes received from internal peers.

<total-prefix-count>—Total number of prefixes in this RIB.

<vpn-rib-state>—State of the RIB. Indicates if a VPN graceful restart is in progress.

<bgp-rsync-ack-queue>

Usage <bgp-rsync-master>
 <bgp-rsync-ack-queue>
 <bgp-rsync-queue-entry>...</bgp-rsync-queue-entry>
 </bgp-rsync-ack-queue>
 </bgp-rsync-master>

Description No documentation is available yet.

Contents <bgp-rsync-queue-entry>—No documentation is available yet.

<bgp-rsync-error-queue>

Usage <bgp-rsync-master>
 <bgp-rsync-error-queue>
 <bgp-rsync-queue-entry>...</bgp-rsync-queue-entry>
 </bgp-rsync-error-queue>
</bgp-rsync-master>

Description No documentation is available yet.

Contents <bgp-rsync-queue-entry>—No documentation is available yet.

<bgp-rsync-estab-queue>

Usage <bgp-rsync-master>
 <bgp-rsync-estab-queue>
 <bgp-rsync-queue-entry>...</bgp-rsync-queue-entry>
 </bgp-rsync-estab-queue>
</bgp-rsync-master>

Description No documentation is available yet.

Contents <bgp-rsync-queue-entry>—No documentation is available yet.

<bgp-rsync-estab-type>

Usage <bgp-rsync-master>
 <bgp-rsync-estab-type>
 <bgp-rsync-queue-entry>...</bgp-rsync-queue-entry>
 </bgp-rsync-estab-type>
</bgp-rsync-master>

Description No documentation is available yet.

Contents <bgp-rsync-queue-entry>—No documentation is available yet.

<bgp-rsync-master>

Usage <bgp-sync-information>
 <bgp-rsync-master>
 <bgp-rsync-session-state>*bgp-rsync-session-state*</bgp-rsync-session-state>
 <bgp-rsync-session-time>*bgp-rsync-session-time*</bgp-rsync-session-time>
 <bgp-rsync-session-flaps>*bgp-rsync-session-flaps*</bgp-rsync-session-flaps>
 <bgp-rsync-session-last-flap-reason>*bgp-rsync-session-last-flap-reason*
 </bgp-rsync-session-last-flap-reason>
 <bgp-rsync-session-last-flap-error>*bgp-rsync-session-last-flap-error*
 </bgp-rsync-session-last-flap-error>
 <bgp-rsync-state>*bgp-rsync-state*</bgp-rsync-state>
 <bgp-rsync-state-time>*bgp-rsync-state-time*</bgp-rsync-state-time>
 <bgp-rsync-flags>*bgp-rsync-flags*</bgp-rsync-flags>
 <bgp-rsync-rt-state>*bgp-rsync-rt-state*</bgp-rsync-rt-state>
 <bgp-rsync-ackwait>*bgp-rsync-ackwait*</bgp-rsync-ackwait>
 <bgp-rsync-sowait>*bgp-rsync-sowait*</bgp-rsync-sowait>
 <bgp-rsync-sched>*bgp-rsync-sched*</bgp-rsync-sched>
 <bgp-rsync-sendbuf-count>*bgp-rsync-sendbuf-count*</bgp-rsync-sendbuf-count>
 <bgp-rsync-walker/>
 <bgp-rsync-walk>...</bgp-rsync-walk>
 <bgp-rsync-estab-type>...</bgp-rsync-estab-type>
 <bgp-rsync-ack-queue>...</bgp-rsync-ack-queue>
 <bgp-rsync-estab-tm>*bgp-rsync-estab-tm*</bgp-rsync-estab-tm>
 <bgp-rsync-error-queue>...</bgp-rsync-error-queue>
 <bgp-rsync-stats>...</bgp-rsync-stats>
 <bgp-rsync-estab-queue>...</bgp-rsync-estab-queue>
 </bgp-rsync-master>
 </bgp-sync-information>

Description No documentation is available yet.

Contents <bgp-rsync-ack-queue>—No documentation is available yet.
 <bgp-rsync-ackwait>—Number of peers waiting for ESTABLISH-ACK message.
 <bgp-rsync-error-queue>—No documentation is available yet.
 <bgp-rsync-estab-queue>—No documentation is available yet.
 <bgp-rsync-estab-tm>—No documentation is available yet.
 <bgp-rsync-estab-type>—No documentation is available yet.
 <bgp-rsync-flags>—No documentation is available yet.
 <bgp-rsync-rt-state>—No documentation is available yet.
 <bgp-rsync-sched>—Number of peers being synchronized.
 <bgp-rsync-sendbuf-count>—Number of bytes in send buffer.
 <bgp-rsync-session-flaps>—Number of BGP resynchronization session flaps.
 <bgp-rsync-session-last-flap-error>—Socket error for most recent BGP

resynchronization session flap.

<bgp-rsync-session-last-flap-reason>—Reason for most recent BGP resynchronization session flap.

<bgp-rsync-session-state>—State of the BGP resynchronization session.

<bgp-rsync-session-time>—Amount of time that the BGP resynchronization session has been Up or Down.

<bgp-rsync-sowait>—Number of peers waiting for socket record boundaries.

<bgp-rsync-state>—No documentation is available yet.

<bgp-rsync-state-time>—Time since last protocol state change.

<bgp-rsync-stats>—No documentation is available yet.

<bgp-rsync-walk>—No documentation is available yet.

<bgp-rsync-walker>—RT walker job running.

<bgp-rsync-queue-entry>

Usage <bgp-rsync-estab-type | bgp-rsync-ack-queue | bgp-rsync-error-queue | bgp-rsync-estab-queue>
<bgp-rsync-queue-entry>
 <rsy-queue-instance>*rsy-queue-instance*</rsy-queue-instance>
 <rsy-queue-addr>*rsy-queue-addr*</rsy-queue-addr>
 <rsy-queue-more/>
</bgp-rsync-queue-entry>
 </bgp-rsync-estab-type | bgp-rsync-ack-queue | bgp-rsync-error-queue | bgp-rsync-estab-queue>

Description No documentation is available yet.

Contents <rsy-queue-addr>—No documentation is available yet.

<rsy-queue-instance>—No documentation is available yet.

<rsy-queue-more>—No documentation is available yet.

<bgp-rsync-stats>

```
Usage      <bgp-rsync-master>
  <bgp-rsync-stats>
    <open-send-count>open-send-count</open-send-count>
    <estab-send-count>estab-send-count</estab-send-count>
    <update-send-count>update-send-count</update-send-count>
    <error-send-count>error-send-count</error-send-count>
    <complete-send-count>complete-send-count</complete-send-count>
    <open-receive-count>open-receive-count</open-receive-count>
    <request-wild-receive-count>request-wild-receive-count
                                </request-wild-receive-count>
    <request-tgt-receive-count>request-tgt-receive-count
                                </request-tgt-receive-count>
    <estab-ack-receive-count>estab-ack-receive-count</estab-ack-receive-count>
    <complete-ack-receive-count>complete-ack-receive-count
                                </complete-ack-receive-count>
  </bgp-rsync-stats>
</bgp-rsync-master>
```

Description No documentation is available yet.

Contents

- <complete-ack-receive-count>—Number of COMPLETE-ACK messages received.
- <complete-send-count>—Number of COMPLETE messages sent.
- <error-send-count>—Number of ERROR messages sent.
- <estab-ack-receive-count>—Number of ESTABLISH-ACK messages received.
- <estab-send-count>—Number of ESTABLISH messages sent.
- <open-receive-count>—Number of OPEN messages received.
- <open-send-count>—Number of OPEN messages sent.
- <request-tgt-receive-count>—Number of targeted REQUEST messages received.
- <request-wild-receive-count>—Number of wildcard REQUEST messages received.
- <update-send-count>—Number of UPDATE messages sent.

<bgp-rsync-walk>

Usage <bgp-rsync-master>
 <bgp-rsync-walk>
 <bgp-rsync-walk-table>*bgp-rsync-walk-table*</bgp-rsync-walk-table>
 <bgp-rsync-walk-prefix>*bgp-rsync-walk-prefix*</bgp-rsync-walk-prefix>
 <bgp-rsync-walk-prefixlen>*bgp-rsync-walk-prefixlen*</bgp-rsync-walk-prefixlen>
 <queue-count>*queue-count*</queue-count>
 </bgp-rsync-walk>
 </bgp-rsync-master>

Description No documentation is available yet.

Contents <bgp-rsync-walk-prefix>—Current Prefix.
 <bgp-rsync-walk-prefixlen>—Current Prefix length.
 <bgp-rsync-walk-table>—Current table name.
 <queue-count>—Number of entries enqueued.

<bgp-rtf-brief>

Usage <bgp-rtf-information>
 <bgp-rtf-brief>
 <group-name>*group-name*</group-name>
 <table-name>*table-name*</table-name>
 <bgp-rtf-state-flags>*bgp-rtf-state-flags*</bgp-rtf-state-flags>
 <bgp-rtf-entries>*bgp-rtf-entries*</bgp-rtf-entries>
 </bgp-rtf-brief>
 </bgp-rtf-information>

Description No documentation is available yet.

Contents <bgp-rtf-entries>—No documentation is available yet.
 <bgp-rtf-state-flags>—No documentation is available yet.
 <group-name>—No documentation is available yet.
 <table-name>—Unicast routing table.

<bgp-rtf-entry>

- Usage** <bgp-rtf-state>
 <bgp-rtf-entry>
 <rtarget>*rtarget*</rtarget>
 <rtarget-mask>*rtarget-mask*</rtarget-mask>
 </bgp-rtf-entry>
 </bgp-rtf-state>
- Description** No documentation is available yet.
- Contents** <rtarget>—Route target community.
 <rtarget-mask>—No documentation is available yet.

<bgp-rtf-group>

- Usage** <bgp-rtf-information>
 <bgp-rtf-group>
 <group-name>*group-name*</group-name>
 <rtarget-recv-mask>*rtarget-recv-mask*</rtarget-recv-mask>
 <default-mask>*default-mask*</default-mask>
 <bgp-rtf-state>...</bgp-rtf-state>
 </bgp-rtf-group>
 </bgp-rtf-information>
- Description** No documentation is available yet.
- Contents** <bgp-rtf-state>—No documentation is available yet.
 <default-mask>—No documentation is available yet.
 <group-name>—No documentation is available yet.
 <rtarget-recv-mask>—No documentation is available yet.

<bgp-rtf-information>

- Usage** <rpc-reply>
 <bgp-rtf-information>
 <bgp-rtf-brief>...</bgp-rtf-brief>
 <bgp-rtf-group>...</bgp-rtf-group>
 </bgp-rtf-information>
 </rpc-reply>
- Description** BGP route target filtering information.
- Contents** <bgp-rtf-brief>—No documentation is available yet.
 <bgp-rtf-group>—No documentation is available yet.

<bgp-rtf-state>

Usage <bgp-rtf-group>
 <bgp-rtf-state>
 <table-name>*table-name*</table-name>
 <bgp-rtf-state-flags>*bgp-rtf-state-flags*</bgp-rtf-state-flags>
 <bgp-rtf-entries>*bgp-rtf-entries*</bgp-rtf-entries>
 <bgp-rtf-entry>...</bgp-rtf-entry>
 </bgp-rtf-state>
 </bgp-rtf-group>

Description No documentation is available yet.

Contents <bgp-rtf-entries>—No documentation is available yet.
 <bgp-rtf-entry>—No documentation is available yet.
 <bgp-rtf-state-flags>—No documentation is available yet.
 <table-name>—Unicast routing table.

<bgp-standby>

Usage <bgp-sync-information>
 <bgp-standby>
 <bgp-standby-state>*bgp-standby-state*</bgp-standby-state>
 <bgp-standby-last-trans>*bgp-standby-last-trans*</bgp-standby-last-trans>
 <bgp-standby-sendbuf>*bgp-standby-sendbuf*</bgp-standby-sendbuf>
 <bgp-unsync-timer>*bgp-unsync-timer*</bgp-unsync-timer>
 <bgp-unsync-pending-tm>*bgp-unsync-pending-tm*</bgp-unsync-pending-tm>
 <bgp-unsync-queue>...</bgp-unsync-queue>
 <bgp-unsync-pending>...</bgp-unsync-pending>
 <bgp-standby-sync-queue>...</bgp-standby-sync-queue>
 </bgp-standby>
 </bgp-sync-information>

Description No documentation is available yet.

Contents <bgp-standby-last-trans>—No documentation is available yet.
 <bgp-standby-sendbuf>—No documentation is available yet.
 <bgp-standby-state>—No documentation is available yet.
 <bgp-standby-sync-queue>—No documentation is available yet.
 <bgp-unsync-pending>—No documentation is available yet.
 <bgp-unsync-pending-tm>—No documentation is available yet.
 <bgp-unsync-queue>—No documentation is available yet.
 <bgp-unsync-timer>—No documentation is available yet.

<bgp-standby-sync-entry>

- Usage** <bgp-standby-sync-queue>
 <bgp-standby-sync-entry>
 <bstandby-iid>*bstandby-iid*</bstandby-iid>
 <bstandby-addr>*bstandby-addr*</bstandby-addr>
 </bgp-standby-sync-entry>
 </bgp-standby-sync-queue>
- Description** No documentation is available yet.
- Contents** <bstandby-addr>—No documentation is available yet.
 <bstandby-iid>—Instance identifier.

<bgp-standby-sync-queue>

- Usage** <bgp-standby>
 <bgp-standby-sync-queue>
 <bgp-standby-sync-entry>...</bgp-standby-sync-entry>
 </bgp-standby-sync-queue>
 </bgp-standby>
- Description** No documentation is available yet.
- Contents** <bgp-standby-sync-entry>—No documentation is available yet.

<bgp-sync-information>

- Usage** <rpc-reply>
 <bgp-sync-information>
 <bgp-rsync-master>...</bgp-rsync-master>
 <bgp-standby>...</bgp-standby>
 </bgp-sync-information>
 </rpc-reply>
- Description** BGP synchronization information.
- Contents** <bgp-rsync-master>—No documentation is available yet.
 <bgp-standby>—No documentation is available yet.

<bgp-traffic-statistics>

Usage <bgp-traffic-statistics-information>
 <bgp-traffic-statistics>
 <bgp-prefix>*bgp-prefix*</bgp-prefix>
 <bgp-traffic-type>*bgp-traffic-type*</bgp-traffic-type>
 <bgp-traffic-error>*bgp-traffic-error*</bgp-traffic-error>
 <bgp-traffic-statistics-packet-count>*bgp-traffic-statistics-packet-count*
 </bgp-traffic-statistics-packet-count>
 <bgp-traffic-statistics-byte-count>*bgp-traffic-statistics-byte-count*
 </bgp-traffic-statistics-byte-count>
 <bgp-traffic-statistics-egress-as>*bgp-traffic-statistics-egress-as*
 </bgp-traffic-statistics-egress-as>
 <bgp-traffic-statistics-advertised-fec-label>*bgp-traffic-statistics-advertised-fec-label*
 </bgp-traffic-statistics-advertised-fec-label>
 </bgp-traffic-statistics>
 </bgp-traffic-statistics-information>

Description No documentation is available yet.

Contents <bgp-prefix>—No documentation is available yet.

<bgp-traffic-error>—Error encountered when querying the statistics.

<bgp-traffic-statistics-advertised-fec-label>—Label advertised for routes in FEC.

<bgp-traffic-statistics-byte-count>—Number of bytes switched for this FEC.

<bgp-traffic-statistics-egress-as>—Egress AS for traffic destined for this prefix.

<bgp-traffic-statistics-packet-count>—Number of packets switched for this FEC.

<bgp-traffic-type>—Type of traffic: ingress or transit.

<bgp-traffic-statistics-error>

Usage <bgp-traffic-statistics-information>
 <bgp-traffic-statistics-error>
 <bgp-traffic-error>*bgp-traffic-error*</bgp-traffic-error>
 </bgp-traffic-statistics-error>
 </bgp-traffic-statistics-information>

Description No documentation is available yet.

Contents <bgp-traffic-error>—Error encountered when querying the statistics.

<bgp-traffic-statistics-header>

- Usage** <bgp-traffic-statistics-information>
 <bgp-traffic-statistics-header>
 <group-name>*group-name*</group-name>
 <group-index>*group-index*</group-index>
 <nlri-name>*nlri-name*</nlri-name>
 </bgp-traffic-statistics-header>
 </bgp-traffic-statistics-information>
- Description** No documentation is available yet.
- Contents** <group-index>—No documentation is available yet.
 <group-name>—No documentation is available yet.
 <nlri-name>—No documentation is available yet.

<bgp-traffic-statistics-information>

- Usage** <rpc-reply>
 <bgp-traffic-statistics-information>
 <bgp-traffic-statistics-header>...</bgp-traffic-statistics-header>
 <bgp-traffic-statistics>...</bgp-traffic-statistics>
 <bgp-traffic-statistics-error>...</bgp-traffic-statistics-error>
 </bgp-traffic-statistics-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <bgp-traffic-statistics>—No documentation is available yet.
 <bgp-traffic-statistics-error>—No documentation is available yet.
 <bgp-traffic-statistics-header>—No documentation is available yet.

<bgp-unsync-entry>

Usage <bgp-unsync-queue | bgp-unsync-pending>
<bgp-unsync-entry>
 <usy-iid>usy-iid</usy-iid>
 <usy-addr>usy-addr</usy-addr>
 <usy-elapsed>usy-elapsed</usy-elapsed>
 <usy-flags>usy-flags</usy-flags>
 <usy-more/>
</bgp-unsync-entry>
 </bgp-unsync-queue | bgp-unsync-pending>

Description No documentation is available yet.

Contents <usy-addr>—No documentation is available yet.
 <usy-elapsed>—No documentation is available yet.
 <usy-flags>—No documentation is available yet.
 <usy-iid>—Instance identifier.
 <usy-more>—No documentation is available yet.

<bgp-unsync-pending>

Usage <bgp-standby>
<bgp-unsync-pending>
 <bgp-unsync-entry>...</bgp-unsync-entry>
</bgp-unsync-pending>
 </bgp-standby>

Description No documentation is available yet.

Contents <bgp-unsync-entry>—No documentation is available yet.

<bgp-unsync-queue>

Usage <bgp-standby>
<bgp-unsync-queue>
 <bgp-unsync-entry>...</bgp-unsync-entry>
</bgp-unsync-queue>
 </bgp-standby>

Description No documentation is available yet.

Contents <bgp-unsync-entry>—No documentation is available yet.

<bootstrap-family>

Usage <pim-bootstrap-information>
 <bootstrap-family>
 <address-family>*address-family*</address-family>
 <address>*address*</address>
 <bootstrap-priority>*bootstrap-priority*</bootstrap-priority>
 <local-address>*local-address*</local-address>
 <local-priority>*local-priority*</local-priority>
 <bootstrap-state>*bootstrap-state*</bootstrap-state>
 <bootstrap-timeout>*bootstrap-timeout*</bootstrap-timeout>
 </bootstrap-family>
 </pim-bootstrap-information>

Description No documentation is available yet.

Contents <address>—No documentation is available yet.

<address-family>—No documentation is available yet.

<bootstrap-priority>—Priority of bootstrap router.

<bootstrap-state>—No documentation is available yet.

<bootstrap-timeout>—Bootstrap router timeout.

<local-address>—No documentation is available yet.

<local-priority>—Local priority.

<bypass-info>

Usage <rsvp-interface>
 <bypass-info>
 <lp-status>*lp-status*</lp-status>
 <lp-requested>*lp-requested*</lp-requested>
 <lp-granted>*lp-granted*</lp-granted>
 <lp-failure>*lp-failure*</lp-failure>
 <total-bypass>*total-bypass*</total-bypass>
 <bypass-name>*bypass-name*</bypass-name>
 <bypass-state>*bypass-state*</bypass-state>
 <bypass-type>*bypass-type*</bypass-type>
 <rsvp-lp-psb-cnt>*rsvp-lp-psb-cnt*</rsvp-lp-psb-cnt>
 <rsvp-lp-backup-lsp-cnt>*rsvp-lp-backup-lsp-cnt*</rsvp-lp-backup-lsp-cnt>
 <lp-history>...</lp-history>
 </bypass-info>
 </rsvp-interface>

Description No documentation is available yet.

Contents <bypass-name>—Name of the bypass.

<bypass-state>—Bypass up/down status.

<bypass-type>—Whether bypass type is link-protect or node-protect.

<lp-failure>—Number of LSPs not granted protection.

<lp-granted>—Number of LSPs granted protection.

<lp-history>—Log of LSP path-related events.

<lp-requested>—Number of LSPs requesting protection.

<lp-status>—Link-protection status.

<rsvp-lp-backup-lsp-cnt>—Number of backup RSVP LSPs tunneled through this bypass.

<rsvp-lp-psb-cnt>—Number of sessions tunneled through this bypass.

<total-bypass>—Number of bypass activated.

<c-multicast-ipv4>

Usage <instance | instance-entry>
 <c-multicast-ipv4>
 <c-multicast-ipv4-entry>...</c-multicast-ipv4-entry>
 </c-multicast-ipv4>
 </instance | instance-entry>

Description No documentation is available yet.

Contents <c-multicast-ipv4-entry>—No documentation is available yet.

<c-multicast-ipv4-entry>

Usage <c-multicast-ipv4>
 <c-multicast-ipv4-entry>
 <c-multicast-address>*c-multicast-address*</c-multicast-address>
 <provider-tunnel-id>*provider-tunnel-id*</provider-tunnel-id>
 <c-multicast-property>*c-multicast-property*</c-multicast-property>
 </c-multicast-ipv4-entry>
 </c-multicast-ipv4>

Description No documentation is available yet.

Contents <c-multicast-address>—Address of the c-multicast route.
 <c-multicast-property>—Special properties of the c-multicast route.
 <provider-tunnel-id>—Provider tunnel identifier.

<c-multicast-summary>

Usage <instance-entry-summary>
 <c-multicast-summary>
 <c-multicast-ipv4-count>*c-multicast-ipv4-count*</c-multicast-ipv4-count>
 </c-multicast-summary>
 </instance-entry-summary>

Description No documentation is available yet.

Contents <c-multicast-ipv4-count>—Number of c-multicast IPv4 routes in the instance.

<ccc-connection>

Usage <ccc-information>
 <ccc-connection>
 <ccc-connection-name>ccc-connection-name</ccc-connection-name>
 <ccc-connection-type>ccc-connection-type</ccc-connection-type>
 <ccc-connection-status>ccc-connection-status</ccc-connection-status>
 <ccc-connection-last-uptime>ccc-connection-last-uptime
 </ccc-connection-last-uptime>
 <ccc-connection-up-transitions>ccc-connection-up-transitions
 </ccc-connection-up-transitions>
 <ccc-connection-circuit>...</ccc-connection-circuit>
 <ccc-connection-in-labels>...</ccc-connection-in-labels>
 <ccc-connection-out-labels>...</ccc-connection-out-labels>
 <ccc-connection-history>...</ccc-connection-history>
 </ccc-connection>
 </ccc-information>

Description No documentation is available yet.

Contents <ccc-connection-circuit>—No documentation is available yet.

<ccc-connection-history>—No documentation is available yet.

<ccc-connection-in-labels>—Incoming labels for this CCC connection.

<ccc-connection-last-uptime>—Time the connection was last up.

<ccc-connection-name>—Connection name.

<ccc-connection-out-labels>—Outgoing labels for this CCC connection.

<ccc-connection-status>—Status of the CCC connection.

<ccc-connection-type>—Type of CCC connection.

<ccc-connection-up-transitions>—Number of transitions to up state.

<ccc-connection-circuit>

Usage <ccc-connection>
 <ccc-connection-circuit>
 <ccc-circuit-name>ccc-circuit-name</ccc-circuit-name>
 <ccc-circuit-type>ccc-circuit-type</ccc-circuit-type>
 <ccc-circuit-status>ccc-circuit-status</ccc-circuit-status>
 </ccc-connection-circuit>
 </ccc-connection>

Description No documentation is available yet.

Contents <ccc-circuit-name>—No documentation is available yet.

<ccc-circuit-status>—No documentation is available yet.

<ccc-circuit-type>—No documentation is available yet.

<ccc-connection-history>

- Usage** <ccc-connection>
 <ccc-connection-history>
 <ccc-connection-history-log>...</ccc-connection-history-log>
 </ccc-connection-history>
 </ccc-connection>
- Description** No documentation is available yet.
- Contents** <ccc-connection-history-log>—No documentation is available yet.

<ccc-connection-history-log>

- Usage** <ccc-connection-history>
 <ccc-connection-history-log>
 <event-time>event-time</event-time>
 <event-name>event-name</event-name>
 <interface-label-info>interface-label-info</interface-label-info>
 <receive-lsp-count>receive-lsp-count</receive-lsp-count>
 <transmit-lsp-count>transmit-lsp-count</transmit-lsp-count>
 </ccc-connection-history-log>
 </ccc-connection-history>
- Description** No documentation is available yet.
- Contents** <event-name>—No documentation is available yet.
- <event-time>—No documentation is available yet.
- <interface-label-info>—No documentation is available yet.
- <receive-lsp-count>—No documentation is available yet.
- <transmit-lsp-count>—No documentation is available yet.

<ccc-connection-in-labels>

- Usage** <ccc-connection>
 <ccc-connection-in-labels>
 <mpls-label>mpls-label</mpls-label>
 <no-label/>
 </ccc-connection-in-labels>
 </ccc-connection>
- Description** Incoming labels for this CCC connection.
- Contents** <mpls-label>—Label of MPLS packet.
- <no-label>—No documentation is available yet.

<ccc-connection-out-labels>

- Usage** <ccc-connection>
 <ccc-connection-out-labels>
 <mpls-label>*mpls-label*</mpls-label>
 <no-label/>
 </ccc-connection-out-labels>
 </ccc-connection>
- Description** Outgoing labels for this CCC connection.
- Contents** <mpls-label>—Label of MPLS packet.
 <no-label>—No documentation is available yet.

<ccc-information>

- Usage** <rpc-reply>
 <ccc-information>
 <ccc-no-connections/>
 <ccc-link-monitoring-status>*ccc-link-monitoring-status*
 </ccc-link-monitoring-status>
 <ccc-restarting/>
 <ccc-connection>...</ccc-connection>
 </ccc-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <ccc-connection>—No documentation is available yet.
 <ccc-link-monitoring-status>—CCC link monitoring status.
 <ccc-no-connections>—No documentation is available yet.
 <ccc-restarting>—No documentation is available yet.

<communities>

- Usage** <rt-entry | attrset | rt>
 <communities>
 <community>*community*</community>
 <extended-community>*extended-community*</extended-community>
 </communities>
 </rt-entry | attrset | rt>
- Description** No documentation is available yet.
- Contents** <community>—Basic community.
 <extended-community>—Extended community.

<connection>

Usage <reference-site | mesh-group-connection | ldp-vpls-reference-site | l2circuit-neighbor>

```

<connection>
  <connection-id>connection-id</connection-id>
  <connection-type>connection-type</connection-type>
  <connection-status>connection-status</connection-status>
  <last-change>last-change</last-change>
  <up-transitions>up-transitions</up-transitions>
  <local-interface>...</local-interface>
  <remote-interface>...</remote-interface>
  <remote-pe>remote-pe</remote-pe>
  <control-word>control-word</control-word>
  <control-word-type>control-word-type</control-word-type>
  <interface-encapsulation>interface-encapsulation</interface-encapsulation>
  <inbound-label>inbound-label</inbound-label>
  <outbound-label>outbound-label</outbound-label>
  <connection-bandwidth>...</connection-bandwidth>
  <vpls-rsvp-te-p2mp-lsp-information>...</vpls-rsvp-te-p2mp-lsp-information>
  <history>...</history>
  <l2vpn-local-site-id>l2vpn-local-site-id</l2vpn-local-site-id>
  <l2vpn-remote-site-id>l2vpn-remote-site-id</l2vpn-remote-site-id>
  <mesh-group-name>mesh-group-name</mesh-group-name>
</connection>
</reference-site | mesh-group-connection | ldp-vpls-reference-site | l2circuit-neighbor>

```

Description No documentation is available yet.

Contents <connection-bandwidth>—Bandwidth of a layer 2 connection.

<connection-id>—No documentation is available yet.

<connection-status>—No documentation is available yet.

<connection-type>—No documentation is available yet.

<control-word>—No documentation is available yet.

<control-word-type>—No documentation is available yet.

<history>—No documentation is available yet.

<inbound-label>—No documentation is available yet.

<interface-encapsulation>—No documentation is available yet.

<l2vpn-local-site-id>—Local site identifier.

<l2vpn-remote-site-id>—Remote site identifier.

<last-change>—No documentation is available yet.

<local-interface>—No documentation is available yet.

<mesh-group-name>—Name of mesh-group.

<outbound-label>—No documentation is available yet.

<remote-interface>—No documentation is available yet.

<remote-pe>—No documentation is available yet.

<up-transitions>—No documentation is available yet.

<vpls-rsvp-te-p2mp-lsp-information>—Information about one or more VPLS RSVP-TE point-to-multipoint LSPs.

<connection-bandwidth>

Usage <rt-entry | layer2-connection | connection>
 <connection-bandwidth>
 <bandwidth>*bandwidth*</bandwidth>
 <class-type>*class-type*</class-type>
 <class-bandwidth>*class-bandwidth*</class-bandwidth>
 </connection-bandwidth>
 </rt-entry | layer2-connection | connection>

Description Bandwidth of a layer 2 connection.

Contents <bandwidth>—No documentation is available yet.
 <class-bandwidth>—No documentation is available yet.
 <class-type>—No documentation is available yet.

<connections-summary>

Usage <mesh-group-connection | reference-site | ldp-vpls-reference-site | l2circuit-neighbor>
 <connections-summary>
 <vc-up-count>*vc-up-count*</vc-up-count>
 <vc-down-count>*vc-down-count*</vc-down-count>
 </connections-summary>
 </mesh-group-connection | reference-site | ldp-vpls-reference-site | l2circuit-neighbor>

Description No documentation is available yet.

Contents <vc-down-count>—No documentation is available yet.
 <vc-up-count>—No documentation is available yet.

<cos-info>

Usage	<pre> <rsvp-interface> <cos-info> <queue-number>queue-number</queue-number> <tx-rate>tx-rate</tx-rate> <tx-rate-percent>tx-rate-percent</tx-rate-percent> <high-priority>high-priority</high-priority> <bw-exact>bw-exact</bw-exact> </cos-info> </rsvp-interface> </pre>
Description	No documentation is available yet.
Contents	<p><bw-exact>—Exact bandwidth allocation.</p> <p><high-priority>—High/Low WRR priority.</p> <p><queue-number>—HW queue number.</p> <p><tx-rate>—No documentation is available yet.</p> <p><tx-rate-percent>—No documentation is available yet.</p>

<cspf-paths>

Usage	<pre> <mpls-cspf> <cspf-paths> <total-paths>total-paths</total-paths> <successful>successful</successful> <no-route>no-route</no-route> <sys-error>sys-error</sys-error> <cspfs>cspfs</cspfs> </cspf-paths> </mpls-cspf> </pre>
Description	CSPF path computations statistics.
Contents	<p><cspfs>—No documentation is available yet.</p> <p><no-route>—No documentation is available yet.</p> <p><successful>—No documentation is available yet.</p> <p><sys-error>—No documentation is available yet.</p> <p><total-paths>—No documentation is available yet.</p>

<cspf-queue>

Usage	<pre> <mpls-cspf> <cspf-queue> <current>current</current> <maximum>maximum</maximum> <dequeued>dequeued</dequeued> </cspf-queue> </mpls-cspf> </pre>
Description	CSPF queue statistics.
Contents	<p><current>—No documentation is available yet.</p> <p><dequeued>—No documentation is available yet.</p> <p><maximum>—No documentation is available yet.</p>

<cspf-timing>

Usage	<pre> <mpls-cspf> <cspf-timing> <total-time>total-time</total-time> <cspf-time>cspf-time</cspf-time> <average-time>average-time</average-time> <rpd-time>rpd-time</rpd-time> </cspf-timing> </mpls-cspf> </pre>
Description	CSPF timing statistics.
Contents	<p><average-time>—No documentation is available yet.</p> <p><cspf-time>—No documentation is available yet.</p> <p><rpd-time>—No documentation is available yet.</p> <p><total-time>—No documentation is available yet.</p>

<dense-event>

- Usage** <join-group>
 <dense-event>
 <dense-receive-prune>...</dense-receive-prune>
 <dense-send-prune>...</dense-send-prune>
 <dense-join>...</dense-join>
 <dense-graft>...</dense-graft>
 </dense-event>
 </join-group>
- Description** No documentation is available yet.
- Contents** <dense-graft>—No documentation is available yet.
 <dense-join>—No documentation is available yet.
 <dense-receive-prune>—No documentation is available yet.
 <dense-send-prune>—No documentation is available yet.

<dense-graft>

- Usage** <dense-event>
 <dense-graft>
 <pim-interface-name>*pim-interface-name*</pim-interface-name>
 <dense-timeout>*dense-timeout*</dense-timeout>
 </dense-graft>
 </dense-event>
- Description** No documentation is available yet.
- Contents** <dense-timeout>—No documentation is available yet.
 <pim-interface-name>—Name of PIM interface.

<dense-join>

- Usage** <dense-event>
 <dense-join>
 <pim-interface-name>*pim-interface-name*</pim-interface-name>
 <dense-timeout>*dense-timeout*</dense-timeout>
 </dense-join>
 </dense-event>
- Description** No documentation is available yet.
- Contents** <dense-timeout>—No documentation is available yet.
 <pim-interface-name>—Name of PIM interface.

<dense-receive-prune>

Usage <dense-event>
 <dense-receive-prune>
 <pim-interface-name>*pim-interface-name*</pim-interface-name>
 <dense-timeout>*dense-timeout*</dense-timeout>
 </dense-receive-prune>
 </dense-event>

Description No documentation is available yet.

Contents <dense-timeout>—No documentation is available yet.
 <pim-interface-name>—Name of PIM interface.

<dense-send-prune>

Usage <dense-event>
 <dense-send-prune>
 <pim-interface-name>*pim-interface-name*</pim-interface-name>
 <dense-timeout>*dense-timeout*</dense-timeout>
 </dense-send-prune>
 </dense-event>

Description No documentation is available yet.

Contents <dense-timeout>—No documentation is available yet.
 <pim-interface-name>—Name of PIM interface.

<destination-network>

Usage <dynamic-tunnel-table>
 <destination-network>
 <prefix>*prefix*</prefix>
 <destination-network-deleted/>
 <dynamic-tunnel>...</dynamic-tunnel>
 </destination-network>
 </dynamic-tunnel-table>

Description No documentation is available yet.

Contents <destination-network-deleted>—Whether this destination network has been unconfigured.
 <dynamic-tunnel>—No documentation is available yet.
 <prefix>—No documentation is available yet.

<detour>

Usage <rsvp-session>
 <detour>
 <lsp-state>lsp-state</lsp-state>
 <sender-tspec>sender-tspec</sender-tspec>
 <adspec>adspec</adspec>
 <path-mtu>path-mtu</path-mtu>
 <path-mtu-in-kernel>path-mtu-in-kernel</path-mtu-in-kernel>
 <packet-information>...</packet-information>
 <explicit-route>...</explicit-route>
 <record-route>...</record-route>
 <label-out>label-out</label-out>
 <lsp-diffserv-info>lsp-diffserv-info</lsp-diffserv-info>
 <ct-bw>ct-bw</ct-bw>
 </detour>
 </rsvp-session>

Description Detour that originated at this LSR.

Contents <adspec>—Adspec data element in an RSVP Path message.

<ct-bw>—Per-class bandwidth requested for E-LSPs and L-LSPs.

<explicit-route>—Explicit Route Object (ERO).

<label-out>—Outgoing label.

<lsp-diffserv-info>—LSP DiffServ info.

<lsp-state>—State of an LSP.

<packet-information>—RSVP packets sent or received per session.

<path-mtu>—The value of the path MTU, as negotiated by the network.

<path-mtu-in-kernel>—The value of the MTU used locally for forwarding.

<record-route>—Record Route Object (RRO).

<sender-tspec>—Sender TSpec.

<detour-bandwidth>

Usage <rsvp-telink>
 <detour-bandwidth>
 <bandwidth-priority>*bandwidth-priority*</bandwidth-priority>
 <total-reserved-bandwidth>*total-reserved-bandwidth*
 </total-reserved-bandwidth>
 <interface-address>*interface-address*</interface-address>
 </detour-bandwidth>
 </rsvp-telink>

Description Bandwidth reserved on detour at different priority levels.

Contents <bandwidth-priority>—No documentation is available yet.

 <interface-address>—No documentation is available yet.

 <total-reserved-bandwidth>—Total amount of bandwidth currently reserved.

<detour-branch>

Usage <rsvp-session>
 <detour-branch>
 <source-address>*source-address*</source-address>
 <skip-address>*skip-address*</skip-address>
 <lsp-state>*lsp-state*</lsp-state>
 <sender-tspec>*sender-tspec*</sender-tspec>
 <adspec>*adspec*</adspec>
 <path-mtu>*path-mtu*</path-mtu>
 <explicit-route>...</explicit-route>
 <record-route>...</record-route>
 <packet-information>...</packet-information>
 <detour-branch-labels>...</detour-branch-labels>
 </detour-branch>
 </rsvp-session>

Description Detour that originated at some other LSR.

Contents <adspec>—Adspec data element in an RSVP Path message.

<detour-branch-labels>—No documentation is available yet.

<explicit-route>—Explicit Route Object (ERO).

<lsp-state>—State of an LSP.

<packet-information>—RSVP packets sent or received per session.

<path-mtu>—The value of the path MTU, as negotiated by the network.

<record-route>—Record Route Object (RRO).

<sender-tspec>—Sender TSpec.

<skip-address>—Address of node or link to be skipped.

<source-address>—No documentation is available yet.

<detour-branch-labels>

Usage <detour-branch>
 <detour-branch-labels>
 <label-in>*label-in*</label-in>
 <label-out>*label-out*</label-out>
 </detour-branch-labels>
 </detour-branch>

Description No documentation is available yet.

Contents <label-in>—Incoming label.

<label-out>—Outgoing label.

<downstream-assert-neighbor>

Usage <sparse-downstream-interface>
 <downstream-assert-neighbor>
 <neighbor-address>*neighbor-address*</neighbor-address>
 <neighbor-assert-metric>*neighbor-assert-metric*
 </neighbor-assert-metric>
 <neighbor-assert-preference>*neighbor-assert-preference*
 </neighbor-assert-preference>
 <neighbor-assert-timeout>*neighbor-assert-timeout*
 </neighbor-assert-timeout>
 </downstream-assert-neighbor>
 </sparse-downstream-interface>

Description Information about the neighbor that won the assert.

Contents <neighbor-address>—IP address of this neighbor.

<neighbor-assert-metric>—Metric of the assert winner for reaching a source or RP.

<neighbor-assert-preference>—Preference of the assert winner for reaching a source or RP.

<neighbor-assert-timeout>—Time remaining before assert winner timer expires.

<downstream-interface>

Usage <join-group>
 <downstream-interface>
 <pim-interface-name>*pim-interface-name*</pim-interface-name>
 <pruned-timeout>*pruned-timeout*</pruned-timeout>
 <pim-interface-state>*pim-interface-state*</pim-interface-state>
 </downstream-interface>
 </join-group>

Description No documentation is available yet.

Contents <pim-interface-name>—Name of PIM interface.

<pim-interface-state>—State of PIM interface.

<pruned-timeout>—No documentation is available yet.

<downstream-neighbor>

Usage <sparse-downstream-interface>
 <downstream-neighbor>
 <neighbor-address>*neighbor-address*</neighbor-address>
 <neighbor-state>*neighbor-state*</neighbor-state>
 <terse-sparse/>
 <terse-rpt/>
 <terse-wc/>
 <neighbor-timeout>*neighbor-timeout*</neighbor-timeout>
 </downstream-neighbor>
 </sparse-downstream-interface>

Description No documentation is available yet.

Contents <neighbor-address>—IP address of this neighbor.
 <neighbor-state>—No documentation is available yet.
 <neighbor-timeout>—No documentation is available yet.
 <terse-rpt>—No documentation is available yet.
 <terse-sparse>—No documentation is available yet.
 <terse-wc>—No documentation is available yet.

<dvmrp-capability-flags>

Usage <dvmrp-neighbor>
 <dvmrp-capability-flags>
 <dvmrp-neighbor-one-way/>
 <dvmrp-neighbor-prune/>
 <dvmrp-neighbor-generation-id/>
 <dvmrp-neighbor-mtrace/>
 <dvmrp-neighbor-leave/>
 <dvmrp-neighbor-snmp/>
 <dvmrp-neighbor-netmask/>
 </dvmrp-capability-flags>
 </dvmrp-neighbor>

Description No documentation is available yet.

Contents <dvmrp-neighbor-generation-id>—No documentation is available yet.

<dvmrp-neighbor-leave>—No documentation is available yet.

<dvmrp-neighbor-mtrace>—No documentation is available yet.

<dvmrp-neighbor-netmask>—No documentation is available yet.

<dvmrp-neighbor-one-way>—No documentation is available yet.

<dvmrp-neighbor-prune>—No documentation is available yet.

<dvmrp-neighbor-snmp>—No documentation is available yet.

<dvmrp-graft>

Usage <dvmrp-instance>
 <dvmrp-graft>
 <multicast-group-address>*multicast-group-address*</multicast-group-address>
 <multicast-source-address>*multicast-source-address*</multicast-source-address>
 <dvmrp-graft-expire-time>*dvmrp-graft-expire-time*</dvmrp-graft-expire-time>
 <dvmrp-neighbor-address>*dvmrp-neighbor-address*</dvmrp-neighbor-address>
 </dvmrp-graft>
 </dvmrp-instance>

Description No documentation is available yet.

Contents <dvmrp-graft-expire-time>—No documentation is available yet.

<dvmrp-neighbor-address>—No documentation is available yet.

<multicast-group-address>—Group address.

<multicast-source-address>—Source address.

<dvmrp-graft-queue-information>

- Usage** <rpc-reply>
 <dvmrp-graft-queue-information>
 <dvmrp-instance>...</dvmrp-instance>
 </dvmrp-graft-queue-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <dvmrp-instance>—No documentation is available yet.

<dvmrp-group>

- Usage** <dvmrp-prefix-entry>
 <dvmrp-group>
 <multicast-group-address>*multicast-group-address*</multicast-group-address>
 <dvmrp-prunes-sent>*dvmrp-prunes-sent*</dvmrp-prunes-sent>
 <dvmrp-grafts-sent>*dvmrp-grafts-sent*</dvmrp-grafts-sent>
 <dvmrp-cache-lifetime>*dvmrp-cache-lifetime*</dvmrp-cache-lifetime>
 <dvmrp-prune-time>*dvmrp-prune-time*</dvmrp-prune-time>
 <dvmrp-prune-lifetime>*dvmrp-prune-lifetime*</dvmrp-prune-lifetime>
 <dvmrp-prune>...</dvmrp-prune>
 </dvmrp-group>
 </dvmrp-prefix-entry>
- Description** No documentation is available yet.
- Contents** <dvmrp-cache-lifetime>—No documentation is available yet.
- <dvmrp-grafts-sent>—No documentation is available yet.
- <dvmrp-prune>—No documentation is available yet.
- <dvmrp-prune-lifetime>—No documentation is available yet.
- <dvmrp-prune-time>—No documentation is available yet.
- <dvmrp-prunes-sent>—No documentation is available yet.
- <multicast-group-address>—Group address.

<dvmrp-instance>

Usage <dvmrp-interfaces-information | dvmrp-graft-queue-information |
dvmrp-neighbors-information | dvmrp-prefix-information | dvmrp-prunes-information>

<dvmrp-instance>

<instance-name>*instance-name*</instance-name>

<dvmrp-interface>...</dvmrp-interface>

<dvmrp-graft>...</dvmrp-graft>

<dvmrp-neighbor>...</dvmrp-neighbor>

<dvmrp-prefix-entry>...</dvmrp-prefix-entry>

<dvmrp-prune>...</dvmrp-prune>

</dvmrp-instance>

</dvmrp-interfaces-information | dvmrp-graft-queue-information |

dvmrp-neighbors-information | dvmrp-prefix-information | dvmrp-prunes-information>

Description No documentation is available yet.

Contents <dvmrp-graft>—No documentation is available yet.

<dvmrp-interface>—No documentation is available yet.

<dvmrp-neighbor>—No documentation is available yet.

<dvmrp-prefix-entry>—No documentation is available yet.

<dvmrp-prune>—No documentation is available yet.

<instance-name>—No documentation is available yet.

<dvmrp-interface>

Usage <dvmrp-instance>
 <dvmrp-interface>
 <interface-name>*interface-name*</interface-name>
 <dvmrp-interface-state>*dvmrp-interface-state*</dvmrp-interface-state>
 <dvmrp-interface-leaf>*dvmrp-interface-leaf*</dvmrp-interface-leaf>
 <dvmrp-interface-metric>*dvmrp-interface-metric*</dvmrp-interface-metric>
 <dvmrp-interface-announcements>*dvmrp-interface-announcements*
 </dvmrp-interface-announcements>
 <dvmrp-interface-mode>*dvmrp-interface-mode*</dvmrp-interface-mode>
 <dvmrp-interface-holdtime>*dvmrp-interface-holdtime*</dvmrp-interface-holdtime>
 </dvmrp-interface>
 </dvmrp-instance>

Description No documentation is available yet.

Contents <dvmrp-interface-announcements>—No documentation is available yet.
 <dvmrp-interface-holdtime>—No documentation is available yet.
 <dvmrp-interface-leaf>—No documentation is available yet.
 <dvmrp-interface-metric>—No documentation is available yet.
 <dvmrp-interface-mode>—No documentation is available yet.
 <dvmrp-interface-state>—No documentation is available yet.
 <interface-name>—No documentation is available yet.

<dvmrp-interfaces-information>

Usage <rpc-reply>
 <dvmrp-interfaces-information>
 <dvmrp-instance>...</dvmrp-instance>
 </dvmrp-interfaces-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <dvmrp-instance>—No documentation is available yet.

<dvmrp-neighbor>

Usage <dvmrp-instance>
 <dvmrp-neighbor>
 <dvmrp-neighbor-address>*dvmrp-neighbor-address*
 </dvmrp-neighbor-address>
 <interface-name>*interface-name*</interface-name>
 <dvmrp-major-version>*dvmrp-major-version*</dvmrp-major-version>
 <dvmrp-minor-version>*dvmrp-minor-version*</dvmrp-minor-version>
 <dvmrp-capability-flags>...</dvmrp-capability-flags>
 <dvmrp-neighbor-routes>*dvmrp-neighbor-routes*</dvmrp-neighbor-routes>
 <dvmrp-neighbor-timeout>*dvmrp-neighbor-timeout*</dvmrp-neighbor-timeout>
 <dvmrp-neighbor-transitions>*dvmrp-neighbor-transitions*
 </dvmrp-neighbor-transitions>
 </dvmrp-neighbor>
 </dvmrp-instance>

Description No documentation is available yet.

Contents <dvmrp-capability-flags>—No documentation is available yet.
 <dvmrp-major-version>—No documentation is available yet.
 <dvmrp-minor-version>—No documentation is available yet.
 <dvmrp-neighbor-address>—No documentation is available yet.
 <dvmrp-neighbor-routes>—No documentation is available yet.
 <dvmrp-neighbor-timeout>—No documentation is available yet.
 <dvmrp-neighbor-transitions>—No documentation is available yet.
 <interface-name>—No documentation is available yet.

<dvmrp-neighbors-information>

Usage <rpc-reply>
 <dvmrp-neighbors-information>
 <dvmrp-instance>...</dvmrp-instance>
 </dvmrp-neighbors-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <dvmrp-instance>—No documentation is available yet.

<dvmrp-prefix-entry>

Usage <dvmrp-instance>
 <dvmrp-prefix-entry>
 <dvmrp-prefix>*dvmrp-prefix*</dvmrp-prefix>
 <dvmrp-prefix-length>*dvmrp-prefix-length*</dvmrp-prefix-length>
 <dvmrp-next-hop>*dvmrp-next-hop*</dvmrp-next-hop>
 <dvmrp-prefix-age>*dvmrp-prefix-age*</dvmrp-prefix-age>
 <dvmrp-group>...</dvmrp-group>
 </dvmrp-prefix-entry>
 </dvmrp-instance>

Description No documentation is available yet.

Contents <dvmrp-group>—No documentation is available yet.

<dvmrp-next-hop>—No documentation is available yet.

<dvmrp-prefix>—No documentation is available yet.

<dvmrp-prefix-age>—No documentation is available yet.

<dvmrp-prefix-length>—No documentation is available yet.

<dvmrp-prefix-information>

Usage <rpc-reply>
 <dvmrp-prefix-information>
 <dvmrp-instance>...</dvmrp-instance>
 </dvmrp-prefix-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <dvmrp-instance>—No documentation is available yet.

<dvmrp-prune>

Usage <dvmrp-group | dvmrp-instance>
<dvmrp-prune>
 <dvmrp-neighbor-address>*dvmrp-neighbor-address*
 </dvmrp-neighbor-address>
 <multicast-group-address>*multicast-group-address*
 </multicast-group-address>
 <multicast-source-address>*multicast-source-address*
 </multicast-source-address>
 <multicast-source-prefix-length>*multicast-source-prefix-length*
 </multicast-source-prefix-length>
 <dvmrp-prune-timeout>*dvmrp-prune-timeout*</dvmrp-prune-timeout>
</dvmrp-prune>
 </dvmrp-group | dvmrp-instance>

Description No documentation is available yet.

Contents <dvmrp-neighbor-address>—No documentation is available yet.
 <dvmrp-prune-timeout>—No documentation is available yet.
 <multicast-group-address>—Group address.
 <multicast-source-address>—Source address.
 <multicast-source-prefix-length>—Source prefix length.

<dvmrp-prunes-information>

Usage <rpc-reply>
<dvmrp-prunes-information>
 <dvmrp-instance>...</dvmrp-instance>
</dvmrp-prunes-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <dvmrp-instance>—No documentation is available yet.

<dynamic-tunnel>

- Usage** <destination-network>
 <dynamic-tunnel>
 <tunnel-destination>*tunnel-destination*</tunnel-destination>
 <tunnel-state>*tunnel-state*</tunnel-state>
 <tunnel-expiry>*tunnel-expiry*</tunnel-expiry>
 <tunnel-reference-count>*tunnel-reference-count*
 </tunnel-reference-count>
 <tunnel-nexthop>...</tunnel-nexthop>
 </dynamic-tunnel>
 </destination-network>
- Description** No documentation is available yet.
- Contents** <tunnel-destination>—Tunnel destination.
 <tunnel-expiry>—Time after which the tunnel will be removed.
 <tunnel-nexthop>—No documentation is available yet.
 <tunnel-reference-count>—Number of references on this tunnel.
 <tunnel-state>—State of the tunnel.

<dynamic-tunnel-table>

- Usage** <dynamic-tunnels-information>
 <dynamic-tunnel-table>
 <table-name>*table-name*</table-name>
 <destination-network>...</destination-network>
 </dynamic-tunnel-table>
 </dynamic-tunnels-information>
- Description** No documentation is available yet.
- Contents** <destination-network>—No documentation is available yet.
 <table-name>—Unicast routing table.

<dynamic-tunnels-information>

- Usage** <rpc-reply>
 <dynamic-tunnels-information>
 <dynamic-tunnel-table>...</dynamic-tunnel-table>
 </dynamic-tunnels-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <dynamic-tunnel-table>—No documentation is available yet.

<end-system-element>

- Usage** `<isis-spf-result>`
 <end-system-element>
 `<end-system-id>end-system-id</end-system-id>`
 `<end-system-metric>end-system-metric</end-system-metric>`
 </end-system-element>
`</isis-spf-result>`
- Description** No documentation is available yet.
- Contents** `<end-system-id>`—Six-octet ISO system ID for a end-system.
`<end-system-metric>`—No documentation is available yet.

<esis-adjacency>

- Usage** `<esis-adjacency-information>`
 <esis-adjacency>
 `<esis-neighbor-type>esis-neighbor-type</esis-neighbor-type>`
 `<esis-neighbor-id>esis-neighbor-id</esis-neighbor-id>`
 `<holdtime>holdtime</holdtime>`
 `<esis-adjacency-advertised-holdtime>esis-adjacency-advertised-holdtime</esis-adjacency-advertised-holdtime>`
 `<snpa>snpa</snpa>`
 `<interface-name>interface-name</interface-name>`
 `<esis-adjacency-log>...</esis-adjacency-log>`
 </esis-adjacency>
`</esis-adjacency-information>`
- Description** No documentation is available yet.
- Contents** `<esis-adjacency-advertised-holdtime>`—Hold time advertised by the adjacency.
`<esis-adjacency-log>`—Entry describing ES-IS adjacency transition.
`<esis-neighbor-id>`—NSAP or NET of the neighbor.
`<esis-neighbor-type>`—Type of neighbor - End system or Intermediate system.
`<holdtime>`—Hold time configured with the hold-time statement. The default hold time is 90 seconds. The hold time is three times the interval at which keepalive messages are sent.
`<interface-name>`—No documentation is available yet.
`<snpa>`—No documentation is available yet.

<esis-adjacency-information>

- Usage** <rpc-reply>
 <esis-adjacency-information>
 <esis-adjacency>...</esis-adjacency>
 </esis-adjacency-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <esis-adjacency>—No documentation is available yet.

<esis-adjacency-log>

- Usage** <esis-adjacency>
 <esis-adjacency-log>
 <esis-adjacency-when>*esis-adjacency-when*</esis-adjacency-when>
 <esis-adjacency-state>*esis-adjacency-state*</esis-adjacency-state>
 <esis-adjacency-event>*esis-adjacency-event*</esis-adjacency-event>
 <esis-adjacency-down-reason>*esis-adjacency-down-reason*
 </esis-adjacency-down-reason>
 </esis-adjacency-log>
 </esis-adjacency>
- Description** Entry describing ES-IS adjacency transition.
- Contents** <esis-adjacency-down-reason>—Reason for the down transition event.
- <esis-adjacency-event>—Event that triggered the transition.
- <esis-adjacency-state>—State of the adjacency.
- <esis-adjacency-when>—Time at which the transition occurred.

<esis-interface>

Usage <esis-interface-information>
 <esis-interface>
 <interface-name>*interface-name*</interface-name>
 <esis-interface-receives>*esis-interface-receives*</esis-interface-receives>
 <esis-interface-sends>*esis-interface-sends*</esis-interface-sends>
 <interface-index>*interface-index*</interface-index>
 <esis-interface-state-value>*esis-interface-state-value*
 </esis-interface-state-value>
 <esis-hello-interval>*esis-hello-interval*</esis-hello-interval>
 <holdtime>*holdtime*</holdtime>
 <esis-esct>*esis-esct*</esis-esct>
 <esis-adjacency-count>*esis-adjacency-count*</esis-adjacency-count>
 <esis-interface-net>*esis-interface-net*</esis-interface-net>
 </esis-interface>
 </esis-interface-information>

Description No documentation is available yet.

Contents <esis-adjacency-count>—Number of adjacencies.

<esis-esct>—Suggested hold time for end systems (default is 180 seconds).

<esis-hello-interval>—Interval between subsequent hellos (one-third of the hold time).

<esis-interface-net>—NET used in hello for this interface.

<esis-interface-receives>—Types of hellos received on this interface - ESH and/or ISH.

<esis-interface-sends>—Type of hello message sent out on this interface - ESH or ISH.

<esis-interface-state-value>—State of ES-IS interface.

<holdtime>—Hold time configured with the hold-time statement. The default hold time is 90 seconds. The hold time is three times the interval at which keepalive messages are sent.

<interface-index>—No documentation is available yet.

<interface-name>—No documentation is available yet.

<esis-interface-information>

- Usage** <rpc-reply>
 <esis-interface-information>
 <esis-interface>...</esis-interface>
 </esis-interface-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <esis-interface>—No documentation is available yet.

<esis-pdu-statistics>

- Usage** <esis-statistics-information>
 <esis-pdu-statistics>
 <esis-pdu-type>esis-pdu-type</esis-pdu-type>
 <packets-received>packets-received</packets-received>
 <packets-processed>packets-processed</packets-processed>
 <packets-dropped>packets-dropped</packets-dropped>
 <packets-sent>packets-sent</packets-sent>
 <packets-retransmitted>packets-retransmitted</packets-retransmitted>
 </esis-pdu-statistics>
 </esis-statistics-information>
- Description** No documentation is available yet.
- Contents** <esis-pdu-type>—Type of ES-IS Protocol Data Unit.
- <packets-dropped>—No documentation is available yet.
- <packets-processed>—No documentation is available yet.
- <packets-received>—No documentation is available yet.
- <packets-retransmitted>—No documentation is available yet.
- <packets-sent>—No documentation is available yet.

<esis-statistics-information>

- Usage** <rpc-reply>
 <esis-statistics-information>
 <esis-pdu-statistics>...</esis-pdu-statistics>
 <esis-totals-information>...</esis-totals-information>
 </esis-statistics-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <esis-pdu-statistics>—No documentation is available yet.
- <esis-totals-information>—No documentation is available yet.

<esis-totals-information>

Usage	<pre> <esis-statistics-information> <esis-totals-information> <packets-received>packets-received</packets-received> <packets-sent>packets-sent</packets-sent> </esis-totals-information> </esis-statistics-information> </pre>
Description	No documentation is available yet.
Contents	<p><packets-received>—No documentation is available yet.</p> <p><packets-sent>—No documentation is available yet.</p>

<everything>

Usage	<pre> <pim-statistics-information> <everything> <pim-statistics-global>...</pim-statistics-global> <pim-statistics-other>...</pim-statistics-other> </everything> </pim-statistics-information> </pre>
Description	No documentation is available yet.
Contents	<p><pim-statistics-global>—No documentation is available yet.</p> <p><pim-statistics-other>—No documentation is available yet.</p>

<explicit-route>

Usage	<pre> <rsvp-session detour detour-branch mpls-lsp-path mpls-restart-path mpls-restart-rsvp> <explicit-route> <address>address</address> <explicit-route-type>explicit-route-type</explicit-route-type> <telink-id>telink-id</telink-id> </explicit-route> </rsvp-session detour detour-branch mpls-lsp-path mpls-restart-path mpls-restart-rsvp> </pre>
Description	Explicit Route Object (ERO).
Contents	<p><address>—No documentation is available yet.</p> <p><explicit-route-type>—No documentation is available yet.</p> <p><telink-id>—Link identifier of unnumbered link.</p>

<fdep-depnode>

Usage	<pre> <fdep-node> fdep-depnode <dep-rtnode-prefix>dep-rtnode-prefix</dep-rtnode-prefix> <dep-rtnode-prefixlen>dep-rtnode-prefixlen</dep-rtnode-prefixlen> <dep-entries>dep-entries</dep-entries> <dep-active>dep-active</dep-active> <dep-flags>dep-flags</dep-flags> /fdep-depnode </fdep-node> </pre>
Description	No documentation is available yet.
Contents	<p><dep-active>—Number of flow routes which match unicast origin.</p> <p><dep-entries>—Number of flow routes with this destination address.</p> <p><dep-flags>—No documentation is available yet.</p> <p><dep-rtnode-prefix>—Prefix of unicast route used to resolve this flow destination.</p> <p><dep-rtnode-prefixlen>—Prefix length of unicast route used to resolve this flow destination.</p>

<fdep-inode>

Usage	<pre> <fdep-node> fdep-inode <fdep-inode-color>fdep-inode-color</fdep-inode-color> <fdep-inode-consist>fdep-inode-consist</fdep-inode-consist> <fdep-inode-asn>fdep-inode-asn</fdep-inode-asn> /fdep-inode </fdep-node> </pre>
Description	No documentation is available yet.
Contents	<p><fdep-inode-asn>—Neighbor AS for all more specific unicast routes.</p> <p><fdep-inode-color>—No documentation is available yet.</p> <p><fdep-inode-consist>—No documentation is available yet.</p>

<fdep-node>

Usage <rtflow-dep-table>
 <fdep-node>
 <fdep-destination>*fdep-destination*</fdep-destination>
 <fdep-prefixlen>*fdep-prefixlen*</fdep-prefixlen>
 <fdep-inode>...</fdep-inode>
 <fdep-rtnode>...</fdep-rtnode>
 <fdep-depnode>...</fdep-depnode>
 </fdep-node>
 </rtflow-dep-table>

Description No documentation is available yet.

Contents <fdep-depnode>—No documentation is available yet.

<fdep-destination>—Destination prefix for tree node.

<fdep-inode>—No documentation is available yet.

<fdep-prefixlen>—Destination prefix length for tree node.

<fdep-rtnode>—Entry that corresponding to a unicast route that is being tracked.

<fdep-rtnode>

Usage <fdep-node>
 <fdep-rtnode>
 <rtnode-state>*rtnode-state*</rtnode-state>
 <rtnode-refcount>*rtnode-refcount*</rtnode-refcount>
 <rtnode-origin>*rtnode-origin*</rtnode-origin>
 <rtnode-next-as>*rtnode-next-as*</rtnode-next-as>
 <rtnode-flags>*rtnode-flags*</rtnode-flags>
 </fdep-rtnode>
 </fdep-node>

Description Entry that corresponding to a unicast route that is being tracked.

Contents <rtnode-flags>—No documentation is available yet.

<rtnode-next-as>—Neighbor AS for active unicast route.

<rtnode-origin>—Unicast route origin (BGP gateway address or originator attribute).

<rtnode-refcount>—Dependent flow destinations.

<rtnode-state>—No documentation is available yet.

<flow-ucast-rt>

Usage	<pre> <rtd-flow-dep> <flow-ucast-rt> <flow-rtn-dest>flow-rtn-dest</flow-rtn-dest> <flow-rtn-plen>flow-rtn-plen</flow-rtn-plen> <flow-rtn-state>flow-rtn-state</flow-rtn-state> </flow-ucast-rt> </rtd-flow-dep> </pre>
Description	Unicast route used for resolution.
Contents	<p><flow-rtn-dest>—Destination address.</p> <p><flow-rtn-plen>—Prefix length.</p> <p><flow-rtn-state>—Validation entry state.</p>

<history>

Usage	<pre> <connection> <history> <log-time-stamp>log-time-stamp</log-time-stamp> <log-event>log-event</log-event> <changed-entity>changed-entity</changed-entity> </history> </connection> </pre>
Description	No documentation is available yet.
Contents	<p><changed-entity>—No documentation is available yet.</p> <p><log-event>—No documentation is available yet.</p> <p><log-time-stamp>—No documentation is available yet.</p>

<host-record>

Usage	<pre> <mgm-group> <host-record> <record-type>record-type</record-type> <receiver>receiver</receiver> <record-timeout>record-timeout</record-timeout> </host-record> </mgm-group> </pre>
Description	No documentation is available yet.
Contents	<p><receiver>—No documentation is available yet.</p> <p><record-timeout>—No documentation is available yet.</p> <p><record-type>—No documentation is available yet.</p>

<hostname-tlv>

Usage	<pre> <isis-tlv> <hostname-tlv> <hostname>hostname</hostname> </hostname-tlv> </isis-tlv> </pre>
Description	No documentation is available yet.
Contents	<hostname>—No documentation is available yet.

<idrp-tlv>

Usage	<pre> <isis-tlv> <idrp-tlv> <tlv-length>tlv-length</tlv-length> </idrp-tlv> </isis-tlv> </pre>
Description	No documentation is available yet.
Contents	<tlv-length>—No documentation is available yet.

<iflist-next-hop>

Usage	<pre> <next-hops-family> <iflist-next-hop> <next-hop-id>next-hop-id</next-hop-id> <next-hop-ref-count>next-hop-ref-count</next-hop-ref-count> <next-hop-kernel-ref-count>next-hop-kernel-ref-count </next-hop-kernel-ref-count> <next-hop-downstream-interface>...</next-hop-downstream-interface> </iflist-next-hop> </next-hops-family> </pre>
Description	No documentation is available yet.
Contents	<p><next-hop-downstream-interface>—No documentation is available yet.</p> <p><next-hop-id>—No documentation is available yet.</p> <p><next-hop-kernel-ref-count>—No documentation is available yet.</p> <p><next-hop-ref-count>—No documentation is available yet.</p>

<igmp-group-information>

- Usage** <rpc-reply>
 <igmp-group-information>
 <mgm-interface-groups>...</mgm-interface-groups>
 </igmp-group-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <mgm-interface-groups>—No documentation is available yet.

<igmp-hosts-information>

- Usage** <rpc-reply>
 <igmp-hosts-information>
 <mgm-disabled-interface-name>*mgm-disabled-interface-name*
 </mgm-disabled-interface-name>
 <mgm-interface>...</mgm-interface>
 </igmp-hosts-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <mgm-disabled-interface-name>—No documentation is available yet.
 <mgm-interface>—No documentation is available yet.

<igmp-interface-information>

- Usage** <rpc-reply>
 <igmp-interface-information>
 <mgm-interface>...</mgm-interface>
 <mgm-configured-parameters>...</mgm-configured-parameters>
 <mgm-derived-parameters>...</mgm-derived-parameters>
 </igmp-interface-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <mgm-configured-parameters>—No documentation is available yet.
 <mgm-derived-parameters>—No documentation is available yet.
 <mgm-interface>—No documentation is available yet.

<igmp-statistics-information>

Usage <rpc-reply>
 <igmp-statistics-information>
 <mgm-statistics-interface>...</mgm-statistics-interface>
 <mgm-statistics-other>...</mgm-statistics-other>
 <mgm-statistics-global>...</mgm-statistics-global>
 <mgm-statistics-all>...</mgm-statistics-all>
 </igmp-statistics-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <mgm-statistics-all>—No documentation is available yet.

 <mgm-statistics-global>—No documentation is available yet.

 <mgm-statistics-interface>—No documentation is available yet.

 <mgm-statistics-other>—No documentation is available yet.

<instance>

Usage <l2vpn-connection-information | vpls-connection-information | vpls-statistics-information
| vpls-ldp-dynamic-interface-repository-entity | mvpn-instance-information>

<instance>

<instance-name>*instance-name*</instance-name>

<instance-display-error>*instance-display-error*</instance-display-error>

<reference-site>...</reference-site>

<ldp-vpls-reference-site>...</ldp-vpls-reference-site>

<vpls-protocol-state>...</vpls-protocol-state>

<vpls-rsvp-te-ingress-p2mp-lsp>...</vpls-rsvp-te-ingress-p2mp-lsp>

<provider-tunnel>...</provider-tunnel>

<neighbor>...</neighbor>

<c-multicast-ipv4>...</c-multicast-ipv4>

</instance>

</l2vpn-connection-information | vpls-connection-information |
vpls-statistics-information | vpls-ldp-dynamic-interface-repository-entity |
mvpn-instance-information>

Description No documentation is available yet.

Contents <c-multicast-ipv4>—No documentation is available yet.

<instance-display-error>—No documentation is available yet.

<instance-name>—No documentation is available yet.

<ldp-vpls-reference-site>—Information about LDP-VPLS.

<neighbor>—No documentation is available yet.

<provider-tunnel>—No documentation is available yet.

<reference-site>—No documentation is available yet.

<vpls-protocol-state>—No documentation is available yet.

<vpls-rsvp-te-ingress-p2mp-lsp>—No documentation is available yet.

<instance-core>

Usage <instance-information>
 <instance-core>
 <instance-name>*instance-name*</instance-name>
 <instance-description>*instance-description*</instance-description>
 <router-id>*router-id*</router-id>
 <instance-type>*instance-type*</instance-type>
 <instance-state>*instance-state*</instance-state>
 <instance-restart-state>*instance-restart-state*</instance-restart-state>
 <instance-pathsel-timeout>*instance-pathsel-timeout*</instance-pathsel-timeout>
 <instance-rib>...</instance-rib>
 <instance-interface>...</instance-interface>
 <instance-vrf>...</instance-vrf>
 </instance-core>
 </instance-information>

Description No documentation is available yet.

Contents <instance-description>—No documentation is available yet.

<instance-interface>—No documentation is available yet.

<instance-name>—No documentation is available yet.

<instance-pathsel-timeout>—Maximum time to defer path selection in instance.

<instance-restart-state>—Whether all tables in instance are done with restart.

<instance-rib>—No documentation is available yet.

<instance-state>—No documentation is available yet.

<instance-type>—No documentation is available yet.

<instance-vrf>—No documentation is available yet.

<router-id>—No documentation is available yet.

<instance-entry>

- Usage** <mvpn-instance>
 <instance-entry>
 <instance-name>*instance-name*</instance-name>
 <instance-display-error>*instance-display-error*</instance-display-error>
 <provider-tunnel>...</provider-tunnel>
 <neighbor>...</neighbor>
 <c-multicast-ipv4>...</c-multicast-ipv4>
 </instance-entry>
 </mvpn-instance>
- Description** No documentation is available yet.
- Contents** <c-multicast-ipv4>—No documentation is available yet.
- <instance-display-error>—No documentation is available yet.
- <instance-name>—No documentation is available yet.
- <neighbor>—No documentation is available yet.
- <provider-tunnel>—No documentation is available yet.

<instance-entry-summary>

- Usage** <mvpn-instance>
 <instance-entry-summary>
 <neighbor-summary>...</neighbor-summary>
 <c-multicast-summary>...</c-multicast-summary>
 </instance-entry-summary>
 </mvpn-instance>
- Description** No documentation is available yet.
- Contents** <c-multicast-summary>—No documentation is available yet.
- <neighbor-summary>—No documentation is available yet.

<instance-information>

- Usage** <rpc-reply>
 <instance-information>
 <instance-core>...</instance-core>
 </instance-information>
 </rpc-reply>
- Description** Operational and configuration information for routing instances.
- Contents** <instance-core>—No documentation is available yet.

<instance-interface>

Usage	<pre> <instance-core> <instance-interface> <interface-name>interface-name</interface-name> </instance-interface> </instance-core> </pre>
Description	No documentation is available yet.
Contents	<interface-name>—No documentation is available yet.

<instance-rib>

Usage	<pre> <instance-core> <instance-rib> <irib-name>irib-name</irib-name> <irib-route-count>irib-route-count</irib-route-count> <irib-active-count>irib-active-count</irib-active-count> <irib-holddown-count>irib-holddown-count</irib-holddown-count> <irib-hidden-count>irib-hidden-count</irib-hidden-count> <irib-restart-state>irib-restart-state</irib-restart-state> </instance-rib> </instance-core> </pre>
Description	No documentation is available yet.
Contents	<p><irib-active-count>—No documentation is available yet.</p> <p><irib-hidden-count>—No documentation is available yet.</p> <p><irib-holddown-count>—No documentation is available yet.</p> <p><irib-name>—No documentation is available yet.</p> <p><irib-restart-state>—No documentation is available yet.</p> <p><irib-route-count>—No documentation is available yet.</p>

<instance-vrf>

Usage	<pre> <instance-core> <instance-vrf> <route-distinguisher>route-distinguisher</route-distinguisher> <vrf-import>vrf-import</vrf-import> <vrf-export>vrf-export</vrf-export> <vrf-import-target>vrf-import-target</vrf-import-target> <vrf-export-target>vrf-export-target</vrf-export-target> </instance-vrf> </instance-core> </pre>
Description	No documentation is available yet.
Contents	<p><route-distinguisher>—No documentation is available yet.</p> <p><vrf-export>—No documentation is available yet.</p> <p><vrf-export-target>—No documentation is available yet.</p> <p><vrf-import>—No documentation is available yet.</p> <p><vrf-import-target>—No documentation is available yet.</p>

<interface>

Usage	<pre> <mesh-group-interfaces reference-site ldp-vpls-reference-site vpls-protocol-state interface-statistics> <interface> <interface-name>interface-name</interface-name> <interface-id>interface-id</interface-id> <interface-description>interface-description</interface-description> <local-interface-index>local-interface-index</local-interface-index> <interface-flags>interface-flags</interface-flags> <interface-flags-description>interface-flags-description </interface-flags-description> </interface> </mesh-group-interfaces reference-site ldp-vpls-reference-site vpls-protocol-state interface-statistics> </pre>
Description	No documentation is available yet.
Contents	<p><interface-description>—No documentation is available yet.</p> <p><interface-flags>—No documentation is available yet.</p> <p><interface-flags-description>—No documentation is available yet.</p> <p><interface-id>—No documentation is available yet.</p> <p><interface-name>—No documentation is available yet.</p> <p><local-interface-index>—SNMP ifIndex of local interface.</p>

<interface-level-data>

Usage <isis-interface>
 <interface-level-data>
 <level>level</level>
 <adjacency-count>adjacency-count</adjacency-count>
 <interface-priority>interface-priority</interface-priority>
 <metric>metric</metric>
 <te-metric>te-metric</te-metric>
 <passive>passive</passive>
 <hello-time>hello-time</hello-time>
 <holdtime>holdtime</holdtime>
 <dr-id-one>dr-id-one</dr-id-one>
 <dr-id-two>dr-id-two</dr-id-two>
 <dr-flag>dr-flag</dr-flag>
 <isis-interface-level-topology>...</isis-interface-level-topology>
 </interface-level-data>
 </isis-interface>

Description No documentation is available yet.

Contents <adjacency-count>—No documentation is available yet.

<dr-flag>—No documentation is available yet.

<dr-id-one>—No documentation is available yet.

<dr-id-two>—No documentation is available yet.

<hello-time>—No documentation is available yet.

<holdtime>—Hold time configured with the hold-time statement. The default hold time is 90 seconds. The hold time is three times the interval at which keepalive messages are sent.

<interface-priority>—No documentation is available yet.

<isis-interface-level-topology>—Topology-specific information for an interface level.

<level>—No documentation is available yet.

<metric>—No documentation is available yet.

<passive>—No documentation is available yet.

<te-metric>—No documentation is available yet.

<interface-statistics>

Usage <vpls-statistics-information>
 <interface-statistics>
 <interface>...</interface>
 <remote-pe>*remote-pe*</remote-pe>
 <broadcast-packets>*broadcast-packets*</broadcast-packets>
 <broadcast-bytes>*broadcast-bytes*</broadcast-bytes>
 <multicast-packets>*multicast-packets*</multicast-packets>
 <multicast-bytes>*multicast-bytes*</multicast-bytes>
 <flooded-packets>*flooded-packets*</flooded-packets>
 <flooded-bytes>*flooded-bytes*</flooded-bytes>
 <unicast-packets>*unicast-packets*</unicast-packets>
 <unicast-bytes>*unicast-bytes*</unicast-bytes>
 <mac-limit>*mac-limit*</mac-limit>
 <num-mac-count>*num-mac-count*</num-mac-count>
 </interface-statistics>
 </vpls-statistics-information>

Description No documentation is available yet.

Contents <broadcast-bytes>—Broadcast bytes.
 <broadcast-packets>—Broadcast packets.
 <flooded-bytes>—Flooded bytes.
 <flooded-packets>—Flooded packets.
 <interface>—No documentation is available yet.
 <mac-limit>—Limit of number of addresses learned on interface.
 <multicast-bytes>—Multicast bytes.
 <multicast-packets>—Multicast packets.
 <num-mac-count>—Number of addresses learned on the interface.
 <remote-pe>—No documentation is available yet.
 <unicast-bytes>—Unicast bytes.
 <unicast-packets>—Unicast packets.

<ip-prefix-tlv>

Usage	<pre> <isis-tlv> <ip-prefix-tlv> <isis-topology-id>isis-topology-id</isis-topology-id> <address-prefix>address-prefix</address-prefix> <metric>metric</metric> <prefix-status>prefix-status</prefix-status> <subtlv-size>subtlv-size</subtlv-size> <isis-prefix-subtlv>...</isis-prefix-subtlv> </ip-prefix-tlv> </isis-tlv> </pre>
Description	No documentation is available yet.
Contents	<p><address-prefix>—No documentation is available yet.</p> <p><isis-prefix-subtlv>—No documentation is available yet.</p> <p><isis-topology-id>—No documentation is available yet.</p> <p><metric>—No documentation is available yet.</p> <p><prefix-status>—No documentation is available yet.</p> <p><subtlv-size>—No documentation is available yet.</p>

<ipaddress-tlv>

Usage	<pre> <isis-tlv> <ipaddress-tlv> <address>address</address> </ipaddress-tlv> </isis-tlv> </pre>
Description	No documentation is available yet.
Contents	<address>—No documentation is available yet.

<ipv6-ra-advertisement>

Usage <ipv6-ra-interface>
<ipv6-ra-advertisement>
 <ipv6-source-address>ipv6-source-address</ipv6-source-address>
 <ipv6-ra-time-since>ipv6-ra-time-since</ipv6-ra-time-since>
 <ipv6-ra-managed-flag>ipv6-ra-managed-flag</ipv6-ra-managed-flag>
 <ipv6-ra-managed-flag-conflict>ipv6-ra-managed-flag-conflict
 </ipv6-ra-managed-flag-conflict>
 <ipv6-ra-other-config-flag>ipv6-ra-other-config-flag
 </ipv6-ra-other-config-flag>
 <ipv6-ra-other-config-flag-conflict>ipv6-ra-other-config-flag-conflict
 </ipv6-ra-other-config-flag-conflict>
 <ipv6-ra-link-mtu>ipv6-ra-link-mtu</ipv6-ra-link-mtu>
 <ipv6-ra-link-mtu-conflict>ipv6-ra-link-mtu-conflict
 </ipv6-ra-link-mtu-conflict>
 <ipv6-ra-reachable-time>ipv6-ra-reachable-time</ipv6-ra-reachable-time>
 <ipv6-ra-reachable-time-conflict>ipv6-ra-reachable-time-conflict
 </ipv6-ra-reachable-time-conflict>
 <ipv6-ra-default-lifetime>ipv6-ra-default-lifetime</ipv6-ra-default-lifetime>
 <ipv6-ra-default-lifetime-conflict>ipv6-ra-default-lifetime-conflict
 </ipv6-ra-default-lifetime-conflict>
 <ipv6-ra-retransmit-timer>ipv6-ra-retransmit-timer</ipv6-ra-retransmit-timer>
 <ipv6-ra-retransmit-timer-conflict>ipv6-ra-retransmit-timer-conflict
 </ipv6-ra-retransmit-timer-conflict>
 <ipv6-ra-current-hop-limit>ipv6-ra-current-hop-limit
 </ipv6-ra-current-hop-limit>
 <ipv6-ra-current-hop-limit-conflict>ipv6-ra-current-hop-limit-conflict
 </ipv6-ra-current-hop-limit-conflict>
 <ipv6-ra-prefix>...</ipv6-ra-prefix>
</ipv6-ra-advertisement>
 </ipv6-ra-interface>

Description No documentation is available yet.

Contents <ipv6-ra-current-hop-limit>—Advertised current hop limit flag.
 <ipv6-ra-current-hop-limit-conflict>—Conflict with the advertised current hop limit flag.
 <ipv6-ra-default-lifetime>—Advertised default lifetime flag.
 <ipv6-ra-default-lifetime-conflict>—Conflict with the advertised default lifetime flag.
 <ipv6-ra-link-mtu>—Advertised link MTU.
 <ipv6-ra-link-mtu-conflict>—Conflict with the advertised link MTU.
 <ipv6-ra-managed-flag>—Advertised managed flag.
 <ipv6-ra-managed-flag-conflict>—Conflict with the advertised managed flag.
 <ipv6-ra-other-config-flag>—Advertised other configuration flag.

`<ipv6-ra-other-config-flag-conflict>`—Conflict with the advertised other configuration flag.

`<ipv6-ra-prefix>`—No documentation is available yet.

`<ipv6-ra-reachable-time>`—Advertised reachable time.

`<ipv6-ra-reachable-time-conflict>`—Conflict with the advertised reachable time.

`<ipv6-ra-retransmit-timer>`—Advertised retransmit timer flag.

`<ipv6-ra-retransmit-timer-conflict>`—Conflict with the advertised retransmit timer flag.

`<ipv6-ra-time-since>`—How long since the advertisement was received.

`<ipv6-source-address>`—Sender of the advertisement.

`<ipv6-ra-information>`

Usage `<rpc-reply>`
 `<ipv6-ra-information>`
 `<ipv6-ra-interface>...</ipv6-ra-interface>`
 `</ipv6-ra-information>`
 `</rpc-reply>`

Description No documentation is available yet.

Contents `<ipv6-ra-interface>`—No documentation is available yet.

<ipv6-ra-interface>

Usage <ipv6-ra-information>
 <ipv6-ra-interface>
 <interface-name>*interface-name*</interface-name>
 <ipv6-ra-advertisements-sent>*ipv6-ra-advertisements-sent*
 </ipv6-ra-advertisements-sent>
 <ipv6-ra-advertisement-sent-time>*ipv6-ra-advertisement-sent-time*
 </ipv6-ra-advertisement-sent-time>
 <ipv6-ra-solicits-received>*ipv6-ra-solicits-received*
 </ipv6-ra-solicits-received>
 <ipv6-ra-solicit-receive-time>*ipv6-ra-solicit-receive-time*
 </ipv6-ra-solicit-receive-time>
 <ipv6-ra-advertisements-received>*ipv6-ra-advertisements-received*
 </ipv6-ra-advertisements-received>
 <vrrp-group>...</vrrp-group>
 <ipv6-ra-advertisement>...</ipv6-ra-advertisement>
 </ipv6-ra-interface>
 </ipv6-ra-information>

Description No documentation is available yet.

Contents <interface-name>—No documentation is available yet.

<ipv6-ra-advertisement>—No documentation is available yet.

<ipv6-ra-advertisement-sent-time>—How long since the last router advertisement was sent.

<ipv6-ra-advertisements-received>—Number of router advertisements received.

<ipv6-ra-advertisements-sent>—Number of router advertisements sent.

<ipv6-ra-solicit-receive-time>—How long since the last router solicitation was sent.

<ipv6-ra-solicits-received>—Number of router solicitations received.

<vrrp-group>—No documentation is available yet.

<ipv6-ra-prefix>

Usage <ipv6-ra-advertisement>
 <ipv6-ra-prefix>
 <ipv6-ra-prefix-address>ipv6-ra-prefix-address</ipv6-ra-prefix-address>
 <ipv6-ra-prefix-valid-lifetime>ipv6-ra-prefix-valid-lifetime
 </ipv6-ra-prefix-valid-lifetime>
 <ipv6-ra-prefix-valid-lifetime-conflict>ipv6-ra-prefix-valid-lifetime-conflict
 </ipv6-ra-prefix-valid-lifetime-conflict>
 <ipv6-ra-prefix-preferred-lifetime>ipv6-ra-prefix-preferred-lifetime
 </ipv6-ra-prefix-preferred-lifetime>
 <ipv6-ra-prefix-preferred-lifetime-conflict>ipv6-ra-prefix-preferred-lifetime-conflict
 </ipv6-ra-prefix-preferred-lifetime-conflict>
 <ipv6-ra-prefix-on-link>ipv6-ra-prefix-on-link</ipv6-ra-prefix-on-link>
 <ipv6-ra-prefix-on-link-conflict>ipv6-ra-prefix-on-link-conflict
 </ipv6-ra-prefix-on-link-conflict>
 <ipv6-ra-prefix-autonomous>ipv6-ra-prefix-autonomous
 </ipv6-ra-prefix-autonomous>
 <ipv6-ra-prefix-autonomous-conflict>ipv6-ra-prefix-autonomous-conflict
 </ipv6-ra-prefix-autonomous-conflict>
 </ipv6-ra-prefix>
 </ipv6-ra-advertisement>

Description No documentation is available yet.

Contents <ipv6-ra-prefix-address>—Advertised prefix.

<ipv6-ra-prefix-autonomous>—Advertised autonomous flag of the prefix.

<ipv6-ra-prefix-autonomous-conflict>—Conflict with the advertised autonomous flag of the prefix.

<ipv6-ra-prefix-on-link>—Advertised on-link flag of the prefix.

<ipv6-ra-prefix-on-link-conflict>—Conflict with the advertised on-link flag of the prefix.

<ipv6-ra-prefix-preferred-lifetime>—Advertised preferred lifetime of the prefix.

<ipv6-ra-prefix-preferred-lifetime-conflict>—Conflict with the advertised preferred lifetime of the prefix.

<ipv6-ra-prefix-valid-lifetime>—Advertised valid lifetime of the prefix.

<ipv6-ra-prefix-valid-lifetime-conflict>—Conflict with the advertised valid lifetime of the prefix.

<ipv6-reachability-tlv>

Usage <isis-tlv>
 <ipv6-reachability-tlv>
 <isis-topology-id>*isis-topology-id*</isis-topology-id>
 <ipv6-address>*ipv6-address*</ipv6-address>
 <metric>*metric*</metric>
 <prefix-extern/>
 <prefix-downflag/>
 <subtlv-size>*subtlv-size*</subtlv-size>
 <isis-prefix-subtlv>...</isis-prefix-subtlv>
 </ipv6-reachability-tlv>
 </isis-tlv>

Description No documentation is available yet.

Contents <ipv6-address>—No documentation is available yet.
 <isis-prefix-subtlv>—No documentation is available yet.
 <isis-topology-id>—No documentation is available yet.
 <metric>—No documentation is available yet.
 <prefix-downflag>—No documentation is available yet.
 <prefix-extern>—No documentation is available yet.
 <subtlv-size>—No documentation is available yet.

<ipv6address-tlv>

Usage <isis-tlv>
 <ipv6address-tlv>
 <address>*address*</address>
 </ipv6address-tlv>
 </isis-tlv>

Description No documentation is available yet.

Contents <address>—No documentation is available yet.

<is-reachability>

Usage <isis-database-local-data>
<is-reachability>
 <isis-fragment>*isis-fragment*</isis-fragment>
 <isis-topology-id>*isis-topology-id*</isis-topology-id>
 <is-neighbor-id>*is-neighbor-id*</is-neighbor-id>
 <flags>*flags*</flags>
 <isis-pseudonode>*isis-pseudonode*</isis-pseudonode>
 <interface-name>*interface-name*</interface-name>
 <metric>*metric*</metric>
 <subtlv-size>*subtlv-size*</subtlv-size>
 <te-metric>*te-metric*</te-metric>
 <local-address>*local-address*</local-address>
 <remote-address>*remote-address*</remote-address>
 <local-ifindex>*local-ifindex*</local-ifindex>
 <remote-ifindex>*remote-ifindex*</remote-ifindex>
 <level>*level*</level>
</is-reachability>
 </isis-database-local-data>

Description No documentation is available yet.

Contents <flags>—Enabled trace flags.

<interface-name>—No documentation is available yet.

<is-neighbor-id>—No documentation is available yet.

<isis-fragment>—No documentation is available yet.

<isis-pseudonode>—No documentation is available yet.

<isis-topology-id>—No documentation is available yet.

<level>—No documentation is available yet.

<local-address>—No documentation is available yet.

<local-ifindex>—Local interface index.

<metric>—No documentation is available yet.

<remote-address>—No documentation is available yet.

<remote-ifindex>—Remote interface index.

<subtlv-size>—No documentation is available yet.

<te-metric>—No documentation is available yet.

<isis-adjacency>

Usage <isis-adjacency-information>
<isis-adjacency>
 <interface-name>*interface-name*</interface-name>
 <system-name>*system-name*</system-name>
 <not-remote-address/>
 <level>*level*</level>
 <adjacency-state>*adjacency-state*</adjacency-state>
 <holdtime>*holdtime*</holdtime>
 <interface-priority>*interface-priority*</interface-priority>
 <transition-count>*transition-count*</transition-count>
 <last-transition-time>*last-transition-time*</last-transition-time>
 <circuit-type>*circuit-type*</circuit-type>
 <adjacency-restart-capable>*adjacency-restart-capable*
 </adjacency-restart-capable>
 <adjacency-advertisement>*adjacency-advertisement*</adjacency-advertisement>
 <adjacency-flag>*adjacency-flag*</adjacency-flag>
 <adjacency-topologies>*adjacency-topologies*</adjacency-topologies>
 <mac-address>*mac-address*</mac-address>
 <lan-id>*lan-id*</lan-id>
 <ip-address>*ip-address*</ip-address>
 <ipv6-address>*ipv6-address*</ipv6-address>
 <snpa>*snpa*</snpa>
 <isis-adjacency-log>...</isis-adjacency-log>
</isis-adjacency>
 </isis-adjacency-information>

Description No documentation is available yet.

Contents <adjacency-advertisement>—State of the adjacency advertisement.
 <adjacency-flag>—No documentation is available yet.
 <adjacency-restart-capable>—Restart capability of the adjacency.
 <adjacency-state>—State of the adjacency.
 <adjacency-topologies>—No documentation is available yet.
 <circuit-type>—No documentation is available yet.
 <holdtime>—Hold time configured with the hold-time statement. The default hold time is 90 seconds. The hold time is three times the interval at which keepalive messages are sent.
 <interface-name>—No documentation is available yet.
 <interface-priority>—No documentation is available yet.
 <ip-address>—No documentation is available yet.
 <ipv6-address>—No documentation is available yet.
 <isis-adjacency-log>—Entry describing adjacency transition.

<lan-id>—No documentation is available yet.

<last-transition-time>—No documentation is available yet.

<level>—No documentation is available yet.

<mac-address>—No documentation is available yet.

<not-remote-address>—No documentation is available yet.

<snpa>—No documentation is available yet.

<system-name>—Hostname for a system.

<transition-count>—No documentation is available yet.

<isis-adjacency-information>

Usage <rpc-reply>
 <isis-adjacency-information>
 <isis-adjacency>...</isis-adjacency>
 </isis-adjacency-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <isis-adjacency>—No documentation is available yet.

<isis-adjacency-log>

Usage <isis-adjacency>
 <isis-adjacency-log>
 <adjacency-when>*adjacency-when*</adjacency-when>
 <adjacency-state>*adjacency-state*</adjacency-state>
 <adjacency-event>*adjacency-event*</adjacency-event>
 <adjacency-down-reason>*adjacency-down-reason*</adjacency-down-reason>
 </isis-adjacency-log>
 </isis-adjacency>

Description Entry describing adjacency transition.

Contents <adjacency-down-reason>—Reason for the down transition event.

<adjacency-event>—Event which triggered the transition.

<adjacency-state>—State of the adjacency.

<adjacency-when>—Time at which the transition occurred.

<isis-authentication-information>

- Usage** <rpc-reply>
 <isis-authentication-information>
 <isis-interface-authentication>...</isis-interface-authentication>
 <isis-lsp-authentication>...</isis-lsp-authentication>
 </isis-authentication-information>
 </rpc-reply>
- Description** ISIS authentication information.
- Contents** <isis-interface-authentication>—No documentation is available yet.
 <isis-lsp-authentication>—Authentication type for LSP packets.

<isis-database>

- Usage** <isis-database-information>
 <isis-database>
 <level>level</level>
 <isis-database-entry>...</isis-database-entry>
 <lsp-count>lsp-count</lsp-count>
 </isis-database>
 </isis-database-information>
- Description** No documentation is available yet.
- Contents** <isis-database-entry>—No documentation is available yet.
 <level>—No documentation is available yet.
 <lsp-count>—No documentation is available yet.

<isis-database-entry>

Usage <isis-database>
 <isis-database-entry>
 <lsp-id>*lsp-id*</lsp-id>
 <sequence-number>*sequence-number*</sequence-number>
 <checksum>*checksum*</checksum>
 <remaining-lifetime>*remaining-lifetime*</remaining-lifetime>
 <lsp-attributes>*lsp-attributes*</lsp-attributes>
 <isis-neighbor>...</isis-neighbor>
 <isis-prefix>...</isis-prefix>
 <isis-header>...</isis-header>
 <isis-packet>...</isis-packet>
 <lsp-stub/>
 <isis-tlv>...</isis-tlv>
 <transmission-status>...</transmission-status>
 <isis-es-neighbor>...</isis-es-neighbor>
 </isis-database-entry>
 </isis-database>

Description No documentation is available yet.

Contents <checksum>—No documentation is available yet.

<isis-es-neighbor>—No documentation is available yet.

<isis-header>—No documentation is available yet.

<isis-neighbor>—No documentation is available yet.

<isis-packet>—No documentation is available yet.

<isis-prefix>—No documentation is available yet.

<isis-tlv>—No documentation is available yet.

<lsp-attributes>—No documentation is available yet.

<lsp-id>—LSP ID or source port for some sender. It is unique to every sender or LSP.

<lsp-stub>—No documentation is available yet.

<remaining-lifetime>—No documentation is available yet.

<sequence-number>—History event number.

<transmission-status>—No documentation is available yet.

<isis-database-information>

- Usage** <rpc-reply>
 <isis-database-information>
 <isis-database>...</isis-database>
 </isis-database-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <isis-database>—No documentation is available yet.

<isis-database-local>

- Usage** <isis-database-local-information>
 <isis-database-local>
 <level>level</level>
 <isis-database-local-entry>...</isis-database-local-entry>
 </isis-database-local>
 </isis-database-local-information>
- Description** Information about one or more entries in the IS-IS database that originated locally.
- Contents** <isis-database-local-entry>—Information about an entry that originated locally.
 <level>—No documentation is available yet.

<isis-database-local-data>

Usage <isis-database-local-entry>
<isis-database-local-data>
 <isis-database-local-data-type>*isis-database-local-data-type*
 </isis-database-local-data-type>
 <isis-database-local-data-name>*isis-database-local-data-name*
 </isis-database-local-data-name>
 <tlv-size>*tlv-size*</tlv-size>
 <address>*address*</address>
 <protocol>*protocol*</protocol>
 <mtid>*mtid*</mtid>
 <router-id>*router-id*</router-id>
 <hostname>*hostname*</hostname>
 <prefix-reachability>...</prefix-reachability>
 <is-reachability>...</is-reachability>
 <unknown-local-data>*unknown-local-data*</unknown-local-data>
</isis-database-local-data>
 </isis-database-local-entry>

Description No documentation is available yet.

Contents <address>—No documentation is available yet.
 <hostname>—No documentation is available yet.
 <is-reachability>—No documentation is available yet.
 <isis-database-local-data-name>—No documentation is available yet.
 <isis-database-local-data-type>—No documentation is available yet.
 <mtid>—No documentation is available yet.
 <prefix-reachability>—No documentation is available yet.
 <protocol>—No documentation is available yet.
 <router-id>—No documentation is available yet.
 <tlv-size>—No documentation is available yet.
 <unknown-local-data>—No documentation is available yet.

<isis-database-local-entry>

Usage <isis-database-local>
 <isis-database-local-entry>
 <lsp-id>*lsp-id*</lsp-id>
 <sequence-number>*sequence-number*</sequence-number>
 <checksum>*checksum*</checksum>
 <remaining-lifetime>*remaining-lifetime*</remaining-lifetime>
 <lsp-attributes>*lsp-attributes*</lsp-attributes>
 <isis-database-local-data>...</isis-database-local-data>
 <estimated-free-bytes>*estimated-free-bytes*</estimated-free-bytes>
 </isis-database-local-entry>
 </isis-database-local>

Description Information about an entry that originated locally.

Contents <checksum>—No documentation is available yet.

<estimated-free-bytes>—No documentation is available yet.

<isis-database-local-data>—No documentation is available yet.

<lsp-attributes>—No documentation is available yet.

<lsp-id>—LSP ID or source port for some sender. It is unique to every sender or LSP.

<remaining-lifetime>—No documentation is available yet.

<sequence-number>—History event number.

<isis-database-local-information>

Usage <rpc-reply>
 <isis-database-local-information>
 <isis-database-local>...</isis-database-local>
 </isis-database-local-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <isis-database-local>—Information about one or more entries in the IS-IS database that originated locally.

<isis-es-neighbor>

Usage <isis-database-entry>
 <isis-es-neighbor>
 <es-neighbor-id>*es-neighbor-id*</es-neighbor-id>
 <metric>*metric*</metric>
 <reachability-delay/>
 <reachability-expense/>
 <reachability-error/>
 </isis-es-neighbor>
</isis-database-entry>

Description No documentation is available yet.

Contents <es-neighbor-id>—No documentation is available yet.

<metric>—No documentation is available yet.

<reachability-delay>—No documentation is available yet.

<reachability-error>—No documentation is available yet.

<reachability-expense>—No documentation is available yet.

<isis-header>

Usage	<pre> <isis-database-entry> <isis-header> <lsp-id>lsp-id</lsp-id> <pdu-length>pdu-length</pdu-length> <allocated-length>allocated-length</allocated-length> <router-id>router-id</router-id> <remaining-lifetime>remaining-lifetime</remaining-lifetime> <level>level</level> <interface-index>interface-index</interface-index> <estimated-free-bytes>estimated-free-bytes</estimated-free-bytes> <actual-free-bytes>actual-free-bytes</actual-free-bytes> <lsdb-timer-type>lsdb-timer-type</lsdb-timer-type> <lsdb-expiration-time>lsdb-expiration-time</lsdb-expiration-time> <needs-rebuild/> <protocol>protocol</protocol> </isis-header> </isis-database-entry> </pre>
Description	No documentation is available yet.
Contents	<p><actual-free-bytes>—No documentation is available yet.</p> <p><allocated-length>—No documentation is available yet.</p> <p><estimated-free-bytes>—No documentation is available yet.</p> <p><interface-index>—No documentation is available yet.</p> <p><level>—No documentation is available yet.</p> <p><lsdb-expiration-time>—No documentation is available yet.</p> <p><lsdb-timer-type>—No documentation is available yet.</p> <p><lsp-id>—LSP ID or source port for some sender. It is unique to every sender or LSP.</p> <p><needs-rebuild>—No documentation is available yet.</p> <p><pdu-length>—No documentation is available yet.</p> <p><protocol>—No documentation is available yet.</p> <p><remaining-lifetime>—No documentation is available yet.</p> <p><router-id>—No documentation is available yet.</p>

<isis-hostname>

- Usage** <isis-hostname-information>
 <isis-hostname>
 <system-id>*system-id*</system-id>
 <system-name>*system-name*</system-name>
 <isis-hostname-type>*isis-hostname-type*</isis-hostname-type>
 </isis-hostname>
</isis-hostname-information>
- Description** Entry in the system-ID-to-hostname mapping table.
- Contents** <isis-hostname-type>—Type of system-ID-to-hostname mapping.

 <system-id>—Six-octet ISO system ID for a system.

 <system-name>—Hostname for a system.

<isis-hostname-information>

- Usage** <rpc-reply>
 <isis-hostname-information>
 <isis-hostname>...</isis-hostname>
 </isis-hostname-information>
</rpc-reply>
- Description** System-ID-to-hostname mapping table.
- Contents** <isis-hostname>—Entry in the system-ID-to-hostname mapping table.

<isis-interface>

Usage <isis-interface-information>
<isis-interface>
 <interface-name>*interface-name*</interface-name>
 <circuit-type>*circuit-type*</circuit-type>
 <circuit-id>*circuit-id*</circuit-id>
 <isis-interface-state-one>*isis-interface-state-one*</isis-interface-state-one>
 <isis-interface-state-two>*isis-interface-state-two*</isis-interface-state-two>
 <interface-disabled-flag/>
 <dr-id-one>*dr-id-one*</dr-id-one>
 <dr-id-two>*dr-id-two*</dr-id-two>
 <metric-one>*metric-one*</metric-one>
 <metric-two>*metric-two*</metric-two>
 <interface-index>*interface-index*</interface-index>
 <interface-state-value>*interface-state-value*</interface-state-value>
 <lsp-interval>*lsp-interval*</lsp-interval>
 <csnp-interval>*csnp-interval*</csnp-interval>
 <hello-padding>*hello-padding*</hello-padding>
 <system-name>*system-name*</system-name>
 <mesh-group>*mesh-group*</mesh-group>
 <adjacency-advertisement>*adjacency-advertisement*</adjacency-advertisement>
 <interface-level-data>...</interface-level-data>
 <igp-ldp-sync-holdtime>*igp-ldp-sync-holdtime*</igp-ldp-sync-holdtime>
 <igp-ldp-sync-state>*igp-ldp-sync-state*</igp-ldp-sync-state>
 <igp-ldp-sync-last-change>*igp-ldp-sync-last-change*</igp-ldp-sync-last-change>
 <igp-ldp-sync-reason>*igp-ldp-sync-reason*</igp-ldp-sync-reason>
 <igp-ldp-sync-timeleft>*igp-ldp-sync-timeleft*</igp-ldp-sync-timeleft>
</isis-interface>
 </isis-interface-information>

Description No documentation is available yet.

Contents <adjacency-advertisement>—State of the adjacency advertisement.

<circuit-id>—No documentation is available yet.

<circuit-type>—No documentation is available yet.

<csnp-interval>—No documentation is available yet.

<dr-id-one>—No documentation is available yet.

<dr-id-two>—No documentation is available yet.

<hello-padding>—No documentation is available yet.

<igp-ldp-sync-holdtime>—Length of time during which the maximum metric is advertised for an interface that is in the hold-down state because synchronization was lost between Label Distribution Protocol (LDP) and the interior gateway protocol (IGP).

<igp-ldp-sync-last-change>—Time since the state of synchronization between Label Distribution Protocol (LDP) and the interior gateway protocol (IGP) last changed.

<igp-ldp-sync-reason>—Reason for the change in the state of synchronization between Label Distribution Protocol (LDP) and the interior gateway protocol (IGP).

<igp-ldp-sync-state>—State of synchronization between Label Distribution Protocol (LDP) and the interior gateway protocol (IGP).

<igp-ldp-sync-timeleft>—Remaining amount of time the interface will remain in the hold-down state because synchronization was lost between Label Distribution Protocol (LDP) and the interior gateway protocol (IGP).

<interface-disabled-flag>—No documentation is available yet.

<interface-index>—No documentation is available yet.

<interface-level-data>—No documentation is available yet.

<interface-name>—No documentation is available yet.

<interface-state-value>—No documentation is available yet.

<isis-interface-state-one>—No documentation is available yet.

<isis-interface-state-two>—No documentation is available yet.

<lsp-interval>—No documentation is available yet.

<mesh-group>—No documentation is available yet.

<metric-one>—No documentation is available yet.

<metric-two>—No documentation is available yet.

<system-name>—Hostname for a system.

<isis-interface-authentication>

Usage **<isis-authentication-information>**
<isis-interface-authentication>
 <interface-name>*interface-name*</interface-name>
 <isis-interface-level-authentication>...</isis-interface-level-authentication>
</isis-interface-authentication>
 </isis-authentication-information>

Description No documentation is available yet.

Contents <interface-name>—No documentation is available yet.
 <isis-interface-level-authentication>—No documentation is available yet.

<isis-interface-information>

- Usage** <rpc-reply>
 <isis-interface-information>
 <isis-interface>...</isis-interface>
 </isis-interface-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <isis-interface>—No documentation is available yet.

<isis-interface-level-authentication>

- Usage** <isis-interface-authentication>
 <isis-interface-level-authentication>
 <level>level</level>
 <isis-interface-level-iih-authentication>isis-interface-level-iih-authentication
 </isis-interface-level-iih-authentication>
 <isis-interface-level-csn-authentication>isis-interface-level-csn-authentication
 </isis-interface-level-csn-authentication>
 <isis-interface-level-psn-authentication>isis-interface-level-psn-authentication
 </isis-interface-level-psn-authentication>
 </isis-interface-level-authentication>
 </isis-interface-authentication>
- Description** No documentation is available yet.
- Contents** <isis-interface-level-csn-authentication>—Authentication type for CSN packets.
- <isis-interface-level-iih-authentication>—Authentication type for IIH packets.
- <isis-interface-level-psn-authentication>—Authentication type for PSN packets.
- <level>—No documentation is available yet.

<isis-interface-level-topology>

- Usage** <interface-level-data>
 <isis-interface-level-topology>
 <isis-topology-id>isis-topology-id</isis-topology-id>
 <isis-topology-metric>isis-topology-metric</isis-topology-metric>
 </isis-interface-level-topology>
 </interface-level-data>
- Description** Topology-specific information for an interface level.
- Contents** <isis-topology-id>—No documentation is available yet.
- <isis-topology-metric>—Metric for a topology.

<isis-iso-prefix-tlv>

Usage <isis-tlv>
 <isis-iso-prefix-tlv>
 <metric>*metric*</metric>
 <metric-flag>*metric-flag*</metric-flag>
 <reachability-delay/>
 <reachability-expense/>
 <reachability-error/>
 <prefix-status>*prefix-status*</prefix-status>
 <iso-prefix>*iso-prefix*</iso-prefix>
 </isis-iso-prefix-tlv>
</isis-tlv>

Description No documentation is available yet.

Contents <iso-prefix>—No documentation is available yet.

<metric>—No documentation is available yet.

<metric-flag>—No documentation is available yet.

<prefix-status>—No documentation is available yet.

<reachability-delay>—No documentation is available yet.

<reachability-error>—No documentation is available yet.

<reachability-expense>—No documentation is available yet.

<isis-level-information>

Usage	<pre> <isis-overview> <isis-level-information> <isis-level>isis-level</isis-level> <isis-preference>isis-preference</isis-preference> <isis-external-preference>isis-external-preference</isis-external-preference> <isis-prefix-export-limit>isis-prefix-export-limit</isis-prefix-export-limit> <isis-narrow-metrics/> <isis-wide-metrics/> </isis-level-information> </isis-overview> </pre>
Description	IS-IS Level Information.
Contents	<p><isis-external-preference>—IS-IS external route preference.</p> <p><isis-level>—IS-IS Level.</p> <p><isis-narrow-metrics>—Generation of narrow metric TLVs is enabled.</p> <p><isis-preference>—IS-IS internal route preference.</p> <p><isis-prefix-export-limit>—IS-IS limit for external route export.</p> <p><isis-wide-metrics>—Generation of wide metric TLVs is enabled.</p>

<isis-lsp-authentication>

Usage	<pre> <isis-authentication-information> <isis-lsp-authentication> <level>level</level> <isis-level-lsp-authentication>isis-level-lsp-authentication </isis-level-lsp-authentication> </isis-lsp-authentication> </isis-authentication-information> </pre>
Description	Authentication type for LSP packets.
Contents	<p><isis-level-lsp-authentication>—Authentication type for LSP packets.</p> <p><level>—No documentation is available yet.</p>

<isis-neighbor>

Usage	<pre> <isis-database-entry> <isis-neighbor> <isis-topology-id>isis-topology-id</isis-topology-id> <is-neighbor-id>is-neighbor-id</is-neighbor-id> <metric>metric</metric> <reachability-delay/> <reachability-expense/> <reachability-error/> </isis-neighbor> </isis-database-entry> </pre>
Description	No documentation is available yet.
Contents	<p><is-neighbor-id>—No documentation is available yet.</p> <p><isis-topology-id>—No documentation is available yet.</p> <p><metric>—No documentation is available yet.</p> <p><reachability-delay>—No documentation is available yet.</p> <p><reachability-error>—No documentation is available yet.</p> <p><reachability-expense>—No documentation is available yet.</p>

<isis-overload-information>

Usage	<pre> <isis-overview> <isis-overload-information> <isis-overload-enabled/> <isis-overload-high-metrics>isis-overload-high-metrics </isis-overload-high-metrics> <isis-overload-timeout>isis-overload-timeout</isis-overload-timeout> <isis-overload-remaining-time>isis-overload-remaining-time </isis-overload-remaining-time> </isis-overload-information> </isis-overview> </pre>
Description	Overload bit behaviour at startup.
Contents	<p><isis-overload-enabled>—Overload bit upon startup is set.</p> <p><isis-overload-high-metrics>—High metrics are used for Overload signaling.</p> <p><isis-overload-remaining-time>—Time remaining on configured overload timeout.</p> <p><isis-overload-timeout>—Clearance of the Overload bit after startup.</p>

<isis-overview>

Usage <isis-overview-information>
<isis-overview>
 <instance-name>*instance-name*</instance-name>
 <isis-router-id>*isis-router-id*</isis-router-id>
 <isis-max-areas>*isis-max-areas*</isis-max-areas>
 <isis-lsp-lifetime>*isis-lsp-lifetime*</isis-lsp-lifetime>
 <isis-reference-bandwidth>*isis-reference-bandwidth*</isis-reference-bandwidth>
 <isis-adjacency-holddown>*isis-adjacency-holddown*</isis-adjacency-holddown>
 <isis-attached-bit-evaluation>*isis-attached-bit-evaluation*
 </isis-attached-bit-evaluation>
 <isis-spf-information>...</isis-spf-information>
 <isis-overload-information>...</isis-overload-information>
 <isis-routing>...</isis-routing>
 <isis-traffic-engineering>...</isis-traffic-engineering>
 <isis-restart>...</isis-restart>
 <isis-level-information>...</isis-level-information>
</isis-overview>
 </isis-overview-information>

Description Overview information for an IS-IS instance.

Contents <instance-name>—No documentation is available yet.

<isis-adjacency-holddown>—IS-IS Adjacency holddown status.

<isis-attached-bit-evaluation>—The IS-IS L1 attached bit evaluation.

<isis-level-information>—IS-IS Level Information.

<isis-lsp-lifetime>—Maximum LSP lifetime.

<isis-max-areas>—Maximum Number of Areas.

<isis-overload-information>—Overload bit behaviour at startup.

<isis-reference-bandwidth>—Bandwidth for calculating metric defaults.

<isis-restart>—IS-IS restart parameters.

<isis-router-id>—IS-IS router ID.

<isis-routing>—List of routed IS-IS address families.

<isis-spf-information>—SPF options.

<isis-traffic-engineering>—Traffic engineering.

<isis-overview-information>

Usage <rpc-reply>
 <isis-overview-information>
 <isis-overview>...</isis-overview>
 </isis-overview-information>
 </rpc-reply>

Description ISIS overview information.

Contents <isis-overview>—Overview information for an IS-IS instance.

<isis-packet>

Usage	<pre> <isis-database-entry> <isis-packet> <lsp-id>lsp-id</lsp-id> <pdu-length>pdu-length</pdu-length> <pdu-lifetime>pdu-lifetime</pdu-lifetime> <checksum>checksum</checksum> <sequence-number>sequence-number</sequence-number> <lsp-attributes>lsp-attributes</lsp-attributes> <nlp-id>nlp-id</nlp-id> <mtid>mtid</mtid> <lsp-length>lsp-length</lsp-length> <pdu-version>pdu-version</pdu-version> <system-id-length>system-id-length</system-id-length> <isis-packet-type>isis-packet-type</isis-packet-type> <packet-version>packet-version</packet-version> <maximum-area>maximum-area</maximum-area> </isis-packet> </isis-database-entry> </pre>
Description	No documentation is available yet.
Contents	<p><checksum>—No documentation is available yet.</p> <p><isis-packet-type>—No documentation is available yet.</p> <p><lsp-attributes>—No documentation is available yet.</p> <p><lsp-id>—LSP ID or source port for some sender. It is unique to every sender or LSP.</p> <p><lsp-length>—No documentation is available yet.</p> <p><maximum-area>—No documentation is available yet.</p> <p><mtid>—No documentation is available yet.</p> <p><nlp-id>—No documentation is available yet.</p> <p><packet-version>—No documentation is available yet.</p> <p><pdu-length>—No documentation is available yet.</p> <p><pdu-lifetime>—No documentation is available yet.</p> <p><pdu-version>—No documentation is available yet.</p> <p><sequence-number>—History event number.</p> <p><system-id-length>—No documentation is available yet.</p>

<isis-pdu-statistics>

Usage <isis-statistics>
 <isis-pdu-statistics>
 <isis-pdu-type>*isis-pdu-type*</isis-pdu-type>
 <packets-received>*packets-received*</packets-received>
 <packets-processed>*packets-processed*</packets-processed>
 <packets-dropped>*packets-dropped*</packets-dropped>
 <packets-sent>*packets-sent*</packets-sent>
 <packets-retransmitted>*packets-retransmitted*</packets-retransmitted>
 </isis-pdu-statistics>
 </isis-statistics>

Description No documentation is available yet.

Contents <isis-pdu-type>—No documentation is available yet.

<packets-dropped>—No documentation is available yet.

<packets-processed>—No documentation is available yet.

<packets-received>—No documentation is available yet.

<packets-retransmitted>—No documentation is available yet.

<packets-sent>—No documentation is available yet.

<isis-prefix>

Usage	<pre> <isis-database-entry> <isis-prefix> <protocol-name>protocol-name</protocol-name> <isis-topology-id>isis-topology-id</isis-topology-id> <address-prefix>address-prefix</address-prefix> <metric>metric</metric> <prefix-flag>prefix-flag</prefix-flag> <prefix-status>prefix-status</prefix-status> <reachability-delay/> <reachability-expense/> <reachability-error/> </isis-prefix> </isis-database-entry> </pre>
Description	No documentation is available yet.
Contents	<p><address-prefix>—No documentation is available yet.</p> <p><isis-topology-id>—No documentation is available yet.</p> <p><metric>—No documentation is available yet.</p> <p><prefix-flag>—No documentation is available yet.</p> <p><prefix-status>—No documentation is available yet.</p> <p><protocol-name>—No documentation is available yet.</p> <p><reachability-delay>—No documentation is available yet.</p> <p><reachability-error>—No documentation is available yet.</p> <p><reachability-expense>—No documentation is available yet.</p>

<isis-prefix-subtlv>

Usage	<pre> <isis-tlv ipv6-reachability-tlv ip-prefix-tlv> <isis-prefix-subtlv> <isis-prefix-tag>...</isis-prefix-tag> </isis-prefix-subtlv> </isis-tlv ipv6-reachability-tlv ip-prefix-tlv> </pre>
Description	No documentation is available yet.
Contents	<isis-prefix-tag>—No documentation is available yet.

<isis-prefix-tag>

Usage	<pre><isis-prefix-subtlv prefix-reachability> <isis-prefix-tag> <isis-prefix-tag-index>isis-prefix-tag-index</isis-prefix-tag-index> <isis-prefix-tag-value>isis-prefix-tag-value</isis-prefix-tag-value> </isis-prefix-tag> </isis-prefix-subtlv prefix-reachability></pre>
Description	No documentation is available yet.
Contents	<pre><isis-prefix-tag-index>—No documentation is available yet. <isis-prefix-tag-value>—No documentation is available yet.</pre>

<isis-reachability-subtlv>

Usage <reachability-tlv | isis-tlv>
<isis-reachability-subtlv>
 <isis-subtlv-type>isis-subtlv-type</isis-subtlv-type>
 <subtlv-length>subtlv-length</subtlv-length>
 <max-bandwidth>max-bandwidth</max-bandwidth>
 <max-reserve-bandwidth>max-reserve-bandwidth</max-reserve-bandwidth>
 <current-bandwidth-header/>
 <current-reserve-bandwidth>current-reserve-bandwidth
 </current-reserve-bandwidth>
 <admin-groups>...</admin-groups>
 <bandwidth-priority>bandwidth-priority</bandwidth-priority>
 <local-ifindex>local-ifindex</local-ifindex>
 <remote-ifindex>remote-ifindex</remote-ifindex>
 <address>address</address>
 <neighbor-prefix>neighbor-prefix</neighbor-prefix>
 <address-prefix>address-prefix</address-prefix>
 <prefix-err-message/>
 <te-metric>te-metric</te-metric>
 <dste-bc-header/>
 <dste-bc-model>dste-bc-model</dste-bc-model>
 <dste-bc-count>dste-bc-count</dste-bc-count>
 <dste-bc-bw>dste-bc-bw</dste-bc-bw>
</isis-reachability-subtlv>
 </reachability-tlv | isis-tlv>

Description No documentation is available yet.

Contents <address>—No documentation is available yet.

<address-prefix>—No documentation is available yet.

<admin-groups>—No documentation is available yet.

<bandwidth-priority>—No documentation is available yet.

<current-bandwidth-header>—No documentation is available yet.

<current-reserve-bandwidth>—No documentation is available yet.

<dste-bc-bw>—DiffServ TE bandwidth constraint BW.

<dste-bc-count>—DiffServ TE bandwidth constraint count.

<dste-bc-header>—No documentation is available yet.

<dste-bc-model>—DiffServ TE bandwidth constraint model.

<isis-subtlv-type>—No documentation is available yet.

<local-ifindex>—Local interface index.

<max-bandwidth>—No documentation is available yet.

<max-reserve-bandwidth>—No documentation is available yet.

<neighbor-prefix>—No documentation is available yet.

<prefix-err-message>—No documentation is available yet.

<remote-ifindex>—Remote interface index.

<subtlv-length>—No documentation is available yet.

<te-metric>—No documentation is available yet.

<isis-replication-adjacency>

Usage <isis-replication-adjacency-information>
 <isis-replication-adjacency>
 <interface-name>*interface-name*</interface-name>
 <system-name>*system-name*</system-name>
 <level>*level*</level>
 <adjacency-state>*adjacency-state*</adjacency-state>
 <snpa>*snpa*</snpa>
 <instance-name>*instance-name*</instance-name>
 <interface-index>*interface-index*</interface-index>
 <reference-count>*reference-count*</reference-count>
 <transition-count>*transition-count*</transition-count>
 <last-transition-time>*last-transition-time*</last-transition-time>
 <adjacency-event>*adjacency-event*</adjacency-event>
 </isis-replication-adjacency>
 </isis-replication-adjacency-information>

Description No documentation is available yet.

Contents <adjacency-event>—Event which triggered the transition.

<adjacency-state>—State of the adjacency.

<instance-name>—No documentation is available yet.

<interface-index>—No documentation is available yet.

<interface-name>—No documentation is available yet.

<last-transition-time>—No documentation is available yet.

<level>—No documentation is available yet.

<reference-count>—No documentation is available yet.

<snpa>—No documentation is available yet.

<system-name>—Hostname for a system.

<transition-count>—No documentation is available yet.

<isis-replication-adjacency-information>

Usage <rpc-reply>
 <isis-replication-adjacency-information>
 <isis-replication-adjacency>...</isis-replication-adjacency>
 </isis-replication-adjacency-information>
 </rpc-reply>

Description Information about the IS-IS adjacency replication.

Contents <isis-replication-adjacency>—No documentation is available yet.

<isis-replication-database>

Usage <isis-replication-database-information>
 <isis-replication-database>
 <instance-name>*instance-name*</instance-name>
 <level>*level*</level>
 <isis-replication-database-entry>...</isis-replication-database-entry>
 <isis-replication-database-entry-count>*isis-replication-database-entry-count*
 </isis-replication-database-entry-count>
 </isis-replication-database>
 </isis-replication-database-information>

Description No documentation is available yet.

Contents <instance-name>—No documentation is available yet.

<isis-replication-database-entry>—No documentation is available yet.

<isis-replication-database-entry-count>—No documentation is available yet.

<level>—No documentation is available yet.

<isis-replication-database-entry>

Usage <isis-replication-database>
 <isis-replication-database-entry>
 <lsp-id>*lsp-id*</lsp-id>
 <sequence-number>*sequence-number*</sequence-number>
 <checksum>*checksum*</checksum>
 <remaining-lifetime>*remaining-lifetime*</remaining-lifetime>
 <replication-entry-in-use>*replication-entry-in-use*</replication-entry-in-use>
 </isis-replication-database-entry>
 </isis-replication-database>

Description No documentation is available yet.

Contents <checksum>—No documentation is available yet.

<lsp-id>—LSP ID or source port for some sender. It is unique to every sender or LSP.

<remaining-lifetime>—No documentation is available yet.

<replication-entry-in-use>—No documentation is available yet.

<sequence-number>—History event number.

<isis-replication-database-information>

Usage <rpc-reply>
 <isis-replication-database-information>
 <isis-replication-database>...</isis-replication-database>
 </isis-replication-database-information>
 </rpc-reply>

Description Information about the IS-IS link-state database replication.

Contents <isis-replication-database>—No documentation is available yet.

<isis-replication-interface>

Usage <isis-replication-interface-information>
 <isis-replication-interface>
 <interface-name>*interface-name*</interface-name>
 <instance-name>*instance-name*</instance-name>
 <circuit-id>*circuit-id*</circuit-id>
 <dr-id-one>*dr-id-one*</dr-id-one>
 <dr-id-two>*dr-id-two*</dr-id-two>
 <isis-interface-state-one>*isis-interface-state-one*</isis-interface-state-one>
 <isis-interface-state-two>*isis-interface-state-two*</isis-interface-state-two>
 <replication-entry-in-use>*replication-entry-in-use*</replication-entry-in-use>
 </isis-replication-interface>
 </isis-replication-interface-information>

Description Information about the IS-IS interface replication.

Contents <circuit-id>—No documentation is available yet.
 <dr-id-one>—No documentation is available yet.
 <dr-id-two>—No documentation is available yet.
 <instance-name>—No documentation is available yet.
 <interface-name>—No documentation is available yet.
 <isis-interface-state-one>—No documentation is available yet.
 <isis-interface-state-two>—No documentation is available yet.
 <replication-entry-in-use>—No documentation is available yet.

<isis-replication-interface-information>

Usage <rpc-reply>
 <isis-replication-interface-information>
 <isis-replication-interface>...</isis-replication-interface>
 </isis-replication-interface-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <isis-replication-interface>—Information about the IS-IS interface replication.

<isis-replication-statistics>

Usage	<pre> <isis-replication-statistics-information> <isis-replication-statistics> <isis-replication-type>isis-replication-type</isis-replication-type> <add-messages>add-messages</add-messages> <change-messages>change-messages</change-messages> <delete-messages>delete-messages</delete-messages> </isis-replication-statistics> </isis-replication-statistics-information> </pre>
Description	Statistics from an IS-IS replication.
Contents	<p><add-messages>—Count of replication add operations.</p> <p><change-messages>—Count of replication change operations.</p> <p><delete-messages>—Count of replication delete operations.</p> <p><isis-replication-type>—Type of replication.</p>

<isis-replication-statistics-information>

Usage	<pre> <rpc-reply> <isis-replication-statistics-information> <isis-replication-statistics>...</isis-replication-statistics> </isis-replication-statistics-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<isis-replication-statistics>—Statistics from an IS-IS replication.

<isis-replication-system-id>

Usage	<pre> <isis-replication-system-id-information> <isis-replication-system-id> <instance-name>instance-name</instance-name> <system-id>system-id</system-id> <replication-entry-in-use>replication-entry-in-use</replication-entry-in-use> </isis-replication-system-id> </isis-replication-system-id-information> </pre>
Description	Information about the IS-IS system ID replication.
Contents	<p><instance-name>—No documentation is available yet.</p> <p><replication-entry-in-use>—No documentation is available yet.</p> <p><system-id>—Six-octet ISO system ID for a system.</p>

<isis-replication-system-id-information>

- Usage** <rpc-reply>
 <isis-replication-system-id-information>
 <isis-replication-system-id>...</isis-replication-system-id>
 </isis-replication-system-id-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <isis-replication-system-id>—Information about the IS-IS system ID replication.

<isis-restart>

- Usage** <isis-overview>
 <isis-restart>
 <isis-restart-enabled>*isis-restart-enabled*</isis-restart-enabled>
 <isis-restart-duration>*isis-restart-duration*</isis-restart-duration>
 <isis-restart-helper-mode-enabled>*isis-restart-helper-mode-enabled*
 </isis-restart-helper-mode-enabled>
 </isis-restart>
 </isis-overview>
- Description** IS-IS restart parameters.
- Contents** <isis-restart-duration>—Duration of IS-IS restart.
- <isis-restart-enabled>—IS-IS restart mode.
- <isis-restart-helper-mode-enabled>—IS-IS helper mode.

<isis-route>

Usage <isis-routing-table>
 <isis-route>
 <address-prefix>*address-prefix*</address-prefix>
 <level>*level*</level>
 <route-version>*route-version*</route-version>
 <metric>*metric*</metric>
 <metric-type>*metric-type*</metric-type>
 <interface-name>*interface-name*</interface-name>
 <isis-next-hop>*isis-next-hop*</isis-next-hop>
 <isis-next-hop-snpa>*isis-next-hop-snpa*</isis-next-hop-snpa>
 </isis-route>
 </isis-routing-table>

Description No documentation is available yet.

Contents <address-prefix>—No documentation is available yet.
 <interface-name>—No documentation is available yet.
 <isis-next-hop>—No documentation is available yet.
 <isis-next-hop-snpa>—No documentation is available yet.
 <level>—No documentation is available yet.
 <metric>—No documentation is available yet.
 <metric-type>—No documentation is available yet.
 <route-version>—No documentation is available yet.

<isis-route-information>

Usage <rpc-reply>
 <isis-route-information>
 <isis-routing-table>...</isis-routing-table>
 </isis-route-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <isis-routing-table>—No documentation is available yet.

<isis-routing>

Usage	<pre> <isis-overview> <isis-routing> <isis-routing-ipv4/> <isis-routing-ipv6/> <isis-routing-clns/> </isis-routing> </isis-overview> </pre>
Description	List of routed IS-IS address families.
Contents	<pre> <isis-routing-clns>—Routing CLNS prefixes is enabled. <isis-routing-ipv4>—Routing IPv4 prefixes is enabled. <isis-routing-ipv6>—Routing IPv6 prefixes is enabled. </pre>

<isis-routing-table>

Usage	<pre> <isis-route-information> <isis-routing-table> <isis-topology-id>isis-topology-id</isis-topology-id> <level-one-version>level-one-version</level-one-version> <level-two-version>level-two-version</level-two-version> <isis-route>...</isis-route> </isis-routing-table> </isis-route-information> </pre>
Description	No documentation is available yet.
Contents	<pre> <isis-route>—No documentation is available yet. <isis-topology-id>—No documentation is available yet. <level-one-version>—No documentation is available yet. <level-two-version>—No documentation is available yet. </pre>

<isis-spf>

Usage	<pre> <isis-spf-information> <isis-spf> <isis-spf-results-header>...</isis-spf-results-header> <isis-spf-result>...</isis-spf-result> <node-count><i>node-count</i></node-count> <isis-spf-log-header>...</isis-spf-log-header> <isis-spf-log>...</isis-spf-log> </isis-spf> </isis-spf-information> </pre>
Description	No documentation is available yet.
Contents	<p><isis-spf-log>—No documentation is available yet.</p> <p><isis-spf-log-header>—No documentation is available yet.</p> <p><isis-spf-result>—No documentation is available yet.</p> <p><isis-spf-results-header>—No documentation is available yet.</p> <p><node-count>—No documentation is available yet.</p>

<isis-spf-information>

Usage	<pre> <isis-overview> <isis-spf-information> <isis-spf-delay><i>isis-spf-delay</i></isis-spf-delay> <isis-spf-holddown><i>isis-spf-holddown</i></isis-spf-holddown> <isis-spf-rapid-runs><i>isis-spf-rapid-runs</i></isis-spf-rapid-runs> <isis-spf>...</isis-spf> </isis-spf-information> </isis-overview> </pre>
Description	SPF options.
Contents	<p><isis-spf>—No documentation is available yet.</p> <p><isis-spf-delay>—Delay before performing SPF calculations.</p> <p><isis-spf-holddown>—Throttling delay between consecutive SPF calculations.</p> <p><isis-spf-rapid-runs>—Number of rapid SPF calculations before SPF holddown.</p>

<isis-spf-log>

Usage <isis-spf>
 <isis-spf-log>
 <start-time>*start-time*</start-time>
 <elapsed-time>*elapsed-time*</elapsed-time>
 <spf-trigger-count>*spf-trigger-count*</spf-trigger-count>
 <logging-reason>*logging-reason*</logging-reason>
 <lsp-name>*lsp-name*</lsp-name>
 <system-name>*system-name*</system-name>
 <interface-name>*interface-name*</interface-name>
 </isis-spf-log>
 </isis-spf>

Description No documentation is available yet.

Contents <elapsed-time>—Time this adjacency or session has been up or down.
 <interface-name>—No documentation is available yet.
 <logging-reason>—No documentation is available yet.
 <lsp-name>—Tunneled into an RSVP LSP.
 <spf-trigger-count>—No documentation is available yet.
 <start-time>—No documentation is available yet.
 <system-name>—Hostname for a system.

<isis-spf-log-header>

Usage <isis-spf>
 <isis-spf-log-header>
 <level>*level*</level>
 <isis-topology-id>*isis-topology-id*</isis-topology-id>
 </isis-spf-log-header>
 </isis-spf>

Description No documentation is available yet.

Contents <isis-topology-id>—No documentation is available yet.
 <level>—No documentation is available yet.

<isis-spf-result>

Usage <isis-spf>
 <isis-spf-result>
 <node-id>*node-id*</node-id>
 <disconnected/>
 <metric>*metric*</metric>
 <no-first-fragment/>
 <next-hop-element>...</next-hop-element>
 <prefix-element>...</prefix-element>
 <end-system-element>...</end-system-element>
 </isis-spf-result>
 </isis-spf>

Description No documentation is available yet.

Contents <disconnected>—No documentation is available yet.
 <end-system-element>—No documentation is available yet.
 <metric>—No documentation is available yet.
 <next-hop-element>—No documentation is available yet.
 <no-first-fragment>—No documentation is available yet.
 <node-id>—No documentation is available yet.
 <prefix-element>—No documentation is available yet.

<isis-spf-results-header>

Usage <isis-spf>
 <isis-spf-results-header>
 <level>*level*</level>
 <isis-topology-id>*isis-topology-id*</isis-topology-id>
 </isis-spf-results-header>
 </isis-spf>

Description No documentation is available yet.

Contents <isis-topology-id>—No documentation is available yet.
 <level>—No documentation is available yet.

<isis-statistics>

Usage	<pre> <isis-statistics-information> <isis-statistics> <system-name>system-name</system-name> <isis-pdu-statistics>...</isis-pdu-statistics> <totals-information>...</totals-information> <snp-queue-length>snp-queue-length</snp-queue-length> <snp-queue-drops>snp-queue-drops</snp-queue-drops> <lsp-queue-length>lsp-queue-length</lsp-queue-length> <lsp-queue-drops>lsp-queue-drops</lsp-queue-drops> <spf-runs>spf-runs</spf-runs> <fragments-rebuilt>fragments-rebuilt</fragments-rebuilt> <lsp-regenerated>lsp-regenerated</lsp-regenerated> <purges-initiated>purges-initiated</purges-initiated> </isis-statistics> </isis-statistics-information> </pre>
Description	No documentation is available yet.
Contents	<p><fragments-rebuilt>—No documentation is available yet.</p> <p><isis-pdu-statistics>—No documentation is available yet.</p> <p><lsp-queue-drops>—No documentation is available yet.</p> <p><lsp-queue-length>—No documentation is available yet.</p> <p><lsp-regenerated>—No documentation is available yet.</p> <p><purges-initiated>—No documentation is available yet.</p> <p><snp-queue-drops>—No documentation is available yet.</p> <p><snp-queue-length>—No documentation is available yet.</p> <p><spf-runs>—No documentation is available yet.</p> <p><system-name>—Hostname for a system.</p> <p><totals-information>—No documentation is available yet.</p>

<isis-statistics-information>

Usage	<pre> <rpc-reply> <isis-statistics-information> <isis-statistics>...</isis-statistics> </isis-statistics-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<isis-statistics>—No documentation is available yet.

<isis-tlv>

Usage <isis-database-entry>
 <isis-tlv>
 <isis-tlv-overhead>...</isis-tlv-overhead>
 <area-address-tlv>...</area-address-tlv>
 <protocols-tlv>...</protocols-tlv>
 <mt-tlv>...</mt-tlv>
 <hostname-tlv>...</hostname-tlv>
 <ipaddress-tlv>...</ipaddress-tlv>
 <ipv6address-tlv>...</ipv6address-tlv>
 <router-id-tlv>...</router-id-tlv>
 <reachability-tlv>...</reachability-tlv>
 <isis-iso-prefix-tlv>...</isis-iso-prefix-tlv>
 <isis-prefix-subtlv>...</isis-prefix-subtlv>
 <ipv6-reachability-tlv>...</ipv6-reachability-tlv>
 <isis-reachability-subtlv>...</isis-reachability-subtlv>
 <authentication-tlv>...</authentication-tlv>
 <idrp-tlv>...</idrp-tlv>
 <ip-prefix-tlv>...</ip-prefix-tlv>
 <unknown-tlv>...</unknown-tlv>
 <tlv-stragglers>...</tlv-stragglers>
 </isis-tlv>
 </isis-database-entry>

Description No documentation is available yet.

Contents <area-address-tlv>—No documentation is available yet.
 <authentication-tlv>—No documentation is available yet.
 <hostname-tlv>—No documentation is available yet.
 <idrp-tlv>—No documentation is available yet.
 <ip-prefix-tlv>—No documentation is available yet.
 <ipaddress-tlv>—No documentation is available yet.
 <ipv6-reachability-tlv>—No documentation is available yet.
 <ipv6address-tlv>—No documentation is available yet.
 <isis-iso-prefix-tlv>—No documentation is available yet.
 <isis-prefix-subtlv>—No documentation is available yet.
 <isis-reachability-subtlv>—No documentation is available yet.
 <isis-tlv-overhead>—No documentation is available yet.
 <mt-tlv>—No documentation is available yet.
 <protocols-tlv>—No documentation is available yet.

<reachability-tlv>—No documentation is available yet.

<router-id-tlv>—No documentation is available yet.

<tlv-stragglers>—No documentation is available yet.

<unknown-tlv>—No documentation is available yet.

<isis-tlv-overhead>

Usage	<pre> <isis-tlv> <isis-tlv-overhead> <isis-tlv-type>isis-tlv-type</isis-tlv-type> <tlv-length>tlv-length</tlv-length> <bytes-left>bytes-left</bytes-left> </isis-tlv-overhead> </isis-tlv> </pre>
Description	No documentation is available yet.
Contents	<p><bytes-left>—No documentation is available yet.</p> <p><isis-tlv-type>—No documentation is available yet.</p> <p><tlv-length>—No documentation is available yet.</p>

<isis-traffic-engineering>

Usage	<pre> <isis-overview> <isis-traffic-engineering> <isis-te-status>isis-te-status</isis-te-status> <isis-te-shortcuts-ipv4/> <isis-te-shortcuts-ipv6/> <isis-te-shortcuts-clns/> <isis-ipv4-multicast-rpf-routes/> <isis-ignore-lsp-metrics/> </isis-traffic-engineering> </isis-overview> </pre>
Description	Traffic engineering.
Contents	<p><isis-ignore-lsp-metrics>—Label-switched path metrics when doing shortcuts are ignored.</p> <p><isis-ipv4-multicast-rpf-routes>—IPv4 routes for multicast RPF checks are installed into inet.2.</p> <p><isis-te-shortcuts-clns>—CLNS Traffic engineering shortcuts are enabled.</p> <p><isis-te-shortcuts-ipv4>—IPv4 Traffic engineering shortcuts are enabled.</p> <p><isis-te-shortcuts-ipv6>—IPv6 Traffic engineering shortcuts are enabled.</p> <p><isis-te-status>—Traffic engineering status.</p>

<join-family>

Usage <pim-join-information>
 <join-family>
 <pim-instance>*pim-instance*</pim-instance>
 <address-family>*address-family*</address-family>
 <join-group>...</join-group>
 </join-family>
 </pim-join-information>

Description No documentation is available yet.

Contents <address-family>—No documentation is available yet.

 <join-group>—No documentation is available yet.

 <pim-instance>—Name of the PIM instance.

<join-group>

Usage <join-family>
 <join-group>
 <multicast-group-address>*multicast-group-address*</multicast-group-address>
 <multicast-source-address>*multicast-source-address*</multicast-source-address>
 <rendezvous-point-address>*rendezvous-point-address*</rendezvous-point-address>
 <pim-group-flags>...</pim-group-flags>
 <upstream-protocol-name>*upstream-protocol-name*</upstream-protocol-name>
 <upstream-interface-name>*upstream-interface-name*</upstream-interface-name>
 <pim-interface-state>*pim-interface-state*</pim-interface-state>
 <upstream-neighbor>*upstream-neighbor*</upstream-neighbor>
 <upstream-neighbor-rpf-origin>*upstream-neighbor-rpf-origin*
 </upstream-neighbor-rpf-origin>
 <dense-event>...</dense-event>
 <downstream-interface>...</downstream-interface>
 <upstream-state-flags>...</upstream-state-flags>
 <keepalive-timeout>*keepalive-timeout*</keepalive-timeout>
 <no-keepalive-timeout/>
 <sparse-downstream-interface>...</sparse-downstream-interface>
 </join-group>
 </join-family>

Description No documentation is available yet.

Contents <dense-event>—No documentation is available yet.

<downstream-interface>—No documentation is available yet.

<keepalive-timeout>—No documentation is available yet.

<multicast-group-address>—Group address.

<multicast-source-address>—Source address.

<no-keepalive-timeout>—No documentation is available yet.

<pim-group-flags>—No documentation is available yet.

<pim-interface-state>—State of PIM interface.

<rendezvous-point-address>—Address of rendezvous point.

<sparse-downstream-interface>—No documentation is available yet.

<upstream-interface-name>—Upstream interface.

<upstream-neighbor>—No documentation is available yet.

<upstream-neighbor-rpf-origin>—Reverse-path forwarding origin of upstream neighbor.

<upstream-protocol-name>—Upstream protocol.

<upstream-state-flags>—No documentation is available yet.

<juniper-routing-aspash>

- Usage** <rpc-reply>
 <juniper-routing-aspash>
 <aspash-domain>...</aspash-domain>
 <aspash-table>...</aspash-table>
 </juniper-routing-aspash>
 </rpc-reply>
- Description** Operational and configuration information for AS paths.
- Contents** <aspash-domain>—No documentation is available yet.
 <aspash-table>—No documentation is available yet.

<l2circuit-connection-information>

- Usage** <rpc-reply>
 <l2circuit-connection-information>
 <l2circuit-neighbor>...</l2circuit-neighbor>
 </l2circuit-connection-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <l2circuit-neighbor>—No documentation is available yet.

<l2circuit-neighbor>

- Usage** <l2circuit-connection-information>
 <l2circuit-neighbor>
 <neighbor-address>*neighbor-address*</neighbor-address>
 <neighbor-display-error>*neighbor-display-error*</neighbor-display-error>
 <lsw-interface-name>*lsw-interface-name*</lsw-interface-name>
 <connection>...</connection>
 <connections-summary>...</connections-summary>
 </l2circuit-neighbor>
 </l2circuit-connection-information>
- Description** No documentation is available yet.
- Contents** <connection>—No documentation is available yet.
 <connections-summary>—No documentation is available yet.
 <lsw-interface-name>—No documentation is available yet.
 <neighbor-address>—IP address of this neighbor.
 <neighbor-display-error>—No documentation is available yet.

<l2ckt-label-repository>

- Usage** <l2ckt-label-repository-information>
 <l2ckt-label-repository>
 <neighbor-id>*neighbor-id*</neighbor-id>
 <vc-id>*vc-id*</vc-id>
 <vc-label>*vc-label*</vc-label>
 <label-repository-state>*label-repository-state*</label-repository-state>
 </l2ckt-label-repository>
 </l2ckt-label-repository-information>
- Description** Information about one or more Layer-2 circuit label replication entries.
- Contents** <label-repository-state>—State of label replication entry.
- <neighbor-id>—No documentation is available yet.
- <vc-id>—No documentation is available yet.
- <vc-label>—VC label.

<l2ckt-label-repository-information>

- Usage** <rpc-reply>
 <l2ckt-label-repository-information>
 <l2ckt-label-repository>...</l2ckt-label-repository>
 </l2ckt-label-repository-information>
 </rpc-reply>
- Description** Information about the Layer-2 circuit label replication.
- Contents** <l2ckt-label-repository>—Information about one or more Layer-2 circuit label replication entries.

<l2iw-domain>

- Usage** <l2iw-peering-information>
 <l2iw-domain>
 <l2iw-domain-name>*l2iw-domain-name*</l2iw-domain-name>
 </l2iw-domain>
 </l2iw-peering-information>
- Description** No documentation is available yet.
- Contents** <l2iw-domain-name>—Name of peering domain.

<l2iw-peering-information>

Usage <rpc-reply>
 <l2iw-peering-information>
 <l2iw-domain>...</l2iw-domain>
 </l2iw-peering-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <l2iw-domain>—No documentation is available yet.

<l2vpn-connection-information>

Usage <rpc-reply>
 <l2vpn-connection-information>
 <instance>...</instance>
 </l2vpn-connection-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <instance>—No documentation is available yet.

<l2vpn-label-repository-information>

Usage <rpc-reply>
 <l2vpn-label-repository-information>
 <l2vpn-route-distinguisher-information>...
 </l2vpn-route-distinguisher-information>
 </l2vpn-label-repository-information>
 </rpc-reply>

Description Information about Layer 2 VPN network label replication.

Contents <l2vpn-route-distinguisher-information>—Information about a route distinguisher replication entry.

<l2vpn-labels>

Usage <l2vpn-labels-information>
 <l2vpn-labels>
 <instance-id>*instance-id*</instance-id>
 <site-id>*site-id*</site-id>
 <label-block-offset>*label-block-offset*</label-block-offset>
 <label-block-base>*label-block-base*</label-block-base>
 <label-block-range>*label-block-range*</label-block-range>
 </l2vpn-labels>
 </l2vpn-labels-information>

Description Information about a Layer 2 VPN allocated label block entry.

Contents <instance-id>—Routing instance identifier.

<label-block-base>—No documentation is available yet.

<label-block-offset>—No documentation is available yet.

<label-block-range>—No documentation is available yet.

<site-id>—Site identifier.

<l2vpn-labels-information>

Usage <rpc-reply>
 <l2vpn-labels-information>
 <l2vpn-labels>...</l2vpn-labels>
 </l2vpn-labels-information>
 </rpc-reply>

Description Information about the l2vpn allocated label blocks.

Contents <l2vpn-labels>—Information about a Layer 2 VPN allocated label block entry.

<l2vpn-nlri-advertisement>

Usage	<pre> <l2vpn-route-distinguisher-information vpls-bgp-route-distinguisher-information> <l2vpn-nlri-advertisement> <site-id>site-id</site-id> <label-block-offset>label-block-offset</label-block-offset> <label-block-base>label-block-base</label-block-base> <label-block-range>label-block-range</label-block-range> <label-repository-state>label-repository-state</label-repository-state> </l2vpn-nlri-advertisement> </l2vpn-route-distinguisher-information vpls-bgp-route-distinguisher-information> </pre>
Description	Information about a Layer 2 VPN network layer reachability information replication entry.
Contents	<p><label-block-base>—No documentation is available yet.</p> <p><label-block-offset>—No documentation is available yet.</p> <p><label-block-range>—No documentation is available yet.</p> <p><label-repository-state>—State of label replication entry.</p> <p><site-id>—Site identifier.</p>

<l2vpn-route-distinguisher-information>

Usage	<pre> <l2vpn-label-repository-information> <l2vpn-route-distinguisher-information> <route-distinguisher>route-distinguisher</route-distinguisher> <instance-id>instance-id</instance-id> <l2vpn-nlri-advertisement>...</l2vpn-nlri-advertisement> </l2vpn-route-distinguisher-information> </l2vpn-label-repository-information> </pre>
Description	Information about a route distinguisher replication entry.
Contents	<p><instance-id>—Routing instance identifier.</p> <p><l2vpn-nlri-advertisement>—Information about a Layer 2 VPN network layer reachability information replication entry.</p> <p><route-distinguisher>—No documentation is available yet.</p>

<label-block>

Usage	<pre> <reference-site> <label-block> <label-block-base>label-block-base</label-block-base> <label-block-offset>label-block-offset</label-block-offset> <label-block-range>label-block-range</label-block-range> <label-block-preference>label-block-preference</label-block-preference> <label-block-status-vector>label-block-status-vector </label-block-status-vector> </label-block> </reference-site> </pre>
Description	No documentation is available yet.
Contents	<p><label-block-base>—No documentation is available yet.</p> <p><label-block-offset>—No documentation is available yet.</p> <p><label-block-preference>—No documentation is available yet.</p> <p><label-block-range>—No documentation is available yet.</p> <p><label-block-status-vector>—No documentation is available yet.</p>

<layer2-connection>

Usage	<pre> <mpls-lsp-path> <layer2-connection> <neighbor-address>neighbor-address</neighbor-address> <interface-name>interface-name</interface-name> <vc-id>vc-id</vc-id> <connection-bandwidth>...</connection-bandwidth> </layer2-connection> </mpls-lsp-path> </pre>
Description	Layer 2 connection using the LSP path.
Contents	<p><connection-bandwidth>—Bandwidth of a layer 2 connection.</p> <p><interface-name>—No documentation is available yet.</p> <p><neighbor-address>—IP address of this neighbor.</p> <p><vc-id>—No documentation is available yet.</p>

<layer2-tspec>

Usage <rsvp-session>
 <layer2-tspec>
 <switching-granularity>*switching-granularity*</switching-granularity>
 <mtu>*mtu*</mtu>
 <atm-vp-bundle-size>*atm-vp-bundle-size*</atm-vp-bundle-size>
 <atm-cell-bundle-size>*atm-cell-bundle-size*</atm-cell-bundle-size>
 </layer2-tspec>
 </rsvp-session>

Description Layer 2 TSpec.

Contents <atm-cell-bundle-size>—Maximum cell bundle size.

 <atm-vp-bundle-size>—VP bundle size.

 <mtu>—MTU along an interface.

 <switching-granularity>—Layer 2 switching granularity.

<ldp-binding>

Usage <ldp-database>
 <ldp-binding>
 <ldp-label>*ldp-label*</ldp-label>
 <ldp-prefix>*ldp-prefix*</ldp-prefix>
 <ldp-binding-filtered/>
 <ldp-binding-stale/>
 <ldp-binding-mtu>*ldp-binding-mtu*</ldp-binding-mtu>
 <ldp-binding-cell-bundle-size>*ldp-binding-cell-bundle-size*
 </ldp-binding-cell-bundle-size>
 <ldp-binding-requested-vlan-id>*ldp-binding-requested-vlan-id*
 </ldp-binding-requested-vlan-id>
 <ldp-binding-bitrate>*ldp-binding-bitrate*</ldp-binding-bitrate>
 <ldp-binding-payload-size>*ldp-binding-payload-size*</ldp-binding-payload-size>
 <ldp-binding-state>*ldp-binding-state*</ldp-binding-state>
 <ldp-binding-age>*ldp-binding-age*</ldp-binding-age>
 <ldp-binding-delete-scheduled>*ldp-binding-delete-scheduled*
 </ldp-binding-delete-scheduled>
 <ldp-binding-queued/>
 <ldp-binding-not-yet-sent/>
 <ldp-binding-standby>...</ldp-binding-standby>
 <ldp-l2circuit-ccv-cc-type>...</ldp-l2circuit-ccv-cc-type>
 <ldp-l2circuit-ccv-cv-type>...</ldp-l2circuit-ccv-cv-type>
 </ldp-binding>
 </ldp-database>

Description No documentation is available yet.

Contents <ldp-binding-age>—No documentation is available yet.

<ldp-binding-bitrate>—No documentation is available yet.

<ldp-binding-cell-bundle-size>—No documentation is available yet.

<ldp-binding-delete-scheduled>—No documentation is available yet.

<ldp-binding-filtered>—No documentation is available yet.

<ldp-binding-mtu>—No documentation is available yet.

<ldp-binding-not-yet-sent>—No documentation is available yet.

<ldp-binding-payload-size>—No documentation is available yet.

<ldp-binding-queued>—No documentation is available yet.

<ldp-binding-requested-vlan-id>—No documentation is available yet.

<ldp-binding-stale>—No documentation is available yet.

<ldp-binding-standby>—Standby binding information.

<ldp-binding-state>—No documentation is available yet.

<ldp-l2circuit-vcv-cc-type>—VCCV connectivity channel types supported by peer.

<ldp-l2circuit-vcv-cv-type>—VCCV connectivity verification types supported by peer.

<ldp-label>—No documentation is available yet.

<ldp-prefix>—No documentation is available yet.

<ldp-binding-standby>

Usage <ldp-binding>
 <ldp-binding-standby>
 <ldp-binding-standby-map-count>*ldp-binding-standby-map-count*
 </ldp-binding-standby-map-count>
 <ldp-binding-standby-rel-count>*ldp-binding-standby-rel-count*
 </ldp-binding-standby-rel-count>
 </ldp-binding-standby>
 </ldp-binding>

Description Standby binding information.

Contents <ldp-binding-standby-map-count>—Count of outstanding map messages received.
 <ldp-binding-standby-rel-count>—Count of outstanding release messages received.

<ldp-database>

Usage <ldp-database-information>
 <ldp-database>
 <ldp-database-type>*ldp-database-type*</ldp-database-type>
 <ldp-session-id>*ldp-session-id*</ldp-session-id>
 <ldp-binding>...</ldp-binding>
 </ldp-database>
 </ldp-database-information>

Description No documentation is available yet.

Contents <ldp-binding>—No documentation is available yet.
 <ldp-database-type>—No documentation is available yet.
 <ldp-session-id>—No documentation is available yet.

<ldp-database-information>

Usage <rpc-reply>
 <ldp-database-information>
 <ldp-database>...</ldp-database>
 </ldp-database-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <ldp-database>—No documentation is available yet.

<ldp-event-statistics>

- Usage** <ldp-statistics>
 <ldp-event-statistics>
 <ldp-event-type>*ldp-event-type*</ldp-event-type>
 <ldp-event-count>*ldp-event-count*</ldp-event-count>
 <ldp-event-count-5seconds>*ldp-event-count-5seconds*</ldp-event-count-5seconds>
 </ldp-event-statistics>
 </ldp-statistics>
- Description** No documentation is available yet.
- Contents** <ldp-event-count>—No documentation is available yet.
- <ldp-event-count-5seconds>—No documentation is available yet.
- <ldp-event-type>—No documentation is available yet.

<ldp-fec-filter>

- Usage** <ldp-fec-filters-information>
 <ldp-fec-filter>
 <ldp-prefix>*ldp-prefix*</ldp-prefix>
 <ldp-ingress-filter>*ldp-ingress-filter*</ldp-ingress-filter>
 <ldp-ingress-filterid>*ldp-ingress-filterid*</ldp-ingress-filterid>
 <ldp-transit-filter>*ldp-transit-filter*</ldp-transit-filter>
 <ldp-transit-filterid>*ldp-transit-filterid*</ldp-transit-filterid>
 </ldp-fec-filter>
 </ldp-fec-filters-information>
- Description** No documentation is available yet.
- Contents** <ldp-ingress-filter>—Ingress firewall filter name.
- <ldp-ingress-filterid>—Ingress firewall filter index.
- <ldp-prefix>—No documentation is available yet.
- <ldp-transit-filter>—Transit firewall filter name.
- <ldp-transit-filterid>—Transit firewall filter index.

<ldp-fec-filters-information>

- Usage** <rpc-reply>
 <ldp-fec-filters-information>
 <ldp-fec-filter>...</ldp-fec-filter>
 </ldp-fec-filters-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <ldp-fec-filter>—No documentation is available yet.

<ldp-interface>

Usage <ldp-interface-information>
<ldp-interface>
 <interface-name>*interface-name*</interface-name>
 <ldp-label-space-id>*ldp-label-space-id*</ldp-label-space-id>
 <ldp-neighbor-count>*ldp-neighbor-count*</ldp-neighbor-count>
 <ldp-next-hello>*ldp-next-hello*</ldp-next-hello>
 <ldp-hello-interval>*ldp-hello-interval*</ldp-hello-interval>
 <ldp-local-hello-interval>*ldp-local-hello-interval*</ldp-local-hello-interval>
 <ldp-holdtime>*ldp-holdtime*</ldp-holdtime>
 <ldp-transport-address>*ldp-transport-address*</ldp-transport-address>
 <ldp-interface-index>*ldp-interface-index*</ldp-interface-index>
 <ldp-block-time>*ldp-block-time*</ldp-block-time>
 <ldp-hello-sent>*ldp-hello-sent*</ldp-hello-sent>
 <ldp-hello-received>*ldp-hello-received*</ldp-hello-received>
</ldp-interface>
 </ldp-interface-information>

Description No documentation is available yet.

Contents <interface-name>—No documentation is available yet.

<ldp-block-time>—No documentation is available yet.

<ldp-hello-interval>—No documentation is available yet.

<ldp-hello-received>—Number of hellos received on this interface.

<ldp-hello-sent>—Number of hellos sent on this interface.

<ldp-holdtime>—No documentation is available yet.

<ldp-interface-index>—No documentation is available yet.

<ldp-label-space-id>—No documentation is available yet.

<ldp-local-hello-interval>—The locally configured hello interval.

<ldp-neighbor-count>—No documentation is available yet.

<ldp-next-hello>—No documentation is available yet.

<ldp-transport-address>—No documentation is available yet.

<ldp-interface-information>

- Usage** <rpc-reply>
 <ldp-interface-information>
 <ldp-interface>...</ldp-interface>
 </ldp-interface-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <ldp-interface>—No documentation is available yet.

<ldp-l2circuit-vccv-cc-type>

- Usage** <ldp-binding>
 <ldp-l2circuit-vccv-cc-type>
 <mpls-type-control-word>mpls-type-control-word</mpls-type-control-word>
 <mpls-type-router-alert>mpls-type-router-alert</mpls-type-router-alert>
 <mpls-type-pw-label>mpls-type-pw-label</mpls-type-pw-label>
 </ldp-l2circuit-vccv-cc-type>
 </ldp-binding>
- Description** VCCV connectivity channel types supported by peer.
- Contents** <mpls-type-control-word>—Indicates that pwe3 control word type is supported.
 <mpls-type-pw-label>—Indicates that pseudowire label with ttl = 1 is supported.
 <mpls-type-router-alert>—Indicates that mpls router alert label is supported.

<ldp-l2circuit-vccv-cv-type>

- Usage** <ldp-binding>
 <ldp-l2circuit-vccv-cv-type>
 <mpls-type-icmp-ping>mpls-type-icmp-ping</mpls-type-icmp-ping>
 <mpls-type-lsp-ping>mpls-type-lsp-ping</mpls-type-lsp-ping>
 </ldp-l2circuit-vccv-cv-type>
 </ldp-binding>
- Description** VCCV connectivity verification types supported by peer.
- Contents** <mpls-type-icmp-ping>—Indicates that ICMP ping is supported.
 <mpls-type-lsp-ping>—Indicates that LSP ping is supported.

<ldp-message-statistics>

Usage <ldp-statistics>
 <ldp-message-statistics>
 <ldp-message-type>*ldp-message-type*</ldp-message-type>
 <ldp-messages-sent>*ldp-messages-sent*</ldp-messages-sent>
 <ldp-messages-received>*ldp-messages-received*</ldp-messages-received>
 <ldp-messages-sent-5seconds>*ldp-messages-sent-5seconds*
 </ldp-messages-sent-5seconds>
 <ldp-messages-received-5seconds>*ldp-messages-received-5seconds*
 </ldp-messages-received-5seconds>
 </ldp-message-statistics>
 </ldp-statistics>

Description No documentation is available yet.

Contents <ldp-message-type>—No documentation is available yet.

<ldp-messages-received>—No documentation is available yet.

<ldp-messages-received-5seconds>—No documentation is available yet.

<ldp-messages-sent>—No documentation is available yet.

<ldp-messages-sent-5seconds>—No documentation is available yet.

<ldp-neighbor>

Usage	<pre> <ldp-neighbor-information> <ldp-neighbor> <ldp-neighbor-address>ldp-neighbor-address</ldp-neighbor-address> <interface-name>interface-name</interface-name> <ldp-label-space-id>ldp-label-space-id</ldp-label-space-id> <ldp-remaining-time>ldp-remaining-time</ldp-remaining-time> <ldp-transport-address>ldp-transport-address</ldp-transport-address> <ldp-config-sequence>ldp-config-sequence</ldp-config-sequence> <ldp-up-time>ldp-up-time</ldp-up-time> <ldp-reference-count>ldp-reference-count</ldp-reference-count> <ldp-holdtime>ldp-holdtime</ldp-holdtime> <ldp-proposed-local-holdtime>ldp-proposed-local-holdtime </ldp-proposed-local-holdtime> <ldp-proposed-peer-holdtime>ldp-proposed-peer-holdtime </ldp-proposed-peer-holdtime> <ldp-neighbor-hello-flags>...</ldp-neighbor-hello-flags> <ldp-neighbor-types>...</ldp-neighbor-types> </ldp-neighbor> </ldp-neighbor-information> </pre>
Description	No documentation is available yet.
Contents	<p><interface-name>—No documentation is available yet.</p> <p><ldp-config-sequence>—No documentation is available yet.</p> <p><ldp-holdtime>—No documentation is available yet.</p> <p><ldp-label-space-id>—No documentation is available yet.</p> <p><ldp-neighbor-address>—No documentation is available yet.</p> <p><ldp-neighbor-hello-flags>—LDP neighbor hello flags.</p> <p><ldp-neighbor-types>—LDP neighbor types.</p> <p><ldp-proposed-local-holdtime>—The local value of the hold time.</p> <p><ldp-proposed-peer-holdtime>—The peer's proposed value of the hold time.</p> <p><ldp-reference-count>—No documentation is available yet.</p> <p><ldp-remaining-time>—No documentation is available yet.</p> <p><ldp-transport-address>—No documentation is available yet.</p> <p><ldp-up-time>—No documentation is available yet.</p>

<ldp-neighbor-hello-flags>

Usage <ldp-neighbor>
 <ldp-neighbor-hello-flags>
 <ldp-neighbor-hello-flag>*ldp-neighbor-hello-flag*</ldp-neighbor-hello-flag>
 </ldp-neighbor-hello-flags>
 </ldp-neighbor>

Description LDP neighbor hello flags.

Contents <ldp-neighbor-hello-flag>—LDP neighbor hello flag.

<ldp-neighbor-information>

Usage <rpc-reply>
 <ldp-neighbor-information>
 <ldp-neighbor>...</ldp-neighbor>
 </ldp-neighbor-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <ldp-neighbor>—No documentation is available yet.

<ldp-neighbor-replication>

Usage <ldp-neighbor-replication-information>
 <ldp-neighbor-replication>
 <ldp-instance-id>*ldp-instance-id*</ldp-instance-id>
 <ldp-neighbor-address>*ldp-neighbor-address*</ldp-neighbor-address>
 <interface-name>*interface-name*</interface-name>
 <ldp-neighbor-replication-state>*ldp-neighbor-replication-state*
 </ldp-neighbor-replication-state>
 <ldp-interface-index>*ldp-interface-index*</ldp-interface-index>
 <ldp-neighbor-replication-age>*ldp-neighbor-replication-age*
 </ldp-neighbor-replication-age>
 <ldp-reference-count>*ldp-reference-count*</ldp-reference-count>
 </ldp-neighbor-replication>
 </ldp-neighbor-replication-information>

Description Neighbor replication entry.

Contents <interface-name>—No documentation is available yet.

<ldp-instance-id>—Routing instance identifier.

<ldp-interface-index>—No documentation is available yet.

<ldp-neighbor-address>—No documentation is available yet.

<ldp-neighbor-replication-age>—Age.

<ldp-neighbor-replication-state>—State of the neighbor replication entry.

<ldp-reference-count>—No documentation is available yet.

<ldp-neighbor-replication-information>

Usage <rpc-reply>
 <ldp-neighbor-replication-information>
 <ldp-neighbor-replication>...</ldp-neighbor-replication>
 </ldp-neighbor-replication-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <ldp-neighbor-replication>—Neighbor replication entry.

<ldp-neighbor-types>

Usage	<pre> <ldp-neighbor ldp-session> <ldp-neighbor-types> <ldp-neighbor-type>ldp-neighbor-type</ldp-neighbor-type> </ldp-neighbor-types> </ldp-neighbor ldp-session> </pre>
Description	LDP neighbor types.
Contents	<ldp-neighbor-type>—LDP neighbor type.

<ldp-nexthop>

Usage	<pre> <ldp-route> <ldp-nexthop> <interface-name>interface-name</interface-name> <lsp-name>lsp-name</lsp-name> <lsp-no-ldp-tunneling/> <interface-address>interface-address</interface-address> <ldp-session-id>ldp-session-id</ldp-session-id> </ldp-nexthop> </ldp-route> </pre>
Description	No documentation is available yet.
Contents	<p><interface-address>—No documentation is available yet.</p> <p><interface-name>—No documentation is available yet.</p> <p><ldp-session-id>—No documentation is available yet.</p> <p><lsp-name>—Tunneled into an RSVP LSP.</p> <p><lsp-no-ldp-tunneling>—LDP tunneling is not configured on LSP.</p>

<ldp-oam-bfd-session>

Usage <ldp-route>
 <ldp-oam-bfd-session>
 <ldp-oam-destination-address>*ldp-oam-destination-address*
 </ldp-oam-destination-address>
 <ldp-oam-bfd-session-state>*ldp-oam-bfd-session-state*
 </ldp-oam-bfd-session-state>
 <ldp-oam-lsp-ping-state>*ldp-oam-lsp-ping-state*</ldp-oam-lsp-ping-state>
 <ldp-oam-nexthop-address>*ldp-oam-nexthop-address*</ldp-oam-nexthop-address>
 <ldp-oam-interface-name>*ldp-oam-interface-name*</ldp-oam-interface-name>
 <ldp-oam-nexthop-lsp>*ldp-oam-nexthop-lsp*</ldp-oam-nexthop-lsp>
 </ldp-oam-bfd-session>
 </ldp-route>

Description LDP OAM state information.

Contents <ldp-oam-bfd-session-state>—No documentation is available yet.

<ldp-oam-destination-address>—No documentation is available yet.

<ldp-oam-interface-name>—No documentation is available yet.

<ldp-oam-lsp-ping-state>—No documentation is available yet.

<ldp-oam-nexthop-address>—No documentation is available yet.

<ldp-oam-nexthop-lsp>—No documentation is available yet.

<ldp-oam-information>

Usage <rpc-reply>
 <ldp-oam-information>
 <ldp-oam-status>...</ldp-oam-status>
 </ldp-oam-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <ldp-oam-status>—No documentation is available yet.

<ldp-oam-path>

Usage <ldp-oam-status>
 <ldp-oam-path>
 <ldp-oam-destination-address>*ldp-oam-destination-address*
 </ldp-oam-destination-address>
 <ldp-oam-nexthop-address>*ldp-oam-nexthop-address*</ldp-oam-nexthop-address>
 <ldp-oam-interface-name>*ldp-oam-interface-name*</ldp-oam-interface-name>
 <ldp-oam-nexthop-lsp>*ldp-oam-nexthop-lsp*</ldp-oam-nexthop-lsp>
 <ldp-oam-bfd-session-state>*ldp-oam-bfd-session-state*
 </ldp-oam-bfd-session-state>
 <ldp-oam-lsp-ping-state>*ldp-oam-lsp-ping-state*</ldp-oam-lsp-ping-state>
 <ldp-oam-path-address>*ldp-oam-path-address*</ldp-oam-path-address>
 </ldp-oam-path>
 </ldp-oam-status>

Description No documentation is available yet.

Contents <ldp-oam-bfd-session-state>—No documentation is available yet.

<ldp-oam-destination-address>—No documentation is available yet.

<ldp-oam-interface-name>—No documentation is available yet.

<ldp-oam-lsp-ping-state>—No documentation is available yet.

<ldp-oam-nexthop-address>—No documentation is available yet.

<ldp-oam-nexthop-lsp>—No documentation is available yet.

<ldp-oam-path-address>—No documentation is available yet.

<ldp-oam-status>

Usage <ldp-oam-information>
 <ldp-oam-status>
 <ldp-oam-prefix>*ldp-oam-prefix*</ldp-oam-prefix>
 <ldp-oam-time>*ldp-oam-time*</ldp-oam-time>
 <ldp-oam-path>...</ldp-oam-path>
 </ldp-oam-status>
 </ldp-oam-information>

Description No documentation is available yet.

Contents <ldp-oam-path>—No documentation is available yet.

<ldp-oam-prefix>—No documentation is available yet.

<ldp-oam-time>—No documentation is available yet.

<ldp-path>

Usage	<pre> <ldp-path-information> <ldp-path> <ldp-outlib-session>ldp-outlib-session</ldp-outlib-session> <ldp-outlib-label>ldp-outlib-label</ldp-outlib-label> <ldp-ingress-label/> <ldp-inlib-session>ldp-inlib-session</ldp-inlib-session> <ldp-inlib-label>ldp-inlib-label</ldp-inlib-label> <ldp-egress-label/> <ldp-path-route>...</ldp-path-route> <ldp-reference-count>ldp-reference-count</ldp-reference-count> <ldp-route-transit/> <ldp-global-label>ldp-global-label</ldp-global-label> <ldp-merged-next-hop/> </ldp-path> </ldp-path-information> </pre>
Description	No documentation is available yet.
Contents	<p><ldp-egress-label>—No documentation is available yet.</p> <p><ldp-global-label>—No documentation is available yet.</p> <p><ldp-ingress-label>—No documentation is available yet.</p> <p><ldp-inlib-label>—No documentation is available yet.</p> <p><ldp-inlib-session>—No documentation is available yet.</p> <p><ldp-merged-next-hop>—Both active and non-active next hop will be merged together.</p> <p><ldp-outlib-label>—No documentation is available yet.</p> <p><ldp-outlib-session>—No documentation is available yet.</p> <p><ldp-path-route>—No documentation is available yet.</p> <p><ldp-reference-count>—No documentation is available yet.</p> <p><ldp-route-transit>—No documentation is available yet.</p>

<ldp-path-information>

Usage	<pre> <rpc-reply> <ldp-path-information> <ldp-path>...</ldp-path> </ldp-path-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<ldp-path>—No documentation is available yet.

<ldp-path-replication>

Usage <ldp-path-replication-information>
<ldp-path-replication>
 <ldp-instance-id>*ldp-instance-id*</ldp-instance-id>
 <ldp-label>*ldp-label*</ldp-label>
 <ldp-path-replication-ingress-selfid>*ldp-path-replication-ingress-selfid*
 </ldp-path-replication-ingress-selfid>
 <ldp-path-replication-transit-selfid>*ldp-path-replication-transit-selfid*
 </ldp-path-replication-transit-selfid>
 <ldp-path-replication-state>*ldp-path-replication-state*
 </ldp-path-replication-state>
 <ldp-reference-count>*ldp-reference-count*</ldp-reference-count>
</ldp-path-replication>
 </ldp-path-replication-information>

Description Path replication entry.

Contents <ldp-instance-id>—Routing instance identifier.
 <ldp-label>—No documentation is available yet.
 <ldp-path-replication-ingress-selfid>—Ingress Self ID.
 <ldp-path-replication-state>—Path replication entry state.
 <ldp-path-replication-transit-selfid>—Transit Self ID.
 <ldp-reference-count>—No documentation is available yet.

<ldp-path-replication-information>

Usage <rpc-reply>
<ldp-path-replication-information>
 <ldp-path-replication>...</ldp-path-replication>
</ldp-path-replication-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <ldp-path-replication>—Path replication entry.

<ldp-path-route>

Usage	<pre> <ldp-path> <ldp-path-route> <ldp-prefix>ldp-prefix</ldp-prefix> <ldp-route-ingress/> </ldp-path-route> </ldp-path> </pre>
Description	No documentation is available yet.
Contents	<p><ldp-prefix>—No documentation is available yet.</p> <p><ldp-route-ingress>—No documentation is available yet.</p>

<ldp-route>

Usage	<pre> <ldp-route-information> <ldp-route> <ldp-prefix>ldp-prefix</ldp-prefix> <ldp-nexthop>...</ldp-nexthop> <ldp-label>ldp-label</ldp-label> <ldp-no-label/> <ldp-topology-entry>ldp-topology-entry</ldp-topology-entry> <ldp-ingress-route-status>ldp-ingress-route-status</ldp-ingress-route-status> <ldp-ingress-route-last-modified-time>ldp-ingress-route-last-modified-time </ldp-ingress-route-last-modified-time> <ldp-merged-next-hop/> <ldp-oam-bfd-session>...</ldp-oam-bfd-session> </ldp-route> </ldp-route-information> </pre>
Description	No documentation is available yet.
Contents	<p><ldp-ingress-route-last-modified-time>—Time since the ingress route was modified.</p> <p><ldp-ingress-route-status>—Status about whether the ingress route is present or not.</p> <p><ldp-label>—No documentation is available yet.</p> <p><ldp-merged-next-hop>—Both active and non-active next hop will be merged together.</p> <p><ldp-nexthop>—No documentation is available yet.</p> <p><ldp-no-label>—No documentation is available yet.</p> <p><ldp-oam-bfd-session>—LDP OAM state information.</p> <p><ldp-prefix>—No documentation is available yet.</p> <p><ldp-topology-entry>—No documentation is available yet.</p>

<ldp-route-information>

Usage <rpc-reply>
 <ldp-route-information>
 <ldp-route>...</ldp-route>
 </ldp-route-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <ldp-route>—No documentation is available yet.

<ldp-session>

Usage <ldp-session-information>

<ldp-session>

```

<ldp-neighbor-address>ldp-neighbor-address</ldp-neighbor-address>
<ldp-session-state>ldp-session-state</ldp-session-state>
<ldp-connection-state>ldp-connection-state</ldp-connection-state>
<ldp-remaining-time>ldp-remaining-time</ldp-remaining-time>
<ldp-session-id>ldp-session-id</ldp-session-id>
<ldp-retry-time>ldp-retry-time</ldp-retry-time>
<ldp-keepalive-time>ldp-keepalive-time</ldp-keepalive-time>
<ldp-session-role>ldp-session-role</ldp-session-role>
<ldp-session-max-pdu>ldp-session-max-pdu</ldp-session-max-pdu>
<ldp-holdtime>ldp-holdtime</ldp-holdtime>
<ldp-neighbor-count>ldp-neighbor-count</ldp-neighbor-count>
<ldp-neighbor-types>...</ldp-neighbor-types>
<ldp-keepalive-interval>ldp-keepalive-interval</ldp-keepalive-interval>
<ldp-retry-interval>ldp-retry-interval</ldp-retry-interval>
<ldp-local-address>ldp-local-address</ldp-local-address>
<ldp-remote-address>ldp-remote-address</ldp-remote-address>
<ldp-graceful-restart-state>ldp-graceful-restart-state
</ldp-graceful-restart-state>
<ldp-local-reconnect-time>ldp-local-reconnect-time</ldp-local-reconnect-time>
<ldp-remote-reconnect-time>ldp-remote-reconnect-time
</ldp-remote-reconnect-time>
<ldp-restart-complete-time>ldp-restart-complete-time
</ldp-restart-complete-time>
<ldp-helper-mode-state>ldp-helper-mode-state</ldp-helper-mode-state>
<ldp-helper-mode-time>ldp-helper-mode-time</ldp-helper-mode-time>
<ldp-local-helper-mode>ldp-local-helper-mode</ldp-local-helper-mode>
<ldp-remote-helper-mode>ldp-remote-helper-mode</ldp-remote-helper-mode>
<ldp-graceful-restart-local>ldp-graceful-restart-local
</ldp-graceful-restart-local>
<ldp-graceful-restart-remote>ldp-graceful-restart-remote
</ldp-graceful-restart-remote>
<ldp-local-maximum-reconnect>ldp-local-maximum-reconnect
</ldp-local-maximum-reconnect>
<ldp-local-maximum-recovery>ldp-local-maximum-recovery
</ldp-local-maximum-recovery>
<ldp-up-time>ldp-up-time</ldp-up-time>
<ldp-last-down-time>ldp-last-down-time</ldp-last-down-time>
<ldp-down-reason>ldp-down-reason</ldp-down-reason>
<ldp-session-flap-count>ldp-session-flap-count</ldp-session-flap-count>
<ldp-session-protection>...</ldp-session-protection>
<ldp-session-nsr-state>ldp-session-nsr-state</ldp-session-nsr-state>
<ldp-session-address>...</ldp-session-address>
<ldp-session-deleted/>
<ldp-session-connect-pending/>
<ldp-session-close-pending/>
<ldp-session-queue-depth>ldp-session-queue-depth</ldp-session-queue-depth>
<ldp-session-read-pending/>
<ldp-session-write-pending/>
<ldp-session-receive-buffer-bytes>ldp-session-receive-buffer-bytes
</ldp-session-receive-buffer-bytes>

```

```

        <ldp-session-transmit-buffer-bytes>ldp-session-transmit-buffer-bytes
        </ldp-session-transmit-buffer-bytes>
        <ldp-session-no-connection/>
        <ldp-session-authentication>ldp-session-authentication
        </ldp-session-authentication>
        <ldp-session-statistics>...</ldp-session-statistics>
    </ldp-session>
</ldp-session-information>

```

Description No documentation is available yet.

Contents

- <ldp-connection-state>—No documentation is available yet.
- <ldp-down-reason>—No documentation is available yet.
- <ldp-graceful-restart-local>—No documentation is available yet.
- <ldp-graceful-restart-remote>—No documentation is available yet.
- <ldp-graceful-restart-state>—No documentation is available yet.
- <ldp-helper-mode-state>—Helping neighbor during graceful restart.
- <ldp-helper-mode-time>—Time left for session re-establishment or label recovery.
- <ldp-holdtime>—No documentation is available yet.
- <ldp-keepalive-interval>—No documentation is available yet.
- <ldp-keepalive-time>—No documentation is available yet.
- <ldp-last-down-time>—No documentation is available yet.
- <ldp-local-address>—No documentation is available yet.
- <ldp-local-helper-mode>—No documentation is available yet.
- <ldp-local-maximum-reconnect>—No documentation is available yet.
- <ldp-local-maximum-recovery>—No documentation is available yet.
- <ldp-local-reconnect-time>—No documentation is available yet.
- <ldp-neighbor-address>—No documentation is available yet.
- <ldp-neighbor-count>—No documentation is available yet.
- <ldp-neighbor-types>—LDP neighbor types.
- <ldp-remaining-time>—No documentation is available yet.
- <ldp-remote-address>—No documentation is available yet.
- <ldp-remote-helper-mode>—No documentation is available yet.
- <ldp-remote-reconnect-time>—No documentation is available yet.

<ldp-restart-complete-time>—No documentation is available yet.

<ldp-retry-interval>—No documentation is available yet.

<ldp-retry-time>—No documentation is available yet.

<ldp-session-address>—No documentation is available yet.

<ldp-session-authentication>—No documentation is available yet.

<ldp-session-close-pending>—No documentation is available yet.

<ldp-session-connect-pending>—No documentation is available yet.

<ldp-session-deleted>—No documentation is available yet.

<ldp-session-flap-count>—Number of times the LDP session has gone down and then come back up.

<ldp-session-id>—No documentation is available yet.

<ldp-session-max-pdu>—No documentation is available yet.

<ldp-session-no-connection>—No documentation is available yet.

<ldp-session-nsr-state>—Synchronization state of nonstop routing for the session.

<ldp-session-protection>—LDP session protection information.

<ldp-session-queue-depth>—No documentation is available yet.

<ldp-session-read-pending>—No documentation is available yet.

<ldp-session-receive-buffer-bytes>—No documentation is available yet.

<ldp-session-role>—No documentation is available yet.

<ldp-session-state>—No documentation is available yet.

<ldp-session-statistics>—No documentation is available yet.

<ldp-session-transmit-buffer-bytes>—No documentation is available yet.

<ldp-session-write-pending>—No documentation is available yet.

<ldp-up-time>—No documentation is available yet.

<ldp-session-address>

Usage	<pre> <ldp-session> <ldp-session-address> <interface-address><i>interface-address</i></interface-address> <interface-name><i>interface-name</i></interface-name> <ldp-session-address-stale/> </ldp-session-address> </ldp-session> </pre>
Description	No documentation is available yet.
Contents	<p><interface-address>—No documentation is available yet.</p> <p><interface-name>—No documentation is available yet.</p> <p><ldp-session-address-stale>—No documentation is available yet.</p>

<ldp-session-information>

Usage	<pre> <rpc-reply> <ldp-session-information> <ldp-session>...</ldp-session> </ldp-session-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<ldp-session>—No documentation is available yet.

<ldp-session-protection>

Usage	<pre> <ldp-session> <ldp-session-protection> <ldp-session-protection-state><i>ldp-session-protection-state</i> </ldp-session-protection-state> <ldp-session-protection-remaining-time><i>ldp-session-protection-remaining-time</i> </ldp-session-protection-remaining-time> </ldp-session-protection> </ldp-session> </pre>
Description	LDP session protection information.
Contents	<p><ldp-session-protection-remaining-time>—Time after which session protection will cease to be active.</p> <p><ldp-session-protection-state>—LDP session protection state.</p>

<ldp-session-replication>

Usage	<pre> <ldp-session-replication-information> <ldp-session-replication> <ldp-instance-id>ldp-instance-id</ldp-instance-id> <ldp-neighbor-address>ldp-neighbor-address</ldp-neighbor-address> <ldp-session-replication-state>ldp-session-replication-state </ldp-session-replication-state> <ldp-reference-count>ldp-reference-count</ldp-reference-count> <ldp-session-replication-age>ldp-session-replication-age </ldp-session-replication-age> </ldp-session-replication> </ldp-session-replication-information> </pre>
Description	Session replication entry.
Contents	<p><ldp-instance-id>—Routing instance identifier.</p> <p><ldp-neighbor-address>—No documentation is available yet.</p> <p><ldp-reference-count>—No documentation is available yet.</p> <p><ldp-session-replication-age>—Age.</p> <p><ldp-session-replication-state>—Session replication entry state.</p>

<ldp-session-replication-information>

Usage	<pre> <rpc-reply> <ldp-session-replication-information> <ldp-session-replication>...</ldp-session-replication> </ldp-session-replication-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<ldp-session-replication>—Session replication entry.

<ldp-session-statistics>

Usage <ldp-session>
 <ldp-session-statistics>
 <ldp-message-type>*ldp-message-type*</ldp-message-type>
 <ldp-messages-sent>*ldp-messages-sent*</ldp-messages-sent>
 <ldp-messages-received>*ldp-messages-received*</ldp-messages-received>
 <ldp-messages-sent-5seconds>*ldp-messages-sent-5seconds*
 </ldp-messages-sent-5seconds>
 <ldp-messages-received-5seconds>*ldp-messages-received-5seconds*
 </ldp-messages-received-5seconds>
 </ldp-session-statistics>
 </ldp-session>

Description No documentation is available yet.

Contents <ldp-message-type>—No documentation is available yet.

<ldp-messages-received>—No documentation is available yet.

<ldp-messages-received-5seconds>—No documentation is available yet.

<ldp-messages-sent>—No documentation is available yet.

<ldp-messages-sent-5seconds>—No documentation is available yet.

<ldp-standby-path>

Usage <ldp-standby-path-information>
 <ldp-standby-path>
 <ldp-reference-count>*ldp-reference-count*</ldp-reference-count>
 <ldp-label>*ldp-label*</ldp-label>
 <ldp-standby-path-prefix>...</ldp-standby-path-prefix>
 </ldp-standby-path>
 </ldp-standby-path-information>

Description LDP standby path entry.

Contents <ldp-label>—No documentation is available yet.

<ldp-reference-count>—No documentation is available yet.

<ldp-standby-path-prefix>—No documentation is available yet.

<ldp-standby-path-information>

- Usage** <rpc-reply>
 <ldp-standby-path-information>
 <ldp-standby-path>...</ldp-standby-path>
 </ldp-standby-path-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <ldp-standby-path>—LDP standby path entry.

<ldp-standby-path-prefix>

- Usage** <ldp-standby-path>
 <ldp-standby-path-prefix>
 <ldp-prefix>*ldp-prefix*</ldp-prefix>
 <ldp-reference-count>*ldp-reference-count*</ldp-reference-count>
 </ldp-standby-path-prefix>
 </ldp-standby-path>
- Description** No documentation is available yet.
- Contents** <ldp-prefix>—No documentation is available yet.
 <ldp-reference-count>—No documentation is available yet.

<ldp-standby-path-reference>

- Usage** <ldp-standby-route>
 <ldp-standby-path-reference>
 <ldp-reference-count>*ldp-reference-count*</ldp-reference-count>
 <ldp-label>*ldp-label*</ldp-label>
 </ldp-standby-path-reference>
 </ldp-standby-route>
- Description** Route to label association entry.
- Contents** <ldp-label>—No documentation is available yet.
 <ldp-reference-count>—No documentation is available yet.

<ldp-standby-route>

Usage	<pre> <ldp-standby-route-information> <ldp-standby-route> <ldp-prefix>ldp-prefix</ldp-prefix> <ldp-standby-route-route/> <ldp-standby-path-reference>...</ldp-standby-path-reference> </ldp-standby-route> </ldp-standby-route-information> </pre>
Description	LDP standby route entry.
Contents	<p><ldp-prefix>—No documentation is available yet.</p> <p><ldp-standby-path-reference>—Route to label association entry.</p> <p><ldp-standby-route-route>—Route present in LDP shadow routing table.</p>

<ldp-standby-route-information>

Usage	<pre> <rpc-reply> <ldp-standby-route-information> <ldp-standby-route>...</ldp-standby-route> </ldp-standby-route-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<ldp-standby-route>—LDP standby route entry.

<ldp-statistics>

Usage	<pre> <ldp-statistics-information> <ldp-statistics> <ldp-message-statistics>...</ldp-message-statistics> <ldp-event-statistics>...</ldp-event-statistics> </ldp-statistics> </ldp-statistics-information> </pre>
Description	No documentation is available yet.
Contents	<p><ldp-event-statistics>—No documentation is available yet.</p> <p><ldp-message-statistics>—No documentation is available yet.</p>

<ldp-statistics-information>

- Usage** <rpc-reply>
 <ldp-statistics-information>
 <ldp-statistics>...</ldp-statistics>
 </ldp-statistics-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <ldp-statistics>—No documentation is available yet.

<ldp-traffic-statistics>

- Usage** <ldp-traffic-statistics-information>
 <ldp-traffic-statistics>
 <ldp-prefix>ldp-prefix</ldp-prefix>
 <ldp-traffic-type>ldp-traffic-type</ldp-traffic-type>
 <ldp-traffic-error>ldp-traffic-error</ldp-traffic-error>
 <ldp-traffic-statistics-packet-count>ldp-traffic-statistics-packet-count
 </ldp-traffic-statistics-packet-count>
 <ldp-traffic-statistics-byte-count>ldp-traffic-statistics-byte-count
 </ldp-traffic-statistics-byte-count>
 <ldp-traffic-multiple-fec>ldp-traffic-multiple-fec</ldp-traffic-multiple-fec>
 </ldp-traffic-statistics>
 </ldp-traffic-statistics-information>
- Description** No documentation is available yet.
- Contents** <ldp-prefix>—No documentation is available yet.
- <ldp-traffic-error>—Error encountered when querying the statistics.
- <ldp-traffic-multiple-fec>—Multiple FECs sharing the same label.
- <ldp-traffic-statistics-byte-count>—Number of bytes switched for this FEC.
- <ldp-traffic-statistics-packet-count>—Number of packets switched for this FEC.
- <ldp-traffic-type>—Type of traffic: ingress or transit.

<ldp-traffic-statistics-error>

- Usage** <ldp-traffic-statistics-information>
 <ldp-traffic-statistics-error>
 <ldp-traffic-error>ldp-traffic-error</ldp-traffic-error>
 </ldp-traffic-statistics-error>
 </ldp-traffic-statistics-information>
- Description** No documentation is available yet.
- Contents** <ldp-traffic-error>—Error encountered when querying the statistics.

<ldp-traffic-statistics-information>

Usage <rpc-reply>
 <ldp-traffic-statistics-information>
 <ldp-traffic-statistics>...</ldp-traffic-statistics>
 <ldp-traffic-statistics-error>...</ldp-traffic-statistics-error>
 </ldp-traffic-statistics-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <ldp-traffic-statistics>—No documentation is available yet.
 <ldp-traffic-statistics-error>—No documentation is available yet.

<ldp-vpls-reference-site>

Usage <instance>
 <ldp-vpls-reference-site>
 <vpls-signaling-protocol-identifier>*vpls-signaling-protocol-identifier*
 </vpls-signaling-protocol-identifier>
 <local-site-id>*local-site-id*</local-site-id>
 <remote-site-id>*remote-site-id*</remote-site-id>
 <vpls-id>*vpls-id*</vpls-id>
 <num-local-interfaces>*num-local-interfaces*</num-local-interfaces>
 <num-local-interfaces-up>*num-local-interfaces-up*</num-local-interfaces-up>
 <irb-present>*irb-present*</irb-present>
 <mesh-group-count>*mesh-group-count*</mesh-group-count>
 <mesh-group-up-count>*mesh-group-up-count*</mesh-group-up-count>
 <mesh-group-interfaces>...</mesh-group-interfaces>
 <interface>...</interface>
 <connection>...</connection>
 <mesh-group-connection>...</mesh-group-connection>
 <connections-summary>...</connections-summary>
 </ldp-vpls-reference-site>
 </instance>

Description Information about LDP-VPLS.

Contents <connection>—No documentation is available yet.

<connections-summary>—No documentation is available yet.

<interface>—No documentation is available yet.

<irb-present>—No documentation is available yet.

<local-site-id>—No documentation is available yet.

<mesh-group-connection>—Information about all vc-connections of a specific mesh-group.

<mesh-group-count>—No documentation is available yet.

<mesh-group-interfaces>—Information about all interfaces associated with a mesh-group.

<mesh-group-up-count>—No documentation is available yet.

<num-local-interfaces>—No documentation is available yet.

<num-local-interfaces-up>—No documentation is available yet.

<remote-site-id>—No documentation is available yet.

<vpls-id>—VPLS instance identifier.

<vpls-signaling-protocol-identifier>—No documentation is available yet.

<lm-control-channel-info>

Usage <lm-peer-control-channels>
 <lm-control-channel-info>
 <lm-control-channel>*lm-control-channel*</lm-control-channel>
 <lm-control-channel-state>*lm-control-channel-state*</lm-control-channel-state>
 </lm-control-channel-info>
 </lm-peer-control-channels>

Description Link management control channel information.

Contents <lm-control-channel>—Peer control channel name.
 <lm-control-channel-state>—Peer control channel state.

<lm-information>

Usage <rpc-reply>
 <lm-information>
 <lm-peer-root-information>...</lm-peer-root-information>
 <lm-te-link-root-information>...</lm-te-link-root-information>
 <lm-resource-root-information>...</lm-resource-root-information>
 </lm-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <lm-peer-root-information>—No documentation is available yet.
 <lm-resource-root-information>—No documentation is available yet.
 <lm-te-link-root-information>—No documentation is available yet.

<lm-input-statistics>

Usage <lm-peer-statistics>
 <lm-input-statistics>
 <lm-received-packets>...</lm-received-packets>
 <lm-received-bad-packets>...</lm-received-bad-packets>
 <lm-received-misordered-packets>...</lm-received-misordered-packets>
 <lm-small-packets>*lm-small-packets*</lm-small-packets>
 <lm-bad-version>*lm-bad-version*</lm-bad-version>
 <lm-no-peer>*lm-no-peer*</lm-no-peer>
 <lm-no-cc>*lm-no-cc*</lm-no-cc>
 <lm-wrong-state>*lm-wrong-state*</lm-wrong-state>
 <lm-stale-ack>*lm-stale-ack*</lm-stale-ack>
 <lm-stale-nack>*lm-stale-nack*</lm-stale-nack>
 </lm-input-statistics>
 </lm-peer-statistics>

Description Input statistics.

Contents <lm-bad-version>—Number of packets with unsupported protocol version.

<lm-no-cc>—Number of messages received for unknown control channel.

<lm-no-peer>—Number of messages received for unknown peer.

<lm-received-bad-packets>—Number of bad packets received.

<lm-received-misordered-packets>—Number of out-of-order packets received.

<lm-received-packets>—Number of packets received.

<lm-small-packets>—Number of packets too small to process.

<lm-stale-ack>—Number of acknowledgements received for unknown messages.

<lm-stale-nack>—Number of negative acknowledgements received for unknown messages.

<lm-wrong-state>—Number of messages received for control channel in wrong state.

<lm-imp-control-channel-flags>

Usage <lm-peer-imp-control-channels>
 <lm-imp-control-channel-flags>
 <cc-restarting/>
 </lm-imp-control-channel-flags>
 </lm-peer-imp-control-channels>

Description Peer control channel flags.

Contents <cc-restarting>—No documentation is available yet.

<lm-output-statistics>

Usage	<pre> <lm-peer-statistics> <lm-output-statistics> <lm-sent-packets>...</lm-sent-packets> <lm-retransmit-packets>...</lm-retransmit-packets> <lm-tossed-packets>...</lm-tossed-packets> </lm-output-statistics> </lm-peer-statistics> </pre>
Description	Output statistics.
Contents	<p><lm-retransmit-packets>—Number of packets retransmitted.</p> <p><lm-sent-packets>—Number of packets sent.</p> <p><lm-tossed-packets>—Number of messages which failed retransmission.</p>

<lm-peer-control-channels>

Usage	<pre> <lm-peer-information> <lm-peer-control-channels> <lm-control-channel-info>...</lm-control-channel-info> </lm-peer-control-channels> </lm-peer-information> </pre>
Description	Link management control channels.
Contents	<lm-control-channel-info>—Link management control channel information.

<lm-peer-information>

Usage <lm-peer-root-information>
 <lm-peer-information>
 <lm-source>*lm-source*</lm-source>
 <lm-sys-id>*lm-sys-id*</lm-sys-id>
 <lm-peer-name>*lm-peer-name*</lm-peer-name>
 <lm-state>*lm-state*</lm-state>
 <lm-peer-control-address>*lm-peer-control-address*</lm-peer-control-address>
 <lm-peer-hello-interval>*lm-peer-hello-interval*</lm-peer-hello-interval>
 <lm-peer-hello-dead-interval>*lm-peer-hello-dead-interval*
 </lm-peer-hello-dead-interval>
 <lm-peer-received-message-id>*lm-peer-received-message-id*
 </lm-peer-received-message-id>
 <lm-peer-sent-message-id>*lm-peer-sent-message-id*</lm-peer-sent-message-id>
 <lm-peer-control-channels>...</lm-peer-control-channels>
 <lm-peer-lmp-control-channels>...</lm-peer-lmp-control-channels>
 <lm-peer-te-links>...</lm-peer-te-links>
 </lm-peer-information>
 </lm-peer-root-information>

Description No documentation is available yet.

Contents <lm-peer-control-address>—Peer control address.

<lm-peer-control-channels>—Link management control channels.

<lm-peer-hello-dead-interval>—LMP hello dead-interval.

<lm-peer-hello-interval>—LMP hello interval.

<lm-peer-lmp-control-channels>—Link management control channels.

<lm-peer-name>—Name of object.

<lm-peer-received-message-id>—LMP last per-peer received message ID.

<lm-peer-sent-message-id>—LMP last per-peer sent message ID.

<lm-peer-te-links>—Link management peer TE links.

<lm-source>—Source of information.

<lm-state>—State of object.

<lm-sys-id>—System identifier of object.

<lm-peer-lmp-control-channels>

Usage <lm-peer-information>
 <lm-peer-lmp-control-channels>
 <lm-lmp-control-channel-local-id>*lm-lmp-control-channel-local-id*
 </lm-lmp-control-channel-local-id>
 <lm-lmp-control-channel-remote-id>*lm-lmp-control-channel-remote-id*
 </lm-lmp-control-channel-remote-id>
 <lm-lmp-control-channel-state>*lm-lmp-control-channel-state*
 </lm-lmp-control-channel-state>
 <lm-lmp-control-channel-flags>...
 </lm-lmp-control-channel-flags>
 <lm-lmp-control-channel-received-message-id>*lm-lmp-ctrl-chnl-recd-msg-id*
 </lm-lmp-control-channel-received-message-id>
 <lm-lmp-control-channel-sent-message-id>*lm-lmp-control-channel-sent-message-id*
 </lm-lmp-control-channel-sent-message-id>
 <lm-lmp-control-channel-rcv-seq-num>*lm-lmp-control-channel-rcv-seq-num*
 </lm-lmp-control-channel-rcv-seq-num>
 <lm-lmp-control-channel-tx-seq-num>*lm-lmp-control-channel-tx-seq-num*
 </lm-lmp-control-channel-tx-seq-num>
 </lm-peer-lmp-control-channels>
 </lm-peer-information>

Description Link management control channels.

Contents <lm-lmp-control-channel-flags>—Peer control channel flags.

<lm-lmp-control-channel-local-id>—Peer control channel local ID.

<lm-lmp-control-channel-rcv-seq-num>—LMP receive sequence number.

<lm-lmp-control-channel-received-message-id>—LMP last per-control-channel received message ID.

<lm-lmp-control-channel-remote-id>—Peer control channel remote ID.

<lm-lmp-control-channel-sent-message-id>—LMP last per-control-channel sent message ID.

<lm-lmp-control-channel-state>—Peer control channel state.

<lm-lmp-control-channel-tx-seq-num>—LMP transmit sequence number.

<lm-peer-root-information>

Usage <lm-information>
 <lm-peer-root-information>
 <lm-peer-information>...</lm-peer-information>
 </lm-peer-root-information>
 </lm-information>

Description No documentation is available yet.

Contents <lm-peer-information>—No documentation is available yet.

<lm-peer-statistics>

Usage	<pre> <lm-statistics-information> <lm-peer-statistics> <lm-peer-name>lm-peer-name</lm-peer-name> <lm-input-statistics>...</lm-input-statistics> <lm-output-statistics>...</lm-output-statistics> </lm-peer-statistics> </lm-statistics-information> </pre>
Description	No documentation is available yet.
Contents	<p><lm-input-statistics>—Input statistics.</p> <p><lm-output-statistics>—Output statistics.</p> <p><lm-peer-name>—Name of object.</p>

<lm-peer-te-links>

Usage	<pre> <lm-peer-information> <lm-peer-te-links> <lm-peer-te-link>lm-peer-te-link</lm-peer-te-link> </lm-peer-te-links> </lm-peer-information> </pre>
Description	Link management peer TE links.
Contents	<lm-peer-te-link>—TE link name contained in peer.

<lm-received-bad-packets>

Usage	<pre> <lm-input-statistics> <lm-received-bad-packets> <lm-packet-type>lm-packet-type</lm-packet-type> <lm-packet-count>lm-packet-count</lm-packet-count> </lm-received-bad-packets> </lm-input-statistics> </pre>
Description	Number of bad packets received.
Contents	<p><lm-packet-count>—Number of packets.</p> <p><lm-packet-type>—Type of packet.</p>

<lm-received-misordered-packets>

Usage <lm-input-statistics>
 <lm-received-misordered-packets>
 <lm-packet-type>*lm-packet-type*</lm-packet-type>
 <lm-packet-count>*lm-packet-count*</lm-packet-count>
 </lm-received-misordered-packets>
 </lm-input-statistics>

Description Number of out-of-order packets received.

Contents <lm-packet-count>—Number of packets.
 <lm-packet-type>—Type of packet.

<lm-received-packets>

Usage <lm-input-statistics>
 <lm-received-packets>
 <lm-packet-type>*lm-packet-type*</lm-packet-type>
 <lm-packet-count>*lm-packet-count*</lm-packet-count>
 </lm-received-packets>
 </lm-input-statistics>

Description Number of packets received.

Contents <lm-packet-count>—Number of packets.
 <lm-packet-type>—Type of packet.

<lm-resource>

Usage	<pre> <lm-resource-root-information> <lm-resource> <lm-resource-name>lm-resource-name</lm-resource-name> <lm-resource-type>lm-resource-type</lm-resource-type> <lm-resource-state>lm-resource-state</lm-resource-state> <lm-sys-id>lm-sys-id</lm-sys-id> <lm-resource-max-allocations>lm-resource-max-allocations </lm-resource-max-allocations> <lm-resource-bandwidth>lm-resource-bandwidth</lm-resource-bandwidth> <lm-resource-traffic-params>lm-resource-traffic-params </lm-resource-traffic-params> </lm-resource> </lm-resource-root-information> </pre>
Description	No documentation is available yet.
Contents	<p><lm-resource-bandwidth>—Total bandwidth of resource.</p> <p><lm-resource-max-allocations>—Maximum number of allocations.</p> <p><lm-resource-name>—Resource name.</p> <p><lm-resource-state>—No documentation is available yet.</p> <p><lm-resource-traffic-params>—Traffic parameters of resource.</p> <p><lm-resource-type>—Resource type.</p> <p><lm-sys-id>—System identifier of object.</p>

<lm-resource-allocation-context>

Usage	<pre> <lm-te-link-resource> <lm-resource-allocation-context> <lm-allocated-bandwidth>lm-allocated-bandwidth</lm-allocated-bandwidth> <lm-allocated-lsp-name>lm-allocated-lsp-name</lm-allocated-lsp-name> <lm-local-label>lm-local-label</lm-local-label> <lm-remote-label>lm-remote-label</lm-remote-label> </lm-resource-allocation-context> </lm-te-link-resource> </pre>
Description	No documentation is available yet.
Contents	<p><lm-allocated-bandwidth>—No documentation is available yet.</p> <p><lm-allocated-lsp-name>—No documentation is available yet.</p> <p><lm-local-label>—No documentation is available yet.</p> <p><lm-remote-label>—No documentation is available yet.</p>

<lm-resource-root-information>

Usage	<pre> <lm-information> <lm-resource-root-information> <lm-source>lm-source</lm-source> <lm-resource>...</lm-resource> </lm-resource-root-information> </lm-information> </pre>
Description	No documentation is available yet.
Contents	<p><lm-resource>—No documentation is available yet.</p> <p><lm-source>—Source of information.</p>

<lm-retransmit-packets>

Usage	<pre> <lm-output-statistics> <lm-retransmit-packets> <lm-packet-type>lm-packet-type</lm-packet-type> <lm-packet-count>lm-packet-count</lm-packet-count> </lm-retransmit-packets> </lm-output-statistics> </pre>
Description	Number of packets retransmitted.
Contents	<p><lm-packet-count>—Number of packets.</p> <p><lm-packet-type>—Type of packet.</p>

<lm-sent-packets>

Usage	<pre> <lm-output-statistics> <lm-sent-packets> <lm-packet-type>lm-packet-type</lm-packet-type> <lm-packet-count>lm-packet-count</lm-packet-count> </lm-sent-packets> </lm-output-statistics> </pre>
Description	Number of packets sent.
Contents	<p><lm-packet-count>—Number of packets.</p> <p><lm-packet-type>—Type of packet.</p>

<lm-statistics-information>

Usage <rpc-reply>
 <lm-statistics-information>
 <lm-peer-statistics>...</lm-peer-statistics>
 </lm-statistics-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <lm-peer-statistics>—No documentation is available yet.

<lm-te-link-information>

Usage <lm-te-link-root-information>
<lm-te-link-information>
 <lm-te-link-name>*lm-te-link-name*</lm-te-link-name>
 <lm-local-id>*lm-local-id*</lm-local-id>
 <lm-remote-id>*lm-remote-id*</lm-remote-id>
 <lm-state>*lm-state*</lm-state>
 <lm-te-link-flags>*lm-te-link-flags*</lm-te-link-flags>
 <lm-te-link-local-flags>...</lm-te-link-local-flags>
 <lm-local-address>*lm-local-address*</lm-local-address>
 <lm-remote-address>*lm-remote-address*</lm-remote-address>
 <lm-encoding>*lm-encoding*</lm-encoding>
 <lm-switching>*lm-switching*</lm-switching>
 <lm-min-bandwidth>*lm-min-bandwidth*</lm-min-bandwidth>
 <lm-max-bandwidth>*lm-max-bandwidth*</lm-max-bandwidth>
 <lm-total-bandwidth>*lm-total-bandwidth*</lm-total-bandwidth>
 <lm-avail-bandwidth>*lm-avail-bandwidth*</lm-avail-bandwidth>
 <lm-te-link-resources>...</lm-te-link-resources>
</lm-te-link-information>
 </lm-te-link-root-information>

Description No documentation is available yet.

Contents <lm-avail-bandwidth>—Unallocated bandwidth on this TE link.

<lm-encoding>—TE-Link encoding type.

<lm-local-address>—Local address of object.

<lm-local-id>—Local identifier of object.

<lm-max-bandwidth>—Maximum reservable bandwidth per allocation.

<lm-min-bandwidth>—Minimum reservable bandwidth per allocation.

<lm-remote-address>—Remote address of object.

<lm-remote-id>—Remote identifier of object.

<lm-state>—State of object.

<lm-switching>—TE-Link switching capability.

<lm-te-link-flags>—Flags for object.

<lm-te-link-local-flags>—No documentation is available yet.

<lm-te-link-name>—Name of object.

<lm-te-link-resources>—No documentation is available yet.

<lm-total-bandwidth>—Total bandwidth available on this TE link.

<Im-te-link-local-flags>

Usage <Im-te-link-information>
 <Im-te-link-local-flags>
 <Im-te-link-nack-sent-flag/>
 </Im-te-link-local-flags>
 </Im-te-link-information>

Description No documentation is available yet.

Contents <Im-te-link-nack-sent-flag>—No documentation is available yet.

<lm-te-link-resource>

Usage <lm-te-link-resources>
<lm-te-link-resource>
 <lm-resource-name>*lm-resource-name*</lm-resource-name>
 <lm-resource-type>*lm-resource-type*</lm-resource-type>
 <lm-sys-id>*lm-sys-id*</lm-sys-id>
 <lm-resource-state>*lm-resource-state*</lm-resource-state>
 <lm-resource-flags>*lm-resource-flags*</lm-resource-flags>
 <lm-resource-local-id>*lm-resource-local-id*</lm-resource-local-id>
 <lm-resource-remote-id>*lm-resource-remote-id*</lm-resource-remote-id>
 <lm-resource-local-addr>*lm-resource-local-addr*</lm-resource-local-addr>
 <lm-resource-remote-addr>*lm-resource-remote-addr*</lm-resource-remote-addr>
 <lm-resource-bandwidth>*lm-resource-bandwidth*</lm-resource-bandwidth>
 <lm-resource-avail-bandwidth>*lm-resource-avail-bandwidth*
 </lm-resource-avail-bandwidth>
 <lm-resource-traffic-params>*lm-resource-traffic-params*
 </lm-resource-traffic-params>
 <lm-resource-max-allocations>*lm-resource-max-allocations*
 </lm-resource-max-allocations>
 <lm-resource-num-allocations>*lm-resource-num-allocations*
 </lm-resource-num-allocations>
 <lm-resource-in-use>*lm-resource-in-use*</lm-resource-in-use>
 <lm-resource-lsp-name>*lm-resource-lsp-name*</lm-resource-lsp-name>
 <lm-resource-allocation-context>...</lm-resource-allocation-context>
</lm-te-link-resource>
 </lm-te-link-resources>

Description No documentation is available yet.

Contents <lm-resource-allocation-context>—No documentation is available yet.

<lm-resource-avail-bandwidth>—Unallocated bandwidth on resource.

<lm-resource-bandwidth>—Total bandwidth of resource.

<lm-resource-flags>—Resource flags.

<lm-resource-in-use>—Resource allocation status.

<lm-resource-local-addr>—Resource local address.

<lm-resource-local-id>—Resource local identifier.

<lm-resource-lsp-name>—Name of LSP using resource.

<lm-resource-max-allocations>—Maximum number of allocations.

<lm-resource-name>—Resource name.

<lm-resource-num-allocations>—Current number of allocations.

<lm-resource-remote-addr>—Resource remote address.

<lm-resource-remote-id>—Resource remote identifier.

`<lm-resource-state>`—No documentation is available yet.

`<lm-resource-traffic-params>`—Traffic parameters of resource.

`<lm-resource-type>`—Resource type.

`<lm-sys-id>`—System identifier of object.

`<lm-te-link-resources>`

Usage `<lm-te-link-information>`
 `<lm-te-link-resources>`
 `<lm-te-link-resource>...</lm-te-link-resource>`
 `</lm-te-link-resources>`
`</lm-te-link-information>`

Description No documentation is available yet.

Contents `<lm-te-link-resource>`—No documentation is available yet.

`<lm-te-link-root-information>`

Usage `<lm-information>`
 `<lm-te-link-root-information>`
 `<lm-te-link-information>...</lm-te-link-information>`
 `</lm-te-link-root-information>`
`</lm-information>`

Description No documentation is available yet.

Contents `<lm-te-link-information>`—No documentation is available yet.

`<lm-tossed-packets>`

Usage `<lm-output-statistics>`
 `<lm-tossed-packets>`
 `<lm-packet-type>lm-packet-type</lm-packet-type>`
 `<lm-packet-count>lm-packet-count</lm-packet-count>`
 `</lm-tossed-packets>`
`</lm-output-statistics>`

Description Number of messages which failed retransmission.

Contents `<lm-packet-count>`—Number of packets.

`<lm-packet-type>`—Type of packet.

<local-asn>

Usage	<pre> <aspath-domain> <local-asn> <asn>asn</asn> <as-loops>as-loops</as-loops> </local-asn> </aspath-domain> </pre>
Description	No documentation is available yet.
Contents	<p><as-loops>—No documentation is available yet.</p> <p><asn>—Autonomous system number.</p>

<local-interface>

Usage	<pre> <connection> <local-interface> <interface-name>interface-name</interface-name> <interface-status>interface-status</interface-status> <interface-encapsulation>interface-encapsulation</interface-encapsulation> <working-status>working-status</working-status> <interface-description>interface-description</interface-description> </local-interface> </connection> </pre>
Description	No documentation is available yet.
Contents	<p><interface-description>—No documentation is available yet.</p> <p><interface-encapsulation>—No documentation is available yet.</p> <p><interface-name>—No documentation is available yet.</p> <p><interface-status>—No documentation is available yet.</p> <p><working-status>—No documentation is available yet.</p>

<log-element>

- Usage** <ospf-log-instance | ospf-log-maximum-length | ospf-log-events>
<log-element>
 <timestamp>*timestamp*</timestamp>
 <ospf-log-type>*ospf-log-type*</ospf-log-type>
 <elapsed-time>*elapsed-time*</elapsed-time>
</log-element>
 </ospf-log-instance | ospf-log-maximum-length | ospf-log-events>
- Description** No documentation is available yet.
- Contents** <elapsed-time>—Time this adjacency or session has been up or down.
 <ospf-log-type>—No documentation is available yet.
 <timestamp>—Time when something occurs.

<lp-history>

- Usage** <rsvp-session | bypass-info>
<lp-history>
 <sequence-number>*sequence-number*</sequence-number>
 <time>*time*</time>
 <log>*log*</log>
 <route>*route*</route>
</lp-history>
 </rsvp-session | bypass-info>
- Description** Log of LSP path-related events.
- Contents** <log>—Supplemental information of the event.
 <route>—Latest RRO contents, as reported by RSVP.
 <sequence-number>—History event number.
 <time>—Time of the event.

<mc-stats-interface>

Usage <multicast-statistics>
<mc-stats-interface>
 <interface-name>*interface-name*</interface-name>
 <protocol-name>*protocol-name*</protocol-name>
 <mc-mismatch-errors>*mc-mismatch-errors*</mc-mismatch-errors>
 <mc-mismatches>*mc-mismatches*</mc-mismatches>
 <mc-mismatches-no-route>*mc-mismatches-no-route*</mc-mismatches-no-route>
 <mc-resolves>*mc-resolves*</mc-resolves>
 <mc-routing-notifies>*mc-routing-notifies*</mc-routing-notifies>
 <mc-resolves-no-route>*mc-resolves-no-route*</mc-resolves-no-route>
 <mc-resolve-errors>*mc-resolve-errors*</mc-resolve-errors>
 <mc-resolves-filtered>*mc-resolves-filtered*</mc-resolves-filtered>
 <mc-routing-notifies-filtered>*mc-routing-notifies-filtered*
 </mc-routing-notifies-filtered>
 <mc-input-kbytes>*mc-input-kbytes*</mc-input-kbytes>
 <mc-input-packets>*mc-input-packets*</mc-input-packets>
 <mc-output-kbytes>*mc-output-kbytes*</mc-output-kbytes>
 <mc-output-packets>*mc-output-packets*</mc-output-packets>
</mc-stats-interface>
 </multicast-statistics>

Description No documentation is available yet.

Contents <interface-name>—No documentation is available yet.

<mc-input-kbytes>—Number of input kilobytes.

<mc-input-packets>—Number of input packets.

<mc-mismatch-errors>—Number of interface mismatch errors.

<mc-mismatches>—Number of interface mismatches.

<mc-mismatches-no-route>—Number of interface mismatches due to no route to source.

<mc-output-kbytes>—Number of output kilobytes.

<mc-output-packets>—Number of output packets.

<mc-resolve-errors>—Number of resolve errors.

<mc-resolves>—Number of resolve requests.

<mc-resolves-filtered>—Number of resolve requests filtered by policy.

<mc-resolves-no-route>—Number of resolve requests with no route to source.

<mc-routing-notifies>—Number of routing notifications.

<mc-routing-notifies-filtered>—Number of routing notifications filtered by policy.

<protocol-name>—No documentation is available yet.

<mdt-active-tunnel>

Usage <pim-mdt-information>
 <mdt-active-tunnel>
 <mdt-customer-source-address>*mdt-customer-source-address*
 </mdt-customer-source-address>
 <mdt-customer-group-address>*mdt-customer-group-address*
 </mdt-customer-group-address>
 <mdt-provider-group-address>*mdt-provider-group-address*
 </mdt-provider-group-address>
 <mdt-tunnel-interface-name>*mdt-tunnel-interface-name*
 </mdt-tunnel-interface-name>
 <mdt-forwarding-rate-kilobits>*mdt-forwarding-rate-kilobits*
 </mdt-forwarding-rate-kilobits>
 <mdt-forwarding-rate-kilobytes>*mdt-forwarding-rate-kilobytes*
 </mdt-forwarding-rate-kilobytes>
 <mdt-configured-threshold-rate>*mdt-configured-threshold-rate*
 </mdt-configured-threshold-rate>
 <mdt-tunnel-uptime>*mdt-tunnel-uptime*</mdt-tunnel-uptime>
 <mdt-default-tunnel-information>*mdt-default-tunnel-information*
 </mdt-default-tunnel-information>
 </mdt-active-tunnel>
 </pim-mdt-information>

Description No documentation is available yet.

Contents <mdt-configured-threshold-rate>—No documentation is available yet.
 <mdt-customer-group-address>—No documentation is available yet.
 <mdt-customer-source-address>—No documentation is available yet.
 <mdt-default-tunnel-information>—No documentation is available yet.
 <mdt-forwarding-rate-kilobits>—No documentation is available yet.
 <mdt-forwarding-rate-kilobytes>—No documentation is available yet.
 <mdt-provider-group-address>—No documentation is available yet.
 <mdt-tunnel-interface-name>—No documentation is available yet.
 <mdt-tunnel-uptime>—No documentation is available yet.

<mesh-group-connection>

Usage <reference-site | ldp-vpls-reference-site | vpls-protocol-state>
<mesh-group-connection>
 <mesh-group-name>*mesh-group-name*</mesh-group-name>
 <connection>...</connection>
 <connections-summary>...</connections-summary>
</mesh-group-connection>
 </reference-site | ldp-vpls-reference-site | vpls-protocol-state>

Description Information about all vc-connections of a specific mesh-group.

Contents <connection>—No documentation is available yet.
 <connections-summary>—No documentation is available yet.
 <mesh-group-name>—Name of mesh-group.

<mesh-group-interfaces>

Usage <reference-site | ldp-vpls-reference-site | vpls-protocol-state>
<mesh-group-interfaces>
 <mesh-group-name>*mesh-group-name*</mesh-group-name>
 <mesh-group-id>*mesh-group-id*</mesh-group-id>
 <mesh-group-state>*mesh-group-state*</mesh-group-state>
 <interface>...</interface>
</mesh-group-interfaces>
 </reference-site | ldp-vpls-reference-site | vpls-protocol-state>

Description Information about all interfaces associated with a mesh-group.

Contents <interface>—No documentation is available yet.
 <mesh-group-id>—Mesh-group Identifier.
 <mesh-group-name>—Name of mesh-group.
 <mesh-group-state>—Mesh-group state.

<message-statistics>

Usage	<rsvp-statistics-information rsvp-interface> <message-statistics> <rsvp-message> <i>rsvp-message</i> </rsvp-message> <messages-sent> <i>messages-sent</i> </messages-sent> <messages-received> <i>messages-received</i> </messages-received> <messages-sent-5seconds> <i>messages-sent-5seconds</i> </messages-sent-5seconds> <messages-received-5seconds> <i>messages-received-5seconds</i> </messages-received-5seconds> </message-statistics> </rsvp-statistics-information rsvp-interface>
Description	Statistics per RSVP message type.
Contents	<messages-received>—Total number of messages received. <messages-received-5seconds>—Number of messages received in the last 5 seconds. <messages-sent>—Total number of messages sent. <messages-sent-5seconds>—Number of messages sent in the last 5 seconds. <rsvp-message>—No documentation is available yet.

<mgm-configured-parameters>

Usage	<igmp-interface-information mld-interface-information> <mgm-configured-parameters> <query-interval> <i>query-interval</i> </query-interval> <query-response-interval> <i>query-response-interval</i> </query-response-interval> <last-member-query-interval> <i>last-member-query-interval</i> </last-member-query-interval> <robustness-count> <i>robustness-count</i> </robustness-count> </mgm-configured-parameters> </igmp-interface-information mld-interface-information>
Description	No documentation is available yet.
Contents	<last-member-query-interval>—No documentation is available yet. <query-interval>—No documentation is available yet. <query-response-interval>—No documentation is available yet. <robustness-count>—No documentation is available yet.

<mgm-derived-parameters>

- Usage** <igmp-interface-information | mld-interface-information>
<mgm-derived-parameters>
 <membership-timeout>*membership-timeout*</membership-timeout>
 <query-other-timeout>*query-other-timeout*</query-other-timeout>
</mgm-derived-parameters>
 </igmp-interface-information | mld-interface-information>
- Description** No documentation is available yet.
- Contents** <membership-timeout>—No documentation is available yet.
 <query-other-timeout>—No documentation is available yet.

<mgm-group>

- Usage** <mgm-interface-groups>
<mgm-group>
 <multicast-group-address>*multicast-group-address*</multicast-group-address>
 <multicast-source-address>*multicast-source-address*</multicast-source-address>
 <mgm-source-timeout>*mgm-source-timeout*</mgm-source-timeout>
 <last-address>*last-address*</last-address>
 <mgm-timeout>*mgm-timeout*</mgm-timeout>
 <mgm-type>*mgm-type*</mgm-type>
 <mgm-group-mode-type>*mgm-group-mode-type*</mgm-group-mode-type>
 <host-record>...</host-record>
 <reverse-oif>...</reverse-oif>
</mgm-group>
 </mgm-interface-groups>
- Description** No documentation is available yet.
- Contents** <host-record>—No documentation is available yet.
 <last-address>—No documentation is available yet.
 <mgm-group-mode-type>—Group operational mode (Include/Exclude).
 <mgm-source-timeout>—Amount of time for which the traffic from source is forwarded.
 <mgm-timeout>—No documentation is available yet.
 <mgm-type>—No documentation is available yet.
 <multicast-group-address>—Group address.
 <multicast-source-address>—Source address.
 <reverse-oif>—No documentation is available yet.

<mgm-host>

Usage <mgm-interface>
 <mgm-host>
 <mgm-host-address>*mgm-host-address*</mgm-host-address>
 <mgm-host-record-count>*mgm-host-record-count*</mgm-host-record-count>
 </mgm-host>
 </mgm-interface>

Description No documentation is available yet.

Contents <mgm-host-address>—No documentation is available yet.
 <mgm-host-record-count>—No documentation is available yet.

<mgm-interface>

Usage <igmp-interface-information | mld-interface-information | igmp-hosts-information | mld-hosts-information>

```

<mgm-interface>
  <interface-name>interface-name</interface-name>
  <querier-address>querier-address</querier-address>
  <mgm-interface-state>mgm-interface-state</mgm-interface-state>
  <querier-timeout>querier-timeout</querier-timeout>
  <mgm-interface-version>mgm-interface-version</mgm-interface-version>
  <mgm-group-count>mgm-group-count</mgm-group-count>
  <mgm-ssm-map>mgm-ssm-map</mgm-ssm-map>
  <mgm-immediate-leave>mgm-immediate-leave</mgm-immediate-leave>
  <mgm-promiscuous-mode>mgm-promiscuous-mode</mgm-promiscuous-mode>
  <mgm-group-policy>mgm-group-policy</mgm-group-policy>
  <mgm-host>...</mgm-host>
</mgm-interface>
</igmp-interface-information | mld-interface-information | igmp-hosts-information | mld-hosts-information>

```

Description No documentation is available yet.

Contents <interface-name>—No documentation is available yet.

<mgm-group-count>—No documentation is available yet.

<mgm-group-policy>—Group filter applied to incoming Report messages.

<mgm-host>—No documentation is available yet.

<mgm-immediate-leave>—Groups are removed immediately without sending last membership queries.

<mgm-interface-state>—No documentation is available yet.

<mgm-interface-version>—No documentation is available yet.

<mgm-promiscuous-mode>—IGMP messages coming from different subnet are accepted.

<mgm-ssm-map>—Name of source-specific multicast map.

<querier-address>—No documentation is available yet.

<querier-timeout>—No documentation is available yet.

<mgm-interface-groups>

- Usage** <igmp-group-information | mld-group-information>
<mgm-interface-groups>
 <interface-name>*interface-name*</interface-name>
 <mgm-group>...</mgm-group>
</mgm-interface-groups>
 </igmp-group-information | mld-group-information>
- Description** No documentation is available yet.
- Contents** <interface-name>—No documentation is available yet.
 <mgm-group>—No documentation is available yet.

<mgm-other-statistic>

- Usage** <mgm-statistics-other | mgm-statistics-global | mgm-statistics-interface>
<mgm-other-statistic>
 <statistic-name>*statistic-name*</statistic-name>
 <statistic-count>*statistic-count*</statistic-count>
</mgm-other-statistic>
 </mgm-statistics-other | mgm-statistics-global | mgm-statistics-interface>
- Description** No documentation is available yet.
- Contents** <statistic-count>—No documentation is available yet.
 <statistic-name>—No documentation is available yet.

<mgm-statistic>

- Usage** <mgm-statistics-group | mgm-statistics-interface>
<mgm-statistic>
 <statistic-name>*statistic-name*</statistic-name>
 <received-count>*received-count*</received-count>
 <sent-count>*sent-count*</sent-count>
 <error-count>*error-count*</error-count>
</mgm-statistic>
 </mgm-statistics-group | mgm-statistics-interface>
- Description** No documentation is available yet.
- Contents** <error-count>—Total number of errors encountered.
 <received-count>—No documentation is available yet.
 <sent-count>—No documentation is available yet.
 <statistic-name>—No documentation is available yet.

<mgm-statistics-all>

- Usage** <igmp-statistics-information | mld-statistics-information>
<mgm-statistics-all>
 <mgm-statistics-group>...</mgm-statistics-group>
 <mgm-statistics-other>...</mgm-statistics-other>
 <mgm-statistics-global>...</mgm-statistics-global>
</mgm-statistics-all>
 </igmp-statistics-information | mld-statistics-information>
- Description** No documentation is available yet.
- Contents** <mgm-statistics-global>—No documentation is available yet.
 <mgm-statistics-group>—No documentation is available yet.
 <mgm-statistics-other>—No documentation is available yet.

<mgm-statistics-global>

- Usage** <mgm-statistics-interface | igmp-statistics-information | mgm-statistics-all | mld-statistics-information>
<mgm-statistics-global>
 <mgm-other-statistic>...</mgm-other-statistic>
</mgm-statistics-global>
 </mgm-statistics-interface | igmp-statistics-information | mgm-statistics-all | mld-statistics-information>
- Description** No documentation is available yet.
- Contents** <mgm-other-statistic>—No documentation is available yet.

<mgm-statistics-group>

- Usage** <mgm-statistics-interface | mgm-statistics-all>
<mgm-statistics-group>
 <mgm-statistic>...</mgm-statistic>
</mgm-statistics-group>
 </mgm-statistics-interface | mgm-statistics-all>
- Description** No documentation is available yet.
- Contents** <mgm-statistic>—No documentation is available yet.

<mgm-statistics-interface>

Usage <igmp-statistics-information | mld-statistics-information>
<mgm-statistics-interface>
 <interface-name>*interface-name*</interface-name>
 <mgm-disabled-interface-name>*mgm-disabled-interface-name*
 </mgm-disabled-interface-name>
 <mgm-interface-all/>
 <mgm-statistics-group>...</mgm-statistics-group>
 <mgm-statistics-other>...</mgm-statistics-other>
 <mgm-statistics-global>...</mgm-statistics-global>
 <mgm-statistic>...</mgm-statistic>
 <mgm-other-statistic>...</mgm-other-statistic>
</mgm-statistics-interface>
 </igmp-statistics-information | mld-statistics-information>

Description No documentation is available yet.

Contents <interface-name>—No documentation is available yet.

<mgm-disabled-interface-name>—No documentation is available yet.

<mgm-interface-all>—No documentation is available yet.

<mgm-other-statistic>—No documentation is available yet.

<mgm-statistic>—No documentation is available yet.

<mgm-statistics-global>—No documentation is available yet.

<mgm-statistics-group>—No documentation is available yet.

<mgm-statistics-other>—No documentation is available yet.

<mgm-statistics-other>

Usage <mgm-statistics-interface | igmp-statistics-information | mgm-statistics-all |
 mld-statistics-information>
<mgm-statistics-other>
 <mgm-other-statistic>...</mgm-other-statistic>
</mgm-statistics-other>
 </mgm-statistics-interface | igmp-statistics-information | mgm-statistics-all |
 mld-statistics-information>

Description No documentation is available yet.

Contents <mgm-other-statistic>—No documentation is available yet.

<mld-group-information>

Usage <rpc-reply>
 <mld-group-information>
 <mgm-interface-groups>...</mgm-interface-groups>
 </mld-group-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <mgm-interface-groups>—No documentation is available yet.

<mld-hosts-information>

Usage <rpc-reply>
 <mld-hosts-information>
 <mgm-disabled-interface-name>*mgm-disabled-interface-name*
 </mgm-disabled-interface-name>
 <mgm-interface>...</mgm-interface>
 </mld-hosts-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <mgm-disabled-interface-name>—No documentation is available yet.
 <mgm-interface>—No documentation is available yet.

<mld-interface-information>

Usage <rpc-reply>
 <mld-interface-information>
 <mgm-interface>...</mgm-interface>
 <mgm-configured-parameters>...</mgm-configured-parameters>
 <mgm-derived-parameters>...</mgm-derived-parameters>
 </mld-interface-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <mgm-configured-parameters>—No documentation is available yet.
 <mgm-derived-parameters>—No documentation is available yet.
 <mgm-interface>—No documentation is available yet.

<mld-statistics-information>

- Usage** <rpc-reply>
 <mld-statistics-information>
 <mgm-statistics-interface>...</mgm-statistics-interface>
 <mgm-statistics-other>...</mgm-statistics-other>
 <mgm-statistics-global>...</mgm-statistics-global>
 <mgm-statistics-all>...</mgm-statistics-all>
 </mld-statistics-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <mgm-statistics-all>—No documentation is available yet.
 <mgm-statistics-global>—No documentation is available yet.
 <mgm-statistics-interface>—No documentation is available yet.
 <mgm-statistics-other>—No documentation is available yet.

<mpls-admin-group>

- Usage** <mpls-admin-group-information>
 <mpls-admin-group>
 <admin-group-name>*admin-group-name*</admin-group-name>
 <index>*index*</index>
 </mpls-admin-group>
 </mpls-admin-group-information>
- Description** No documentation is available yet.
- Contents** <admin-group-name>—Name of the admin group.
 <index>—No documentation is available yet.

<mpls-admin-group-information>

- Usage** <rpc-reply>
 <mpls-admin-group-information>
 <mpls-admin-group>...</mpls-admin-group>
 </mpls-admin-group-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <mpls-admin-group>—No documentation is available yet.

<mpls-call-admission-control>

- Usage** <mpls-call-admission-control-information>
 <mpls-call-admission-control>
 <mpls-lsp>...</mpls-lsp>
 </mpls-call-admission-control>
 </mpls-call-admission-control-information>
- Description** No documentation is available yet.
- Contents** <mpls-lsp>—MPLS label-switched path information.

<mpls-call-admission-control-information>

- Usage** <rpc-reply>
 <mpls-call-admission-control-information>
 <mpls-call-admission-control>...</mpls-call-admission-control>
 </mpls-call-admission-control-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <mpls-call-admission-control>—No documentation is available yet.

<mpls-cspf>

- Usage** <mpls-cspf-information>
 <mpls-cspf>
 <cspf-queue>...</cspf-queue>
 <cspf-paths>...</cspf-paths>
 <cspf-timing>...</cspf-timing>
 </mpls-cspf>
 </mpls-cspf-information>
- Description** No documentation is available yet.
- Contents** <cspf-paths>—CSPF path computations statistics.
 <cspf-queue>—CSPF queue statistics.
 <cspf-timing>—CSPF timing statistics.

<mpls-cspf-information>

- Usage** <rpc-reply>
 <mpls-cspf-information>
 <mpls-cspf>...</mpls-cspf>
 </mpls-cspf-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <mpls-cspf>—No documentation is available yet.

<mpls-diffserv-te-information>

- Usage** <rpc-reply>
 <mpls-diffserv-te-information>
 <bandwidth-model>*bandwidth-model*</bandwidth-model>
 <te-class-map>...</te-class-map>
 </mpls-diffserv-te-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <bandwidth-model>—Bandwidth model in use.
 <te-class-map>—No documentation is available yet.

<mpls-error>

- Usage** <rpc-reply>
 <mpls-error>
 <mpls-error-msg>*mpls-error-msg*</mpls-error-msg>
 </mpls-error>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <mpls-error-msg>—MPLS error message.

<mpls-interface>

- Usage** <mpls-interface-information>
 <mpls-interface>
 <interface-name>*interface-name*</interface-name>
 <mpls-interface-state>*mpls-interface-state*</mpls-interface-state>
 <no-group-flag/>
 <admin-group-name>*admin-group-name*</admin-group-name>
 <admin-group-number>*admin-group-number*</admin-group-number>
 </mpls-interface>
 </mpls-interface-information>
- Description** No documentation is available yet.
- Contents** <admin-group-name>—Name of the admin group.
 <admin-group-number>—Number of the admin group.
 <interface-name>—No documentation is available yet.
 <mpls-interface-state>—No documentation is available yet.
 <no-group-flag>—No documentation is available yet.

<mpls-interface-information>

Usage <rpc-reply>
 <mpls-interface-information>
 <mpls-interface>...</mpls-interface>
 </mpls-interface-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <mpls-interface>—No documentation is available yet.

<mpls-lsp>

Usage <rsvp-session | mpls-call-admission-control>

```

<mpls-lsp>
  <destination-address>destination-address</destination-address>
  <source-address>source-address</source-address>
  <lsp-state>lsp-state</lsp-state>
  <route-count>route-count</route-count>
  <active-path>active-path</active-path>
  <is-primary/>
  <name>name</name>
  <bidirectional/>
  <lsp-description>lsp-description</lsp-description>
  <lsp-pktbytes>lsp-pktbytes</lsp-pktbytes>
  <no-statistics/>
  <mpls-p2mp-name>mpls-p2mp-name</mpls-p2mp-name>
  <is-fastreroute/>
  <is-linkprotection/>
  <is-nodeprotection/>
  <requires-intra-domain-path/>
  <load-balance>load-balance</load-balance>
  <lsp-diffserv-te-info>lsp-diffserv-te-info</lsp-diffserv-te-info>
  <metric>metric</metric>
  <revert-timer>revert-timer</revert-timer>
  <revert-timer-remain>revert-timer-remain</revert-timer-remain>
  <optimize-protection-timer>optimize-protection-timer
    </optimize-protection-timer>
  <admin-groups>...</admin-groups>
  <lsp-creation-time>lsp-creation-time</lsp-creation-time>
  <lsp-soft-preemption-counter>lsp-soft-preemption-counter
    </lsp-soft-preemption-counter>
  <lsp-soft-preemption-time>lsp-soft-preemption-time</lsp-soft-preemption-time>
  <retry-timer>retry-timer</retry-timer>
  <retry-limit>retry-limit</retry-limit>
  <mpls-lsp-autobandwidth>...</mpls-lsp-autobandwidth>
  <mpls-lsp-path>...</mpls-lsp-path>
  <mpls-lsp-attributes>...</mpls-lsp-attributes>
</mpls-lsp>
</rsvp-session | mpls-call-admission-control>

```

Description MPLS label-switched path information.

Contents

- <active-path>—Path that the LSP is currently using.
- <admin-groups>—No documentation is available yet.
- <bidirectional>—LSP is bidirectional.
- <destination-address>—Session destination address.
- <is-fastreroute>—Detours will be established for an LSP so that if a node or link in the LSP fails, the traffic on the LSP can be rerouted with minimal packet loss.
- <is-linkprotection>—Protect links via bypass LSPs.

<is-nodeprotection>—Protect link/node via bypass LSPs.

<is-primary>—Path is a primary path.

<load-balance>—Load-balancing algorithm chosen.

<lsp-creation-time>—Time when the LSP was created.

<lsp-description>—LSP description string (up to 80 characters).

<lsp-diffserv-te-info>—LSP support of DiffServ-TE extensions.

<lsp-pktbytes>—No documentation is available yet.

<lsp-soft-preemption-counter>—Number of times the LSP was soft preempted.

<lsp-soft-preemption-time>—Time when the LSP was last soft preempted.

<lsp-state>—State of an LSP.

<metric>—No documentation is available yet.

<mpls-lsp-attributes>—No documentation is available yet.

<mpls-lsp-autobandwidth>—No documentation is available yet.

<mpls-lsp-path>—Primary or secondary LSP path.

<mpls-p2mp-name>—No documentation is available yet.

<name>—No documentation is available yet.

<no-statistics>—No statistics are available for this session.

<optimize-protection-timer>—Optimize interval for fast-reroute detours, or link-protection bypasses.

<requires-intra-domain-path>—LSP path should be within the TE domain.

<retry-limit>—Maximum number of times the ingress tries to establish the primary path. It is reset each time primary path is created successfully.

<retry-timer>—Amount of time the ingress router waits between attempts to establish primary path.

<revert-timer>—Hold-down time before reverting to primary path.

<revert-timer-remain>—Time remaining before reverting:.

<route-count>—Number of active routes.

<source-address>—No documentation is available yet.

<mpls-lsp-attributes>

Usage <mpls-lsp | mpls-restart-lsp>
<mpls-lsp-attributes>
 <signal-type>*signal-type*</signal-type>
 <encoding-type>*encoding-type*</encoding-type>
 <switching-type>*switching-type*</switching-type>
 <gpId>*gpId*</gpId>
 <protection-type>*protection-type*</protection-type>
</mpls-lsp-attributes>
 </mpls-lsp | mpls-restart-lsp>

Description No documentation is available yet.

Contents <encoding-type>—LSP encoding type.

<gpId>—LSP generalized PID.

<protection-type>—LSP protection desired.

<signal-type>—No documentation is available yet.

<switching-type>—LSP switching capability.

<mpls-lsp-autobandwidth>

Usage <mpls-lsp>
 <mpls-lsp-autobandwidth>
 <monitor-lsp-bandwidth/>
 <minimum-bandwidth>*minimum-bandwidth*</minimum-bandwidth>
 <maximum-bandwidth>*maximum-bandwidth*</maximum-bandwidth>
 <adjust-timer>*adjust-timer*</adjust-timer>
 <bandwidth>*bandwidth*</bandwidth>
 <time-to-adjust>*time-to-adjust*</time-to-adjust>
 <adjust-threshold>*adjust-threshold*</adjust-threshold>
 <overflow-limit>*overflow-limit*</overflow-limit>
 <overflow-sample-count>*overflow-sample-count*</overflow-sample-count>
 </mpls-lsp-autobandwidth>
 </mpls-lsp>

Description No documentation is available yet.

Contents <adjust-threshold>—Percentage change in average LSP utilization to trigger autoadjustment.

<adjust-timer>—Configured LSP adjust timer.

<bandwidth>—No documentation is available yet.

<maximum-bandwidth>—Configured LSP maximum bandwidth.

<minimum-bandwidth>—Configured LSP minimum bandwidth.

<monitor-lsp-bandwidth>—LSP adjusts bandwidth automatically, but continue to passively monitor the maximum average bandwidth usage of the LSP.

<overflow-limit>—On encountering the configured limit of consecutive overflow samples, LSP will attempt to autoadjust bandwidth.

<overflow-sample-count>—Number of consecutive overflow samples encountered.

<time-to-adjust>—Time in which LSP will autoadjust bandwidth.

<mpls-lsp-defaults>

Usage	<pre> <mpls-lsp-defaults-information> <mpls-lsp-defaults> <lsp-setup-priority>lsp-setup-priority</lsp-setup-priority> <lsp-hold-priority>lsp-hold-priority</lsp-hold-priority> <lsp-retry-timer>lsp-retry-timer</lsp-retry-timer> <lsp-hoplimit>lsp-hoplimit</lsp-hoplimit> <lsp-bandwidth>lsp-bandwidth</lsp-bandwidth> </mpls-lsp-defaults> </mpls-lsp-defaults-information> </pre>
Description	No documentation is available yet.
Contents	<p><lsp-bandwidth>—Default LSP Bandwidth.</p> <p><lsp-hold-priority>—Hold priority determines whether a session can be preempted by another session. Range is 0 to 7.</p> <p><lsp-hoplimit>—Maximum number of hops that can be traversed.</p> <p><lsp-retry-timer>—Amount of time the ingress router waits between attempts to establish primary path.</p> <p><lsp-setup-priority>—Setup priority determines the ability of a session to preempt existing session. Range is 0 to 7.</p>

<mpls-lsp-defaults-information>

Usage	<pre> <rpc-reply> <mpls-lsp-defaults-information> <mpls-lsp-defaults>...</mpls-lsp-defaults> </mpls-lsp-defaults-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<mpls-lsp-defaults>—No documentation is available yet.

<mpls-lsp-information>

Usage	<pre> <rpc-reply> <mpls-lsp-information> <rsvp-session-data>...</rsvp-session-data> </mpls-lsp-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<rsvp-session-data>—No documentation is available yet.

<mpls-lsp-path>

Usage <mpls-lsp>
 <mpls-lsp-path>
 <path-active/>
 <title>*title*</title>
 <name>*name*</name>
 <path-state>*path-state*</path-state>
 <cos>*cos*</cos>
 <no-decrement-ttl/>
 <preference>*preference*</preference>
 <path-soft-preemption-pending/>
 <setup-priority>*setup-priority*</setup-priority>
 <hold-priority>*hold-priority*</hold-priority>
 <bandwidth>*bandwidth*</bandwidth>
 <actual-bandwidth>*actual-bandwidth*</actual-bandwidth>
 <per-class-bandwidth-heading>*per-class-bandwidth-heading*
 </per-class-bandwidth-heading>
 <bandwidth_ct0>*bandwidth_ct0*</bandwidth_ct0>
 <bandwidth_ct1>*bandwidth_ct1*</bandwidth_ct1>
 <bandwidth_ct2>*bandwidth_ct2*</bandwidth_ct2>
 <bandwidth_ct3>*bandwidth_ct3*</bandwidth_ct3>
 <path-adaptive/>
 <path-no-recordroute/>
 <hoplimit>*hoplimit*</hoplimit>
 <optimize-timer>*optimize-timer*</optimize-timer>
 <smart-optimize-timer>*smart-optimize-timer*</smart-optimize-timer>
 <admin-groups>...</admin-groups>
 <retry-timer>*retry-timer*</retry-timer>
 <retry-limit>*retry-limit*</retry-limit>
 <cspf-status>*cspf-status*</cspf-status>
 <explicit-route>...</explicit-route>
 <received-rro>*received-rro*</received-rro>
 <oam-state>*oam-state*</oam-state>
 <path-history>...</path-history>
 <path-available-bandwidth>...</path-available-bandwidth>
 <layer2-connection>...</layer2-connection>
 </mpls-lsp-path>
 </mpls-lsp>

Description Primary or secondary LSP path.

Contents <actual-bandwidth>—No documentation is available yet.

<admin-groups>—No documentation is available yet.

<bandwidth>—No documentation is available yet.

<bandwidth_ct0>—No documentation is available yet.

<bandwidth_ct1>—No documentation is available yet.

<bandwidth_ct2>—No documentation is available yet.

<bandwidth_ct3>—No documentation is available yet.

<cos>—CoS value.

<cspf-status>—Status returned by CSPF computation.

<explicit-route>—Explicit Route Object (ERO).

<hold-priority>—Hold priority determines whether a session can be preempted by another session. Range is 0 to 7.

<hoplimit>—Maximum number of hops that can be traversed.

<layer2-connection>—Layer 2 connection using the LSP path.

<name>—No documentation is available yet.

<no-decrement-ttl>—TTL.

<oam-state>—OAM state information.

<optimize-timer>—Frequency of reoptimization operation for LSPs that are already set up. It is useful only when CSPF is enabled.

<path-active>—Whether the path is active or not.

<path-adaptive>—During reroute, the bandwidth on links shared by the old and new paths is not double-counted. SE-style reservation is used to assist in smooth transition during rerouting.

<path-available-bandwidth>—Available bandwidth on an LSP path.

<path-history>—Log over time of LSP path-related events.

<path-no-recordroute>—LSP does not actively record routes in the path.

<path-soft-preemption-pending>—Soft preemption pending for this path.

<path-state>—State of the MPLS path.

<per-class-bandwidth-heading>—No documentation is available yet.

<preference>—Preference value configured with the preference statement. The default preference value is 170.

<received-rro>—RRO returned by the signaling protocol.

<retry-limit>—Maximum number of times the ingress tries to establish the primary path. It is reset each time primary path is created successfully.

<retry-timer>—Amount of time the ingress router waits between attempts to establish primary path.

<setup-priority>—Setup priority determines the ability of a session to preempt existing session. Range is 0 to 7.

<smart-optimize-timer>—Path optimization interval after a link traversed by the path

goes down.

<title>—No documentation is available yet.

<mpls-p2mp-lsp>

Usage <rsvp-session-data>
 <mpls-p2mp-lsp>
 <mpls-p2mp-name>*mpls-p2mp-name*</mpls-p2mp-name>
 <mpls-p2mp-branch-count>*mpls-p2mp-branch-count*</mpls-p2mp-branch-count>
 </mpls-p2mp-lsp>
 </rsvp-session-data>

Description No documentation is available yet.

Contents <mpls-p2mp-branch-count>—No documentation is available yet.
 <mpls-p2mp-name>—No documentation is available yet.

<mpls-path>

Usage <mpls-path-information>
 <mpls-path>
 <name>*name*</name>
 <address>*address*</address>
 <path-type>*path-type*</path-type>
 <telink-id>*telink-id*</telink-id>
 </mpls-path>
 </mpls-path-information>

Description No documentation is available yet.

Contents <address>—No documentation is available yet.
 <name>—No documentation is available yet.
 <path-type>—No documentation is available yet.
 <telink-id>—Link identifier of unnumbered link.

<mpls-path-information>

Usage <rpc-reply>
 <mpls-path-information>
 <mpls-path>...</mpls-path>
 </mpls-path-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <mpls-path>—No documentation is available yet.

<mpls-restart-database>

Usage <mpls-restart-database-information>
 <mpls-restart-database>
 <mpls-restart-lsp>...</mpls-restart-lsp>
 </mpls-restart-database>
 </mpls-restart-database-information>

Description No documentation is available yet.

Contents <mpls-restart-lsp>—No documentation is available yet.

<mpls-restart-database-information>

Usage <rpc-reply>
 <mpls-restart-database-information>
 <mpls-restart-database>...</mpls-restart-database>
 </mpls-restart-database-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <mpls-restart-database>—No documentation is available yet.

<mpls-restart-lsp>

Usage <mpls-restart-database>
 <mpls-restart-lsp>
 <name>*name*</name>
 <destination-address>*destination-address*</destination-address>
 <source-address>*source-address*</source-address>
 <lsp-state>*lsp-state*</lsp-state>
 <lsp-flags>*lsp-flags*</lsp-flags>
 <lsp-path-count>*lsp-path-count*</lsp-path-count>
 <mpls-lsp-attributes>...</mpls-lsp-attributes>
 <mpls-restart-path>...</mpls-restart-path>
 </mpls-restart-lsp>
 </mpls-restart-database>

Description No documentation is available yet.

Contents <destination-address>—Session destination address.

<lsp-flags>—No documentation is available yet.

<lsp-path-count>—No documentation is available yet.

<lsp-state>—State of an LSP.

<mpls-lsp-attributes>—No documentation is available yet.

<mpls-restart-path>—No documentation is available yet.

<name>—No documentation is available yet.

<source-address>—No documentation is available yet.

<mpls-restart-path>

Usage <mpls-restart-lsp>
 <mpls-restart-path>
 <lsp-path-type>lsp-path-type</lsp-path-type>
 <name>name</name>
 <path-standby/>
 <path-active/>
 <path-state>path-state</path-state>
 <lsp-id>lsp-id</lsp-id>
 <tunnel-id>tunnel-id</tunnel-id>
 <path-flags>path-flags</path-flags>
 <bandwidth>bandwidth</bandwidth>
 <per-class-bandwidth-heading>per-class-bandwidth-heading
 </per-class-bandwidth-heading>
 <bandwidth_ct0>bandwidth_ct0</bandwidth_ct0>
 <bandwidth_ct1>bandwidth_ct1</bandwidth_ct1>
 <bandwidth_ct2>bandwidth_ct2</bandwidth_ct2>
 <bandwidth_ct3>bandwidth_ct3</bandwidth_ct3>
 <explicit-route>...</explicit-route>
 <mpls-restart-rsvp>...</mpls-restart-rsvp>
 </mpls-restart-path>
 </mpls-restart-lsp>

Description No documentation is available yet.

Contents <bandwidth>—No documentation is available yet.

<bandwidth_ct0>—No documentation is available yet.

<bandwidth_ct1>—No documentation is available yet.

<bandwidth_ct2>—No documentation is available yet.

<bandwidth_ct3>—No documentation is available yet.

<explicit-route>—Explicit Route Object (ERO).

<lsp-id>—LSP ID or source port for some sender. It is unique to every sender or LSP.

<lsp-path-type>—Primary or secondary LSP path.

<mpls-restart-rsvp>—No documentation is available yet.

<name>—No documentation is available yet.

<path-active>—Whether the path is active or not.

<path-flags>—No documentation is available yet.

<path-standby>—No documentation is available yet.

<path-state>—State of the MPLS path.

<per-class-bandwidth-heading>—No documentation is available yet.

< tunnel-id>—Tunnel ID or destination port for this session. It is unique to every session.

<mpls-restart-rsvp>

Usage <mpls-restart-path>
 <mpls-restart-rsvp>
 <next-hop>next-hop</next-hop>
 <interface-name>interface-name</interface-name>
 <telink-name>telink-name</telink-name>
 <upstream-label-in>upstream-label-in</upstream-label-in>
 <label-out>label-out</label-out>
 <self-id>self-id</self-id>
 <explicit-route>...</explicit-route>
 </mpls-restart-rsvp>
 </mpls-restart-path>

Description No documentation is available yet.

Contents <explicit-route>—Explicit Route Object (ERO).

<interface-name>—No documentation is available yet.

<label-out>—Outgoing label.

<next-hop>—Next-hop address.

<self-id>—Unique identifier for RSVP path state control block.

<telink-name>—Name of the TE link.

<upstream-label-in>—Incoming upstream label.

<msdp-instance>

Usage	<pre> <msdp-source-active-information msdp-source-information msdp-statistics-information> <msdp-instance> <instance-name><i>instance-name</i></instance-name> <msdp-no-routes><i>msdp-no-routes</i></msdp-no-routes> <msdp-route>...</msdp-route> <msdp-no-source><i>msdp-no-source</i></msdp-no-source> <msdp-source>...</msdp-source> <msdp-global-active-source-limit-exceeded><i>msdp-global-active-source-limit-exceeded</i> </msdp-global-active-source-limit-exceeded> <msdp-peer-statistics>...</msdp-peer-statistics> </msdp-instance> </msdp-source-active-information msdp-source-information msdp-statistics-information> </pre>
Description	No documentation is available yet.
Contents	<p><instance-name>—No documentation is available yet.</p> <p><msdp-global-active-source-limit-exceeded>—No documentation is available yet.</p> <p><msdp-no-routes>—No documentation is available yet.</p> <p><msdp-no-source>—No documentation is available yet.</p> <p><msdp-peer-statistics>—No documentation is available yet.</p> <p><msdp-route>—No documentation is available yet.</p> <p><msdp-source>—No documentation is available yet.</p>

<msdp-peer>

Usage <msdp-peer-information>
 <msdp-peer>
 <msdp-peer-address>*msdp-peer-address*</msdp-peer-address>
 <msdp-local-address>*msdp-local-address*</msdp-local-address>
 <msdp-state>*msdp-state*</msdp-state>
 <msdp-state-change>*msdp-state-change*</msdp-state-change>
 <msdp-group-name>*msdp-group-name*</msdp-group-name>
 <msdp-connect-retries>*msdp-connect-retries*</msdp-connect-retries>
 <msdp-state-timeout>*msdp-state-timeout*</msdp-state-timeout>
 <msdp-peer-timeout>*msdp-peer-timeout*</msdp-peer-timeout>
 <msdp-sa-accepted>*msdp-sa-accepted*</msdp-sa-accepted>
 <msdp-sa-received>*msdp-sa-received*</msdp-sa-received>
 </msdp-peer>
 </msdp-peer-information>

Description No documentation is available yet.

Contents <msdp-connect-retries>—No documentation is available yet.
 <msdp-group-name>—No documentation is available yet.
 <msdp-local-address>—No documentation is available yet.
 <msdp-peer-address>—No documentation is available yet.
 <msdp-peer-timeout>—No documentation is available yet.
 <msdp-sa-accepted>—Number of SAs accepted from peer.
 <msdp-sa-received>—Number of SAs received from peer.
 <msdp-state>—No documentation is available yet.
 <msdp-state-change>—No documentation is available yet.
 <msdp-state-timeout>—No documentation is available yet.

<msdp-peer-information>

Usage <rpc-reply>
 <msdp-peer-information>
 <msdp-no-peers/>
 <msdp-peer>...</msdp-peer>
 </msdp-peer-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <msdp-no-peers>—No documentation is available yet.
 <msdp-peer>—No documentation is available yet.

<msdp-peer-statistics>

Usage <msdp-instance>
<msdp-peer-statistics>
 <msdp-peer-address>*msdp-peer-address*</msdp-peer-address>
 <msdp-state-change-absolute>*msdp-state-change-absolute*
 </msdp-state-change-absolute>
 <msdp-state-change>*msdp-state-change*</msdp-state-change>
 <msdp-message-received-absolute>*msdp-message-received-absolute*
 </msdp-message-received-absolute>
 <msdp-message-received>*msdp-message-received*</msdp-message-received>
 <msdp-rpf-failures>*msdp-rpf-failures*</msdp-rpf-failures>
 <msdp-remote-closes>*msdp-remote-closes*</msdp-remote-closes>
 <msdp-peer-timeouts>*msdp-peer-timeouts*</msdp-peer-timeouts>
 <msdp-sa-messages-sent>*msdp-sa-messages-sent*</msdp-sa-messages-sent>
 <msdp-sa-messages-received>*msdp-sa-messages-received*
 </msdp-sa-messages-received>
 <msdp-sa-requests-sent>*msdp-sa-requests-sent*</msdp-sa-requests-sent>
 <msdp-sa-requests-received>*msdp-sa-requests-received*
 </msdp-sa-requests-received>
 <msdp-sa-responses-sent>*msdp-sa-responses-sent*</msdp-sa-responses-sent>
 <msdp-sa-responses-received>*msdp-sa-responses-received*
 </msdp-sa-responses-received>
 <msdp-active-source-limit-exceeded>*msdp-active-source-limit-exceeded*
 </msdp-active-source-limit-exceeded>
 <msdp-keepalives-sent>*msdp-keepalives-sent*</msdp-keepalives-sent>
 <msdp-keepalives-received>*msdp-keepalives-recd*</msdp-keepalives-received>
 <msdp-unknowns-received>*msdp-unknowns-received*</msdp-unknowns-received>
 <msdp-errors-received>*msdp-errors-received*</msdp-errors-received>
</msdp-peer-statistics>
 </msdp-instance>

Description No documentation is available yet.

Contents <msdp-active-source-limit-exceeded>—No documentation is available yet.
 <msdp-errors-received>—No documentation is available yet.
 <msdp-keepalives-received>—No documentation is available yet.
 <msdp-keepalives-sent>—No documentation is available yet.
 <msdp-message-received>—No documentation is available yet.
 <msdp-message-received-absolute>—No documentation is available yet.
 <msdp-peer-address>—No documentation is available yet.
 <msdp-peer-timeouts>—No documentation is available yet.
 <msdp-remote-closes>—No documentation is available yet.
 <msdp-rpf-failures>—No documentation is available yet.
 <msdp-sa-messages-received>—No documentation is available yet.

<msdp-sa-messages-sent>—No documentation is available yet.

<msdp-sa-requests-received>—No documentation is available yet.

<msdp-sa-requests-sent>—No documentation is available yet.

<msdp-sa-responses-received>—No documentation is available yet.

<msdp-sa-responses-sent>—No documentation is available yet.

<msdp-state-change>—No documentation is available yet.

<msdp-state-change-absolute>—No documentation is available yet.

<msdp-unknowns-received>—No documentation is available yet.

<msdp-route>

Usage <msdp-instance>
 <msdp-route>
 <multicast-group-address>*multicast-group-address*</multicast-group-address>
 <multicast-source-address>*multicast-source-address*</multicast-source-address>
 <msdp-route-peer>...</msdp-route-peer>
 </msdp-route>
 </msdp-instance>

Description No documentation is available yet.

Contents <msdp-route-peer>—No documentation is available yet.

<multicast-group-address>—Group address.

<multicast-source-address>—Source address.

<msdp-route-peer>

Usage <msdp-route>
 <msdp-route-peer>
 <msdp-peer-address>*msdp-peer-address*</msdp-peer-address>
 <msdp-originator>*msdp-originator*</msdp-originator>
 <msdp-route-peer-flags>...</msdp-route-peer-flags>
 </msdp-route-peer>
 </msdp-route>

Description No documentation is available yet.

Contents <msdp-originator>—No documentation is available yet.

<msdp-peer-address>—No documentation is available yet.

<msdp-route-peer-flags>—No documentation is available yet.

<msdp-route-peer-flags>

Usage	<pre> <msdp-route-peer> <msdp-route-peer-flags> <msdp-accept/> <msdp-reject/> <msdp-filtered/> </msdp-route-peer-flags> </msdp-route-peer> </pre>
Description	No documentation is available yet.
Contents	<p><msdp-accept>—No documentation is available yet.</p> <p><msdp-filtered>—No documentation is available yet.</p> <p><msdp-reject>—No documentation is available yet.</p>

<msdp-source>

Usage	<pre> <msdp-instance> <msdp-source> <msdp-source-prefix>msdp-source-prefix</msdp-source-prefix> <msdp-source-prefix-length>msdp-source-prefix-length </msdp-source-prefix-length> <msdp-source-type>msdp-source-type</msdp-source-type> <msdp-source-limit-maximum>msdp-source-limit-maximum </msdp-source-limit-maximum> <msdp-source-limit-threshold>msdp-source-limit-threshold </msdp-source-limit-threshold> <msdp-source-limit-exceeded>msdp-source-limit-exceeded </msdp-source-limit-exceeded> </msdp-source> </msdp-instance> </pre>
Description	No documentation is available yet.
Contents	<p><msdp-source-limit-exceeded>—No documentation is available yet.</p> <p><msdp-source-limit-maximum>—No documentation is available yet.</p> <p><msdp-source-limit-threshold>—No documentation is available yet.</p> <p><msdp-source-prefix>—No documentation is available yet.</p> <p><msdp-source-prefix-length>—No documentation is available yet.</p> <p><msdp-source-type>—No documentation is available yet.</p>

<msdp-source-active-information>

Usage <rpc-reply>
 <msdp-source-active-information>
 <msdp-instance>...</msdp-instance>
 </msdp-source-active-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <msdp-instance>—No documentation is available yet.

<msdp-source-information>

Usage <rpc-reply>
 <msdp-source-information>
 <msdp-instance>...</msdp-instance>
 </msdp-source-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <msdp-instance>—No documentation is available yet.

<msdp-statistics-information>

Usage <rpc-reply>
 <msdp-statistics-information>
 <msdp-no-peer>*msdp-no-peer*</msdp-no-peer>
 <msdp-instance>...</msdp-instance>
 </msdp-statistics-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <msdp-instance>—No documentation is available yet.

 <msdp-no-peer>—No documentation is available yet.

<mt-tlv>

Usage <isis-tlv>
 <mt-tlv>
 <mtid>*mtid*</mtid>
 </mt-tlv>
 </isis-tlv>

Description No documentation is available yet.

Contents <mtid>—No documentation is available yet.

<multicast-backup-pe-address-information>

Usage <rpc-reply>
 <multicast-backup-pe-address-information>
 <multicast-backup-pe-address>*multicast-backup-pe-address*
 </multicast-backup-pe-address>
 <multicast-backup-pe-group-list>...</multicast-backup-pe-group-list>
 <pe-address-local>*pe-address-local*</pe-address-local>
 <lsp-to-pe-up>*lsp-to-pe-up*</lsp-to-pe-up>
 </multicast-backup-pe-address-information>
 </rpc-reply>

Description Information about multicast backup PE.

Contents <lsp-to-pe-up>—Indicates if the LSP to this PE is up.

<multicast-backup-pe-address>—Backup PE address.

<multicast-backup-pe-group-list>—Information about multicast backup PE groups associatd with PE.

<pe-address-local>—Indicates if this address belongs to this local PE.

<multicast-backup-pe-group>

Usage <multicast-backup-pe-groups>
 <multicast-backup-pe-group>
 <multicast-backup-pe-group-name>*multicast-backup-pe-group-name*
 </multicast-backup-pe-group-name>
 <designated-pe>*designated-pe*</designated-pe>
 <transitions>*transitions*</transitions>
 <last-transition>*last-transition*</last-transition>
 <local-pe-address>*local-pe-address*</local-pe-address>
 <backup-pes>...</backup-pes>
 </multicast-backup-pe-group>
 </multicast-backup-pe-groups>

Description Information about a multicast backup PE group.

Contents <backup-pes>—Backup PE addresses.

<designated-pe>—Address of the designated PE.

<last-transition>—Time since last designated PE transition (hours:minutes:seconds).

<local-pe-address>—Local address used in designated router election.

<multicast-backup-pe-group-name>—Name of the backup PE group.

<transitions>—Number of times desginated PE has changed.

<multicast-backup-pe-group-list>

- Usage** `<multicast-backup-pe-address-information>`
 <multicast-backup-pe-group-list>
 `<multicast-backup-pe-group-member>...</multicast-backup-pe-group-member>`
 </multicast-backup-pe-group-list>
`</multicast-backup-pe-address-information>`
- Description** Information about multicast backup PE groups associatd with PE.
- Contents** `<multicast-backup-pe-group-member>`—Information about a multicast backup PE group.

<multicast-backup-pe-group-member>

- Usage** `<multicast-backup-pe-group-list>`
 <multicast-backup-pe-group-member>
 `<multicast-backup-pe-group-name>multicast-backup-pe-group-name`
 `</multicast-backup-pe-group-name>`
 </multicast-backup-pe-group-member>
`</multicast-backup-pe-group-list>`
- Description** Information about a multicast backup PE group.
- Contents** `<multicast-backup-pe-group-name>`—Name of the backup PE group.

<multicast-backup-pe-groups>

- Usage** `<multicast-backup-pe-groups-information>`
 <multicast-backup-pe-groups>
 `<instance-name>instance-name</instance-name>`
 `<multicast-backup-pe-group>...</multicast-backup-pe-group>`
 </multicast-backup-pe-groups>
`</multicast-backup-pe-groups-information>`
- Description** Information about multicast backup PE groups for one routing instance.
- Contents** `<instance-name>`—No documentation is available yet.
- `<multicast-backup-pe-group>`—Information about a multicast backup PE group.

<multicast-backup-pe-groups-information>

- Usage** `<rpc-reply>`
 <multicast-backup-pe-groups-information>
 `<multicast-backup-pe-groups>...</multicast-backup-pe-groups>`
 </multicast-backup-pe-groups-information>
`</rpc-reply>`
- Description** Information about multicast backup PE groups for one or more routing instances.
- Contents** `<multicast-backup-pe-groups>`—Information about multicast backup PE groups for one routing instance.

<multicast-flow-map>

Usage <multicast-flow-maps>
 <multicast-flow-map>
 <flow-map-name>*flow-map-name*</flow-map-name>
 <policy-name>*policy-name*</policy-name>
 <cache-timeout>*cache-timeout*</cache-timeout>
 <flow-bandwidth>*flow-bandwidth*</flow-bandwidth>
 <bandwidth-type>*bandwidth-type*</bandwidth-type>
 <redundant-sources>...</redundant-sources>
 </multicast-flow-map>
 </multicast-flow-maps>

Description Information about a multicast flow map.

Contents <bandwidth-type>—Bandwidth type for matched flows.

<cache-timeout>—Delay before discarding a matched cache entry.

<flow-bandwidth>—Bandwidth for matched flows.

<flow-map-name>—Name of the flow map.

<policy-name>—Name of the policy.

<redundant-sources>—Redundant source addresses.

<multicast-flow-maps>

Usage <multicast-flow-maps-information>
 <multicast-flow-maps>
 <instance-name>*instance-name*</instance-name>
 <multicast-flow-map>...</multicast-flow-map>
 </multicast-flow-maps>
 </multicast-flow-maps-information>

Description Information about multicast flow maps for one routing instance.

Contents <instance-name>—No documentation is available yet.

<multicast-flow-map>—Information about a multicast flow map.

<multicast-flow-maps-information>

Usage <rpc-reply>
 <multicast-flow-maps-information>
 <multicast-flow-maps>...</multicast-flow-maps>
 </multicast-flow-maps-information>
 </rpc-reply>

Description Information about multicast flow maps for one or more routing instances.

Contents <multicast-flow-maps>—Information about multicast flow maps for one routing instance.

<multicast-group>

Usage <multicast-usage-information>
 <multicast-group>
 <multicast-group-address>*multicast-group-address*</multicast-group-address>
 <multicast-source-count>*multicast-source-count*</multicast-source-count>
 <multicast-packet-count>*multicast-packet-count*</multicast-packet-count>
 <multicast-byte-count>*multicast-byte-count*</multicast-byte-count>
 <multicast-group-source>...</multicast-group-source>
 </multicast-group>
 </multicast-usage-information>

Description No documentation is available yet.

Contents <multicast-byte-count>—No documentation is available yet.
 <multicast-group-address>—Group address.
 <multicast-group-source>—No documentation is available yet.
 <multicast-packet-count>—No documentation is available yet.
 <multicast-source-count>—No documentation is available yet.

<multicast-group-source>

Usage <multicast-group>
 <multicast-group-source>
 <multicast-source-address>*multicast-source-address*</multicast-source-address>
 <multicast-source-prefix-length>*multicast-source-prefix-length*
 </multicast-source-prefix-length>
 <multicast-packet-count>*multicast-packet-count*</multicast-packet-count>
 <multicast-byte-count>*multicast-byte-count*</multicast-byte-count>
 </multicast-group-source>
 </multicast-group>

Description No documentation is available yet.

Contents <multicast-byte-count>—No documentation is available yet.
 <multicast-packet-count>—No documentation is available yet.
 <multicast-source-address>—Source address.
 <multicast-source-prefix-length>—Source prefix length.

<multicast-interface>

Usage <multicast-interface-information>
 <multicast-interface>
 <interface-name>*interface-name*</interface-name>
 <interface-max-bandwidth>*interface-max-bandwidth*</interface-max-bandwidth>
 <interface-remaining-bandwidth>*interface-remaining-bandwidth*
 </interface-remaining-bandwidth>
 <interface-reverse-oif-mapping>*interface-reverse-oif-mapping*
 </interface-reverse-oif-mapping>
 <interface-subscriber-leave-timer>*interface-subscriber-leave-timer*
 </interface-subscriber-leave-timer>
 </multicast-interface>
 </multicast-interface-information>

Description Information about a multicast interface.

Contents <interface-max-bandwidth>—Maximum bandwidth for multicast flows.
 <interface-name>—No documentation is available yet.
 <interface-remaining-bandwidth>—Remaining bandwidth for multicast flows.
 <interface-reverse-oif-mapping>—Reverse OIF mapping is enabled.
 <interface-subscriber-leave-timer>—Bw restore waiting time after subscriber leaves group.

<multicast-interface-information>

Usage <rpc-reply>
 <multicast-interface-information>
 <multicast-interface>...</multicast-interface>
 </multicast-interface-information>
 </rpc-reply>

Description Information about one or more multicast interfaces.

Contents <multicast-interface>—Information about a multicast interface.

<multicast-next-hops-information>

Usage <rpc-reply>
 <multicast-next-hops-information>
 <next-hops-family>...</next-hops-family>
 </multicast-next-hops-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <next-hops-family>—No documentation is available yet.

<multicast-route>

Usage <route-family>
<multicast-route>
 <multicast-group-address>*multicast-group-address*</multicast-group-address>
 <multicast-source-address>*multicast-source-address*</multicast-source-address>
 <multicast-route-vlan-id>*multicast-route-vlan-id*</multicast-route-vlan-id>
 <multicast-route-bridge-domain>*multicast-route-bridge-domain*
 </multicast-route-bridge-domain>
 <multicast-route-mesh-group>*multicast-route-mesh-group*
 </multicast-route-mesh-group>
 <multicast-source-prefix-length>*multicast-source-prefix-length*
 </multicast-source-prefix-length>
 <multicast-route-source>...</multicast-route-source>
 <session-name>*session-name*</session-name>
 <forwarding-rate-kilobytes>*forwarding-rate-kilobytes*
 </forwarding-rate-kilobytes>
 <forwarding-rate-packets>*forwarding-rate-packets*</forwarding-rate-packets>
 <forwarded-packet-count>*forwarded-packet-count*</forwarded-packet-count>
 <bandwidth-for-admission-control>*bandwidth-for-admission-control*
 </bandwidth-for-admission-control>
 <upstream-interface-name>*upstream-interface-name*</upstream-interface-name>
 <rpf-check-disabled/>
 <downstream-interface-names>*downstream-interface-names*
 </downstream-interface-names>
 <rejected-downstream-interface-names>*rejected-downstream-interface-names*
 </rejected-downstream-interface-names>
 <next-hop-id>*next-hop-id*</next-hop-id>
 <upstream-protocol>*upstream-protocol*</upstream-protocol>
 <multicast-route-forwarding-state>*multicast-route-forwarding-state*
 </multicast-route-forwarding-state>
 <multicast-route-state>*multicast-route-state*</multicast-route-state>
 <multicast-route-timeout>*multicast-route-timeout*</multicast-route-timeout>
 <interface-mismatch-count>*interface-mismatch-count*</interface-mismatch-count>
</multicast-route>
 </route-family>

Description No documentation is available yet.

Contents <bandwidth-for-admission-control>—Bandwidth used for admission control.

<downstream-interface-names>—No documentation is available yet.

<forwarded-packet-count>—No documentation is available yet.

<forwarding-rate-kilobytes>—No documentation is available yet.

<forwarding-rate-packets>—No documentation is available yet.

<interface-mismatch-count>—No documentation is available yet.

<multicast-group-address>—Group address.

<multicast-route-bridge-domain>—No documentation is available yet.

<multicast-route-forwarding-state>—No documentation is available yet.

<multicast-route-mesh-group>—No documentation is available yet.

<multicast-route-source>—No documentation is available yet.

<multicast-route-state>—No documentation is available yet.

<multicast-route-timeout>—No documentation is available yet.

<multicast-route-vlan-id>—No documentation is available yet.

<multicast-source-address>—Source address.

<multicast-source-prefix-length>—Source prefix length.

<next-hop-id>—No documentation is available yet.

<rejected-downstream-interface-names>—Downstream interfaces rejected by bandwidth admission control.

<rpf-check-disabled>—Reverse path forwarding check is disabled.

<session-name>—No documentation is available yet.

<upstream-interface-name>—Upstream interface.

<upstream-protocol>—No documentation is available yet.

<multicast-route-information>

Usage <rpc-reply>
 <multicast-route-information>
 <multicast-route-no-group-prefix>*multicast-route-no-group-prefix*
 </multicast-route-no-group-prefix>
 <multicast-route-no-family>*multicast-route-no-family*
 </multicast-route-no-family>
 <multicast-statistics-timed-out/>
 <route-family>...</route-family>
 </multicast-route-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <multicast-route-no-family>—No documentation is available yet.

<multicast-route-no-group-prefix>—No documentation is available yet.

<multicast-statistics-timed-out>—No documentation is available yet.

<route-family>—No documentation is available yet.

<multicast-route-source>

Usage <multicast-route>
 <multicast-route-source>
 <multicast-source-address>*multicast-source-address*</multicast-source-address>
 </multicast-route-source>
 </multicast-route>

Description No documentation is available yet.

Contents <multicast-source-address>—Source address.

<multicast-rpf-information>

Usage <rpc-reply>
 <multicast-rpf-information>
 <rpf-family>...</rpf-family>
 </multicast-rpf-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <rpf-family>—No documentation is available yet.

<multicast-scope>

Usage <multicast-scope-information>
 <multicast-scope>
 <scope-name>*scope-name*</scope-name>
 <address-prefix>*address-prefix*</address-prefix>
 <interface-name>*interface-name*</interface-name>
 <scope-rejects>*scope-rejects*</scope-rejects>
 <scope-state>*scope-state*</scope-state>
 </multicast-scope>
 </multicast-scope-information>

Description No documentation is available yet.

Contents <address-prefix>—No documentation is available yet.
 <interface-name>—No documentation is available yet.
 <scope-name>—Name of multicast scope.
 <scope-rejects>—Number of rejects in multicast scope.
 <scope-state>—No documentation is available yet.

<multicast-scope-information>

Usage	<pre> <rpc-reply> <multicast-scope-information> <multicast-scope-policy><i>multicast-scope-policy</i></multicast-scope-policy> <multicast-scope-policy-interfaces>...</multicast-scope-policy-interfaces> <multicast-scope>...</multicast-scope> </multicast-scope-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<p><multicast-scope>—No documentation is available yet.</p> <p><multicast-scope-policy>—No documentation is available yet.</p> <p><multicast-scope-policy-interfaces>—No documentation is available yet.</p>

<multicast-scope-policy-interface>

Usage	<pre> <multicast-scope-policy-interfaces> <multicast-scope-policy-interface> <interface-name><i>interface-name</i></interface-name> <scope-rejects><i>scope-rejects</i></scope-rejects> </multicast-scope-policy-interface> </multicast-scope-policy-interfaces> </pre>
Description	No documentation is available yet.
Contents	<p><interface-name>—No documentation is available yet.</p> <p><scope-rejects>—Number of rejects in multicast scope.</p>

<multicast-scope-policy-interfaces>

Usage	<pre> <multicast-scope-information> <multicast-scope-policy-interfaces> <instance-name><i>instance-name</i></instance-name> <address-family><i>address-family</i></address-family> <multicast-scope-policy-interface>...</multicast-scope-policy-interface> </multicast-scope-policy-interfaces> </multicast-scope-information> </pre>
Description	No documentation is available yet.
Contents	<p><address-family>—No documentation is available yet.</p> <p><instance-name>—No documentation is available yet.</p> <p><multicast-scope-policy-interface>—No documentation is available yet.</p>

<multicast-session>

Usage <multicast-sessions-information>
 <multicast-session>
 <session-announcement>*session-announcement*</session-announcement>
 <session-name>*session-name*</session-name>
 <session-version>*session-version*</session-version>
 <session-origin>...</session-origin>
 <upstream-protocol>*upstream-protocol*</upstream-protocol>
 <session-description>*session-description*</session-description>
 <session-uri>*session-uri*</session-uri>
 <session-email>*session-email*</session-email>
 <session-phone>*session-phone*</session-phone>
 <session-connection-data>...</session-connection-data>
 <session-bandwidth>*session-bandwidth*</session-bandwidth>
 <session-start-time>*session-start-time*</session-start-time>
 <session-stop-time>*session-stop-time*</session-stop-time>
 <session-encryption-key>*session-encryption-key*</session-encryption-key>
 <session-attribute>*session-attribute*</session-attribute>
 <session-media>*session-media*</session-media>
 </multicast-session>
 </multicast-sessions-information>

Description No documentation is available yet.

Contents <session-announcement>—No documentation is available yet.
 <session-attribute>—No documentation is available yet.
 <session-bandwidth>—No documentation is available yet.
 <session-connection-data>—No documentation is available yet.
 <session-description>—No documentation is available yet.
 <session-email>—No documentation is available yet.
 <session-encryption-key>—No documentation is available yet.
 <session-media>—No documentation is available yet.
 <session-name>—No documentation is available yet.
 <session-origin>—No documentation is available yet.
 <session-phone>—No documentation is available yet.
 <session-start-time>—No documentation is available yet.
 <session-stop-time>—No documentation is available yet.
 <session-uri>—No documentation is available yet.
 <session-version>—No documentation is available yet.

<upstream-protocol>—No documentation is available yet.

<multicast-sessions-information>

Usage <rpc-reply>
 <multicast-sessions-information>
 <multicast-session>...</multicast-session>
 <multicast-session-count>*multicast-session-count*</multicast-session-count>
 <multicast-sessions-type>*multicast-sessions-type*</multicast-sessions-type>
 </multicast-sessions-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <multicast-session>—No documentation is available yet.
 <multicast-session-count>—No documentation is available yet.
 <multicast-sessions-type>—No documentation is available yet.

<multicast-source>

Usage <multicast-usage-information>
 <multicast-source>
 <multicast-source-address>*multicast-source-address*</multicast-source-address>
 <multicast-source-prefix-length>*multicast-source-prefix-length*
 </multicast-source-prefix-length>
 <multicast-group-count>*multicast-group-count*</multicast-group-count>
 <multicast-packet-count>*multicast-packet-count*</multicast-packet-count>
 <multicast-byte-count>*multicast-byte-count*</multicast-byte-count>
 <multicast-source-group>...</multicast-source-group>
 </multicast-source>
 </multicast-usage-information>

Description No documentation is available yet.

Contents <multicast-byte-count>—No documentation is available yet.
 <multicast-group-count>—No documentation is available yet.
 <multicast-packet-count>—No documentation is available yet.
 <multicast-source-address>—Source address.
 <multicast-source-group>—No documentation is available yet.
 <multicast-source-prefix-length>—Source prefix length.

<multicast-source-group>

Usage <multicast-source>
 <multicast-source-group>
 <multicast-group-address>*multicast-group-address*</multicast-group-address>
 <multicast-packet-count>*multicast-packet-count*</multicast-packet-count>
 <multicast-byte-count>*multicast-byte-count*</multicast-byte-count>
 </multicast-source-group>
 </multicast-source>

Description No documentation is available yet.

Contents <multicast-byte-count>—No documentation is available yet.

 <multicast-group-address>—Group address.

 <multicast-packet-count>—No documentation is available yet.

<multicast-statistics>

Usage <multicast-statistics-information>
 <multicast-statistics>
 <instance-name>*instance-name*</instance-name>
 <address-family>*address-family*</address-family>
 <mc-stats-interface>...</mc-stats-interface>
 <mc-resolves-no-mc-interface>*mc-resolves-no-mc-interface*
 </mc-resolves-no-mc-interface>
 <mc-global-resolves-no-route>*mc-global-resolves-no-route*
 </mc-global-resolves-no-route>
 <mc-notifies-no-mc-interface>*mc-notifies-no-mc-interface*
 </mc-notifies-no-mc-interface>
 <mc-notifies-no-route>*mc-notifies-no-route*</mc-notifies-no-route>
 <mc-mismatches-no-mc-interface>*mc-mismatches-no-mc-interface*
 </mc-mismatches-no-mc-interface>
 <mc-groups-no-mc-interface>*mc-groups-no-mc-interface*
 </mc-groups-no-mc-interface>
 </multicast-statistics>
 </multicast-statistics-information>

Description No documentation is available yet.

Contents <address-family>—No documentation is available yet.

<instance-name>—No documentation is available yet.

<mc-global-resolves-no-route>—Number of resolve requests with no route to source.

<mc-groups-no-mc-interface>—Number of group memberships on non-multicast interfaces.

<mc-mismatches-no-mc-interface>—Number of interface mismatches on non-multicast interfaces.

<mc-notifies-no-mc-interface>—Number of routing notifications on non-multicast interfaces.

<mc-notifies-no-route>—Number of routing notifications with no route to source.

<mc-resolves-no-mc-interface>—Number of resolve requests on non-multicast interfaces.

<mc-stats-interface>—No documentation is available yet.

<multicast-statistics-information>

- Usage** <rpc-reply>
 <multicast-statistics-information>
 <multicast-statistics>...</multicast-statistics>
 </multicast-statistics-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <multicast-statistics>—No documentation is available yet.

<multicast-tunnel>

- Usage** <multicast-tunnels-information>
 <multicast-tunnel>
 <interface-name>*interface-name*</interface-name>
 <tunnel-local-address>*tunnel-local-address*</tunnel-local-address>
 <tunnel-remote-address>*tunnel-remote-address*</tunnel-remote-address>
 <tunnel-ttl>*tunnel-ttl*</tunnel-ttl>
 </multicast-tunnel>
 </multicast-tunnels-information>
- Description** No documentation is available yet.
- Contents** <interface-name>—No documentation is available yet.
- <tunnel-local-address>—No documentation is available yet.
- <tunnel-remote-address>—No documentation is available yet.
- <tunnel-ttl>—No documentation is available yet.

<multicast-tunnels-information>

- Usage** <rpc-reply>
 <multicast-tunnels-information>
 <multicast-tunnel>...</multicast-tunnel>
 </multicast-tunnels-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <multicast-tunnel>—No documentation is available yet.

<multicast-usage-information>

Usage <rpc-reply>
 <multicast-usage-information>
 <multicast-usage-no-group-prefix>*multicast-usage-no-group-prefix*
 </multicast-usage-no-group-prefix>
 <multicast-usage-strange-family>*multicast-usage-strange-family*
 </multicast-usage-strange-family>
 <multicast-usage-timed-out/>
 <multicast-group>...</multicast-group>
 <multicast-source>...</multicast-source>
 </multicast-usage-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <multicast-group>—No documentation is available yet.
 <multicast-source>—No documentation is available yet.
 <multicast-usage-no-group-prefix>—No documentation is available yet.
 <multicast-usage-strange-family>—No documentation is available yet.
 <multicast-usage-timed-out>—No documentation is available yet.

<mvpn-instance>

Usage <mvpn-instance-information>
 <mvpn-instance>
 <instance-entry>...</instance-entry>
 <instance-entry-summary>...</instance-entry-summary>
 </mvpn-instance>
 </mvpn-instance-information>

Description No documentation is available yet.

Contents <instance-entry>—No documentation is available yet.
 <instance-entry-summary>—No documentation is available yet.

<mvpn-instance-information>

Usage	<pre> <rpc-reply> <mvpn-instance-information> <mvpn-instance>...</mvpn-instance> <instance>...</instance> </mvpn-instance-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<p><instance>—No documentation is available yet.</p> <p><mvpn-instance>—No documentation is available yet.</p>

<neighbor>

Usage	<pre> <instance instance-entry> <neighbor> <neighbor-entry>...</neighbor-entry> </neighbor> </instance instance-entry> </pre>
Description	No documentation is available yet.
Contents	<neighbor-entry>—No documentation is available yet.

<neighbor-entry>

Usage	<pre> <neighbor> <neighbor-entry> <neighbor-identifier>neighbor-identifier</neighbor-identifier> <provider-tunnel-id>provider-tunnel-id</provider-tunnel-id> </neighbor-entry> </neighbor> </pre>
Description	No documentation is available yet.
Contents	<p><neighbor-identifier>—Neighbor IPv4 address.</p> <p><provider-tunnel-id>—Provider tunnel identifier.</p>

<neighbor-summary>

Usage	<pre> <instance-entry-summary> <neighbor-summary> <neighbor-summary-count>neighbor-summary-count</neighbor-summary-count> </neighbor-summary> </instance-entry-summary> </pre>
Description	No documentation is available yet.
Contents	<neighbor-summary-count>—Number of neighbors in the instance.

<next-hop-address>

Usage	<pre> <ospf-route ospf3-route> <next-hop-address> <interface-address>interface-address</interface-address> <lsp-name>lsp-name</lsp-name> </next-hop-address> </ospf-route ospf3-route> </pre>
Description	No documentation is available yet.
Contents	<p><interface-address>—No documentation is available yet.</p> <p><lsp-name>—Tunneled into an RSVP LSP.</p>

<next-hop-downstream-interface>

Usage	<pre> <iflist-next-hop> <next-hop-downstream-interface> <interface-name>interface-name</interface-name> <interface-index>interface-index</interface-index> </next-hop-downstream-interface> </iflist-next-hop> </pre>
Description	No documentation is available yet.
Contents	<p><interface-index>—No documentation is available yet.</p> <p><interface-name>—No documentation is available yet.</p>

<next-hop-element>

Usage	<pre> <isis-spf-result> <next-hop-element> <interface-name>interface-name</interface-name> <isis-next-hop>isis-next-hop</isis-next-hop> <snpa>snpa</snpa> </next-hop-element> </isis-spf-result> </pre>
Description	No documentation is available yet.
Contents	<p><interface-name>—No documentation is available yet.</p> <p><isis-next-hop>—No documentation is available yet.</p> <p><snpa>—No documentation is available yet.</p>

<next-hop-name>

Usage	<ospf-route ospf3-route> <next-hop-name> <interface-name> <i>interface-name</i> </interface-name> <interface-link-name> <i>interface-link-name</i> </interface-link-name> </next-hop-name> </ospf-route ospf3-route>
Description	No documentation is available yet.
Contents	<interface-link-name>—No documentation is available yet. <interface-name>—No documentation is available yet.

<next-hops-family>

Usage	<multicast-next-hops-information krt-iflist-nexthop-information> <next-hops-family> <address-family> <i>address-family</i> </address-family> <iflist-next-hop>...</iflist-next-hop> </next-hops-family> </multicast-next-hops-information krt-iflist-nexthop-information>
Description	No documentation is available yet.
Contents	<address-family>—No documentation is available yet. <iflist-next-hop>—No documentation is available yet.

<nh>

Usage <rt-entry | protocol-nh | indirect-nexthop | flood-nh | krt-nexthop>

```

<nh>
  <selected-next-hop/>
  <weight>weight</weight>
  <balance>balance</balance>
  <filter>filter</filter>
  <via>via</via>
  <nh-local-interface>nh-local-interface</nh-local-interface>
  <nh-table-receive>nh-table-receive</nh-table-receive>
  <nh-table>nh-table</nh-table>
  <to>to</to>
  <lsp-name>lsp-name</lsp-name>
  <mpls-label>mpls-label</mpls-label>
  <nh-service>nh-service</nh-service>
  <nh-service-pkt-dist>nh-service-pkt-dist</nh-service-pkt-dist>
  <nh-service-app-data>nh-service-app-data</nh-service-app-data>
  <nh-address>nh-address</nh-address>
  <nh-index>nh-index</nh-index>
</nh>
</rt-entry | protocol-nh | indirect-nexthop | flood-nh | krt-nexthop>

```

Description Next-hop gateway information.

Contents <balance>—Next-hop balance.

<filter>—Next-hop firewall filter.

<lsp-name>—Tunneled into an RSVP LSP.

<mpls-label>—Label of MPLS packet.

<nh-address>—Address of next hop.

<nh-index>—Next-hop index.

<nh-local-interface>—Destination is a local interface.

<nh-service>—Next-hop service.

<nh-service-app-data>—Multi services application specific data.

<nh-service-pkt-dist>—Multi services packet distribution type.

<nh-table>—Indirect pointing to another table.

<nh-table-receive>—Destination is a local address.

<selected-next-hop>—Present if this next hop is selected.

<to>—Neighbor address to which to send (next-hop address).

<via>—Reachable via a local interface.

<weight>—Next-hop weight.

<nlri-flags>

Usage <nlri-information>
 <nlri-flags>
 <bgp-nlri-flag-explicit-null-for-all-routes/>
 <bgp-nlri-flag-explicit-null-for-connected-routes/>
 <bgp-nlri-flag-aggregate-label/>
 <bgp-nlri-flag-per-prefix-label/>
 <bgp-nlri-flag-per-group-label/>
 <bgp-nlri-flag-traffic-stats/>
 <bgp-nlri-flag-l2vpn-status-vector/>
 <bgp-nlri-flag-no-l2vpn-status-vector/>
 </nlri-flags>
 </nlri-information>

Description No documentation is available yet.

Contents <bgp-nlri-flag-aggregate-label>—No documentation is available yet.
 <bgp-nlri-flag-explicit-null-for-all-routes>—No documentation is available yet.
 <bgp-nlri-flag-explicit-null-for-connected-routes>—No documentation is available yet.
 <bgp-nlri-flag-l2vpn-status-vector>—No documentation is available yet.
 <bgp-nlri-flag-no-l2vpn-status-vector>—No documentation is available yet.
 <bgp-nlri-flag-per-group-label>—No documentation is available yet.
 <bgp-nlri-flag-per-prefix-label>—No documentation is available yet.
 <bgp-nlri-flag-traffic-stats>—No documentation is available yet.

<nlr-info>

Usage	<pre> <bgp-option-information> <nlr-info> <nlr-type>nlr-type</nlr-type> <nlr-flags>...</nlr-flags> <nlr-traffic-stats>...</nlr-traffic-stats> <nlr-flow-novalidate>nlr-flow-novalidate</nlr-flow-novalidate> </nlr-info> </bgp-option-information> </pre>
Description	No documentation is available yet.
Contents	<p><nlr-flags>—No documentation is available yet.</p> <p><nlr-flow-novalidate>—Policy to accept flow routes without validation.</p> <p><nlr-traffic-stats>—No documentation is available yet.</p> <p><nlr-type>—Type of NLRI being limited.</p>

<nlr-traffic-stats>

Usage	<pre> <nlr-info> <nlr-traffic-stats> <tracing-information>...</tracing-information> <traffic-stats-interval>traffic-stats-interval</traffic-stats-interval> </nlr-traffic-stats> </nlr-info> </pre>
Description	No documentation is available yet.
Contents	<p><tracing-information>—No documentation is available yet.</p> <p><traffic-stats-interval>—No documentation is available yet.</p>

<node>

Usage <route-resolution-tree>
 <node>
 <node-prefix>*node-prefix*</node-prefix>
 <node-prefix-length>*node-prefix-length*</node-prefix-length>
 <originating-rib>*originating-rib*</originating-rib>
 <metric>*metric*</metric>
 <node-path-count>*node-path-count*</node-path-count>
 <forwarding-nh-count>*forwarding-nh-count*</forwarding-nh-count>
 <indirect-nh-count>*indirect-nh-count*</indirect-nh-count>
 <composite-nh-count>*composite-nh-count*</composite-nh-count>
 <protocol-nh>...</protocol-nh>
 </node>
 </route-resolution-tree>

Description No documentation is available yet.

Contents <composite-nh-count>—Number of composite next hops.

<forwarding-nh-count>—Number of indirect path forwarding next hops.

<indirect-nh-count>—Number of indirect next hops.

<metric>—No documentation is available yet.

<node-path-count>—Number of paths for this node.

<node-prefix>—No documentation is available yet.

<node-prefix-length>—No documentation is available yet.

<originating-rib>—Routing table from which this route was learned.

<protocol-nh>—Protocol next hop.

<operational-routing-instance-information>

Usage <rpc-reply>
 <operational-routing-instance-information>
 <instance-name>*instance-name*</instance-name>
 </operational-routing-instance-information>
 </rpc-reply>

Description Operational routing instances that can be passed to netapp commands.

Contents <instance-name>—No documentation is available yet.

<ospf-area-header>

- Usage** <ospf-database-information>
 <ospf-area-header>
 <ospf-area>ospf-area</ospf-area>
 </ospf-area-header>
</ospf-database-information>
- Description** No documentation is available yet.
- Contents** <ospf-area>—Area ID.

<ospf-area-overview>

Usage <ospf-overview>
 <ospf-area-overview>
 <ospf-area>ospf-area</ospf-area>
 <ospf-stub-type>ospf-stub-type</ospf-stub-type>
 <ospf-stub-cost>ospf-stub-cost</ospf-stub-cost>
 <ospf-virtual-transit/>
 <authentication-type>authentication-type</authentication-type>
 <ospf-abr-count>ospf-abr-count</ospf-abr-count>
 <ospf-asbr-count>ospf-asbr-count</ospf-asbr-count>
 <ospf-nbr-overview>...</ospf-nbr-overview>
 <ospf-dna-uncapable/>
 <ospf-area-dc-bit-clear-count>ospf-area-dc-bit-clear-count
 </ospf-area-dc-bit-clear-count>
 <ospf-area-indications-count>ospf-area-indications-count
 </ospf-area-indications-count>
 <ospf-area-self-indicating/>
 <ospf-link-dc-bit-clear-count>ospf-link-dc-bit-clear-count
 </ospf-link-dc-bit-clear-count>
 </ospf-area-overview>
 </ospf-overview>

Description Overview information for an OSPF area.

Contents <authentication-type>—Type of authentication.

<ospf-abr-count>—Number of area border routers.

<ospf-area>—Area ID.

<ospf-area-dc-bit-clear-count>—Number of area scope link-state advertisements received with DC bit clear.

<ospf-area-indications-count>—Number of indication link-state advertisements received.

<ospf-area-self-indicating>—Router generated an indication link-state advertisement.

<ospf-asbr-count>—Number of autonomous system boundary routers.

<ospf-dna-uncapable>—Not safe to generate DoNotAge LSAs.

<ospf-link-dc-bit-clear-count>—Number of link local scope link-state advertisements received with no DC bit clear.

<ospf-nbr-overview>—No documentation is available yet.

<ospf-stub-cost>—Cost of default route in stub area.

<ospf-stub-type>—Stub type of area.

<ospf-virtual-transit>—Area is transit for virtual links.

<ospf-database>

Usage	<pre> <ospf-database-information> <ospf-database> <lsa-type>lsa-type</lsa-type> <our-entry/> <lsa-id>lsa-id</lsa-id> <advertising-router>advertising-router</advertising-router> <sequence-number>sequence-number</sequence-number> <age>age</age> <ospf-do-not-age/> <options>options</options> <checksum>checksum</checksum> <lsa-length>lsa-length</lsa-length> <ospf-router-lsa>...</ospf-router-lsa> <ospf-network-lsa>...</ospf-network-lsa> <ospf-opaque-area-lsa>...</ospf-opaque-area-lsa> <ospf-opaque-link-local-lsa>...</ospf-opaque-link-local-lsa> <ospf-summary-lsa>...</ospf-summary-lsa> <ospf-external-lsa>...</ospf-external-lsa> <ospf-database-extensive>...</ospf-database-extensive> </ospf-database> </ospf-database-information> </pre>
Description	No documentation is available yet.
Contents	<p><advertising-router>—No documentation is available yet.</p> <p><age>—No documentation is available yet.</p> <p><checksum>—No documentation is available yet.</p> <p><lsa-id>—No documentation is available yet.</p> <p><lsa-length>—No documentation is available yet.</p> <p><lsa-type>—No documentation is available yet.</p> <p><options>—No documentation is available yet.</p> <p><ospf-database-extensive>—No documentation is available yet.</p> <p><ospf-do-not-age>—DoNotAge bit is set on the link-state advertisement received.</p> <p><ospf-external-lsa>—No documentation is available yet.</p> <p><ospf-network-lsa>—No documentation is available yet.</p> <p><ospf-opaque-area-lsa>—No documentation is available yet.</p> <p><ospf-opaque-link-local-lsa>—No documentation is available yet.</p> <p><ospf-router-lsa>—No documentation is available yet.</p> <p><ospf-summary-lsa>—No documentation is available yet.</p>

<our-entry>—No documentation is available yet.

<sequence-number>—History event number.

<ospf-database-extensive>

Usage <ospf-database | ospf3-database>
<ospf-database-extensive>
 <generation-timer>*generation-timer*</generation-timer>
 <aging-timer>*aging-timer*</aging-timer>
 <installation-time>*installation-time*</installation-time>
 <expiration-time>*expiration-time*</expiration-time>
 <send-time>*send-time*</send-time>
 <lsa-changed-time>*lsa-changed-time*</lsa-changed-time>
 <lsa-change-count>*lsa-change-count*</lsa-change-count>
 <indication-lsa/>
 <database-entry-state>*database-entry-state*</database-entry-state>
 <database-telink-id>*database-telink-id*</database-telink-id>
 <standby-flood-status>*standby-flood-status*</standby-flood-status>
</ospf-database-extensive>
 </ospf-database | ospf3-database>

Description No documentation is available yet.

Contents <aging-timer>—No documentation is available yet.

<database-entry-state>—No documentation is available yet.

<database-telink-id>—No documentation is available yet.

<expiration-time>—No documentation is available yet.

<generation-timer>—No documentation is available yet.

<indication-lsa>—Indication link-state advertisement.

<installation-time>—No documentation is available yet.

<lsa-change-count>—Number of times link-state advertisement changed.

<lsa-changed-time>—Time elapsed since the link-state advertisement changed.

<send-time>—No documentation is available yet.

<standby-flood-status>—Flooding status to standby Routing Engine.

<ospf-database-information>

Usage <rpc-reply>
 <ospf-database-information>
 <ospf-area-header>...</ospf-area-header>
 <ospf-intf-header>...</ospf-intf-header>
 <ospf-database>...</ospf-database>
 <ospf-database-summary>...</ospf-database-summary>
 </ospf-database-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <ospf-area-header>—No documentation is available yet.
 <ospf-database>—No documentation is available yet.
 <ospf-database-summary>—No documentation is available yet.
 <ospf-intf-header>—No documentation is available yet.

<ospf-database-replication>

Usage <ospf-database-replication-information | ospf3-database-replication-information>
<ospf-database-replication>
 <lsa-type>lsa-type</lsa-type>
 <lsa-id>lsa-id</lsa-id>
 <advertising-router>advertising-router</advertising-router>
 <sequence-number>sequence-number</sequence-number>
 <age>age</age>
 <ospf-do-not-age/>
 <ospf-synchronization-state>ospf-synchronization-state
 </ospf-synchronization-state>
 <ospf-route-table-index>ospf-route-table-index</ospf-route-table-index>
 <ospf-area>ospf-area</ospf-area>
 <ospf-router-id>ospf-router-id</ospf-router-id>
 <ospf-ifl-index>ospf-ifl-index</ospf-ifl-index>
 <interface-address>interface-address</interface-address>
 <installation-time>installation-time</installation-time>
 <ospf-unsync-reason>ospf-unsync-reason</ospf-unsync-reason>
</ospf-database-replication>
 </ospf-database-replication-information | ospf3-database-replication-information>

Description OSPF LSA replication information.

Contents <advertising-router>—No documentation is available yet.

<age>—No documentation is available yet.

<installation-time>—No documentation is available yet.

<interface-address>—No documentation is available yet.

<lsa-id>—No documentation is available yet.

<lsa-type>—No documentation is available yet.

<ospf-area>—Area ID.

<ospf-do-not-age>—DoNotAge bit is set on the link-state advertisement received.

<ospf-ifl-index>—Interface index.

<ospf-route-table-index>—Route table index.

<ospf-router-id>—OSPF router ID.

<ospf-synchronization-state>—Synchronization state of the replicated entry.

<ospf-unsync-reason>—No documentation is available yet.

<sequence-number>—History event number.

<ospf-database-replication-information>

- Usage** <rpc-reply>
 <ospf-database-replication-information>
 <ospf-database-replication>...</ospf-database-replication>
 </ospf-database-replication-information>
 </rpc-reply>
- Description** OSPFv2 LSA replication information.
- Contents** <ospf-database-replication>—OSPF LSA replication information.

<ospf-database-summary>

- Usage** <ospf-database-information>
 <ospf-database-summary>
 <ospf-area>ospf-area</ospf-area>
 <ospf-intf>ospf-intf</ospf-intf>
 <ospf-lsa-count>ospf-lsa-count</ospf-lsa-count>
 <ospf-lsa-type>ospf-lsa-type</ospf-lsa-type>
 </ospf-database-summary>
 </ospf-database-information>
- Description** No documentation is available yet.
- Contents** <ospf-area>—Area ID.
- <ospf-intf>—Name of interface.
- <ospf-lsa-count>—No documentation is available yet.
- <ospf-lsa-type>—No documentation is available yet.

<ospf-errors>**Usage** <ospf-io-statistics | ospf-statistics>**<ospf-errors>**

```

<run-header-error>run-header-error</run-header-error>
<short-packets-error>short-packets-error</short-packets-error>
<bad-version-error>bad-version-error</bad-version-error>
<truncated-packets-error>truncated-packets-error</truncated-packets-error>
<checksum-error>checksum-error</checksum-error>
<subnet-mismatch-error>subnet-mismatch-error</subnet-mismatch-error>
<virtual-link-error>virtual-link-error</virtual-link-error>
<area-mismatch-error>area-mismatch-error</area-mismatch-error>
<authentication-mismatch-error>authentication-mismatch-error
  </authentication-mismatch-error>
<authentication-failure-error>authentication-failure-error
  </authentication-failure-error>
<bad-packettype-error>bad-packettype-error</bad-packettype-error>
<netmask-mismatch-error>netmask-mismatch-error</netmask-mismatch-error>
<hello-interval-mismatch-error>hello-interval-mismatch-error
  </hello-interval-mismatch-error>
<dead-interval-mismatch-error>dead-interval-mismatch-error
  </dead-interval-mismatch-error>
<stub-area-mismatch-error>stub-area-mismatch-error</stub-area-mismatch-error>
<nssa-mismatch-error>nssa-mismatch-error</nssa-mismatch-error>
<default-exclusion-mismatch-error>default-exclusion-mismatch-error
  </default-exclusion-mismatch-error>
<mtu-mismatch-error>mtu-mismatch-error</mtu-mismatch-error>
<hello-received-error>hello-received-error</hello-received-error>
<no-interface-error>no-interface-error</no-interface-error>
<no-router-id-error>no-router-id-error</no-router-id-error>
<instance-id-mismatch-error>instance-id-mismatch-error
  </instance-id-mismatch-error>
<lanp2p-cfgmismatch-error>lanp2p-cfgmismatch-error</lanp2p-cfgmismatch-error>
<no-error/>

```

</ospf-errors>

</ospf-io-statistics | ospf-statistics>

Description No documentation is available yet.**Contents** <area-mismatch-error>—No documentation is available yet.

<authentication-failure-error>—No documentation is available yet.

<authentication-mismatch-error>—No documentation is available yet.

<bad-packettype-error>—No documentation is available yet.

<bad-version-error>—No documentation is available yet.

<checksum-error>—No documentation is available yet.

<dead-interval-mismatch-error>—No documentation is available yet.

<default-exclusion-mismatch-error>—No documentation is available yet.

<hello-interval-mismatch-error>—No documentation is available yet.

<hello-received-error>—No documentation is available yet.

<instance-id-mismatch-error>—No documentation is available yet.

<lanp2p-cfgmismatch-error>—No documentation is available yet.

<mtu-mismatch-error>—No documentation is available yet.

<netmask-mismatch-error>—No documentation is available yet.

<no-error>—No documentation is available yet.

<no-interface-error>—No documentation is available yet.

<no-router-id-error>—No documentation is available yet.

<nssa-mismatch-error>—No documentation is available yet.

<runt-header-error>—No documentation is available yet.

<short-packets-error>—No documentation is available yet.

<stub-area-mismatch-error>—No documentation is available yet.

<subnet-mismatch-error>—No documentation is available yet.

<truncated-packets-error>—No documentation is available yet.

<virtual-link-error>—No documentation is available yet.

<ospf-external-lsa>

Usage <ospf-database>
 <ospf-external-lsa>
 <address-mask>*address-mask*</address-mask>
 <ospf-external-lsa-topology>...</ospf-external-lsa-topology>
 </ospf-external-lsa>
 </ospf-database>

Description No documentation is available yet.

Contents <address-mask>—No documentation is available yet.

<ospf-external-lsa-topology>—OSPF topology specific information for an external LSA.

<ospf-external-lsa-topology>

Usage <ospf-external-lsa>
 <ospf-external-lsa-topology>
 <ospf-topology-name>*ospf-topology-name*</ospf-topology-name>
 <ospf-topology-id>*ospf-topology-id*</ospf-topology-id>
 <type-value>*type-value*</type-value>
 <ospf-topology-metric>*ospf-topology-metric*</ospf-topology-metric>
 <forward-address>*forward-address*</forward-address>
 <tag>*tag*</tag>
 </ospf-external-lsa-topology>
 </ospf-external-lsa>

Description OSPF topology specific information for an external LSA.

Contents <forward-address>—No documentation is available yet.

<ospf-topology-id>—OSPF topology id.

<ospf-topology-metric>—OSPF topology specific metric.

<ospf-topology-name>—OSPF topology name.

<tag>—No documentation is available yet.

<type-value>—No documentation is available yet.

<ospf-instance-neighbor>

Usage <ospf-neighbor-information-all>
 <ospf-instance-neighbor>
 <ospf-instance-name>*ospf-instance-name*</ospf-instance-name>
 <ospf-neighbor>...</ospf-neighbor>
 </ospf-instance-neighbor>
 </ospf-neighbor-information-all>

Description Information about OSPF neighbors within this routing instance.

Contents <ospf-instance-name>—Name of OSPF instance.

<ospf-neighbor>—No documentation is available yet.

<ospf-interface>

Usage <ospf-interface-information>

```

<ospf-interface>
  <interface-name>interface-name</interface-name>
  <ospf-interface-state>ospf-interface-state</ospf-interface-state>
  <ospf-area>ospf-area</ospf-area>
  <dr-id>dr-id</dr-id>
  <bdr-id>bdr-id</bdr-id>
  <neighbor-count>neighbor-count</neighbor-count>
  <interface-type>interface-type</interface-type>
  <interface-address>interface-address</interface-address>
  <address-mask>address-mask</address-mask>
  <mtu>mtu</mtu>
  <interface-cost>interface-cost</interface-cost>
  <virtual-link-transit-area>virtual-link-transit-area
    </virtual-link-transit-area>
  <virtual-link-destination>virtual-link-destination</virtual-link-destination>
  <sham-link-local>sham-link-local</sham-link-local>
  <sham-link-remote>sham-link-remote</sham-link-remote>
  <dr-address>dr-address</dr-address>
  <bdr-address>bdr-address</bdr-address>
  <adj-count>adj-count</adj-count>
  <router-priority>router-priority</router-priority>
  <interface-secondary/>
  <passive>passive</passive>
  <hello-interval>hello-interval</hello-interval>
  <poll-interval>poll-interval</poll-interval>
  <dead-interval>dead-interval</dead-interval>
  <retransmit-interval>retransmit-interval</retransmit-interval>
  <ospf-stub-type>ospf-stub-type</ospf-stub-type>
  <ipsec-sa>ipsec-sa</ipsec-sa>
  <authentication-type>authentication-type</authentication-type>
  <ospf-interface-topology>...</ospf-interface-topology>
  <active-key-id>active-key-id</active-key-id>
  <active-key-start-time>active-key-start-time</active-key-start-time>
  <igp-ldp-sync-holdtime>igp-ldp-sync-holdtime</igp-ldp-sync-holdtime>
  <igp-ldp-sync-state>igp-ldp-sync-state</igp-ldp-sync-state>
  <igp-ldp-sync-last-change>igp-ldp-sync-last-change</igp-ldp-sync-last-change>
  <igp-ldp-sync-reason>igp-ldp-sync-reason</igp-ldp-sync-reason>
  <igp-ldp-sync-timeleft>igp-ldp-sync-timeleft</igp-ldp-sync-timeleft>
  <interface-flood-list-count>interface-flood-list-count
    </interface-flood-list-count>
  <flood-list-count>flood-list-count</flood-list-count>
  <lsa-list>lsa-list</lsa-list>
  <interface-description-list>interface-description-list
    </interface-description-list>
</ospf-interface>
</ospf-interface-information>

```

Description No documentation is available yet.

Contents <active-key-id>—No documentation is available yet.

<active-key-start-time>—No documentation is available yet.

<address-mask>—No documentation is available yet.

<adj-count>—Count of fully adjacent neighbors.

<authentication-type>—Type of authentication.

<bdr-address>—IP address of BDR.

<bdr-id>—No documentation is available yet.

<dead-interval>—No documentation is available yet.

<dr-address>—IP address of DR.

<dr-id>—No documentation is available yet.

<flood-list-count>—No documentation is available yet.

<hello-interval>—Rate at which RSVP hellos are sent out. Default is 3 seconds.

<igp-ldp-sync-holdtime>—Length of time during which the maximum metric is advertised for an interface that is in the hold-down state because synchronization was lost between Label Distribution Protocol (LDP) and the interior gateway protocol (IGP).

<igp-ldp-sync-last-change>—Time since the state of synchronization between Label Distribution Protocol (LDP) and the interior gateway protocol (IGP) last changed.

<igp-ldp-sync-reason>—Reason for the change in the state of synchronization between Label Distribution Protocol (LDP) and the interior gateway protocol (IGP).

<igp-ldp-sync-state>—State of synchronization between Label Distribution Protocol (LDP) and the interior gateway protocol (IGP).

<igp-ldp-sync-timeleft>—Remaining amount of time the interface will remain in the hold-down state because synchronization was lost between Label Distribution Protocol (LDP) and the interior gateway protocol (IGP).

<interface-address>—No documentation is available yet.

<interface-cost>—Cost associated with this interface.

<interface-description-list>—No documentation is available yet.

<interface-flood-list-count>—No documentation is available yet.

<interface-name>—No documentation is available yet.

<interface-secondary>—OSPF interface is secondary.

<interface-type>—No documentation is available yet.

<ipsec-sa>—No documentation is available yet.

<lsa-list>—No documentation is available yet.

<mtu>—MTU along an interface.

<neighbor-count>—Number of neighbors on PIM interface.

<ospf-area>—Area ID.

<ospf-interface-state>—No documentation is available yet.

<ospf-interface-topology>—OSPF topology specific information for an interface.

<ospf-stub-type>—Stub type of area.

<passive>—No documentation is available yet.

<poll-interval>—No documentation is available yet.

<retransmit-interval>—No documentation is available yet.

<router-priority>—Router priority used in DR election on broadcast or NBMA interface.

<sham-link-local>—Sham link local end point.

<sham-link-remote>—Sham link remote end point.

<virtual-link-destination>—Virtual link destination address.

<virtual-link-transit-area>—Virtual link transit area.

<ospf-interface-information>

Usage <rpc-reply>
 <ospf-interface-information>
 <ospf-interface>...</ospf-interface>
 </ospf-interface-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <ospf-interface>—No documentation is available yet.

<ospf-interface-replication>

Usage <ospf-interface-replication-information | ospf3-interface-replication-information>
<ospf-interface-replication>
 <interface-name>*interface-name*</interface-name>
 <interface-address>*interface-address*</interface-address>
 <ospf-area>*ospf-area*</ospf-area>
 <ospf-synchronization-state>*ospf-synchronization-state*
 </ospf-synchronization-state>
 <ospf-ifl-index>*ospf-ifl-index*</ospf-ifl-index>
 <ospf-router-id>*ospf-router-id*</ospf-router-id>
 <ospf-route-table-index>*ospf-route-table-index*</ospf-route-table-index>
 <ospf-internal-index>*ospf-internal-index*</ospf-internal-index>
 <ospf-sync-dr-id>*ospf-sync-dr-id*</ospf-sync-dr-id>
 <ospf-sync-bdr-id>*ospf-sync-bdr-id*</ospf-sync-bdr-id>
 <dr-address>*dr-address*</dr-address>
 <bdr-address>*bdr-address*</bdr-address>
 <ospf-sync-dr-status>*ospf-sync-dr-status*</ospf-sync-dr-status>
 <ospf-sync-bdr-status>*ospf-sync-bdr-status*</ospf-sync-bdr-status>
 <ospf-unsync-reason>*ospf-unsync-reason*</ospf-unsync-reason>
</ospf-interface-replication>
 </ospf-interface-replication-information | ospf3-interface-replication-information>

Description OSPF interface replication information.

Contents <bdr-address>—IP address of BDR.

<dr-address>—IP address of DR.

<interface-address>—No documentation is available yet.

<interface-name>—No documentation is available yet.

<ospf-area>—Area ID.

<ospf-ifl-index>—Interface index.

<ospf-internal-index>—Interface internal index.

<ospf-route-table-index>—Route table index.

<ospf-router-id>—OSPF router ID.

<ospf-sync-bdr-id>—Backup designated router ID.

<ospf-sync-bdr-status>—Backup designated router status.

<ospf-sync-dr-id>—Designated router ID.

<ospf-sync-dr-status>—Designated router status.

<ospf-synchronization-state>—Synchronization state of the replicated entry.

<ospf-unsync-reason>—No documentation is available yet.

<ospf-interface-replication-information>

- Usage** <rpc-reply>
 <ospf-interface-replication-information>
 <ospf-interface-replication>...</ospf-interface-replication>
 </ospf-interface-replication-information>
 </rpc-reply>
- Description** OSPFv2 interface replication information.
- Contents** <ospf-interface-replication>—OSPF interface replication information.

<ospf-interface-topology>

- Usage** <ospf-interface>
 <ospf-interface-topology>
 <ospf-topology-name>ospf-topology-name</ospf-topology-name>
 <ospf-topology-id>ospf-topology-id</ospf-topology-id>
 <ospf-topology-passive/>
 <ospf-topology-disabled/>
 <ospf-topology-down/>
 <ospf-topology-metric>ospf-topology-metric</ospf-topology-metric>
 </ospf-interface-topology>
 </ospf-interface>
- Description** OSPF topology specific information for an interface.
- Contents** <ospf-topology-disabled>—OSPF topology is disabled.
- <ospf-topology-down>—OSPF topology is down.
- <ospf-topology-id>—OSPF topology id.
- <ospf-topology-metric>—OSPF topology specific metric.
- <ospf-topology-name>—OSPF topology name.
- <ospf-topology-passive>—OSPF topology is passive.

<ospf-intf-header>

- Usage** <ospf-database-information>
 <ospf-intf-header>
 <ospf-intf>ospf-intf</ospf-intf>
 <ospf-area>ospf-area</ospf-area>
 </ospf-intf-header>
 </ospf-database-information>
- Description** No documentation is available yet.
- Contents** <ospf-area>—Area ID.
- <ospf-intf>—Name of interface.

<ospf-io-statistics>

Usage	<code><ospf-io-statistics-information ospf3-io-statistics-information></code> <code><ospf-io-statistics></code> <code><packets-read>packets-read</packets-read></code> <code><average-per-run>average-per-run</average-per-run></code> <code><max-run>max-run</max-run></code> <code><ospf-errors>...</ospf-errors></code> <code></ospf-io-statistics></code> <code></ospf-io-statistics-information ospf3-io-statistics-information></code>
Description	No documentation is available yet.
Contents	<code><average-per-run></code> —No documentation is available yet. <code><max-run></code> —No documentation is available yet. <code><ospf-errors></code> —No documentation is available yet. <code><packets-read></code> —No documentation is available yet.

<ospf-io-statistics-information>

Usage	<code><rpc-reply></code> <code><ospf-io-statistics-information></code> <code><ospf-io-statistics>...</ospf-io-statistics></code> <code></ospf-io-statistics-information></code> <code></rpc-reply></code>
Description	No documentation is available yet.
Contents	<code><ospf-io-statistics></code> —No documentation is available yet.

<ospf-link>

Usage <ospf-router-lsa>
 <ospf-link>
 <link-id>*link-id*</link-id>
 <link-data>*link-data*</link-data>
 <link-type-name>*link-type-name*</link-type-name>
 <link-type-value>*link-type-value*</link-type-value>
 <ospf-topology-count>*ospf-topology-count*</ospf-topology-count>
 <metric>*metric*</metric>
 <ospf-router-link-topology>...</ospf-router-link-topology>
 </ospf-link>
 </ospf-router-lsa>

Description No documentation is available yet.

Contents <link-data>—No documentation is available yet.

<link-id>—No documentation is available yet.

<link-type-name>—No documentation is available yet.

<link-type-value>—No documentation is available yet.

<metric>—No documentation is available yet.

<ospf-router-link-topology>—OSPF topology specific information for a router link.

<ospf-topology-count>—Number of topologies advertised for this link.

<ospf-link-local-grace-lsa>

Usage <ospf-opaque-link-local-lsa>
 <ospf-link-local-grace-lsa>
 <tlv-grace-type-name>*tlv-grace-type-name*</tlv-grace-type-name>
 <tlv-grace-value>*tlv-grace-value*</tlv-grace-value>
 </ospf-link-local-grace-lsa>
 </ospf-opaque-link-local-lsa>

Description No documentation is available yet.

Contents <tlv-grace-type-name>—No documentation is available yet.

<tlv-grace-value>—No documentation is available yet.

<ospf-link-local-te-lsa>

Usage <ospf-opaque-link-local-lsa>
 <ospf-link-local-te-lsa>
 <ospf-link-local-te-tlv>...</ospf-link-local-te-tlv>
 <ospf-link-local-te-subtlv>...</ospf-link-local-te-subtlv>
 </ospf-link-local-te-lsa>
 </ospf-opaque-link-local-lsa>

Description No documentation is available yet.

Contents <ospf-link-local-te-subtlv>—No documentation is available yet.
 <ospf-link-local-te-tlv>—No documentation is available yet.

<ospf-link-local-te-subtlv>

Usage <ospf-link-local-te-lsa>
 <ospf-link-local-te-subtlv>
 <link-local-te-tlv-type-name>*link-local-te-tlv-type-name*
 </link-local-te-tlv-type-name>
 <tlv-type-value>*tlv-type-value*</tlv-type-value>
 <tlv-length>*tlv-length*</tlv-length>
 <bytes-left>*bytes-left*</bytes-left>
 <formatted-tlv-data>*formatted-tlv-data*</formatted-tlv-data>
 </ospf-link-local-te-subtlv>
 </ospf-link-local-te-lsa>

Description No documentation is available yet.

Contents <bytes-left>—No documentation is available yet.
 <formatted-tlv-data>—No documentation is available yet.
 <link-local-te-tlv-type-name>—No documentation is available yet.
 <tlv-length>—No documentation is available yet.
 <tlv-type-value>—No documentation is available yet.

<ospf-link-local-te-tlv>

Usage	<pre> <ospf-link-local-te-lsa> <ospf-link-local-te-tlv> <link-local-te-tlv-type-name>link-local-te-tlv-type-name </link-local-te-tlv-type-name> <tlv-type-value>tlv-type-value</tlv-type-value> <tlv-length>tlv-length</tlv-length> <bytes-left>bytes-left</bytes-left> <formatted-tlv-data>formatted-tlv-data</formatted-tlv-data> </ospf-link-local-te-tlv> </ospf-link-local-te-lsa> </pre>
Description	No documentation is available yet.
Contents	<p><bytes-left>—No documentation is available yet.</p> <p><formatted-tlv-data>—No documentation is available yet.</p> <p><link-local-te-tlv-type-name>—No documentation is available yet.</p> <p><tlv-length>—No documentation is available yet.</p> <p><tlv-type-value>—No documentation is available yet.</p>

<ospf-log-events>

Usage	<pre> <ospf-topology-log ospf3-log-information> <ospf-log-events> <log-element>...</log-element> <number-events>number-events</number-events> </ospf-log-events> </ospf-topology-log ospf3-log-information> </pre>
Description	No documentation is available yet.
Contents	<p><log-element>—No documentation is available yet.</p> <p><number-events>—No documentation is available yet.</p>

<ospf-log-information>

Usage	<pre> <rpc-reply> <ospf-log-information> <ospf-topology-log>...</ospf-topology-log> </ospf-log-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<ospf-topology-log>—OSPF topology specific SPF log information.

<ospf-log-instance>

Usage	<ospf-topology-log ospf3-log-information> <ospf-log-instance> <log-element>...</log-element> </ospf-log-instance> </ospf-topology-log ospf3-log-information>
Description	No documentation is available yet.
Contents	<log-element>—No documentation is available yet.

<ospf-log-maximum-length>

Usage	<ospf-topology-log ospf3-log-information> <ospf-log-maximum-length> <log-element>...</log-element> </ospf-log-maximum-length> </ospf-topology-log ospf3-log-information>
Description	No documentation is available yet.
Contents	<log-element>—No documentation is available yet.

<ospf-nbr-overview>

Usage	<ospf-area-overview> <ospf-nbr-overview> <ospf-nbr-up-count>ospf-nbr-up-count</ospf-nbr-up-count> </ospf-nbr-overview> </ospf-area-overview>
Description	No documentation is available yet.
Contents	<ospf-nbr-up-count>—Number of neighbors in full state.

<ospf-neighbor>

Usage <ospf-neighbor-information | ospf-instance-neighbor>
<ospf-neighbor>
 <neighbor-address>*neighbor-address*</neighbor-address>
 <interface-name>*interface-name*</interface-name>
 <ospf-neighbor-state>*ospf-neighbor-state*</ospf-neighbor-state>
 <neighbor-id>*neighbor-id*</neighbor-id>
 <neighbor-priority>*neighbor-priority*</neighbor-priority>
 <activity-timer>*activity-timer*</activity-timer>
 <ospf-area>*ospf-area*</ospf-area>
 <options>*options*</options>
 <neighbor-secondary/>
 <dr-address>*dr-address*</dr-address>
 <bdr-address>*bdr-address*</bdr-address>
 <neighbor-up-time>*neighbor-up-time*</neighbor-up-time>
 <neighbor-adjacency-time>*neighbor-adjacency-time*</neighbor-adjacency-time>
 <neighbor-suppress-hello>*neighbor-suppress-hello*</neighbor-suppress-hello>
 <master-slave>*master-slave*</master-slave>
 <sequence-number>*sequence-number*</sequence-number>
 <dbd-retransmit-time>*dbd-retransmit-time*</dbd-retransmit-time>
 <lsreq-retransmit-time>*lsreq-retransmit-time*</lsreq-retransmit-time>
 <lsreq-enqueued/>
 <lsreq-active/>
 <lsa-list>*lsa-list*</lsa-list>
 <ospf-neighbor-topology>...</ospf-neighbor-topology>
</ospf-neighbor>
 </ospf-neighbor-information | ospf-instance-neighbor>

Description No documentation is available yet.

Contents <activity-timer>—No documentation is available yet.

<bdr-address>—IP address of BDR.

<dbd-retransmit-time>—Seconds until DBD is retransmitted.

<dr-address>—IP address of DR.

<interface-name>—No documentation is available yet.

<lsa-list>—No documentation is available yet.

<lsreq-active>—No documentation is available yet.

<lsreq-enqueued>—No documentation is available yet.

<lsreq-retransmit-time>—Seconds until LSREQ is retransmitted.

<master-slave>—No documentation is available yet.

<neighbor-address>—IP address of this neighbor.

<neighbor-adjacency-time>—Time when neighbor became adjacent.

<neighbor-id>—No documentation is available yet.

<neighbor-priority>—No documentation is available yet.

<neighbor-secondary>—OSPF neighbor is on secondary interface.

<neighbor-suppress-hello>—Time when neighbor suppressed hellos.

<neighbor-up-time>—Time when neighbor came up.

<options>—No documentation is available yet.

<ospf-area>—Area ID.

<ospf-neighbor-state>—No documentation is available yet.

<ospf-neighbor-topology>—OSPF topology specific neighbor information.

<sequence-number>—History event number.

<ospf-neighbor-information>

Usage <rpc-reply>
 <ospf-neighbor-information>
 <ospf-neighbor>...</ospf-neighbor>
 </ospf-neighbor-information>
 </rpc-reply>

Description Information about OSPF neighbors in a routing instance.

Contents <ospf-neighbor>—No documentation is available yet.

<ospf-neighbor-information-all>

Usage <rpc-reply>
 <ospf-neighbor-information-all>
 <ospf-instance-neighbor>...</ospf-instance-neighbor>
 </ospf-neighbor-information-all>
 </rpc-reply>

Description Information about OSPF neighbors in all routing instances.

Contents <ospf-instance-neighbor>—Information about OSPF neighbors within this routing instance.

<ospf-neighbor-replication>

Usage <ospf-neighbor-replication-information | ospf3-neighbor-replication-information>
<ospf-neighbor-replication>
 <interface-name>*interface-name*</interface-name>
 <ospf-area>*ospf-area*</ospf-area>
 <neighbor-id>*neighbor-id*</neighbor-id>
 <ospf-synchronization-state>*ospf-synchronization-state*
 </ospf-synchronization-state>
 <ospf-neighbor-state>*ospf-neighbor-state*</ospf-neighbor-state>
 <ospf-ifl-index>*ospf-ifl-index*</ospf-ifl-index>
 <ospf-route-table-index>*ospf-route-table-index*</ospf-route-table-index>
 <ospf-unsync-reason>*ospf-unsync-reason*</ospf-unsync-reason>
</ospf-neighbor-replication>
 </ospf-neighbor-replication-information | ospf3-neighbor-replication-information>

Description OSPF neighbor replication information.

Contents <interface-name>—No documentation is available yet.

<neighbor-id>—No documentation is available yet.

<ospf-area>—Area ID.

<ospf-ifl-index>—Interface index.

<ospf-neighbor-state>—No documentation is available yet.

<ospf-route-table-index>—Route table index.

<ospf-synchronization-state>—Synchronization state of the replicated entry.

<ospf-unsync-reason>—No documentation is available yet.

<ospf-neighbor-replication-information>

Usage <rpc-reply>
<ospf-neighbor-replication-information>
 <ospf-neighbor-replication>...</ospf-neighbor-replication>
</ospf-neighbor-replication-information>
 </rpc-reply>

Description OSPFv2 neighbor replication information.

Contents <ospf-neighbor-replication>—OSPF neighbor replication information.

<ospf-neighbor-topology>

Usage <ospf-neighbor>
 <ospf-neighbor-topology>
 <ospf-topology-name>*ospf-topology-name*</ospf-topology-name>
 <ospf-topology-id>*ospf-topology-id*</ospf-topology-id>
 <ospf-neighbor-topology-state>*ospf-neighbor-topology-state*
 </ospf-neighbor-topology-state>
 </ospf-neighbor-topology>
 </ospf-neighbor>

Description OSPF topology specific neighbor information.

Contents <ospf-neighbor-topology-state>—State of the neighbor in a topology.

<ospf-topology-id>—OSPF topology id.

<ospf-topology-name>—OSPF topology name.

<ospf-network-lsa>

Usage <ospf-database>
 <ospf-network-lsa>
 <address-mask>*address-mask*</address-mask>
 <attached-router>*attached-router*</attached-router>
 </ospf-network-lsa>
 </ospf-database>

Description No documentation is available yet.

Contents <address-mask>—No documentation is available yet.

<attached-router>—No documentation is available yet.

<ospf-opaque-area-lsa>

Usage <ospf-database>
 <ospf-opaque-area-lsa>
 <tlv-block>...</tlv-block>
 <te-subtlv>...</te-subtlv>
 </ospf-opaque-area-lsa>
 </ospf-database>

Description No documentation is available yet.

Contents <te-subtlv>—No documentation is available yet.

<tlv-block>—No documentation is available yet.

<ospf-opaque-link-local-lsa>

- Usage** <ospf-database | ospf3-database>
 <ospf-opaque-link-local-lsa>
 <ospf-link-local-grace-lsa>...</ospf-link-local-grace-lsa>
 <ospf-link-local-te-lsa>...</ospf-link-local-te-lsa>
 </ospf-opaque-link-local-lsa>
 </ospf-database | ospf3-database>
- Description** No documentation is available yet.
- Contents** <ospf-link-local-grace-lsa>—No documentation is available yet.
 <ospf-link-local-te-lsa>—No documentation is available yet.

<ospf-overview>

Usage <ospf-overview-information | ospf3-overview-information>

```

<ospf-overview>
  <instance-name>instance-name</instance-name>
  <ospf-router-id>ospf-router-id</ospf-router-id>
  <ospf-route-table-index>ospf-route-table-index</ospf-route-table-index>
  <ospf-configured-overload/>
  <ospf-configured-overload-remaining-time>ospf-configured-overload-remaining-time
    </ospf-configured-overload-remaining-time>

  <ospf-abr/>
  <ospf-asbr/>
  <ospf-nssa-router/>
  <ospf-lsa-refresh-time>ospf-lsa-refresh-time</ospf-lsa-refresh-time>
  <ospf-traffic-engineering/>
  <ospf-restart>ospf-restart</ospf-restart>
  <ospf-restart-enabled>ospf-restart-enabled</ospf-restart-enabled>
  <ospf-restart-duration>ospf-restart-duration</ospf-restart-duration>
  <ospf-restart-grace-period>ospf-restart-grace-period
    </ospf-restart-grace-period>
  <ospf-restart-helper-mode>ospf-restart-helper-mode</ospf-restart-helper-mode>
  <no-rfc-1583/>
  <ospf-dna-uncapable/>
  <ospf-as-dc-bit-clear-count>ospf-as-dc-bit-clear-count
    </ospf-as-dc-bit-clear-count>
  <ospf-area-dc-bit-clear-count>ospf-area-dc-bit-clear-count
    </ospf-area-dc-bit-clear-count>
  <ospf-area-indications-count>ospf-area-indications-count
    </ospf-area-indications-count>
  <ospf-link-dc-bit-clear-count>ospf-link-dc-bit-clear-count
    </ospf-link-dc-bit-clear-count>
  <tracing-information>...</tracing-information>
  <ospf-area-overview>...</ospf-area-overview>
  <ospf-topology-overview>...</ospf-topology-overview>
</ospf-overview>
</ospf-overview-information | ospf3-overview-information>

```

Description Overview information for an OSPF instance.

Contents <instance-name>—No documentation is available yet.

<no-rfc-1583>—RFC1583 compatibility is disabled.

<ospf-abr>—Router is an area border router.

<ospf-area-dc-bit-clear-count>—Number of area scope link-state advertisements received with DC bit clear.

<ospf-area-indications-count>—Number of indication link-state advertisements received.

<ospf-area-overview>—Overview information for an OSPF area.

<ospf-as-dc-bit-clear-count>—Number of AS scope link-state advertisements received with DC bit clear.

<ospf-asbr>—Router is an autonomous system boundary router.

<ospf-configured-overload>—Instance is configured to be in overload.

<ospf-configured-overload-remaining-time>—Time remaining on configured overload timeout.

<ospf-dna-uncapable>—Not safe to generate DoNotAge LSAs.

<ospf-link-dc-bit-clear-count>—Number of link local scope link-state advertisements received with no DC bit clear.

<ospf-lsa-refresh-time>—Refresh period for link-state advertisement (in minutes).

<ospf-nssa-router>—Router is a not-so-stubby area router.

<ospf-restart>—OSPF restart parameters.

<ospf-restart-duration>—Duration of OSPF restart (seconds).

<ospf-restart-enabled>—OSPF restart mode.

<ospf-restart-grace-period>—Grace period for OSPF restart (seconds).

<ospf-restart-helper-mode>—OSPF helper mode.

<ospf-route-table-index>—Route table index.

<ospf-router-id>—OSPF router ID.

<ospf-topology-overview>—OSPF topology specific overview information.

<ospf-traffic-engineering>—Traffic engineering is enabled.

<tracing-information>—No documentation is available yet.

<ospf-overview-information>

Usage	<pre> <rpc-reply> <ospf-overview-information> <ospf-overview>...</ospf-overview> </ospf-overview-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<ospf-overview>—Overview information for an OSPF instance.

<ospf-route>

Usage <ospf-topology-route-table>
<ospf-route>
 <address-prefix>*address-prefix*</address-prefix>
 <route-path-type>*route-path-type*</route-path-type>
 <route-type>*route-type*</route-type>
 <next-hop-type>*next-hop-type*</next-hop-type>
 <interface-cost>*interface-cost*</interface-cost>
 <next-hop-name>...</next-hop-name>
 <next-hop-address>...</next-hop-address>
 <ospf-area>*ospf-area*</ospf-area>
 <optional-capability>*optional-capability*</optional-capability>
 <route-origin>*route-origin*</route-origin>
 <route-priority>*route-priority*</route-priority>
 <type7/>
 <pbit/>
 <forward-nz/>
</ospf-route>
 </ospf-topology-route-table>

Description No documentation is available yet.

Contents <address-prefix>—No documentation is available yet.

<forward-nz>—No documentation is available yet.

<interface-cost>—Cost associated with this interface.

<next-hop-address>—No documentation is available yet.

<next-hop-name>—No documentation is available yet.

<next-hop-type>—No documentation is available yet.

<optional-capability>—VEB bits received in the router LSA.

<ospf-area>—Area ID.

<pbit>—No documentation is available yet.

<route-origin>—No documentation is available yet.

<route-path-type>—No documentation is available yet.

<route-priority>—No documentation is available yet.

<route-type>—No documentation is available yet.

<type7>—No documentation is available yet.

<ospf-route-information>

- Usage** <rpc-reply>
 <ospf-route-information>
 <ospf-topology-route-table>...</ospf-topology-route-table>
 </ospf-route-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <ospf-topology-route-table>—OSPF topology specific routing table.

<ospf-router-link-topology>

- Usage** <ospf-link>
 <ospf-router-link-topology>
 <ospf-topology-name>ospf-topology-name</ospf-topology-name>
 <ospf-topology-id>ospf-topology-id</ospf-topology-id>
 <ospf-topology-metric>ospf-topology-metric</ospf-topology-metric>
 </ospf-router-link-topology>
 </ospf-link>
- Description** OSPF topology specific information for a router link.
- Contents** <ospf-topology-id>—OSPF topology id.
- <ospf-topology-metric>—OSPF topology specific metric.
- <ospf-topology-name>—OSPF topology name.

<ospf-router-lsa>

- Usage** <ospf-database>
 <ospf-router-lsa>
 <bits>bits</bits>
 <link-count>link-count</link-count>
 <ospf-link>...</ospf-link>
 </ospf-router-lsa>
 </ospf-database>
- Description** No documentation is available yet.
- Contents** <bits>—No documentation is available yet.
- <link-count>—No documentation is available yet.
- <ospf-link>—No documentation is available yet.

<ospf-statistics>

Usage <ospf-statistics-information | ospf3-statistics-information>

```

<ospf-statistics>
  <packet-statistics>...</packet-statistics>
  <dbds-retransmit>dbds-retransmit</dbds-retransmit>
  <dbds-retransmit-5seconds>dbds-retransmit-5secs</dbds-retransmit-5seconds>
  <lsas-flooded>lsas-flooded</lsas-flooded>
  <lsas-flooded-5seconds>lsas-flooded-5seconds</lsas-flooded-5seconds>
  <lsas-high-prio-flooded>lsas-high-prio-flooded</lsas-high-prio-flooded>
  <lsas-high-prio-flooded-5seconds>lsas-high-prio-flooded-5seconds
    </lsas-high-prio-flooded-5seconds>
  <lsas-retransmit>lsas-retransmit</lsas-retransmit>
  <lsas-retransmit-5seconds>lsas-retransmit-5seconds</lsas-retransmit-5seconds>
  <lsas-nbr-transmit>lsas-nbr-transmit</lsas-nbr-transmit>
  <lsas-nbr-transmit-5seconds>lsas-nbr-transmit-5seconds
    </lsas-nbr-transmit-5seconds>
  <lsas-requested>lsas-requested</lsas-requested>
  <lsas-requested-5seconds>lsas-requested-5seconds</lsas-requested-5seconds>
  <lsas-acknowledged>lsas-acknowledged</lsas-acknowledged>
  <lsas-acknowledged-5seconds>lsas-acknowledged-5seconds
    </lsas-acknowledged-5seconds>
  <flood-queue-depth>flood-queue-depth</flood-queue-depth>
  <total-retransmits>total-retransmits</total-retransmits>
  <total-database-summaries>total-db-summaries</total-database-summaries>
  <total-linkstate-request>total-linkstate-request</total-linkstate-request>
  <ospf-errors>...</ospf-errors>
</ospf-statistics>
</ospf-statistics-information | ospf3-statistics-information>

```

Description No documentation is available yet.

Contents <dbds-retransmit>—No documentation is available yet.

<dbds-retransmit-5seconds>—No documentation is available yet.

<flood-queue-depth>—No documentation is available yet.

<lsas-acknowledged>—No documentation is available yet.

<lsas-acknowledged-5seconds>—No documentation is available yet.

<lsas-flooded>—No documentation is available yet.

<lsas-flooded-5seconds>—No documentation is available yet.

<lsas-high-prio-flooded>—No documentation is available yet.

<lsas-high-prio-flooded-5seconds>—No documentation is available yet.

<lsas-nbr-transmit>—No documentation is available yet.

<lsas-nbr-transmit-5seconds>—No documentation is available yet.

<lsas-requested>—No documentation is available yet.

<lsas-requested-5seconds>—No documentation is available yet.

<lsas-retransmit>—No documentation is available yet.

<lsas-retransmit-5seconds>—No documentation is available yet.

<ospf-errors>—No documentation is available yet.

<packet-statistics>—No documentation is available yet.

<total-database-summaries>—No documentation is available yet.

<total-linkstate-request>—No documentation is available yet.

<total-retransmits>—No documentation is available yet.

<ospf-statistics-information>

Usage <rpc-reply>
 <ospf-statistics-information>
 <ospf-statistics>...</ospf-statistics>
 </ospf-statistics-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <ospf-statistics>—No documentation is available yet.

<ospf-summary-lsa>

Usage <ospf-database>
 <ospf-summary-lsa>
 <address-mask>*address-mask*</address-mask>
 <ospf-summary-lsa-topology>...</ospf-summary-lsa-topology>
 </ospf-summary-lsa>
 </ospf-database>

Description No documentation is available yet.

Contents <address-mask>—No documentation is available yet.

<ospf-summary-lsa-topology>—OSPF topology specific information for a summary LSA.

<ospf-summary-lsa-topology>

Usage	<pre> <ospf-summary-lsa> <ospf-summary-lsa-topology> <ospf-topology-name>ospf-topology-name</ospf-topology-name> <ospf-topology-id>ospf-topology-id</ospf-topology-id> <ospf-topology-metric>ospf-topology-metric</ospf-topology-metric> </ospf-summary-lsa-topology> </ospf-summary-lsa> </pre>
Description	OSPF topology specific information for a summary LSA.
Contents	<p><ospf-topology-id>—OSPF topology id.</p> <p><ospf-topology-metric>—OSPF topology specific metric.</p> <p><ospf-topology-name>—OSPF topology name.</p>

<ospf-topology-log>

Usage	<pre> <ospf-log-information> <ospf-topology-log> <ospf-topology-name>ospf-topology-name</ospf-topology-name> <ospf-log-instance>...</ospf-log-instance> <ospf-log-maximum-length>...</ospf-log-maximum-length> <ospf-log-events>...</ospf-log-events> </ospf-topology-log> </ospf-log-information> </pre>
Description	OSPF topology specific SPF log information.
Contents	<p><ospf-log-events>—No documentation is available yet.</p> <p><ospf-log-instance>—No documentation is available yet.</p> <p><ospf-log-maximum-length>—No documentation is available yet.</p> <p><ospf-topology-name>—OSPF topology name.</p>

<ospf-topology-overview>

Usage <ospf-overview>
 <ospf-topology-overview>
 <ospf-topology-name>ospf-topology-name</ospf-topology-name>
 <ospf-topology-id>ospf-topology-id</ospf-topology-id>
 <ospf-topology-configured-overload/>
 <ospf-topology-dynamic-overload/>
 <ospf-prefix-export-count>ospf-prefix-export-count</ospf-prefix-export-count>
 <ospf-prefix-export-limit>ospf-prefix-export-limit</ospf-prefix-export-limit>
 <ospf-full-spf-count>ospf-full-spf-count</ospf-full-spf-count>
 <ospf-spf-delay>ospf-spf-delay</ospf-spf-delay>
 <ospf-spf-holddown>ospf-spf-holddown</ospf-spf-holddown>
 <ospf-spf-rapid-runs>ospf-spf-rapid-runs</ospf-spf-rapid-runs>
 <ospf-te-shortcuts/>
 </ospf-topology-overview>
 </ospf-overview>

Description OSPF topology specific overview information.

Contents <ospf-full-spf-count>—Number of full SPF calculations.

<ospf-prefix-export-count>—Number of prefixes exported into the topology.

<ospf-prefix-export-limit>—Number of prefixes we are allowed to exported into the topology.

<ospf-spf-delay>—Delay before performing consecutive SPF calculations.

<ospf-spf-holddown>—Time to hold down before running an SPF.

<ospf-spf-rapid-runs>—Number of rapid SPF runs before SPF holddown.

<ospf-te-shortcuts>—Traffic engineering shortcuts are enabled.

<ospf-topology-configured-overload>—Topology is configured to be in overload.

<ospf-topology-dynamic-overload>—Topology is in dynamic overload i.e. prefix limit was exceeded.

<ospf-topology-id>—OSPF topology id.

<ospf-topology-name>—OSPF topology name.

<ospf-topology-route-table>

Usage <ospf-route-information>
 <ospf-topology-route-table>
 <ospf-topology-name>*ospf-topology-name*</ospf-topology-name>
 <ospf-route>...</ospf-route>
 </ospf-topology-route-table>
 </ospf-route-information>

Description OSPF topology specific routing table.

Contents <ospf-route>—No documentation is available yet.
 <ospf-topology-name>—OSPF topology name.

<ospf3-area-header>

Usage <ospf3-database-information>
 <ospf3-area-header>
 <ospf-area>*ospf-area*</ospf-area>
 </ospf3-area-header>
 </ospf3-database-information>

Description No documentation is available yet.

Contents <ospf-area>—Area ID.

<ospf3-database>

Usage <ospf3-database-information>
<ospf3-database>
 <lsa-type>*lsa-type*</lsa-type>
 <our-entry/>
 <lsa-id>*lsa-id*</lsa-id>
 <advertising-router>*advertising-router*</advertising-router>
 <sequence-number>*sequence-number*</sequence-number>
 <age>*age*</age>
 <ospf-do-not-age/>
 <checksum>*checksum*</checksum>
 <lsa-length>*lsa-length*</lsa-length>
 <ospf3-router-lsa>...</ospf3-router-lsa>
 <ospf3-network-lsa>...</ospf3-network-lsa>
 <ospf3-inter-area-prefix-lsa>...</ospf3-inter-area-prefix-lsa>
 <ospf3-inter-area-router-lsa>...</ospf3-inter-area-router-lsa>
 <ospf3-external-lsa>...</ospf3-external-lsa>
 <ospf3-link-lsa>...</ospf3-link-lsa>
 <ospf3-intra-area-prefix-lsa>...</ospf3-intra-area-prefix-lsa>
 <ospf-database-extensive>...</ospf-database-extensive>
 <ospf-opaque-link-local-lsa>...</ospf-opaque-link-local-lsa>
</ospf3-database>
 </ospf3-database-information>

Description No documentation is available yet.

Contents <advertising-router>—No documentation is available yet.

<age>—No documentation is available yet.

<checksum>—No documentation is available yet.

<lsa-id>—No documentation is available yet.

<lsa-length>—No documentation is available yet.

<lsa-type>—No documentation is available yet.

<ospf-database-extensive>—No documentation is available yet.

<ospf-do-not-age>—DoNotAge bit is set on the link-state advertisement received.

<ospf-opaque-link-local-lsa>—No documentation is available yet.

<ospf3-external-lsa>—No documentation is available yet.

<ospf3-inter-area-prefix-lsa>—No documentation is available yet.

<ospf3-inter-area-router-lsa>—No documentation is available yet.

<ospf3-intra-area-prefix-lsa>—No documentation is available yet.

<ospf3-link-lsa>—No documentation is available yet.

<ospf3-network-lsa>—No documentation is available yet.

<ospf3-router-lsa>—No documentation is available yet.

<our-entry>—No documentation is available yet.

<sequence-number>—History event number.

<ospf3-database-information>

Usage <rpc-reply>
 <ospf3-database-information>
 <ospf3-area-header>...</ospf3-area-header>
 <ospf3-intf-header>...</ospf3-intf-header>
 <ospf3-database>...</ospf3-database>
 <ospf3-database-summary>...</ospf3-database-summary>
 </ospf3-database-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <ospf3-area-header>—No documentation is available yet.
 <ospf3-database>—No documentation is available yet.
 <ospf3-database-summary>—No documentation is available yet.
 <ospf3-intf-header>—No documentation is available yet.

<ospf3-database-replication-information>

Usage <rpc-reply>
 <ospf3-database-replication-information>
 <ospf-database-replication>...</ospf-database-replication>
 </ospf3-database-replication-information>
 </rpc-reply>

Description OSPFv3 LSA replication information.

Contents <ospf-database-replication>—OSPF LSA replication information.

<ospf3-database-summary>

- Usage** <ospf3-database-information>
 <ospf3-database-summary>
 <ospf-area>ospf-area</ospf-area>
 <ospf-intf>ospf-intf</ospf-intf>
 <ospf-lsa-count>ospf-lsa-count</ospf-lsa-count>
 <ospf-lsa-type>ospf-lsa-type</ospf-lsa-type>
 </ospf3-database-summary>
 </ospf3-database-information>
- Description** No documentation is available yet.
- Contents** <ospf-area>—Area ID.
 <ospf-intf>—Name of interface.
 <ospf-lsa-count>—No documentation is available yet.
 <ospf-lsa-type>—No documentation is available yet.

<ospf3-external-lsa>

- Usage** <ospf3-database>
 <ospf3-external-lsa>
 <ospf3-prefix>ospf3-prefix</ospf3-prefix>
 <ospf3-prefix-options>ospf3-prefix-options</ospf3-prefix-options>
 <type-value>type-value</type-value>
 <metric>metric</metric>
 <forward-address>forward-address</forward-address>
 <tag>tag</tag>
 </ospf3-external-lsa>
 </ospf3-database>
- Description** No documentation is available yet.
- Contents** <forward-address>—No documentation is available yet.
 <metric>—No documentation is available yet.
 <ospf3-prefix>—No documentation is available yet.
 <ospf3-prefix-options>—No documentation is available yet.
 <tag>—No documentation is available yet.
 <type-value>—No documentation is available yet.

<ospf3-instance-neighbor>

Usage <ospf3-neighbor-information-all>
 <ospf3-instance-neighbor>
 <ospf-instance-name>*ospf-instance-name*</ospf-instance-name>
 <ospf3-realm-neighbor>...</ospf3-realm-neighbor>
 </ospf3-instance-neighbor>
 </ospf3-neighbor-information-all>

Description Information about OSPFv3 neighbors within this routing instance.

Contents <ospf-instance-name>—Name of OSPF instance.
 <ospf3-realm-neighbor>—Information about OSPFv3 neighbors within this realm.

<ospf3-inter-area-prefix-lsa>

Usage <ospf3-database>
 <ospf3-inter-area-prefix-lsa>
 <ospf3-prefix>*ospf3-prefix*</ospf3-prefix>
 <ospf3-prefix-options>*ospf3-prefix-options*</ospf3-prefix-options>
 <metric>*metric*</metric>
 </ospf3-inter-area-prefix-lsa>
 </ospf3-database>

Description No documentation is available yet.

Contents <metric>—No documentation is available yet.
 <ospf3-prefix>—No documentation is available yet.
 <ospf3-prefix-options>—No documentation is available yet.

<ospf3-inter-area-router-lsa>

Usage <ospf3-database>
 <ospf3-inter-area-router-lsa>
 <destination-router-id>*destination-router-id*</destination-router-id>
 <ospf3-options>*ospf3-options*</ospf3-options>
 <metric>*metric*</metric>
 </ospf3-inter-area-router-lsa>
 </ospf3-database>

Description No documentation is available yet.

Contents <destination-router-id>—No documentation is available yet.
 <metric>—No documentation is available yet.
 <ospf3-options>—No documentation is available yet.

<ospf3-interface>

Usage <ospf3-interface-information>
<ospf3-interface>
 <interface-name>*interface-name*</interface-name>
 <ospf-interface-state>*ospf-interface-state*</ospf-interface-state>
 <ospf-area>*ospf-area*</ospf-area>
 <dr-id>*dr-id*</dr-id>
 <bdr-id>*bdr-id*</bdr-id>
 <neighbor-count>*neighbor-count*</neighbor-count>
 <interface-address>*interface-address*</interface-address>
 <prefix-length>*prefix-length*</prefix-length>
 <ospf3-interface-index>*ospf3-interface-index*</ospf3-interface-index>
 <interface-type>*interface-type*</interface-type>
 <mtu>*mtu*</mtu>
 <interface-cost>*interface-cost*</interface-cost>
 <virtual-link-transit-area>*virtual-link-transit-area*
 </virtual-link-transit-area>
 <virtual-link-destination>*virtual-link-destination*</virtual-link-destination>
 <dr-address>*dr-address*</dr-address>
 <bdr-address>*bdr-address*</bdr-address>
 <adj-count>*adj-count*</adj-count>
 <router-priority>*router-priority*</router-priority>
 <passive>*passive*</passive>
 <hello-interval>*hello-interval*</hello-interval>
 <poll-interval>*poll-interval*</poll-interval>
 <dead-interval>*dead-interval*</dead-interval>
 <retransmit-interval>*retransmit-interval*</retransmit-interval>
 <ospf-stub-type>*ospf-stub-type*</ospf-stub-type>
 <ipsec-sa>*ipsec-sa*</ipsec-sa>
 <igp-ldp-sync-holdtime>*igp-ldp-sync-holdtime*</igp-ldp-sync-holdtime>
 <igp-ldp-sync-state>*igp-ldp-sync-state*</igp-ldp-sync-state>
 <igp-ldp-sync-last-change>*igp-ldp-sync-last-change*</igp-ldp-sync-last-change>
 <igp-ldp-sync-reason>*igp-ldp-sync-reason*</igp-ldp-sync-reason>
 <igp-ldp-sync-timeleft>*igp-ldp-sync-timeleft*</igp-ldp-sync-timeleft>
 <interface-flood-list-count>*interface-flood-list-count*
 </interface-flood-list-count>
 <flood-list-count>*flood-list-count*</flood-list-count>
 <lsa-list>*lsa-list*</lsa-list>
 <interface-description-list>*interface-description-list*
 </interface-description-list>
</ospf3-interface>
 </ospf3-interface-information>

Description No documentation is available yet.

Contents <adj-count>—Count of fully adjacent neighbors.

<bdr-address>—IP address of BDR.

<bdr-id>—No documentation is available yet.

<dead-interval>—No documentation is available yet.

<dr-address>—IP address of DR.

<dr-id>—No documentation is available yet.

<flood-list-count>—No documentation is available yet.

<hello-interval>—Rate at which RSVP hellos are sent out. Default is 3 seconds.

<igp-ldp-sync-holdtime>—Length of time during which the maximum metric is advertised for an interface that is in the hold-down state because synchronization was lost between Label Distribution Protocol (LDP) and the interior gateway protocol (IGP).

<igp-ldp-sync-last-change>—Time since the state of synchronization between Label Distribution Protocol (LDP) and the interior gateway protocol (IGP) last changed.

<igp-ldp-sync-reason>—Reason for the change in the state of synchronization between Label Distribution Protocol (LDP) and the interior gateway protocol (IGP).

<igp-ldp-sync-state>—State of synchronization between Label Distribution Protocol (LDP) and the interior gateway protocol (IGP).

<igp-ldp-sync-timeleft>—Remaining amount of time the interface will remain in the hold-down state because synchronization was lost between Label Distribution Protocol (LDP) and the interior gateway protocol (IGP).

<interface-address>—No documentation is available yet.

<interface-cost>—Cost associated with this interface.

<interface-description-list>—No documentation is available yet.

<interface-flood-list-count>—No documentation is available yet.

<interface-name>—No documentation is available yet.

<interface-type>—No documentation is available yet.

<ipsec-sa>—No documentation is available yet.

<lsa-list>—No documentation is available yet.

<mtu>—MTU along an interface.

<neighbor-count>—Number of neighbors on PIM interface.

<ospf-area>—Area ID.

<ospf-interface-state>—No documentation is available yet.

<ospf-stub-type>—Stub type of area.

<ospf3-interface-index>—No documentation is available yet.

<passive>—No documentation is available yet.

<poll-interval>—No documentation is available yet.

<prefix-length>—No documentation is available yet.

<retransmit-interval>—No documentation is available yet.

<router-priority>—Router priority used in DR election on broadcast or NBMA interface.

<virtual-link-destination>—Virtual link destination address.

<virtual-link-transit-area>—Virtual link transit area.

<ospf3-interface-information>

Usage <rpc-reply>
 <ospf3-interface-information>
 <ospf3-interface>...</ospf3-interface>
 </ospf3-interface-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <ospf3-interface>—No documentation is available yet.

<ospf3-interface-replication-information>

Usage <rpc-reply>
 <ospf3-interface-replication-information>
 <ospf-interface-replication>...</ospf-interface-replication>
 </ospf3-interface-replication-information>
 </rpc-reply>

Description OSPFv3 interface replication information.

Contents <ospf-interface-replication>—OSPF interface replication information.

<ospf3-intf-header>

Usage <ospf3-database-information>
 <ospf3-intf-header>
 <ospf-intf>ospf-intf</ospf-intf>
 <ospf-area>ospf-area</ospf-area>
 </ospf3-intf-header>
 </ospf3-database-information>

Description No documentation is available yet.

Contents <ospf-area>—Area ID.

<ospf-intf>—Name of interface.

<ospf3-intra-area-prefix-lsa>

Usage <ospf3-database>
 <ospf3-intra-area-prefix-lsa>
 <reference-lsa-type>reference-lsa-type</reference-lsa-type>
 <reference-lsa-id>reference-lsa-id</reference-lsa-id>
 <reference-lsa-router-id>reference-lsa-router-id</reference-lsa-router-id>
 <prefix-count>prefix-count</prefix-count>
 <ospf3-prefix>ospf3-prefix</ospf3-prefix>
 <ospf3-prefix-options>ospf3-prefix-options</ospf3-prefix-options>
 <ospf3-prefix-metric>ospf3-prefix-metric</ospf3-prefix-metric>
 </ospf3-intra-area-prefix-lsa>
 </ospf3-database>

Description No documentation is available yet.

Contents <ospf3-prefix>—No documentation is available yet.

<ospf3-prefix-metric>—No documentation is available yet.

<ospf3-prefix-options>—No documentation is available yet.

<prefix-count>—Number of prefixes accepted before action is taken.

<reference-lsa-id>—No documentation is available yet.

<reference-lsa-router-id>—No documentation is available yet.

<reference-lsa-type>—No documentation is available yet.

<ospf3-io-statistics-information>

Usage <rpc-reply>
 <ospf3-io-statistics-information>
 <ospf-io-statistics>...</ospf-io-statistics>
 </ospf3-io-statistics-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <ospf-io-statistics>—No documentation is available yet.

<ospf3-link>

Usage	<pre> <ospf3-router-lsa> <ospf3-link> <link-type-name>link-type-name</link-type-name> <link-type-value>link-type-value</link-type-value> <link-intf-id>link-intf-id</link-intf-id> <nbr-intf-id>nbr-intf-id</nbr-intf-id> <nbr-rtr-id>nbr-rtr-id</nbr-rtr-id> <link-metric>link-metric</link-metric> </ospf3-link> </ospf3-router-lsa> </pre>
Description	No documentation is available yet.
Contents	<p><link-intf-id>—No documentation is available yet.</p> <p><link-metric>—No documentation is available yet.</p> <p><link-type-name>—No documentation is available yet.</p> <p><link-type-value>—No documentation is available yet.</p> <p><nbr-intf-id>—No documentation is available yet.</p> <p><nbr-rtr-id>—No documentation is available yet.</p>

<ospf3-link-lsa>

Usage	<pre> <ospf3-database> <ospf3-link-lsa> <linklocal-address>linklocal-address</linklocal-address> <ospf3-options>ospf3-options</ospf3-options> <router-priority>router-priority</router-priority> <prefix-count>prefix-count</prefix-count> <ospf3-prefix>ospf3-prefix</ospf3-prefix> <ospf3-prefix-options>ospf3-prefix-options</ospf3-prefix-options> </ospf3-link-lsa> </ospf3-database> </pre>
Description	No documentation is available yet.
Contents	<p><linklocal-address>—No documentation is available yet.</p> <p><ospf3-options>—No documentation is available yet.</p> <p><ospf3-prefix>—No documentation is available yet.</p> <p><ospf3-prefix-options>—No documentation is available yet.</p> <p><prefix-count>—Number of prefixes accepted before action is taken.</p> <p><router-priority>—Router priority used in DR election on broadcast or NBMA interface.</p>

<ospf3-log-information>

Usage <rpc-reply>
 <ospf3-log-information>
 <ospf-log-instance>...</ospf-log-instance>
 <ospf-log-maximum-length>...</ospf-log-maximum-length>
 <ospf-log-events>...</ospf-log-events>
 </ospf3-log-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <ospf-log-events>—No documentation is available yet.

 <ospf-log-instance>—No documentation is available yet.

 <ospf-log-maximum-length>—No documentation is available yet.

<ospf3-neighbor>

Usage <ospf3-neighbor-information | ospf3-realm-neighbor>
<ospf3-neighbor>
 <neighbor-id>*neighbor-id*</neighbor-id>
 <interface-name>*interface-name*</interface-name>
 <ospf-neighbor-state>*ospf-neighbor-state*</ospf-neighbor-state>
 <neighbor-priority>*neighbor-priority*</neighbor-priority>
 <activity-timer>*activity-timer*</activity-timer>
 <neighbor-address>*neighbor-address*</neighbor-address>
 <ospf-area>*ospf-area*</ospf-area>
 <options>*options*</options>
 <ospf3-interface-index>*ospf3-interface-index*</ospf3-interface-index>
 <dr-id>*dr-id*</dr-id>
 <bdr-id>*bdr-id*</bdr-id>
 <neighbor-up-time>*neighbor-up-time*</neighbor-up-time>
 <neighbor-adjacency-time>*neighbor-adjacency-time*</neighbor-adjacency-time>
 <neighbor-suppress-hello>*neighbor-suppress-hello*</neighbor-suppress-hello>
 <master-slave>*master-slave*</master-slave>
 <sequence-number>*sequence-number*</sequence-number>
 <dbd-retransmit-time>*dbd-retransmit-time*</dbd-retransmit-time>
 <lsreq-retransmit-time>*lsreq-retransmit-time*</lsreq-retransmit-time>
 <lsreq-enqueued/>
 <lsreq-active/>
 <lsa-list>*lsa-list*</lsa-list>
</ospf3-neighbor>
 </ospf3-neighbor-information | ospf3-realm-neighbor>

Description No documentation is available yet.

Contents <activity-timer>—No documentation is available yet.
 <bdr-id>—No documentation is available yet.
 <dbd-retransmit-time>—Seconds until DBD is retransmitted.
 <dr-id>—No documentation is available yet.
 <interface-name>—No documentation is available yet.
 <lsa-list>—No documentation is available yet.
 <lsreq-active>—No documentation is available yet.
 <lsreq-enqueued>—No documentation is available yet.
 <lsreq-retransmit-time>—Seconds until LSREQ is retransmitted.
 <master-slave>—No documentation is available yet.
 <neighbor-address>—IP address of this neighbor.
 <neighbor-adjacency-time>—Time when neighbor became adjacent.
 <neighbor-id>—No documentation is available yet.

<neighbor-priority>—No documentation is available yet.

<neighbor-suppress-hello>—Time when neighbor suppressed hellos.

<neighbor-up-time>—Time when neighbor came up.

<options>—No documentation is available yet.

<ospf-area>—Area ID.

<ospf-neighbor-state>—No documentation is available yet.

<ospf3-interface-index>—No documentation is available yet.

<sequence-number>—History event number.

<ospf3-neighbor-information>

Usage <rpc-reply>
 <ospf3-neighbor-information>
 <ospf3-neighbor>...</ospf3-neighbor>
 </ospf3-neighbor-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <ospf3-neighbor>—No documentation is available yet.

<ospf3-neighbor-information-all>

Usage <rpc-reply>
 <ospf3-neighbor-information-all>
 <ospf3-instance-neighbor>...</ospf3-instance-neighbor>
 </ospf3-neighbor-information-all>
 </rpc-reply>

Description Information about OSPFv3 neighbors in all routing instances.

Contents <ospf3-instance-neighbor>—Information about OSPFv3 neighbors within this routing instance.

<ospf3-neighbor-replication-information>

Usage <rpc-reply>
 <ospf3-neighbor-replication-information>
 <ospf-neighbor-replication>...</ospf-neighbor-replication>
 </ospf3-neighbor-replication-information>
 </rpc-reply>

Description OSPFv3 neighbor replication information.

Contents <ospf-neighbor-replication>—OSPF neighbor replication information.

<ospf3-network-lsa>

- Usage** <ospf3-database>
 <ospf3-network-lsa>
 <ospf3-options>*ospf3-options*</ospf3-options>
 <attached-router>*attached-router*</attached-router>
 </ospf3-network-lsa>
 </ospf3-database>
- Description** No documentation is available yet.
- Contents** <attached-router>—No documentation is available yet.
 <ospf3-options>—No documentation is available yet.

<ospf3-overview-information>

- Usage** <rpc-reply>
 <ospf3-overview-information>
 <ospf-overview>...</ospf-overview>
 </ospf3-overview-information>
 </rpc-reply>
- Description** Overview information for an OSPFv3 instance.
- Contents** <ospf-overview>—Overview information for an OSPF instance.

<ospf3-realm-neighbor>

- Usage** <ospf3-instance-neighbor>
 <ospf3-realm-neighbor>
 <ospf3-realm-name>*ospf3-realm-name*</ospf3-realm-name>
 <ospf3-neighbor>...</ospf3-neighbor>
 </ospf3-realm-neighbor>
 </ospf3-instance-neighbor>
- Description** Information about OSPFv3 neighbors within this realm.
- Contents** <ospf3-neighbor>—No documentation is available yet.
 <ospf3-realm-name>—Name of OSPFv3 realm.

<ospf3-route>

Usage <ospf3-route-information>
<ospf3-route>
 <address-prefix>*address-prefix*</address-prefix>
 <route-path-type>*route-path-type*</route-path-type>
 <route-type>*route-type*</route-type>
 <next-hop-type>*next-hop-type*</next-hop-type>
 <interface-cost>*interface-cost*</interface-cost>
 <next-hop-name>...</next-hop-name>
 <next-hop-address>...</next-hop-address>
 <ospf-area>*ospf-area*</ospf-area>
 <optional-capability>*optional-capability*</optional-capability>
 <route-origin>*route-origin*</route-origin>
 <route-priority>*route-priority*</route-priority>
 <type7/>
 <pbit/>
 <forward-nz/>
</ospf3-route>
 </ospf3-route-information>

Description No documentation is available yet.

Contents <address-prefix>—No documentation is available yet.

<forward-nz>—No documentation is available yet.

<interface-cost>—Cost associated with this interface.

<next-hop-address>—No documentation is available yet.

<next-hop-name>—No documentation is available yet.

<next-hop-type>—No documentation is available yet.

<optional-capability>—VEB bits received in the router LSA.

<ospf-area>—Area ID.

<pbit>—No documentation is available yet.

<route-origin>—No documentation is available yet.

<route-path-type>—No documentation is available yet.

<route-priority>—No documentation is available yet.

<route-type>—No documentation is available yet.

<type7>—No documentation is available yet.

<ospf3-route-information>

- Usage** <rpc-reply>
 <ospf3-route-information>
 <ospf3-route>...</ospf3-route>
 </ospf3-route-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <ospf3-route>—No documentation is available yet.

<ospf3-router-lsa>

- Usage** <ospf3-database>
 <ospf3-router-lsa>
 <bits>*bits*</bits>
 <ospf3-options>*ospf3-options*</ospf3-options>
 <ospf3-link>...</ospf3-link>
 </ospf3-router-lsa>
 </ospf3-database>
- Description** No documentation is available yet.
- Contents** <bits>—No documentation is available yet.
- <ospf3-link>—No documentation is available yet.
- <ospf3-options>—No documentation is available yet.

<ospf3-statistics-information>

- Usage** <rpc-reply>
 <ospf3-statistics-information>
 <ospf-statistics>...</ospf-statistics>
 </ospf3-statistics-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <ospf-statistics>—No documentation is available yet.

<overbooked-bandwidth>

Usage <rsvp-telink>
 <overbooked-bandwidth>
 <bandwidth-priority>*bandwidth-priority*</bandwidth-priority>
 <total-reserved-bandwidth>*total-reserved-bandwidth*</total-reserved-bandwidth>
 </overbooked-bandwidth>
 </rsvp-telink>

Description Bandwidth overbooked at different priority levels.

Contents <bandwidth-priority>—No documentation is available yet.
 <total-reserved-bandwidth>—Total amount of bandwidth currently reserved.

<overbooked-ct-bandwidth>

Usage <rsvp-telink>
 <overbooked-ct-bandwidth>
 <ct-class>*ct-class*</ct-class>
 <ct-bw0>*ct-bw0*</ct-bw0>
 <ct-bw1>*ct-bw1*</ct-bw1>
 <ct-bw2>*ct-bw2*</ct-bw2>
 <ct-bw3>*ct-bw3*</ct-bw3>
 <ct-bw4>*ct-bw4*</ct-bw4>
 <ct-bw5>*ct-bw5*</ct-bw5>
 <ct-bw6>*ct-bw6*</ct-bw6>
 <ct-bw7>*ct-bw7*</ct-bw7>
 </overbooked-ct-bandwidth>
 </rsvp-telink>

Description Bandwidth overbooked at different class/priority levels.

Contents <ct-bw0>—No documentation is available yet.
 <ct-bw1>—No documentation is available yet.
 <ct-bw2>—No documentation is available yet.
 <ct-bw3>—No documentation is available yet.
 <ct-bw4>—No documentation is available yet.
 <ct-bw5>—No documentation is available yet.
 <ct-bw6>—No documentation is available yet.
 <ct-bw7>—No documentation is available yet.
 <ct-class>—Class type (0..7).

<packet-information>

Usage <rsvp-session | detour | detour-branch>
<packet-information>
 <previous-hop>*previous-hop*</previous-hop>
 <next-hop>*next-hop*</next-hop>
 <interface-name>*interface-name*</interface-name>
 <count>*count*</count>
</packet-information>
 </rsvp-session | detour | detour-branch>

Description RSVP packets sent or received per session.

Contents <count>—Number of entries.
 <interface-name>—No documentation is available yet.
 <next-hop>—Next-hop address.
 <previous-hop>—Previous-hop address.

<packet-statistics>

Usage <ospf-statistics>
<packet-statistics>
 <ospf-packet-type>*ospf-packet-type*</ospf-packet-type>
 <packets-sent>*packets-sent*</packets-sent>
 <packets-received>*packets-received*</packets-received>
 <packets-sent-5seconds>*packets-sent-5seconds*</packets-sent-5seconds>
 <packets-received-5seconds>*packets-received-5seconds*
 </packets-received-5seconds>
</packet-statistics>
 </ospf-statistics>

Description No documentation is available yet.

Contents <ospf-packet-type>—No documentation is available yet.
 <packets-received>—No documentation is available yet.
 <packets-received-5seconds>—No documentation is available yet.
 <packets-sent>—No documentation is available yet.
 <packets-sent-5seconds>—No documentation is available yet.

<path-available-bandwidth>

Usage	<pre> <mpls-lsp-path> <path-available-bandwidth> <bandwidth>bandwidth</bandwidth> <class-type>class-type</class-type> <class-bandwidth>class-bandwidth</class-bandwidth> </path-available-bandwidth> </mpls-lsp-path> </pre>
Description	Available bandwidth on an LSP path.
Contents	<p><bandwidth>—No documentation is available yet.</p> <p><class-bandwidth>—No documentation is available yet.</p> <p><class-type>—No documentation is available yet.</p>

<path-history>

Usage	<pre> <mpls-lsp-path> <path-history> <sequence-number>sequence-number</sequence-number> <time>time</time> <log>log</log> <route>route</route> </path-history> </mpls-lsp-path> </pre>
Description	Log over time of LSP path-related events.
Contents	<p><log>—Supplemental information of the event.</p> <p><route>—Latest RRO contents, as reported by RSVP.</p> <p><sequence-number>—History event number.</p> <p><time>—Time of the event.</p>

<pim-bootstrap-information>

Usage	<pre> <rpc-reply> <pim-bootstrap-information> <pim-instance>pim-instance</pim-instance> <bootstrap-family>...</bootstrap-family> </pim-bootstrap-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<p><bootstrap-family>—No documentation is available yet.</p> <p><pim-instance>—Name of the PIM instance.</p>

<pim-group-flags>

Usage <join-group>
 <pim-group-flags>
 <sparse/>
 <dense/>
 <delete/>
 <rptree/>
 <wildcard/>
 <spt/>
 <spt-pending/>
 </pim-group-flags>
 </join-group>

Description No documentation is available yet.

Contents <delete>—No documentation is available yet.

<dense>—No documentation is available yet.

<rptree>—No documentation is available yet.

<sparse>—No documentation is available yet.

<spt>—No documentation is available yet.

<spt-pending>—No documentation is available yet.

<wildcard>—No documentation is available yet.

<pim-interface>

Usage <pim-interfaces-information | pim-neighbors-information>
<pim-interface>
 <pim-interface-name>*pim-interface-name*</pim-interface-name>
 <status>*status*</status>
 <pim-interface-mode>*pim-interface-mode*</pim-interface-mode>
 <ip-protocol-version>*ip-protocol-version*</ip-protocol-version>
 <protocol-version>*protocol-version*</protocol-version>
 <interface-state>*interface-state*</interface-state>
 <neighbor-count>*neighbor-count*</neighbor-count>
 <interface-join-count>*interface-join-count*</interface-join-count>
 <designated-router-address>*designated-router-address*
 </designated-router-address>
 <pim-neighbor>...</pim-neighbor>
</pim-interface>
 </pim-interfaces-information | pim-neighbors-information>

Description No documentation is available yet.

Contents <designated-router-address>—Designated router address of PIM interface.

<interface-join-count>—Number of joins sent on the interface.

<interface-state>—State of PIM interface.

<ip-protocol-version>—IP protocol version of PIM interface.

<neighbor-count>—Number of neighbors on PIM interface.

<pim-interface-mode>—Mode of PIM interface.

<pim-interface-name>—Name of PIM interface.

<pim-neighbor>—No documentation is available yet.

<protocol-version>—PIM protocol version of PIM interface.

<status>—Status of PIM interface.

<pim-interfaces-information>

Usage <rpc-reply>
<pim-interfaces-information>
 <pim-instance>*pim-instance*</pim-instance>
 <pim-interface>...</pim-interface>
</pim-interfaces-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <pim-instance>—Name of the PIM instance.

<pim-interface>—No documentation is available yet.

<pim-join-information>

Usage <rpc-reply>
 <pim-join-information>
 <join-family>...</join-family>
 </pim-join-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <join-family>—No documentation is available yet.

<pim-mdt-information>

Usage <rpc-reply>
 <pim-mdt-information>
 <pim-instance>*pim-instance*</pim-instance>
 <mdt-default-group-address>*mdt-default-group-address*
 </mdt-default-group-address>
 <mdt-default-interface-name>*mdt-default-interface-name*
 </mdt-default-interface-name>
 <mdt-tunnel-direction>*mdt-tunnel-direction*</mdt-tunnel-direction>
 <mdt-pim-instance>*mdt-pim-instance*</mdt-pim-instance>
 <mdt-default-tunnel-information>*mdt-default-tunnel-information*
 </mdt-default-tunnel-information>
 <mdt-active-tunnel>...</mdt-active-tunnel>
 </pim-mdt-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <mdt-active-tunnel>—No documentation is available yet.

<mdt-default-group-address>—No documentation is available yet.

<mdt-default-interface-name>—No documentation is available yet.

<mdt-default-tunnel-information>—No documentation is available yet.

<mdt-pim-instance>—No documentation is available yet.

<mdt-tunnel-direction>—No documentation is available yet.

<pim-instance>—Name of the PIM instance.

<pim-neighbor>

Usage <pim-interface>
 <pim-neighbor>
 <pim-interface-name>*pim-interface-name*</pim-interface-name>
 <ip-protocol-version>*ip-protocol-version*</ip-protocol-version>
 <protocol-version>*protocol-version*</protocol-version>
 <pim-interface-mode>*pim-interface-mode*</pim-interface-mode>
 <neighbor-join-count>*neighbor-join-count*</neighbor-join-count>
 <pim-neighbor-flags>...</pim-neighbor-flags>
 <pim-neighbor-uptime>*pim-neighbor-uptime*</pim-neighbor-uptime>
 <pim-neighbor-address>*pim-neighbor-address*</pim-neighbor-address>
 <pim-neighbor-secondary-address>*pim-neighbor-secondary-address*
 </pim-neighbor-secondary-address>
 <hello-holdtime>*hello-holdtime*</hello-holdtime>
 <hello-holdtime-remaining>*hello-holdtime-remaining*</hello-holdtime-remaining>
 <hello-default-holdtime>*hello-default-holdtime*</hello-default-holdtime>
 <hello-default-holdtime-remaining>*hello-default-holdtime-remaining*
 </hello-default-holdtime-remaining>
 <hello-dr-priority>*hello-dr-priority*</hello-dr-priority>
 <hello-generation-id>*hello-generation-id*</hello-generation-id>
 <hello-lanprune-delay>*hello-lanprune-delay*</hello-lanprune-delay>
 <hello-override-interval>*hello-override-interval*</hello-override-interval>
 <pim-neighbor-bfd>...</pim-neighbor-bfd>
 <pim-neighbor-join>...</pim-neighbor-join>
 <pim-neighbor-assert>...</pim-neighbor-assert>
 </pim-neighbor>
 </pim-interface>

Description No documentation is available yet.

Contents <hello-default-holdtime>—PIM neighbor default holdtime.
 <hello-default-holdtime-remaining>—PIM neighbor timeout from default holdtime.
 <hello-dr-priority>—No documentation is available yet.
 <hello-generation-id>—No documentation is available yet.
 <hello-holdtime>—No documentation is available yet.
 <hello-holdtime-remaining>—No documentation is available yet.
 <hello-lanprune-delay>—No documentation is available yet.
 <hello-override-interval>—No documentation is available yet.
 <ip-protocol-version>—IP protocol version of PIM interface.
 <neighbor-join-count>—Number of joins sent to the neighbor.
 <pim-interface-mode>—Mode of PIM interface.
 <pim-interface-name>—Name of PIM interface.

<pim-neighbor-address>—PIM neighbor address.

<pim-neighbor-assert>—No documentation is available yet.

<pim-neighbor-bfd>—No documentation is available yet.

<pim-neighbor-flags>—No documentation is available yet.

<pim-neighbor-join>—No documentation is available yet.

<pim-neighbor-secondary-address>—PIM neighbor secondary address.

<pim-neighbor-uptime>—PIM neighbor uptime.

<protocol-version>—PIM protocol version of PIM interface.

<pim-neighbor-assert>

Usage <pim-neighbor>
 <pim-neighbor-assert>
 <multicast-group-address>*multicast-group-address*</multicast-group-address>
 <multicast-source-address>*multicast-source-address*</multicast-source-address>
 <assert-state>*assert-state*</assert-state>
 <pim-neighbor-address>*pim-neighbor-address*</pim-neighbor-address>
 <assert-timeout>*assert-timeout*</assert-timeout>
 </pim-neighbor-assert>
 </pim-neighbor>

Description No documentation is available yet.

Contents <assert-state>—No documentation is available yet.
 <assert-timeout>—No documentation is available yet.
 <multicast-group-address>—Group address.
 <multicast-source-address>—Source address.
 <pim-neighbor-address>—PIM neighbor address.

<pim-neighbor-bfd>

Usage	<pre> <pim-neighbor> <pim-neighbor-bfd> <configuration-state>configuration-state</configuration-state> <operational-state>operational-state</operational-state> </pim-neighbor-bfd> </pim-neighbor> </pre>
Description	No documentation is available yet.
Contents	<p><configuration-state>—State (enabled or disabled) of Bidirectional Forwarding Detection for a PIM neighbor.</p> <p><operational-state>—Operational state of Bidirectional Forwarding Detection session for a PIM neighbor.</p>

<pim-neighbor-flags>

Usage	<pre> <pim-neighbor> <pim-neighbor-flags> <pim-neighbor-hold-time-flag/> <pim-neighbor-priority-flag/> <pim-neighbor-lan-prune-flag/> <pim-neighbor-generation-id-flag/> <pim-neighbor-bidirectional-flag/> <pim-neighbor-t-bit-flag/> </pim-neighbor-flags> </pim-neighbor> </pre>
Description	No documentation is available yet.
Contents	<p><pim-neighbor-bidirectional-flag>—No documentation is available yet.</p> <p><pim-neighbor-generation-id-flag>—No documentation is available yet.</p> <p><pim-neighbor-hold-time-flag>—No documentation is available yet.</p> <p><pim-neighbor-lan-prune-flag>—No documentation is available yet.</p> <p><pim-neighbor-priority-flag>—No documentation is available yet.</p> <p><pim-neighbor-t-bit-flag>—No documentation is available yet.</p>

<pim-neighbor-join>

Usage	<pre> <pim-neighbor> <pim-neighbor-join> <multicast-group-address><i>multicast-group-address</i></multicast-group-address> <multicast-source-address><i>multicast-source-address</i></multicast-source-address> <join-timeout><i>join-timeout</i></join-timeout> </pim-neighbor-join> </pim-neighbor> </pre>
Description	No documentation is available yet.
Contents	<p><join-timeout>—No documentation is available yet.</p> <p><multicast-group-address>—Group address.</p> <p><multicast-source-address>—Source address.</p>

<pim-neighbors-information>

Usage	<pre> <rpc-reply> <pim-neighbors-information> <pim-instance><i>pim-instance</i></pim-instance> <pim-interface>...</pim-interface> </pim-neighbors-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<p><pim-instance>—Name of the PIM instance.</p> <p><pim-interface>—No documentation is available yet.</p>

<pim-other-statistic>

Usage	<pre> <pim-statistics-other> <pim-other-statistic> <statistic-name><i>statistic-name</i></statistic-name> <statistic-count><i>statistic-count</i></statistic-count> </pim-other-statistic> </pim-statistics-other> </pre>
Description	No documentation is available yet.
Contents	<p><statistic-count>—No documentation is available yet.</p> <p><statistic-name>—No documentation is available yet.</p>

<pim-rps-information>

Usage <rpc-reply>
 <pim-rps-information>
 <pim-instance>*pim-instance*</pim-instance>
 <rp-family>...</rp-family>
 <rendezvous-point-address-info>...</rendezvous-point-address-info>
 </pim-rps-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <pim-instance>—Name of the PIM instance.

<rendezvous-point-address-info>—No documentation is available yet.

<rp-family>—No documentation is available yet.

<pim-source>

Usage <source-family>
 <pim-source>
 <multicast-source-address>*multicast-source-address*</multicast-source-address>
 <route-prefix>*route-prefix*</route-prefix>
 <upstream-interface-name>*upstream-interface-name*</upstream-interface-name>
 <upstream-neighbor>*upstream-neighbor*</upstream-neighbor>
 <upstream-group>...</upstream-group>
 </pim-source>
 </source-family>

Description No documentation is available yet.

Contents <multicast-source-address>—Source address.

<route-prefix>—No documentation is available yet.

<upstream-group>—No documentation is available yet.

<upstream-interface-name>—Upstream interface.

<upstream-neighbor>—No documentation is available yet.

<pim-source-information>

Usage <rpc-reply>
 <pim-source-information>
 <source-family>...</source-family>
 </pim-source-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <source-family>—No documentation is available yet.

<pim-statistic>

- Usage** <pim-statistics-interface | pim-statistics-global>
<pim-statistic>
 <statistic-name>*statistic-name*</statistic-name>
 <received-count>*received-count*</received-count>
 <sent-count>*sent-count*</sent-count>
 <error-count>*error-count*</error-count>
</pim-statistic>
 </pim-statistics-interface | pim-statistics-global>
- Description** No documentation is available yet.
- Contents** <error-count>—Total number of errors encountered.
 <received-count>—No documentation is available yet.
 <sent-count>—No documentation is available yet.
 <statistic-name>—No documentation is available yet.

<pim-statistics-all>

- Usage** <pim-statistics-information>
<pim-statistics-all>
 <pim-instance>*pim-instance*</pim-instance>
 <pim-statistics-global>...</pim-statistics-global>
 <pim-statistics-other>...</pim-statistics-other>
</pim-statistics-all>
 </pim-statistics-information>
- Description** No documentation is available yet.
- Contents** <pim-instance>—Name of the PIM instance.
 <pim-statistics-global>—No documentation is available yet.
 <pim-statistics-other>—No documentation is available yet.

<pim-statistics-global>

- Usage** <pim-statistics-all | everything>
<pim-statistics-global>
 <pim-statistic>...</pim-statistic>
</pim-statistics-global>
 </pim-statistics-all | everything>
- Description** No documentation is available yet.
- Contents** <pim-statistic>—No documentation is available yet.

<pim-statistics-information>

Usage	<pre> <rpc-reply> <pim-statistics-information> <statistics-family>...</statistics-family> <pim-statistics-all>...</pim-statistics-all> <everything>...</everything> </pim-statistics-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<p><everything>—No documentation is available yet.</p> <p><pim-statistics-all>—No documentation is available yet.</p> <p><statistics-family>—No documentation is available yet.</p>

<pim-statistics-interface>

Usage	<pre> <statistics-family> <pim-statistics-interface> <pim-interface-name>pim-interface-name</pim-interface-name> <pim-statistic>...</pim-statistic> </pim-statistics-interface> </statistics-family> </pre>
Description	No documentation is available yet.
Contents	<p><pim-interface-name>—Name of PIM interface.</p> <p><pim-statistic>—No documentation is available yet.</p>

<pim-statistics-other>

Usage	<pre> <pim-statistics-all everything> <pim-statistics-other> <pim-other-statistic>...</pim-other-statistic> </pim-statistics-other> </pim-statistics-all everything> </pre>
Description	No documentation is available yet.
Contents	<pim-other-statistic>—No documentation is available yet.

<prefix-element>

Usage	<pre> <isis-spf-result> <prefix-element> <address-prefix>address-prefix</address-prefix> <prefix-metric>prefix-metric</prefix-metric> <external-prefix-metric>external-prefix-metric</external-prefix-metric> </prefix-element> </isis-spf-result> </pre>
Description	No documentation is available yet.
Contents	<p><address-prefix>—No documentation is available yet.</p> <p><external-prefix-metric>—No documentation is available yet.</p> <p><prefix-metric>—No documentation is available yet.</p>

<prefix-limit>

Usage	<pre> <bgp-option-information> <prefix-limit> <nlri-type>nlri-type</nlri-type> <prefix-count>prefix-count</prefix-count> <limit-action>limit-action</limit-action> <warning-percentage>warning-percentage</warning-percentage> </prefix-limit> </bgp-option-information> </pre>
Description	No documentation is available yet.
Contents	<p><limit-action>—Action taken upon reaching limit.</p> <p><nlri-type>—Type of NLRI being limited.</p> <p><prefix-count>—Number of prefixes accepted before action is taken.</p> <p><warning-percentage>—Percentage of limit at which to log a warning.</p>

<prefix-reachability>

Usage <isis-database-local-data>
 <prefix-reachability>
 <address-prefix>*address-prefix*</address-prefix>
 <route-type>*route-type*</route-type>
 <metric>*metric*</metric>
 <flags>*flags*</flags>
 <level>*level*</level>
 <isis-fragment>*isis-fragment*</isis-fragment>
 <tsi>*tsi*</tsi>
 <isis-topology-id>*isis-topology-id*</isis-topology-id>
 <isis-prefix-tag>...</isis-prefix-tag>
 </prefix-reachability>
 </isis-database-local-data>

Description No documentation is available yet.

Contents <address-prefix>—No documentation is available yet.

<flags>—Enabled trace flags.

<isis-fragment>—No documentation is available yet.

<isis-prefix-tag>—No documentation is available yet.

<isis-topology-id>—No documentation is available yet.

<level>—No documentation is available yet.

<metric>—No documentation is available yet.

<route-type>—No documentation is available yet.

<tsi>—Task-specific information.

<protocol-nh>

Usage	<pre> <rt-entry node krt-nexthop> <protocol-nh> <to>to</to> <metric>metric</metric> <indirect-nh>indirect-nh</indirect-nh> <composite-nh>composite-nh</composite-nh> <vpnlabel-nh>vpnlabel-nh</vpnlabel-nh> <mpls-label>mpls-label</mpls-label> <balance>balance</balance> <forwarding-nh-count>forwarding-nh-count</forwarding-nh-count> <nh-type>nh-type</nh-type> <nh>...</nh> </protocol-nh> </rt-entry node krt-nexthop> </pre>
Description	Protocol next hop.
Contents	<p><balance>—Next-hop balance.</p> <p><composite-nh>—No documentation is available yet.</p> <p><forwarding-nh-count>—Number of indirect path forwarding next hops.</p> <p><indirect-nh>—No documentation is available yet.</p> <p><metric>—No documentation is available yet.</p> <p><mpls-label>—Label of MPLS packet.</p> <p><nh>—Next-hop gateway information.</p> <p><nh-type>—Special next hop: Reject, Blackhole, Receive, Multicast, Local, or Unused.</p> <p><to>—Neighbor address to which to send (next-hop address).</p> <p><vpnlabel-nh>—No documentation is available yet.</p>

<protocols>

Usage	<pre> <route-table> <protocols> <protocol-name>protocol-name</protocol-name> <protocol-route-count>protocol-route-count</protocol-route-count> <active-route-count>active-route-count</active-route-count> </protocols> </route-table> </pre>
Description	No documentation is available yet.
Contents	<p><active-route-count>—Active routes.</p> <p><protocol-name>—No documentation is available yet.</p> <p><protocol-route-count>—Total protocol routes.</p>

<protocols-tlv>

Usage	<pre> <isis-tlv> <protocols-tlv> <protocol>protocol</protocol> </protocols-tlv> </isis-tlv> </pre>
Description	No documentation is available yet.
Contents	<protocol>—No documentation is available yet.

<provider-tunnel>

Usage	<pre> <instance instance-entry> <provider-tunnel> <provider-tunnel-id>provider-tunnel-id</provider-tunnel-id> </provider-tunnel> </instance instance-entry> </pre>
Description	No documentation is available yet.
Contents	<provider-tunnel-id>—Provider tunnel identifier.

<reachability-tlv>

Usage	<pre> <isis-tlv> <reachability-tlv> <isis-topology-id>isis-topology-id</isis-topology-id> <address-prefix>address-prefix</address-prefix> <metric>metric</metric> <metric-flag>metric-flag</metric-flag> <reachability-delay/> <reachability-expense/> <reachability-error/> <prefix-status>prefix-status</prefix-status> <address>address</address> <neighbor-prefix>neighbor-prefix</neighbor-prefix> <tlv-length>tlv-length</tlv-length> <isis-reachability-subtlv>...</isis-reachability-subtlv> </reachability-tlv> </isis-tlv> </pre>
Description	No documentation is available yet.
Contents	<p><address>—No documentation is available yet.</p> <p><address-prefix>—No documentation is available yet.</p> <p><isis-reachability-subtlv>—No documentation is available yet.</p> <p><isis-topology-id>—No documentation is available yet.</p> <p><metric>—No documentation is available yet.</p> <p><metric-flag>—No documentation is available yet.</p> <p><neighbor-prefix>—No documentation is available yet.</p> <p><prefix-status>—No documentation is available yet.</p> <p><reachability-delay>—No documentation is available yet.</p> <p><reachability-error>—No documentation is available yet.</p> <p><reachability-expense>—No documentation is available yet.</p> <p><tlv-length>—No documentation is available yet.</p>

<record-route>

Usage <rsvp-session | detour | detour-branch>
<record-route>
 <address>*address*</address>
 <telink-id>*telink-id*</telink-id>
 <self/>
 <incomplete/>
</record-route>
 </rsvp-session | detour | detour-branch>

Description Record Route Object (RRO).

Contents <address>—No documentation is available yet.
 <incomplete>—No documentation is available yet.
 <self>—No documentation is available yet.
 <telink-id>—Link identifier of unnumbered link.

<redundant-sources>

Usage <multicast-flow-map>
<redundant-sources>
 <multicast-source-address>*multicast-source-address*</multicast-source-address>
</redundant-sources>
 </multicast-flow-map>

Description Redundant source addresses.

Contents <multicast-source-address>—Source address.

<reference-site>

Usage <instance | vpls-protocol-state>
<reference-site>
 <vpls-signaling-protocol-identifier>*vpls-signaling-protocol-identifier*
 </vpls-signaling-protocol-identifier>
 <local-site-id>*local-site-id*</local-site-id>
 <vpls-id>*vpls-id*</vpls-id>
 <num-local-interfaces>*num-local-interfaces*</num-local-interfaces>
 <num-local-interfaces-up>*num-local-interfaces-up*</num-local-interfaces-up>
 <irb-present>*irb-present*</irb-present>
 <mesh-group-count>*mesh-group-count*</mesh-group-count>
 <mesh-group-up-count>*mesh-group-up-count*</mesh-group-up-count>
 <remote-site-id>*remote-site-id*</remote-site-id>
 <mesh-group-interfaces>...</mesh-group-interfaces>
 <interface>...</interface>
 <label-block>...</label-block>
 <connection>...</connection>
 <mesh-group-connection>...</mesh-group-connection>
 <automatic-site-name>*automatic-site-name*</automatic-site-name>
 <automatic-site-id-status>*automatic-site-id-status*</automatic-site-id-status>
 <automatic-site-claim-id>*automatic-site-claim-id*</automatic-site-claim-id>
 <automatic-site-collisions>*automatic-site-collisions*
 </automatic-site-collisions>
 <automatic-site-timer-status>*automatic-site-timer-status*
 </automatic-site-timer-status>
 <automatic-site-timers>...</automatic-site-timers>
 <connections-summary>...</connections-summary>
</reference-site>
 </instance | vpls-protocol-state>

Description No documentation is available yet.

Contents <automatic-site-claim-id>—Claim site identifier.
 <automatic-site-collisions>—Number of collisions.
 <automatic-site-id-status>—VPLS automatic site identifier status.
 <automatic-site-name>—VPLS automatic site name.
 <automatic-site-timer-status>—VPLS automatic site timer status.
 <automatic-site-timers>—No documentation is available yet.
 <connection>—No documentation is available yet.
 <connections-summary>—No documentation is available yet.
 <interface>—No documentation is available yet.
 <irb-present>—No documentation is available yet.
 <label-block>—No documentation is available yet.

<local-site-id>—No documentation is available yet.

<mesh-group-connection>—Information about all vc-connections of a specific mesh-group.

<mesh-group-count>—No documentation is available yet.

<mesh-group-interfaces>—Information about all interfaces associated with a mesh-group.

<mesh-group-up-count>—No documentation is available yet.

<num-local-interfaces>—No documentation is available yet.

<num-local-interfaces-up>—No documentation is available yet.

<remote-site-id>—No documentation is available yet.

<vpls-id>—VPLS instance identifier.

<vpls-signaling-protocol-identifier>—No documentation is available yet.

<remote-interface>

Usage <connection>
 <remote-interface>
 <interface-name>*interface-name*</interface-name>
 <interface-status>*interface-status*</interface-status>
 <interface-encapsulation>*interface-encapsulation*</interface-encapsulation>
 </remote-interface>
 </connection>

Description No documentation is available yet.

Contents <interface-encapsulation>—No documentation is available yet.
 <interface-name>—No documentation is available yet.
 <interface-status>—No documentation is available yet.

<rendezvous-point>

Usage <rp-family>
<rendezvous-point>
 <rendezvous-point-address>*rendezvous-point-address*</rendezvous-point-address>
 <rp-flag-static/>
 <rp-flag-autorp/>
 <rp-flag-bootstrap/>
 <rp-flag-embedded-rp/>
 <rendezvous-point-from-address>*rendezvous-point-from-address*
 </rendezvous-point-from-address>
 <rendezvous-point-holdtime>*rendezvous-point-holdtime*
 </rendezvous-point-holdtime>
 <rendezvous-point-refcount>*rendezvous-point-refcount*
 </rendezvous-point-refcount>
 <rendezvous-point-time-active>*rendezvous-point-time-active*
 </rendezvous-point-time-active>
 <rendezvous-point-holdtime-remaining>*rendezvous-point-holdtime-remaining*
 </rendezvous-point-holdtime-remaining>
 <rp-interface-device-index>*rp-interface-device-index*
 </rp-interface-device-index>
 <rp-interface-device-subunit>*rp-interface-device-subunit*
 </rp-interface-device-subunit>
 <pim-interface-name>*pim-interface-name*</pim-interface-name>
 <rendezvous-point-timeout>*rendezvous-point-timeout*</rendezvous-point-timeout>
 <rendezvous-point-active-groups>*rendezvous-point-active-groups*
 </rendezvous-point-active-groups>
 <rendezvous-point-group-prefixes>...</rendezvous-point-group-prefixes>
 <rendezvous-point-active-group-prefixes>...
 </rendezvous-point-active-group-prefixes>
 <rendezvous-point-register-state>...</rendezvous-point-register-state>
 <rendezvous-point-anycast-pim-rpset>...</rendezvous-pnt-anycast-pim-rpset>
 <rendezvous-point-anycast-pim-local-address>*rendez-pnt-anycast-pim-local-addr*
 </rendezvous-point-anycast-pim-local-address>
 <rendezvous-point-anycast-register-state>...
 </rendezvous-point-anycast-register-state>
</rendezvous-point>
 </rp-family>

Description No documentation is available yet.

Contents <pim-interface-name>—Name of PIM interface.

<rendezvous-point-active-group-prefixes>—No documentation is available yet.

<rendezvous-point-active-groups>—No documentation is available yet.

<rendezvous-point-address>—Address of rendezvous point.

<rendezvous-point-anycast-pim-local-address>—Local address for replicating register messages to anycast RPs.

<rendezvous-point-anycast-pim-rpset>—IPv4 address of one or more remote anycast RPs.

<rendezvous-point-anycast-register-state>—Anycast register state.

<rendezvous-point-from-address>—No documentation is available yet.

<rendezvous-point-group-prefixes>—No documentation is available yet.

<rendezvous-point-holdtime>—No documentation is available yet.

<rendezvous-point-holdtime-remaining>—No documentation is available yet.

<rendezvous-point-refcount>—No documentation is available yet.

<rendezvous-point-register-state>—No documentation is available yet.

<rendezvous-point-time-active>—No documentation is available yet.

<rendezvous-point-timeout>—No documentation is available yet.

<rp-flag-autorp>—No documentation is available yet.

<rp-flag-bootstrap>—No documentation is available yet.

<rp-flag-embedded-rp>—No documentation is available yet.

<rp-flag-static>—No documentation is available yet.

<rp-interface-device-index>—No documentation is available yet.

<rp-interface-device-subunit>—No documentation is available yet.

<rendezvous-point-active-group-prefix>

Usage <rendezvous-point-active-group-prefixes>
 <rendezvous-point-active-group-prefix>
 <multicast-group-address>*multicast-group-address*</multicast-group-address>
 </rendezvous-point-active-group-prefix>
 </rendezvous-point-active-group-prefixes>

Description No documentation is available yet.

Contents <multicast-group-address>—Group address.

<rendezvous-point-active-group-prefixes>

- Usage** <rendezvous-point>
 <rendezvous-point-active-group-prefixes>
 <rendezvous-point-active-group-prefix>...
 </rendezvous-point-active-group-prefix>
 <rendezvous-point-active-groups>*rendezvous-point-active-groups*
 </rendezvous-point-active-groups>
 </rendezvous-point-active-group-prefixes>
 </rendezvous-point>
- Description** No documentation is available yet.
- Contents** <rendezvous-point-active-group-prefix>—No documentation is available yet.
 <rendezvous-point-active-groups>—No documentation is available yet.

<rendezvous-point-address-info>

- Usage** <pim-rps-information>
 <rendezvous-point-address-info>
 <pim-instance>*pim-instance*</pim-instance>
 <rendezvous-point-trees>...</rendezvous-point-trees>
 <rendezvous-point-address>*rendezvous-point-address*</rendezvous-point-address>
 <rendezvous-point-embedded-rp-address/>
 <rendezvous-point-no-address>*rendezvous-point-no-address*
 </rendezvous-point-no-address>
 </rendezvous-point-address-info>
 </pim-rps-information>
- Description** No documentation is available yet.
- Contents** <pim-instance>—Name of the PIM instance.
 <rendezvous-point-address>—Address of rendezvous point.
 <rendezvous-point-embedded-rp-address>—No documentation is available yet.
 <rendezvous-point-no-address>—No documentation is available yet.
 <rendezvous-point-trees>—No documentation is available yet.

<rendezvous-point-addresses>

- Usage** <rendezvous-point-trees>
 <rendezvous-point-addresses>
 <rendezvous-point-address>*rendezvous-point-address*</rendezvous-point-address>
 <rendezvous-point-hash>*rendezvous-point-hash*</rendezvous-point-hash>
 </rendezvous-point-addresses>
 </rendezvous-point-trees>
- Description** No documentation is available yet.
- Contents** <rendezvous-point-address>—Address of rendezvous point.
 <rendezvous-point-hash>—No documentation is available yet.

<rendezvous-point-anycast-pim-rpset>

- Usage** <rendezvous-point>
 <rendezvous-point-anycast-pim-rpset>
 <multicast-group-address>*multicast-group-address*</multicast-group-address>
 </rendezvous-point-anycast-pim-rpset>
 </rendezvous-point>
- Description** IPv4 address of one or more remote anycast RPs.
- Contents** <multicast-group-address>—Group address.

<rendezvous-point-anycast-register-state>

- Usage** <rendezvous-point>
 <rendezvous-point-anycast-register-state>
 <multicast-group-address>*multicast-group-address*</multicast-group-address>
 <multicast-source-address>*multicast-source-address*</multicast-source-address>
 <pim-anycast-register-state-origin>*pim-anycast-register-state-origin*
 </pim-anycast-register-state-origin>
 </rendezvous-point-anycast-register-state>
 </rendezvous-point>
- Description** Anycast register state.
- Contents** <multicast-group-address>—Group address.
 <multicast-source-address>—Source address.
 <pim-anycast-register-state-origin>—Origin of anycast register state.

<rendezvous-point-group-prefixes>

Usage	<pre> <rendezvous-point> <rendezvous-point-group-prefixes> <multicast-group-prefix><i>multicast-group-prefix</i></multicast-group-prefix> <rp-group-timeout><i>rp-group-timeout</i></rp-group-timeout> <rp-group-state><i>rp-group-state</i></rp-group-state> </rendezvous-point-group-prefixes> </rendezvous-point> </pre>
Description	No documentation is available yet.
Contents	<p><multicast-group-prefix>—Group prefix.</p> <p><rp-group-state>—No documentation is available yet.</p> <p><rp-group-timeout>—Time remaining for RP group prefix.</p>

<rendezvous-point-register-state>

Usage	<pre> <rendezvous-point> <rendezvous-point-register-state> <multicast-group-address><i>multicast-group-address</i></multicast-group-address> <multicast-source-address><i>multicast-source-address</i></multicast-source-address> <first-hop-address><i>first-hop-address</i></first-hop-address> <rendezvous-point-address><i>rendezvous-point-address</i></rendezvous-point-address> <pim-register-state><i>pim-register-state</i></pim-register-state> <pim-register-timeout><i>pim-register-timeout</i></pim-register-timeout> </rendezvous-point-register-state> </rendezvous-point> </pre>
Description	No documentation is available yet.
Contents	<p><first-hop-address>—No documentation is available yet.</p> <p><multicast-group-address>—Group address.</p> <p><multicast-source-address>—Source address.</p> <p><pim-register-state>—No documentation is available yet.</p> <p><pim-register-timeout>—No documentation is available yet.</p> <p><rendezvous-point-address>—Address of rendezvous point.</p>

<rendezvous-point-trees>

Usage <rendezvous-point-address-info>
 <rendezvous-point-trees>
 <multicast-group-prefix>*multicast-group-prefix*</multicast-group-prefix>
 <rendezvous-point-addresses>...</rendezvous-point-addresses>
 </rendezvous-point-trees>
 </rendezvous-point-address-info>

Description No documentation is available yet.

Contents <multicast-group-prefix>—Group prefix.
 <rendezvous-point-addresses>—No documentation is available yet.

<reserved-bandwidth>

Usage <rsvp-telink>
 <reserved-bandwidth>
 <bandwidth-priority>*bandwidth-priority*</bandwidth-priority>
 <total-reserved-bandwidth>*total-reserved-bandwidth*</total-reserved-bandwidth>
 </reserved-bandwidth>
 </rsvp-telink>

Description Bandwidth reserved at different priority levels.

Contents <bandwidth-priority>—No documentation is available yet.
 <total-reserved-bandwidth>—Total amount of bandwidth currently reserved.

<reserved-ct-bandwidth>

Usage <rsvp-telink>
 <reserved-ct-bandwidth>
 <ct-class>ct-class</ct-class>
 <ct-bw0>ct-bw0</ct-bw0>
 <ct-bw1>ct-bw1</ct-bw1>
 <ct-bw2>ct-bw2</ct-bw2>
 <ct-bw3>ct-bw3</ct-bw3>
 <ct-bw4>ct-bw4</ct-bw4>
 <ct-bw5>ct-bw5</ct-bw5>
 <ct-bw6>ct-bw6</ct-bw6>
 <ct-bw7>ct-bw7</ct-bw7>
 </reserved-ct-bandwidth>
 </rsvp-telink>

Description Bandwidth reserved at different class and priority levels.

Contents <ct-bw0>—No documentation is available yet.
 <ct-bw1>—No documentation is available yet.
 <ct-bw2>—No documentation is available yet.
 <ct-bw3>—No documentation is available yet.
 <ct-bw4>—No documentation is available yet.
 <ct-bw5>—No documentation is available yet.
 <ct-bw6>—No documentation is available yet.
 <ct-bw7>—No documentation is available yet.
 <ct-class>—Class type (0..7).

<reverse-oif>

Usage <mgm-group>
 <reverse-oif>
 <oif-name>oif-name</oif-name>
 <host-count>host-count</host-count>
 </reverse-oif>
 </mgm-group>

Description No documentation is available yet.

Contents <host-count>—Host reference count.
 <oif-name>—Reverse OIF name.

<rip-error>

Usage	<pre> <rpc-reply> <rip-error> <rip-error-message>rip-error-message</rip-error-message> </rip-error> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<rip-error-message>—RIP error message.

<rip-general-statistics>

Usage	<pre> <rip-general-statistics-information> <rip-general-statistics> <rip-protocol-name>rip-protocol-name</rip-protocol-name> <rip-bad-messages>rip-bad-messages</rip-bad-messages> <rip-interface-count>rip-interface-count</rip-interface-count> <rip-current-memory>rip-current-memory</rip-current-memory> <rip-maximum-memory>rip-maximum-memory</rip-maximum-memory> </rip-general-statistics> </rip-general-statistics-information> </pre>
Description	No documentation is available yet.
Contents	<p><rip-bad-messages>—Number of bad messages received so far.</p> <p><rip-current-memory>—Amount of memory currently allocated by the protocol. This value is zero if the protocol is not running.</p> <p><rip-interface-count>—Number of interfaces on which the protocol is enabled.</p> <p><rip-maximum-memory>—Maximum amount of memory the protocol ever used. This value might be nonzero even if the protocol is not currently running.</p> <p><rip-protocol-name>—Protocol name for the subsequent information: either RIPv2 or RIPv6.</p>

<rip-general-statistics-information>

Usage	<pre> <rpc-reply> <rip-general-statistics-information> <rip-general-statistics>...</rip-general-statistics> </rip-general-statistics-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<rip-general-statistics>—No documentation is available yet.

<rip-global-statistics>

Usage <rip-statistics-information | rip-instance-statistics>
<rip-global-statistics>
 <rip-routes-learned>*rip-routes-learned*</rip-routes-learned>
 <rip-routes-holddown>*rip-routes-holddown*</rip-routes-holddown>
 <rip-requests-dropped>*rip-requests-dropped*</rip-requests-dropped>
 <rip-responses-dropped>*rip-responses-dropped*</rip-responses-dropped>
</rip-global-statistics>
 </rip-statistics-information | rip-instance-statistics>

Description RIP global statistics.

Contents <rip-requests-dropped>—Number of requests dropped.
 <rip-responses-dropped>—Number of responses dropped.
 <rip-routes-holddown>—Number of routes in hold-down state.
 <rip-routes-learned>—Number of routes learned.

<rip-instance-neighbor>

Usage <rip-neighbor-information-all>
<rip-instance-neighbor>
 <rip-instance-name>*rip-instance-name*</rip-instance-name>
 <rip-neighbor>...</rip-neighbor>
</rip-instance-neighbor>
 </rip-neighbor-information-all>

Description Information about RIP neighbors within this routing instance.

Contents <rip-instance-name>—Name of RIP instance.
 <rip-neighbor>—No documentation is available yet.

<rip-instance-statistics>

Usage <rip-statistics-information-all>
 <rip-instance-statistics>
 <rip-instance-name>*rip-instance-name*</rip-instance-name>
 <rip-timer-values>...</rip-timer-values>
 <rip-restart-values>...</rip-restart-values>
 <rip-global-statistics>...</rip-global-statistics>
 <rip-neighbor-statistics>...</rip-neighbor-statistics>
 </rip-instance-statistics>
 </rip-statistics-information-all>

Description Information about statistics for this routing instance.

Contents <rip-global-statistics>—RIP global statistics.

<rip-instance-name>—Name of RIP instance.

<rip-neighbor-statistics>—RIP neighbor statistics.

<rip-restart-values>—Information about RIP restart values.

<rip-timer-values>—Information about RIP timer values.

<rip-message-statistics>

Usage <rip-neighbor-statistics>
 <rip-message-statistics>
 <rip-message>*rip-message*</rip-message>
 <rip-message-total>*rip-message-total*</rip-message-total>
 <rip-message-last-5minutes>*rip-message-last-5minutes*
 </rip-message-last-5minutes>
 <rip-message-last-minute>*rip-message-last-minute*</rip-message-last-minute>
 </rip-message-statistics>
 </rip-neighbor-statistics>

Description No documentation is available yet.

Contents <rip-message>—No documentation is available yet.

<rip-message-last-5minutes>—Number of messages in the last 5 minutes.

<rip-message-last-minute>—Number of messages in the last minute.

<rip-message-total>—Total number of messages.

<rip-neighbor>

Usage <rip-neighbor-information | rip-instance-neighbor>

```

<rip-neighbor>
  <rip-neighbor-name>rip-neighbor-name</rip-neighbor-name>
  <rip-neighbor-state>rip-neighbor-state</rip-neighbor-state>
  <rip-neighbor-metric-in>rip-neighbor-metric-in</rip-neighbor-metric-in>
  <rip-local-address-ipv4>rip-local-address-ipv4</rip-local-address-ipv4>
  <rip-remote-address-ipv4>rip-remote-address-ipv4</rip-remote-address-ipv4>
  <send-mode-ripv2>send-mode-ripv2</send-mode-ripv2>
  <receive-mode-ripv2>receive-mode-ripv2</receive-mode-ripv2>
  <rip-local-address-ipv6>rip-local-address-ipv6</rip-local-address-ipv6>
  <rip-remote-address-ipv6>rip-remote-address-ipv6</rip-remote-address-ipv6>
  <send-mode-ripng>send-mode-ripng</send-mode-ripng>
  <receive-mode-ripng>receive-mode-ripng</receive-mode-ripng>
</rip-neighbor>
</rip-neighbor-information | rip-instance-neighbor>

```

Description No documentation is available yet.

Contents <receive-mode-ripng>—Receive state of the neighbor, which determines whether RIPv2 packets are accepted through that interface.

<receive-mode-ripv2>—Receive state of the neighbor, which determines which RIPv2 packets are accepted. It is one of four values: (1) v1 only--only RIPv1 packets are received, (2) v2 only--only RIPv2 packets are received, (3) both--both RIPv1 and RIPv2 packets are received, or (4) none--no packets are received.

<rip-local-address-ipv4>—Local address of this neighbor (IPv4 address of the interface over which the protocol is configured).

<rip-local-address-ipv6>—Local address of this neighbor (IPv6 address of the interface over which the protocol is configured).

<rip-neighbor-metric-in>—Metric value to add to incoming routes. This is a value between 1 and 15.

<rip-neighbor-name>—Name of the interface over which the protocol is configured.

<rip-neighbor-state>—Whether neighbor is up or down.

<rip-remote-address-ipv4>—Remote address for this neighbor. If the neighbor is configured for broadcast mode, this is the broadcast address; otherwise, it is the RIPv2 multicast address.

<rip-remote-address-ipv6>—Remote address of this neighbor (RIPv2 multicast address).

<send-mode-ripng>—Send state of the neighbor, which determines whether the neighbor sends RIPv2 updates.

<send-mode-ripv2>—Send state of the neighbor, which determines how RIPv2 updates are sent. It is one of four values: (1) bcast--broadcast of RIPv2 packets (compatible with RIPv1), (2) mcast--multicast of RIPv2 packets, (3) v1--broadcast of RIPv1 packets, or (4) none--silent neighbor; no updates sent.

<rip-neighbor-information>

Usage <rpc-reply>
 <rip-neighbor-information>
 <rip-neighbor>...</rip-neighbor>
 </rip-neighbor-information>
</rpc-reply>

Description Information about RIP neighbors in a routing instance.

Contents <rip-neighbor>—No documentation is available yet.

<rip-neighbor-information-all>

Usage <rpc-reply>
 <rip-neighbor-information-all>
 <rip-instance-neighbor>...</rip-instance-neighbor>
 </rip-neighbor-information-all>
</rpc-reply>

Description Information about RIP neighbors in all routing instances.

Contents <rip-instance-neighbor>—Information about RIP neighbors within this routing instance.

<rip-neighbor-statistics>

Usage	<pre> <rip-statistics-information rip-instance-statistics> <rip-neighbor-statistics> <rip-neighbor-name>rip-neighbor-name</rip-neighbor-name> <rip-neighbor-learned-routes>rip-neighbor-learned-routes </rip-neighbor-learned-routes> <rip-neighbor-advertised-routes>rip-neighbor-advertised-routes </rip-neighbor-advertised-routes> <rip-neighbor-route-timeout>rip-neighbor-route-timeout </rip-neighbor-route-timeout> <rip-neighbor-update-interval>rip-neighbor-update-interval </rip-neighbor-update-interval> <rip-message-statistics>...</rip-message-statistics> </rip-neighbor-statistics> </rip-statistics-information rip-instance-statistics> </pre>
Description	RIP neighbor statistics.
Contents	<p><rip-message-statistics>—No documentation is available yet.</p> <p><rip-neighbor-advertised-routes>—Number of routes advertised by this neighbor.</p> <p><rip-neighbor-learned-routes>—Number of routes learned by this neighbor.</p> <p><rip-neighbor-name>—Name of the interface over which the protocol is configured.</p> <p><rip-neighbor-route-timeout>—Timeout value for routes learned from this neighbor.</p> <p><rip-neighbor-update-interval>—Value of update interval timer for this neighbor.</p>

<rip-restart-values>

Usage	<pre> <rip-statistics-information rip-instance-statistics> <rip-restart-values> <rip-restart-state>rip-restart-state</rip-restart-state> <rip-restart-time>rip-restart-time</rip-restart-time> <rip-restart-timeout>rip-restart-timeout</rip-restart-timeout> </rip-restart-values> </rip-statistics-information rip-instance-statistics> </pre>
Description	Information about RIP restart values.
Contents	<p><rip-restart-state>—Indicates if graceful restart is in progress.</p> <p><rip-restart-time>—Restart time locally configured.</p> <p><rip-restart-timeout>—Time after which graceful restart is complete.</p>

<rip-statistics-information>

Usage <rpc-reply>
 <rip-statistics-information>
 <rip-timer-values>...</rip-timer-values>
 <rip-restart-values>...</rip-restart-values>
 <rip-global-statistics>...</rip-global-statistics>
 <rip-neighbor-statistics>...</rip-neighbor-statistics>
 </rip-statistics-information>
 </rpc-reply>

Description Information about RIP statistics for a routing instance.

Contents <rip-global-statistics>—RIP global statistics.
 <rip-neighbor-statistics>—RIP neighbor statistics.
 <rip-restart-values>—Information about RIP restart values.
 <rip-timer-values>—Information about RIP timer values.

<rip-statistics-information-all>

Usage <rpc-reply>
 <rip-statistics-information-all>
 <rip-instance-statistics>...</rip-instance-statistics>
 </rip-statistics-information-all>
 </rpc-reply>

Description Information about RIP statistics for all routing instances.

Contents <rip-instance-statistics>—Information about statistics for this routing instance.

<rip-timer-values>

Usage <rip-statistics-information | rip-instance-statistics>
 <rip-timer-values>
 <rip-protocol-name>*rip-protocol-name*</rip-protocol-name>
 <rip-port>*rip-port*</rip-port>
 <rip-holddown>*rip-holddown*</rip-holddown>
 </rip-timer-values>
 </rip-statistics-information | rip-instance-statistics>

Description Information about RIP timer values.

Contents <rip-holddown>—Value of the hold-down timer.
 <rip-port>—Port on which the protocol is running.
 <rip-protocol-name>—Protocol name for the subsequent information: either RIPv2 or RIPv6.

<route-family>

- Usage** <multicast-route-information>
 <route-family>
 <address-family>*address-family*</address-family>
 <multicast-route>...</multicast-route>
 </route-family>
 </multicast-route-information>
- Description** No documentation is available yet.
- Contents** <address-family>—No documentation is available yet.
 <multicast-route>—No documentation is available yet.

<route-filter>

- Usage** <rt-martians | unconfigured-peers>
 <route-filter>
 <address>*address*</address>
 <flags>*flags*</flags>
 <extended-information>*extended-information*</extended-information>
 </route-filter>
 </rt-martians | unconfigured-peers>
- Description** Entries in martian table.
- Contents** <address>—No documentation is available yet.
 <extended-information>—No documentation is available yet.
 <flags>—Enabled trace flags.

<route-flap-damping>

Usage <rt-entry>
 <route-flap-damping>
 <merit>*merit*</merit>
 <last-merit>*last-merit*</last-merit>
 <damping-parameters>*damping-parameters*</damping-parameters>
 <default-damping-parameters/>
 <last-update>*last-update*</last-update>
 <first-update>*first-update*</first-update>
 <route-flap-count>*route-flap-count*</route-flap-count>
 <suppressed/>
 <reuse-time>*reuse-time*</reuse-time>
 <reuse-preference>*reuse-preference*</reuse-preference>
 <expire-time>*expire-time*</expire-time>
 </route-flap-damping>
 </rt-entry>

Description No documentation is available yet.

Contents <damping-parameters>—No documentation is available yet.

<default-damping-parameters>—Default damping parameters used.

<expire-time>—Time when this damping entry expires.

<first-update>—No documentation is available yet.

<last-merit>—Last merit value.

<last-update>—No documentation is available yet.

<merit>—Current merit value.

<reuse-preference>—Preference to use when this route is reused.

<reuse-time>—Time until this route is reusable.

<route-flap-count>—Number of times this route has flapped.

<suppressed>—This route is suppressed.

<route-information>

Usage <rpc-reply>
 <route-information>
 <as-number>*as-number*</as-number>
 <router-id>*router-id*</router-id>
 <route-table>...</route-table>
 <rt-martians>...</rt-martians>
 <rt-ribgroup>...</rt-ribgroup>
 <rt-test-policy-prefix>...</rt-test-policy-prefix>
 <rt-test-policy>...</rt-test-policy>
 </route-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <as-number>—No documentation is available yet.
 <route-table>—No documentation is available yet.
 <router-id>—No documentation is available yet.
 <rt-martians>—No documentation is available yet.
 <rt-ribgroup>—No documentation is available yet.
 <rt-test-policy>—No documentation is available yet.
 <rt-test-policy-prefix>—No documentation is available yet.

<route-queue>

Usage <bgp-peer | bgp-group>
 <route-queue>
 <timer>*timer*</timer>
 <state>*state*</state>
 <element>*element*</element>
 </route-queue>
 </bgp-peer | bgp-group>

Description No documentation is available yet.

Contents <element>—No documentation is available yet.
 <state>—No documentation is available yet.
 <timer>—No documentation is available yet.

<route-resolution-information>

Usage <rpc-reply>
 <route-resolution-information>
 <route-resolution-tree>...</route-resolution-tree>
 </route-resolution-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <route-resolution-tree>—No documentation is available yet.

<route-resolution-tree>

Usage <route-resolution-information>
 <route-resolution-tree>
 <tree-index>*tree-index*</tree-index>
 <nodes>*nodes*</nodes>
 <tree-reference-count>*tree-reference-count*</tree-reference-count>
 <tree-contributing-ribs>*tree-contributing-ribs*</tree-contributing-ribs>
 <tree-policy>*tree-policy*</tree-policy>
 <node>...</node>
 </route-resolution-tree>
 </route-resolution-information>

Description No documentation is available yet.

Contents <node>—No documentation is available yet.

<nodes>—Number of resolution nodes in the tree.

<tree-contributing-ribs>—Name of routing table inserting routes in the tree.

<tree-index>—Index of the resolution tree.

<tree-policy>—Import policy on the tree.

<tree-reference-count>—Reference count on the tree.

<route-summary-information>

Usage <rpc-reply>
 <route-summary-information>
 <as-number>*as-number*</as-number>
 <router-id>*router-id*</router-id>
 <route-table>...</route-table>
 </route-summary-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <as-number>—No documentation is available yet.
 <route-table>—No documentation is available yet.
 <router-id>—No documentation is available yet.

<route-table>

Usage <route-information | route-summary-information>
 <route-table>
 <protocols>...</protocols>
 <table-name>*table-name*</table-name>
 <destination-count>*destination-count*</destination-count>
 <total-route-count>*total-route-count*</total-route-count>
 <active-route-count>*active-route-count*</active-route-count>
 <holddown-route-count>*holddown-route-count*</holddown-route-count>
 <hidden-route-count>*hidden-route-count*</hidden-route-count>
 <restart-state>*restart-state*</restart-state>
 <rt>...</rt>
 </route-table>
 </route-information | route-summary-information>

Description No documentation is available yet.

Contents <active-route-count>—Active routes.
 <destination-count>—Number of destinations in this rib.
 <hidden-route-count>—No documentation is available yet.
 <holddown-route-count>—No documentation is available yet.
 <protocols>—No documentation is available yet.
 <restart-state>—No documentation is available yet.
 <rt>—No documentation is available yet.
 <table-name>—Unicast routing table.
 <total-route-count>—No documentation is available yet.

<router-id-tlv>

Usage	<pre> <isis-tlv> <router-id-tlv> <router-id>router-id</router-id> </router-id-tlv> </isis-tlv> </pre>
Description	No documentation is available yet.
Contents	<router-id>—No documentation is available yet.

<rp-family>

Usage	<pre> <pim-rps-information> <rp-family> <address-family>address-family</address-family> <rendezvous-point>...</rendezvous-point> </rp-family> </pim-rps-information> </pre>
Description	No documentation is available yet.
Contents	<address-family>—No documentation is available yet. <rendezvous-point>—No documentation is available yet.

<rpf-family>

Usage	<pre> <multicast-rpf-information> <rpf-family> <address-family>address-family</address-family> <rpf-table-name>rpf-table-name</rpf-table-name> <rpf-table-entry-count>rpf-table-entry-count</rpf-table-entry-count> <rpf-route>...</rpf-route> </rpf-family> </multicast-rpf-information> </pre>
Description	No documentation is available yet.
Contents	<address-family>—No documentation is available yet. <rpf-route>—No documentation is available yet. <rpf-table-entry-count>—No documentation is available yet. <rpf-table-name>—No documentation is available yet.

<rpf-route>

Usage <rpf-family>
 <rpf-route>
 <prefix>*prefix*</prefix>
 <rpf-route-inactive/>
 <rpf-route-protocol>*rpf-route-protocol*</rpf-route-protocol>
 <interface-name>*interface-name*</interface-name>
 <rpf-route-neighbor>*rpf-route-neighbor*</rpf-route-neighbor>
 </rpf-route>
 </rpf-family>

Description No documentation is available yet.

Contents <interface-name>—No documentation is available yet.
 <prefix>—No documentation is available yet.
 <rpf-route-inactive>—No documentation is available yet.
 <rpf-route-neighbor>—No documentation is available yet.
 <rpf-route-protocol>—No documentation is available yet.

<rsvp-error>

Usage <rsvp-statistics-information>
 <rsvp-error>
 <error-message>*error-message*</error-message>
 <error-count>*error-count*</error-count>
 <error-count-5seconds>*error-count-5seconds*</error-count-5seconds>
 </rsvp-error>
 </rsvp-statistics-information>

Description No documentation is available yet.

Contents <error-count>—Total number of errors encountered.
 <error-count-5seconds>—Number of errors encountered in the last 5 seconds.
 <error-message>—No documentation is available yet.

<rsvp-graceful-restart>

Usage <rsvp-neighbor | rsvp-replication-neighbor | rsvp-version>
<rsvp-graceful-restart>
 <restart-status>*restart-status*</restart-status>
 <helper-status>*helper-status*</helper-status>
 <maximum-helper-restart-time>*maximum-helper-restart-time*
 </maximum-helper-restart-time>
 <maximum-helper-recovery-time>*maximum-helper-recovery-time*
 </maximum-helper-recovery-time>
 <restart-time>*restart-time*</restart-time>
 <recovery-time>*recovery-time*</recovery-time>
</rsvp-graceful-restart>
 </rsvp-neighbor | rsvp-replication-neighbor | rsvp-version>

Description No documentation is available yet.

Contents <helper-status>—No documentation is available yet.

<maximum-helper-recovery-time>—Maximum state re-synchronization time for restarting neighbor.

<maximum-helper-restart-time>—Maximum wait time from down event to neighbor dead.

<recovery-time>—Recovery time advertised.

<restart-status>—No documentation is available yet.

<restart-time>—Restart time advertised.

<rsvp-interface>

Usage <rsvp-interface-information>
<rsvp-interface>
 <interface-name>*interface-name*</interface-name>
 <rsvp-status>*rsvp-status*</rsvp-status>
 <active-control-channel>*active-control-channel*</active-control-channel>
 <control-channel-unusable/>
 <index>*index*</index>
 <authentication-flag>*authentication-flag*</authentication-flag>
 <aggregate-flag>*aggregate-flag*</aggregate-flag>
 <ack-flag>*ack-flag*</ack-flag>
 <protect-flag>*protect-flag*</protect-flag>
 <hello-interval>*hello-interval*</hello-interval>
 <forward-rsvp/>
 <interface-address>*interface-address*</interface-address>
 <loopback-address>*loopback-address*</loopback-address>
 <rsvp-telink>...</rsvp-telink>
 <message-statistics>...</message-statistics>
 <bypass-info>...</bypass-info>
 <cos-info>...</cos-info>
</rsvp-interface>
 </rsvp-interface-information>

Description No documentation is available yet.

Contents <ack-flag>—No documentation is available yet.

<active-control-channel>—Currently active control channel for the peer.

<aggregate-flag>—No documentation is available yet.

<authentication-flag>—No documentation is available yet.

<bypass-info>—No documentation is available yet.

<control-channel-unusable>—Control channel does not have RSVP enabled on it.

<cos-info>—No documentation is available yet.

<forward-rsvp>—Allow forwarding of incoming RSVP messages on this interface when RSVP is disabled on the interface.

<hello-interval>—Rate at which RSVP hellos are sent out. Default is 3 seconds.

<index>—No documentation is available yet.

<interface-address>—No documentation is available yet.

<interface-name>—No documentation is available yet.

<loopback-address>—No documentation is available yet.

<message-statistics>—Statistics per RSVP message type.

<protect-flag>—No documentation is available yet.

<rsvp-status>—Whether RSVP has been enabled, whether an RSVP interface is up or down, or whether aggregation of messages is supported.

<rsvp-telink>—No documentation is available yet.

<rsvp-interface-information>

Usage <rpc-reply>
<rsvp-interface-information>
 <active-count>active-count</active-count>
 <rsvp-interface>...</rsvp-interface>
</rsvp-interface-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <active-count>—Number of active RSVP interfaces.
 <rsvp-interface>—No documentation is available yet.

<rsvp-interface-replication-information>

Usage <rpc-reply>
<rsvp-interface-replication-information>
 <rsvp-replication-te-link>...</rsvp-replication-te-link>
</rsvp-interface-replication-information>
 </rpc-reply>

Description Information about one or more replicated RSVP traffic-engineering links.

Contents <rsvp-replication-te-link>—Information about a replicated traffic-engineering link.

<rsvp-neighbor>

Usage <rsvp-neighbor-information>
<rsvp-neighbor>
 <rsvp-neighbor-address>*rsvp-neighbor-address*</rsvp-neighbor-address>
 <rsvp-neighbor-interface>*rsvp-neighbor-interface*</rsvp-neighbor-interface>
 <rsvp-neighbor-status>*rsvp-neighbor-status*</rsvp-neighbor-status>
 <rsvp-neighbor-remote/>
 <neighbor-idle>*neighbor-idle*</neighbor-idle>
 <neighbor-up-count>*neighbor-up-count*</neighbor-up-count>
 <neighbor-down-count>*neighbor-down-count*</neighbor-down-count>
 <last-changed-time>*last-changed-time*</last-changed-time>
 <hello-interval>*hello-interval*</hello-interval>
 <hellos-sent>*hellos-sent*</hellos-sent>
 <hellos-received>*hellos-received*</hellos-received>
 <messages-received>*messages-received*</messages-received>
 <rsvp-neighbor-remote-instance>*rsvp-neighbor-remote-instance*
 </rsvp-neighbor-remote-instance>
 <rsvp-neighbor-local-instance>*rsvp-neighbor-local-instance*
 </rsvp-neighbor-local-instance>
 <rsvp-message>*rsvp-message*</rsvp-message>
 <rsvp-refresh-reduct-status>*rsvp-refresh-reduct-status*
 </rsvp-refresh-reduct-status>
 <rsvp-refresh-reduct-remote-status>*rsvp-refresh-reduct-remote-status*
 </rsvp-refresh-reduct-remote-status>
 <rsvp-refresh-reduct-ack-status>*rsvp-refresh-reduct-ack-status*
 </rsvp-refresh-reduct-ack-status>
 <rsvp-graceful-restart>...</rsvp-graceful-restart>
</rsvp-neighbor>
 </rsvp-neighbor-information>

Description No documentation is available yet.

Contents <hello-interval>—Rate at which RSVP hellos are sent out. Default is 3 seconds.
 <hellos-received>—Number of hellos received.
 <hellos-sent>—Number of hellos sent.
 <last-changed-time>—Time this neighbor last changed state.
 <messages-received>—Total number of messages received.
 <neighbor-down-count>—Number of times neighbor went down.
 <neighbor-idle>—Length of time this neighbor has been idle.
 <neighbor-up-count>—Number of times neighbor came up.
 <rsvp-graceful-restart>—No documentation is available yet.
 <rsvp-message>—No documentation is available yet.
 <rsvp-neighbor-address>—No documentation is available yet.

`<rsvp-neighbor-interface>`—Local interface name.

`<rsvp-neighbor-local-instance>`—Local instance.

`<rsvp-neighbor-remote>`—The address is an RSVP remote neighbor for the endpoint of a backup LSP that was created because of a link or node failure for facility-based protection. A remote neighbor is deleted if the local node does not receive RSVP messages from it for 180 seconds.

`<rsvp-neighbor-remote-instance>`—Remote instance.

`<rsvp-neighbor-status>`—No documentation is available yet.

`<rsvp-refresh-reduct-ack-status>`—No documentation is available yet.

`<rsvp-refresh-reduct-remote-status>`—No documentation is available yet.

`<rsvp-refresh-reduct-status>`—No documentation is available yet.

`<rsvp-neighbor-information>`

Usage `<rpc-reply>`
 `<rsvp-neighbor-information>`
 `<rsvp-neighbor-count>`*rsvp-neighbor-count*`</rsvp-neighbor-count>`
 `<rsvp-neighbor>`...`</rsvp-neighbor>`
 `</rsvp-neighbor-information>`
`</rpc-reply>`

Description No documentation is available yet.

Contents `<rsvp-neighbor>`—No documentation is available yet.
 `<rsvp-neighbor-count>`—Number of RSVP neighbors learned.

`<rsvp-neighbor-replication-information>`

Usage `<rpc-reply>`
 `<rsvp-neighbor-replication-information>`
 `<rsvp-replication-neighbor>`...`</rsvp-replication-neighbor>`
 `</rsvp-neighbor-replication-information>`
`</rpc-reply>`

Description Information about one or more RSVP replication neighbors.

Contents `<rsvp-replication-neighbor>`—Replication information for an RSVP neighbor.

<rsvp-path-state-replication-information>

- Usage** <rpc-reply>
 <rsvp-path-state-replication-information>
 <rsvp-replication-path-state>...</rsvp-replication-path-state>
 </rsvp-path-state-replication-information>
 </rpc-reply>
- Description** Information about one or more replicated RSVP PATH state blocks.
- Contents** <rsvp-replication-path-state>—Information about a replicated RSVP PATH state block.

<rsvp-replication-neighbor>

- Usage** <rsvp-neighbor-replication-information>
 <rsvp-replication-neighbor>
 <replication-neighbor-address>*replication-neighbor-address*
 </replication-neighbor-address>
 <neighbor-interface>*neighbor-interface*</neighbor-interface>
 <neighbor-status>*neighbor-status*</neighbor-status>
 <replication-neighbor-up-count>*replication-neighbor-up-count*
 </replication-neighbor-up-count>
 <neighbor-flags>*neighbor-flags*</neighbor-flags>
 <neighbor-replication-sync-status>*neighbor-replication-sync-status*
 </neighbor-replication-sync-status>
 <neighbor-remote-instance>*neighbor-remote-instance*</neighbor-remote-instance>
 <neighbor-local-instance>*neighbor-local-instance*</neighbor-local-instance>
 <rsvp-graceful-restart>...</rsvp-graceful-restart>
 </rsvp-replication-neighbor>
 </rsvp-neighbor-replication-information>
- Description** Replication information for an RSVP neighbor.
- Contents** <neighbor-flags>—Neighbor flags.
- <neighbor-interface>—Local interface ID.
- <neighbor-local-instance>—Local instance.
- <neighbor-remote-instance>—Remote instance.
- <neighbor-replication-sync-status>—Neighbor replication synchronization status.
- <neighbor-status>—Status of neighbor.
- <replication-neighbor-address>—Neighbor address.
- <replication-neighbor-up-count>—Number of times neighbor came up.
- <rsvp-graceful-restart>—No documentation is available yet.

<rsvp-replication-path-state>

Usage <rsvp-path-state-replication-information>
<rsvp-replication-path-state>
 <path-state-address>*path-state-address*</path-state-address>
 <path-state-interface-id>*path-state-interface-id*</path-state-interface-id>
 <path-state-session-id>*path-state-session-id*</path-state-session-id>
 <path-state-self-id>*path-state-self-id*</path-state-self-id>
 <path-state-tag>*path-state-tag*</path-state-tag>
 <path-state-nh-type>*path-state-nh-type*</path-state-nh-type>
 <path-state-nh-outgoing-interface>*path-state-nh-outgoing-interface*
 </path-state-nh-outgoing-interface>
 <path-state-nh-upstream-tag>*path-state-nh-upstream-tag*
 </path-state-nh-upstream-tag>
 <path-state-nh-te-link-id>*path-state-nh-te-link-id*</path-state-nh-te-link-id>
 <path-state-nh-peer-address>*path-state-nh-peer-address*
 </path-state-nh-peer-address>
 <path-state-nh-avoid-address>*path-state-nh-avoid-address*
 </path-state-nh-avoid-address>
 <path-state-nh-ero>*path-state-nh-ero*</path-state-nh-ero>
</rsvp-replication-path-state>
 </rsvp-path-state-replication-information>

Description Information about a replicated RSVP PATH state block.

Contents <path-state-address>—IP address of the originator.
 <path-state-interface-id>—Interface ID.
 <path-state-nh-avoid-address>—IP address to avoid while computing bypass.
 <path-state-nh-ero>—Next-hop Explicit Route Object.
 <path-state-nh-outgoing-interface>—Outgoing interface.
 <path-state-nh-peer-address>—IP address of the next-hop peer.
 <path-state-nh-te-link-id>—TE link ID.
 <path-state-nh-type>—Next-hop type.
 <path-state-nh-upstream-tag>—Label value sent upstream.
 <path-state-self-id>—Self ID.
 <path-state-session-id>—Session ID.
 <path-state-tag>—Path state block tag.

<rsvp-replication-resv-state>

Usage	<pre> <rsvp-resv-state-replication-information> <rsvp-replication-resv-state> <resv-state-interface-id>resv-state-interface-id</resv-state-interface-id> <resv-state-session-id>resv-state-session-id</resv-state-session-id> <resv-state-self-id>resv-state-self-id</resv-state-self-id> </rsvp-replication-resv-state> </rsvp-resv-state-replication-information> </pre>
Description	Information about replicated RESV state block.
Contents	<pre> <resv-state-interface-id>—Interface ID. <resv-state-self-id>—Self ID. <resv-state-session-id>—Session ID. </pre>

<rsvp-replication-session>

Usage	<pre> <rsvp-session-replication-information> <rsvp-replication-session> <destination-address>destination-address</destination-address> <source-address>source-address</source-address> <label-in>label-in</label-in> <self-id>self-id</self-id> <session-id>session-id</session-id> <name>name</name> <replication-state>replication-state</replication-state> </rsvp-replication-session> </rsvp-session-replication-information> </pre>
Description	Information about a replicated RSVP session.
Contents	<pre> <destination-address>—Session destination address. <label-in>—Incoming label. <name>—No documentation is available yet. <replication-state>—Session replication state. <self-id>—Unique identifier for RSVP path state control block. <session-id>—Unique identifier for RSVP session. <source-address>—No documentation is available yet. </pre>

<rsvp-replication-te-link>

- Usage** <rsvp-interface-replication-information>
 <rsvp-replication-te-link>
 <te-link-id>*te-link-id*</te-link-id>
 <te-link-interface-id>*te-link-interface-id*</te-link-interface-id>
 <te-link-reference-count>*te-link-reference-count*</te-link-reference-count>
 </rsvp-replication-te-link>
 </rsvp-interface-replication-information>
- Description** Information about a replicated traffic-engineering link.
- Contents** <te-link-id>—Link identifier.
 <te-link-interface-id>—Local interface ID.
 <te-link-reference-count>—Reference count.

<rsvp-resv-state-replication-information>

- Usage** <rpc-reply>
 <rsvp-resv-state-replication-information>
 <rsvp-replication-resv-state>...</rsvp-replication-resv-state>
 </rsvp-resv-state-replication-information>
 </rpc-reply>
- Description** Information about one or more replicated RSVP RESV state blocks.
- Contents** <rsvp-replication-resv-state>—Information about replicated RESV state block.

<rsvp-session>

Usage <rsvp-session-data>

```

<rsvp-session>
  <destination-address>destination-address</destination-address>
  <is-detour/>
  <source-address>source-address</source-address>
  <lsp-state>lsp-state</lsp-state>
  <lsp-pktbytes>lsp-pktbytes</lsp-pktbytes>
  <bypass-name>bypass-name</bypass-name>
  <no-statistics/>
  <route-count>route-count</route-count>
  <rsb-count>rsb-count</rsb-count>
  <resv-style>resv-style</resv-style>
  <label-in>label-in</label-in>
  <label-out>label-out</label-out>
  <name>name</name>
  <mpls-p2mp-lsp-name>mpls-p2mp-lsp-name</mpls-p2mp-lsp-name>
  <lsp-path-type>lsp-path-type</lsp-path-type>
  <graceful-deletion-triggered/>
  <source-tna-address>source-tna-address</source-tna-address>
  <destination-tna-address>destination-tna-address</destination-tna-address>
  <bidirectional/>
  <upstream-label-in>upstream-label-in</upstream-label-in>
  <upstream-label-out>upstream-label-out</upstream-label-out>
  <suggested-label-in>suggested-label-in</suggested-label-in>
  <suggested-label-out>suggested-label-out</suggested-label-out>
  <recovery-label-in>recovery-label-in</recovery-label-in>
  <recovery-label-out>recovery-label-out</recovery-label-out>
  <psb-lifetime>psb-lifetime</psb-lifetime>
  <psb-creation-time>psb-creation-time</psb-creation-time>
  <path-mtu>path-mtu</path-mtu>
  <path-mtu-in-kernel>path-mtu-in-kernel</path-mtu-in-kernel>
  <sender-tspec>sender-tspec</sender-tspec>
  <layer2-tspec>...</layer2-tspec>
  <adspec>adspec</adspec>
  <ct-bw>ct-bw</ct-bw>
  <lsp-diffserv-info>lsp-diffserv-info</lsp-diffserv-info>
  <lsp-id>lsp-id</lsp-id>
  <tunnel-id>tunnel-id</tunnel-id>
  <proto-id>proto-id</proto-id>
  <self-id>self-id</self-id>
  <session-id>session-id</session-id>
  <is-fastreroute/>
  <is-linkprotection/>
  <is-nodeprotection/>
  <is-soft-preemption/>
  <rsvp-path-status>rsvp-path-status</rsvp-path-status>
  <rsvp-lp-backup-route-cnt>rsvp-lp-backup-route-cnt</rsvp-lp-backup-route-cnt>
  <rsvp-lp-backup-lsp-cnt>rsvp-lp-backup-lsp-cnt</rsvp-lp-backup-lsp-cnt>
  <packet-information>...</packet-information>
  <explicit-route>...</explicit-route>
  <record-route>...</record-route>
  <lp-history>...</lp-history>

```

```

    <rsvp-telink>...</rsvp-telink>
    <detour>...</detour>
    <detour-branch>...</detour-branch>
    <mpls-lsp>...</mpls-lsp>
  </rsvp-session>
</rsvp-session-data>

```

Description Single RSVP session.

Contents <adspec>—Adspec data element in an RSVP Path message.

<bidirectional>—LSP is bidirectional.

<bypass-name>—Name of the bypass.

<ct-bw>—Per-class bandwidth requested for E-LSPs and L-LSPs.

<destination-address>—Session destination address.

<destination-tna-address>—Destination TNA address for the connection.

<detour>—Detour that originated at this LSR.

<detour-branch>—Detour that originated at some other LSR.

<explicit-route>—Explicit Route Object (ERO).

<graceful-deletion-triggered>—Initiated graceful deletion procedure for the LSP.

<is-detour>—Session is a detour session.

<is-fastreroute>—Detours will be established for an LSP so that if a node or link in the LSP fails, the traffic on the LSP can be rerouted with minimal packet loss.

<is-linkprotection>—Protect links via bypass LSPs.

<is-nodeprotection>—Protect link/node via bypass LSPs.

<is-soft-preemption>—Attempt make-before-break service while preempting this LSP.

<label-in>—Incoming label.

<label-out>—Outgoing label.

<layer2-tspec>—Layer 2 TSpec.

<lp-history>—Log of LSP path-related events.

<lsp-diffserv-info>—LSP DiffServ info.

<lsp-id>—LSP ID or source port for some sender. It is unique to every sender or LSP.

<lsp-path-type>—Primary or secondary LSP path.

<lsp-pktbytes>—No documentation is available yet.

<lsp-state>—State of an LSP.

<mpls-lsp>—MPLS label-switched path information.

<mpls-p2mp-lsp-name>—No documentation is available yet.

<name>—No documentation is available yet.

<no-statistics>—No statistics are available for this session.

<packet-information>—RSVP packets sent or received per session.

<path-mtu>—The value of the path MTU, as negotiated by the network.

<path-mtu-in-kernel>—The value of the MTU used locally for forwarding.

<proto-id>—No documentation is available yet.

<psb-creation-time>—Time when this PSB was created.

<psb-lifetime>—Timer that maintains the soft state of a PSB.

<record-route>—Record Route Object (RRO).

<recovery-label-in>—No documentation is available yet.

<recovery-label-out>—No documentation is available yet.

<resv-style>—Reservation style (FF or SE).

<route-count>—Number of active routes.

<rsb-count>—Number of RSBs.

<rsvp-lp-backup-lsp-cnt>—Number of backup RSVP LSPs tunneled through this bypass.

<rsvp-lp-backup-route-cnt>—Number of routes tunneled through this bypass.

<rsvp-path-status>—No documentation is available yet.

<rsvp-telink>—No documentation is available yet.

<self-id>—Unique identifier for RSVP path state control block.

<sender-tspec>—Sender TSpec.

<session-id>—Unique identifier for RSVP session.

<source-address>—No documentation is available yet.

<source-tna-address>—Source TNA address for the connection.

<suggested-label-in>—Suggested label received.

<suggested-label-out>—Suggested label sent.

`<tunnel-id>`—Tunnel ID or destination port for this session. It is unique to every session.

`<upstream-label-in>`—Incoming upstream label.

`<upstream-label-out>`—Outgoing upstream label.

`<rsvp-session-data>`

Usage `<rsvp-session-information | mpls-lsp-information>`
`<rsvp-session-data>`
`<session-type>session-type</session-type>`
`<count>count</count>`
`<display-count>display-count</display-count>`
`<up-count>up-count</up-count>`
`<down-count>down-count</down-count>`
`<detours>detours</detours>`
`<rsvp-session>...</rsvp-session>`
`<mpls-p2mp-lsp>...</mpls-p2mp-lsp>`
`</rsvp-session-data>`
`</rsvp-session-information | mpls-lsp-information>`

Description No documentation is available yet.

Contents `<count>`—Number of entries.

`<detours>`—Number of detour sessions.

`<display-count>`—Number of sessions displayed.

`<down-count>`—Number of sessions in down state.

`<mpls-p2mp-lsp>`—No documentation is available yet.

`<rsvp-session>`—Single RSVP session.

`<session-type>`—Whether the router is at the ingress, egress, or transit for this session.

`<up-count>`—Number of sessions in up state.

`<rsvp-session-information>`

Usage `<rpc-reply>`
`<rsvp-session-information>`
`<rsvp-session-data>...</rsvp-session-data>`
`</rsvp-session-information>`
`</rpc-reply>`

Description No documentation is available yet.

Contents `<rsvp-session-data>`—No documentation is available yet.

<rsvp-session-replication-information>

Usage <rpc-reply>
 <rsvp-session-replication-information>
 <rsvp-replication-session>...</rsvp-replication-session>
 </rsvp-session-replication-information>
 </rpc-reply>

Description Information about one or more replicated RSVP sessions.

Contents <rsvp-replication-session>—Information about a replicated RSVP session.

<rsvp-statistics-information>

Usage <rpc-reply>
 <rsvp-statistics-information>
 <message-statistics>...</message-statistics>
 <rsvp-error>...</rsvp-error>
 </rsvp-statistics-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <message-statistics>—Statistics per RSVP message type.

<rsvp-error>—No documentation is available yet.

<rsvp-telink>

Usage <rsvp-session | rsvp-interface>

```

<rsvp-telink>
  <telink-name>telink-name</telink-name>
  <telink-local-id>telink-local-id</telink-local-id>
  <telink-state>telink-state</telink-state>
  <active-reservation>active-reservation</active-reservation>
  <subscription>subscription</subscription>
  <ct-subscription>ct-subscription</ct-subscription>
  <static-bandwidth>static-bandwidth</static-bandwidth>
  <available-bandwidth>available-bandwidth</available-bandwidth>
  <max-available-bandwidth>max-available-bandwidth</max-available-bandwidth>
  <max-available-description>max-available-description
    </max-available-description>
  <static-bc-bandwidth>static-bc-bandwidth</static-bc-bandwidth>
  <total-reserved-bandwidth>total-reserved-bandwidth</total-reserved-bandwidth>
  <bc>bc</bc>
  <bc-description>bc-description</bc-description>
  <ct-class>ct-class</ct-class>
  <ct-bw0>ct-bw0</ct-bw0>
  <ct-bw1>ct-bw1</ct-bw1>
  <ct-bw2>ct-bw2</ct-bw2>
  <ct-bw3>ct-bw3</ct-bw3>
  <ct-bw4>ct-bw4</ct-bw4>
  <ct-bw5>ct-bw5</ct-bw5>
  <ct-bw6>ct-bw6</ct-bw6>
  <ct-bw7>ct-bw7</ct-bw7>
  <high-watermark>high-watermark</high-watermark>
  <preemption-count>preemption-count</preemption-count>
  <soft-preemption-count>soft-preemption-count</soft-preemption-count>
  <soft-preemption-pending>soft-preemption-pending</soft-preemption-pending>
  <update-threshold>update-threshold</update-threshold>
  <reserved-bandwidth>...</reserved-bandwidth>
  <reserved-ct-bandwidth>...</reserved-ct-bandwidth>
  <detour-bandwidth>...</detour-bandwidth>
  <overbooked-bandwidth>...</overbooked-bandwidth>
  <overbooked-ct-bandwidth>...</overbooked-ct-bandwidth>
</rsvp-telink>
</rsvp-session | rsvp-interface>

```

Description No documentation is available yet.

Contents <active-reservation>—Number of active reservations.

<available-bandwidth>—Amount of bandwidth available for reservations.

<bc>—Bandwidth constraint (0..7).

<bc-description>—Description of the bandwidth constraint.

<ct-bw0>—No documentation is available yet.

<ct-bw1>—No documentation is available yet.

<ct-bw2>—No documentation is available yet.

<ct-bw3>—No documentation is available yet.

<ct-bw4>—No documentation is available yet.

<ct-bw5>—No documentation is available yet.

<ct-bw6>—No documentation is available yet.

<ct-bw7>—No documentation is available yet.

<ct-class>—Class type (0..7).

<ct-subscription>—Subscription percentage per traffic class.

<detour-bandwidth>—Bandwidth reserved on detour at different priority levels.

<high-watermark>—Maximum bandwidth that was ever reserved.

<max-available-bandwidth>—Maximum amount of bandwidth available for reservations, including the subscription factor.

<max-available-description>—Description of the computation of the maximum available bandwidth.

<overbooked-bandwidth>—Bandwidth overbooked at different priority levels.

<overbooked-ct-bandwidth>—Bandwidth overbooked at different class/priority levels.

<preemption-count>—Number of preemptions that occurred on an interface.

<reserved-bandwidth>—Bandwidth reserved at different priority levels.

<reserved-ct-bandwidth>—Bandwidth reserved at different class and priority levels.

<soft-preemption-count>—Number of soft preemptions that occurred on an interface.

<soft-preemption-pending>—Number of soft preemptions pending on an interface.

<static-bandwidth>—Static bandwidth capacity of the link.

<static-bc-bandwidth>—Static bandwidth capacity for a bandwidth constraint.

<subscription>—Percentage of link capacity available for bandwidth reservations.

<telink-local-id>—Local identifier of TE link.

<telink-name>—Name of the TE link.

<telink-state>—State of the TE link.

<total-reserved-bandwidth>—Total amount of bandwidth currently reserved.

<update-threshold>—Percentage change in reserved bandwidth to trigger IGP

update.

<rsvp-version>

Usage <rsvp-version-information>
<rsvp-version>
 <rsvp-status>*rsvp-status*</rsvp-status>
 <rsvp-restart-flag>*rsvp-restart-flag*</rsvp-restart-flag>
 <refresh-timer>*refresh-timer*</refresh-timer>
 <keep-multiplier>*keep-multiplier*</keep-multiplier>
 <preemption-type>*preemption-type*</preemption-type>
 <soft-preemption-cleanup-timer>*soft-preemption-cleanup-timer*
 </soft-preemption-cleanup-timer>
 <graceful-deletion-timeout>*graceful-deletion-timeout*
 </graceful-deletion-timeout>
 <rsvp-nsr-mode>*rsvp-nsr-mode*</rsvp-nsr-mode>
 <rsvp-nsr-state>*rsvp-nsr-state*</rsvp-nsr-state>
 <rsvp-graceful-restart>...</rsvp-graceful-restart>
</rsvp-version>
 </rsvp-version-information>

Description No documentation is available yet.

Contents <graceful-deletion-timeout>—Maximum wait time for graceful deletion signaling to complete after which forced deletion will be initiated.

<keep-multiplier>—A measure of the number of RSVP message losses that can be tolerated before a state is timed out. Default is 3.

<preemption-type>—Type of preemption scheme.

<refresh-timer>—Indicates the rate at which RSVP refresh messages (Path and Resv) are sent out to maintain the soft state. Default is 30 seconds.

<rsvp-graceful-restart>—No documentation is available yet.

<rsvp-nsr-mode>—RSVP nonstop-routing mode.

<rsvp-nsr-state>—RSVP nonstop-routing state.

<rsvp-restart-flag>—RSVP restart is in progress.

<rsvp-status>—Whether RSVP has been enabled, whether an RSVP interface is up or down, or whether aggregation of messages is supported.

<soft-preemption-cleanup-timer>—The time after which soft-preempted LSPs will be removed.

<rsvp-version-information>

- Usage** <rpc-reply>
 <rsvp-version-information>
 <rsvp-version>...</rsvp-version>
 </rsvp-version-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <rsvp-version>—No documentation is available yet.

<rt>

- Usage** <route-table>
 <rt>
 <rt-destination>*rt-destination*</rt-destination>
 <rt-prefix-length>*rt-prefix-length*</rt-prefix-length>
 <rt-entry-count>*rt-entry-count*</rt-entry-count>
 <rt-announced-count>*rt-announced-count*</rt-announced-count>
 <rt-state>*rt-state*</rt-state>
 <rt-entry>...</rt-entry>
 <tsi>*tsi*</tsi>
 <communities>...</communities>
 </rt>
 </route-table>
- Description** No documentation is available yet.
- Contents** <communities>—No documentation is available yet.
- <rt-announced-count>—Number of announced route entries.
- <rt-destination>—No documentation is available yet.
- <rt-entry>—No documentation is available yet.
- <rt-entry-count>—Number of route entries in this route.
- <rt-prefix-length>—No documentation is available yet.
- <rt-state>—State of this route.
- <tsi>—Task-specific information.

<rt-entry>**Usage** <rt>**<rt-entry>**

```

<active-tag>active-tag</active-tag>
<last-active/>
<current-active/>
<protocol-name>protocol-name</protocol-name>
<preference>preference</preference>
<preference2>preference2</preference2>
<route-distinguisher>route-distinguisher</route-distinguisher>
<pmsi>pmsi</pmsi>
<color>color</color>
<rt-isis-level>rt-isis-level</rt-isis-level>
<color2>color2</color2>
<rt-isis-downbit>rt-isis-downbit</rt-isis-downbit>
<age>age</age>
<metric>metric</metric>
<metric2>metric2</metric2>
<med-plus-igp>med-plus-igp</med-plus-igp>
<rt-tag>rt-tag</rt-tag>
<rt-tag2>rt-tag2</rt-tag2>
<rt-ospf-area>rt-ospf-area</rt-ospf-area>
<learned-from>learned-from</learned-from>
<peer-as>peer-as</peer-as>
<local-as>local-as</local-as>
<rt-entry-state>rt-entry-state</rt-entry-state>
<inactive-reason>inactive-reason</inactive-reason>
<task-name>task-name</task-name>
<announce-bits>announce-bits</announce-bits>
<announce-tasks>announce-tasks</announce-tasks>
<bgp-rt-flag>bgp-rt-flag</bgp-rt-flag>
<label-base>label-base</label-base>
<label-range>label-range</label-range>
<l2vpn-status-vector>l2vpn-status-vector</l2vpn-status-vector>
<vc-label>vc-label</vc-label>
<mtu>mtu</mtu>
<cell-bundle-size>cell-bundle-size</cell-bundle-size>
<vlan-id>vlan-id</vlan-id>
<tdm-payload-size>tdm-payload-size</tdm-payload-size>
<tdm-bitrate>tdm-bitrate</tdm-bitrate>
<connection-bandwidth>...</connection-bandwidth>
<cac-bandwidth-failure/>
<vpn-label>vpn-label</vpn-label>
<route-label>route-label</route-label>
<bgp-no-label-reason>bgp-no-label-reason</bgp-no-label-reason>
<rtd-flow-dep>...</rtd-flow-dep>
<as-path>as-path</as-path>
<communities>...</communities>
<helper-nhid>helper-nhid</helper-nhid>
<helper-refcount>helper-refcount</helper-refcount>
<bgp-metric-flags>bgp-metric-flags</bgp-metric-flags>
<local-preference>local-preference</local-preference>
<med>med</med>

```

```

<peer-id>peer-id</peer-id>
<cluster-id>cluster-id</cluster-id>
<originator>originator</originator>
<attrset>...</attrset>
<bgp-group-name>bgp-group-name</bgp-group-name>
<deleted/>
<route-flap-damping>...</route-flap-damping>
<aggregate>...</aggregate>
<gateway>gateway</gateway>
<indirect-nh-count>indirect-nh-count</indirect-nh-count>
<composite-nh-count>composite-nh-count</composite-nh-count>
<nh-type>nh-type</nh-type>
<nh-index>nh-index</nh-index>
<nh-reference-count>nh-reference-count</nh-reference-count>
<nh>...</nh>
<protocol-nh>...</protocol-nh>
<rtrib-primary>rtrib-primary</rtrib-primary>
<rtrib-secondary>rtrib-secondary</rtrib-secondary>
<backup-pe-group-name>backup-pe-group-name</backup-pe-group-name>
<designated-forwarder>designated-forwarder</designated-forwarder>
</rt-entry>
</rt>

```

Description No documentation is available yet.

Contents

- <active-tag>—Visual indication of active state of this route entry.
- <age>—No documentation is available yet.
- <aggregate>—No documentation is available yet.
- <announce-bits>—No documentation is available yet.
- <announce-tasks>—No documentation is available yet.
- <as-path>—AS path of this route.
- <attrset>—No documentation is available yet.
- <backup-pe-group-name>—Name of the backup PE group.
- <bgp-group-name>—No documentation is available yet.
- <bgp-metric-flags>—BGP metrics flags.
- <bgp-no-label-reason>—BGP label allocation failure.
- <bgp-rt-flag>—BGP route flag.
- <cac-bandwidth-failure>—Call admission control failure due to insufficient bandwidth.
- <cell-bundle-size>—Cell bundle size.
- <cluster-id>—No documentation is available yet.

<color>—No documentation is available yet.

<color2>—No documentation is available yet.

<communities>—No documentation is available yet.

<composite-nh-count>—Number of composite next hops.

<connection-bandwidth>—Bandwidth of a layer 2 connection.

<current-active>—This route entry is currently active.

<deleted>—No documentation is available yet.

<designated-forwarder>—Indicates if we are the designated forwarder for this route.

<gateway>—Sourcing gateway.

<helper-nhid>—Helper nexthop index.

<helper-refcount>—Reference count of those needing helper route.

<inactive-reason>—No documentation is available yet.

<indirect-nh-count>—Number of indirect next hops.

<l2vpn-status-vector>—No documentation is available yet.

<label-base>—Label base for l2vpn.

<label-range>—Label range for l2vpn.

<last-active>—This route entry was the last active route entry.

<learned-from>—Peer address from which this route was learned.

<local-as>—Local AS number.

<local-preference>—No documentation is available yet.

<med>—Multiple exit discriminator.

<med-plus-igp>—No documentation is available yet.

<metric>—No documentation is available yet.

<metric2>—No documentation is available yet.

<mtu>—MTU along an interface.

<nh>—Next-hop gateway information.

<nh-index>—Next-hop index.

<nh-reference-count>—Number of references to this next hop.

<nh-type>—Special next hop: Reject, Blackhole, Receive, Multicast, Local, or Unused.

<originator>—No documentation is available yet.

<peer-as>—Peer AS number.

<peer-id>—Router identifier of the peer.

<pmsi>—P-multicast service interface.

<preference>—Preference value configured with the preference statement. The default preference value is 170.

<preference2>—No documentation is available yet.

<protocol-name>—No documentation is available yet.

<protocol-nh>—Protocol next hop.

<route-distinguisher>—No documentation is available yet.

<route-flap-damping>—No documentation is available yet.

<route-label>—Route label.

<rt-entry-state>—State of this route entry.

<rt-isis-downbit>—No documentation is available yet.

<rt-isis-level>—No documentation is available yet.

<rt-ospf-area>—No documentation is available yet.

<rt-tag>—No documentation is available yet.

<rt-tag2>—No documentation is available yet.

<rtd-flow-dep>—No documentation is available yet.

<rtrib-primary>—Primary routing table.

<rtrib-secondary>—Secondary routing table.

<task-name>—Name of this task.

<tdm-bitrate>—No documentation is available yet.

<tdm-payload-size>—No documentation is available yet.

<vc-label>—VC label.

<vlan-id>—No documentation is available yet.

<vpn-label>—VPN label.

<rt-martians>

Usage <route-information>
 <rt-martians>
 <rt-martian-table-name>*rt-martian-table-name*</rt-martian-table-name>
 <route-filter>...</route-filter>
 </rt-martians>
 </route-information>

Description No documentation is available yet.

Contents <route-filter>—Entries in martian table.

 <rt-martian-table-name>—Name of the martian table, for example, inet.0.

<rt-ribgroup>

Usage	<pre> <route-information> <rt-ribgroup> <rt-ribgroup-name><i>rt-ribgroup-name</i></rt-ribgroup-name> <rt-ribgroup-address><i>rt-ribgroup-address</i></rt-ribgroup-address> <rt-ribgroup-flags><i>rt-ribgroup-flags</i></rt-ribgroup-flags> <rt-ribgroup-address-family><i>rt-ribgroup-address-family</i> </rt-ribgroup-address-family> <rt-ribgroup-refcount><i>rt-ribgroup-refcount</i></rt-ribgroup-refcount> <rt-ribgroup-export-name><i>rt-ribgroup-export-name</i></rt-ribgroup-export-name> <rt-ribgroup-import-name><i>rt-ribgroup-import-name</i></rt-ribgroup-import-name> <rt-ribgroup-import-policy-name><i>rt-ribgroup-import-policy-name</i> </rt-ribgroup-import-policy-name> <rt-ribgroup-import-secondary-name><i>rt-ribgroup-import-secondary-name</i> </rt-ribgroup-import-secondary-name> <rt-ribgroup-union-head-name><i>rt-ribgroup-union-head-name</i> </rt-ribgroup-union-head-name> <rt-ribgroup-union-child-name><i>rt-ribgroup-union-child-name</i> </rt-ribgroup-union-child-name> </rt-ribgroup> </route-information> </pre>
Description	No documentation is available yet.
Contents	<p><rt-ribgroup-address>—Rib-group address.</p> <p><rt-ribgroup-address-family>—Rib-group address family.</p> <p><rt-ribgroup-export-name>—Export RIB name.</p> <p><rt-ribgroup-flags>—Rib-group flags.</p> <p><rt-ribgroup-import-name>—Import RIB name.</p> <p><rt-ribgroup-import-policy-name>—Import policy name.</p> <p><rt-ribgroup-import-secondary-name>—Import secondary RIB name.</p> <p><rt-ribgroup-name>—Rib-group name.</p> <p><rt-ribgroup-refcount>—Rib-group refcount.</p> <p><rt-ribgroup-union-child-name>—Rib-group union child name.</p> <p><rt-ribgroup-union-head-name>—Rib-group union head name.</p>

<rt-test-policy>

Usage	<pre> <route-information> <rt-test-policy> <rt-policy-name><i>rt-policy-name</i></rt-policy-name> <rt-route-accepted><i>rt-route-accepted</i></rt-route-accepted> <rt-route-rejected><i>rt-route-rejected</i></rt-route-rejected> </rt-test-policy> </route-information> </pre>
Description	No documentation is available yet.
Contents	<p><rt-policy-name>—No documentation is available yet.</p> <p><rt-route-accepted>—No documentation is available yet.</p> <p><rt-route-rejected>—No documentation is available yet.</p>

<rt-test-policy-prefix>

Usage	<pre> <route-information> <rt-test-policy-prefix> <rt-policy-name><i>rt-policy-name</i></rt-policy-name> <rt-destination><i>rt-destination</i></rt-destination> <rt-prefix-length><i>rt-prefix-length</i></rt-prefix-length> <rt-test-policy-term>...</rt-test-policy-term> </rt-test-policy-prefix> </route-information> </pre>
Description	No documentation is available yet.
Contents	<p><rt-destination>—No documentation is available yet.</p> <p><rt-policy-name>—No documentation is available yet.</p> <p><rt-prefix-length>—No documentation is available yet.</p> <p><rt-test-policy-term>—No documentation is available yet.</p>

<rt-test-policy-term>

Usage	<pre> <rt-test-policy-prefix> rt-test-policy-term <rt-policy-term-name><i>rt-policy-term-name</i></rt-policy-term-name> <rt-policy-term-result><i>rt-policy-term-result</i></rt-policy-term-result> <rt-policy-term-action><i>rt-policy-term-action</i></rt-policy-term-action> /rt-test-policy-term </rt-test-policy-prefix> </pre>
Description	No documentation is available yet.
Contents	<p><rt-policy-term-action>—No documentation is available yet.</p> <p><rt-policy-term-name>—No documentation is available yet.</p> <p><rt-policy-term-result>—No documentation is available yet.</p>

<rtd-flow-dep>

Usage	<pre> <rt-entry> rtd-flow-dep <flow-origin><i>flow-origin</i></flow-origin> <flow-dep-state><i>flow-dep-state</i></flow-dep-state> <flow-ucast-rt>...</flow-ucast-rt> /rtd-flow-dep </rt-entry> </pre>
Description	No documentation is available yet.
Contents	<p><flow-dep-state>—Flow dependency state.</p> <p><flow-origin>—Originator of the flow information.</p> <p><flow-ucast-rt>—Unicast route used for resolution.</p>

<rte-instance>

Usage	<pre> <rteexport-table-information> <rte-instance> <instance-name>instance-name</instance-name> <rte-instance-type>rte-instance-type</rte-instance-type> <instance-flags>instance-flags</instance-flags> <instance-options>instance-options</instance-options> <import-policy>import-policy</import-policy> <export-policy>export-policy</export-policy> </rte-instance> </rteexport-table-information> </pre>
Description	No documentation is available yet.
Contents	<p><export-policy>—No documentation is available yet.</p> <p><import-policy>—No documentation is available yet.</p> <p><instance-flags>—No documentation is available yet.</p> <p><instance-name>—No documentation is available yet.</p> <p><instance-options>—No documentation is available yet.</p> <p><rte-instance-type>—No documentation is available yet.</p>

<rte-table>

Usage	<pre> <rteexport-table-information> <rte-table> <table-name>table-name</table-name> <table-export-on>table-export-on</table-export-on> <import-list>import-list</import-list> <table-flags>table-flags</table-flags> <table-usage>table-usage</table-usage> </rte-table> </rteexport-table-information> </pre>
Description	No documentation is available yet.
Contents	<p><import-list>—No documentation is available yet.</p> <p><table-export-on>—No documentation is available yet.</p> <p><table-flags>—No documentation is available yet.</p> <p><table-name>—Unicast routing table.</p> <p><table-usage>—Number of exported routes.</p>

<rte-target>

Usage	<pre> <rteexport-table-information> <rte-target> <target-string>target-string</target-string> <family>family</family> <subaf>subaf</subaf> <import-count>import-count</import-count> <export-count>export-count</export-count> <import-list>import-list</import-list> <export-list>export-list</export-list> </rte-target> </rteexport-table-information> </pre>
Description	No documentation is available yet.
Contents	<p><export-count>—No documentation is available yet.</p> <p><export-list>—No documentation is available yet.</p> <p><family>—No documentation is available yet.</p> <p><import-count>—No documentation is available yet.</p> <p><import-list>—No documentation is available yet.</p> <p><subaf>—No documentation is available yet.</p> <p><target-string>—Route target.</p>

<rteexport-table-information>

Usage	<pre> <rpc-reply> <rteexport-table-information> <rte-table>...</rte-table> <rte-target>...</rte-target> <rte-instance>...</rte-instance> </rteexport-table-information> </rpc-reply> </pre>
Description	Operational information policy-based instance export.
Contents	<p><rte-instance>—No documentation is available yet.</p> <p><rte-table>—No documentation is available yet.</p> <p><rte-target>—No documentation is available yet.</p>

<rtflow-dep-information>

- Usage** <rpc-reply>
 <rtflow-dep-information>
 <rtflow-dep-table>...</rtflow-dep-table>
 </rtflow-dep-information>
 </rpc-reply>
- Description** Operational information on flow route validation.
- Contents** <rtflow-dep-table>—No documentation is available yet.

<rtflow-dep-table>

- Usage** <rtflow-dep-information>
 <rtflow-dep-table>
 <table-name>table-name</table-name>
 <fdep-node>...</fdep-node>
 </rtflow-dep-table>
 </rtflow-dep-information>
- Description** No documentation is available yet.
- Contents** <fdep-node>—No documentation is available yet.
 <table-name>—Unicast routing table.

<sap-listen>

- Usage** <sap-listen-information>
 <sap-listen>
 <sap-listen-group>sap-listen-group</sap-listen-group>
 <sap-listen-port>sap-listen-port</sap-listen-port>
 </sap-listen>
 </sap-listen-information>
- Description** No documentation is available yet.
- Contents** <sap-listen-group>—Listening group address.
 <sap-listen-port>—Listening port.

<sap-listen-information>

- Usage** <rpc-reply>
 <sap-listen-information>
 <sap-listen>...</sap-listen>
 </sap-listen-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <sap-listen>—No documentation is available yet.

<session-connection-data>

Usage	<pre> <multicast-session> <session-connection-data> <session-address>session-address</session-address> <session-ttl>session-ttl</session-ttl> <session-layers>session-layers</session-layers> </session-connection-data> </multicast-session> </pre>
Description	No documentation is available yet.
Contents	<p><session-address>—No documentation is available yet.</p> <p><session-layers>—No documentation is available yet.</p> <p><session-ttl>—No documentation is available yet.</p>

<session-origin>

Usage	<pre> <multicast-session> <session-origin> <session-originator-username>session-originator-username </session-originator-username> <session-originator-address>session-originator-address </session-originator-address> </session-origin> </multicast-session> </pre>
Description	No documentation is available yet.
Contents	<p><session-originator-address>—No documentation is available yet.</p> <p><session-originator-username>—No documentation is available yet.</p>

<source-family>

Usage	<pre> <pim-source-information> <source-family> <pim-instance>pim-instance</pim-instance> <address-family>address-family</address-family> <pim-source>...</pim-source> </source-family> </pim-source-information> </pre>
Description	No documentation is available yet.
Contents	<p><address-family>—No documentation is available yet.</p> <p><pim-instance>—Name of the PIM instance.</p> <p><pim-source>—No documentation is available yet.</p>

<sparse-downstream-interface>

Usage <join-group>
 <sparse-downstream-interface>
 <pim-interface-name>*pim-interface-name*</pim-interface-name>
 <register-rp>*register-rp*</register-rp>
 <register-interface-name>*register-interface-name*</register-interface-name>
 <pim-interface-state>*pim-interface-state*</pim-interface-state>
 <pim-pseudo-downstream-interface-name>*pim-pseudo-downstream-interface-name*
 </pim-pseudo-downstream-interface-name>
 <downstream-neighbor>...</downstream-neighbor>
 <downstream-assert-neighbor>...</downstream-assert-neighbor>
 </sparse-downstream-interface>
 </join-group>

Description No documentation is available yet.

Contents <downstream-assert-neighbor>—Information about the neighbor that won the assert.

<downstream-neighbor>—No documentation is available yet.

<pim-interface-name>—Name of PIM interface.

<pim-interface-state>—State of PIM interface.

<pim-pseudo-downstream-interface-name>—Downstream pseudo interface representing aggregated IGMP interfaces.

<register-interface-name>—No documentation is available yet.

<register-rp>—No documentation is available yet.

<statistics-family>

Usage <pim-statistics-information>
 <statistics-family>
 <address-family>*address-family*</address-family>
 <pim-statistics-interface>...</pim-statistics-interface>
 </statistics-family>
 </pim-statistics-information>

Description No documentation is available yet.

Contents <address-family>—No documentation is available yet.

<pim-statistics-interface>—No documentation is available yet.

<switching-capability-descriptor>

Usage <ted-link>
<switching-capability-descriptor>
 <encoding-type>*encoding-type*</encoding-type>
 <switching-type>*switching-type*</switching-type>
 <maximum-lsp-bw0>*maximum-lsp-bw0*</maximum-lsp-bw0>
 <maximum-lsp-bw1>*maximum-lsp-bw1*</maximum-lsp-bw1>
 <maximum-lsp-bw2>*maximum-lsp-bw2*</maximum-lsp-bw2>
 <maximum-lsp-bw3>*maximum-lsp-bw3*</maximum-lsp-bw3>
 <maximum-lsp-bw4>*maximum-lsp-bw4*</maximum-lsp-bw4>
 <maximum-lsp-bw5>*maximum-lsp-bw5*</maximum-lsp-bw5>
 <maximum-lsp-bw6>*maximum-lsp-bw6*</maximum-lsp-bw6>
 <maximum-lsp-bw7>*maximum-lsp-bw7*</maximum-lsp-bw7>
 <minimum-lsp-bw>*minimum-lsp-bw*</minimum-lsp-bw>
 <mtu>*mtu*</mtu>
 <tdm-indication>*tdm-indication*</tdm-indication>
</switching-capability-descriptor>
 </ted-link>

Description Switching capability of an interface.

Contents <encoding-type>—LSP encoding type.

<maximum-lsp-bw0>—No documentation is available yet.

<maximum-lsp-bw1>—No documentation is available yet.

<maximum-lsp-bw2>—No documentation is available yet.

<maximum-lsp-bw3>—No documentation is available yet.

<maximum-lsp-bw4>—No documentation is available yet.

<maximum-lsp-bw5>—No documentation is available yet.

<maximum-lsp-bw6>—No documentation is available yet.

<maximum-lsp-bw7>—Maximum bandwidth an LSP could reserve.

<minimum-lsp-bw>—Minimum bandwidth an LSP could reserve.

<mtu>—MTU along an interface.

<switching-type>—LSP switching capability.

<tdm-indication>—Whether the interface supports Standard or Arbitrary SDH.

<task>

Usage	<pre><task-information task-timer-information> <task> <task-name>task-name</task-name> <task-no-information/> <task-timer>...</task-timer> </task> </task-information task-timer-information></pre>
Description	No documentation is available yet.
Contents	<p><task-name>—Name of this task.</p> <p><task-no-information>—No information is available for this task.</p> <p><task-timer>—No documentation is available yet.</p>

<task-block>

Usage	<pre> <task-block-list> <task-block> <tb-name>tb-name</tb-name> <tb-size>tb-size</tb-size> <tb-alloc-size>tb-alloc-size</tb-alloc-size> <tb-terse-transient/> <tb-terse-fullpage/> <tb-terse-debug/> <tb-alloc-blocks>tb-alloc-blocks</tb-alloc-blocks> <tb-alloc-bytes>tb-alloc-bytes</tb-alloc-bytes> <tb-max-alloc-blocks>tb-max-alloc-blocks</tb-max-alloc-blocks> <tb-max-alloc-bytes>tb-max-alloc-bytes</tb-max-alloc-bytes> </task-block> </task-block-list> </pre>
Description	No documentation is available yet.
Contents	<pre> <tb-alloc-blocks>—Number of allocated structures. <tb-alloc-bytes>—Number of allocated bytes. <tb-alloc-size>—Allocated size for this block. <tb-max-alloc-blocks>—Maximum number of structures ever allocated. <tb-max-alloc-bytes>—Maximum number of bytes ever allocated. <tb-name>—Name for this block. <tb-size>—Actual size of this block. <tb-terse-debug>—No documentation is available yet. <tb-terse-fullpage>—No documentation is available yet. <tb-terse-transient>—No documentation is available yet. </pre>

<task-block-list>

Usage	<pre> <task-memory-allocator-report> <task-block-list> <task-block>...</task-block> </task-block-list> </task-memory-allocator-report> </pre>
Description	No documentation is available yet.
Contents	<task-block>—No documentation is available yet.

<task-information>

Usage	<pre><rpc-reply> <task-information> <task>...</task> </task-information> </rpc-reply></pre>
Description	No documentation is available yet.
Contents	<task>—No documentation is available yet.

<task-lite-page>

Usage	<pre><task-lite-page-list> <task-lite-page> <tlp-name>tlp-name</tlp-name> <tlp-alloc-pages>tlp-alloc-pages</tlp-alloc-pages> <tlp-alloc-bytes>tlp-alloc-bytes</tlp-alloc-bytes> <tlp-max-alloc-pages>tlp-max-alloc-pages</tlp-max-alloc-pages> <tlp-max-alloc-bytes>tlp-max-alloc-bytes</tlp-max-alloc-bytes> </task-lite-page> </task-lite-page-list></pre>
Description	No documentation is available yet.
Contents	<p><tlp-alloc-bytes>—Number of bytes allocated.</p> <p><tlp-alloc-pages>—Number of pages allocated.</p> <p><tlp-max-alloc-bytes>—Maximum bytes ever allocated.</p> <p><tlp-max-alloc-pages>—Maximum pages ever allocated.</p> <p><tlp-name>—Name of this pool.</p>

<task-lite-page-list>

Usage	<pre><task-memory-allocator-report> <task-lite-page-list> <task-lite-page>...</task-lite-page> </task-lite-page-list> </task-memory-allocator-report></pre>
Description	No documentation is available yet.
Contents	<task-lite-page>—No documentation is available yet.

<task-malloc>

Usage	<pre> <task-malloc-list> <task-malloc> <tm-name><i>tm-name</i></tm-name> <tm-allocs><i>tm-allocs</i></tm-allocs> <tm-alloc-bytes><i>tm-alloc-bytes</i></tm-alloc-bytes> <tm-max-allocs><i>tm-max-allocs</i></tm-max-allocs> <tm-max-alloc-bytes><i>tm-max-alloc-bytes</i></tm-max-alloc-bytes> <tm-function-calls><i>tm-function-calls</i></tm-function-calls> </task-malloc> </task-malloc-list> </pre>
Description	No documentation is available yet.
Contents	<p><tm-alloc-bytes>—Number of bytes allocated.</p> <p><tm-allocs>—Number of allocations out.</p> <p><tm-function-calls>—Number of function calls.</p> <p><tm-max-alloc-bytes>—Maximum bytes allocated.</p> <p><tm-max-allocs>—Maximum allocations ever out.</p> <p><tm-name>—No documentation is available yet.</p>

<task-malloc-list>

Usage	<pre> <task-memory-malloc-usage-report> <task-malloc-list> <task-malloc>...</task-malloc> </task-malloc-list> </task-memory-malloc-usage-report> </pre>
Description	No documentation is available yet.
Contents	<task-malloc>—No documentation is available yet.

<task-memory-allocator-report>

Usage <task-memory-information>
 <task-memory-allocator-report>
 <task-block-list>...</task-block-list>
 <task-lite-page-list>...</task-lite-page-list>
 <task-memory-total-bytes>*task-memory-total-bytes*</task-memory-total-bytes>
 <task-memory-total-max-bytes>*task-memory-total-max-bytes*
 </task-memory-total-max-bytes>
 </task-memory-allocator-report>
</task-memory-information>

Description No documentation is available yet.

Contents <task-block-list>—No documentation is available yet.

<task-lite-page-list>—No documentation is available yet.

<task-memory-total-bytes>—No documentation is available yet.

<task-memory-total-max-bytes>—No documentation is available yet.

<task-memory-information>

Usage <rpc-reply>
<task-memory-information>
 <task-memory-in-use-size>task-memory-in-use-size</task-memory-in-use-size>
 <task-memory-in-use-avail>task-memory-in-use-avail</task-memory-in-use-avail>
 <task-memory-max-size>task-memory-max-size</task-memory-max-size>
 <task-memory-max-avail>task-memory-max-avail</task-memory-max-avail>
 <task-memory-max-when>task-memory-max-when</task-memory-max-when>
 <task-memory-free-size>task-memory-free-size</task-memory-free-size>
 <task-memory-overall-report>...</task-memory-overall-report>
 <task-memory-allocator-report>...</task-memory-allocator-report>
 <task-memory-malloc-usage-report>...</task-memory-malloc-usage-report>
 <task-memory-dynamic-allocs>task-memory-dynamic-allocs
 </task-memory-dynamic-allocs>
 <task-memory-max-dynamic-allocs>task-memory-max-dynamic-allocs
 </task-memory-max-dynamic-allocs>
 <task-memory-bss-bytes>task-memory-bss-bytes</task-memory-bss-bytes>
 <task-memory-max-bss-bytes>task-memory-max-bss-bytes
 </task-memory-max-bss-bytes>
 <task-memory-page-data-bytes>task-memory-page-data-bytes
 </task-memory-page-data-bytes>
 <task-memory-max-page-data-bytes>task-memory-max-page-data-bytes
 </task-memory-max-page-data-bytes>
 <task-memory-dir-bytes>task-memory-dir-bytes</task-memory-dir-bytes>
 <task-memory-max-dir-bytes>task-memory-max-dir-bytes
 </task-memory-max-dir-bytes>
 <task-memory-total-bytes-in-use>task-memory-total-bytes-in-use
 </task-memory-total-bytes-in-use>
 <task-memory-total-bytes-percent>task-memory-total-bytes-percent
 </task-memory-total-bytes-percent>
</task-memory-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <task-memory-allocator-report>—No documentation is available yet.
 <task-memory-bss-bytes>—No documentation is available yet.
 <task-memory-dir-bytes>—No documentation is available yet.
 <task-memory-dynamic-allocs>—No documentation is available yet.
 <task-memory-free-size>—No documentation is available yet.
 <task-memory-in-use-avail>—No documentation is available yet.
 <task-memory-in-use-size>—No documentation is available yet.
 <task-memory-malloc-usage-report>—No documentation is available yet.
 <task-memory-max-avail>—No documentation is available yet.
 <task-memory-max-bss-bytes>—No documentation is available yet.

<task-memory-max-dir-bytes>—No documentation is available yet.

<task-memory-max-dynamic-allocs>—No documentation is available yet.

<task-memory-max-page-data-bytes>—No documentation is available yet.

<task-memory-max-size>—No documentation is available yet.

<task-memory-max-when>—No documentation is available yet.

<task-memory-overall-report>—No documentation is available yet.

<task-memory-page-data-bytes>—No documentation is available yet.

<task-memory-total-bytes-in-use>—No documentation is available yet.

<task-memory-total-bytes-percent>—No documentation is available yet.

<task-memory-malloc-usage-report>

Usage <task-memory-information>
 <task-memory-malloc-usage-report>
 <task-malloc-list>...</task-malloc-list>
 <task-memory-total-bytes>*task-memory-total-bytes*</task-memory-total-bytes>
 <task-memory-total-max-bytes>*task-memory-total-max-bytes*
 </task-memory-total-max-bytes>
 </task-memory-malloc-usage-report>
 </task-memory-information>

Description No documentation is available yet.

Contents <task-malloc-list>—No documentation is available yet.
 <task-memory-total-bytes>—No documentation is available yet.
 <task-memory-total-max-bytes>—No documentation is available yet.

<task-memory-overall-report>

Usage <task-memory-information>
 <task-memory-overall-report>
 <task-size-block-list>...</task-size-block-list>
 <task-memory-stats-list>...</task-memory-stats-list>
 <task-memory-total-bytes>*task-memory-total-bytes*</task-memory-total-bytes>
 <task-memory-total-max-bytes>*task-memory-total-max-bytes*
 </task-memory-total-max-bytes>
 <task-memory-total-free-bytes>*task-memory-total-free-bytes*
 </task-memory-total-free-bytes>
 </task-memory-overall-report>
 </task-memory-information>

Description No documentation is available yet.

Contents <task-memory-stats-list>—No documentation is available yet.

<task-memory-total-bytes>—No documentation is available yet.

<task-memory-total-free-bytes>—No documentation is available yet.

<task-memory-total-max-bytes>—No documentation is available yet.

<task-size-block-list>—No documentation is available yet.

<task-memory-stats>

Usage <task-memory-stats-list>
 <task-memory-stats>
 <tms-name>*tms-name*</tms-name>
 <tms-allocs>*tms-allocs*</tms-allocs>
 <tms-mallocs>*tms-mallocs*</tms-mallocs>
 <tms-alloc-bytes>*tms-alloc-bytes*</tms-alloc-bytes>
 <tms-max-allocs>*tms-max-allocs*</tms-max-allocs>
 <tms-max-bytes>*tms-max-bytes*</tms-max-bytes>
 <tms-free-bytes>*tms-free-bytes*</tms-free-bytes>
 </task-memory-stats>
 </task-memory-stats-list>

Description No documentation is available yet.

Contents <tms-alloc-bytes>—Number of bytes now allocated.

<tms-allocs>—Number of items allocated.

<tms-free-bytes>—No documentation is available yet.

<tms-mallocs>—Number of items allocated using malloc.

<tms-max-allocs>—Maximum items ever allocated.

<tms-max-bytes>—Maximum bytes ever allocated.

<tms-name>—No documentation is available yet.

<task-memory-stats-list>

Usage <task-memory-overall-report>
 <task-memory-stats-list>
 <task-memory-stats>...</task-memory-stats>
 </task-memory-stats-list>
 </task-memory-overall-report>

Description No documentation is available yet.

Contents <task-memory-stats>—No documentation is available yet.

<task-replication-state>

Usage <rpc-reply>
 <task-replication-state>
 <task-gres-state>*task-gres-state*</task-gres-state>
 <task-re-mode>*task-re-mode*</task-re-mode>
 <task-protocol-replication-state>*task-protocol-replication-state*
 </task-protocol-replication-state>
 <task-protocol-replication-name>*task-protocol-replication-name*
 </task-protocol-replication-name>
 </task-replication-state>
 </rpc-reply>

Description Current state of task replication.

Contents <task-gres-state>—Current state of graceful Routing Engine Switchover.
 <task-protocol-replication-name>—No documentation is available yet.
 <task-protocol-replication-state>—No documentation is available yet.
 <task-re-mode>—Current mastership state of Routing Engine.

<task-size-block>

Usage <task-size-block-list>
 <task-size-block>
 <tsb-size>*tsb-size*</tsb-size>
 <tsb-terse-transient/>
 <tsb-terse-fullpage/>
 <tsb-allocs>*tsb-allocs*</tsb-allocs>
 <tsb-mallocs>*tsb-mallocs*</tsb-mallocs>
 <tsb-alloc-bytes>*tsb-alloc-bytes*</tsb-alloc-bytes>
 <tsb-max-allocs>*tsb-max-allocs*</tsb-max-allocs>
 <tsb-max-bytes>*tsb-max-bytes*</tsb-max-bytes>
 <tsb-free-bytes>*tsb-free-bytes*</tsb-free-bytes>
 </task-size-block>
 </task-size-block-list>

Description No documentation is available yet.

Contents <tsb-alloc-bytes>—Number of items allocated in bytes.
 <tsb-allocs>—Number of items allocated now not using malloc.
 <tsb-free-bytes>—Number of free bytes.
 <tsb-mallocs>—Number of items allocated using malloc.
 <tsb-max-allocs>—Maximum items ever allocated.
 <tsb-max-bytes>—Maximum items ever allocated in bytes.
 <tsb-size>—Size of this block.
 <tsb-terse-fullpage>—No documentation is available yet.
 <tsb-terse-transient>—No documentation is available yet.

<task-size-block-list>

Usage <task-memory-overall-report>
 <task-size-block-list>
 <task-size-block>...</task-size-block>
 </task-size-block-list>
 </task-memory-overall-report>

Description No documentation is available yet.

Contents <task-size-block>—No documentation is available yet.

<task-timer>

Usage <task>
 <task-timer>
 <timer-name>*timer-name*</timer-name>
 <timer-late/>
 <timer-expires>*timer-expires*</timer-expires>
 <timer-jitter>*timer-jitter*</timer-jitter>
 <timer-interval>*timer-interval*</timer-interval>
 <timer-flags>*timer-flags*</timer-flags>
 </task-timer>
 </task>

Description No documentation is available yet.

Contents <timer-expires>—Time after which timer expires.
 <timer-flags>—No documentation is available yet.
 <timer-interval>—Time to sleep between timer jobs.
 <timer-jitter>—Jitter, in percent.
 <timer-late>—Timer is expired but is still running.
 <timer-name>—Timer name.

<task-timer-information>

Usage <rpc-reply>
 <task-timer-information>
 <task>...</task>
 </task-timer-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <task>—No documentation is available yet.

<te-class-map>

Usage	<pre> <mpls-diffserv-te-information> <te-class-map> <te-class>te-class</te-class> <traffic-class>traffic-class</traffic-class> <te-prio>te-prio</te-prio> </te-class-map> </mpls-diffserv-te-information> </pre>
Description	No documentation is available yet.
Contents	<p><te-class>—TE class.</p> <p><te-prio>—Priority associated with a particular traffic class.</p> <p><traffic-class>—Traffic class.</p>

<te-subtlv>

Usage	<pre> <ospf-opaque-area-lsa> <te-subtlv> <tlv-type-name>tlv-type-name</tlv-type-name> <tlv-type-value>tlv-type-value</tlv-type-value> <tlv-length>tlv-length</tlv-length> <bytes-left>bytes-left</bytes-left> <formatted-tlv-data>formatted-tlv-data</formatted-tlv-data> </te-subtlv> </ospf-opaque-area-lsa> </pre>
Description	No documentation is available yet.
Contents	<p><bytes-left>—No documentation is available yet.</p> <p><formatted-tlv-data>—No documentation is available yet.</p> <p><tlv-length>—No documentation is available yet.</p> <p><tlv-type-name>—No documentation is available yet.</p> <p><tlv-type-value>—No documentation is available yet.</p>

<ted-database>

Usage <ted-database-information>
 <ted-database>
 <ted-database-id>*ted-database-id*</ted-database-id>
 <ted-database-id-overload>*ted-database-id-overload*</ted-database-id-overload>
 <ted-database-type>*ted-database-type*</ted-database-type>
 <ted-database-age>*ted-database-age*</ted-database-age>
 <ted-database-link-in>*ted-database-link-in*</ted-database-link-in>
 <ted-database-link-out>*ted-database-link-out*</ted-database-link-out>
 <ted-database-protocol>*ted-database-protocol*</ted-database-protocol>
 <ted-link>...</ted-link>
 <ted-database-lcl-addr>...</ted-database-lcl-addr>
 </ted-database>
 </ted-database-information>

Description MPLS traffic engineering database.

Contents <ted-database-age>—No documentation is available yet.
 <ted-database-id>—No documentation is available yet.
 <ted-database-id-overload>—No documentation is available yet.
 <ted-database-lcl-addr>—No documentation is available yet.
 <ted-database-link-in>—No documentation is available yet.
 <ted-database-link-out>—No documentation is available yet.
 <ted-database-protocol>—No documentation is available yet.
 <ted-database-type>—No documentation is available yet.
 <ted-link>—No documentation is available yet.

<ted-database-information>

Usage <rpc-reply>
 <ted-database-information>
 <ted-database-summary>...</ted-database-summary>
 <ted-database>...</ted-database>
 </ted-database-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <ted-database>—MPLS traffic engineering database.
 <ted-database-summary>—No documentation is available yet.

<ted-database-lcl-addr>

- Usage** <ted-database>
 <ted-database-lcl-addr>
 <ted-lcl-addr>*ted-lcl-addr*</ted-lcl-addr>
 </ted-database-lcl-addr>
 </ted-database>
- Description** No documentation is available yet.
- Contents** <ted-lcl-addr>—No documentation is available yet.

<ted-database-summary>

- Usage** <ted-database-information>
 <ted-database-summary>
 <ted-database-iso-count>*ted-database-iso-count*</ted-database-iso-count>
 <ted-database-inet-count>*ted-database-inet-count*</ted-database-inet-count>
 </ted-database-summary>
 </ted-database-information>
- Description** No documentation is available yet.
- Contents** <ted-database-inet-count>—No documentation is available yet.
 <ted-database-iso-count>—No documentation is available yet.

<ted-link>

Usage <ted-database | ted-link-information>

```

<ted-link>
  <ted-link-from>ted-link-from</ted-link-from>
  <ted-link-to>ted-link-to</ted-link-to>
  <ted-link-local-address>ted-link-local-address</ted-link-local-address>
  <ted-link-remote-address>ted-link-remote-address</ted-link-remote-address>
  <ted-link-local-ifindex>ted-link-local-ifindex</ted-link-local-ifindex>
  <ted-link-remote-ifindex>ted-link-remote-ifindex</ted-link-remote-ifindex>
  <admin-groups>...</admin-groups>
  <ted-link-metric>ted-link-metric</ted-link-metric>
  <ted-link-link-out>ted-link-link-out</ted-link-link-out>
  <ted-link-static-bandwidth>ted-link-static-bandwidth
    </ted-link-static-bandwidth>
  <ted-link-reservable-bandwidth>ted-link-reservable-bandwidth
    </ted-link-reservable-bandwidth>
  <ted-link-forwarding-adjacency/>
  <ted-link-local-bw0>ted-link-local-bw0</ted-link-local-bw0>
  <ted-link-local-bw1>ted-link-local-bw1</ted-link-local-bw1>
  <ted-link-local-bw2>ted-link-local-bw2</ted-link-local-bw2>
  <ted-link-local-bw3>ted-link-local-bw3</ted-link-local-bw3>
  <ted-link-local-bw4>ted-link-local-bw4</ted-link-local-bw4>
  <ted-link-local-bw5>ted-link-local-bw5</ted-link-local-bw5>
  <ted-link-local-bw6>ted-link-local-bw6</ted-link-local-bw6>
  <ted-link-local-bw7>ted-link-local-bw7</ted-link-local-bw7>
  <ted-link-avail-bw0>ted-link-avail-bw0</ted-link-avail-bw0>
  <ted-link-avail-bw1>ted-link-avail-bw1</ted-link-avail-bw1>
  <ted-link-avail-bw2>ted-link-avail-bw2</ted-link-avail-bw2>
  <ted-link-avail-bw3>ted-link-avail-bw3</ted-link-avail-bw3>
  <ted-link-avail-bw4>ted-link-avail-bw4</ted-link-avail-bw4>
  <ted-link-avail-bw5>ted-link-avail-bw5</ted-link-avail-bw5>
  <ted-link-avail-bw6>ted-link-avail-bw6</ted-link-avail-bw6>
  <ted-link-avail-bw7>ted-link-avail-bw7</ted-link-avail-bw7>
  <ted-link-model>ted-link-model</ted-link-model>
  <ted-link-ct-bw0>ted-link-ct-bw0</ted-link-ct-bw0>
  <ted-link-ct-bw1>ted-link-ct-bw1</ted-link-ct-bw1>
  <ted-link-ct-bw2>ted-link-ct-bw2</ted-link-ct-bw2>
  <ted-link-ct-bw3>ted-link-ct-bw3</ted-link-ct-bw3>
  <ted-link-ct-bw4>ted-link-ct-bw4</ted-link-ct-bw4>
  <ted-link-ct-bw5>ted-link-ct-bw5</ted-link-ct-bw5>
  <ted-link-ct-bw6>ted-link-ct-bw6</ted-link-ct-bw6>
  <ted-link-ct-bw7>ted-link-ct-bw7</ted-link-ct-bw7>
  <switching-capability-descriptor>...</switching-capability-descriptor>
  <ted-link-unreserved-bw-tlv-meaning>ted-link-unreserved-bw-tlv-meaning
    </ted-link-unreserved-bw-tlv-meaning>
  <ted-link-dste-tlv-meaning>ted-link-dste-tlv-meaning
    </ted-link-dste-tlv-meaning>
</ted-link>
</ted-database | ted-link-information>

```

Description No documentation is available yet.

Contents <admin-groups>—No documentation is available yet.

<switching-capability-descriptor>—Switching capability of an interface.

<ted-link-avail-bw0>—No documentation is available yet.

<ted-link-avail-bw1>—No documentation is available yet.

<ted-link-avail-bw2>—No documentation is available yet.

<ted-link-avail-bw3>—No documentation is available yet.

<ted-link-avail-bw4>—No documentation is available yet.

<ted-link-avail-bw5>—No documentation is available yet.

<ted-link-avail-bw6>—No documentation is available yet.

<ted-link-avail-bw7>—No documentation is available yet.

<ted-link-ct-bw0>—No documentation is available yet.

<ted-link-ct-bw1>—No documentation is available yet.

<ted-link-ct-bw2>—No documentation is available yet.

<ted-link-ct-bw3>—No documentation is available yet.

<ted-link-ct-bw4>—No documentation is available yet.

<ted-link-ct-bw5>—No documentation is available yet.

<ted-link-ct-bw6>—No documentation is available yet.

<ted-link-ct-bw7>—No documentation is available yet.

<ted-link-dste-tlv-meaning>—No documentation is available yet.

<ted-link-forwarding-adjacency>—Indicates that the link is a forwarding adjacency.

<ted-link-from>—No documentation is available yet.

<ted-link-link-out>—No documentation is available yet.

<ted-link-local-address>—No documentation is available yet.

<ted-link-local-bw0>—No documentation is available yet.

<ted-link-local-bw1>—No documentation is available yet.

<ted-link-local-bw2>—No documentation is available yet.

<ted-link-local-bw3>—No documentation is available yet.

<ted-link-local-bw4>—No documentation is available yet.

<ted-link-local-bw5>—No documentation is available yet.

<ted-link-local-bw6>—No documentation is available yet.

<ted-link-local-bw7>—No documentation is available yet.

<ted-link-local-ifindex>—Local interface index.

<ted-link-metric>—No documentation is available yet.

<ted-link-model>—No documentation is available yet.

<ted-link-remote-address>—No documentation is available yet.

<ted-link-remote-ifindex>—Remote interface index.

<ted-link-reservable-bandwidth>—No documentation is available yet.

<ted-link-static-bandwidth>—No documentation is available yet.

<ted-link-to>—No documentation is available yet.

<ted-link-unreserved-bw-tlv-meaning>—No documentation is available yet.

<ted-link-information>

Usage <rpc-reply>
 <ted-link-information>
 <ted-link>...</ted-link>
 </ted-link-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <ted-link>—No documentation is available yet.

<ted-protocol>

Usage <ted-protocol-information>
 <ted-protocol>
 <ted-protocol-name>*ted-protocol-name*</ted-protocol-name>
 <ted-protocol-credibility>*ted-protocol-credibility*</ted-protocol-credibility>
 <ted-protocol-self-node>*ted-protocol-self-node*</ted-protocol-self-node>
 </ted-protocol>
 </ted-protocol-information>

Description No documentation is available yet.

Contents <ted-protocol-credibility>—No documentation is available yet.

 <ted-protocol-name>—Protocol that filled in the TED entry.

 <ted-protocol-self-node>—No documentation is available yet.

<ted-protocol-information>

- Usage** <rpc-reply>
 <ted-protocol-information>
 <ted-protocol>...</ted-protocol>
 </ted-protocol-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <ted-protocol>—No documentation is available yet.

<tlv-block>

- Usage** <ospf-opaque-area-lsa>
 <tlv-block>
 <tlv-type-name>*tlv-type-name*</tlv-type-name>
 <tlv-type-value>*tlv-type-value*</tlv-type-value>
 <tlv-length>*tlv-length*</tlv-length>
 <bytes-left>*bytes-left*</bytes-left>
 <formatted-tlv-data>*formatted-tlv-data*</formatted-tlv-data>
 </tlv-block>
 </ospf-opaque-area-lsa>
- Description** No documentation is available yet.
- Contents** <bytes-left>—No documentation is available yet.
- <formatted-tlv-data>—No documentation is available yet.
- <tlv-length>—No documentation is available yet.
- <tlv-type-name>—No documentation is available yet.
- <tlv-type-value>—No documentation is available yet.

<tlv-stragglers>

- Usage** <isis-tlv>
 <tlv-stragglers>
 <bytes-left>*bytes-left*</bytes-left>
 </tlv-stragglers>
 </isis-tlv>
- Description** No documentation is available yet.
- Contents** <bytes-left>—No documentation is available yet.

<totals-information>

Usage <isis-statistics>
 <totals-information>
 <packets-received>*packets-received*</packets-received>
 <packets-sent>*packets-sent*</packets-sent>
 </totals-information>
 </isis-statistics>

Description No documentation is available yet.

Contents <packets-received>—No documentation is available yet.
 <packets-sent>—No documentation is available yet.

<tracing-information>

Usage <nlrri-traffic-stats | bgp-peer | bgp-group | ospf-overview>
 <tracing-information>
 <flags>*flags*</flags>
 <filename>*filename*</filename>
 <filesize>*filesize*</filesize>
 <filelimit>*filelimit*</filelimit>
 </tracing-information>
 </nlri-traffic-stats | bgp-peer | bgp-group | ospf-overview>

Description No documentation is available yet.

Contents <filelimit>—Maximum number of retained trace files.
 <filename>—Name of the trace file.
 <filesize>—Maximum size of the trace file.
 <flags>—Enabled trace flags.

<transmission-status>

Usage <isis-database-entry>
 <transmission-status>
 <transmit-count>*transmit-count*</transmit-count>
 <message>*message*</message>
 <interface-name>*interface-name*</interface-name>
 <transmit-time>*transmit-time*</transmit-time>
 </transmission-status>
 </isis-database-entry>

Description No documentation is available yet.

Contents <interface-name>—No documentation is available yet.
 <message>—No documentation is available yet.
 <transmit-count>—No documentation is available yet.
 <transmit-time>—Time at which this message is queued for transmission.

<tunnel-nexthop>

Usage <dynamic-tunnel>
 <tunnel-nexthop>
 <tunnel-nh-type>*tunnel-nh-type*</tunnel-nh-type>
 <tunnel-nh-src>*tunnel-nh-src*</tunnel-nh-src>
 <via>*via*</via>
 <tunnel-nh-state>*tunnel-nh-state*</tunnel-nh-state>
 <tunnel-nh-reason>*tunnel-nh-reason*</tunnel-nh-reason>
 </tunnel-nexthop>
 </dynamic-tunnel>

Description No documentation is available yet.

Contents <tunnel-nh-reason>—Reason why the tunnel next hop is not up.
 <tunnel-nh-src>—Source address for this tunnel next hop.
 <tunnel-nh-state>—State of the tunnel next hop.
 <tunnel-nh-type>—Type of next hop.
 <via>—Reachable via a local interface.

<unconfigured-peers>

- Usage** <bgp-group>
 <unconfigured-peers>
 <route-filter>...</route-filter>
 </unconfigured-peers>
 </bgp-group>
- Description** Set of address prefixes from which this group allows peering.
- Contents** <route-filter>—Entries in martian table.

<unknown-tlv>

- Usage** <isis-tlv>
 <unknown-tlv>
 <isis-tlv-type>isis-tlv-type</isis-tlv-type>
 <tlv-length>tlv-length</tlv-length>
 </unknown-tlv>
 </isis-tlv>
- Description** No documentation is available yet.
- Contents** <isis-tlv-type>—No documentation is available yet.
 <tlv-length>—No documentation is available yet.

<upstream-group>

- Usage** <pim-source>
 <upstream-group>
 <multicast-group-address>multicast-group-address</multicast-group-address>
 </upstream-group>
 </pim-source>
- Description** No documentation is available yet.
- Contents** <multicast-group-address>—Group address.

<upstream-state-flags>

Usage	<pre> <join-group> <upstream-state-flags> <none/> <local-source/> <local-rp/> <join-to-rp/> <join-to-source/> <prune-to-rp/> <prune-to-source/> </upstream-state-flags> </join-group> </pre>
Description	No documentation is available yet.
Contents	<pre> <join-to-rp>—No documentation is available yet. <join-to-source>—No documentation is available yet. <local-rp>—No documentation is available yet. <local-source>—No documentation is available yet. <none>—No documentation is available yet. <prune-to-rp>—No documentation is available yet. <prune-to-source>—No documentation is available yet. </pre>

<vpls-auto-site-repository>

Usage	<pre> <vpls-auto-site-repository-information> <vpls-auto-site-repository> <route-distinguisher>route-distinguisher</route-distinguisher> <instance-id>instance-id</instance-id> <local-site-id>local-site-id</local-site-id> <auto-site-count>auto-site-count</auto-site-count> <auto-site-repository-state>auto-site-repository-state </auto-site-repository-state> </vpls-auto-site-repository> </vpls-auto-site-repository-information> </pre>
Description	Information about one or more automatic site replication entries.
Contents	<pre> <auto-site-count>—Count of label blocks advertised per site. <auto-site-repository-state>—State of automatic site replication entry. <instance-id>—Routing instance identifier. <local-site-id>—No documentation is available yet. <route-distinguisher>—No documentation is available yet. </pre>

<vpls-auto-site-repository-information>

- Usage** <rpc-reply>
 <vpls-auto-site-repository-information>
 <vpls-auto-site-repository>...</vpls-auto-site-repository>
 </vpls-auto-site-repository-information>
 </rpc-reply>
- Description** Information about automatic site replication repository.
- Contents** <vpls-auto-site-repository>—Information about one or more automatic site replication entries.

<vpls-bgp-label-repository-information>

- Usage** <rpc-reply>
 <vpls-bgp-label-repository-information>
 <vpls-bgp-route-distinguisher-information>...
 </vpls-bgp-route-distinguisher-information>
 </vpls-bgp-label-repository-information>
 </rpc-reply>
- Description** Information about VPLS label replication using BGP signaling.
- Contents** <vpls-bgp-route-distinguisher-information>—Information about one or more VPLS route distinguisher replication entries.

<vpls-bgp-route-distinguisher-information>

- Usage** <vpls-bgp-label-repository-information>
 <vpls-bgp-route-distinguisher-information>
 <route-distinguisher>*route-distinguisher*</route-distinguisher>
 <instance-id>*instance-id*</instance-id>
 <l2vpn-nlri-advertisement>...</l2vpn-nlri-advertisement>
 </vpls-bgp-route-distinguisher-information>
 </vpls-bgp-label-repository-information>
- Description** Information about one or more VPLS route distinguisher replication entries.
- Contents** <instance-id>—Routing instance identifier.
- <l2vpn-nlri-advertisement>—Information about a Layer 2 VPN network layer reachability information replication entry.
- <route-distinguisher>—No documentation is available yet.

<vpls-connection-information>

- Usage** <rpc-reply>
 <vpls-connection-information>
 <instance>...</instance>
 </vpls-connection-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <instance>—No documentation is available yet.

<vpls-dynamic-interface-repository>

- Usage** <vpls-dynamic-interface-repository-information>
 <vpls-dynamic-interface-repository>
 <instance-id>*instance-id*</instance-id>
 <local-site-id>*local-site-id*</local-site-id>
 <remote-site-id>*remote-site-id*</remote-site-id>
 <interface-name>*interface-name*</interface-name>
 <local-interface-index>*local-interface-index*</local-interface-index>
 <vpls-label>*vpls-label*</vpls-label>
 <interface-repository-state>*interface-repository-state*
 </interface-repository-state>
 <mesh-group-id>*mesh-group-id*</mesh-group-id>
 </vpls-dynamic-interface-repository>
 </vpls-dynamic-interface-repository-information>
- Description** Information about one or more dynamic interface replication entries.
- Contents** <instance-id>—Routing instance identifier.
- <interface-name>—No documentation is available yet.
- <interface-repository-state>—State of dynamic interface replication entry.
- <local-interface-index>—SNMP ifIndex of local interface.
- <local-site-id>—No documentation is available yet.
- <mesh-group-id>—Mesh-group Identifier.
- <remote-site-id>—No documentation is available yet.
- <vpls-label>—Label assigned to a dynamic interface.

<vpls-dynamic-interface-repository-information>

Usage <rpc-reply>
 <vpls-dynamic-interface-repository-information>
 <vpls-dynamic-interface-repository>...</vpls-dynamic-interface-repository>
 <vpls-ldp-dynamic-interface-repository-entity>...
 </vpls-ldp-dynamic-interface-repository-entity>
 </vpls-dynamic-interface-repository-information>
 </rpc-reply>

Description Information about the VPLS dynamic interface replication repository.

Contents <vpls-dynamic-interface-repository>—Information about one or more dynamic interface replication entries.

<vpls-ldp-dynamic-interface-repository-entity>—Information about the VPLS dynamic interface using LDP signaling.

<vpls-ldp-dynamic-interface-repository>

Usage <vpls-ldp-dynamic-interface-repository-entity>
 <vpls-ldp-dynamic-interface-repository>
 <vpls-id>*vpls-id*</vpls-id>
 <neighbor-id>*neighbor-id*</neighbor-id>
 <interface-name>*interface-name*</interface-name>
 <vpls-label>*vpls-label*</vpls-label>
 <ifl-repository-state>*ifl-repository-state*</ifl-repository-state>
 <mesh-group-id>*mesh-group-id*</mesh-group-id>
 </vpls-ldp-dynamic-interface-repository>
 </vpls-ldp-dynamic-interface-repository-entity>

Description Information about one or more dynamic interface replication entries.

Contents <ifl-repository-state>—No documentation is available yet.

<interface-name>—No documentation is available yet.

<mesh-group-id>—Mesh-group Identifier.

<neighbor-id>—No documentation is available yet.

<vpls-id>—VPLS instance identifier.

<vpls-label>—Label assigned to a dynamic interface.

<vpls-ldp-dynamic-interface-repository-entity>

- Usage** <vpls-dynamic-interface-repository-information>
 <vpls-ldp-dynamic-interface-repository-entity>
 <instance>...</instance>
 <vpls-ldp-dynamic-interface-repository>...
 </vpls-ldp-dynamic-interface-repository>
 </vpls-ldp-dynamic-interface-repository-entity>
 </vpls-dynamic-interface-repository-information>
- Description** Information about the VPLS dynamic interface using LDP signaling.
- Contents** <instance>—No documentation is available yet.
- <vpls-ldp-dynamic-interface-repository>—Information about one or more dynamic interface replication entries.

<vpls-ldp-label-repository>

- Usage** <vpls-ldp-label-repository-entity>
 <vpls-ldp-label-repository>
 <neighbor-id>*neighbor-id*</neighbor-id>
 <vpls-id>*vpls-id*</vpls-id>
 <vpls-label>*vpls-label*</vpls-label>
 <label-repository-state>*label-repository-state*</label-repository-state>
 </vpls-ldp-label-repository>
 </vpls-ldp-label-repository-entity>
- Description** Information about one or more VPLS label replication entries.
- Contents** <label-repository-state>—State of label replication entry.
- <neighbor-id>—No documentation is available yet.
- <vpls-id>—VPLS instance identifier.
- <vpls-label>—Label assigned to a dynamic interface.

<vpls-ldp-label-repository-entity>

- Usage** <vpls-ldp-label-repository-information>
 <vpls-ldp-label-repository-entity>
 <instance-name>*instance-name*</instance-name>
 <vpls-ldp-label-repository>...</vpls-ldp-label-repository>
 </vpls-ldp-label-repository-entity>
 </vpls-ldp-label-repository-information>
- Description** Information about VPLS label replication using LDP signaling.
- Contents** <instance-name>—No documentation is available yet.
- <vpls-ldp-label-repository>—Information about one or more VPLS label replication entries.

<vpls-ldp-label-repository-information>

Usage	<pre> <rpc-reply> vpls-ldp-label-repository-information <vpls-ldp-label-repository-entity>...</vpls-ldp-label-repository-entity> </rpc-reply> </pre>
Description	Information about VPLS label replication using LDP signaling.
Contents	<vpls-ldp-label-repository-entity>—Information about VPLS label replication using LDP signaling.

<vpls-protocol-state>

Usage	<pre> <instance> vpls-protocol-state <vpls-signaling-protocol-identifier>vpls-signaling-protocol-identifier</vpls-signaling-protocol-identifier> <num-local-interfaces>num-local-interfaces</num-local-interfaces> <num-local-interfaces-up>num-local-interfaces-up</num-local-interfaces-up> <irb-present>irb-present</irb-present> <mesh-group-count>mesh-group-count</mesh-group-count> <mesh-group-up-count>mesh-group-up-count</mesh-group-up-count> <mesh-group-interfaces>...</mesh-group-interfaces> <interface>...</interface> <mesh-group-connection>...</mesh-group-connection> <reference-site>...</reference-site> </instance> </pre>
Description	No documentation is available yet.
Contents	<p><interface>—No documentation is available yet.</p> <p><irb-present>—No documentation is available yet.</p> <p><mesh-group-connection>—Information about all vc-connections of a specific mesh-group.</p> <p><mesh-group-count>—No documentation is available yet.</p> <p><mesh-group-interfaces>—Information about all interfaces associated with a mesh-group.</p> <p><mesh-group-up-count>—No documentation is available yet.</p> <p><num-local-interfaces>—No documentation is available yet.</p> <p><num-local-interfaces-up>—No documentation is available yet.</p> <p><reference-site>—No documentation is available yet.</p> <p><vpls-signaling-protocol-identifier>—No documentation is available yet.</p>

<vpls-rsvp-te-ingress-p2mp-lsp>

Usage <instance>
 <vpls-rsvp-te-ingress-p2mp-lsp>
 <vpls-ingress-p2mp-lsp-name>*vpls-ingress-p2mp-lsp-name*
 </vpls-ingress-p2mp-lsp-name>
 <vpls-rsvp-te-p2mp-flood-nexthop-id>*vpls-rsvp-te-p2mp-flood-nexthop-id*
 </vpls-rsvp-te-p2mp-flood-nexthop-id>
 </vpls-rsvp-te-ingress-p2mp-lsp>
 </instance>

Description No documentation is available yet.

Contents <vpls-ingress-p2mp-lsp-name>—Name of ingress point-to-multipoint LSP.
 <vpls-rsvp-te-p2mp-flood-nexthop-id>—Identifier for VPLS RSVP traffic-engineering ingress flood next hop.

<vpls-rsvp-te-p2mp-lsp-information>

Usage <connection>
 <vpls-rsvp-te-p2mp-lsp-information>
 <vpls-ingress-p2mp-branch-lsp-name>*vpls-ingress-p2mp-branch-lsp-name*
 </vpls-ingress-p2mp-branch-lsp-name>
 <vpls-ingress-p2mp-branch-lsp-state>*vpls-ingress-p2mp-branch-lsp-state*
 </vpls-ingress-p2mp-branch-lsp-state>
 <vpls-egress-p2mp-branch-lsp-name>*vpls-egress-p2mp-branch-lsp-name*
 </vpls-egress-p2mp-branch-lsp-name>
 <vpls-egress-p2mp-branch-lsp-state>*vpls-egress-p2mp-branch-lsp-state*
 </vpls-egress-p2mp-branch-lsp-state>
 </vpls-rsvp-te-p2mp-lsp-information>
 </connection>

Description Information about one or more VPLS RSVP-TE point-to-multipoint LSPs.

Contents <vpls-egress-p2mp-branch-lsp-name>—Name of egress point-to-multipoint branch LSP.
 <vpls-egress-p2mp-branch-lsp-state>—State of egress point-to-multipoint branch LSP.
 <vpls-ingress-p2mp-branch-lsp-name>—Name of ingress point-to-multipoint branch LSP.
 <vpls-ingress-p2mp-branch-lsp-state>—State of ingress point-to-multipoint branch LSP.

<vpls-statistics-information>

Usage <rpc-reply>
 <vpls-statistics-information>
 <instance>...</instance>
 <interface-statistics>...</interface-statistics>
 </vpls-statistics-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <instance>—No documentation is available yet.
 <interface-statistics>—No documentation is available yet.

<vrrp-group>

Usage <ipv6-ra-interface>
 <vrrp-group>
 <vrrp-group-id>vrrp-group-id</vrrp-group-id>
 <vrrp-advertisements-sent>vrrp-advertisements-sent</vrrp-advertisements-sent>
 <vrrp-advertisement-sent-time>vrrp-advertisement-sent-time
 </vrrp-advertisement-sent-time>
 <vrrp-solicits-received>vrrp-solicits-received</vrrp-solicits-received>
 <vrrp-solicit-receive-time>vrrp-solicit-receive-time
 </vrrp-solicit-receive-time>
 <vrrp-advertisements-received>vrrp-advertisements-received
 </vrrp-advertisements-received>
 </vrrp-group>
 </ipv6-ra-interface>

Description No documentation is available yet.

Contents <vrrp-advertisement-sent-time>—How long since the last advertisement was sent.
 <vrrp-advertisements-received>—Number of advertisements received.
 <vrrp-advertisements-sent>—Number of advertisements sent.
 <vrrp-group-id>—Group ID of the configured VRRP group.
 <vrrp-solicit-receive-time>—How long since the last solicitation was sent.
 <vrrp-solicits-received>—Number of router solicitations received.

Summary of RPM Response Tags

This section lists JUNOS XML tags that contain operational information about real-time performance monitoring (RPM). The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-rpm>. To review the DTD for the tags, see “DTD for RPM Response Tags” on page 2023.

<active-servers>

Usage	<pre><rpc-reply> <active-servers> <configured-servers>...</configured-servers> </active-servers> </rpc-reply></pre>
Description	No documentation is available yet.
Contents	<configured-servers>—No documentation is available yet.

<configured-servers>

Usage	<pre><active-servers> <configured-servers> <protocol>protocol</protocol> <port>port</port> <destination-interface>destination-interface</destination-interface> </configured-servers> </active-servers></pre>
Description	No documentation is available yet.
Contents	<p><destination-interface>—Name of output interface for probes.</p> <p><port>—Port.</p> <p><protocol>—Protocol.</p>

<connection>

Usage <twamp-server-information>
 <connection>
 <connection-id>*connection-id*</connection-id>
 <client-address>*client-address*</client-address>
 <client-port>*client-port*</client-port>
 <server-address>*server-address*</server-address>
 <server-port>*server-port*</server-port>
 <session-count>*session-count*</session-count>
 <authentication-mode>*authentication-mode*</authentication-mode>
 </connection>
 </twamp-server-information>

Description Server connection.

Contents <authentication-mode>—Authentication mode.

<client-address>—Client address.

<client-port>—Client port.

<connection-id>—Connection ID.

<server-address>—Server address.

<server-port>—Server port.

<session-count>—Number of sessions.

<history-results>

Usage <rpc-reply>
 <history-results>
 <history-test-results>...</history-test-results>
 </history-results>
 </rpc-reply>

Description No documentation is available yet.

Contents <history-test-results>—No documentation is available yet.

<history-test-results>

Usage <history-results>
 <history-test-results>
 <owner>owner</owner>
 <test-name>test-name</test-name>
 <target-address>target-address</target-address>
 <target-url>target-url</target-url>
 <source-address>source-address</source-address>
 <destination-interface>destination-interface</destination-interface>
 <probe-type>probe-type</probe-type>
 <probe-single-results>...</probe-single-results>
 <probe-test-current-results>...</probe-test-current-results>
 <loss-thresh-total>loss-thresh-total</loss-thresh-total>
 <loss-thresh-succ>loss-thresh-succ</loss-thresh-succ>
 <delay-thresh>delay-thresh</delay-thresh>
 <jitter-thresh>jitter-thresh</jitter-thresh>
 <stddev-thresh>stddev-thresh</stddev-thresh>
 <egress-thresh>egress-thresh</egress-thresh>
 <egress-jitter-thresh>egress-jitter-thresh</egress-jitter-thresh>
 <ingress-thresh>ingress-thresh</ingress-thresh>
 <ingress-jitter-thresh>ingress-jitter-thresh</ingress-jitter-thresh>
 </history-test-results>
 </history-results>

Description No documentation is available yet.

Contents <delay-thresh>—Maximum delay threshold.

<destination-interface>—Name of output interface for probes.

<egress-jitter-thresh>—Maximum egress jitter threshold.

<egress-thresh>—Maximum egress delay threshold.

<ingress-jitter-thresh>—Maximum ingress jitter threshold.

<ingress-thresh>—Maximum ingress delay threshold.

<jitter-thresh>—Maximum jitter threshold.

<loss-thresh-succ>—Maximum number of successive lost probes.

<loss-thresh-total>—Maximum number of all lost probes.

<owner>—Test owner name.

<probe-single-results>—No documentation is available yet.

<probe-test-current-results>—No documentation is available yet.

<probe-type>—Name of the probe.

<source-address>—Source address of test.

<stddev-thresh>—Maximum standard deviation threshold.

<target-address>—Target address of test.

<target-url>—Target URL of test.

<test-name>—Name of test.

<packet-statistics>

Usage <session | server-statistics>
<packet-statistics>
 <request-sessions-received>*request-sessions-received*
 </request-sessions-received>
 <accept-sessions-sent>*accept-sessions-sent*</accept-sessions-sent>
 <start-sessions-received>*start-sessions-received*</start-sessions-received>
 <stop-sessions-received>*stop-sessions-received*</stop-sessions-received>
 <test-packets-received>*test-packets-received*</test-packets-received>
 <test-packets-reflected>*test-packets-reflected*</test-packets-reflected>
 <last-sequence-number-received>*last-sequence-number-received*
 </last-sequence-number-received>
 <last-sequence-number-sent>*last-sequence-number-sent*
 </last-sequence-number-sent>
 <test-packets-dropped>*test-packets-dropped*</test-packets-dropped>
 <test-packets-dropped-details>...</test-packets-dropped-details>
</packet-statistics>
 </session | server-statistics>

Description Test session packet statistics.

Contents <accept-sessions-sent>—Accept sessions sent.

<last-sequence-number-received>—Last sequence number received.

<last-sequence-number-sent>—Last sequence number sent.

<request-sessions-received>—Request sessions received.

<start-sessions-received>—Start sessions received.

<stop-sessions-received>—Stop sessions received.

<test-packets-dropped>—Test packets dropped.

<test-packets-dropped-details>—Test packets dropped details.

<test-packets-received>—Test packets received.

<test-packets-reflected>—Test packets reflected.

<probe-last-test-info>

- Usage** <probe-test-generic-results>
 <probe-last-test-info>
 <last-test-time>*last-test-time*</last-test-time>
 </probe-last-test-info>
 </probe-test-generic-results>
- Description** No documentation is available yet.
- Contents** <last-test-time>—Time at which last test was completed.

<probe-last-test-results>

- Usage** <probe-test-results>
 <probe-last-test-results>
 <probe-test-generic-results>...</probe-test-generic-results>
 </probe-last-test-results>
 </probe-test-results>
- Description** No documentation is available yet.
- Contents** <probe-test-generic-results>—No documentation is available yet.

<probe-results>

- Usage** <rpc-reply>
 <probe-results>
 <probe-test-results>...</probe-test-results>
 </probe-results>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <probe-test-results>—No documentation is available yet.

<probe-single-results>

Usage <probe-test-results | history-test-results>
<probe-single-results>
 <owner>owner</owner>
 <test-name>test-name</test-name>
 <probe-time>probe-time</probe-time>
 <probe-status>probe-status</probe-status>
 <hardware-timestamp-status>hardware-timestamp-status</hardware-timestamp-status>
 <rtt>rtt</rtt>
 <ingress>ingress</ingress>
 <egress>egress</egress>
 <egress-jitter>egress-jitter</egress-jitter>
 <ingress-jitter>ingress-jitter</ingress-jitter>
 <round-trip-jitter>round-trip-jitter</round-trip-jitter>
 <egress-interarrival-jitter>egress-interarrival-jitter</egress-interarrival-jitter>
 <ingress-interarrival-jitter>ingress-interarrival-jitter</ingress-interarrival-jitter>
 <round-trip-interarrival-jitter>round-trip-interarrival-jitter</round-trip-interarrival-jitter>
</probe-single-results>
 </probe-test-results | history-test-results>

Description No documentation is available yet.

Contents <egress>—Egress trip time of probes.
 <egress-interarrival-jitter>—Egress interarrival jitter of probes.
 <egress-jitter>—Egress jitter of probes.
 <hardware-timestamp-status>—Use of hardware timestamps in probes.
 <ingress>—Ingress trip time of probes.
 <ingress-interarrival-jitter>—Ingress interarrival jitter of probes.
 <ingress-jitter>—Ingress jitter of probes.
 <owner>—Test owner name.
 <probe-status>—Operation response status from probes.
 <probe-time>—Time at which probe response was received or timed out.
 <round-trip-interarrival-jitter>—Round trip interarrival jitter of probes.
 <round-trip-jitter>—Round trip jitter of probes.
 <rtt>—Round trip time of probes.
 <test-name>—Name of test.

<probe-summary-results>

Usage <probe-test-rtt | probe-test-egress | probe-test-ingress | probe-test-positive-egress-jitter | probe-test-negative-egress-jitter | probe-test-positive-ingress-jitter | probe-test-negative-ingress-jitter | probe-test-positive-round-trip-jitter | probe-test-negative-round-trip-jitter>

<probe-summary-results>

<probe-results-type>*probe-results-type*</probe-results-type>

<min-delay>*min-delay*</min-delay>

<max-delay>*max-delay*</max-delay>

<avg-delay>*avg-delay*</avg-delay>

<jitter-delay>*jitter-delay*</jitter-delay>

<stddev-delay>*stddev-delay*</stddev-delay>

<sum-delay>*sum-delay*</sum-delay>

<samples>*samples*</samples>

</probe-summary-results>

</probe-test-rtt | probe-test-egress | probe-test-ingress | probe-test-positive-egress-jitter | probe-test-negative-egress-jitter | probe-test-positive-ingress-jitter | probe-test-negative-ingress-jitter | probe-test-positive-round-trip-jitter | probe-test-negative-round-trip-jitter>

Description No documentation is available yet.

Contents <avg-delay>—Average delay time.

<jitter-delay>—Difference between maximum and minimum delay times.

<max-delay>—Maximum delay time.

<min-delay>—Minimum delay time.

<probe-results-type>—Results type.

<samples>—Number of samples.

<stddev-delay>—Standard deviation of delay time.

<sum-delay>—Sum of delay times.

<probe-test-current-results>

Usage <probe-test-results | history-test-results>

<probe-test-current-results>

<probe-test-generic-results>...</probe-test-generic-results>

</probe-test-current-results>

</probe-test-results | history-test-results>

Description No documentation is available yet.

Contents <probe-test-generic-results>—No documentation is available yet.

<probe-test-egress>

Usage <probe-test-generic-results>
 <probe-test-egress>
 <probe-summary-results>...</probe-summary-results>
 </probe-test-egress>
 </probe-test-generic-results>

Description No documentation is available yet.

Contents <probe-summary-results>—No documentation is available yet.

<probe-test-generic-results>

Usage <probe-test-current-results | probe-last-test-results | probe-test-moving-results | probe-test-global-results>

```

<probe-test-generic-results>
  <probes-sent>probes-sent</probes-sent>
  <probe-responses>probe-responses</probe-responses>
  <loss-percentage>loss-percentage</loss-percentage>
  <results-scope>results-scope</results-scope>
  <probe-last-test-info>...</probe-last-test-info>
  <probe-test-rtt>...</probe-test-rtt>
  <probe-test-egress>...</probe-test-egress>
  <probe-test-ingress>...</probe-test-ingress>
  <probe-test-positive-egress-jitter>...</probe-test-positive-egress-jitter>
  <probe-test-negative-egress-jitter>...</probe-test-negative-egress-jitter>
  <probe-test-positive-ingress-jitter>...</probe-test-positive-ingress-jitter>
  <probe-test-negative-ingress-jitter>...</probe-test-negative-ingress-jitter>
  <probe-test-positive-round-trip-jitter>...
    </probe-test-positive-round-trip-jitter>
  <probe-test-negative-round-trip-jitter>...
    </probe-test-negative-round-trip-jitter>
</probe-test-generic-results>
</probe-test-current-results | probe-last-test-results | probe-test-moving-results |
probe-test-global-results>

```

Description No documentation is available yet.

Contents <loss-percentage>—Percentage of probes lost (no response).

<probe-last-test-info>—No documentation is available yet.

<probe-responses>—Responses from probes.

<probe-test-egress>—No documentation is available yet.

<probe-test-ingress>—No documentation is available yet.

<probe-test-negative-egress-jitter>—No documentation is available yet.

<probe-test-negative-ingress-jitter>—No documentation is available yet.

<probe-test-negative-round-trip-jitter>—No documentation is available yet.

<probe-test-positive-egress-jitter>—No documentation is available yet.

<probe-test-positive-ingress-jitter>—No documentation is available yet.

<probe-test-positive-round-trip-jitter>—No documentation is available yet.

<probe-test-rtt>—No documentation is available yet.

<probes-sent>—Number of probes sent.

<results-scope>—Scope of results.

<probe-test-global-results>

Usage <probe-test-results>
 <probe-test-global-results>
 <probe-test-generic-results>...</probe-test-generic-results>
 </probe-test-global-results>
 </probe-test-results>

Description No documentation is available yet.

Contents <probe-test-generic-results>—No documentation is available yet.

<probe-test-ingress>

Usage <probe-test-generic-results>
 <probe-test-ingress>
 <probe-summary-results>...</probe-summary-results>
 </probe-test-ingress>
 </probe-test-generic-results>

Description No documentation is available yet.

Contents <probe-summary-results>—No documentation is available yet.

<probe-test-moving-results>

Usage <probe-test-results>
 <probe-test-moving-results>
 <probe-test-generic-results>...</probe-test-generic-results>
 </probe-test-moving-results>
 </probe-test-results>

Description No documentation is available yet.

Contents <probe-test-generic-results>—No documentation is available yet.

<probe-test-negative-egress-jitter>

Usage <probe-test-generic-results>
 <probe-test-negative-egress-jitter>
 <probe-summary-results>...</probe-summary-results>
 </probe-test-negative-egress-jitter>
 </probe-test-generic-results>

Description No documentation is available yet.

Contents <probe-summary-results>—No documentation is available yet.

<probe-test-negative-ingress-jitter>

- Usage** <probe-test-generic-results>
 <probe-test-negative-ingress-jitter>
 <probe-summary-results>...</probe-summary-results>
 </probe-test-negative-ingress-jitter>
 </probe-test-generic-results>
- Description** No documentation is available yet.
- Contents** <probe-summary-results>—No documentation is available yet.

<probe-test-negative-round-trip-jitter>

- Usage** <probe-test-generic-results>
 <probe-test-negative-round-trip-jitter>
 <probe-summary-results>...</probe-summary-results>
 </probe-test-negative-round-trip-jitter>
 </probe-test-generic-results>
- Description** No documentation is available yet.
- Contents** <probe-summary-results>—No documentation is available yet.

<probe-test-positive-egress-jitter>

- Usage** <probe-test-generic-results>
 <probe-test-positive-egress-jitter>
 <probe-summary-results>...</probe-summary-results>
 </probe-test-positive-egress-jitter>
 </probe-test-generic-results>
- Description** No documentation is available yet.
- Contents** <probe-summary-results>—No documentation is available yet.

<probe-test-positive-ingress-jitter>

- Usage** <probe-test-generic-results>
 <probe-test-positive-ingress-jitter>
 <probe-summary-results>...</probe-summary-results>
 </probe-test-positive-ingress-jitter>
 </probe-test-generic-results>
- Description** No documentation is available yet.
- Contents** <probe-summary-results>—No documentation is available yet.

<probe-test-positive-round-trip-jitter>

Usage <probe-test-generic-results>
 <probe-test-positive-round-trip-jitter>
 <probe-summary-results>...</probe-summary-results>
 </probe-test-positive-round-trip-jitter>
 </probe-test-generic-results>

Description No documentation is available yet.

Contents <probe-summary-results>—No documentation is available yet.

<probe-test-results>

Usage <probe-results>
 <probe-test-results>
 <owner>owner</owner>
 <test-name>test-name</test-name>
 <target-address>target-address</target-address>
 <target-url>target-url</target-url>
 <source-address>source-address</source-address>
 <destination-interface>destination-interface</destination-interface>
 <probe-type>probe-type</probe-type>
 <test-size>test-size</test-size>
 <routing-instance-name>routing-instance-name</routing-instance-name>
 <loss-thresh-total>loss-thresh-total</loss-thresh-total>
 <loss-thresh-succ>loss-thresh-succ</loss-thresh-succ>
 <delay-thresh>delay-thresh</delay-thresh>
 <jitter-thresh>jitter-thresh</jitter-thresh>
 <stddev-thresh>stddev-thresh</stddev-thresh>
 <egress-thresh>egress-thresh</egress-thresh>
 <egress-jitter-thresh>egress-jitter-thresh</egress-jitter-thresh>
 <egress-stddev-thresh>egress-stddev-thresh</egress-stddev-thresh>
 <ingress-thresh>ingress-thresh</ingress-thresh>
 <ingress-jitter-thresh>ingress-jitter-thresh</ingress-jitter-thresh>
 <ingress-stddev-thresh>ingress-stddev-thresh</ingress-stddev-thresh>
 <probe-single-results>...</probe-single-results>
 <probe-test-current-results>...</probe-test-current-results>
 <probe-last-test-results>...</probe-last-test-results>
 <probe-test-moving-results>...</probe-test-moving-results>
 <probe-test-global-results>...</probe-test-global-results>
 </probe-test-results>
 </probe-results>

Description No documentation is available yet.

Contents <delay-thresh>—Maximum delay threshold.
 <destination-interface>—Name of output interface for probes.
 <egress-jitter-thresh>—Maximum egress jitter threshold.
 <egress-stddev-thresh>—Maximum egress standard deviation threshold.
 <egress-thresh>—Maximum egress delay threshold.
 <ingress-jitter-thresh>—Maximum ingress jitter threshold.
 <ingress-stddev-thresh>—Maximum ingress standard deviation threshold.
 <ingress-thresh>—Maximum ingress delay threshold.
 <jitter-thresh>—Maximum jitter threshold.
 <loss-thresh-succ>—Maximum number of successive lost probes.
 <loss-thresh-total>—Maximum number of all lost probes.

<owner>—Test owner name.

<probe-last-test-results>—No documentation is available yet.

<probe-single-results>—No documentation is available yet.

<probe-test-current-results>—No documentation is available yet.

<probe-test-global-results>—No documentation is available yet.

<probe-test-moving-results>—No documentation is available yet.

<probe-type>—Name of the probe.

<routing-instance-name>—Routing Instance Name.

<source-address>—Source address of test.

<stddev-thresh>—Maximum standard deviation threshold.

<target-address>—Target address of test.

<target-url>—Target URL of test.

<test-name>—Name of test.

<test-size>—Number of probes in test.

<probe-test-rtt>

Usage <probe-test-generic-results>
 <probe-test-rtt>
 <probe-summary-results>...</probe-summary-results>
 </probe-test-rtt>
 </probe-test-generic-results>

Description No documentation is available yet.

Contents <probe-summary-results>—No documentation is available yet.

<server>

Usage <twamp-server-information>
 <server>
 <session>...</session>
 </server>
 </twamp-server-information>

Description Server information.

Contents <session>—Server session.

<server-statistics>

- Usage** <twamp-server-information>
 <server-statistics>
 <packet-statistics>...</packet-statistics>
 </server-statistics>
</twamp-server-information>
- Description** Server statistics.
- Contents** <packet-statistics>—Test session packet statistics.

<session>

Usage <server>
 <session>
 <session-id>*session-id*</session-id>
 <connection-id>*connection-id*</connection-id>
 <sender-address>*sender-address*</sender-address>
 <sender-port>*sender-port*</sender-port>
 <reflector-address>*reflector-address*</reflector-address>
 <reflector-port>*reflector-port*</reflector-port>
 <session-state>*session-state*</session-state>
 <authentication-mode>*authentication-mode*</authentication-mode>
 <ip-version>*ip-version*</ip-version>
 <padding-length>*padding-length*</padding-length>
 <start-time>*start-time*</start-time>
 <timeout>*timeout*</timeout>
 <packet-statistics>...</packet-statistics>
 </session>
 </server>

Description Server session.

Contents <authentication-mode>—Authentication mode.
 <connection-id>—Connection ID.
 <ip-version>—IP version.
 <packet-statistics>—Test session packet statistics.
 <padding-length>—Padding length.
 <reflector-address>—Reflector address.
 <reflector-port>—Reflector port.
 <sender-address>—Sender address.
 <sender-port>—Sender port.
 <session-id>—Session ID.
 <session-state>—Session state.
 <start-time>—Starting time.
 <timeout>—Timeout.

<test-packets-dropped-details>

Usage	<pre> <packet-statistics> <test-packets-dropped-details> <session-nonexist>session-nonexist</session-nonexist> <session-notactive>session-notactive</session-notactive> <packet-unsupported>packet-unsupported</packet-unsupported> <packet-malformed>packet-malformed</packet-malformed> <internal-error>internal-error</internal-error> </test-packets-dropped-details> </packet-statistics> </pre>
Description	Test packets dropped details.
Contents	<pre> <internal-error>—Internal error. <packet-malformed>—Packet malformed. <packet-unsupported>—Packet unsupported. <session-nonexist>—Test packets dropped because session does not exist. <session-notactive>—Test packets dropped because session is not active. </pre>

<twamp-server-information>

Usage	<pre> <rpc-reply> <twamp-server-information> <connection>...</connection> <server>...</server> <server-statistics>...</server-statistics> </twamp-server-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<pre> <connection>—Server connection. <server>—Server information. <server-statistics>—Server statistics. </pre>

Summary of SDX Response Tags

This section lists JUNOS XML tags that contain operational information about the Service Deployment System (SDX) for the JUNOS software. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-sdx>. To review the DTD for the tags, see “DTD for SDX Response Tags” on page 2029.

<connection-status>

Usage <sdx-information>
 <connection-status>
 <state>state</state>
 <address>address</address>
 <port>port</port>
 <date-time>date-time</date-time>
 </connection-status>
 </sdx-information>

Description Status of the connection to SDX.

Contents <address>—No documentation is available yet.
 <date-time>—No documentation is available yet.
 <port>—No documentation is available yet.
 <state>—No documentation is available yet.

<keepalive-information>

Usage <sdx-information>
 <keepalive-information>
 <interval>interval</interval>
 <keepalive-count>keepalive-count</keepalive-count>
 <elapsed-time>elapsed-time</elapsed-time>
 </keepalive-information>
 </sdx-information>

Description Keepalive settings and statistics.

Contents <elapsed-time>—No documentation is available yet.
 <interval>—Interval.
 <keepalive-count>—Number of keepalives sent since process start.

<notification-information>

Usage	<pre> <sdx-information> <notification-information> <notification-count><i>notification-count</i></notification-count> <elapsed-time><i>elapsed-time</i></elapsed-time> </notification-information> </sdx-information> </pre>
Description	Notification statistics.
Contents	<p><elapsed-time>—No documentation is available yet.</p> <p><notification-count>—Number of notifications sent since process started.</p>

<peer-information>

Usage	<pre> <sdx-information> <peer-information> <elapsed-time><i>elapsed-time</i></elapsed-time> </peer-information> </sdx-information> </pre>
Description	Peer statistics.
Contents	<elapsed-time>—No documentation is available yet.

<sdx-information>

Usage	<pre> <rpc-reply> <sdx-information> <unconfigured/> <connection-status>...</connection-status> <keepalive-information>...</keepalive-information> <notification-information>...</notification-information> <peer-information>...</peer-information> </sdx-information> </rpc-reply> </pre>
Description	Information about service deployment application.
Contents	<p><connection-status>—Status of the connection to SDX.</p> <p><keepalive-information>—Keepalive settings and statistics.</p> <p><notification-information>—Notification statistics.</p> <p><peer-information>—Peer statistics.</p> <p><unconfigured>—SDX daemon is not configured.</p>

Summary of Services Accounting Response Tags

This section lists JUNOS XML tags that contain operational information about services accounting records. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-services-accounting>. To review the DTD for the tags, see “DTD for Services Accounting Response Tags” on page 2031.

<detail-entry>

Usage <flow-detail | flow-aggregate-template-detail-ipv4 | flow-aggregate-template-detail-mpls | flow-aggregate-template-detail-mpls-ipv4 | flow-aggregate-as-detail | flow-aggregate-protocol-port-detail | flow-aggregate-source-prefix-detail | flow-aggregate-destination-prefix-detail | flow-aggregate-source-destination-prefix-detail>

<detail-entry>

```
<tos>tos</tos>
<protocol>protocol</protocol>
<tcp-flags>tcp-flags</tcp-flags>
<source-address>source-address</source-address>
<source-prefix-length>source-prefix-length</source-prefix-length>
<destination-address>destination-address</destination-address>
<destination-prefix-length>destination-prefix-length
</destination-prefix-length>
<source-port>source-port</source-port>
<destination-port>destination-port</destination-port>
<input-snmp-interface-index>input-snmp-interface-index
</input-snmp-interface-index>
<output-snmp-interface-index>output-snmp-interface-index
</output-snmp-interface-index>
<input-interface-name>input-interface-name</input-interface-name>
<output-interface-name>output-interface-name</output-interface-name>
<source-as>source-as</source-as>
<destination-as>destination-as</destination-as>
<start-time>start-time</start-time>
<end-time>end-time</end-time>
<packet-count>packet-count</packet-count>
<byte-count>byte-count</byte-count>
<last-active-timeout>...</last-active-timeout>
<source-mask>source-mask</source-mask>
<destination-mask>destination-mask</destination-mask>
<icmp-type>icmp-type</icmp-type>
<mpls-label-1>mpls-label-1</mpls-label-1>
<mpls-label-2>mpls-label-2</mpls-label-2>
<mpls-label-3>mpls-label-3</mpls-label-3>
<flow-count>flow-count</flow-count>
```

</detail-entry>

```
</flow-detail | flow-aggregate-template-detail-ipv4 | flow-aggregate-template-detail-mpls
| flow-aggregate-template-detail-mpls-ipv4 | flow-aggregate-as-detail |
flow-aggregate-protocol-port-detail | flow-aggregate-source-prefix-detail |
flow-aggregate-destination-prefix-detail | flow-aggregate-source-destination-prefix-detail>
```

Description Detail entry.

Contents <byte-count>—Number of bytes in the flow.

<destination-address>—Destination address of flow.

<destination-as>—Destination autonomous system number.

<destination-mask>—Destination mask.

<destination-port>—Destination port.

<destination-prefix-length>—Destination prefix length.

<end-time>—System uptime at end of flow.

<flow-count>—Number of flows in the aggregate.

<icmp-type>—ICMP type.

<input-interface-name>—Input interface name.

<input-snmp-interface-index>—Input SNMP interface index.

<last-active-timeout>—Last active timeout data.

<mpls-label-1>—MPLS label 1.

<mpls-label-2>—MPLS label 2.

<mpls-label-3>—MPLS label 3.

<output-interface-name>—Output interface name.

<output-snmp-interface-index>—Output SNMP interface index.

<packet-count>—Number of packets in the flow.

<protocol>—Protocol.

<source-address>—Source address of flow.

<source-as>—Source autonomous system number.

<source-mask>—Source mask.

<source-port>—Source port.

<source-prefix-length>—Source prefix length.

<start-time>—System uptime at start of flow.

<tcp-flags>—TCP flags.

<tos>—Type of service.

<error-information>

Usage	<pre> <services-accounting-information> <error-information> <error-packets-dropped-no-memory>error-packets-dropped-no-memory </error-packets-dropped-no-memory> <error-packets-dropped-not-ip>error-packets-dropped-not-ip </error-packets-dropped-not-ip> <error-packets-dropped-not-ipv4>error-packets-dropped-not-ipv4 </error-packets-dropped-not-ipv4> <error-packets-too-small>error-packets-too-small</error-packets-too-small> <error-allocation-failures>error-allocation-failures </error-allocation-failures> <error-free-failures>error-free-failures</error-free-failures> <error-free-list-failures>error-free-list-failures</error-free-list-failures> <error-memory-warning>error-memory-warning</error-memory-warning> <error-memory-overload>error-memory-overload</error-memory-overload> <error-packets-per-second-overload>error-packets-per-second-overload </error-packets-per-second-overload> <error-bytes-per-second-overload>error-bytes-per-second-overload </error-bytes-per-second-overload> </error-information> </services-accounting-information> </pre>
Description	Service accounting error information.
Contents	<p><error-allocation-failures>—Number of failed attempts to allocate memory.</p> <p><error-bytes-per-second-overload>—Whether the number of incoming bytes exceeds the designed per-second limit.</p> <p><error-free-failures>—Number of failed attempts to free memory.</p> <p><error-free-list-failures>—Number of operations that failed because free list memory is exhausted.</p> <p><error-memory-overload>—Whether memory is exhausted.</p> <p><error-memory-warning>—Reached low memory condition.</p> <p><error-packets-dropped-no-memory>—Number of packets dropped because memory is exhausted.</p> <p><error-packets-dropped-not-ip>—Number of packets dropped because they are not IP.</p> <p><error-packets-dropped-not-ipv4>—Number of packets dropped because they are not IPv4.</p> <p><error-packets-per-second-overload>—Whether the number of incoming packets exceeds the designed per-second limit.</p> <p><error-packets-too-small>—Number of packets dropped because their header is too small.</p>

<flow-aggregate-as-detail>

Usage <services-accounting-information>
 <flow-aggregate-as-detail>
 <detail-entry>...</detail-entry>
 </flow-aggregate-as-detail>
 </services-accounting-information>

Description Service accounting AS flow aggregate record detail.

Contents <detail-entry>—Detail entry.

<flow-aggregate-destination-prefix-detail>

Usage <services-accounting-information>
 <flow-aggregate-destination-prefix-detail>
 <detail-entry>...</detail-entry>
 </flow-aggregate-destination-prefix-detail>
 </services-accounting-information>

Description Service accounting destination prefix aggregate record detail.

Contents <detail-entry>—Detail entry.

<flow-aggregate-protocol-port-detail>

Usage <services-accounting-information>
 <flow-aggregate-protocol-port-detail>
 <detail-entry>...</detail-entry>
 </flow-aggregate-protocol-port-detail>
 </services-accounting-information>

Description Service accounting protocol-port aggregate record detail.

Contents <detail-entry>—Detail entry.

<flow-aggregate-source-destination-prefix-detail>

Usage <services-accounting-information>
 <flow-aggregate-source-destination-prefix-detail>
 <detail-entry>...</detail-entry>
 </flow-aggregate-source-destination-prefix-detail>
 </services-accounting-information>

Description Service accounting source-destination prefix aggregate record detail.

Contents <detail-entry>—Detail entry.

<flow-aggregate-source-prefix-detail>

- Usage** <services-accounting-information>
 <flow-aggregate-source-prefix-detail>
 <detail-entry>...</detail-entry>
 </flow-aggregate-source-prefix-detail>
 </services-accounting-information>
- Description** Service accounting source prefix aggregate record detail.
- Contents** <detail-entry>—Detail entry.

<flow-aggregate-template-detail>

- Usage** <services-accounting-information>
 <flow-aggregate-template-detail>
 <flow-aggregate-template-detail-ipv4>...</flow-aggregate-template-detail-ipv4>
 <flow-aggregate-template-detail-mpls>...</flow-aggregate-template-detail-mpls>
 <flow-aggregate-template-detail-mpls-ipv4>...
 </flow-aggregate-template-detail-mpls-ipv4>
 </flow-aggregate-template-detail>
 </services-accounting-information>
- Description** Service accounting template aggregate record detail.
- Contents** <flow-aggregate-template-detail-ipv4>—No documentation is available yet.
 <flow-aggregate-template-detail-mpls>—No documentation is available yet.
 <flow-aggregate-template-detail-mpls-ipv4>—No documentation is available yet.

<flow-aggregate-template-detail-ipv4>

- Usage** <flow-aggregate-template-detail>
 <flow-aggregate-template-detail-ipv4>
 <detail-entry>...</detail-entry>
 </flow-aggregate-template-detail-ipv4>
 </flow-aggregate-template-detail>
- Description** No documentation is available yet.
- Contents** <detail-entry>—Detail entry.

<flow-aggregate-template-detail-mpls>

- Usage** <flow-aggregate-template-detail>
 <flow-aggregate-template-detail-mpls>
 <detail-entry>...</detail-entry>
 </flow-aggregate-template-detail-mpls>
 </flow-aggregate-template-detail>
- Description** No documentation is available yet.
- Contents** <detail-entry>—Detail entry.

<flow-aggregate-template-detail-mpls-ipv4>

- Usage** <flow-aggregate-template-detail>
 <flow-aggregate-template-detail-mpls-ipv4>
 <detail-entry>...</detail-entry>
 </flow-aggregate-template-detail-mpls-ipv4>
 </flow-aggregate-template-detail>
- Description** No documentation is available yet.
- Contents** <detail-entry>—Detail entry.

<flow-detail>

- Usage** <services-accounting-information>
 <flow-detail>
 <detail-entry>...</detail-entry>
 </flow-detail>
 </services-accounting-information>
- Description** Service accounting flow record detail.
- Contents** <detail-entry>—Detail entry.

<flow-information>

Usage <services-accounting-information>
 <flow-information>
 <flow-packets>*flow-packets*</flow-packets>
 <flow-bytes>*flow-bytes*</flow-bytes>
 <flow-packets-ten-second-rate>*flow-packets-ten-second-rate*
 </flow-packets-ten-second-rate>
 <flow-bytes-ten-second-rate>*flow-bytes-ten-second-rate*
 </flow-bytes-ten-second-rate>
 <active-flows>*active-flows*</active-flows>
 <flows>*flows*</flows>
 <flows-exported>*flows-exported*</flows-exported>
 <flow-packets-exported>*flow-packets-exported*</flow-packets-exported>
 <flows-expired>*flows-expired*</flows-expired>
 <flows-aged>*flows-aged*</flows-aged>
 </flow-information>
 </services-accounting-information>

Description Service accounting flow information.

Contents <active-flows>—Active flows.

<flow-bytes>—Flow bytes.

<flow-bytes-ten-second-rate>—Flow bytes 10-second rate.

<flow-packets>—Flow packets.

<flow-packets-exported>—Flows packets exported.

<flow-packets-ten-second-rate>—Flow packets 10-second rate.

<flows>—Flows.

<flows-aged>—Flows active timed out.

<flows-expired>—Flows inactive timed out.

<flows-exported>—Flows exported.

<last-active-timeout>

Usage <detail-entry>
 <last-active-timeout>
 <time-delta>*time-delta*</time-delta>
 <last-packet-count>*last-packet-count*</last-packet-count>
 <last-byte-count>*last-byte-count*</last-byte-count>
 </last-active-timeout>
 </detail-entry>

Description Last active timeout data.

Contents <last-byte-count>—Bytes exported in last active timeout.
 <last-packet-count>—Packets exported in last active timeout.
 <time-delta>—Time since last active timeout.

<memory-information>

Usage <services-accounting-information>
 <memory-information>
 <allocation-count>*allocation-count*</allocation-count>
 <free-count>*free-count*</free-count>
 <maximum-allocated>*maximum-allocated*</maximum-allocated>
 <allocations-per-second>*allocations-per-second*</allocations-per-second>
 <frees-per-second>*frees-per-second*</frees-per-second>
 <memory-used>*memory-used*</memory-used>
 <memory-free>*memory-free*</memory-free>
 <v9-memory-used>*v9-memory-used*</v9-memory-used>
 </memory-information>
 </services-accounting-information>

Description Service accounting memory utilization.

Contents <allocation-count>—Flow record allocations.
 <allocations-per-second>—Flow record allocations per second.
 <free-count>—Flow record frees.
 <frees-per-second>—Flow record frees per second.
 <maximum-allocated>—Maximum flow records allocated.
 <memory-free>—Total memory free.
 <memory-used>—Total memory used.
 <v9-memory-used>—Memory used by v9.

<packet-distribution-information>

Usage <services-accounting-information>
 <packet-distribution-information>
 <packet-size-range-start>*packet-size-range-start*</packet-size-range-start>
 <packet-size-range-end>*packet-size-range-end*</packet-size-range-end>
 <range-number-packets>*range-number-packets*</range-number-packets>
 <range-percentage-packets>*range-percentage-packets*</range-percentage-packets>
 </packet-distribution-information>
 </services-accounting-information>

Description Service accounting packet distribution information.

Contents <packet-size-range-end>—End of packet size range.
 <packet-size-range-start>—Start of packet size range.
 <range-number-packets>—Number of packets in range.
 <range-percentage-packets>—Percentage of packets in range.

<services-accounting-information>

Usage <rpc-reply>
 <services-accounting-information>
 <service-name>*service-name*</service-name>
 <interface-name>*interface-name*</interface-name>
 <pic-status>*pic-status*</pic-status>
 <local-index>*local-index*</local-index>
 <usage-information>...</usage-information>
 <memory-information>...</memory-information>
 <flow-information>...</flow-information>
 <packet-distribution-information>...</packet-distribution-information>
 <error-information>...</error-information>
 <v9-error-information>...</v9-error-information>
 <status-information>...</status-information>
 <flow-detail>...</flow-detail>
 <flow-aggregate-template-detail>...</flow-aggregate-template-detail>
 <flow-aggregate-as-detail>...</flow-aggregate-as-detail>
 <flow-aggregate-protocol-port-detail>...</flow-aggregate-protocol-port-detail>
 <flow-aggregate-source-prefix-detail>...</flow-aggregate-source-prefix-detail>
 <flow-aggregate-destination-prefix-detail>...
 </flow-aggregate-destination-prefix-detail>
 <flow-aggregate-source-destination-prefix-detail>...
 </flow-aggregate-source-destination-prefix-detail>
 </services-accounting-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <error-information>—Service accounting error information.

<flow-aggregate-as-detail>—Service accounting AS flow aggregate record detail.

<flow-aggregate-destination-prefix-detail>—Service accounting destination prefix aggregate record detail.

<flow-aggregate-protocol-port-detail>—Service accounting protocol-port aggregate record detail.

<flow-aggregate-source-destination-prefix-detail>—Service accounting source-destination prefix aggregate record detail.

<flow-aggregate-source-prefix-detail>—Service accounting source prefix aggregate record detail.

<flow-aggregate-template-detail>—Service accounting template aggregate record detail.

<flow-detail>—Service accounting flow record detail.

<flow-information>—Service accounting flow information.

<interface-name>—Physical interface name.

<local-index>—Local physical interface index.

<memory-information>—Service accounting memory utilization.

<packet-distribution-information>—Service accounting packet distribution information.

<pic-status>—Current interface state.

<service-name>—Service name.

<status-information>—Service accounting status information.

<usage-information>—Service accounting CPU utilization.

<v9-error-information>—Jflow-v9 accounting error information.

<status-information>

Usage <services-accounting-information>
<status-information>
 <status-service-id>status-service-id</status-service-id>
 <status-export-interval>status-export-interval</status-export-interval>
 <status-export-format>status-export-format</status-export-format>
 <status-proto>status-proto</status-proto>
 <status-engine-type>status-engine-type</status-engine-type>
 <status-engine-id>status-engine-id</status-engine-id>
 <status-route-record-count>status-route-record-count
 </status-route-record-count>
 <status-ifl-snmp-map-count>status-ifl-snmp-map-count
 </status-ifl-snmp-map-count>
 <status-as-count>status-as-count</status-as-count>
 <status-monitor-time-set>status-monitor-time-set</status-monitor-time-set>
 <status-monitor-config-set>status-monitor-config-set
 </status-monitor-config-set>
 <status-monitor-route-record-set>status-monitor-route-record-set
 </status-monitor-route-record-set>
 <status-monitor-ifl-snmp-set>status-monitor-ifl-snmp-set
 </status-monitor-ifl-snmp-set>
</status-information>
 </services-accounting-information>

Description Service accounting status information.

Contents <status-as-count>—Autonomous system number count.
 <status-engine-id>—Engine ID.
 <status-engine-type>—Engine type.
 <status-export-format>—Export format.
 <status-export-interval>—Export interval, in seconds.
 <status-ifl-snmp-map-count>—Local index to SNMP index count.
 <status-monitor-config-set>—Configuration set on PIC.
 <status-monitor-ifl-snmp-set>—Local index to SNMP index map set on PIC.
 <status-monitor-route-record-set>—Route records set on PIC.
 <status-monitor-time-set>—Time set on PIC.
 <status-proto>—Protocol.
 <status-route-record-count>—Route record count.
 <status-service-id>—Service ID.

<usage-information>

Usage	<pre> <services-accounting-information> <usage-information> <uptime>uptime</uptime> <inttime>inttime</inttime> <five-second-load>five-second-load</five-second-load> <one-minute-load>one-minute-load</one-minute-load> </usage-information> </services-accounting-information> </pre>
Description	Service accounting CPU utilization.
Contents	<p><five-second-load>—5-second load.</p> <p><inttime>—CPU interrupt time, in microseconds.</p> <p><one-minute-load>—1-minute load.</p> <p><uptime>—CPU uptime, in milliseconds.</p>

<v9-error-information>

Usage	<pre> <services-accounting-information> <v9-error-information> <service-set-dropped>service-set-dropped</service-set-dropped> <active-timeout-failures>active-timeout-failures</active-timeout-failures> <export-packet-failures>export-packet-failures</export-packet-failures> <flow-creation-failures>flow-creation-failures</flow-creation-failures> <memory-overload>memory-overload</memory-overload> </v9-error-information> </services-accounting-information> </pre>
Description	Jflow-v9 accounting error information.
Contents	<p><active-timeout-failures>—Number of active timeout failures.</p> <p><export-packet-failures>—Number of export packet failures.</p> <p><flow-creation-failures>—Number of flow creation failures.</p> <p><memory-overload>—Memory overload status.</p> <p><service-set-dropped>—Number of service set drops.</p>

Summary of Services Flow Collector Response Tags

This section lists JUNOS XML tags that contain operational information about services flow collector records. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-services-flow-collector>. To review the DTD for the tags, see “DTD for Services Flow Collector Response Tags” on page 2037.

<export-channel>

Usage <statistics-information>
 <export-channel>
 <export-channel-index>*export-channel-index*</export-channel-index>
 <current-server>*current-server*</current-server>
 <primary-server-state>*primary-server-state*</primary-server-state>
 <secondary-server-state>*secondary-server-state*</secondary-server-state>
 </export-channel>
 </statistics-information>

Description Export channel on interface.

Contents <current-server>—Currently used server.
 <export-channel-index>—Export channel index.
 <primary-server-state>—Primary server state.
 <secondary-server-state>—Secondary server state.

<file>

Usage <file-information>
 <file>
 <file-name>*file-name*</file-name>
 <flow-records>*flow-records*</flow-records>
 <flow-records-per-second>*flow-records-per-second*</flow-records-per-second>
 <peak-flow-records-per-second>*peak-flow-records-per-second*
 </peak-flow-records-per-second>
 <uncompressed-bytes>*uncompressed-bytes*</uncompressed-bytes>
 <uncompressed-bytes-per-second>*uncompressed-bytes-per-second*
 </uncompressed-bytes-per-second>
 <peak-uncompressed-bytes-per-second>*peak-uncompressed-bytes-per-second*
 </peak-uncompressed-bytes-per-second>
 <compressed-bytes>*compressed-bytes*</compressed-bytes>
 <compressed-bytes-per-second>*compressed-bytes-per-second*
 </compressed-bytes-per-second>
 <peak-compressed-bytes-per-second>*peak-compressed-bytes-per-second*
 </peak-compressed-bytes-per-second>
 <compressed-block-count>*compressed-block-count*</compressed-block-count>
 <block-count>*block-count*</block-count>
 <state>*state*</state>
 <transfer-attempts>*transfer-attempts*</transfer-attempts>
 </file>
 </file-information>

Description File statistics.

Contents <block-count>—Number of blocks in file.

<compressed-block-count>—Number of compressed blocks.

<compressed-bytes>—Compressed bytes.

<compressed-bytes-per-second>—Compressed bytes per second.

<file-name>—Filename.

<flow-records>—Flow records in file.

<flow-records-per-second>—Flow records per second.

<peak-compressed-bytes-per-second>—Peak compressed bytes per second.

<peak-flow-records-per-second>—Peak flow records per second.

<peak-uncompressed-bytes-per-second>—Peak uncompressed bytes per second.

<state>—Current state of the file.

<transfer-attempts>—Number of FTP transfer attempts.

<uncompressed-bytes>—Uncompressed bytes.

<uncompressed-bytes-per-second>—Uncompressed bytes per second.

<file-information>

Usage	<pre> <services-flow-collector-information> <file-information> <file>...</file> </file-information> </services-flow-collector-information> </pre>
Description	Service flow collector information about files.
Contents	<file>—File statistics.

<input>

Usage	<pre> <input-information> <input> <input-interface>input-interface</input-interface> <packets>packets</packets> <bytes>bytes</bytes> </input> </input-information> </pre>
Description	Input interface statistics.
Contents	<bytes>—Bytes. <input-interface>—Input interface. <packets>—Packets.

<input-information>

Usage	<pre> <services-flow-collector-information> <input-information> <input>...</input> </input-information> </services-flow-collector-information> </pre>
Description	Service flow collector information for each input.
Contents	<input>—Input interface statistics.

<services-flow-collector-information>

Usage <rpc-reply>
 <services-flow-collector-information>
 <interface-name>*interface-name*</interface-name>
 <pic-status>*pic-status*</pic-status>
 <statistics-information>...</statistics-information>
 <file-information>...</file-information>
 <input-information>...</input-information>
 <flow-collector-destination-response>*flow-collector-destination-response*
 </flow-collector-destination-response>
 <test-file-transfer-response>*test-file-transfer-response*
 </test-file-transfer-response>
 <clear-flow-collector-statistics-response>*clear-flow-collector-statistics-response*
 </clear-flow-collector-statistics-response>
 </services-flow-collector-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <clear-flow-collector-statistics-response>—No documentation is available yet.

<file-information>—Service flow collector information about files.

<flow-collector-destination-response>—Selected destination.

<input-information>—Service flow collector information for each input.

<interface-name>—Physical interface name.

<pic-status>—Current interface state.

<statistics-information>—Service flow collector application information.

<test-file-transfer-response>—No documentation is available yet.

<statistics-information>

Usage <services-flow-collector-information>

```

<statistics-information>
  <memory-used>memory-used</memory-used>
  <memory-free>memory-free</memory-free>
  <packets>packets</packets>
  <packets-per-second>packets-per-second</packets-per-second>
  <peak-packets-per-second>peak-packets-per-second</peak-packets-per-second>
  <bytes>bytes</bytes>
  <bytes-per-second>bytes-per-second</bytes-per-second>
  <peak-bytes-per-second>peak-bytes-per-second</peak-bytes-per-second>
  <flow-record-processed>flow-record-processed</flow-record-processed>
  <flow-record-processed-per-second>flow-record-processed-per-second
    </flow-record-processed-per-second>
  <peak-flow-record-processed-per-second>peak-flow-record-processed-per-second
    </peak-flow-record-processed-per-second>
  <blocks-allocated>blocks-allocated</blocks-allocated>
  <blocks-allocated-per-second>blocks-allocated-per-second
    </blocks-allocated-per-second>
  <peak-blocks-allocated-per-second>peak-blocks-allocated-per-second
    </peak-blocks-allocated-per-second>
  <blocks-freed>blocks-freed</blocks-freed>
  <blocks-freed-per-second>blocks-freed-per-second</blocks-freed-per-second>
  <peak-blocks-freed-per-second>peak-blocks-freed-per-second
    </peak-blocks-freed-per-second>
  <blocks-unavailable>blocks-unavailable</blocks-unavailable>
  <blocks-unavailable-per-second>blocks-unavailable-per-second
    </blocks-unavailable-per-second>
  <peak-blocks-unavailable-per-second>peak-blocks-unavailable-per-second
    </peak-blocks-unavailable-per-second>
  <files-created>files-created</files-created>
  <files-created-per-second>files-created-per-second</files-created-per-second>
  <peak-files-created-per-second>peak-files-created-per-second
    </peak-files-created-per-second>
  <files-exported>files-exported</files-exported>
  <files-exported-per-second>files-exported-per-second
    </files-exported-per-second>
  <peak-files-exported-per-second>peak-files-exported-per-second
    </peak-files-exported-per-second>
  <files-destroyed>files-destroyed</files-destroyed>
  <files-destroyed-per-second>files-destroyed-per-second
    </files-destroyed-per-second>
  <peak-files-destroyed-per-second>peak-files-destroyed-per-second
    </peak-files-destroyed-per-second>
  <uncompressed-bytes>uncompressed-bytes</uncompressed-bytes>
  <uncompressed-bytes-per-second>uncompressed-bytes-per-second
    </uncompressed-bytes-per-second>
  <peak-uncompressed-bytes-per-second>peak-uncompressed-bytes-per-second
    </peak-uncompressed-bytes-per-second>
  <compressed-bytes>compressed-bytes</compressed-bytes>
  <compressed-bytes-per-second>compressed-bytes-per-second
    </compressed-bytes-per-second>
  <peak-compressed-bytes-per-second>peak-compressed-bytes-per-second

```

```

        </peak-compressed-bytes-per-second>
    <packet-no-memory-drops>packet-no-memory-drops</packet-no-memory-drops>
    <packet-not-ip-drops>packet-not-ip-drops</packet-not-ip-drops>
    <packet-not-ipv4-drops>packet-not-ipv4-drops</packet-not-ipv4-drops>
    <packet-too-small-drops>packet-too-small-drops</packet-too-small-drops>
    <packet-ip-fragment-drops>packet-ip-fragment-drops</packet-ip-fragment-drops>
    <packet-icmp-drops>packet-icmp-drops</packet-icmp-drops>
    <packet-tcp-drops>packet-tcp-drops</packet-tcp-drops>
    <packet-unknown-drops>packet-unknown-drops</packet-unknown-drops>
    <packet-not-jflow-drops>packet-not-jflow-drops</packet-not-jflow-drops>
    <ftp-bytes>ftp-bytes</ftp-bytes>
    <ftp-bytes-per-second>ftp-bytes-per-second</ftp-bytes-per-second>
    <peak-ftp-bytes-per-second>peak-ftp-bytes-per-second
        </peak-ftp-bytes-per-second>
    <ftp-files>ftp-files</ftp-files>
    <ftp-files-per-second>ftp-files-per-second</ftp-files-per-second>
    <peak-ftp-files-per-second>peak-ftp-files-per-second
        </peak-ftp-files-per-second>
    <ftp-failures>ftp-failures</ftp-failures>
    <export-channel>...</export-channel>
</statistics-information>
</services-flow-collector-information>

```

Description Service flow collector application information.

Contents

- <blocks-allocated>—Blocks allocated.
- <blocks-allocated-per-second>—Blocks allocated per second.
- <blocks-freed>—Blocks freed.
- <blocks-freed-per-second>—Blocks freed per second.
- <blocks-unavailable>—Blocks unavailable.
- <blocks-unavailable-per-second>—Blocks unavailable per second.
- <bytes>—Bytes.
- <bytes-per-second>—Bytes per second.
- <compressed-bytes>—Compressed bytes.
- <compressed-bytes-per-second>—Compressed bytes per second.
- <export-channel>—Export channel on interface.
- <files-created>—Files created.
- <files-created-per-second>—Files created per second.
- <files-destroyed>—Files destroyed.
- <files-destroyed-per-second>—Files destroyed per second.

<files-exported>—Files exported.

<files-exported-per-second>—Files exported per second.

<flow-record-processed>—Flow records processed.

<flow-record-processed-per-second>—Flow records processed per second.

<ftp-bytes>—FTP bytes.

<ftp-bytes-per-second>—FTP bytes per second.

<ftp-failures>—Number of ftp transfer failures.

<ftp-files>—FTP files.

<ftp-files-per-second>—FTP files per second.

<memory-free>—Memory free, in bytes.

<memory-used>—Memory used, in bytes.

<packet-icmp-drops>—Packets dropped because they were ICMP packets.

<packet-ip-fragment-drops>—Packets dropped because they were fragments.

<packet-no-memory-drops>—Packets dropped because of insufficient memory.

<packet-not-ip-drops>—Packets dropped because they were not IP packets.

<packet-not-ipv4-drops>—Packets dropped because they were not IPv4 packets.

<packet-not-jflow-drops>—Packets dropped because they were not JUNOS flow packets.

<packet-tcp-drops>—Packets dropped because they were TCP packets.

<packet-too-small-drops>—Packets dropped because they were too small.

<packet-unknown-drops>—Packets dropped because they were an unknown type.

<packets>—Packets.

<packets-per-second>—Packets per second.

<peak-blocks-allocated-per-second>—Peak blocks allocated per second.

<peak-blocks-freed-per-second>—Peak blocks freed per second.

<peak-blocks-unavailable-per-second>—Peak blocks unavailable per second.

<peak-bytes-per-second>—Peak bytes per second.

<peak-compressed-bytes-per-second>—Peak compressed bytes per second.

<peak-files-created-per-second>—Peak files created per second.

<peak-files-destroyed-per-second>—Peak files destroyed per second.

<peak-files-exported-per-second>—Peak files exported per second.

<peak-flow-record-processed-per-second>—Peak flow records processed per second.

<peak-ftp-bytes-per-second>—Peak FTP bytes per second.

<peak-ftp-files-per-second>—Peak FTP files per second.

<peak-packets-per-second>—Peak packets per second.

<peak-uncompressed-bytes-per-second>—Peak uncompressed bytes per second.

<uncompressed-bytes>—Uncompressed bytes.

<uncompressed-bytes-per-second>—Uncompressed bytes per second.

Summary of Shutdown Response Tags

This section lists JUNOS XML tags that contain operational information about routing platform shutdown. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-shutdown>. To review the DTD for the tags, see “DTD for Shutdown Response Tags” on page 2041.

<clear-reboot-status>

Usage	<pre> <rpc-reply> <clear-reboot-status> <reboot-information-results>reboot-information-results </reboot-information-results> <clear-reboot-status-results>clear-reboot-status-results </clear-reboot-status-results> </clear-reboot-status> </rpc-reply> </pre>
Description	Clear any pending reboots.
Contents	<p><clear-reboot-status-results>—Status of clear reboot request.</p> <p><reboot-information-results>—Reboot status.</p>

<reboot-information>

Usage	<pre> <rpc-reply> <reboot-information> <reboot-information-results>reboot-information-results </reboot-information-results> </reboot-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<reboot-information-results>—Reboot status.

<request-reboot-results>

Usage	<pre> <rpc-reply> <request-reboot-results> <request-reboot-status>request-reboot-status</request-reboot-status> </request-reboot-results> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<request-reboot-status>—Reboot request status.

Summary of SNMP Response Tags

This section lists JUNOS XML tags that contain operational information about the Simple Network Management Protocol (SNMP). The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-snmp>. To review the DTD for the tags, see “DTD for SNMP Response Tags” on page 2043.

<health-monitor-information>

Usage <rpc-reply>
 <health-monitor-information>
 <rmon-alarm-information>...</rmon-alarm-information>
 <rmon-log-information>...</rmon-log-information>
 <rmon-history-information>...</rmon-history-information>
 </health-monitor-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <rmon-alarm-information>—No documentation is available yet.
 <rmon-history-information>—No documentation is available yet.
 <rmon-log-information>—No documentation is available yet.

<history-sample>

Usage <rmon-history-information>
<history-sample>
 <history-sample-index>*history-sample-index*</history-sample-index>
 <history-sample-start-time>*history-sample-start-time*
 </history-sample-start-time>
 <history-sample-drop-events>*history-sample-drop-events*
 </history-sample-drop-events>
 <history-sample-octect>*history-sample-octect*</history-sample-octect>
 <history-sample-packets>*history-sample-packets*</history-sample-packets>
 <history-sample-broadcast-packets>*history-sample-broadcast-packets*
 </history-sample-broadcast-packets>
 <history-sample-multicast-packets>*history-sample-multicast-packets*
 </history-sample-multicast-packets>
 <history-sample-crc-errors>*history-sample-crc-errors*
 </history-sample-crc-errors>
 <history-sample-undersize-packets>*history-sample-undersize-packets*
 </history-sample-undersize-packets>
 <history-sample-oversize-packets>*history-sample-oversize-packets*
 </history-sample-oversize-packets>
 <history-sample-fragments>*history-sample-fragments*</history-sample-fragments>
 <history-sample-jabbers>*history-sample-jabbers*</history-sample-jabbers>
 <history-sample-collisions>*history-sample-collisions*
 </history-sample-collisions>
 <history-sample-utilization>*history-sample-utilization*
 </history-sample-utilization>
</history-sample>
 </rmon-history-information>

Description No documentation is available yet.

Contents <history-sample-broadcast-packets>—Number of broadcast packets.
 <history-sample-collisions>—Number of collisions.
 <history-sample-crc-errors>—Crc errors.
 <history-sample-drop-events>—Sample drop events.
 <history-sample-fragments>—Number of fragment.
 <history-sample-index>—History sample instance identifier.
 <history-sample-jabbers>—Number of jabbers.
 <history-sample-multicast-packets>—Number of multicast packets.
 <history-sample-octect>—Octets.
 <history-sample-oversize-packets>—Number of oversize packets.
 <history-sample-packets>—Packets.
 <history-sample-start-time>—History sample collection start time .

<history-sample-undersize-packets>—Number of undersize packets.

<history-sample-utilization>—Utilization .

<index>

Usage <snmp-object>
 <index>
 <index-name>*index-name*</index-name>
 <index-value>*index-value*</index-value>
 </index>
 </snmp-object>

Description No documentation is available yet.

Contents <index-name>—SNMP index name.

<index-value>—SNMP index value.

<rmon-alarm>

Usage <rmon-alarm-information>
 <rmon-alarm>
 <alarm-index>*alarm-index*</alarm-index>
 <var-name>*var-name*</var-name>
 <var-oid>*var-oid*</var-oid>
 <sample-type>*sample-type*</sample-type>
 <alarm-value>*alarm-value*</alarm-value>
 <startup>*startup*</startup>
 <alarm-interval>*alarm-interval*</alarm-interval>
 <rising-threshold>*rising-threshold*</rising-threshold>
 <falling-threshold>*falling-threshold*</falling-threshold>
 <rising-event-index>*rising-event-index*</rising-event-index>
 <falling-event-index>*falling-event-index*</falling-event-index>
 <alarm-owner>*alarm-owner*</alarm-owner>
 <alarm-subtag>*alarm-subtag*</alarm-subtag>
 <alarm-creator>*alarm-creator*</alarm-creator>
 <alarm-state>*alarm-state*</alarm-state>
 <rmon-alarm-instance-information>...</rmon-alarm-instance-information>
 </rmon-alarm>
 </rmon-alarm-information>

Description No documentation is available yet.

Contents <alarm-creator>—Method by which entry was created.

<alarm-index>—Alarm instance identifier.

<alarm-interval>—Interval between samples, in seconds.

<alarm-owner>—Name of owner of this entry.

<alarm-state>—Current state of the entry.

<alarm-subtag>—Additional tag added to system logs for this entry.

<alarm-value>—Most recently monitored value.

<falling-event-index>—Event generated when a falling alarm is sent.

<falling-threshold>—Falling alarm threshold.

<rising-event-index>—Event generated when a rising alarm is sent.

<rising-threshold>—Rising alarm threshold.

<rmon-alarm-instance-information>—Information about one or more alarm instances.

<sample-type>—Method of sampling the monitored variable.

<startup>—Alarm that might be sent when entry is activated.

<var-name>—Monitored variable name.

`<var-oid>`—Monitored variable OID.

`<rmon-alarm-information>`

- Usage** `<rmon-information | health-monitor-information>`
 `<rmon-alarm-information>`
 `<rmon-alarm>...</rmon-alarm>`
 `</rmon-alarm-information>`
 `</rmon-information | health-monitor-information>`
- Description** No documentation is available yet.
- Contents** `<rmon-alarm>`—No documentation is available yet.

`<rmon-alarm-instance>`

- Usage** `<rmon-alarm-instance-information>`
 `<rmon-alarm-instance>`
 `<inst-var-name>inst-var-name</inst-var-name>`
 `<inst-description>inst-description</inst-description>`
 `<inst-value>inst-value</inst-value>`
 `<inst-state>inst-state</inst-state>`
 `</rmon-alarm-instance>`
 `</rmon-alarm-instance-information>`
- Description** Information about an alarm instance.
- Contents** `<inst-description>`—Monitored variable description.
- `<inst-state>`—Current state of the alarm instance.
- `<inst-value>`—Most recently monitored value.
- `<inst-var-name>`—Monitored variable name.

`<rmon-alarm-instance-information>`

- Usage** `<rmon-alarm>`
 `<rmon-alarm-instance-information>`
 `<rmon-alarm-instance>...</rmon-alarm-instance>`
 `</rmon-alarm-instance-information>`
 `</rmon-alarm>`
- Description** Information about one or more alarm instances.
- Contents** `<rmon-alarm-instance>`—Information about an alarm instance.

<rmon-event>

Usage <rmon-event-information>
 <rmon-event>
 <event-index>*event-index*</event-index>
 <event-descr>*event-descr*</event-descr>
 <event-type>*event-type*</event-type>
 <community>*community*</community>
 <last-time-sent>*last-time-sent*</last-time-sent>
 <event-owner>*event-owner*</event-owner>
 <event-creator>*event-creator*</event-creator>
 <event-state>*event-state*</event-state>
 </rmon-event>
 </rmon-event-information>

Description No documentation is available yet.

Contents <community>—Trap group to which trap is sent.
 <event-creator>—Method by which the entry was created.
 <event-descr>—Comment describing the event entry.
 <event-index>—Event instance identifier.
 <event-owner>—Name of owner of the event.
 <event-state>—Current state of the entry.
 <event-type>—Type of notification made about this event.
 <last-time-sent>—Time this event was last generated.

<rmon-event-information>

Usage <rmon-information>
 <rmon-event-information>
 <rmon-event>...</rmon-event>
 </rmon-event-information>
 </rmon-information>

Description No documentation is available yet.

Contents <rmon-event>—No documentation is available yet.

<rmon-history>

Usage	<pre> <rmon-history-information> <rmon-history> <history-index>history-index</history-index> <history-interface>history-interface</history-interface> <history-requested-buckets>history-requested-buckets </history-requested-buckets> <history-interval>history-interval</history-interval> <history-owner>history-owner</history-owner> </rmon-history> </rmon-history-information> </pre>
Description	No documentation is available yet.
Contents	<p><history-index>—History instance identifier.</p> <p><history-interface>—Comment describing the RMON interface.</p> <p><history-interval>—Interval for statistics collection on the RMON interface.</p> <p><history-owner>—Owner for RMON history.</p> <p><history-requested-buckets>—Requested buckets for the RMON interface.</p>

<rmon-history-information>

Usage	<pre> <rmon-information health-monitor-information> <rmon-history-information> <rmon-history>...</rmon-history> <history-sample>...</history-sample> </rmon-history-information> </rmon-information health-monitor-information> </pre>
Description	No documentation is available yet.
Contents	<p><history-sample>—No documentation is available yet.</p> <p><rmon-history>—No documentation is available yet.</p>

<rmon-information>

Usage	<pre> <rpc-reply> <rmon-information> <rmon-alarm-information>...</rmon-alarm-information> <rmon-event-information>...</rmon-event-information> <rmon-history-information>...</rmon-history-information> </rmon-information> </rpc-reply> </pre>
Description	No documentation is available yet.
Contents	<p><rmon-alarm-information>—No documentation is available yet.</p> <p><rmon-event-information>—No documentation is available yet.</p> <p><rmon-history-information>—No documentation is available yet.</p>

<rmon-log>

Usage	<pre> <rmon-log-information> <rmon-log> <rmon-log-event-index>rmon-log-event-index</rmon-log-event-index> <rmon-log-index>rmon-log-index</rmon-log-index> <rmon-log-descr>rmon-log-descr</rmon-log-descr> <rmon-log-time>rmon-log-time</rmon-log-time> </rmon-log> </rmon-log-information> </pre>
Description	No documentation is available yet.
Contents	<p><rmon-log-descr>—Log description.</p> <p><rmon-log-event-index>—Event instance identifier.</p> <p><rmon-log-index>—Log instance identifier.</p> <p><rmon-log-time>—Time this event was last generated.</p>

<rmon-log-information>

Usage	<pre> <health-monitor-information> <rmon-log-information> <rmon-log>...</rmon-log> </rmon-log-information> </health-monitor-information> </pre>
Description	No documentation is available yet.
Contents	<rmon-log>—No documentation is available yet.

<snmp-generate-trap-results>

```
Usage  <rpc-reply>
      <snmp-generate-trap-results>
        <snmp-generate-trap-result>snmp-generate-trap-result
        </snmp-generate-trap-result>
      </snmp-generate-trap-results>
    </rpc-reply>
```

Description No documentation is available yet.

Contents <snmp-generate-trap-result>—Result of SNMP 'generate-trap' request.

<snmp-input-statistics>

Usage <snmp-statistics>
 <snmp-input-statistics>
 <packets>*packets*</packets>
 <bad-versions>*bad-versions*</bad-versions>
 <bad-community-names>*bad-community-names*</bad-community-names>
 <bad-community-uses>*bad-community-uses*</bad-community-uses>
 <asn-parse-errors>*asn-parse-errors*</asn-parse-errors>
 <too-bigs>*too-bigs*</too-bigs>
 <no-such-names>*no-such-names*</no-such-names>
 <bad-values>*bad-values*</bad-values>
 <read-onlys>*read-onlys*</read-onlys>
 <general-errors>*general-errors*</general-errors>
 <total-request-varbinds>*total-request-varbinds*</total-request-varbinds>
 <total-set-varbinds>*total-set-varbinds*</total-set-varbinds>
 <get-requests>*get-requests*</get-requests>
 <get-nexts>*get-nexts*</get-nexts>
 <set-requests>*set-requests*</set-requests>
 <get-responses>*get-responses*</get-responses>
 <traps>*traps*</traps>
 <silent-drops>*silent-drops*</silent-drops>
 <proxy-drops>*proxy-drops*</proxy-drops>
 <throttle-drops>*throttle-drops*</throttle-drops>
 <commit-pending-drops>*commit-pending-drops*</commit-pending-drops>
 <duplicate-request-drops>*duplicate-request-drops*</duplicate-request-drops>
 </snmp-input-statistics>
 </snmp-statistics>

Description No documentation is available yet.

Contents <asn-parse-errors>—No documentation is available yet.

<bad-community-names>—No documentation is available yet.

<bad-community-uses>—No documentation is available yet.

<bad-values>—No documentation is available yet.

<bad-versions>—No documentation is available yet.

<commit-pending-drops>—No documentation is available yet.

<duplicate-request-drops>—Number of duplicate requests that were dropped.

<general-errors>—No documentation is available yet.

<get-nexts>—No documentation is available yet.

<get-requests>—No documentation is available yet.

<get-responses>—No documentation is available yet.

<no-such-names>—No documentation is available yet.

<packets>—No documentation is available yet.

<proxy-drops>—No documentation is available yet.

<read-onlys>—No documentation is available yet.

<set-requests>—No documentation is available yet.

<silent-drops>—No documentation is available yet.

<throttle-drops>—No documentation is available yet.

<too-bigs>—No documentation is available yet.

<total-request-varbinds>—No documentation is available yet.

<total-set-varbinds>—No documentation is available yet.

<traps>—No documentation is available yet.

<snmp-object>

Usage <snmp-object-information>
 <snmp-object>
 <name>*name*</name>
 <index>...</index>
 <oid>*oid*</oid>
 <object-value>*object-value*</object-value>
 <object-value-type>*object-value-type*</object-value-type>
 <error>*error*</error>
 </snmp-object>
 </snmp-object-information>

Description No documentation is available yet.

Contents <error>—SNMP object error.

<index>—No documentation is available yet.

<name>—SNMP object name.

<object-value>—SNMP object value.

<object-value-type>—No documentation is available yet.

<oid>—SNMP object identifier.

<snmp-object-information>

Usage <rpc-reply>
 <snmp-object-information>
 <snmp-object>...</snmp-object>
 <snmp-request-error>...</snmp-request-error>
 </snmp-object-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <snmp-object>—No documentation is available yet.
 <snmp-request-error>—No documentation is available yet.

<snmp-output-statistics>

Usage <snmp-statistics>
 <snmp-output-statistics>
 <packets>*packets*</packets>
 <too-bigs>*too-bigs*</too-bigs>
 <no-such-names>*no-such-names*</no-such-names>
 <bad-values>*bad-values*</bad-values>
 <general-errors>*general-errors*</general-errors>
 <get-requests>*get-requests*</get-requests>
 <get-nexts>*get-nexts*</get-nexts>
 <set-requests>*set-requests*</set-requests>
 <get-responses>*get-responses*</get-responses>
 <traps>*traps*</traps>
 </snmp-output-statistics>
 </snmp-statistics>

Description No documentation is available yet.

Contents <bad-values>—No documentation is available yet.
 <general-errors>—No documentation is available yet.
 <get-nexts>—No documentation is available yet.
 <get-requests>—No documentation is available yet.
 <get-responses>—No documentation is available yet.
 <no-such-names>—No documentation is available yet.
 <packets>—No documentation is available yet.
 <set-requests>—No documentation is available yet.
 <too-bigs>—No documentation is available yet.
 <traps>—No documentation is available yet.

<snmp-request-error>

- Usage** <snmp-object-information>
 <snmp-request-error>
 <snmp-req-error-value>*snmp-req-error-value*</snmp-req-error-value>
 </snmp-request-error>
 </snmp-object-information>
- Description** No documentation is available yet.
- Contents** <snmp-req-error-value>—SNMP request error.

<snmp-set-stats>

- Usage** <snmp-statistics>
 <snmp-set-stats>
 <nvs-commit-pending>*nvs-commit-pending*</nvs-commit-pending>
 <nvs-conflock-failures>*nvs-conflock-failures*</nvs-conflock-failures>
 <nvs-rpc-mgd-failures>*nvs-rpc-mgd-failures*</nvs-rpc-mgd-failures>
 <nvs-journal-write-failures>*nvs-journal-write-failures*
 </nvs-journal-write-failures>
 <nvs-mgd-connect-failures>*nvs-mgd-connect-failures*</nvs-mgd-connect-failures>
 <nvs-commit-failures>*nvs-commit-failures*</nvs-commit-failures>
 </snmp-set-stats>
 </snmp-statistics>
- Description** No documentation is available yet.
- Contents** <nvs-commit-failures>—Set requests failed because of a general commit error.
- <nvs-commit-pending>—Set requests failed because of a pending commit.
- <nvs-conflock-failures>—Set requests failed because of configuration lock conflict.
- <nvs-journal-write-failures>—Set requests failed because of journal write error.
- <nvs-mgd-connect-failures>—Set requests failed because snmpd could not connect to mgd.
- <nvs-rpc-mgd-failures>—Set requests failed because of a management daemon rpc error.

<snmp-spoof-trap-results>

Usage <rpc-reply>
 <snmp-spoof-trap-results>
 <snmp-spoof-trap-result>*snmp-spoof-trap-result*</snmp-spoof-trap-result>
 <snmp-spoofable-traps>*snmp-spoofable-traps*</snmp-spoofable-traps>
 </snmp-spoof-trap-results>
 </rpc-reply>

Description No documentation is available yet.

Contents <snmp-spoof-trap-result>—Result of SNMP 'spoof-trap' request.
 <snmp-spoofable-traps>—SNMP traps supported for spoofing.

<snmp-statistics>

Usage <rpc-reply>
 <snmp-statistics>
 <snmp-input-statistics>...</snmp-input-statistics>
 <snmp-v3-input-statistics>...</snmp-v3-input-statistics>
 <snmp-output-statistics>...</snmp-output-statistics>
 <sub-agent-control-blocks>...</sub-agent-control-blocks>
 <sub-agent-registration>...</sub-agent-registration>
 <trap-queue-stats>...</trap-queue-stats>
 <trap-throttle-stats>...</trap-throttle-stats>
 <snmp-set-stats>...</snmp-set-stats>
 </snmp-statistics>
 </rpc-reply>

Description No documentation is available yet.

Contents <snmp-input-statistics>—No documentation is available yet.
 <snmp-output-statistics>—No documentation is available yet.
 <snmp-set-stats>—No documentation is available yet.
 <snmp-v3-input-statistics>—No documentation is available yet.
 <sub-agent-control-blocks>—No documentation is available yet.
 <sub-agent-registration>—No documentation is available yet.
 <trap-queue-stats>—No documentation is available yet.
 <trap-throttle-stats>—No documentation is available yet.

<snmp-v3-access>

Usage <snmp-v3-access-information>
 <snmp-v3-access>
 <group-name>group-name</group-name>
 <context-prefix>context-prefix</context-prefix>
 <security-model>security-model</security-model>
 <security-level>security-level</security-level>
 <context-match>context-match</context-match>
 <read-view>read-view</read-view>
 <write-view>write-view</write-view>
 <notify-view>notify-view</notify-view>
 <storage-type>storage-type</storage-type>
 <row-status>row-status</row-status>
 </snmp-v3-access>
 </snmp-v3-access-information>

Description No documentation is available yet.

Contents <context-match>—No documentation is available yet.

<context-prefix>—Context prefix.

<group-name>—Group name.

<notify-view>—MIB view allowed for notifications.

<read-view>—MIB view allowed for read access.

<row-status>—Status for this entry.

<security-level>—Security level.

<security-model>—Security model.

<storage-type>—Type of storage for this entry.

<write-view>—MIB view allowed for write access.

<snmp-v3-access-information>

Usage <snmp-v3-information>
 <snmp-v3-access-information>
 <snmp-v3-access>...</snmp-v3-access>
 </snmp-v3-access-information>
 </snmp-v3-information>

Description No documentation is available yet.

Contents <snmp-v3-access>—No documentation is available yet.

<snmp-v3-community>

Usage <snmp-v3-community-information>
 <snmp-v3-community>
 <community-index>*community-index*</community-index>
 <security-name>*security-name*</security-name>
 <context-name>*context-name*</context-name>
 <transport-tag>*transport-tag*</transport-tag>
 <storage-type>*storage-type*</storage-type>
 <row-status>*row-status*</row-status>
 </snmp-v3-community>
 </snmp-v3-community-information>

Description SNMPv3 community.

Contents <community-index>—Community index in this community table entry.
 <context-name>—Context name used when performing access control.
 <row-status>—Status for this entry.
 <security-name>—Security name.
 <storage-type>—Type of storage for this entry.
 <transport-tag>—Transport tag used to identify a set of targets.

<snmp-v3-community-information>

Usage <snmp-v3-information>
 <snmp-v3-community-information>
 <snmp-v3-community>...</snmp-v3-community>
 </snmp-v3-community-information>
 </snmp-v3-information>

Description SNMPv3 community information.

Contents <snmp-v3-community>—SNMPv3 community.

<snmp-v3-engine-information>

Usage <snmp-v3-general-information>
 <snmp-v3-engine-information>
 <engine-id>*engine-id*</engine-id>
 <engine-boots>*engine-boots*</engine-boots>
 <engine-time>*engine-time*</engine-time>
 <max-msg-size>*max-msg-size*</max-msg-size>
 </snmp-v3-engine-information>
 </snmp-v3-general-information>

Description No documentation is available yet.

Contents <engine-boots>—Number of times this engine has booted.
 <engine-id>—Engine ID.
 <engine-time>—Number of seconds since this engine has booted.
 <max-msg-size>—Maximum message size allowed by this engine.

<snmp-v3-general-information>

Usage <snmp-v3-information>
 <snmp-v3-general-information>
 <snmp-v3-engine-information>...</snmp-v3-engine-information>
 </snmp-v3-general-information>
 </snmp-v3-information>

Description No documentation is available yet.

Contents <snmp-v3-engine-information>—No documentation is available yet.

<snmp-v3-group>

Usage <snmp-v3-group-information>
 <snmp-v3-group>
 <group-name>group-name</group-name>
 <security-model>security-model</security-model>
 <security-name>security-name</security-name>
 <storage-type>storage-type</storage-type>
 <row-status>row-status</row-status>
 </snmp-v3-group>
 </snmp-v3-group-information>

Description No documentation is available yet.

Contents <group-name>—Group name.
 <row-status>—Status for this entry.
 <security-model>—Security model.
 <security-name>—Security name.
 <storage-type>—Type of storage for this entry.

<snmp-v3-group-information>

Usage <snmp-v3-information>
 <snmp-v3-group-information>
 <snmp-v3-group>...</snmp-v3-group>
 </snmp-v3-group-information>
 </snmp-v3-information>

Description No documentation is available yet.

Contents <snmp-v3-group>—No documentation is available yet.

<snmp-v3-information>

Usage <rpc-reply>
 <snmp-v3-information>
 <snmp-v3-general-information>...</snmp-v3-general-information>
 <snmp-v3-usm-user-information>...</snmp-v3-usm-user-information>
 <snmp-v3-group-information>...</snmp-v3-group-information>
 <snmp-v3-access-information>...</snmp-v3-access-information>
 <snmp-v3-target-information>...</snmp-v3-target-information>
 <snmp-v3-notify-information>...</snmp-v3-notify-information>
 <snmp-v3-notify-filter-information>...</snmp-v3-notify-filter-information>
 <snmp-v3-community-information>...</snmp-v3-community-information>
 </snmp-v3-information>
 </rpc-reply>

Description No documentation is available yet.

Contents <snmp-v3-access-information>—No documentation is available yet.
 <snmp-v3-community-information>—SNMPv3 community information.
 <snmp-v3-general-information>—No documentation is available yet.
 <snmp-v3-group-information>—No documentation is available yet.
 <snmp-v3-notify-filter-information>—SNMPv3 notify filter information.
 <snmp-v3-notify-information>—SNMPv3 notify information.
 <snmp-v3-target-information>—No documentation is available yet.
 <snmp-v3-usm-user-information>—No documentation is available yet.

<snmp-v3-input-statistics>

Usage <snmp-statistics>
 <snmp-v3-input-statistics>
 <unknown-secmodels>*unknown-secmodels*</unknown-secmodels>
 <invalid-msgs>*invalid-msgs*</invalid-msgs>
 <unknown-pduhandlers>*unknown-pduhandlers*</unknown-pduhandlers>
 <unavail-contexts>*unavail-contexts*</unavail-contexts>
 <unknown-contexts>*unknown-contexts*</unknown-contexts>
 <unsupported-seclevels>*unsupported-seclevels*</unsupported-seclevels>
 <not-in-timewindows>*not-in-timewindows*</not-in-timewindows>
 <unknown-usernames>*unknown-usernames*</unknown-usernames>
 <unknown-eids>*unknown-eids*</unknown-eids>
 <wrong-digests>*wrong-digests*</wrong-digests>
 <decrypt-errors>*decrypt-errors*</decrypt-errors>
 </snmp-v3-input-statistics>
 </snmp-statistics>

Description No documentation is available yet.

Contents <decrypt-errors>—No documentation is available yet.

<invalid-msgs>—No documentation is available yet.

<not-in-timewindows>—No documentation is available yet.

<unavail-contexts>—No documentation is available yet.

<unknown-contexts>—No documentation is available yet.

<unknown-eids>—No documentation is available yet.

<unknown-pduhandlers>—No documentation is available yet.

<unknown-secmodels>—No documentation is available yet.

<unknown-usernames>—No documentation is available yet.

<unsupported-seclevels>—No documentation is available yet.

<wrong-digests>—No documentation is available yet.

<snmp-v3-notify>

Usage	<pre> <snmp-v3-notify-information> <snmp-v3-notify> <notify-name>notify-name</notify-name> <notify-tag>notify-tag</notify-tag> <notify-type>notify-type</notify-type> <storage-type>storage-type</storage-type> <row-status>row-status</row-status> </snmp-v3-notify> </snmp-v3-notify-information> </pre>
Description	SNMPv3 notify.
Contents	<p><notify-name>—Notify name.</p> <p><notify-tag>—Notify tag used to identify all acceptable targets.</p> <p><notify-type>—No documentation is available yet.</p> <p><row-status>—Status for this entry.</p> <p><storage-type>—Type of storage for this entry.</p>

<snmp-v3-notify-filter>

Usage	<pre> <snmp-v3-notify-filter-information> <snmp-v3-notify-filter> <filter-name>filter-name</filter-name> <subtree>subtree</subtree> <filter-type>filter-type</filter-type> <storage-type>storage-type</storage-type> <row-status>row-status</row-status> </snmp-v3-notify-filter> </snmp-v3-notify-filter-information> </pre>
Description	SNMPv3 notify filter.
Contents	<p><filter-name>—Notify filter name.</p> <p><filter-type>—No documentation is available yet.</p> <p><row-status>—Status for this entry.</p> <p><storage-type>—Type of storage for this entry.</p> <p><subtree>—MIB subtree for this filter.</p>

<snmp-v3-notify-filter-information>

Usage <snmp-v3-information>
 <snmp-v3-notify-filter-information>
 <snmp-v3-notify-filter>...</snmp-v3-notify-filter>
 </snmp-v3-notify-filter-information>
 </snmp-v3-information>

Description SNMPv3 notify filter information.

Contents <snmp-v3-notify-filter>—SNMPv3 notify filter.

<snmp-v3-notify-information>

Usage <snmp-v3-information>
 <snmp-v3-notify-information>
 <snmp-v3-notify>...</snmp-v3-notify>
 </snmp-v3-notify-information>
 </snmp-v3-information>

Description SNMPv3 notify information.

Contents <snmp-v3-notify>—SNMPv3 notify.

<snmp-v3-target-address-information>

Usage <snmp-v3-target-information>
 <snmp-v3-target-address-information>
 <snmp-v3-target_address>...</snmp-v3-target_address>
 </snmp-v3-target-address-information>
 </snmp-v3-target-information>

Description SNMPv3 target address information.

Contents <snmp-v3-target_address>—SNMPv3 target address.

<snmp-v3-target-information>

Usage <snmp-v3-information>
 <snmp-v3-target-information>
 <snmp-v3-target-address-information>...</snmp-v3-target-address-information>
 <snmp-v3-target-parameters-information>...
 </snmp-v3-target-parameters-information>
 </snmp-v3-target-information>
 </snmp-v3-information>

Description No documentation is available yet.

Contents <snmp-v3-target-address-information>—SNMPv3 target address information.
 <snmp-v3-target-parameters-information>—SNMPv3 target parameters information.

<snmp-v3-target-parameters-information>

- Usage** <snmp-v3-target-information>
 <snmp-v3-target-parameters-information>
 <snmp-v3-target_parameters>...</snmp-v3-target_parameters>
 </snmp-v3-target-parameters-information>
 </snmp-v3-target-information>
- Description** SNMPv3 target parameters information.
- Contents** <snmp-v3-target_parameters>—SNMPv3 target parameters.

<snmp-v3-target_address>

- Usage** <snmp-v3-target-address-information>
 <snmp-v3-target_address>
 <target-address-name>target-address-name</target-address-name>
 <address>address</address>
 <port>port</port>
 <target-parameters-name>target-parameters-name</target-parameters-name>
 <storage-type>storage-type</storage-type>
 <row-status>row-status</row-status>
 </snmp-v3-target_address>
 </snmp-v3-target-address-information>
- Description** SNMPv3 target address.
- Contents** <address>—Target address.
- <port>—Target port number.
- <row-status>—Status for this entry.
- <storage-type>—Type of storage for this entry.
- <target-address-name>—Target address name in target address table.
- <target-parameters-name>—Target parameters name.

<snmp-v3-target_parameters>

Usage <snmp-v3-target-parameters-information>
 <snmp-v3-target_parameters>
 <target-parameters-name>*target-parameters-name*</target-parameters-name>
 <security-name>*security-name*</security-name>
 <security-model>*security-model*</security-model>
 <security-level>*security-level*</security-level>
 <notify-filter-name>*notify-filter-name*</notify-filter-name>
 <storage-type>*storage-type*</storage-type>
 <row-status>*row-status*</row-status>
 </snmp-v3-target_parameters>
 </snmp-v3-target-parameters-information>

Description SNMPv3 target parameters.

Contents <notify-filter-name>—Notify filter name in the notify filter table.

<row-status>—Status for this entry.

<security-level>—Security level.

<security-model>—Security model.

<security-name>—Security name.

<storage-type>—Type of storage for this entry.

<target-parameters-name>—Target parameters name.

<snmp-v3-usm-user>

Usage <snmp-v3-usm-user-information>
 <snmp-v3-usm-user>
 <user-name>*user-name*</user-name>
 <auth-type>*auth-type*</auth-type>
 <priv-type>*priv-type*</priv-type>
 <storage-type>*storage-type*</storage-type>
 <row-status>*row-status*</row-status>
 </snmp-v3-usm-user>
 </snmp-v3-usm-user-information>

Description No documentation is available yet.

Contents <auth-type>—Type of authentication required by this user.

<priv-type>—Type of encryption required by this user.

<row-status>—Status for this entry.

<storage-type>—Type of storage for this entry.

<user-name>—User name.

<snmp-v3-usm-user-engine-id>

- Usage** <snmp-v3-usm-user-information>
 <snmp-v3-usm-user-engine-id>
 <user-engine-id>*user-engine-id*</user-engine-id>
 </snmp-v3-usm-user-engine-id>
 </snmp-v3-usm-user-information>
- Description** No documentation is available yet.
- Contents** <user-engine-id>—Engine ID.

<snmp-v3-usm-user-information>

- Usage** <snmp-v3-information>
 <snmp-v3-usm-user-information>
 <snmp-v3-usm-user-engine-id>...</snmp-v3-usm-user-engine-id>
 <snmp-v3-usm-user>...</snmp-v3-usm-user>
 </snmp-v3-usm-user-information>
 </snmp-v3-information>
- Description** No documentation is available yet.
- Contents** <snmp-v3-usm-user>—No documentation is available yet.
 <snmp-v3-usm-user-engine-id>—No documentation is available yet.

<sub-agent-control-blocks>

- Usage** <snmp-statistics>
 <sub-agent-control-blocks>
 <total>*total*</total>
 <currently-active>*currently-active*</currently-active>
 <max-active>*max-active*</max-active>
 <not-found>*not-found*</not-found>
 <timed-out>*timed-out*</timed-out>
 <max-latency>*max-latency*</max-latency>
 </sub-agent-control-blocks>
 </snmp-statistics>
- Description** No documentation is available yet.
- Contents** <currently-active>—No documentation is available yet.
 <max-active>—No documentation is available yet.
 <max-latency>—No documentation is available yet.
 <not-found>—No documentation is available yet.
 <timed-out>—No documentation is available yet.
 <total>—No documentation is available yet.

<sub-agent-registration>

Usage	<pre> <snmp-statistics> <sub-agent-registration> <group-registers>group-registers</group-registers> <group-deregisters>group-deregisters</group-deregisters> <group-removes>group-removes</group-removes> </sub-agent-registration> </snmp-statistics> </pre>
Description	No documentation is available yet.
Contents	<p><group-deregisters>—No documentation is available yet.</p> <p><group-registers>—No documentation is available yet.</p> <p><group-removes>—No documentation is available yet.</p>

<trap-queue-stats>

Usage	<pre> <snmp-statistics> <trap-queue-stats> <current-queued>current-queued</current-queued> <total-queued>total-queued</total-queued> <total-discards>total-discards</total-discards> <total-overflows>total-overflows</total-overflows> </trap-queue-stats> </snmp-statistics> </pre>
Description	No documentation is available yet.
Contents	<p><current-queued>—No documentation is available yet.</p> <p><total-discards>—No documentation is available yet.</p> <p><total-overflows>—No documentation is available yet.</p> <p><total-queued>—No documentation is available yet.</p>

<trap-throttle-stats>

Usage	<pre> <snmp-statistics> <trap-throttle-stats> <current-throttled>current-throttled</current-throttled> <total-throttles>total-throttles</total-throttles> </trap-throttle-stats> </snmp-statistics> </pre>
Description	No documentation is available yet.
Contents	<p><current-throttled>—No documentation is available yet.</p> <p><total-throttles>—No documentation is available yet.</p>

Summary of Telephony Gateway Module Response Tags

This section lists JUNOS XML tags that contain operational information about the Telephony Gateway Module, a component that supports voice-over-IP services on some models of J-series Services Router. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-tgmd>. To review the DTD for the tags, see “DTD for Telephony Gateway Module Response Tags” on page 2063.

<dynamic-cac-information>

Usage <tgmd-dynamic-cac-list>
 <dynamic-cac-information>
 <dynamic-cac-interface-name>*dynamic-cac-interface-name*
 </dynamic-cac-interface-name>
 <dynamic-cac-interface-state>*dynamic-cac-interface-state*
 </dynamic-cac-interface-state>
 <dynamic-cac-activation-priority>*dynamic-cac-activation-priority*
 </dynamic-cac-activation-priority>
 <dynamic-cac-bbl>*dynamic-cac-bbl*</dynamic-cac-bbl>
 </dynamic-cac-information>
 </tgmd-dynamic-cac-list>

Description Information about dynamic call admission control.

Contents <dynamic-cac-activation-priority>—Activation priority configured on the interface.
 <dynamic-cac-bbl>—Bearer bandwidth limit configured on the interface.
 <dynamic-cac-interface-name>—Dynamic call admission control configured interface.
 <dynamic-cac-interface-state>—State of the interface.

<media-gateway-controller-configuration>

Usage <tgmd-information>
 <media-gateway-controller-configuration>
 <media-gateway-controller>*media-gateway-controller*</media-gateway-controller>
 </media-gateway-controller-configuration>
 </tgmd-information>

Description Information about a telephony gateway module (TGM) media gateway controller.

Contents <media-gateway-controller>—IPv4 address of the TGM media gateway controller.

<telephony-interface-module-status>

- Usage** <telephony-interface-module-status-information>
 <telephony-interface-module-status>
 <slot>*slot*</slot>
 <tim-state>*tim-state*</tim-state>
 <offline-reason>*offline-reason*</offline-reason>
 </telephony-interface-module-status>
 </telephony-interface-module-status-information>
- Description** Status of the telephony interface modules.
- Contents** <offline-reason>—Offline reason.
- <slot>—Slot number of the telephony interface module.
- <tim-state>—No documentation is available yet.

<telephony-interface-module-status-information>

- Usage** <rpc-reply>
 <telephony-interface-module-status-information>
 <telephony-interface-module-status>...</telephony-interface-module-status>
 </telephony-interface-module-status-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <telephony-interface-module-status>—Status of the telephony interface modules.

<tgm-dsp-capacity-information>

- Usage** <rpc-reply>
 <tgm-dsp-capacity-information>
 <dsp-capacity>*dsp-capacity*</dsp-capacity>
 </tgm-dsp-capacity-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <dsp-capacity>—Dsp resources available in the TGM.

<tgmdynamic-cac-information>

- Usage** <rpc-reply>
 <tgmdynamic-cac-information>
 <tgmdynamic-cac-reported-bearer-bandwidth-limit>*tgmdynamic-cac-reported-bearer-bandwidth-limit*
 </tgmdynamic-cac-reported-bearer-bandwidth-limit>
 <tgmdynamic-cac-list>...</tgmdynamic-cac-list>
 </tgmdynamic-cac-information>
 </rpc-reply>
- Description** Information about dynamic call admission control.
- Contents** <tgmdynamic-cac-list>—List of dynamic call admission control configured interfaces.
- <tgmdynamic-cac-reported-bearer-bandwidth-limit>—Reported bearer bandwidth limit.

<tgmdynamic-cac-list>

- Usage** <tgmdynamic-cac-information>
 <tgmdynamic-cac-list>
 <dynamic-cac-information>...</dynamic-cac-information>
 </tgmdynamic-cac-list>
 </tgmdynamic-cac-information>
- Description** List of dynamic call admission control configured interfaces.
- Contents** <dynamic-cac-information>—Information about dynamic call admission control.

<tgm-information>

- Usage** <rpc-reply>
 <tgm-information>
 <media-gateway-controller-configuration>...
 </media-gateway-controller-configuration>
 </tgm-information>
 </rpc-reply>
- Description** No documentation is available yet.
- Contents** <media-gateway-controller-configuration>—Information about a telephony gateway module (TGM) media gateway controller.

Summary of Subscribers Response Tags

This section lists JUNOS XML tags that contain operational information about the Subscriber element. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-subscribers>. To review the DTD for the tags, see “DTD for Subscribers Response Tags” on page 2053.

<error>

Usage <subscribers-information>
 <error>
 <input-error-message>input-error-message</input-error-message>
 </error>
 </subscribers-information>

Description No documentation is available yet.

Contents <input-error-message>—Input error message.

<subscriber>

Usage <subscribers-information>
 <subscriber>
 <access-type>*access-type*</access-type>
 <user-name>*user-name*</user-name>
 <ip-address>*ip-address*</ip-address>
 <logical-system>*logical-system*</logical-system>
 <routing-instance>*routing-instance*</routing-instance>
 <interface>*interface*</interface>
 <vlan-id>*vlan-id*</vlan-id>
 <profile>*profile*</profile>
 <mac-address>*mac-address*</mac-address>
 <login-time>*login-time*</login-time>
 <number-of-subscribers>*number-of-subscribers*</number-of-subscribers>
 <no-information>*no-information*</no-information>
 </subscriber>
 </subscribers-information>

Description Active subscriber.

Contents <access-type>—Access type of subscriber.
 <interface>—Interface name of subscriber.
 <ip-address>—IP address of subscriber.
 <logical-system>—Logical system where the subscriber resides.
 <login-time>—Login time of subscriber.
 <mac-address>—MAC address of subscriber.
 <no-information>—No documentation is available yet.
 <number-of-subscribers>—Number of active subscribers that match with search criteria.
 <profile>—Dynamic profile with which subscriber is activated.
 <routing-instance>—Routing instance where the subscriber resides.
 <user-name>—User name of subscriber.
 <vlan-id>—VLAN identifier.

<subscribers-information>

Usage <rpc-reply>
 <subscribers-information>
 <subscriber>...</subscriber>
 <error>...</error>
 </subscribers-information>
 </rpc-reply>

Description Subscribers.

Contents <error>—No documentation is available yet.
 <subscriber>—Active subscriber.

Summary of UDP Forwarding Helper Response Tags

This section lists JUNOS XML tags that contain operational information about the User Datagram Protocol (UDP) forwarding helper. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-helper>. To review the DTD for the tags, see “DTD for UDP Forwarding Helper Response Tags” on page 2065.

<helper-statistics-information>

Usage	<pre> <rpc-reply> <helper-statistics-information> <helper-statistics-service-information>... </helper-statistics-service-information> </helper-statistics-information> </rpc-reply> </pre>
Description	Port forwarding helper statistics.
Contents	<helper-statistics-service-information>—Port forwarding helper statistics for a particular service.

<helper-statistics-service-information>

Usage <helper-statistics-information>
 <helper-statistics-service-information>
 <service-name>*service-name*</service-name>
 <received-packets>*received-packets*</received-packets>
 <forwarded-packets>*forwarded-packets*</forwarded-packets>
 <dropped-packets>*dropped-packets*</dropped-packets>
 <dropped-packets-nointerface>*dropped-packets-nointerface*
 </dropped-packets-nointerface>
 <dropped-packets-nortinst>*dropped-packets-nortinst*</dropped-packets-nortinst>
 <dropped-packets-badread>*dropped-packets-badread*</dropped-packets-badread>
 <dropped-packets-badsend>*dropped-packets-badsend*</dropped-packets-badsend>
 <dropped-packets-badaddr>*dropped-packets-badaddr*</dropped-packets-badaddr>
 <dropped-packets-nolocaladdr>*dropped-packets-nolocaladdr*
 </dropped-packets-nolocaladdr>
 <dropped-packets-noroute>*dropped-packets-noroute*</dropped-packets-noroute>
 </helper-statistics-service-information>
 </helper-statistics-information>

Description Port forwarding helper statistics for a particular service.

Contents <dropped-packets>—Number of packets dropped.

<dropped-packets-badaddr>—Number of packets dropped because of an invalid server address.

<dropped-packets-badread>—Number of packets dropped because of an error during the packet read.

<dropped-packets-badsend>—Number of packets dropped because of an error during the packet send.

<dropped-packets-nointerface>—Number of packets dropped because of no interface.

<dropped-packets-nolocaladdr>—Number of packets dropped because of no valid local address.

<dropped-packets-noroute>—Number of packets dropped because of no route to server/client.

<dropped-packets-nortinst>—Number of packets dropped because of no routing instance.

<forwarded-packets>—Number of packets forwarded.

<received-packets>—Number of packets received.

<service-name>—Name of this service.

Summary of System Process Response Tags

This section lists JUNOS XML tags that contain operational information about system processes. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-process>. To review the DTD for the tags, see DTD for System Process Response Tags on page 2055

<command-line-argument>

Usage <command-line-argument-list>
 <command-line-argument>
 <argument-index>*argument-index*</argument-index>
 <argument>*argument*</argument>
 </command-line-argument>
 </command-line-argument-list>

Description No documentation is available yet.

Contents <argument>—Command-line argument.
 <argument-index>—Command-line argument index.

<command-line-argument-list>

Usage <process>
 <command-line-argument-list>
 <command-line-argument>...</command-line-argument>
 </command-line-argument-list>
 </process>

Description List of arguments that were passed to the command.

Contents <command-line-argument>—No documentation is available yet.

<memory-statistics>

Usage <process | memory-statistics-information>
 <memory-statistics>
 <memory-load>*memory-load*</memory-load>
 <virtual-size>*virtual-size*</virtual-size>
 <resident-set-size>*resident-set-size*</resident-set-size>
 <resident-set-before-swap>*resident-set-before-swap*</resident-set-before-swap>
 <text-size>*text-size*</text-size>
 <data-size>*data-size*</data-size>
 <stack-size>*stack-size*</stack-size>
 </memory-statistics>
 </process | memory-statistics-information>

Description Memory usage statistics for the process.

Contents <data-size>—Process data segment size, in kilobytes.

<memory-load>—Percentage of memory used by this process.

<resident-set-before-swap>—Resident set size of the process before last swap, in kilobytes.

<resident-set-size>—Resident set size of the process, in kilobytes.

<stack-size>—Process stack size, in kilobytes.

<text-size>—Process text segment size, in kilobytes.

<virtual-size>—Virtual size of the process, in kilobytes.

<process>

Usage <process-information>
 <process>
 <process-id>*process-id*</process-id>
 <name>*name*</name>
 <alias>*alias*</alias>
 <external-identifier>*external-identifier*</external-identifier>
 <primary-instance/>
 <login-id>*login-id*</login-id>
 <start-time>*start-time*</start-time>
 <parent-process-id>*parent-process-id*</parent-process-id>
 <process-group-id>*process-group-id*</process-group-id>
 <command>*command*</command>
 <command-line-argument-list>...</command-line-argument-list>
 <terminal-device>*terminal-device*</terminal-device>
 <priority>*priority*</priority>
 <nice>*nice*</nice>
 <process-status>*process-status*</process-status>
 <process-flags>...</process-flags>
 <sleep-information>...</sleep-information>
 <resource-usage>...</resource-usage>
 <memory-statistics>...</memory-statistics>
 </process>
 </process-information>

Description Information about a running process.

Contents <alias>—Process short name.

<command>—Command being executed.

<command-line-argument-list>—List of arguments that were passed to the command.

<external-identifier>—Process external identifier.

<login-id>—Effective login ID for the process.

<memory-statistics>—Memory usage statistics for the process.

<name>—Process formal name.

<nice>—Niceness value applied to the process priority.

<parent-process-id>—Parent process identifier.

<primary-instance>—Process is JUNOS process primary instance.

<priority>—Priority of the process.

<process-flags>—Process flags.

<process-group-id>—Process group identifier.

<process-id>—Process identifier.

<process-status>—Run status of the process.

<resource-usage>—Resource usage statistics for the process.

<sleep-information>—No documentation is available yet.

<start-time>—UTC time when the process started, in seconds.

<terminal-device>—Terminal device associated with the process.

<process-flags>

Usage	<pre> <process> <process-flags> <interruptible/> <advisory-lock/> <controlling-terminal/> <in-memory/> <wait-child/> <profiling/> <select/> <set-id-privileges/> <system-process/> <timing-out/> <debug-trace/> <debug-wait/> <exiting/> <exec/> </process-flags> </process> </pre>
Description	Process flags.
Contents	<p><advisory-lock>—Process may hold a POSIX advisory lock.</p> <p><controlling-terminal>—Process has a controlling terminal.</p> <p><debug-trace>—Debugged process being traced.</p> <p><debug-wait>—Debugging process has waited for child.</p> <p><exec>—Process called exec.</p> <p><exiting>—Process is working on exiting.</p> <p><in-memory>—Process is loaded into memory.</p> <p><interruptible>—Process is in an interruptible sleep.</p> <p><profiling>—Process has started profiling.</p> <p><select>—Process is waiting on select system call.</p> <p><set-id-privileges>—Process set ID privileges after the last exec.</p> <p><system-process>—Process is a system process -- no signals, statistics, or swapping.</p> <p><timing-out>—Process is timing out during sleep.</p> <p><wait-child>—Process is waiting for child to exec or exit.</p>

<process-information>

Usage <rpc-reply>
 <process-information>
 <scale-information>...</scale-information>
 <process>...</process>
 <system-information>...</system-information>
 </process-information>
 </rpc-reply>

Description Information about running processes.

Contents <process>—Information about a running process.

 <scale-information>—Information about values used in computing scales for this report.

 <system-information>—Information about the system.

<resource-usage>

Usage <process>
 <resource-usage>
 <cpu-load>*cpu-load*</cpu-load>
 <user-time>*user-time*</user-time>
 <system-time>*system-time*</system-time>
 <maximum-resident-set>*maximum-resident-set*</maximum-resident-set>
 <page-reclaims>*page-reclaims*</page-reclaims>
 <page-faults>*page-faults*</page-faults>
 <swaps>*swaps*</swaps>
 <block-input-operation>*block-input-operation*</block-input-operation>
 <block-output-operation>*block-output-operation*</block-output-operation>
 <messages-sent>*messages-sent*</messages-sent>
 <messages-received>*messages-received*</messages-received>
 <signals>*signals*</signals>
 <voluntary-context-switch>*voluntary-context-switch*</voluntary-context-switch>
 <involuntary-context-switch>*involuntary-context-switch*
 </involuntary-context-switch>
 </resource-usage>
 </process>

Description Resource usage statistics for the process.

Contents <block-input-operation>—Block input operations by the process.
 <block-output-operation>—Block output operations by the process.
 <cpu-load>—Percentage of CPU time used by this process.
 <involuntary-context-switch>—Involuntary context switches for the process.
 <maximum-resident-set>—Maximum resident set size for the process.
 <messages-received>—Messages received by the process.
 <messages-sent>—Messages sent by the process.
 <page-faults>—Page faults incurred by the process.
 <page-reclaims>—Page reclaims by the process.
 <signals>—Signals received by the process.
 <swaps>—Number of process swaps for the process.
 <system-time>—System CPU time for the process.
 <user-time>—User CPU time for the process.
 <voluntary-context-switch>—Voluntary context switches for the process.

<scale-information>

Usage <process-information>
 <scale-information>
 <memory-page-size>*memory-page-size*</memory-page-size>
 <physical-memory-pages>*physical-memory-pages*</physical-memory-pages>
 </scale-information>
</process-information>

Description Information about values used in computing scales for this report.

Contents <memory-page-size>—Memory page size for platform, in bytes.
 <physical-memory-pages>—Maximum number of physical memory pages.

<sleep-information>

Usage <process>
 <sleep-information>
 <reason>*reason*</reason>
 <address>*address*</address>
 </sleep-information>
</process>

Description No documentation is available yet.

Contents <address>—Sleep address.
 <reason>—Reason for sleeping.

<system-cpu-states>

Usage <system-information>
 <system-cpu-states>
 <cpu-total-time>*cpu-total-time*</cpu-total-time>
 <cpu-user-time>*cpu-user-time*</cpu-user-time>
 <cpu-user-time-percent>*cpu-user-time-percent*</cpu-user-time-percent>
 <cpu-nice-time>*cpu-nice-time*</cpu-nice-time>
 <cpu-nice-time-percent>*cpu-nice-time-percent*</cpu-nice-time-percent>
 <cpu-system-time>*cpu-system-time*</cpu-system-time>
 <cpu-system-time-percent>*cpu-system-time-percent*</cpu-system-time-percent>
 <cpu-interrupts-time>*cpu-interrupts-time*</cpu-interrupts-time>
 <cpu-interrupts-time-percent>*cpu-interrupts-time-percent*
 </cpu-interrupts-time-percent>
 <cpu-idle-time>*cpu-idle-time*</cpu-idle-time>
 <cpu-idle-time-percent>*cpu-idle-time-percent*</cpu-idle-time-percent>
 </system-cpu-states>
 </system-information>

Description Process state information.

Contents <cpu-idle-time>—CPU time spent in idle state.
 <cpu-idle-time-percent>—CPU time spent in idle state.
 <cpu-interrupts-time>—CPU time spent in interrupts state.
 <cpu-interrupts-time-percent>—CPU time spent in interrupts state.
 <cpu-nice-time>—CPU time spent in nice state.
 <cpu-nice-time-percent>—CPU time spent in nice state.
 <cpu-system-time>—CPU time spent in system state.
 <cpu-system-time-percent>—CPU time spent in system state.
 <cpu-total-time>—Total CPU time spent.
 <cpu-user-time>—CPU time spent in user state.
 <cpu-user-time-percent>—CPU time spent in user state.

<system-information>**Usage** <process-information>**<system-information>**

```

<system-hardware-cpu-architecture>system-hardware-cpu-architecture
    </system-hardware-cpu-architecture>
<system-hardware-cpu-model>system-hardware-cpu-model
    </system-hardware-cpu-model>
<system-hardware-cpu-count>system-hardware-cpu-count
    </system-hardware-cpu-count>
<system-boot-device>system-boot-device</system-boot-device>
<system-boot-next-device>system-boot-next-device</system-boot-next-device>
<system-hardware-physical-memory>system-hardware-physical-memory
    </system-hardware-physical-memory>
<system-hardware-user-memory>system-hardware-user-memory
    </system-hardware-user-memory>
<system-hardware-page-size>system-hardware-page-size
    </system-hardware-page-size>
<system-virtual-memory-page-size>system-virtual-memory-page-size
    </system-virtual-memory-page-size>
<system-hardware-page-available>system-hardware-page-available
    </system-hardware-page-available>
<system-hardware-routing-engine-name>system-hardware-routing-engine-name
    </system-hardware-routing-engine-name>
<system-hardware-routing-engine-model>system-hardware-routing-engine-model
    </system-hardware-routing-engine-model>

```

```

<system-hardware-routing-engine-serial-number>system-hardware-routing-engine-serial-number
    </system-hardware-routing-engine-serial-number>

```

```

<system-hardware-routing-engine-other-present/>
<system-hardware-routing-engine-other-alive/>
<system-virtual-memory-swap-enabled/>
<system-virtual-memory-context-switches>system-virtual-memory-context-switches
    </system-virtual-memory-context-switches>
<system-virtual-memory-trap>system-virtual-memory-trap
    </system-virtual-memory-trap>
<system-virtual-memory-syscall>system-virtual-memory-syscall
    </system-virtual-memory-syscall>
<system-virtual-memory-hard-interrupts>system-virtual-memory-hard-interrupts
    </system-virtual-memory-hard-interrupts>
<system-virtual-memory-soft-interrupts>system-virtual-memory-soft-interrupts
    </system-virtual-memory-soft-interrupts>
<system-virtual-memory-faults>system-virtual-memory-faults
    </system-virtual-memory-faults>

```

```

<system-virtual-memory-copy-on-write-faults>system-virtual-memory-copy-on-write-faults
    </system-virtual-memory-copy-on-write-faults>

```

```

<system-virtual-memory-copy-on-write-optimized>system-virtual-memory-copy-on-write-optimized
    </system-virtual-memory-copy-on-write-optimized>

```

```

<system-virtual-memory-zeroed-pages>system-virtual-memory-zeroed-pages
    </system-virtual-memory-zeroed-pages>

```

```

<system-virtual-memory-zeroed-pages-optimized>system-virtual-memory-zeroed-pages-o
ptimized
    </system-virtual-memory-zeroed-pages-optimized>
    <system-virtual-memory-swapin>system-virtual-memory-swapin
    </system-virtual-memory-swapin>
    <system-virtual-memory-swapout>system-virtual-memory-swapout
    </system-virtual-memory-swapout>

<system-virtual-memory-swapped-in-pages>system-virtual-memory-swapped-in-pages
    </system-virtual-memory-swapped-in-pages>

<system-virtual-memory-swapped-out-pages>system-virtual-memory-swapped-out-pages
    </system-virtual-memory-swapped-out-pages>

<system-virtual-memory-reactivated-pages>system-virtual-memory-reactivated-pages
    </system-virtual-memory-reactivated-pages>
    <system-virtual-memory-vnode-in>system-virtual-memory-vnode-in
    </system-virtual-memory-vnode-in>
    <system-virtual-memory-vnode-out>system-virtual-memory-vnode-out
    </system-virtual-memory-vnode-out>
    <system-virtual-memory-vnode-page-ins>system-virtual-memory-vnode-page-ins
    </system-virtual-memory-vnode-page-ins>
    <system-virtual-memory-vnode-page-outs>system-virtual-memory-vnode-page-outs
    </system-virtual-memory-vnode-page-outs>
    <system-virtual-memory-pager-wakes>system-virtual-memory-pager-wakes
    </system-virtual-memory-pager-wakes>
    <system-virtual-memory-pager-scans>system-virtual-memory-pager-scans
    </system-virtual-memory-pager-scans>
    <system-virtual-memory-page-count>system-virtual-memory-page-count
    </system-virtual-memory-page-count>
    <system-virtual-memory-free-reserved>system-virtual-memory-free-reserved
    </system-virtual-memory-free-reserved>
    <system-virtual-memory-free-minimum>system-virtual-memory-free-minimum
    </system-virtual-memory-free-minimum>
    <system-virtual-memory-free-pages>system-virtual-memory-free-pages
    </system-virtual-memory-free-pages>
    <system-virtual-memory-wired-pages>system-virtual-memory-wired-pages
    </system-virtual-memory-wired-pages>
    <system-virtual-memory-active-pages>system-virtual-memory-active-pages
    </system-virtual-memory-active-pages>
    <system-virtual-memory-cache-pages>system-virtual-memory-cache-pages
    </system-virtual-memory-cache-pages>

<system-virtual-memory-cache-pages-minimum>system-virtual-memory-cache-pages-min
imum
    </system-virtual-memory-cache-pages-minimum>

<system-virtual-memory-cache-pages-maximum>system-virtual-memory-cache-pages-ma
ximum
    </system-virtual-memory-cache-pages-maximum>
    <system-virtual-memory-load-averages>...</system-virtual-memory-load-averages>
    <system-last-pid>system-last-pid</system-last-pid>
    <system-process-counts>...</system-process-counts>

```

```

    <system-cpu-states>...</system-cpu-states>
  </system-information>
</process-information>

```

Description Information about the system.

Contents

- <system-boot-device>—Device the system booted from.
- <system-boot-next-device>—Device the system booted from.
- <system-cpu-states>—Process state information.
- <system-hardware-cpu-architecture>—CPU architecture.
- <system-hardware-cpu-count>—Number of active CPUs.
- <system-hardware-cpu-model>—CPU model.
- <system-hardware-page-available>—Pages of memory available.
- <system-hardware-page-size>—System memory page size, in bytes.
- <system-hardware-physical-memory>—Physical memory in system, in bytes.
- <system-hardware-routing-engine-model>—Routing Engine model.
- <system-hardware-routing-engine-name>—Routing Engine name.
- <system-hardware-routing-engine-other-alive>—Other Routing Engine is operational.
- <system-hardware-routing-engine-other-present>—Other Routing Engine is present.
- <system-hardware-routing-engine-serial-number>—Routing Engine serial number.
- <system-hardware-user-memory>—Physical memory available to user processes, in bytes.
- <system-last-pid>—Last PID assigned.
- <system-process-counts>—Number of processes on system.
- <system-virtual-memory-active-pages>—Pages recently statistically used by user processes.
- <system-virtual-memory-cache-pages>—Pages ready for use or clean.
- <system-virtual-memory-cache-pages-maximum>—Maximum cache pages.
- <system-virtual-memory-cache-pages-minimum>—Minimum cache pages.
- <system-virtual-memory-context-switches>—Number of context switches.
- <system-virtual-memory-copy-on-write-faults>—Copy on write page faults.
- <system-virtual-memory-copy-on-write-optimized>—Optimized copy on write page faults.

<system-virtual-memory-faults>—Virtual memory page faults.

<system-virtual-memory-free-minimum>—Minimum free pages.

<system-virtual-memory-free-pages>—Free pages.

<system-virtual-memory-free-reserved>—Reserved free pages.

<system-virtual-memory-hard-interrupts>—Number of hardware interrupts.

<system-virtual-memory-load-averages>—Load averages.

<system-virtual-memory-page-count>—Total page count.

<system-virtual-memory-page-size>—Size of page, in bytes.

<system-virtual-memory-pager-scans>—Pager page scans.

<system-virtual-memory-pager-wakes>—Pager wakeup events.

<system-virtual-memory-reactivated-pages>—Re-activated pages.

<system-virtual-memory-soft-interrupts>—Number of software interrupts.

<system-virtual-memory-swap-enabled>—Swapping is enabled.

<system-virtual-memory-swapin>—Swap-in operations.

<system-virtual-memory-swapout>—Swap-out operations.

<system-virtual-memory-swapped-in-pages>—Swapped in pages.

<system-virtual-memory-swapped-out-pages>—Swapped out pages.

<system-virtual-memory-syscall>—Number of system calls.

<system-virtual-memory-trap>—Number of traps.

<system-virtual-memory-vnode-in>—Vnodein operations.

<system-virtual-memory-vnode-out>—Vnodeout operations.

<system-virtual-memory-vnode-page-ins>—Vnode page-ins.

<system-virtual-memory-vnode-page-outs>—Vnode page-outs.

<system-virtual-memory-wired-pages>—Pages fixed in memory.

<system-virtual-memory-zeroed-pages>—Zero filled pages.

<system-virtual-memory-zeroed-pages-optimized>—Optimized zero filled pages.

<system-process-counts>

Usage <system-information>
 <system-process-counts>
 <process-total>*process-total*</process-total>
 <process-run>*process-run*</process-run>
 <process-sleep>*process-sleep*</process-sleep>
 <process-start>*process-start*</process-start>
 <process-stop>*process-stop*</process-stop>
 <process-zombie>*process-zombie*</process-zombie>
 </system-process-counts>
 </system-information>

Description Number of processes on system.

Contents <process-run>—Running processes.
 <process-sleep>—Sleeping processes.
 <process-start>—Starting processes.
 <process-stop>—Stopped processes.
 <process-total>—Total number of processes.
 <process-zombie>—Zombie processes.

<system-virtual-memory-load-averages>

Usage <system-information>
 <system-virtual-memory-load-averages>
 <load-average-one-minute>*load-average-one-minute*</load-average-one-minute>
 <load-average-five-minute>*load-average-five-minute*</load-average-five-minute>
 <load-average-fifteen-minute>*load-average-fifteen-minute*
 </load-average-fifteen-minute>
 </system-virtual-memory-load-averages>
 </system-information>

Description Load averages.

Contents <load-average-fifteen-minute>—Fifteen minute run queue average length.
 <load-average-five-minute>—Five minute run queue average length.
 <load-average-one-minute>—One minute run queue average length.

Summary of Virtual Router Redundancy Protocol Response Tags

This section lists JUNOS XML tags that contain operational information about the Virtual Router Redundancy Protocol (VRRP). The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-vrrpd>. To review the DTD for the tags, see “DTD for Virtual Router Redundancy Protocol Response Tags” on page 2067.

<bandwidth>

Usage <vrrp-interface | track-vrrpd-interface>
<bandwidth>
 <bandwidth-threshold>*bandwidth-threshold*</bandwidth-threshold>
 <bandwidth-priority-cost>*bandwidth-priority-cost*</bandwidth-priority-cost>
 <bandwidth-active>*bandwidth-active*</bandwidth-active>
 <priority-down-status>*priority-down-status*</priority-down-status>
 <priority-cost>*priority-cost*</priority-cost>
 <priority-active>*priority-active*</priority-active>
</bandwidth>
 </vrrp-interface | track-vrrpd-interface>

Description Display bandwidth parameters.

Contents <bandwidth-active>—Check if threshold is active for a given tracked interface.

<bandwidth-priority-cost>—Cost to reduce if tracked interface's bandwidth drops beyond threshold.

<bandwidth-threshold>—Threshold for the tracked interface.

<priority-active>—Display if priority is active(when down-priority cost > 0).

<priority-cost>—The value subtracted from the configured VRRP priority.

<priority-down-status>—Display the status when the interface is down.

<group-vrrp-pdu-error-statistics>

Usage <vrrp-interface>
 <group-vrrp-pdu-error-statistics>
 <bad-authentication-type-received>*bad-authentication-type-received*
 </bad-authentication-type-received>
 <bad-password-received>*bad-password-received*</bad-password-received>
 <bad-md5-digest-received>*bad-md5-digest-received*</bad-md5-digest-received>
 <bad-advertisement-timer-received>*bad-advertisement-timer-received*
 </bad-advertisement-timer-received>
 <bad-vip-count-received>*bad-vip-count-received*</bad-vip-count-received>
 <bad-vipaddr-received>*bad-vipaddr-received*</bad-vipaddr-received>
 </group-vrrp-pdu-error-statistics>
 </vrrp-interface>

Description Errored statistics for the VRRP group.

Contents <bad-advertisement-timer-received>—Number of invalid advertisements timers received from VRRP PDUs.

<bad-authentication-type-received>—Number of VRRP PDUs received with an invalid authentication type.

<bad-md5-digest-received>—Number of invalid digest received from VRRP PDUs.

<bad-password-received>—Number of VRRP PDUs received with an invalid password.

<bad-vip-count-received>—Number of invalid virtual IP count received from VRRP PDUs.

<bad-vipaddr-received>—Number of invalid virtual IP addresses received from VRRP PDUs.

<group-vrrp-pdu-statistics>

Usage <vrrp-interface>
 <group-vrrp-pdu-statistics>
 <advertisement-sent>*advertisement-sent*</advertisement-sent>
 <advertisement-received>*advertisement-received*</advertisement-received>
 </group-vrrp-pdu-statistics>
 </vrrp-interface>

Description Number of VRRP advertisements sent and received by the group.

Contents <advertisement-received>—Number of VRRP advertisement PDUs received from an interface.

<advertisement-sent>—Number of VRRP advertisement that the interface has transmitted.

<group-vrrp-state-transition-statistics>

Usage <vrrp-interface>
 <group-vrrp-state-transition-statistics>
 <idle-master-transitions>*idle-master-transitions*</idle-master-transitions>
 <idle-backup-transitions>*idle-backup-transitions*</idle-backup-transitions>
 <backup-master-transitions>*backup-master-transitions*
 </backup-master-transitions>
 <master-backup-transitions>*master-backup-transitions*
 </master-backup-transitions>
 </group-vrrp-state-transition-statistics>
 </vrrp-interface>

Description State transition statistics for the VRRP group.

Contents <backup-master-transitions>—VRRP instance transitioned from the backup to the master state.

<idle-backup-transitions>—VRRP instances transitioned from the idle to the backup state.

<idle-master-transitions>—VRRP instances transitioned from the idle to the master state.

<master-backup-transitions>—VRRP instances transitioned from the master to the backup state.

<preempt-hold>

Usage <vrrp-interface>
 <preempt-hold>
 <preempt>*preempt*</preempt>
 <preempt-hold-time>*preempt-hold-time*</preempt-hold-time>
 <accept-data-mode>*accept-data-mode*</accept-data-mode>
 <vip-count>*vip-count*</vip-count>
 <vip>*vip*</vip>
 </preempt-hold>
 </vrrp-interface>

Description Display preempt related parameters.

Contents <accept-data-mode>—Accept packets destined for the virtual IP address.

<preempt>—Allow the master router to be preempted.

<preempt-hold-time>—Seconds before a backup router preempts the master router.

<vip>—List of virtual IP addresses configured on the interface.

<vip-count>—Number of virtual IP addresses configured on the interface.

<track-route-entry>

Usage <vrrp-interface>
 <track-route-entry>
 <route-addr>*route-addr*</route-addr>
 <route-state>*route-state*</route-state>
 <route-priority>*route-priority*</route-priority>
 <interface>*interface*</interface>
 <group>*group*</group>
 <configured-priority>*configured-priority*</configured-priority>
 <current-priority>*current-priority*</current-priority>
 <vrrp-state>*vrrp-state*</vrrp-state>
 </track-route-entry>
 </vrrp-interface>

Description Route Tracking entry table.

Contents <configured-priority>—Priority configured to track an interface of a virtual router.

<current-priority>—The current VRRP priority for the VRID.

<group>—Identifies the VRRP group.(0-255).

<interface>—Name of the logical interface.

<route-addr>—IP route to be tracked.

<route-priority>—Based on the tracked IP route state changes VRRP priority.

<route-state>—State of an IP route or the reachability of a route.

<vrrp-state>—VRRP state information.

<track-route-node-information>

Usage <vrrp-interface>
 <track-route-node-information>
 <route-addr>*route-addr*</route-addr>
 <route-instance>*route-instance*</route-instance>
 <route-state>*route-state*</route-state>
 <route-priority>*route-priority*</route-priority>
 </track-route-node-information>
 </vrrp-interface>

Description Display route tracking details.

Contents <route-addr>—IP route to be tracked.

<route-instance>—Route tracking instance(value is Default).

<route-priority>—Based on the tracked IP route state changes VRRP priority.

<route-state>—State of an IP route or the reachability of a route.

<track-vrrpd-interface>

Usage <vrrp-interface>
 <track-vrrpd-interface>
 <tracked-interface>*tracked-interface*</tracked-interface>
 <interface-state>*interface-state*</interface-state>
 <interface-speed>*interface-speed*</interface-speed>
 <current-priority-cost>*current-priority-cost*</current-priority-cost>
 <bandwidth>...</bandwidth>
 </track-vrrpd-interface>
 </vrrp-interface>

Description Display VRRP interface tracking details.

Contents <bandwidth>—Display bandwidth parameters.

<current-priority-cost>—Current cost to lower the priority of the VRRP master.

<interface-speed>—The speed on an physical interface.

<interface-state>—State of the interface.

<tracked-interface>—VRRP tracked name and unit number.

<vrrp-information>

Usage <rpc-reply>
 <vrrp-information>
 <vrrp-interface>...</vrrp-interface>
 </vrrp-information>
 </rpc-reply>

Description Display vrrp information.

Contents <vrrp-interface>—Describes vrrp interface.

<vrrp-interface>

Usage <vrrp-information>

```

<b>vrrp-interface</b>
  <groups>groups</groups>
  <active>active</active>
  <physical-interface>physical-interface</physical-interface>
  <interface>interface</interface>
  <address>address</address>
  <interface-state>interface-state</interface-state>
  <group>group</group>
  <vrrp-state>vrrp-state</vrrp-state>
  <timer-name>timer-name</timer-name>
  <timer-value>timer-value</timer-value>
  <local-interface-address>local-interface-address</local-interface-address>
  <vrrp-vlan>...</vrrp-vlan>
  <bandwidth>...</bandwidth>
  <group-vrrp-pdu-statistics>...</group-vrrp-pdu-statistics>
  <group-vrrp-pdu-error-statistics>...</group-vrrp-pdu-error-statistics>
  <group-vrrp-state-transition-statistics>...
    </group-vrrp-state-transition-statistics>
  <preempt-hold>...</preempt-hold>
  <virtual-ip-address>virtual-ip-address</virtual-ip-address>
  <unit>unit</unit>
  <index>index</index>
  <interface-index>interface-index</interface-index>
  <snmp-interface-index>snmp-interface-index</snmp-interface-index>
  <vrrp-traps>vrrp-traps</vrrp-traps>
  <group-priority>group-priority</group-priority>
  <advertisement-interval>advertisement-interval</advertisement-interval>
  <authentication-type>authentication-type</authentication-type>
  <delay-threshold>delay-threshold</delay-threshold>
  <computed-send-rate>computed-send-rate</computed-send-rate>
  <preempt>preempt</preempt>
  <accept-data-mode>accept-data-mode</accept-data-mode>
  <vip-count>vip-count</vip-count>
  <vip>vip</vip>
  <dead-timer>dead-timer</dead-timer>
  <master-priority>master-priority</master-priority>
  <master-router-ip>master-router-ip</master-router-ip>
  <master-router>master-router</master-router>
  <router-ip>router-ip</router-ip>
  <virtual-router-uptime>virtual-router-uptime</virtual-router-uptime>
  <master-router-uptime>master-router-uptime</master-router-uptime>
  <virtual-mac>virtual-mac</virtual-mac>
  <tracking>tracking</tracking>
  <preempt-hold-time>preempt-hold-time</preempt-hold-time>
  <current-priority>current-priority</current-priority>
  <configured-priority>configured-priority</configured-priority>
  <priority-hold-time>priority-hold-time</priority-hold-time>
  <remaining-time>remaining-time</remaining-time>
  <pending-priority>pending-priority</pending-priority>
  <interface-tracking-state>interface-tracking-state</interface-tracking-state>
  <interface-count>interface-count</interface-count>

```

```

<route-tracking-state>route-tracking-state</route-tracking-state>
<route-count>route-count</route-count>
<interface-speed>interface-speed</interface-speed>
<current-priority-cost>current-priority-cost</current-priority-cost>
<tracked-interface>tracked-interface</tracked-interface>
<track-route-node-information>...</track-route-node-information>
<track-vrrp-interface>...</track-vrrp-interface>
<track-route-entry>...</track-route-entry>
<vrrp-message>...</vrrp-message>
<invalid-ipah-next-type-received>invalid-ipah-next-type-received
    </invalid-ipah-next-type-received>
<invalid-vrrp-ttl-value-received>invalid-vrrp-ttl-value-received
    </invalid-vrrp-ttl-value-received>
<invalid-vrrp-version-received>invalid-vrrp-version-received
    </invalid-vrrp-version-received>
<invalid-vrrp-pdu-type-received>invalid-vrrp-pdu-type-received
    </invalid-vrrp-pdu-type-received>
<invalid-vrrp-authentication-type-received>invalid-vrrp-authentication-type-received
    </invalid-vrrp-authentication-type-received>
<invalid-vrrp-ip-count-received>invalid-vrrp-ip-count-received
    </invalid-vrrp-ip-count-received>
<invalid-vrrp-checksum-received>invalid-vrrp-checksum-received
    </invalid-vrrp-checksum-received>
<advertisement-timer>advertisement-timer</advertisement-timer>
<packets-received>packets-received</packets-received>
<no-group-match-received>no-group-match-received</no-group-match-received>
<advertisement-sent>advertisement-sent</advertisement-sent>
<advertisement-received>advertisement-received</advertisement-received>
</vrrp-interface>
</vrrp-information>

```

Description Describes vrrp interface.

Contents

- <accept-data-mode>—Accept packets destined for the virtual IP address.
- <active>—Total number of VRRP groups that are active.
- <address>—Address of the physical interface.
- <advertisement-interval>—Advertisement interval for sending advertisement packets.
- <advertisement-received>—Number of VRRP advertisement PDUs received from an interface.
- <advertisement-sent>—Number of VRRP advertisement that the interface has transmitted.
- <advertisement-timer>—How long, in seconds, until the advertisement timer expires.
- <authentication-type>—Configured VRRP authentication type(none, simple, or md5).
- <bandwidth>—Display bandwidth parameters.

<computed-send-rate>—The advertisement send rate in packets per second.

<configured-priority>—Priority configured to track an interface of a virtual router.

<current-priority>—The current VRRP priority for the VRID.

<current-priority-cost>—Current cost to lower the priority of the VRRP master.

<dead-timer>—How long until the Master Is Dead.

<delay-threshold>—Number of advertisement timer drifted beyond threshold.

<group>—Identifies the VRRP group.(0-255).

<group-priority>—Value used to elect the master virtual router in the VRRP group.

<group-vrrp-pdu-error-statistics>—Errored statistics for the VRRP group.

<group-vrrp-pdu-statistics>—Number of VRRP advertisements sent and received by the group.

<group-vrrp-state-transition-statistics>—State transition statistics for the VRRP group.

<groups>—Total number of VRRP groups configured on the interface.

<index>—Physical interface's index number(initialization sequence).

<interface>—Name of the logical interface.

<interface-count>—Number of tracked interfaces.

<interface-index>—Interface index.

<interface-speed>—The speed on an physical interface.

<interface-state>—State of the interface.

<interface-tracking-state>—State of the interface being tracked.

<invalid-ipah-next-type-received>—Number of packets received that use IPAH.

<invalid-vrrp-authentication-type-received>—Packets received with invalid VRRP authentication type.

<invalid-vrrp-checksum-received>—Packets received with invalid VRRP checksum.

<invalid-vrrp-ip-count-received>—Number of packets received whose VRRP IP count exceeds 8.

<invalid-vrrp-pdu-type-received>—Number of packets received whose VRRP PDU type is not 1.

<invalid-vrrp-ttl-value-received>—Number of packets received whose IP TTL value is not 255.

<invalid-vrrp-version-received>—Number of packets received whose VRRP version is

not 2.

<local-interface-address>—Local interface address.

<master-priority>—Priority value of the router acting as the master.

<master-router>—IP address of the interface that is acting as the master.

<master-router-ip>—IP address of the interface that is acting as the master.

<master-router-uptime>—How long, in seconds, that the master router has been up.

<no-group-match-received>—Packets received for nonexistent VRRP groups on the interface.

<packets-received>—Number of VRRP packets received for VRRP groups on the interface.

<pending-priority>—Priority to decrease if incoming VRRP packet priority is higher.

<physical-interface>—Name of the physical interface.

<preempt>—Allow the master router to be preempted.

<preempt-hold>—Display preempt related parameters.

<preempt-hold-time>—Seconds before a backup router preempts the master router.

<priority-hold-time>—Time that must elapse between dynamic priority changes.

<remaining-time>—Predicts the time remaining before it becomes master.

<route-count>—Number of tracked IP routes.

<route-tracking-state>—State of the route being tracked.

<router-ip>—IP address of the router.

<snmp-interface-index>—SNMP index number for the physical interface.

<timer-name>—VRRP timer name.

<timer-value>—VRRP timer information.

<track-route-entry>—Route Tracking entry table.

<track-route-node-information>—Display route tracking details.

<track-vrrpd-interface>—Display VRRP interface tracking details.

<tracked-interface>—VRRP tracked name and unit number.

<tracking>—Whether tracking is enabled or disabled.

<unit>—Logical unit number.

<vip>—List of virtual IP addresses configured on the interface.

<vip-count>—Number of virtual IP addresses configured on the interface.

<virtual-ip-address>—Virtual Router IP Address .

<virtual-mac>—MAC address associated with the virtual IP address.

<virtual-router-uptime>—How long, in seconds, that the virtual router has been up.

<vrrp-message>—Display vrrp message.

<vrrp-state>—VRRP state information.

<vrrp-traps>—Status of VRRP traps: Enabled or Disabled.

<vrrp-vlan>—Display vrrp when configured on vlan.

<vrrp-interface-profile>

Usage <vrrp-profile-statistics>
<vrrp-interface-profile>
 <interface>*interface*</interface>
 <unit>*unit*</unit>
 <group>*group*</group>
 <advertisement-timer>*advertisement-timer*</advertisement-timer>
 <delay>*delay*</delay>
</vrrp-interface-profile>
 </vrrp-profile-statistics>

Description Profile of vrrp interface.

Contents <advertisement-timer>—How long, in seconds, until the advertisement timer expires.

<delay>—Maximum %age advertisement interval delay.

<group>—Identifies the VRRP group.(0-255).

<interface>—Name of the logical interface.

<unit>—Logical unit number.

<vrrp-message>

Usage <vrrp-interface>
<vrrp-message>
 <message>*message*</message>
</vrrp-message>
 </vrrp-interface>

Description Display vrrp message.

Contents <message>—Message to be displayed in case of error conditions.

<vrrp-profile-statistics>

Usage <rpc-reply>
<vrrp-profile-statistics>
 <vrrp-interface-profile>...</vrrp-interface-profile>
 <parse-time>*parse-time*</parse-time>
 <delay-violations>*delay-violations*</delay-violations>
 <delay-violations-rate>*delay-violations-rate*</delay-violations-rate>
 <peak-delay-violations-rate>*peak-delay-violations-rate*
 </peak-delay-violations-rate>
 <missed-three-consecutive-send>*missed-three-consecutive-send*
 </missed-three-consecutive-send>
 <send-rate>*send-rate*</send-rate>
 <peak-send-rate>*peak-send-rate*</peak-send-rate>
 <receive-rate>*receive-rate*</receive-rate>
 <peak-receive-rate>*peak-receive-rate*</peak-receive-rate>
 <expirations>*expirations*</expirations>
 <expiration-rate>*expiration-rate*</expiration-rate>
 <peak-expiration-rate>*peak-expiration-rate*</peak-expiration-rate>
</vrrp-profile-statistics>
 </rpc-reply>

Description Vrrp profile statistics.

Contents <delay-violations>—Many times advertisement delay was violated.

<delay-violations-rate>—Advertisement timer drift beyond threshold in the last second.

<expiration-rate>—Expired dead timer per second.

<expirations>—Expired dead timer count.

<missed-three-consecutive-send>—The adv timer delayed beyond the maximum to become master.

<parse-time>—Maximum configuration time.

<peak-delay-violations-rate>—Advertisement delay drift per second.

<peak-expiration-rate>—Peak expiration dead timer per second.

<peak-receive-rate>—Peak advertisement receive rate.

<peak-send-rate>—Peak advertisement send rate.

<receive-rate>—Advertisement packets received per second.

<send-rate>—Advertisement packets send per second.

<vrrp-interface-profile>—Profile of vrrp interface.

<vrrp-vlan>

Usage <vrrp-interface>
 <vrrp-vlan>
 <physical-interface>*physical-interface*</physical-interface>
 <unit>*unit*</unit>
 <vlan-id>*vlan-id*</vlan-id>
 <vlan-tag>*vlan-tag*</vlan-tag>
 <vlan-address>*vlan-address*</vlan-address>
 </vrrp-vlan>
 </vrrp-interface>

Description Display vrrp when configured on vlan.

Contents <physical-interface>—Name of the physical interface.
 <unit>—Logical unit number.
 <vlan-address>—Virtual Lan IP address and mask.
 <vlan-id>—A valid VLAN identifier.
 <vlan-tag>—VLAN tag ID for a logical interface.

Summary of X.509 Certificate Response Tags

This section lists JUNOS XML tags that contain operational information about X.509 certificates. The associated XML namespace is <http://xml.juniper.net/junos/9.3R1/junos-x509-certificate>. To review the DTD for the tags, see “DTD for X.509 Certificate Response Tags” on page 2073.

<alternate-subject-list>

- Usage** `<x509-certificate-info>`
 <alternate-subject-list>
 `<alternate-subject>alternate-subject</alternate-subject>`
 </alternate-subject-list>
 `</x509-certificate-info>`
- Description** No documentation is available yet.
- Contents** `<alternate-subject>`—Series of alternate subject in X.509 certificate.

<auto-re-enrollment>

- Usage** `<x509-certificate-info>`
 <auto-re-enrollment>
 `<auto-re-enrollment-status>auto-re-enrollment-status`
 `</auto-re-enrollment-status>`
 `<auto-re-enrollment-next-trigger-time>auto-re-enrollment-next-trigger-time`
 `</auto-re-enrollment-next-trigger-time>`
 </auto-re-enrollment>
 `</x509-certificate-info>`
- Description** No documentation is available yet.
- Contents** `<auto-re-enrollment-next-trigger-time>`—Auto-re-enrollment next trigger time.
 `<auto-re-enrollment-status>`—Auto-re-enrollment information.

<crl-issuer-alternate-subject-list>

- Usage** `<x509-crl-information>`
 <crl-issuer-alternate-subject-list>
 `<crl-issuer-alternate-subject>crl-issuer-alternate-subject`
 `</crl-issuer-alternate-subject>`
 </crl-issuer-alternate-subject-list>
 `</x509-crl-information>`
- Description** No documentation is available yet.
- Contents** `<crl-issuer-alternate-subject>`—One or more alternate subject names for CRL issuer.

<crl-issuer-detail>

- Usage** <x509-crl-information>
 <crl-issuer-detail>
 <distinguished-name>...</distinguished-name>
 </crl-issuer-detail>
 </x509-crl-information>
- Description** Distinguished name of CRL issuer.
- Contents** <distinguished-name>—No documentation is available yet.

<crl-revocation-list>

- Usage** <x509-crl-information>
 <crl-revocation-list>
 <revoked-cert-serial-number>*revoked-cert-serial-number*
 </revoked-cert-serial-number>
 <crl-revocation-date>*crl-revocation-date*</crl-revocation-date>
 </crl-revocation-list>
 </x509-crl-information>
- Description** No documentation is available yet.
- Contents** <crl-revocation-date>—Revocation date.
- <revoked-cert-serial-number>—Serial number of revoked certificate.

<crl-validity>

- Usage** <x509-crl-information>
 <crl-validity>
 <effective-date>*effective-date*</effective-date>
 <next-update>*next-update*</next-update>
 </crl-validity>
 </x509-crl-information>
- Description** Information about validity period for X.509 certificate revocation list.
- Contents** <effective-date>—Effective date of CRL.
- <next-update>—Next update of CRL.

<distinguished-name>

Usage	<issuer subject crl-issuer-detail> <distinguished-name> <organization-name> <i>organization-name</i> </organization-name> <organizational-unit-name> <i>organizational-unit-name</i> </organizational-unit-name> <country-name> <i>country-name</i> </country-name> <state-or-province-name> <i>state-or-province-name</i> </state-or-province-name> <locality-name> <i>locality-name</i> </locality-name> <common-name> <i>common-name</i> </common-name> <email-address> <i>email-address</i> </email-address> <domain-component> <i>domain-component</i> </domain-component> </distinguished-name> </issuer subject crl-issuer-detail>
Description	No documentation is available yet.
Contents	<common-name>—Common name. <country-name>—Country name. <domain-component>—Domain component. <email-address>—E-mail address. <locality-name>—Locality. <organization-name>—Organization. <organizational-unit-name>—Organization unit. <state-or-province-name>—State.

<distribution-crl-list>

Usage	<x509-certificate-info> <distribution-crl-list> <distribution-crl> <i>distribution-crl</i> </distribution-crl> </distribution-crl-list> </x509-certificate-info>
Description	Information about one or more distribution certificate revocation lists.
Contents	<distribution-crl>—Information about a distribution CRL.

<fingerprint>

Usage	<pre> <x509-certificate-info> <fingerprint> <fingerprint-hash-algorithm><i>fingerprint-hash-algorithm</i> </fingerprint-hash-algorithm> <fingerprint-content><i>fingerprint-content</i></fingerprint-content> </fingerprint> </x509-certificate-info> </pre>
Description	Fingerprint.
Contents	<p><fingerprint-content>—No documentation is available yet.</p> <p><fingerprint-hash-algorithm>—No documentation is available yet.</p>

<issue-info>

Usage	<pre> <x509-certificate-info> <issue-info> <recipient><i>recipient</i></recipient> <issued-by><i>issued-by</i></issued-by> </issue-info> </x509-certificate-info> </pre>
Description	No documentation is available yet.
Contents	<p><issued-by>—No documentation is available yet.</p> <p><recipient>—No documentation is available yet.</p>

<issuer>

Usage	<pre> <x509-certificate-info> <issuer> <distinguished-name>...</distinguished-name> </issuer> </x509-certificate-info> </pre>
Description	Identifies the CA that issued certificate.
Contents	<distinguished-name>—No documentation is available yet.

<key-usage-list>

Usage	<pre> <x509-certificate-info> <key-usage-list> <key-usage><i>key-usage</i></key-usage> </key-usage-list> </x509-certificate-info> </pre>
Description	No documentation is available yet.
Contents	<key-usage>—Purpose for which X.509 key is used.

<public-key>

- Usage** <x509-certificate-info>
 <public-key>
 <public-key-algorithm>*public-key-algorithm*</public-key-algorithm>
 <public-key-length>*public-key-length*</public-key-length>
 <public-key-verification-status>*public-key-verification-status*
 </public-key-verification-status>
 </public-key>
 </x509-certificate-info>
- Description** Information about an X.509 public key.
- Contents** <public-key-algorithm>—Algorithm used for creating the subject public key.
 <public-key-length>—Length of X.509 public.
 <public-key-verification-status>—Verification status of X.509 public key.

<public-key-contents-list>

- Usage** <x509-certificate-info>
 <public-key-contents-list>
 <key-contents>*key-contents*</key-contents>
 </public-key-contents-list>
 </x509-certificate-info>
- Description** No documentation is available yet.
- Contents** <key-contents>—Contents of an X.509 public key.

<serial-number-list>

- Usage** <x509-certificate-info>
 <serial-number-list>
 <serial-number-x509>*serial-number-x509*</serial-number-x509>
 </serial-number-list>
 </x509-certificate-info>
- Description** Serial numbers of one or more X.509 certificate.
- Contents** <serial-number-x509>—Serial number of an X.509 certificate.

<subject>

- Usage** <x509-certificate-info>
 <subject>
 <distinguished-name>...</distinguished-name>
 </subject>
 </x509-certificate-info>
- Description** Information about certificate owner.
- Contents** <distinguished-name>—No documentation is available yet.

<validity>

Usage <x509-certificate-info>
 <validity>
 <not-before>*not-before*</not-before>
 <not-after>*not-after*</not-after>
 </validity>
 </x509-certificate-info>

Description Information about validity period for X.509 certificate.

Contents <not-after>—End date of validity period.
 <not-before>—Start date of validity period.

<x509-certificate-add-results>

Usage <rpc-reply>
 <x509-certificate-add-results>
 <x509-certificate-add-success/>
 <x509-certificate-info>...</x509-certificate-info>
 </x509-certificate-add-results>
 </rpc-reply>

Description No documentation is available yet.

Contents <x509-certificate-add-success>—Certificate added successfully.
 <x509-certificate-info>—Detailed information about an X.509 certificate.

<x509-certificate-info>

Usage <x509-certificate-info-list | x509-certificate-add-results>
<x509-certificate-info>
 <issue-info>...</issue-info>
 <serial-number-list>...</serial-number-list>
 <public-key>...</public-key>
 <fingerprint>...</fingerprint>
 <public-key-contents-list>...</public-key-contents-list>
 <alternate-subject-list>...</alternate-subject-list>
 <key-usage-list>...</key-usage-list>
 <distribution-crl-list>...</distribution-crl-list>
 <signature-algorithm>*signature-algorithm*</signature-algorithm>
 <identifier>*identifier*</identifier>
 <validity>...</validity>
 <version>*version*</version>
 <auto-re-enrollment>...</auto-re-enrollment>
 <certificate-type>*certificate-type*</certificate-type>
 <status>*status*</status>
 <issuer>...</issuer>
 <subject>...</subject>
</x509-certificate-info>
 </x509-certificate-info-list | x509-certificate-add-results>

Description Detailed information about an X.509 certificate.

Contents <alternate-subject-list>—No documentation is available yet.

<auto-re-enrollment>—No documentation is available yet.

<certificate-type>—X.509 certificate type.

<distribution-crl-list>—Information about one or more distribution certificate revocation lists.

<fingerprint>—Fingerprint.

<identifier>—Certificate identifier.

<issue-info>—No documentation is available yet.

<issuer>—Identifies the CA that issued certificate.

<key-usage-list>—No documentation is available yet.

<public-key>—Information about an X.509 public key.

<public-key-contents-list>—No documentation is available yet.

<serial-number-list>—Serial numbers of one or more X.509 certificate.

<signature-algorithm>—Algorithm used by the CA to sign the certificate.

<status>—No documentation is available yet.

<subject>—Information about certificate owner.

<validity>—Information about validity period for X.509 certificate.

<version>—Certificate version.

<x509-certificate-info-list>

Usage <rpc-reply>
 <x509-certificate-info-list>
 <x509-certificate-info>...</x509-certificate-info>
 </x509-certificate-info-list>
 </rpc-reply>

Description No documentation is available yet.

Contents <x509-certificate-info>—Detailed information about an X.509 certificate.

<x509-crl-information>

Usage <rpc-reply>
 <x509-crl-information>
 <crl-number>*crl-number*</crl-number>
 <crl-revocation-list>...</crl-revocation-list>
 <crl-validity>...</crl-validity>
 <crl-version>*crl-version*</crl-version>
 <crl-issuer>*crl-issuer*</crl-issuer>
 <identifier>*identifier*</identifier>
 <crl-issuer-alternate-subject-list>...</crl-issuer-alternate-subject-list>
 <crl-issuer-detail>...</crl-issuer-detail>
 </x509-crl-information>
 </rpc-reply>

Description Detailed information about X.509 certificate revocation list.

Contents <crl-issuer>—CRL issuer name.

<crl-issuer-alternate-subject-list>—No documentation is available yet.

<crl-issuer-detail>—Distinguished name of CRL issuer.

<crl-number>—CRL sequence number.

<crl-revocation-list>—No documentation is available yet.

<crl-validity>—Information about validity period for X.509 certificate revocation list.

<crl-version>—CRL version.

<identifier>—Certificate identifier.