

Chapter 11

Setting Up AIM User Groups

This chapter describes how to set up Advanced Insight Manager (AIM) user groups. User groups contain a list of selected users. The user group name must be unique within the AIM installation. AIM users should be created before AIM user groups. User group members are selected from the existing pool of AIM users. For more information about creating users, see “Setting Up AIM Users” on page 89.

Once created, user groups can be associated with device groups. This can be done on the User Group Settings page, or on the Device Group Settings Page. For more information about creating AIM device groups, see “Creating Device Groups” on page 72.

To create AIM user groups, you must be the AIM administrator or have AIM Admin Settings enabled in the user settings.

This chapter includes the following information:

- Creating a New User Group on page 99
- Deleting a User Group on page 103

Creating a New User Group

You must be the AIM administrator or have AIM Admin Setting privileges to create a user group. When you create a user group, the User Group table appears without the Associated Device Groups table displayed.

To create an AIM user group, follow these steps:

1. Click Settings > User Groups. The User Group page appears. The User Group table is empty until you add a new user group.

User Groups

User Groups (1 - 4 of 4)

<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input type="button" value="Add New"/>	<input type="button" value="Delete"/>	<input type="button" value="↑↓"/>	<input type="button" value="✕"/>
↑↓	Name	↑↓	Users	↑↓	Device Groups

- Click Add New. The User Group page appears.

User Group

Save Changes

* Name:

MyNewUserGroup

Users (1 - 4)

	User
<input checked="" type="checkbox"/>	admin
<input checked="" type="checkbox"/>	aimuser
<input type="checkbox"/>	anewuser
<input checked="" type="checkbox"/>	demo

Page: 1 of 1

Go

- In the Name field, type a unique name for the user group.
- In the Users table, select the users you want to add to the user group.
- Click Save Changes. This saves the new user group settings. For more information about the User Group page, see “User Group Page Description” on page 102.

The Associate Device Groups table appears below the User’s table.

User Group

Save Changes

* Name:

MyNewUserGroup

Users (1 - 4)

	User
<input checked="" type="checkbox"/>	admin
<input checked="" type="checkbox"/>	aimuser
<input type="checkbox"/>	anewuser
<input checked="" type="checkbox"/>	demo

Page: 1 of 1

Go

Associated Device Groups (0)

Associate Device Groups		
Name	Organization	Devices
No items found.		

6. Click Associate Device Groups. The Associate Device Groups page appears. Device groups can be associated with one or more user groups.

Associate Device Groups

Device Groups (1 - 2 of 2)

<input type="checkbox"/> <input type="checkbox"/> Save Changes <input type="button" value="↑↓"/> <input type="button" value="✕"/>			
<input type="checkbox"/>	Name	Organization	Devices
<input checked="" type="checkbox"/>	Group1	Customer XYZ	device1-re0, device2-re0, device3-re0
<input checked="" type="checkbox"/>	Group2	Customer XYZ	device4-re0, device5-re0, device6-re0

7. Select the device groups that you want to associated to the user group. Click Save Changes. The User Group page appears with the selected users and the device groups that have been associated with the AIM user group.

User Group

Save Changes

* Name: MyNewUserGroup

Users (1 - 4)

<input type="checkbox"/> <input type="checkbox"/> <input type="button" value="↑↓"/> <input type="button" value="✕"/> <input type="button" value="⊞"/>	
<input type="checkbox"/>	User
<input checked="" type="checkbox"/>	admin
<input checked="" type="checkbox"/>	aimuser
<input type="checkbox"/>	anewuser
<input checked="" type="checkbox"/>	demo

Page: 1 of 1 Go

Associated Device Groups (1 - 2 of 2)

Associate Device Groups <input type="button" value="↑↓"/> <input type="button" value="✕"/>		
Name	Organization	Devices
Group1	Customer XYZ	device1-re0, device2-re0, device3-re0
Group2	Customer XYZ	device4-re0, device5-re0

8. Click Save Changes. The new user group appears in the User Groups table.

User Groups

User Groups (1 - 5 of 5)

<input type="checkbox"/> <input type="checkbox"/> Add New Delete <input type="button" value="↑↓"/> <input type="button" value="✕"/>			
<input type="checkbox"/>	Name	Users	Device Groups
<input type="checkbox"/>	admins	admin	all-devices
<input type="checkbox"/>	MyNewUserGroup	admin, anewuser, demo	Group1, Group2

9. Repeat Steps 2 through 8 to create more user groups. For more information on the User Groups table, See “Associate Device Groups Table Element Descriptions” on page 103 and “User Group Table Elements Descriptions” on page 102.

User Group Page Description

Table 51 describes the User Group page columns.

Table 51: User Group Page Element Description

Element	Description	Privileges	Enabled/ Disabled	Results
Save Changes command button	Saves the user group.	AIM Admin Settings	Enabled if admin privileges	Error message is displayed if settings were not saved
Name field	Unique user group name	AIM Admin Settings	32 characters	Blank
User Table	Displays the names of existing AIM users from which you can select to be in the new user group	AIM Admin Settings	Enabled if admin privileges	Selected users will be associated with this User Group when you click Save Changes
Associated Device Groups table command button	Displays the Associate Device Groups page, from which existing device groups can be selected for association to this user group	AIM Admin Settings	Enabled if admin privileges	Displays page to set which device groups are associated
Associate Device Groups table	Lists the existing AIM device groups by name, organization, and devices that are included	Not allowed to modify	Enabled if admin privileges	N/A

User Group Table Elements Descriptions

Table 52 describes the User Group table elements.

Table 52: User Group Table Command Button Description

Button Name	Description	Privileges	Enabled/ Disabled	Results
Add New	Displays User Group page used to add a new AIM user group. When you first add a user group, the User Group table is empty and the Associate Device Group table does not appear.	AIM Admin Settings	Enabled if admin privileges	Displays User Groups page
Delete	Deletes a selected user group	AIM Admin Settings	Enabled if admin privileges	Deletes user group from User Group table and the database

Table 53 describes the User Group table columns.

Table 53: User Group Table Column Descriptions

Name	Description	Privileges	Range/ Length	Default
Name	Unique name of user group. Click user group name link to view the User Group page so you can modify the user group name, users, and associated device groups.	Not allowed to modify	N/A	N/A
Users	List of existing users selected to be in user group.	Not allowed to modify	N/A	N/A
Device Groups	List of existing device groups that have been associated with the user group	Not allowed to modify	N/A	N/A

Associate Device Groups Table Element Descriptions

Table 54 describes the Associate Device Groups table command button.

Table 54: Associated Device Groups Table Command Button Description

Button Name	Description	Privileges	Enabled/ Disabled	Results
Save Changes	Saves modifications to a user group in the Associate Device Groups table	AIM Admin Settings	Enabled if admin privileges	Device groups selected are associated with the user group, then the User Group Detail page appears.

Table 55 describes the Associate Device Groups table columns.

Table 55: Associated Device Groups Table Columns Descriptions

Name	Description	Privileges	Enabled/ Disabled	Results
Name	Name of the device groups available to associate	Not allowed to modify	N/A	N/A
Organization	Name of the organization with which the device group is associated	Not allowed to modify	N/A	N/A
Device	Lists the devices that are included in the device group	Not allowed to modify	N/A	N/A

Deleting a User Group

To delete a User Group, follow these steps.

1. Click Settings > User Groups. The User Group page appears. The User Group table is empty until you add a new user group.
2. Select the user group(s) that you want to delete.

3. Click Delete. This action removes the AIM user group with all associations from the database.