

## pppoe max-session-vsa

---

**Syntax**    pppoe max-session-vsa { override | ignore }  
no pppoe max-session-vsa override

**Release Information**    Command introduced in JUNOS Release 9.3.0.

**Description**    Configures the PPPoE application to override the current PPPoE maximum session value set with the **pppoe sessions** command with the PPPoE maximum session value returned by the RADIUS server in the Max-Clients-Per-Interface VSA [26-143] in Access-Accept messages. The **no** version restores the default behavior, which ignores the PPPoE maximum session value returned by RADIUS.



**NOTE:** The router never overrides the maximum number of PPPoE subinterfaces supported per line module with a value from RADIUS that is either 0 (zero) or greater than the maximum number of supported PPPoE subinterfaces. See *JUNOS Release Notes, Appendix A, System Maximums* corresponding to your software release for information about the maximum number of PPPoE subinterfaces supported for each line module.

---

**Mode**    Interface Configuration, Profile Configuration, Subinterface Configuration

---

Published: 2010-01-07