

# EX8200 Line Cards: Special Instructions Card

Certain line cards that are supported on Juniper Networks EX8200 Ethernet Switches require a particular minimum Junos operating system (Junos OS) release. If the software running on the switch does not meet the particular minimum release requirement, the line card will not power on after you install it in the switch.

The following table lists the EX8200 line cards that have a minimum Junos OS release requirement.

**Table 1:** EX8200 Line Card Models and Part Numbers

Line Card Model	Line Card Part Number with Applicable Revision
EX8200-40XS-ES	750-036593 REV 12 or later
EX8200-48F-ES	750-047322 REV 03 or later
EX8200-8XS-ES	750-047323 REV 03 or later
EX8200-48T-ES	750-047324 REV 03 or later
EX8200-40XS	750-046751 REV 06 or later
EX8200-48F	750-047325 REV 03 or later
EX8200-8XS	750-047326 REV 03 or later
EX8200-48T	750-047327 REV 03 or later

Each of the line cards listed in Table 1 has a tag on its left ejector and a label on its faceplate that indicate this requirement.

**NOTE:** You must remove the tag before you install the line card in a switch.

If you install the line cards listed in Table 1 in a switch that is not running the minimum Junos OS release listed below, the line cards will not power up. For the line cards to power up and function properly, upgrade your switch to one of the following Junos OS releases:

**Table 2:** Junos OS Releases Supported on EX8200 Line Cards

Junos OS Release	Releases Supported
Junos OS Release 12.3	Junos OS Release 12.3R10-S1 or later
Junos OS Release 13.2	Junos OS Release 13.2X50 or later
Junos OS Release 14.1	Junos OS Release 14.1X53 or later

For details about troubleshooting line cards, see <http://www.juniper.net/techpubs/>. (Navigate to **Switching > EX Series > EX8208 or EX8216** and then go to the Troubleshooting section).

For technical support, see <http://www.juniper.net/support/requesting-support.html>

