

deactivation-delay

Syntax	deactivation-delay <i>seconds</i> ;
Hierarchy Level	[edit interfaces <i>dln</i> unit <i>logical-unit-number</i> dialer-options]
Release Information	Statement introduced before JUNOS Release 7.4.
Description	On J Series Services Routers with ISDN interfaces, configure the ISDN deactivation delay. Used only for dialer backup and dialer watch cases.
Options	<i>seconds</i> —Interval before the backup interface is deactivated after the primary interface has comes up. Range: 1 through 4,294,967,295 seconds Default: 0 (zero)
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Topics	<ul style="list-style-type: none">■ Configuring ISDN Logical Interface Properties■ <i>JUNOS Software Interfaces and Routing Configuration Guide for Security Devices</i>

Published: 2010-04-20