

## icmpv6-rate-limit

---

<b>Syntax</b>	icmpv6-rate-limit { bucket-size <i>seconds</i> ; packet-rate <i>packet-rate</i> ; }
<b>Hierarchy Level</b>	[edit system internet-options]
<b>Release Information</b>	Statement introduced before JUNOS Release 7.4. Statement introduced in JUNOS Release 9.0 for EX Series switches.
<b>Description</b>	Configure rate-limiting parameters for ICMPv6 messages sent.
<b>Options</b>	<p>bucket-size <i>seconds</i>—Number of seconds in the rate-limiting bucket. <b>Range:</b> 0 through 4294967295 seconds <b>Default:</b> 5</p> <p>packet-rate <i>pps</i>—Rate-limiting packets earned per second. <b>Range:</b> 0 through 4294967295 pps <b>Default:</b> 1000</p>
<b>Required Privilege Level</b>	admin—To view this statement in the configuration. admin-control—To add this statement to the configuration.
<b>Related Topics</b>	■ <a href="#">Configuring the JUNOS Software ICMPv6 Rate Limit for ICMPv6 Routing Engine Messages</a>

---

Published: 2010-04-26