

## vrrp-inet6-group

---

**Syntax** `vrrp-inet6-group group-id {  
(accept-data | no-accept-data);  
fast-interval milliseconds;  
inet6-advertise-interval seconds;  
(preempt | no-preempt) {  
    hold-time seconds;  
}  
priority number;  
track {  
    interface interface-name {  
        bandwidth-threshold bits-per-second priority-cost priority;  
        priority-cost priority;  
    }  
    priority-hold-time seconds;  
    route prefix/prefix-length routing-instance instance-name priority-cost priority;  
}  
}  
virtual-inet6-address [ addresses ];  
virtual-link-local-address ipv6-address;  
}`

**Hierarchy Level** [edit interfaces *interface-name* unit *logical-unit-number* family inet6 address *address*],  
[edit logical-systems *logical-system-name* interfaces *interface-name* unit *logical-unit-number*  
family inet6 address *address*]

**Release Information** Statement introduced before JUNOS Release 7.4.

**Description** Configure a Virtual Router Redundancy Protocol (VRRP) IPv6 group.

**Options** *group-id*—VRRP group identifier. If you enable MAC source address filtering on the interface, you must include the virtual MAC address in the list of source MAC addresses that you specify in the `source-address-filter` statement. MAC addresses ranging from 00:00:5e:00:01:00 through 00:00:5e:00:01:ff are reserved for VRRP, as defined in RFC 2338. The VRRP group number must be the decimal equivalent of the last hexadecimal byte of the virtual MAC address.

**Range:** 0 through 255

The remaining statements are explained separately.

**Required Privilege Level** interface—To view this statement in the configuration.  
interface-control—To add this statement to the configuration.

- Related Topics**
- Configuring Basic VRRP Support
  - VRRP for IPv6 Configuration Hierarchy

Published: 2010-04-28