

ACTIVATE YOUR QFABRIC SYSTEM AND ITS FEATURES AND CAPACITY

This document briefly describes how to generate a MAC address range and license activation key(s) for your Juniper Networks® QFabric™ System.

1. Gather your QFabric System serial number and, if activating additional features, authorization code(s).
QFabric System serial number: This is a unique 14-digit numeric code used to identify your Juniper Networks QFabric System. You received your QFabric System serial number in an e-mail sent in response to your order. The QFabric System will show its serial number in response to the command-line interface (CLI) command "show version."
Authorization code: The 16-digit alphanumeric authorization code is sent in response to your order. The authorization code is required to generate license activation key(s)—it is not the license activation key itself.
2. Sign into the Juniper Networks License Management System (LMS) by following the Manage Product Licenses Generate License Keys link found at www.juniper.net/generate_license. A Juniper Customer Support Center login ID is required. Select the "QFX Series Product" link in the product list dropdown. Select "QFX Series Product Fabric" and continue.
3. For existing QFabric System installations that already have a media access control (MAC) address range (found in response to the "show version" CLI command) skip to step 6. For new QFabric System installations, continue to step 4.
4. Generate a MAC address range for your QFabric System.
 - Enter the QFabric System serial number into the LMS
 - Move the cursor to another field (the LMS will respond with this QFabric System's MAC address range)
 - Select the option "Download/Email MAC Address" range (do not enter authorization codes into LMS at this time as the QFabric System needs to be set up first)
 - Exit the LMS
5. Perform an initial setup of a QFabric System as described in the product documentation.
6. To add additional capacity/features to your QFabric System, return to the LMS and log in. Select the "QFX Series Product" link in the product list dropdown. Select "QFX Series Product Fabric" and continue.
7. Enter the 14-digit QFabric System serial number into the LMS and move your cursor to another field. If the "QFabric System ID" field is blank:
 - Return to the QFabric System and reveal the 36-character QFabric System ID by using the "show version" CLI command
 - Enter the QFabric System ID into the LMS
8. Enter authorization codes(s) for QFabric System features/capacity.
 - Select confirm
 - Review the information and if correct, select "generate license"
 - Download or e-mail the product activation key(s)
9. Enter the license activation key(s) into the QFabric System by following the product instructions.

For detailed information about license key types, generating a new license key, and upgrading existing license keys, see the QFX Series Technical Documentation at: www.juniper.net/techpubs.

For additional assistance, you may contact Juniper Networks Customer Care at +1-888-314-5822 (United States) or +1-408-936-1572 (outside the United States). Alternately, you may also open a case online via the Juniper Customer Support Center (CSC) Case Manager.