


## callback

---

<b>Syntax</b>	callback;
<b>Hierarchy Level</b>	[edit interfaces dln unit <i>logical-unit-number</i> dialer-options incoming-map], [edit logical-systems <i>logical-system-name</i> interfaces dln unit <i>logical-unit-number</i> dialer-options incoming-map]
<b>Release Information</b>	Statement introduced in JUNOS Release 7.5.
<b>Description</b>	(J-series Services Routers) For interfaces configured for ISDN, configure the dialer to terminate the incoming call and call back the originator after the callback wait period. The default wait time is 5 seconds. To configure the wait time, include the <code>callback-wait-period</code> statement at the [edit interfaces dl <i>n</i> unit <i>logical-unit-number</i> dialer-options] hierarchy level.
	<b>NOTE:</b> The <code>incoming-map</code> statement is mandatory for the router to accept any incoming ISDN calls.
	If the <code>callback</code> statement is configured, you cannot use the caller <i>caller-id</i> statement at the [edit interfaces dln unit <i>logical-unit-number</i> dialer-options] hierarchy level.
<b>Usage Guidelines</b>	See Configuring ISDN Logical Interface Properties.
<b>Required Privilege Level</b>	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
<b>Related Topics</b>	<i>J-series Services Router Basic LAN and WAN Access Configuration Guide</i>

