

input-policer

Syntax	<code>input-policer <i>policer-name</i>;</code>
Hierarchy Level	[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> layer2-policer]
Release Information	Statement introduced in JUNOS Release 8.2.
Description	Associate a Layer 2 policer with a logical interface. The <code>input-policer</code> and <code>input-three-color</code> statements are mutually exclusive.
Options	<i>policer-name</i> —Name of the policer that you define at the [edit firewall] hierarchy level.
Usage Guidelines	See Configuring Gigabit Ethernet Policers.
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Topics	output-policer

