

output-three-color

Syntax	output-three-color <i>policer-name</i> ;
Hierarchy Level	[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> layer2-policer]
Release Information	Statement introduced in JUNOS Release 8.2.
Description	Associate a Layer 2, three-color policer with a logical interface. The output-three-color and output-policer statements are mutually exclusive.
Options	<i>policer-name</i> —Name of the three-color policer that you define at the [edit firewall] hierarchy level.
Usage Guidelines	See Configuring Gigabit Ethernet Policers.
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Topics	input-three-color

