

## Example: Configuring a Link Services Interface with MLFR FRF.15

---

```
[edit interfaces]
t1-0/0/0 {
  encapsulation frame-relay;
  unit 0 {
    dlc1 16;
    family mlfr-end-to-end {
      bundle ls-0/3/0.0;
    }
  }
}
t1-0/0/1 {
  encapsulation frame-relay;
  unit 0 {
    dlc1 16;
    family mlfr-end-to-end {
      bundle ls-0/3/0.0;
    }
  }
}
ls-0/3/0 {
  unit 0 {
    encapsulation multilink-frame-relay-end-to-end;
    family inet {
      address 10.16.1.2/32 {
        destination 10.16.1.1;
      }
    }
    family iso;
    family inet6 {
      address 2001:DB8:1:2/12;
    }
  }
}
```

---

Published: 2010-04-28