

force

Syntax force (protect | working);

Hierarchy Level [edit interfaces *interface-name* sonet-options aps]

Release Information Statement introduced before JUNOS Release 7.4.

Description Perform a forced switch between the protect and working circuits. This statement is honored only if there are no higher-priority reasons to switch. It can be overridden by a signal failure on the protect circuit, thus causing a switch to the working circuit.

Options protect—Request the circuit to become the protect circuit.

working—Request the circuit to become the working circuit.

Required Privilege Level interface—To view this statement in the configuration.
interface-control—To add this statement to the configuration.

Related Topics

- Configuring Switching Between the Working and Protect Circuits
- request

Published: 2010-04-20