

ignore-encapsulation-mismatch

Syntax ignore-encapsulation-mismatch;

Hierarchy Level [edit logical-systems *logical-system-name* protocols l2circuit local-switching interface *interface-name* neighbor *address*],
[edit protocols l2circuit neighbor *address* interface *interface-name*]

Release Information Statement introduced in JUNOS Release 9.2.

Description Allow a Layer 2 circuit to be established even though the encapsulation configured on the CE device interface does not match the encapsulation configured on the Layer 2 circuit interface.

Required Privilege Level routing—To view this statement in the configuration.
routing-control—To add this statement to the configuration

Related Topics ■ Configuring Interfaces for Layer 2 Circuits

Published: 2010-04-28