

input-policer

Syntax	input-policer <i>policer-name</i> ;
Hierarchy Level	[edit interfaces <i>interface-name</i> unit <i>logical-unit-number</i> layer2-policer]
Release Information	Statement introduced in JUNOS Release 8.2.
Description	Associate a Layer 2 policer with a logical interface. The input-policer and input-three-color statements are mutually exclusive.
Options	<i>policer-name</i> —Name of the policer that you define at the [edit firewall] hierarchy level.
Usage Guidelines	See Applying Layer 2 Policers to Gigabit Ethernet Interfaces.
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Topics	output-policer

Published: 2010-04-15