

bchannel-allocation

Syntax	bchannel-allocation (ascending descending);
Hierarchy Level	[edit interfaces <i>interface-name</i> isdn-options]
Release Information	Statement introduced in JUNOS Release 8.3.
Description	(J-series Services Routers equipped with a Dual-Port Channelized T1/E1 PIM) For Integrated Services Digital Network Primary Rate Interfaces (ISDN PRI), allocate PRI dialout B-channels in ascending or descending order.
Options	(ascending descending)—Allocate the B-channels in ascending (from low to high) or descending (from high to low) order. Default: Descending order
Usage Guidelines	See Allocating B-Channels for Dialout.
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Topics	<i>J-series Services Router Basic LAN and WAN Access Configuration Guide</i>

