

pop-all-labels

Syntax	pop-all-labels { required-depth <i>number</i> ; }
Hierarchy Level	[edit interfaces <i>interface-name</i> atm-options mpls], [edit interfaces <i>interface-name</i> sonet-options mpls], [edit interfaces <i>interface-name</i> fastether-options mpls], [edit interfaces <i>interface-name</i> gigeether-options mpls]
Release Information	Statement introduced before JUNOS Release 7.4.
Description	<p>For passive monitoring on ATM and SONET/SDH interfaces only, removes up to two MPLS labels from incoming IP packets.</p> <p>This statement has no effect on IP packets with more than two MPLS labels. Packets with MPLS labels cannot be processed by the Monitoring Services PIC; if packets with MPLS labels are forwarded to the Monitoring Services PIC, they are discarded.</p> <p>The remaining statement is explained separately.</p>
Default	If you omit this statement, the MPLS labels are not removed, and the packet is not processed by the Monitoring Services PIC.
Usage Guidelines	See Removing MPLS Labels from Incoming Packets and Enabling Passive Monitoring on SONET/SDH Interfaces.
Required Privilege Level	interface—To view this statement in the configuration. interface-control—To add this statement to the configuration.
Related Topics	<i>JUNOS Services Interfaces Configuration Guide</i>

